



# **Agilent V2891A Upconverter**

## **Specifications**



**Agilent Technologies**

# Notices

---

© Agilent Technologies, Inc. 2010

No part of this manual may be reproduced in any form or by any means (including electronic storage and retrieval or translation into a foreign language) without prior agreement and written consent from Agilent Technologies, Inc. as governed by United States and international copyright laws.

## Manual Part Number

V2891-90002

## Edition

First edition, March 2010

Printed in USA

Agilent Technologies, Inc.

## Sales and Technical Support

To contact Agilent for sales and technical support, refer to the “support” links on the following Agilent web resources:

- [www.agilent.com/find/V2891A](http://www.agilent.com/find/V2891A)  
(product-specific information and support)
- [www.agilent.com/find/assist](http://www.agilent.com/find/assist)  
(worldwide contact information for repair and service)

Information on preventing damage to your Agilent equipment can be found at [www.agilent.com/find/tips](http://www.agilent.com/find/tips).

## Warranty

**The material contained in this document is provided “as is,” and is subject to being changed, without notice, in future editions. Further, to the maximum extent permitted by applicable law, Agilent disclaims all warranties, either express or implied, with regard to this manual and any information contained herein, including but not limited to the implied warranties of merchantability and fitness for a particular purpose. Agilent shall not be liable for errors or for incidental or consequential damages in connection with the furnishing, use, or performance of this document or of any information contained herein. Should Agilent and the user have a separate written agreement with warranty terms covering the material in this document that conflict with these terms, the warranty terms in the separate agreement shall control.**

## Technology Licenses

The hardware and/or software described in this document are furnished under a license and may be used or copied only in accordance with the terms of such license.

## Restricted Rights Legend

If software is for use in the performance of a U.S. Government prime contract or subcontract, Software is delivered and licensed as “Commercial computer software” as defined in DFAR 252.227-7014 (June 1995), or as a “commercial item” as defined in FAR 2.101(a) or as “Restricted computer software” as defined in FAR 52.227-19 (June 1987) or any equivalent agency regulation or contract clause. Use, duplication or disclosure of Software is subject to Agilent Technologies’ standard commercial license terms, and non-DOD Departments and Agencies of the U.S. Government will receive no greater than Restricted Rights as defined in FAR 52.227-19(c)(1-2) (June 1987). U.S. Government users will receive no greater than Limited Rights as defined in FAR 52.227-14 (June 1987) or DFAR 252.227-7015 (b)(2) (November 1995), as applicable in any technical data.

## Safety Notices

The following safety precautions should be

### CAUTION

A **CAUTION** notice denotes a hazard. It calls attention to an operating procedure, practice, or the like that, if not correctly performed or adhered to, could result in damage to the product or loss of important data. Do not proceed beyond a **CAUTION** notice until the indicated conditions are fully understood and met.

### WARNING

A **WARNING** notice denotes a hazard. It calls attention to an operating procedure, practice, or the like that, if not correctly performed or adhered to, could result in personal injury or death. Do not proceed beyond a **WARNING** notice until the indicated conditions are fully understood and met.

## Specification notes

**Specifications (warranted performance):** Specifications describe the configuration or instrument's warranted performance.

---

**NOTE:** Accuracy specifications are based on operation at 23°C ±5°C and between 5% and 70% RH. Refer to the product specifications for derating factors outside these ranges. Air-conditioned environments are highly recommended.

---

**Nominal data (mean or expected value):** "Nominal" values indicate expected performance, or describe product performance that is useful in the application of the product, but is not covered by product warranty.

## V2891A Upconverter Output Performance <sup>1, 2, 3, 4</sup>

Parameter	Nominal
<b>Waveform 1 – 40MHz WLAN, 802.11n</b>	
EVM	-41 dB RMS EVM
<b>Waveform 2 – Single 18 MHz Offset Tone</b>	
Unwanted sideband suppression	-51 dBc
Carrier suppression	-68 dBc

<sup>1</sup> Performance data is nominal, which is the mean value of units tested at 25 degrees C.

<sup>2</sup> The Agilent V2891A Upconverter is optimized for each specific waveform type.

<sup>3</sup> Tested using a calibrated vector source and the Agilent V2820A as a vector receiver.

<sup>4</sup> Test setup is with 1 V peak differential signal.

## V2891A Baseband Section (I and Q)

Parameter	Nominal
<b>Input Ports <sup>1</sup></b>	
A & B (I & Q) Inputs	± 2.0 Vp Max
<b>Input Port Impedance</b>	
Impedance high	100 kΩ
Impedance low	50 Ω
<b>Output Level</b>	
Differential output	Unity gain with differential termination of 100 Ω
<b>Output Port Impedance</b>	
I&Q differential outputs	100 Ω
<b>Offset Adjustment</b>	
Output offset adjustment range	± 3.5 VDC + AC waveform maximum
<b>Small Signal Bandwidth</b>	
-0.1dB, 0.2 V peak-peak	130 MHz
<b>Input and Output Connectors</b>	SMB

<sup>1</sup> Absolute maximum input is +/- 5 VDC + AC on any input pin.

### V2891A Upconversion Modulator Parameters

Parameter	Nominal
<b>Modulator Gain Ranging</b> <sup>1</sup>	
Input voltage for full modulation (differential)	0.24 to 1.5 Vp
Attenuator	127 Steps
Attenuator step size	0.125 dB
Attenuator range	0 to 15.875 dB
Input offset adjustment range	± 4.095 Volts
<b>Input Port Impedance</b>	
Impedance high	100 kΩ
Impedance low	50 Ω
<b>Input Connectors</b>	SMB

<sup>1</sup> Absolute maximum input is ± 5VDC + AC on any input pin.

### V2891A RF Output Parameters

Parameter	Nominal
Carrier frequency <sup>1</sup>	622.10 MHz (tolerance and drift depends on 10 MHz reference)
Maximum RF output power	9 dBm CW maximum
Output impedance	50 Ω, AC coupled
Return Loss @ 622.1 MHz	16 dB
Connector type	SMA

<sup>1</sup> A low-noise, precision frequency reference input is required for operation and maximum performance.

### V2891A External Reference Input Parameters

Parameter	Nominal
<b>External Reference Input</b> <sup>1</sup>	
Input frequency	10.0 MHz
Input impedance	50 Ω, AC Coupled
Input signal level	-3 dBm to +10 dBm
Connector type	SMB

<sup>1</sup> A low-noise, precision frequency reference input is required for operation and maximum performance.

## V2891A General Specifications

Parameter	Specification										
EMC compliance	<ul style="list-style-type: none"> <li>▪ Complies with European EMC Directive 2004/108/EC</li> <li>▪ IEC/EN 61326-1 or IEC/EN 61326-2-1</li> <li>▪ CISPR Pub 11 Group 1, class A</li> <li>▪ AS/NZS CISPR 11</li> <li>▪ ICES/NMB-001: This ISM device complies with Canadian ICES-001. (Cet appareil ISM est conforme a la norme NMB du Canada.)</li> </ul>										
Acoustic compliance	<ul style="list-style-type: none"> <li>▪ This instrument is in conformance with the German Regulation on Noise Declaration for Machines (Laermangabe nach der Maschinenlaermverordnung - 3.GSGV Deutschland):</li> </ul> <table border="1" style="margin-left: 40px; border-collapse: collapse;"> <thead> <tr> <th style="text-align: left;">Acoustic noise emission</th> <th style="text-align: left;">Geraeuschemission</th> </tr> </thead> <tbody> <tr> <td>LpA &lt; 70 dB</td> <td>LpA &lt; 70 dB</td> </tr> <tr> <td>Operator position</td> <td>Am Arbeitsplatz</td> </tr> <tr> <td>Normal position</td> <td>Normaler Betrieb</td> </tr> <tr> <td>Per ISO 7779</td> <td>Nach DIN 45635 t.19</td> </tr> </tbody> </table>	Acoustic noise emission	Geraeuschemission	LpA < 70 dB	LpA < 70 dB	Operator position	Am Arbeitsplatz	Normal position	Normaler Betrieb	Per ISO 7779	Nach DIN 45635 t.19
Acoustic noise emission	Geraeuschemission										
LpA < 70 dB	LpA < 70 dB										
Operator position	Am Arbeitsplatz										
Normal position	Normaler Betrieb										
Per ISO 7779	Nach DIN 45635 t.19										
Power requirements (use the supplied AC/DC converter)	100 to 240 VAC; 50 to 60 Hz ; 10 VA max										
Calibration	2 year										
Interface	USB 2.0 full speed compatible, USB "B-style" connector										
Environment (for indoor use only)	<ul style="list-style-type: none"> <li>▪ 18°C to 28°C specified operating, unless otherwise noted</li> <li>▪ 0°C to 50°C operating range</li> <li>▪ -25°C to 65°C. non-operating (AC power off) storage</li> <li>▪ Altitude: 2000 meters above sea level maximum specified operating</li> <li>▪ Cooling: Convection</li> </ul>										
Mechanical vibration and shock	MIL-PRF-28800F CL3 random vibration, 3 axes										
General mechanical information	<ul style="list-style-type: none"> <li>▪ Height: 58 mm (2.3 inches)</li> <li>▪ Width: 130 mm (5.1 inches)</li> <li>▪ Depth: 185 mm (7.3 inches)</li> <li>▪ Weight: 1 kg (2.2 lb)</li> </ul>										
Warranty	1 year										

Specifications are subject to change without notice.