

S E R V I C E N O T E

SUPERSEDES: NONE

6627A Multiple Output System DC Power Supply

Serial Numbers: 0000A00000 / 3151A00820

Replacement of AC input module with new design requires replacement of associated cables.**Duplicate Service Notes:**

6621A-07
 6622A-05
 6623A-09
 6624A-07
 6625A-03
 6626A-03
 6627A-01
 6628A-03
 6629A-03

To Be Performed By: Agilent-Qualified Personnel**Parts Required:**

Part No.	Description
9135-0419	Line module
5060-3441	Cable assembly
5060-3442	Cable assembly
5060-3443	Cable assembly

Continued

DATE: 06 June 1994

ADMINISTRATIVE INFORMATION

SERVICE NOTE CLASSIFICATION:

INFORMATION ONLY

AUTHOR:

DF

ENTITY:

2100

ADDITIONAL INFORMATION:

Situation:

The AC input module, 9135-0306, has been replaced with a new design and the new part is incompatible with the old cables.

Solution/Action:

When replacing the line module also replace the three cables, W2, W3 and W4, to the module. Capacitor, CO (0.22uF 250V) is built into the new module so the external cap is not used. The unit should be tested to insure proper operation at the four line voltage options.