

Test Equipment Solutions Datasheet

Test Equipment Solutions Ltd specialise in the second user sale, rental and distribution of quality test & measurement (T&M) equipment. We stock all major equipment types such as spectrum analyzers, signal generators, oscilloscopes, power meters, logic analysers etc from all the major suppliers such as Agilent, Tektronix, Anritsu and Rohde & Schwarz.

We are focused at the professional end of the marketplace, primarily working with customers for whom high performance, quality and service are key, whilst realising the cost savings that second user equipment offers. As such, we fully test & refurbish equipment in our in-house, traceable Lab. Items are supplied with manuals, accessories and typically a full no-quibble 2 year warranty. Our staff have extensive backgrounds in T&M, totalling over 150 years of combined experience, which enables us to deliver industry-leading service and support. We endeavour to be customer focused in every way right down to the detail, such as offering free delivery on sales, covering the cost of warranty returns BOTH ways (plus supplying a loan unit, if available) and supplying a free business tool with every order.

As well as the headline benefit of cost saving, second user offers shorter lead times, higher reliability and multivendor solutions. Rental, of course, is ideal for shorter term needs and offers fast delivery, flexibility, try-before-you-buy, zero capital expenditure, lower risk and off balance sheet accounting. Both second user and rental improve the key business measure of Return On Capital Employed.

We are based near Heathrow Airport in the UK from where we supply test equipment worldwide. Our facility incorporates Sales, Support, Admin, Logistics and our own in-house Lab.

All products supplied by Test Equipment Solutions include:

- No-quibble parts & labour warranty (we provide transport for UK mainland addresses).
- Free loan equipment during warranty repair, if available.
- Full electrical, mechanical and safety refurbishment in our in-house Lab.
- Certificate of Conformance (calibration available on request).
- Manuals and accessories required for normal operation.
- Free insured delivery to your UK mainland address (sales).
- Support from our team of seasoned Test & Measurement engineers.
- ISO9001 quality assurance.

Test equipment Solutions Ltd
Unit 8 Elder Way
Waterside Drive
Langley
Berkshire
SL3 6EP

T: +44 (0)1753 596000
F: +44 (0)1753 596001

Email: info@TestEquipmentHQ.com
Web: www.TestEquipmentHQ.com





HP 8991A



HP 84815A

HP 84814A

HP 84813A

HP 84812A



HP 8990A and HP 8991A Peak Power Analyzers and HP 8992A Digital Video Power Analyzer

Complete Pulse Power Characterization

The HP 8990A and HP 8991A peak power analyzers provide complete and accurate characterization of today's complex pulsed signals. They are capable of performing seven automatic timing measurements (rise time, fall time, pulse width, PRI, PRF, duty cycle, and delay) and five automatic power measurements (peak power, average power, pulse top/base amplitude, and overshoot) with pushbutton ease. Front-panel operation is intuitive and straightforward. Data entries can be typed in or made with the front-panel knob; automatic measurements are made with simple keystrokes.

The HP 8990A and 8991A offer two sensor channels plus two external triggering/oscilloscope channels, allowing the simultaneous measurement of modulating signals and detected power envelopes. Powerful measurement and display routines put you in control of your most demanding pulse applications. Measurement statistics, high-speed/high-sensitivity triggering, amplitude and time markers, dual-timebase windowing, measurement limit test, waveform storage, and waveform math are some of the new capabilities featured in the HP 8990A and 8991A.

The HP 8990A is optimized for linear display applications, and better rise/fall times than the HP 8991A. The HP 8991A is optimized for log display applications, providing higher resolution power measurements and improved power accuracy (when used with the HP 84815A sensor) than the HP 8990A. In addition, the HP 8991A is priced significantly less than the HP 8990A.

The peak power analyzers are compatible with the HP 84812/13A/14A/15A peak power sensors. These sensors give you outstanding measurement accuracy in demanding situations and include automatic temperature sensing and correction. The HP 8992 digital video power analyzer is very important for digital transmission applications. The HP 8992A's ability to characterize random peak power events make it possible to monitor receiver headroom and digital modulation quality.

HP 8990A, 8991A, and 8992A Specifications

Sensor Inputs (Channels 1 and 4)

Frequency Range: 20 MHz to 40 GHz, sensor dependent

	HP 8990A			HP 8991A/92A		
Power measurement range	-32 to +20 dBm			-33 to +20 dBm		
Rise/fall time	Power dBm	Video BW	Tr/Tf	Video BW	Tr/Tf	
	0 to +20	150 MHz	<5 ns	High	<10 ns	
	-16 to 0	150 MHz	<6 ns	Low	<1 μs	
	-26 to -16	500 kHz	<1 μs	CW	<100 μs	
	-32 to -26	8 kHz	<80 μs			
(Note: Rise/fall times limited to <45 ns with HP 84815 sensor)						
Instrumentation uncertainty (including noise and offset)	±(3.5% + (0.07 μW/signal power) x 100%)			±(0.07+1/(signal power in dBm+26)) dB (high bandwidth) ±(0.07+1.3/(signal power in dBm + 33)) dB (low, CW bandwidth) ±0.07 dB, -15 to +20 dBm (using HP 84815A sensor and 50 MHz, 0 dBm reference source)		

Max. Pulse Repetition Rate: 100 MHz externally triggered, 1 MHz internally triggered

Video Inputs (Channels 2 and 3)

Bandwidth: dc-coupled: dc to 100 MHz (repetitive); dc to 1 MHz (single shot). ac-coupled: 10 Hz to 100 MHz (repetitive); 10 Hz to 1 MHz (single shot).

Rise Time: <5 ns (HP 8990A) <10 ns (HP 8991A)

Vertical Sensitivity: 100 mV/div to 500 mV/div

Vertical Gain Accuracy: ±1.5%

Available Offset Range: ±20 Vdc, ±10 Vac

Time Base

Range: 2 ns/div to 5 s/div in 1-2-5 sequence

Resolution: 100 ps

Accuracy: 0.005%

General Characteristics

Power Requirements: Voltage: 90 to 132 or 198 to 264 Vac;

48 to 66 Hz. Power: 250 VA max

HP-IB Codes: SH1, AH1, T5, L4, SR1, RL1, PP1, DC1, DT1, C0, E2

Size: 422 mm W x 194 mm H x 366 mm D (16.62 in x 7.65 in x 14.4 in)

Weight: Net, 12.8 kg (28 lb); shipping, 20.1 kg (44 lb)

HP 84812A/13A/14A/15A Specifications:

Frequency Range: HP 84812A: 500 MHz to 18 GHz

HP 84813A: 500 MHz to 26.5 GHz

HP 84814A: 500 MHz to 40 GHz

HP 84815A: 20 MHz to 18 GHz

Power Range: See table

Sensor Input SWR (reflection coefficient):

50 MHz to 18 GHz: 1.25 (0.11)

6 to 18 GHz: 1.30 (0.13) (HP 84815A only)

18 GHz to 26.5 GHz: 1.35 (0.15)

26.5 GHz to 40 GHz: 1.60 (0.23)

Sensor Calibration Uncertainty:

Frequency	RSS uncertainty
< 4 GHz	±3.6%
<12 GHz	±3.8%
<18 GHz	±4.3%
<26.5 GHz	±5.5%
<40 GHz	±6.5%

Connector Type: HP 84812A, HP 84815A: Type-N (m)

HP 84813A: APC-3.5 mm (m)

HP 84814A: 2.4 mm (m)

General Characteristics

Size: HP 84812A, HP 84815A: 37 mm W x 27 mm H x 137 mm D

(1.45 in x 1.05 in x 5.4 in)

HP 84813A, HP 84814A: 37 mm W x 27 mm H x 127 mm D

(1.45 in x 1.05 in x 5.0 in)

Weight: Net, 0.29 kg (0.64 lb); shipping, 0.64 kg (1.4 lb)

Ordering Information

HP 8990A Peak Power Analyzer

Opt 001 Deletes Channel 4

Opt W30 Extended Repair Service (see page 592)

HP 8991A Peak Power Analyzer

HP 8992A Digital Video Power Analyzer

Opt 001 Deletes Channel 4

Opt W30 Extended Repair Service

HP 84812A Peak Power Sensor

Opt W30 Extended Repair Service (see page 592)

HP 84813A Peak Power Sensor

Opt W30 Extended Repair Service (see page 592)

HP 84814A Peak Power Sensor

Opt W30 Extended Repair Service (see page 592)

HP 84815A Peak Power Sensor

Opt W30 Extended Repair Service (see page 592)

To have a Hewlett-Packard representative help you place an order or to get more information see inside back cover