

Programming Compatibility Guide

Agilent Technologies E4428C/38C ESG Signal Generators

This guide applies to the following signal generator models:

E4428C ESG Analog Signal Generator

E4438C ESG Vector Signal Generator

Due to our continuing efforts to improve our products through firmware and hardware revisions, signal generator design and operation may vary from descriptions in this guide. We recommend that you use the latest revision of this guide to ensure you have up-to-date product information. Compare the print date of this guide (see bottom of page) with the latest revision, which can be downloaded from the following website:

<http://www.agilent.com/find/esg>



Manufacturing Part Number: E4400-90543

Printed in USA

March 2005

© Copyright 2002-2005 Agilent Technologies, Inc.

Notice

The material contained in this document is provided “as is”, and is subject to being changed, without notice, in future editions.

Further, to the maximum extent permitted by applicable law, Agilent disclaims all warranties, either express or implied with regard to this manual and to any of the Agilent products to which it pertains, including but not limited to the implied warranties of merchantability and fitness for a particular purpose. Agilent shall not be liable for errors or for incidental or consequential damages in connection with the furnishing, use, or performance of this document or any of the Agilent products to which it pertains. Should Agilent have a written contract with the User and should any of the contract terms conflict with these terms, the contract terms shall control.

Questions or Comments about our Documentation?

We welcome any questions or comments you may have about our documentation. Please send us an E-mail at sources_manuals@am.exch.agilent.com.

1. Overview	1
Inside This Guide	2
Changing the Signal Generator Identification String	3
:SYSTem:IDN	3
Functional E4428C/38C SCPI Commands While in a Compatible Language Mode	4
:SYSTem:LANGuage	4
:SYSTem:ERRor[:NEXT]	5
2. E4428C/38C SCPI Commands	7
Memory Subsystem (:MEMORY)	8
:DATA:PRAM	8
:DATA:PRAM:BLOCk	8
:DATA:PRAM:LIST	8
Digital Modulation Subsystem (:SOURce)	9
:DM:IQADjustment:SKEW	9
3. ESG E44xxB Commands	11
System Function Commands	12
IEEE Common Commands	12
Calibration Subsystem	12
Communication Subsystem	13
Diagnostic Subsystem	13
Display Subsystem	14
Memory Subsystem	14
Output Subsystem	18
Route Subsystem	18
Status Subsystem	19
System Subsystem	21
Trigger Subsystem	22
Unit Subsystem	23
Analog Function Commands	24
Amplitude Modulation Subsystem	24
Frequency Subsystem	25
Frequency Modulation Subsystem	26
List/Sweep Subsystem	26
Low Frequency Subsystem	28
Phase Modulation Subsystem	28
Power Subsystem	29

Contents

Pulse Modulation Subsystem	31
Digital Function Commands	32
AWGN Subsystem	32
Bluetooth Subsystem	32
Calculate Subsystem	34
CDMA ARB Subsystem	35
CDMA2000 ARB Subsystem	37
CDMA2000 BBG Subsystem	40
Custom Subsystem	51
Data Subsystem	53
Digital Modulation Subsystem	54
Dmodulation Subsystem	55
DECT Subsystem	57
Dual ARB Subsystem	64
EDGE Subsystem	66
GSM Subsystem	70
Input Subsystem	75
Measure Subsystem	75
Multi-Tone Subsystem	76
NADC Subsystem	77
PDC Subsystem	81
PHS Subsystem	85
Sense Subsystem	89
TETRA Subsystem	94
Wideband CDMA ARB Subsystem	99
Wideband CDMA BBG Subsystem	103
4. 8648A/B/C/D Commands	113
System Function Commands	114
IEEE Common Commands	114
Status Subsystem	114
System Subsystem	115
Analog Function Commands	116
Amplitude Subsystem	116
Frequency Subsystem	116
Amplitude Modulation Subsystem	117
Frequency Modulation Subsystem	117
Phase Modulation Subsystem	118

Pulse Modulation Subsystem	119
5. 8656B, 8657A/B/D/J Programming Codes	123
Programming Codes	124
Compatible Codes	124
Non-Compatible Codes	127
Command Mapping	128
P0 (Digital Modulation Off)	128
P4 (Digital Modulation On)—E4438C	129
PF (Pulse Modulation-Fast Mode) or PM (Pulse Modulation)	129
S1, S2, or S3 used with AM	129
S1, S2, or S3 used with FM	130
S4 (Modulation Source Off)	131
S5 (DC FM)	132

Contents

1 Overview

Inside This Guide

This guide provides a comprehensive listing of SCPI commands and programming codes for signal generator models that are supported by the E4428C/38C. The following list shows the supported models along with the language type for each one:

E4428C/38C	SCPI commands
E44xxB	SCPI commands
8648A/B/C/D	SCPI commands
8656B	programming codes
8657A/B/D/J	programming codes

These commands and programming codes are separated into compatible and non-compatible sections. In most instances, the non-compatible section has the least number of commands/codes, thus providing a more time-efficient way of determining whether or not a command/code is supported by the E4428C/38C.

In some cases, SCPI commands are only partially supported. This usually occurs due to a variance in parameters between the E4428C/38C and other signal generator models. When this condition occurs, the SCPI command will appear in both the compatible and non-compatible sections showing the exact SCPI command syntax that is supported and unsupported.

In addition to providing the compatible command/code listing, this guide also provides you with E4428C/38C SCPI commands that lets you change the signal generator identification output (see “[:SYSTem:IDN](#)” on page 3), select a compatible programming language (see “[:SYSTem:LANGuage](#)” on page 4), and query the signal generator for errors (see “[:SYSTem:ERRor\[:NEXT\]](#)” on page 5).

Changing the Signal Generator Identification String

:SYSTem:IDN

Supported All

```
:SYSTem: IDN "<string>"
```

This ESG signal generator command modifies the identification string that the *IDN? query returns. Sending an empty string returns the *IDN? query output to its factory shipped setting. The maximum string length is 72 characters.

Modification of the *IDN? query output enables the ESG signal generator to identify itself as another signal generator when it is used as a backward compatible replacement. This modification of the identification string does not affect the display diagnostic information, which is shown by pressing the **Diagnostic Info** softkey.

Functional E4428C/38C SCPI Commands While in a Compatible Language Mode

The commands in this section are used for configuring the signal generator compatible programming language and for isolating problems.

:SYSTem:LANGuage

Supported All

```
:SYSTem:LANGuage "SCPI" | "COMP" | "NADC" | "PDC" | "PHS" | "8648"  
:SYSTem:LANGuage?
```

This command sets the remote language for the signal generator.

The setting enabled by this command is not affected by signal generator power-on, preset, or *RST.

SCPI This choice provides compatibility for SCPI commands.

COMP This choice provides compatibility for the 8656B, 8657A/B signal generator which is supported only through a GPIB interface.

NADC This choice provides compatibility for the 8657D NADC personality which is supported only through a GPIB interface (E4438C only).

PDC This choice provides compatibility for the 8657D PDC personality which is supported only through a GPIB interface (E4438C only).

PHS This choice provides compatibility for the 8657J PHS personality which is supported only through a GPIB interface (E4438C only).

8648 This choice provides compatibility for the 8648A/B/C/D signal generator which is supported only through a GPIB interface.

Key Entry **SCPI** **8656B,8657A/B** **8657D NADC** **8657D PDC** **8657J PHS**
8648A/B/C/D

:SYSTem:ERRor[:NEXT]**Supported** All**:SYSTem:ERRor[:NEXT]?**

This query returns the most recent error message from the signal generator error queue. If there are no error messages, the query returns the following output:

```
+0, "No error"
```

When there is more than one error message, the query will need to be sent for each message. Each error message is erased after being queried.

Key Entry [Error Info](#) [View Next Error Message](#)

Overview

Functional E4428C/38C SCPI Commands While in a Compatible Language Mode

2 E4428C/38C SCPI Commands

This chapter contains commands that have either been replaced or deleted from the E4428C/38C SCPI Command Reference.

Memory Subsystem (:MEMORY)

:DATA:PRAM

Supported E4438C with Option 001/601 or 002/602

:MEMORY:DATA:PRAM

This query indicates whether or not user-defined pattern RAM (PRAM) data is in memory. This command is compatible only with the “[:DATA:PRAM:BLOCK](#)” or “[:DATA:PRAM:LIST](#)” commands.

***RST** 0

:DATA:PRAM:BLOCK

Supported E4438C with Option 001/601 or 002/602

:MEMORY:DATA:PRAM:BLOCK <datablock>

This command downloads block-formatted data directly into pattern RAM (PRAM) memory.

Remarks This command was replaced by the DATA:PRAM:FILE:BLOCK command. Refer to the *ESG SCPI Command Reference* for more information.

:DATA:PRAM:LIST

Supported E4438C with Option 001/601 or 002/602

:MEMORY:DATA:PRAM:LIST <uint8>[,<uint8>,<...>]

This command downloads list-formatted data directly into pattern RAM (PRAM) memory.

<uint8> This variable is any of the valid 8-bit, unsigned integer values between 0 and 255.

[,<uint8>,<...>] This variable identifies the value of the second and subsequent 8-bit unsigned integer variables.

Range 0–255

Remarks This command was replaced by the DATA:PRAM:FILE:LIST command. Refer to the *ESG SCPI Command Reference* for more information.

Digital Modulation Subsystem (:SOURce)

:DM:IQADjustment:SKEW

Supported All

[:SOURce] :DM: IQADjustment:SKEW <val><unit>

[:SOURce] :DM: IQADjustment:SKEW?

This command changes the input skew to the I and Q paths. Equal and opposite skew is applied to both paths (RF Output path and I/Q output paths) simultaneously. A positive value delays the I signal relative to the Q signal, and a negative value delays the Q signal relative to the I signal.

If the internal I/Q correction path is set to RF or BB the I/Q signals are already optimized and adjusting I/Q skew would add an impairment to the signals. If the internal I/Q correction path is set to Off, then adjusting the I/Q skew could improve the I/Q signals. The I/Q skew adjustment cannot be performed on the MSK, FSK, and C4FM constant envelope modulations.

I/Q skew adjustments are preserved when the instrument state is saved. I/Q skew adjustment are also preserved when instrument settings are changed. If the signal generator is calibrated, the skew adjustments are added to the calibration value used for the given signal generator state. If the signal generator is uncalibrated, the skew adjustments re applied directly.

Using I/Q skew while playing a user FIR file greater than 32 symbols will generate an error.

The variable <val> is expressed in units of picoseconds or nanoseconds.

***RST** +0.0000000E+000

Range -5.0 to 5.0

Key Entry I/Q Skew

Remarks This command is no longer supported and has been replaced by:

[:SOURce] :DM: IQADjustment:SKEW[:DELay] <val>

E4428C/38C SCPI Commands
Digital Modulation Subsystem (:SOURce)

3 ESG E44xxB Commands

System Function Commands

IEEE Common Commands

Compatible Commands

```
*CLS  
*ESE <data>  
*ESE?  
*ESR?  
*IDN?  
*OPC  
*OPC?  
*RCL <reg_num>  
*RST  
*SAV <reg_num>  
*SRE <data>  
*SRE?  
*STB?  
*TRG  
*TST?  
*WAI
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Calibration Subsystem

Compatible Commands

```
:CALibration:DCFM  
:CALibration:IQ
```

```
:CALibration:IQ:DEFault
:CALibration:IQ:FULL
:CALibration:IQ:STARt <val>
:CALibration:IQ:STARt?
:CALibration:IQ:STOP <val>
:CALibration:IQ:STOP?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Communication Subsystem

Compatible Commands

```
:SYSTem:COMMUnicatE:GPIB:ADDReSS <number>
:SYSTem:COMMUnicatE:GPIB:ADDReSS?
:SYSTem:COMMUnicatE:SERial:BAUD <number>
:SYSTem:COMMUnicatE:SERial:BAUD?
:SYSTem:COMMUnicatE:SERial:ECHO ON|OFF
:SYSTem:COMMUnicatE:SERial:ECHO?
:SYSTem:COMMUnicatE:SERial:RESet
:SYSTem:COMMUnicatE:SERial:TOUT <val>
:SYSTem:COMMUnicatE:SERial:TOUT?
```

Non-Compatible Commands

```
:SYSTem:COMMUnicatE:SERial:CONTrol:RTS ON|OFF|IBFull|RFR
:SYSTem:COMMUnicatE:SERial:CONTrol:RTS?
```

Diagnostic Subsystem

Compatible Commands

```
:DIAGnostic[:CPU]:INFOrmation:BOARds?
:DIAGnostic[:CPU]:INFOrmation:CCOunt:ATTenuator?
:DIAGnostic[:CPU]:INFOrmation:CCOunt:PON?
:DIAGnostic[:CPU]:INFOrmation:CCOunt:PROTection?
```

ESG E44xxB Commands

System Function Commands

```
:DIAGnostic[:CPU]:INFOrmation:DISPlay:OTIMe?  
:DIAGnostic[:CPU]:INFOrmation:LIDN?  
:DIAGnostic[:CPU]:INFOrmation:OPTIONS?  
:DIAGnostic[:CPU]:INFOrmation:OPTIONS:DETail?  
:DIAGnostic[:CPU]:INFOrmation:OTIMe?  
:DIAGnostic[:CPU]:INFOrmation:SDATe?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Display Subsystem

Compatible Commands

```
:DISPlay:BRIGHTness <val>  
:DISPlay:BRIGHTness?  
  
:DISPlay:CONTRast <val>  
:DISPlay:CONTrast?  
  
:DISPlay:INVerse ON|OFF|1|0  
:DISPlay:INVerse?  
  
:DISPlay:REMote ON|OFF|1|0  
:DISPlay:REMote?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Memory Subsystem

Compatible Commands

```
:MEMory:CATalog:BINary?  
:MEMory:CATalog:BIT?  
:MEMory:CATalog:CDMa?  
:MEMory:CATalog:DMOD?  
:MEMory:CATalog:DWCdMa?
```

```
:MEMory:CATalog:FCDMa?  
:MEMory:CATalog:FIR?  
:MEMory:CATalog:FSK?  
:MEMory:CATalog:FWCDma?  
:MEMory:CATalog:IQ?  
:MEMory:CATalog:LIST?  
:MEMory:CATalog:MCDMa?  
:MEMory:CATalog:MDMod?  
:MEMory:CATalog:MDWCdma?  
:MEMory:CATalog:MFCdma?  
:MEMory:CATalog:MFWCdma?  
:MEMory:CATalog:MTONE?  
:MEMory:CATalog:RCDMa?  
:MEMory:CATalog:RWCDma?  
:MEMory:CATalog:SEQ?  
:MEMory:CATalog:SHAPe?  
:MEMory:CATalog:STATE?  
:MEMory:CATalog:UWCDma?  
:MEMory:CATalog:WCDMa?  
:MEMory:CATalog[:ALL]?  
:MEMory:COPY[:NAME] "<file name>","<file name>"  
:MEMory:DATA "<file name>,<.datablock>  
:MEMory:DATA? "<file name>"  
:MEMory:DATA:BIT "<file name>,<bit_count>,<.datablock>  
:MEMory:DATA:BIT? "<file name>"  
:MEMory:DATA:FIR "<file name>,"osr,coefficient{,coefficient}  
:MEMory:DATA:FIR? "<file name>"  
:MEMory:DATA:FSK "<file name>,<num_states>,<f0>,<f1>,...<f(n)>[<diff_state>,<num_diff_states>,<diff0>,<diff1>,...<diff(n)>]
```

ESG E44xxB Commands

System Function Commands

```
:MEMORY:DATA:FSK? "<file name>"  
:MEMORY:DATA:IQ "<file name>,<offsetQ>,<num_states>,<i0>,<q0>,<i1>,<q1>,...<i(n),q(n)>[,<diff_state>,<num_diff_states>,<diff0>,<diff1>,...<diff(n)>]  
:MEMORY:DATA:IQ? "<file name>"  
:MEMORY:DATA:PRAM?  
:MEMORY:DATA:PRAM:BLOCK <datablock>  
:MEMORY:DATA:PRAM:LIST <uint8>{,<uint8>,<...>}  
:MEMORY:DATA:SHAPE "<file name>,<num_rise_points>,<rp0>,<rp1>,...<rp(n)>,<num_fall_points>,<fp0>,<fp1>,...<fp(n)>  
:MEMORY:DATA:SHAPE? "<file name>"  
:MEMORY:DELETE:ALL  
:MEMORY:DELETE:BINary  
:MEMORY:DELETE:BIT  
:MEMORY:DELETE:CDMa  
:MEMORY:DELETE:DMOD  
:MEMORY:DELETE:DWCDma  
:MEMORY:DELETE:FCDMa  
:MEMORY:DELETE:FIR  
:MEMORY:DELETE:FSK  
:MEMORY:DELETE:FWCDma  
:MEMORY:DELETE:IQ  
:MEMORY:DELETE:LIST  
:MEMORY:DELETE:MCDMa  
:MEMORY:DELETE:MDMod  
:MEMORY:DELETE:MDWCdma  
:MEMORY:DELETE:MFCdma  
:MEMORY:DELETE:MFWCdma  
:MEMORY:DELETE:MTONE
```

```
:MEMory:DELetE:RCDMa
:MEMory:DELetE:RWCDma
:MEMory:DELetE:SEQ
:MEMory:DELetE:SHAPE
:MEMory:DELetE:STATE
:MEMory:DELetE:UWCDma
:MEMory:DELetE:WCDma
:MEMory:DELetE[:NAME] "<file name>"?
:MEMory:FREE[:ALL]?
:MEMory:LOAD:LIST "<file name>"?
:MEMory:MOVE <src_file>,<dest_file>
:MEMory:STATE:COMMent <reg_num>,<seq_num>,"<comment>"?
:MEMory:STATE:COMMent? <reg_num>,<seq_num>?
:MEMory:STORe:LIST "<file name>"?
:MMEMory:CATalog? "<msus>"?
:MMEMory:COPY "<file name>","<file name>"?
:MMEMory:DATA "<file name>",<datablock>
:MMEMory:DATA? "<file name>"?
:MMEMory:DELetE[:NAME] "<file name>,[ "<msus>" ]
:MMEMory:LOAD:ARB:ALL
:MMEMory:LOAD:LIST "<file name>"?
:MMEMory:MOVE <src_file>,<dest_file>
:MMEMory:STORe:ARB:ALL
:MMEMory:STORe:LIST "<file name>"?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Output Subsystem

Compatible Commands

```
:OUTPut:MODulation[:STATe] ON|OFF|1|0
:OUTPut:MODulation[:STATe]?
:OUTPut:PROTection:CLEar
:OUTPut:PROTection:TRIPped?
:OUTPut[:STATe] ON|OFF|1|0
:OUTPut[:STATe]?
```

Non-Compatible Commands

```
:OUTPut:PROTection:MODE "NORMAL"|"8648"
:OUTPut:PROTection:MODE?
```

Route Subsystem

Compatible Commands

```
:ROUTe:HARDware:DGENerator:INPut:BPOLarity POSitive|NEGative
:ROUTe:HARDware:DGENerator:INPut:BPOLarity?
:ROUTe:HARDware:DGENerator:INPut:CPOLarity POSitive|NEGative
:ROUTe:HARDware:DGENerator:INPut:CPOLarity?
:ROUTe:HARDware:DGENerator:INPut:DPOLarity POSitive|NEGative
:ROUTe:HARDware:DGENerator:INPut:DPOLarity?
:ROUTe:HARDware:DGENerator:INPut:SPOLarity POSitive|NEGative
:ROUTe:HARDware:DGENerator:INPut:SPOLarity?
:ROUTe:HARDware:DGENerator:INPut:TPOLarity POSitive|NEGative
:ROUTe:HARDware:DGENerator:INPut:TPOLarity?
:ROUTe:HARDware:DGENerator:IPOLarity:BGATe POSitive|NEGative
:ROUTe:HARDware:DGENerator:IPOLarity:BGATe?
:ROUTe:HARDware:DGENerator:IPOLarity:CLOCK POSitive|NEGative
:ROUTe:HARDware:DGENerator:IPOLarity:CLOCK?
:ROUTe:HARDware:DGENerator:IPOLarity:DATA POSitive|NEGative
:ROUTe:HARDware:DGENerator:IPOLarity:DATA?
:ROUTe:HARDware:DGENerator:IPOLarity:SSYNC POSitive|NEGative
```

```
:ROUTE:HARDware:DGENerator:IPOLarity:SSYNC?  
:ROUTE:HARDware:DGENerator:IPOLarity:TRIGger POSitive|NEGative  
:ROUTE:HARDware:DGENerator:IPOLarity:TRIGger?  
  
:ROUTE:HARDware:DGENerator:OPOLarity:CLOCK POSitive|NEGative  
:ROUTE:HARDware:DGENerator:OPOLarity:CLOCK?  
  
:ROUTE:HARDware:DGENerator:OPOLarity:DATA POSitive|NEGative  
:ROUTE:HARDware:DGENerator:OPOLarity:DATA?  
  
:ROUTE:HARDware:DGENerator:OPOLarity:EVENT[1]|2|3|4 POSitive|NEGative  
:ROUTE:HARDware:DGENerator:OPOLarity:EVENT[1]|2|3|4?  
  
:ROUTE:HARDware:DGENerator:OPOLarity:SSYNC POSitive|NEGative  
:ROUTE:HARDware:DGENerator:OPOLarity:SSYNC?  
  
:ROUTE:HARDware:DGENerator:OUTPut:CPOLarity POSitive|NEGative  
:ROUTE:HARDware:DGENerator:OUTPut:CPOLarity?  
  
:ROUTE:HARDware:DGENerator:OUTPut:DCS[:STATE] ON|OFF|1|0  
:ROUTE:HARDware:DGENerator:OUTPut:DCS[:STATE]?  
  
:ROUTE:HARDware:DGENerator:OUTPut:DPOLarity POSitive|NEGative  
:ROUTE:HARDware:DGENerator:OUTPut:DPOLarity?  
  
:ROUTE:HARDware:DGENerator:OUTPut:EPOL[1]|2|3|4 POSitive|NEGative  
:ROUTE:HARDware:DGENerator:OUTPut:EPOL[1]|2|3|4?  
  
:ROUTE:HARDware:DGENerator:OUTPut:SPOLarity POSitive|NEGative  
:ROUTE:HARDware:DGENerator:OUTPut:SPOLarity?
```

Non-Compatible Commands

```
:ROUTE:HARDware:DGENerator:OPOLarity:EVEN[1]|2 POSitive|NEGative  
:ROUTE:HARDware:DGENerator:OPOLarity:EVEN[1]|2?  
  
:ROUTE:HARDware:DGENerator:OUTPut:EPOL[1]|2 POSitive|NEGative  
:ROUTE:HARDware:DGENerator:OUTPut:EPOL[1]|2?
```

Status Subsystem

Compatible Commands

```
:STATus:OPERation:CONDITION?  
:STATus:OPERation:ENABLE <val>  
:STATus:OPERation:ENABLE?
```

System Function Commands

```
:STATUs:OPERation:NTRansition <val>
:STATUs:OPERation:NTRansition?

:STATUs:OPERation:PTRansition <val>
:STATUs:OPERation:PTRansition?

:STATUs:OPERation[:EVENT]?

:STATUs:PRESet

:STATUs:QUEStionable:BERT:CONDITION?

:STATUs:QUEStionable:BERT:ENABLE <val>
:STATUs:QUEStionable:BERT:ENABLE?

:STATUs:QUEStionable:BERT:NTRansition <val>
:STATUs:QUEStionable:BERT:NTRansition?

:STATUs:QUEStionable:BERT:PTRansition <val>
:STATUs:QUEStionable:BERT:PTRansition?

:STATUs:QUEStionable:BERT[:EVENT]?

:STATUs:QUEStionable:CALibration:CONDITION?

:STATUs:QUEStionable:CALibration:ENABLE <val>
:STATUs:QUEStionable:CALibration:ENABLE?

:STATUs:QUEStionable:CALibration:NTRansition <val>
:STATUs:QUEStionable:CALibration:NTRansition?

:STATUs:QUEStionable:CALibration:PTRansition <val>
:STATUs:QUEStionable:CALibration:PTRansition?

:STATUs:QUEStionable:CALibration[:EVENT]?

:STATUs:QUEStionable:CONDITION?

:STATUs:QUEStionable:ENABLE <val>
:STATUs:QUEStionable:ENABLE?

:STATUs:QUEStionable:FREQuency:CONDITION?

:STATUs:QUEStionable:FREQuency:ENABLE <val>
:STATUs:QUEStionable:FREQuency:ENABLE?

:STATUs:QUEStionable:FREQuency:NTRansition <val>
:STATUs:QUEStionable:FREQuency:NTRansition?

:STATUs:QUEStionable:FREQuency:PTRansition <val>
:STATUs:QUEStionable:FREQuency:PTRansition?
```

```
:STATus:QUESTIONable:FREQuency[:EVENT]?
:STATus:QUESTIONable:MODulation:CONDITION?
:STATus:QUESTIONable:MODulation:ENABLE <val>
:STATus:QUESTIONable:MODulation:ENABLE?
:STATus:QUESTIONable:MODulation:NTRansition <val>
:STATus:QUESTIONable:MODulation:NTRansition?
:STATus:QUESTIONable:MODulation:PTRansition <val>
:STATus:QUESTIONable:MODulation:PTRansition?
:STATus:QUESTIONable:MODulation[:EVENT]?
:STATus:QUESTIONable:NTRansition <val>
:STATus:QUESTIONable:NTRansition?
:STATus:QUESTIONable:POWeR:CONDITION?
:STATus:QUESTIONable:POWeR:ENABLE <val>
:STATus:QUESTIONable:POWeR:ENABLE?
:STATus:QUESTIONable:POWeR:NTRansition <val>
:STATus:QUESTIONable:POWeR:NTRansition?
:STATus:QUESTIONable:POWeR:PTRansition <val>
:STATus:QUESTIONable:POWeR:PTRansition?
:STATus:QUESTIONable:POWeR[:EVENT]?
:STATus:QUESTIONable:PTRansition <val>
:STATus:QUESTIONable:PTRansition?
:STATus:QUESTIONable[:EVENT]?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

System Subsystem

Compatible Commands

```
:SYSTem:CAPability?
:SYSTem:ERRor[:NEXT]?
:SYSTem:HELP:MODE SINGLE|CONTinuous
:SYSTem:HELP:MODE?
```

ESG E44xxB Commands

System Function Commands

```
:SYSTem:LANGuage "SCPI" | "COMP" | "NADC" | "PDC" | "PHS" | "8648"  
:SYSTem:LANGuage?  
  
:SYSTem:PON:TYPE PRESet|LAST  
:SYSTem:PON:TYPE?  
  
:SYSTem:PRESet  
  
:SYSTem:PRESet:ALL  
  
:SYSTem:PRESet:LANGuage "SCPI" | "COMP" | "NADC" | "PDC" | "PHS" | "8648"  
:SYSTem:PRESet:LANGuage?  
  
:SYSTem:PRESet:PERsistent  
  
:SYSTem:PRESet:PN9 NORMAL|QUICK  
:SYSTem:PRESet:PN9?  
  
:SYSTem:PRESet:TYPE NORMAL|USER  
:SYSTem:PRESet:TYPE?  
  
:SYSTem:PRESet[:USER]:SAVE  
  
:SYSTem:SSAver:DElay <val>  
:SYSTem:SSAver:DElay?  
  
:SYSTem:SSAver:MODE LIGHT|TEXT  
:SYSTem:SSAver:MODE?  
  
:SYSTem:SSAver:STATE ON|OFF  
:SYSTem:SSAver:STATE?  
  
:SYSTem:VERSion?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Trigger Subsystem

Compatible Commands

```
:ABORT  
  
:INITiate:CONTinuous[:ALL] ON|OFF|1|0  
:INITiate:CONTinuous[:ALL]?  
  
:INITiate[:IMMediate][:ALL]  
  
:TRIGger:OUTPut:POLarity POSitive|NEGative
```

```
:TRIGger:OUTPut:POLarity?  
:TRIGger[:SEQUence]:SLOPe POSitive|NEGative  
:TRIGger[:SEQUence]:SLOPe?  
:TRIGger[:SEQUence]:SOURce BUS|IMMEDIATE|EXTernal|KEY  
:TRIGger[:SEQUence]:SOURce?  
:TRIGger[:SEQUence][:IMMEDIATE]
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Unit Subsystem

Compatible Commands

```
:UNIT:POWer DBM|DBUV|DBUVEMF|V|VEMF  
:UNIT:POWer?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Analog Function Commands

Amplitude Modulation Subsystem

Compatible Commands

```
[ :SOURce]:AM:WIDeband:STATE ON|OFF|1|0
[ :SOURce]:AM:WIDeband:STATE?

[ :SOURce]:AM[1]|2:EXTernal[1]|2:COUpling AC|DC
[ :SOURce]:AM[1]|2:EXTernal[1]|2:COUpling?

[ :SOURce]:AM[1]|2:INTernal[1]:FREQuency <val><unit>
[ :SOURce]:AM[1]|2:INTernal[1]:FREQuency?

[ :SOURce]:AM[1]|2:INTernal[1]:FREQuency:ALTerNate <val><unit>
[ :SOURce]:AM[1]|2:INTernal[1]:FREQuency:ALTerNate?

[ :SOURce]:AM[1]|2:INTernal[1]:FREQuency:ALTerNate:AMPLitude:
PERCent <val><unit>
[ :SOURce]:AM[1]|2:INTernal[1]:FREQuency:ALTerNate:AMPLitude:PERCent?

[ :SOURce]:AM[1]|2:INTernal[1]:FUNCTION:SHAPe <enum>
[ :SOURce]:AM[1]|2:INTernal[1]:FUNCTION:SHAPe?

[ :SOURce]:AM[1]|2:INTernal[1]:SWEep:TIME <val><unit>
[ :SOURce]:AM[1]|2:INTernal[1]:SWEep:TIME?

[ :SOURce]:AM[1]|2:INTernal[1]:SWEep:TRIGger <enum>
[ :SOURce]:AM[1]|2:INTernal[1]:SWEep:TRIGger?

[ :SOURce]:AM[1]|2:SOURce INT[1]|EXT1|EXT2
[ :SOURce]:AM[1]|2:SOURce?

[ :SOURce]:AM[1]|2:STATE ON|OFF|1|0
[ :SOURce]:AM[1]|2:STATE?

[ :SOURce]:AM[1]|2[:DEPTH] <val><unit>
[ :SOURce]:AM[1]|2[:DEPTH]?

[ :SOURce]:AM[1]|2[:DEPTH]:TRACK ON|OFF|1|0
[ :SOURce]:AM[1]|2[:DEPTH]:TRACK?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Frequency Subsystem

Compatible Commands

```
[ :SOURce ] :FREQuency:FIXed <val><unit>
[ :SOURce ] :FREQuency:FIXed?

[ :SOURce ] :FREQuency:MODE CW|FIXed|LIST
[ :SOURce ] :FREQuency:MODE?

[ :SOURce ] :FREQuency:MULTiplier <val>
[ :SOURce ] :FREQuency:MULTiplier?

[ :SOURce ] :FREQuency:OFFSet <val><unit>
[ :SOURce ] :FREQuency:OFFSet?

[ :SOURce ] :FREQuency:REFerence <val><unit>
[ :SOURce ] :FREQuency:REFerence?

[ :SOURce ] :FREQuency:REFerence:STATe ON|OFF|1|0
[ :SOURce ] :FREQuency:REFerence:STATe?

[ :SOURce ] :FREQuency:STARt <val><unit>
[ :SOURce ] :FREQuency:STARt?

[ :SOURce ] :FREQuency:STOP <val><unit>
[ :SOURce ] :FREQuency:STOP?

[ :SOURce ] :FREQuency:SYNthesis <val>
[ :SOURce ] :FREQuency:SYNthesis?

[ :SOURce ] :FREQuency[:CW] <val><unit>
[ :SOURce ] :FREQuency[:CW]?

[ :SOURce ] :PHASe:REFerence

[ :SOURce ] :PHASe[:ADJust] <val><unit>
[ :SOURce ] :PHASe[:ADJust]?

[ :SOURce ] :ROSCillator:SOURce?
[ :SOURce ] :ROSCillator:SOURce:AUTO ON|OFF|1|0
[ :SOURce ] :ROSCillator:SOURce:AUTO?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Frequency Modulation Subsystem

Compatible Commands

```
[ :SOURce]:FM[1]|2:EXTernal[1]|2:COUpling AC|DC
[:SOURce]:FM[1]|2:EXTernal[1]|2:COUpling?
[:SOURce]:FM[1]|2:INTernal[1]:FREQuency <val><unit>
[:SOURce]:FM[1]|2:INTernal[1]:FREQuency?
[:SOURce]:FM[1]|2:INTernal[1]:FREQuency:ALTerNate <val><unit>
[:SOURce]:FM[1]|2:INTernal[1]:FREQuency:ALTerNate?
[:SOURce]:FM[1]|2:INTernal[1]:FREQuency:ALTerNate:AMPLitude:
PERCent <val><unit>
[:SOURce]:FM[1]|2:INTernal[1]:FREQuency:ALTerNate:AMPLitude:PERCent?
[:SOURce]:FM[1]|2:INTernal[1]:FUNCTION:SHAPe SINE|TRIangle|SQUare|RAMP|
NOISE|DUALsine|SWEPtsine
[:SOURce]:FM[1]|2:INTernal[1]:FUNCTION:SHAPe?
[:SOURce]:FM[1]|2:INTernal[1]:SWEep:TIME <val><unit>
[:SOURce]:FM[1]|2:INTernal[1]:SWEep:TIME?
[:SOURce]:FM[1]|2:INTernal[1]:SWEep:TRIGger IMMEDIATE|KEY|EXTernal|BUS
[:SOURce]:FM[1]|2:INTernal[1]:SWEep:TRIGger?
[:SOURce]:FM[1]|2:SOURce INT[1]|EXT[1]|EXT2
[:SOURce]:FM[1]|2:SOURce?
[:SOURce]:FM[1]|2:STATE ON|OFF|1|0
[:SOURce]:FM[1]|2:STATE?
[:SOURce]:FM[1]|2[:DEViation] <val><unit>
[:SOURce]:FM[1]|2[:DEViation]?
[:SOURce]:FM[1]|2[:DEViation]:TRACK ON|OFF|1|0
[:SOURce]:FM[1]|2[:DEViation]:TRACK?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

List/Sweep Subsystem

Compatible Commands

```
[ :SOURce]:LIST:DIRection UP|DOWN
```

```
[ :SOURce]:LIST:DIRection?  
[ :SOURce]:LIST:DWELL <val>{,<val>}  
[ :SOURce]:LIST:DWELL?  
[ :SOURce]:LIST:DWELL:POINTs?  
[ :SOURce]:LIST:DWELL:TYPE LIST|STEP  
[ :SOURce]:LIST:DWELL:TYPE?  
[ :SOURce]:LIST:FREQuency <val>{,<val>}  
[ :SOURce]:LIST:FREQuency?  
[ :SOURce]:LIST:FREQuency:POINTs?  
[ :SOURce]:LIST:MANual <val>  
[ :SOURce]:LIST:MANual?  
[ :SOURce]:LIST:MODE AUTO|MANual  
[ :SOURce]:LIST:MODE?  
[ :SOURce]:LIST:POWER <val>{,<val>}  
[ :SOURce]:LIST:POWER?  
[ :SOURce]:LIST:POWER:POINTs?  
[ :SOURce]:LIST:TRIGger:SOURce BUS|IMMEDIATE|EXTernal|KEY  
[ :SOURce]:LIST:TRIGger:SOURce?  
[ :SOURce]:LIST:TYPE LIST|STEP  
[ :SOURce]:LIST:TYPE?  
[ :SOURce]:LIST:TYPE:LIST:INITialize:FSTep  
[ :SOURce]:LIST:TYPE:LIST:INITialize:PRESet  
[ :SOURce]:SWEep:DWELL <val>  
[ :SOURce]:SWEep:DWELL?  
[ :SOURce]:SWEep:POINTs <val>  
[ :SOURce]:SWEep:POINTs?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Low Frequency Subsystem

Compatible Commands

```
[ :SOURce ] :LFOOutput :AMPLitude <val><unit>
[ :SOURce ] :LFOOutput :AMPLitude?

[ :SOURce ] :LFOOutput :FUNCTION :FREQuency <val><unit>
[ :SOURce ] :LFOOutput :FUNCTION :FREQuency?

[ :SOURce ] :LFOOutput :FUNCTION :FREQuency :ALTerNate <val><unit>
[ :SOURce ] :LFOOutput :FUNCTION :FREQuency :ALTerNate?

[ :SOURce ] :LFOOutput :FUNCTION :FREQuency :ALTerNate :AMPLitude :PERCent <val><unit>
[ :SOURce ] :LFOOutput :FUNCTION :FREQuency :ALTerNate :AMPLitude :PERCent?

[ :SOURce ] :LFOOutput :FUNCTION :PERiod <val><unit>
[ :SOURce ] :LFOOutput :FUNCTION :PERiod?

[ :SOURce ] :LFOOutput :FUNCTION :PWIDth <val><unit>
[ :SOURce ] :LFOOutput :FUNCTION :PWIDth?

[ :SOURce ] :LFOOutput :FUNCTION :SHAPe <enum>
[ :SOURce ] :LFOOutput :FUNCTION :SHAPe?

[ :SOURce ] :LFOOutput :FUNCTION :SWEep :TIME <val><unit>
[ :SOURce ] :LFOOutput :FUNCTION :SWEep :TIME?

[ :SOURce ] :LFOOutput :FUNCTION :SWEep :TRIGger <enum>
[ :SOURce ] :LFOOutput :FUNCTION :SWEep :TRIGger?

[ :SOURce ] :LFOOutput :SOURce INT[1] | FUNCTion
[ :SOURce ] :LFOOutput :SOURce?

[ :SOURce ] :LFOOutput :STATE ON | OFF | 1 | 0
[ :SOURce ] :LFOOutput :STATE?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Phase Modulation Subsystem

Compatible Commands

```
[ :SOURce ] :PM[1] | 2 :BANDwidth | BWIDth NORMAL | HIGH
[ :SOURce ] :PM[1] | 2 :BANDwidth | BWIDth?
```

```
[ :SOURce] :PM[1]|2:EXTernal[1]:COUPling AC|DC
[ :SOURce] :PM[1]|2:EXTernal[1]:COUPling?

[ :SOURce] :PM[1]|2:INTERNAL[1]:FREQuency <val><unit>
[ :SOURce] :PM[1]|2:INTERNAL[1]:FREQuency?

[ :SOURce] :PM[1]|2:INTERNAL[1]:FREQuency:ALTerNate <val><unit>
[ :SOURce] :PM[1]|2:INTERNAL[1]:FREQuency:ALTerNate?

[ :SOURce] :PM[1]|2:INTERNAL[1]:FREQuency:ALTerNate:AMPLitude:
PERCent <val><unit>
[ :SOURce] :PM[1]|2:INTERNAL[1]:FREQuency:ALTerNate:AMPLitude:PERCent?

[ :SOURce] :PM[1]|2:INTERNAL[1]:FUNCTION:SHAPe SINE|TRIangle|SQUare|RAMP|
NOISe|DUALsine|SWEPtsine
[ :SOURce] :PM[1]|2:INTERNAL[1]:FUNCTION:SHAPe?

[ :SOURce] :PM[1]|2:INTERNAL[1]:SWEep:TIME <val><unit>
[ :SOURce] :PM[1]|2:INTERNAL[1]:SWEep:TIME?

[ :SOURce] :PM[1]|2:INTERNAL[1]:SWEep:TRIGger IMMEDIATE|KEY|EXTernal|BUS
[ :SOURce] :PM[1]|2:INTERNAL[1]:SWEep:TRIGger?

[ :SOURce] :PM[1]|2:SOURce INT[1]|EXT[1]|EXT2
[ :SOURce] :PM[1]|2:SOURce?

[ :SOURce] :PM[1]|2:STATE ON|OFF|1|0
[ :SOURce] :PM[1]|2:STATE?

[ :SOURce] :PM[1]|2[:DEViation] <val><unit>
[ :SOURce] :PM[1]|2[:DEViation]?

[ :SOURce] :PM[1]|2[:DEViation]:TRACK ON|OFF|1|0
[ :SOURce] :PM[1]|2[:DEViation]:TRACK?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Power Subsystem

Compatible Commands

```
[ :SOURce] :POWer:ALC:BANDwidth|BWIDth NORMAL|NARRow
[ :SOURce] :POWer:ALC:BANDwidth|BWIDth?

[ :SOURce] :POWer:ALC:SEARch ON|OFF|1|0|ONCE
[ :SOURce] :POWer:ALC:SEARch?
```

ESG E44xxB Commands

Analog Function Commands

```
[ :SOURce ] :POWER:ALC:SEARch:REFERENCE FIXed|MODulated
[ :SOURce ] :POWER:ALC:SEARch:REFERENCE?

[ :SOURce ] :POWER:ALC[:STATe] ON|OFF|1|0
[ :SOURce ] :POWER:ALC[:STATe]?

[ :SOURce ] :POWER:ALTerNate:AMPLitude <val>
[ :SOURce ] :POWER:ALTerNate:AMPLitude?

[ :SOURce ] :POWER:ALTerNate:MANual MAIN|DELta
[ :SOURce ] :POWER:ALTerNate:MANual?

[ :SOURce ] :POWER:ALTerNate:STATE ON|OFF|1|0
[ :SOURce ] :POWER:ALTerNate:STATE?

[ :SOURce ] :POWER:ALTerNate:TRIGger[:SOURce] INTernal|EXTernal|MANual
[ :SOURce ] :POWER:ALTerNate:TRIGger[:SOURce]?

[ :SOURce ] :POWER:ATTenuation:AUTO ON|OFF|1|0
[ :SOURce ] :POWER:ATTenuation:AUTO?

[ :SOURce ] :POWER:MODE FIXed|LIST
[ :SOURce ] :POWER:MODE?

[ :SOURce ] :POWER:REFerence <val><unit>
[ :SOURce ] :POWER:REFerence?

[ :SOURce ] :POWER:REFerence:STATE ON|OFF|1|0
[ :SOURce ] :POWER:REFerence:STATE?

[ :SOURce ] :POWER:STARt <val><unit>
[ :SOURce ] :POWER:STARt?

[ :SOURce ] :POWER:STOP <val><unit>
[ :SOURce ] :POWER:STOP?

[ :SOURce ] :POWER[:LEVel][:IMMediate]:OFFSet <val><unit>
[ :SOURce ] :POWER[:LEVel][:IMMediate]:OFFSet?

[ :SOURce ] :POWER[:LEVel][:IMMediate][:AMPLitude] <val><unit>
[ :SOURce ] :POWER[:LEVel][:IMMediate][:AMPLitude]?
```

Non-Compatible Commands

```
[ :SOURce ] :POWER:ATTenuation <val><unit>
[ :SOURce ] :POWER:ATTenuation?
```

Pulse Modulation Subsystem

Compatible Commands

```
[ :SOURce ] :PULM:FAST:STATE ON|OFF|1|0
[ :SOURce ] :PULM:FAST:STATE?

[ :SOURce ] :PULM:INTERNAL[1]:FREQuency <val><unit>
[ :SOURce ] :PULM:INTERNAL[1]:FREQuency?

[ :SOURce ] :PULM:INTERNAL[1]:FUNCTION:SHAPe <enum>
[ :SOURce ] :PULM:INTERNAL[1]:FUNCTION:SHAPe?

[ :SOURce ] :PULM:INTERNAL[1]:PERiod <val><unit>
[ :SOURce ] :PULM:INTERNAL[1]:PERiod?

[ :SOURce ] :PULM:INTERNAL[1]:PWIDth <val><unit>
[ :SOURce ] :PULM:INTERNAL[1]:PWIDth?

[ :SOURce ] :PULM:SOURce INT|EXT2
[ :SOURce ] :PULM:SOURce?

[ :SOURce ] :PULM:STATE ON|OFF|1|0
[ :SOURce ] :PULM:STATE?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Digital Function Commands

AWGN Subsystem

Compatible Commands

```
[ :SOURce]:RADIo:AWGN:ARB:BWIDth <val>
[:SOURce]:RADIo:AWGN:ARB:BWIDth?

[:SOURce]:RADIo:AWGN:ARB:LENgth <val>
[:SOURce]:RADIo:AWGN:ARB:LENgth?

[:SOURce]:RADIo:AWGN:ARB:SEED FIXed|RANDom
[:SOURce]:RADIo:AWGN:ARB:SEED?

[:SOURce]:RADIo:AWGN:ARB[:STATe] ON|OFF|1|0
[:SOURce]:RADIo:AWGN:ARB[:STATe]?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Bluetooth Subsystem

Compatible Commands

```
[ :SOURce]:RADIo:BLUETOOTH:ARB:AMADdr <val>
[:SOURce]:RADIo:BLUETOOTH:ARB:AMADdr?

[:SOURce]:RADIo:BLUETOOTH:ARB:BDADDr <val>
[:SOURce]:RADIo:BLUETOOTH:ARB:BDADDr?

[:SOURce]:RADIo:BLUETOOTH:ARB:BURSt[:STATe] ON|OFF|1|0
[:SOURce]:RADIo:BLUETOOTH:ARB:BURSt[:STATe]?

[:SOURce]:RADIo:BLUETOOTH:ARB:CGDelay <val>
[:SOURce]:RADIo:BLUETOOTH:ARB:CGDelay?

[:SOURce]:RADIo:BLUETOOTH:ARB:DATA PN9|TPN9|CPN9 |<val>
[:SOURce]:RADIo:BLUETOOTH:ARB:DATA?

[:SOURce]:RADIo:BLUETOOTH:ARB:IMPaIrments ON|OFF|1|0
[:SOURce]:RADIo:BLUETOOTH:ARB:IMPaIrments?

[:SOURce]:RADIo:BLUETOOTH:ARB:IMPaIrments:AWGN ON|OFF|1|0
```

```
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:AWGN?  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:AWGN:CNR <val>  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:AWGN:CNR?  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:AWGN:NSEED <val>  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:AWGN:NSEED?  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:FDRIFT <val>  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:FDRIFT?
```

NOTE The above command is not recommended; the following command is the preferred syntax for the ESG E44xxB.

```
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:DDEVIACTION <val>  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:DDEVIACTION?  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:FDTYPE LINEAR|SINE  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:FDTYPE?  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:FOFFSET <val>  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:FOFFSET?
```

NOTE The above command is not recommended; the following command is the preferred syntax for the ESG E44xxB.

```
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:FOFFSET <val>  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:FOFFSET?  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:MINDEX <val>  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:MINDEX?
```

NOTE The above command is not recommended; the following command is the preferred syntax for the ESG E44xxB.

```
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:MINDEX <val>  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:MINDEX?  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:STERROR <val>  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:IMPAIRMENTS:STERROR?  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:PACKET DH1  
[ :SOURce ] :RADIO:BLUETOOTH:ARB:PACKET?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce] :RADIo:BLUEtooth:ARB:RSYMBOLs <val>
[ :SOURce] :RADIo:BLUEtooth:ARB:RSYMBOLs?
[ :SOURce] :RADIo:BLUEtooth:ARB[:STATe] ON|OFF|1|0
[ :SOURce] :RADIo:BLUEtooth:ARB[:STATe]?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Calculate Subsystem

Compatible Commands

```
:CALCulate:BERT:BTS:LOOPback:EDGE:MCS5:COMParator:CRITeria:ERATE <val>
:CALCulate:BERT:BTS:LOOPback:EDGE:MCS5:COMParator:CRITeria:ERATE?

:CALCulate:BERT:BTS:LOOPback:EDGE:MCS5:COMParator:
CRITeria[:SElect] ERATE|NOLimit
:CALCulate:BERT:BTS:LOOPback:EDGE:MCS5:COMParator:CRITeria[:SElect]?

:CALCulate:BERT:BTS:LOOPback:EDGE:MCS9:COMParator:CRITeria:ERATE <val>
:CALCulate:BERT:BTS:LOOPback:EDGE:MCS9:COMParator:CRITeria:ERATE?

:CALCulate:BERT:BTS:LOOPback:EDGE:MCS9:COMParator:
CRITeria[:SElect] ERATE|NOLimit
:CALCulate:BERT:BTS:LOOPback:EDGE:MCS9:COMParator:CRITeria[:SElect]?

:CALCulate:BERT:BTS:LOOPback:EDGE:UNCoded:COMParator:CRITeria:ERATE <val>
:CALCulate:BERT:BTS:LOOPback:EDGE:UNCoded:COMParator:CRITeria:ERATE?

:CALCulate:BERT:BTS:LOOPback:EDGE:UNCoded:COMParator:CRITeria[:SElect]?

:CALCulate:BERT:BTS:LOOPback:GSM:COMParator:CRITeria:CIB <val>
:CALCulate:BERT:BTS:LOOPback:GSM:COMParator:CRITeria:CIB?

:CALCulate:BERT:BTS:LOOPback:GSM:COMParator:CRITeria:CII <val>
:CALCulate:BERT:BTS:LOOPback:GSM:COMParator:CRITeria:CII?

:CALCulate:BERT:BTS:LOOPback:GSM:COMParator:CRITeria:FERasure <val>
:CALCulate:BERT:BTS:LOOPback:GSM:COMParator:CRITeria:FERasure?

:CALCulate:BERT[:BASEband]:COMParator:CRITeria[:SElect] FERasure|CLIB|
CLII|ANY|NOLimit
:CALCulate:BERT[:BASEband]:COMParator:CRITeria[:SElect]?
```

```
:CALCulate:BERT[ :BASEband ]:COMParator:MODE CEND|FHOLD
:CALCulate:BERT[ :BASEband ]:COMParator:MODE?

:CALCulate:BERT[ :BASEband ]:COMParator:THreshold <val>
:CALCulate:BERT[ :BASEband ]:COMParator:THreshold?

:CALCulate:BERT[ :BASEband ]:DISPlay:MODE PERCent|SCIentific
:CALCulate:BERT[ :BASEband ]:DISPlay:MODE?

:CALCulate:BERT[ :BASEband ]:DISPlay:UPDate CEND|CONT
:CALCulate:BERT[ :BASEband ]:DISPlay:UPDate?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

CDMA ARB Subsystem

Compatible Commands

```
[ :SOURce ]:RADIO:CDMA:ARB:CLIPping:I <10-100%>
[:SOURce ]:RADIO:CDMA:ARB:CLIPping:I?

[:SOURce ]:RADIO:CDMA:ARB:CLIPping:POSITION PRE|POST
[:SOURce ]:RADIO:CDMA:ARB:CLIPping:POSITION?

[:SOURce ]:RADIO:CDMA:ARB:CLIPping:Q <10-100%>
[:SOURce ]:RADIO:CDMA:ARB:CLIPping:Q?

[:SOURce ]:RADIO:CDMA:ARB:CLIPping:TYPE IJQ|IQRQ
[:SOURce ]:RADIO:CDMA:ARB:CLIPping:TYPE?

[:SOURce ]:RADIO:CDMA:ARB:CLIPping[:IJQ] <10-100%>
[:SOURce ]:RADIO:CDMA:ARB:CLIPping[:IJQ]?

[:SOURce ]:RADIO:CDMA:ARB:CRATe <val>
[:SOURce ]:RADIO:CDMA:ARB:CRATe?

[:SOURce ]:RADIO:CDMA:ARB:FILTter RNYQuist|NYQuist|GAUSSian|RECTangle|IS95|
IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|IS2000SR3DS|UGGaussian| "<user FIR>"|
[:SOURce ]:RADIO:CDMA:ARB:FILTter?

[:SOURce ]:RADIO:CDMA:ARB:FILTter:ALPHA <val>
[:SOURce ]:RADIO:CDMA:ARB:FILTter:ALPHA?

[:SOURce ]:RADIO:CDMA:ARB:FILTter:BBT <val>
[:SOURce ]:RADIO:CDMA:ARB:FILTter:BBT?

[:SOURce ]:RADIO:CDMA:ARB:FILTter:CHANnel EVM|ACP
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce] :RADio:CDMA:ARB:FILTer:CHANnel?  
[ :SOURce] :RADio:CDMA:ARB:IQMap NORMAL|INVerted  
[ :SOURce] :RADio:CDMA:ARB:IQMap?  
[ :SOURce] :RADio:CDMA:ARB:OSAMple <val>  
[ :SOURce] :RADio:CDMA:ARB:OSAMple?  
[ :SOURce] :RADio:CDMA:ARB:RETRigger 1|0
```

NOTE The above command is not recommended; the following command is the preferred syntax for the ESG E44xxB.

```
[ :SOURce] :RADio:CDMA:ARB:RETRigger ON|OFF  
[ :SOURce] :RADio:CDMA:ARB:RETRigger?
```

NOTE The above query for the ESG Vector Signal Generator (E4438C) only returns the string ON or OFF. This is different from the ESG E44xxB query which returns a 1 or 0.

```
[ :SOURce] :RADio:CDMA:ARB:SETup FWD9|FWD32|FWD64|PILot|REVerse|MCArrier|<file name>  
[ :SOURce] :RADio:CDMA:ARB:SETup?  
  
[ :SOURce] :RADio:CDMA:ARB:SETup:CHANnel IS97|EQUAL|SCALE|NONE{,PILOT|SYNC|PAGING|TRAFFic,<walsh_val>,<power_val>,<pnofs_val>,RANDOM|<data_val>}  
[ :SOURce] :RADio:CDMA:ARB:SETup:CHANnel?  
  
[ :SOURce] :RADio:CDMA:ARB:SETup:MCArrier CAR3|CAR4|<file name>  
[ :SOURce] :RADio:CDMA:ARB:SETup:MCArrier?  
  
[ :SOURce] :RADio:CDMA:ARB:SETup:MCArrier:STORE "<file name>"  
  
[ :SOURce] :RADio:CDMA:ARB:SETup:MCArrier:TABLE FWD9|FWD32|FWD64|PILOT|CUSTom,"<file name>"|<freq_offset>,<power>{,FWD9|FWD32|FWD64|PILOT|CUSTom,"<file name>"|<freq_offset>,<power>}  
[ :SOURce] :RADio:CDMA:ARB:SETup:MCArrier:TABLE?  
  
[ :SOURce] :RADio:CDMA:ARB:SETup:STORE "<file name>"  
  
[ :SOURce] :RADio:CDMA:ARB:TRIGger:TYPE CONT|SINGLE|GATE  
[ :SOURce] :RADio:CDMA:ARB:TRIGger:TYPE?  
  
[ :SOURce] :RADio:CDMA:ARB:TRIGger:TYPE:GATE:ACTive LOW|HIGH  
[ :SOURce] :RADio:CDMA:ARB:TRIGger:TYPE:GATE:ACTive?  
  
[ :SOURce] :RADio:CDMA:ARB:TRIGger[:SOURce] KEY|EXT|BUS
```

```
[ :SOURce ] :RADIO:CDMA:ARB:TRIGger[ :SOURce ]?  
[ :SOURce ] :RADIO:CDMA:ARB:TRIGger[ :SOURce ] :EXTernal:DELay <val>  
[ :SOURce ] :RADIO:CDMA:ARB:TRIGger[ :SOURce ] :EXTernal:DELay?  
[ :SOURce ] :RADIO:CDMA:ARB:TRIGger[ :SOURce ] :EXTernal:DELay:STATe ON|OFF|1|0  
[ :SOURce ] :RADIO:CDMA:ARB:TRIGger[ :SOURce ] :EXTernal:DELay:STATe?  
[ :SOURce ] :RADIO:CDMA:ARB:TRIGger[ :SOURce ] :EXTernal:SLOPe POSitive|NEGative  
[ :SOURce ] :RADIO:CDMA:ARB:TRIGger[ :SOURce ] :EXTernal:SLOPe?  
[ :SOURce ] :RADIO:CDMA:ARB:WLENgth <val>  
[ :SOURce ] :RADIO:CDMA:ARB:WLENgth?  
[ :SOURce ] :RADIO:CDMA:ARB[ :STATe ] ON|OFF|1|0  
[ :SOURce ] :RADIO:CDMA:ARB[ :STATe ]?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

CDMA2000 ARB Subsystem

Compatible Commands

```
[ :SOURce ] :RADIO:CDMA2000:ARB:CLIPping:I <10-100%>  
[ :SOURce ] :RADIO:CDMA2000:ARB:CLIPping:I?  
[ :SOURce ] :RADIO:CDMA2000:ARB:CLIPping:POSITION PRE|POST  
[ :SOURce ] :RADIO:CDMA2000:ARB:CLIPping:POSITION?  
[ :SOURce ] :RADIO:CDMA2000:ARB:CLIPping:Q <10-100%>  
[ :SOURce ] :RADIO:CDMA2000:ARB:CLIPping:Q?  
[ :SOURce ] :RADIO:CDMA2000:ARB:CLIPping:TYPE IJQ|IQRQ  
[ :SOURce ] :RADIO:CDMA2000:ARB:CLIPping:TYPE?  
[ :SOURce ] :RADIO:CDMA2000:ARB:CLIPping[:IJQ] <10-100%>  
[ :SOURce ] :RADIO:CDMA2000:ARB:CLIPping[:IJQ]?  
[ :SOURce ] :RADIO:CDMA2000:ARB:FILTter RNYQuist|NYQuist|GAUSSian|RECTangle|IS95|  
IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|IS2000SR3DS|UGaussian|"<user FIR>"  
[ :SOURce ] :RADIO:CDMA2000:ARB:FILTter?  
[ :SOURce ] :RADIO:CDMA2000:ARB:FILTter:ALPHA <val>  
[ :SOURce ] :RADIO:CDMA2000:ARB:FILTter:ALPHA?  
[ :SOURce ] :RADIO:CDMA2000:ARB:FILTter:BBT <val>  
[ :SOURce ] :RADIO:CDMA2000:ARB:FILTter:BBT?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:CDMA2000:ARB:FILTer:CHANnel EVM|ACP
[ :SOURce]:RADio:CDMA2000:ARB:FILTer:CHANnel?

[ :SOURce]:RADio:CDMA2000:ARB:IQMap NORMal|INVert|INVerted
[ :SOURce]:RADio:CDMA2000:ARB:IQMap?

[ :SOURce]:RADio:CDMA2000:ARB:LINK FORWARD|REVerse
[ :SOURce]:RADio:CDMA2000:ARB:LINK?

[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup S1Pilot|S3DPilot|S3MPilot|
S19Chan|S3D9chan|S3M9chan|MCARrier| "<file name>""
[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup?

[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:MCARrier CAR2|CAR3|CAR4|
"<file name>""
[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:MCARrier?

[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:MCARrier:STORe "<file name>""
[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:MCARrier:TABLE INIT|APPend|
<chan_num>,S1Pilot|S3DPilot|S3MPilot|S19Chan|S3D9chan|S3M9chan|
"<file name>",<freq_offset>,<power>
[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:MCARrier:TABLE? <chan_num>
[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:MCARrier:TABLE:NCARriers?
[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:STORe "<file name>""
[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:TABLE:APPLy

[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:TABLE:CHANnel INIT|APPend|
<chan_num>,<chan_type>,<config>,<data_rate>,<walsh>,<power>,<pn_offset>,
RANDOM|<data_val>
[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:TABLE:CHANnel? <chan_num>
[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:TABLE:NCHannels?
[ :SOURce]:RADio:CDMA2000:ARB:LINK:FORward:SETup:TABLE:PADJust EQUal|SCALe
[ :SOURce]:RADio:CDMA2000:ARB:LINK:REVerse:RConfig <val>
[ :SOURce]:RADio:CDMA2000:ARB:LINK:REVerse:RConfig?

[ :SOURce]:RADio:CDMA2000:ARB:LINK:REVerse: SETupS1Pilot|S3Pilot|S15Chan|
S35Chan|S18Chan| "<file name>""
[ :SOURce]:RADio:CDMA2000:ARB:LINK:REVerse:SETup?

[ :SOURce]:RADio:CDMA2000:ARB:LINK:REVerse:SETup:STORe "<file name>""
[ :SOURce]:RADio:CDMA2000:ARB:LINK:REVerse:SETup:TABLE:APPLy
[ :SOURce]:RADio:CDMA2000:ARB:LINK:REVerse:SETup:TABLE:CHANnel INIT|APPend|
```

```
<chan_num>, <chan_type>, <data_rate>, <power>, RANDOM | <data_val>
[ :SOURce ] :RADIO:CDMA2000:ARB:LINK:REVerse:SETup:TABLE:CHANnel? <chan_num>
[ :SOURce ] :RADIO:CDMA2000:ARB:LINK:REVerse:SETup:TABLE:NCHannels?
[ :SOURce ] :RADIO:CDMA2000:ARB:LINK:REVerse:SETup:TABLE:PADJust EQUal | SCALE
[ :SOURce ] :RADIO:CDMA2000:ARB:RETRigger 1|0
```

NOTE The above command is not recommended; the following command is the preferred syntax for the ESG E44xxB.

```
[ :SOURce ] :RADIO:CDMA2000:ARB:RETRigger ON|OFF
[ :SOURce ] :RADIO:CDMA2000:ARB:RETRigger?
```

NOTE The above query for the ESG Vector Signal Generator (E4438C) only returns the string ON or OFF. This is different from the ESG E44xxB query which returns a 1 or 0.

```
[ :SOURce ] :RADIO:CDMA2000:ARB:REVision?
[ :SOURce ] :RADIO:CDMA2000:ARB:SPReading:RATE 1|3
[ :SOURce ] :RADIO:CDMA2000:ARB:SPReading:RATE?

[ :SOURce ] :RADIO:CDMA2000:ARB:SPReading:TYPE DIRect | MCARrier
[ :SOURce ] :RADIO:CDMA2000:ARB:SPReading:TYPE?

[ :SOURce ] :RADIO:CDMA2000:ARB:SPReading:TYPE:MCARrier:SPACing 1.23MHz |
1.25MHz
[ :SOURce ] :RADIO:CDMA2000:ARB:SPReading:TYPE:MCARrier:SPACing?
[ :SOURce ] :RADIO:CDMA2000:ARB:SPReading:TYPE:MCARrier:SPACing?

[ :SOURce ] :RADIO:CDMA2000:ARB:TRIGger:TYPE CONT | SINGLE | GATE
[ :SOURce ] :RADIO:CDMA2000:ARB:TRIGger:TYPE?

[ :SOURce ] :RADIO:CDMA2000:ARB:TRIGger:TYPE:GATE:ACTive LOW | HIGH
[ :SOURce ] :RADIO:CDMA2000:ARB:TRIGger:TYPE:GATE:ACTive?

[ :SOURce ] :RADIO:CDMA2000:ARB:TRIGger[ :SOURce ] KEY | EXT | BUS
[ :SOURce ] :RADIO:CDMA2000:ARB:TRIGger[ :SOURce ]?

[ :SOURce ] :RADIO:CDMA2000:ARB:TRIGger[ :SOURce ] :EXTernal:DELay <val>
[ :SOURce ] :RADIO:CDMA2000:ARB:TRIGger[ :SOURce ] :EXTernal:DELay?

[ :SOURce ] :RADIO:CDMA2000:ARB:TRIGger[ :SOURce ] :EXTernal:DELay:
STATE ON | OFF | 1 | 0
[ :SOURce ] :RADIO:CDMA2000:ARB:TRIGger[ :SOURce ] :EXTernal:DELay:STATE?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADIO:CDMA2000:ARB:TRIGger[:SOURce]:EXTernal:  
SLOPe POSitive|NEGative  
[:SOURce]:RADIO:CDMA2000:ARB:TRIGger[:SOURce]:EXTernal:SLOPe?  
[:SOURce]:RADIO:CDMA2000:ARB[:STATE] ON|OFF|1|0  
[:SOURce]:RADIO:CDMA2000:ARB[:STATE]?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

CDMA2000 BBG Subsystem

Compatible Commands

```
[ :SOURce]:RADIO:CDMA2000[:BBG]:LINK FORWARD|REVerse  
[:SOURce]:RADIO:CDMA2000[:BBG]:LINK?  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:BBClock INT[1]|EXT[1]  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:BBClock?  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:ESDelay <0.5-128.0>  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:ESDelay?  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:CRATe <50 cps-1.3 Mcps>  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:CRATe?  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:FILTer:ALPHA <0-1.0>  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:FILTer:ALPHA?  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:FILTer:BBT <0-1.0>  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:FILTer:BBT?  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:FILTer:CHANnel EVM|ACP  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:FILTer:CHANnel?  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:FILTer RNYQuist|NYQuist|GAUSSian|  
RECTangle|IS95|IS95_EQ|{IS95_MOD}|IS95_MOD_EQ|AC4Fm|UGGaussian|"<user FIR>"  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:FILTer?  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:LCMask <val>  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:LCMask?  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:LCSTate <val>  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:LCSTate?  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:PADJust EQUal|SCALe  
[:SOURce]:RADIO:CDMA2000[:BBG]:REVerse:POLarity NORMal|INVerted
```

```
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:POLarity?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:POLarity:ALL NORMAL | INVerted  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:POLarity:ALL?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH:SETup:DATA PN9 | PN15 | FIX4 |  
" <file name>"  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH:SETup:DATA?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH:SETup:DATA:FIX4 <val>  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH:SETup:DATA:FIX4?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH:SETup:FLENgth?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH:SETup:FOFFset <val>  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH:SETup:FOFFset?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH:SETup:POWeR <val>  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH:SETup:POWeR?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH:SETup:RATE?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH[ :STATE ] ON | OFF | 1 | 0  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RACH[ :STATE ]?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:DATA PN9 | PN15 | FIX4 |  
" <file name>"  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:DATA?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:DATA:FIX4 <val>  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:DATA:FIX4?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:FLENgth <val>  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:FLENgth?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:FOFFset <val>  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:FOFFset?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:POWeR <val>  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:POWeR?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:RATE <val>  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:RATE?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:WALSh <val>  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh:SETup:WALSh?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh[ :STATE ] ON | OFF | 1 | 0  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RCCCh[ :STATE ]?  
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RConfig <val>
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:RConfig?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:DATA PN9|PN15|FIX4|  
"<file name>"  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:DATA?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:DATA:FIX4 <val>  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:DATA:FIX4?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:FLENgth <val>  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:FLENgth?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:FOFFset <val>  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:FOFFset?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:POWer <val>  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:POWer?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:RATE?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:WALSh <val>  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh:SETup:WALSh?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh[:STATE] ON|OFF|1|0  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RDCCh[:STATE]?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:DATA PN9|PN15|FIX4|  
"<file name>"  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:DATA?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:DATA:FIX4 <val>  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:DATA:FIX4?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:FLENgth <val>  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:FLENgth?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:FOFFset <val>  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:FOFFset?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:POWer <val>  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:POWer?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:RATE <val>  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:RATE?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:WALSh <val>  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH:SETup:WALSh?  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH[:STATE] ON|OFF|1|0  
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:REACH[:STATE]?
```

```
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:DATA PN9|PN15|FIX4|<file name>
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:DATA?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:DATA:FIX4 <val>
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:DATA:FIX4?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:FLENgth <5-20>
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:FLENgth?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:FOFFset <0-15>
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:FOFFset?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:POWer <val>
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:POWer?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:
RATE <1.5kbps-14.4kbps>
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:RATE?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:WALSh <val>
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH:SETup:WALSh?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH[:STATE] ON|OFF|1|0
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RFCH[:STATE]?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RPICh:SETup:GRATe FULL|HALF|QUARTER
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RPICh:SETup:GRATe?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RPICh:SETup:PCB <val>
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RPICh:SETup:PCB?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RPICh:SETup:POWer <val>
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RPICh:SETup:POWer?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RPICh:SETup:WALSh?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RPICh[:STATE] ON|OFF|1|0
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RPICh[:STATE]?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RSCH1:SETup:DATA PN9|PN15|FIX4|<file name>|EXT
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RSCH1:SETup:DATA?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RSCH1:SETup:DATA:FIX4 <val>
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RSCH1:SETup:DATA:FIX4?
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RSCH1:SETup:FLENgth <val>
[ :SOURce] :RADIO:CDMA2000[ :BBG] :REVerse:RSCH1:SETup:FLENgth?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1:SETup:F OFFset <val>
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1:SETup:F OFFset?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1:SETup:POWer <val>
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1:SETup:POWer?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1:SETup:RATE <val>
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1:SETup:RATE?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1:SETup:TCODE ON|OFF|1|0
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1:SETup:TCODE?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1:SETup:WALSh <val>
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1:SETup:WALSh?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1[:STATE] ON|OFF|1|0
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH1[:STATE]?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:DATA PN9|PN15|FIX4|
"<file name>"|EXT
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:DATA?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:DATA:FIX4 <val>
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:DATA:FIX4?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:F LENGTH <val>
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:F LENGTH?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:F OFFset <val>
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:F OFFset?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:POWer <val>
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:POWer?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:RATE <val>
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:RATE?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:TCODE ON|OFF|1|0
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:TCODE?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:WALSh <val>
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2:SETup:WALSh?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2[:STATE] ON|OFF|1|0
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH2[:STATE]?

[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH:SETup:DATA PN9|PN15|FIX4|
"<file name>"|EXT
[:SOURce]:RADio:CDMA2000[:BBG]:REVerse:RSCH:SETup:DATA?
```

```
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:DATA:FIX4 <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:DATA:FIX4?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:FLENgth <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:FLENgth?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:FOFFset <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:FOFFset?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:POWer <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:POWer?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:RATE <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:RATE?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:WALSh <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH:SETup:WALSh?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH[ :STATE] ON|OFF|1|0
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:RSCH[ :STATE]?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:SPReading:RATE?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:TADVance <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:TADVance?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:TEDGE RISING|FALLing
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] :REVerse:TEDGE?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :CRATe <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :CRATe?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:DATA PN9|PN15|FIX4|
"<file name>"|EXT
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:DATA?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:DATA:FIX4 <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:DATA:FIX4?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:FOFFset <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:FOFFset?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:LCMask?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:LCMask:ESN <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:LCMask:ESN?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:LCMask:HEADer <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:LCMask:HEADer?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ] [ :FORWard ] :FFCH:SETup:POWer <val>
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:POWer?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:PPUNcture ON|OFF|1|0  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:PPUNcture?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:PRAMp <val>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:PRAMp?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:QOF <val>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:QOF?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:RATE <val>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:RATE?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:RConfig <val>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:RConfig?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:WALSh <val>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FFCH:SETup:WALSh?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:DATA DEFault |  
"<file name>"  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:DATA?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:LCMask?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:LCMask:F1 <val>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:LCMask:F1?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:LCMask:F2 <val>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:LCMask:F2?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:LCMask:F3 <val>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:LCMask:F3?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:  
MESSage <bit_count>, <datablock>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:POWer <val>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:POWer?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:RATE 4.8ksps|9.6ksps  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:RATE?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:WALSh <val>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPCH:SETup:WALSh?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPICH:SETup:PNOFFset <val>  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPICH:SETup:PNOFFset?  
[:SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FPICH:SETup:POWer <val>
```

[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FPICh:SETUp:POWER?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:DATA PN9|PN15|
FIX4| "<file name>" | EXT
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:DATA?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:DATA:FIX4 <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:DATA:FIX4?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:FOFFset <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:FOFFset?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:LCMask?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:LCMask:ESN <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:LCMask:ESN?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:LCMask:HEADer <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:LCMask:HEADer?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:POWer <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:POWer?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:QOF <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:QOF?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:RATE <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:RATE?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:RConfig <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:RConfig?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:TCODE ON|OFF|1|0
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:TCODE?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:WALSh <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSCH[1] | 2:SETUp:WALSh?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSYNC:SETUp:CFREquency <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSYNC:SETUp:CFREquency?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSYNC:SETUp:DAYLt <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSYNC:SETUp:DAYLt?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSYNC:SETUp:ECFRequency <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSYNC:SETUp:ECFRequency?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSYNC:SETUp:LCSTate <val>
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSYNC:SETUp:LCSTate?
[:SOURce] :RADIO:CDMA2000[:BBG] [:FORWard] :FSYNC:SETUp:LPSec <val>

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:LPSec?  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:LTMoff <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:LTMoff?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:MPREv <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:MPREv?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:MSGType <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:MSGType?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:NID <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:NID?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:POWer <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:POWer?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:PRATe <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:PRATe?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:PREV <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:PREV?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:REServed <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:REServed?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:SID <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:SID?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:STYPe IS95|JSTD8|IS2000  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:STYPe?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:SYSTime <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:SYSTime?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:WALSh <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:FSYNC:SETup:WALSh?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:OCNS:SETup:POWer <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:OCNS:SETup:POWer?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:OCNS:SETup:WALSh <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:OCNS:SETup:WALSh?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:POLarity:ALL NORMAL|INVerted  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:POLarity:ALL?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:QPCH:SETup:CCI <val>  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:QPCH:SETup:CCI?  
  
[ :SOURce]:RADio:CDMA2000[:BBG][ :FORward]:QPCH:SETup:PI <val>
```

```
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :QPCH:SETUp:PI?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :QPCH:SETUp:POWer <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :QPCH:SETUp:POWer?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :QPCH:SETUp:RATE <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :QPCH:SETUp:RATE?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :QPCH:SETUp:WALSh <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :QPCH:SETUp:WALSh?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :QPCH[:STATe] ON|OFF|1|0
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :QPCH[:STATe]?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :SPReading:RATE?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :BBClock INT[1]|EXT[1]
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :BBClock?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :ESDelay <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :ESDelay?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FFCH[:STATe] ON|OFF|1|0
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FFCH[:STATe]?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FILTter RNYQuist|NYQuist|GAUSSian|
RECTangle|IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|"<user FIR>"|
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FILTter?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FILTter:ALPHa <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FILTter:ALPHa?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FILTter:BBT <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FILTter:BBT?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FILTter:CHANnel EVM|ACP
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FILTter:CHANnel?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FPCh[:STATe] ON|OFF|1|0
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FPCh[:STATe]?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FPICh[:STATe] ON|OFF|1|0
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FPICh[:STATe]?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FSCH[1]|2[:STATe] ON|OFF|1|0
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FSCH[1]|2[:STATe]?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FSYNC[:STATe] ON|OFF|1|0
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :FSYNC[:STATe]?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :OCNS[:STATe] ON|OFF|1|0
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:CDMA2000[:BBG][:FORward]:OCNS[:STATE]?
[ :SOURce]:RADio:CDMA2000[:BBG][:FORward]:PADJust EQUal|SCALe
[ :SOURce]:RADio:CDMA2000[:BBG][:FORward]:POLarity NORMAl|INVerted
[ :SOURce]:RADio:CDMA2000[:BBG][:FORward]:POLarity?
[ :SOURce]:RADio:CDMA2000[:BBG][:STATE] ON|OFF|1|0
[ :SOURce]:RADio:CDMA2000[:BBG][:STATE]?
```

Non-Compatible Commands

```
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC12:
DCOut CCLK|CLK20ms|CLK80ms|CLK4khz|CLK307khz
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC12:DCOut?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC12:DOUT LCODE|IOUT|QOUT
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC12:DOUT?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC12:EVENT DESecond|PNSync
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC12:EVENT?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC12:SSOut EVENsecond|LCSync
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC12:SSOut?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC34:DCOut CCLK|CLK5ms|
CLK10ms|CLK20ms|CLK40ms|CLK80ms
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC34:DCOut?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC34:DOUT LCODE|PILOT|
RSCHcoded|RDCChcoded|RFCHcoded|RCCChcoded|REACHcoded|ZI|ZQ
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC34:DOUT?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC34:EVENT DESecond|PNSync
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:BNCMux:RC34:EVENT?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:IQ:PPOTher <0-4>
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:IQ:PPOTher?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:IQ:PPower?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:IQ:SCALE <-40dB to 0dB>
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:IQ:SCALE?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:IQ:TVoltage?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:IQ:TVOTher <0-4V>
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:IQ:TVOTher?
[ :SOURce]:RADio:CDMA2000[:BBG]:REVerse:IQRotation?
```

```
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :BNCMux:DOUT PCRamp | D80Trigger
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :BNCMux:DOUT?

[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :BNCMux:EVENT DESecond | D20Trigger | D80Trigger
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :BNCMux:EVENT?

[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :IQ:PPOTher <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :IQ:PPOTher?

[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :IQ:PPoWer?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :IQ:SCALe <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :IQ:SCALe?

[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :IQ:TVoLtaGe?
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :IQ:TVoLtaGe <val>
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :IQ:TVoLtaGe?

[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :IQRoTation STANDARD | ROTated
[ :SOURce ] :RADIO:CDMA2000[ :BBG ][ :FORWard ] :IQRoTation?
```

Custom Subsystem

Compatible Commands

```
[ :SOURce ] :RADIO:CUSTOm:ALPHa <val>
[ :SOURce ] :RADIO:CUSTOm:ALPHa?

[ :SOURce ] :RADIO:CUSTOm:BBClock INT[1] | EXT[1]
[ :SOURce ] :RADIO:CUSTOm:BBClock?

[ :SOURce ] :RADIO:CUSTOm:BBT <val>
[ :SOURce ] :RADIO:CUSTOm:BBT?

[ :SOURce ] :RADIO:CUSTOm:BRATe <val>
[ :SOURce ] :RADIO:CUSTOm:BRATe?

[ :SOURce ] :RADIO:CUSTOm:BURSt:SHAPe:FALL:DELaY <val>
[ :SOURce ] :RADIO:CUSTOm:BURSt:SHAPe:FALL:DELaY?

[ :SOURce ] :RADIO:CUSTOm:BURSt:SHAPe:FALL:TIME <val>
[ :SOURce ] :RADIO:CUSTOm:BURSt:SHAPe:FALL:TIME?

[ :SOURce ] :RADIO:CUSTOm:BURSt:SHAPe:FDELaY <val>
[ :SOURce ] :RADIO:CUSTOm:BURSt:SHAPe:FDELaY?

[ :SOURce ] :RADIO:CUSTOm:BURSt:SHAPe:FTIMe <val>
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce] :RADio:CUSTom:BURSt:SHAPe:FTIME?
[ :SOURce] :RADio:CUSTom:BURSt:SHAPe:RDElAy <val>
[ :SOURce] :RADio:CUSTom:BURSt:SHAPe:RDElAy?

[ :SOURce] :RADio:CUSTom:BURSt:SHAPe:RISE:DElAy <val>
[ :SOURce] :RADio:CUSTom:BURSt:SHAPe:RISE:DElAy?

[ :SOURce] :RADio:CUSTom:BURSt:SHAPe:RISE:TIME <val>
[ :SOURce] :RADio:CUSTom:BURSt:SHAPe:RISE:TIME?

[ :SOURce] :RADio:CUSTom:BURSt:SHAPe:RTIMe <val>
[ :SOURce] :RADio:CUSTom:BURSt:SHAPe:RTIMe?

[ :SOURce] :RADio:CUSTom:BURSt:SHAPe[:TYPE] SINE| "<file name>" 
[ :SOURce] :RADio:CUSTom:BURSt:SHAPe[:TYPE]?

[ :SOURce] :RADio:CUSTom:DATA PN9|PN11|PN15|PN20|PN23|FIX4| "<file name>" |
EXT|P4|P8|P16|P32|P64
[ :SOURce] :RADio:CUSTom:DATA?

[ :SOURce] :RADio:CUSTom:DATA:FIX4 <val>
[ :SOURce] :RADio:CUSTom:DATA:FIX4?

[ :SOURce] :RADio:CUSTom:DENCode ON|OFF|1|0
[ :SOURce] :RADio:CUSTom:DENCode?

[ :SOURce] :RADio:CUSTom:EDATa:DElAy?

[ :SOURce] :RADio:CUSTom:EDClock SYMBol|NORMal
[ :SOURce] :RADio:CUSTom:EDClock?

[ :SOURce] :RADio:CUSTom:FILTter RNYQuist|NYQuist|GAUSSian|RECTangle|IS95|
IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|IS2000SR3DS|UGGaussian| "<user FIR>" 
[ :SOURce] :RADio:CUSTom:FILTter?

[ :SOURce] :RADio:CUSTom:IQ:SCALE <val>
[ :SOURce] :RADio:CUSTom:IQ:SCALE?

[ :SOURce] :RADio:CUSTom:MODulation:FSK[:DEViation] <val>
[ :SOURce] :RADio:CUSTom:MODulation:FSK[:DEViation]?

[ :SOURce] :RADio:CUSTom:MODulation:MSK[:PHASe] <val>
[ :SOURce] :RADio:CUSTom:MODulation:MSK[:PHASe]?

[ :SOURce] :RADio:CUSTom:MODulation:UFSK "<file name>" 
[ :SOURce] :RADio:CUSTom:MODulation:UFSK?

[ :SOURce] :RADio:CUSTom:MODulation:UIQ "<file name>" 
[ :SOURce] :RADio:CUSTom:MODulation:UIQ?
```

```
[ :SOURce ] :RADIO:CUSTOM:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|GRAYQPSK|OQPSK|  
IS95OQPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|FSK2|FSK4|FSK8|FSK16|C4FM|QAM4|QAM16|  
QAM32|QAM64|QAM256|UIQ|UFSK  
[ :SOURce ] :RADIO:CUSTOM:MODulation[:TYPE]?  
[ :SOURce ] :RADIO:CUSTOM:POLarity[:ALL] NORMAL|INVerted  
[ :SOURce ] :RADIO:CUSTOM:POLarity[:ALL]?  
[ :SOURce ] :RADIO:CUSTOM:REPeat SINGLE|CONTinuous  
[ :SOURce ] :RADIO:CUSTOM:REPeat?  
[ :SOURce ] :RADIO:CUSTOM:SRATe <val>  
[ :SOURce ] :RADIO:CUSTOM:SRATe?  
[ :SOURce ] :RADIO:CUSTOM:STANDARD:SElect NONE|AC4Fm|ACQPsk|BLUETOOTH|CDPD  
[ :SOURce ] :RADIO:CUSTOM:STANDARD:SElect?  
[ :SOURce ] :RADIO:CUSTOM:TRIGger[:SOURce] KEY|EXT|BUS  
[ :SOURce ] :RADIO:CUSTOM:TRIGger[:SOURce]?  
[ :SOURce ] :RADIO:CUSTOM:TRIGger[:SOURce]:EXTernal:DELay <val>  
[ :SOURce ] :RADIO:CUSTOM:TRIGger[:SOURce]:EXTernal:DELay?  
[ :SOURce ] :RADIO:CUSTOM:TRIGger[:SOURce]:EXTernal:DELay:STATE ON|OFF|1|0  
[ :SOURce ] :RADIO:CUSTOM:TRIGger[:SOURce]:EXTernal:DELay:STATE?  
[ :SOURce ] :RADIO:CUSTOM[:STATE] ON|OFF|1|0  
[ :SOURce ] :RADIO:CUSTOM[:STATE]?
```

Non-Compatible Commands

```
[ :SOURce ] :RADIO:CUSTOM:CHANnel EVM|ACP  
[ :SOURce ] :RADIO:CUSTOM:CHANnel?
```

Data Subsystem

Compatible Commands

```
:DATA:BERT:BTS:LOOPback:EDGE:MCS5[:DATA]?  
:DATA:BERT:BTS:LOOPback:EDGE:MCS9[:DATA]?  
:DATA:BERT:BTS:LOOPback:EDGE:UNCoded[:DATA]?  
:DATA:BERT[:BASEband]?:BEC|BITC|BER|ALL|TBEC|TBIT|TBER|JUDGE  
:DATA[:DATA]?:BEC|BITC|BER|ALL|TBEC|TBIT|TBER|JUDGE
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Digital Modulation Subsystem

Compatible Commands

```
[ :SOURce ] :BURSt:SOURce EXTERNAL[1]|INTERNAL[1]
[ :SOURce ] :BURSt:SOURce?
[ :SOURce ] :BURSt:STATE ON|OFF|1|0
[ :SOURce ] :BURSt:STATE?

[ :SOURce ] :DM:BBFilter THRough
[ :SOURce ] :DM:BBFilter?

[ :SOURce ] :DM:EXTernal:ALC:BANDwidth|BWIDth NORMal|NARRow
[ :SOURce ] :DM:EXTernal:ALC:BANDwidth|BWIDth?

[ :SOURce ] :DM:EXTernal:HICRest[:STATE] ON|OFF|1|0
[ :SOURce ] :DM:EXTernal:HICRest[:STATE]?

[ :SOURce ] :DM:IQADjustment:Gain <val><unit>
[ :SOURce ] :DM:IQADjustment:Gain?

[ :SOURce ] :DM:IQADjustment:IOFFset <val><unit>
[ :SOURce ] :DM:IQADjustment:IOFFset?

[ :SOURce ] :DM:IQADjustment:QOFFset <val><unit>
[ :SOURce ] :DM:IQADjustment:QOFFset?

[ :SOURce ] :DM:IQADjustment:QSKEw <val><unit>
[ :SOURce ] :DM:IQADjustment:QSKEw?

[ :SOURce ] :DM:IQADjustment[:STATE] ON|OFF|1|0
[ :SOURce ] :DM:IQADjustment[:STATE]?

[ :SOURce ] :DM:SOURce EXTERNAL|INTERNAL[1]
[ :SOURce ] :DM:SOURce?

[ :SOURce ] :DM:STATE ON|OFF|1|0
[ :SOURce ] :DM:STATE?
```

Non-Compatible Commands

```
[ :SOURce ] :DM:BBFilter <val>
[ :SOURce ] :DM:BBFilter?
```

```
[ :SOURce ] :DM:EXTernal:POLarity NORMal | INVerted  
[ :SOURce ] :DM:EXTernal:POLarity?
```

Dmodulation Subsystem

Compatible Commands

```
[ :SOURce ] :RADIO:DMODulation:ARB:FILTer RNYQuist|NYQuist|GAUSSian|RECTangle|  
IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|WCDMa|AC4Fm|IS2000SR3DS|UGGaussian|  
"<user FIR>"  
[ :SOURce ] :RADIO:DMODulation:ARB:FILTer?  
[ :SOURce ] :RADIO:DMODulation:ARB:FILTer:ALPHA <val>  
[ :SOURce ] :RADIO:DMODulation:ARB:FILTer:ALPHA?  
[ :SOURce ] :RADIO:DMODulation:ARB:FILTer:BBT <val>  
[ :SOURce ] :RADIO:DMODulation:ARB:FILTer:BBT?  
[ :SOURce ] :RADIO:DMODulation:ARB:FILTer:CHANnel EVM|ACP  
[ :SOURce ] :RADIO:DMODulation:ARB:FILTer:CHANnel?  
[ :SOURce ] :RADIO:DMODulation:ARB:MODulation:FSK[ :DEViation] <val><unit>  
[ :SOURce ] :RADIO:DMODulation:ARB:MODulation:FSK[ :DEViation]?  
[ :SOURce ] :RADIO:DMODulation:ARB:MODulation[:TYPE]  
[ :SOURce ] :RADIO:DMODulation:ARB:RETRigger 1|0
```

NOTE The above command is not recommended; the following command is the preferred syntax for the ESG E44xxB.

```
[ :SOURce ] :RADIO:DMODulation:ARB:RETRigger ON|OFF  
[ :SOURce ] :RADIO:DMODulation:ARB:RETRigger?
```

NOTE The above query for the ESG Vector Signal Generator (E4438C) only returns the string ON or OFF. This is different from the ESG E44xxB query which returns a 1 or 0.

```
[ :SOURce ] :RADIO:DMODulation:ARB:SETup GSM|NADC|PDC|PHS|DECT|AC4Fm|ACQPsK|  
CDPD|PWT|EDGE|TETRa|MCARrier|"<file name>"  
[ :SOURce ] :RADIO:DMODulation:ARB:SETup?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:DMODulation:ARB:SETup:MCARrier GSM|NADC|PDC|PHS|DECT|
AC4Fm|ACQPsK|CDPD|PWT|EDGE|TETRa,<num carriers>,<freq spacing>|"<file name>"
```

```
[ :SOURce]:RADio:DMODulation:ARB:SETup:MCARrier?
```

```
[ :SOURce]:RADio:DMODulation:ARB:SETup:MCARrier:PHASe FIXed|RANDOM
```

```
[ :SOURce]:RADio:DMODulation:ARB:SETup:MCARrier:PHASe?
```

```
[ :SOURce]:RADio:DMODulation:ARB:SETup:MCARrier:STORe "<file name>"
```

```
[ :SOURce]:RADio:DMODulation:ARB:SETup:MCARrier:TABLE INIT|APPend|
<carrier_num>,GSM|NADC|PDC|PHS|DECT|AC4Fm|ACQPsK|CDPD|PWT|EDGE|TETRa|
"<file name>",<freq_offset>,<power>
```

```
[ :SOURce]:RADio:DMODulation:ARB:SETup:MCARrier:TABLE? <carrier_num>
```

```
[ :SOURce]:RADio:DMODulation:ARB:SETup:MCARrier:TABLE:NCARriers?
```

```
[ :SOURce]:RADio:DMODulation:ARB:SETup:STORe "<file name>"
```

```
[ :SOURce]:RADio:DMODulation:ARB:SRATE <val>
```

```
[ :SOURce]:RADio:DMODulation:ARB:SRATE?
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger:TYPE CONT|SINGLE|GATE
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger:TYPE?
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger:TYPE:GATE:ACTive LOW|HIGH
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger:TYPE:GATE:ACTIVE?
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger[:SOURce] KEY|EXT|BUS
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger[:SOURce]?
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger[:SOURce]:EXTernal:DELay <val>
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger[:SOURce]:EXTernal:DELay?
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger[:SOURce]:EXTernal:DELay:
```

```
STATE ON|OFF|1|0
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger[:SOURce]:EXTernal:DELay:STATE?
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger[:SOURce]:EXTernal:
```

```
SLOPe POSitive|NEGative
```

```
[ :SOURce]:RADio:DMODulation:ARB:TRIGger[:SOURce]:EXTernal:SLOPe?
```

```
[ :SOURce]:RADio:DMODulation:ARB[:STATE] ON|OFF|1|0
```

```
[ :SOURce]:RADio:DMODulation:ARB[:STATE]?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

DECT Subsystem

Compatible Commands

```
[ :SOURce ] :RADIO:DECT:ALPHA <val>
[ :SOURce ] :RADIO:DECT:ALPHA?

[ :SOURce ] :RADIO:DECT:BBCLOCK INT[1]|EXT[1]
[ :SOURce ] :RADIO:DECT:BBCLOCK?

[ :SOURce ] :RADIO:DECT:BBT <val>
[ :SOURce ] :RADIO:DECT:BBT?

[ :SOURce ] :RADIO:DECT:BRATE <val>
[ :SOURce ] :RADIO:DECT:BRATE?

[ :SOURce ] :RADIO:DECT:BURSt:PN9 NORMAl|QUICK
[ :SOURce ] :RADIO:DECT:BURSt:PN9?

[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:FALL:DELay <val>
[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:FALL:DELay?

[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:FALL:TIME <val>
[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:FALL:TIME?

[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:FDELay <val>
[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:FDELay?

[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:FTIMe <val>
[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:FTIMe?

[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:RDELay <val>
[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:RDELay?

[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:RISE:DELay <val>
[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:RISE:DELay?

[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:RISE:TIME <val>
[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:RISE:TIME?

[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:RTIMe <val>
[ :SOURce ] :RADIO:DECT:BURSt:SHAPE:RTIMe?

[ :SOURce ] :RADIO:DECT:BURSt[:TYPE] SINE|"<file name>"|
[ :SOURce ] :RADIO:DECT:BURSt[:TYPE]?

[ :SOURce ] :RADIO:DECT:BURSt[:STATE] ON|OFF|1|0
[ :SOURce ] :RADIO:DECT:BURSt[:STATE]?

[ :SOURce ] :RADIO:DECT:DATA PN9|PN11|PN15|PN20|PN23|FIX4|"<file name>"|EXT|P4|
```

ESG E44xxB Commands

Digital Function Commands

```
P8|P16|P32|P64
[:SOURce]:RADIo:DECT:DATA?
[:SOURce]:RADIo:DECT:DATA:FIX4 <val>
[:SOURce]:RADIo:DECT:DATA:FIX4?
[:SOURce]:RADIo:DECT:DEFault
[:SOURce]:RADIo:DECT:EDATA:DELay?
[:SOURce]:RADIo:DECT:EDClock SYMBol|NORMal
[:SOURce]:RADIo:DECT:EDClock?
[:SOURce]:RADIo:DECT:FILTter RNYQuist|NYQuist|GAUSSian|RECTangle|IS95|IS95_EQ|
IS95_MOD|IS95_MOD_EQ|AC4Fm|IS2000SR3DS|UGGaussian|"<user FIR>""
[:SOURce]:RADIo:DECT:FILTter?
[:SOURce]:RADIo:DECT:IQ:SCALe <val>
[:SOURce]:RADIo:DECT:IQ:SCALe?
[:SOURce]:RADIo:DECT:MODulation:FSK[:DEViation] <val>
[:SOURce]:RADIo:DECT:MODulation:FSK[:DEViation]?
[:SOURce]:RADIo:DECT:MODulation:MSK[:PHASe] <val>
[:SOURce]:RADIo:DECT:MODulation:MSK[:PHASe]?

[:SOURce]:RADIo:DECT:MODulation:UFSK "<file name>""
[:SOURce]:RADIo:DECT:MODulation:UFSK?

[:SOURce]:RADIo:DECT:MODulation:UIQ "<file name>""
[:SOURce]:RADIo:DECT:MODulation:UIQ?

[:SOURce]:RADIo:DECT:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|GRAYQPSK|
QOQPSK|IS95OQPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|FSK2|FSK4|FSK8|FSK16|
C4FM|QAM4|QAM16|QAM32|QAM64|QAM256|UIQ|UFSK
[:SOURce]:RADIo:DECT:MODulation[:TYPE]?

[:SOURce]:RADIo:DECT:POLarity[:ALL] NORMAL|INVERTed
[:SOURce]:RADIo:DECT:POLarity[:ALL]?

[:SOURce]:RADIo:DECT:PPart:SLOT0|[1]|2|3|4[:TYPE] CUSTom|TRAFFic|LCAPacity|
ZTRaffic|ZLCapacity
[:SOURce]:RADIo:DECT:PPart:SLOT0|[1]|2|3|4[:TYPE]?

[:SOURce]:RADIo:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:
CUSTom PN9|PN15|FIX4|"<file name>"|EXT|FDEV1_HS|FDEV1_FS|FDEV2_FS|FACCuracy|
DM1|DM0|P4|P8|P16|P32|P64
[:SOURce]:RADIo:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:CUSTom?
[:SOURce]:RADIo:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:CUSTom:FIX4 <val>
```

```

[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:CUSTom:FIX4?
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:A <val>
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:A?
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:P <val>
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:P?
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:S <val>
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:S?

[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:
LCAPacity[:B] PN9|PN15|FIX4|"<file name>"|EXT|FDEV1_HS|FDEV1_FS|FDEV2_FS|
FACCuracy|DM1|DM0 |P4|P8|P16|P32|P64
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity[:B]?
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity[:B]:FIX4 <val>
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity[:B]:FIX4?

[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:POWeR MAIN|DELTa
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:POWeR?

[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:STATe ON|OFF|1|0
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:STATe?

[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:A <val>
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:A?
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:P <val>
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:P?

[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:S <val>
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:S?

[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:
TRAFFic[:B] PN9|PN15|FIX4|"<file name>"|EXT|FDEV1_HS|FDEV1_FS|FDEV2_FS|
FACCuracy|DM1|DM0 |P4|P8|P16|P32|P64
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic[:B]?
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic[:B]:FIX4 <val>
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic[:B]:FIX4?

[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity:A <val>
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity:A?
[ :SOURce]:RADIO:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity:P <val>

```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity:P?  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity:S <val>  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity:S?  
  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:  
ZLCapacity[:B] PN9|PN15|FIX4|"<file name>"|EXT|FDEV1_HS|FDEV1_FS|FDEV2_FS|  
FACCuracy|DM1|DM0| P4|P8|P16|P32|P64  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity[:B]?  
  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity[:B]:  
FIX4 <val>  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity[:B]:  
FIX4?  
  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:A <val>  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:A?  
  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:P <val>  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:P?  
  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:S <val>  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:S?  
  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:  
ZTRaffic[:B] PN9|PN15|FIX4|"<file name>"|EXT|FDEV1_HS|FDEV1_FS|FDEV2_FS|  
FACCuracy|DM1|DM0| P4|P8|P16|P32|P64  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic[:B]?  
  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic[:B]:  
FIX4 <val>  
[ :SOURce]:RADio:DECT:PPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic[:B]:FIX4?  
  
[ :SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4[:TYPE] CUSTOM|DUMM[1]|DUMM2|  
TRAFFic|LCAPacity|ZTRaffic|ZLCapacity  
[ :SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4[:TYPE]?  
  
[ :SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:  
CUSTOM PN9|PN15|FIX4|"<file name>"|EXT|FDEV1_HS|FDEV1_FS|FDEV2_FS|FACCuracy|  
DM1|DM0| P4|P8|P16|P32|P64  
[ :SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:CUSTOM?  
  
[ :SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:CUSTOM:  
FIX4 <val>  
[ :SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:CUSTOM:FIX4?  
  
[ :SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM2:A <val>  
[ :SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM2:A?
```

```
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM2:P <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM2:P?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM2:S <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM2:S?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM[1]:A <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM[1]:A?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM[1]:P <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM[1]:P?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM[1]:S <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:DUMM[1]:S?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:A <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:A?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:P <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:P?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:S <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity:S?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:
LCAPacity[:B] PN9|PN15|FIX4|"<file name>"|EXT|FDEV1_HS|FDEV1_FS|FDEV2_FS|
FACCuracy|DM1|DM0| P4|P8|P16|P32|P64
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity[:B]?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity[:B]:
FIX4 <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:LCAPacity[:B]:
FIX4?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:POWer MAIN|DELTa
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:POWer?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:STATe ON|OFF|1|0
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:STATe?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:A <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:A?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:P <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:P?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:S <val>
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic:S?

[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:
```

ESG E44xxB Commands

Digital Function Commands

```
TRAFFic[:B] PN9|PN15|FIX4|"<file name>"|EXT|FDEV1_HS|FDEV1_FS|FDEV2_FS|
FACCuracy|DM1|DM0| P4|P8|P16|P32|P64
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic[:B]?
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic[:B]:
FIX4 <val>
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:TRAFFic[:B]:
FIX4?

[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:
ZLCapacity:A <val>
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity:A?
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:
ZLCapacity:P <val>
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity:P?
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:
ZLCapacity:S <val>
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity:S?
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:
ZLCapacity[:B] PN9|PN15|FIX4|"<file name>"|EXT|FDEV1_HS|FDEV1_FS|FDEV2_FS|
FACCuracy|DM1|DM0| P4|P8|P16|P32|P64
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity[:B]?
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity[:B]:
FIX4 <val>
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZLCapacity[:B]:
FIX4?

[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:A <val>
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:A?
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:P <val>
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:P?
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:S <val>
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic:S?
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:
ZTRaffic[:B] PN9|PN15|FIX4|"<file name>"|EXT|FDEV1_HS|FDEV1_FS|FDEV2_FS|
FACCuracy|DM1|DM0| P4|P8|P16|P32|P64
[:SOURce]:RADio:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic[:B]?
```

```
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic[:B]:  
FIX4 <val>  
[ :SOURce]:RADIO:DECT:RFPart:SLOT0|[1]|2|3|4|5|6|7|8|9|10|11:ZTRaffic[:B]:  
FIX4?  
[ :SOURce]:RADIO:DECT:SEConrary:RECall  
[ :SOURce]:RADIO:DECT:SEConrary:SAVE  
[ :SOURce]:RADIO:DECT:SEConrary:TRIGger[:SOURce] KEY|EXT|BUS  
[ :SOURce]:RADIO:DECT:SEConrary:TRIGger[:SOURce]?  
[ :SOURce]:RADIO:DECT:SEConrary[:STATe] ON|OFF|1|0  
[ :SOURce]:RADIO:DECT:SEConrary[:STATe]?  
[ :SOURce]:RADIO:DECT:SOUT FRAME|SLOT|ALL  
[ :SOURce]:RADIO:DECT:SOUT?  
[ :SOURce]:RADIO:DECT:SOUT:OFFSet <val>  
[ :SOURce]:RADIO:DECT:SOUT:OFFSet?  
[ :SOURce]:RADIO:DECT:SOUT:SLOT <val>  
[ :SOURce]:RADIO:DECT:SOUT:SLOT?  
[ :SOURce]:RADIO:DECT:SRATE <val>  
[ :SOURce]:RADIO:DECT:SRATE?  
[ :SOURce]:RADIO:DECT:TRIGger[:SOURce] KEY|EXT|BUS  
[ :SOURce]:RADIO:DECT:TRIGger[:SOURce]?  
[ :SOURce]:RADIO:DECT:TRIGger[:SOURce]:EXTerinal:DELay <val>  
[ :SOURce]:RADIO:DECT:TRIGger[:SOURce]:EXTerinal:DELay?  
[ :SOURce]:RADIO:DECT:TRIGger[:SOURce]:EXTerinal:DELay:STATe ON|OFF|1|0  
[ :SOURce]:RADIO:DECT:TRIGger[:SOURce]:EXTerinal:DELay:STATe?  
[ :SOURce]:RADIO:DECT[:STATe] ON|OFF|1|0  
[ :SOURce]:RADIO:DECT[:STATe]?
```

Non-Compatible Commands

```
[ :SOURce]:RADIO:DECT:CHANnel EVM|ACP  
[ :SOURce]:RADIO:DECT:CHANnel?  
[ :SOURce]:RADIO:DECT:FCHannel:BAND STANDARD  
[ :SOURce]:RADIO:DECT:FCHannel:BAND?  
[ :SOURce]:RADIO:DECT:FCHannel:NUMBER <val>  
[ :SOURce]:RADIO:DECT:FCHannel:NUMBER?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADIo:DECT:FCHannel[:STATe] ON|OFF|1|0
[ :SOURce]:RADIo:DECT:FCHannel[:STATe]?

[ :SOURce]:RADIo:DECT:REPeat SINGLE|CONTinuous
[ :SOURce]:RADIo:DECT:REPeat?

[ :SOURce]:RADIo:DECT:TRIGger[:SOURce]:EXTernal[:TYPE] SINGLE|GATE|RESET|
MANual
[ :SOURce]:RADIo:DECT:TRIGger[:SOURce]:EXTernal[:TYPE]?
```

Dual ARB Subsystem

Compatible Commands

```
[ :SOURce]:RADIo:ARB:CLIPping "<file name>",IJQ|IORQ,<10-100%>
[ :SOURce]:RADIo:ARB:CLOCK:SRATE <val>
[ :SOURce]:RADIo:ARB:CLOCK:SRATE?

[ :SOURce]:RADIo:ARB:MARKer:CLEar "<file name>",<mkr(1|2)>,<first_point>,
<last_point>
[ :SOURce]:RADIo:ARB:MARKer:CLEar:ALL "<file name>",<mkr(1|2)>
[ :SOURce]:RADIo:ARB:MARKer:POLarity NEGative|POSitive
[ :SOURce]:RADIo:ARB:MARKer:POLarity?

[ :SOURce]:RADIo:ARB:MARKer:RFBLink ON|OFF|1|0
[ :SOURce]:RADIo:ARB:MARKer:RFBLink?

[ :SOURce]:RADIo:ARB:MARKer[:SET] "<file name>",<mkr(1|2)>,<first_Point>,
<last_point>,<skip_count>
[ :SOURce]:RADIo:ARB:RETRigger 1|0
```

NOTE The above command is not recommended; the following command is the preferred syntax for the ESG E44xxB.

```
[ :SOURce]:RADIo:ARB:RETRigger ON|OFF
[ :SOURce]:RADIo:ARB:RETRigger?
```

NOTE The above query for the ESG Vector Signal Generator (E4438C) only returns the string ON or OFF. This is different from the ESG E44xxB query which returns a 1 or 0.

[:SOURce] :RADIO:ARB:RFILTER <val> | THROugh

NOTE The above command performs no function within the ESG Vector Signal Generator (E4438C), however it is accepted when executed without errors. Notice that the query form of the command is not compatible.

```
[ :SOURce ] :RADIO:ARB:SCALing "<file name>",<1%-100%>
[ :SOURce ] :RADIO:ARB:SEQUence "<file name>","<waveform>",<reps>,<mkr1(1|0)>,
<mkr2(1|0)>{,<waveform>,<rep>,<mkr1(1|0)>,<mkr2(1|0)>}
[ :SOURce ] :RADIO:ARB:SEQUence? "<file name>"
[ :SOURce ] :RADIO:ARB:TRIGger:TYPE CONTinuous|SINGle|GATE|SADVance
[ :SOURce ] :RADIO:ARB:TRIGger:TYPE?
[ :SOURce ] :RADIO:ARB:TRIGger:TYPE:GATE:ACTIVE LOW|HIGH
[ :SOURce ] :RADIO:ARB:TRIGger:TYPE:GATE:ACTIVE?
[ :SOURce ] :RADIO:ARB:TRIGger[:SOURce] KEY|EXT|BUS
[ :SOURce ] :RADIO:ARB:TRIGger[:SOURce]?
[ :SOURce ] :RADIO:ARB:TRIGger[:SOURce]:EXTernal:DELay <val>
[ :SOURce ] :RADIO:ARB:TRIGger[:SOURce]:EXTernal:DELay?
[ :SOURce ] :RADIO:ARB:TRIGger[:SOURce]:EXTernal:DELay:STATE ON|OFF|1|0
[ :SOURce ] :RADIO:ARB:TRIGger[:SOURce]:EXTernal:DELay:STATE?
[ :SOURce ] :RADIO:ARB:TRIGger[:SOURce]:EXTernal:SLOPe POSitive|NEGative
[ :SOURce ] :RADIO:ARB:TRIGger[:SOURce]:EXTernal:SLOPe?
[ :SOURce ] :RADIO:ARB:WAVeform "<file name>"
```

[:SOURce] :RADIO:ARB:WAVeform?

```
[ :SOURce ] :RADIO:ARB[:STATE] ON|OFF|1|0
[ :SOURce ] :RADIO:ARB[:STATE]?
```

Non-Compatible Commands

```
[ :SOURce] :RADio:ARB:RFILter?  
[ :SOURce] :RADio:ARB:CLOCK:REference:EXTernal:FREQuency <val>  
[ :SOURce] :RADio:ARB:CLOCK:REference:EXTernal:FREQuency?
```

NOTE Using the above command will set the external frequency value for all arb personalities. The ESG Vector Signal Generator (E4438C) has commands to set the external frequency for each arb personality. For more information on this command, see the SCPI Command Reference.

```
[ :SOURce] :RADio:ARB:CLOCK:REference[ :SOURce] INTERNAL|EXTernal  
[ :SOURce] :RADio:ARB:CLOCK:REference[ :SOURce]?
```

NOTE Using the above command will set the reference source to internal or external for all arb personalities. The ESG Vector Signal Generator (E4438C) has commands to set the reference source for each arb personality. For more information on this command, see the SCPI Command Reference.

EDGE Subsystem

Compatible Commands

```
[ :SOURce] :RADio:EDGE:ALPHa <val>  
[ :SOURce] :RADio:EDGE:ALPHa?  
  
[ :SOURce] :RADio:EDGE:BBClock INT[1]|EXT[1]  
[ :SOURce] :RADio:EDGE:BBClock?  
  
[ :SOURce] :RADio:EDGE:BBT <val>  
[ :SOURce] :RADio:EDGE:BBT?  
  
[ :SOURce] :RADio:EDGE:BNCMux:DCOut BClock|GClock  
[ :SOURce] :RADio:EDGE:BNCMux:DCOut?  
  
[ :SOURce] :RADio:EDGE:BNCMux:DOUT MDATA|EDATA  
[ :SOURce] :RADio:EDGE:BNCMux:DOUT?  
  
[ :SOURce] :RADio:EDGE:BNCMux:EVENT MTRigger|FTTrigger  
[ :SOURce] :RADio:EDGE:BNCMux:EVENT?  
  
[ :SOURce] :RADio:EDGE:BNCMux:SSOut IGAT|TBSync  
[ :SOURce] :RADio:EDGE:BNCMux:SSOut?
```

```
[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:FALL:DELay <val>
[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:FALL:DELay?

[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:FALL:TIME <val>
[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:FALL:TIME?

[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:FDELay <val>
[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:FDELay?

[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:FTIMe <val>
[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:FTIMe?

[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:RDELay <val>
[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:RDELay?

[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:RISE:DELay <val>
[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:RISE:DELay?

[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:RISE:TIME <val>
[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:RISE:TIME?

[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:RTIMe <val>
[ :SOURce ] :RADIO:EDGE:BURSt:SHAPe:RTIMe?

[ :SOURce ] :RADIO:EDGE:BURSt[:TYPE] SINE | "<file name>" 
[ :SOURce ] :RADIO:EDGE:BURSt[:TYPE]?

[ :SOURce ] :RADIO:EDGE:BURSt[:STATE] ON|OFF|1|0
[ :SOURce ] :RADIO:EDGE:BURSt[:STATE]?

[ :SOURce ] :RADIO:EDGE:DATA PN9|PN15|FIX4 | "<file name>" | EXT|P4|P8|P16|P32|P64
[ :SOURce ] :RADIO:EDGE:DATA?

[ :SOURce ] :RADIO:EDGE:DATA:FIX4 <val>
[ :SOURce ] :RADIO:EDGE:DATA:FIX4?

[ :SOURce ] :RADIO:EDGE:DEFault

[ :SOURce ] :RADIO:EDGE:EDATA:DELay?

[ :SOURce ] :RADIO:EDGE:EDClock SYMBOL|NORMAl
[ :SOURce ] :RADIO:EDGE:EDClock?

[ :SOURce ] :RADIO:EDGE:EREference ON|OFF|1|0
[ :SOURce ] :RADIO:EDGE:EREference?

[ :SOURce ] :RADIO:EDGE:FILTter RNYQuist|NYQuist|GAUSSian|RECTangle|IS95|IS95_EQ|
IS95_MOD|IS95_MOD_EQ|EDGE|AC4Fm|IS2000SR3DS|UGaussian| "<user FIR>" 
[ :SOURce ] :RADIO:EDGE:FILTter?

[ :SOURce ] :RADIO:EDGE:IQ:SCALe <val>
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:EDGE:IQ:SCALe?  
[:SOURce]:RADio:EDGE:MODulation:FSK[:DEViation] <val>  
[:SOURce]:RADio:EDGE:MODulation:FSK[:DEViation]?  
[:SOURce]:RADio:EDGE:MODulation:MSK[:PHASe] <val>  
[:SOURce]:RADio:EDGE:MODulation:MSK[:PHASe]?  
[:SOURce]:RADio:EDGE:MODulation:UFSK "<file name>"  
[:SOURce]:RADio:EDGE:MODulation:UFSK?  
[:SOURce]:RADio:EDGE:MODulation:UIQ "<file name>"  
[:SOURce]:RADio:EDGE:MODulation:UIQ?  
[:SOURce]:RADio:EDGE:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|GRAYQPSK|OQPSK|  
IS95OQPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|FSK2|FSK4|FSK8|FSK16|C4FM|QAM4|QAM16|  
QAM32|QAM64|QAM256|EDGE|UIQ|UFSK  
[:SOURce]:RADio:EDGE:MODulation[:TYPE]?  
[:SOURce]:RADio:EDGE:POLarity[:ALL] NORMal|INVerted  
[:SOURce]:RADio:EDGE:POLarity[:ALL]?  
[:SOURce]:RADio:EDGE:SECondary:RECall  
[:SOURce]:RADio:EDGE:SECondary:SAVE  
[:SOURce]:RADio:EDGE:SECondary:TRIGger[:SOURce] KEY|EXT|BUS  
[:SOURce]:RADio:EDGE:SECondary:TRIGger[:SOURce]?  
[:SOURce]:RADio:EDGE:SECondary[:STATE] ON|OFF|1|0  
[:SOURce]:RADio:EDGE:SECondary[:STATE]?  
[:SOURce]:RADio:EDGE:SLOT0|[1]|2|3|4|5|6|7:CUSTOm PN9|PN15|FIX4|  
"<file name>"|EXT|P4|P8|P16|P32|P64  
[:SOURce]:RADio:EDGE:SLOT0|[1]|2|3|4|5|6|7:CUSTOm?  
[:SOURce]:RADio:EDGE:SLOT0|[1]|2|3|4|5|6|7:CUSTOm:FIX4 <val>  
[:SOURce]:RADio:EDGE:SLOT0|[1]|2|3|4|5|6|7:CUSTOm:FIX4?  
[:SOURce]:RADio:EDGE:SLOT0|[1]|2|3|4|5|6|7:CUSTOm:GUARD <val>  
[:SOURce]:RADio:EDGE:SLOT0|[1]|2|3|4|5|6|7:CUSTOm:GUARD?  
[:SOURce]:RADio:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCRyption PN9|PN15|FIX4|  
"<file name>"|EXT|P4|P8|P16|P32|P64|DMCS9|UMCS9|DMCS5|UMCS5|ETCHF43|UNCoded  
[:SOURce]:RADio:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCRyption?  
[:SOURce]:RADio:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCRyption:DLINK:MCS5:  
DATA PN9|PN15  
[:SOURce]:RADio:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCRyption:DLINK:MCS5:DATA?
```

```
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:DLINK:MCS9:  
DATA PN9 | PN15
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:DLINK:MCS9:DATA?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:ETCH:F43:  
DATA PN9 | PN15
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:ETCH:F43:DATA?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:FIX4 <0-15>
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:FIX4?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:ULINK:MCS5:  
DATA PN9 | PN15
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:ULINK:MCS5:DATA?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:ULINK:MCS9:  
DATA PN9 | PN15
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:ULINK:MCS9:DATA?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:UNCoded PN9 | PN15
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:ENCryption:UNCoded?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:GUARD <val>
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:GUARD?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:T1 <val>
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:T1?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:T2 <val>
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:T2?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:TSEQUence TSC0|TSC1|TSC2|  
TSC3|TSC4|TSC5|TSC6|TSC7|<val>
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:NORMAl:TSEQUence?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:POWer MAIN|DELTa
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:POWer?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:STATE ON|OFF|1|0
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7:STATE?
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7[:TYPE] CUSTOM|NORMAl|NORMAL_ALL
[ :SOURce] :RADIO:EDGE:SLOT0|[1]|2|3|4|5|6|7[:TYPE]?
[ :SOURce] :RADIO:EDGE:SOUT FRAME|SLOT|ALL
[ :SOURce] :RADIO:EDGE:SOUT?
[ :SOURce] :RADIO:EDGE:SOUT:OFFSet <val>
[ :SOURce] :RADIO:EDGE:SOUT:OFFSet?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:EDGE:SOUT:SLOT <val>
[ :SOURce]:RADio:EDGE:SOUT:SLOT?

[ :SOURce]:RADio:EDGE:SRATE <val>
[ :SOURce]:RADio:EDGE:SRATE?

[ :SOURce]:RADio:EDGE:TRIGger[:SOURce] KEY|EXT|BUS
[ :SOURce]:RADio:EDGE:TRIGger[:SOURce]?

[ :SOURce]:RADio:EDGE:TRIGger[:SOURce]:EXTernal:DELay <val>
[ :SOURce]:RADio:EDGE:TRIGger[:SOURce]:EXTernal:DELay?

[ :SOURce]:RADio:EDGE:TRIGger[:SOURce]:EXTernal:DELay:STATE ON|OFF|1|0
[ :SOURce]:RADio:EDGE:TRIGger[:SOURce]:EXTernal:DELay:STATE?

[ :SOURce]:RADio:EDGE[:STATE] ON|OFF|1|0
[ :SOURce]:RADio:EDGE[:STATE]?
```

Non-Compatible Commands

```
[ :SOURce]:RADio:EDGE:CHANnel EVM|ACP
[ :SOURce]:RADio:EDGE:CHANnel?

[ :SOURce]:RADio:EDGE:FCHannel:BAND BPGSm|MPGSm|BEGSm|MEGSm|BRGSm|MRGSm|BDCS|
MDCS|BPCS|MPCS
[ :SOURce]:RADio:EDGE:FCHannel:BAND?

[ :SOURce]:RADio:EDGE:FCHannel:NUMBER <val>
[ :SOURce]:RADio:EDGE:FCHannel:NUMBER?

[ :SOURce]:RADio:EDGE:FCHannel[:STATE] ON|OFF|1|0
[ :SOURce]:RADio:EDGE:FCHannel[:STATE]?

[ :SOURce]:RADio:EDGE:REPeat SINGLE|CONTinuous
[ :SOURce]:RADio:EDGE:REPeat?

[ :SOURce]:RADio:EDGE:TRIGger[:SOURce]:EXTernal[:TYPE] SINGLE|GATE|
RESet|MANual
[ :SOURce]:RADio:EDGE:TRIGger[:SOURce]:EXTernal[:TYPE]?
```

GSM Subsystem

Compatible Commands

```
[ :SOURce]:RADio:GSM:ALPHa <val>
[ :SOURce]:RADio:GSM:ALPHa?

[ :SOURce]:RADio:GSM:BBClock INT[1]|EXT[1]
```

```
[ :SOURce ] :RADIO:GSM:BBClock?  
[ :SOURce ] :RADIO:GSM:BBT <val>  
[ :SOURce ] :RADIO:GSM:BBT?  
  
[ :SOURce ] :RADIO:GSM:BRATE <val>  
[ :SOURce ] :RADIO:GSM:BRATE?  
  
[ :SOURce ] :RADIO:GSM:BURSt:PN9 NORMAl|QUICK  
[ :SOURce ] :RADIO:GSM:BURSt:PN9?  
  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:FALL:DELay <val>  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:FALL:DELay?  
  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:FALL:TIME <val>  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:FALL:TIME?  
  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:FDELay <val>  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:FDELay?  
  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:FTIMe <val>  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:FTIMe?  
  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:RDElay <val>  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:RDElay?  
  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:RISE:DELay <val>  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:RISE:DELay?  
  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:RISE:TIME <val>  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:RISE:TIME?  
  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:RTIMe <val>  
[ :SOURce ] :RADIO:GSM:BURSt:SHAPE:RTIMe?  
  
[ :SOURce ] :RADIO:GSM:BURSt[:STATe] ON|OFF|1|0  
[ :SOURce ] :RADIO:GSM:BURSt[:STATe]?  
  
[ :SOURce ] :RADIO:GSM:DATA PN9|PN15|FIX4|"<file name>"|EXT|P4|P8|P16|P32|P64  
[ :SOURce ] :RADIO:GSM:DATA?  
  
[ :SOURce ] :RADIO:GSM:DATA:FIX4 <val>  
[ :SOURce ] :RADIO:GSM:DATA:FIX4?  
  
[ :SOURce ] :RADIO:GSM:DEFault  
  
[ :SOURce ] :RADIO:GSM:DENCode ON|OFF|1|0  
[ :SOURce ] :RADIO:GSM:DENCode?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:GSM:EDATa:DELay?  
[:SOURce]:RADio:GSM:EDClock SYMBoL|NORMal  
[:SOURce]:RADio:GSM:EDClock?  
[:SOURce]:RADio:GSM:EREference ON|OFF|1|0  
[:SOURce]:RADio:GSM:EREference?  
[:SOURce]:RADio:GSM:FILTer RNYQuist|NYQuist|GAUSSian|RECTangle|IS95|IS95_EQ|  
IS95_MOD|IS95_MOD_EQ|GSM|AC4Fm|IS2000SR3DS|UGGaussian|"<user FIR>"  
[:SOURce]:RADio:GSM:FILTer?  
[:SOURce]:RADio:GSM:IQ:SCALe <val>  
[:SOURce]:RADio:GSM:IQ:SCALe?  
[:SOURce]:RADio:GSM:MODulation:FSK[:DEViation] <val>  
[:SOURce]:RADio:GSM:MODulation:FSK[:DEViation]?  
[:SOURce]:RADio:GSM:MODulation:MSK[:PHASe] <val>  
[:SOURce]:RADio:GSM:MODulation:MSK[:PHASe]?  
[:SOURce]:RADio:GSM:MODulation:UFSK "<file name>"  
[:SOURce]:RADio:GSM:MODulation:UFSK?  
[:SOURce]:RADio:GSM:MODulation:UIQ "<file name>"  
[:SOURce]:RADio:GSM:MODulation:UIQ?  
[:SOURce]:RADio:GSM:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|GRAYQPSK|OQPSK|  
IS95OQPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|FSK2|FSK4|FSK8|FSK16|C4FM|QAM4|QAM16|  
QAM32|QAM64|QAM256|GSM|UIQ|UFSK  
[:SOURce]:RADio:GSM:MODulation[:TYPE]?  
[:SOURce]:RADio:GSM:POLarity[:ALL] NORMal|INVerted  
[:SOURce]:RADio:GSM:POLarity[:ALL]?  
[:SOURce]:RADio:GSM:SECondary:RECall  
[:SOURce]:RADio:GSM:SECondary:SAVE  
[:SOURce]:RADio:GSM:SECondary:TRIGger[:SOURce] KEY|EXT|BUS  
[:SOURce]:RADio:GSM:SECondary:TRIGger[:SOURce]?  
[:SOURce]:RADio:GSM:SECondary[:STATe] ON|OFF|1|0  
[:SOURce]:RADio:GSM:SECondary[:STATe]?  
[:SOURce]:RADio:GSM:SLOT0|[1]|2|3|4|5|6|7:ACCess:  
ENCRYption PN9|PN15|FIX4|"<file name>"|EXT|P4|P8|P16|P32|P64  
[:SOURce]:RADio:GSM:SLOT0|[1]|2|3|4|5|6|7:ACCess:ENCRYption?  
[:SOURce]:RADio:GSM:SLOT0|[1]|2|3|4|5|6|7:ACCess:ENCRYption:FIX4 <val>
```

```
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :ACCess:ENCRyption:FIX4?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :ACCess:ETAIl <val>
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :ACCess:ETAIl?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :ACCess:SSEQuence <val>
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :ACCess:SSEQuence?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :CUSTOM PN9 | PN15 | FIX4 | "<file name>" |
EXT | P4 | P8 | P16 | P32 | P64
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :CUSTOM?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :CUSTOM:FIX4 <val>
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :CUSTOM:FIX4?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :CUSTOM:DUMMy:TSEQuence TSC0 | TSC1 |
TSC2 | TSC3 | TSC4 | TSC5 | TSC6 | TSC7 | <val>
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :CUSTOM:DUMMy:TSEQuence?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :CUSTOM <val>
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :CUSTOM?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption PN9 | PN15 | FIX4 |
"<file name>" | EXT | P4 | P8 | P16 | P32 | P64 | MPN9 | MPN15 | TCHFS | CS1 | CS4 | DMCS1 | UMCS1
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:CS1:DATA PN9 | PN15
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:CS1:DATA?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:CS4:DATA PN9 | PN15
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:CS4:DATA?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:DLINK:MCS1:
DATA PN9 | PN15
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:DLINK:MCS1:DATA?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:FIX4 <0-15>
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:FIX4?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:TCH:FS:
DATA PN9 | PN15
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:TCH:FS:DATA?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:ULINK:MCS1:
DATA PN9 | PN15
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:ENCRyption:ULINK:MCS1:DATA?
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:STEal <val>
[ :SOURce ] :RADIO:GSM: SLOT0 | [1] | 2 | 3 | 4 | 5 | 6 | 7 :NORMAl:STEal?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:NORMAl:TSEQuence TSC0|TSC1|TSC2|
TSC3|TSC4|TSC5|TSC6|TSC7|<val>
[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:NORMAl:TSEQuence?
[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:POWER MAIN|DELTa
[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:POWER?

[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:STATE ON|OFF|1|0
[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:STATE?

[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRYption PN9|PN15|FIX4|
"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRYption?
[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRYption:FIX4 <val>
[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRYption:FIX4?

[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRYption:TSEQuence <val>
[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7:SYNC:ENCRYption:TSEQuence?

[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7[:TYPE] CUSTOM|NORMAL|NORMAL_ALL
[:SOURce]:RADio:GSM: SLOT0|[1]|2|3|4|5|6|7[:TYPE]?

[:SOURce]:RADio:GSM: SOUT FRAME|SLOT|ALL
[:SOURce]:RADio:GSM: SOUT?

[:SOURce]:RADio:GSM: SOUT:OFFSet <val>
[:SOURce]:RADio:GSM: SOUT:OFFSet?

[:SOURce]:RADio:GSM: SOUT:SLOT <val>
[:SOURce]:RADio:GSM: SOUT:SLOT?

[:SOURce]:RADio:GSM: SRATE <val>
[:SOURce]:RADio:GSM: SRATE?

[:SOURce]:RADio:GSM: TRIGger[:SOURce] KEY|EXT|BUS
[:SOURce]:RADio:GSM: TRIGger[:SOURce]?

[:SOURce]:RADio:GSM: TRIGger[:SOURce]: EXTERNAL:DELay <val>
[:SOURce]:RADio:GSM: TRIGger[:SOURce]: EXTERNAL:DELay?

[:SOURce]:RADio:GSM: TRIGger[:SOURce]: EXTERNAL:DELay:STATE ON|OFF|1|0
[:SOURce]:RADio:GSM: TRIGger[:SOURce]: EXTERNAL:DELay:STATE?

[:SOURce]:RADio:GSM[:STATE] ON|OFF|1|0
[:SOURce]:RADio:GSM[:STATE]?
```

Non-Compatible Commands

```
[ :SOURce]:RADio:GSM: CHANnel EVM|ACP
```

```
[ :SOURce ] :RADIO:GSM:CHANnel?  
[ :SOURce ] :RADIO:GSM:FCHannel:BAND BPGSm|MPGSm|BEGSm|MEGSm|BRGSm|MRGSm|BDCS|  
MDCS|BPCS|MPCS  
[ :SOURce ] :RADIO:GSM:FCHannel:BAND?  
[ :SOURce ] :RADIO:GSM:FCHannel:NUMBer <val>  
[ :SOURce ] :RADIO:GSM:FCHannel:NUMBer?  
[ :SOURce ] :RADIO:GSM:FCHannel[:STATe] ON|OFF|1|0  
[ :SOURce ] :RADIO:GSM:FCHannel[:STATe]?  
[ :SOURce ] :RADIO:GSM:REPeat SINGLE|CONTinuous  
[ :SOURce ] :RADIO:GSM:REPeat?  
[ :SOURce ] :RADIO:GSM:TRIGger[:SOURce]:EXTernal[:TYPE] SINGLE|GATE|  
RESET|MANual  
[ :SOURce ] :RADIO:GSM:TRIGger[:SOURce]:EXTernal[:TYPE]?
```

Input Subsystem

Compatible Commands

```
:INPut:BERT[:BASeband]:CGATe:POLarity POSitive|NEGative  
:INPut:BERT[:BASeband]:CGATe:POLarity?  
:INPut:BERT[:BASeband]:CGATe[:STATe] ON|OFF|1|0  
:INPut:BERT[:BASeband]:CGATe[:STATe]?  
:INPut:BERT[:BASeband]:CLOCK:POLarity POSitive|NEGative  
:INPut:BERT[:BASeband]:CLOCK:POLarity?  
:INPut:BERT[:BASeband]:DATA:POLarity POSitive|NEGative  
:INPut:BERT[:BASeband]:DATA:POLarity?  
:INPut:BERT[:BASeband]:IMPedance OHM_75|HIGH  
:INPut:BERT[:BASeband]:IMPedance?
```

Non-Compatible Commands

```
:INPut:BERT[:BASeband]:IMPedance TTL
```

Measure Subsystem

Compatible Commands

```
:MEASure[:SCALar]:BERT:BTS:LOOPback:EDGE:MCS5[:SENSitivity]?
```

ESG E44xxB Commands

Digital Function Commands

```
:MEASure[ :SCALar ] :BERT:BTS:LOOPback:EDGE:MCS9[:SENSitivity]?
:MEASure[ :SCALar ] :BERT:BTS:LOOPback:EDGE:UNCoded[:SENSitivity]?
:MEASure[ :SCALar ] :BERT:BTS:LOOPback:GSM[:SENSitivity]?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Multi-Tone Subsystem

Compatible Commands

```
[ :SOURce ] :RADio:MTONe:ARB:SETup "<file name>"  
[:SOURce] :RADio:MTONe:ARB:SETup?  
  
[:SOURce] :RADio:MTONe:ARB:SETup:STORe "<file name>"  
  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE <freq_spacing>,<num_tones>{,<phase>,  
<state>}  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE?  
  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE:FSPacing <freq_spacing>  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE:FSPacing?  
  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE:NTONes <num_tones>  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE:NTONes?  
  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE:PHASE:INITialize FIXed|RANDom  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE:PHASE:INITialize?  
  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE:PHASE:INITialize:SEED FIXed|RANDom  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE:PHASE:INITialize:SEED?  
  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE:ROW <row_number>,<power>,<phase>,  
<state>  
[:SOURce] :RADio:MTONe:ARB:SETup:TABLE:ROW? <row_number>  
  
[:SOURce] :RADio:MTONe:ARB[:STATE] ON|OFF|1|0  
[:SOURce] :RADio:MTONe:ARB[:STATE]?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

NADC Subsystem

Compatible Commands

```
[ :SOURce] :RADIO:NADC:BURSt:SHAPe[:TYPE] SINE| "<file name>"  
[ :SOURCe] :RADIO:NADC:BURSt:SHAPe[:TYPE]?  
  
[ :SOURce] :RADIO[:NADC]:ALPHa <val>  
[ :SOURce] :RADIO[:NADC]:ALPHa?  
  
[ :SOURce] :RADIO[:NADC]:BBClock INT[1]|EXT[1]  
[ :SOURce] :RADIO[:NADC]:BBClock?  
  
[ :SOURce] :RADIO[:NADC]:BBT <val>  
[ :SOURce] :RADIO[:NADC]:BBT?  
  
[ :SOURce] :RADIO[:NADC]:BRATe <val>  
[ :SOURce] :RADIO[:NADC]:BRATe?  
  
[ :SOURce] :RADIO[:NADC]:BURSt:PN9 NORMAl|QUICK  
[ :SOURce] :RADIO[:NADC]:BURSt:PN9?  
  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:FALL:DELay <val>  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:FALL:DELay?  
  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:FALL:TIME <val>  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:FALL:TIME?  
  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:FDELay <val>  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:FDELay?  
  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:FTIMe <val>  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:FTIMe?  
  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:RDELay <val>  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:RDELay?  
  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:RISE:DELay <val>  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:RISE:DELay?  
  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:RISE:TIME <val>  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:RISE:TIME?  
  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:RTIMe <val>  
[ :SOURce] :RADIO[:NADC]:BURSt:SHAPe:RTIMe?  
  
[ :SOURce] :RADIO[:NADC]:BURSt[:STATe] ON|OFF|1|0  
[ :SOURce] :RADIO[:NADC]:BURSt[:STATe]?  
  
[ :SOURce] :RADIO[:NADC]:CHANnel EVM|ACP
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio[ :NADC]:CHANnel?  
[:SOURce]:RADio[ :NADC]:DATA PN9|PN11|PN15|PN20|PN23|FIX4|"<file name>"|  
EXT|P4|P8|P16|P32|P64  
[:SOURce]:RADio[ :NADC]:DATA?  
[:SOURce]:RADio[ :NADC]:DATA:FIX4 <val>  
[:SOURce]:RADio[ :NADC]:DATA:FIX4?  
[:SOURce]:RADio[ :NADC]:DEFault  
[:SOURce]:RADio[ :NADC]:EDATA:DELay?  
[:SOURce]:RADio[ :NADC]:EDClock SYMBol|NORMal  
[:SOURce]:RADio[ :NADC]:EDClock?  
[:SOURce]:RADio[ :NADC]:FCHannel:BAND BASE|MOBILE  
[:SOURce]:RADio[ :NADC]:FCHannel:BAND?  
[:SOURce]:RADio[ :NADC]:FCHannel:NUMBer <number>  
[:SOURce]:RADio[ :NADC]:FCHannel:NUMBer?  
[:SOURce]:RADio[ :NADC]:FCHannel[:STATe] ON|OFF|1|0  
[:SOURce]:RADio[ :NADC]:FCHannel[:STATe]?  
[:SOURce]:RADio[ :NADC]:FILTter RNYQuist|NYQuist|GAUSSian|RECTangle|IS95|  
IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|IS2000SR3DS|UGGaussian|"<user FIR>"  
[:SOURce]:RADio[ :NADC]:FILTter?  
[:SOURce]:RADio[ :NADC]:FRATe FULL|HALF  
[:SOURce]:RADio[ :NADC]:FRATe?  
[:SOURce]:RADio[ :NADC]:IQ:SCALE <val>  
[:SOURce]:RADio[ :NADC]:IQ:SCALE?  
[:SOURce]:RADio[ :NADC]:MODulation:FSK[:DEViation] <val><unit>  
[:SOURce]:RADio[ :NADC]:MODualtion:FSK[:DEViation]?  
[:SOURce]:RADio[ :NADC]:MODulation:MSK[:PHASe] <val><unit>  
[:SOURce]:RADio[ :NADC]:MODualtion:MSK[:PHASe]?  
[:SOURce]:RADio[ :NADC]:MODulation:UFSK "<file name>"  
[:SOURce]:RADio[ :NADC]:MODualtion:UFSK?  
[:SOURce]:RADio[ :NADC]:MODulation:UIQ "<file name>"  
[:SOURce]:RADio[ :NADC]:MODualtion:UIQ?  
[:SOURce]:RADio[ :NADC]:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|GRAYQPSK|OQPSK|  
IS95OQPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|FSK2|FSK4|FSK8|FSK16|C4FM|QAM4|QAM16|  
QAM32|QAM64|QAM256|UIQ|UFSK
```

```
[ :SOURce] :RADIO[ :NADC] :MODulation[ :TYPE]?
[ :SOURce] :RADIO[ :NADC] :POLarity[ :ALL] NORMAL|INverted
[ :SOURce] :RADIO[ :NADC] :POLarity[ :ALL]?

[ :SOURce] :RADIO[ :NADC] :REPeat SINGLE|CONTinuous
[ :SOURce] :RADIO[ :NADC] :REPeat?

[ :SOURce] :RADIO[ :NADC] :SECondary:RECall
[ :SOURce] :RADIO[ :NADC] :SECondary:SAVE

[ :SOURce] :RADIO[ :NADC] :SECondary:TRIGger[ :SOURce] KEY|EXT|BUS
[ :SOURce] :RADIO[ :NADC] :SECondary:TRIGger[ :SOURce]?

[ :SOURce] :RADIO[ :NADC] :SECondary[ :STATE] ON|OFF|1|0
[ :SOURce] :RADIO[ :NADC] :SECondary[ :STATE]?

[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DCCustom PN9|PN15|FIX4|
"<file name>" | EXT|P4|P8|P16|P32|P64
[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DCCustom?

[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DCCustom:FIX4 <val>
[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DCCustom:FIX4?

[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel:CDLocator <bit_pattern>
[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel:CDLocator?

[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel:CDVCcode <bit_pattern>
[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel:CDVCcode?

[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel:SACChannel <bit_pattern>
[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel:SACChannel?

[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel:SWORD <bit_pattern>
[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel:SWORD?

[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel[ :DATA] PN9|PN15|FIX4|
"<file name>" | EXT|P4|P8|P16|P32|P64
[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel[ :DATA]?

[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel[ :DATA]:FIX4 <val>
[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:DTCHannel[ :DATA]:FIX4?

[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:POWer MAIN|DELta
[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:POWer?

[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:STATE ON|OFF|1|0
[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:STATE?

[ :SOURce] :RADIO[ :NADC] :SLOT[1] | 2 | 3 | 4 | 5 | 6:UCUStom PN9|PN15|FIX4| "<file name>" |
```

ESG E44xxB Commands

Digital Function Commands

```
EXT|P4|P8|P16|P32|P64
[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UCUSTom?
[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UCUSTom:FIX4 <val>
[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UCUSTom:FIX4?

[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:CDVCcode <bit_pattern>
[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:CDVCcode?

[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:SACChannel <bit_pattern>
[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:SACChannel?

[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:SWORD <bit_pattern>
[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel:SWORD?

[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel[:DATA] PN9|PN15|FIX4|
"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel[:DATA]?

[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel[:DATA]:FIX4 <val>
[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6:UTCHannel[:DATA]:FIX4?

[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6[:TYPE] UCUSTom|DCUSTom|UTCH|
UTCH_ALL|DTCH|DTCH_ALL
[:SOURce]:RADio[:NADC]:SLOT[1]|2|3|4|5|6[:TYPE]?

[:SOURce]:RADio[:NADC]:SOUT FRAME|SLOT|ALL
[:SOURce]:RADio[:NADC]:SOUT?

[:SOURce]:RADio[:NADC]:SOUT:OFFSet <val>
[:SOURce]:RADio[:NADC]:SOUT:OFFSet?

[:SOURce]:RADio[:NADC]:SOUT:SLOT <val>
[:SOURce]:RADio[:NADC]:SOUT:SLOT?

[:SOURce]:RADio[:NADC]:SRATe <val>
[:SOURce]:RADio[:NADC]:SRATe?

[:SOURce]:RADio[:NADC]:TRIGger[:SOURce] KEY|EXT|BUS
[:SOURce]:RADio[:NADC]:TRIGger[:SOURce]?

[:SOURce]:RADio[:NADC]:TRIGger[:SOURce]:EXTernal:DELay:STATE ON|OFF|1|0
[:SOURce]:RADio[:NADC]:TRIGger[:SOURce]:EXTernal:DELay:STATE?

[:SOURce]:RADio[:NADC]:TRIGger[:SOURce]:EXTernal[:TYPE] SINGLE|GATE|RESET|
MANual
[:SOURce]:RADio[:NADC]:TRIGger[:SOURce]:EXTernal[:TYPE]?

[:SOURce]:RADio[:NADC][:STATE] ON|OFF|1|0
[:SOURce]:RADio[:NADC][:STATE]?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

PDC Subsystem

Compatible Commands

```
[ :SOURce ] :RADIo:PDC:ALPHa <val>
[ :SOURce ] :RADIo:PDC:ALPHa?

[ :SOURce ] :RADIo:PDC:BBClock INT[1]|EXT[1]
[ :SOURce ] :RADIo:PDC:BBClock?

[ :SOURce ] :RADIo:PDC:BBT <val>
[ :SOURce ] :RADIo:PDC:BBT?

[ :SOURce ] :RADIo:PDC:BRATE <val>
[ :SOURce ] :RADIo:PDC:BRATE?

[ :SOURce ] :RADIo:PDC:BURSt:PN9 NORMAl|QUICK
[ :SOURce ] :RADIo:PDC:BURSt:PN9?

[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:FALL:DELay <val>
[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:FALL:DELay?

[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:FALL:TIME <val>
[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:FALL:TIME?

[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:FDELay <val>
[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:FDELay?

[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:FTIMe <val>
[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:FTIMe?

[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:RDELay <val>
[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:RDELay?

[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:RISE:DELay <val>
[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:RISE:DELay?

[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:RISE:TIME <val>
[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:RISE:TIME?

[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:RTIMe <val>
[ :SOURce ] :RADIo:PDC:BURSt:SHAPe:RTIMe?

[ :SOURce ] :RADIo:PDC:BURSt:SHAPe[:TYPE] SINE| "<file name>"
[ :SOURce ] :RADIo:PDC:BURSt:SHAPe[:TYPE]
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:PDC:BURSt[:STATe] ON|OFF|1|0
[ :SOURce]:RADio:PDC:BURSt[:STATe]?

[ :SOURce]:RADio:PDC:DATA PN9|PN11|PN15|PN20|PN23|FIX4|"<file name>" |
EXT|P4|P8|P16|P32|P64
[ :SOURce]:RADio:PDC:DATA?

[ :SOURce]:RADio:PDC:DATA:FIX4 <0-15>
[ :SOURce]:RADio:PDC:DATA:FIX4?

[ :SOURce]:RADio:PDC:DEFault

[ :SOURce]:RADio:PDC:EDATA:DELay?

[ :SOURce]:RADio:PDC:EDClock SYMBoL|NORMal
[ :SOURce]:RADio:PDC:EDClock?

[ :SOURce]:RADio:PDC:FILTter RNYQuist|NYQuist|GAUSSian|RECTangle|IS95|
IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|IS2000SR3DS|UGGaussian|"<user FIR>"|
[ :SOURce]:RADio:PDC:FILTter?

[ :SOURce]:RADio:PDC:FRATe FULL|HALF
[ :SOURce]:RADio:PDC:FRATe?

[ :SOURce]:RADio:PDC:IQ:SCALe <val>
[ :SOURce]:RADio:PDC:IQ:SCALe?

[ :SOURce]:RADio:PDC:MODulation:FSK[:DEViation] <val><unit>
[ :SOURce]:RADio:PDC:MODulation:FSK[:DEViation]?

[ :SOURce]:RADio:PDC:MODulation:MSK[:PHASe] <val><unit>
[ :SOURce]:RADio:PDC:MODulation:MSK[:PHASe]?

[ :SOURce]:RADio:PDC:MODulation:UFSK "<file name>"|
[ :SOURce]:RADio:PDC:MODulation:UFSK?

[ :SOURce]:RADio:PDC:MODulation:UIQ "<file name>"|
[ :SOURce]:RADio:PDC:MODulation:UIQ

[ :SOURce]:RADio:PDC:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|GRAYQPSK|
QOQPSK|IS95OQPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|FSK2|FSK4|FSK8|
FSK16|C4FM|QAM4|QAM16|QAM32|QAM64|QAM256|UIQ|UFSK
[ :SOURce]:RADio:PDC:MODulation[:TYPE]?

[ :SOURce]:RADio:PDC:POLarity[:ALL] NORMal|INVerted
[ :SOURce]:RADio:PDC:POLarity[:ALL]?

[ :SOURce]:RADio:PDC:SECondary:RECall
[ :SOURce]:RADio:PDC:SECondary:SAVE
```

```
[ :SOURce ] :RADIO:PDC:SECondary:TRIGger[:SOURce] KEY|EXT|BUS
[ :SOURce ] :RADIO:PDC:SECondary:TRIGger[:SOURce]?

[ :SOURce ] :RADIO:PDC:SECondary[:STATE] ON|OFF|1|0
[ :SOURce ] :RADIO:PDC:SECondary[:STATE]?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DCUSTom PN9|PN15|FIX4|
"<file name>"|EXT|P4|P8|P16|P32|P64
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DCUSTom?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DCUSTom:FIX4 <0-15>
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DCUSTom:FIX4?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DTCHannel:CCODE <bit_pattern>
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DTCHannel:CCODE?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DTCHannel:SACChannel <bit_pattern>
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DTCHannel:SACChannel?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DTCHannel:SWORD <bit_pattern>
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DTCHannel:SWORD?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DTCHannel[:TCHannel] PN9|PN15|
FIX4|"<file name>"|EXT|P4|P8|P16|P32|P64
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DTCHannel[:TCHannel]?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DTCHannel[:TCHannel]:FIX4 <0-15>
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:DTCHannel[:TCHannel]:FIX4?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:POWER MAIN|DELTA
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:POWER?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:STATE ON|OFF|1|0
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:STATE?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:UCUSTom PN9|PN15|FIX4|
"<file name>"|EXT|P4|P8|P16|P32|P64
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:UCUSTom?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:UCUSTom:FIX4 <0-15>
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:UCUSTom:FIX4?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:UTCChannel:CCODE <bit_pattern>
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:UTCChannel:CCODE?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:UTCChannel:SACChannel <bit_pattern>
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:UTCChannel:SACChannel?

[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:UTCChannel:SWORD <bit_pattern>
[ :SOURce ] :RADIO:PDC:SLOT0|[1]|2|3|4|5:UTCChannel:SWORD?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel[:TChannel] PN9|PN15|
FIX4|"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel[:TChannel]?
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel[:TChannel]:FIX4 <0-15>
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UTCHannel[:TChannel]:FIX4?

[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UVOX:CCODE <bit_pattern>
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UVOX:CCODE?

[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UVOX:SACChannel <bit_pattern>
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UVOX:SACChannel?

[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UVOX:SWORD <bit_pattern>
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5:UVOX:SWORD?

[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5[:TYPE] UCUSTOM|DCUSTOM|UTCH|
UTCH_ALL|UVOX|DTCH|DTCH_ALL
[:SOURce]:RADio:PDC:SLOT0|[1]|2|3|4|5[:TYPE]?

[:SOURce]:RADio:PDC:SOUT FRAME|SLOT|ALL
[:SOURce]:RADio:PDC:SOUT?

[:SOURce]:RADio:PDC:SOUT:OFFSet <val>
[:SOURce]:RADio:PDC:SOUT:OFFSet?

[:SOURce]:RADio:PDC:SOUT:SLOT <val>
[:SOURce]:RADio:PDC:SOUT:SLOT?

[:SOURce]:RADio:PDC:SRATE <val>
[:SOURce]:RADio:PDC:SRATE?

[:SOURce]:RADio:PDC:TRIGger[:SOURce] KEY|EXT|BUS
[:SOURce]:RADio:PDC:TRIGger[:SOURce]?

[:SOURce]:RADio:PDC:TRIGger[:SOURce]:EXTernal:DELay <val>
[:SOURce]:RADio:PDC:TRIGger[:SOURce]:EXTernal:DELay?

[:SOURce]:RADio:PDC:TRIGger[:SOURce]:EXTernal:DELay:STATe ON|OFF|1|0
[:SOURce]:RADio:PDC:TRIGger[:SOURce]:EXTernal:DELay:STATe?

[:SOURce]:RADio:PDC[:STATE] ON|OFF|1|0
[:SOURce]:RADio:PDC[:STATE]?
```

Non-Compatible Commands

```
[ :SOURce]:RADio:PDC:CHANnel EVM|ACP
[:SOURce]:RADio:PDC:CHANnel?

[:SOURce]:RADio:PDC:FCHannel:BAND B8|M8|B15|M15
```

```
[ :SOURce ] :RADIO:PDC:FChannel:BAND?  
[ :SOURce ] :RADIO:PDC:FChannel:NUMBer <number>  
[ :SOURce ] :RADIO:PDC:FChannel:NUMBer?  
[ :SOURce ] :RADIO:PDC:FChannel[:STATe] ON|OFF|1|0  
[ :SOURce ] :RADIO:PDC:FChannel[:STATe]?  
[ :SOURce ] :RADIO:PDC:REPeat SINGLE|CONTinuous  
[ :SOURce ] :RADIO:PDC:REPeat?  
[ :SOURce ] :RADIO:PDC:TRIGger[:SOURce]:EXTernal[:TYPE] SINGLE|GATE|RESet  
[ :SOURce ] :RADIO:PDC:TRIGger[:SOURce]:EXTernal[:TYPE]?
```

PHS Subsystem

Compatible Commands

```
[ :SOURce ] :RADIO:PHS:ALPHA <val>  
[ :SOURce ] :RADIO:PHS:ALPHA?  
[ :SOURce ] :RADIO:PHS:BBClock INT[1]|EXT[1]  
[ :SOURce ] :RADIO:PHS:BBClock?  
[ :SOURce ] :RADIO:PHS:BBT <val>  
[ :SOURce ] :RADIO:PHS:BBT?  
[ :SOURce ] :RADIO:PHS:BRATE <val>  
[ :SOURce ] :RADIO:PHS:BRATE?  
[ :SOURce ] :RADIO:PHS:BURSt:PN9 NORMAL|QUICK  
[ :SOURce ] :RADIO:PHS:BURSt:PN9?  
[ :SOURce ] :RADIO:PHS:BURSt:SCRamble:SEED <16-bit val>  
[ :SOURce ] :RADIO:PHS:BURSt:SCRamble:SEED?  
[ :SOURce ] :RADIO:PHS:BURSt:SCRamble[:STATe] ON|OFF|1|0  
[ :SOURce ] :RADIO:PHS:BURSt:SCRamble[:STATe]?  
[ :SOURce ] :RADIO:PHS:BURSt:SHAPE:FALL:DELay <val>  
[ :SOURce ] :RADIO:PHS:BURSt:SHAPE:FALL:DELay?  
[ :SOURce ] :RADIO:PHS:BURSt:SHAPE:FALL:TIME <val>  
[ :SOURce ] :RADIO:PHS:BURSt:SHAPE:FALL:TIME?  
[ :SOURce ] :RADIO:PHS:BURSt:SHAPE:FDELay <val>  
[ :SOURce ] :RADIO:PHS:BURSt:SHAPE:FDELay?  
[ :SOURce ] :RADIO:PHS:BURSt:SHAPE:FTIME <val>
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:PHS:BURSt:SHAPe:FTIMe?  
[:SOURce]:RADio:PHS:BURSt:SHAPe:RDELay <val>  
[:SOURce]:RADio:PHS:BURSt:SHAPe:RDELay?  
[:SOURce]:RADio:PHS:BURSt:SHAPe:RISE:DELay <val>  
[:SOURce]:RADio:PHS:BURSt:SHAPe:RISE:DELay?  
[:SOURce]:RADio:PHS:BURSt:SHAPe:RISE:TIME <val>  
[:SOURce]:RADio:PHS:BURSt:SHAPe:RISE:TIME?  
[:SOURce]:RADio:PHS:BURSt:SHAPe:RTIMe <val>  
[:SOURce]:RADio:PHS:BURSt:SHAPe:RTIMe?  
[:SOURce]:RADio:PHS:BURSt[:TYPE] SINE| "<file name>"  
[:SOURce]:RADio:PHS:BURSt[:TYPE]?  
[:SOURce]:RADio:PHS:BURSt[:STATe] ON|OFF|1|0  
[:SOURce]:RADio:PHS:BURSt[:STATe]?  
[:SOURce]:RADio:PHS:DATA PN9|PN11|PN15|PN20|PN23|FIX4| "<file name>" |EXT|P4|  
P8|P16|P32|P64  
[:SOURce]:RADio:PHS:DATA?  
[:SOURce]:RADio:PHS:DATA:FIX4 <val>  
[:SOURce]:RADio:PHS:DATA:FIX4?  
[:SOURce]:RADio:PHS:DEFault  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:CUSTom PN9|PN15|FIX4| "<file name>" |  
EXT|P4|P8|P16|P32|P64  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:CUSTom?  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:CUSTom:FIX4 <val>  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:CUSTom:FIX4?  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:POWER MAIN|DELTa  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:POWER?  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:SCHannel:CSID <bit_pattern>  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:SCHannel:CSID?  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:SCHannel:IDLE <bit_pattern>  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:SCHannel:IDLE?  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:SCHannel:PSID <bit_pattern>  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:SCHannel:PSID?  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:SCHannel:UWORD <bit_pattern>  
[:SOURce]:RADio:PHS:DLINK:SLOT[1]|2|3|4:SCHannel:UWORD?
```

```
[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4]:STATE ON|OFF|1|0
[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4]:STATE?

[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4]:TCHannel:SACChannel <bit_pattern>
[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4]:TCHannel:SACChannel?

[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4]:TCHannel:UWORD <bit_pattern>
[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4]:TCHannel:UWORD?

[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4]:TCHannel[:TCHannel] PN9|PN15|FIX4|
"<file name>"|EXT|P4|P8|P16|P32|P64
[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4]:TCHannel[:TCHannel]?

[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4]:TCHannel[:TCHannel]:FIX4 <val>
[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4]:TCHannel[:TCHannel]:FIX4?

[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4][:TYPE] CUSTOM|TCH|TCH_ALL|SYNC
[ :SOURce ] :RADIO:PHS:DLINK:SLOT[1|2|3|4][:TYPE]?

[ :SOURce ] :RADIO:PHS:EDATA:DELay?
[ :SOURce ] :RADIO:PHS:EDClock SYMBoL|NORMal
[ :SOURce ] :RADIO:PHS:EDClock?

[ :SOURce ] :RADIO:PHS:FILTter RNYQuist|NYQuist|GAUSSian|RECTangle|IS95|IS95_EQ|
IS95_MOD|IS95_MOD_EQ|AC4Fm|IS2000SR3DS|UGGaussian|"<user FIR>"
[ :SOURce ] :RADIO:PHS:FILTter?

[ :SOURce ] :RADIO:PHS:IQ:SCALe <val>
[ :SOURce ] :RADIO:PHS:IQ:SCALe?

[ :SOURce ] :RADIO:PHS:MODulation:FSK[:DEViation] <val><unit>
[ :SOURce ] :RADIO:PHS:MODulation:FSK[:DEViation]?

[ :SOURce ] :RADIO:PHS:MODulation:MSK[:PHASe] <val><unit>
[ :SOURce ] :RADIO:PHS:MODulation:MSK[:PHASe]?

[ :SOURce ] :RADIO:PHS:MODulation:UFSK "<file name>" 
[ :SOURce ] :RADIO:PHS:MODulation:UFSK?

[ :SOURce ] :RADIO:PHS:MODulation:UIQ "<file name>" 
[ :SOURce ] :RADIO:PHS:MODulation:UIQ?

[ :SOURce ] :RADIO:PHS:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|GRAYQPSK|OQPSK|
IS95OQPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|FSK2|FSK4|FSK8|FSK16|C4FM|QAM4|QAM16|
QAM32|QAM64|QAM256|UIQ|UFSK
[ :SOURce ] :RADIO:PHS:MODulation[:TYPE]?

[ :SOURce ] :RADIO:PHS:POLarity[:ALL] NORMal|INVerted
[ :SOURce ] :RADIO:PHS:POLarity[:ALL]?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:PHS:SECondary:RECall
[ :SOURce]:RADio:PHS:SECondary:SAVE
[ :SOURce]:RADio:PHS:SECondary:TRIGger[:SOURce] KEY|EXT|BUS
[ :SOURce]:RADio:PHS:SECondary:TRIGger[:SOURce]?
[ :SOURce]:RADio:PHS:SECondary[:STATe] ON|OFF|1|0
[ :SOURce]:RADio:PHS:SECondary[:STATe]?

[ :SOURce]:RADio:PHS:SOUT FRAME|SLOT|ALL
[ :SOURce]:RADio:PHS:SOUT?

[ :SOURce]:RADio:PHS:SOUT:OFFSet <val>
[ :SOURce]:RADio:PHS:SOUT:OFFSet?

[ :SOURce]:RADio:PHS:SOUT:SLOT <val>
[ :SOURce]:RADio:PHS:SOUT:SLOT?

[ :SOURce]:RADio:PHS:SRATE <val>
[ :SOURce]:RADio:PHS:SRATE?

[ :SOURce]:RADio:PHS:TRIGger[:SOURce] KEY|EXT|BUS
[ :SOURce]:RADio:PHS:TRIGger[:SOURce]?

[ :SOURce]:RADio:PHS:TRIGger[:SOURce]:EXTernal:DELay <val>
[ :SOURce]:RADio:PHS:TRIGger[:SOURce]:EXTernal:DELay?

[ :SOURce]:RADio:PHS:TRIGger[:SOURce]:EXTernal:DELay:STATe ON|OFF|1|0
[ :SOURce]:RADio:PHS:TRIGger[:SOURce]:EXTernal:DELay:STATe?

[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:CUSTom PN9|PN15|FIX4|"<file name>" |
EXT|P4|P8|P16|P32|P64
[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:CUSTom?

[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:CUSTom:FIX4 <val>
[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:CUSTom:FIX4?

[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:POWER MAIN|DELTa
[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:POWER?

[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:SCHannel:CSID <bit_pattern>
[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:SCHannel:CSID?

[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:SCHannel:IDLE <bit_pattern>
[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:SCHannel:IDLE?

[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:SCHannel:PSID <bit_pattern>
[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:SCHannel:PSID?

[ :SOURce]:RADio:PHS:ULINK:SLOT[1]|2|3|4:SCHannel:UWORD <bit_pattern>
```

```
[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4]:SCHannel:UWORD?
[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4]:STATE ON|OFF|1|0
[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4]:STATE?

[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4]:TCHannel:SACChannel <bit_pattern>
[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4]:TCHannel:SACChannel?

[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4]:TCHannel:UWORD <bit_pattern>
[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4]:TCHannel:UWORD?

[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4]:TCHannel[:TCHannel] PN9|PN15|FIX4|
"<file name>"|EXT|P4|P8|P16|P32|P64
[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4]:TCHannel[:TCHannel]?

[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4]:TCHannel[:TCHannel]:FIX4 <val>
[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4]:TCHannel[:TCHannel]:FIX4?

[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4][:TYPE] CUSTOM|TCH|TCH_ALL|SYNC
[ :SOURce ] :RADIO:PHS:ULINK:SLOT[1|2|3|4][:TYPE]?

[ :SOURce ] :RADIO:PHS[:STATE] ON|OFF|1|0
[ :SOURce ] :RADIO:PHS[:STATE]?
```

Non-Compatible Commands

```
[ :SOURce ] :RADIO:PHS:CHANnel EVM|ACP
[ :SOURce ] :RADIO:PHS:CHANnel?

[ :SOURce ] :RADIO:PHS:FCHannel:BAND STANDARD
[ :SOURce ] :RADIO:PHS:FCHannel:BAND?

[ :SOURce ] :RADIO:PHS:FCHannel:NUMBer <number>
[ :SOURce ] :RADIO:PHS:FCHannel:NUMBer?

[ :SOURce ] :RADIO:PHS:FCHannel[:STATE] ON|OFF|1|0
[ :SOURce ] :RADIO:PHS:FCHannel[:STATE]?

[ :SOURce ] :RADIO:PHS:REPeat SINGLE|CONTinuous
[ :SOURce ] :RADIO:PHS:REPeat?

[ :SOURce ] :RADIO:PHS:TRIGger[:SOURCE]:EXTernal[:TYPE] SINGLE|GATE|RESET|MANual
[ :SOURce ] :RADIO:PHS:TRIGger[:SOURCE]:EXTernal[:TYPE]?
```

Sense Subsystem

Compatible Commands

```
:SENSe:BERT:BTS:LOOPback:EDGE:FTrigger:DELay <val>
```

ESG E44xxB Commands
Digital Function Commands

```
:SENSe:BTS:LOOPback:EDGE:FTRigger:DELay?  
:SENSe:BTS:LOOPback:EDGE:FTRigger:POLarity POSitive|NEGative  
:SENSe:BTS:LOOPback:EDGE:FTRigger:POLarity?  
:SENSe:BTS:LOOPback:EDGE:MCS5:BLOCK:COUNT <val>  
:SENSe:BTS:LOOPback:EDGE:MCS5:BLOCK:COUNT?  
:SENSe:BTS:LOOPback:EDGE:MCS5:CONTain ON|OFF|1|0  
:SENSe:BTS:LOOPback:EDGE:MCS5:CONTain?  
:SENSe:BTS:LOOPback:EDGE:MCS5:ESENSitivity <val>  
:SENSe:BTS:LOOPback:EDGE:MCS5:ESENSitivity?  
:SENSe:BTS:LOOPback:EDGE:MCS5:HAMPLitude <val><unit>  
:SENSe:BTS:LOOPback:EDGE:MCS5:HAMPLitude?  
:SENSe:BTS:LOOPback:EDGE:MCS5:LAMPLitude <val><unit>  
:SENSe:BTS:LOOPback:EDGE:MCS5:LAMPLitude?  
:SENSe:BTS:LOOPback:EDGE:MCS5:PAMPLitude <val><unit>  
:SENSe:BTS:LOOPback:EDGE:MCS5:PAMPLitude?  
:SENSe:BTS:LOOPback:EDGE:MCS5:SBlock:COUNt <val>  
:SENSe:BTS:LOOPback:EDGE:MCS5:SBlock:COUNt?  
:SENSe:BTS:LOOPback:EDGE:MCS5:SBlock:INITial <val>  
:SENSe:BTS:LOOPback:EDGE:MCS5:SBlock:INITial?  
:SENSe:BTS:LOOPback:EDGE:MCS5:STOP:CRITeria:EBLock <val>  
:SENSe:BTS:LOOPback:EDGE:MCS5:STOP:CRITeria:EBLock?  
:SENSe:BTS:LOOPback:EDGE:MCS5:STOP:CRITeria[:SELECT] EBLOCK|NONE  
:SENSe:BTS:LOOPback:EDGE:MCS5:STOP:CRITeria[:SELECT]?  
:SENSe:BTS:LOOPback:EDGE:MCS9:BLOCK:COUNT <val>  
:SENSe:BTS:LOOPback:EDGE:MCS9:BLOCK:COUNT?  
:SENSe:BTS:LOOPback:EDGE:MCS9:CONTain ON|OFF|1|0  
:SENSe:BTS:LOOPback:EDGE:MCS9:CONTain?  
:SENSe:BTS:LOOPback:EDGE:MCS9:ESENSitivity <val>  
:SENSe:BTS:LOOPback:EDGE:MCS9:ESENSitivity?  
:SENSe:BTS:LOOPback:EDGE:MCS9:HAMPLitude <val><unit>  
:SENSe:BTS:LOOPback:EDGE:MCS9:HAMPLitude?  
:SENSe:BTS:LOOPback:EDGE:MCS9:LAMPLitude <val><unit>  
:SENSe:BTS:LOOPback:EDGE:MCS9:LAMPLitude?
```

```
:SENSe:BERT:BTS:LOOPback:EDGE:MCS9:PAMplitude?  
:SENSe:BERT:BTS:LOOPback:EDGE:MCS9:SBLock:COUNT <val>  
:SENSe:BERT:BTS:LOOPback:EDGE:MCS9:SBLock:COUNT?  
:SENSe:BERT:BTS:LOOPback:EDGE:MCS9:SBLock:INITial <val>  
:SENSe:BERT:BTS:LOOPback:EDGE:MCS9:SBLock:INITial?  
:SENSe:BERT:BTS:LOOPback:EDGE:MCS9:STOP:CRITeria:EBLock <val>  
:SENSe:BERT:BTS:LOOPback:EDGE:MCS9:STOP:CRITeria:EBLock?  
:SENSe:BERT:BTS:LOOPback:EDGE:MCS9:STOP:CRITeria[:SElect] EBLock|NONE  
:SENSe:BERT:BTS:LOOPback:EDGE:MCS9:STOP:CRITeria[:SElect]?  
:SENSe:BERT:BTS:LOOPback:EDGE:MEASurement:STOP  
:SENSe:BERT:BTS:LOOPback:EDGE:MEASurement:TSLot 0|1|2|3|4|5|6|7  
:SENSe:BERT:BTS:LOOPback:EDGE:MEASurement:TSLot?  
:SENSe:BERT:BTS:LOOPback:EDGE:MEASurement[:MODE] BLER|SSEarch  
:SENSe:BERT:BTS:LOOPback:EDGE:MEASurement[:MODE]?  
:SENSe:BERT:BTS:LOOPback:EDGE:SINVert ON|OFF|1|0  
:SENSe:BERT:BTS:LOOPback:EDGE:SINVert?  
:SENSe:BERT:BTS:LOOPback:EDGE:SYNC:AGAin  
:SENSe:BERT:BTS:LOOPback:EDGE:SYNC:RF  
:SENSe:BERT:BTS:LOOPback:EDGE:SYNC[:SOURCE] BCH|PDCH  
:SENSe:BERT:BTS:LOOPback:EDGE:SYNC[:SOURCE]?  
:SENSe:BERT:BTS:LOOPback:EDGE:TRIGger[:SOURce] IMMEDIATE|KEY|EXT|BUS  
:SENSe:BERT:BTS:LOOPback:EDGE:TRIGger[:SOURce]?  
:SENSe:BERT:BTS:LOOPback:EDGE:ULINK:OFFSet <val>  
:SENSe:BERT:BTS:LOOPback:EDGE:ULINK:OFFSet?  
:SENSe:BERT:BTS:LOOPback:EDGE:UNCoded:BIT:COUNT <val>  
:SENSe:BERT:BTS:LOOPback:EDGE:UNCoded:BIT:COUNT?  
:SENSe:BERT:BTS:LOOPback:EDGE:UNCoded:ESENSitivity <val>  
:SENSe:BERT:BTS:LOOPback:EDGE:UNCoded:ESENSitivity?  
:SENSe:BERT:BTS:LOOPback:EDGE:UNCoded:HAMPLitude <val><unit>  
:SENSe:BERT:BTS:LOOPback:EDGE:UNCoded:HAMPLitude?  
:SENSe:BERT:BTS:LOOPback:EDGE:UNCoded:LAMPLitude <val><unit>  
:SENSe:BERT:BTS:LOOPback:EDGE:UNCoded:LAMPLitude?  
:SENSe:BERT:BTS:LOOPback:EDGE:UNCoded:PAMplitude <val><unit>
```

ESG E44xxB Commands

Digital Function Commands

```
:SENSe:BTS:LOOPback:EDGE:UNCoded:PAMplitude?  
:SENSe:BTS:LOOPback:EDGE:UNCoded:SBIT:COUNT <val>  
:SENSe:BTS:LOOPback:EDGE:UNCoded:SBIT:COUNT?  
:SENSe:BTS:LOOPback:EDGE:UNCoded:SBIT:INITial <val>  
:SENSe:BTS:LOOPback:EDGE:UNCoded:SBIT:INITial?  
:SENSe:BTS:LOOPback:EDGE:UNCoded:STOP:CRITERia:EBIT <val>  
:SENSe:BTS:LOOPback:EDGE:UNCoded:STOP:CRITERia:EBIT?  
:SENSe:BTS:LOOPback:EDGE:UNCoded:STOP:CRITERia[:SElect] EBIT|NONE  
:SENSe:BTS:LOOPback:EDGE:UNCoded:STOP:CRITERia[:SElect]?  
:SENSe:BTS:LOOPback:EDGE[:STATE] ON|OFF|1|0  
:SENSe:BTS:LOOPback:EDGE[:STATE]?  
:SENSe:BTS:LOOPback:GSM:ESENsitivity <val>  
:SENSe:BTS:LOOPback:GSM:ESENsitivity?  
:SENSe:BTS:LOOPback:GSM:FRAMe:CIB?  
:SENSe:BTS:LOOPback:GSM:FRAMe:CII?  
:SENSe:BTS:LOOPback:GSM:FRAMe:COUNT <val>  
:SENSe:BTS:LOOPback:GSM:FRAMe:COUNT?  
:SENSe:BTS:LOOPback:GSM:HAMPplitude <val><unit>  
:SENSe:BTS:LOOPback:GSM:HAMPplitude?  
:SENSe:BTS:LOOPback:GSM:MEASurement:STOP  
:SENSe:BTS:LOOPback:GSM:MEASurement:TSLOT 0|1|2|3|4|5|6|7  
:SENSe:BTS:LOOPback:GSM:MEASurement:TSLOT?  
:SENSe:BTS:LOOPback:GSM:MEASurement[:MODE] BER|SSEarch  
:SENSe:BTS:LOOPback:GSM:MEASurement[:MODE]?  
:SENSe:BTS:LOOPback:GSM:PAMplitude <val><unit>  
:SENSe:BTS:LOOPback:GSM:PAMplitude?  
:SENSe:BTS:LOOPback:GSM:SFRame:COUNT <val>  
:SENSe:BTS:LOOPback:GSM:SFRame:COUNT?  
:SENSe:BTS:LOOPback:GSM:SFRame:INITial <val>  
:SENSe:BTS:LOOPback:GSM:SFRame:INITial?  
:SENSe:BTS:LOOPback:GSM:SINVert ON|OFF|1|0
```

```
:SENSe:BERT:BTS:LOOPback:GSM:SINVert?  
:SENSe:BERT:BTS:LOOPback:GSM:STOP:CRITeria:CIB <val>  
:SENSe:BERT:BTS:LOOPback:GSM:STOP:CRITeria:CIB?  
:SENSe:BERT:BTS:LOOPback:GSM:STOP:CRITeria:CII <val>  
:SENSe:BERT:BTS:LOOPback:GSM:STOP:CRITeria:CII?  
:SENSe:BERT:BTS:LOOPback:GSM:STOP:CRITeria:FERasure <val>  
:SENSe:BERT:BTS:LOOPback:GSM:STOP:CRITeria:FERasure?  
:SENSe:BERT:BTS:LOOPback:GSM:STOP:CRITeria[:SElect] FERasure|CLIB|CLII|ANY|  
NONE  
:SENSe:BERT:BTS:LOOPback:GSM:STOP:CRITeria[:SElect]?  
:SENSe:BERT:BTS:LOOPback:GSM:SYNC:RF  
:SENSe:BERT:BTS:LOOPback:GSM:SYNC[:SOURce] BCH|TCH  
:SENSe:BERT:BTS:LOOPback:GSM:SYNC[:SOURce]?  
:SENSe:BERT:BTS:LOOPback:GSM:TRIGger[:SOURce] IMMEDIATE|KEY|EXT|BUS  
:SENSe:BERT:BTS:LOOPback:GSM:TRIGger[:SOURce]?  
:SENSe:BERT:BTS:LOOPback:GSM:ULINK:OFFSet <val>  
:SENSe:BERT:BTS:LOOPback:GSM:ULINK:OFFSet?  
:SENSe:BERT:BTS:LOOPback:GSM[:STATe] ON|OFF|1|0  
:SENSe:BERT:BTS:LOOPback:GSM[:STATe]?  
:SENSe:BERT[:BASeband]:PRBS:FUNCTION:SPIgnore:DATA ALL_0|ALL_1  
:SENSe:BERT[:BASeband]:PRBS:FUNCTION:SPIgnore:DATA?  
:SENSe:BERT[:BASeband]:PRBS:FUNCTION:SPIgnore[:STATe] ON|OFF|1|0  
:SENSe:BERT[:BASeband]:PRBS:FUNCTION:SPIgnore[:STATe]?  
:SENSe:BERT[:BASeband]:PRBS[:DATA] PN9|PN15  
:SENSe:BERT[:BASeband]:PRBS[:DATA]?  
:SENSe:BERT[:BASeband]:RSYNc:THreshold <val>  
:SENSe:BERT[:BASeband]:RSYNc:THreshold?  
:SENSe:BERT[:BASeband]:RSYNc[:STATe] ON|OFF|1|0  
:SENSe:BERT[:BASeband]:RSYNc[:STATe]?  
:SENSe:BERT[:BASeband]:STATE ON|OFF|1|0  
:SENSe:BERT[:BASeband]:STATE?  
:SENSe:BERT[:BASeband]:TBITS <val>  
:SENSe:BERT[:BASeband]:TBITS?  
:SENSe:BERT[:BASeband]:TRIGger:BDELay <val>
```

ESG E44xxB Commands

Digital Function Commands

```
:SENSe:BERT[:BASEband]:TRIGger:BDELay?  
:SENSe:BERT[:BASEband]:TRIGger:BDELay:STATE ON|OFF|1|0  
:SENSe:BERT[:BASEband]:TRIGger:BDELay:STATE?  
  
:SENSe:BERT[:BASEband]:TRIGger:COUNt <val>  
:SENSe:BERT[:BASEband]:TRIGger:COUNt?  
  
:SENSe:BERT[:BASEband]:TRIGger[:SOURce] IMMEDIATE|KEY|EXT|BUS  
:SENSe:BERT[:BASEband]:TRIGger[:SOURce]?
```

Non-Compatible Commands

```
:SENSe:BERT[:BASEband]:PRBS:MDRate BPS_2M|BPS_10M  
:SENSe:BERT[:BASEband]:PRBS:MDRate?
```

TETRA Subsystem

Compatible Commands

```
[ :SOURce]:RADio:TETRa:ALPHa <val>  
[ :SOURce]:RADio:TETRa:ALPHa?  
  
[ :SOURce]:RADio:TETRa:BBClock INT[1]|EXT[1]  
[ :SOURce]:RADio:TETRa:BBClock?  
  
[ :SOURce]:RADio:TETRa:BBT <val>  
[ :SOURce]:RADio:TETRa:BBT?  
  
[ :SOURce]:RADio:TETRa:BRATe <val>  
[ :SOURce]:RADio:TETRa:BRATe?  
  
[ :SOURce]:RADio:TETRa:BURSt:PN9 NORMAL|QUICK  
[ :SOURce]:RADio:TETRa:BURSt:PN9?  
  
[ :SOURce]:RADio:TETRa:BURSt:SCRamble:SEED <val>  
[ :SOURce]:RADio:TETRa:BURSt:SCRamble:SEED?  
  
[ :SOURce]:RADio:TETRa:BURSt:SCRamble[:STATe] ON|OFF|1|0  
[ :SOURce]:RADio:TETRa:BURSt:SCRamble[:STATe]?  
  
[ :SOURce]:RADio:TETRa:BURSt:SHAPe:FALL:DELay <val>  
[ :SOURce]:RADio:TETRa:BURSt:SHAPe:FALL:DELay?  
  
[ :SOURce]:RADio:TETRa:BURSt:SHAPe:FALL:TIME <val>  
[ :SOURce]:RADio:TETRa:BURSt:SHAPe:FALL:TIME?  
  
[ :SOURce]:RADio:TETRa:BURSt:SHAPe:FDELay <val>  
[ :SOURce]:RADio:TETRa:BURSt:SHAPe:FDELay?
```

```
[ :SOURce ] :RADIO:TETRa:BURSt:SHAPe:FTIMe <val>
[ :SOURce ] :RADIO:TETRa:BURSt:SHAPe:FTIMe?

[ :SOURce ] :RADIO:TETRa:BURSt:SHAPe:RDELay <val>
[ :SOURce ] :RADIO:TETRa:BURSt:SHAPe:RDELay?

[ :SOURce ] :RADIO:TETRa:BURSt:SHAPe:RISE:DELay <val>
[ :SOURce ] :RADIO:TETRa:BURSt:SHAPe:RISE:DELay?

[ :SOURce ] :RADIO:TETRa:BURSt:SHAPe:RISE:TIME <val>
[ :SOURce ] :RADIO:TETRa:BURSt:SHAPe:RISE:TIME?

[ :SOURce ] :RADIO:TETRa:BURSt:SHAPe:RTIMe <val>
[ :SOURce ] :RADIO:TETRa:BURSt:SHAPe:RTIMe?

[ :SOURce ] :RADIO:TETRa:BURSt[:TYPE] SINE | "<file name>" 
[ :SOURce ] :RADIO:TETRa:BURSt[:TYPE]?

[ :SOURce ] :RADIO:TETRa:BURSt[:STATe] ON|OFF|1|0
[ :SOURce ] :RADIO:TETRa:BURSt[:STATe]?

[ :SOURce ] :RADIO:TETRa:DATA PN9|PN11|PN15|PN20|PN23|FIX4|"<file name>"|EXT|P4|
P8|P16|P32|P64
[ :SOURce ] :RADIO:TETRa:DATA?
```



```
[ :SOURce ] :RADIO:TETRa:DATA:FIX4 <val>
[ :SOURce ] :RADIO:TETRa:DATA:FIX4?

[ :SOURce ] :RADIO:TETRa:DEFault

[ :SOURce ] :RADIO:TETRa:EDATA:DELay?

[ :SOURce ] :RADIO:TETRa:EDClock SYMBOL|NORMAL
[ :SOURce ] :RADIO:TETRa:EDClock?
```



```
[ :SOURce ] :RADIO:TETRa:FILTter RNYQuist|NYQuist|GAUSSian|RECTangle|IS95|
IS95_EQ|IS95_MOD_EQ|AC4Fm|UGGaussian|"<user FIR>" 
[ :SOURce ] :RADIO:TETRa:FILTter?
```



```
[ :SOURce ] :RADIO:TETRa:IQ:SCALe <val>
[ :SOURce ] :RADIO:TETRa:IQ:SCALe?

[ :SOURce ] :RADIO:TETRa:MODulation:FSK[:DEVIation] <val><unit>
[ :SOURce ] :RADIO:TETRa:MODulation:FSK[:DEVIation]?

[ :SOURce ] :RADIO:TETRa:MODulation:MSK[:PHASe] <val><unit>
[ :SOURce ] :RADIO:TETRa:MODulation:MSK[:PHASe]?
```



```
[ :SOURce ] :RADIO:TETRa:MODulation:UFSK "<file name>" 
[ :SOURce ] :RADIO:TETRa:MODulation:UFSK?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADIo:TETRa:MODulation:UIQ "<file name>"  
[:SOURce]:RADIo:TETRa:MODulation:UIQ?  
  
[:SOURce]:RADIo:TETRa:MODulation[:TYPE] BPSK|QPSK|IS95QPSK|GRAYQPSK|OQPSK|  
IS950QPSK|P4DQPSK|PSK8|PSK16|D8PSK|MSK|FSK2|FSK4|FSK8|FSK16|C4FM|QAM4|QAM16|  
QAM32|QAM64|QAM256|UIQ|UFSK  
[:SOURce]:RADIo:TETRa:MODulation[:TYPE]?  
  
[:SOURce]:RADIo:TETRa:POLarity[:ALL] NORMal|INVerted  
[:SOURce]:RADIo:TETRa:POLarity[:ALL]?  
  
[:SOURce]:RADIo:TETRa:SECondary:RECall  
  
[:SOURce]:RADIo:TETRa:SECondary:SAVE  
  
[:SOURce]:RADIo:TETRa:SECondary:TRIGger[:SOURCE] KEY|EXT|BUS  
[:SOURce]:RADIo:TETRa:SECondary:TRIGger[:SOURCE]?  
  
[:SOURce]:RADIo:TETRa:SECondary[:STATe] ON|OFF|1|0  
[:SOURce]:RADIo:TETRa:SECondary[:STATe]?  
  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCCustom PN9|PN15|FIX4|"<file name>"|  
EXT|P4|P8|P16|P32|P64  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCCustom?  
  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCCustom:FIX4 <val>  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCCustom:FIX4?  
  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCNormal:B1 <14 bit value>  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCNormal:B1?  
  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCNormal:B2 <16 bit value>  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCNormal:B2?  
  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCNormal:TSEQUence <30 bit value>  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCNormal:TSEQUence?  
  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCNormal[:DATA] PN9|PN15|FIX4|  
"<file name>"|EXT|P4|P8|P16|P32|64  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCNormal[:DATA]?  
  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCNormal[:DATA]:FIX4 <val>  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCNormal[:DATA]:FIX4?  
  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCSync:B <30 bit value>  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCSync:B?  
  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCSync:FCOR <80 bit value>  
[:SOURce]:RADIo:TETRa:SLOT[1]|2|3|4:DCSync:FCOR?
```

```

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync:SSB <120 bit value>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync:SSB?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync:STS <38 bit value>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync:STS?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync[:DATA] PN9|PN15|FIX4|
"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync[:DATA]?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync[:DATA]:FIX4 <val>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DCSync[:DATA]:FIX4?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDCustom PN9|PN15|FIX4|"<file name>"|EXT|
P4|P8|P16|P32|P64
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDCustom?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDCustom:FIX4 <val>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDCustom:FIX4?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:B1 <14 bit value>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:B1?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:B2 <16 bit value>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:B2?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:TSEQUENCE <30 bit value>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal:TSEQUENCE?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal[:DATA]
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal[:DATA]?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal[:DATA]:FIX4 <val>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDNormal[:DATA]:FIX4?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDSync:B <30 bit value>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDSync:B?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDSync:FCOR <80 bit value>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDSync:FCOR?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDSync:SSB <120 bit value>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDSync:SSB?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDSync:STS <38 bit value>
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDSync:STS?

[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDSync[:DATA] PN9|PN15|FIX4|
"<file name>"|EXT|P4|P8|P16|P32|P64
[:SOURce]:RADIO:TETRA:SLOT[1]|2|3|4:DDSync[:DATA]?

```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:TETRa:SLOT[1]|2|3|4:DDSync[:DATA]:FIX4 <val>
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:DDSync[:DATA]:FIX4?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:POWeR MAIN|DELTa
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:POWeR?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:STATe ON|OFF|1|0
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:STATe?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UC1[:DATA] PN9|PN15|FIX4|"<file name>" |
EXT|P4|P8|P16|P32|P64
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UC1[:DATA]?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UC1[:DATA]:FIX4 <val>
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UC1[:DATA]:FIX4?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UC2:TSEQuence <30 bit value>
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UC2:TSEQuence?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UC2[:DATA] PN9|PN15|FIX4|"<file name>" |
EXT|P4|P8|P16|P32|P64
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UC2[:DATA]?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UC2[:DATA]:FIX4 <val>
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UC2[:DATA]:FIX4?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UCUStom PN9|PN15|FIX4|"<file name>" |
EXT|P4|P8|P16|P32|P64
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UCUStom?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UCUStom:FIX4 <val>
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UCUStom:FIX4?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UNORmal:TSEQuence <22 bit value>
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UNORmal:TSEQuence?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UNORmal[:DATA] PN9|PN15|FIX4|
"<file name>" |EXT|P4|P8|P16|P32|P64
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UNORmal[:DATA]?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UNORmal[:DATA]:FIX4 <val>
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4:UNORmal[:DATA]:FIX4?

[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4[:TYPE] UCUStom|UC1|UC2|UNORmal|DDNormal |
DDSync|DCNormal|DCSync|DCCustom|DDCustom
[:SOURce]:RADio:TETRa:SLOT[1]|2|3|4[:TYPE]?

[:SOURce]:RADio:TETRa:SOUT FRAME|SLOT|ALL
[:SOURce]:RADio:TETRa:SOUT?
```

```
[ :SOURce ] :RADIO:TETRa:SOUT:OFFSet <val>
[ :SOURce ] :RADIO:TETRa:SOUT:OFFSet?

[ :SOURce ] :RADIO:TETRa:SOUT:SLOT <val>
[ :SOURce ] :RADIO:TETRa:SOUT:SLOT?

[ :SOURce ] :RADIO:TETRa:SRATE <val>
[ :SOURce ] :RADIO:TETRa:SRATE?

[ :SOURce ] :RADIO:TETRa:TRIGger[ :SOURce ] KEY|EXT|BUS
[ :SOURce ] :RADIO:TETRa:TRIGger[ :SOURce ]?

[ :SOURce ] :RADIO:TETRa:TRIGger[ :SOURce ]:EXTernal:DELay <val>
[ :SOURce ] :RADIO:TETRa:TRIGger[ :SOURce ]:EXTernal:DELay?

[ :SOURce ] :RADIO:TETRa:TRIGger[ :SOURce ]:EXTernal:DELay:STATE ON|OFF|1|0
[ :SOURce ] :RADIO:TETRa:TRIGger[ :SOURce ]:EXTernal:DELay:STATE?

[ :SOURce ] :RADIO:TETRa[:STATE] ON|OFF|1|0
[ :SOURce ] :RADIO:TETRa[:STATE]?
```

Non-Compatible Commands

```
[ :SOURce ] :RADIO:TETRa:CHANnel EVM|ACP
[ :SOURce ] :RADIO:TETRa:CHANnel?

[ :SOURce ] :RADIO:TETRa:FChannel:BAND B390|B420|B460|B915|M380|M410|M450|M870
[ :SOURce ] :RADIO:TETRa:FChannel:BAND?

[ :SOURce ] :RADIO:TETRa:FChannel:NUMBer <number>
[ :SOURce ] :RADIO:TETRa:FChannel:NUMBer?

[ :SOURce ] :RADIO:TETRa:FChannel[:STATE] ON|OFF|1|0
[ :SOURce ] :RADIO:TETRa:FChannel[:STATE]?

[ :SOURce ] :RADIO:TETRa:FILTER IS2000SR3DS

[ :SOURce ] :RADIO:TETRa:REPeat SINGLE|CONTinuous
[ :SOURce ] :RADIO:TETRa:REPeat?

[ :SOURce ] :RADIO:TETRa:TRIGger[ :SOURce ]:EXTernal[:TYPE] SINGLE|GATE|RESet|
MANual
[ :SOURce ] :RADIO:TETRa:TRIGger[ :SOURce ]:EXTernal[:TYPE]?
```

Wideband CDMA ARB Subsystem

Compatible Commands

```
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:CLIPping:I <val>
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:WCDMa:TGPP:ARB:CLIPping:I?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:CLIPping:POSITION PRE|POST  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:CLIPping:POSITION?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:CLIPping:Q <val>  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:CLIPping:Q?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:CLIPping:TYPE IJQ|IORQ  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:CLIPping:TYPE?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:CLIPping[:IJQ] <val>  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:CLIPping[:IJQ]?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:CRATe <val>  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:CRATe?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:FILTter RNYQuist|NYQuist|GAUSSian|RECTangle|  
WCDMA|AC4Fm|IS2000SR3DS|UGaussian|"<user FIR>"  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:FILTter?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:FILTter:ALPHA <val>  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:FILTter:ALPHA?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:FILTter:BBT <val>  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:FILTter:BBT?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:FILTter:CHANnel EVM|ACP  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:FILTter:CHANnel?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:IQMap NORMal|INVerted  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:IQMap?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:LINK DOWN|UP  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:LINK?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:LINK:DOWN:SETup DPCH1|DPCH3|PPSCH|PPDPCH1|  
PPDPCH3|TM1D16|TM1D32|TM1D64|TM2|TM3D16|TM3D32|TM4|MCArrier|"<file name>"  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:LINK:DOWN:SETup?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:LINK:DOWN:SETup:MCARrier CAR2|CAR3|CAR4|  
"<file name>"  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:LINK:DOWN:SETup:MCARrier?  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:LINK:DOWN:SETup:MCARrier:STORE "<file name>"  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:LINK:DOWN:SETup:MCARrier:TABLE INIT|APPend|  
<carrier_num>,DPCH1|DPCH3|PPSCH|PPDPCH1|PPDPCH3|TM1D16|TM1D32|TM1D64|TM2|  
TM3D16|TM3D32|"<file name>",<freq_offset>,<power>  
[ :SOURce]:RADio:WCDMa:TGPP:ARB:LINK:DOWN:SETup:MCARrier:TABLE? <carrier_num>
```

```
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:DOWN:SETup:MCARrier:TABLE:NCARriers?  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:DOWN:SETup:STORE "<file name>"  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:DOWN:SETup:TABLE:APPLY  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:DOWN:SETup:TABLE:CHANnel INIT|APPend|  
<chan_num>, <chan_type>, <symbol_rate>, <spread_code>, <power>, <tDPCH_offset>,  
<TFCI>, <TPC>, <scramble_code>, STANDARD|RALTernate|LALTernate,  
<scramble_offset>, RANDOM|PN9|PINDicator|<data_val>, <TFCI_power>, <TPC_power>,  
<pilot_power>, <pilot_bits>  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:DOWN:SETup:TABLE:CHANnel? <chan_num>  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:DOWN:SETup:TABLE:NChannels?  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:DOWN:SETup:TABLE:PADJust EQUal|SCALE  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:DOWN:TFCI ON|OFF|1|0  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:DOWN:TFCI?  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SCRamble <val>  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SCRamble?  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SDPDch I|Q  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SDPDch?  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SETup DPCCH|DDPDCH1|DDPDCH2|DDPDCH3|  
DDPDCH4|DDPDCH5|<file name>"  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SETup?  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SETup:STORE "<file name>"  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SETup:TABLE:APPLY  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SETup:TABLE:CHANnel INIT|APPend|  
<chan_num>, <chan_type>, <symbol_rate>, <spread_code>, <power>, <TFCI>, <TPC>,|  
RANDOM|<data_VAL>, <fbi_bits_count>, <fbi_bits_value>  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SETup:TABLE:CHANnel? <chan_num>  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SETup:TABLE:GUNIT DB|LINEar|INDEX  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SETup:TABLE:GUNIT?  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:SETup:TABLE:NChannels?  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:TFCI ON|OFF|1|0  
[ :SOURce ] :RADIO:WCDMa:TGPP:ARB:LINK:UP:TFCI?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :RETRigger 1 | 0
```

NOTE The above command is not recommended; the following command is the preferred syntax for the ESG E44xxB.

```
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :RETRigger ON | OFF  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :RETRigger?
```

NOTE The above query for the ESG Vector Signal Generator (E4438C) only returns the string ON or OFF. This is different from the ESG E44xxB query which returns a 1 or 0.

```
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :REVision?  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger :TYPE CONT | SINGLE | GATE  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger :TYPE?  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger :TYPE :GATE :ACTive LOW | HIGH  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger :TYPE :GATE :ACTive?  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger [ :SOURce ] KEY | EXT | BUS  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger [ :SOURce ]?  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger [ :SOURce ] :EXTernal :DELay <val>  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger [ :SOURce ] :EXTernal :DELay?  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger [ :SOURce ] :EXTernal :DELay :STATE ON | OFF |  
1 | 0  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger [ :SOURce ] :EXTernal :DELay :STATE?  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger [ :SOURce ] :EXTernal :SLOPe POSitive |  
NEGative  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB :TRIGger [ :SOURce ] :EXTernal :SLOPe?  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB [ :STATe ] ON | OFF | 1 | 0  
[ :SOURce ] :RADio :WCDMa :TGPP :ARB [ :STATe ]?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Wideband CDMA BBG Subsystem

Compatible Commands

```
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :BBClock INT[1] | EXT[1]
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :BBClock?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :BBClock:EXT:POLarity POSitive|NEGative
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :BBClock:EXT:POLarity?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :BBClock:EXT:RATE X1|X2|X3|X4
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :BBClock:EXT:RATE

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:APPLY
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:APPLY?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:CPICh:CCODE?
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:CPICh:POWer <val>
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:CPICh:POWer?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:CPICh[:STATe] ON|OFF|1|0
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:CPICh[:STATe]?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:CRATE <val>
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:CRATE?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :BLKSize <val>
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :BLKSize?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :BPFRame?
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :BRATE?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :CODE HCONv|TCONv|
TURBo|NONE
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :CODE?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :CRC 0|8|12|16|24
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :CRC?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA PN9|FIX4|
"<file name>""
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:FIX4 <val>
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:FIX4?

[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :NBLocks <val>
[ :SOURce] :RADIO:WCDMa:TGPP[ :BBG] :DLINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :NBLocks?
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DCH[1|2|3|4|5|6]:PPERcentage?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DCH[1|2|3|4|5|6]:RMATch <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DCH[1|2|3|4|5|6]:RMATch?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DCH[1|2|3|4|5|6]:TTI 10000|20000|  
40000|80000  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DCH[1|2|3|4|5|6]:TTI?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DCH[1|2|3|4|5|6[:STATE] ON|OFF|1|0  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DCH[1|2|3|4|5|6[:STATE]?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:CCODE <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:CCODE?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:DATA PN9|PN15|FIX4|  
"<file name>" |TRANspch  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:DATA?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:DATA:FIX4 <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:DATA:FIX4?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:POWER <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:POWER?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:SLOTformat <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:SLOTformat?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:SRATE?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:SSCodeos <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:SSCodeos?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:TFCI:PATTern <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:TFCI:PATTern?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:TOFFset <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:TOFFset?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:TPC:NUMSteps <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:TPC:NUMSteps?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:TPC:PATTern UDOWn|DUP|  
UALL|DALL  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2]:TPC:PATTern?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2[:STATE] ON|OFF|1|0  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:DPCH[1|2[:STATE]?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:FILTer RNYQuist|NYQuist|GAUSSian|
```

```

RECTangle|IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian| "<user FIR>"  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:FILTter?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:FILTter:ALPHa <val>  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:FILTter:ALPHa?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:FILTter:BBT <val>  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:FILTter:BBT?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:FILTter:CHANnel <EVM|ACP>  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:FILTter:CHANnel?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4:CCODE <val>  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4:CCODE?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4:POWER <val>  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4:POWER?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4:SRATE 7.5|15|30|60|120|  

240|480|960  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4:SRATE?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4:DATA PN9|PN15  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4:DATA?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4:SSCodeos <val>  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4:SSCodeos?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4[:STATE] ON|OFF|1|0  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:OCNS[1]|2|3|4[:STATE]?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PCCPch:BCHData PN9|PN15|FIX4|  

"<file name>"|TRANspch  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PCCPch:BCHData?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PCCPch:BCHData:FIX4 <val>  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PCCPch:BCHData:FIX4?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PCCPch:CCODE <val>  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PCCPch:CCODE?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PCCPch:POWER <val>  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PCCPch:POWER?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PCCPch[:STATE] ON|OFF|1|0  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PCCPch[:STATE]?  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PICH:CCODE <val>  

[ :SOURce]:RADIO:WCDMa:TGPP[:BBG]:DLINK:PICH:CCODE?

```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH:DATA PN9|PN15|FIX4|
"<file name>"  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH:DATA?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH:DATA:FIX4 <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH:DATA:FIX4?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH:PIBits?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH:PIndicator?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH:POWer <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH:POWer?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH[:STATE] ON|OFF|1|0  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PICH[:STATE]?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PSCH:POWer <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PSCH:POWer?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PSCH[:STATE] ON|OFF|1|0  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:PSCH[:STATE]?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:SCRamblecode <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:SCRamblecode?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:SSCH:POWer <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:SSCH:POWer?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:SSGRoup?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:SSCH[:STATE] ON|OFF|1|0  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:DLINK:SSCH[:STATE]?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:LINK DOWN|UP  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:LINK?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:POLarity[:ALL] NORMal|INVerted  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:POLarity[:ALL]?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:ULINK:APPLY  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:ULINK:APPLY?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:ULINK:CRATE <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:ULINK:CRATE?  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:ULINK:DCH[1|2|3|4|5|6:BLKSize <val>  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:ULINK:DCH[1|2|3|4|5|6:BLKSize]  
[:SOURce]:RADio:WCDMa:TGPP[:BBG]:ULINK:DCH[1|2|3|4|5|6:CODE HCONv|TCONv|
TURBo|NONE
```

```
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :CODE?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :CRC <val>
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :CRC?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA PN9|FIX4|
"<file name>" 
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:BER:ACTual?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:BER:ERRor:BIT?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:BER:TOTal:BIT?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:
BER[ :VALue ] <val>
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:BER[ :VALue ]?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:BLER:ACTual?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:BLER:ERRor:
BLOCK?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:BLER:TOTal:
BLOCK?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:
BLER[ :VALue ] <val>
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:BLER[ :VALue ]?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:EINSert BLER|
BER|NONE
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:EINSert?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:FIX4 <val>
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :DATA:FIX4?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :NBLock <val>
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :NBLock?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :RMATch <val>
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :RMATch?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :TTI <val>
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6 :TTI?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6[:STATE] ON|OFF|1|0
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DCH[1] | 2 | 3 | 4 | 5 | 6[:STATE]?
[ :SOURce ] :RADIO:WCDMa:TGPP[ :BBG ] :ULINK:DPCCh:BETA <val>
```

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:BETA?  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:CCODE <val>  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:CCODE?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:FBI:PATTern PN9|PN15|FIX|  
"<file name>"  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:FBI:PATTern?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:FBI:FIX <val>  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:FBI:FIX?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:FBI[:STATE]?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:POWer <val>  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:POWer?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:RATE?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:SLOTformat <val>  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:SLOTformat?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TFCI:PATTern PN9|PN15|FIX|  
"<file name>"  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TFCI:PATTern?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TFCI:FIX <val>  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TFCI:FIX?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TFCI[:STATE]?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TPC:NSTeps <val>  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TPC:NSTeps?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TPC:PATTern PN9|PN15|FIX4|  
"<file name>" | UDOW | DUP | UALL | DALL  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TPC:PATTern?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TPC:PATTern:FIX4 <val>  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TPC:PATTern:FIX4?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TPC:PATTern:TRIGger:  
POLarity POSitive|NEGative  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TPC:PATTern:TRIGger:POLarity?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TPC:PATTern:TRIGger[:STATE] ON|  
OFF|1|0  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh:TPC:PATTern:TRIGger[:STATE]?  
  
[:SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:DPCCh[:STATE] ON|OFF|1|0
```

[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPCCh[:STATE] ?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:BETA <val>
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:BETA?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:CCODE <val>
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:CCODE?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:DATA PN9|PN15|FIX4|"
" <file name>" |TRANSpch
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:DATA?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:DATA:FIX4 <val>
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:DATA:FIX4?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:POWer <val>
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:POWer?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:RATE <val>
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:RATE?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:SLOTformat <val>
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh:SLOTformat?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh[:STATE] ON|OFF|1|0
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:DPDCh[:STATE] ?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:FCLock:INTerval FCL10|FCL20|
FCL40|FCL80
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:FCLock:INTerval?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:FCLock:POLarity POSitive|NEGative
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:FCLock:POLarity?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:FILTER RNYQuist|NYQuist|GAUSSian|
RECTangle|IS95|IS95_EQ|IS95_MOD|IS95_MOD_EQ|AC4Fm|UGGaussian|" <user FIR>"
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:FILTER?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:FILTER:BBT <val>
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:FILTER:BBT?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:FILTER:CHANnel EVM|ACP
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:FILTER:CHANnel?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:PADJust EQUal|SCALE
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:SCRamblecode <val>
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:SCRamblecode?
[:SOURce] :RADIO:WCDMA:TGPP[:BBG] :ULINK:SDELay <val>

ESG E44xxB Commands

Digital Function Commands

```
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:SDELay?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:SFNRst:POLarity POSitive|NEGative  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:SFNRst:POLarity?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:SYNC:MODE SINGLE|CONTinuous  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:SYNC:MODE?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:SYNC[ :SOURce] SFN_RST|FClock  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:SYNC[ :SOURce]?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:TOFFset <val>  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :ULINK:TOFFset?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] [:STATe] ON|OFF|1|0  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] [:STATe]?
```

Non-Compatible Commands

```
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:CCODE <val>  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:CCODE?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:DATA PN9|PN15|FIX4|  
" <file name>" | TRANspch  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:DATA?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:DATA:FIX4 <val>  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:DATA:FIX4?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:POWer <val>  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:POWer?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:SLOTformat <val>  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:SLOTformat?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:SRATE?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:SSCodeos <val>  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:SSCodeos?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:TFCI:PATTern <val>  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:TFCI:PATTern?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:TOFFset <val>  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:TOFFset?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:TPC:NUMSteps <val>  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:TPC:NUMSteps?  
[ :SOURce] :RADio:WCDMa:TGPP[ :BBG] :DLINK:DPCH3 | 4:TPC:PATTern UDOWn|DUP|
```

UALL|DALL
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:DLINK:DPCH3|4:TPC:PATTern?
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:DLINK:DPCH3|4[:STATe] ON|OFF|1|0
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:DLINK:DPCH3|4[:STATe]?
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:DLINK:RCSetup REF122|REF64|REF144|REF384|
AMR122|UDI64|ISDN
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:DLINK:RCSetup?
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:IQ:PPoWer? <val>
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:IQ:PPPaired <val>
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:IQ:PPPaired?
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:IQ:SCALe <val>
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:IQ:SCALe?
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:IQ:TVOLtage?
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:IQ:TVPaired <val>
[:SOURce]:RADIo:WCDMa:TGPP[:BBG]:IQ:TVPaired?

4 8648A/B/C/D Commands

System Function Commands

IEEE Common Commands

Compatible Commands

```
*RST?  
*IDN?  
*TST?  
*WAI?  
*CLS?  
*ESE <dec. num. data>  
*ESE?  
*OPC  
*OPC?  
*RCL <reg_num>[,<seq_num>]  
*SAV <reg_num>[,<seq_num>]  
*SRE <dec. num. data>  
*SRE?  
*STB?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Status Subsystem

Compatible Commands

```
[ :SOURce ] :STATus:QUESTIONable:POWeR:CONDition?  
[ :SOURce ] :STATus:QUESTIONable:POWeR:ENABLE <NR1>  
[ :SOURce ] :STATus:QUESTIONable:POWeR:ENABLE?  
[ :SOURce ] :STATus:QUESTIONable:POWeR:EVENT?
```

```
[ :SOURce ] :STATUs :QUEStionable :MODulation :CONDition?  
[ :SOURce ] :STATUs :QUEStionable :MODulation :ENABLE <NR1>  
[ :SOURce ] :STATUs :QUEStionable :MODulation :ENABLE?  
[ :SOURce ] :STATUs :QUEStionable :MODulation :EVENT?  
[ :SOURce ] :STATUs :QUEStionable :CALibration :FEXTension[ :EVENT ]?  
[ :SOURce ] :STATUs :QUEStionable :CALibration :FEXTension :CONDition?  
[ :SOURce ] :STATUs :QUEStionable :CALibration :FEXTension :ENABLE <NR1>  
[ :SOURce ] :STATUs :QUEStionable :CALibration :FEXTension :ENABLE?
```

Non-Compatible Commands

```
[ :SOURce ] :STATUs :QUEStionable :PAGing :CONDition?  
[ :SOURce ] :STATUs :QUEStionable :PAGing :ENABLE <NR1>  
[ :SOURce ] :STATUs :QUEStionable :PAGing :ENABLE?  
[ :SOURce ] :STATUs :QUEStionable :PAGing :EVENT?
```

System Subsystem

Compatible Commands

```
[ :SOURce ] :SYSTem :LANGuage "COMP" | "SCPI"  
[ :SOURce ] :SYSTem :LANGuage?  
[ :SOURce ] :SYSTem :ERRor?  
[ :SOURce ] :SYSTem :VERSion?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Analog Function Commands

Amplitude Subsystem

Compatible Commands

```
[ :SOURce ] :OUTPut :STATE ON|OFF
[ :SOURce ] :OUTPut :STATE?

[ :SOURce ] :POWER :AMPLitude <val><units>
[ :SOURce ] :POWER :AMPLitude?

[ :SOURce ] :POWER :ATTenuation :AUTO ON|OFF
[ :SOURce ] :POWER :ATTenuation :AUTO?

[ :SOURce ] :POWER :REFerence <val><units>
[ :SOURce ] :POWER :REFerence?

[ :SOURce ] :POWER :REFerence :STATE ON|OFF
[ :SOURce ] :POWER :REFerence :STATE?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Frequency Subsystem

Compatible Commands

```
[ :SOURce ] :FREQuency :CW <val><units>
[ :SOURce ] :FREQuency :CW?

[ :SOURce ] :FREQuency :REFerence <val><units>
[ :SOURce ] :FREQuency :REFerence?

[ :SOURce ] :FREQuency :REFerence :STATE ON|OFF
[ :SOURce ] :FREQuency :REFerence :STATE?
```

Non-Compatible Commands

There are no non-compatible SCPI commands for this subsystem.

Amplitude Modulation Subsystem

Compatible Commands

```
[ :SOURce ] :AM:DEPTh <val>PCT
[ :SOURce ] :AM:DEPTh?

[ :SOURce ] :AM:STATE ON|OFF
[ :SOURce ] :AM:STATE?

[ :SOURce ] :AM:SOURce INTernal[1]|2
[ :SOURce ] :AM:SOURce INTernal|EXTernal
[ :SOURce ] :AM:SOURce?

[ :SOURce ] :AM:INTernal:FREQuency 1kHz
[ :SOURce ] :AM:INTernal:FREQuency 400Hz

[ :SOURce ] :AM:INTernal:FREQuency?

[ :SOURce ] :AM:INTernal2:FREQuency <val><units>
[ :SOURce ] :AM:INTernal2:FREQuency?

[ :SOURce ] :AM:INTernal2:FUNCTION:SHAPe TRIangle|SQUARE|SINE
[ :SOURce ] :AM:INTernal2:FUNCTION:SHAPe?

[ :SOURce ] :AM:EXTernal:COUpling AC|DC
[ :SOURce ] :AM:EXTernal:COUpling?
```

Non-Compatible Commands

```
[ :SOURce ] :AM:INTernal2:FUNCTION:SHAPe SAW
```

Frequency Modulation Subsystem

Compatible Commands

```
[ :SOURce ] :CALibration:DCFm
[ :SOURce ] :FM:DEViation <val>kHz
[ :SOURce ] :FM:DEViation?

[ :SOURce ] :FM:STATE ON|OFF
[ :SOURce ] :FM:STATE?

[ :SOURce ] :FM:SOURce INTernal[1]|2
[ :SOURce ] :FM:SOURce INTernal|EXTernal
```

8648A/B/C/D Commands

Analog Function Commands

```
[ :SOURce]:FM:SOURce?  
[:SOURce]:FM:INTERNAL:FREQuency 1kHz  
[:SOURce]:FM:INTERNAL:FREQuency 400Hz  
[:SOURce]:FM:INTERNAL:FREQuency?  
[:SOURce]:FM:INTERNAL2:FREQuency <val><units>  
[:SOURce]:FM:INTERNAL2:FREQuency?  
[:SOURce]:FM:INTERNAL2:FUNCTION:SHAPE TRIangle|SQUARE|SINE  
[:SOURce]:FM:INTERNAL2:FUNCTION:SHAPE?  
[:SOURce]:FM:EXTERNAL:COUPLING AC|DC  
[:SOURce]:FM:EXTERNAL:COUPLING?
```

Non-Compatible Commands

```
[ :SOURce]:FM:INTERNAL2:FUNCTION:SHAPE SAW
```

Phase Modulation Subsystem

Compatible Commands

```
[ :SOURce]:PM:DEVIATION <val>RAD  
[:SOURce]:PM:DEVIATION?  
[:SOURce]:PM:STATE ON|OFF  
[:SOURce]:PM:STATE?  
[:SOURce]:PM:SOURce INTERNAL[1]|2  
[:SOURce]:PM:SOURce INTERNAL|EXTERNAL  
[:SOURce]:PM:SOURce?  
[:SOURce]:PM:INTERNAL:FREQuency 1kHz  
[:SOURce]:PM:INTERNAL:FREQuency 400Hz  
[:SOURce]:PM:INTERNAL:FREQuency?  
[:SOURce]:PM:INTERNAL2:FREQuency <val><units>  
[:SOURce]:PM:INTERNAL2:FREQuency?  
[:SOURce]:PM:INTERNAL2:FUNCTION:SHAPE TRIangle|SQUARE|SINE  
[:SOURce]:PM:INTERNAL2:FUNCTION:SHAPE?  
[:SOURce]:PM:EXTERNAL:COUPLING AC|DC  
[:SOURce]:PM:EXTERNAL:COUPLING?
```

Non-Compatible Commands

[:SOURce] :PM:INTernal2:FUNCTION:SHAPe SAW

Pulse Modulation Subsystem

Compatible Commands

[:SOURce] :PULM:STATE ON|OFF

[:SOURce] :PULM:STATE?

Non-Compatible Commands

[:SOURce] :INITiate:IMMediate

[:SOURce] :ABORT

[:SOURce] :TRIGger:COUNT <val>

[:SOURce] :TRIGger:COUNT?

[:SOURce] :DM:FORMAT FSK2|FSK4

[:SOURce] :DM:FORMAT?

[:SOURce] :DM:STATE ON|OFF

[:SOURce] :DM:STATE?

[:SOURce] :DM:DEViation <val>

[:SOURce] :DM:DEViation?

[:SOURce] :DM:POLarity NORMAL|INVert

[:SOURce] :DM:POLarity?

[:SOURce] :DM:FILTTER:STATE ON|OFF

[:SOURce] :DM:FILTTER:STATE?

[:SOURce] :PAGing:SElect POCS|FLEX|FTD|RESY|PN15

[:SOURce] :PAGing:SElect?

[:SOURce] :PAGing:{POCS|FLEX|FTD|PN15}:RATE <val>

[:SOURce] :PAGing:{POCS|FLEX|FTD|PN15}:RATE?

[:SOURce] :PAGing:{POCS|FLEX|FTD}:MESSAge:SElect <val>

[:SOURce] :PAGing:{POCS|FLEX|FTD}:MESSAge:SElect?

[:SOURce] :PAGing:{POCS|FLEX|FTD}:MESSAge:DEFine "string"

[:SOURce] :PAGing:{POCS|FLEX|FTD}:MESSAge:DEFine?

[:SOURce] :PAGing:{POCS|FLEX|FTD}:MESSAge:LENGTH <val>

[:SOURce] :PAGing:{POCS|FLEX|FTD}:MESSAge:LENGTH?

Analog Function Commands

```
[ :SOURce]:PAGing:{POCS|FLEX|FTD}:ARBitrary:DEFine <val>,...<val(n)>
[ :SOURce]:PAGing:{POCS|FLEX|FTD}:ARBitrary:STARt <val>
[ :SOURce]:PAGing:{POCS|FLEX|FTD}:ARBitrary:STARt?
[ :SOURce]:PAGing:{POCS|FLEX|FTD}:ARBitrary:STOP <val>
[ :SOURce]:PAGing:{POCS|FLEX|FTD}:ARBitrary:STOP?
[ :SOURce]:PAGing:{FLEX|FTD}:TYPE TONE|NUMeric|ALPHanumeric|HBINary
[ :SOURce]:PAGing:{FLEX|FTD}:TYPE?
[ :SOURce]:PAGing:{FLEX|FTD}:VECTor STANDARD|SPECial|NUMBered
[ :SOURce]:PAGing:{FLEX|FTD}:VECTor?
[ :SOURce]:PAGing:{FLEX|FTD}:NUMBered <val>
[ :SOURce]:PAGing:{FLEX|FTD}:NUMBered?
[ :SOURce]:PAGing:{FLEX|FTD}:CYCLE <val>
[ :SOURce]:PAGing:{FLEX|FTD}:CYCLE?
[ :SOURce]:PAGing:{FLEX|FTD}:FRAMe <val>
[ :SOURce]:PAGing:{FLEX|FTD}:FRAMe?
[ :SOURce]:PAGing:{FLEX|FTD}:CCOut?
[ :SOURce]:PAGing:{FLEX|FTD}:FCOut?
[ :SOURce]:PAGing:{FLEX|FTD}:PHASe A|B|C|D
[ :SOURce]:PAGing:{FLEX|FTD}:PHASe?
[ :SOURce]:PAGing:{FLEX|FTD}:COLLapse <val>
[ :SOURce]:PAGing:{FLEX|FTD}:COLLapse?
[ :SOURce]:PAGing:{FLEX|FTD}:CODE <val>
[ :SOURce]:PAGing:{FLEX|FTD}:CODE?
[ :SOURce]:PAGing:{FLEX|FTD}:ATYPe SHORT|LONG
[ :SOURce]:PAGing:{FLEX|FTD}:ATYPe?
[ :SOURce]:PAGing:{FLEX|FTD}:ADDRess{1|2} <val>
[ :SOURce]:PAGing:{FLEX|FTD}:ADDRess{1|2}?
[ :SOURce]:PAGing:{FLEX|FTD}:ISTop:STATE ON|OFF
[ :SOURce]:PAGing:{FLEX|FTD}:ISTop:STATE?
[ :SOURce]:PAGing:{FLEX|FTD}:HEADER:STATE ON|OFF
[ :SOURce]:PAGing:{FLEX|FTD}:HEADER:STATE?
[ :SOURce]:PAGing:{FLEX|FTD}:TERMinator:STATE ON|OFF
[ :SOURce]:PAGing:{FLEX|FTD}:TERMinator:STATE?
```

```
[ :SOURce] :PAGing:{FLEX|FTD} :VECTor STANDARD|SPECial|NUMBERed
[ :SOURce] :PAGing:{FLEX|FTD} :VECTor?

[ :SOURce] :PAGing:{FLEX|FTD} :HBINary BIT1|BIT7|BIT8|BIT14|BIT16
[ :SOURce] :PAGing:{FLEX|FTD} :HBINary?

[ :SOURce] :PAGing:{FLEX|FTD} :DCAL:STATE ON|OFF
[ :SOURce] :PAGing:{FLEX|FTD} :DCAL:STATE?

[ :SOURce] :PAGing:{FLEX|FTD} :DCAL:ADDress{1|2} <val>
[ :SOURce] :PAGing:{FLEX|FTD} :DCAL:ADDress{1|2}?

[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SElect NONE|SSID|NID
[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SElect?

[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SSID:LID <val>
[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SSID:LID?

[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SSID:CZONe <val>
[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SSID:CZONe

[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SSID:CCODE <val>
[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SSID:CCODE?

[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SSID:TMF <val>
[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SSID:TMF?

[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SSID:FOFF <val>
[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:SSID:FOFF?

[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:NID:ADDRess <val>
[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:NID:ADDRess?

[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:NID:AREA <val>
[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:NID:AREA?

[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:NID:MULTiplier <val>
[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:NID:MULTiplier?

[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:NID:TMF <val>
[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:NID:TMF?

[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:NID:FOFF <val>
[ :SOURce] :PAGing:{FLEX|FTD} :ROAMing:NID:FOFF?

[ :SOURce] :PAGing:FTD:REFerence <val>
[ :SOURce] :PAGing:FTD:REFerence?

[ :SOURce] :PAGing:FTD:RCO?

[ :SOURce] :PAGing:POCS:TYPE TONE|NUMeric|ALPHanumeric|ALPH7|ALPH8
```

Analog Function Commands

```
[ :SOURce ] :PAGing:POCS:TYPE?  
[:SOURce]:PAGing:POCS:CODE <val>  
[ :SOURce ] :PAGing:POCS:CODE?  
[ :SOURce ] :PAGing:POCS:FUNCTION 0|1|2|3  
[ :SOURce ] :PAGing:POCS:FUNCTION?
```

5 8656B, 8657A/B/D/J Programming Codes

Programming Codes

Compatible Codes

8656B, 8657A/B/D/J Codes ^a	Description	Equivalent SCPI Command Syntax
AM	Amplitude Modulation	[:SOURce] :AM[1] 2[:DEPTH] [:LINEar] <val><unit> UP DOWN For additional commands, refer to, “ S1, S2, or S3 used with AM ” on page 129
AO	Amplitude Offset	[:SOURce] :POWER[:LEVEL][IMMEDIATE]: OFFSet <val><unit>
AP	Amplitude (carrier)	[:SOURce] :POWER[:LEVEL][:IMMEDIATE] [:AMPLitude] <val><unit>
DB	Unit used with the power command	DB
DF	Unit used with the power command	DB
DM	Unit used with the power command	DBM
DN	Step Down	No equivalent SCPI command
EM	Unit used with the power command	EMF
FM	Frequency Modulation	[:SOURce] :FM[1] 2[:DEVIATION] <val><unit> For additional commands, refer to, “ S1, S2, or S3 used with FM ” on page 130.
FR	Frequency (carrier)	[:SOURce] :FREQUENCY[:CW] <val><unit>
GT	Flexible Sequence	No equivalent SCPI command

8656B, 8657A/B/D/J Codes^a	Description	Equivalent SCPI Command Syntax
HZ	Unit used with the frequency command	HZ
IS ^b	Increment Set	No equivalent SCPI command
KZ	Unit used with the frequency command	kHZ
MV	Unit used with the power command	mV
MZ	Unit used with the frequency command	MHZ
P0 ^c	Digital Modulation Off	Refer to, “P0 (Digital Modulation Off)” on page 128.
P4 ^c	Digital Modulation On	Refer to, “P4 (Digital Modulation On)—E4438C” on page 129.
PC ^d	Unit used with the modulation command	PCT
PD	Phase Decrement	[:SOURce] :PHASE[:ADJust] <val><RAD>
PF	Pulse Modulation (Fast Mode)	Refer to, “PF (Pulse Modulation-Fast Mode) or PM (Pulse Modulation)” on page 129.
PI	Phase Increment	[:SOURce] :PHASE[:ADJust] <val><RAD>
PM	Pulse Modulation	[:SOURce] :PULM:SOURce EXT2 [:SOURce] :PULM:STATe ON
QS	Reverse Sequence	*RCL <reg>
RC	Recall (0–9)	*RCL <reg>
RL	Recall (0–99)	*RCL <reg>
RP ^e	Reverse Power Protection Reset	No equivalent SCPI command
R2	RF Off	OUTPut[:STATe] OFF

Programming Codes

8656B, 8657A/B/D/J Codes^a	Description	Equivalent SCPI Command Syntax
R3	RF On	OUTPut[:STATE] ON
R5	RF Dead (Full Attenuator)	OUTPut[:STATE] OFF
SQ	Sequence	*RCL <reg>
ST	Save (0–9)	*SAV <reg>
SV	Save (0–99)	*RCL <reg>
S1	External Modulation Source	Refer to, “S1, S2, or S3 used with AM” on page 129 or “S1, S2, or S3 used with FM” on page 130.
S2	Internal 400 Hz Modulation Source	Refer to, “S1, S2, or S3 used with AM” on page 129 or “S1, S2, or S3 used with FM” on page 130.
S3	Internal 1 kHz Modulation Source	Refer to, “S1, S2, or S3 used with AM” on page 129 or “S1, S2, or S3 used with FM” on page 130.
S4	Modulation Source Off	Refer to, “S4 (Modulation Source Off)” on page 131.
S5	DC FM	Refer to, “S5 (DC FM)” on page 132.
UP	Step Up	No equivalent SCPI command
UV	Unit used with the power command	UV
VL	Unit used with the power command	V
0–9	Numerals 0–9	0–9
–	Minus Sign	–
.	Decimal Point	.
% ^d	Unit used with the modulation command	PCT

- a. Program codes are either upper or lower case.
- b. Increment Set is implemented for frequency (FR) and amplitude (AP) only.

- c. This code is used with the NADC, PDC, and PHS digital modulation.
- d. Either PC or % can be used.
- e. The source of reverse power must be removed.

Non-Compatible Codes

8656B, 8657A/B/D/J Codes	Description
HI	HI ALC
LO	LO ALC
R0	Standby
R1	On

Command Mapping

When using the 8656B, 8657A/B/D/J-compatible programming codes, the E4428C/38C internally maps these codes to an equivalent SCPI response. In addition, the modulation source selections for the 8656B, 8657A/B/D/J differ from those available in the E4428C/38C and therefore, are mapped to a valid selection. (Refer to [Table 5-1](#).)

Table 5-1

Modulation Sources	
8656B, 8657A/B/D/J	ESG Signal Generators
AM, Internal	AM1, Internal 1
AM, External	AM2, External 1
FM, Internal	FM1, Internal 1
FM, External	FM2, External 1
AM, Internal and External	AM1, Internal 1 and AM2, External 1
FM, Internal and External	FM1, Internal 1 and FM2, External 1

NOTE The 8656, 8657A/B/D/J signal generators allow multiple modulations to use the same input; the E4428C/38C does not. If you configure multiple modulations on the same input, the E4428C/38C automatically disables the modulations.

The mapping between the 8656B, 8657A/B/D/J-compatible programming codes and the SCPI commands changes depending on the programming codes being executed. Refer to the following sections for explanations of the codes that are affected.

P0 (Digital Modulation Off)

NOTE This section contains a command that is only applicable to the E4438C vector signal generator.

This code turns off the digital modulation for NADC (8657D), PDC (8657D), and PHS (8657J). Replace <format> with either NADC, PDC, or PHS as needed. The P0 code is mapped to the following SCPI command:

```
[ :SOURce ] :RADio:<format>:STATe OFF
```

P4 (Digital Modulation On)—E4438C

This code turns off the AM and FM modulation and turns on the digital modulation for NADC (8657D), PDC (8657D), and PHS (8657J).

The P4 code is mapped to the following SCPI commands:

- [:SOURce] :AM[1]:STATe OFF
- [:SOURce] :AM2:STATe OFF
- [:SOURce] :FM[1]:STATe OFF
- [:SOURce] :FM2:STATe OFF
- [:SOURce] :DM:SOURce INTERNAL1
- [:SOURce] :RADIO:<format>:STATe ON
- [:SOURce] :RADIO:<format>:REPeat CONT
- [:SOURce] :RADIO:<format>:DATA EXTERNAL
- [:SOURce] :DM:STATe ON

where <format> is either NADC, PDC, or PHS depending on the specific compatibility language selected.

PF (Pulse Modulation-Fast Mode) or PM (Pulse Modulation)

The E4428C/38C supports only one input selection for pulse which is EXTERNAL 2 (EXT 2 INPUT connector). This is a DC-coupled input. Internal pulse modulation, therefore, is not supported in the 8656B, 8657A/B/D/J-compatible language modes. The PF or PM code is mapped to the following SCPI commands:

- [:SOURce] :PULM:SOURce EXTERNAL2
- [:SOURce] :PULM:STATe ON

S1, S2, or S3 used with AM

When the AM code is executed, the following occurs:

- AM becomes the active function.
- AM1 and AM2 depth values are coupled by mapping to the following command:

Command Mapping

[:SOURce] :AM[1] | 2[:DEPTH] :TRACK ON.

If AM is on, or there is no active modulation, a sequence of SCPI commands are implemented when an AM code is executed with a modulation source code. [Table 5-2](#) shows the sequence of SCPI commands that are implemented.

Table 5-2

	AM On	No Active Modulation
S1	[:SOURce] :AM2:EXTernal[1]: COUpling AC [:SOURce] :AM2:SOURce EXTERNAL1	[:SOURce] :AM2:EXTernal[1]: COUpling AC [:SOURce] :AM2:SOURce EXTERNAL1 [:SOURce] :AM2:STATE ON
S2	[:SOURce] :AM[1]:SOURce INT[1] [:SOURce] :AM[1]:INTERNAL[1]: FREQuency 400 HZ	[:SOURce] :AM[1]:SOURce INT[1] [:SOURce] :AM[1]:INTERNAL[1]: FREQuency 400 HZ [:SOURce] :AM[1]:STATE ON
S3	[:SOURce] :AM[1]:SOURce INT[1] [:SOURce] :AM[1]:INTERNAL[1]: FREQuency 1 kHz	[:SOURce] :AM[1]:SOURce INT[1] [:SOURce] :AM[1]:INTERNAL[1]: FREQuency 1 kHz [:SOURce] :AM[1]:STATE ON

- If FM or pulse modulation is on, the signal generator attempts to set up AM with the same settings. [Table 5-3](#) shows the SCPI commands that are mapped.

Table 5-3

	FM1 On	FM2 or Pulse On
S1, S2, or S3	[:SOURce] :AM[1]:SOURce INT[1] [:SOURce] :AM[1]:STATE ON [:SOURce] :FM[1]:STATE OFF	[:SOURce] :AM2:SOURce EXTERNAL1 [:SOURce] :AM2:STATE ON [:SOURce] :FM2:STATE OFF [:SOURce] :PULM:STATE OFF

S1, S2, or S3 used with FM

When the FM code is executed, the following occurs:

- FM becomes the active function.
- FM1 and FM2 deviation values are coupled by mapping to the following command:
[:SOURce] :FM[1] | 2[:DEViation] :TRACK ON.

If FM is on, or there is no active modulation, a sequence of SCPI commands are implemented when an FM code is executed with a modulation source code. [Table 5-4](#) shows the sequence of SCPI commands that are implemented.

Table 5-4

	FM On	No Active Modulation
S1	[:SOURce]:FM2:EXTernal[1]: COUpling AC [:SOURce]:FM2:SOURce EXTernal1	[:SOURce]:FM2:EXTernal[1]: COUpling AC [:SOURce]:FM2:SOURce EXTernal1 [:SOURce]:FM2:STATE ON
S2	[:SOURce]:FM[1]:SOURce INT[1] [:SOURce]:FM[1]:INTERNAL[1]: FREQuency 400 HZ	[:SOURce]:FM[1]:SOURce INT[1] [:SOURce]:FM[1]:INTERNAL[1]: FREQuency 400 HZ [:SOURce]:FM[1]:STATE ON
S3	[:SOURce]:FM[1]:SOURce INT[1] [:SOURce]:FM[1]:INTERNAL[1]: FREQuency 1 kHz	[:SOURce]:FM[1]:SOURce INT[1] [:SOURce]:FM[1]:INTERNAL[1]: FREQuency 1 kHz [:SOURce]:FM[1]:STATE ON

- If AM or pulse modulation is on, the signal generator attempts to set up FM with the same settings. [Table 5-5](#) shows the SCPI commands that are mapped.

Table 5-5

	AM1 On	AM2 or Pulse On
S1, S2, or S3	[:SOURce]:FM[1]:SOURce INT[1] [:SOURce]:FM[1]:STATE ON [:SOURce]:AM[1]:STATE OFF	[:SOURce]:FM2: SOURce EXTernal1 [:SOURce]:FM2:STATE ON [:SOURce]:AM2:STATE OFF [:SOURce]:PULM:STATE OFF

S4 (Modulation Source Off)

- If PM is the current active function, pulse modulation is disabled by mapping to the following command:

[:SOURce] :PULM:STATE OFF

- If the last code executed is S2 or S3, internal modulation is turned off for the AM and FM on path one by mapping to the following commands:

[:SOURce] :AM[1]:STATE OFF

Command Mapping

[:SOURce] :FM[1] :STATe OFF

- If the last code executed is S1, external modulation is turned off for the AM and FM on path two by mapping to the following commands:

[:SOURce] :AM2 :STATe OFF

[:SOURce] :FM2 :STATe OFF

- If the current active function is AM or FM, both paths are turned off by mapping to the following commands:

[:SOURce] :AM[1] :STATe OFF

[:SOURce] :AM2 :STATe OFF

[:SOURce] :FM[1] :STATe OFF

[:SOURce] :FM2 :STATe OFF

- If S4 is executed with S1, S2, or S3, it will turn off the current active modulation type.

S5 (DC FM)

- FM becomes the active function.
- In addition, the following commands are mapped:

[:SOURce] :FM2 :SOURce EXTer nal1

[:SOURce] :PULM :STATe OFF

[:SOURce] :AM[1] :STATe OFF

[:SOURce] :AM2 :STATe OFF

[:SOURce] :FM2 :EXTer nal[1] :COUpling DC

[:SOURce] :FM2 :STATe ON