

Agilent Technologies
E444xA Option HBA

User's and Service Guide Supplement

Agilent Technologies

E444xA Option HBA

User's and Service Guide Supplement



Agilent Technologies

Manufacturing Part Number: E4443-90001

Printed in USA
January 2005

© Copyright 2004, 2005 Agilent Technologies, Inc. All rights reserved.

Warranty Statement

THE MATERIAL CONTAINED IN THIS DOCUMENT IS PROVIDED “AS IS,” AND IS SUBJECT TO BEING CHANGED, WITHOUT NOTICE, IN FUTURE EDITIONS. FURTHER, TO THE MAXIMUM EXTENT PERMITTED BY APPLICABLE LAW, AGILENT DISCLAIMS ALL WARRANTIES, EITHER EXPRESS OR IMPLIED WITH REGARD TO THIS MANUAL AND ANY INFORMATION CONTAINED HEREIN, INCLUDING BUT NOT LIMITED TO THE IMPLIED WARRANTIES OF MERCHANTABILITY AND FITNESS FOR A PARTICULAR PURPOSE. AGILENT SHALL NOT BE LIABLE FOR ERRORS OR FOR INCIDENTAL OR CONSEQUENTIAL DAMAGES IN CONNECTION WITH THE FURNISHING, USE, OR PERFORMANCE OF THIS DOCUMENT OR ANY INFORMATION CONTAINED HEREIN. SHOULD AGILENT AND THE USER HAVE A SEPARATE WRITTEN AGREEMENT WITH WARRANTY TERMS COVERING THE MATERIAL IN THIS DOCUMENT THAT CONFLICT WITH THESE TERMS, THE WARRANTY TERMS IN THE SEPARATE AGREEMENT WILL CONTROL.

DFARS/Restricted Rights Notice

If software is for use in the performance of a U.S. Government prime contract or subcontract, Software is delivered and licensed as “Commercial computer software” as defined in DFAR 252.227-7014 (June 1995), or as a “commercial item” as defined in FAR 2.101(a) or as “Restricted computer software” as defined in FAR 52.227-19 (June 1987) or any equivalent agency regulation or contract clause. Use, duplication or disclosure of Software is subject to Agilent Technologies’ standard commercial license terms, and non-DOD Departments and Agencies of the U.S. Government will receive no greater than Restricted Rights as defined in FAR 52.227-19(c)(1-2) (June 1987). U.S. Government users will receive no greater than Limited Rights as defined in FAR 52.227-14 (June 1987) or DFAR 252.227-7015 (b)(2) (November 1995), as applicable in any technical data.

Safety Notes

The following safety notes are used throughout this document. Familiarize yourself with each of these notes and its meaning before performing any of the procedures in this document.

WARNING	Warning denotes a hazard. It calls attention to a procedure which, if not correctly performed or adhered to, could result in injury or loss of life. Do not proceed beyond a warning note until the indicated conditions are fully understood and met.
CAUTION	Caution denotes a hazard. It calls attention to a procedure that, if not correctly performed or adhered to, could result in damage to or destruction of the instrument. Do not proceed beyond a caution sign until the indicated conditions are fully understood and met.

Definitions

- Specifications describe the performance of parameters covered by the product warranty (temperature –0 to 55 °C, unless otherwise noted.)
- *Typical* describes additional product performance information that is not covered by the product warranty. It is performance beyond specification that 80% of the units exhibit with a 95% confidence level over the temperature range 20 to 30 °C. Typical performance does not include measurement uncertainty.
- *Nominal* values indicate expected performance, or describe product performance that is useful in the application of the product, but is not covered by the product warranty.

Verifying the Shipment

Inspect the shipping container. If the container or packing material is damaged, it should be kept until the contents of the shipment have been checked mechanically and electrically. If there is physical damage please notify the nearest Agilent Technologies office. Refer to “[Contacting Agilent](#)” on page 7. Keep the damaged shipping materials (if any) for inspection by the carrier and an Agilent Technologies representative.

For information concerning the operation and connections, refer to the PSA User's and Service Guide supplied with the standard product.

Contents

E444xA Option HBA

Introduction	2
Performance Verification	3
Displayed Average Noise Level	3
Equipment Required	3
Procedure	3
Contacting Agilent	7

Contents

E444xA Option HBA

Introduction

The E444xA Option HBA locates the RF input on the rear panel, using a 3.5 mm (male) connector. This option utilizes the 21.4 MHz IF output connector hole on the rear panel, therefore special Option HB2 is not available with Option HBA.

The Displayed Average Noise Level (DANL) will degrade slightly in instruments with Option HBA. This is due to the additional cabling required to move the RF input to the rear panel of the instrument. This DANL degradation increases as the RF input frequency increases. The DANL will nominally degrade approximately 1 dB at 13.2 GHz and approximately 2 dB at 26.5 GHz when compared to the DANL of a standard PSA. In all other respects Option HBA specification are identical to the standard PSA product specifications.

The following equation may be used to predict how the DANL will nominally degrade based on the frequency of interest.

Equation 1 E4440/43/45A Option HBA Nominal DANL

$$DHBA = D + 28.4 \times \left(\frac{5.758 + 4.89 \times F - 0.146 \times F^2 + 2.433 \times 10^{-3} \times F^3}{1200} \right)$$

For [Equation 1](#):

- F is the Frequency in GHz.
- D is the term used for representing the instruments DANL specification found in the PSA Series Specification Guide.
- $DHBA$ is the term used to represent the resultant instrument DANL from the inclusion of Option HBA.

Performance Verification

This test measures the Displayed Average Noise Level (DANL) of the PSA. The test measures the noise in zero span with a 1 kHz resolution bandwidth, and then normalizes the amplitude to a 1 Hz bandwidth.

DANL is defined as the average of the displayed trace. There is no practical method for manually reading the average of the trace. This procedure averages the trace 100 times and then the operator scrolls the display line to the middle of the trace. The display line reading is considered the trace average. The reading is normalized to a 1 Hz RBW by subtracting 30 dB ($10 \times \log(1000)$) from the display line value.

Displayed Average Noise Level

Equipment Required

- Termination, 50 Ω, 3.5 mm (f)

Procedure

1. Connect the appropriate termination to the PSA RF input connector.
Press **System, Alignments, Align All Now**.

2. Press **Preset**. Set the analyzer controls by pressing the following keys:

SPAN, Span, 0 Hz
Sweep, Sweep Time, 20 ms
Amplitude, Ref Level, -100 dBm
Amplitude, Attenuation, Man, 0 dB
BW/Avg, Res BW, 1 kHz
BW/Avg, Average, On
Single

3. If the analyzer does not have Option 1DS (Internal Preamplifier) installed, then continue with [step 11](#).

4. Press **AMPLITUDE, More 1 of 3, Int Preamp, On**.

5. Press **FREQUENCY** and enter the first frequency listed in [Table 1](#).

Table 1 DANL (PSA with Option 1DS)

Frequency	Normalized DANL
100 kHz	1)
199 kHz	2)
201 kHz	3)
499 kHz	4)
501 kHz	5)
9.9 MHz	6)
10.1 MHz	7)
1.0 GHz	8)
1.2 GHz	9)
2.4 GHz	10)
2.6 GHz	11)
3.0 GHz	12)

6. Press **Single** and wait for 100 averages.
7. Press **Display, Display Line, On**.
8. Scroll the display line so that it bisects the trace. Read the display line amplitude and subtract 30 from the value. Record the result under Normalized DANL in the table.
9. Repeat [step 5](#) through [step 8](#) for all frequencies listed in [Table 1](#).
10. Press **AMPLITUDE, More 1 of 3, Int Preamp, Off**.

11. Press **FREQUENCY** and enter the first frequency listed in [Table 2](#).

Table 2 DANL (All PSA Instruments)

Frequency	Normalized DANL
10 kHz	13)
99 kHz	14)
101 kHz	15)
990 kHz	16)
1.01 MHz	17)
500 MHz	18)
1.1 GHz	19)
1.3 GHz	20)
2.0 GHz	21)
2.4 GHz	22)
2.6 GHz	23)
3.0 GHz	24)
3.1 GHz	25)
4.0 GHz	26)
5.0 GHz	27)
6.5 GHz	28)
6.7 GHz	29)

12. Press **Single** and wait for 100 averages.

13. Press **Display, Display Line, On**.

14. Scroll the display line so that it bisects the trace. Read the display line amplitude and subtract 30 from the value. Record the result under Normalized DANL in the table.

15. Repeat [step 11](#) through [step 14](#) for all frequencies listed in [Table 2](#).

16. If the analyzer is an E4443A stop here.

17. Repeat step 11 through step 14 for all frequencies listed in Table 3.

Table 3 DANL (PSA E4445A, E4440A)

Frequency	Normalized DANL
8.0 GHz	30)
9.0 GHz	31)
10.0 GHz	32)
11.0 GHz	33)
12.0 GHz	34)
13.1 GHz	35)

18. If the analyzer is an E4445A stop here.

19. Repeat step 11 through step 14 for all frequencies listed in Table 4.

Table 4 DANL (PSA E4440A)

Frequency	Normalized DANL
13.3 GHz	36)
14.0 GHz	37)
15.0 GHz	38)
16.0 GHz	39)
17.0 GHz	40)
18.0 GHz	41)
19.9 GHz	42)
20.1 GHz	43)
21.0 GHz	44)
22.4 GHz	45)
22.6 GHz	46)
24.0 GHz	47)
25.0 GHz	48)
26.4 GHz	49)

20. If the analyzer is an E4440A stop here.

Contacting Agilent

By internet, phone, or fax, get assistance with all your test and measurement needs.

This information supersedes all prior HP contact information.			
Online assistance: www.agilent.com/find/assist			
Americas			
Brazil (tel) (+55) 11 3351 7012 (fax) (+55) 11 3351 7024	Canada (tel) +1 877 894 4414 (fax) +1 303 662 3369	Mexico (tel) 1 800 254 2440 (fax) 1 800 254 4222	United States (tel) 800 829 4444 (alt) (+1) 303 662 3998 (fax) 800 829 4433
Asia Pacific and Japan			
Australia (tel) 1 800 225 574 (fax) 1 800 681 776 (fax) 1 800 225 539	China (tel) 800 810 0508 (alt) 800 810 0510 (fax) 800 810 0507 (fax) 800 810 0362	Hong Kong (tel) 800 933 229 (fax) 800 900 701	India (tel) 1600 112 626 (fax) 1600 112 727 (fax) 1600 113 040
Japan (Bench) (tel) 0120 32 0119 (alt) (+81) 426 56 7799 (fax) 0120 01 2144	Japan (On-Site) (tel) 0120 802 363 (alt) (+81) 426 56 7498 (fax) (+81) 426 60 8953	Singapore (tel) 1 800 275 0880 (fax) (+65) 6755 1235 (fax) (+65) 6755 1214	South Korea (tel) 080 778 0011 (fax) 080 778 0013
Taiwan (tel) 0800 047 669 (fax) 0800 047 667 (fax) 886 3492 0779	Thailand (tel) 1 800 2758 5822 (alt) (+66) 2267 5913 (fax) 1 800 656 336	Malaysia (tel) 1800 880 399 (fax) 1800 801 054	
Europe			
Austria (tel) 0820 87 44 11* (fax) 0820 87 44 22	Belgium (tel) (+32) (0)2 404 9340 (alt) (+32) (0)2 404 9000 (fax) (+32) (0)2 404 9395	Denmark (tel) (+45) 7013 1515 (alt) (+45) 7013 7313 (fax) (+45) 7013 1555	Finland (tel) (+358) 10 855 2100 (fax) (+358) (0) 10 855 2923
France (tel) 0825 010 700* (alt) (+33) (0)1 6453 5623 (fax) 0825 010 701*	Germany (tel) 01805 24 6333* (alt) 01805 24 6330* (fax) 01805 24 6336*	Ireland (tel) (+353) (0)1 890 924 204 (alt) (+353) (0)1 890 924 206 (fax) (+353) (0)1 890 924 024	Israel (tel) (+972) 3 9288 500 (fax) (+972) 3 9288 501
Italy (tel) (+39) (0)2 9260 8484 (fax) (+39) (0)2 9544 1175	Luxemburg (tel) (+32) (0)2 404 9340 (alt) (+32) (0)2 404 9000 (fax) (+32) (0)2 404 9395	Netherlands (tel) (+31) (0)20 547 2111 (alt) (+31) (0)20 547 2000 (fax) (+31) (0)20 547 2190	Russia (tel) (+7) 095 797 3963 (alt) (+7) 095 797 3900 (fax) (+7) 095 797 3901
Spain (tel) (+34) 91 631 3300 (alt) (+34) 91 631 3000 (fax) (+34) 91 631 3301	Sweden (tel) 0200 88 22 55* (alt) (+46) (0)8 5064 8686 (fax) 020 120 2266*	Switzerland (French) (tel) 0800 80 5353 opt. 2* (alt) (+33) (0)1 6453 5623 (fax) (+41) (0)22 567 5313	Switzerland (German) (tel) 0800 80 5353 opt. 1* (alt) (+49) (0)7031 464 6333 (fax) (+41) (0)1 272 7373
Switzerland (Italian) (tel) 0800 80 5353 opt. 3* (alt) (+39) (0)2 9260 8484 (fax) (+41) (0)22 567 5314	United Kingdom (tel) (+44) (0)7004 666666 (alt) (+44) (0)7004 123123 (fax) (+44) (0)7004 444555		

(tel) = primary telephone number; (alt) = alternate telephone number; (fax) = FAX number; * = in country number 11/16/04

