optional IR sensor

whole-house audio system

3-button power/volume control

in-wall keypad

remote control capability

RJ-45 connection

use with PA 4000

KP 1

IN-WALL KEYPAD

Whole-house audio control. The

Harman Kardon KP 1. Designed for

use with the Harman Kardon PA 4000

multiroom power amplifier, the KP 1 is a

convenient in-wall keypad that allows you

to power up the system and control the

volume independently for each room or

zone. It's styled to match standard Decora®

wall plates, and may be used with an

optional IR sensor and third-party remotes.

The Harman Kardon KP 1. The simple

control solution for multiroom systems.

harman/kardon®
Power for the Digital Revolution.™

KP 1

IN-WALL KEYPAD

Specifications

• Mounting System: Compatible With Most Standard Electrical Junction Boxes

• Connections: 8P8C (RJ-45) Straight-Through (Standard T568B) System Connection to PA 4000 Amplifier; Three-Pin Eurostyle Terminal Block Connector for Use With Optional Third-Party IR Sensor (+12 Volts, Signal, Ground)

• Dimensions (H x W x D): 4" x 1-5/8" x 1-9/16" (103mm x 41.2mm x 40.1mm)

• Recommended Third-Party Optional Infrared Sensor: Xantech® Micro Link™ Model 490-00

• Dimensions of Cutout for Third-Party Optional IR Sensor: 1/2" (12.7mm)

[NOTE: Dimensions include buttons and chassis, but not optional infrared sensor.] All features and specifications are subject to change without notice.

Features

Remotely Controls Power On/Off and Volume Up/Down When Used With PA 4000 Amplifier • Simple Three-Button Design Is Easy to Use • May Be Used With Optional Third-Party Infrared Sensor to Control Harman Kardon or Other Products Equipped With IR Remote Input Jacks • Easy Installation in Standard Electrical In-Wall Junction Box Using Single-Cable Connection to PA 4000 • Three-Pin Connector Provides Connection for Power When Using Third-Party Sensor • Decora-Style In-Wall Mounting System Blends In With Room Décor (Wall Plate Not Included)