



DaqScan/2000™ Series

Ethernet-Based Data Acquisition System Components



Features

- Adds analog I/O, digital I/O and frequency I/O to Ethernet-based test systems
- All I/O can be synchronous, enabling precise timing between various I/O functions
- 8 differential, or 16 single-ended inputs, expandable up to 256 voltage or 896 TC channels using signal conditioning and expansion options
- Up to 40 built-in TTL-level digital I/O, expandable up to 256 channels of isolated I/O using low-cost isolation modules
- Includes support for Visual Basic®, C/C++, IVI*, ActiveX/COM, LabVIEW®, MATLAB®, and DASyLab®
- Includes *Out-of-the-Box™* DaqView™ software to facilitate signal and wiring verification with no programming required
- Convenient 1U high 19" rack mount package minimizes rack space in test systems



The DaqScan/2000 series provides compact data acquisition capability for Ethernet-based test systems

The DaqScan/2000™ series of Ethernet-based system components provide analog, digital, and frequency I/O capability for Ethernet-based test systems. The DaqScan series builds on IOtech's IEEE 488-based predecessors, the ADC488™, DAC488™, Digital488™, and TempScan/1100™ which provide similar capability for IEEE 488-based systems.

All DaqScan models are packaged in 1U high-full rack package, and include a rack-mount kit that can attach to either the front or the rear of the enclosure. Multiple DaqScan models can be combined in the same system and synchronized using a

simple SYNC connection between units. All I/O is accessed via female DB37 connectors located on the rear of the unit, making cabling easy from the DaqScan to your device-under-test.

Four models in the DaqScan series are available, ranging from the DaqScan/2002 model which offers digital/frequency I/O, to the full-featured DaqScan/2001 which includes 16 analog inputs, 4 analog outputs, 40 digital I/O, 4 frequency inputs and 2 timer outputs.

The DaqScan includes comprehensive drivers for all popular Windows-based environments, including Visual Basic, C/C++, IVI, ActiveX/COM, LabVIEW, MATLAB, and DASyLab. Also included with the DaqScan

is DaqView, an interactive spreadsheet-style application that is ideal for verifying signal connections during system design.

The DaqScan/2000 series has the same signal I/O, synchronous scanning, triggering, and signal expansion capability as our DaqBook/2000. The compact 1U high 19" rack packaging of the DaqScan make it a compact component for rack-based systems.

In addition to the built-in I/O provided by the DaqScan/2000 series, a wide variety of signal conditioning and expansion options are available. Below are some sample systems that can be derived from the DaqScan along with DBK options.

* Contact factory for availability
† CE pending

DaqScan/2000 Series Selection Chart

Model	Analog Inputs SE/DIFF	Digital I/O	Frequency/Pulse Inputs	Timer Outputs	Analog Outputs
DaqScan/2001	16/8	40	4	2	4
DaqScan/2002	0	40	4	2	0
DaqScan/2004	0	40	4	2	4
DaqScan/2005	16/8	40	4	2	0

For the latest information on software and hardware options for the DaqScan, visit www.iotech.com/DaqScan



DaqScan/2000™ Series

General Information

High Channel Count Thermocouple Measurements

When combined with the DBK90™ thermocouple input module, the DaqScan can measure up to 896 channels of TC input. In the example system to the right, any TC type can be installed into any channel using standard mini TC connectors. Each 56 channel DBK90 option consumes 2U of rack space, and can be mounted on the front or rear of the rack chassis. Built-in cold junction compensation coupled with TC conversion algorithms built into the software make temperature measurements easy. Thermocouples are measured at 1 ms/channel in a system based on the DBK90.



The 168 TC channel system consists of one DaqScan/2005 plus three DBK90 modules with rack-mount kits

High-Isolation Voltage & Thermocouple Measurements

The DaqScan can be combined with DBK207/CJC™ options to create an isolated system capable of measuring up to 256 channels of voltage, thermocouple, RTD and strain gage inputs. All input channels can be scanned up to 200 kHz, and are isolated by 500V from other channels and from system common. Any combination of input signals are possible by selecting the appropriate 5B signal conditioning module for the DBK207/CJC. DBK207/CJCs can be mounted in the front or rear of the rack, and attach to the DaqScan via a simple CA-37-x cable.



The 24-channel isolated system includes a DaqScan/2005 plus two DBK207/CJC boards. The system is capable of scanning all channels at 5 μsec per channel, and provides 500V isolation for all inputs.

Isolated Digital I/O System

When the DaqScan/2002 is combined with the DBK208™ or DBK210™ options, up to 256 channels of isolated digital I/O is possible, capable of controlling AC or DC voltages up to 250V, or sensing the presence of AC or DC voltages. All channels are isolated from one another and from the system by up to 500V. Inputs can be scanned in 16-bit increments at speeds up to 200 Kreadings/s. The DBK208 and DBK210 can be mounted in the front or rear of the rack.



The 64-channel isolated discrete I/O system consists of one DaqScan/2002 plus two DBK210 boards with rack-mount kits



DaqScan/2000™ Series

General Information & Specifications

High-speed Voltage Measurement System

The DaqScan/2005 can be combined with DBK85™ 16-channel voltage input modules to build a 5 µs/channel voltage measurement system up to 256 channels. All inputs can have a different, software programmable input range, from 156 mV FS to 10V FS, programmable on a per-channel basis. The 16 BNC inputs on the DBK85 can be accessed from either the front or the rear of a rack system.



The 80 channel high-speed scanning system consists of one DaqScan/2005 plus five DBK85 16-channel voltage scanning modules. All channels can be measured at the maximum rate of 5 µs/channel.

Multifunction I/O System

All of the afore-mentioned capabilities can be combined into one system, using one DaqScan/2001 as the heart of the system.



The system provides 56 non-isolated TC inputs, 16 isolated voltage inputs, 16 low-voltage inputs, 4 analog outputs, 4 frequency inputs, and 32 isolated discrete high-voltage outputs

Specifications

General

Supply Voltage Range: 90 to 250 VAC
Power Required: 15W (assuming no DBK options)
Operating Temperature: 0° to +50°C
Storage Temperature: -40° to +80°C
Relative Humidity: 0 to 95%, non-condensing
Signal I/O Connector: DB37 male for P1, P2, and P3
Dimensions: 425 mm W x 220 mm D x 45 mm H (16.75" x 8.5" x 1.75")
Weight: 2.3 kg (5 lbs)
Power Available for External DBK Options: 10W

A/D Specifications

Type: Successive approximation
Resolution: 16 bit
Conversion Time: 5 µs
Maximum Sample Rate: 200 kHz
Nonlinearity (Integral): ±1 LSB
Nonlinearity (Differential): No missing codes

Analog Inputs

Channels

Model /2001, /2005: 16 single-ended or 8 differential, programmable on a per-channel basis as single-ended or differential and unipolar or bipolar
Expansion: Up to 896 TC channels when used with DBK90 expansion option (1 ms/channel), or up to 256 channels when used with all other expansion option (5 µs/channel)
Settling Time: 5 µsec to 1 LSB for full-scale step
Temperature Coefficient: ±(10ppm +0.3 LSB)/°C outside the range of 0° to 35°C
Input Impedance: 10M Ohm (single-ended), 20M Ohm (differential)
Bias Current: <1nA (0 to 35°C)
Common Mode Rejection: 86 dB, DC to 60 Hz for gains < =8; >100 dB for gains > =16
Maximum Input Voltage (without damage): ±11V relative to analog common
Over-Voltage Protection: ±35V
Ranges: Software or sequencer selectable on a per-channel basis
Crosstalk: -100 dB DC to 60 Hz; 86 dB @10 kHz

Voltage Range*	Accuracy** One Year, 0-35°C (% reading+% range)
	Absolute
0 to +10V	0.015 + 0.005
0 to +5V	0.015 + 0.005
0 to +2.5V	0.015 + 0.005
0 to +1.25V	0.015 + 0.008
0 to +0.625V	0.015 + 0.008
0 to +0.3125V	0.015 + 0.008
-10 to +10V	0.015 + 0.005
-5 to +5V	0.015 + 0.005
-2.5 to +2.5V	0.015 + 0.005
-1.25 to +1.25V	0.015 + 0.005
-0.625 to +0.625V	0.015 + 0.008
-0.3125 to +0.3125V	0.015 + 0.008
-0.156 to +0.156V	0.02 + 0.008

* Specifications assume differential input single channel scan, 200-kHz scan rate, unfiltered
 ** Accuracy specification is exclusive of noise



DaqScan/2000™ Series

Specifications & Ordering Information

Input Sequencer

Analog, digital and frequency inputs can be scanned synchronously, based on either an internal programmable timer, or an external clock source.

Scan Clock Sources: 2

1. Internal, programmable from 5 μ s to 5.96 hours in 1 μ s steps
2. External, TTL level input up to 200 kHz max

Programmable Parameters per Scan: Channel (random order), gain, unipolar/bipolar

Depth: 16,384 locations

On-Board Channel-to-Channel Scan Rate: 5 or 10 μ s per channel, programmable

Expansion Channel Scan Rate: 5 μ s, 10 μ s, or 1000 μ sec per channel, programmable

External Acquisition Scan Clock Input

Maximum Rate: 200 kHz

Clock Signal Range: 0V to +5V

Minimum Pulse Width: 50 ns high, 50 ns low

External SYNC Port: Available on rear panel, allows multiple DaqScan units to be scan-synchronous (post trigger)

Triggering

Trigger Sources: 6, individually selectable for starting and stopping an acquisition. Stop acquisition can occur on a different channel than start acquisition; stop acquisition can be triggered via modes 2, 4, 5 or 6 described below.

1. Single-Channel Analog Hardware Trigger

Any analog input channel can be software programmed as the analog trigger channel, including any of the 256 analog expansion channels.

2. Single-Channel Analog Software Trigger

Any analog input channel, including any of the 256 analog expansion channels, can be selected as the software trigger channel. If the trigger channel involves a calculation, such as temperature, then the driver automatically compensates for the delay required to obtain the reading, resulting in a maximum latency of one scan period.

3. Single-Channel Digital Trigger

A separate digital input is provided for digital triggering.

4. Digital Pattern Triggering

8- or 16-bit pattern triggering on any of the digital input ports. Programmable for trigger on equal, above, below, or within/outside of a window. Individual bits can be masked for "don't care" condition.

5. Counter/Totalizer Triggering

Counter/totalizer inputs can trigger an acquisition. User can select to trigger on a frequency or on total counts that are equal, above, below, or within/outside of a window.

6. Software Triggering

Trigger can be initiated under program control.

Analog Output (Models /2001 & /2004)

The four analog output channels are updated synchronously relative to scanned inputs, and clocked from either an internal onboard clock, or an external clock source. Analog outputs can also be updated asynchronously, independent of any other scanning in the system.

Channels: 4

Resolution: 16 bits

Data Buffer: 256 Ksample

Output Voltage Range: \pm 10V

Output Current: \pm 10 mA

Offset Error: \pm 0.0045V max

Digital Feedthru: 50 mV when updated

Gain Error: \pm 0.01%

Update Rate: 100 kHz max, 1.5 Hz min (no minimum with external clock)

Settling Time: 10 μ sec max to 1 LSB for full-scale step

Scan Sources: 4, programmable

1. Onboard D/A clock, independent of scanning input clock
2. Onboard scanning input clock
3. External D/A input clock, independent of external scanning input clock
4. External scanning input clock

Digital I/O

Channels: 40, expandable up to 272 with external digital DBK options

Input Scanning Modes: 2

1. Asynchronous, under program control at any time relative to input scanning
2. Synchronous with input scanning

Ports: 3 x 8-bit (82C55 emulation), and 1 x 16-bit; each port is programmable as input or output

Input Protection: \pm 8KV ESD clamp diodes parallel

I/O Levels: TTL

Sampling Rate: 200 kHz max

Update Rate: Asynchronous under program control

Frequency/Pulse Counters

Counter inputs can be scanned synchronously along with analog and digital scanned inputs, based either on internal programmable timer, or an external clock source. Counters can be configured to clear when read, or to totalize and clear under program control.

Channels: 4 x 16-bit; cascadable as 2 x 32-bit

Frequency Measurement Rate: 10 MHz max

Input Signal Range: -15V to +15V

Trigger Level: TTL

Minimum Pulse Width: 50 ns high, 50 ns low

Frequency/Pulse Generators

Channels: 2 x 16-bit

Output Waveform: Square wave

Output Rate: 1-MHz base rate divided by 1 to 65535 (programmable)

High-Level Output Voltage: 2.0V min @ -3.75 mA; 3.0V min @ -2.5 mA

Low-Level Output Voltage: 0.4V max @ 2.5 mA

Ordering Information

Description

All DaqScan models include 10/100BaseT Ethernet interface; drivers for IVI, LabVIEW®, DASyLab, C++, Visual Basic®, and ActiveX/COM; DB37 connectors, external SYNC, and rack-mount kit

Description	Part No.
Analog I/O, digital I/O, and frequency I/O	DaqScan/2001
Digital I/O, and frequency I/O	DaqScan/2002
Analog output, digital I/O, and frequency I/O	DaqScan/2004
Analog input, digital I/O, and frequency I/O	DaqScan/2005

For complete information on accessories and cables, visit www.iotech.com/acc

Related Products

Hardware

DBK1	p. 116
DBK2	p. 117
DBK4	p. 118
DBK5	p. 120
DBK7	p. 122
DBK8	p. 124
DBK9	p. 125
DBK10	p. 126
DBK11A	p. 127
DBK15	p. 128
DBK16	p. 130
DBK17	p. 132
DBK18	p. 134
DBK20	p. 136
DBK21	p. 136
DBK23	p. 137
DBK24	p. 139
DBK25	p. 141
DBK32A	p. 143
DBK40	p. 145
DBK41	p. 146
DBK42	p. 148
DBK43A	p. 150
DBK44	p. 152
DBK45	p. 154
DBK50	p. 156
DBK51	p. 156
DBK55	p. 158
DBK60	p. 160
DBK65	p. 162
DBK70	p. 164
DBK80	p. 169
DBK81	p. 170
DBK82	p. 170
DBK83	p. 170
DBK84	p. 170
DBK85	p. 172
DBK90	p. 173
DBK100	p. 175
DBK101	p. 175
DBK202	p. 200
DBK203	p. 200
DBK206	p. 177
DBK207	p. 178
DBK207/CJC	p. 178
DBK208	p. 180
DBK210	p. 182