

# IC-F22SR

Can be used by  
**Anyone,**  
**Anytime,**  
**Anywhere!**



- 52 CTCSS/83 DTCS tone frequencies reduces interference from other radios and allows for more private communication
- 16 different call ring tones allow you to form work groups
- Smart Ring function lets you know whether a recipient has received your call
- Power Save function prolongs the battery life
- Wide range of accessories available

- Licence Free\* Radio - no running costs (you only have to recharge the batteries), no call charge, no age restriction (\*Licence is required in some countries)
- Hundreds of applications from leisure to business use
- Easy to use - only three main controls (transmit button, volume control and channel selector)
- Slim design and tough body
- Compact and lightweight body




**SPECIFICATIONS**

- Frequency coverage : 446.00625–446.09375MHz
  - Number of channels : 8 (Simplex)
  - Power supply requirement : 7.2V DC
  - Current drain
    - Tx High (0.5W ERP) : 0.6A (approx.)
    - Rx Rated audio : 250mA
  - Operating temperature range : -25°C to +55°C
  - Dimensions (proj. not included): 54(W)×128(H)×37(D)mm
  - Weight (with BP-222) : 317g
  - Output power (at 7.2V DC) : 500mW ERP
  - External mic. connector : 3-conductor 2.5(d)mm /2.2kΩ
  - Audio output power : 500mW typical at 5% (at 7.2V DC) distortion with an 8Ω load
  - External speaker connector: 2-conductor 3.5(d)mm /8Ω
  - Communication range\* : Approx. 3km (Wide open space)
- \* Communication range may differ depending on operational environment or weather conditions, etc.

**Supplied accessories:**  
 • Battery pack; BP-222 • Belt clip; MB-68 • Battery charger

Measurements made in accordance with ETS 300 296.  
 All stated specifications are subject to change without notice or obligation.



**OPTIONS**


**BATTERY PACKS AND CASE**



BATTERY PACKS AND CASE	BP-208	BP-209	BP-210	BP-222
BATTERY LIFE	-	14.5 hours	21.5 hours	8.0 hours

Battery life is approx. time; (Tx: Rx: standby=5:5:90)

**REGULAR CHARGER**




**BC-146 DESKTOP CHARGER**  
 + **BC-147A/E AC ADAPTER**  
 Charges the battery pack, BP-209, BP-210 or BP-222 with/without transceiver in 12, 18.5, 6.5 hours (approx.), respectively. The BC-147 AC ADAPTER is additionally required.

**RAPID CHARGERS**




**BC-144 DESKTOP CHARGER + BC-145A/E/V AC ADAPTER**  
 For rapid charging of battery pack, BP-209, BP-210 or BP-222. An AC adapter, BC-145, is supplied with the charger depending on version. Charging time: 1.5 to 2 hours. BC-119 is also available for rapid charging.  
**BC-121 MULTI-CHARGER + AD-94 (Ver. 11) DESKTOP CHARGER ADAPTER + BC-124 AC ADAPTER**  
 For rapid charging of up to 6 battery packs (Six AD-94s are required), BP-209, BP-210 or BP-222. An AC adapter, BC-124, may be supplied, depending on version. Charging time: 1.5 to 2 hours.

**SPEAKER-MICROPHONES**



HM-46L: Slim dimensions. Equipped with an earphone jack and a transmit indicator.  
 HM-75A: Allows you to remotely select operating channel, etc., according to cloning.  
 HM-131L: Compact and durable body. Equipped with an earphone jack and a revolving clip.



For hands-free operation. Includes VOX, PTT and "one-touch" PTT with a time-out timer.



Flexible boom microphone and rotating earbud with a spring earhook. Use with the VS-1L.



Allows you hands-free operation. Use with the HS-94.

**BELT CLIPS**



MB-74: Alligator type. Clips to almost anything in a variety of convenient places.  
 MB-68: Same as that supplied.

**HM-128L EARPHONE-MICROPHONE**



The light weight earphone-mic. has a compact microphone with PTT switch that clips to your lapel.

**SP-13 EARPHONE**



Provides clear audio even in noisy environments.

**Icom Inc.**

1-1-32, Kamiminami, Hirano-ku, Osaka 547-0003, Japan Phone: 06 6793 5302 Fax: 06 6793 0013 URL: <http://www.icom.co.jp/world/index.html>

**Count on us!**

**Icom America Inc.**  
 <Corporate Headquarters>  
 2380 116th Avenue N.E., Bellevue, WA 98004, U.S.A.  
 Phone: (425) 454-8155 Fax: (425) 454-1509  
 URL : <http://www.icomamerica.com>  
 <Customer Service> Phone : (425) 454-7619

**Icom Canada**  
 Glenwood Centre #150-6165 Highway 17,  
 Delta, B.C., V4K 5B8, Canada  
 Phone: (604) 952-4266 Fax: (604) 952-0090  
 URL : <http://www.icomcanada.com>

**Icom (Australia) Pty. Ltd.**  
 A.B.N. 88 006 092 575  
 290-294 Albert Street, Brunswick, Victoria, 3056, Australia  
 Phone: 03 9387 0666 Fax: 03 9387 0022  
 URL : <http://www.icom.net.au>

**Icom New Zealand**  
 146A Harris Road, East Tamaki, Auckland, New Zealand  
 Phone: 09 274 4062 Fax: 09 274 4708  
 URL : <http://www.icom.co.nz>

**Icom (Europe) GmbH**  
 Communication Equipment  
 Himmelgeister Str. 100, D-40225 Düsseldorf, Germany  
 Phone: 0211 346047 Fax: 0211 333639  
 URL : <http://www.icomeurope.com>

**Icom Spain S.L.**  
 Ctra. de Gracia a Manresa Km. 14,750  
 08190 Sant Cugat del Valles Barcelona, SPAIN  
 Phone: (93) 590 26 70 Fax: (93) 589 04 46  
 URL : <http://www.icomspain.com>

**Icom (UK) Ltd.**  
 Unit 9, Sea St., Herne Bay, Kent, CT6 8LD, U.K.  
 Phone: 01227 741741 Fax: 01227 741742  
 URL : <http://www.icomuk.co.uk>

**Icom France S.a**  
 Zac de la Plaine, Rue Brindejonc des Moulinais  
 BP 5804, 31505 Toulouse Cedex, France  
 Phone: 561 36 03 03 Fax: 561 36 03 00  
 URL : <http://www.icom-france.com>

**Asia Icom Inc.**  
 6F No. 68, Sec. 1 Cheng-Teh Road,  
 Taipei, Taiwan, R.O.C.  
 Phone: (02) 2559 1899 Fax: (02) 2559 1874  
 URL : <http://www.asia-icom.com>

Your local distributor/dealer:



Certificate Number Q14190

Icom Inc. (Japan), is an ISO9001 certification acquired company.