



VHF MARINE TRANSCEIVER

IC-M34

It floats!

FLOATING

Submersible

1m depth for 30 minutes




Introducing the world's first*¹ 5W VHF marine transceiver that floats! If you drop the IC-M34 into water, the radio comes up to the surface so that you can easily retrieve it from out of the water. As the radio has a rugged submersible body*², it will keep on working even after it has been submerged. Reliable marine communications that won't let you down in or out of your boat!

When floating in calm water, the base of the radio is level with the water surface.
*¹ First as a 5W VHF marine handheld transceiver as researched by Icom as of November 2006.
*² 1m depth for 30 minutes, equivalent to IPX7. The IC-M34 is not designed to be used underwater.

Easy to see LCD with large channel indication

The IC-M34 has an easy to see LCD (32 x16 mm; 1¼x5⁄8 in) with large 2-digit channel number indication. The volume and SQL levels are shown in the display. LCD and key backlighting is standard for night time operation.



Actual display size.

Easy to use, easy to hold

9 large buttons on the front panel provide simple straight forward operation. It weighs only 305g, and the IC-M34's easy-to-hold rounded body fits comfortably in your hand.

Quick channel selection with favorite channel function

The favorite channel function offers quick channel access to tagged channels by pushing the "FAV" button, while ignoring untagged channels.

Li-Ion battery and charger standard

A Lithium-Ion battery pack and battery charger are supplied as standard. The BP-252 Lithium-Ion battery pack provides 9 hours* of operating time.

* Typical operation with Tx (Hi): Rx: standby=5:5:90

AquaQuake draining function

The AquaQuake draining function emits a vibrating sound that clears water away from the speaker grill.

Optional speaker-microphone, HM-165

A new waterproof speaker-microphone, HM-165, is optional. It uses a waterproof, screw-type connector to the IC-M34 and still allows the IC-M34 to float when connected.

Other features

- Powerful 5W output power
- Dual/Tri-watch functions
- 4-step battery life indicator
- Weather channel with weather alert
- 2-step power saver
- Auto scan function
- Instant access to Ch 16 or Ch 9
- Optional battery case for using with alkaline cells*

(* The IC-M34 floats when used with most common-brand AAA batteries. Battery weight varies by manufacturer. Please check your IC-M34 for buoyancy in a shallow area when using AAA batteries.)

SPECIFICATIONS

GENERAL

- Frequency range :
 - Tx 156.025–157.425MHz
 - Rx 156.050–163.275MHz
- Usable channels : INT, USA, CAN, WX channels
- Type of emission : 16K0G3E (FM)
- Current drain (at 7.4V DC) :
 - Tx at 5W output 1.5A
 - Rx AF max. 200mA typical
- Operating temp. range : -20°C to +60°C; -4°F to +140°F
- Antenna impedance : 50Ω (STUD)
- Dimensions (W×H×D) : 62×141.5×41 mm; 2⅞×5⅝×1⅞ in
- Weight (approx.) : 305g; 10.8oz (With BP-252, FA-SC58V and MB-109)

TRANSMITTER

- Output power : 5W (High), 1W (Low) 2W (High, with alkaline cells)
- Max. frequency deviation : ±5kHz
- Frequency error : ±10ppm
- Spurious emissions : -68dBc
- Adjacent channel power : 70dB
- Audio harmonic distortion : 10% (at 60% dev.)
- Residual modulation : 40dB

RECEIVER

- Receive system : Double-conversion superheterodyne
- Sensitivity (at 12dB SINAD) : 0.25µV typical
- SQL sensitivity (at threshold) : 0.35µV typical
- Adjacent Ch. selectivity : 70dB typical
- Spurious response : 70dB typical
- Intermodulation rejection : 70dB typical
- Hum and noise ratio : 40dB
- Audio output power : 0.35W typical at 10% distortion with an 8Ω load


Measured in accordance with TIA/EIA-603. All stated specifications are subject to change without notice or obligation.

Supplied accessories:


- Li-Ion battery pack, BP-252
 - AC adapter, BC-174A/E*
 - Antenna, FA-SC58V
 - Battery charger, BC-173
 - Belt clip, MB-109
 - Hand strap
- (* Depending on version)

OPTIONS

Some options may not be available in some countries. Please ask your dealer for details.



BP-251 AAA (LR03)×5 BATTERY CASE
Output power: 2W (at high power).
BP-252 7.4V/980mAh Li-Ion BATTERY PACK
Provides 9 hours operating time (approx.).
(Typical operation with Tx (Hi): Rx: stand-by=5:5:90)



BC-173 DESKTOP CHARGER
+ **BC-174A/E** AC ADAPTER
Regularly charges the battery pack, BP-252 in 10 hours (approx.).



BC-162 DESKTOP CHARGER
+ **BC-145A/E** AC ADAPTER
Rapidly charges the battery pack, BP-252 in 2 hours (approx.).



HM-165 SPEAKER-MICROPHONE
Waterproof construction equivalent to IPX7 (1 m depth for 30 min.).



MB-109 BELT CLIP
Alligator type. Same as supplied.



FA-SC58V ANTENNA
Soft flexible antenna. Same as supplied.

Icom Inc. 1-1-32, Kami-minami, Hirano-ku, Osaka 547-0003, Japan Phone: +81 (06) 6793 5302 Fax: +81 (06) 6793 0013

URL: <http://www.icom.co.jp/world/index.html>

Count on us!

Icom America Inc.

2380 116th Avenue NE,
Bellevue, WA 98004, U.S.A.
Phone : +1 (425) 454-8155
Fax : +1 (425) 454-1509
E-mail : sales@icomamerica.com
URL : <http://www.icomamerica.com>

Icom New Zealand

146A Harris Road, East Tamaki,
Auckland, New Zealand
Phone : +64 (09) 274 4062
Fax : +64 (09) 274 4708
E-mail : inquiries@icom.co.nz
URL : <http://www.icom.co.nz>

Icom (UK) Ltd.

Unit 9, Sea St., Herne Bay,
Kent, CT6 8LD, U.K.
Phone : +44 (01227) 741741
Fax : +44 (01227) 741742
E-mail : info@icomuk.co.uk
URL : <http://www.icomuk.co.uk>

Asia Icom Inc.

6F No. 68, Sec. 1 Cheng-Teh Road,
Taipei, Taiwan, R.O.C.
Phone : +886 (02) 2559 1899
Fax : +886 (02) 2559 1874
E-mail : sales@asia-icom.com
URL : <http://www.asia-icom.com>

Your local distributor/dealer:

Icom Canada

Glenwood Centre #150-6165 Highway 17,
Delta, B.C., V4K 5B8, Canada
Phone : +1 (604) 952-4266
Fax : +1 (604) 952-0090
E-mail : info@icomcanada.com
URL : <http://www.icomcanada.com>

Icom (Europe) GmbH

Communication Equipment
Himmelgeister Str. 100,
D-40225 Düsseldorf, Germany
Phone : +49 (0211) 346047
Fax : +49 (0211) 333639
E-mail : info@icomeurope.com
URL : <http://www.icomeurope.com>

Icom France s.a.s.

Zac de la Plaine,
1 Rue Brindejonn des Moulinais, BP 45804,
31505 Toulouse Cedex 5, France
Phone : +33 (5) 61 36 03 03
Fax : +33 (5) 61 36 03 00
E-mail : icom@icom-france.com
URL : <http://www.icom-france.com>

Icom (Australia) Pty. Ltd.

Unit 1 / 103 Garden Road,
Clayton VIC 3168 Australia
Phone : +61 (03) 9549 7500
Fax : +61 (03) 9549 7505
E-mail : sales@icom.net.au
URL : <http://www.icom.net.au>

Icom Spain S.L.

Ctra. Rubi, No. 88 "Edificio Can Castanyer"
08190, Sant Cugat del Valles, Barcelona, Spain
Phone : +34 (93) 590 26 70
Fax : +34 (93) 590 04 46
E-mail : icom@icomspain.com
URL : <http://www.icomspain.com>

Icom Polska

Sopot, 3 maja 54, Poland
Phone : +48 (58) 550 7135
Fax : +48 (58) 551 0484
E-mail : icompolkska@icompolkska.com.pl
URL : <http://www.icompolkska.com.pl>