

JVC

SERVICE MANUAL

COLOUR TELEVISION

AV-RX29_(HK)

BASIC CHASSIS

JK

The following item for the AV-RX29(HK) model were changed from those of the AV-29RS model. Therefore, this service manual describes only the items which differ from those of the AV-29RS service manual.

For details other than those described in this manual, please refer to the AV-29RS service manual (No.51730, Jul, 2000).

■ MAIN DIFFERENCE ITEMS

ITEMS No.	ITEMS	AV-29RS (No.51730)	AV-RX29(HK) (No.51748)	Remarks
1	Tele text	FLOF(fastext) / WST	NON	
2	Power plug	Round Pin type	UK pin type	
3	Instruction Book	English	English & Chinese	
4	Remote control unit	RM-C112	RM-C115	
5	OSD Language	Eng. / Ara. / Fre. / Rus.	Eng. / Chinese	
6	Main PWB	SJK-1003A-H2	SJK-1011A-H2	See next page

■ DIFFERENCE PARTS LIST

● EXPLODED VIEW PARTS LIST (Page35,36)

△	Ref. No.	Model No. & Parts No.		Parts Name	Remarks
		AV-29RSB (No.51726)	AV-SX29(HK) (No.51746)		
△	13	QMP40D0-200J5	QMPN050-200-E2	POWER CORD	Not Interchangeable
△	16	LC20377-001B-H	LC20377-012B-H	RATING LABEL	↑
△	37	LC10761-002B-H	LC10761-012B-H	FRONT CABI. ASS'Y	↑
	38	LC20532-003B-H	LC20532-007B-H	DOOR	↑

● PACKING (Page49)

	1	LC10845-006A-H	LC10845-009A-H	PACKING CASE	↑
	4	RM-C112-2H	RM-C115-2H	REMOCON UNIT	↑
△	6	LCT0660-001B-H	LCT0813-001A-H	INST BOOK	↑

● MAIN PWB PARTS LIST (Page38-41)

△	Ref. No.	Parts Number		Parts Name	Remarks
		AV-29RS(No.51730)	AV-RX29(HK)(No.51748)		
		SJK-1003A-H2	SJK-1011A-H2		
R1329		NRSA02J-102X	NRSA02J-0R0X	CHIP RESISTER	
R1330		NRSA02J-472X	NRSA02J-0R0X	CHIP RESISTER	
R1522		NRSA02J-153X	_____	CHIP RESISTER	
R1523		NRSA02J-103X	_____	CHIP RESISTER	
R1524		NRSA02J-152X	_____	CHIP RESISTER	
R1661		NRSA02J-103X	_____	CHIP RESISTER	
R1664		NRSA02J-562X	_____	CHIP RESISTER	
R1871		NRSA02J-102X	_____	CHIP RESISTER	
R1872-74		NRSA02J-222X	_____	CHIP RESISTER	
R1875		NRSA02J-0R0X	_____	CHIP RESISTER	
R1876		NRSA02J-102X	_____	CHIP RESISTER	
R1877		NRSA02J-393X	_____	CHIP RESISTER	
R1878-80		NRSA02J-182X	_____	CHIP RESISTER	
R1881-82		NRSA02J-181X	_____	CHIP RESISTER	
R1883		NRSA02J-102X	_____	CHIP RESISTER	
R1884		NRSA02J-181X	_____	CHIP RESISTER	
C1312		_____	NDC21HJ-680X	C CAP.	68pF 50V J
C1324-26		QETN1HM-105Z	_____	E CAP.	
C1334-36		_____	NCB21HK-103X	E CAP.	0.01 μF 50V K
C1871		NCB21EK-104X	_____	CHIP C CAP.	
C1872		NCB21HK-223X	_____	CHIP C CAP.	
C1873		NDC21HJ-221X	_____	CHIP C CAP.	
C1874-75		NDC21HJ-150X	_____	CHIP C CAP.	
C1876		NDC21HJ-221X	_____	CHIP C CAP.	
C1877		NCB21EK-104X	_____	CHIP C CAP.	
C1878		NCB21HK-102X	_____	CHIP C CAP.	
C1879		NDC21HJ-221X	_____	CHIP C CAP.	
C1880		QETN1AM-477Z	_____	E CAP.	
C1881		NCB21EK-104X	_____	CHIP C CAP.	
C1882		QETN1EM-476Z	_____	E CAP.	
C1883		NCB21HK-103X	_____	CHIP C CAP.	
C1884		NCB21EK-104X	_____	CHIP C CAP.	
C1885		NCB21EK-104X	_____	CHIP C CAP.	
C1886		NCB21HK-103X	_____	CHIP C CAP.	
L1871		QQL244K-4R7Z	_____	PEAKING COIL	
L1872		QQL244K-3R3Z	_____	PEAKING COIL	
D1303		MA111-X	_____	CHIP DIODE	
Q1501		2SC2412K/QR/-X	_____	CHIP TRANSISTER	
Q1613		2SA1037AK/QR/-X	_____	SI TRANSISTER	
Q1871		2SA1037AK/QR/-X	_____	SI TRANSISTER	
Q1872		2SC2412K/QR/-X	_____	CHIP TRANSISTER	
IC1701		M37280MF-173SP	M37280MF-171SP	I.C.	
IC1871		ET417	_____	I.C.	
IC1872		ET211	_____	I.C.	
X1871		CE41257-001Z	_____	X TAL	



VICTOR COMPANY OF JAPAN, LIMITED

HOME AV NETWORK BUSINESS UNIT 1106 Heta, Iwai-city, Ibaraki-prefecture, 306-0698, Japan

