

PARTS LIST

CONTENTS

■ USING PW BOARD & REMOTE CONTROL UNIT	23
■ EXPLODED VIEW PARTS LIST	24
■ EXPLODED VIEW	25
■ PRINTED WIRING BOARD PARTS LIST	

[AV-28BT8ENS / AV-28BT8ENB / AV-28BT80EN]

● MAIN PW BOARD ASS'Y	26
● CRT SOCKET PW BOARD ASSY	30
● FRONT CONTROL PW BOARD ASS'Y	30
● FRONT AV & HEADPHONE PW BOARD ASS'Y	30

[AV-28BT8EPS / AV-28BT8EPB / AV-28BT80EP]

● MAIN PW BOARD ASS'Y	31
● CRT SOCKET PW BOARD ASSY	34
● FRONT CONTROL PW BOARD ASS'Y	34
● FRONT AV & HEADPHONE PW BOARD ASSY	34

[AV-28BT8EES / AV-28BT8EEB]

● MAIN PW BOARD ASS'Y	35
● CRT SOCKET PW BOARD ASSY	38
● FRONT CONTROL PW BOARD ASS'Y	38
● FRONT AV & HEADPHONE PW BOARD ASSY	38

[AV-28BS88EN]

● MAIN PW BOARD ASS'Y	39
● CRT SOCKET PW BOARD ASSY	42
● FRONT CONTROL PW BOARD ASS'Y	42
● FRONT AV & HEADPHONE PW BOARD ASSY	42
■ PACKING / PACKING PARTS LIST	43

USING PW BOARD & REMOTE CONTROL UNIT


PWB ASS'Y / Model	AV-28BT8ENS AV-28BT8ENB AV-28BT80EN	AV-28BT8EPS AV-28BT8EPB AV-28BT80EP	AV-28BT8EES AV-28BT8EEB	AV-28BS88EN
MAIN PWB	VE-20101577	VE-20101576	VE-20101622	VE-20101578
CRT SOCKET PWB	VE-20094670	←	←	←
FRONT CONTROL PWB	VE-20082481	←	←	←
FRONT AV & HEADPHONE PWB	VE-20083646	←	←	←
REMOTE CONTROL UNIT	VE-30017763 (RM-C1100)	←	←	←

AV-28BT8ENS / AV-28BT8ENB / AV-28BT80EN
 AV-28BT8EPS / AV-28BT8EPB / AV-28BT80EP
 AV-28BT8EES / AV-28BT8EEB / AV-28BS88EN

EXPLODED VIEW PARTS LIST

△ Ref.No.	Part No.	Part Name	Description
△ V01	VE-30002751	PICTURE TUBE	(ITC)
△ L01	VE-30002138	DEG COIL	
△ TR601	VE-30017522	FBT	Within MAIN PWB
△ 1	VE-20083491	BUTTON ON/OFF	(SILVER MODEL)
△ 1	VE-20069016	BUTTON ON/OFF	(BLACK MODEL)
△ 2	VE-35004544	SPRING	
△ 3	VE-20069218	LENS (except AV-28BT80EN, AV-28BT80EP, AV-28BS88EN)	
△ 3	VE-20096162	LENS SILVER (AV-28BT80EN, AV-28BT80EP, AV-28BS88EN)	
△ 4	VE-20078776	LENS LED	
△ 5	VE-20004339	LENS PRE-AMP	
△ 6	VE-20101840	FRONT AV DOOR	(SILVER MODEL)
△ 6	VE-20101841	FRONT AV DOOR	(BLACK MODEL)
△ 7	VE-20003605	PIN (FRONT AV DOOR) (X2)	
△ 8	VE-40000026	EJECTOR	
△ 9	VE-20082289	FRONT CABINET	(SILVER MODEL)
△ 9	VE-20081489	FRONT CABINET	(BLACK MODEL)
△ 10	VE-30001946	SPEAKER 8R 15W	(X2)
△ 11	VE-20083502	BUTTON FUNCTION	(SILVER MODEL)
△ 11	VE-20069014	BUTTON FUNCTION	(BLACK MODEL)
△ 12	VE-20081578	BASE	
△ 13	VE-20094516	SHASSIS FRAME	
△ 14	VE-30015614	PFC TRF	
△ 15	VE-35000217	SCREW (3.5X9.5)	(X2)
△ 16	VE-20084616	BACK COVER	(SILVER MODEL)
△ 16	VE-20069018	BACK COVER	(BLACK MODEL)
△ 17	VE-35004572	SCREW (4X20)	(X8)
△ 18	VE-20067720	AV TERMINAL BOARD	
△ 19	VE-35000211	SCREW (2.9X9.5)	(X4)
△ 20	VE-20102137	RATING LABEL	(AV-28BT8ENS)
△ 20	VE-20102147	RATING LABEL	(AV-28BT8ENB)
△ 20	VE-20101937	RATING LABEL	(AV-28BT8EPS)
△ 20	VE-20101939	RATING LABEL	(AV-28BT8EPB)
△ 20	VE-20101919	RATING LABEL	(AV-28BT8EES)
△ 20	VE-20101920	RATING LABEL	(AV-28BT8EES POLAND)
△ 20	VE-20101915	RATING LABEL	(AV-28BT8EEB)
△ 20	VE-20101913	RATING LABEL	(AV-28BT8EEB POLAND)
△ 20	VE-20102144	RATING LABEL	(AV-28BT80EN)
△ 20	VE-20101934	RATING LABEL	(AV-28BT80EP)
△ 20	VE-20102141	RATING LABEL	(AV-28BS88EN)
△ 21	VE-40009154	LOGO JVC	(SILVER MODEL)
△ 21	VE-40009152	LOGO JVC	(BLACK MODEL)

EXPLODED VIEW



PRINTED WIRING BOARD PARTS LIST

[AV-28BT8ENS / AV-28BT8ENB / AV-28BT80EN]

MAIN P.W. BOARD ASS'Y (VE-20101577)

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R102	VE-30012657	SMD RES.	1/16W 1K J
R103	VE-30012657	SMD RES.	1/16W 1K J
R106	VE-30012713	SMD RES.	1/16W 75R J
R107	VE-30012649	SMD RES.	1/16W 150R J
R109	VE-30012713	SMD RES.	1/16W 75R J
R110	VE-30012713	SMD RES.	1/16W 75R J
R111	VE-30012649	SMD RES.	1/16W 150R J
R113	VE-30012713	SMD RES.	1/16W 75R J
R114	VE-30012713	SMD RES.	1/16W 75R J
R115	VE-30012713	SMD RES.	1/16W 75R J
R117	VE-30000792	CF RES.	1/4W 75R J
R118	VE-30012713	SMD RES.	1/16W 75R J
R121	VE-30012649	SMD RES.	1/16W 150R J
R122	VE-30000792	CF RES.	1/4W 75R J
R123	VE-30000792	CF RES.	1/4W 75R J
R124	VE-30012649	SMD RES.	1/16W 150R J
R126	VE-30012657	SMD RES.	1/16W 1K J
R129	VE-30012713	SMD RES.	1/16W 75R J
R135	VE-30012657	SMD RES.	1/16W 1K J
R137	VE-30000466	CF RES.	1/4W 1K J
R138	VE-30012657	SMD RES.	1/16W 1K J
R139	VE-30012713	SMD RES.	1/16W 75R J
R141	VE-30012657	SMD RES.	1/16W 1K J
R145	VE-30012713	SMD RES.	1/16W 75R J
R149	VE-30012703	SMD RES.	1/16W 56K J
R151	VE-30012696	SMD RES.	1/16W 47K J
R152	VE-30000752	CF RES.	1/4W 56K J
R153	VE-30012657	SMD RES.	1/16W 1K J
R154	VE-30000723	CF RES.	1/4W 47K J
R155	VE-30012649	SMD RES.	1/16W 150R J
R169	VE-30012703	SMD RES.	1/16W 56K J
R171	VE-30012713	SMD RES.	1/16W 75R J
R172	VE-30012692	SMD RES.	1/16W 4.7K J
R174	VE-30012713	SMD RES.	1/16W 75R J
R175	VE-30012713	SMD RES.	1/16W 75R J
R176	VE-30012703	SMD RES.	1/16W 56K J
R201	VE-30012674	SMD RES.	1/16W 27K J
R202	VE-30012692	SMD RES.	1/16W 4.7K J
R204	VE-30000459	CF RES.	1/4W 100R J
R206	VE-30000459	CF RES.	1/4W 100R J
R319	VE-30014076	SMD RES.	1/16W 4.7R J
R320	VE-30014076	SMD RES.	1/16W 4.7R J
R324	VE-30012667	SMD RES.	1/16W 220K J
R328	VE-30012649	SMD RES.	1/16W 150R J
R329	VE-30012692	SMD RES.	1/16W 4.7K J
R332	VE-30012641	SMD RES.	1/16W 10K J
R333	VE-30012702	SMD RES.	1/16W 560R J
R338	VE-30012641	SMD RES.	1/16W 10K J
R340	VE-30012644	SMD RES.	1/16W 12K J
R341	VE-30012702	SMD RES.	1/16W 560R J
R343	VE-30012659	SMD RES.	1/16W 2.2K J
R370	VE-30012669	SMD RES.	1/16W 22K J
R371	VE-30012669	SMD RES.	1/16W 22K J
R391	VE-30012696	SMD RES.	1/16W 47K J
R417	VE-30012510	SMD RES.	1/16W 100R J
R418	VE-30012510	SMD RES.	1/16W 100R J
R419	VE-30012649	SMD RES.	1/16W 150R J
R420	VE-30000466	CF RES.	1/4W 1K J
R421	VE-30012650	SMD RES.	1/16W 15K J
R422	VE-30012659	SMD RES.	1/16W 2.2K J
R423	VE-30012712	SMD RES.	1/16W 8.2K J
R425	VE-30012510	SMD RES.	1/16W 100R J
R426	VE-30012659	SMD RES.	1/16W 2.2K J
R427	VE-30012674	SMD RES.	1/16W 27K J
R428	VE-30012510	SMD RES.	1/16W 100R J
R430	VE-30012702	SMD RES.	1/16W 560R J
R431	VE-30012674	SMD RES.	1/16W 27K J
R432	VE-30012707	SMD RES.	1/16W 680R J
R433	VE-30012683	SMD RES.	1/16W 330K J
R437	VE-30000466	CF RES.	1/4W 1K J
R438	VE-30000466	CF RES.	1/4W 1K J
R439	VE-30012657	SMD RES.	1/16W 1K J
R440	VE-30012714	SMD RES.	1/16W 820R J
R441	VE-30012674	SMD RES.	1/16W 27K J
R442	VE-30000466	CF RES.	1/4W 1K J
R446	VE-30012714	SMD RES.	1/16W 820R J
R447	VE-30012714	SMD RES.	1/16W 820R J
R448	VE-30012683	SMD RES.	1/16W 330K J
R449	VE-30012659	SMD RES.	1/16W 2.2K J

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R450	VE-30012702	SMD RES.	1/16W 560R J
R458	VE-30012510	SMD RES.	1/16W 100R J
R459	VE-30012668	SMD RES.	1/16W 220R J
R460	VE-30012668	SMD RES.	1/16W 220R J
R461	VE-30012668	SMD RES.	1/16W 220R J
R462	VE-30012510	SMD RES.	1/16W 100R J
R467	VE-30000670	CF RES.	1/4W 330K J
R468	VE-30000670	CF RES.	1/4W 330K J
R469	VE-30000628	CF RES.	1/4W 2.7K J
R471	VE-30014022	SMD RES.	1/16W 47R J
R472	VE-30012662	SMD RES.	1/16W 2.7K J
R474	VE-30012662	SMD RES.	1/16W 2.7K J
R481	VE-30000466	CF RES.	1/4W 1K J
R482	VE-30012657	SMD RES.	1/16W 1K J
R483	VE-30012657	SMD RES.	1/16W 1K J
R485	VE-30012657	SMD RES.	1/16W 1K J
R486	VE-30012657	SMD RES.	1/16W 1K J
R487	VE-30012657	SMD RES.	1/16W 1K J
R507	VE-30000466	CF RES.	1/4W 1K J
R508	VE-30012510	SMD RES.	1/16W 100R J
R509	VE-30012641	SMD RES.	1/16W 10K J
R510	VE-30012702	SMD RES.	1/16W 560R J
R511	VE-30012657	SMD RES.	1/16W 1K J
R512	VE-30000495	CF RES.	1/4W 1.2K J
R513	VE-30000459	CF RES.	1/4W 100R J
R514	VE-30000459	CF RES.	1/4W 100R J
R515	VE-30012659	SMD RES.	1/16W 2.2K J
R516	VE-30012659	SMD RES.	1/16W 2.2K J
R517	VE-30012692	SMD RES.	1/16W 4.7K J
R518	VE-30000471	CF RES.	1/4W 10K J
R519	VE-30012698	SMD RES.	1/16W 5.6K J
R525	VE-30012649	SMD RES.	1/16W 150R J
R526	VE-30012641	SMD RES.	1/16W 10K J
R527	VE-30012692	SMD RES.	1/16W 4.7K J
R528	VE-30012698	SMD RES.	1/16W 5.6K J
R529	VE-30012698	SMD RES.	1/16W 5.6K J
R530	VE-30012698	SMD RES.	1/16W 5.6K J
R532	VE-30012659	SMD RES.	1/16W 2.2K J
R533	VE-30012644	SMD RES.	1/16W 12K J
R534	VE-30000628	CF RES.	1/4W 2.7K J
R537	VE-30012641	SMD RES.	1/16W 10K J
R538	VE-30012698	SMD RES.	1/16W 5.6K J
R539	VE-30012659	SMD RES.	1/16W 2.2K J
R540	VE-30012644	SMD RES.	1/16W 12K J
R545	VE-30012644	SMD RES.	1/16W 12K J
R548	VE-30012641	SMD RES.	1/16W 10K J
R554	VE-30012641	SMD RES.	1/16W 10K J
R555	VE-30012659	SMD RES.	1/16W 2.2K J
R556	VE-30012657	SMD RES.	1/16W 1K J
R560	VE-30012674	SMD RES.	1/16W 27K J
R561	VE-30012692	SMD RES.	1/16W 4.7K J
R568	VE-30000594	CF RES.	1/4W 22K J
R572	VE-30012659	SMD RES.	1/16W 2.2K J
R573	VE-30012641	SMD RES.	1/16W 10K J
R574	VE-30012657	SMD RES.	1/16W 1K J
R603	VE-30000459	CF RES.	1/4W 100R J
R604	VE-30012510	SMD RES.	1/16W 100R J
R606	VE-30000471	CF RES.	1/4W 10K J
R607	VE-30000554	CF RES.	1/4W 180R J
R608	VE-30000859	MF RES.	1/2W 1R F
R609	VE-30000711	CF RES.	1/2W 470R J
R610	VE-30000599	CF RES.	1/4W 220K J
R611	VE-30012708	SMD RES.	1/16W 68K J
R614	VE-30012509	SMD RES.	1/16W 100K J
R616	VE-30012669	SMD RES.	1/16W 22K J
R617	VE-30000572	CF RES.	1/4W 2K J
R630	VE-30012702	SMD RES.	1/16W 560R J
R634	VE-30000633	CF RES.	1/4W 27K J
R639	VE-30000471	CF RES.	1/4W 10K J
R640	VE-30000628	CF RES.	1/4W 2.7K J
R646	VE-30000531	CF RES.	1/4W 15K J
R647	VE-30000466	CF RES.	1/4W 1K J
△ R648	VE-30001246	FUSE RES.	1W 0.47R J
△ R650	VE-30012702	SMD RES.	1/16W 560R J
R651	VE-30012668	SMD RES.	1/16W 220R J
△ R656	VE-30001230	FUSE RES.	1/2W 27R J
△ R657	VE-30001228	FUSE RES.	1/2W 2.2R J
R662	VE-30012674	SMD RES.	1/16W 27K J
R666	VE-30000815	CF RES.	1/4W 8.2K J

[AV-28BT8ENS / AV-28BT8ENB / AV-28BT80EN]

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R668	VE-30000790	CF RES.	1/4W 6.8R J
R669	VE-30012510	SMD RES.	1/16W 100R J
R670	VE-30012510	SMD RES.	1/16W 100R J
R674	VE-30012662	SMD RES.	1/16W 2.7K J
△ R675	VE-30001244	FUSE RES.	1/2W 0.47R J
R677	VE-30001124	MO RES.	3W 220R J
R678	VE-30014022	SMD RES.	1/16W 47R J
R680	VE-30000477	CF RES.	1/4W 100K J
R681	VE-30012509	SMD RES.	1/16W 100K J
R682	VE-30008856	MO RES.	2W 270R J
R683	VE-30017083	WW RES.	5W 2.2K J RAD.
R689	VE-30000718	CF RES.	1/4W 4.7K J
R690	VE-30000466	CF RES.	1/4W 1K J
R691	VE-30012696	SMD RES.	1/16W 47K J
R692	VE-30012509	SMD RES.	1/16W 100K J
R693	VE-30012708	SMD RES.	1/16W 68K J
R694	VE-30000689	CF RES.	1/4W 3.9K J
R695	VE-30000471	CF RES.	1/4W 10K J
R696-Y	VE-30013350	ZENER DIODE	12V
R697	VE-30000712	CF RES.	1/4W 470R J
R698	VE-30012657	SMD RES.	1/16W 1K J
R699	VE-30012685	SMD RES.	1/16W 33K J
R700	VE-30012649	SMD RES.	1/16W 150R J
R701	VE-30000459	CF RES.	1/4W 100R J
R703	VE-30000459	CF RES.	1/4W 100R J
R705	VE-30000459	CF RES.	1/4W 100R J
R715	VE-30012702	SMD RES.	1/16W 560R J
R717	VE-30012702	SMD RES.	1/16W 560R J
R719	VE-30012657	SMD RES.	1/16W 1K J
R721	VE-30012510	SMD RES.	1/16W 100R J
R722	VE-30012510	SMD RES.	1/16W 100R J
R723	VE-30012510	SMD RES.	1/16W 100R J
R724	VE-30012510	SMD RES.	1/16W 100R J
R801	VE-30000718	CF RES.	1/4W 4.7K J
R803	VE-30012659	SMD RES.	1/16W 2.2K J
R805	VE-30000650	CF RES.	1/4W 33R J
R806	VE-30000982	MF RES.	1/4W 4.7K J
R807	VE-30001173	MO RES.	1W 0.47R J
R809	VE-30007784	MO RES.	5W 33K J (RADIAL)
△ R810	VE-30001257	MG RES.	1/2W 4.7M J
R811	VE-30000718	CF RES.	1/4W 4.7K J
R812	VE-30012641	SMD RES.	1/16W 10K J
R813	VE-30000466	CF RES.	1/4W 1K J
R814	VE-30000466	CF RES.	1/4W 1K J
R817	VE-30000880	MF RES.	1/4W 130K F
R818	VE-30012675	SMD RES.	1/16W 2K J
R819	VE-30000526	CF RES.	1/4W 1.5K J
R828	VE-30000530	CF RES.	1/2W 15K J
R829	VE-30000530	CF RES.	1/2W 15K J
R834	VE-30001159	MO RES.	1W 0.33R J
R836	VE-30012662	SMD RES.	1/16W 2.7K J
R839	VE-30000526	CF RES.	1/4W 1.5K J
R842	VE-30014128	SMD RES.	1/16W 33R J
R844	VE-30012641	SMD RES.	1/16W 10K J
R845	VE-30012509	SMD RES.	1/16W 100K J
R846	VE-30012692	SMD RES.	1/16W 4.7K J
R847	VE-30014128	SMD RES.	1/16W 33R J
R848	VE-30012641	SMD RES.	1/16W 10K J
R849	VE-30012510	SMD RES.	1/16W 100R J
R851	VE-30000718	CF RES.	1/4W 4.7K J
R852	VE-30000650	CF RES.	1/4W 33R J
R853	VE-30012642	SMD RES.	1/16W 120K J
R855	VE-30000459	CF RES.	1/4W 100R J
R856	VE-30012694	SMD RES.	1/16W 470K J

CAPACITOR

C141	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C142	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C143	VE-30012589	SMD CAP.	4.7NF 50V K
C144	VE-30012589	SMD CAP.	4.7NF 50V K
C145	VE-30012589	SMD CAP.	4.7NF 50V K
C146	VE-30012589	SMD CAP.	4.7NF 50V K
C147	VE-30012589	SMD CAP.	4.7NF 50V K
C148	VE-30012589	SMD CAP.	4.7NF 50V K
C149	VE-30012589	SMD CAP.	4.7NF 50V K
C150	VE-30012589	SMD CAP.	4.7NF 50V K
C155	VE-30012560	SMD CAP.	100PF 50V J
C157	VE-30012560	SMD CAP.	100PF 50V J
C159	VE-30000352	EL CAP.	100UF 16V M
C160	VE-30000345	EL CAP.	10UF 50V M
C161	VE-30000345	EL CAP.	10UF 50V M

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C162	VE-30012573	SMD CAP.	47PF 50V J
C164	VE-30012692	SMD RES.	1/16W 4.7K J
C165	VE-30000413	EL CAP.	4.7UF 50V M
C201	VE-30000400	EL CAP.	47UF 50V M
C205	VE-30000345	EL CAP.	10UF 50V M
C206	VE-30012610	SMD CAP.	10NF 50V J
C207	VE-30012610	SMD CAP.	10NF 50V J
C230	VE-30016654	SMD CAP.	100NF 16V K R
C246	VE-30000295	CER CAP.	100NF 50V Z F
C303	VE-30000100	MKT CAP.	330NF 63V J
C305	VE-30012590	SMD CAP.	47NF 50V K
C310	VE-30000345	EL CAP.	10UF 50V M
C333	VE-30000083	MKT CAP.	150NF 63V J
C363	VE-30000083	MKT CAP.	150NF 63V J
C364	VE-30012590	SMD CAP.	47NF 50V K
C366	VE-30000407	EL CAP.	470UF 16V M
C368	VE-30012590	SMD CAP.	47NF 50V K
C404	VE-30000190	CER CAP.	100PF 50V J CH
C408	VE-30012586	SMD CAP.	22NF 50V K
C409	VE-30000345	EL CAP.	10UF 50V M
C410	VE-30000384	EL CAP.	2.2UF 50V M
C411	VE-30000345	EL CAP.	10UF 50V M
C412	VE-30016654	SMD CAP.	100NF 16V K R
C413	VE-30000362	EL CAP.	1UF 50V M
C414	VE-30012585	SMD CAP.	2.2NF 50V K R
C415	VE-30012581	SMD CAP.	1NF 50V K
C416	VE-30000362	EL CAP.	1UF 50V M
C417	VE-30000362	EL CAP.	1UF 50V M
C418	VE-30016654	SMD CAP.	100NF 16V K R
C419	VE-30000384	EL CAP.	2.2UF 50V M
C420	VE-30000100	MKT CAP.	330NF 63V J
C422	VE-30000352	EL CAP.	100UF 16V M
C423	VE-30000352	EL CAP.	100UF 16V M
C424	VE-30000352	EL CAP.	100UF 16V M
C425	VE-30016654	SMD CAP.	100NF 16V K R
C427	VE-30016654	SMD CAP.	100NF 16V K R
C429	VE-30012589	SMD CAP.	4.7NF 50V K
C430	VE-30016654	SMD CAP.	100NF 16V K R
C431	VE-30000362	EL CAP.	1UF 50V M
C432	VE-30016654	SMD CAP.	100NF 16V K R
C433	VE-30000345	EL CAP.	10UF 50V M
C434	VE-30016654	SMD CAP.	100NF 16V K R
C435	VE-30016654	SMD CAP.	100NF 16V K R
C436	VE-30000384	EL CAP.	2.2UF 50V M
C437	VE-30016654	SMD CAP.	100NF 16V K R
C438	VE-30016654	SMD CAP.	100NF 16V K R
C439	VE-30016654	SMD CAP.	100NF 16V K R
C440	VE-30000295	CER CAP.	100NF 50V Z F
C441	VE-30012582	SMD CAP.	10NF 50V K R
C442	VE-30000362	EL CAP.	1UF 50V M
C443	VE-30000362	EL CAP.	1UF 50V M
C444	VE-30000384	EL CAP.	2.2UF 50V M
C448	VE-30012586	SMD CAP.	22NF 50V K
C449	VE-30012560	SMD CAP.	100PF 50V J
C453	VE-30000352	EL CAP.	100UF 16V M
C455	VE-30000345	EL CAP.	10UF 50V M
C459	VE-30012560	SMD CAP.	100PF 50V J
C501	VE-30016654	SMD CAP.	100NF 16V K R
C502	VE-30000400	EL CAP.	47UF 50V M
C504	VE-30016654	SMD CAP.	100NF 16V K R
C505	VE-30012589	SMD CAP.	4.7NF 50V K
C507	VE-30000345	EL CAP.	10UF 50V M
C510	VE-30016654	SMD CAP.	100NF 16V K R
C511	VE-30012566	SMD CAP.	22PF 50V J
C513	VE-30000345	EL CAP.	10UF 50V M
C514	VE-30016654	SMD CAP.	100NF 16V K R
C515	VE-30012560	SMD CAP.	100PF 50V J
C517	VE-30016654	SMD CAP.	100NF 16V K R
C518	VE-30016654	SMD CAP.	100NF 16V K R
C519	VE-30012560	SMD CAP.	100PF 50V J
C520	VE-30012560	SMD CAP.	100PF 50V J
C521	VE-30012562	SMD CAP.	15PF 50V J
C522	VE-30012562	SMD CAP.	15PF 50V J
C523	VE-30012585	SMD CAP.	2.2NF 50V K R
C524	VE-30012566	SMD CAP.	22PF 50V J
C525	VE-30012566	SMD CAP.	22PF 50V J
C526	VE-30016654	SMD CAP.	100NF 16V K R
C527	VE-30000345	EL CAP.	10UF 50V M
C529	VE-30012589	SMD CAP.	4.7NF 50V K
C530	VE-30012589	SMD CAP.	4.7NF 50V K
C532	VE-30016654	SMD CAP.	100NF 16V K R
C536	VE-30000295	CER CAP.	100NF 50V Z F
C541	VE-30000362	EL CAP.	1UF 50V M

[AV-28BT8ENS / AV-28BT8ENB / AV-28BT80EN]

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C542	VE-30000107	MKT CAP.	47NF 250V J
C543	VE-30000431	CER CAP.	100PF 1KV M
C544	VE-30000345	EL CAP.	100UF 50V M
C547	VE-30000345	EL CAP.	100UF 50V M
C565	VE-30016654	SMD CAP.	100NF 16V K R
C566	VE-30016654	SMD CAP.	100NF 16V K R
C567	VE-30000431	CER CAP.	100PF 1KV M
C602	VE-30017319	MKT CAP.	120NF 63V J
C604	VE-30000356	EL CAP.	100UF 63V M
C605	VE-30000360	EL CAP.	1000UF 25V M
C607	VE-30012581	SMD CAP.	1NF 50V K R
△ C618	VE-30000159	MKT CAP.	4.7NF 1.6KV J
△ C621	VE-30000179	MKT CAP.	9.1NF 1600V J
C622	VE-30000121	KP CAP.	27NF 630V J
△ C625	VE-30000156	MKT CAP.	430NF 250V J
C627	VE-30000167	MKT CAP.	560NF 250V J
C629	VE-30000177	MKT CAP.	820NF 250V J
C632	VE-30000100	MKT CAP.	330NF 63V J
C635	VE-30000385	EL CAP.	2.2UF 250V M
C636	VE-30000387	EL CAP.	33UF 50V M
C640	VE-30000100	MKT CAP.	330NF 63V J
C641	VE-30000090	MKT CAP.	22NF 100V J
C642	VE-30000407	EL CAP.	470UF 16V M
C644	VE-30000409	EL CAP.	470UF 25V M
C645	VE-30000090	MKT CAP.	22NF 100V J
C646	VE-30000100	MKT CAP.	330NF 63V J
C647	VE-30007748	EL CAP.	1000UF 35V M
C648	VE-30000394	EL CAP.	3.3UF 160V M
C649	VE-30000295	CER CAP.	100NF 50V Z F
C652	VE-30000330	CER CAP.	4.7NF 50V K B
C653	VE-30000107	MKT CAP.	47NF 250V J
C655	VE-30000415	EL CAP.	4.7UF 250V M
C700	VE-30012565	SMD CAP.	1.8PF 50V J CH
C701	VE-30012565	SMD CAP.	1.8PF 50V J CH
C702	VE-30012576	SMD CAP.	56PF 50V J CH
C703	VE-30012576	SMD CAP.	56PF 50V J CH
C704	VE-30012576	SMD CAP.	56PF 50V J CH
C705	VE-30000345	EL CAP.	100UF 50V M
C706	VE-30000345	EL CAP.	100UF 50V M
C708	VE-30016654	SMD CAP.	100NF 16V K R
C712	VE-30000345	EL CAP.	100UF 50V M
C713	VE-30016654	SMD CAP.	100NF 16V K R
C714	VE-30000100	MKT CAP.	330NF 63V J
C716	VE-30000100	MKT CAP.	330NF 63V J
C717	VE-30000100	MKT CAP.	330NF 63V J
C718	VE-30000100	MKT CAP.	330NF 63V J
C719	VE-30016654	SMD CAP.	100NF 16V K R
C720	VE-30000345	EL CAP.	100UF 50V M
C721	VE-30000100	MKT CAP.	330NF 63V J
C723	VE-30000100	MKT CAP.	330NF 63V J
C724	VE-30000345	EL CAP.	100UF 50V M
C729	VE-30016654	SMD CAP.	100NF 16V K R
C730	VE-30000393	EL CAP.	3.3UF 50V M
C733	VE-30000345	EL CAP.	100UF 50V M
C734	VE-30000345	EL CAP.	100UF 50V M
C735	VE-30016654	SMD CAP.	100NF 16V K R
C736	VE-30000345	EL CAP.	100UF 50V M
C737	VE-30000384	EL CAP.	2.2UF 50V M
C738	VE-30000384	EL CAP.	2.2UF 50V M
C739	VE-30000384	EL CAP.	2.2UF 50V M
C740	VE-30000384	EL CAP.	2.2UF 50V M
C741	VE-30012589	SMD CAP.	4.7NF 50V K
C742	VE-30012589	SMD CAP.	4.7NF 50V K
C745	VE-30016654	SMD CAP.	100NF 16V K R
△ C801	VE-30000094	MKT CAP.	220NF 275V M AC
△ C802	VE-30000094	MKT CAP.	220NF 275V M AC
△ C803	VE-30000433	CER CAP.	1NF 1KV M B
△ C804	VE-30000433	CER CAP.	1NF 1KV M B
C808	VE-30012590	SMD CAP.	47NF 50V K
C809	VE-30000420	EL CAP.	150UF 400V M
C810	VE-30000387	EL CAP.	33UF 50V M
C811	VE-30000161	MKT CAP.	47NF 630V J
C812	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
△ C816	VE-30000440	CER CAP.	2.2NF 4KV M
C817	VE-30000198	CER CAP.	120PF 500V J SL
C818	VE-30012590	SMD CAP.	47NF 50V K
C819	VE-30012590	SMD CAP.	47NF 50V K
C822	VE-30007308	CER CAP.	220PF 1KV K (PULSE)
C826	VE-30000406	EL CAP.	47UF 250V M (HR)
C827	VE-30000411	EL CAP.	4700UF 16V M
C828	VE-30012590	SMD CAP.	47NF 50V K
C829	VE-30000407	EL CAP.	470UF 16V M
C830	VE-30000383	EL CAP.	2200UF 25V M

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C832	VE-30012590	SMD CAP.	47NF 50V K
C833	VE-30000407	EL CAP.	470UF 16V M
C834	VE-30012590	SMD CAP.	47NF 50V K
C835	VE-30012590	SMD CAP.	47NF 50V K
C838	VE-30000407	EL CAP.	470UF 16V M
C839	VE-30000407	EL CAP.	470UF 16V M
C840	VE-30000407	EL CAP.	470UF 16V M
C848	VE-30000407	EL CAP.	470UF 16V M
C850	VE-30000383	EL CAP.	2200UF 25V M
C851	VE-30012590	SMD CAP.	47NF 50V K
△ C852	VE-30000440	CER CAP.	2.2NF 4KV M
C857	VE-30000106	MKT CAP.	47NF 100V J
C858	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
C859	VE-30009208	CER CAP.	470PF 1KV K (PULSE)
C860	VE-30000296	CER CAP.	100NF 100V Z F
C872	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
TRANSF			
TR600	VE-30002090	LINE DRIVER	
△ TR601	VE-30017522	FBT TRF	
△ TR802	VE-30018785	SMPS TRF	
COIL			
L101	VE-30001971	FERRITE BEAT	
L102	VE-30001971	FERRITE BEAT	
L106	VE-30001971	FERRITE BEAT	
L108	VE-30001971	FERRITE BEAT	
L109	VE-30001971	FERRITE BEAT	
L110	VE-30001971	FERRITE BEAT	
L111	VE-30001971	FERRITE BEAT	
L112	VE-30001971	FERRITE BEAT	
L113	VE-30001971	FERRITE BEAT	
L114	VE-30001971	FERRITE BEAT	
L115	VE-30001971	FERRITE BEAT	
L116	VE-30001971	FERRITE BEAT	
L117	VE-30001971	FERRITE BEAT	
L201	VE-30001979	FIXD COIL	1UH
L210	VE-30001971	FERRITE BEAT	
L215	VE-30001971	FERRITE BEAT	
L401	VE-30001971	FERRITE BEAT	
L402	VE-30001992	FIXD COIL	10UH
L403	VE-30001971	FERRITE BEAT	
L405	VE-30014048	ADJ. COIL	44MHz
L406	VE-30001971	FERRITE BEAT	
L408	VE-30001992	FIXD COIL	10UH
L501	VE-30001971	FERRITE BEAT	
L502	VE-30001971	FERRITE BEAT	
L503	VE-30001971	FERRITE BEAT	
L504	VE-30001971	FERRITE BEAT	
L600	VE-30002031	FIXD COIL	15MH
L602	VE-30002156	LINEARITY COIL	30UH
L603	VE-30002026	FIXD COIL	1MH
L700	VE-30001971	FERRITE BEAT	
L701	VE-30001971	FERRITE BEAT	
L702	VE-30001992	FIXD COIL	10UH
L703	VE-30001971	FERRITE BEAT	
L704	VE-30001971	FERRITE BEAT	
L801	VE-30002011	CHOKE COIL	150UH
L803	VE-30001992	FIXD COIL	10UH
DIODE			
D105	VE-30007760	ZENER DIODE	
D106	VE-30007760	ZENER DIODE	
D107	VE-30007760	ZENER DIODE	
D303	VE-30001329	DIODE	
D405	VE-30007763	ZENER DIODE	
D407	VE-30001284	DIODE	
D408	VE-30001285	DIODE	
D409	VE-30001284	DIODE	
D413	VE-30018526	ZENER DIODE	
D501	VE-30001285	DIODE	
D505	VE-30001285	DIODE	
D506	VE-30001284	DIODE	
D512	VE-30001285	DIODE	
D513	VE-30001369	ZENER DIODE	
D533	VE-30001377	ZENER DIODE	

[AV-28BT8ENS / AV-28BT8ENB / AV-28BT80EN]

△ Symbol No. Part No. Part Name Description

DIODE

D601	VE-30001329	DIODE	
D603	VE-30001285	DIODE	
D605	VE-30001320	DIODE	
D606	VE-30001323	DIODE	
D609	VE-30001318	DIODE	
D610	VE-30001318	DIODE	
D613	VE-30001318	DIODE	
D614	VE-30001285	DIODE	
D616	VE-30003696	DIODE	
D617	VE-30001318	DIODE	
D651	VE-30001285	DIODE	
D653	VE-30001285	DIODE	
D656	VE-30007763	ZENER DIODE	
D657	VE-30007763	ZENER DIODE	
D658	VE-30007763	ZENER DIODE	
D659	VE-30001350	ZENER DIODE	
D660	VE-30001347	ZENER DIODE	
D661	VE-30001350	ZENER DIODE	
D700	VE-30001285	DIODE	
D701	VE-30001369	ZENER DIODE	
D800	VE-30001318	DIODE	
D801	VE-30001372	ZENER DIODE	
D802	VE-30001318	DIODE	
D803	VE-30001315	DIODE	
D804	VE-30001318	DIODE	
D805	VE-30001315	DIODE	
D806	VE-30001315	DIODE	
D808	VE-20092405	CN. ASY	
D809	VE-30001329	DIODE	
D810	VE-30009366	DIODE	
D811	VE-30009366	DIODE	
D812	VE-30001285	DIODE	
D889	VE-30001384	TR	
△ D891	VE-30007758	BRIDGE DIODE	
D892	VE-30001318	DIODE	
D893	VE-30001318	DIODE	
D894	VE-30001285	DIODE	
D897	VE-30001329	DIODE	

TRANSISTOR

Q104	VE-30001457	TR	
Q106	VE-30001457	TR	
Q141	VE-30001457	TR	
Q142	VE-30001457	TR	
Q307	VE-30001457	TR	
Q316	VE-30001458	TR	
Q403	VE-30001457	TR	
Q404	VE-30001457	TR	
Q503	VE-30001457	TR	
Q504	VE-30001458	TR	
△ Q600	VE-30001435	TR	
Q601	VE-30001441	TR	H. OUT
Q602	VE-30001429	TR	
Q603	VE-30001458	TR	
Q604	VE-30001457	TR	
Q605	VE-30001458	TR	
Q700	VE-30001458	TR	
Q801	VE-30001386	TR	
Q802	VE-30001457	TR	
Q804	VE-30001454	TR	

IC

IC301	VE-30016113	IC	
IC403	VE-30014521	IC	
IC500	VE-20099532	IC	(SERVICE)
IC501	VE-20093395	IC	(MICOM)
IC601	VE-30013985	IC	
IC700	VE-30013658	IC	
IC800	VE-30011968	IC	
△ IC801	VE-30015087	IC	
IC802	VE-30001622	IC	
IC803	VE-30001500	IC	
IC804	VE-30001622	IC	
IC818	VE-30001506	IC	

△ Symbol No. Part No. Part Name Description

OTHERS

△ TR801	VE-30002104	LINE FILTER	
△ F801	VE-30001731	FUSE	2.5A
△ TH800	VE-30001270	PTC	9 OHM
TU201	VE-30009637	TUNER	
VR800	VE-30001064	RES ADJ	
X401	VE-30001749	XTAL	
X402	VE-30015592	XTAL	
X501	VE-30002851	XTAL	
X700	VE-30001756	XTAL	
Z401	VE-30001705	SAW FILTER	
Z402	VE-30015591	SAW FILTER	

[AV-28BT8ENS / AV-28BT8ENB / AV-28BT80EN]

CRT SOCKET P.W. BOARD ASS'Y (VE-20094670)

Symbol No.	Part No.	Part Name	Description
RESISTOR			
R900	30000788	CF RES.	1/4W 6.8M J
R902	30000459	CF RES.	1/4W 100R J
R903	30000459	CF RES.	1/4W 100R J
R904	30000459	CF RES.	1/4W 100R J
R906	30000535	CF RES.	1/2W 150K J
R907	30000477	CF RES.	1/4W 100K J
R908	30000477	CF RES.	1/4W 100K J
R909	30000525	CF RES.	1/2W 1.5K J
R910	30000525	CF RES.	1/2W 1.5K J
R911	30000525	CF RES.	1/2W 1.5K J
R912	30000477	CF RES.	1/4W 100K J
R913	30000525	CF RES.	1/2W 1.5K J
R914	30001084	MO RES.	1W 1K J
R916	30001170	MO RES.	1W 4.7K J
R917	30001208	FUSE RES.	1W 10R J
R918	30000471	CF RES.	1/4W 10K J
R921	30000599	CF RES.	1/4W 220K J
R922	30000590	CF RES.	1/4W 2.2K J

CAPACITOR

C900	30000075	MKT CAP.	100NF 250V K (DC)
C902	30000415	EL CAP.	4.7UF 250V M
C903	30000438	CER CAP.	2.2NF 2KV
C904	30000295	CER CAP.	100NF 50V Z F
C905	30000234	CER CAP.	270PF 50V J SL
C906	30000350	EL CAP.	10UF 250V M
C907	30000075	MKT CAP.	100NF 250V K (DC)
C909	30000385	EL CAP.	2.2UF 250V M
C910	30000438	CER CAP.	2.2NF 2KV
C911	30000433	CER CAP.	1NF 1KV M B

COIL

L900	30002170	COIL
------	----------	------

DIODE

D901	30001329	DIODE
D902	30001318	DIODE
D903	30001329	DIODE
D904	30001329	DIODE
D905	30001284	DIODE
D906	30001284	DIODE
D907	30001284	DIODE
D908	30001284	DIODE
D909	30001344	ZENER DIODE
NOT1	30001329	DIODE

TRANSISTOR

Q900	30001427	TR
Q901	30001454	TR

IC

IC900	30008721	IC
-------	----------	----

OTHERS

PL902	30001855	CRT SOCKET	
SG901	30000428	SPARK GAP	300V
SG902	30000428	SPARK GAP	300V
SG903	30000428	SPARK GAP	300V
SG904	30000428	SPARK GAP	300V

FRONT CONTROL P.W. BOARD ASS'Y (VE-20082481)

Symbol No.	Part No.	Part Name	Description
RESISTOR			
R2	VE-30000526	CF RES.	1/4W 1.5K J
R3	VE-30000770	CF RES.	1/4W 680R J
R4	VE-30000712	CF RES.	1/4W 470R J
R5	VE-30000622	CF RES.	1/4W 270R J

DIODE

D1	VE-30001279	LED RED/GREEN
----	-------------	---------------

IC

IC1	VE-30001670	PREAMPLIFIER
-----	-------------	--------------

OTHERS

SW1	VE-30002181	SWITCH TACT
SW2	VE-30002181	SWITCH TACT
SW3	VE-30002181	SWITCH TACT
SW4	VE-30002181	SWITCH TACT
SW5	VE-30002181	SWITCH TACT

FRONT AV & HEADPHONE P.W. BOARD ASS'Y (VE-20083646)

Symbol No.	Part No.	Part Name	Description
RESISTOR			
R109	VE-30000594	CF RES.	1/4W 22K J
R110	VE-30000712	CF RES.	1/4W 470R J
R113	VE-30000744	CF RES.	1/4W 560R J
R114	VE-30000744	CF RES.	1/4W 560R J
R115	VE-30000712	CF RES.	1/4W 470R J
R116	VE-30000712	CF RES.	1/4W 470R J

CAPACITOR

C103	VE-30000213	CER CAP.	180PF 50V J
C104	VE-30000213	CER CAP.	180PF 50V J
C106	VE-30000190	CER CAP.	100PF 50V J

COIL

L103	VE-30001996	FIXED COIL	22UH Q40 K
L104	VE-30001996	FIXED COIL	22UH Q40 K

PRINTED WIRING BOARD PARTS LIST

[AV-28BT8EPS / AV-28BT8EPB / AV-28BT80EP]

MAIN P.W. BOARD ASS'Y (VE-20101576)

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R102	VE-30012657	SMD RES.	1/10W 1K J
R103	VE-30012657	SMD RES.	1/10W 1K J
R106	VE-30012713	SMD RES.	1/10W 75R J
R107	VE-30012649	SMD RES.	1/10W 150R J
R109	VE-30012713	SMD RES.	1/10W 75R J
R110	VE-30012713	SMD RES.	1/10W 75R J
R111	VE-30012649	SMD RES.	1/10W 150R J
R113	VE-30012713	SMD RES.	1/10W 75R J
R114	VE-30012713	SMD RES.	1/10W 75R J
R115	VE-30012713	SMD RES.	1/10W 75R J
R117	VE-30000792	CF RES.	1/4W 75R J
R118	VE-30012713	SMD RES.	1/10W 75R J
R121	VE-30012649	SMD RES.	1/10W 150R J
R122	VE-30000792	CF RES.	1/4W 75R J
R123	VE-30000792	CF RES.	1/4W 75R J
R124	VE-30012649	SMD RES.	1/10W 150R J
R126	VE-30012657	SMD RES.	1/10W 1K J
R129	VE-30012713	SMD RES.	1/10W 75R J
R135	VE-30012657	SMD RES.	1/10W 1K J
R137	VE-30000466	CF RES.	1/4W 1K J
R138	VE-30012657	SMD RES.	1/10W 1K J
R139	VE-30012713	SMD RES.	1/10W 75R J
R141	VE-30012657	SMD RES.	1/10W 1K J
R145	VE-30012713	SMD RES.	1/10W 75R J
R149	VE-30012703	SMD RES.	1/10W 56K J
R151	VE-30012696	SMD RES.	1/10W 47K J
R152	VE-30000752	CF RES.	1/4W 56K J
R153	VE-30012657	SMD RES.	1/10W 1K J
R154	VE-30000723	CF RES.	1/4W 47K J
R155	VE-30012649	SMD RES.	1/10W 150R J
R169	VE-30012703	SMD RES.	1/10W 56K J
R171	VE-30012713	SMD RES.	1/10W 75R J
R172	VE-30012692	SMD RES.	1/10W 4.7K J
R174	VE-30012713	SMD RES.	1/10W 75R J
R175	VE-30012713	SMD RES.	1/10W 75R J
R176	VE-30012703	SMD RES.	1/10W 56K J
R201	VE-30012674	SMD RES.	1/10W 27K J
R202	VE-30012692	SMD RES.	1/10W 4.7K J
R204	VE-30000459	CF RES.	1/4W 100R J
R206	VE-30000459	CF RES.	1/4W 100R J
R319	VE-30014076	SMD RES.	1/10W 4.7K J
R320	VE-30014076	SMD RES.	1/10W 4.7K J
R324	VE-30012667	SMD RES.	1/10W 220K J
R328	VE-30012649	SMD RES.	1/10W 150R J
R329	VE-30012692	SMD RES.	1/10W 4.7K J
R332	VE-30012641	SMD RES.	1/10W 10K J
R333	VE-30012702	SMD RES.	1/10W 560R J
R338	VE-30012641	SMD RES.	1/10W 10K J
R340	VE-30012644	SMD RES.	1/10W 12K J
R341	VE-30012702	SMD RES.	1/10W 560R J
R343	VE-30012659	SMD RES.	1/10W 2.2K J
R370	VE-30012669	SMD RES.	1/10W 22K J
R371	VE-30012669	SMD RES.	1/10W 22K J
R391	VE-30012696	SMD RES.	1/10W 47K J
R402	VE-30012692	SMD RES.	1/10W 4.7K J
R407	VE-30000471	CF RES.	1/4W 10K J
R410	VE-30000471	CF RES.	1/4W 10K J
R412	VE-30000723	CF RES.	1/4W 47K J
R417	VE-30012510	SMD RES.	1/10W 100R J
R418	VE-30012510	SMD RES.	1/10W 100R J
R419	VE-30012649	SMD RES.	1/10W 150R J
R420	VE-30000466	CF RES.	1/4W 1K J
R421	VE-30012650	SMD RES.	1/10W 15K J
R422	VE-30012659	SMD RES.	1/10W 2.2K J
R423	VE-30012712	SMD RES.	1/10W 8.2K J
R425	VE-30012510	SMD RES.	1/10W 100R J
R426	VE-30012659	SMD RES.	1/10W 2.2K J
R427	VE-30012674	SMD RES.	1/10W 27K J
R428	VE-30012510	SMD RES.	1/10W 100R J
R430	VE-30012702	SMD RES.	1/10W 560R J
R431	VE-30012674	SMD RES.	1/10W 27K J
R432	VE-30012707	SMD RES.	1/10W 680R J
R433	VE-30012683	SMD RES.	1/10W 330K J
R437	VE-30000466	CF RES.	1/4W 1K J
R438	VE-30000466	CF RES.	1/4W 1K J
R439	VE-30012657	SMD RES.	1/10W 1K J
R440	VE-30012714	SMD RES.	1/10W 820R J
R441	VE-30012674	SMD RES.	1/10W 27K J
R442	VE-30000466	CF RES.	1/4W 1K J
R446	VE-30012714	SMD RES.	1/10W 820R J

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R447	VE-30012714	SMD RES.	1/10W 820R J
R448	VE-30012683	SMD RES.	1/10W 330K J
R449	VE-30012659	SMD RES.	1/10W 2.2K J
R450	VE-30012702	SMD RES.	1/10W 560R J
R458	VE-30012510	SMD RES.	1/10W 100R J
R459	VE-30012668	SMD RES.	1/10W 220R J
R460	VE-30012668	SMD RES.	1/10W 220R J
R461	VE-30012668	SMD RES.	1/10W 220R J
R462	VE-30012510	SMD RES.	1/10W 100R J
R467	VE-30000670	CF RES.	1/4W 330K J
R468	VE-30000670	CF RES.	1/4W 330K J
R469	VE-30000628	CF RES.	1/4W 2.7K J
R471	VE-30014022	SMD RES.	1/10W 47R J
R472	VE-30012662	SMD RES.	1/10W 2.7K J
R474	VE-30012662	SMD RES.	1/10W 2.7K J
R481	VE-30000466	CF RES.	1/4W 1K J
R482	VE-30012657	SMD RES.	1/10W 1K J
R483	VE-30012657	SMD RES.	1/10W 1K J
R485	VE-30012657	SMD RES.	1/10W 1K J
R486	VE-30012657	SMD RES.	1/10W 1K J
R487	VE-30012657	SMD RES.	1/10W 1K J
R507	VE-30000466	CF RES.	1/4W 1K J
R508	VE-30012510	SMD RES.	1/10W 100R J
R509	VE-30012641	SMD RES.	1/10W 10K J
R510	VE-30012702	SMD RES.	1/10W 560R J
R511	VE-30012657	SMD RES.	1/10W 1K J
R512	VE-30000495	CF RES.	1/4W 1.2K J
R513	VE-30000459	CF RES.	1/4W 100R J
R514	VE-30000459	CF RES.	1/4W 100R J
R515	VE-30012659	SMD RES.	1/10W 2.2K J
R516	VE-30012659	SMD RES.	1/10W 2.2K J
R517	VE-30012692	SMD RES.	1/10W 4.7K J
R518	VE-30000471	CF RES.	1/4W 10K J
R519	VE-30012698	SMD RES.	1/10W 5.6K J
R525	VE-30012649	SMD RES.	1/10W 150R J
R526	VE-30012641	SMD RES.	1/10W 10K J
R527	VE-30012692	SMD RES.	1/10W 4.7K J
R528	VE-30012698	SMD RES.	1/10W 5.6K J
R529	VE-30012698	SMD RES.	1/10W 5.6K J
R530	VE-30012698	SMD RES.	1/10W 5.6K J
R532	VE-30012659	SMD RES.	1/10W 2.2K J
R533	VE-30012644	SMD RES.	1/10W 12K J
R534	VE-30000628	CF RES.	1/4W 2.7K J
R537	VE-30012641	SMD RES.	1/10W 10K J
R538	VE-30012698	SMD RES.	1/10W 4.7K J
R539	VE-30012659	SMD RES.	1/10W 2.2K J
R540	VE-30012644	SMD RES.	1/10W 12K J
R545	VE-30012644	SMD RES.	1/10W 12K J
R548	VE-30012641	SMD RES.	1/10W 10K J
R552	VE-30012692	SMD RES.	1/10W 4.7K J
R554	VE-30012641	SMD RES.	1/10W 10K J
R555	VE-30012659	SMD RES.	1/10W 2.2K J
R556	VE-30012657	SMD RES.	1/10W 1K J
R560	VE-30012674	SMD RES.	1/10W 27K J
R561	VE-30012692	SMD RES.	1/10W 4.7K J
R568	VE-30000594	CF RES.	1/4W 22K J
R572	VE-30012659	SMD RES.	1/10W 2.2K J
R573	VE-30012641	SMD RES.	1/10W 10K J
R574	VE-30012657	SMD RES.	1/10W 1K J
R603	VE-30000459	CF RES.	1/4W 100R J
R604	VE-30012510	SMD RES.	1/10W 100R J
R606	VE-30000471	CF RES.	1/4W 10K J
R607	VE-30000554	CF RES.	1/4W 180R J
R608	VE-30000859	MF RES.	1/2W 1R F
R609	VE-30000711	CF RES.	1/2W 470R J
R610	VE-30000599	CF RES.	1/4W 220K J
R611	VE-30012708	SMD RES.	1/10W 68K J
R614	VE-30012509	SMD RES.	1/10W 100K J
R616	VE-30012669	SMD RES.	1/10W 22K J
R617	VE-30000572	CF RES.	1/4W 2K J
R630	VE-30012702	SMD RES.	1/10W 560R J
R634	VE-30000633	CF RES.	1/4W 27K J
R639	VE-30000471	CF RES.	1/4W 10K J
R640	VE-30000628	CF RES.	1/4W 2.7K J
R646	VE-30000531	CF RES.	1/4W 15K J
R647	VE-30000466	CF RES.	1/4W 1K J
△ R648	VE-30001246	FUSE RES.	1W 0.47R J
R650	VE-30012702	SMD RES.	1/10W 560R J
R651	VE-30012668	SMD RES.	1/10W 220R J
△ R656	VE-30001230	FUSE RES.	1/2W 27R J

[AV-28BT8EPS / AV-28BT8EPB / AV-28BT80EP]

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

RESISTOR

△ R657	VE-30001228	FUSE RES.	1/2W 2.2R J
R662	VE-30012674	SMD RES.	1/16W 27K J
R666	VE-30000815	CF RES.	1/4W 8.2K J
R668	VE-30000790	CF RES.	1/4W 6.8R J
R669	VE-30012510	SMD RES.	1/16W 100R J
R670	VE-30012510	SMD RES.	1/16W 100R J
R674	VE-30012662	SMD RES.	1/16W 2.7K J
△ R675	VE-30001244	FUSE RES.	1/2W 0.47R J
R677	VE-30001124	MO RES.	3W 220R J
R678	VE-30014022	SMD RES.	1/16W 47R J
R680	VE-30000477	CF RES.	1/4W 100K J
R681	VE-30012509	SMD RES.	1/16W 100K J
R682	VE-30008856	MO RES.	2W 270R J
R683	VE-30017083	WW RES.	5W 2.2K J RAD.
R689	VE-30000718	CF RES.	1/4W 4.7K J
R690	VE-30000466	CF RES.	1/4W 1K J
R691	VE-30012696	SMD RES.	1/16W 47K J
R692	VE-30012509	SMD RES.	1/16W 100K J
R693	VE-30012708	SMD RES.	1/16W 68K J
R694	VE-30000689	CF RES.	1/4W 3.9K J
R695	VE-30000471	CF RES.	1/4W 10K J
R696-Y	VE-30001350	ZENER DIODE	12V
R697	VE-30000712	CF RES.	1/4W 470R J
R698	VE-30012657	SMD RES.	1/16W 1K J
R699	VE-30012685	SMD RES.	1/16W 33K J
R700	VE-30012649	SMD RES.	1/16W 150R J
R701	VE-30000459	CF RES.	1/4W 100R J
R703	VE-30000459	CF RES.	1/4W 100R J
R705	VE-30000459	CF RES.	1/4W 100R J
R715	VE-30012702	SMD RES.	1/16W 560R J
R717	VE-30012702	SMD RES.	1/16W 560R J
R719	VE-30012657	SMD RES.	1/16W 1K J
R721	VE-30012510	SMD RES.	1/16W 100R J
R722	VE-30012510	SMD RES.	1/16W 100R J
R723	VE-30012510	SMD RES.	1/16W 100R J
R724	VE-30012510	SMD RES.	1/16W 100R J
R801	VE-30000718	CF RES.	1/4W 4.7K J
R803	VE-30012659	SMD RES.	1/16W 2.2K J
R805	VE-30000650	CF RES.	1/4W 33R J
R806	VE-30000982	MF RES.	1/4W 4.7K J
R807	VE-30001173	MO RES.	1W 0.47R J
R809	VE-30007784	MO RES.	5W 33K J (RADIAL)
△ R810	VE-30001257	MG RES.	1/2W 4.7M J
R811	VE-30000718	CF RES.	1/4W 4.7K J
R812	VE-30012641	SMD RES.	1/16W 10K J
R813	VE-30000466	CF RES.	1/4W 1K J
R814	VE-30000466	CF RES.	1/4W 1K J
R817	VE-30000880	MF RES.	1/4W 130K F
R818	VE-30012675	SMD RES.	1/16W 2K J
R819	VE-30000526	CF RES.	1/4W 1.5K J
R828	VE-30000530	CF RES.	1/2W 15K J
R829	VE-30000530	CF RES.	1/2W 15K J
R834	VE-30001159	MO RES.	1W 0.33R J
R836	VE-30012662	SMD RES.	1/16W 2.7K J
R839	VE-30000526	CF RES.	1/4W 1.5K J
R842	VE-30014128	SMD RES.	1/16W 33R J
R844	VE-30012641	SMD RES.	1/16W 10K J
R845	VE-30012509	SMD RES.	1/16W 100K J
R846	VE-30012692	SMD RES.	1/16W 4.7K J
R847	VE-30014128	SMD RES.	1/16W 33R J
R848	VE-30012641	SMD RES.	1/16W 10K J
R849	VE-30012510	SMD RES.	1/16W 100R J
R851	VE-30000718	CF RES.	1/4W 4.7K J
R852	VE-30000650	CF RES.	1/4W 33R J
R853	VE-30012642	SMD RES.	1/16W 120K J
R855	VE-30000459	CF RES.	1/4W 100R J
R856	VE-30012694	SMD RES.	1/16W 470K J

CAPACITOR

C141	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C142	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C143	VE-30012589	SMD CAP.	4.7NF 50V K
C144	VE-30012589	SMD CAP.	4.7NF 50V K
C145	VE-30012589	SMD CAP.	4.7NF 50V K
C146	VE-30012589	SMD CAP.	4.7NF 50V K
C147	VE-30012589	SMD CAP.	4.7NF 50V K
C148	VE-30012589	SMD CAP.	4.7NF 50V K
C149	VE-30012589	SMD CAP.	4.7NF 50V K
C150	VE-30012589	SMD CAP.	4.7NF 50V K
C155	VE-30012560	SMD CAP.	100PF 50V J
C157	VE-30012560	SMD CAP.	100PF 50V J
C159	VE-30000352	EL CAP.	100UF 16V M

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

CAPACITOR

C160	VE-30000345	EL CAP.	10UF 50V M
C161	VE-30000345	EL CAP.	10UF 50V M
C162	VE-30012573	SMD CAP.	47PF 50V J
C164	VE-30012692	SMD RES.	1/16W 4.7K J
C165	VE-30000413	EL CAP.	4.7UF 50V M
C201	VE-30000400	EL CAP.	47UF 50V M
C205	VE-30000345	EL CAP.	10UF 50V M
C206	VE-30012610	SMD CAP.	10NF 50V J
C207	VE-30012610	SMD CAP.	10NF 50V J
C230	VE-30016654	SMD CAP.	100NF 16V K R
C246	VE-30000295	CER CAP.	100NF 50V Z F
C303	VE-30000100	MKT CAP.	330NF 63V J
C305	VE-30012590	SMD CAP.	47NF 50V K
C310	VE-30000345	EL CAP.	10UF 50V M
C333	VE-30000083	MKT CAP.	150NF 63V J
C363	VE-30000083	MKT CAP.	150NF 63V J
C364	VE-30012590	SMD CAP.	47NF 50V K
C366	VE-30000407	EL CAP.	470UF 16V M
C368	VE-30012590	SMD CAP.	47NF 50V K
C404	VE-30000190	CER CAP.	100PF 50V J CH
C408	VE-30012586	SMD CAP.	22NF 50V K
C409	VE-30000345	EL CAP.	10UF 50V M
C410	VE-30000384	EL CAP.	2.2UF 50V M
C411	VE-30000345	EL CAP.	10UF 50V M
C412	VE-30016654	SMD CAP.	100NF 16V K R
C413	VE-30000362	EL CAP.	1UF 50V M
C414	VE-30012585	SMD CAP.	2.2NF 50V K R
C415	VE-30012581	SMD CAP.	1NF 50V K R
C416	VE-30000362	EL CAP.	1UF 50V M
C417	VE-30000362	EL CAP.	1UF 50V M
C418	VE-30016654	SMD CAP.	100NF 16V K R
C419	VE-30000384	EL CAP.	2.2UF 50V M
C420	VE-30000100	MKT CAP.	330NF 63V J
C422	VE-30000352	EL CAP.	100UF 16V M
C423	VE-30000352	EL CAP.	100UF 16V M
C424	VE-30000352	EL CAP.	100UF 16V M
C425	VE-30016654	SMD CAP.	100NF 16V K R
C427	VE-30016654	SMD CAP.	100NF 16V K R
C429	VE-30012589	SMD CAP.	4.7NF 50V K
C430	VE-30016654	SMD CAP.	100NF 16V K R
C431	VE-30000362	EL CAP.	1UF 50V M
C432	VE-30016654	SMD CAP.	100NF 16V K R
C433	VE-30000345	EL CAP.	10UF 50V M
C434	VE-30016654	SMD CAP.	100NF 16V K R
C435	VE-30016654	SMD CAP.	100NF 16V K R
C436	VE-30000384	EL CAP.	2.2UF 50V M
C437	VE-30016654	SMD CAP.	100NF 16V K R
C438	VE-30016654	SMD CAP.	100NF 16V K R
C439	VE-30016654	SMD CAP.	100NF 16V K R
C440	VE-30000295	CER CAP.	100NF 50V Z F
C441	VE-30012582	SMD CAP.	10NF 50V K R
C442	VE-30000362	EL CAP.	1UF 50V M
C443	VE-30000362	EL CAP.	1UF 50V M
C444	VE-30000384	EL CAP.	2.2UF 50V M
C446	VE-30000345	EL CAP.	10UF 50V M
C448	VE-30012586	SMD CAP.	22NF 50V K
C449	VE-30012560	SMD CAP.	100PF 50V J
C453	VE-30000352	EL CAP.	100UF 16V M
C455	VE-30000345	EL CAP.	10UF 50V M
C457	VE-30012560	SMD CAP.	100PF 50V J
C459	VE-30012560	SMD CAP.	100PF 50V J
C501	VE-30016654	SMD CAP.	100NF 16V K R
C502	VE-30000400	EL CAP.	47UF 50V M
C504	VE-30016654	SMD CAP.	100NF 16V K R
C505	VE-30012589	SMD CAP.	4.7NF 50V K
C507	VE-30000345	EL CAP.	10UF 50V M
C510	VE-30016654	SMD CAP.	100NF 16V K R
C511	VE-30012566	SMD CAP.	22PF 50V J
C513	VE-30000345	EL CAP.	10UF 50V M
C514	VE-30016654	SMD CAP.	100NF 16V K R
C515	VE-30012560	SMD CAP.	100PF 50V J
C517	VE-30016654	SMD CAP.	100NF 16V K R
C518	VE-30016654	SMD CAP.	100NF 16V K R
C519	VE-30012560	SMD CAP.	100PF 50V J
C520	VE-30012560	SMD CAP.	100PF 50V J
C521	VE-30012562	SMD CAP.	15PF 50V J
C522	VE-30012562	SMD CAP.	15PF 50V J
C523	VE-30012585	SMD CAP.	2.2NF 50V K R
C524	VE-30012566	SMD CAP.	22PF 50V J
C525	VE-30012566	SMD CAP.	22PF 50V J
C526	VE-30016654	SMD CAP.	100NF 16V K R
C527	VE-30000345	EL CAP.	10UF 50V M
C529	VE-30012589	SMD CAP.	4.7NF 50V K
C530	VE-30012589	SMD CAP.	4.7NF 50V K

[AV-28BT8EPS / AV-28BT8EPB / AV-28BT80EP]

Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C532	VE-30016654	SMD CAP.	100NF 16V K R
C536	VE-30000295	CER CAP.	100NF 50V Z F
C541	VE-30000362	EL CAP.	1UF 50V M
C542	VE-30000107	MKT CAP.	47NF 250V J
C543	VE-30000431	CER CAP.	100PF 1KV M
C544	VE-30000345	EL CAP.	10UF 50V M
C547	VE-30000345	EL CAP.	10UF 50V M
C565	VE-30016654	SMD CAP.	100NF 16V K R
C566	VE-30016654	SMD CAP.	100NF 16V K R
C567	VE-30000431	CER CAP.	100PF 1KV M
C602	VE-30017319	MKT CAP.	120NF 63V J
C604	VE-30000356	EL CAP.	100UF 63V M
C605	VE-30000360	EL CAP.	100UF 25V M
C607	VE-30012581	SMD CAP.	1NF 50V K R
C618	VE-30000159	MKT CAP.	4.7NF 1.6KV J
C621	VE-30000179	MKT CAP.	9.1NF 1600V X3.5
C622	VE-30000121	KP CAP.	27NF 630V J
C625	VE-30000156	MKT CAP.	430NF 250V J
C627	VE-30000167	MKT CAP.	560NF 250V J
C629	VE-30000177	MKT CAP.	820NF 250V J
C632	VE-30000100	MKT CAP.	330NF 63V J
C635	VE-30000385	EL CAP.	2.2UF 250V M
C636	VE-30000387	EL CAP.	33UF 50V M
C640	VE-30000100	MKT CAP.	330NF 63V J
C641	VE-30000090	MKT CAP.	22NF 100V J
C642	VE-30000407	EL CAP.	470UF 16V M
C644	VE-30000409	EL CAP.	470UF 25V M
C645	VE-30000090	MKT CAP.	22NF 100V J
C646	VE-30000100	MKT CAP.	330NF 63V J
C647	VE-30007748	EL CAP.	1000UF 35V M
C648	VE-30000394	EL CAP.	3.3UF 160V M
C649	VE-30000295	CER CAP.	100NF 50V Z F
C652	VE-30000330	CER CAP.	4.7NF 50V K B
C653	VE-30000107	MKT CAP.	47NF 250V J
C655	VE-30000415	EL CAP.	4.7UF 250V M
C700	VE-30012565	SMD CAP.	1.8PF 50V J CH
C701	VE-30012565	SMD CAP.	1.8PF 50V J CH
C702	VE-30012576	SMD CAP.	56PF 50V J CH
C703	VE-30012576	SMD CAP.	56PF 50V J CH
C704	VE-30012576	SMD CAP.	56PF 50V J CH
C705	VE-30000345	EL CAP.	10UF 50V M
C706	VE-30000345	EL CAP.	10UF 50V M
C708	VE-30016654	SMD CAP.	100NF 16V K R
C712	VE-30000345	EL CAP.	10UF 50V M
C713	VE-30016654	SMD CAP.	100NF 16V K R
C714	VE-30000100	MKT CAP.	330NF 63V J
C716	VE-30000100	MKT CAP.	330NF 63V J
C717	VE-30000100	MKT CAP.	330NF 63V J
C718	VE-30000100	MKT CAP.	330NF 63V J
C719	VE-30016654	SMD CAP.	100NF 16V K R
C720	VE-30000345	EL CAP.	10UF 50V M
C721	VE-30000100	MKT CAP.	330NF 63V J
C723	VE-30000100	MKT CAP.	330NF 63V J
C724	VE-30000345	EL CAP.	10UF 50V M
C729	VE-30016654	SMD CAP.	100NF 16V K R
C730	VE-30000393	EL CAP.	3.3UF 50V M
C733	VE-30000345	EL CAP.	10UF 50V M
C734	VE-30000345	EL CAP.	10UF 50V M
C735	VE-30016654	SMD CAP.	100NF 16V K R
C736	VE-30000345	EL CAP.	10UF 50V M
C737	VE-30000384	EL CAP.	2.2UF 50V M
C738	VE-30000384	EL CAP.	2.2UF 50V M
C739	VE-30000384	EL CAP.	2.2UF 50V M
C740	VE-30000384	EL CAP.	2.2UF 50V M
C741	VE-30012589	SMD CAP.	4.7NF 50V K
C742	VE-30012589	SMD CAP.	4.7NF 50V K
C745	VE-30016654	SMD CAP.	100NF 16V K R
C801	VE-30000094	MKT CAP.	220NF 275V M AC
C802	VE-30000094	MKT CAP.	220NF 275V M AC
C803	VE-30000433	CER CAP.	1NF 1KV M B
C804	VE-30000433	CER CAP.	1NF 1KV M B
C808	VE-30012590	SMD CAP.	47NF 50V K
C809	VE-30000420	EL CAP.	150UF 400V M
C810	VE-30000387	EL CAP.	33UF 50V M
C811	VE-30000161	MKT CAP.	47NF 630V J
C812	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
C816	VE-30000440	CER CAP.	2.2NF 4KV M
C817	VE-30000198	CER CAP.	120PF 500V J SL
C818	VE-30012590	SMD CAP.	47NF 50V K
C819	VE-30012590	SMD CAP.	47NF 50V K
C822	VE-30007308	CER CAP.	220PF 1KV K (PULSE)
C826	VE-30000406	EL CAP.	470UF 250V M (HR)
C827	VE-30000411	EL CAP.	4700UF 16V M
C828	VE-30012590	SMD CAP.	47NF 50V K

Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C829	VE-30000407	EL CAP.	470UF 16V M
C830	VE-30000383	EL CAP.	220UF 25V M
C832	VE-30012590	SMD CAP.	47NF 50V K
C833	VE-30000407	EL CAP.	470UF 16V M
C834	VE-30012590	SMD CAP.	47NF 50V K
C835	VE-30012590	SMD CAP.	47NF 50V K
C838	VE-30000407	EL CAP.	470UF 16V M
C839	VE-30000407	EL CAP.	470UF 16V M
C840	VE-30000407	EL CAP.	470UF 16V M
C848	VE-30000407	EL CAP.	470UF 16V M
C850	VE-30000383	EL CAP.	220UF 25V M
C851	VE-30012590	SMD CAP.	47NF 50V K
C852	VE-30000440	CER CAP.	2.2NF 4KV M
C857	VE-30000106	MKT CAP.	47NF 100V J
C858	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
C859	VE-30009208	CER CAP.	470PF 1KV K (PULSE)
C860	VE-30000296	CER CAP.	100NF 100V Z F
C872	VE-30007708	CER CAP.	1NF 1KV K (PULSE)

TRANSF

TR600	VE-30002090	LINE DRIVER
TR601	VE-30017522	FBT TRF
TR802	VE-30018785	SMPS TRF

COIL

L101	VE-30001971	FERRITE BEAT
L102	VE-30001971	FERRITE BEAT
L106	VE-30001971	FERRITE BEAT
L108	VE-30001971	FERRITE BEAT
L109	VE-30001971	FERRITE BEAT
L110	VE-30001971	FERRITE BEAT
L111	VE-30001971	FERRITE BEAT
L112	VE-30001971	FERRITE BEAT
L113	VE-30001971	FERRITE BEAT
L114	VE-30001971	FERRITE BEAT
L115	VE-30001971	FERRITE BEAT
L116	VE-30001971	FERRITE BEAT
L117	VE-30001971	FERRITE BEAT
L201	VE-30001979	FIXED COIL
L210	VE-30001971	FERRITE BEAT
L215	VE-30001971	FERRITE BEAT
L401	VE-30001971	FERRITE BEAT
L402	VE-30001992	FIXED COIL
L403	VE-30001971	FERRITE BEAT
L404	VE-30001990	FIXED COIL
L405	VE-30014048	ADJ. COIL
L406	VE-30001971	FERRITE BEAT
L407	VE-30001992	FIXED COIL
L408	VE-30001992	FIXED COIL
L501	VE-30001971	FERRITE BEAT
L502	VE-30001971	FERRITE BEAT
L503	VE-30001971	FERRITE BEAT
L504	VE-30001971	FERRITE BEAT
L600	VE-30002031	FIXED COIL
L602	VE-30002156	LINEARITY COIL
L603	VE-30002026	FIXED COIL
L700	VE-30001971	FERRITE BEAT
L701	VE-30001971	FERRITE BEAT
L702	VE-30001992	FIXED COIL
L703	VE-30001971	FERRITE BEAT
L704	VE-30001971	FERRITE BEAT
L801	VE-30002011	CHOKE COIL
L803	VE-30001992	FIXED COIL

DIODE

D105	VE-30007760	ZENER DIODE
D106	VE-30007760	ZENER DIODE
D107	VE-30007760	ZENER DIODE
D303	VE-30001329	DIODE
D402	VE-30012411	DIODE
D405	VE-30007763	ZENER DIODE
D407	VE-30001284	DIODE
D408	VE-30001285	DIODE
D409	VE-30001284	DIODE
D413	VE-30018526	ZENER DIODE
D501	VE-30001285	DIODE
D505	VE-30001285	DIODE
D506	VE-30001284	DIODE

[AV-28BT8EPS / AV-28BT8EPB / AV-28BT80EP]

Symbol No.	Part No.	Part Name	Description
DIODE			
D512	VE-30001285	DIODE	
D513	VE-30001369	ZENER DIODE	
D533	VE-30001377	ZENER DIODE	
D601	VE-30001329	DIODE	
D603	VE-30001285	DIODE	
D605	VE-30001320	DIODE	
D606	VE-30001323	DIODE	
D609	VE-30001318	DIODE	
D610	VE-30001318	DIODE	
D613	VE-30001318	DIODE	
D614	VE-30001285	DIODE	
D616	VE-30003696	DIODE	
D617	VE-30001318	DIODE	
D651	VE-30001285	DIODE	
D653	VE-30001285	DIODE	
D656	VE-30007763	ZENER DIODE	
D657	VE-30007763	ZENER DIODE	
D658	VE-30007763	ZENER DIODE	
D659	VE-30001350	ZENER DIODE	
D660	VE-30001347	ZENER DIODE	
D661	VE-30001350	ZENER DIODE	
D700	VE-30001285	DIODE	
D701	VE-30001369	ZENER DIODE	
D800	VE-30001318	DIODE	
D801	VE-30001372	ZENER DIODE	
D802	VE-30001318	DIODE	
D803	VE-30001315	DIODE	
D804	VE-30001318	DIODE	
D805	VE-30001315	DIODE	
D806	VE-30001315	DIODE	
D808	VE-20092405	CN. ASY	
D809	VE-30001329	DIODE	
D810	VE-30009366	DIODE	
D811	VE-30009366	DIODE	
D812	VE-30001285	DIODE	
D889	VE-30001384	TR	
D891	VE-30007758	BRIDGE DIODE	
D892	VE-30001318	DIODE	
D893	VE-30001318	DIODE	
D894	VE-30001285	DIODE	
D897	VE-30001329	DIODE	

TRANSISTOR

Q104	VE-30001457	TR	
Q106	VE-30001457	TR	
Q141	VE-30001457	TR	
Q142	VE-30001457	TR	
Q307	VE-30001457	TR	
Q316	VE-30001458	TR	
Q402	VE-30001457	TR	
Q403	VE-30001457	TR	
Q404	VE-30001457	TR	
Q503	VE-30001457	TR	
Q504	VE-30001458	TR	
Q600	VE-30001435	TR	
Q601	VE-30001441	TR	
Q602	VE-30001429	TR	
Q603	VE-30001458	TR	
Q604	VE-30001457	TR	
Q605	VE-30001458	TR	
Q700	VE-30001458	TR	
Q801	VE-30001386	TR	
Q802	VE-30001457	TR	
Q804	VE-30001454	TR	

IC

IC301	VE-30016113	IC	
IC408	VE-30014510	IC	
IC500	VE-20099534	IC	(SERVICE)
IC501	VE-20093395	IC	(MICOM)
IC601	VE-30013985	IC	
IC700	VE-30013658	IC	
IC800	VE-30011968	IC	
IC801	VE-30015087	IC	
IC802	VE-30001622	IC	
IC808	VE-30001500	IC	
IC804	VE-30001622	IC	
IC818	VE-30001506	IC	

Symbol No.	Part No.	Part Name	Description
OTHERS			
TR801	VE-30002104	LINE FILTER	
F801	VE-30001731	FUSE	2.5A
TH800	VE-30001270	PTC	9 OHM
TU201	VE-30009637	TUNER	
VR800	VE-30001064	RES ADJ	
X401	VE-30001749	XTAL	
X402	VE-30015592	XTAL	
X501	VE-30002851	XTAL	
X700	VE-30001756	XTAL	
Z401	VE-30012545	SAW FILTER	
Z402	VE-30014261	SAW FILTER	
Z404	VE-30001724	SER FILTER	

CRT SOCKET P.W. BOARD ASS'Y (VE-20094670)

Refer to PARTS LIST in page 30 for this P.W. board

**FRONT CONTROL P.W. BOARD ASS'Y
(VE-20082481)**

Refer to PARTS LIST in page 30 for this P.W. board

**FRONT AV & HEADPHONE P.W. BOARD ASS'Y
(VE-20083646)**

Refer to PARTS LIST in page 30 for this P.W. board

PRINTED WIRING BOARD PARTS LIST

[AV-28BT8EES / AV-28BT8EEB]

MAIN P.W. BOARD ASS'Y (VE-20101622)

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R102	VE-30012657	SMD RES.	1/10W 1K J
R103	VE-30012657	SMD RES.	1/10W 1K J
R106	VE-30012713	SMD RES.	1/10W 75R J
R107	VE-30012649	SMD RES.	1/10W 150R J
R109	VE-30012713	SMD RES.	1/10W 75R J
R110	VE-30012713	SMD RES.	1/10W 75R J
R111	VE-30012649	SMD RES.	1/10W 150R J
R113	VE-30012713	SMD RES.	1/10W 75R J
R114	VE-30012713	SMD RES.	1/10W 75R J
R115	VE-30012713	SMD RES.	1/10W 75R J
R117	VE-30000792	CF RES.	1/4W 75R J
R118	VE-30012713	SMD RES.	1/10W 75R J
R121	VE-30012649	SMD RES.	1/10W 150R J
R122	VE-30000792	CF RES.	1/4W 75R J
R123	VE-30000792	CF RES.	1/4W 75R J
R124	VE-30012649	SMD RES.	1/10W 150R J
R126	VE-30012657	SMD RES.	1/10W 1K J
R129	VE-30012713	SMD RES.	1/10W 75R J
R135	VE-30012657	SMD RES.	1/10W 1K J
R137	VE-30000466	CF RES.	1/4W 1K J
R138	VE-30012657	SMD RES.	1/10W 1K J
R139	VE-30012713	SMD RES.	1/10W 75R J
R141	VE-30012657	SMD RES.	1/10W 1K J
R145	VE-30012713	SMD RES.	1/10W 75R J
R149	VE-30012703	SMD RES.	1/10W 56K J
R151	VE-30012696	SMD RES.	1/10W 47K J
R152	VE-30000752	CF RES.	1/4W 56K J
R153	VE-30012657	SMD RES.	1/10W 1K J
R154	VE-30000723	CF RES.	1/4W 47K J
R155	VE-30012649	SMD RES.	1/10W 150R J
R169	VE-30012703	SMD RES.	1/10W 56K J
R171	VE-30012713	SMD RES.	1/10W 75R J
R172	VE-30012692	SMD RES.	1/10W 4.7K J
R174	VE-30012713	SMD RES.	1/10W 75R J
R175	VE-30012713	SMD RES.	1/10W 75R J
R176	VE-30012703	SMD RES.	1/10W 56K J
R201	VE-30012674	SMD RES.	1/10W 27K J
R202	VE-30012692	SMD RES.	1/10W 4.7K J
R204	VE-30000459	CF RES.	1/4W 100R J
R206	VE-30000459	CF RES.	1/4W 100R J
R319	VE-30014076	SMD RES.	1/10W 4.7K J
R320	VE-30014076	SMD RES.	1/10W 4.7K J
R324	VE-30012667	SMD RES.	1/10W 220K J
R328	VE-30012649	SMD RES.	1/10W 150R J
R329	VE-30012692	SMD RES.	1/10W 4.7K J
R332	VE-30012641	SMD RES.	1/10W 10K J
R333	VE-30012702	SMD RES.	1/10W 560R J
R338	VE-30012641	SMD RES.	1/10W 10K J
R340	VE-30012644	SMD RES.	1/10W 12K J
R341	VE-30012702	SMD RES.	1/10W 560R J
R343	VE-30012659	SMD RES.	1/10W 2.2K J
R370	VE-30012669	SMD RES.	1/10W 22K J
R371	VE-30012669	SMD RES.	1/10W 22K J
R391	VE-30012696	SMD RES.	1/10W 47K J
R417	VE-30012510	SMD RES.	1/10W 100R J
R418	VE-30012510	SMD RES.	1/10W 100R J
R419	VE-30012649	SMD RES.	1/10W 150R J
R420	VE-30000466	CF RES.	1/4W 1K J
R421	VE-30012650	SMD RES.	1/10W 15K J
R422	VE-30012659	SMD RES.	1/10W 2.2K J
R423	VE-30012712	SMD RES.	1/10W 8.2K J
R425	VE-30012510	SMD RES.	1/10W 100R J
R426	VE-30012659	SMD RES.	1/10W 2.2K J
R427	VE-30012674	SMD RES.	1/10W 27K J
R428	VE-30012510	SMD RES.	1/10W 100R J
R430	VE-30012702	SMD RES.	1/10W 560R J
R431	VE-30012674	SMD RES.	1/10W 27K J
R432	VE-30012707	SMD RES.	1/10W 680R J
R433	VE-30012683	SMD RES.	1/10W 330K J
R437	VE-30000466	CF RES.	1/4W 1K J
R438	VE-30000466	CF RES.	1/4W 1K J
R439	VE-30012657	SMD RES.	1/10W 1K J
R440	VE-30012714	SMD RES.	1/10W 820R J
R441	VE-30012674	SMD RES.	1/10W 27K J
R442	VE-30000466	CF RES.	1/4W 1K J
R446	VE-30012714	SMD RES.	1/10W 820R J
R447	VE-30012714	SMD RES.	1/10W 820R J
R448	VE-30012683	SMD RES.	1/10W 330K J
R449	VE-30012659	SMD RES.	1/10W 2.2K J

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R450	VE-30012702	SMD RES.	1/10W 560R J
R458	VE-30012510	SMD RES.	1/10W 100R J
R459	VE-30012668	SMD RES.	1/10W 220R J
R460	VE-30012668	SMD RES.	1/10W 220R J
R461	VE-30012668	SMD RES.	1/10W 220R J
R462	VE-30012510	SMD RES.	1/10W 100R J
R467	VE-30000670	CF RES.	1/4W 330K J
R468	VE-30000670	CF RES.	1/4W 330K J
R469	VE-30000628	CF RES.	1/4W 2.7K J
R471	VE-30014022	SMD RES.	1/10W 47R J
R472	VE-30012662	SMD RES.	1/10W 2.7K J
R474	VE-30012662	SMD RES.	1/10W 2.7K J
R481	VE-30000466	CF RES.	1/4W 1K J
R482	VE-30012657	SMD RES.	1/10W 1K J
R483	VE-30012657	SMD RES.	1/10W 1K J
R485	VE-30012657	SMD RES.	1/10W 1K J
R486	VE-30012657	SMD RES.	1/10W 1K J
R487	VE-30012657	SMD RES.	1/10W 1K J
R507	VE-30000466	CF RES.	1/4W 1K J
R508	VE-30012510	SMD RES.	1/10W 100R J
R509	VE-30012641	SMD RES.	1/10W 10K J
R510	VE-30012702	SMD RES.	1/10W 560R J
R511	VE-30012657	SMD RES.	1/10W 1K J
R512	VE-30000495	CF RES.	1/4W 1.2K J
R513	VE-30000459	CF RES.	1/4W 100R J
R514	VE-30000459	CF RES.	1/4W 100R J
R515	VE-30012659	SMD RES.	1/10W 2.2K J
R516	VE-30012659	SMD RES.	1/10W 2.2K J
R517	VE-30012692	SMD RES.	1/10W 4.7K J
R518	VE-30000471	CF RES.	1/4W 10K J
R519	VE-30012698	SMD RES.	1/10W 5.6K J
R525	VE-30012649	SMD RES.	1/10W 150R J
R526	VE-30012641	SMD RES.	1/10W 10K J
R527	VE-30012692	SMD RES.	1/10W 4.7K J
R528	VE-30012698	SMD RES.	1/10W 5.6K J
R529	VE-30012698	SMD RES.	1/10W 5.6K J
R530	VE-30012698	SMD RES.	1/10W 5.6K J
R532	VE-30012659	SMD RES.	1/10W 2.2K J
R533	VE-30012644	SMD RES.	1/10W 12K J
R534	VE-30000628	CF RES.	1/4W 2.7K J
R537	VE-30012641	SMD RES.	1/10W 10K J
R538	VE-30012698	SMD RES.	1/10W 5.6K J
R539	VE-30012659	SMD RES.	1/10W 2.2K J
R540	VE-30012644	SMD RES.	1/10W 12K J
R545	VE-30012644	SMD RES.	1/10W 12K J
R548	VE-30012641	SMD RES.	1/10W 10K J
R554	VE-30012641	SMD RES.	1/10W 10K J
R555	VE-30012659	SMD RES.	1/10W 2.2K J
R556	VE-30012657	SMD RES.	1/10W 1K J
R560	VE-30012674	SMD RES.	1/10W 27K J
R561	VE-30012692	SMD RES.	1/10W 4.7K J
R568	VE-30000594	CF RES.	1/4W 22K J
R572	VE-30012659	SMD RES.	1/10W 2.2K J
R573	VE-30012641	SMD RES.	1/10W 10K J
R574	VE-30012657	SMD RES.	1/10W 1K J
R603	VE-30000459	CF RES.	1/4W 100R J
R604	VE-30012510	SMD RES.	1/10W 100R J
R606	VE-30000471	CF RES.	1/4W 10K J
R607	VE-30000554	CF RES.	1/4W 180R J
R608	VE-30000859	MF RES.	1/2W 1R F
R609	VE-30000711	CF RES.	1/2W 470R J
R610	VE-30000599	CF RES.	1/4W 220K J
R611	VE-30012708	SMD RES.	1/10W 68K J
R614	VE-30012509	SMD RES.	1/10W 100K J
R616	VE-30012669	SMD RES.	1/10W 22K J
R617	VE-30000572	CF RES.	1/4W 2K J
R630	VE-30012702	SMD RES.	1/10W 560R J
R634	VE-30000633	CF RES.	1/4W 27K J
R639	VE-30000471	CF RES.	1/4W 10K J
R640	VE-30000628	CF RES.	1/4W 2.7K J
R646	VE-30000531	CF RES.	1/4W 15K J
R647	VE-30000466	CF RES.	1/4W 1K J
△ R648	VE-30001246	FUSE RES.	1W 0.47R J
R650	VE-30012702	SMD RES.	1/10W 560R J
R651	VE-30012668	SMD RES.	1/10W 220R J
△ R656	VE-30001230	FUSE RES.	1/2W 27R J
△ R657	VE-30001228	FUSE RES.	1/2W 2.2R J
R662	VE-30012674	SMD RES.	1/10W 27K J
R666	VE-30000815	CF RES.	1/4W 8.2K J

[AV-28BT8EES / AV-28BT8EEB]

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

RESISTOR

R668	VE-30000790	CF RES.	1/4W 6.8R J
R669	VE-30012510	SMD RES.	1/16W 100R J
R670	VE-30012510	SMD RES.	1/16W 100R J
R674	VE-30012662	SMD RES.	1/16W 2.7K J
△ R675	VE-30001244	FUSE RES.	1/2W 0.47R J
R677	VE-30001124	MO RES.	3W 220R J
R678	VE-30014022	SMD RES.	1/16W 47R J
R680	VE-30000477	CF RES.	1/4W 100K J
R681	VE-30012509	SMD RES.	1/16W 100K J
R682	VE-30008856	MO RES.	2W 270R J
R683	VE-30017083	WM RES.	5W 2.2K J RAD.
R689	VE-30000718	CF RES.	1/4W 4.7K J
R690	VE-30000466	CF RES.	1/4W 1K J
R691	VE-30012696	SMD RES.	1/16W 47K J
R692	VE-30012509	SMD RES.	1/16W 100K J
R693	VE-30012708	SMD RES.	1/16W 68K J
R694	VE-30000689	CF RES.	1/4W 3.9K J
R695	VE-30000471	CF RES.	1/4W 10K J
R696-Y	VE-30001350	ZENER DIODE	12V
R697	VE-30000712	CF RES.	1/4W 470R J
R698	VE-30012657	SMD RES.	1/16W 1K J
R699	VE-30012685	SMD RES.	1/16W 33K J
R700	VE-30012649	SMD RES.	1/16W 150R J
R701	VE-30000459	CF RES.	1/4W 100R J
R703	VE-30000459	CF RES.	1/4W 100R J
R705	VE-30000459	CF RES.	1/4W 100R J
R715	VE-30012702	SMD RES.	1/16W 560R J
R717	VE-30012702	SMD RES.	1/16W 560R J
R719	VE-30012657	SMD RES.	1/16W 1K J
R721	VE-30012510	SMD RES.	1/16W 100R J
R722	VE-30012510	SMD RES.	1/16W 100R J
R723	VE-30012510	SMD RES.	1/16W 100R J
R724	VE-30012510	SMD RES.	1/16W 100R J
R801	VE-30000718	CF RES.	1/4W 4.7K J
R803	VE-30012659	SMD RES.	1/16W 2.2K J
R805	VE-30000650	CF RES.	1/4W 33R J
R806	VE-30000982	MF RES.	1/4W 4.7K J
R807	VE-30001173	MO RES.	1W 0.47R J
R809	VE-30007784	MO RES.	5W 33K J (RADIAL)
△ R810	VE-30001257	MG RES.	1/2W 4.7M J
R811	VE-30000718	CF RES.	1/4W 4.7K J
R812	VE-30012641	SMD RES.	1/16W 10K J
R813	VE-30000466	CF RES.	1/4W 1K J
R814	VE-30000466	CF RES.	1/4W 1K J
R817	VE-30000880	MF RES.	1/4W 130K F
R818	VE-30012675	SMD RES.	1/16W 2K J
R819	VE-30000526	CF RES.	1/4W 1.5K J
R828	VE-30000530	CF RES.	1/2W 15K J
R829	VE-30000530	CF RES.	1/2W 15K J
R834	VE-30001159	MO RES.	1W 0.33R J
R836	VE-30012662	SMD RES.	1/16W 2.7K J
R839	VE-30000526	CF RES.	1/4W 1.5K J
R842	VE-30014128	SMD RES.	1/16W 33R J
R844	VE-30012641	SMD RES.	1/16W 10K J
R845	VE-30012509	SMD RES.	1/16W 100K J
R846	VE-30012692	SMD RES.	1/16W 4.7K J
R847	VE-30014128	SMD RES.	1/16W 33R J
R848	VE-30012641	SMD RES.	1/16W 10K J
R849	VE-30012510	SMD RES.	1/16W 100R J
R851	VE-30000718	CF RES.	1/4W 4.7K J
R852	VE-30000650	CF RES.	1/4W 33R J
R853	VE-30012642	SMD RES.	1/16W 120K J
R855	VE-30000459	CF RES.	1/4W 100R J
R856	VE-30012694	SMD RES.	1/16W 470K J

CAPACITOR

C141	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C142	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C143	VE-30012589	SMD CAP.	4.7NF 50V K
C144	VE-30012589	SMD CAP.	4.7NF 50V K
C145	VE-30012589	SMD CAP.	4.7NF 50V K
C146	VE-30012589	SMD CAP.	4.7NF 50V K
C147	VE-30012589	SMD CAP.	4.7NF 50V K
C148	VE-30012589	SMD CAP.	4.7NF 50V K
C149	VE-30012589	SMD CAP.	4.7NF 50V K
C150	VE-30012589	SMD CAP.	4.7NF 50V K
C155	VE-30012560	SMD CAP.	100PF 50V J
C157	VE-30012560	SMD CAP.	100PF 50V J
C159	VE-30000352	EL CAP.	100UF 16V M
C160	VE-30000345	EL CAP.	10UF 50V M
C161	VE-30000345	EL CAP.	10UF 50V M

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

CAPACITOR

C162	VE-30012573	SMD CAP.	47PF 50V J
C164	VE-30012692	SMD RES.	1/16W 4.7K J
C165	VE-30000413	EL CAP.	4.7UF 50V M
C201	VE-30000400	EL CAP.	47UF 50V M
C205	VE-30000345	EL CAP.	10UF 50V M
C206	VE-30012610	SMD CAP.	10NF 50V J
C207	VE-30012610	SMD CAP.	10NF 50V J
C230	VE-30016654	SMD CAP.	100NF 16V K R
C246	VE-30000295	CER CAP.	100NF 50V Z F
C303	VE-30000100	MKT CAP.	330NF 63V J
C305	VE-30012590	SMD CAP.	47NF 50V K
C310	VE-30000345	EL CAP.	10UF 50V M
C333	VE-30000083	MKT CAP.	150NF 63V J
C363	VE-30000083	MKT CAP.	150NF 63V J
C364	VE-30012590	SMD CAP.	47NF 50V K
C366	VE-30000407	EL CAP.	470UF 16V M
C368	VE-30012590	SMD CAP.	47NF 50V K
C404	VE-30000190	CER CAP.	100PF 50V J CH
C408	VE-30012586	SMD CAP.	22NF 50V K
C409	VE-30000345	EL CAP.	10UF 50V M
C410	VE-30000384	EL CAP.	2.2UF 50V M
C411	VE-30000345	EL CAP.	10UF 50V M
C412	VE-30016654	SMD CAP.	100NF 16V K R
C413	VE-30000362	EL CAP.	1UF 50V M
C414	VE-30012585	SMD CAP.	2.2NF 50V K R
C415	VE-30012581	SMD CAP.	1NF 50V K R
C416	VE-30000362	EL CAP.	1UF 50V M
C417	VE-30000362	EL CAP.	1UF 50V M
C418	VE-30016654	SMD CAP.	100NF 16V K R
C419	VE-30000384	EL CAP.	2.2UF 50V M
C420	VE-30000100	MKT CAP.	330NF 63V J
C422	VE-30000352	EL CAP.	100UF 16V M
C423	VE-30000352	EL CAP.	100UF 16V M
C424	VE-30000352	EL CAP.	100UF 16V M
C425	VE-30016654	SMD CAP.	100NF 16V K R
C427	VE-30016654	SMD CAP.	100NF 16V K R
C429	VE-30012589	SMD CAP.	4.7NF 50V K
C430	VE-30016654	SMD CAP.	100NF 16V K R
C431	VE-30000362	EL CAP.	1UF 50V M
C432	VE-30016654	SMD CAP.	100NF 16V K R
C433	VE-30000345	EL CAP.	10UF 50V M
C434	VE-30016654	SMD CAP.	100NF 16V K R
C435	VE-30016654	SMD CAP.	100NF 16V K R
C436	VE-30000384	EL CAP.	2.2UF 50V M
C437	VE-30016654	SMD CAP.	100NF 16V K R
C438	VE-30016654	SMD CAP.	100NF 16V K R
C439	VE-30016654	SMD CAP.	100NF 16V K R
C440	VE-30000295	CER CAP.	100NF 50V Z F
C441	VE-30012582	SMD CAP.	10NF 50V K R
C442	VE-30000362	EL CAP.	1UF 50V M
C443	VE-30000362	EL CAP.	1UF 50V M
C444	VE-30000384	EL CAP.	2.2UF 50V M
C448	VE-30012586	SMD CAP.	22NF 50V K
C449	VE-30012560	SMD CAP.	100PF 50V J
C453	VE-30000352	EL CAP.	100UF 16V M
C455	VE-30000345	EL CAP.	10UF 50V M
C459	VE-30012560	SMD CAP.	100PF 50V J
C501	VE-30016654	SMD CAP.	100NF 16V K R
C502	VE-30000400	EL CAP.	47UF 50V M
C504	VE-30016654	SMD CAP.	100NF 16V K R
C505	VE-30012589	SMD CAP.	4.7NF 50V K
C507	VE-30000345	EL CAP.	10UF 50V M
C510	VE-30016654	SMD CAP.	100NF 16V K R
C511	VE-30012566	SMD CAP.	22PF 50V J
C513	VE-30000345	EL CAP.	10UF 50V M
C514	VE-30016654	SMD CAP.	100NF 16V K R
C515	VE-30012560	SMD CAP.	100PF 50V J
C517	VE-30016654	SMD CAP.	100NF 16V K R
C518	VE-30016654	SMD CAP.	100NF 16V K R
C519	VE-30012560	SMD CAP.	100PF 50V J
C520	VE-30012560	SMD CAP.	100PF 50V J
C521	VE-30012562	SMD CAP.	15PF 50V J
C522	VE-30012562	SMD CAP.	15PF 50V J
C523	VE-30012585	SMD CAP.	2.2NF 50V K R
C524	VE-30012566	SMD CAP.	22PF 50V J
C525	VE-30012566	SMD CAP.	22PF 50V J
C526	VE-30016654	SMD CAP.	100NF 16V K R
C527	VE-30000345	EL CAP.	10UF 50V M
C529	VE-30012589	SMD CAP.	4.7NF 50V K
C530	VE-30012589	SMD CAP.	4.7NF 50V K
C532	VE-30016654	SMD CAP.	100NF 16V K R
C536	VE-30000295	CER CAP.	100NF 50V Z F
C541	VE-30000362	EL CAP.	1UF 50V M

[AV-28BT8EES / AV-28BT8EEB]

Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C542	VE-30000107	MKT CAP.	47NF 250V J
C543	VE-30000431	CER CAP.	100PF 1KV M
C544	VE-30000345	EL CAP.	10UF 50V M
C547	VE-30000345	EL CAP.	10UF 50V M
C565	VE-30016654	SMD CAP.	100NF 16V K R
C566	VE-30016654	SMD CAP.	100NF 16V K R
C567	VE-30000431	CER CAP.	100PF 1KV M
C602	VE-30017319	MKT CAP.	120NF 63V J
C604	VE-30000356	EL CAP.	100UF 63V M
C605	VE-30000360	EL CAP.	100UF 25V M
C607	VE-30012581	SMD CAP.	1NF 50V K R
△ C618	VE-30000159	MKT CAP.	4.7NF 1.6KV J
△ C621	VE-30000179	MKT CAP.	9.1NF 1600V X.5
C622	VE-30000121	KP CAP.	27NF 630V J
△ C625	VE-30000156	MKT CAP.	430NF 250V J
C627	VE-30000167	MKT CAP.	560NF 250V J
C629	VE-30000177	MKT CAP.	820NF 250V J
C632	VE-30000100	MKT CAP.	330NF 63V J
C635	VE-30000385	EL CAP.	2.2UF 250V M
C636	VE-30000387	EL CAP.	33UF 50V M
C640	VE-30000100	MKT CAP.	330NF 63V J
C641	VE-30000090	MKT CAP.	22NF 100V J
C642	VE-30000407	EL CAP.	470UF 16V M
C644	VE-30000409	EL CAP.	470UF 25V M
C645	VE-30000090	MKT CAP.	22NF 100V J
C646	VE-30000100	MKT CAP.	330NF 63V J
C647	VE-30007748	EL CAP.	1000UF 35V M
C648	VE-30000394	EL CAP.	3.3UF 160V M
C649	VE-30000295	CER CAP.	100NF 50V Z F
C652	VE-30000330	CER CAP.	4.7NF 50V K B
C653	VE-30000107	MKT CAP.	47NF 250V J
C655	VE-30000415	EL CAP.	4.7UF 250V M
C700	VE-30012565	SMD CAP.	1.8PF 50V J CH
C701	VE-30012565	SMD CAP.	1.8PF 50V J CH
C702	VE-30012576	SMD CAP.	56PF 50V J CH
C703	VE-30012576	SMD CAP.	56PF 50V J CH
C704	VE-30012576	SMD CAP.	56PF 50V J CH
C705	VE-30000345	EL CAP.	10UF 50V M
C706	VE-30000345	EL CAP.	10UF 50V M
C708	VE-30016654	SMD CAP.	100NF 16V K R
C712	VE-30000345	EL CAP.	10UF 50V M
C713	VE-30016654	SMD CAP.	100NF 16V K R
C714	VE-30000100	MKT CAP.	330NF 63V J
C716	VE-30000100	MKT CAP.	330NF 63V J
C717	VE-30000100	MKT CAP.	330NF 63V J
C718	VE-30000100	MKT CAP.	330NF 63V J
C719	VE-30016654	SMD CAP.	100NF 16V K R
C720	VE-30000345	EL CAP.	10UF 50V M
C721	VE-30000100	MKT CAP.	330NF 63V J
C723	VE-30000100	MKT CAP.	330NF 63V J
C724	VE-30000345	EL CAP.	10UF 50V M
C729	VE-30016654	SMD CAP.	100NF 16V K R
C730	VE-30000393	EL CAP.	3.3UF 50V M
C733	VE-30000345	EL CAP.	10UF 50V M
C734	VE-30000345	EL CAP.	10UF 50V M
C735	VE-30016654	SMD CAP.	100NF 16V K R
C736	VE-30000345	EL CAP.	10UF 50V M
C737	VE-30000384	EL CAP.	2.2UF 50V M
C738	VE-30000384	EL CAP.	2.2UF 50V M
C739	VE-30000384	EL CAP.	2.2UF 50V M
C740	VE-30000384	EL CAP.	2.2UF 50V M
C741	VE-30012589	SMD CAP.	4.7NF 50V K
C742	VE-30012589	SMD CAP.	4.7NF 50V K
C745	VE-30016654	SMD CAP.	100NF 16V K R
△ C801	VE-30000094	MKT CAP.	220NF 275V M AC
△ C802	VE-30000094	MKT CAP.	220NF 275V M AC
△ C803	VE-30000433	CER CAP.	1NF 1KV M B
△ C804	VE-30000433	CER CAP.	1NF 1KV M B
C808	VE-30012590	SMD CAP.	47NF 50V K
C809	VE-30000420	EL CAP.	150UF 400V M
C810	VE-30000387	EL CAP.	33UF 50V M
C811	VE-30000161	MKT CAP.	47NF 630V J
△ C812	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
C816	VE-30000440	CER CAP.	2.2NF 4KV M
C817	VE-30000198	CER CAP.	120PF 500V J SL
C818	VE-30012590	SMD CAP.	47NF 50V K
C819	VE-30012590	SMD CAP.	47NF 50V K
C822	VE-30007308	CER CAP.	220PF 1KV K (PULSE)
C826	VE-30000406	EL CAP.	47UF 250V M (HR)
C827	VE-30000411	EL CAP.	470UF 16V M
C828	VE-30012590	SMD CAP.	47NF 50V K
C829	VE-30000407	EL CAP.	470UF 16V M
C830	VE-30000383	EL CAP.	220UF 25V M

Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C832	VE-30012590	SMD CAP.	47NF 50V K
C833	VE-30000407	EL CAP.	470UF 16V M
C834	VE-30012590	SMD CAP.	47NF 50V K
C835	VE-30012590	SMD CAP.	47NF 50V K
C838	VE-30000407	EL CAP.	470UF 16V M
C839	VE-30000407	EL CAP.	470UF 16V M
C840	VE-30000407	EL CAP.	470UF 16V M
C848	VE-30000407	EL CAP.	470UF 16V M
C850	VE-30000383	EL CAP.	220UF 25V M
C851	VE-30012590	SMD CAP.	47NF 50V K
△ C852	VE-30000440	CER CAP.	2.2NF 4KV M
C857	VE-30000106	MKT CAP.	47NF 100V J
C858	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
C859	VE-30009208	CER CAP.	470PF 1KV K (PULSE)
C860	VE-30000296	CER CAP.	100NF 100V Z F
C872	VE-30007708	CER CAP.	1NF 1KV K (PULSE)

TRANSF

TR600	VE-30002090	LINE DRIVER
△ TR601	VE-30017522	FBT TRF
△ TR802	VE-30018785	SMPS TRF

COIL

L101	VE-30001971	FERRITE BEAT
L102	VE-30001971	FERRITE BEAT
L106	VE-30001971	FERRITE BEAT
L108	VE-30001971	FERRITE BEAT
L109	VE-30001971	FERRITE BEAT
L110	VE-30001971	FERRITE BEAT
L111	VE-30001971	FERRITE BEAT
L112	VE-30001971	FERRITE BEAT
L113	VE-30001971	FERRITE BEAT
L114	VE-30001971	FERRITE BEAT
L115	VE-30001971	FERRITE BEAT
L116	VE-30001971	FERRITE BEAT
L117	VE-30001971	FERRITE BEAT
L201	VE-30001979	FIXED COIL 10UH
L210	VE-30001971	FERRITE BEAT
L215	VE-30001971	FERRITE BEAT
L401	VE-30001971	FERRITE BEAT
L402	VE-30001992	FIXED COIL 10UH
L403	VE-30001971	FERRITE BEAT
L404	VE-30001990	FIXED COIL 6.8UH Q75 K
L405	VE-30014048	ADJ. COIL 44MHZ
L406	VE-30001971	FERRITE BEAT
L408	VE-30001992	FIXED COIL 10UH
L501	VE-30001971	FERRITE BEAT
L502	VE-30001971	FERRITE BEAT
L503	VE-30001971	FERRITE BEAT
L504	VE-30001971	FERRITE BEAT
L600	VE-30002031	FIXED COIL 15MH
L602	VE-30002156	LINEARITY COIL 30UH
L603	VE-30002026	FIXED COIL 1MH
L700	VE-30001971	FERRITE BEAT
L701	VE-30001971	FERRITE BEAT
L702	VE-30001992	FIXED COIL 10UH
L703	VE-30001971	FERRITE BEAT
L704	VE-30001971	FERRITE BEAT
L801	VE-30002011	CHOKE COIL 150UH
L803	VE-30001992	FIXED COIL 10UH

DIODE

D105	VE-30007760	ZENER DIODE
D106	VE-30007760	ZENER DIODE
D107	VE-30007760	ZENER DIODE
D303	VE-30001329	DIODE
D405	VE-30007763	ZENER DIODE
D407	VE-30001284	DIODE
D408	VE-30001285	DIODE
D409	VE-30001284	DIODE
D413	VE-30018526	ZENER DIODE
D501	VE-30001285	DIODE
D505	VE-30001285	DIODE
D506	VE-30001284	DIODE
D512	VE-30001285	DIODE
D513	VE-30001369	ZENER DIODE
D533	VE-30001377	ZENER DIODE

[AV-28BT8EES / AV-28BT8EEB]

Symbol No.	Part No.	Part Name	Description
DIODE			
D601	VE-30001329	DIODE	
D603	VE-30001285	DIODE	
D605	VE-30001320	DIODE	
D606	VE-30001323	DIODE	
D609	VE-30001318	DIODE	
D610	VE-30001318	DIODE	
D613	VE-30001318	DIODE	
D614	VE-30001285	DIODE	
D616	VE-30003696	DIODE	
D617	VE-30001318	DIODE	
D651	VE-30001285	DIODE	
D653	VE-30001285	DIODE	
D656	VE-30007763	ZENER DIODE	
D657	VE-30007763	ZENER DIODE	
D658	VE-30007763	ZENER DIODE	
D659	VE-30001350	ZENER DIODE	
D660	VE-30001347	ZENER DIODE	
D661	VE-30001350	ZENER DIODE	
D700	VE-30001285	DIODE	
D701	VE-30001369	ZENER DIODE	
D800	VE-30001318	DIODE	
D801	VE-30001372	ZENER DIODE	
D802	VE-30001318	DIODE	
D803	VE-30001315	DIODE	
D804	VE-30001318	DIODE	
D805	VE-30001315	DIODE	
D806	VE-30001315	DIODE	
D808	VE-20092405	CN. ASY	
D809	VE-30001329	DIODE	
D810	VE-30009366	DIODE	
D811	VE-30009366	DIODE	
D812	VE-30001285	DIODE	
D889	VE-30001384	TR	
△ D891	VE-30007758	BRIDGE DIODE	
D892	VE-30001318	DIODE	
D893	VE-30001318	DIODE	
D894	VE-30001285	DIODE	
D897	VE-30001329	DIODE	

TRANSISTOR

Q104	VE-30001457	TR	
Q106	VE-30001457	TR	
Q141	VE-30001457	TR	
Q142	VE-30001457	TR	
Q307	VE-30001457	TR	
Q316	VE-30001458	TR	
Q403	VE-30001457	TR	
Q404	VE-30001457	TR	
Q503	VE-30001457	TR	
Q504	VE-30001458	TR	
Q600	VE-30001435	TR	
△ Q601	VE-30001441	TR	H. OUT
Q602	VE-30001429	TR	
Q603	VE-30001458	TR	
Q604	VE-30001457	TR	
Q605	VE-30001458	TR	
Q700	VE-30001458	TR	
Q801	VE-30001386	TR	
Q802	VE-30001457	TR	
Q804	VE-30001454	TR	

IC

IC301	VE-30016113	IC	
IC408	VE-30014510	IC	
IC500	VE-20101623	IC	(SERVICE)
IC501	VE-20093395	IC	(MICOM)
IC601	VE-30013985	IC	
IC700	VE-30013658	IC	
IC800	VE-30011968	IC	
△ IC801	VE-30015087	IC	
IC802	VE-30001622	IC	
IC803	VE-30001500	IC	
IC804	VE-30001622	IC	
IC818	VE-30001506	IC	

Symbol No.	Part No.	Part Name	Description
OTHERS			
△ TR801	VE-30002104	LINE FILTER	
△ F801	VE-30001731	FUSE	2.5A
△ TH800	VE-30001270	PTC	9 OHM
TU201	VE-30009637	TUNER	
VR800	VE-30001064	RES ADJ	
X401	VE-30001749	XTAL	
X402	VE-30015592	XTAL	
X501	VE-30002851	XTAL	
X700	VE-30001756	XTAL	
Z401	VE-30013163	SAW FILTER	
Z402	VE-30014261	SAW FILTER	
Z404	VE-30001724	SER FILTER	

CRT SOCKET P.W. BOARD ASS'Y (VE-20094670)

Refer to PARTS LIST in page 30 for this P.W. board

**FRONT CONTROL P.W. BOARD ASS'Y
(VE-20082481)**

Refer to PARTS LIST in page 30 for this P.W. board

**FRONT AV & HEADPHONE P.W. BOARD ASS'Y
(VE-20083646)**

Refer to PARTS LIST in page 30 for this P.W. board

PRINTED WIRING BOARD PARTS LIST

[AV-28BS88EN]

MAIN P.W. BOARD ASS'Y (VE-20101578)

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R102	VE-30012657	SMD RES.	1/10W 1K J
R103	VE-30012657	SMD RES.	1/10W 1K J
R106	VE-30012713	SMD RES.	1/10W 75R J
R107	VE-30012649	SMD RES.	1/10W 150R J
R109	VE-30012713	SMD RES.	1/10W 75R J
R110	VE-30012713	SMD RES.	1/10W 75R J
R111	VE-30012649	SMD RES.	1/10W 150R J
R113	VE-30012713	SMD RES.	1/10W 75R J
R114	VE-30012713	SMD RES.	1/10W 75R J
R115	VE-30012713	SMD RES.	1/10W 75R J
R117	VE-30000792	CF RES.	1/4W 75R J
R118	VE-30012713	SMD RES.	1/10W 75R J
R121	VE-30012649	SMD RES.	1/10W 150R J
R122	VE-30000792	CF RES.	1/4W 75R J
R123	VE-30000792	CF RES.	1/4W 75R J
R124	VE-30012649	SMD RES.	1/10W 150R J
R126	VE-30012657	SMD RES.	1/10W 1K J
R129	VE-30012713	SMD RES.	1/10W 75R J
R135	VE-30012657	SMD RES.	1/10W 1K J
R137	VE-30000466	CF RES.	1/4W 1K J
R138	VE-30012657	SMD RES.	1/10W 1K J
R139	VE-30012713	SMD RES.	1/10W 75R J
R141	VE-30012657	SMD RES.	1/10W 1K J
R145	VE-30012713	SMD RES.	1/10W 75R J
R149	VE-30012703	SMD RES.	1/10W 56K J
R151	VE-30012696	SMD RES.	1/10W 47K J
R152	VE-30000752	CF RES.	1/4W 56K J
R153	VE-30012657	SMD RES.	1/10W 1K J
R154	VE-30000723	CF RES.	1/4W 47K J
R155	VE-30012649	SMD RES.	1/10W 150R J
R169	VE-30012703	SMD RES.	1/10W 56K J
R171	VE-30012713	SMD RES.	1/10W 75R J
R172	VE-30012692	SMD RES.	1/10W 4.7K J
R174	VE-30012713	SMD RES.	1/10W 75R J
R175	VE-30012713	SMD RES.	1/10W 75R J
R176	VE-30012703	SMD RES.	1/10W 56K J
R201	VE-30012674	SMD RES.	1/10W 27K J
R202	VE-30012692	SMD RES.	1/10W 4.7K J
R204	VE-30000459	CF RES.	1/4W 100R J
R206	VE-30000459	CF RES.	1/4W 100R J
R319	VE-30014076	SMD RES.	1/10W 4.7K J
R320	VE-30014076	SMD RES.	1/10W 4.7K J
R324	VE-30012667	SMD RES.	1/10W 220K J
R328	VE-30012649	SMD RES.	1/10W 150R J
R329	VE-30012692	SMD RES.	1/10W 4.7K J
R332	VE-30012641	SMD RES.	1/10W 10K J
R333	VE-30012702	SMD RES.	1/10W 560R J
R338	VE-30012641	SMD RES.	1/10W 10K J
R340	VE-30012644	SMD RES.	1/10W 12K J
R341	VE-30012702	SMD RES.	1/10W 560R J
R343	VE-30012659	SMD RES.	1/10W 2.2K J
R370	VE-30012669	SMD RES.	1/10W 22K J
R371	VE-30012669	SMD RES.	1/10W 22K J
R391	VE-30012696	SMD RES.	1/10W 47K J
R417	VE-30012510	SMD RES.	1/10W 100R J
R418	VE-30012510	SMD RES.	1/10W 100R J
R419	VE-30012649	SMD RES.	1/10W 150R J
R420	VE-30000466	CF RES.	1/4W 1K J
R421	VE-30012650	SMD RES.	1/10W 15K J
R422	VE-30012659	SMD RES.	1/10W 2.2K J
R423	VE-30012712	SMD RES.	1/10W 8.2K J
R425	VE-30012510	SMD RES.	1/10W 100R J
R426	VE-30012659	SMD RES.	1/10W 2.2K J
R427	VE-30012674	SMD RES.	1/10W 27K J
R428	VE-30012510	SMD RES.	1/10W 100R J
R430	VE-30012702	SMD RES.	1/10W 560R J
R431	VE-30012674	SMD RES.	1/10W 27K J
R432	VE-30012707	SMD RES.	1/10W 680R J
R433	VE-30012683	SMD RES.	1/10W 330K J
R437	VE-30000466	CF RES.	1/4W 1K J
R438	VE-30000466	CF RES.	1/4W 1K J
R439	VE-30012657	SMD RES.	1/10W 1K J
R440	VE-30012714	SMD RES.	1/10W 820R J
R441	VE-30012674	SMD RES.	1/10W 27K J
R442	VE-30000466	CF RES.	1/4W 1K J
R446	VE-30012714	SMD RES.	1/10W 820R J
R447	VE-30012714	SMD RES.	1/10W 820R J
R448	VE-30012683	SMD RES.	1/10W 330K J
R449	VE-30012659	SMD RES.	1/10W 2.2K J

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R450	VE-30012702	SMD RES.	1/10W 560R J
R458	VE-30012510	SMD RES.	1/10W 100R J
R459	VE-30012668	SMD RES.	1/10W 220R J
R460	VE-30012668	SMD RES.	1/10W 220R J
R461	VE-30012668	SMD RES.	1/10W 220R J
R462	VE-30012510	SMD RES.	1/10W 100R J
R467	VE-30000670	CF RES.	1/4W 330K J
R468	VE-30000670	CF RES.	1/4W 330K J
R469	VE-30000628	CF RES.	1/4W 2.7K J
R471	VE-30014022	SMD RES.	1/10W 47R J
R472	VE-30012662	SMD RES.	1/10W 2.7K J
R474	VE-30012662	SMD RES.	1/10W 2.7K J
R481	VE-30000466	CF RES.	1/4W 1K J
R482	VE-30012657	SMD RES.	1/10W 1K J
R483	VE-30012657	SMD RES.	1/10W 1K J
R485	VE-30012657	SMD RES.	1/10W 1K J
R486	VE-30012657	SMD RES.	1/10W 1K J
R487	VE-30012657	SMD RES.	1/10W 1K J
R507	VE-30000466	CF RES.	1/4W 1K J
R508	VE-30012510	SMD RES.	1/10W 100R J
R509	VE-30012641	SMD RES.	1/10W 10K J
R510	VE-30012702	SMD RES.	1/10W 560R J
R511	VE-30012657	SMD RES.	1/10W 1K J
R512	VE-30000495	CF RES.	1/4W 1.2K J
R513	VE-30000459	CF RES.	1/4W 100R J
R514	VE-30000459	CF RES.	1/4W 100R J
R515	VE-30012659	SMD RES.	1/10W 2.2K J
R516	VE-30012659	SMD RES.	1/10W 2.2K J
R517	VE-30012692	SMD RES.	1/10W 4.7K J
R518	VE-30000471	CF RES.	1/4W 10K J
R519	VE-30012698	SMD RES.	1/10W 5.6K J
R525	VE-30012649	SMD RES.	1/10W 150R J
R526	VE-30012641	SMD RES.	1/10W 10K J
R527	VE-30012692	SMD RES.	1/10W 4.7K J
R528	VE-30012698	SMD RES.	1/10W 5.6K J
R529	VE-30012698	SMD RES.	1/10W 5.6K J
R530	VE-30012698	SMD RES.	1/10W 5.6K J
R532	VE-30012659	SMD RES.	1/10W 2.2K J
R533	VE-30012644	SMD RES.	1/10W 12K J
R534	VE-30000628	CF RES.	1/4W 2.7K J
R537	VE-30012641	SMD RES.	1/10W 10K J
R538	VE-30012698	SMD RES.	1/10W 5.6K J
R539	VE-30012659	SMD RES.	1/10W 2.2K J
R540	VE-30012644	SMD RES.	1/10W 12K J
R545	VE-30012644	SMD RES.	1/10W 12K J
R548	VE-30012641	SMD RES.	1/10W 10K J
R554	VE-30012641	SMD RES.	1/10W 10K J
R555	VE-30012659	SMD RES.	1/10W 2.2K J
R556	VE-30012657	SMD RES.	1/10W 1K J
R560	VE-30012674	SMD RES.	1/10W 27K J
R561	VE-30012692	SMD RES.	1/10W 4.7K J
R568	VE-30000594	CF RES.	1/4W 22K J
R572	VE-30012659	SMD RES.	1/10W 2.2K J
R573	VE-30012641	SMD RES.	1/10W 10K J
R574	VE-30012657	SMD RES.	1/10W 1K J
R603	VE-30000459	CF RES.	1/4W 100R J
R604	VE-30012510	SMD RES.	1/10W 100R J
R606	VE-30000471	CF RES.	1/4W 10K J
R607	VE-30000554	CF RES.	1/4W 180R J
R608	VE-30000859	MF RES.	1/2W 1R F
R609	VE-30000711	CF RES.	1/2W 470R J
R610	VE-30000599	CF RES.	1/4W 220K J
R611	VE-30012708	SMD RES.	1/10W 68K J
R614	VE-30012509	SMD RES.	1/10W 100K J
R616	VE-30012669	SMD RES.	1/10W 22K J
R617	VE-30000572	CF RES.	1/4W 2K J
R630	VE-30012702	SMD RES.	1/10W 560R J
R634	VE-30000633	CF RES.	1/4W 27K J
R639	VE-30000471	CF RES.	1/4W 10K J
R640	VE-30000628	CF RES.	1/4W 2.7K J
R646	VE-30000531	CF RES.	1/4W 15K J
R647	VE-30000466	CF RES.	1/4W 1K J
△ R648	VE-30001246	FUSE RES.	1W 0.47R J
R650	VE-30012702	SMD RES.	1/10W 560R J
R651	VE-30012668	SMD RES.	1/10W 220R J
△ R656	VE-30001230	FUSE RES.	1/2W 27R J
△ R657	VE-30001228	FUSE RES.	1/2W 2.2R J
R662	VE-30012674	SMD RES.	1/10W 27K J
R666	VE-30000815	CF RES.	1/4W 8.2K J

[AV-28BS88EN]

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

RESISTOR

R668	VE-30000790	CF RES.	1/4W 6.8R J
R669	VE-30012510	SMD RES.	1/16W 100R J
R670	VE-30012510	SMD RES.	1/16W 100R J
R674	VE-30012662	SMD RES.	1/16W 2.7K J
△ R675	VE-30001244	FUSE RES.	1/2W 0.47R J
R677	VE-30001124	MO RES.	3W 220R J
R678	VE-30014022	SMD RES.	1/16W 47R J
R680	VE-30000477	CF RES.	1/4W 100K J
R681	VE-30012509	SMD RES.	1/16W 100K J
R682	VE-30008856	MO RES.	2W 270R J
R683	VE-30017083	WM RES.	5W 2.2K J RAD.
R689	VE-30000718	CF RES.	1/4W 4.7K J
R690	VE-30000466	CF RES.	1/4W 1K J
R691	VE-30012696	SMD RES.	1/16W 47K J
R692	VE-30012509	SMD RES.	1/16W 100K J
R693	VE-30012708	SMD RES.	1/16W 68K J
R694	VE-30000689	CF RES.	1/4W 3.9K J
R695	VE-30000471	CF RES.	1/4W 10K J
R696-Y	VE-30001350	ZENER DIODE	12V
R697	VE-30000712	CF RES.	1/4W 470R J
R698	VE-30012657	SMD RES.	1/16W 1K J
R699	VE-30012685	SMD RES.	1/16W 33K J
R700	VE-30012649	SMD RES.	1/16W 150R J
R701	VE-30000459	CF RES.	1/4W 100R J
R703	VE-30000459	CF RES.	1/4W 100R J
R705	VE-30000459	CF RES.	1/4W 100R J
R715	VE-30012702	SMD RES.	1/16W 560R J
R717	VE-30012702	SMD RES.	1/16W 560R J
R719	VE-30012657	SMD RES.	1/16W 1K J
R721	VE-30012510	SMD RES.	1/16W 100R J
R722	VE-30012510	SMD RES.	1/16W 100R J
R723	VE-30012510	SMD RES.	1/16W 100R J
R724	VE-30012510	SMD RES.	1/16W 100R J
R801	VE-30000718	CF RES.	1/4W 4.7K J
R803	VE-30012659	SMD RES.	1/16W 2.2K J
R805	VE-30000650	CF RES.	1/4W 33R J
R806	VE-30000982	MF RES.	1/4W 4.7K J
R807	VE-30001173	MO RES.	1W 0.47R J
R809	VE-30007784	MO RES.	5W 33K J (RADIAL)
△ R810	VE-30001257	MG RES.	1/2W 4.7M J
R811	VE-30000718	CF RES.	1/4W 4.7K J
R812	VE-30012641	SMD RES.	1/16W 10K J
R813	VE-30000466	CF RES.	1/4W 1K J
R814	VE-30000466	CF RES.	1/4W 1K J
R817	VE-30000880	MF RES.	1/4W 130K F
R818	VE-30012675	SMD RES.	1/16W 2K J
R819	VE-30000526	CF RES.	1/4W 1.5K J
R828	VE-30000530	CF RES.	1/2W 15K J
R829	VE-30000530	CF RES.	1/2W 15K J
R834	VE-30001159	MO RES.	1W 0.33R J
R836	VE-30012662	SMD RES.	1/16W 2.7K J
R839	VE-30000526	CF RES.	1/4W 1.5K J
R842	VE-30014128	SMD RES.	1/16W 33R J
R844	VE-30012641	SMD RES.	1/16W 10K J
R845	VE-30012509	SMD RES.	1/16W 100K J
R846	VE-30012692	SMD RES.	1/16W 4.7K J
R847	VE-30014128	SMD RES.	1/16W 33R J
R848	VE-30012641	SMD RES.	1/16W 10K J
R849	VE-30012510	SMD RES.	1/16W 100R J
R851	VE-30000718	CF RES.	1/4W 4.7K J
R852	VE-30000650	CF RES.	1/4W 33R J
R853	VE-30012642	SMD RES.	1/16W 120K J
R855	VE-30000459	CF RES.	1/4W 100R J
R856	VE-30012694	SMD RES.	1/16W 470K J

CAPACITOR

C141	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C142	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C143	VE-30012589	SMD CAP.	4.7NF 50V K
C144	VE-30012589	SMD CAP.	4.7NF 50V K
C145	VE-30012589	SMD CAP.	4.7NF 50V K
C146	VE-30012589	SMD CAP.	4.7NF 50V K
C147	VE-30012589	SMD CAP.	4.7NF 50V K
C148	VE-30012589	SMD CAP.	4.7NF 50V K
C149	VE-30012589	SMD CAP.	4.7NF 50V K
C150	VE-30012589	SMD CAP.	4.7NF 50V K
C155	VE-30012560	SMD CAP.	100PF 50V J
C157	VE-30012560	SMD CAP.	100PF 50V J
C159	VE-30000352	EL CAP.	100UF 16V M
C160	VE-30000345	EL CAP.	10UF 50V M
C161	VE-30000345	EL CAP.	10UF 50V M

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

CAPACITOR

C162	VE-30012573	SMD CAP.	47PF 50V J
C164	VE-30012692	SMD RES.	1/16W 4.7K J
C165	VE-30000413	EL CAP.	4.7UF 50V M
C201	VE-30000400	EL CAP.	47UF 50V M
C205	VE-30000345	EL CAP.	10UF 50V M
C206	VE-30012610	SMD CAP.	10NF 50V J
C207	VE-30012610	SMD CAP.	10NF 50V J
C230	VE-30016654	SMD CAP.	100NF 16V K R
C246	VE-30000295	CER CAP.	100NF 50V Z F
C303	VE-30000100	MKT CAP.	330NF 63V J
C305	VE-30012590	SMD CAP.	47NF 50V K
C310	VE-30000345	EL CAP.	10UF 50V M
C333	VE-30000083	MKT CAP.	150NF 63V J
C363	VE-30000083	MKT CAP.	150NF 63V J
C364	VE-30012590	SMD CAP.	47NF 50V K
C366	VE-30000407	EL CAP.	47UF 16V M
C368	VE-30012590	SMD CAP.	47NF 50V K
C404	VE-30000190	CER CAP.	100PF 50V J CH
C408	VE-30012586	SMD CAP.	22NF 50V K
C409	VE-30000345	EL CAP.	10UF 50V M
C410	VE-30000384	EL CAP.	2.2UF 50V M
C411	VE-30000345	EL CAP.	10UF 50V M
C412	VE-30016654	SMD CAP.	100NF 16V K R
C413	VE-30000362	EL CAP.	1UF 50V M
C414	VE-30012585	SMD CAP.	2.2NF 50V K R
C415	VE-30012581	SMD CAP.	1NF 50V K R
C416	VE-30000362	EL CAP.	1UF 50V M
C417	VE-30000362	EL CAP.	1UF 50V M
C418	VE-30016654	SMD CAP.	100NF 16V K R
C419	VE-30000384	EL CAP.	2.2UF 50V M
C420	VE-30000100	MKT CAP.	330NF 63V J
C422	VE-30000352	EL CAP.	100UF 16V M
C423	VE-30000352	EL CAP.	100UF 16V M
C424	VE-30000352	EL CAP.	100UF 16V M
C425	VE-30016654	SMD CAP.	100NF 16V K R
C427	VE-30016654	SMD CAP.	100NF 16V K R
C429	VE-30012589	SMD CAP.	4.7NF 50V K
C430	VE-30016654	SMD CAP.	100NF 16V K R
C431	VE-30000362	EL CAP.	1UF 50V M
C432	VE-30016654	SMD CAP.	100NF 16V K R
C433	VE-30000345	EL CAP.	10UF 50V M
C434	VE-30016654	SMD CAP.	100NF 16V K R
C435	VE-30016654	SMD CAP.	100NF 16V K R
C436	VE-30000384	EL CAP.	2.2UF 50V M
C437	VE-30016654	SMD CAP.	100NF 16V K R
C438	VE-30016654	SMD CAP.	100NF 16V K R
C439	VE-30016654	SMD CAP.	100NF 16V K R
C440	VE-30000295	CER CAP.	100NF 50V Z F
C441	VE-30012582	SMD CAP.	10NF 50V K R
C442	VE-30000362	EL CAP.	1UF 50V M
C443	VE-30000362	EL CAP.	1UF 50V M
C444	VE-30000384	EL CAP.	2.2UF 50V M
C448	VE-30012586	SMD CAP.	22NF 50V K
C449	VE-30012560	SMD CAP.	100PF 50V J
C453	VE-30000352	EL CAP.	100UF 16V M
C455	VE-30000345	EL CAP.	10UF 50V M
C459	VE-30012560	SMD CAP.	100PF 50V J
C501	VE-30016654	SMD CAP.	100NF 16V K R
C502	VE-30000400	EL CAP.	47UF 50V M
C504	VE-30016654	SMD CAP.	100NF 16V K R
C505	VE-30012589	SMD CAP.	4.7NF 50V K
C507	VE-30000345	EL CAP.	10UF 50V M
C510	VE-30016654	SMD CAP.	100NF 16V K R
C511	VE-30012566	SMD CAP.	22PF 50V J
C513	VE-30000345	EL CAP.	10UF 50V M
C514	VE-30016654	SMD CAP.	100NF 16V K R
C515	VE-30012560	SMD CAP.	100PF 50V J
C517	VE-30016654	SMD CAP.	100NF 16V K R
C518	VE-30016654	SMD CAP.	100NF 16V K R
C519	VE-30012560	SMD CAP.	100PF 50V J
C520	VE-30012560	SMD CAP.	100PF 50V J
C521	VE-30012562	SMD CAP.	15PF 50V J
C522	VE-30012562	SMD CAP.	15PF 50V J
C523	VE-30012585	SMD CAP.	2.2NF 50V K R
C524	VE-30012566	SMD CAP.	22PF 50V J
C525	VE-30012566	SMD CAP.	22PF 50V J
C526	VE-30016654	SMD CAP.	100NF 16V K R
C527	VE-30000345	EL CAP.	10UF 50V M
C529	VE-30012589	SMD CAP.	4.7NF 50V K
C530	VE-30012589	SMD CAP.	4.7NF 50V K
C532	VE-30016654	SMD CAP.	100NF 16V K R
C536	VE-30000295	CER CAP.	100NF 50V Z F
C541	VE-30000362	EL CAP.	1UF 50V M

[AV-28BS88EN]

Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C542	VE-30000107	MKT CAP.	47NF 250V J
C543	VE-30000431	CER CAP.	100PF 1KV M
C544	VE-30000345	EL CAP.	10UF 50V M
C547	VE-30000345	EL CAP.	10UF 50V M
C565	VE-30016654	SMD CAP.	100NF 16V K R
C566	VE-30016654	SMD CAP.	100NF 16V K R
C567	VE-30000431	CER CAP.	100PF 1KV M
C602	VE-30017319	MKT CAP.	120NF 63V J
C604	VE-30000356	EL CAP.	100UF 63V M
C605	VE-30000360	EL CAP.	100UF 25V M
C607	VE-30012581	SMD CAP.	1NF 50V K R
△ C618	VE-30000159	MKT CAP.	4.7NF 1.6KV J
△ C621	VE-30000179	MKT CAP.	9.1NF 1600V X3.5
C622	VE-30000121	KP CAP.	27NF 630V J
△ C625	VE-30000156	MKT CAP.	430NF 250V J
C627	VE-30000167	MKT CAP.	560NF 250V J
C629	VE-30000177	MKT CAP.	820NF 250V J
C632	VE-30000100	MKT CAP.	330NF 63V J
C635	VE-30000385	EL CAP.	2.2UF 250V M
C636	VE-30000387	EL CAP.	33UF 50V M
C640	VE-30000100	MKT CAP.	330NF 63V J
C641	VE-30000090	MKT CAP.	22NF 100V J
C642	VE-30000407	EL CAP.	470UF 16V M
C644	VE-30000409	EL CAP.	470UF 25V M
C645	VE-30000090	MKT CAP.	22NF 100V J
C646	VE-30000100	MKT CAP.	330NF 63V J
C647	VE-30007748	EL CAP.	1000UF 35V M
C648	VE-30000394	EL CAP.	3.3UF 160V M
C649	VE-30000295	CER CAP.	100NF 50V Z F
C652	VE-30000330	CER CAP.	4.7NF 50V K B
C653	VE-30000107	MKT CAP.	47NF 250V J
C655	VE-30000415	EL CAP.	4.7UF 250V M
C700	VE-30012565	SMD CAP.	1.8PF 50V J CH
C701	VE-30012565	SMD CAP.	1.8PF 50V J CH
C702	VE-30012576	SMD CAP.	56PF 50V J CH
C703	VE-30012576	SMD CAP.	56PF 50V J CH
C704	VE-30012576	SMD CAP.	56PF 50V J CH
C705	VE-30000345	EL CAP.	10UF 50V M
C706	VE-30000345	EL CAP.	10UF 50V M
C708	VE-30016654	SMD CAP.	100NF 16V K R
C712	VE-30000345	EL CAP.	10UF 50V M
C713	VE-30016654	SMD CAP.	100NF 16V K R
C714	VE-30000100	MKT CAP.	330NF 63V J
C716	VE-30000100	MKT CAP.	330NF 63V J
C717	VE-30000100	MKT CAP.	330NF 63V J
C718	VE-30000100	MKT CAP.	330NF 63V J
C719	VE-30016654	SMD CAP.	100NF 16V K R
C720	VE-30000345	EL CAP.	10UF 50V M
C721	VE-30000100	MKT CAP.	330NF 63V J
C723	VE-30000100	MKT CAP.	330NF 63V J
C724	VE-30000345	EL CAP.	10UF 50V M
C729	VE-30016654	SMD CAP.	100NF 16V K R
C730	VE-30000393	EL CAP.	3.3UF 50V M
C733	VE-30000345	EL CAP.	10UF 50V M
C734	VE-30000345	EL CAP.	10UF 50V M
C735	VE-30016654	SMD CAP.	100NF 16V K R
C736	VE-30000345	EL CAP.	10UF 50V M
C737	VE-30000384	EL CAP.	2.2UF 50V M
C738	VE-30000384	EL CAP.	2.2UF 50V M
C739	VE-30000384	EL CAP.	2.2UF 50V M
C740	VE-30000384	EL CAP.	2.2UF 50V M
C741	VE-30012589	SMD CAP.	4.7NF 50V K
C742	VE-30012589	SMD CAP.	4.7NF 50V K
C745	VE-30016654	SMD CAP.	100NF 16V K R
△ C801	VE-30000094	MKT CAP.	220NF 275V M AC
△ C802	VE-30000094	MKT CAP.	220NF 275V M AC
△ C803	VE-30000433	CER CAP.	1NF 1KV M B
△ C804	VE-30000433	CER CAP.	1NF 1KV M B
C808	VE-30012590	SMD CAP.	47NF 50V K
C809	VE-30000420	EL CAP.	150UF 400V M
C810	VE-30000387	EL CAP.	33UF 50V M
C811	VE-30000161	MKT CAP.	47NF 630V J
△ C812	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
C816	VE-30000440	CER CAP.	2.2NF 4KV M
C817	VE-30000198	CER CAP.	120PF 500V J SL
C818	VE-30012590	SMD CAP.	47NF 50V K
C819	VE-30012590	SMD CAP.	47NF 50V K
C822	VE-30007308	CER CAP.	220PF 1KV K (PULSE)
C826	VE-30000406	EL CAP.	47UF 250V M (HR)
C827	VE-30000411	EL CAP.	470UF 16V M
C828	VE-30012590	SMD CAP.	47NF 50V K
C829	VE-30000407	EL CAP.	470UF 16V M
C830	VE-30000383	EL CAP.	220UF 25V M

Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C832	VE-30012590	SMD CAP.	47NF 50V K
C833	VE-30000407	EL CAP.	470UF 16V M
C834	VE-30012590	SMD CAP.	47NF 50V K
C835	VE-30012590	SMD CAP.	47NF 50V K
C838	VE-30000407	EL CAP.	470UF 16V M
C839	VE-30000407	EL CAP.	470UF 16V M
C840	VE-30000407	EL CAP.	470UF 16V M
C848	VE-30000407	EL CAP.	470UF 16V M
C850	VE-30000383	EL CAP.	220UF 25V M
C851	VE-30012590	SMD CAP.	47NF 50V K
△ C852	VE-30000440	CER CAP.	2.2NF 4KV M
C857	VE-30000106	MKT CAP.	47NF 100V J
C858	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
C859	VE-30009208	CER CAP.	470PF 1KV K (PULSE)
C860	VE-30000296	CER CAP.	100NF 100V Z F
C872	VE-30007708	CER CAP.	1NF 1KV K (PULSE)

TRANSF

TR600	VE-30002090	LINE DRIVER
△ TR601	VE-30017522	FBT TRF
△ TR802	VE-30018785	SMPS TRF

COIL

L101	VE-30001971	FERRITE BEAT
L102	VE-30001971	FERRITE BEAT
L106	VE-30001971	FERRITE BEAT
L108	VE-30001971	FERRITE BEAT
L109	VE-30001971	FERRITE BEAT
L110	VE-30001971	FERRITE BEAT
L111	VE-30001971	FERRITE BEAT
L112	VE-30001971	FERRITE BEAT
L113	VE-30001971	FERRITE BEAT
L114	VE-30001971	FERRITE BEAT
L115	VE-30001971	FERRITE BEAT
L116	VE-30001971	FERRITE BEAT
L117	VE-30001971	FERRITE BEAT
L201	VE-30001979	FIXED COIL 10UH
L210	VE-30001971	FERRITE BEAT
L215	VE-30001971	FERRITE BEAT
L401	VE-30001971	FERRITE BEAT
L402	VE-30001992	FIXED COIL 10UH
L403	VE-30001971	FERRITE BEAT
L405	VE-30014048	ADJ. COIL 44MHZ
L406	VE-30001971	FERRITE BEAT
L408	VE-30001992	FIXED COIL 10UH
L501	VE-30001971	FERRITE BEAT
L502	VE-30001971	FERRITE BEAT
L503	VE-30001971	FERRITE BEAT
L504	VE-30001971	FERRITE BEAT
L600	VE-30002031	FIXED COIL 15MH
L602	VE-30002156	LINEARITY COIL 30UH
L603	VE-30002026	FIXED COIL 1MH
L700	VE-30001971	FERRITE BEAT
L701	VE-30001971	FERRITE BEAT
L702	VE-30001992	FIXED COIL 10UH
L703	VE-30001971	FERRITE BEAT
L704	VE-30001971	FERRITE BEAT
L801	VE-30002011	CHOKE COIL 150UH
L803	VE-30001992	FIXED COIL 10UH

DIODE

D105	VE-30007760	ZENER DIODE
D106	VE-30007760	ZENER DIODE
D107	VE-30007760	ZENER DIODE
D303	VE-30001329	DIODE
D405	VE-30007763	ZENER DIODE
D407	VE-30001284	DIODE
D408	VE-30001285	DIODE
D409	VE-30001284	DIODE
D413	VE-30018526	ZENER DIODE
D501	VE-30001285	DIODE
D505	VE-30001285	DIODE
D506	VE-30001284	DIODE
D512	VE-30001285	DIODE
D513	VE-30001369	ZENER DIODE
D533	VE-30001377	ZENER DIODE

[AV-28BS88EN]

Symbol No.	Part No.	Part Name	Description
DIODE			
D601	VE-30001329	DIODE	
D603	VE-30001285	DIODE	
D605	VE-30001320	DIODE	
D606	VE-30001323	DIODE	
D609	VE-30001318	DIODE	
D610	VE-30001318	DIODE	
D613	VE-30001318	DIODE	
D614	VE-30001285	DIODE	
D616	VE-30003696	DIODE	
D617	VE-30001318	DIODE	
D651	VE-30001285	DIODE	
D653	VE-30001285	DIODE	
D656	VE-30007763	ZENER DIODE	
D657	VE-30007763	ZENER DIODE	
D658	VE-30007763	ZENER DIODE	
D659	VE-30001350	ZENER DIODE	
D660	VE-30001347	ZENER DIODE	
D661	VE-30001350	ZENER DIODE	
D700	VE-30001285	DIODE	
D701	VE-30001369	ZENER DIODE	
D800	VE-30001318	DIODE	
D801	VE-30001372	ZENER DIODE	
D802	VE-30001318	DIODE	
D803	VE-30001315	DIODE	
D804	VE-30001318	DIODE	
D805	VE-30001315	DIODE	
D806	VE-30001315	DIODE	
D808	VE-20092405	CN. ASSY	
D809	VE-30001329	DIODE	
D810	VE-30009366	DIODE	
D811	VE-30009366	DIODE	
D812	VE-30001285	DIODE	
D889	VE-30001384	TR	
D891	VE-30007758	BRIDGE DIODE	
D892	VE-30001318	DIODE	
D893	VE-30001318	DIODE	
D894	VE-30001285	DIODE	
D897	VE-30001329	DIODE	

TRANSISTOR

Q104	VE-30001457	TR	
Q106	VE-30001457	TR	
Q141	VE-30001457	TR	
Q142	VE-30001457	TR	
Q307	VE-30001457	TR	
Q316	VE-30001458	TR	
Q403	VE-30001457	TR	
Q404	VE-30001457	TR	
Q503	VE-30001457	TR	
Q504	VE-30001458	TR	
Q600	VE-30001435	TR	
Q601	VE-30001441	TR	H. OUT
Q602	VE-30001429	TR	
Q603	VE-30001458	TR	
Q604	VE-30001457	TR	
Q605	VE-30001458	TR	
Q700	VE-30001458	TR	
Q801	VE-30001386	TR	
Q802	VE-30001457	TR	
Q804	VE-30001454	TR	

IC

IC301	VE-30016113	IC	
IC408	VE-30014521	IC	
IC500	VE-20101581	IC	(SERVICE)
IC501	VE-20101580	IC	(MICOM)
IC601	VE-30013985	IC	
IC700	VE-30009354	IC	
IC800	VE-30011968	IC	
IC801	VE-30015087	IC	
IC802	VE-30001622	IC	
IC803	VE-30001500	IC	
IC804	VE-30001622	IC	
IC818	VE-30001506	IC	

Symbol No.	Part No.	Part Name	Description
OTHERS			
TR801	VE-30002104	LINE FILTER	
F801	VE-30001731	FUSE	2.5A
TH800	VE-30001270	PTC	9 OHM
TU201	VE-30009637	TUNER	
VR800	VE-30001064	RES ADJ	
X401	VE-30001749	XTAL	
X402	VE-30015592	XTAL	
X501	VE-30002851	XTAL	
X700	VE-30001756	XTAL	
Z401	VE-30001705	SAW FILTER	
Z402	VE-30015591	SAW FILTER	

CRT SOCKET P.W. BOARD ASS'Y (VE-20094670)

Refer to PARTS LIST in page 30 for this P.W. board


FRONT CONTROL P.W. BOARD ASS'Y (VE-20082481)

Refer to PARTS LIST in page 30 for this P.W. board

FRONT AV & HEADPHONE P.W. BOARD ASS'Y (VE-20083646)

Refer to PARTS LIST in page 30 for this P.W. board

PACKING



PACKING PARTS LIST

△ Ref.No.	Part No.	Part Name	Description
1	VE-50028496	CARTON BOX	(AV-28BT8ENS)
1	VE-50028502	CARTON BOX	(AV-28BT8ENB)
1	VE-50028500	CARTON BOX	(AV-28BT80EN)
1	VE-50028498	CARTON BOX	(AV-28BS88EN)
1	VE-50028423	CARTON BOX	(AV-28BT8EPS)
1	VE-50028424	CARTON BOX	(AV-28BT8EPB)
1	VE-50028221	CARTON BOX	(AV-28BT80EP)
1	VE-50028218	CARTON BOX	(AV-28BT8EES)
1	VE-50028216	CARTON BOX	(AV-28BT8EEB)
2	VE-20081396	CUSHION ASS'Y	4pcs in 1set
3	VE-50026637	POLY BAG	
4	VE-70000587	POLY BAG	
5	VE-30017763	REMOTE CONTROL UNIT (RM-C1100)	
△ 6	VE-50028493	INST BOOK	(AV-28BT8ENS, ENB, AV-28BT80EN)
△ 6	VE-50028296	INST BOOK	(AV-28BT8EPS, EPB, AV-28BT80EP)
△ 6	VE-50028326	INST BOOK	(AV-28BT8EES, EEB)
△ 6	VE-50028511	INST BOOK	(AV-28BS88EN)
7	BT-54013-2TK	WARRANTY CARD	
8	VE-20102137	LABEL	(AV-28BT8ENS)
8	VE-20102147	LABEL	(AV-28BT8ENB)
8	VE-20102144	LABEL	(AV-28BT80EN)
8	VE-20102141	LABEL	(AV-28BS88EN)
8	VE-20101937	LABEL	(AV-28BT8EPS)
8	VE-20101939	LABEL	(AV-28BT8EPB)
8	VE-20101934	LABEL	(AV-28BT80EP)
8	VE-20101919	LABEL	(AV-28BT8EES)
8	VE-20101920	LABEL	(AV-28BT8EES POLAND)
8	VE-20101915	LABEL	(AV-28BT8EEB)
8	VE-20101913	LABEL	(AV-28BT8EEB POLAND)



JVC

VICTOR COMPANY OF JAPAN, LIMITED

HOME AV NETWORK BUSINESS UNIT 12, 3-chome, Moriya-cho, Kanagawa-ku, Yokohama, Kanagawa-prefecture, 221-8528, Japan



VP 0207
DP20588051