

PARTS LIST

CONTENTS

■ USING P.W. BOARD & REMOTE CONTROL UNIT	23
■ EXPLODED VIEW PARTS LIST	24
■ EXPLODED VIEW	25
■ PRINTED WIRING BOARD PARTS LIST	

[AV-29BF11ENS]

● MAIN P.W. BOARD ASS'Y	26
● CRT SOCKET P.W. BOARD ASS'Y	30
● FRONT AV & HEADPHONE P.W. BOARD ASS'Y	30
● FRONT CONTROL P.W. BOARD ASS'Y	30

[AV-29BF11EPS]

● MAIN P.W. BOARD ASS'Y	31
● CRT SOCKET P.W. BOARD ASS'Y	30
● FRONT AV & HEADPHONE P.W. BOARD ASS'Y	30
● FRONT CONTROL P.W. BOARD ASS'Y	30

[AV-29BF11EES]

● MAIN P.W. BOARD ASS'Y	35
● CRT SOCKET P.W. BOARD ASS'Y	30
● FRONT AV & HEADPHONE P.W. BOARD ASS'Y	30
● FRONT CONTROL P.W. BOARD ASS'Y	30

■ PACKING / PACKING PARTS LIST	39
--------------------------------------	----

USING P.W. BOARD & REMOTE CONTROL UNIT

Model PWB ASS'Y	AV-29BF11ENS	AV-29BF11EPS	AV-29BF11EES
MAIN PWB	VE-20103272	VE-20103267	VE-20103265
CRT SOCKET PWB	VE-20094670	←	←
FRONT AV & HEADPHONE PWB	VE-20083646	←	←
FRONT CONTROL PWB	VE-20100168	←	←
REMOTE CONTROL UNIT	VE-30017763 (RM-C1100)	←	←


AV-29BF11ENS
AV-29BF11EPS
AV-29BF11EES

EXPLODED VIEW PARTS LIST

[AV-29BF11ENS, AV-29BF11EPS, AV-29BF11EES]

△ Ref.No.	Part No.	Part Name	Description
△ V01	VE-20098924	CRT KIT	Inc. DEG COIL(VE-30012971), CONN.ASSY,SPRING
△ TR601	VE-30017522	FBT	
△ 1	VE-30012971	DEG COIL&EARTH CB.	
△ 3	VE-35000013	SPRING(ON/OFF SWITCH)	
△ 4	VE-20059930	BUTTON(ON/OFF)	
△ 5	VE-20003605	PIN(CONTROL PANEL DOOR)(×2)	
△ 6	VE-40000026	EJECTOR CLIP-CLAP	
△ 7	VE-20102640	CONTROL PANEL DOOR	
△ 8	VE-20103272	FRONT PANEL	
△ 9	VE-20081212	LENS LED	
△ 10	VE-20082371	BUTTON FUNCTION	
△ 11	VE-40009351	SPONGE	(×2)
△ 12	VE-30001950	SPEAKER(8R 15W)	(×2)
△ 13	VE-30001947	TWEETER(8R 15W)	(×2)
△ 14	VE-20097423	BACK COVER(REAR COVER)	
△ 15	VE-35004572	SCREW	(×8)
△ 16	VE-20067720	BACK DOOR(TERMINAL BOARD)	
△ 17	VE-35000211	SCREW	(×4)
△ 18	VE-40009154	JVC LOGO	
△ 19	VE-20103656	LABEL	[AV-29BF11ENS]
△ 19	VE-20103677	LABEL	[AV-29BF11ENS(for GER models)]
△ 19	VE-20103679	LABEL	[AV-29BF11ENS(for ITA models)]
△ 19	VE-20103654	LABEL	[AV-29BF11EPS]
△ 19	VE-20103640	LABEL	[AV-29BF11EES]
△ 19	VE-20103638	LABEL	[AV-29BF11EES(for POL models)]
△ 20	VE-30002174	MAIN SWITCH (ON/OFF)	
△ --	VE-30016513	POWER CORD	2.2MT(W/FILTER)
△ --	VE-50025747	WARNING LABEL(HUN)	[AV-29BF11EES]

EXPLODED VIEW



PRINTED WIRING BOARD PARTS LIST

[AV-29BF11ENS]

MAIN P.W. BOARD ASS'Y (VE-20103272)

Symbol No.	Part No.	Part Name	Description
VARIABLE RESISTOR			
VR800	VE-30001064	RES ADJ	1/10W 470R VER (MAN)

RESISTOR

R102	VE-30012657	SMD RES.	1/16W 1K J
R103	VE-30012657	SMD RES.	1/16W 1K J
R106	VE-30012713	SMD RES.	1/16W 75R J
R107	VE-30012649	SMD RES.	1/16W 150R J
R109	VE-30012713	SMD RES.	1/16W 75R J
R110	VE-30012713	SMD RES.	1/16W 75R J
R111	VE-30012649	SMD RES.	1/16W 150R J
R113	VE-30012713	SMD RES.	1/16W 75R J
R114	VE-30012713	SMD RES.	1/16W 75R J
R115	VE-30012713	SMD RES.	1/16W 75R J
R117	VE-30000792	CF RES.	1/4W 75R J
R118	VE-30012713	SMD RES.	1/16W 75R J
R121	VE-30012649	SMD RES.	1/16W 150R J
R122	VE-30000792	CF RES.	1/4W 75R J
R123	VE-30000792	CF RES.	1/4W 75R J
R124	VE-30012649	SMD RES.	1/16W 150R J
R126	VE-30012657	SMD RES.	1/16W 1K J
R129	VE-30012713	SMD RES.	1/16W 75R J
R135	VE-30012657	SMD RES.	1/16W 1K J
R137	VE-30000466	CF RES.	1/4W 1K J
R138	VE-30012657	SMD RES.	1/16W 1K J
R139	VE-30012713	SMD RES.	1/16W 75R J
R141	VE-30012657	SMD RES.	1/16W 1K J
R145	VE-30012713	SMD RES.	1/16W 75R J
R149	VE-30012703	SMD RES.	1/16W 56K J
R151	VE-30012696	SMD RES.	1/16W 47K J
R152	VE-30000752	CF RES.	1/4W 56K J
R153	VE-30012657	SMD RES.	1/16W 1K J
R154	VE-30000723	CF RES.	1/4W 47K J
R155	VE-30012649	SMD RES.	1/16W 150R J
R169	VE-30012703	SMD RES.	1/16W 56K J
R171	VE-30012713	SMD RES.	1/16W 75R J
R172	VE-30012692	SMD RES.	1/16W 4.7K J
R174	VE-30012713	SMD RES.	1/16W 75R J
R175	VE-30012713	SMD RES.	1/16W 75R J
R176	VE-30012703	SMD RES.	1/16W 56K J
R201	VE-30012674	SMD RES.	1/16W 27K J
R202	VE-30012692	SMD RES.	1/16W 4.7K J
R204	VE-30000459	CF RES.	1/4W 100R J
R206	VE-30000459	CF RES.	1/4W 100R J
R319	VE-30014076	SMD RES.	1/16W 4.7R J
R320	VE-30014076	SMD RES.	1/16W 4.7R J
R324	VE-30012667	SMD RES.	1/16W 220K J
R328	VE-30012649	SMD RES.	1/16W 150R J
R329	VE-30012692	SMD RES.	1/16W 4.7K J
R332	VE-30012641	SMD RES.	1/16W 10K J
R333	VE-30012702	SMD RES.	1/16W 560R J
R338	VE-30012641	SMD RES.	1/16W 10K J
R340	VE-30012644	SMD RES.	1/16W 12K J
R341	VE-30012702	SMD RES.	1/16W 560R J
R343	VE-30012659	SMD RES.	1/16W 2.2K J
R370	VE-30012669	SMD RES.	1/16W 22K J
R371	VE-30012669	SMD RES.	1/16W 22K J
R391	VE-30012696	SMD RES.	1/16W 47K J
R417	VE-30012510	SMD RES.	1/16W 100R J
R418	VE-30012510	SMD RES.	1/16W 100R J
R419	VE-30012649	SMD RES.	1/16W 150R J
R420	VE-30000466	CF RES.	1/4W 1K J
R421	VE-30012650	SMD RES.	1/16W 15K J
R422	VE-30012659	SMD RES.	1/16W 2.2K J
R423	VE-30012712	SMD RES.	1/16W 8.2K J
R425	VE-30012510	SMD RES.	1/16W 100R J
R426	VE-30012659	SMD RES.	1/16W 2.2K J
R427	VE-30012674	SMD RES.	1/16W 27K J
R428	VE-30012510	SMD RES.	1/16W 100R J
R430	VE-30012702	SMD RES.	1/16W 560R J
R431	VE-30012674	SMD RES.	1/16W 27K J
R432	VE-30012707	SMD RES.	1/16W 680R J
R433	VE-30012683	SMD RES.	1/16W 330K J
R437	VE-30000466	CF RES.	1/4W 1K J
R438	VE-30000466	CF RES.	1/4W 1K J
R439	VE-30012657	SMD RES.	1/16W 1K J
R440	VE-30012714	SMD RES.	1/16W 820R J
R441	VE-30012674	SMD RES.	1/16W 27K J
R442	VE-30000466	CF RES.	1/4W 1K J
R446	VE-30012714	SMD RES.	1/16W 820R J

Symbol No.	Part No.	Part Name	Description
RESISTOR			

R447	VE-30012714	SMD RES.	1/16W 820R J
R448	VE-30012683	SMD RES.	1/16W 330K J
R450	VE-30012702	SMD RES.	1/16W 560R J
R458	VE-30012510	SMD RES.	1/16W 100R J
R459	VE-30012668	SMD RES.	1/16W 220R J
R460	VE-30012668	SMD RES.	1/16W 220R J
R461	VE-30012668	SMD RES.	1/16W 220R J
R449	VE-30012659	SMD RES.	1/16W 2.2K J
R462	VE-30012510	SMD RES.	1/16W 100R J
R467	VE-30000670	CF RES.	1/4W 330K J
R468	VE-30000670	CF RES.	1/4W 330K J
R469	VE-30000628	CF RES.	1/4W 2.7K J
R471	VE-30014022	SMD RES.	1/16W 47R J
R472	VE-30012662	SMD RES.	1/16W 2.7K J
R474	VE-30012662	SMD RES.	1/16W 2.7K J
R481	VE-30000466	CF RES.	1/4W 1K J
R482	VE-30012657	SMD RES.	1/16W 1K J
R483	VE-30012657	SMD RES.	1/16W 1K J
R485	VE-30012657	SMD RES.	1/16W 1K J
R486	VE-30012657	SMD RES.	1/16W 1K J
R487	VE-30012657	SMD RES.	1/16W 1K J
R507	VE-30000466	CF RES.	1/4W 1K J
R508	VE-30012510	SMD RES.	1/16W 100R J
R509	VE-30012641	SMD RES.	1/16W 10K J
R510	VE-30012702	SMD RES.	1/16W 560R J
R511	VE-30012657	SMD RES.	1/16W 1K J
R512	VE-30000495	CF RES.	1/4W 1.2K J
R513	VE-30000459	CF RES.	1/4W 100R J
R514	VE-30000459	CF RES.	1/4W 100R J
R515	VE-30012659	SMD RES.	1/16W 2.2K J
R516	VE-30012659	SMD RES.	1/16W 2.2K J
R517	VE-30012692	SMD RES.	1/16W 4.7K J
R518	VE-30000471	CF RES.	1/4W 10K J
R519	VE-30012698	SMD RES.	1/16W 5.6K J
R525	VE-30012649	SMD RES.	1/16W 150R J
R526	VE-30012641	SMD RES.	1/16W 10K J
R527	VE-30012692	SMD RES.	1/16W 4.7K J
R528	VE-30012698	SMD RES.	1/16W 5.6K J
R529	VE-30012698	SMD RES.	1/16W 5.6K J
R530	VE-30012698	SMD RES.	1/16W 5.6K J
R532	VE-30012659	SMD RES.	1/16W 2.2K J
R533	VE-30012644	SMD RES.	1/16W 12K J
R534	VE-30000628	CF RES.	1/4W 2.7K J
R537	VE-30012641	SMD RES.	1/16W 10K J
R538	VE-30012698	SMD RES.	1/16W 5.6K J
R539	VE-30012659	SMD RES.	1/16W 2.2K J
R540	VE-30012644	SMD RES.	1/16W 12K J
R545	VE-30012644	SMD RES.	1/16W 12K J
R548	VE-30012641	SMD RES.	1/16W 10K J
R554	VE-30012641	SMD RES.	1/16W 10K J
R555	VE-30012659	SMD RES.	1/16W 2.2K J
R556	VE-30012657	SMD RES.	1/16W 1K J
R560	VE-30012674	SMD RES.	1/16W 27K J
R561	VE-30012692	SMD RES.	1/16W 4.7K J
R568	VE-30000594	CF RES.	1/4W 22K J
R572	VE-30012659	SMD RES.	1/16W 2.2K J
R573	VE-30012641	SMD RES.	1/16W 10K J
R574	VE-30012657	SMD RES.	1/16W 1K J
R603	VE-30000459	CF RES.	1/4W 100R J
R604	VE-30012510	SMD RES.	1/16W 100R J
R606	VE-30000471	CF RES.	1/4W 10K J
R607	VE-30000554	CF RES.	1/4W 180R J
R608	VE-30000859	MF RES.	1/2W 1R F
R609	VE-30000711	CF RES.	1/2W 470R J
R610	VE-30000599	CF RES.	1/4W 220K J
R611	VE-30012708	SMD RES.	1/16W 68K J
R616	VE-30012685	SMD RES.	1/16W 33K J
R617	VE-30000572	CF RES.	1/4W 2K J
R630	VE-30012702	SMD RES.	1/16W 560R J
R634	VE-30000633	CF RES.	1/4W 27K J
R639	VE-30000471	CF RES.	1/4W 10K J
R640	VE-30000628	CF RES.	1/4W 2.7K J
R646	VE-30000775	CF RES.	1/4W 6.8K J
R647	VE-30000466	CF RES.	1/4W 1K J
△ R648	VE-30001246	FUSE RES.	1W 0.47R J
R650	VE-30012702	SMD RES.	1/16W 560R J
R651	VE-30012668	SMD RES.	1/16W 220R J
△ R656	VE-30001247	FUSE RES.	1/2W 4.7R J
△ R657	VE-30001228	FUSE RES.	1/2W 2.2R J
R662	VE-30012674	SMD RES.	1/16W 27K J
R666	VE-30000531	CF RES.	1/4W 15K J

[AV-29BF11ENS]

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R668	VE-30000607	CF RES.	1/4W 2.2R J
R669	VE-30012510	SMD RES.	1/16W 100R J
R670	VE-30012510	SMD RES.	1/16W 100R J
R677	VE-30001124	MO RES.	3W 220R J
R678	VE-30014022	SMD RES.	1/16W 47R J
R680	VE-30000477	CF RES.	1/4W 100K J
R681	VE-30012509	SMD RES.	1/16W 100K J
R674	VE-30012662	SMD RES.	1/16W 2.7K J
△ R675	VE-30001208	FUSE RES.	1W 10R J
R682	VE-30017082	WW RES.	5W 75R J RAD.
R683	VE-30017083	WW RES.	5W 2.2K J RAD.
R689	VE-30000718	CF RES.	1/4W 4.7K J
R690	VE-30000466	CF RES.	1/4W 1K J
R691	VE-30012696	SMD RES.	1/16W 47K J
R692	VE-30012509	SMD RES.	1/16W 100K J
R693	VE-30012708	SMD RES.	1/16W 68K J
R694	VE-30000689	CF RES.	1/4W 3.9K J
R695	VE-30000775	CF RES.	1/4W 6.8K J
R696-Y	VE-30001350	ZENER DIODE	12V
R697	VE-30000712	CF RES.	1/4W 470R J
R698	VE-30012657	SMD RES.	1/16W 1K J
R700	VE-30012649	SMD RES.	1/16W 150R J
R701	VE-30000459	CF RES.	1/4W 100R J
R703	VE-30000459	CF RES.	1/4W 100R J
R705	VE-30000459	CF RES.	1/4W 100R J
R715	VE-30012702	SMD RES.	1/16W 560R J
R717	VE-30012702	SMD RES.	1/16W 560R J
R719	VE-30012657	SMD RES.	1/16W 1K J
R721	VE-30012510	SMD RES.	1/16W 100R J
R722	VE-30012510	SMD RES.	1/16W 100R J
R723	VE-30012510	SMD RES.	1/16W 100R J
R724	VE-30012510	SMD RES.	1/16W 100R J
R801	VE-30000718	CF RES.	1/4W 4.7K J
R803	VE-30012659	SMD RES.	1/16W 2.2K J
R805	VE-30000650	CF RES.	1/4W 33R J
R806	VE-30000982	MF RES.	1/4W 4.7K J
R807	VE-30001173	MO RES.	1W 0.47R J
△ R809	VE-30007784	MO RES.	5W 33K J (RADIAL)
R810	VE-30001257	MG RES.	1/2W 4.7M J
R811	VE-30000718	CF RES.	1/4W 4.7K J
R812	VE-30012641	SMD RES.	1/16W 10K J
R813	VE-30000466	CF RES.	1/4W 1K J
R814	VE-30000466	CF RES.	1/4W 1K J
R817	VE-30000880	MF RES.	1/4W 130K F
R818	VE-30012675	SMD RES.	1/16W 2K J
R819	VE-30000526	CF RES.	1/4W 1.5K J
R828	VE-30000530	CF RES.	1/2W 15K J
R829	VE-30000530	CF RES.	1/2W 15K J
R834	VE-30001159	MO RES.	1W 0.33R J
R836	VE-30012662	SMD RES.	1/16W 2.7K J
R839	VE-30000526	CF RES.	1/4W 1.5K J
R842	VE-30014128	SMD RES.	1/16W 33R J
R844	VE-30012641	SMD RES.	1/16W 10K J
R845	VE-30012509	SMD RES.	1/16W 100K J
R846	VE-30012692	SMD RES.	1/16W 4.7K J
R847	VE-30014128	SMD RES.	1/16W 33R J
R848	VE-30012641	SMD RES.	1/16W 10K J
R849	VE-30012510	SMD RES.	1/16W 100R J
R851	VE-30000718	CF RES.	1/4W 4.7K J
R852	VE-30000650	CF RES.	1/4W 33R J
R853	VE-30012642	SMD RES.	1/16W 120K J
R855	VE-30000459	CF RES.	1/4W 100R J
R856	VE-30012694	SMD RES.	1/16W 470K J
R857	VE-30001263	WW RES.	5W 3.9R J (RAD)

CAPACITOR

C141	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C142	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C143	VE-30012589	SMD CAP.	4.7NF 50V K
C144	VE-30012589	SMD CAP.	4.7NF 50V K
C145	VE-30012589	SMD CAP.	4.7NF 50V K
C146	VE-30012589	SMD CAP.	4.7NF 50V K
C147	VE-30012589	SMD CAP.	4.7NF 50V K
C148	VE-30012589	SMD CAP.	4.7NF 50V K
C149	VE-30012589	SMD CAP.	4.7NF 50V K
C150	VE-30012589	SMD CAP.	4.7NF 50V K
C155	VE-30012560	SMD CAP.	100PF 50V J
C157	VE-30012560	SMD CAP.	100PF 50V J
C159	VE-30000352	EL CAP.	100UF 16V M
C160	VE-30000345	EL CAP.	10UF 50V M
C161	VE-30000345	EL CAP.	10UF 50V M

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C162	VE-30012573	SMD CAP.	47PF 50V J
C164	VE-30012692	SMD RES.	1/16W 4.7K J
C165	VE-30000413	EL CAP.	4.7UF 50V M
C201	VE-30000400	EL CAP.	47UF 50V M
C205	VE-30000345	EL CAP.	10UF 50V M
C206	VE-30012610	SMD CAP.	10NF 50V J
C207	VE-30012610	SMD CAP.	10NF 50V J
C230	VE-30016654	SMD CAP.	100NF 16V K R
C246	VE-30000295	CER CAP.	100NF 50V Z F
C303	VE-30000100	MKT CAP.	330NF 63V J
C305	VE-30012590	SMD CAP.	47NF 50V K
C310	VE-30000345	EL CAP.	10UF 50V M
C333	VE-30000083	MKT CAP.	150NF 63V J
C363	VE-30000083	MKT CAP.	150NF 63V J
C364	VE-30012590	SMD CAP.	47NF 50V K
C366	VE-30000407	EL CAP.	470UF 16V M
C368	VE-30012590	SMD CAP.	47NF 50V K
C404	VE-30000190	CER CAP.	100PF 50V J CH
C408	VE-30012586	SMD CAP.	22NF 50V K
C409	VE-30000345	EL CAP.	10UF 50V M
C410	VE-30000384	EL CAP.	2.2UF 50V M
C411	VE-30000345	EL CAP.	10UF 50V M
C412	VE-30016654	SMD CAP.	100NF 16V K R
C413	VE-30000362	EL CAP.	1UF 50V M
C414	VE-30012585	SMD CAP.	2.2NF 50V K R
C415	VE-30012581	SMD CAP.	1NF 50V K R
C416	VE-30000362	EL CAP.	1UF 50V M
C417	VE-30000362	EL CAP.	1UF 50V M
C418	VE-30016654	SMD CAP.	100NF 16V K R
C419	VE-30000384	EL CAP.	2.2UF 50V M
C420	VE-30000100	MKT CAP.	330NF 63V J
C422	VE-30000352	EL CAP.	100UF 16V M
C423	VE-30000352	EL CAP.	100UF 16V M
C424	VE-30000352	EL CAP.	100UF 16V M
C425	VE-30016654	SMD CAP.	100NF 16V K R
C427	VE-30016654	SMD CAP.	100NF 16V K R
C429	VE-30012589	SMD CAP.	4.7NF 50V K
C430	VE-30016654	SMD CAP.	100NF 16V K R
C431	VE-30000362	EL CAP.	1UF 50V M
C432	VE-30016654	SMD CAP.	100NF 16V K R
C433	VE-30000345	EL CAP.	10UF 50V M
C434	VE-30016654	SMD CAP.	100NF 16V K R
C435	VE-30016654	SMD CAP.	100NF 16V K R
C436	VE-30000109	MKT CAP.	470NF 63V J
C437	VE-30016654	SMD CAP.	100NF 16V K R
C438	VE-30016654	SMD CAP.	100NF 16V K R
C439	VE-30016654	SMD CAP.	100NF 16V K R
C440	VE-30000295	CER CAP.	100NF 50V Z F
C441	VE-30012582	SMD CAP.	10NF 50V K R
C442	VE-30000109	MKT CAP.	470NF 63V J
C443	VE-30000362	EL CAP.	1UF 50V M
C444	VE-30000384	EL CAP.	2.2UF 50V M
C448	VE-30012586	SMD CAP.	22NF 50V K
C449	VE-30012560	SMD CAP.	100PF 50V J
C453	VE-30000352	EL CAP.	100UF 16V M
C455	VE-30000345	EL CAP.	10UF 50V M
C459	VE-30012560	SMD CAP.	100PF 50V J
C501	VE-30016654	SMD CAP.	100NF 16V K R
C502	VE-30000400	EL CAP.	47UF 50V M
C504	VE-30016654	SMD CAP.	100NF 16V K R
C505	VE-30012589	SMD CAP.	4.7NF 50V K
C507	VE-30000345	EL CAP.	10UF 50V M
C510	VE-30016654	SMD CAP.	100NF 16V K R
C511	VE-30012566	SMD CAP.	22PF 50V J
C513	VE-30000345	EL CAP.	10UF 50V M
C514	VE-30016654	SMD CAP.	100NF 16V K R
C515	VE-30012560	SMD CAP.	100PF 50V J
C517	VE-30016654	SMD CAP.	100NF 16V K R
C518	VE-30016654	SMD CAP.	100NF 16V K R
C519	VE-30012560	SMD CAP.	100PF 50V J
C520	VE-30012560	SMD CAP.	100PF 50V J
C521	VE-30012562	SMD CAP.	15PF 50V J
C522	VE-30012562	SMD CAP.	15PF 50V J
C523	VE-30012585	SMD CAP.	2.2NF 50V K R
C524	VE-30012566	SMD CAP.	22PF 50V J
C525	VE-30012566	SMD CAP.	22PF 50V J
C526	VE-30016654	SMD CAP.	100NF 16V K R
C527	VE-30000345	EL CAP.	10UF 50V M
C529	VE-30012589	SMD CAP.	4.7NF 50V K
C530	VE-30012589	SMD CAP.	4.7NF 50V K
C532	VE-30016654	SMD CAP.	100NF 16V K R
C536	VE-30000295	CER CAP.	100NF 50V Z F
C541	VE-30000362	EL CAP.	1UF 50V M

[AV-29BF11ENS]

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C542	VE-30000107	MKT CAP.	47NF 250V J
C543	VE-30000431	CER CAP.	100PF 1KV M
C544	VE-30000345	EL CAP.	10UF 50V M
C547	VE-30000345	EL CAP.	10UF 50V M
C565	VE-30016654	SMD CAP.	100NF 16V K R
C566	VE-30016654	SMD CAP.	100NF 16V K R
C567	VE-30000431	CER CAP.	100PF 1KV M
C602	VE-30017319	MKT CAP.	120NF 63V J
C604	VE-30000356	EL CAP.	100UF 63V M
C605	VE-30000356	EL CAP.	1000UF 25V M
C607	VE-30012581	SMD CAP.	1NF 50V K R
△ C618	VE-30000168	MKT CAP.	6.2NF 1.6KV 3.5%
△ C621	VE-30000136	MKT CAP.	12NF 2000V 3.5%
C622	VE-30012003	MKT CAP.	18NF 630V J
C623	VE-30000406	EL CAP.	47UF 250V M (HR)
△ C625	VE-30000177	MKT CAP.	820NF 250V J
C627	VE-30000162	MKT CAP.	470NF 250V J
C629	VE-30013003	MKT CAP.	1UF 250V J P-15
C632	VE-30000100	MKT CAP.	330NF 63V J
C635	VE-30000385	EL CAP.	2.2UF 250V M
C636	VE-30000387	EL CAP.	33UF 50V M
C640	VE-30000100	MKT CAP.	330NF 63V J
C641	VE-30000090	MKT CAP.	22NF 100V J
C642	VE-30000407	EL CAP.	470UF 16V M
C644	VE-30000409	EL CAP.	470UF 25V M
C645	VE-30000090	MKT CAP.	22NF 100V J
C646	VE-30000100	MKT CAP.	330NF 63V J
C647	VE-30007748	EL CAP.	1000UF 35V M
C648	VE-30000394	EL CAP.	3.3UF 160V M
C649	VE-30000295	CER CAP.	100NF 50V Z F
C652	VE-30000330	CER CAP.	4.7NF 50V K B
C653	VE-30000107	MKT CAP.	47NF 250V J
C700	VE-30012565	SMD CAP.	1.8PF 50V J CH
C701	VE-30012565	SMD CAP.	1.8PF 50V J CH
C702	VE-30012576	SMD CAP.	56PF 50V J CH
C703	VE-30012576	SMD CAP.	56PF 50V J CH
C704	VE-30012576	SMD CAP.	56PF 50V J CH
C705	VE-30000345	EL CAP.	10UF 50V M
C706	VE-30000345	EL CAP.	10UF 50V M
C708	VE-30016654	SMD CAP.	100NF 16V K R
C712	VE-30000345	EL CAP.	10UF 50V M
C713	VE-30016654	SMD CAP.	100NF 16V K R
C714	VE-30000100	MKT CAP.	330NF 63V J
C716	VE-30000100	MKT CAP.	330NF 63V J
C717	VE-30000100	MKT CAP.	330NF 63V J
C718	VE-30000100	MKT CAP.	330NF 63V J
C719	VE-30016654	SMD CAP.	100NF 16V K R
C720	VE-30000345	EL CAP.	10UF 50V M
C721	VE-30000100	MKT CAP.	330NF 63V J
C723	VE-30000100	MKT CAP.	330NF 63V J
C724	VE-30000345	EL CAP.	10UF 50V M
C729	VE-30016654	SMD CAP.	100NF 16V K R
C730	VE-30000393	EL CAP.	3.3UF 50V M
C733	VE-30000345	EL CAP.	10UF 50V M
C734	VE-30000345	EL CAP.	10UF 50V M
C735	VE-30016654	SMD CAP.	100NF 16V K R
C736	VE-30000345	EL CAP.	10UF 50V M
C737	VE-30000384	EL CAP.	2.2UF 50V M
C738	VE-30000384	EL CAP.	2.2UF 50V M
C739	VE-30000384	EL CAP.	2.2UF 50V M
C740	VE-30000384	EL CAP.	2.2UF 50V M
C741	VE-30012589	SMD CAP.	4.7NF 50V K
C742	VE-30012589	SMD CAP.	4.7NF 50V K
C745	VE-30016654	SMD CAP.	100NF 16V K R
△ C801	VE-30000094	MKT CAP.	220NF AC275V M
△ C802	VE-30000094	MKT CAP.	220NF AC275V M
△ C803	VE-30000433	CER CAP.	1NF 1KV M B
△ C804	VE-30000433	CER CAP.	1NF 1KV M B
C808	VE-30012590	SMD CAP.	47NF 50V K
C809	VE-30000421	EL CAP.	220UF 400V M (FOR 28'')
C810	VE-30000387	EL CAP.	33UF 50V M
C811	VE-30000161	MKT CAP.	47NF 630V J
C812	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
△ C816	VE-30000440	CER CAP.	2.2NF 4KV M
C817	VE-30000198	CER CAP.	120PF 500V J SL
C818	VE-30012590	SMD CAP.	47NF 50V K
C819	VE-30012590	SMD CAP.	47NF 50V K
C822	VE-30007308	CER CAP.	220PF 1KV K (PULSE)
C826	VE-30000406	EL CAP.	47UF 250V M (HR)
C827	VE-30000411	EL CAP.	4700UF 16V M
C828	VE-30012590	SMD CAP.	47NF 50V K
C829	VE-30000407	EL CAP.	470UF 16V M
C830	VE-30000383	EL CAP.	2200UF 25V M

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C832	VE-30012590	SMD CAP.	47NF 50V K
C833	VE-30000407	EL CAP.	470UF 16V M
C834	VE-30012590	SMD CAP.	47NF 50V K
C835	VE-30012590	SMD CAP.	47NF 50V K
C838	VE-30000407	EL CAP.	470UF 16V M
C839	VE-30000407	EL CAP.	470UF 16V M
C840	VE-30000407	EL CAP.	470UF 16V M
C848	VE-30000407	EL CAP.	470UF 16V M
C850	VE-30000383	EL CAP.	2200UF 25V M
C851	VE-30012590	SMD CAP.	47NF 50V K
△ C852	VE-30000440	CER CAP.	2.2NF 4KV M
C857	VE-30000106	MKT CAP.	47NF 100V J
C858	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
C859	VE-30009208	CER CAP.	470PF 1KV K (PULSE)
C860	VE-30000296	CER CAP.	100NF 100V Z F
C872	VE-30007708	CER CAP.	1NF 1KV K (PULSE)

TRANSF

TR600	VE-30002090	LINE DRIVER
△ TR601	VE-30017522	FBT TRF
△ TR802	VE-30018785	SMPS TRF

COIL

L101	VE-30001971	FERRITE BEAT
L102	VE-30001971	FERRITE BEAT
L106	VE-30001971	FERRITE BEAT
L108	VE-30001971	FERRITE BEAT
L109	VE-30001971	FERRITE BEAT
L110	VE-30001971	FERRITE BEAT
L111	VE-30001971	FERRITE BEAT
L112	VE-30001971	FERRITE BEAT
L113	VE-30001971	FERRITE BEAT
L114	VE-30001971	FERRITE BEAT
L115	VE-30001971	FERRITE BEAT
L116	VE-30001971	FERRITE BEAT
L117	VE-30001971	FERRITE BEAT
L201	VE-30001979	FIXED COIL
L210	VE-30001971	FERRITE BEAT
L215	VE-30001971	FERRITE BEAT
L401	VE-30001971	FERRITE BEAT
L402	VE-30001992	FIXED COIL
L403	VE-30001971	FERRITE BEAT
L405	VE-30014048	ADJ. COIL
L406	VE-30001971	FERRITE BEAT
L408	VE-30001992	FIXED COIL
L501	VE-30001971	FERRITE BEAT
L502	VE-30001971	FERRITE BEAT
L503	VE-30001971	FERRITE BEAT
L504	VE-30001971	FERRITE BEAT
L600	VE-30002031	FIXED COIL
L602	VE-30017085	LINEARITY COIL
L603	VE-30016083	FIXED COIL
L700	VE-30001971	FERRITE BEAT
L701	VE-30001971	FERRITE BEAT
L702	VE-30001992	FIXED COIL
L703	VE-30001971	FERRITE BEAT
L704	VE-30001971	FERRITE BEAT
L801	VE-30002011	COIL CHOKE
L803	VE-30001992	FIXED COIL

DIODE

D101	VE-30007760	ZENER DIODE
D104	VE-30007760	ZENER DIODE
D105	VE-30007760	ZENER DIODE
D106	VE-30007760	ZENER DIODE
D107	VE-30007760	ZENER DIODE
D303	VE-30001329	DIODE
D405	VE-30007763	ZENER DIODE
D407	VE-30001284	DIODE
D408	VE-30001285	DIODE
D409	VE-30001284	DIODE
D413	VE-30018526	ZENER DIODE
D501	VE-30001285	DIODE
D505	VE-30001285	DIODE
D506	VE-30001284	DIODE
D512	VE-30001285	DIODE
D513	VE-30001369	ZENER DIODE

[AV-29BF11ENS]

△ Symbol No.	Part No.	Part Name	Description	△ Symbol No.	Part No.	Part Name	Description
DIODE				OTHERS			
D533	VE-30001377	ZENER DIODE		△ F801	VE-30001731	FUSE	2.5A 250V 5*20MM
D601	VE-30001329	DIODE		△ TH800	VE-30001270	PTC	9 OHM
D603	VE-30001285	DIODE		△ TR801	VE-30002104	LINE FILTER	
D605	VE-30001320	DIODE		TU201	VE-30009637	TUNER	WSP (PLL) 38.9 MK2 - BATC
D606	VE-30007681	DIODE		X401	VE-30001749	XTAL	
D609	VE-30001318	DIODE		X402	VE-30015592	XTAL	
D610	VE-30001318	DIODE		X501	VE-30002851	XTAL	
D613	VE-30001318	DIODE		X700	VE-30001756	XTAL	
D614	VE-30001285	DIODE		Z401	VE-30001705	SAW FILTER	
D616	VE-30003696	DIODE		Z402	VE-30015591	SAW FILTER	
D617	VE-30001318	DIODE			VE-30001964	FERRITE BAR	
D651	VE-30001285	DIODE					
D653	VE-30001285	DIODE					
D657	VE-30007763	ZENER DIODE					
D658	VE-30007763	ZENER DIODE					
D659	VE-30001350	ZENER DIODE					
D661	VE-30001350	ZENER DIODE					
D700	VE-30001285	DIODE					
D701	VE-30001369	ZENER DIODE					
D800	VE-30001318	DIODE					
D801	VE-30001372	ZENER DIODE					
D802	VE-30001318	DIODE					
D803	VE-30001315	DIODE					
D804	VE-30001318	DIODE					
D805	VE-30001315	DIODE					
D806	VE-30001315	DIODE					
D808	VE-20092405	CN. ASY.	UF5407+FERRITE				
D809	VE-30001329	DIODE					
D810	VE-30009366	DIODE					
D811	VE-30009366	DIODE					
D812	VE-30001285	DIODE					
△ D889	VE-30001384	TR					
D891	VE-30007758	DIODE					
D892	VE-30001318	DIODE					
D893	VE-30001318	DIODE					
D894	VE-30001285	DIODE					
D897	VE-30001329	DIODE					
TRANSISTOR							
Q104	VE-30001457	TR					
Q106	VE-30001457	TR					
Q141	VE-30001457	TR					
Q142	VE-30001457	TR					
Q307	VE-30001457	TR					
Q316	VE-30001458	TR					
Q403	VE-30001457	TR					
Q404	VE-30001457	TR					
Q503	VE-30001457	TR					
Q504	VE-30001458	TR					
△ Q600	VE-30001435	TR					
Q601	VE-30001441	TR					
Q602	VE-30001429	TR					
Q603	VE-30001458	TR					
Q604	VE-30001457	TR					
Q605	VE-30001458	TR					
Q700	VE-30001458	TR					
Q801	VE-30001386	TR					
Q802	VE-30001457	TR					
Q804	VE-30001454	TR					
IC							
IC301	VE-30016113	IC					
IC403	VE-30014521	IC					
IC500	VE-20103251	IC	(SERVICE)				
IC501	VE-20093395	PR. IC.	(MICOM)				
IC601	VE-30013985	IC					
IC700	VE-30013658	IC					
IC800	VE-30011968	IC					
△ IC801	VE-30015087	IC					
IC802	VE-30001622	IC					
IC803	VE-30001500	IC					
IC804	VE-30001622	IC					
IC818	VE-30001506	IC					

[AV-29BF11ENS]

CRT SOCKET P.W. BOARD ASS'Y
(VE-20094670 : Common to all models)

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R900	VE-30000788	CF RES.	1/4W 6.8M J
R902	VE-30000459	CF RES.	1/4W 100R J
R903	VE-30000459	CF RES.	1/4W 100R J
R904	VE-30000459	CF RES.	1/4W 100R J
R906	VE-30000535	CF RES.	1/2W 150K J
R907	VE-30000477	CF RES.	1/4W 100K J
R908	VE-30000477	CF RES.	1/4W 100K J
R909	VE-30000525	CF RES.	1/2W 1.5K J
R910	VE-30000525	CF RES.	1/2W 1.5K J
R911	VE-30000525	CF RES.	1/2W 1.5K J
R912	VE-30000477	CF RES.	1/4W 100K J
R913	VE-30000525	CF RES.	1/2W 1.5K J
R914	VE-30001084	MO RES.	1W 1K J
R916	VE-30001170	MO RES.	1W 4.7K J
R917	VE-30001208	FUSE RES.	1W 10R J
R918	VE-30000471	CF RES.	1/4W 10K J
R921	VE-30000599	CF RES.	1/4W 220K J
R922	VE-30000590	CF RES.	1/4W 2.2K J

CAPACITOR

C900	VE-30000075	MKT CAP.	100NF 250V K (DC)
C902	VE-30000415	EL CAP.	4.7UF 250V M
C903	VE-30000438	CER CAP.	2.2NF 2KV
C904	VE-30000295	CER CAP.	100NF 50V Z F
C905	VE-30000234	CER CAP.	270PF 50V J SL
C906	VE-30000350	EL CAP.	10UF 250V M
C907	VE-30000075	MKT CAP.	100NF 250V K (DC)
C909	VE-30000385	EL CAP.	2.2UF 250V M
C910	VE-30000438	CER CAP.	2.2NF 2KV
C911	VE-30000433	CER CAP.	1NF 1KV M B

COIL

L900	VE-30002170	FTZ/RAD COIL	
------	-------------	--------------	--

DIODE

D901	VE-30001329	DIODE	
D902	VE-30001318	DIODE	
D903	VE-30001329	DIODE	
D904	VE-30001329	DIODE	
D905	VE-30001284	DIODE	
D906	VE-30001284	DIODE	
D907	VE-30001284	DIODE	
D908	VE-30001284	DIODE	
D909	VE-30001344	ZENER DIODE	
NOT1	VE-30001329	DIODE	

TRANSISTOR

Q900	VE-30001427	TR	
Q901	VE-30001454	TR	

IC

IC900	VE-30008721	IC	
-------	-------------	----	--

OTHERS

△ PL900	VE-30001855	CRT SOCKET	
SG901	VE-30000428	SPARK GAP	300V
SG902	VE-30000428	SPARK GAP	300V
SG903	VE-30000428	SPARK GAP	300V
SG904	VE-30000428	SPARK GAP	300V
	VE-20000954	HE. ASY.	CONTAINS HEATSINK+IC900

FRONT AV & HEADPHONE P.W. BOARD ASS'Y
(VE-20083646 : Common to all models)

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R107	VE-30000594	CF RES.	1/4W 22K J
R108	VE-30000712	CF RES.	1/4W 470R J
R109	VE-30000594	CF RES.	1/4W 22K J
R110	VE-30000712	CF RES.	1/4W 470R J
R113	VE-30000744	CF RES.	1/4W 560R J
R114	VE-30000744	CF RES.	1/4W 560R J
R115	VE-30000712	CF RES.	1/4W 470R J
R116	VE-30000712	CF RES.	1/4W 470R J

CAPACITOR

C103	VE-30000213	CER CAP.	180PF 50V J CH
C104	VE-30000213	CER CAP.	180PF 50V J CH
C106	VE-30000190	CER CAP.	100PF 50V J CH

TRANSF

T103	VE-30001962	FERRITE	
T104	VE-30001963	FERRITE	
T107	VE-30001963	FERRITE	

COIL

L103	VE-30001996	FIXED COIL	22UH Q40 K
L104	VE-30001996	FIXED COIL	22UH Q40 K

OTHERS

CON102	VE-30001893	RCA JACK	
CON103	VE-30001891	RCA JACK	
CON104	VE-30001892	RCA JACK	
CON106	VE-30001900	HEADPHONE JACK	HP01/2/3/4/5/6

FRONT CONTROL P.W. BOARD ASS'Y
(VE-20100168 : Common to all models)

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R1	VE-30000689	CF RES.	1/4W 3.9K J
R2	VE-30000526	CF RES.	1/4W 1.5K J
R3	VE-30000770	CF RES.	1/4W 680R J
R4	VE-30000712	CF RES.	1/4W 470R J
R5	VE-30000623	CF RES.	1/4W 270R G

CAPACITOR

C1	VE-30000295	CER CAP.	100NF 50V Z F
----	-------------	----------	---------------

OTHERS

LD102	VE-30001279	LED RED/GREEN	
MD101	VE-30001670	PREAMPLIFIER	
PL1	VE-30002302	CONN. ASSY.	6/45 FC (CRT)
S101	VE-30002181	SWITCH TACT	P+
S102	VE-30002181	SWITCH TACT	P-
S103	VE-30002181	SWITCH TACT	V-
S104	VE-30002181	SWITCH TACT	V+
S105	VE-30002181	SWITCH TACT	MENU

PRINTED WIRING BOARD PARTS LIST

[AV-29BF11EPS]

MAIN P.W. BOARD ASS'Y (VE-20103267)

△ Symbol No.	Part No.	Part Name	Description
VARIABLE RESISTOR			
VR800	VE-30001064	ADJ RES	1/10W 470R VER (MAN)
RESISTOR			
R102	VE-30012657	SMD RES.	1/16W 1K J
R103	VE-30012657	SMD RES.	1/16W 1K J
R106	VE-30012713	SMD RES.	1/16W 75R J
R107	VE-30012649	SMD RES.	1/16W 150R J
R109	VE-30012713	SMD RES.	1/16W 75R J
R110	VE-30012713	SMD RES.	1/16W 75R J
R111	VE-30012649	SMD RES.	1/16W 150R J
R113	VE-30012713	SMD RES.	1/16W 75R J
R114	VE-30012713	SMD RES.	1/16W 75R J
R115	VE-30012713	SMD RES.	1/16W 75R J
R117	VE-30000792	CF RES.	1/4W 75R J
R118	VE-30012713	SMD RES.	1/16W 75R J
R121	VE-30012649	SMD RES.	1/16W 150R J
R122	VE-30000792	CF RES.	1/4W 75R J
R123	VE-30000792	CF RES.	1/4W 75R J
R124	VE-30012649	SMD RES.	1/16W 150R J
R126	VE-30012657	SMD RES.	1/16W 1K J
R129	VE-30012713	SMD RES.	1/16W 75R J
R135	VE-30012657	SMD RES.	1/16W 1K J
R137	VE-30000466	CF RES.	1/4W 1K J
R138	VE-30012657	SMD RES.	1/16W 1K J
R139	VE-30012713	SMD RES.	1/16W 75R J
R141	VE-30012657	SMD RES.	1/16W 1K J
R145	VE-30012713	SMD RES.	1/16W 75R J
R149	VE-30012703	SMD RES.	1/16W 56K J
R151	VE-30012696	SMD RES.	1/16W 47K J
R152	VE-30000752	CF RES.	1/4W 56K J
R153	VE-30012657	SMD RES.	1/16W 1K J
R154	VE-30000723	CF RES.	1/4W 47K J
R155	VE-30012649	SMD RES.	1/16W 150R J
R169	VE-30012703	SMD RES.	1/16W 56K J
R171	VE-30012713	SMD RES.	1/16W 75R J
R172	VE-30012692	SMD RES.	1/16W 4.7K J
R174	VE-30012713	SMD RES.	1/16W 75R J
R175	VE-30012713	SMD RES.	1/16W 75R J
R176	VE-30012703	SMD RES.	1/16W 56K J
R201	VE-30012674	SMD RES.	1/16W 27K J
R202	VE-30012692	SMD RES.	1/16W 4.7K J
R204	VE-30000459	CF RES.	1/4W 100R J
R206	VE-30000459	CF RES.	1/4W 100R J
R319	VE-30014076	SMD RES.	1/16W 4.7R J
R320	VE-30014076	SMD RES.	1/16W 4.7R J
R324	VE-30012667	SMD RES.	1/16W 220K J
R328	VE-30012649	SMD RES.	1/16W 150R J
R329	VE-30012692	SMD RES.	1/16W 4.7K J
R332	VE-30012641	SMD RES.	1/16W 10K J
R333	VE-30012702	SMD RES.	1/16W 560R J
R338	VE-30012641	SMD RES.	1/16W 10K J
R340	VE-30012644	SMD RES.	1/16W 12K J
R341	VE-30012702	SMD RES.	1/16W 560R J
R343	VE-30012659	SMD RES.	1/16W 2.2K J
R370	VE-30012669	SMD RES.	1/16W 22K J
R371	VE-30012669	SMD RES.	1/16W 22K J
R391	VE-30012696	SMD RES.	1/16W 47K J
R402	VE-30012692	SMD RES.	1/16W 4.7K J
R407	VE-30000590	CF RES.	1/4W 2.2K J
R412	VE-30000723	CF RES.	1/4W 47K J
R417	VE-30012510	SMD RES.	1/16W 100R J
R418	VE-30012510	SMD RES.	1/16W 100R J
R419	VE-30012649	SMD RES.	1/16W 150R J
R420	VE-30000466	CF RES.	1/4W 1K J
R421	VE-30012650	SMD RES.	1/16W 15K J
R422	VE-30012659	SMD RES.	1/16W 2.2K J
R423	VE-30012712	SMD RES.	1/16W 8.2K J
R425	VE-30012510	SMD RES.	1/16W 100R J
R426	VE-30012659	SMD RES.	1/16W 2.2K J
R427	VE-30012674	SMD RES.	1/16W 27K J
R428	VE-30012510	SMD RES.	1/16W 560R J
R430	VE-30012702	SMD RES.	1/16W 560R J
R431	VE-30012674	SMD RES.	1/16W 27K J
R432	VE-30012707	SMD RES.	1/16W 680R J
R433	VE-30012683	SMD RES.	1/16W 330K J
R437	VE-30000466	CF RES.	1/4W 1K J
R438	VE-30000466	CF RES.	1/4W 1K J
R439	VE-30012657	SMD RES.	1/16W 1K J
R440	VE-30012714	SMD RES.	1/16W 820R J

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R441	VE-30012674	SMD RES.	1/16W 27K J
R442	VE-30000466	CF RES.	1/4W 1K J
R446	VE-30012714	SMD RES.	1/16W 820R J
R447	VE-30012714	SMD RES.	1/16W 820R J
R448	VE-30012683	SMD RES.	1/16W 330K J
R450	VE-30012702	SMD RES.	1/16W 560R J
R458	VE-30012510	SMD RES.	1/16W 100R J
R459	VE-30012668	SMD RES.	1/16W 220R J
R460	VE-30012668	SMD RES.	1/16W 220R J
R461	VE-30012668	SMD RES.	1/16W 220R J
R449	VE-30012659	SMD RES.	1/16W 2.2K J
R462	VE-30012510	SMD RES.	1/16W 100R J
R467	VE-30000670	CF RES.	1/4W 330K J
R468	VE-30000670	CF RES.	1/4W 330K J
R469	VE-30000628	CF RES.	1/4W 2.7K J
R471	VE-30014022	SMD RES.	1/16W 47R J
R472	VE-30012662	SMD RES.	1/16W 2.7K J
R474	VE-30012662	SMD RES.	1/16W 2.7K J
R481	VE-30000466	CF RES.	1/4W 1K J
R482	VE-30012657	SMD RES.	1/16W 1K J
R483	VE-30012657	SMD RES.	1/16W 1K J
R485	VE-30012657	SMD RES.	1/16W 1K J
R486	VE-30012657	SMD RES.	1/16W 1K J
R487	VE-30012657	SMD RES.	1/16W 1K J
R507	VE-30000466	CF RES.	1/4W 1K J
R508	VE-30012510	SMD RES.	1/16W 100R J
R509	VE-30012641	SMD RES.	1/16W 10K J
R510	VE-30012702	SMD RES.	1/16W 560R J
R511	VE-30012657	SMD RES.	1/16W 1K J
R512	VE-30000495	CF RES.	1/4W 1.2K J
R513	VE-30000459	CF RES.	1/4W 100R J
R514	VE-30000459	CF RES.	1/4W 100R J
R515	VE-30012659	SMD RES.	1/16W 2.2K J
R516	VE-30012659	SMD RES.	1/16W 2.2K J
R517	VE-30012692	SMD RES.	1/16W 4.7K J
R518	VE-30000471	CF RES.	1/4W 10K J
R519	VE-30012698	SMD RES.	1/16W 5.6K J
R525	VE-30012649	SMD RES.	1/16W 150R J
R526	VE-30012641	SMD RES.	1/16W 10K J
R527	VE-30012692	SMD RES.	1/16W 4.7K J
R528	VE-30012698	SMD RES.	1/16W 5.6K J
R529	VE-30012698	SMD RES.	1/16W 5.6K J
R530	VE-30012698	SMD RES.	1/16W 5.6K J
R532	VE-30012659	SMD RES.	1/16W 2.2K J
R533	VE-30012644	SMD RES.	1/16W 12K J
R534	VE-30000628	CF RES.	1/4W 2.7K J
R537	VE-30012641	SMD RES.	1/16W 10K J
R538	VE-30012698	SMD RES.	1/16W 5.6K J
R539	VE-30012659	SMD RES.	1/16W 2.2K J
R540	VE-30012644	SMD RES.	1/16W 12K J
R545	VE-30012644	SMD RES.	1/16W 12K J
R548	VE-30012641	SMD RES.	1/16W 10K J
R552	VE-30012692	SMD RES.	1/16W 4.7K J
R554	VE-30012641	SMD RES.	1/16W 10K J
R555	VE-30012659	SMD RES.	1/16W 2.2K J
R556	VE-30012657	SMD RES.	1/16W 1K J
R560	VE-30012674	SMD RES.	1/16W 27K J
R561	VE-30012692	SMD RES.	1/16W 4.7K J
R568	VE-30000594	CF RES.	1/4W 22K J
R572	VE-30012659	SMD RES.	1/16W 2.2K J
R573	VE-30012641	SMD RES.	1/16W 10K J
R574	VE-30012657	SMD RES.	1/16W 1K J
R603	VE-30000459	CF RES.	1/4W 100R J
R604	VE-30012510	SMD RES.	1/16W 100R J
R606	VE-30000471	CF RES.	1/4W 10K J
R607	VE-30000554	CF RES.	1/4W 180R J
R608	VE-30000859	MF RES.	1/2W 1R F
R609	VE-30000711	CF RES.	1/2W 470R J
R610	VE-30000599	CF RES.	1/4W 220K J
R611	VE-30012708	SMD RES.	1/16W 68K J
R616	VE-30012685	SMD RES.	1/16W 33K J
R617	VE-30000572	CF RES.	1/4W 2K J
R630	VE-30012702	SMD RES.	1/16W 560R J
R634	VE-30000633	CF RES.	1/4W 27K J
R639	VE-30000471	CF RES.	1/4W 10K J
R640	VE-30000628	CF RES.	1/4W 2.7K J
R646	VE-30000775	CF RES.	1/4W 6.8K J
R647	VE-30000466	CF RES.	1/4W 1K J
△ R648	VE-30001246	FUSE RES.	1W 0.47R J
R650	VE-30012702	SMD RES.	1/16W 560R J
R651	VE-30012668	SMD RES.	1/16W 220R J

[AV-29BF11EPS]

△ Symbol No. Part No. Part Name Description

RESISTOR

△ R656	VE-30001247	FUSE RES.	1/2W 4.7K J
△ R657	VE-30001228	FUSE RES.	1/2W 2.2K J
R662	VE-30012674	SMD RES.	1/16W 27K J
R666	VE-30000531	CF RES.	1/4W 15K J
R668	VE-30000607	CF RES.	1/4W 2.2K J
R669	VE-30012510	SMD RES.	1/16W 100R J
R670	VE-30012510	SMD RES.	1/16W 100R J
R677	VE-30001124	MO RES.	3W 220R J
R678	VE-30014022	SMD RES.	1/16W 47R J
R680	VE-30000477	CF RES.	1/4W 100K J
R681	VE-30012509	SMD RES.	1/16W 100K J
R674	VE-30012662	SMD RES.	1/16W 2.7K J
△ R675	VE-30001208	FUSE RES.	1W 10R J
R682	VE-30017082	WW RES.	5W 75R J RAD.
R683	VE-30017083	WW RES.	5W 2.2K J RAD.
R689	VE-30000718	CF RES.	1/4W 4.7K J
R690	VE-30000466	CF RES.	1/4W 1K J
R691	VE-30012696	SMD RES.	1/16W 47K J
R692	VE-30012509	SMD RES.	1/16W 100K J
R693	VE-30012708	SMD RES.	1/16W 68K J
R694	VE-30000689	CF RES.	1/4W 3.9K J
R695	VE-30000775	CF RES.	1/4W 6.8K J
R696-Y	VE-30001350	ZENER DIODE	12V
R697	VE-30000712	CF RES.	1/4W 470R J
R698	VE-30012657	SMD RES.	1/16W 1K J
R700	VE-30012649	SMD RES.	1/16W 150R J
R701	VE-30000459	CF RES.	1/4W 100R J
R703	VE-30000459	CF RES.	1/4W 100R J
R705	VE-30000459	CF RES.	1/4W 100R J
R715	VE-30012702	SMD RES.	1/16W 560R J
R717	VE-30012702	SMD RES.	1/16W 560R J
R719	VE-30012657	SMD RES.	1/16W 1K J
R721	VE-30012510	SMD RES.	1/16W 100R J
R722	VE-30012510	SMD RES.	1/16W 100R J
R723	VE-30012510	SMD RES.	1/16W 100R J
R724	VE-30012510	SMD RES.	1/16W 100R J
R801	VE-30000718	CF RES.	1/4W 4.7K J
R803	VE-30012659	SMD RES.	1/16W 2.2K J
R805	VE-30000650	CF RES.	1/4W 33R J
R806	VE-30000982	MF RES.	1/4W 4.7K J
R807	VE-30001173	MO RES.	1W 0.47R J
R809	VE-30007784	MO RES.	5W 33K J(RADIAL)
△ R810	VE-30001257	MG RES.	1/2W 4.7M J
R811	VE-30000718	CF RES.	1/4W 4.7K J
R812	VE-30012641	SMD RES.	1/16W 10K J
R813	VE-30000466	CF RES.	1/4W 1K J
R814	VE-30000466	CF RES.	1/4W 1K J
R817	VE-30000880	MF RES.	1/4W 130K F
R818	VE-30012675	SMD RES.	1/16W 2K J
R819	VE-30000526	CF RES.	1/4W 1.5K J
R828	VE-30000530	CF RES.	1/2W 15K J
R829	VE-30000530	CF RES.	1/2W 15K J
R834	VE-30001159	MO RES.	1W 0.33R J
R836	VE-30012662	SMD RES.	1/16W 2.7K J
R839	VE-30000526	CF RES.	1/4W 1.5K J
R842	VE-30014128	SMD RES.	1/16W 33R J
R844	VE-30012641	SMD RES.	1/16W 10K J
R845	VE-30012509	SMD RES.	1/16W 100K J
R846	VE-30012692	SMD RES.	1/16W 4.7K J
R847	VE-30014128	SMD RES.	1/16W 33R J
R848	VE-30012641	SMD RES.	1/16W 10K J
R849	VE-30012510	SMD RES.	1/16W 100R J
R851	VE-30000718	CF RES.	1/4W 4.7K J
R852	VE-30000650	CF RES.	1/4W 33R J
R853	VE-30012642	SMD RES.	1/16W 120K J
R855	VE-30000459	CF RES.	1/4W 100R J
R856	VE-30012694	SMD RES.	1/16W 470K J
R857	VE-30001263	WW RES.	5W 3.9R J (RAD)

CAPACITOR

C141	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C142	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C143	VE-30012589	SMD CAP.	4.7NF 50V K
C144	VE-30012589	SMD CAP.	4.7NF 50V K
C145	VE-30012589	SMD CAP.	4.7NF 50V K
C146	VE-30012589	SMD CAP.	4.7NF 50V K
C147	VE-30012589	SMD CAP.	4.7NF 50V K
C148	VE-30012589	SMD CAP.	4.7NF 50V K
C149	VE-30012589	SMD CAP.	4.7NF 50V K
C150	VE-30012589	SMD CAP.	4.7NF 50V K
C155	VE-30012560	SMD CAP.	100PF 50V J

△ Symbol No. Part No. Part Name Description

CAPACITOR

C157	VE-30012560	SMD CAP.	100PF 50V J
C159	VE-30000352	EL CAP.	100UF 16V M
C160	VE-30000345	EL CAP.	10UF 50V M
C161	VE-30000345	EL CAP.	10UF 50V M
C162	VE-30012573	SMD CAP.	47PF 50V J
C164	VE-30012692	SMD RES.	1/16W 4.7K J
C165	VE-30000413	EL CAP.	4.7UF 50V M
C201	VE-30000400	EL CAP.	47UF 50V M
C205	VE-30000345	EL CAP.	10UF 50V M
C206	VE-30012610	SMD CAP.	10NF 50V J
C207	VE-30012610	SMD CAP.	10NF 50V J
C230	VE-30016654	SMD CAP.	100NF 16V K R
C246	VE-30000295	CER CAP.	100NF 50V Z F
C303	VE-30000100	MKT CAP.	330NF 63V J
C305	VE-30012590	SMD CAP.	47NF 50V K
C310	VE-30000345	EL CAP.	10UF 50V M
C333	VE-30000083	MKT CAP.	150NF 63V J
C363	VE-30000083	MKT CAP.	150NF 63V J
C364	VE-30012590	SMD CAP.	47NF 50V K
C366	VE-30000407	EL CAP.	470UF 16V M
C368	VE-30012590	SMD CAP.	47NF 50V K
C404	VE-30000190	CER CAP.	100PF 50V J CH
C408	VE-30012586	SMD CAP.	22NF 50V K
C409	VE-30000345	EL CAP.	10UF 50V M
C410	VE-30000384	EL CAP.	2.2UF 50V M
C411	VE-30000345	EL CAP.	10UF 50V M
C412	VE-30016654	SMD CAP.	100NF 16V K R
C413	VE-30000362	EL CAP.	1UF 50V M
C414	VE-30012585	SMD CAP.	2.2NF 50V K R
C415	VE-30012581	SMD CAP.	1NF 50V K R
C416	VE-30000362	EL CAP.	1UF 50V M
C417	VE-30000362	EL CAP.	1UF 50V M
C418	VE-30016654	SMD CAP.	100NF 16V K R
C419	VE-30000384	EL CAP.	2.2UF 50V M
C420	VE-30000100	MKT CAP.	330NF 63V J
C422	VE-30000352	EL CAP.	100UF 16V M
C423	VE-30000352	EL CAP.	100UF 16V M
C424	VE-30000352	EL CAP.	100UF 16V M
C425	VE-30016654	SMD CAP.	100NF 16V K R
C427	VE-30016654	SMD CAP.	100NF 16V K R
C429	VE-30012589	SMD CAP.	4.7NF 50V K
C430	VE-30016654	SMD CAP.	100NF 16V K R
C431	VE-30000362	EL CAP.	1UF 50V M
C432	VE-30016654	SMD CAP.	100NF 16V K R
C433	VE-30000345	EL CAP.	10UF 50V M
C434	VE-30016654	SMD CAP.	100NF 16V K R
C435	VE-30016654	SMD CAP.	100NF 16V K R
C436	VE-30000109	MKT CAP.	470NF 63V J
C437	VE-30016654	SMD CAP.	100NF 16V K R
C438	VE-30016654	SMD CAP.	100NF 16V K R
C439	VE-30016654	SMD CAP.	100NF 16V K R
C440	VE-30000295	CER CAP.	100NF 50V Z F
C441	VE-30012582	SMD CAP.	10NF 50V K R
C442	VE-30000109	MKT CAP.	470NF 63V J
C443	VE-30000362	EL CAP.	1UF 50V M
C444	VE-30000384	EL CAP.	2.2UF 50V M
C446	VE-30000345	EL CAP.	10UF 50V M
C448	VE-30012586	SMD CAP.	22NF 50V K
C449	VE-30012560	SMD CAP.	100PF 50V J
C453	VE-30000352	EL CAP.	100UF 16V M
C455	VE-30000345	EL CAP.	10UF 50V M
C457	VE-30012560	SMD CAP.	100PF 50V J
C459	VE-30012560	SMD CAP.	100PF 50V J
C501	VE-30016654	SMD CAP.	100NF 16V K R
C502	VE-30000400	EL CAP.	47UF 50V M
C504	VE-30016654	SMD CAP.	100NF 16V K R
C505	VE-30012589	SMD CAP.	4.7NF 50V K
C507	VE-30000345	EL CAP.	10UF 50V M
C510	VE-30016654	SMD CAP.	100NF 16V K R
C511	VE-30012566	SMD CAP.	22PF 50V J
C513	VE-30000345	EL CAP.	10UF 50V M
C514	VE-30016654	SMD CAP.	100NF 16V K R
C515	VE-30012560	SMD CAP.	100PF 50V J
C517	VE-30016654	SMD CAP.	100NF 16V K R
C518	VE-30016654	SMD CAP.	100NF 16V K R
C519	VE-30012560	SMD CAP.	100PF 50V J
C520	VE-30012560	SMD CAP.	100PF 50V J
C521	VE-30012562	SMD CAP.	15PF 50V J
C522	VE-30012562	SMD CAP.	15PF 50V J
C523	VE-30012585	SMD CAP.	2.2NF 50V K R
C524	VE-30012566	SMD CAP.	22PF 50V J
C525	VE-30012566	SMD CAP.	22PF 50V J
C526	VE-30016654	SMD CAP.	100NF 16V K R
C527	VE-30000345	EL CAP.	10UF 50V M

[AV-29BF11EPS]

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C529	VE-30012589	SMD CAP.	4.7NF 50V K
C530	VE-30012589	SMD CAP.	4.7NF 50V K
C532	VE-30016654	SMD CAP.	100NF 16V K R
C536	VE-30000295	CER CAP.	100NF 50V Z F
C541	VE-30000362	EL CAP.	1UF 50V M
C542	VE-30000107	MKT CAP.	47NF 250V J
C543	VE-30000431	CER CAP.	100PF 1KV M
C544	VE-30000345	EL CAP.	10UF 50V M
C547	VE-30000345	EL CAP.	10UF 50V M
C457	VE-30012560	SMD CAP.	100PF 50V J
C565	VE-30016654	SMD CAP.	100NF 16V K R
C566	VE-30016654	SMD CAP.	100NF 16V K R
C567	VE-30000431	CER CAP.	100PF 1KV M
C602	VE-30017319	MKT CAP.	120NF 63V J
C604	VE-30000356	EL CAP.	100UF 63V M
C605	VE-30000360	EL CAP.	100UF 25V M
C607	VE-30012581	SMD CAP.	1NF 50V K R
△ C618	VE-30000168	MKT CAP.	6.2NF 1.6KV 3.5%
△ C621	VE-30000136	MKT CAP.	12NF 2000V 3.5%
C622	VE-30012003	MKT CAP.	18NF 630V J
C623	VE-30000406	EL CAP.	47UF 250V M (HR)
△ C625	VE-30000177	MKT CAP.	820NF 250V J
C627	VE-30000162	MKT CAP.	470NF 250V J
C629	VE-30013003	MKT CAP.	1UF 250V J P=15
C632	VE-30000100	MKT CAP.	330NF 63V J
C635	VE-30000385	EL CAP.	2.2UF 250V M
C636	VE-30000387	EL CAP.	33UF 50V M
C640	VE-30000100	MKT CAP.	330NF 63V J
C641	VE-30000090	MKT CAP.	22NF 100V J
C642	VE-30000407	EL CAP.	470UF 16V M
C644	VE-30000409	EL CAP.	470UF 25V M
C645	VE-30000090	MKT CAP.	22NF 100V J
C646	VE-30000100	MKT CAP.	330NF 63V J
C647	VE-30007748	EL CAP.	1000UF 35V M
C648	VE-30000394	EL CAP.	3.3UF 160V M
C649	VE-30000295	CER CAP.	100NF 50V Z F
C652	VE-30000330	CER CAP.	4.7NF 50V K B
C653	VE-30000107	MKT CAP.	47NF 250V J
C700	VE-30012565	SMD CAP.	1.8PF 50V J CH
C701	VE-30012565	SMD CAP.	1.8PF 50V J CH
C702	VE-30012576	SMD CAP.	56PF 50V J CH
C703	VE-30012576	SMD CAP.	56PF 50V J CH
C704	VE-30012576	SMD CAP.	56PF 50V J CH
C705	VE-30000345	EL CAP.	10UF 50V M
C706	VE-30000345	EL CAP.	10UF 50V M
C708	VE-30016654	SMD CAP.	100NF 16V K R
C712	VE-30000345	EL CAP.	10UF 50V M
C713	VE-30016654	SMD CAP.	100NF 16V K R
C714	VE-30000100	MKT CAP.	330NF 63V J
C716	VE-30000100	MKT CAP.	330NF 63V J
C717	VE-30000100	MKT CAP.	330NF 63V J
C718	VE-30000100	MKT CAP.	330NF 63V J
C719	VE-30016654	SMD CAP.	100NF 16V K R
C720	VE-30000345	EL CAP.	10UF 50V M
C721	VE-30000100	MKT CAP.	330NF 63V J
C723	VE-30000100	MKT CAP.	330NF 63V J
C724	VE-30000345	EL CAP.	10UF 50V M
C729	VE-30016654	SMD CAP.	100NF 16V K R
C730	VE-30000393	EL CAP.	3.3UF 50V M
C733	VE-30000345	EL CAP.	10UF 50V M
C734	VE-30000345	EL CAP.	10UF 50V M
C735	VE-30016654	SMD CAP.	100NF 16V K R
C736	VE-30000345	EL CAP.	10UF 50V M
C737	VE-30000384	EL CAP.	2.2UF 50V M
C738	VE-30000384	EL CAP.	2.2UF 50V M
C739	VE-30000384	EL CAP.	2.2UF 50V M
C740	VE-30000384	EL CAP.	2.2UF 50V M
C741	VE-30012589	SMD CAP.	4.7NF 50V K
C742	VE-30012589	SMD CAP.	4.7NF 50V K
C745	VE-30016654	SMD CAP.	100NF 16V K R
△ C801	VE-30000094	MKT CAP.	220NF AC275V M
△ C802	VE-30000094	MKT CAP.	220NF AC275V M
△ C803	VE-30000433	CER CAP.	1NF 1KV M B
△ C804	VE-30000433	CER CAP.	1NF 1KV M B
C808	VE-30012590	SMD CAP.	47NF 50V K
C809	VE-30000421	EL CAP.	220UF 400V M (FOR 28'')
C810	VE-30000387	EL CAP.	33UF 50V M
C811	VE-30000161	MKT CAP.	47NF 630V J
C812	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
△ C816	VE-30000440	CER CAP.	2.2NF 4KV M
C817	VE-30000198	CER CAP.	120PF 500V J SL
C818	VE-30012590	SMD CAP.	47NF 50V K
C819	VE-30012590	SMD CAP.	47NF 50V K

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C822	VE-30007308	CER CAP.	220PF 1KV K (PULSE)
C826	VE-30000406	EL CAP.	47UF 250V M (HR)
C827	VE-30000411	EL CAP.	4700UF 16V M
C828	VE-30012590	SMD CAP.	47NF 50V K
C829	VE-30000407	EL CAP.	470UF 16V M
C830	VE-30000383	EL CAP.	2200UF 25V M
C832	VE-30012590	SMD CAP.	47NF 50V K
C833	VE-30000407	EL CAP.	470UF 16V M
C834	VE-30012590	SMD CAP.	47NF 50V K
C835	VE-30012590	SMD CAP.	47NF 50V K
C838	VE-30000407	EL CAP.	470UF 16V M
C839	VE-30000407	EL CAP.	470UF 16V M
C840	VE-30000407	EL CAP.	470UF 16V M
C848	VE-30000407	EL CAP.	470UF 16V M
C850	VE-30000383	EL CAP.	2200UF 25V M
C851	VE-30012590	SMD CAP.	47NF 50V K
△ C852	VE-30000440	CER CAP.	2.2NF 4KV M
C857	VE-30000106	MKT CAP.	47NF 100V J
C858	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
C859	VE-30009208	CER CAP.	470PF 1KV K (PULSE)
C860	VE-30000296	CER CAP.	100NF 100V Z F
C872	VE-30007708	CER CAP.	1NF 1KV K (PULSE)

TRANSF

△ TR600	VE-30002090	LINE DRIVER
△ TR601	VE-30017522	FBT TRF
△ TR802	VE-30018785	SMPS TRF

COIL

L101	VE-30001971	FERRITE BEAT
L102	VE-30001971	FERRITE BEAT
L106	VE-30001971	FERRITE BEAT
L108	VE-30001971	FERRITE BEAT
L109	VE-30001971	FERRITE BEAT
L110	VE-30001971	FERRITE BEAT
L111	VE-30001971	FERRITE BEAT
L112	VE-30001971	FERRITE BEAT
L113	VE-30001971	FERRITE BEAT
L114	VE-30001971	FERRITE BEAT
L115	VE-30001971	FERRITE BEAT
L116	VE-30001971	FERRITE BEAT
L117	VE-30001971	FERRITE BEAT
L201	VE-30001979	FIXED COIL
L210	VE-30001971	FERRITE BEAT
L215	VE-30001971	FERRITE BEAT
L401	VE-30001971	FERRITE BEAT
L402	VE-30001992	FIXED COIL
L403	VE-30001971	FERRITE BEAT
L404	VE-30001990	FIXED COIL
L405	VE-30014048	ADJ. COIL
L406	VE-30001971	FERRITE BEAT
L407	VE-30001992	FIXED COIL
L408	VE-30001992	FIXED COIL
L501	VE-30001971	FERRITE BEAT
L502	VE-30001971	FERRITE BEAT
L503	VE-30001971	FERRITE BEAT
L504	VE-30001971	FERRITE BEAT
L600	VE-30002031	FIXED COIL
L602	VE-30017085	LINEARITY COIL
L603	VE-30016083	FIXED COIL
L700	VE-30001971	FERRITE BEAT
L701	VE-30001971	FERRITE BEAT
L702	VE-30001992	FIXED COIL
L703	VE-30001971	FERRITE BEAT
L704	VE-30001971	FERRITE BEAT
L801	VE-30002011	CHOKE COIL
L803	VE-30001992	FIXED COIL

DIODE

D101	VE-30007760	ZENER DIODE
D104	VE-30007760	ZENER DIODE
D105	VE-30007760	ZENER DIODE
D106	VE-30007760	ZENER DIODE
D107	VE-30007760	ZENER DIODE
D303	VE-30001329	DIODE
D405	VE-30007763	ZENER DIODE
D407	VE-30001284	DIODE

[AV-29BF11EPS]

△ Symbol No.	Part No.	Part Name	Description
DIODE			
D408	VE-30001285	DIODE	
D409	VE-30001284	DIODE	
D413	VE-30018526	ZENER DIODE	
D414	VE-30001283	DIODE	
D501	VE-30001285	DIODE	
D505	VE-30001285	DIODE	
D506	VE-30001284	DIODE	
D512	VE-30001285	DIODE	
D513	VE-30001369	ZENER DIODE	
D533	VE-30001377	ZENER DIODE	
D601	VE-30001329	DIODE	
D603	VE-30001285	DIODE	
D605	VE-30001320	DIODE	
D606	VE-30007681	DIODE	
D609	VE-30001318	DIODE	
D610	VE-30001318	DIODE	
D613	VE-30001318	DIODE	
D614	VE-30001285	DIODE	
D616	VE-30003696	DIODE	
D617	VE-30001318	DIODE	
D651	VE-30001285	DIODE	
D653	VE-30001285	DIODE	
D657	VE-30007763	ZENER DIODE	
D658	VE-30007763	ZENER DIODE	
D659	VE-30001350	ZENER DIODE	
D661	VE-30001350	ZENER DIODE	
D700	VE-30001285	DIODE	
D701	VE-30001369	ZENER DIODE	
D800	VE-30001318	DIODE	
D801	VE-30001372	ZENER DIODE	
D802	VE-30001318	DIODE	
D803	VE-30001315	DIODE	
D804	VE-30001318	DIODE	
D805	VE-30001315	DIODE	
D806	VE-30001315	DIODE	
D808	VE-20092405	CN. ASY.	UF5407+FERRITE
D809	VE-30001329	DIODE	
D810	VE-30009366	DIODE	
D811	VE-30009366	DIODE	
D812	VE-30001285	DIODE	
D889	VE-30001384	TR	
△ D891	VE-30007758	DIODE	
D892	VE-30001318	DIODE	
D893	VE-30001318	DIODE	
D894	VE-30001285	DIODE	
D897	VE-30001329	DIODE	

TRANSISTOR

Q104	VE-30001457	TR	
Q106	VE-30001457	TR	
Q141	VE-30001457	TR	
Q142	VE-30001457	TR	
Q307	VE-30001457	TR	
Q316	VE-30001458	TR	
Q402	VE-30001457	TR	
Q403	VE-30001457	TR	
Q404	VE-30001457	TR	
Q503	VE-30001457	TR	
Q504	VE-30001458	TR	
Q600	VE-30001435	TR	
△ Q601	VE-30001441	TR	
Q602	VE-30001429	TR	
Q603	VE-30001458	TR	
Q604	VE-30001457	TR	
Q605	VE-30001458	TR	
Q700	VE-30001458	TR	
Q801	VE-30001386	TR	
Q802	VE-30001457	TR	
Q804	VE-30001454	TR	

IC

IC301	VE-30016113	IC	
IC403	VE-30014510	IC	
IC500	VE-20103268	IC	(SERVICE)
IC501	VE-20093395	PR. IC.	(MICOM)
IC601	VE-30013985	IC	
IC700	VE-30013658	IC	
IC800	VE-30011968	IC	

△ Symbol No.	Part No.	Part Name	Description
IC			
△ IC801	VE-30015087	IC	
IC802	VE-30001622	IC	
IC803	VE-30001500	IC	
IC804	VE-30001622	IC	
IC818	VE-30001506	IC	

OTHERS

△ F801	VE-30001731	FUSE	2.5A 250V 5*20MM
△ TH800	VE-30001270	PTC	9 OHM
△ TR801	VE-30002104	LINE FILTER	
TU201	VE-30009637	TUNER	WSP (PLL) 38.9 MK2 - BATC
X401	VE-30001749	XTAL	
X402	VE-30015592	XTAL	
X501	VE-30002851	XTAL	
X700	VE-30001756	XTAL	
Z401	VE-30012545	SAW FILTER	
Z402	VE-30014261	SAW FILTER	
Z404	VE-30001724	SER FILTER	

CRT SOCKET P.W. BOARD ASS'Y (VE-20094670)

Refer to PARTS LIST in page 30 for this P.W. board

FRONT AV & HEADPHONE P.W. BOARD ASS'Y (VE-20083646)

Refer to PARTS LIST in page 30 for this P.W. board

FRONT CONTROL P.W. BOARD ASS'Y (VE-20100168)

Refer to PARTS LIST in page 30 for this P.W. board

PRINTED WIRING BOARD PARTS LIST

[AV-29BF11EES]

MAIN P.W. BOARD ASS'Y (VE-20103265)

△ Symbol No.	Part No.	Part Name	Description
VARIABLE RESISTOR			
VR800	VE-30001064	ADJ RES	1/10W 470R VER (MAN)
RESISTOR			
R102	VE-30012657	SMD RES.	1/16W 1K J
R103	VE-30012657	SMD RES.	1/16W 1K J
R106	VE-30012713	SMD RES.	1/16W 75R J
R107	VE-30012649	SMD RES.	1/16W 150R J
R109	VE-30012713	SMD RES.	1/16W 75R J
R110	VE-30012713	SMD RES.	1/16W 75R J
R111	VE-30012649	SMD RES.	1/16W 150R J
R113	VE-30012713	SMD RES.	1/16W 75R J
R114	VE-30012713	SMD RES.	1/16W 75R J
R115	VE-30012713	SMD RES.	1/16W 75R J
R117	VE-30000792	CF RES.	1/4W 75R J
R118	VE-30012713	SMD RES.	1/16W 75R J
R121	VE-30012649	SMD RES.	1/16W 150R J
R122	VE-30000792	CF RES.	1/4W 75R J
R123	VE-30000792	CF RES.	1/4W 75R J
R124	VE-30012649	SMD RES.	1/16W 150R J
R126	VE-30012657	SMD RES.	1/16W 1K J
R129	VE-30012713	SMD RES.	1/16W 75R J
R135	VE-30012657	SMD RES.	1/16W 1K J
R137	VE-30000466	CF RES.	1/4W 1K J
R138	VE-30012657	SMD RES.	1/16W 1K J
R139	VE-30012713	SMD RES.	1/16W 75R J
R141	VE-30012657	SMD RES.	1/16W 1K J
R145	VE-30012713	SMD RES.	1/16W 75R J
R149	VE-30012703	SMD RES.	1/16W 56K J
R151	VE-30012696	SMD RES.	1/16W 47K J
R152	VE-30000752	CF RES.	1/4W 56K J
R153	VE-30012657	SMD RES.	1/16W 1K J
R154	VE-30000723	CF RES.	1/4W 47K J
R155	VE-30012649	SMD RES.	1/16W 150R J
R169	VE-30012703	SMD RES.	1/16W 56K J
R171	VE-30012713	SMD RES.	1/16W 75R J
R172	VE-30012692	SMD RES.	1/16W 4.7K J
R174	VE-30012713	SMD RES.	1/16W 75R J
R175	VE-30012713	SMD RES.	1/16W 75R J
R176	VE-30012703	SMD RES.	1/16W 56K J
R201	VE-30012674	SMD RES.	1/16W 27K J
R202	VE-30012692	SMD RES.	1/16W 4.7K J
R204	VE-30000459	CF RES.	1/4W 100R J
R206	VE-30000459	CF RES.	1/4W 100R J
R319	VE-30014076	SMD RES.	1/16W 4.7R J
R320	VE-30014076	SMD RES.	1/16W 4.7R J
R324	VE-30012667	SMD RES.	1/16W 220K J
R328	VE-30012649	SMD RES.	1/16W 150R J
R329	VE-30012692	SMD RES.	1/16W 4.7K J
R332	VE-30012641	SMD RES.	1/16W 10K J
R333	VE-30012702	SMD RES.	1/16W 560R J
R338	VE-30012641	SMD RES.	1/16W 10K J
R340	VE-30012644	SMD RES.	1/16W 12K J
R341	VE-30012702	SMD RES.	1/16W 560R J
R343	VE-30012659	SMD RES.	1/16W 2.2K J
R370	VE-30012669	SMD RES.	1/16W 22K J
R371	VE-30012669	SMD RES.	1/16W 2.2K J
R391	VE-30012696	SMD RES.	1/16W 47K J
R417	VE-30012510	SMD RES.	1/16W 100R J
R418	VE-30012510	SMD RES.	1/16W 100R J
R419	VE-30012649	SMD RES.	1/16W 150R J
R420	VE-30000466	CF RES.	1/4W 1K J
R421	VE-30012650	SMD RES.	1/16W 15K J
R422	VE-30012659	SMD RES.	1/16W 2.2K J
R423	VE-30012712	SMD RES.	1/16W 8.2K J
R425	VE-30012510	SMD RES.	1/16W 100R J
R426	VE-30012659	SMD RES.	1/16W 2.2K J
R427	VE-30012674	SMD RES.	1/16W 27K J
R428	VE-30012510	SMD RES.	1/16W 100R J
R430	VE-30012702	SMD RES.	1/16W 560R J
R431	VE-30012674	SMD RES.	1/16W 27K J
R432	VE-30012707	SMD RES.	1/16W 680R J
R433	VE-30012683	SMD RES.	1/16W 330K J
R437	VE-30000466	CF RES.	1/4W 1K J
R438	VE-30000466	CF RES.	1/4W 1K J
R439	VE-30012657	SMD RES.	1/16W 1K J
R440	VE-30012714	SMD RES.	1/16W 820R J
R441	VE-30012674	SMD RES.	1/16W 27K J
R442	VE-30000466	CF RES.	1/4W 1K J
R446	VE-30012714	SMD RES.	1/16W 820R J

△ Symbol No.	Part No.	Part Name	Description
RESISTOR			
R447	VE-30012714	SMD RES.	1/16W 820R J
R448	VE-30012683	SMD RES.	1/16W 330K J
R450	VE-30012702	SMD RES.	1/16W 560R J
R458	VE-30012510	SMD RES.	1/16W 100R J
R459	VE-30012668	SMD RES.	1/16W 220R J
R460	VE-30012668	SMD RES.	1/16W 220R J
R461	VE-30012668	SMD RES.	1/16W 220R J
R449	VE-30012659	SMD RES.	1/16W 2.2K J
R462	VE-30012510	SMD RES.	1/16W 100R J
R467	VE-30000670	CF RES.	1/4W 330K J
R468	VE-30000670	CF RES.	1/4W 330K J
R469	VE-30000628	CF RES.	1/4W 2.7K J
R471	VE-30014022	SMD RES.	1/16W 47R J
R472	VE-30012662	SMD RES.	1/16W 2.7K J
R474	VE-30012662	SMD RES.	1/16W 2.7K J
R481	VE-30000466	CF RES.	1/4W 1K J
R482	VE-30012657	SMD RES.	1/16W 1K J
R483	VE-30012657	SMD RES.	1/16W 1K J
R485	VE-30012657	SMD RES.	1/16W 1K J
R486	VE-30012657	SMD RES.	1/16W 1K J
R487	VE-30012657	SMD RES.	1/16W 1K J
R507	VE-30000466	CF RES.	1/4W 1K J
R508	VE-30012510	SMD RES.	1/16W 100R J
R509	VE-30012641	SMD RES.	1/16W 10K J
R510	VE-30012702	SMD RES.	1/16W 560R J
R511	VE-30012657	SMD RES.	1/16W 1K J
R512	VE-30000495	CF RES.	1/4W 1.2K J
R513	VE-30000459	CF RES.	1/4W 100R J
R514	VE-30000459	CF RES.	1/4W 100R J
R515	VE-30012659	SMD RES.	1/16W 2.2K J
R516	VE-30012659	SMD RES.	1/16W 2.2K J
R517	VE-30012692	SMD RES.	1/16W 4.7K J
R518	VE-30000471	CF RES.	1/4W 10K J
R519	VE-30012698	SMD RES.	1/16W 5.6K J
R525	VE-30012649	SMD RES.	1/16W 150R J
R526	VE-30012641	SMD RES.	1/16W 10K J
R527	VE-30012692	SMD RES.	1/16W 4.7K J
R528	VE-30012698	SMD RES.	1/16W 5.6K J
R529	VE-30012698	SMD RES.	1/16W 5.6K J
R530	VE-30012698	SMD RES.	1/16W 5.6K J
R532	VE-30012659	SMD RES.	1/16W 2.2K J
R533	VE-30012644	SMD RES.	1/16W 12K J
R534	VE-30000628	CF RES.	1/4W 2.7K J
R537	VE-30012641	SMD RES.	1/16W 10K J
R538	VE-30012698	SMD RES.	1/16W 5.6K J
R539	VE-30012659	SMD RES.	1/16W 2.2K J
R540	VE-30012644	SMD RES.	1/16W 12K J
R545	VE-30012644	SMD RES.	1/16W 12K J
R548	VE-30012641	SMD RES.	1/16W 10K J
R554	VE-30012641	SMD RES.	1/16W 10K J
R555	VE-30012659	SMD RES.	1/16W 2.2K J
R556	VE-30012657	SMD RES.	1/16W 1K J
R560	VE-30012674	SMD RES.	1/16W 27K J
R561	VE-30012692	SMD RES.	1/16W 4.7K J
R568	VE-30000594	CF RES.	1/4W 22K J
R572	VE-30012659	SMD RES.	1/16W 2.2K J
R573	VE-30012641	SMD RES.	1/16W 10K J
R574	VE-30012657	SMD RES.	1/16W 1K J
R603	VE-30000459	CF RES.	1/4W 100R J
R604	VE-30012510	SMD RES.	1/16W 100R J
R606	VE-30000471	CF RES.	1/4W 10K J
R607	VE-30000554	CF RES.	1/4W 180R J
R608	VE-30000859	MF RES.	1/2W 1R F
R609	VE-30000711	CF RES.	1/2W 470R J
R610	VE-30000599	CF RES.	1/4W 220K J
R611	VE-30012708	SMD RES.	1/16W 68K J
R616	VE-30012685	SMD RES.	1/16W 33K J
R617	VE-30000572	CF RES.	1/4W 2K J
R630	VE-30012702	SMD RES.	1/16W 560R J
R634	VE-30000633	CF RES.	1/4W 27K J
R639	VE-30000471	CF RES.	1/4W 10K J
R640	VE-30000628	CF RES.	1/4W 2.7K J
R646	VE-30000775	CF RES.	1/4W 6.8K J
R647	VE-30000466	CF RES.	1/4W 1K J
△ R648	VE-30001246	FUSE RES.	1W 0.47R J
R650	VE-30012702	SMD RES.	1/16W 560R J
R651	VE-30012668	SMD RES.	1/16W 220R J
△ R656	VE-30001247	FUSE RES.	1/2W 4.7R J
△ R657	VE-30001228	FUSE RES.	1/2W 2.2R J
R662	VE-30012674	SMD RES.	1/16W 27K J
R666	VE-30000531	CF RES.	1/4W 15K J

[AV-29BF11EES]

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

RESISTOR

R668	VE-30000607	CF RES.	1/4W 2.2R J
R669	VE-30012510	SMD RES.	1/16W 100R J
R670	VE-30012510	SMD RES.	1/16W 100R J
R677	VE-30001124	MO RES.	3W 220R J
R678	VE-30014022	SMD RES.	1/16W 47R J
R680	VE-30000477	CF RES.	1/4W 100K J
R681	VE-30012509	SMD RES.	1/16W 100K J
R674	VE-30012662	SMD RES.	1/16W 2.7K J
△ R675	VE-30001208	FUSE RES.	1W 10R J
R682	VE-30017082	WW RES.	5W 75R J RAD.
R683	VE-30017083	WW RES.	5W 2.2K J RAD.
R689	VE-30000718	CF RES.	1/4W 4.7K J
R690	VE-30000466	CF RES.	1/4W 1K J
R691	VE-30012696	SMD RES.	1/16W 47K J
R692	VE-30012509	SMD RES.	1/16W 100K J
R693	VE-30012708	SMD RES.	1/16W 68K J
R694	VE-30000689	CF RES.	1/4W 3.9K J
R695	VE-30000775	CF RES.	1/4W 6.8K J
R696-Y	VE-30001350	ZENER DIODE	12V
R697	VE-30000712	CF RES.	1/4W 470R J
R698	VE-30012657	SMD RES.	1/16W 1K J
R700	VE-30012649	SMD RES.	1/16W 150R J
R701	VE-30000459	CF RES.	1/4W 100R J
R703	VE-30000459	CF RES.	1/4W 100R J
R705	VE-30000459	CF RES.	1/4W 100R J
R715	VE-30012702	SMD RES.	1/16W 560R J
R717	VE-30012702	SMD RES.	1/16W 560R J
R719	VE-30012657	SMD RES.	1/16W 1K J
R721	VE-30012510	SMD RES.	1/16W 100R J
R722	VE-30012510	SMD RES.	1/16W 100R J
R723	VE-30012510	SMD RES.	1/16W 100R J
R724	VE-30012510	SMD RES.	1/16W 100R J
R801	VE-30000718	CF RES.	1/4W 4.7K J
R803	VE-30012659	SMD RES.	1/16W 2.2K J
R805	VE-30000650	CF RES.	1/4W 33R J
R806	VE-30000982	MF RES.	1/4W 4.7K J
R807	VE-30001173	MO RES.	1W 0.47R J
△ R809	VE-30007784	MO RES.	5W 33K J (RADIAL)
R810	VE-30001257	MG RES.	1/2W 4.7H J
R811	VE-30000718	CF RES.	1/4W 4.7K J
R812	VE-30012641	SMD RES.	1/16W 10K J
R813	VE-30000466	CF RES.	1/4W 1K J
R814	VE-30000466	CF RES.	1/4W 1K J
R817	VE-30000880	MF RES.	1/4W 130K F
R818	VE-30012675	SMD RES.	1/16W 2K J
R819	VE-30000526	CF RES.	1/4W 1.5K J
R828	VE-30000530	CF RES.	1/2W 15K J
R829	VE-30000530	CF RES.	1/2W 15K J
R834	VE-30001159	MO RES.	1W 0.33R J
R836	VE-30012662	SMD RES.	1/16W 2.7K J
R839	VE-30000526	CF RES.	1/4W 1.5K J
R842	VE-30014128	SMD RES.	1/16W 33R J
R844	VE-30012641	SMD RES.	1/16W 10K J
R845	VE-30012509	SMD RES.	1/16W 100K J
R846	VE-30012692	SMD RES.	1/16W 4.7K J
R847	VE-30014128	SMD RES.	1/16W 33R J
R848	VE-30012641	SMD RES.	1/16W 10K J
R849	VE-30012510	SMD RES.	1/16W 100R J
R851	VE-30000718	CF RES.	1/4W 4.7K J
R852	VE-30000650	CF RES.	1/4W 33R J
R853	VE-30012642	SMD RES.	1/16W 120K J
R855	VE-30000459	CF RES.	1/4W 100R J
R856	VE-30012694	SMD RES.	1/16W 470K J
R857	VE-30001263	WW RES.	5W 3.9R J (RAD)

CAPACITOR

C141	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C142	VE-30007081	EL CAP.	4.7UF 50V M (NPL)
C143	VE-30012589	SMD CAP.	4.7NF 50V K
C144	VE-30012589	SMD CAP.	4.7NF 50V K
C145	VE-30012589	SMD CAP.	4.7NF 50V K
C146	VE-30012589	SMD CAP.	4.7NF 50V K
C147	VE-30012589	SMD CAP.	4.7NF 50V K
C148	VE-30012589	SMD CAP.	4.7NF 50V K
C149	VE-30012589	SMD CAP.	4.7NF 50V K
C150	VE-30012589	SMD CAP.	4.7NF 50V K
C155	VE-30012560	SMD CAP.	100PF 50V J
C157	VE-30012560	SMD CAP.	100PF 50V J
C159	VE-30000352	EL CAP.	100UF 16V M
C160	VE-30000345	EL CAP.	10UF 50V M
C161	VE-30000345	EL CAP.	10UF 50V M

Symbol No.	Part No.	Part Name	Description
------------	----------	-----------	-------------

CAPACITOR

C162	VE-30012573	SMD CAP.	47PF 50V J
C164	VE-30012692	SMD RES.	1/16W 4.7K J
C165	VE-30000413	EL CAP.	4.7UF 50V M
C201	VE-30000400	EL CAP.	47UF 50V M
C205	VE-30000345	EL CAP.	10UF 50V M
C206	VE-30012610	SMD CAP.	10NF 50V J
C207	VE-30012610	SMD CAP.	10NF 50V J
C230	VE-30016654	SMD CAP.	100NF 16V K R
C246	VE-30000295	CER CAP.	100NF 50V Z F
C303	VE-30000100	MKT CAP.	330NF 63V J
C305	VE-30012590	SMD CAP.	47NF 50V K
C310	VE-30000345	EL CAP.	10UF 50V M
C333	VE-30000083	MKT CAP.	150NF 63V J
C363	VE-30000083	MKT CAP.	150NF 63V J
C364	VE-30012590	SMD CAP.	47NF 50V K
C366	VE-30000407	EL CAP.	470UF 16V M
C368	VE-30012590	SMD CAP.	47NF 50V K
C404	VE-30000190	CER CAP.	100PF 50V J CH
C408	VE-30012586	SMD CAP.	22NF 50V K
C409	VE-30000345	EL CAP.	10UF 50V M
C410	VE-30000384	EL CAP.	2.2UF 50V M
C411	VE-30000345	EL CAP.	10UF 50V M
C412	VE-30016654	SMD CAP.	100NF 16V K R
C413	VE-30000362	EL CAP.	1UF 50V M
C414	VE-30012585	SMD CAP.	2.2NF 50V K R
C415	VE-30012581	SMD CAP.	1NF 50V K R
C416	VE-30000362	EL CAP.	1UF 50V M
C417	VE-30000362	EL CAP.	1UF 50V M
C418	VE-30016654	SMD CAP.	100NF 16V K R
C419	VE-30000384	EL CAP.	2.2UF 50V M
C420	VE-30000100	MKT CAP.	330NF 63V J
C422	VE-30000352	EL CAP.	100UF 16V M
C423	VE-30000352	EL CAP.	100UF 16V M
C424	VE-30000352	EL CAP.	100UF 16V M
C425	VE-30016654	SMD CAP.	100NF 16V K R
C427	VE-30016654	SMD CAP.	100NF 16V K R
C429	VE-30012589	SMD CAP.	4.7NF 50V K
C430	VE-30016654	SMD CAP.	100NF 16V K R
C431	VE-30000362	EL CAP.	1UF 50V M
C432	VE-30016654	SMD CAP.	100NF 16V K R
C433	VE-30000345	EL CAP.	10UF 50V M
C434	VE-30016654	SMD CAP.	100NF 16V K R
C435	VE-30016654	SMD CAP.	100NF 16V K R
C436	VE-30000109	MKT CAP.	470NF 63V J
C437	VE-30016654	SMD CAP.	100NF 16V K R
C438	VE-30016654	SMD CAP.	100NF 16V K R
C439	VE-30016654	SMD CAP.	100NF 16V K R
C440	VE-30000295	CER CAP.	100NF 50V Z F
C441	VE-30012582	SMD CAP.	10NF 50V K R
C442	VE-30000109	MKT CAP.	470NF 63V J
C443	VE-30000362	EL CAP.	1UF 50V M
C444	VE-30000384	EL CAP.	2.2UF 50V M
C448	VE-30012586	SMD CAP.	22NF 50V K
C449	VE-30012560	SMD CAP.	100PF 50V J
C453	VE-30000352	EL CAP.	100UF 16V M
C455	VE-30000345	EL CAP.	10UF 50V M
C457	VE-30012578	SMD CAP.	68PF 50V J
C459	VE-30012560	SMD CAP.	100PF 50V J
C501	VE-30016654	SMD CAP.	100NF 16V K R
C502	VE-30000400	EL CAP.	47UF 50V M
C504	VE-30016654	SMD CAP.	100NF 16V K R
C505	VE-30012589	SMD CAP.	4.7NF 50V K
C507	VE-30000345	EL CAP.	10UF 50V M
C510	VE-30016654	SMD CAP.	100NF 16V K R
C511	VE-30012566	SMD CAP.	22PF 50V J
C513	VE-30000345	EL CAP.	10UF 50V M
C514	VE-30016654	SMD CAP.	100NF 16V K R
C515	VE-30012560	SMD CAP.	100PF 50V J
C517	VE-30016654	SMD CAP.	100NF 16V K R
C518	VE-30016654	SMD CAP.	100NF 16V K R
C519	VE-30012560	SMD CAP.	100PF 50V J
C520	VE-30012560	SMD CAP.	100PF 50V J
C521	VE-30012562	SMD CAP.	15PF 50V J
C522	VE-30012562	SMD CAP.	15PF 50V J
C523	VE-30012585	SMD CAP.	2.2NF 50V K R
C524	VE-30012566	SMD CAP.	22PF 50V J
C525	VE-30012566	SMD CAP.	22PF 50V J
C526	VE-30016654	SMD CAP.	100NF 16V K R
C527	VE-30000345	EL CAP.	10UF 50V M
C529	VE-30012589	SMD CAP.	4.7NF 50V K
C530	VE-30012589	SMD CAP.	4.7NF 50V K
C532	VE-30016654	SMD CAP.	100NF 16V K R
C536	VE-30000295	CER CAP.	100NF 50V Z F

[AV-29BF11EES]

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C541	VE-30000362	EL CAP.	1UF 50V M
C542	VE-30000107	MKT CAP.	47NF 250V J
C543	VE-30000431	CER CAP.	100PF 1KV M
C544	VE-30000345	EL CAP.	10UF 50V M
C547	VE-30000345	EL CAP.	10UF 50V M
C565	VE-30016654	SMD CAP.	100NF 16V K R
C566	VE-30016654	SMD CAP.	100NF 16V K R
C567	VE-30000431	CER CAP.	100PF 1KV M
C602	VE-30017319	MKT CAP.	120NF 63V J
C604	VE-30000356	EL CAP.	100UF 63V M
C605	VE-30000360	EL CAP.	1000UF 25V M
C607	VE-30012581	SMD CAP.	1NF 50V K R
△ C618	VE-30000168	MKP CAP.	6.2NF 1.6KV 3.5%
△ C621	VE-30000136	MKP CAP.	12NF 2000V 3.5
C622	VE-30012003	MKP CAP.	18NF 630V J
C623	VE-30000406	EL CAP.	47UF 250V M (HR)
△ C625	VE-30000177	MKP CAP.	820NF 250V J
C627	VE-30000162	MKP CAP.	470NF 250V J
C629	VE-30013003	MKP CAP.	1UF 250V J P=15
C632	VE-30000100	MKT CAP.	330NF 63V J
C635	VE-30000385	EL CAP.	2.2UF 250V M
C636	VE-30000387	EL CAP.	33UF 50V M
C640	VE-30000100	MKT CAP.	330NF 63V J
C641	VE-30000090	MKT CAP.	22NF 100V J
C642	VE-30000407	EL CAP.	470UF 16V M
C644	VE-30000409	EL CAP.	470UF 25V M
C645	VE-30000090	MKT CAP.	22NF 100V J
C646	VE-30000100	MKT CAP.	330NF 63V J
C647	VE-30007748	EL CAP.	1000UF 35V M
C648	VE-30000394	EL CAP.	3.3UF 160V M
C649	VE-30000295	CER CAP.	100NF 50V Z F
C652	VE-30000330	CER CAP.	4.7NF 50V K B
C653	VE-30000107	MKT CAP.	47NF 250V J
C700	VE-30012565	SMD CAP.	1.8PF 50V J CH
C701	VE-30012565	SMD CAP.	1.8PF 50V J CH
C702	VE-30012576	SMD CAP.	56PF 50V J CH
C703	VE-30012576	SMD CAP.	56PF 50V J CH
C704	VE-30012576	SMD CAP.	56PF 50V J CH
C705	VE-30000345	EL CAP.	10UF 50V M
C706	VE-30000345	EL CAP.	10UF 50V M
C708	VE-30016654	SMD CAP.	100NF 16V K R
C712	VE-30000345	EL CAP.	10UF 50V M
C713	VE-30016654	SMD CAP.	100NF 16V K R
C714	VE-30000100	MKT CAP.	330NF 63V J
C716	VE-30000100	MKT CAP.	330NF 63V J
C717	VE-30000100	MKT CAP.	330NF 63V J
C718	VE-30000100	MKT CAP.	330NF 63V J
C719	VE-30016654	SMD CAP.	100NF 16V K R
C720	VE-30000345	EL CAP.	10UF 50V M
C721	VE-30000100	MKT CAP.	330NF 63V J
C723	VE-30000100	MKT CAP.	330NF 63V J
C724	VE-30000345	EL CAP.	10UF 50V M
C729	VE-30016654	SMD CAP.	100NF 16V K R
C730	VE-30000393	EL CAP.	3.3UF 50V M
C733	VE-30000345	EL CAP.	10UF 50V M
C734	VE-30000345	EL CAP.	10UF 50V M
C735	VE-30016654	SMD CAP.	100NF 16V K R
C736	VE-30000345	EL CAP.	10UF 50V M
C737	VE-30000384	EL CAP.	2.2UF 50V M
C738	VE-30000384	EL CAP.	2.2UF 50V M
C739	VE-30000384	EL CAP.	2.2UF 50V M
C740	VE-30000384	EL CAP.	2.2UF 50V M
C741	VE-30012589	SMD CAP.	4.7NF 50V K
C742	VE-30012589	SMD CAP.	4.7NF 50V K
C745	VE-30016654	SMD CAP.	100NF 16V K R
△ C801	VE-30000094	MKT CAP.	220NF AC275V M
△ C802	VE-30000094	MKT CAP.	220NF AC275V M
△ C803	VE-30000433	CER CAP.	1NF 1KV M B
△ C804	VE-30000433	CER CAP.	1NF 1KV M B
C808	VE-30012590	SMD CAP.	47NF 50V K
C809	VE-30000421	EL CAP.	220UF 400V M (FOR 28'')
C810	VE-30000387	EL CAP.	33UF 50V M
C811	VE-30000161	MKP CAP.	47NF 630V J
C812	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
△ C816	VE-30000440	CER CAP.	2.2NF 4KV M
C817	VE-30000198	CER CAP.	120PF 500V J SL
C818	VE-30012590	SMD CAP.	47NF 50V K
C819	VE-30012590	SMD CAP.	47NF 50V K
C822	VE-30007308	CER CAP.	220PF 1KV K (PULSE)
C826	VE-30000406	EL CAP.	47UF 250V M (HR)
C827	VE-30000411	EL CAP.	4700UF 16V M
C828	VE-30012590	SMD CAP.	47NF 50V K
C829	VE-30000407	EL CAP.	470UF 16V M

△ Symbol No.	Part No.	Part Name	Description
CAPACITOR			
C830	VE-30000383	EL CAP.	2200UF 25V M
C832	VE-30012590	SMD CAP.	47NF 50V K
C833	VE-30000407	EL CAP.	470UF 16V M
C834	VE-30012590	SMD CAP.	47NF 50V K
C835	VE-30012590	SMD CAP.	47NF 50V K
C838	VE-30000407	EL CAP.	470UF 16V M
C839	VE-30000407	EL CAP.	470UF 16V M
C840	VE-30000407	EL CAP.	470UF 16V M
C848	VE-30000407	EL CAP.	470UF 16V M
C850	VE-30000383	EL CAP.	2200UF 25V M
C851	VE-30012590	SMD CAP.	47NF 50V K
△ C852	VE-30000440	CER CAP.	2.2NF 4KV M
C857	VE-30000106	MKT CAP.	47NF 100V J
C858	VE-30007708	CER CAP.	1NF 1KV K (PULSE)
C859	VE-30009208	CER CAP.	470PF 1KV K (PULSE)
C860	VE-30000296	CER CAP.	100NF 100V Z F
C872	VE-30007708	CER CAP.	1NF 1KV K (PULSE)

TRANSF

△ TR600	VE-30002090	LINE DRIVER
△ TR601	VE-30017522	FBT TRF
△ TR802	VE-30018785	SMPS TRF

COIL

L101	VE-30001971	FERRITE BEAT
L102	VE-30001971	FERRITE BEAT
L106	VE-30001971	FERRITE BEAT
L108	VE-30001971	FERRITE BEAT
L109	VE-30001971	FERRITE BEAT
L110	VE-30001971	FERRITE BEAT
L111	VE-30001971	FERRITE BEAT
L112	VE-30001971	FERRITE BEAT
L113	VE-30001971	FERRITE BEAT
L114	VE-30001971	FERRITE BEAT
L115	VE-30001971	FERRITE BEAT
L116	VE-30001971	FERRITE BEAT
L117	VE-30001971	FERRITE BEAT
L201	VE-30001979	FIXED COIL
L210	VE-30001971	FERRITE BEAT
L215	VE-30001971	FERRITE BEAT
L401	VE-30001971	FERRITE BEAT
L402	VE-30001992	FIXED COIL
L403	VE-30001971	FERRITE BEAT
L404	VE-30001990	FIXED COIL
L405	VE-30014048	ADJ. COIL
L406	VE-30001971	FERRITE BEAT
L408	VE-30001992	FIXED COIL
L501	VE-30001971	FERRITE BEAT
L502	VE-30001971	FERRITE BEAT
L503	VE-30001971	FERRITE BEAT
L504	VE-30001971	FERRITE BEAT
L600	VE-30002031	FIXED COIL
L602	VE-30017085	LINEARITY COIL
L603	VE-30016083	FIXED COIL
L700	VE-30001971	FERRITE BEAT
L701	VE-30001971	FERRITE BEAT
L702	VE-30001992	FIXED COIL
L703	VE-30001971	FERRITE BEAT
L704	VE-30001971	FERRITE BEAT
L801	VE-30002011	CHOKE COIL
L803	VE-30001992	FIXED COIL

DIODE

D101	VE-30007760	ZENER DIODE
D104	VE-30007760	ZENER DIODE
D105	VE-30007760	ZENER DIODE
D106	VE-30007760	ZENER DIODE
D107	VE-30007760	ZENER DIODE
D303	VE-30001329	DIODE
D405	VE-30007763	ZENER DIODE
D407	VE-30001284	DIODE
D408	VE-30001285	DIODE
D409	VE-30001284	DIODE
D413	VE-30018526	ZENER DIODE
D501	VE-30001285	DIODE
D505	VE-30001285	DIODE
D506	VE-30001284	DIODE

[AV-29BF11EES]

△ Symbol No.	Part No.	Part Name	Description
DIODE			
D512	VE-30001285	DIODE	
D513	VE-30001369	ZENER DIODE	
D533	VE-30001377	ZENER DIODE	
D601	VE-30001329	DIODE	
D603	VE-30001285	DIODE	
D605	VE-30001320	DIODE	
D606	VE-30007681	DIODE	
D609	VE-30001318	DIODE	
D610	VE-30001318	DIODE	
D613	VE-30001318	DIODE	
D614	VE-30001285	DIODE	
D616	VE-30003696	DIODE	
D617	VE-30001318	DIODE	
D651	VE-30001285	DIODE	
D653	VE-30001285	DIODE	
D657	VE-30007763	ZENER DIODE	
D658	VE-30007763	ZENER DIODE	
D659	VE-30001350	ZENER DIODE	
D661	VE-30001350	ZENER DIODE	
D700	VE-30001285	DIODE	
D701	VE-30001369	ZENER DIODE	
D800	VE-30001318	DIODE	
D801	VE-30001372	ZENER DIODE	
D802	VE-30001318	DIODE	
D803	VE-30001315	DIODE	
D804	VE-30001318	DIODE	
D805	VE-30001315	DIODE	
D806	VE-30001315	DIODE	
D808	VE-20092405	CN. ASY.	UF5407+FERRITE
D809	VE-30001329	DIODE	
D810	VE-30009366	DIODE	
D811	VE-30009366	DIODE	
D812	VE-30001285	DIODE	
△ D889	VE-30001384	TR	
△ D891	VE-30007758	DIODE	
D892	VE-30001318	DIODE	
D893	VE-30001318	DIODE	
D894	VE-30001285	DIODE	
D897	VE-30001329	DIODE	

TRANSISTOR

Q104	VE-30001457	TR	
Q106	VE-30001457	TR	
Q141	VE-30001457	TR	
Q142	VE-30001457	TR	
Q307	VE-30001457	TR	
Q316	VE-30001458	TR	
Q403	VE-30001457	TR	
Q404	VE-30001457	TR	
Q503	VE-30001457	TR	
Q504	VE-30001458	TR	
△ Q600	VE-30001435	TR	
△ Q601	VE-30001441	TR	
Q602	VE-30001429	TR	
Q603	VE-30001458	TR	
Q604	VE-30001457	TR	
Q605	VE-30001458	TR	
Q700	VE-30001458	TR	
Q801	VE-30001386	TR	
Q802	VE-30001457	TR	
Q804	VE-30001454	TR	

IC

IC301	VE-30016113	IC	
IC403	VE-30014510	IC	
IC500	VE-20103266	IC	
IC501	VE-20104642	PR. IC.	(SERVICE)
IC601	VE-30013985	IC	(MICOM)
IC700	VE-30013658	IC	
IC800	VE-30011968	IC	
△ IC801	VE-30015087	IC	
IC802	VE-30001622	IC	
IC803	VE-30001500	IC	
IC804	VE-30001622	IC	
IC818	VE-30001506	IC	

△ Symbol No.	Part No.	Part Name	Description
OTHERS			
△ F801	VE-30001731	FUSE	2.5A 250V 5*20MM
△ TH800	VE-30001270	PTC	9 OHM
△ TR801	VE-30002104	LINE FILTER	
TU201	VE-30009637	TUNER	
X401	VE-30001749	XTAL	
X402	VE-30015592	XTAL	
X501	VE-30002851	XTAL	
X700	VE-30001756	XTAL	
Z401	VE-30013163	SAW FILTER	
Z402	VE-30014261	SAW FILTER	
Z404	VE-30001724	SER FILTER	

CRT SOCKET P.W. BOARD ASS'Y (VE-20094670)

Refer to PARTS LIST in page 30 for this P.W. board


FRONT AV & HEADPHONE P.W. BOARD ASS'Y (VE-20083646)

Refer to PARTS LIST in page 30 for this P.W. board

FRONT CONTROL P.W. BOARD ASS'Y (VE-20100168)

Refer to PARTS LIST in page 30 for this P.W. board

PACKING



PACKING PARTS LIST

△ Ref.No.	Part No.	Part Name	Description
1	VE-50028949	CARTON BOX	[AV-29BF11ENS]
1	VE-50028950	CARTON BOX	[AV-29BF11ENS(for GER models)]
1	VE-50028947	CARTON BOX	[AV-29BF11EPS]
1	VE-50028945	CARTON BOX	[AV-29BF11EES]
2	VE-20048248	CUSHION ASSY	4 pcs in 1 set
3	VE-50026637	POLY BAG	(1250*1000)
4	VE-70000587	POLY BAG	
5	VE-30017763	REMOTE CONTROL UNIT (RM-C1100)	
△ 6	VE-50028493	INST BOOK	[AV-29BF11ENS]
△ 6	VE-50028296	INST BOOK	[AV-29BF11EPS]
△ 6	VE-50028326	INST BOOK	[AV-29BF11EES]
7	BT-54013-2TK	WARRANTY CARD	
△ 8	VE-20103656	LABEL	[AV-29BF11ENS]
△ 8	VE-20103677	LABEL	[AV-29BF11ENS(for GER models)]
△ 8	VE-20103679	LABEL	[AV-29BF11ENS(for ITA models)]
△ 8	VE-20103654	LABEL	[AV-29BF11EPS]
△ 8	VE-20103640	LABEL	[AV-29BF11EES]
△ 8	VE-20103638	LABEL	[AV-29BF11EES(for POL models)]



JVC

VICTOR COMPANY OF JAPAN, LIMITED

HOME AV NETWORK BUSINESS UNIT 12, 3-chome, Moriya-cho, Kanagawa-ku, Yokohama, Kanagawa-prefecture, 221-8528, Japan



Printed in Japan
0209 WPC
DP205851