

# SECTION 5 PARTS LIST

MODEL	MARK
GR-DVL210U	A
GR-DVL310U	B
GR-DVL515U	C

## SAFETY PRECAUTION

Parts identified by the  $\triangle$  symbol are critical for safety. Replace only with specified part numbers.

### 5.1 ELECTRICAL PARTS LIST

# $\triangle$ REF No.	PART No.	PART NAME, DESCRIPTION	# $\triangle$ REF No.	PART No.	PART NAME, DESCRIPTION
*****					
<b>MAIN BOARD ASSEMBLY &lt;01&gt;</b>					
PW	YB10330A-01	MAIN BOARD ASSY,B,C	Q1003	DTC143EE	TRANSISTOR
	YB10330B-01	MAIN BOARD ASSY,A	Q1004	DTA114EE	TRANSISTOR
IC1001	UPD703039F1-A15	IC(MICRO C ROM)		or PDTA114EE	TRANSISTOR
	or UPD70F3040F1A15	IC(MICRO C ROM)		or RN2102	TRANSISTOR
IC1002	RS5C314	IC	Q1005	DTC144EE	TRANSISTOR
IC1003	AT25160N-10SC-X	IC		or UN9213J	TRANSISTOR
	or X25170S8I-2.5-X	IC		or RN1104	TRANSISTOR
	or 25LC160-I/SN-X	IC		or PDTC144EE	TRANSISTOR
IC1004	TC7S56FU	IC	Q1006	DTA114EE	TRANSISTOR
IC1005	TC7S00FU	IC		or PDTA114EE	TRANSISTOR
	or SN74AHC1G00K	IC		or RN2102	TRANSISTOR
IC1006	MB90097PFV139	IC(MICRO C ROM)	Q1007	DTC144EE	TRANSISTOR
IC1007	TC74VHC08FT	IC(DIGITAL)		or UN9213J	TRANSISTOR
	or SN74LV08APW	IC		or PDTC144EE	TRANSISTOR
IC1009	IC-PST9323U-X	IC		or RN1104	TRANSISTOR
IC1301	SN74LV08APW	IC	Q1301	2SC4617/RS/-X	TRANSISTOR
	or TC74VHC08FT	IC(DIGITAL)	Q1401	DTA114EE	TRANSISTOR
IC1302	MAX3221CAE	IC		or PDTA114EE	TRANSISTOR
IC1303	TC7S32FU	IC(DIGITAL)		or RN2102	TRANSISTOR
	or SN74AHC1G32K	IC	Q1402	UMC3N	TRANSISTOR
IC1304	TC7S02FU	IC(DIGITAL)	Q1403	UMC3N	TRANSISTOR
	or SN74AHC1G02K	IC	Q1404	DTC144EE	TRANSISTOR
IC1401	YQ44901A	CSP IC ASSY		or PDTC144EE	TRANSISTOR
IC1402	TC7W66FK	IC		or RN1104	TRANSISTOR
IC1403	TC7W53FU	IC(DIGITAL)		or UN9213J	TRANSISTOR
	or SN74AHC2G53T	IC	Q1601	UMC3N	TRANSISTOR
IC1404	TC7W14FU	IC(DIGITAL)	Q2001	UMX1N	PAIR TRANSISTOR
	or SN74AHC2G14T	IC	Q2002	2SC4617/RS/-X	TRANSISTOR
IC1601	BD6630KV	IC	Q2004	2SC4617/RS/-X	TRANSISTOR
IC2001	AK4560AVQ	IC	Q3501	2SC4226/4/-X	TRANSISTOR
IC2301	JCY0137	IC	Q3502	2SD1979/S/-X	TRANSISTOR
IC3001	JCY0106-2	IC	Q3503	2SD1979/S/-X	TRANSISTOR
IC3002	M51V18165D50TSK	IC(DIGITAL)	Q3504	2SC4226/4/-X	TRANSISTOR
IC3005	SN74AHC1G04K	IC	Q3551	2SA1577/RS/-X	TRANSISTOR
IC3007	TC7SL00FU	IC(DIGITAL)	Q3552	DTC144EE	TRANSISTOR
IC3101	PDI1394P11ABD	IC		or PDTC144EE	TRANSISTOR
IC3201	JCY0107-2	IC		or UN9213J	TRANSISTOR
IC3202	TC7SH00FU	IC(DIGITAL)		or RN1104	TRANSISTOR
IC3301	JCY0108	IC	Q3701	UMT2N	PAIR TRANSISTOR
	or JCY0181	IC	Q3702	UMZ1N	PAIR TRANSISTOR
IC3501	AN3731FHQ	IC(DIGITAL)		or PUMZ1	PAIR TRANSISTOR
IC3701	BA7665FS	IC	Q4301	UMT2N	PAIR TRANSISTOR
IC4201	HD49326BF	IC	Q4302	UMT2N	PAIR TRANSISTOR
IC4202	MM1385HN	IC	Q4801	2SC4655/BC/-X	TRANSISTOR
IC4301	JCY0150	IC	Q4851	2SC4617/RS/-X	TRANSISTOR
IC4302	TMS4C2973-28-X	IC	Q6001	DTC144EE	TRANSISTOR
IC4304	MM1385NN	IC		or PDTC144EE	TRANSISTOR
IC4802	TA75W01FU	IC		or RN1104	TRANSISTOR
IC4803	TA75W01FU	IC		or UN9213J	TRANSISTOR
IC4804	UPC358G2/5/-W	IC	Q6002	2SK3019	MOS FET
IC4806	TC7W00FK	IC	Q6003	2SJ347	MOS FET
IC4851	UPD16879GS	IC	Q6004	2SB1121/TU/-X	TRANSISTOR
IC5501	JCY0117	IC	Q6101	2SK3019	MOS FET
IC6001	S-80842ANNP-W	IC	Q6102	2SK3019	MOS FET
IC6101	FA3698F	IC	Q6201	NDS352AP	MOS FET
Q1001	DTC124EE	TRANSISTOR	Q6202	2SA1577/RS/-X	TRANSISTOR
Q1002	2SC4617/RS/-X	TRANSISTOR	Q6203	SSM6J07FU	MOS FET
			Q6204	CPH3304	MOS FET
			Q6205	CPH3101	TRANSISTOR
			Q6206	2SC4617/RS/-X	TRANSISTOR
			Q6207	2SD1621/TU/-X	TRANSISTOR,B,C

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	#	△ REF No.	PART No.	PART NAME, DESCRIPTION
	Q6208	SSM6J07FU	MOS FET		R1033	NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W
	Q6210	SSM6J07FU	MOS FET		R1034	NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W
	Q6211	NDS352AP	MOS FET		R1037	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W
	Q6212	HN1C01FU/G/-X	PAIR TRANSISTOR		R1039	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W
		or PUMX1	PAIR TRANSISTOR		R1040	NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W
	Q6213	2SA1577/RS/-X	TRANSISTOR		R1044	NRSA6AJ-123W	MG RESISTOR 12kΩ,1/16W
	Q6214	DTC144EE	TRANSISTOR		R1045	NRSA6AJ-822W	MG RESISTOR 8.2kΩ,1/16W
		or PDTC144EE	TRANSISTOR		R1046	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W
		or RN1104	TRANSISTOR		R1047	NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W
		or UN9213J	TRANSISTOR		R1048	NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W
	Q6215	HN1A01FU/G/-X	PAIR TRANSISTOR		R1049	NRSA6AJ-393W	MG RESISTOR 39kΩ,1/16W
		or PUMT1	PAIR TRANSISTOR		R1050	NRSA6AJ-223W	MG RESISTOR 22kΩ,1/16W
	Q6216	2SC4617/RS/-X	TRANSISTOR		R1051	NRSA6AJ-272W	MG RESISTOR 2.7kΩ,1/16W
	Q6217	UMZ1N	PAIR TRANSISTOR,B,C		R1052	NRSA6AJ-183W	MG RESISTOR 18kΩ,1/16W
	Q6701	TPC6102	MOS FET		R1053	NRSA6AJ-154W	MG RESISTOR 150kΩ,1/16W
	D1001	DA221	DIODE		R1054	NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W
	D1302	RB501V-40-X	SB DIODE		R1055	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W
	D1602	DAP222	DIODE		R1056	NRSA6AJ-472W	MG RESISTOR 4.7kΩ,1/16W
	D1603	DAP222	DIODE		R1057	NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W
	D1604	DAP222	DIODE		R1058	NRSA6AJ-222W	MG RESISTOR 2.2kΩ,1/16W
	D5501	1SS355	DIODE		R1061	NRSA6AJ-104W	MG RESISTOR 100kΩ,1/16W
△	D6002	RB715F	SB DIODE		R1062	NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W
	D6201	EP10LA03	SB DIODE		R1080	NRSA6AJ-104W	MG RESISTOR 100kΩ,1/16W
	D6202	EP10LA03	SB DIODE		R1081	NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
	D6203	EP10LA03	SB DIODE		R1302	NRSA6AJ-472W	MG RESISTOR 4.7kΩ,1/16W
	D6204	EP10LA03	SB DIODE		R1306	NRSA6AJ-472W	MG RESISTOR 4.7kΩ,1/16W
	D6205	EP10LA03	SB DIODE		R1401	NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W
	D6206	1SS383	SB DIODE		R1402	NRSA6AJ-222W	MG RESISTOR 2.2kΩ,1/16W
	D6207	MA8091/L/-X	ZENER DIODE		R1403	NRSA6AJ-222W	MG RESISTOR 2.2kΩ,1/16W
	D6701	CRS09	SB DIODE		R1408	NRSA6AJ-472W	MG RESISTOR 4.7kΩ,1/16W
	D6702	CRS09	SB DIODE		R1409	NRSA6AJ-331W	MG RESISTOR 330Ω,1/16W
	R1001	NRSA6AJ-104W	MG RESISTOR 100kΩ,1/16W		R1410	NRSA6AJ-331W	MG RESISTOR 330Ω,1/16W
	R1002	NRSA6AJ-224W	MG RESISTOR 220kΩ,1/16W		R1411	NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W
	R1003	NRSA6AJ-472W	MG RESISTOR 4.7kΩ,1/16W		R1412	NRSA6AJ-331W	MG RESISTOR 330Ω,1/16W
	R1004	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W		R1414	NRSA6AJ-331W	MG RESISTOR 330Ω,1/16W
	R1005	NRSA6AJ-153W	MG RESISTOR 15kΩ,1/16W		R1415	NRSA6AJ-331W	MG RESISTOR 330Ω,1/16W
	R1006	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W		R1416	NRSA6AJ-331W	MG RESISTOR 330Ω,1/16W
	R1007	NRSA6AJ-334W	MG RESISTOR 330kΩ,1/16W		R1418	NRSA6AJ-221W	MG RESISTOR 220Ω,1/16W
	R1008	NRSA6AJ-561W	MG RESISTOR 560Ω,1/16W		R1419	NRSA6AJ-221W	MG RESISTOR 220Ω,1/16W
	R1009	NRSA6AJ-151W	MG RESISTOR 150Ω,1/16W		R1420	NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W
	R1010	NRSA6AJ-221W	MG RESISTOR 220Ω,1/16W		R1422	NRSA6AJ-332W	MG RESISTOR 3.3kΩ,1/16W
	R1011	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W		R1423	NRSA6AJ-332W	MG RESISTOR 3.3kΩ,1/16W
	R1012	NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W		R1424	NRSA6AJ-332W	MG RESISTOR 3.3kΩ,1/16W
	R1013	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W		R1425	NRVA6AD-753W	CMF RESISTOR 75kΩ,1/16W
	R1014	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W		R1426	NRSA6AJ-334W	MG RESISTOR 330kΩ,1/16W
	R1015	NRSA6AJ-474W	MG RESISTOR 470kΩ,1/16W		R1427	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W
	R1016	NRSA6AJ-474W	MG RESISTOR 470kΩ,1/16W		R1428	NRSA6AJ-153W	MG RESISTOR 15kΩ,1/16W
	R1017	NRSA6AJ-104W	MG RESISTOR 100kΩ,1/16W		R1429	NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W
	R1018	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W		R1430	NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W
	R1019	NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W		R1432	NRSA6AJ-820W	MG RESISTOR 82Ω,1/16W
	R1020	NRSA6AJ-331W	MG RESISTOR 330Ω,1/16W		R1434	NRSA6AJ-683W	MG RESISTOR 68kΩ,1/16W
	R1021	NRSA6AJ-331W	MG RESISTOR 330Ω,1/16W		R1436	NRSA6AJ-683W	MG RESISTOR 68kΩ,1/16W
	R1022	NRSA6AJ-331W	MG RESISTOR 330Ω,1/16W		R1437	NRVA6AD-103W	CMF RESISTOR 10kΩ,1/16W
	R1023	NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W		R1439	NRSA6AJ-332W	MG RESISTOR 3.3kΩ,1/16W
	R1024	NRSA6AJ-823W	MG RESISTOR 82kΩ,1/16W		R1440	NRSA6AJ-332W	MG RESISTOR 3.3kΩ,1/16W
	R1025	NRVA6AD-623W	CMF RESISTOR 62kΩ,1/16W		R1441	NRSA6AJ-332W	MG RESISTOR 3.3kΩ,1/16W
	R1026	NRSA6AJ-104W	MG RESISTOR 100kΩ,1/16W		R1442	NRSA6AJ-332W	MG RESISTOR 3.3kΩ,1/16W
	R1027	NRSA6AJ-104W	MG RESISTOR 100kΩ,1/16W		R1445	NRSA6AJ-101W	MG RESISTOR 100Ω,1/16W
	R1028	NRSA6AJ-185W	MG RESISTOR 1.8MΩ,1/16W		R1446	NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W
	R1029	NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W		R1447	NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W
	R1030	NRSA6AJ-104W	MG RESISTOR 100kΩ,1/16W		R1601	NRSA6AJ-681W	MG RESISTOR 680Ω,1/16W
	R1031	NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W		R1602	NRSA6AJ-124W	MG RESISTOR 120kΩ,1/16W
	R1032	NRSA6AJ-104W	MG RESISTOR 100kΩ,1/16W		R1603	NRSA6AJ-472W	MG RESISTOR 4.7kΩ,1/16W

#	△ REF No.	PART No.	PART NAME, DESCRIPTION		#	△ REF No.	PART No.	PART NAME, DESCRIPTION	
R1604		NRSA6AJ-104W	MG RESISTOR	100kΩ,1/16W	R2128		NRSA6AJ-472W	MG RESISTOR	4.7kΩ,1/16W
R1605		NRV142F-R22X	CMF RESISTOR	0.22Ω,1/4W	R2129		NRSA6AJ-332W	MG RESISTOR	3.3kΩ,1/16W
R1606		NRSA6AJ-103W	MG RESISTOR	10kΩ,1/16W	R2130		NRSA6AJ-332W	MG RESISTOR	3.3kΩ,1/16W
R1608		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R2201		NRSA6AJ-182W	MG RESISTOR	1.8kΩ,1/16W
R1609		NRV142F-R33X	CMF RESISTOR	0.33Ω,1/4W	R2202		NRSA6AJ-182W	MG RESISTOR	1.8kΩ,1/16W
R1610		NRSA6AJ-471W	MG RESISTOR	470Ω,1/16W	R2301		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R1611		NRSA6AJ-471W	MG RESISTOR	470Ω,1/16W	R2302		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R1612		NRSA6AJ-104W	MG RESISTOR	100kΩ,1/16W	R2303		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R1613		NRSA6AJ-102W	MG RESISTOR	1kΩ,1/16W	R2304		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W
R1614		NRVA6AD-682W	CMF RESISTOR	6.8kΩ,1/16W	R2305		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W
R1615		NRSA6AJ-103W	MG RESISTOR	10kΩ,1/16W	R2306		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W
R1616		NRSA6AJ-391W	MG RESISTOR	390Ω,1/16W	R2307		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W
R1617		NRSA6AJ-224W	MG RESISTOR	220kΩ,1/16W	R2308		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W
R1618		NRSA6AJ-154W	MG RESISTOR	150kΩ,1/16W	R2309		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W
R1619		NRSA6AJ-223W	MG RESISTOR	22kΩ,1/16W	R2311		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W
R1620		NRSA6AJ-103W	MG RESISTOR	10kΩ,1/16W	R3002		NRSA6AJ-105W	MG RESISTOR	1MΩ,1/16W
R1621		NRSA6AJ-103W	MG RESISTOR	10kΩ,1/16W	R3008		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R1622		NRSA6AJ-103W	MG RESISTOR	10kΩ,1/16W	R3012		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R1624		NRVA6AD-123W	CMF RESISTOR	12kΩ,1/16W	R3013		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R1625		NRSA6AJ-181W	MG RESISTOR	180Ω,1/16W	R3016		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R1626		NRSA6AJ-181W	MG RESISTOR	180Ω,1/16W	R3017		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R1628		NRVA6AD-271W	CMF RESISTOR	270Ω,1/16W	R3018		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R1629		NRSA6AJ-684W	MG RESISTOR	680kΩ,1/16W	R3019		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R1635		NRSA6AJ-472W	MG RESISTOR	4.7kΩ,1/16W	R3030		NRVA6AD-682W	CMF RESISTOR	6.8kΩ,1/16W
R1636		NRSA6AJ-103W	MG RESISTOR	10kΩ,1/16W	R3031		NRSA6AJ-472W	MG RESISTOR	4.7kΩ,1/16W
R1637		NRSA6AJ-154W	MG RESISTOR	150kΩ,1/16W	R3032		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W
R2006		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W	R3036		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W
R2007		NRSA6AJ-102W	MG RESISTOR	1kΩ,1/16W	R3048		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W
R2008		NRSA6AJ-102W	MG RESISTOR	1kΩ,1/16W	R3052		NRSA6AJ-101W	MG RESISTOR	100Ω,1/16W
R2009		NRSA6AJ-332W	MG RESISTOR	3.3kΩ,1/16W	R3054		NRSA6AJ-331W	MG RESISTOR	330Ω,1/16W
R2014		NRSA6AJ-820W	MG RESISTOR	82Ω,1/16W	R3056		NRSA6AJ-471W	MG RESISTOR	470Ω,1/16W
R2015		NRSA6AJ-820W	MG RESISTOR	82Ω,1/16W	R3057		NRSA6AJ-101W	MG RESISTOR	100Ω,1/16W
R2016		NRSA6AJ-820W	MG RESISTOR	82Ω,1/16W	R3058		NRSA6AJ-105W	MG RESISTOR	1MΩ,1/16W
R2017		NRSA6AJ-102W	MG RESISTOR	1kΩ,1/16W	R3059		NRSA6AJ-101W	MG RESISTOR	100Ω,1/16W
R2018		NRSA6AJ-103W	MG RESISTOR	10kΩ,1/16W	R3060		NRSA6AJ-105W	MG RESISTOR	1MΩ,1/16W
R2019		NRSA6AJ-2R7W	MG RESISTOR	2.7Ω,1/16W	R3061		NRSA6AJ-272W	MG RESISTOR	2.7kΩ,1/16W
R2020		NRSA6AJ-2R7W	MG RESISTOR	2.7Ω,1/16W	R3062		NRSA6AJ-124W	MG RESISTOR	120kΩ,1/16W
R2023		NRSA6AJ-102W	MG RESISTOR	1kΩ,1/16W	R3063		NRSA6AJ-124W	MG RESISTOR	120kΩ,1/16W
R2024		NRSA6AJ-183W	MG RESISTOR	18kΩ,1/16W	R3064		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R2025		NRSA6AJ-104W	MG RESISTOR	100kΩ,1/16W	R3101		NRSA6AJ-331W	MG RESISTOR	330Ω,1/16W
R2026		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W	R3102		NRSA6AJ-103W	MG RESISTOR	10kΩ,1/16W
R2027		NRSA6AJ-332W	MG RESISTOR	3.3kΩ,1/16W	R3103		NRSA6AJ-104W	MG RESISTOR	100kΩ,1/16W
R2028		NRSA6AJ-224W	MG RESISTOR	220kΩ,1/16W	R3105		NRSA6AJ-104W	MG RESISTOR	100kΩ,1/16W
R2029		NRSA6AJ-0R0W	MG RESISTOR	0Ω,1/16W	R3106		NRSA6AJ-471W	MG RESISTOR	470Ω,1/16W
R2101		NRSA6AJ-182W	MG RESISTOR	1.8kΩ,1/16W	R3113		NRSA6AJ-394W	MG RESISTOR	390kΩ,1/16W
R2102		NRSA6AJ-182W	MG RESISTOR	1.8kΩ,1/16W	R3115		NRSA6AJ-472W	MG RESISTOR	4.7kΩ,1/16W
R2103		NRSA6AJ-153W	MG RESISTOR	15kΩ,1/16W	R3117		NRSA6AJ-560W	MG RESISTOR	56Ω,1/16W
R2104		NRSA6AJ-153W	MG RESISTOR	15kΩ,1/16W	R3118		NRSA6AJ-560W	MG RESISTOR	56Ω,1/16W
R2105		NRSA6AJ-104W	MG RESISTOR	100kΩ,1/16W	R3119		NRSA6AJ-560W	MG RESISTOR	56Ω,1/16W
R2106		NRSA6AJ-104W	MG RESISTOR	100kΩ,1/16W	R3120		NRSA6AJ-560W	MG RESISTOR	56Ω,1/16W
R2107		NRSA6AJ-473W	MG RESISTOR	47kΩ,1/16W	R3121		NRSA6AJ-512W	MG RESISTOR	5.1kΩ,1/16W
R2108		NRSA6AJ-473W	MG RESISTOR	47kΩ,1/16W	R3128		NRVA6AD-272W	CMF RESISTOR	2.7kΩ,1/16W
R2109		NRSA6AJ-472W	MG RESISTOR	4.7kΩ,1/16W	R3129		NRVA6AD-362W	CMF RESISTOR	3.6kΩ,1/16W
R2110		NRSA6AJ-472W	MG RESISTOR	4.7kΩ,1/16W	R3201		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R2111		NRSA6AJ-222W	MG RESISTOR	2.2kΩ,1/16W	R3202		NRSA6AJ-100W	MG RESISTOR	10Ω,1/16W
R2112		NRSA6AJ-222W	MG RESISTOR	2.2kΩ,1/16W	R3203		NRSA6AJ-272W	MG RESISTOR	2.7kΩ,1/16W
R2113		NRSA6AJ-153W	MG RESISTOR	15kΩ,1/16W	R3204		NRSA6AJ-473W	MG RESISTOR	47kΩ,1/16W
R2114		NRSA6AJ-153W	MG RESISTOR	15kΩ,1/16W	R3208		NRSA6AJ-820W	MG RESISTOR	82Ω,1/16W
R2117		NRSA6AJ-472W	MG RESISTOR	4.7kΩ,1/16W	R3209		NRSA6AJ-101W	MG RESISTOR	100Ω,1/16W
R2118		NRSA6AJ-472W	MG RESISTOR	4.7kΩ,1/16W	R3211		NRSA6AJ-105W	MG RESISTOR	1MΩ,1/16W
R2119		NRSA6AJ-153W	MG RESISTOR	15kΩ,1/16W	R3303		NRSA6AJ-823W	MG RESISTOR	82kΩ,1/16W
R2120		NRSA6AJ-153W	MG RESISTOR	15kΩ,1/16W	R3305		NRSA6AJ-121W	MG RESISTOR	120Ω,1/16W
R2127		NRSA6AJ-472W	MG RESISTOR	4.7kΩ,1/16W	R3306		NRSA6AJ-391W	MG RESISTOR	390Ω,1/16W

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	#	△ REF No.	PART No.	PART NAME, DESCRIPTION
R3308		NRSA6AJ-152W	MG RESISTOR 1.5kΩ,1/16W	R3712		NRSA6AD-680W	MG RESISTOR 68Ω,1/16W
R3310		NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W	R3713		NRSA6AD-680W	MG RESISTOR 68Ω,1/16W
R3312		NRSA6AJ-222W	MG RESISTOR 2.2kΩ,1/16W	R3714		NRSA6AJ-123W	MG RESISTOR 12kΩ,1/16W
R3315		NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W	R3715		NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W
R3316		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W	R3717		NRSA6AJ-561W	MG RESISTOR 560Ω,1/16W
R3317		NRSA6AJ-222W	MG RESISTOR 2.2kΩ,1/16W	R3718		NRSA6AJ-561W	MG RESISTOR 560Ω,1/16W
R3318		NRSA6AJ-562W	MG RESISTOR 5.6kΩ,1/16W	R3719		NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W
R3319		NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W	R3723		NRSA6AJ-472W	MG RESISTOR 4.7kΩ,1/16W
R3320		NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W	R3724		NRSA6AJ-392W	MG RESISTOR 3.9kΩ,1/16W
R3322		NRSA6AJ-222W	MG RESISTOR 2.2kΩ,1/16W	R4202		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3323		NRSA6AJ-823W	MG RESISTOR 82kΩ,1/16W	R4203		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3324		NRSA6AJ-223W	MG RESISTOR 22kΩ,1/16W	R4204		NRSA6AJ-220W	MG RESISTOR 22Ω,1/16W
R3325		NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W	R4205		NRSA6AJ-243W	MG RESISTOR 24kΩ,1/16W
R3326		NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W	R4206		NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W
R3327		NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W	R4207		NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W
R3328		NRSA6AJ-822W	MG RESISTOR 8.2kΩ,1/16W	R4208		NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W
R3329		NRSA6AJ-105W	MG RESISTOR 1MΩ,1/16W	R4301		NRSA6AJ-101W	MG RESISTOR 100Ω,1/16W
R3330		NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W	R4303		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3331		NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W	R4305		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3332		NRSA6AJ-104W	MG RESISTOR 100kΩ,1/16W	R4307		NRSA6AD-333W	MG RESISTOR 33kΩ,1/16W
R3333		NRSA6AJ-333W	MG RESISTOR 33kΩ,1/16W	R4308		NRSA6AD-682W	MG RESISTOR 6.8kΩ,1/16W
R3334		NRSA6AJ-105W	MG RESISTOR 1MΩ,1/16W	R4309		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3335		NRSA6AJ-822W	MG RESISTOR 8.2kΩ,1/16W	R4311		NRSA6AD-272W	MG RESISTOR 2.7kΩ,1/16W
R3336		NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W	R4312		NRSA6AD-272W	MG RESISTOR 2.7kΩ,1/16W
R3337		NRSA6AJ-123W	MG RESISTOR 12kΩ,1/16W	R4313		NRSA6AD-272W	MG RESISTOR 2.7kΩ,1/16W
R3338		NRSA6AJ-273W	MG RESISTOR 27kΩ,1/16W	R4314		NRSA6AD-123W	MG RESISTOR 12kΩ,1/16W
R3339		NRSA6AJ-273W	MG RESISTOR 27kΩ,1/16W	R4315		NRSA6AD-103W	MG RESISTOR 10kΩ,1/16W
R3341		NRSA6AJ-223W	MG RESISTOR 22kΩ,1/16W	R4316		NRSA6AD-111W	MG RESISTOR 110Ω,1/16W
R3342		NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W	R4317		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3344		NRSA6AJ-820W	MG RESISTOR 82Ω,1/16W	R4318		NRSA6AJ-152W	MG RESISTOR 1.5kΩ,1/16W
R3349		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W	R4319		NRSA6AD-111W	MG RESISTOR 110Ω,1/16W
R3350		NRSA6AJ-471W	MG RESISTOR 470Ω,1/16W	R4320		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3351		NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W	R4321		NRSA6AJ-152W	MG RESISTOR 1.5kΩ,1/16W
R3352		NRSA6AJ-562W	MG RESISTOR 5.6kΩ,1/16W	R4322		NRSA6AD-111W	MG RESISTOR 110Ω,1/16W
R3353		NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W	R4323		NRSA6AD-101W	MG RESISTOR 100Ω,1/16W
R3502		NRSA6AJ-471W	MG RESISTOR 470Ω,1/16W	R4324		NRSA6AJ-152W	MG RESISTOR 1.5kΩ,1/16W
R3503		NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W	R4326		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3504		NRSA6AJ-471W	MG RESISTOR 470Ω,1/16W	R4327		NRSA6AJ-152W	MG RESISTOR 1.5kΩ,1/16W
R3505		NRSA6AJ-680W	MG RESISTOR 68Ω,1/16W	R4328		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3506		NRSA6AJ-152W	MG RESISTOR 1.5kΩ,1/16W	R4329		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3507		NRSA6AJ-123W	MG RESISTOR 12kΩ,1/16W	R4333		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3508		NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W	R4336		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3509		NRSA6AJ-181W	MG RESISTOR 180Ω,1/16W	R4337		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3510		NRSA6AJ-181W	MG RESISTOR 180Ω,1/16W	R4338		NRSA6AJ-220W	MG RESISTOR 22Ω,1/16W
R3511		NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W	R4339		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3512		NRSA6AJ-123W	MG RESISTOR 12kΩ,1/16W	R4340		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3513		NRSA6AJ-152W	MG RESISTOR 1.5kΩ,1/16W	R4341		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3514		NRSA6AJ-680W	MG RESISTOR 68Ω,1/16W	R4343		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3515		NRSA6AJ-100W	MG RESISTOR 10Ω,1/16W	R4344		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W
R3516		NRSA6AJ-152W	MG RESISTOR 1.5kΩ,1/16W	R4347		NRSA6AJ-223W	MG RESISTOR 22kΩ,1/16W
R3517		NRSA6AJ-102W	MG RESISTOR 1kΩ,1/16W	R4348		NRSA6AJ-223W	MG RESISTOR 22kΩ,1/16W
R3551		NRSA6AJ-473W	MG RESISTOR 47kΩ,1/16W	R4349		NRSA6AJ-223W	MG RESISTOR 22kΩ,1/16W
R3552		NRSA6AJ-392W	MG RESISTOR 3.9kΩ,1/16W	R4350		NRSA6AJ-223W	MG RESISTOR 22kΩ,1/16W
R3554		NRSA6AJ-471W	MG RESISTOR 470Ω,1/16W	R4351		NRSA6AJ-223W	MG RESISTOR 22kΩ,1/16W
R3555		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W	R4804		NRSA6AJ-331W	MG RESISTOR 330Ω,1/16W
R3556		NRSA6AJ-0R0W	MG RESISTOR 0Ω,1/16W	R4805		NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W
R3701		NRSA6AD-241W	MG RESISTOR 240Ω,1/16W	R4806		NRSA6AJ-683W	MG RESISTOR 68kΩ,1/16W
R3702		NRSA6AD-241W	MG RESISTOR 240Ω,1/16W	R4807		NRSA6AJ-823W	MG RESISTOR 82kΩ,1/16W
R3703		NRSA6AJ-472W	MG RESISTOR 4.7kΩ,1/16W	R4808		NRSA6AJ-243W	MG RESISTOR 24kΩ,1/16W
R3706		NRSA6AD-221W	MG RESISTOR 220Ω,1/16W	R4809		NRSA6AJ-681W	MG RESISTOR 680Ω,1/16W
R3707		NRSA6AD-221W	MG RESISTOR 220Ω,1/16W	R4810		NRSA6AJ-103W	MG RESISTOR 10kΩ,1/16W
R3708		NRSA6AJ-472W	MG RESISTOR 4.7kΩ,1/16W	R4811		NRSA6AJ-824W	MG RESISTOR 820kΩ,1/16W
R3711		NRSA6AD-680W	MG RESISTOR 68Ω,1/16W	R4812		NRSA6AJ-153W	MG RESISTOR 15kΩ,1/16W

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	#	△ REF No.	PART No.	PART NAME, DESCRIPTION	
	R4814	NRSA6AJ-105W	MG RESISTOR		R6117	NRSA6AJ-0R0W	MG RESISTOR	0Ω, 1/16W
	R4815	NRSA6AJ-472W	MG RESISTOR		R6118	NRSA6AJ-102W	MG RESISTOR	1kΩ, 1/16W
	R4816	NRSA6AJ-105W	MG RESISTOR		R6122	NRSA6AJ-104W	MG RESISTOR	100kΩ, 1/16W
	R4817	NRSA6AJ-334W	MG RESISTOR		R6124	NRSA6AJ-102W	MG RESISTOR	1kΩ, 1/16W
	R4818	NRSA6AJ-154W	MG RESISTOR		R6201	NRVA6AD-243W	CMF RESISTOR	24kΩ, 1/16W
	R4819	NRSA6AJ-103W	MG RESISTOR		R6203	NRVA6AD-123W	CMF RESISTOR	12kΩ, 1/16W
	R4820	NRSA6AJ-104W	MG RESISTOR		R6204	NRSA6AJ-473W	MG RESISTOR	47kΩ, 1/16W
	R4821	NRSA6AJ-104W	MG RESISTOR		R6205	NRSA6AJ-102W	MG RESISTOR	1kΩ, 1/16W
	R4822	NRSA6AJ-333W	MG RESISTOR		R6206	NRVA6AD-183W	CMF RESISTOR	18kΩ, 1/16W
	R4823	NRSA6AJ-102W	MG RESISTOR		R6207	NRVA6AD-153W	CMF RESISTOR	15kΩ, 1/16W
	R4824	NRSA6AJ-472W	MG RESISTOR		R6208	NRVA6AD-123W	CMF RESISTOR	12kΩ, 1/16W
	R4833	NRSA6AJ-104W	MG RESISTOR		R6209	NRVA6AD-153W	CMF RESISTOR	15kΩ, 1/16W
	R4836	NRSA6AJ-102W	MG RESISTOR		R6210	NRVA6AD-183W	CMF RESISTOR	18kΩ, 1/16W
	R4856	NRSA63J-6R8X	MG RESISTOR		R6212	NRVA6AD-472W	CMF RESISTOR	4.7kΩ, 1/16W
	R4857	NRSA63J-6R8X	MG RESISTOR		R6213	NRSA6AJ-103W	MG RESISTOR	10kΩ, 1/16W
	R4858	NRSA6AJ-333W	MG RESISTOR		R6214	NRSA6AJ-152W	MG RESISTOR	1.5kΩ, 1/16W
	R4862	NRSA63J-6R8X	MG RESISTOR		R6215	NRSA6AJ-473W	MG RESISTOR	47kΩ, 1/16W
	R4863	NRSA63J-6R8X	MG RESISTOR		R6217	NRSA6AJ-151W	MG RESISTOR,B,C	150Ω, 1/16W
	R4864	NRSA6AJ-102W	MG RESISTOR		R6218	NRSA6AJ-104W	MG RESISTOR,B,C	100kΩ, 1/16W
	R4865	NRSA6AJ-102W	MG RESISTOR		R6219	NRVA6AD-243W	CMF RESISTOR	24kΩ, 1/16W
	R4866	NRSA6AJ-102W	MG RESISTOR		R6220	NRVA6AD-302W	CMF RESISTOR	3kΩ, 1/16W
	R4867	NRSA6AJ-102W	MG RESISTOR		R6221	NRVA6AD-104W	CMF RESISTOR	100kΩ, 1/16W
	R4868	NRSA6AJ-0R0W	MG RESISTOR		R6223	NRVA6AD-123W	CMF RESISTOR	12kΩ, 1/16W
	R4870	NRSA6AJ-271W	MG RESISTOR		R6224	NRVA6AD-473W	CMF RESISTOR	47kΩ, 1/16W
	R4874	NRSA6AJ-0R0W	MG RESISTOR		R6225	NRVA6AD-562W	CMF RESISTOR	5.6kΩ, 1/16W
	R5501	NRSA6AJ-0R0W	MG RESISTOR		R6226	NRVA6AD-223W	CMF RESISTOR	22kΩ, 1/16W
	R5503	NRSA6AJ-0R0W	MG RESISTOR		R6227	NRVA6AD-473W	CMF RESISTOR	47kΩ, 1/16W
	R5504	NRSA6AJ-0R0W	MG RESISTOR		R6228	NRVA6AD-473W	CMF RESISTOR	47kΩ, 1/16W
	R5505	NRSA6AJ-0R0W	MG RESISTOR		R6229	NRVA6AD-332W	CMF RESISTOR	3.3kΩ, 1/16W
	R5506	NRSA6AJ-0R0W	MG RESISTOR		R6230	NRSA6AJ-272W	MG RESISTOR	2.7kΩ, 1/16W
	R5507	NRSA6AJ-0R0W	MG RESISTOR		R6231	NRVA6AD-104W	CMF RESISTOR	100kΩ, 1/16W
	R5509	NRSA6AJ-470W	MG RESISTOR		R6232	NRVA6AD-473W	CMF RESISTOR	47kΩ, 1/16W
	R5510	NRSA6AJ-470W	MG RESISTOR		R6233	NRSA6AJ-822W	MG RESISTOR	8.2kΩ, 1/16W
	R5511	NRSA6AJ-470W	MG RESISTOR		R6234	NRSA6AJ-273W	MG RESISTOR	27kΩ, 1/16W
	R5512	NRSA6AJ-102W	MG RESISTOR		R6235	NRVA6AD-683W	CMF RESISTOR	68kΩ, 1/16W
	R5513	NRSA6AJ-102W	MG RESISTOR		R6236	NRVA6AD-473W	CMF RESISTOR	47kΩ, 1/16W
	R5514	NRSA6AJ-102W	MG RESISTOR		R6237	NRVA6AD-753W	CMF RESISTOR	75kΩ, 1/16W
	R5517	NRSA6AJ-0R0W	MG RESISTOR		R6238	NRVA6AD-104W	CMF RESISTOR	100kΩ, 1/16W
	R6001	NRSA6AJ-104W	MG RESISTOR		R6239	NRSA6AJ-103W	MG RESISTOR	10kΩ, 1/16W
	R6002	NRSA6AJ-104W	MG RESISTOR		R6240	NRSA6AJ-333W	MG RESISTOR	33kΩ, 1/16W
	R6003	NRSA6AJ-224W	MG RESISTOR		R6241	NRSA6AJ-102W	MG RESISTOR	1kΩ, 1/16W
	R6004	NRSA6AJ-183W	MG RESISTOR		R6242	NRSA6AJ-104W	MG RESISTOR,B,C	100kΩ, 1/16W
	R6005	NRSA6AJ-104W	MG RESISTOR		R6243	NRSA6AJ-823W	MG RESISTOR,B,C	82kΩ, 1/16W
△	R6009	NRSA63J-102X	MG RESISTOR		R6244	NRSA6AJ-152W	MG RESISTOR,B,C	1.5kΩ, 1/16W
	R6010	NRSA6AJ-473W	MG RESISTOR		R6245	NRSA6AJ-562W	MG RESISTOR,B,C	5.6kΩ, 1/16W
	R6011	NRSA6AJ-102W	MG RESISTOR		R6246	NRSA6AJ-222W	MG RESISTOR,B,C	2.2kΩ, 1/16W
	R6012	NRVA6AD-104W	CMF RESISTOR		R6701	NRZ0058-R20X	MG RESISTOR	0.2Ω, 1/2W
	R6013	NRVA6AD-683W	CMF RESISTOR		R6702	NRVA6AD-104W	CMF RESISTOR	100kΩ, 1/16W
	R6015	NRVA6AD-104W	CMF RESISTOR		R6703	NRVA6AD-123W	CMF RESISTOR	12kΩ, 1/16W
	R6016	NRVA6AD-333W	CMF RESISTOR		R6712	NRVA6AD-823W	CMF RESISTOR	82kΩ, 1/16W
	R6101	NRVA6AD-103W	CMF RESISTOR		R6713	NRVA6AD-333W	CMF RESISTOR	33kΩ, 1/16W
	R6102	NRVA6AD-751W	CMF RESISTOR		RA1001	NRZ0034-102W	NETWORK RESISTOR	1kΩ
	R6103	NRVA6AD-333W	CMF RESISTOR		RA1002	NRZ0034-102W	NETWORK RESISTOR	1kΩ
	R6104	NRSA6AJ-104W	MG RESISTOR		RA1003	NRZ0034-102W	NETWORK RESISTOR	1kΩ
	R6105	NRVA6AD-123W	CMF RESISTOR		RA1004	NRZ0034-102W	NETWORK RESISTOR	1kΩ
	R6106	NRSA6AJ-333W	MG RESISTOR		RA1005	NRZ0034-102W	NETWORK RESISTOR	1kΩ
	R6107	NRVA6AD-562W	CMF RESISTOR		RA1006	NRZ0034-102W	NETWORK RESISTOR	1kΩ
	R6108	NRSA6AJ-223W	MG RESISTOR		RA1007	NRZ0034-102W	NETWORK RESISTOR	1kΩ
	R6110	NRSA6AJ-0R0W	MG RESISTOR		RA1008	NRZ0034-104W	NETWORK RESISTOR	100kΩ
	R6113	NRSA6AJ-472W	MG RESISTOR		RA1009	NRZ0034-104W	NETWORK RESISTOR	100kΩ
	R6114	NRSA6AJ-823W	MG RESISTOR		RA1010	NRZ0034-104W	NETWORK RESISTOR	100kΩ
	R6115	NRSA6AJ-823W	MG RESISTOR		RA1401	NRZ0034-473W	NETWORK RESISTOR	47kΩ
	R6116	NRVA6AD-153W	CMF RESISTOR		RA1403	NRZ0034-102W	NETWORK RESISTOR	1kΩ

#	△ REF No.	PART No.	PART NAME, DESCRIPTION		#	△ REF No.	PART No.	PART NAME, DESCRIPTION	
	RA3001	NRZ0034-100W	NETWORK RESISTOR	10Ω		C1603	NBE21AM-106X	T CAPACITOR	10μF,10V
	RA3002	NRZ0034-100W	NETWORK RESISTOR	10Ω		C1605	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	RA4301	NRZ0034-101W	NETWORK RESISTOR	100Ω		C1606	NCB31HK-152X	CAPACITOR	0.0015μF,50V
	RA4302	NRZ0034-101W	NETWORK RESISTOR	100Ω		C1607	NCBA1AK-473W	CAPACITOR	0.047μF,10V
	RA4303	NRZ0034-101W	NETWORK RESISTOR	100Ω		C1614	NBE21AM-106X	T CAPACITOR	10μF,10V
	C1001	NBE20JM-226X	T CAPACITOR	22μF,6.3V		C1618	NCBA1HK-222W	CAPACITOR	0.0022μF,50V
△	C1002	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C1619	NCBA1HK-222W	CAPACITOR	0.0022μF,50V
	C1003	NBE20JM-226X	T CAPACITOR	22μF,6.3V		C1620	NCBA1HK-222W	CAPACITOR	0.0022μF,50V
	C1004	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C1621	NCB21CK-105X	CAPACITOR	1μF,16V
	C1005	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C1622	NCBA1CK-223W	CAPACITOR	0.022μF,16V
	C1006	NDCA1HJ-130W	CAPACITOR	13pF,50V		C1623	NCBA1AK-473W	CAPACITOR	0.047μF,10V
	C1007	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C1624	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C1009	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C1625	NCBA1AK-473W	CAPACITOR	0.047μF,10V
	C1010	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C1626	NCBA1HK-331W	CAPACITOR	330pF,50V
	C1011	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C1627	NCBA1CK-822W	CAPACITOR	0.0082μF,16V
	C1012	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C1628	NCB21CK-224X	CAPACITOR	0.22μF,16V
	C1014	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C1632	NBE21AM-106X	T CAPACITOR	10μF,10V
	C1015	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C1633	NCB21CK-474X	CAPACITOR	0.47μF,16V
	C1016	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C1635	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C1017	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C1641	NCB21CK-474X	CAPACITOR	0.47μF,16V
	C1019	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C2001	NBE20JM-106X	T CAPACITOR	10μF,6.3V
	C1023	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2002	NBE20JM-106X	T CAPACITOR	10μF,6.3V
	C1026	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2004	NCB21CK-105X	CAPACITOR	1μF,16V
	C1027	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C2005	NCB21CK-105X	CAPACITOR	1μF,16V
	C1028	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C2006	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C1029	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C2007	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C1030	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C2008	NCB21CK-105X	CAPACITOR	1μF,16V
	C1031	NCB30JK-105X	CAPACITOR	1μF,6.3V		C2009	NCB21CK-105X	CAPACITOR	1μF,16V
	C1034	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2010	NCB21CK-105X	CAPACITOR	1μF,16V
	C1035	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2011	NBE20JM-106X	T CAPACITOR	10μF,6.3V
	C1036	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2012	NBE20JM-106X	T CAPACITOR	10μF,6.3V
	C1037	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2013	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C1038	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2014	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C1039	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2015	NBE20JM-106X	T CAPACITOR	10μF,6.3V
	C1040	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2016	NCBA1CK-223W	CAPACITOR	0.022μF,16V
	C1041	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2017	NCBA1AK-333W	CAPACITOR	0.033μF,10V
	C1042	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C2018	NCB31CK-104X	CAPACITOR	0.1μF,16V
	C1301	NCBA1AK-104W	CAPACITOR	0.1μF,10V		C2019	NCB31CK-104X	CAPACITOR	0.1μF,16V
	C1302	NCBA1AK-104W	CAPACITOR	0.1μF,10V		C2020	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C1303	NCBA1AK-104W	CAPACITOR	0.1μF,10V		C2021	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C1304	NCBA1AK-104W	CAPACITOR	0.1μF,10V		C2101	NCB31CK-104X	CAPACITOR	0.1μF,16V
	C1305	NCBA1AK-104W	CAPACITOR	0.1μF,10V		C2102	NCB31CK-104X	CAPACITOR	0.1μF,16V
	C1306	NCBA1AK-104W	CAPACITOR	0.1μF,10V		C2103	NCB21CK-105X	CAPACITOR	1μF,16V
	C1307	NCBA1AK-104W	CAPACITOR	0.1μF,10V		C2104	NCB21CK-105X	CAPACITOR	1μF,16V
	C1401	NBE20JM-106X	T CAPACITOR	10μF,6.3V		C2109	NBE20JM-106X	T CAPACITOR	10μF,6.3V
	C1402	NBE20JM-106X	T CAPACITOR	10μF,6.3V		C2110	NCB21CK-105X	CAPACITOR	1μF,16V
	C1405	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2111	NCBA1EK-472W	CAPACITOR	0.0047μF,25V
	C1406	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2112	NCBA1EK-472W	CAPACITOR	0.0047μF,25V
	C1408	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2113	NCBA1EK-472W	CAPACITOR	0.0047μF,25V
	C1409	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2114	NCBA1EK-472W	CAPACITOR	0.0047μF,25V
	C1410	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2115	NCB31CK-104X	CAPACITOR	0.1μF,16V
	C1411	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2116	NCB31CK-104X	CAPACITOR	0.1μF,16V
	C1412	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2121	NCBA1CK-223W	CAPACITOR	0.022μF,16V
	C1413	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C2122	NCBA1CK-223W	CAPACITOR	0.022μF,16V
	C1414	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C2123	NCBA1CK-223W	CAPACITOR	0.022μF,16V
	C1415	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C2124	NCBA1CK-223W	CAPACITOR	0.022μF,16V
	C1416	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C2125	NCBA1CK-223W	CAPACITOR	0.022μF,16V
	C1417	NCBA1CK-223W	CAPACITOR	0.022μF,16V		C2126	NCBA1CK-223W	CAPACITOR	0.022μF,16V
	C1418	NCBA1CK-223W	CAPACITOR	0.022μF,16V		C2131	NCBA1HK-102W	CAPACITOR	0.001μF,50V
	C1419	NCBA1CK-223W	CAPACITOR	0.022μF,16V		C2132	NCBA1HK-102W	CAPACITOR	0.001μF,50V
	C1420	NCBA1CK-223W	CAPACITOR	0.022μF,16V		C2133	NCBA1CK-223W	CAPACITOR	0.022μF,16V
	C1601	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C2134	NCBA1CK-223W	CAPACITOR	0.022μF,16V
	C1602	NBE21AM-106X	T CAPACITOR	10μF,10V		C2201	NCBA1CK-103W	CAPACITOR	0.01μF,16V

#	△ REF No.	PART No.	PART NAME, DESCRIPTION		#	△ REF No.	PART No.	PART NAME, DESCRIPTION	
	C2202	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3311	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C2301	NBE20JM-106X	T CAPACITOR	10μF,6.3V		C3312	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C2302	NCB31CK-104X	CAPACITOR	0.1μF,16V		C3313	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C2304	NDCA1HJ-101W	CAPACITOR	100pF,50V		C3314	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C2306	NDCA1HJ-101W	CAPACITOR	100pF,50V		C3315	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C2307	NDCA1HJ-101W	CAPACITOR	100pF,50V		C3316	NCB20JK-225X	CAPACITOR	2.2μF,6.3V
	C3003	NBE20JM-106X	T CAPACITOR	10μF,6.3V		C3317	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C3004	NBE20GM-226X	T CAPACITOR	22μF,4.0V		C3318	NCBA1AK-683W	CAPACITOR	0.068μF,10V
	C3006	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3319	NCB20JK-225X	CAPACITOR	2.2μF,6.3V
	C3009	NDCA1HJ-100W	CAPACITOR	10pF,50V		C3320	NCBA1AK-333W	CAPACITOR	0.033μF,10V
	C3010	NDCA1HJ-100W	CAPACITOR	10pF,50V		C3321	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3011	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3322	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C3012	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3324	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3022	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3325	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3023	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3326	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C3027	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3327	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C3028	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3328	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C3035	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3329	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3037	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3330	NDCA1HJ-100W	CAPACITOR	10pF,50V
	C3038	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3331	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C3040	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3332	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3041	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3501	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3042	NCB30JK-474X	CAPACITOR	0.47μF,6.3V		C3502	NCB30JK-105X	CAPACITOR	1μF,6.3V
	C3043	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3503	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3048	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3504	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3049	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3505	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3050	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3506	NCBA1HK-152W	CAPACITOR	0.0015μF,50V
	C3101	NDCA1EJ-271W	CAPACITOR	270pF,25V		C3507	NBE90JM-106X	T CAPACITOR	10μF,6.3V
	C3102	NCB30JK-105X	CAPACITOR	1μF,6.3V		C3508	NDCA1HJ-330W	CAPACITOR	33pF,50V
	C3103	NCB30JK-105X	CAPACITOR	1μF,6.3V		C3509	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3104	NCB30JK-105X	CAPACITOR	1μF,6.3V		C3510	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3105	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3511	NDCA1HJ-220W	CAPACITOR	22pF,50V
	C3106	NBE20JM-106X	T CAPACITOR	10μF,6.3V		C3512	NBE90JM-106X	T CAPACITOR	10μF,6.3V
	C3107	NBE20JM-106X	T CAPACITOR	10μF,6.3V		C3513	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3108	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3514	NBE90JM-106X	T CAPACITOR	10μF,6.3V
	C3109	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3515	NDCA1HJ-220W	CAPACITOR	22pF,50V
	C3201	NBE20JM-106X	T CAPACITOR	10μF,6.3V		C3516	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3202	NCB30JK-105X	CAPACITOR	1μF,6.3V		C3517	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3203	NBE20JM-106X	T CAPACITOR	10μF,6.3V		C3518	NDCA1HJ-330W	CAPACITOR	33pF,50V
	C3205	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3519	NBE90JM-106X	T CAPACITOR	10μF,6.3V
	C3206	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3520	NCBA1HK-152W	CAPACITOR	0.0015μF,50V
	C3207	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3521	NCBA1HK-122W	CAPACITOR	0.0012μF,50V
	C3208	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3522	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3209	NCBA1AK-104W	CAPACITOR	0.1μF,10V		C3523	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3210	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3524	NDCA1HJ-470W	CAPACITOR	47pF,50V
	C3211	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3525	NCBA1HK-681W	CAPACITOR	680pF,50V
	C3212	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3526	NBE90JM-106X	T CAPACITOR	10μF,6.3V
	C3213	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3527	NBE90JM-106X	T CAPACITOR	10μF,6.3V
	C3214	NCBA1AK-104W	CAPACITOR	0.1μF,10V		C3528	NBE90JM-106X	T CAPACITOR	10μF,6.3V
	C3215	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3529	NCBA1AK-104W	CAPACITOR	0.1μF,10V
	C3216	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3551	NBE40JM-476X	T CAPACITOR	47μF,6.3V
	C3217	NCFA1AZ-104W	CAPACITOR	0.1μF,10V		C3552	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3221	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3701	NBE20JM-106X	T CAPACITOR	10μF,6.3V
	C3222	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3702	NDCA1HJ-151W	CAPACITOR	150pF,50V
	C3301	NCB30JK-105X	CAPACITOR	1μF,6.3V		C3703	NDCA1HJ-330W	CAPACITOR	33pF,50V
	C3302	NBE20JM-106X	T CAPACITOR	10μF,6.3V		C3704	NDCA1HJ-101W	CAPACITOR	100pF,50V
	C3303	NBE20JM-106X	T CAPACITOR	10μF,6.3V		C3705	NDCA1HJ-330W	CAPACITOR	33pF,50V
	C3304	NCB30JK-105X	CAPACITOR	1μF,6.3V		C3706	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3305	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3707	NCFA1AZ-104W	CAPACITOR	0.1μF,10V
	C3306	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3708	NCB30JK-105X	CAPACITOR	1μF,6.3V
	C3308	NCBA1CK-103W	CAPACITOR	0.01μF,16V		C3709	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3309	NCBA1HK-102W	CAPACITOR	0.001μF,50V		C3710	NCBA1CK-103W	CAPACITOR	0.01μF,16V
	C3310	NDCA1HJ-151W	CAPACITOR	150pF,50V		C3711	NBE20GM-226X	T CAPACITOR	22μF,4.0V

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	#	△ REF No.	PART No.	PART NAME, DESCRIPTION	
C3712		NBE40GM-107X	T CAPACITOR	100μF,4.0V	C4350	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C3713		NEA70GM-337X	E CAPACITOR	330μF,4.0V	C4803	NBE20JM-106X	T CAPACITOR	10μF,6.3V
C4201		NBE40GM-107X	T CAPACITOR	100μF,4.0V	C4804	NCFA1AZ-104W	CAPACITOR	0.1μF,10V
C4202		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4805	NCFA1AZ-104W	CAPACITOR	0.1μF,10V
C4203		NCB30JK-105X	CAPACITOR	1μF,6.3V	C4806	NCFA1AZ-104W	CAPACITOR	0.1μF,10V
C4204		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4808	NCB30JK-105X	CAPACITOR	1μF,6.3V
C4205		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4809	NCFA1AZ-104W	CAPACITOR	0.1μF,10V
C4206		NCB21CK-105X	CAPACITOR	1μF,16V	C4810	NCBA1CK-103W	CAPACITOR	0.01μF,16V
C4207		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4811	NCBA1CK-103W	CAPACITOR	0.01μF,16V
C4208		NCBA1HK-392W	CAPACITOR	0.0039μF,50V	C4812	NCFA1AZ-104W	CAPACITOR	0.1μF,10V
C4209		NCB30JK-105X	CAPACITOR	1μF,6.3V	C4813	NCFA1AZ-104W	CAPACITOR	0.1μF,10V
C4210		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4814	NCFA1AZ-104W	CAPACITOR	0.1μF,10V
C4211		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4815	NCB31HK-152X	CAPACITOR	0.0015μF,50V
C4212		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4819	NCB31CK-104X	CAPACITOR	0.1μF,16V
C4213		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4851	NBE20JM-106X	T CAPACITOR	10μF,6.3V
C4214		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4852	NCFA1AZ-104W	CAPACITOR	0.1μF,10V
C4215		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4853	NBE21AM-335X	T CAPACITOR	3.3μF,10V
C4216		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4854	NBE21AM-106X	T CAPACITOR	10μF,10V
C4301		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4855	NCB31CK-104X	CAPACITOR	0.1μF,16V
C4303		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4858	NDCA1HJ-330W	CAPACITOR	33pF,50V
C4304		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4859	NCBA1HK-102W	CAPACITOR	0.001μF,50V
C4305		NBE20JM-106X	T CAPACITOR	10μF,6.3V	C4860	NCBA1HK-102W	CAPACITOR	0.001μF,50V
C4306		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4861	NCBA1HK-102W	CAPACITOR	0.001μF,50V
C4307		NBE20JM-106X	T CAPACITOR	10μF,6.3V	C4862	NCBA1HK-102W	CAPACITOR	0.001μF,50V
C4308		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4864	NBE20JM-106X	T CAPACITOR	10μF,6.3V
C4309		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C4865	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4310		NBE20JM-106X	T CAPACITOR	10μF,6.3V	C5501	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4311		NCB30JK-105X	CAPACITOR	1μF,6.3V	C5503	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4312		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5504	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4313		NBE20JM-226X	T CAPACITOR	22μF,6.3V	C5505	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4314		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5506	NBE40GM-476X	T CAPACITOR	47μF,4.0V
C4315		NBE20JM-106X	T CAPACITOR	10μF,6.3V	C5507	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4317		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5508	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4318		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5509	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4319		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5510	NBP21VM-105X	T CAPACITOR	1μF,35V
C4320		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5511	NBP21DM-475X	T CAPACITOR	4.7μF,20V
C4321		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5512	NBE21AM-106X	T CAPACITOR	10μF,10V
C4323		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5513	NCB31CK-104X	CAPACITOR	0.1μF,16V
C4324		NBE20JM-106X	T CAPACITOR	10μF,6.3V	C5514	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4325		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5515	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4327		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5516	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4328		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5517	NCB31CK-104X	CAPACITOR	0.1μF,16V
C4329		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5518	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4330		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C5519	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4331		NBE20JM-106X	T CAPACITOR	10μF,6.3V	C5520	NCBA1CK-103W	CAPACITOR	0.01μF,16V
C4332		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6001	NCBA1CK-103W	CAPACITOR	0.01μF,16V
C4333		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6004	NCB21CK-105X	CAPACITOR	1μF,16V
C4334		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6005	NDCA1HJ-101W	CAPACITOR	100pF,50V
C4335		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6101	NCB21CK-105X	CAPACITOR	1μF,16V
C4336		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6102	NEA71CM-106X	E CAPACITOR	10μF,16V
C4337		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6103	NCB21CK-105X	CAPACITOR	1μF,16V
C4338		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6105	NCB21CK-105X	CAPACITOR	1μF,16V
C4339		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6106	NCB21CK-105X	CAPACITOR	1μF,16V
C4340		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6107	NCB21CK-105X	CAPACITOR	1μF,16V
C4341		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6108	NCB21CK-105X	CAPACITOR	1μF,16V
C4342		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6109	NCB21CK-105X	CAPACITOR	1μF,16V
C4343		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6110	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4344		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6111	NCBA1AK-104W	CAPACITOR	0.1μF,10V
C4345		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6112	NCBA1AK-333W	CAPACITOR	0.033μF,10V
C4346		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6113	NCBA1HK-561W	CAPACITOR	560pF,50V
C4347		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6114	NCBA1HK-272W	CAPACITOR	0.0027μF,50V
C4348		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6115	NCBA1HK-561W	CAPACITOR	560pF,50V
C4349		NCBA1AK-104W	CAPACITOR	0.1μF,10V	C6116	NCBA1CK-103W	CAPACITOR	0.01μF,16V



#	△ REF No.	PART No.	PART NAME, DESCRIPTION	#	△ REF No.	PART No.	PART NAME, DESCRIPTION
C6117		NCBA1AK-104W	CAPACITOR 0.1μF,10V	L3102		NQR0269-017X	FERRITE BEAD
C6118		NCBA1AK-104W	CAPACITOR 0.1μF,10V	L3103		NQR0384-003X	COIL
C6119		NDCA1HJ-101W	CAPACITOR 100pF,50V	L3104		NQR0384-003X	COIL
C6120		NCB11CK-105X	CAPACITOR 1μF,16V	L3201		NQR0006-001X	FERRITE BEAD
C6121		NCB31CK-104X	CAPACITOR 0.1μF,16V	L3202		NQR0129-002X	FERRITE BEAD
C6122		NCBA1CK-223W	CAPACITOR 0.022μF,16V	L3203		NQR0129-002X	FERRITE BEAD
C6123		NCBA1CK-103W	CAPACITOR 0.01μF,16V	L3301		NQR0006-001X	FERRITE BEAD
C6124		NCBA1CK-103W	CAPACITOR 0.01μF,16V	L3302		NQL04DK-100X	COIL 10μH
C6125		NCBA1CK-103W	CAPACITOR 0.01μF,16V	L3303		NQL04DK-100X	COIL 10μH
C6126		NCBA1CK-103W	CAPACITOR 0.01μF,16V	L3304		NQR0006-001X	FERRITE BEAD
C6127		NCBA1HK-102W	CAPACITOR 0.001μF,50V	L3501		NQL04DK-220X	COIL 22μH
C6128		NCB21CK-105X	CAPACITOR 1μF,16V	L3502		NQL04DK-220X	COIL 22μH
C6129		NCBA1HK-561W	CAPACITOR 560pF,50V	L3503		NQL302N-100X	COIL 10μH
C6130		NCBA1AK-104W	CAPACITOR 0.1μF,10V	L3504		NQL302N-100X	COIL 10μH
C6131		NCBA1AK-104W	CAPACITOR 0.1μF,10V	L3505		NQL38DK-100X	COIL 10μH
C6132		NCBA1AK-104W	CAPACITOR 0.1μF,10V	L3551		NQR0006-001X	FERRITE BEAD
C6133		NCBA1AK-104W	CAPACITOR 0.1μF,10V	L3701		NQL315K-100X	COIL 10μH
C6134		NCBA1AK-104W	CAPACITOR 0.1μF,10V	L4201		NQR0129-002X	FERRITE BEAD
C6201		NCB21CK-105X	CAPACITOR 1μF,16V	L4301		NQR0129-002X	FERRITE BEAD
C6202		NCB10JK-106X	CAPACITOR 10μF,6.3V	L4302		NQR0129-002X	FERRITE BEAD
C6203		NCBA1HK-102W	CAPACITOR 0.001μF,50V	L4303		NQL315K-100X	COIL 10μH
C6204		NCBA1HK-561W	CAPACITOR 560pF,50V	L4304		NQL315K-220X	COIL 22μH
C6205		NCB21CK-105X	CAPACITOR 1μF,16V	L4305		NQR0129-002X	FERRITE BEAD
C6206		NCB21CK-105X	CAPACITOR 1μF,16V	L4306		NQR0129-002X	FERRITE BEAD
C6207		NCB10JK-106X	CAPACITOR 10μF,6.3V	L4307		NQL315K-100X	COIL 10μH
C6208		NCBA1EK-472W	CAPACITOR 0.0047μF,25V	L4802		NQL302N-100X	COIL 10μH
C6209		NCB21CK-105X	CAPACITOR 1μF,16V	L4851		NQR0129-002X	FERRITE BEAD
C6210		NCB10JK-106X	CAPACITOR 10μF,6.3V	L4852		NQL315K-100X	COIL 10μH
C6211		NCBA1HK-102W	CAPACITOR 0.001μF,50V	L4853		NQL315K-100X	COIL 10μH
C6212		NCB21CK-104X	CAPACITOR,B,C 0.1μF,16V	L5501		NQL315K-100X	COIL 10μH
C6213		NCB11EK-105X	CAPACITOR,B,C 1μF,25V	L5502		NQR0129-002X	FERRITE BEAD
C6214		NCB21CK-105X	CAPACITOR 1μF,16V	L5503		NQR0129-002X	FERRITE BEAD
C6215		NCB21CK-105X	CAPACITOR 1μF,16V	L5504		NQR0129-002X	FERRITE BEAD
C6216		NCBA1AK-683W	CAPACITOR 0.068μF,10V	L5505		NQL315K-100X	COIL 10μH
C6217		NCB21CK-105X	CAPACITOR 1μF,16V	L5506		NQL315K-100X	COIL 10μH
C6218		NCB21CK-105X	CAPACITOR 1μF,16V	L6101		NQLZ011-4R7X	COIL 4.7μH
C6219		NCB21CK-224X	CAPACITOR 0.22μF,16V	L6102		NQLZ011-4R7X	COIL 4.7μH
C6220		NCB21CK-105X	CAPACITOR 1μF,16V	L6201		NQLZ011-390X	COIL 39μH
C6221		NCB11EK-105X	CAPACITOR 1μF,25V	L6202		NQLZ011-390X	COIL 39μH
C6222		NCB11EK-105X	CAPACITOR 1μF,25V	L6203		NQLZ011-390X	COIL 39μH
C6224		NCBA1HK-102W	CAPACITOR 0.001μF,50V	L6204		NQL144K-220X	COIL 22μH
C6225		NCBA1CK-103W	CAPACITOR 0.01μF,16V	L6205		NQL35BK-100X	COIL,B,C 10μH
C6226		NCB21CK-105X	CAPACITOR 1μF,16V	L6206		NQLZ011-470X	COIL 47μH
C6227		NCB11EK-105X	CAPACITOR 1μF,25V	L6207		NQLZ011-470X	COIL 47μH
C6228		NCB11EK-105X	CAPACITOR 1μF,25V	L6208		NQLZ011-221X	COIL 220μH
C6230		NCB21CK-105X	CAPACITOR 1μF,16V	L6209		NQL144K-221X	COIL 220μH
C6231		NCBA1CK-103W	CAPACITOR 0.01μF,16V	L6210		NQL144K-220X	COIL 22μH
C6701		NCB21CK-105X	CAPACITOR 1μF,16V	L6701		NQLZ007-100X	COIL 10μH
C6703		NCB11CK-105X	CAPACITOR 1μF,16V	X1001		NAX0474-001X	C OSCILLATOR
L1001		NQL315K-100X	COIL 10μH	X1002		NAX0325-001X	CRYSTAL RESONATOR
L1002		NQL315K-100X	COIL 10μH	X3001		NAX0206-001X	CRYSTAL RESONATOR
L1401		NQR0006-001X	FERRITE BEAD	X3301		NAX0296-001X	C OSCILLATOR
L1402		NRSA02J-0R0X	MG RESISTOR 0Ω, 1/10W	X5501		NAX0356-001X	CXO
L2001		NQL315K-100X	COIL 10μH	S6001		NSW0096-001X	SLIDE SWITCH
L2002		NQL38DK-220X	COIL 22μH	WR1		WJT0045-001A	E-CARD WIRE,CN103-JACK
L2201		NRSA63J-0R0X	MG RESISTOR 0Ω, 1/16W	WR2		WJJ0206-001A	E-SI C WIRE C-C,CN104-REAR
L2202		NRSA63J-0R0X	MG RESISTOR 0Ω, 1/16W	J101		NNZ0041-001X	D CONNECTOR
L2203		NRSA63J-0R0X	MG RESISTOR 0Ω, 1/16W	CN101		QGF0508F1-40X	FPC CONNECTOR
L2301		NQL402M-100X	COIL 10μH	CN102		QGA1002F1-09X	CONNECTOR
L3001		NQR0129-002X	FERRITE BEAD	CN103		QGF0505F2-14X	FPC CONNECTOR
L3002		NQR0129-002X	FERRITE BEAD	CN104		QGA1002C1-10X	CONNECTOR
L3005		NQR0006-001X	FERRITE BEAD	CN105		QGB0801K2-20X	CONNECTOR
L3101		NQR0269-017X	FERRITE BEAD	CN106		QGA1201F2-03X	CONNECTOR

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	
	CN107	QGF0507F3-20X	FFC/FPC CONNECTOR	
	CN108	QGF0507F3-24X	FFC/FPC CONNECTOR	
	CN109	QGF0507F3-15X	FFC/FPC CONNECTOR	
	CN110	QGF0513F1-08X	FPC CONNECTOR	
	CN111	QGF0503C1-06V	FFC/FPC CONNECTOR	
	CN112	QGF0505F2-18X	FPC CONNECTOR	
	CN113	QGF0508F1-34X	FPC CONNECTOR	
△	F6101	NMFZ007-2R0X-K	FUSE	2.0A
	OT1	LY43017-001A	SHIELD SHEET	
	SD1	LY32080-001A	SHIELD CASE	

#	△ REF No.	PART No.	PART NAME, DESCRIPTION
---	-----------	----------	------------------------