

SECTION 5 PARTS LIST

SAFETY PRECAUTION

Parts identified by the \triangle symbol are critical for safety. Replace only with specified part numbers.

5.1 ELECTRICAL PARTS LIST

# \triangle	REF No.	PART No.	PART NAME, DESCRIPTION	# \triangle	REF No.	PART No.	PART NAME, DESCRIPTION

MAIN BOARD ASSEMBLY <03>							
PW1		LPA10131-22A1	MAIN BOARD ASSY			or RN1309	TRANSISTOR
IC1		JCP8020-MSD-2	IC			or UN521E	TRANSISTOR
IC201		LC74789N-9795	IC (OSD)	Q2054		2SA1576A/QR/-X	TRANSISTOR
IC3001		HD6432194SXD06F	IC (MCU)			or 2PA1576/R/-X	TRANSISTOR
IC3002		IC-PST3427U-X	IC			or 2SB1218A/QR/-X	TRANSISTOR
IC3003		AT24C08N-10SC-X	IC	Q2055		DTC144WU	TRANSISTOR
		or X24C08S	IC			or PDTC144WU	TRANSISTOR
		or 24LC08B/SN-X	IC			or RN1309	TRANSISTOR
		or BR24C08F	IC			or UN521E	TRANSISTOR
IC3004		BA6956AN	IC	Q2251		DTA144WU	TRANSISTOR
IC5301		L5431	IC			or PDTA144WU	TRANSISTOR
		or MM1431AT	IC			or RN2309	TRANSISTOR
		or UTCTL431	IC			or UN511E	TRANSISTOR
IC7001		PT6956	IC	Q2252		DTC114EU	TRANSISTOR
IC7002		GP1U291Q	IR DETECT UNIT			or PDTC114EU	TRANSISTOR
		or PIC-28143LJ	IR DETECT UNIT			or RN1302	TRANSISTOR
		or PNA4652M00YC	IR DETECT UNIT			or UN5211	TRANSISTOR
		or PIC-37143LJ	IR DETECT UNIT	Q3001		2SD1819A/QRS/-X	TRANSISTOR
Q1		2SC4081/S/-X	TRANSISTOR			or 2PC4081/R/-X	TRANSISTOR
Q2		2SC4081/S/-X	TRANSISTOR			or 2SC4081/QRS/-X	TRANSISTOR
Q3		2SC4081/S/-X	TRANSISTOR	Q3003		PTZ-NV16	PHOTO TRANSISTOR
Q4		2SC4081/S/-X	TRANSISTOR			or PTZ-NV16A	PHOTO TRANSISTOR
Q23		2SA1576A/QR/-X	TRANSISTOR	Q3004		2SD1819A/QRS/-X	TRANSISTOR
		or 2PA1576/R/-X	TRANSISTOR			or 2PC4081/R/-X	TRANSISTOR
Q38		2SC4081/QRS/-X	TRANSISTOR			or 2SC4081/QRS/-X	TRANSISTOR
Q39		UN521E	TRANSISTOR	Q3005		2SD1819A/QRS/-X	TRANSISTOR
		or DTC144WU	TRANSISTOR			or 2SC4081/QRS/-X	TRANSISTOR
		or PDTC144WU	TRANSISTOR			or 2PC4081/R/-X	TRANSISTOR
		or RN1309	TRANSISTOR	Q4001		UN5211	TRANSISTOR
Q41		UN521E	TRANSISTOR			or RN1302	TRANSISTOR
		or RN1309	TRANSISTOR			or DTC114EU	TRANSISTOR
		or DTC144WU	TRANSISTOR			or PDTC114EU	TRANSISTOR
		or PDTC144WU	TRANSISTOR	Q5101		2SK2632-CB14	POWER MOS FET
Q201		2SC4081/QRS/-X	TRANSISTOR			or 2SK2632	POWER MOS FET
		or 2PC4081/R/-X	TRANSISTOR			or 2SK2129	POWER MOS FET
Q2001		2SC4081/QRS/-X	TRANSISTOR			or 2SK2129-LT	POWER MOS FET
		or 2SD1819A/QRS/-X	TRANSISTOR	Q5102		2SD2144S/UV/-T	TRANSISTOR
		or 2PC4081/R/-X	TRANSISTOR	Q5302		2SD2375/QP/	TRANSISTOR
Q2002		2SC4081/QRS/-X	TRANSISTOR	Q5303		2SD1819A/RS/-X	TRANSISTOR
		or 2PC4081/R/-X	TRANSISTOR			or 2SC4081/RS/-X	TRANSISTOR
		or 2SD1819A/QRS/-X	TRANSISTOR			or 2PC4081/R/-X	TRANSISTOR
Q2003		DTA144WU	TRANSISTOR	Q5304		2SC3616/ML/-T	TRANSISTOR
		or PDTA144WU	TRANSISTOR	Q5305		DTA114EU	TRANSISTOR
		or RN2309	TRANSISTOR			or PDTA114EU	TRANSISTOR
		or UN511E	TRANSISTOR			or RN2302	TRANSISTOR
Q2006		2SC4081/QRS/-X	TRANSISTOR			or UN5111	TRANSISTOR
		or 2SD1819A/QRS/-X	TRANSISTOR	Q5306		DTC114EU	TRANSISTOR
		or 2PC4081/R/-X	TRANSISTOR			or RN1302	TRANSISTOR
Q2051		2SC4081/QRS/-X	TRANSISTOR			or UN5211	TRANSISTOR
		or 2PC4081/R/-X	TRANSISTOR			or PDTC114EU	TRANSISTOR
		or 2SD1819A/QRS/-X	TRANSISTOR	Q6030		2SB1218A/RS/-X	TRANSISTOR
Q2052		2SA1576A/QR/-X	TRANSISTOR	Q6031		DTC114EU	TRANSISTOR
		or 2SB1218A/QR/-X	TRANSISTOR			or PDTC114EU	TRANSISTOR
		or 2PA1576/R/-X	TRANSISTOR			or RN1302	TRANSISTOR
Q2053		DTC144WU	TRANSISTOR			or UN5211	TRANSISTOR
		or PDTC144WU	TRANSISTOR	Q6032		DTC114EU	TRANSISTOR
						or PDTC114EU	TRANSISTOR
						or RN1302	TRANSISTOR
						or UN5211	TRANSISTOR

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	#	△ REF No.	PART No.	PART NAME, DESCRIPTION	
	Q7001	DTA143TU	TRANSISTOR			or RD15ES/B3/-T2	ZENER DIODE	
	Q7002	DTA143TU	TRANSISTOR	D5302	QUY160-100Y		IM BUS WIRE	
	Q7003	DTA143TU	TRANSISTOR	D5303	RD5.1JS/B2/-T2		ZENER DIODE	
	Q7004	DTA143TU	TRANSISTOR			or MA4051N/M/-T2	ZENER DIODE	
	Q7005	DTA143TU	TRANSISTOR	D5304	1SS133		DIODE	
	Q7105	2SA1576A/QRS/-X	TRANSISTOR			or 1SS270A	DIODE	
		or 2PA1576/R/-X	TRANSISTOR	D5305	11ES2		DIODE	
D6		MTZJ5.6C	ZENER DIODE			or ERA15-02-T2	DIODE	
		or RD5.6ES/B3/-T2	ZENER DIODE			or 1A3G	DIODE	
D201		1SS133	DIODE	D5307	QUY160-100Y		IM BUS WIRE	
		or 1SS270A	DIODE	D5308	MTZJ11C		ZENER DIODE	
D202		1SS133	DIODE			or RD11ES/B3/-T2	ZENER DIODE	
		or 1SS270A	DIODE	D5316	QUY160-100Y		IM BUS WIRE	
D203		1SS133	DIODE	D6002	HZ30-2L-T2		ZENER DIODE	
		or 1SS270A	DIODE			or HZ30-2LTD	Z DIODE (M)	
D2101		MTZJ8.2C	ZENER DIODE	D7101	1SS133		DIODE	
D3001		LNB2301L01VI	LE DIODE	D7102	1SS133		DIODE	
D3002		1SS133	DIODE	D7103	QUY160-100Y		IM BUS WIRE	
		or 1SS270A	DIODE	R1	NRSA02J-682X		MG RESISTOR	6.8kΩ,1/10W
D3003		RD39ES/B3/-T2	ZENER DIODE	R2	NRSA02J-152X		MG RESISTOR	1.5kΩ,1/10W
		or MTZJ39C	ZENER DIODE	R3	NRSA02J-822X		MG RESISTOR	8.2kΩ,1/10W
D3004		11ES2	DIODE	R5	NRSA02J-0R0X		MG RESISTOR	0Ω,1/10W
		or 1A3G	DIODE	R6	NRSA02J-273X		MG RESISTOR	27kΩ,1/10W
D3005		11ES2	DIODE	R7	NRSA02J-821X		MG RESISTOR	820Ω,1/10W
		or 1A3G	DIODE	R8	QRE141J-101Y		RESISTOR	100Ω,1/4W
△ D3006		RB721Q-40-T2	SB DIODE	R9	QRE141J-101Y		RESISTOR	100Ω,1/4W
D4001		QUY153-050Y	IM BUS WIRE	R12	QRE141J-101Y		RESISTOR	100Ω,1/4W
D4002		QUY153-050Y	IM BUS WIRE	R21	NRSA02J-102X		MG RESISTOR	1kΩ,1/10W
D5001		S1WB/A/60-4102	BRIDGE DIODE	R22	NRSA02J-102X		MG RESISTOR	1kΩ,1/10W
		or S1WB/A/60-X	BRIDGE DIODE	R37	NRSA02J-0R0X		MG RESISTOR	0Ω,1/10W
		or S1WB(A)60F4072X	BRIDGE DIODE	R46	NRSA02J-331X		MG RESISTOR	330Ω,1/10W
D5101		AU01	FR DIODE	R50	NRSA02J-102X		MG RESISTOR	1kΩ,1/10W
		or ERA18-04-T2	FR DIODE	R77	NRSA02J-103X		MG RESISTOR	10kΩ,1/10W
		or 1SR153-400-T2	FR DIODE	R90	NRSA02J-391X		MG RESISTOR	390Ω,1/10W
		or 10ELS4	FR DIODE	R92	NRSA02J-152X		MG RESISTOR	1.5kΩ,1/10W
D5102		AU01	FR DIODE	R93	NRSA02J-222X		MG RESISTOR	2.2kΩ,1/10W
		or ERA18-04-T2	FR DIODE	R104	NRSA02J-682X		MG RESISTOR	6.8kΩ,1/10W
		or 1SR153-400-T2	FR DIODE	R202	NRSA02J-103X		MG RESISTOR	10kΩ,1/10W
		or 10ELS4	FR DIODE	R203	NRSA02J-103X		MG RESISTOR	10kΩ,1/10W
D5103		1SS133	DIODE	R204	NRSA02J-103X		MG RESISTOR	10kΩ,1/10W
		or 1SS270A	DIODE	R213	NRSA02J-222X		MG RESISTOR	2.2kΩ,1/10W
D5105		1SS133	DIODE	R216	NRSA02J-103X		MG RESISTOR	10kΩ,1/10W
		or 1SS270A	DIODE	R220	NRSA02J-0R0X		MG RESISTOR	0Ω,1/10W
D5201		AU01Z	FR DIODE	R224	NRSA02J-681X		MG RESISTOR	680Ω,1/10W
		or ERA18-02-T2	FR DIODE	R225	QUY160-100Y		IM BUS WIRE	
		or PG104RS	FR DIODE	R2001	QRE141J-681Y		RESISTOR	680Ω,1/4W
		or 10ELS2	FR DIODE	R2002	NRSA02J-272X		MG RESISTOR	2.7kΩ,1/10W
		or 1SR153-400-T2	FR DIODE	R2003	NRSA02J-101X		MG RESISTOR	100Ω,1/10W
D5203		AU01Z	FR DIODE	R2004	NRSA02J-332X		MG RESISTOR	3.3kΩ,1/10W
		or 10ELS2	FR DIODE	R2005	NRSA02J-682X		MG RESISTOR	6.8kΩ,1/10W
D5204		AU01Z	FR DIODE	R2006	NRSA02J-393X		MG RESISTOR	39kΩ,1/10W
		or 10ELS2	FR DIODE	R2007	NRSA02J-393X		MG RESISTOR	39kΩ,1/10W
D5208		RK14LF-B2	BARRIER DIODE	R2009	NRSA02J-123X		MG RESISTOR	12kΩ,1/10W
		or SB240-F26	SB DIODE	R2010	NRSA02J-123X		MG RESISTOR	12kΩ,1/10W
		or 21DQ04	BARRIER DIODE	R2013	NRSA02J-682X		MG RESISTOR	6.8kΩ,1/10W
D5210		AU01Z	FR DIODE	R2014	NRSA02J-224X		MG RESISTOR	220kΩ,1/10W
		or ERA18-02-T2	FR DIODE	R2015	NRSA02J-181X		MG RESISTOR	180Ω,1/10W
		or PG104RS	FR DIODE	R2016	NRSA02J-393X		MG RESISTOR	39kΩ,1/10W
		or 10ELS2	FR DIODE	R2017	NRSA02J-183X		MG RESISTOR	18kΩ,1/10W
		or 1SR153-400-T2	FR DIODE	R2018	NRSA02J-472X		MG RESISTOR	4.7kΩ,1/10W
D5301		MTZJ15C	ZENER DIODE	R2019	NRSA02J-472X		MG RESISTOR	4.7kΩ,1/10W

#	△	REF No.	PART No.	PART NAME, DESCRIPTION	#	△	REF No.	PART No.	PART NAME, DESCRIPTION	
R2022			NRSA02J-562X	MG RESISTOR	5.6kΩ,1/10W	R3071		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R2053			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R3072		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R2054			NRSA02J-123X	MG RESISTOR	12kΩ,1/10W	R3073		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R2055			NRSA02J-3R3X	MG RESISTOR	3.3Ω,1/10W	R3074		QRE141J-102Y	RESISTOR	1kΩ,1/4W
R2056			QRE141J-820Y	RESISTOR	82Ω,1/4W	R3075		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
R2057			NRSA02J-473X	MG RESISTOR	47kΩ,1/10W	R3076		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
R2058			NRSA02J-183X	MG RESISTOR	18kΩ,1/10W	R3077		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R2059			NRSA02J-473X	MG RESISTOR	47kΩ,1/10W	R3078		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R2060			NRSA02J-183X	MG RESISTOR	18kΩ,1/10W	R3079		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R2201			QRE141J-151Y	RESISTOR	150Ω,1/4W	R3080		NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W
R2206			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	R3081		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R2207			NRSA02J-332X	MG RESISTOR	3.3kΩ,1/10W	R3085		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R2213			NRSA02J-393X	MG RESISTOR	39kΩ,1/10W	R3086		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R2215			NRSA02J-153X	MG RESISTOR	15kΩ,1/10W	R3087		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R2217			NRSA02J-682X	MG RESISTOR	6.8kΩ,1/10W	R3088		QUY160-100Y	IM BUS WIRE	
R2218			NRSA02J-393X	MG RESISTOR	39kΩ,1/10W	R3089		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R2219			NRSA02J-393X	MG RESISTOR	39kΩ,1/10W	R3090		QRE141J-102Y	RESISTOR	1kΩ,1/4W
R2220			NRSA02J-393X	MG RESISTOR	39kΩ,1/10W	R3093		QUY160-100Y	IM BUS WIRE	
R2223			NRSA02J-123X	MG RESISTOR	12kΩ,1/10W	R3104		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R2224			QRE141J-123Y	RESISTOR	12kΩ,1/4W	R3105		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R2225			QRE141J-153Y	RESISTOR	15kΩ,1/4W	R3201		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R2228			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R3202		NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W
R2229			NRSA02J-563X	MG RESISTOR	56kΩ,1/10W	R3203		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R2251			NRSA02J-471X	MG RESISTOR	470Ω,1/10W	R3204		NRSA02J-222X	MG RESISTOR	2.2kΩ,1/10W
R3013			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R3205		QRE141J-181Y	RESISTOR	180Ω,1/4W
R3014			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R3206		NRSA02J-183X	MG RESISTOR	18kΩ,1/10W
R3015			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R3207		NRSA02J-183X	MG RESISTOR	18kΩ,1/10W
R3016			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R3208		QRE141J-181Y	RESISTOR	180Ω,1/4W
R3018			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R3209		QRE141J-273Y	RESISTOR	27kΩ,1/4W
R3020			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R3210		NRSA02J-181X	MG RESISTOR	180Ω,1/10W
R3021			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R3211		NRSA02J-273X	MG RESISTOR	27kΩ,1/10W
R3022			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R3212		NRSA02J-474X	MG RESISTOR	470kΩ,1/10W
R3026			NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R3213		NRSA02J-334X	MG RESISTOR	330kΩ,1/10W
R3027			NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R3214		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R3028			NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R3215		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R3029			QRE141J-472Y	RESISTOR	4.7kΩ,1/4W	R3216		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R3030			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R3217		NRSA02J-562X	MG RESISTOR	5.6kΩ,1/10W
R3032			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R3218		QRE141J-472Y	RESISTOR	4.7kΩ,1/4W
R3034			QUY160-100Y	IM BUS WIRE		R3219		NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W
R3035			NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R3220		NRSA02J-104X	MG RESISTOR	100kΩ,1/10W
R3036			NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	△ R3221		QRE141J-102Y	RESISTOR	1kΩ,1/4W
R3037			NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R3222		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R3038			NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R3223		NRSA02J-152X	MG RESISTOR	1.5kΩ,1/10W
R3039			QRE141J-102Y	RESISTOR	1kΩ,1/4W	R3224		NRSA02J-152X	MG RESISTOR	1.5kΩ,1/10W
R3041			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R3225		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R3042			QRE141J-102Y	RESISTOR	1kΩ,1/4W	R3226		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R3047			NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R3227		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R3048			NRSA63J-0R0X	MG RESISTOR	0Ω,1/16W	R3229		NRSA02J-105X	MG RESISTOR	1MΩ,1/10W
R3049			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	R3230		NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W
R3050			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	R3231		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R3052			NRSA02J-471X	MG RESISTOR	470Ω,1/10W	R3235		NRSA02J-332X	MG RESISTOR	3.3kΩ,1/10W
R3053			NRSA02J-471X	MG RESISTOR	470Ω,1/10W	R3236		NRSA02J-332X	MG RESISTOR	3.3kΩ,1/10W
R3054			NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R3240		NRSA02J-105X	MG RESISTOR	1MΩ,1/10W
R3055			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R3251		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R3058			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R4003		NRSA02J-561X	MG RESISTOR	560Ω,1/10W
R3059			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R4004		NRSA02J-561X	MG RESISTOR	560Ω,1/10W
R3060			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R4005		NRSA02J-562X	MG RESISTOR	5.6kΩ,1/10W
R3061			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R4007		QRE141J-102Y	RESISTOR	1kΩ,1/4W
R3062			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R4008		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R3066			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R4009		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R3069			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	R4010		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	#	△ REF No.	PART No.	PART NAME, DESCRIPTION
R4011		NRSA02J-472X	MG RESISTOR 4.7kΩ,1/10W	R7034		NRSA02J-272X	MG RESISTOR 2.7kΩ,1/10W
R4012		NRSA02J-222X	MG RESISTOR 2.2kΩ,1/10W	R7035		NRSA02J-472X	MG RESISTOR 4.7kΩ,1/10W
R4013		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R7036		NRSA02J-682X	MG RESISTOR 6.8kΩ,1/10W
R4014		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	R7037		NRSA02J-563X	MG RESISTOR 56kΩ,1/10W
R4015		NRSA02J-562X	MG RESISTOR 5.6kΩ,1/10W	R7121		NRSA02J-221X	MG RESISTOR 220Ω,1/10W
R4017		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R7123		NRSA02J-221X	MG RESISTOR 220Ω,1/10W
R4018		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R7126		NRSA02J-750X	MG RESISTOR 75Ω,1/10W
R4019		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W	R7127		NRSA02J-101X	MG RESISTOR 100Ω,1/10W
R4020		QRE141J-103Y	RESISTOR 10kΩ,1/4W	R7128		NRSA02J-101X	MG RESISTOR 100Ω,1/10W
R4021		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W	R7130		NRSA02J-750X	MG RESISTOR 75Ω,1/10W
R5101		QRE141J-224Y	RESISTOR 220kΩ,1/4W	R7131		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5102		QRE141J-224Y	RESISTOR 220kΩ,1/4W	R7132		QRE123J-331X	RESISTOR 330Ω,1/2W
R5103		QRE141J-683Y	RESISTOR 68kΩ,1/4W	R7135		NRSA63J-0R0X	MG RESISTOR 0Ω,1/16W
R5104		QRG02GJ-683	OMF RESISTOR 68kΩ,2W	R7160		NRSA02J-331X	MG RESISTOR 330Ω,1/10W
R5106		QRT01DJ-R39X	MF RESISTOR 0.39Ω,1W	R7161		NRSA02J-331X	MG RESISTOR 330Ω,1/10W
R5107		QRE121J-331Y	RESISTOR 330Ω,1/2W	R7162		NRSA02J-331X	MG RESISTOR 330Ω,1/10W
R5108		NRSA02J-152X	MG RESISTOR 1.5kΩ,1/10W	R7163		NRSA02J-750X	MG RESISTOR 75Ω,1/10W
R5109		QRE141J-681Y	RESISTOR 680Ω,1/4W	B5		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5110		NRSA02J-224X	MG RESISTOR 220kΩ,1/10W	B24		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5111		NRSA02J-681X	MG RESISTOR 680Ω,1/10W	B28		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5112		NRSA02J-221X	MG RESISTOR 220Ω,1/10W	B35		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5301		NRSA02J-472X	MG RESISTOR 4.7kΩ,1/10W	B71		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5302		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	B2051		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5303		NRSA02J-122X	MG RESISTOR 1.2kΩ,1/10W	B3002		QUY153-050Y	IM BUS WIRE
R5304		NRSA02J-471X	MG RESISTOR 470Ω,1/10W	B5001		QUY160-100Y	IM BUS WIRE
R5305		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	B5002		QUY160-100Y	IM BUS WIRE
R5306		NRSA02J-471X	MG RESISTOR 470Ω,1/10W	B5301		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5308		NRSA02J-471X	MG RESISTOR 470Ω,1/10W	B5302		QUY153-050Y	IM BUS WIRE
R5309		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W	B6510		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5310		NRSA02J-471X	MG RESISTOR 470Ω,1/10W	B6511		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5311		NRSA02J-473X	MG RESISTOR 47kΩ,1/10W	B7003		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5312		QRE141J-332Y	RESISTOR 3.3kΩ,1/4W	B7008		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5313		NRSA02D-332X	MG RESISTOR 3.3kΩ,1/10W	B7009		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5314		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	B7109		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5316		NRSA02D-103X	MG RESISTOR 10kΩ,1/10W	B7111		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5317		NRSA02J-473X	MG RESISTOR 47kΩ,1/10W	B7113		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5330		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	B7118		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R5333		QRL02DJ-391X	OMF RESISTOR 390Ω,2W	C1		NCB21HK-103X	CAPACITOR 0.01μF,50V
R5334		QRL02DJ-391X	OMF RESISTOR 390Ω,2W	C2		NCB21HK-103X	CAPACITOR 0.01μF,50V
R6020		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	C3		NCB21HK-103X	CAPACITOR 0.01μF,50V
R6021		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	C4		NCB21HK-103X	CAPACITOR 0.01μF,50V
R6030		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	C5		QEKJ0JM-227	E CAPACITOR 220μF,6.3V
R6031		NRSA02J-271X	MG RESISTOR 270Ω,1/10W	C6		NCB21EK-104X	CAPACITOR 0.1μF,25V
R6032		NRSA02J-272X	MG RESISTOR 2.7kΩ,1/10W	C8		NCB21EK-473X	CAPACITOR 0.047μF,25V
R6033		NRSA02J-562X	MG RESISTOR 5.6kΩ,1/10W	C10		NDC21HJ-151X	CAPACITOR 150pF,50V
R6050		QRE141J-101Y	RESISTOR 100Ω,1/4W	C11		NCB21EK-104X	CAPACITOR 0.1μF,25V
R6051		NRSA02J-101X	MG RESISTOR 100Ω,1/10W	C12		NDC21HJ-470X	CAPACITOR 47pF,50V
R6052		NRSA02J-101X	MG RESISTOR 100Ω,1/10W	C14		NCB21EK-104X	CAPACITOR 0.1μF,25V
R6056		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	C15		NCB21HK-103X	CAPACITOR 0.01μF,50V
R7001		NRSA02J-331X	MG RESISTOR 330Ω,1/10W	C16		NCB21EK-104X	CAPACITOR 0.1μF,25V
R7015		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	C17		QEKJ1HM-335	E CAPACITOR 3.3μF,50V
R7020		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W	C19		QEKJ1HM-225	E CAPACITOR 2.2μF,50V
R7021		NRSA02J-122X	MG RESISTOR 1.2kΩ,1/10W	C20		QEQF1HM-105	NP E CAPACITOR 1μF,50V
R7022		NRSA02J-182X	MG RESISTOR 1.8kΩ,1/10W	C21		NCB21EK-104X	CAPACITOR 0.1μF,25V
R7023		NRSA02J-222X	MG RESISTOR 2.2kΩ,1/10W	C22		QEKJ0JM-476	E CAPACITOR 47μF,6.3V
R7024		NRSA02J-272X	MG RESISTOR 2.7kΩ,1/10W	C23		NCB21EK-104X	CAPACITOR 0.1μF,25V
R7025		NRSA02J-472X	MG RESISTOR 4.7kΩ,1/10W	C24		NCB21EK-104X	CAPACITOR 0.1μF,25V
R7030		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W	C25		NDC21HJ-4R0X	CAPACITOR 4pF,50V
R7031		NRSA02J-122X	MG RESISTOR 1.2kΩ,1/10W	C27		NCB21EK-223X	CAPACITOR 0.022μF,25V
R7032		NRSA02J-182X	MG RESISTOR 1.8kΩ,1/10W	C28		QEKJ1HM-335	E CAPACITOR 3.3μF,50V
R7033		NRSA02J-222X	MG RESISTOR 2.2kΩ,1/10W	C29		NCB21EK-333X	CAPACITOR 0.033μF,25V

#	△	REF No.	PART No.	PART NAME, DESCRIPTION		#	△	REF No.	PART No.	PART NAME, DESCRIPTION		
C30			QEKJ1HM-474	E CAPACITOR	0.47μF,50V	C2215			QEKJ1HM-475	E CAPACITOR	4.7μF,50V	
C31			QEKJ0JM-476	E CAPACITOR	47μF,6.3V	C2216			QEKJ1HM-474	E CAPACITOR	0.47μF,50V	
C32			NCB21EK-104X	CAPACITOR	0.1μF,25V	C2217			QEKJ1EM-106	E CAPACITOR	10μF,25V	
C33			QEKJ1HM-225	E CAPACITOR	2.2μF,50V	C2218			QEKJ1HM-474	E CAPACITOR	0.47μF,50V	
C34			NCB21CK-224X	CAPACITOR	0.22μF,16V	C2219			QEKJ1EM-106	E CAPACITOR	10μF,25V	
C35			NCB21HK-103X	CAPACITOR	0.01μF,50V	C2220			QEKJ1HM-475	E CAPACITOR	4.7μF,50V	
C36			QERF1EM-475	E CAPACITOR	4.7μF,25V	C2221			NCB21HK-103X	CAPACITOR	0.01μF,50V	
C37			QEKJ1HM-105	E CAPACITOR	1μF,50V	C2222			QEKJ1HM-474	E CAPACITOR	0.47μF,50V	
C38			QEKJ0JM-476	E CAPACITOR	47μF,6.3V	C2223			QEKJ1HM-474	E CAPACITOR	0.47μF,50V	
C39			NCB21EK-104X	CAPACITOR	0.1μF,25V	C2224			NCB21HK-103X	CAPACITOR	0.01μF,50V	
C40			QEKJ1EM-106	E CAPACITOR	10μF,25V	C2225			QEKJ1HM-475	E CAPACITOR	4.7μF,50V	
C51			QEKJ1HM-105	E CAPACITOR	1μF,50V	C2226			QEKJ1EM-106	E CAPACITOR	10μF,25V	
C52			QEKJ1HM-105	E CAPACITOR	1μF,50V	C2227			NCB21EK-104X	CAPACITOR	0.1μF,25V	
C53			NRSA02J-0R0X	MG RESISTOR	0Ω, 1/10W	C2251			QEKJ0JM-476	E CAPACITOR	47μF,6.3V	
C62			NCB21EK-104X	CAPACITOR	0.1μF,25V	C2252			QDYB1CM-103Y	CAPACITOR	0.01μF,16V	
C64			NDC21HJ-220X	CAPACITOR	22pF,50V	C2253			NCB21HK-103X	CAPACITOR	0.01μF,50V	
C65			QEKJ1HM-105	E CAPACITOR	1μF,50V	C2254			NCB21HK-103X	CAPACITOR	0.01μF,50V	
C69			NCB21HK-103X	CAPACITOR	0.01μF,50V	C2255			NDC21HJ-181X	CAPACITOR	180pF,50V	
C70			NCB21HK-103X	CAPACITOR	0.01μF,50V	C3001			NCF21EZ-104X	CAPACITOR	0.1μF,25V	
C81			NCB21HK-103X	CAPACITOR	0.01μF,50V	C3002			NCB21HK-103X	CAPACITOR	0.01μF,50V	
C94			NRSA02J-0R0X	MG RESISTOR	0Ω, 1/10W	C3003			QEKJ1HM-106	E CAPACITOR	10μF,50V	
C106			NCB21HK-821X	CAPACITOR	820pF,50V	C3004			NCB21EK-473X	CAPACITOR	0.047μF,25V	
C108			NDC21HJ-680X	CAPACITOR	68pF,50V	C3011			QETL0JM-338	E CAPACITOR	3300μF,6.3V	
C109			NCB21CK-224X	CAPACITOR	0.22μF,16V	C3012			QEKJ0JM-476	E CAPACITOR	47μF,6.3V	
C110			NDC21HJ-820X	CAPACITOR	82pF,50V	C3014			QERF0JM-476	E CAPACITOR	47μF,6.3V	
C112			NDC21HJ-120X	CAPACITOR	12pF,50V	C3016			NCB21EK-473X	CAPACITOR	0.047μF,25V	
C114			NDC21HJ-181X	CAPACITOR	180pF,50V	C3022			NCB21EK-473X	CAPACITOR	0.047μF,25V	
C204			NCB21HK-103X	CAPACITOR	0.01μF,50V	C3024			NDC21HJ-220X	CAPACITOR	22pF,50V	
C206			NDC21HJ-330X	CAPACITOR	33pF,50V	C3025			QAT3725-300Z	TRIM CAPACITOR,TIMER CLOCK		
C207			NDC21HJ-330X	CAPACITOR	33pF,50V	C3026			NCB21HK-103X	CAPACITOR	0.01μF,50V	
C209			NCB21CK-474X	CAPACITOR	0.47μF,16V	C3027			QEKJ1CM-106	E CAPACITOR	10μF,16V	
C214			NCB21CK-224X	CAPACITOR	0.22μF,16V	C3030			QEKJ0JM-476	E CAPACITOR	47μF,6.3V	
C217			NDC21HJ-560X	CAPACITOR	56pF,50V	C3031			NCB21EK-473X	CAPACITOR	0.047μF,25V	
C218			NCB21CK-105X	CAPACITOR	1μF,16V	C3032			NCB21EK-473X	CAPACITOR	0.047μF,25V	
C222			QERF1HM-105	E CAPACITOR	1μF,50V	C3033			NCB21EK-473X	CAPACITOR	0.047μF,25V	
C226			QERF0JM-107	E CAPACITOR	100μF,6.3V	C3036			NDC21HJ-180X	CAPACITOR	18pF,50V	
C2001			QEKJ1HM-475	E CAPACITOR	4.7μF,50V	C3037			NDC21HJ-120X	CAPACITOR	12pF,50V	
C2002			QEKJ1EM-106	E CAPACITOR	10μF,25V	C3040			NCB21EK-473X	CAPACITOR	0.047μF,25V	
C2003			QEKJ0JM-476	E CAPACITOR	47μF,6.3V	C3045			NDC21HJ-101X	CAPACITOR	100pF,50V	
C2005			QEKJ1HM-475	E CAPACITOR	4.7μF,50V	C3050			NCF21EZ-104X	CAPACITOR	0.1μF,25V	
C2006			NCB21HK-123X	CAPACITOR	0.012μF,50V	C3051			NCB21EK-104X	CAPACITOR	0.1μF,25V	
C2007			QEKJ1CM-226	E CAPACITOR	22μF,16V	C3101			QER61CM-106	E CAPACITOR	10μF,16V	
C2008			QEKJ1HM-475	E CAPACITOR	4.7μF,50V	C4002			QDYB1CM-103Y	CAPACITOR	0.01μF,16V	
C2009			NCB21HK-102X	CAPACITOR	0.001μF,50V	C4003			NCB21HK-102X	CAPACITOR	0.001μF,50V	
C2010			NCB21HK-152X	CAPACITOR	0.0015μF,50V	C4004			QERF1CM-226	E CAPACITOR	22μF,16V	
C2011			QEKJ1HM-475	E CAPACITOR	4.7μF,50V	C4005			NCB21HK-222X	CAPACITOR	0.0022μF,50V	
C2012			QEK1HM-475	E CAPACITOR	4.7μF,50V	C4006			QERF0JM-476	E CAPACITOR	47μF,6.3V	
C2013			NCB21HK-331X	CAPACITOR	330pF,50V	C4008			QEQF1HM-105	NP E CAPACITOR	1μF,50V	
C2051			NCB21HK-331X	CAPACITOR	330pF,50V	C4009			NCB21HK-563X	CAPACITOR	0.056μF,50V	
C2052			QFLC1HJ-823Z	F CAPACITOR	0.082μF,50V	C4010			NCB21EK-223X	CAPACITOR	0.022μF,25V	
C2053			NCB21HK-472X	CAPACITOR	0.0047μF,50V	C4011			NCB21EK-104X	CAPACITOR	0.1μF,25V	
C2054			NCB21EK-223X	CAPACITOR	0.022μF,25V	C4012			QERF1HM-105	E CAPACITOR	1μF,50V	
C2055			QEKJ1EM-106	E CAPACITOR	10μF,25V	C4013			NCB21HK-563X	CAPACITOR	0.056μF,50V	
C2201			NCB21EK-104X	CAPACITOR	0.1μF,25V	C4014			NDC21HJ-101X	CAPACITOR	100pF,50V	
C2202			NCB21EK-333X	CAPACITOR	0.033μF,25V	C4015			NCB21HK-102X	CAPACITOR	0.001μF,50V	
C2203			QEKJ1EM-106	E CAPACITOR	10μF,25V	C4016			NDC21HJ-101X	CAPACITOR	100pF,50V	
C2204			NCB21HK-102X	CAPACITOR	0.001μF,50V	△			C5001	QFZ9073-683	F CAPACITOR	0.068μF,250V
C2205			QEKJ1HM-105	E CAPACITOR	1μF,50V	△			C5004	QCZ9071-222	CAPACITOR	0.0022μF,250V
C2206			QEKJ1EM-106	E CAPACITOR	10μF,25V	C5006			QEZ0375-686	E CAPACITOR	68μF,400V	
C2207			QEKJ1CM-476	E CAPACITOR	47μF,16V	C5101			QCZ0212-472	CAPACITOR	0.0047μF,1kV	
C2208			QEKJ1HM-475	E CAPACITOR	4.7μF,50V	C5102			QCZ0302-330Z	CAPACITOR	33pF,1kV	

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	#	△ REF No.	PART No.	PART NAME, DESCRIPTION
C5104		QEK1HM-105	E CAPACITOR 1μF,50V	X3002		QAX0527-001	CRYSTAL RESONATOR
C5105		QFN31HJ-183	F CAPACITOR 0.018μF,50V	S3001		QSW0602-004	PUSH SWITCH,REC SAFETY
C5106		QCBB1HJ-271	CAPACITOR 270pF,50V	S7001		QSW0456-002Z	TACT SWITCH,POWER
C5107		QFV91HJ-104	F CAPACITOR 0.1μF,50V	S7002		QSW0456-002Z	TACT SWITCH,CH-
C5201		QETN0JM-107	E CAPACITOR 100μF,6.3V	S7004		QSW0456-002Z	TACT SWITCH,REC
C5202		QEMT1CM-687	E CAPACITOR 680μF,16V	S7006		QSW0456-002Z	TACT SWITCH,PAUSE
C5203		QEMT1AM-128	E CAPACITOR 1200μF,10V	S7008		QSW0456-002Z	TACT SWITCH,STOP/EJECT
C5204		QETN2AM-475	E CAPACITOR 4.7μF,100V	S7010		QSW0456-002Z	TACT SWITCH,REC LINK
C5206		QETN1AM-476	E CAPACITOR 47μF,10V	S7012		QSW0456-002Z	TACT SWITCH,PLAY
C5207		QETN1CM-107	E CAPACITOR 100μF,16V	S7014		QSW0456-002Z	TACT SWITCH,REW
C5301		QEKJ1CM-107	E CAPACITOR 100μF,16V	S7015		QSW0456-002Z	TACT SWITCH,FF
C5302		QETJ1CM-107	E CAPACITOR 100μF,16V	S7016		QSW0456-002Z	TACT SWITCH,CH+
C5303		QEKJ1CM-107	E CAPACITOR 100μF,16V	K2001		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
C5304		QFLC1HJ-102Z	F CAPACITOR 0.001μF,50V	K2002		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
C5305		QFV91HJ-154	F CAPACITOR 0.15μF,50V	K2003		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
C6007		QEK0JM-227	E CAPACITOR 220μF,6.3V	K2004		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
C6012		QEKJ1AM-107	E CAPACITOR 100μF,10V	K2251		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
C6013		NCB21HK-103X	CAPACITOR 0.01μF,50V	K2252		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
C6023		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	K2253		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
C6027		NCB21HK-103X	CAPACITOR 0.01μF,50V	K5101		QQR0678-001Z	FERRITE BEAD
C6032		NCB21HK-152X	CAPACITOR 0.0015μF,50V	K5102		QQR0678-001Z	FERRITE BEAD
C6037		QEKJ1CM-106	E CAPACITOR 10μF,16V	PC3001		GP3S123	IC(PHOTO SENSOR)
C6501		QEKJ0JM-227	E CAPACITOR 220μF,6.3V	PC3002		GP3S123	IC(PHOTO SENSOR)
C7001		NCB21HK-103X	CAPACITOR 0.01μF,50V	△ PC5101		PS2561L1-1/L/	IC(PHOTO COUPLER)
C7002		QEKJ0JM-476	E CAPACITOR 47μF,6.3V	T2051		PELN0832	OSC TRANSFORMER
C7011		QEKJ0JM-227	E CAPACITOR 220μF,6.3V	△ T5001		QQS0030-002	SW TRANSFORMER
C7012		NCB21HK-103X	CAPACITOR 0.01μF,50V	△ TB1		LP20316-007B	TERMINAL BOARD
C7118		QETN0JM-477	E CAPACITOR 470μF,6.3V	TU6001		QAU0212-001	TUNER
C7119		NCB21HK-471X	CAPACITOR 470pF,50V	DI7001		LTG-Y2K16M-J	LE DIODE
C7120		NCB21HK-471X	CAPACITOR 470pF,50V	ET1		PQ21623-2-5	EARTH PLATE(RF)
C7128		QEKJ1CM-107	E CAPACITOR 100μF,16V	HS1		LP40090-001A	HEAT SINK,Q5101
C7129		NCB31CK-104X	CAPACITOR 0.1μF,16V	SD1		LP21033-001A	SHIELD CASE(PRE)
C7164		NCB21HK-681X	CAPACITOR 680pF,50V	OT1		QYTDST3006Z	SCREW,Q5101
C7166		NCB21HK-681X	CAPACITOR 680pF,50V	FC5001		QNG0006-001Z	FUSE CLIP,F5001
L1		QQL29BJ-100Z	COIL 10μH	FC5002		QNG0006-001Z	FUSE CLIP,F5001
L2		QUY153-050Y	IM BUS WIRE	J7103		QNN0286-002	PIN JACK,REAR OUT
L3		QQL29BJ-100Z	COIL 10μH	J7104		QNN0380-002	PIN JACK,REAR IN
L4		QQL29BJ-100Z	COIL 10μH	J7105		QNN0381-002	PIN JACK,FRONT IN
L5		QQL29BJ-100Z	COIL 10μH	△ LF5002		QQR0532-001	LINE FILTER
L11		QQL01BJ-120Z	COIL 12μH	CN1		QGF1028C1-11	FPC CONNECTOR,(1-11)U.DRUM
L13		QQL071J-330Y	COIL 33μH	CN2001		QGF1207C1-07	FPC CONNECTOR,(1-7)A/C HEAD
L24		QQL071J-270Y	COIL 27μH	CN2002		QGB2532J1-02	CONNECTOR,(1-2)FE HEAD
L27		QQL071J-330Y	COIL 33μH	CN3001		QGF1207C1-05	FPC CONNECTOR,(1-5)DRUM MDA
L28		QQL071J-680Y	COIL 68μH	CN3002		QGB2532J1-02	CONNECTOR,(1-2)LOADING MOTOR
L201		QQL29BK-1R0Z	COIL 1.0μH	CN3003		QGB2015M2-08	CONNECTOR,(1-8)CAPSTAN MOTOR
L202		QUY153-050Y	IM BUS WIRE	CN3004		QGB2534J2-04	CONNECTOR,(1-4)ROTARY ENCODER
L203		QQL29BJ-220Z	COIL 22μH	CN3005		QGD2001C1-02	WIRE TRAP CONNECTOR,(1-2)LT BATTERY
L206		QQL071J-220Y	COIL 22μH	△ CN5001		QGA7901C3-02	CONNECTOR,(1-2)AC IN
L207		QUY153-050Y	IM BUS WIRE	△ CP4001		ICP-N25	CIRCUIT PROTECTOR
L2001		QUY153-050Y	IM BUS WIRE	△ CP5302		ICP-N25	CIRCUIT PROTECTOR
L2251		QQL29BJ-100Z	COIL 10μH	△ F5001		QMF51E2-2R0J1	FUSE T2.0A,AC250V
L2252		QQL29BJ-151Z	COIL 150μH				
L3101		QQL29BJ-100Z	COIL 10μH				
L5201		PELN1184	COIL 33μH				
L5202		PELN1184	COIL 33μH				
L6001		QQL29BK-1R0Z	COIL 1.0μH				
L6003		QQL29BJ-470Z	COIL 47μH				
L7107		QQL01BJ-100Z	COIL 10μH				
X1		QAX0576-001Z	CRYSTAL RESONATOR				
X2		QAX0575-001Z	CRYSTAL RESONATOR				
X3001		QAX0445-001	CRYSTAL RESONATOR				