

SECTION 5 PARTS LIST

SAFETY PRECAUTION

Parts identified by the \triangle symbol are critical for safety. Replace only with specified part numbers.

5.1 ELECTRICAL PARTS LIST

# \triangle	REF No.	PART No.	PART NAME, DESCRIPTION	# \triangle	REF No.	PART No.	PART NAME, DESCRIPTION

MAIN BOARD ASSEMBLY <03>							
	PW1	LPA10140-05B	MAIN BOARD ASSY		Q40	DTC144WU	TRANSISTOR
	IC1	JCP8050-MSA	IC			or PDTC144WU	TRANSISTOR
	IC201	LC74776-9791	IC			or RN1309	TRANSISTOR
	IC301	LA7358	IC			or UN521E	TRANSISTOR
	IC3001	HD6432194SBD04F	IC(MCU)		Q41	DTC144WU	TRANSISTOR
	IC3002	IC-PST3427U-X	IC			or PDTC144WU	TRANSISTOR
	IC3003	24LC32A-I/SN-X	IC			or RN1309	TRANSISTOR
		or BR24C32F	IC			or UN521E	TRANSISTOR
		or HN58X2432FPI	IC		Q207	2SB1218A/QR/-X	TRANSISTOR
	IC3004	BA6956AN	IC			or 2SA1576A/QR/-X	TRANSISTOR
	IC5301	L5431	IC			or 2PA1576/R/-X	TRANSISTOR
		or MM1431AT	IC		Q208	2SD1819A/QRS/-X	TRANSISTOR
		or UTCTL431	IC			or 2PC4081/R/-X	TRANSISTOR
	IC7001	PT6312LQ	IC			or 2SC4081/QRS/-X	TRANSISTOR
		or UPD16312GB/H/	IC		Q302	UN511E	TRANSISTOR
	IC7003	GP1U291Q	IR DETECT UNIT			or RN2309	TRANSISTOR
		or PIC-28143LJ	IR DETECT UNIT			or DTA144WU	TRANSISTOR
		or PIC-37143LJ	IR DETECT UNIT			or PDA144WU	TRANSISTOR
		or PNA4652M00YC	IR DETECT UNIT		Q2001	2SC4081/QRS/-X	TRANSISTOR
	Q1	2SC4081/S/-X	TRANSISTOR			or 2PC4081/R/-X	TRANSISTOR
	Q2	2SC4081/S/-X	TRANSISTOR			or 2SD1819A/QRS/-X	TRANSISTOR
	Q3	2SC4081/S/-X	TRANSISTOR		Q2002	2SC4081/QRS/-X	TRANSISTOR
	Q4	2SC4081/S/-X	TRANSISTOR			or 2SD1819A/QRS/-X	TRANSISTOR
	Q5	2SB1218A/QR/-X	TRANSISTOR			or 2PC4081/R/-X	TRANSISTOR
		or 2SA1576A/QR/-X	TRANSISTOR		Q2003	DTA144WU	TRANSISTOR
		or 2PA1576/R/-X	TRANSISTOR			or PDA144WU	TRANSISTOR
	Q7	2SD1819A/QRS/-X	TRANSISTOR			or RN2309	TRANSISTOR
		or 2SC4081/QRS/-X	TRANSISTOR			or UN511E	TRANSISTOR
		or 2PC4081/R/-X	TRANSISTOR		Q2004	DTC114EU	TRANSISTOR
	Q8	2SD1819A/QRS/-X	TRANSISTOR			or PDTC114EU	TRANSISTOR
		or 2PC4081/R/-X	TRANSISTOR			or RN1302	TRANSISTOR
		or 2SC4081/QRS/-X	TRANSISTOR			or UN5211	TRANSISTOR
	Q9	2SB1218A/QR/-X	TRANSISTOR		Q2051	2SC4081/QRS/-X	TRANSISTOR
		or 2SA1576A/QR/-X	TRANSISTOR			or 2SD1819A/QRS/-X	TRANSISTOR
		or 2PA1576/R/-X	TRANSISTOR			or 2PC4081/R/-X	TRANSISTOR
	Q10	2SA1576A/QR/-X	TRANSISTOR		Q2052	2SA1576A/QR/-X	TRANSISTOR
	Q11	DTC144WU	TRANSISTOR			or 2PA1576/R/-X	TRANSISTOR
		or PDTC144WU	TRANSISTOR			or 2SB1218A/QR/-X	TRANSISTOR
		or RN1309	TRANSISTOR		Q2053	DTC144WU	TRANSISTOR
		or UN521E	TRANSISTOR			or PDTC144WU	TRANSISTOR
	Q17	DTC144WU	TRANSISTOR			or RN1309	TRANSISTOR
		or PDTC144WU	TRANSISTOR			or UN521E	TRANSISTOR
		or RN1309	TRANSISTOR		Q2054	2SA1576A/QR/-X	TRANSISTOR
		or UN521E	TRANSISTOR			or 2SB1218A/QR/-X	TRANSISTOR
	Q21	2SB1218A/QR/-X	TRANSISTOR			or 2PA1576/R/-X	TRANSISTOR
		or 2PA1576/R/-X	TRANSISTOR		Q2055	DTC144WU	TRANSISTOR
		or 2SA1576A/QR/-X	TRANSISTOR			or PDTC144WU	TRANSISTOR
	Q24	2SB1218A/QR/-X	TRANSISTOR			or RN1309	TRANSISTOR
		or 2SA1576A/QR/-X	TRANSISTOR			or UN521E	TRANSISTOR
		or 2PA1576/R/-X	TRANSISTOR		Q2251	DTA144WU	TRANSISTOR
	Q38	2SD1819A/QRS/-X	TRANSISTOR			or PDA144WU	TRANSISTOR
		or 2SC4081/QRS/-X	TRANSISTOR			or RN2309	TRANSISTOR
		or 2PC4081/R/-X	TRANSISTOR			or UN511E	TRANSISTOR
					Q2252	DTC114EU	TRANSISTOR
						or PDTC114EU	TRANSISTOR
						or RN1302	TRANSISTOR
						or UN5211	TRANSISTOR

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	#	△ REF No.	PART No.	PART NAME, DESCRIPTION	
Q3001		2SD1819A/QRS/-X	TRANSISTOR			or 2PA1576/R/-X	TRANSISTOR	
		or 2PC4081/R/-X	TRANSISTOR	Q6031		DTC114EU	TRANSISTOR	
		or 2SC4081/QRS/-X	TRANSISTOR			or PDTC114EU	TRANSISTOR	
Q3002		PTZ-NV16	PHOTO TRANSISTOR			or RN1302	TRANSISTOR	
		or PTZ-NV16A	PHOTO TRANSISTOR			or UN5211	TRANSISTOR	
Q3003		PTZ-NV16	PHOTO TRANSISTOR	Q6032		DTC114EU	TRANSISTOR	
		or PTZ-NV16A	PHOTO TRANSISTOR			or PDTC114EU	TRANSISTOR	
Q3004		2SD1819A/QRS/-X	TRANSISTOR			or UN5211	TRANSISTOR	
		or 2SC4081/QRS/-X	TRANSISTOR			or RN1302	TRANSISTOR	
		or 2PC4081/R/-X	TRANSISTOR	Q7201		2SC1317/RS/-T	TRANSISTOR	
Q3005		2SD1819A/QRS/-X	TRANSISTOR	D1		DA204U	DIODE	
		or 2PC4081/R/-X	TRANSISTOR	D6		MTZJ5.1C	ZENER DIODE	
		or 2SC4081/QRS/-X	TRANSISTOR	D201		QRE141J-152Y	RESISTOR	1.5kΩ,1/4W
Q3007		UN521E	TRANSISTOR	D202		QRE141J-101Y	RESISTOR	100Ω,1/4W
		or DTC144WU	TRANSISTOR	D203		QRE141J-101Y	RESISTOR	100Ω,1/4W
		or RN1309	TRANSISTOR	D2202		MTZJ8.2C	ZENER DIODE	
		or PDTC144WU	TRANSISTOR	D3001		LNB2301L01VI	LE DIODE	
Q4001		UN5211	TRANSISTOR	D3002		1SS133	DIODE	
		or DTC114EU	TRANSISTOR			or 1SS270A	DIODE	
		or PDTC114EU	TRANSISTOR	D3003		RD39ES/B3/-T2	ZENER DIODE	
		or RN1302	TRANSISTOR			or MTZJ39C	ZENER DIODE	
Q5101		2SK2632-CB14	POWER MOS FET	D3004		11ES2	DIODE	
		or 2SK2129-LT	POWER MOS FET			or 1A3G	DIODE	
		or 2SK2129	POWER MOS FET	D3005		11ES2	DIODE	
		or 2SK2632	POWER MOS FET			or 1A3G	DIODE	
Q5102		2SD2144S/UV/-T	TRANSISTOR	D3008		1SS355	DIODE	
Q5301		2SB1256	TRANSISTOR	D4001		QUY153-050Y	IM BUS WIRE	
Q5302		2SD2375/QP/	TRANSISTOR	D4002		QUY153-050Y	IM BUS WIRE	
Q5303		2SD1819A/RS/-X	TRANSISTOR	D5001		S1WB/A/60-4102	BRIDGE DIODE	
		or 2PC4081/R/-X	TRANSISTOR			or S1WB/A/60-X	BRIDGE DIODE	
		or 2SC4081/RS/-X	TRANSISTOR			or S1WB(A)60F4072X	BRIDGE DIODE	
Q5304		2SC3616/ML/-T	TRANSISTOR	D5101		AU01	FR DIODE	
Q5305		DTA114EU	TRANSISTOR			or ERA18-04-T2	FR DIODE	
		or PDTA114EU	TRANSISTOR			or 1SR153-400-T2	FR DIODE	
		or RN2302	TRANSISTOR			or 10ELS4	FR DIODE	
		or UN5111	TRANSISTOR	D5102		AU01	FR DIODE	
Q5306		DTC114EU	TRANSISTOR			or ERA18-04-T2	FR DIODE	
		or PDTC114EU	TRANSISTOR			or 1SR153-400-T2	FR DIODE	
		or RN1302	TRANSISTOR			or 10ELS4	FR DIODE	
		or UN5211	TRANSISTOR	D5103		1SS133	DIODE	
Q5308		2SA1576A/RS/-X	TRANSISTOR			or 1SS270A	DIODE	
Q5311		DTC114TU	TRANSISTOR	D5105		1SS133	DIODE	
		or PDTC114TU	TRANSISTOR			or 1SS270A	DIODE	
		or UN5215	TRANSISTOR	D5201		AU01Z	FR DIODE	
		or RN1311	TRANSISTOR			or 10ELS2	FR DIODE	
Q5312		2SD2144S/UV/-T	TRANSISTOR	D5203		AU01Z	FR DIODE	
Q5318		DTA114EU	TRANSISTOR			or 10ELS2	FR DIODE	
		or PDTA114EU	TRANSISTOR	D5204		AU01Z	FR DIODE	
		or UN5111	TRANSISTOR			or 10ELS2	FR DIODE	
		or RN2302	TRANSISTOR	D5206		FMB-24	BARRIER DIODE	
Q5320		DTC114EU	TRANSISTOR			or FSQ05A04B	SB DIODE	
		or PDTC114EU	TRANSISTOR			or SB640FCT	SB DIODE	
		or RN1302	TRANSISTOR			or SF5SC4	SB DIODE	
		or UN5211	TRANSISTOR			or YG801C04	SB DIODE	
Q5322		DTC114TU	TRANSISTOR	D5209		ERA18-02-T2	FR DIODE	
		or PDTC114TU	TRANSISTOR			or PG104RS	FR DIODE	
		or RN1311	TRANSISTOR			or 10ELS2	FR DIODE	
		or UN5215	TRANSISTOR			or 1SR153-400-T2	FR DIODE	
Q5323		2SB927/ST/-T	TRANSISTOR	D5210		AU01Z	FR DIODE	
Q6030		2SB1218A/QR/-X	TRANSISTOR			or ERA18-02-T2	FR DIODE	
		or 2SA1576A/QR/-X	TRANSISTOR			or PG104RS	FR DIODE	

#	△ REF No.	PART No.	PART NAME, DESCRIPTION		#	△ REF No.	PART No.	PART NAME, DESCRIPTION	
		or 1SR153-400-T2	FR DIODE		R25		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
		or 10ELS2	FR DIODE		R26		NRSA02J-682X	MG RESISTOR	6.8kΩ,1/10W
D5211		AU01Z	FR DIODE		R27		NRSA02J-221X	MG RESISTOR	220Ω,1/10W
		or ERA18-02-T2	FR DIODE		R28		NRSA02J-221X	MG RESISTOR	220Ω,1/10W
		or PG104RS	FR DIODE		R29		NRSA02J-561X	MG RESISTOR	560Ω,1/10W
		or 1SR153-400-T2	FR DIODE		R30		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
		or 10ELS2	FR DIODE		R31		NRSA02J-152X	MG RESISTOR	1.5kΩ,1/10W
D5301		MTZJ15C	ZENER DIODE		R32		NRSA02J-471X	MG RESISTOR	470Ω,1/10W
		or RD15ES/B3/-T2	ZENER DIODE		R33		NRSA02J-153X	MG RESISTOR	15kΩ,1/10W
D5302		1SS133	DIODE		R36		NRSA02J-182X	MG RESISTOR	1.8kΩ,1/10W
		or 1SS270A	DIODE		R38		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
D5303		RD5.1JS/B2/-T2	ZENER DIODE		R39		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
		or MA4051N/M/-T2	ZENER DIODE		R40		NRSA02J-222X	MG RESISTOR	2.2kΩ,1/10W
D5304		1SS133	DIODE		R41		NRSA02J-392X	MG RESISTOR	3.9kΩ,1/10W
		or 1SS270A	DIODE		R42		NRSA02J-681X	MG RESISTOR	680Ω,1/10W
D5305		AK04	DIODE		R46		NRSA02J-561X	MG RESISTOR	560Ω,1/10W
		or 1S4	SB DIODE		R48		QRE141J-102Y	RESISTOR	1kΩ,1/4W
		or 11EQS04	SB DIODE		R51		NRSA02J-122X	MG RESISTOR	1.2kΩ,1/10W
D5307		11ES2	DIODE		R70		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
		or 1A3G	DIODE		R77		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
		or ERA15-02-T2	DIODE		R88		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
D5308		MTZJ11B	ZENER DIODE		R90		NRSA02J-391X	MG RESISTOR	390Ω,1/10W
		or RD11ES/B2/-T2	ZENER DIODE		R92		NRSA02J-152X	MG RESISTOR	1.5kΩ,1/10W
D5309		MTZJ27C	ZENER DIODE		R93		NRSA02J-222X	MG RESISTOR	2.2kΩ,1/10W
		or RD27ES/B3/-T2	ZENER DIODE		R104		NRSA02J-682X	MG RESISTOR	6.8kΩ,1/10W
D5310		1SS133	DIODE		R113		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
		or 1SS270A	DIODE		R118		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
D5316		QUY160-100Y	IM BUS WIRE		R201		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
D5317		1SS133	DIODE		R202		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
		or 1SS270A	DIODE		R208		NRSA02J-222X	MG RESISTOR	2.2kΩ,1/10W
D5318		11ES2	DIODE		R209		NRSA02J-682X	MG RESISTOR	6.8kΩ,1/10W
		or 1A3G	DIODE		R210		NRSA02J-182X	MG RESISTOR	1.8kΩ,1/10W
		or ERA15-02-T2	DIODE		R211		NRSA02J-562X	MG RESISTOR	5.6kΩ,1/10W
D5319		11ES2	DIODE		R212		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
		or 1A3G	DIODE		R213		QRE141J-0R0Y	RESISTOR	0Ω,1/4W
		or ERA15-02-T2	DIODE		R216		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
D6002		HZ30-2L-T2	ZENER DIODE		R224		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
		or HZ30-2LTD	Z DIODE (M)		R225		NRSA02J-471X	MG RESISTOR	470Ω,1/10W
D7001		RD9.1ES/B2/-T2	ZENER DIODE		R226		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
		or UZ9.1BSB	ZENER DIODE		R301		NRSA02J-273X	MG RESISTOR	27kΩ,1/10W
		or MTZJ9.1B	ZENER DIODE		R302		NRSA02J-124X	MG RESISTOR	120kΩ,1/10W
D7003		1SS133	DIODE		R303		NRSA02J-273X	MG RESISTOR	27kΩ,1/10W
		or 1SS270A	DIODE		R306		NRSA02J-273X	MG RESISTOR	27kΩ,1/10W
D7004		1SS133	DIODE		R307		NRSA02J-222X	MG RESISTOR	2.2kΩ,1/10W
		or 1SS270A	DIODE		R308		NRSA02J-222X	MG RESISTOR	2.2kΩ,1/10W
D7005		1SS133	DIODE		R312		NRSA02J-272X	MG RESISTOR	2.7kΩ,1/10W
		or 1SS270A	DIODE		R313		NRSA02J-223X	MG RESISTOR	22kΩ,1/10W
D7008		SLR-325MC-T	LE DIODE		R314		NRVA02D-243X	CMF RESISTOR	24kΩ,1/10W
D7009		SLR-325VC-T	LE DIODE		R315		NRSA02J-564X	MG RESISTOR	560kΩ,1/10W
R1		NRVA02D-682X	CMF RESISTOR	6.8kΩ,1/10W	R316		NRSA02J-124X	MG RESISTOR	120kΩ,1/10W
R2		NRVA02D-152X	CMF RESISTOR	1.5kΩ,1/10W	R329		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R3		NRSA02J-182X	MG RESISTOR	1.8kΩ,1/10W	R2001		NRSA02J-681X	MG RESISTOR	680Ω,1/10W
R4		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R2002		NRSA02J-272X	MG RESISTOR	2.7kΩ,1/10W
R5		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R2003		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
R6		NRSA02J-273X	MG RESISTOR	27kΩ,1/10W	R2005		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R7		NRSA02J-681X	MG RESISTOR	680Ω,1/10W	R2006		NRSA02J-393X	MG RESISTOR	39kΩ,1/10W
R8		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R2007		NRSA02J-393X	MG RESISTOR	39kΩ,1/10W
R9		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R2008		NRSA02J-123X	MG RESISTOR	12kΩ,1/10W
R21		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R2009		NRSA02J-123X	MG RESISTOR	12kΩ,1/10W
R22		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	R2010		NRSA02J-123X	MG RESISTOR	12kΩ,1/10W
R23		NRSA02J-182X	MG RESISTOR	1.8kΩ,1/10W	R2013		NRSA02J-682X	MG RESISTOR	6.8kΩ,1/10W

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	#	△ REF No.	PART No.	PART NAME, DESCRIPTION
R2014		NRSA02J-224X	MG RESISTOR 220kΩ,1/10W	R3036		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2015		NRSA02J-181X	MG RESISTOR 180Ω,1/10W	R3038		NRSA02J-152X	MG RESISTOR 1.5kΩ,1/10W
R2016		NRSA02J-393X	MG RESISTOR 39kΩ,1/10W	R3039		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R2017		NRSA02J-183X	MG RESISTOR 18kΩ,1/10W	R3040		NRSA02J-472X	MG RESISTOR 4.7kΩ,1/10W
R2018		NRSA02J-472X	MG RESISTOR 4.7kΩ,1/10W	R3041		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2019		NRSA02J-472X	MG RESISTOR 4.7kΩ,1/10W	R3042		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2053		NRSA02J-472X	MG RESISTOR 4.7kΩ,1/10W	R3044		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2054		NRSA02J-123X	MG RESISTOR 12kΩ,1/10W	R3046		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R2055		NRSA02J-3R3X	MG RESISTOR 3.3Ω,1/10W	R3047		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R2056		NRSA02J-820X	MG RESISTOR 82Ω,1/10W	R3048		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2057		NRSA02J-473X	MG RESISTOR 47kΩ,1/10W	R3049		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2058		NRSA02J-183X	MG RESISTOR 18kΩ,1/10W	R3050		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2059		NRSA02J-473X	MG RESISTOR 47kΩ,1/10W	R3051		NRSA02J-471X	MG RESISTOR 470Ω,1/10W
R2060		NRSA02J-183X	MG RESISTOR 18kΩ,1/10W	R3052		NRSA02J-471X	MG RESISTOR 470Ω,1/10W
R2201		QRE141J-121Y	RESISTOR 120Ω,1/4W	R3053		NRSA02J-471X	MG RESISTOR 470Ω,1/10W
R2202		NRSA02J-222X	MG RESISTOR 2.2kΩ,1/10W	R3054		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R2203		NRSA02J-222X	MG RESISTOR 2.2kΩ,1/10W	R3055		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R2204		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3056		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R2205		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3057		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R2206		NRSA02J-101X	MG RESISTOR 100Ω,1/10W	R3058		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R2208		NRSA02J-101X	MG RESISTOR 100Ω,1/10W	R3059		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2209		NRSA02J-101X	MG RESISTOR 100Ω,1/10W	R3060		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R2210		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W	R3061		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R2211		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W	R3062		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W
R2213		NRSA02J-393X	MG RESISTOR 39kΩ,1/10W	R3063		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2215		NRSA02J-153X	MG RESISTOR 15kΩ,1/10W	R3066		NRSA02J-472X	MG RESISTOR 4.7kΩ,1/10W
R2217		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	R3069		NRSA02J-101X	MG RESISTOR 100Ω,1/10W
R2218		NRSA02J-393X	MG RESISTOR 39kΩ,1/10W	R3071		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W
R2219		NRSA02J-393X	MG RESISTOR 39kΩ,1/10W	R3072		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2220		NRSA02J-393X	MG RESISTOR 39kΩ,1/10W	R3073		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2222		NRSA02J-123X	MG RESISTOR 12kΩ,1/10W	R3074		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2223		NRSA02J-123X	MG RESISTOR 12kΩ,1/10W	R3075		NRSA02J-471X	MG RESISTOR 470Ω,1/10W
R2224		NRSA02J-123X	MG RESISTOR 12kΩ,1/10W	R3076		NRSA02J-471X	MG RESISTOR 470Ω,1/10W
R2225		NRSA02J-153X	MG RESISTOR 15kΩ,1/10W	R3077		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2226		NRSA02J-123X	MG RESISTOR 12kΩ,1/10W	R3078		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2227		NRSA02J-123X	MG RESISTOR 12kΩ,1/10W	R3079		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2228		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W	R3080		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2229		NRSA02J-563X	MG RESISTOR 56kΩ,1/10W	R3081		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R2251		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3083		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3011		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3085		NRSA02J-222X	MG RESISTOR 2.2kΩ,1/10W
R3012		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3086		NRSA02J-222X	MG RESISTOR 2.2kΩ,1/10W
R3013		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3087		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3014		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3088		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3015		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3089		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3016		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3091		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3017		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3092		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R3018		NRSA02J-682X	MG RESISTOR 6.8kΩ,1/10W	R3093		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3019		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3094		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3020		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3095		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3021		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3096		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3022		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3097		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3025		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3103		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3026		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3104		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3027		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3105		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3029		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3106		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R3030		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3201		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W
R3031		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3202		NRSA02J-472X	MG RESISTOR 4.7kΩ,1/10W
R3032		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W	R3203		NRSA02J-103X	MG RESISTOR 10kΩ,1/10W
R3033		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	R3204		NRSA02J-222X	MG RESISTOR 2.2kΩ,1/10W
R3034		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	R3205		QRE141J-181Y	RESISTOR 180Ω,1/4W
R3035		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	R3206		NRSA02J-183X	MG RESISTOR 18kΩ,1/10W

#	△	REF No.	PART No.	PART NAME, DESCRIPTION	#	△	REF No.	PART No.	PART NAME, DESCRIPTION	
R3207			QRE141J-183Y	RESISTOR	18kΩ,1/4W	R5304		NRSA02J-471X	MG RESISTOR	470Ω,1/10W
R3208			NRSA02J-181X	MG RESISTOR	180Ω,1/10W	R5305		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R3209			NRSA02J-273X	MG RESISTOR	27kΩ,1/10W	R5306		NRSA02J-221X	MG RESISTOR	220Ω,1/10W
R3210			NRSA02J-181X	MG RESISTOR	180Ω,1/10W	R5308		NRSA02J-471X	MG RESISTOR	470Ω,1/10W
R3211			NRSA02J-273X	MG RESISTOR	27kΩ,1/10W	R5309		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R3212			QRE141J-474Y	RESISTOR	470kΩ,1/4W	R5310		NRSA02J-221X	MG RESISTOR	220Ω,1/10W
R3213			NRSA02J-334X	MG RESISTOR	330kΩ,1/10W	R5311		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R3214			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R5312		NRVA02D-332X	CMF RESISTOR	3.3kΩ,1/10W
R3215			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R5313		NRVA02D-332X	CMF RESISTOR	3.3kΩ,1/10W
R3216			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R5314		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R3217			QRE141J-562Y	RESISTOR	5.6kΩ,1/4W	R5316		NRVA02D-123X	CMF RESISTOR	12kΩ,1/10W
R3218			QRE141J-472Y	RESISTOR	4.7kΩ,1/4W	R5317		NRSA02J-473X	MG RESISTOR	47kΩ,1/10W
R3219			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	△ R5318		QRZ9005-221X	FUSI RESISTOR	220Ω,1/4W
R3220			NRSA02J-104X	MG RESISTOR	100kΩ,1/10W	R5320		NRSA02J-273X	MG RESISTOR	27kΩ,1/10W
R3222			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R5321		NRSA02J-273X	MG RESISTOR	27kΩ,1/10W
R3223			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R5324		NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W
R3224			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R5325		QRE141J-222Y	RESISTOR	2.2kΩ,1/4W
R3225			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R5326		QUY153-050Y	IM BUS WIRE	
R3229			NRSA02J-105X	MG RESISTOR	1MΩ,1/10W	R5327		NRSA02J-222X	MG RESISTOR	2.2kΩ,1/10W
R3230			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R5329		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R3231			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R5330		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R3233			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R5332		QRE141J-222Y	RESISTOR	2.2kΩ,1/4W
R3234			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R5344		NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W
R3235			NRSA02J-332X	MG RESISTOR	3.3kΩ,1/10W	R5345		QRE121J-561Y	RESISTOR	560Ω,1/2W
R3236			NRSA02J-332X	MG RESISTOR	3.3kΩ,1/10W	R6020		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R3237			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R6021		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R3238			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R6030		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
R3239			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R6031		NRSA02J-271X	MG RESISTOR	270Ω,1/10W
R3240			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R6032		NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W
R3241			QRE141J-104Y	RESISTOR	100kΩ,1/4W	R6033		NRSA02J-182X	MG RESISTOR	1.8kΩ,1/10W
R3242			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R6050		QRE141J-101Y	RESISTOR	100Ω,1/4W
R4003			NRSA02J-561X	MG RESISTOR	560Ω,1/10W	R6051		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
R4004			NRSA02J-561X	MG RESISTOR	560Ω,1/10W	R6052		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
R4005			NRSA02J-562X	MG RESISTOR	5.6kΩ,1/10W	R7001		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R4007			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R7002		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R4008			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R7003		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R4009			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R7004		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R4010			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R7005		NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W
R4011			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	R7006		NRSA02J-471X	MG RESISTOR	470Ω,1/10W
R4012			NRSA02J-222X	MG RESISTOR	2.2kΩ,1/10W	R7007		QRE141J-103Y	RESISTOR	10kΩ,1/4W
R4013			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R7008		QRE141J-563Y	RESISTOR	56kΩ,1/4W
R4015			NRSA02J-562X	MG RESISTOR	5.6kΩ,1/10W	R7009		QRE141J-103Y	RESISTOR	10kΩ,1/4W
R4017			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R7010		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R4018			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	R7011		NRSA02J-333X	MG RESISTOR	33kΩ,1/10W
R4019			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R7012		NRSA02J-333X	MG RESISTOR	33kΩ,1/10W
R4020			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R7013		NRSA02J-333X	MG RESISTOR	33kΩ,1/10W
R4021			NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	R7014		NRSA02J-333X	MG RESISTOR	33kΩ,1/10W
R5101			QRE141J-334Y	RESISTOR	330kΩ,1/4W	R7015		QRE141J-472Y	RESISTOR	4.7kΩ,1/4W
R5102			QRE141J-334Y	RESISTOR	330kΩ,1/4W	R7016		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W
R5103			QRE141J-683Y	RESISTOR	68kΩ,1/4W	R7017		NRSA02J-331X	MG RESISTOR	330Ω,1/10W
R5104			QRG029J-154G	OMF RESISTOR	150kΩ,2W	R7018		NRSA02J-331X	MG RESISTOR	330Ω,1/10W
R5106			QRT01DJ-R39X	MF RESISTOR	0.39Ω,1W	R7160		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
R5107			QRE121J-331Y	RESISTOR	330Ω,1/2W	R7161		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
R5108			NRSA02J-122X	MG RESISTOR	1.2kΩ,1/10W	R7162		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
R5109			QRE141J-681Y	RESISTOR	680Ω,1/4W	R7163		NRSA02J-750X	MG RESISTOR	75Ω,1/10W
R5110			NRSA02J-224X	MG RESISTOR	220kΩ,1/10W	R7202		NRSA02J-221X	MG RESISTOR	220Ω,1/10W
R5111			NRSA02J-561X	MG RESISTOR	560Ω,1/10W	R7203		NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W
R5112			NRSA02J-221X	MG RESISTOR	220Ω,1/10W	R7204		QRE121J-100Y	RESISTOR	10Ω,1/2W
R5301			NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	B3		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R5302			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	B8		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
R5303			NRSA02J-122X	MG RESISTOR	1.2kΩ,1/10W	B12		QUY160-220Y	IM BUS WIRE	

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	#	△ REF No.	PART No.	PART NAME, DESCRIPTION
B52		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	C71		NCB21HK-103X	CAPACITOR 0.01μF,50V
B55		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	C72		NDC21HJ-470X	CAPACITOR 47pF,50V
B65		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	C73		NDC21HJ-120X	CAPACITOR 12pF,50V
B203		QUY153-050Y	IM BUS WIRE	C80		NCB21HK-103X	CAPACITOR 0.01μF,50V
B204		QUY153-050Y	IM BUS WIRE	C106		NCB21HK-821X	CAPACITOR 820pF,50V
B214		QUY160-280Y	IM BUS WIRE	C108		NDC21HJ-680X	CAPACITOR 68pF,50V
B2051		QUY153-050Y	IM BUS WIRE	C109		NCB21CK-224X	CAPACITOR 0.22μF,16V
B3004		QUY160-120Y	IM BUS WIRE	C110		NDC21HJ-820X	CAPACITOR 82pF,50V
B3179		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	C114		NDC21HJ-181X	CAPACITOR 180pF,50V
B5001		QUY160-100Y	IM BUS WIRE	C139		NDC21HJ-470X	CAPACITOR 47pF,50V
B5002		QUY160-100Y	IM BUS WIRE	C143		QCFB1HZ-104	CAPACITOR 0.1μF,50V
B5302		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	C201		QEKJ0JM-227	E CAPACITOR 220μF,6.3V
B5304		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W	C204		NCB21HK-103X	CAPACITOR 0.01μF,50V
C1		NCB21HK-103X	CAPACITOR 0.01μF,50V	C206		NDC21HJ-330X	CAPACITOR 33pF,50V
C2		NCB21HK-103X	CAPACITOR 0.01μF,50V	C207		NDC21HJ-330X	CAPACITOR 33pF,50V
C3		NCB21HK-103X	CAPACITOR 0.01μF,50V	C209		NCB21CK-474X	CAPACITOR 0.47μF,16V
C4		NCB21HK-103X	CAPACITOR 0.01μF,50V	C210		NDC21HJ-101X	CAPACITOR 100pF,50V
C5		QEKJ0JM-476	E CAPACITOR 47μF,6.3V	C211		NDC21HJ-101X	CAPACITOR 100pF,50V
C6		QCBB1HK-103	CAPACITOR 0.01μF,50V	C212		NCB21EK-104X	CAPACITOR 0.1μF,25V
C7		NCB21HK-102X	CAPACITOR 0.001μF,50V	C213		QERF1EM-475	E CAPACITOR 4.7μF,25V
C8		NCB21EK-104X	CAPACITOR 0.1μF,25V	C214		NCB21CK-224X	CAPACITOR 0.22μF,16V
C9		QEKJ1HM-225	E CAPACITOR 2.2μF,50V	C215		NCB21CK-224X	CAPACITOR 0.22μF,16V
C10		NDC21HG-151X	CAPACITOR 150pF,50V	C217		NDC21HJ-560X	CAPACITOR 56pF,50V
C11		NCB21EK-104X	CAPACITOR 0.1μF,25V	C218		QERF1HM-105	E CAPACITOR 1μF,50V
C12		NDC21HJ-8R0X	CAPACITOR 8pF,50V	C222		NCB21CK-105X	CAPACITOR 1μF,16V
C14		NCB21EK-104X	CAPACITOR 0.1μF,25V	C225		QERF1AM-227	E CAPACITOR 220μF,10V
C15		NCB21HK-103X	CAPACITOR 0.01μF,50V	C301		NDC21HJ-151X	CAPACITOR 150pF,50V
C16		NCB21EK-104X	CAPACITOR 0.1μF,25V	C302		NCB21CK-105X	CAPACITOR 1μF,16V
C17		QEKJ1HM-335	E CAPACITOR 3.3μF,50V	C303		NCB21HK-682X	CAPACITOR 0.0068μF,50V
C19		QEKJ1HM-225	E CAPACITOR 2.2μF,50V	C304		NCB21HK-682X	CAPACITOR 0.0068μF,50V
C20		QEKJ1HM-105	E CAPACITOR 1μF,50V	C305		NCB21HK-103X	CAPACITOR 0.01μF,50V
C21		NCB21EK-104X	CAPACITOR 0.1μF,25V	C306		NCB21CK-105X	CAPACITOR 1μF,16V
C22		QEKJ0JM-476	E CAPACITOR 47μF,6.3V	C307		NDC21HJ-151X	CAPACITOR 150pF,50V
C23		NCB21EK-104X	CAPACITOR 0.1μF,25V	C308		NCB21HK-103X	CAPACITOR 0.01μF,50V
C24		QCBB1HK-104	CAPACITOR 0.1μF,50V	C309		NCB21EK-104X	CAPACITOR 0.1μF,25V
C25		NDC21HJ-4R0X	CAPACITOR 4pF,50V	C310		NCB21HK-103X	CAPACITOR 0.01μF,50V
C26		NCB21EK-104X	CAPACITOR 0.1μF,25V	C311		NCB21HK-103X	CAPACITOR 0.01μF,50V
C27		NCB21HK-223X	CAPACITOR 0.022μF,50V	C315		NCB21CK-105X	CAPACITOR 1μF,16V
C28		QEKJ1HM-335	E CAPACITOR 3.3μF,50V	C318		NCB21EK-223X	CAPACITOR 0.022μF,25V
C29		NCB21EK-333X	CAPACITOR 0.033μF,25V	C319		NCB21CK-105X	CAPACITOR 1μF,16V
C30		NCB21CK-474X	CAPACITOR 0.47μF,16V	C320		NCB21HK-103X	CAPACITOR 0.01μF,50V
C31		QEKJ0JM-476	E CAPACITOR 47μF,6.3V	C321		NDC21HG-301X	CAPACITOR 300pF,50V
C32		QCBB1HK-104	CAPACITOR 0.1μF,50V	C322		NCB21CK-474X	CAPACITOR 0.47μF,16V
C33		QEKJ1HM-225	E CAPACITOR 2.2μF,50V	C323		QEKJ0JM-476	E CAPACITOR 47μF,6.3V
C34		NCB21EK-104X	CAPACITOR 0.1μF,25V	C2001		QEKJ1HM-475	E CAPACITOR 4.7μF,50V
C35		NCB21HK-103X	CAPACITOR 0.01μF,50V	C2002		QEKJ1EM-106	E CAPACITOR 10μF,25V
C36		QEKJ1HM-475	E CAPACITOR 4.7μF,50V	C2003		QEKJ0JM-476	E CAPACITOR 47μF,6.3V
C37		QEKJ1HM-105	E CAPACITOR 1μF,50V	C2005		QEKJ1HM-475	E CAPACITOR 4.7μF,50V
C38		QEKJ0JM-476	E CAPACITOR 47μF,6.3V	C2006		NCB21EK-123X	CAPACITOR 0.012μF,25V
C39		NCB21EK-104X	CAPACITOR 0.1μF,25V	C2007		QEKJ1CM-226	E CAPACITOR 22μF,16V
C40		QEKJ1EM-106	E CAPACITOR 10μF,25V	C2008		QEKJ1HM-475	E CAPACITOR 4.7μF,50V
C45		QCBB1HK-104	CAPACITOR 0.1μF,50V	C2009		NCB21HK-102X	CAPACITOR 0.001μF,50V
C46		NDC21HJ-101X	CAPACITOR 100pF,50V	C2010		NCB21HK-152X	CAPACITOR 0.0015μF,50V
C59		NCB21HK-103X	CAPACITOR 0.01μF,50V	C2011		QEKJ1HM-475	E CAPACITOR 4.7μF,50V
C60		QEKJ0JM-476	E CAPACITOR 47μF,6.3V	C2012		QEKJ1HM-475	E CAPACITOR 4.7μF,50V
C61		NCB21HK-103X	CAPACITOR 0.01μF,50V	C2013		NDC21HJ-680X	CAPACITOR 68pF,50V
C63		NCB21EK-104X	CAPACITOR 0.1μF,25V	C2015		NCB21HK-682X	CAPACITOR 0.0068μF,50V
C64		NDC21HJ-220X	CAPACITOR 22pF,50V	C2051		NCB21HK-331X	CAPACITOR 330pF,50V
C65		QEKJ1HM-105	E CAPACITOR 1μF,50V	C2052		QFLC1HJ-823Z	F CAPACITOR 0.082μF,50V
C69		NCB21EK-104X	CAPACITOR 0.1μF,25V	C2053		NCB21HK-472X	CAPACITOR 0.0047μF,50V
C70		NCB21EK-104X	CAPACITOR 0.1μF,25V	C2054		NCB21HK-223X	CAPACITOR 0.022μF,50V

#	△	REF No.	PART No.	PART NAME, DESCRIPTION	#	△	REF No.	PART No.	PART NAME, DESCRIPTION
C2055			QEKJ1EM-106	E CAPACITOR	C4010		NCB21EK-223X	CAPACITOR	0.022μF,25V
C2201			NCB21EK-104X	CAPACITOR	C4011		NCB21EK-104X	CAPACITOR	0.1μF,25V
C2202			NCB21EK-333X	CAPACITOR	C4012		NCB21AK-105X	CAPACITOR	1μF,10V
C2203			QEKJ1EM-106	E CAPACITOR	C4013		NCB21HK-563X	CAPACITOR	0.056μF,50V
C2204			QDGB1HK-102Y	CAPACITOR	C4014		NDC21HJ-101X	CAPACITOR	100pF,50V
C2205			QEKJ1HM-105	E CAPACITOR	C4015		NCB21HK-102X	CAPACITOR	0.001μF,50V
C2206			QEKJ1EM-106	E CAPACITOR	△ C5001		QFZ9073-683	F CAPACITOR	0.068μF,250V
C2207			QEKJ1CM-476	E CAPACITOR	△ C5004		QCZ9071-222	CAPACITOR	0.0022μF,250V
C2208			QEKJ1HM-475	E CAPACITOR	C5006		QEZ0375-686	E CAPACITOR	68μF,400V
C2213			QEKJ1EM-106	E CAPACITOR	C5101		QCZ0212-472	CAPACITOR	0.0047μF,1kV
C2214			QEKJ1EM-106	E CAPACITOR	C5102		QCZ0302-330Z	CAPACITOR	33pF,1kV
C2215			QEKJ1HM-475	E CAPACITOR	C5104		QEKJ1HM-105	E CAPACITOR	1μF,50V
C2216			QEKJ1HM-474	E CAPACITOR	C5105		QFN31HJ-183	F CAPACITOR	0.018μF,50V
C2217			QEKJ1EM-106	E CAPACITOR	C5106		QCB1HJ-271	CAPACITOR	270pF,50V
C2218			QEKJ1HM-474	E CAPACITOR	C5107		QFV91HJ-104	F CAPACITOR	0.1μF,50V
C2219			QEKJ1EM-106	E CAPACITOR	C5201		QEMU0JM-227	E CAPACITOR	220μF,6.3V
C2220			QEKJ1HM-475	E CAPACITOR	C5202		QEMT1CM-687	E CAPACITOR	680μF,16V
C2221			NCB21HK-103X	CAPACITOR	C5203		QEMT1AM-128	E CAPACITOR	1200μF,10V
C2222			QEKJ1HM-474	E CAPACITOR	C5204		QETN2AM-475	E CAPACITOR	4.7μF,100V
C2223			QEKJ1HM-474	E CAPACITOR	C5205		QETN1HM-106	E CAPACITOR	10μF,50V
C2224			NCB21HK-103X	CAPACITOR	C5206		QETN1EM-476	E CAPACITOR	47μF,25V
C2225			QEKJ1HM-475	E CAPACITOR	C5207		QETN1CM-107	E CAPACITOR	100μF,16V
C2226			QEKJ1EM-106	E CAPACITOR	C5208		QEMU1EM-187	E CAPACITOR	180μF,25V
C2227			NCB21CK-104X	CAPACITOR	C5301		QEKJ1CM-107	E CAPACITOR	100μF,16V
C2228			NCB21CK-104X	CAPACITOR	C5302		QEKJ1CM-476	E CAPACITOR	47μF,16V
C2251			QEKJ0JM-476	E CAPACITOR	C5303		QEKJ1CM-107	E CAPACITOR	100μF,16V
C2252			NCB21HK-103X	CAPACITOR	C5304		QFLC1HJ-102Z	F CAPACITOR	0.001μF,50V
C2253			NCB21HK-103X	CAPACITOR	C5305		QFV91HJ-224	F CAPACITOR	0.22μF,50V
C2254			NCB21HK-103X	CAPACITOR	C5311		NCB21HK-103X	CAPACITOR	0.01μF,50V
C2255			NDC21HJ-181X	CAPACITOR	C5351		QUY153-050Y	IM BUS WIRE	
C3001			NCB21EK-104X	CAPACITOR	C6007		QEMU0JM-227	E CAPACITOR	220μF,6.3V
C3003			QEKJ1EM-106	E CAPACITOR	C6008		NCB21HK-103X	CAPACITOR	0.01μF,50V
C3008			NCB21HK-102X	CAPACITOR	C6012		QEKJ1CM-107	E CAPACITOR	100μF,16V
C3011			QETL0JM-338	E CAPACITOR	C6013		NCB21HK-103X	CAPACITOR	0.01μF,50V
C3012			QEKJ0JM-476	E CAPACITOR	C6023		NRSA02J-0R0X	MG RESISTOR	Ω, 1/10W
C3014			QEKJ0JM-476	E CAPACITOR	C6032		NCF21EZ-473X	CAPACITOR	0.047μF,25V
C3015			NCB21EK-104X	CAPACITOR	C6037		QEKJ1EM-106	E CAPACITOR	10μF,25V
C3016			NCB21EK-104X	CAPACITOR	C6052		NDC21HJ-101X	CAPACITOR	100pF,50V
C3020			NDC21HJ-101X	CAPACITOR	C6053		NDC21HJ-101X	CAPACITOR	100pF,50V
C3021			NDC21HJ-101X	CAPACITOR	C6501		QEKJ0JM-107	E CAPACITOR	100μF,6.3V
C3022			NCB21EK-104X	CAPACITOR	C6502		NCB21HK-103X	CAPACITOR	0.01μF,50V
C3024			NDC21HJ-220X	CAPACITOR	C7001		QEKJ0JM-476	E CAPACITOR	47μF,6.3V
C3025			QAT3725-300Z	TRIM CAPACITOR,TIMER CLOCK	C7003		QEKJ0JM-227	E CAPACITOR	220μF,6.3V
C3026			NCB21HK-103X	CAPACITOR	C7005		NDC21HJ-470X	CAPACITOR	47pF,50V
C3027			QEKJ1EM-106	E CAPACITOR	C7006		NDC21HJ-330X	CAPACITOR	33pF,50V
C3030			QEKJ0JM-476	E CAPACITOR	C7007		QEKJ1HM-106	E CAPACITOR	10μF,50V
C3031			NCB21EK-104X	CAPACITOR	C7008		NCB21HK-102X	CAPACITOR	0.001μF,50V
C3032			NCB21EK-104X	CAPACITOR	C7011		QCFB1HZ-104	CAPACITOR	0.1μF,50V
C3033			NCB21EK-104X	CAPACITOR	C7165		NCB21HK-681X	CAPACITOR	680pF,50V
C3036			NDC21HJ-180X	CAPACITOR	C7167		NCB21HK-681X	CAPACITOR	680pF,50V
C3037			NDC21HJ-120X	CAPACITOR	C7202		QETJ0JM-477	E CAPACITOR	470μF,6.3V
C3040			NCB21HK-103X	CAPACITOR	L1		QQL29BJ-100Z	COIL	10μH
C3050			NCB21EK-104X	CAPACITOR	L2		QQL071J-121Y	COIL	120μH
C4002			NCB21EK-104X	CAPACITOR	L3		QQL29BJ-100Z	COIL	10μH
C4003			NCB21HK-102X	CAPACITOR	L4		QQL29BJ-100Z	COIL	10μH
C4004			QEKJ1AM-226	E CAPACITOR	L5		QQR0521-012Z	NOISE FILTER	
C4005			NCB21HK-222X	CAPACITOR	L11		QQL01BJ-120Z	COIL	12μH
C4006			QEKJ0JM-476	E CAPACITOR	L13		QQL071J-330Y	COIL	33μH
C4007			NCB21HK-102X	CAPACITOR	L15		QQL29BJ-100Z	COIL	10μH
C4008			NCB21AK-105X	CAPACITOR	L18		QQL071J-220Y	COIL	22μH
C4009			NCB21HK-563X	CAPACITOR	L19		QQL071J-120Y	COIL	12μH

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	
L20		QUY153-050Y	IM BUS WIRE	
L24		QQL071J-270Y	COIL	27μH
L27		QQL071J-330Y	COIL	33μH
L28		QQL071J-680Y	COIL	68μH
L30		QUY153-050Y	IM BUS WIRE	
L201		QQL29BK-1R0Z	COIL	1.0μH
L202		QUY153-050Y	IM BUS WIRE	
L203		QQL29BJ-220Z	COIL	22μH
L204		QQL29BJ-100Z	COIL	10μH
L206		QQL071J-220Y	COIL	22μH
L301		QQL29BJ-100Z	COIL	10μH
L302		QQL231J-6R8Y	COIL	6.8μH
L2001		QUY153-050Y	IM BUS WIRE	
L2251		QQL29BJ-100Z	COIL	10μH
L2252		QQL29BJ-151Z	COIL	150μH
L3001		QUY153-050Y	IM BUS WIRE	
L3011		QUY153-050Y	IM BUS WIRE	
L3012		QUY153-050Y	IM BUS WIRE	
L4001		QUY153-050Y	IM BUS WIRE	
L5201		PELN1184	COIL	33μH
L5202		PU60944-330K	COIL	33μH
L6001		QQL29BJ-100Z	COIL	10μH
L6003		QQL29BJ-470Z	COIL	47μH
L7201		QQL29BJ-100Z	COIL	10μH
X1		QAX0576-001Z	CRYSTAL RESONATOR	
X3001		QAX0445-001	CRYSTAL RESONATOR	
X3002		QAX0527-001	CRYSTAL RESONATOR	
S3001		QSW0602-004	PUSH SWITCH,REC SAFETY	
S3002		QSW0695-001	PUSH SWITCH,S.CASS SW	
S7001		QSW0456-002Z	TACT SWITCH,POWER	
S7002		QSW0456-002Z	TACT SWITCH,A.DUB	
S7004		QSW0456-002Z	TACT SWITCH,REC	
S7006		QSW0456-002Z	TACT SWITCH,PAUSE	
S7008		QSW0456-002Z	TACT SWITCH,STOP/EJECT	
S7010		QSW0456-002Z	TACT SWITCH,PLAY	
S7012		QSW0456-002Z	TACT SWITCH,E.PROG.	
S7016		QSW0456-002Z	TACT SWITCH,REC LINK	
K2001		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
K2002		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
K2003		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
K2004		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
K2251		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
K2252		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
K2253		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W
K5101		QQR0678-001Z	FERRITE BEAD	
K5102		QUY153-050Y	IM BUS WIRE	
K5301		QUY153-050Y	IM BUS WIRE	
K6080		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W
PC3001		GP3S123	IC(PHOTO SENSOR	
PC3002		GP3S123	IC(PHOTO SENSOR	
△ PC5101		PS2561L1-1/L/	IC(PHOTO COUPLER)	
T2051		PELN0832	OSC TRANSFORMER	
△ T5001		QQS0033-001	SW TRANSFORMER	
TU6001		QAU0208-002	TUNER	
ET1		PQ21623-2-5	EARTH PLATE(RF)	
DI7001		QLF0031-001	FL TUBE	
HD1		PQ35479-1-4	HOLDER(FDP)	
HS1		LP40621-001A	HEAT SINK,Q5101	
OT1		QYTDSF3010Z	SCREW,X2	
OT2		QYTDST3008Z	SCREW,Q5101	
SD1		LP30864-001A	SHIELD CASE(PRE)	

#	△ REF No.	PART No.	PART NAME, DESCRIPTION	
FC5001		QNG0006-001Z	FUSE CLIP,F5001	
FC5002		QNG0006-001Z	FUSE CLIP,F5001	
J7105		QNN0381-002	PIN JACK,F_IN NI	
△ LF5002		QQR0978-001	LINE FILTER	
CN1		QGF1028C1-11	FPC CONNECTOR,(1-11)U.DRUM	
CN901		QGB2024K1-10S	CONNECTOR,(1-10)TERMINAL	
CN902		QGB2024K1-12S	CONNECTOR,(1-12)TERMINAL	
CN903		QGB2024K1-10S	CONNECTOR,(1-10)TERMINAL	
CN904		QGB2024K1-11S	CONNECTOR,(1-11)TERMINAL	
CN905		QGB2024K1-09S	CONNECTOR,(1-9)TERMINAL	
CN2001		QGF1207C1-07	FPC CONNECTOR,(1-7)A/C HEAD	
CN2002		QGB2532J1-02	CONNECTOR,(1-2)FE HEAD	
CN3001		QGF1207C1-05	FPC CONNECTOR,(1-5)DRUM MDA	
CN3002		QGB2532J1-02	CONNECTOR,(1-2)LOADING MOTOR	
CN3003		QGB2015M2-08	CONNECTOR,(1-8)CAPSTAN MOTOR	
CN3004		QGB2534J2-04	CONNECTOR,(1-4)ROTARY ENCODER	
△ CN5001		QGA7901C3-02	CONNECTOR,(1-2)AC IN	
CN7001		QGF1207C1-09	FPC CONNECTOR,(1-9)ADV.JOG	
△ CP3002		ICP-N25	CIRCUIT PROTECTOR	
CP4001		QUY153-050Y	IM BUS WIRE	
△ CP5303		NMFZ012-1R5X-M	FUSE	T1.5A,50V
△ CP5304		NMFZ012-1R0X-M	FUSE	T1.0A,50V
△ F5001		QMF51E2-2R0J1	FUSE	T2.0A,AC250V

TERMINAL BOARD ASSEMBLY <06>

PW1	LPA10138-04A	TERMINAL BOARD ASSY
IC501	JCP8018	IC
	or JCP8028	IC
	or JCP8028-01	IC
	or JCP8038	IC
IC502	VC2076DP	IC
IC901	BH7636S	IC
Q901	UN5211	TRANSISTOR
	or RN1302	TRANSISTOR
	or DTC114EU	TRANSISTOR
	or PDTC114EU	TRANSISTOR
Q902	2SB1218A/QR/-X	TRANSISTOR
	or 2SA1576A/QR/-X	TRANSISTOR
	or 2PA1576/R/-X	TRANSISTOR
Q905	UN521E	TRANSISTOR
	or RN1309	TRANSISTOR
	or DTC144WU	TRANSISTOR
	or PDTC144WU	TRANSISTOR
Q906	2SD1819A/QRS/-X	TRANSISTOR
	or 2SC4081/QRS/-X	TRANSISTOR
	or 2PC4081/R/-X	TRANSISTOR
Q907	2SD1819A/QRS/-X	TRANSISTOR
	or 2PC4081/R/-X	TRANSISTOR
	or 2SC4081/QRS/-X	TRANSISTOR
Q908	2SD1819A/QRS/-X	TRANSISTOR
	or 2SC4081/QRS/-X	TRANSISTOR
	or 2PC4081/R/-X	TRANSISTOR
Q909	2SB1218A/QR/-X	TRANSISTOR
	or 2PA1576/R/-X	TRANSISTOR
	or 2SA1576A/QR/-X	TRANSISTOR

#	△	REF No.	PART No.	PART NAME, DESCRIPTION	#	△	REF No.	PART No.	PART NAME, DESCRIPTION	
Q910			2SB1218A/QR/-X	TRANSISTOR	R939		QRE141J-101Y	RESISTOR	100Ω,1/4W	
			or 2SA1576A/QR/-X	TRANSISTOR	R940		NRSA02J-103X	MG RESISTOR	10kΩ,1/10W	
			or 2PA1576/R/-X	TRANSISTOR	R941		NRSA02J-332X	MG RESISTOR	3.3kΩ,1/10W	
Q911			UN521E	TRANSISTOR	R942		NRSA02J-472X	MG RESISTOR	4.7kΩ,1/10W	
			or RN1309	TRANSISTOR	R943		NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	
			or DTC144WU	TRANSISTOR	R944		NRSA02J-272X	MG RESISTOR	2.7kΩ,1/10W	
			or PDC144WU	TRANSISTOR	R945		NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	
Q912			UN5215	TRANSISTOR	R946		NRSA02J-561X	MG RESISTOR	560Ω,1/10W	
			or RN1311	TRANSISTOR	R947		NRSA02J-682X	MG RESISTOR	6.8kΩ,1/10W	
			or DTC114TU	TRANSISTOR	R949		QRE121J-331Y	RESISTOR	330Ω,1/2W	
			or PDC114TU	TRANSISTOR	R951		NRSA02J-332X	MG RESISTOR	3.3kΩ,1/10W	
R503			NRSA02J-221X	MG RESISTOR	220Ω,1/10W	R952		NRSA02J-562X	MG RESISTOR	5.6kΩ,1/10W
R504			NRSA02J-332X	MG RESISTOR	3.3kΩ,1/10W	R953		NRSA02J-562X	MG RESISTOR	5.6kΩ,1/10W
R505			NRSA02J-392X	MG RESISTOR	3.9kΩ,1/10W	R964		NRSA02J-101X	MG RESISTOR	100Ω,1/10W
R506			NRSA02J-391X	MG RESISTOR	390Ω,1/10W	C501		QEKJ1HM-225	E CAPACITOR	2.2μF,50V
R507			NRSA02J-122X	MG RESISTOR	1.2kΩ,1/10W	C502		QEKJ1HM-475	E CAPACITOR	4.7μF,50V
R508			NRSA02J-151X	MG RESISTOR	150Ω,1/10W	C503		QEKJ1HM-225	E CAPACITOR	2.2μF,50V
R509			NRSA02J-162X	MG RESISTOR	1.6kΩ,1/10W	C504		NCB21EK-104X	CAPACITOR	0.1μF,25V
R510			NRVA02D-102X	CMF RESISTOR	1kΩ,1/10W	C505		QEKJ1HM-475	E CAPACITOR	4.7μF,50V
R511			NRVA02D-471X	CMF RESISTOR	470Ω,1/10W	C506		NCB21HK-103X	CAPACITOR	0.01μF,50V
R512			NRVA02D-102X	CMF RESISTOR	1kΩ,1/10W	C507		QEKJ0JM-476	E CAPACITOR	47μF,6.3V
R513			NRVA02D-152X	CMF RESISTOR	1.5kΩ,1/10W	C508		QEKJ1HM-474	E CAPACITOR	0.47μF,50V
R514			NRVA02D-332X	CMF RESISTOR	3.3kΩ,1/10W	C509		QEKJ1CM-106	E CAPACITOR	10μF,16V
R515			NRVA02D-332X	CMF RESISTOR	3.3kΩ,1/10W	C510		QEKJ0JM-476	E CAPACITOR	47μF,6.3V
R516			QUY160-100Y	IM BUS WIRE		C511		NCB21HK-103X	CAPACITOR	0.01μF,50V
R517			QUY160-100Y	IM BUS WIRE		C512		NCB21HK-103X	CAPACITOR	0.01μF,50V
R525			QRE141J-125Y	RESISTOR	1.2MΩ,1/4W	C513		QEKJ1HM-475	E CAPACITOR	4.7μF,50V
R531			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C514		NCB21HK-103X	CAPACITOR	0.01μF,50V
R532			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C515		NCB21HK-103X	CAPACITOR	0.01μF,50V
R533			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C516		NCB21HK-103X	CAPACITOR	0.01μF,50V
R534			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C518		NCB21EK-104X	CAPACITOR	0.1μF,25V
R535			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C519		QEKJ1HM-225	E CAPACITOR	2.2μF,50V
R536			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C520		QEKJ1HM-475	E CAPACITOR	4.7μF,50V
R901			NRSA02J-750X	MG RESISTOR	75Ω,1/10W	C521		QEKJ1HM-475	E CAPACITOR	4.7μF,50V
R902			NRSA02J-750X	MG RESISTOR	75Ω,1/10W	C522		QEKJ1HM-225	E CAPACITOR	2.2μF,50V
R903			QRE141J-680Y	RESISTOR	68Ω,1/4W	C523		QEKJ1HM-225	E CAPACITOR	2.2μF,50V
R904			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C524		NDC21HG-301X	CAPACITOR	300pF,50V
R905			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C525		NDC21HG-301X	CAPACITOR	300pF,50V
R906			QRE141J-101Y	RESISTOR	100Ω,1/4W	C526		NDC21HJ-101X	CAPACITOR	100pF,50V
R907			QRE141J-101Y	RESISTOR	100Ω,1/4W	C527		NDC21HJ-181X	CAPACITOR	180pF,50V
R908			NRSA02J-0R0X	MG RESISTOR	0Ω,1/10W	C528		NDC21HG-271X	CAPACITOR	270pF,50V
R909			NRSA02J-750X	MG RESISTOR	75Ω,1/10W	C529		NDC21HG-820X	CAPACITOR	82pF,50V
R910			NRSA02J-750X	MG RESISTOR	75Ω,1/10W	C530		NDC21HG-221X	CAPACITOR	220pF,50V
R911			NRSA02J-750X	MG RESISTOR	75Ω,1/10W	C531		NDC21HG-301X	CAPACITOR	300pF,50V
R912			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C532		NDC21HG-301X	CAPACITOR	300pF,50V
R913			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C533		NCB21HK-103X	CAPACITOR	0.01μF,50V
R914			QRE141J-101Y	RESISTOR	100Ω,1/4W	C534		QEKJ0JM-476	E CAPACITOR	47μF,6.3V
R915			QRE141J-101Y	RESISTOR	100Ω,1/4W	C535		NCB21HK-103X	CAPACITOR	0.01μF,50V
R916			NRSA02J-102X	MG RESISTOR	1kΩ,1/10W	C551		QEKJ1HM-105	E CAPACITOR	1μF,50V
R917			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C553		QCB1HK-103	CAPACITOR	0.01μF,50V
R918			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C554		QEKJ1HM-105	E CAPACITOR	1μF,50V
R929			NRSA02J-820X	MG RESISTOR	82Ω,1/10W	C556		QCB1HK-103	CAPACITOR	0.01μF,50V
R930			NRSA02J-750X	MG RESISTOR	75Ω,1/10W	C557		QEKJ1HM-105	E CAPACITOR	1μF,50V
R931			NRSA02J-101X	MG RESISTOR	100Ω,1/10W	C559		NCB21HK-103X	CAPACITOR	0.01μF,50V
R932			NRSA02J-511X	MG RESISTOR	510Ω,1/10W	C560		QEKJ1HM-105	E CAPACITOR	1μF,50V
R933			NRSA02J-471X	MG RESISTOR	470Ω,1/10W	C561		QEKJ1HM-105	E CAPACITOR	1μF,50V
R934			QRE141J-101Y	RESISTOR	100Ω,1/4W	C562		QEKJ1HM-105	E CAPACITOR	1μF,50V
R935			QRE141J-101Y	RESISTOR	100Ω,1/4W	C564		NCB21HK-103X	CAPACITOR	0.01μF,50V
R936			QRE141J-101Y	RESISTOR	100Ω,1/4W	C566		NCB21HK-103X	CAPACITOR	0.01μF,50V
R937			QRE141J-101Y	RESISTOR	100Ω,1/4W	C910		NCB21HK-102X	CAPACITOR	0.001μF,50V
R938			QRE141J-101Y	RESISTOR	100Ω,1/4W	C912		NCB21HK-102X	CAPACITOR	0.001μF,50V

#	△ REF No.	PART No.	PART NAME, DESCRIPTION
C915		NCB21HK-103X	CAPACITOR 0.01μF,50V
C916		NCB21HK-223X	CAPACITOR 0.022μF,50V
C917		NCB21HK-223X	CAPACITOR 0.022μF,50V
C918		QCBB1HK-223	CAPACITOR 0.022μF,50V
C923		QEKJ1CM-476	E CAPACITOR 47μF,16V
C924		NCB21HK-103X	CAPACITOR 0.01μF,50V
C925		NCB21HK-223X	CAPACITOR 0.022μF,50V
C927		QEKJ1CM-476	E CAPACITOR 47μF,16V
C928		NCB21HK-103X	CAPACITOR 0.01μF,50V
C931		QEKJ1EM-106	E CAPACITOR 10μF,25V
C943		QEKJ1CM-107	E CAPACITOR 100μF,16V
C945		QEKJ1EM-106	E CAPACITOR 10μF,25V
C946		QEKJ1EM-106	E CAPACITOR 10μF,25V
C951		QEKJ1CM-476	E CAPACITOR 47μF,16V
L501		QQL29BJ-100Z	COIL 10μH
L503		QQL29BJ-100Z	COIL 10μH
L504		QQL29BJ-100Z	COIL 10μH
L901		QUY153-050Y	IM BUS WIRE
L902		QUY153-050Y	IM BUS WIRE
L903		QUY153-050Y	IM BUS WIRE
L904		QUY153-050Y	IM BUS WIRE
L907		QUY153-050Y	IM BUS WIRE
L913		QUY153-050Y	IM BUS WIRE
L914		QUY153-050Y	IM BUS WIRE
L915		QUY153-050Y	IM BUS WIRE
L916		QUY153-050Y	IM BUS WIRE
L917		QUY153-050Y	IM BUS WIRE
L918		QUY153-050Y	IM BUS WIRE
L919		QUY153-050Y	IM BUS WIRE
L920		QUY153-050Y	IM BUS WIRE
ET1		LP30918-001A	EARTH PLATE
ET2		LP30915-001A	EARTH PLATE
△ TB1		LP21028-001A	TERMINAL BOARD
OT1		QYTDSF3008Z	SCREW,X6
J901		PEMC1177	RGB21PIN SOCKET,AV1
J902		PEMC1177	RGB21PIN SOCKET,AV2
J915		QNN0418-003	PIN JACK,A.OUT(L)
J916		QNN0418-002	PIN JACK,A.OUT(R)
J921		PU60659	MINI JACK,SAT.CTL
CN511		QGF1208F1-11	FPC CONNECTOR,(1-11)S/P CONVERTER
CN911		QGB2024J1-10S	CONNECTOR,(1-10)MAIN
CN912		QGB2024J1-12S	CONNECTOR,(1-12)MAIN
CN913		QGB2024J1-10S	CONNECTOR,(1-10)MAIN
CN914		QGB2024J1-11S	CONNECTOR,(1-11)MAIN
CN915		QGB2024J1-09S	CONNECTOR,(1-9)MAIN
CN916		QGF1208F1-04	FPC CONNECTOR,(1-4)MAIN

#	△ REF No.	PART No.	PART NAME, DESCRIPTION
R6711		NRSA02J-822X	MG RESISTOR 8.2kΩ,1/10W
R6715		NRSA02J-100X	MG RESISTOR 10Ω,1/10W
R6716		NRSA02J-101X	MG RESISTOR 100Ω,1/10W
R6717		NRSA02J-101X	MG RESISTOR 100Ω,1/10W
R6719		NRSA02J-3R3X	MG RESISTOR 3.3Ω,1/10W
R6721		NRSA02J-392X	MG RESISTOR 3.9kΩ,1/10W
R6722		NRSA02J-472X	MG RESISTOR 4.7kΩ,1/10W
R6723		NRSA02J-470X	MG RESISTOR 47Ω,1/10W
R6724		NRSA02J-221X	MG RESISTOR 220Ω,1/10W
R6725		NRSA02J-101X	MG RESISTOR 100Ω,1/10W
R6726		NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
B6702		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
C6701		QEKJ1HM-225	E CAPACITOR 2.2μF,50V
C6702		NCB21HK-682X	CAPACITOR 0.0068μF,50V
C6703		QEKJ1HM-225	E CAPACITOR 2.2μF,50V
C6704		NCB21HK-682X	CAPACITOR 0.0068μF,50V
C6705		NCF21CZ-474X	CAPACITOR 0.47μF,16V
C6706		NCF21CZ-474X	CAPACITOR 0.47μF,16V
C6713		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
C6716		NCF21CZ-474X	CAPACITOR 0.47μF,16V
C6718		NCB21EK-224X	CAPACITOR 0.22μF,25V
C6719		NCB21HK-103X	CAPACITOR 0.01μF,50V
C6720		QEKJ1HM-105	E CAPACITOR 1μF,50V
C6722		NCF21CZ-474X	CAPACITOR 0.47μF,16V
C6723		NDC21HJ-101X	CAPACITOR 100pF,50V
C6724		NDC21HJ-101X	CAPACITOR 100pF,50V
C6728		NCB21HK-103X	CAPACITOR 0.01μF,50V
C6729		QEKJ1HM-225	E CAPACITOR 2.2μF,50V
C6730		QEKJ1CM-476	E CAPACITOR 47μF,16V
C6731		NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
C6732		NCB21HK-103X	CAPACITOR 0.01μF,50V
C6733		NCB21HK-222X	CAPACITOR 0.0022μF,50V
C6734		NCB21HK-103X	CAPACITOR 0.01μF,50V
L6702		QQL231J-1R0Y	COIL 1.0μH
L6703		QQL231J-3R3Y	COIL 3.3μH
X6701		QAX0560-001	CRYSTAL RESONATOR
K6701		NQR0200-003X	FERRITE BEAD
K6703		NQR0200-003X	FERRITE BEAD
K6704		NQR0200-003X	FERRITE BEAD
K6705		NQR0200-003X	FERRITE BEAD
K6706		NQR0200-003X	FERRITE BEAD
K6707		NQR0200-003X	FERRITE BEAD
BK1		LP40425-001A	BRACKET(BOARD)
CN6701		QGG2502K1-10	HEADER PIN

DEMODO BOARD ASSEMBLY <14>

PW1	LPA10060-04A	DEMODO BOARD ASSY
IC6701	TDA9874AH/V2	IC
Q6701	2SC3936/BC/-X	TRANSISTOR
R6701	NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R6703	NRSA02J-102X	MG RESISTOR 1kΩ,1/10W
R6705	NRSA02J-100X	MG RESISTOR 10Ω,1/10W
R6706	NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W
R6708	NRSA02J-0R0X	MG RESISTOR 0Ω,1/10W