

Selector Guide

Digital Multimeters

Model	197A	2000	2000-20	2010	2001	2002
Digits	5½	6½	6½	7½	7½	8½
Expansion Channels		10	20	10	10	10
DC Volts						
Sensitivity	1 µV	100 nV	100 nV	10 nV	10 nV	1 nV
Maximum Reading	1000 V	1000 V	1000 V	1000 V	1100 V	1100 V
Basic Accuracy	0.011%	0.002%	0.002%	0.0018%	0.0018%	0.0006%
Ratio				•	Option	Option
DC Peak Spikes					•	•
AC Volts (TRMS)						
Sensitivity	1 µV	100 nV	100 nV	100 nV	100 nV	100 nV
Maximum Reading	750 V	750 V	750 V	750 V	775 V (1100 V pk)	775 V (1100 V pk)
Basic Accuracy	0.35%	0.05%	0.05%	0.05%	0.03%	0.02%
Bandwidth	20 Hz–100kHz	3 Hz–300 kHz	3 Hz–300 kHz	3 Hz–300 kHz	1 Hz–2 MHz	1 Hz–2 MHz
dB, dBm	•	•	•	•	•	•
Frequency, Period		•	•	•	•	•
Peak/Avg/RMS					•	•
AC, AC + DC					•	•
THD, Harmonics						
4V Sine Source						
9V Sine Source						
Ohms (2/4 Wire)						
Sensitivity	1 mΩ	100 µΩ	100 µΩ	1 µΩ	1 µΩ	100 nΩ
Maximum Reading	220 MΩ	120 MΩ	120 MΩ	120 MΩ	1 GΩ	1 GΩ
Basic Accuracy	0.018%	0.008%	0.008%	0.0032%	0.0032%	0.0007%
Continuity Test		•	*	•		
Diode Test		•	*	•		
Offset Compensation				•	•	•
Dry Circuit				•		
Constant Current		•	•	•	•	•
Open Source Detect						•
DC Amps						
Sensitivity	1 nA	10 nA	10 nA	10 nA	10 pA	10 pA
Range Span	200 µA–10 A	10 mA–3 A	10 mA–3 A	10 mA–3 A	200 µA–2 A	200 µA–2 A
Basic Accuracy	0.1%	0.03%	0.03%	0.03%	0.03%	0.027%
In Circuit Current					•	•
AC Amps (TRMS)						
Sensitivity	1 nA	1 µA	1 µA	1 µA	100 pA	100 pA
Range Span	200 µA–10 A	1 A–3 A	1 A–3 A	1 A–3 A	200 µA–2 A	200 µA–2 A
Basic Accuracy	0.8%	0.1%	0.1%	0.1%	0.1%	0.1%
Bandwidth	20 Hz–30 kHz	3 Hz–5 kHz	3 Hz–5 kHz	3 Hz–5 kHz	20 Hz–100 kHz	20 Hz–100 kHz
General Features						
Interface		GPIB, RS-232	GPIB, RS-232	GPIB, RS-232	GPIB	GPIB
Reading Hold	Min/Max hold	•	•	•		
Digital I/O					•	•
Reading Memory	100 rdg.	1024 rdg.	1024 rdg.	1024 rdg.	Opt to 30,000	Opt to 30,000
Maximum Speed	3 rdg/s	2000 rdg/s	2000 rdg/s	2000 rdg/s	2000 rdg/s	2000 rdg/s
Temperature Meas.		T/C	T/C	T/C, RTD	T/C, RTD	T/C, RTD
Language Emulation		8840/42, 196/199	8840/42, 196/199	196/199		HP 3458

1.888.KEITHLEY (U.S. only)

www.keithley.com

KEITHLEY

A GREATER MEASURE OF CONFIDENCE

Selector Guide

Digital Multimeters

Model	2015, 2015-P	2016	2700	2701	2750
Digits	6½	6½	6½	6½	6½
Expansion Channels			80	80	200
DC Volts					
Sensitivity	100 nV	100 nV	100 nV	100 nV	100 nV
Maximum Reading	1000 V	1000 V	1000 V	1000 V	1000 V
Basic Accuracy	0.002%	0.002%	0.002%	0.002%	0.002%
Ratio			Available w/MUX card	Available w/MUX card	Available w/MUX card
DC Peak Spikes					
AC Volts (TRMS)					
Sensitivity	100 nV	100 nV	100 nV	100 nV	100 nV
Maximum Reading	750 V	750 V	750 V	750 V	750 V
Basic Accuracy	0.05%	0.05%	0.06%	0.06%	0.06%
Bandwidth	3 Hz–300 kHz	3 Hz–300 kHz	3 Hz–300 kHz	3 Hz–300 kHz	3 Hz–300 kHz
dB, dBm	•	•			
Frequency, Period	•	•	•	•	•
Peak/Avg/RMS	•	•			
AC, AC + DC					
THD, Harmonics	•	•			
Spectrum Peaks	• (2015-P)				
4V Sine Source	•				
9V Sine Source		•			
Ohms (2/4 Wire)					
Sensitivity	100 μΩ	100 μΩ	100 μΩ	100 μΩ	1 μΩ
Maximum Reading	120 MΩ	120 MΩ	120 MΩ	120 MΩ	120 MΩ
Basic Accuracy	0.008%	0.008%	0.008%	0.008%	0.008%
Continuity Test			•	•	•
Diode Test	•	•			
Offset Compensation	•		•	•	•
Dry Circuit					•
Constant Current	•	•	•	•	•
Open Source Detect					
DC Amps					
Sensitivity	10 nA	10 nA	10 nA	10 nA	10 nA
Range Span	10 mA–3 A	10 mA–3 A	20 mA–3 A	20 mA–3 A	20 mA–3 A
Basic Accuracy	0.03%	0.03%	0.03%	0.03%	0.03%
In Circuit Current					
AC Amps (TRMS)					
Sensitivity	1 μA	1 μA	1 μA	1 μA	1 μA
Range Span	1 A–3 A	1 A–3 A	1 A–3 A	1 A–3 A	1 A–3 A
Basic Accuracy	0.1%	0.1%	0.15%	0.16%	0.15%
Bandwidth	3 Hz–5 kHz	3 Hz–5 kHz	3 Hz–5 kHz	3 Hz–5 kHz	3 Hz–5 kHz
General Features					
Interface	GPIB, RS-232	GPIB, RS-232	GPIB, RS-232	Ethernet, RS-232	GPIB, RS-232
Reading Hold	•	•	•	•	
Digital I/O	2 in/5 out (TTL)	2 in/5 out (TTL)	2 in/5 out (TTL)		
Reading Memory	1024 rdg.	1024 rdg.	55,000 rdg.	450,000 rdg.	110,000 rdg.
Maximum Speed	2000 rdg/s	2000 rdg/s	2000 rdg/s	3500 rdg/s	2500 rdg/s
Temperature Meas.	T/C	T/C	T/C, RTD, Thermistor	T/C, RTD, Thermistor	T/C, RTD, Thermistor
Language Emulation					

1.888.KEITHLEY (U.S. only)

www.keithley.com

KEITHLEY

A GREATER MEASURE OF CONFIDENCE

Selector Guide: Digital Multimeters

DIGITAL MULTIMETERS