



Model 2500A/2501A

Precision AC Divider

120 to 1,000,000 Volts

Outputs of 120 & 1V AC

Loss Measurement Systems

Power Calibration Systems

IEEE488 Interface

Division Accuracy < 20 PPM

Calibration Period 3 to 5 years

General Description:

The model 2500A is the low voltage arm of a high voltage capacitive divider. Based on the compensated current-comparator capacitive divider principle, it provides ultra precise ratio division of high AC voltages down to workable levels. The model 2500A also provides an easy means of interfacing directly to precision wattmeter (2010A) for direct measurements of transformer losses under control of the IEEE488 interface.

The model 2500A will accept inputs up to 10mA. Several gain ranges of 1, 2, 5, 10, 20, 50 & 100 are also built in to allow flexibility for various input voltages. On range 1 the full scale input is 120 kV, through a 100 pF low-loss high voltage standard capacitor while range 100 offers a full scale input of 1200 volts. The full scale output is 120 volts.

The model 2501A will also accept inputs up to 10mA but it's maximum input voltage is 2400 volts. The gain stages are set for inputs of 2400, 1200, 600, 480, 360, 240 and 120 volts.

Both models are front panel and IEEE488 controllable. The two LCD displays monitor the null and output of the divider. The divider is housed in a rack mounted enclosure and is fully protected against transients. All connections are made to the rear of the instrument.

The model 2500A compares the current through the high voltage capacitor to a low voltage standard capacitor connected to the feed-back circuit of the current comparator. The current comparator automatically corrects for any phase and magnitude errors. The divider output is determined solely by the capacitance ratio of the two standard capacitors. Recommended calibration for the 2500A is 3 to 5 years.

Model 2500A & 2501A

Specifications:

2500A

Input Capacitor 100 pF	Input Voltage: 100, 50, 20, 10, 5, 2, 1 kV
	Output Voltage: 100 Volts
Input Capacitor 50 pF	Input Voltage: 200, 100, 50, 20, 10, 5, 2 kV
	Output Voltage: 100 Volts
Input Capacitor 33 pF	Input Voltage: 1000, 500, 200, 100, 50, 20, 10 kV
	Output Voltage: 100 Volts

2501A

Input Capacitor 1000 pF	Input Voltage: 2400, 1200, 600, 480, 360, 240, 120 V
	Output Voltage: 120 Volts

Other input and output voltages are available, consult factory

General

Maximum Input Current	10mA
Maximum Primary Output Voltage	120 VAC RMS with 10% Over Range
Division Ratio Uncertainty 50 – 60Hz	Magnitude <20 ppm Quadrature <20 ppm
Optional: Secondary Output Voltage (max)	1 VAC RMS with 10% Over Range
Division Ratio Uncertainty 50 – 60Hz	Magnitude <50 ppm Quadrature <50 ppm
Frequency Range of Measured Values	40 Hz to 3 kHz
Gain Selection	7 Gain Settings of 1,2,5,10,20,50,100
Warm Up Time	30 Minutes to Full Rated Accuracy
Operating Environment	18 to 34°C, 10 to 80% RH
Warranty	1 Year Parts & Labor

Dimensions: 221 x 482 x 584 mm

Weight: 18 kg

Shipping Weight: 22 kg

Accessories: Standard Capacitors

Operating Power: 100, 120, 220, 240V - 50/60 Hz

Distributed By:

How to Order:

Model 2500A - High Voltage Divider

Model 2501A - High Voltage Divider

Data Subject to Change

Printed in Canada



Measurements International

118 Pirelli Dr., PO Box 2359, Prescott, Ontario, Canada K0E 1T0
Ph. 613.925.5934 • Fx. 613.925.1195 • North America: 1.800.324.4988

Form MI 67, Rev. 1, Dated 01-11-15 (QAP 19, App. "O")