A 1422 Active 3-phase Adapter







The A 1422 Multifunctional test adapter has all functionalities as its predecessor A 1322 plus complete support for testing of Arc Welding Equipment. This makes it a perfect test and troubleshooting instrument for the demanding user.

As its predecessor it has unique functions such as active polarity testing, differential leakage testing and testing of 3-phase RCD's, which makes the A 1422 Active 3-phase Adapter an ideal instrument for advanced applications. The A 1422 adapter is designed for use alongside the MI 3321 MultiservicerXA and the MI 3310/MI 3310A SigmaPAT enabling functional tests to be carried out on machines up to 40 A. Several test socket outlets make this instrument an ideal tester for testing industrial extension leads that may also be RCD protected.

The test results and parameters can be saved into the large built-in memory for further downloading, analysis and the test report printing with the help of the PC SW PAT Link PRO that is provided with both supporting test instruments.

POWERFUL FUNCTIONS FOR FAST AND EFFICIENT PERIODIC TESTING:

	MI 3310/MI 3310A	MI 3321
Earth bond / continuity resistance	✓	 ✓
Continuity (single / auto)	×	 ✓
Insulation resistance	 ✓ 	 ✓
Insulation resistance – s	 ✓ 	 ✓
High voltage test	×	 Image: A set of the set of the
Loop impedance and prospective fault current	×	 Image: A set of the set of the
Discharging time	×	 ✓
Voltage, frequency, three-phase rotary field	×	 ✓
Substitute leakage current	✓	V
Substitute leakage – s	✓	 ✓
Differential leakage current	 ✓ 	 Image: A set of the set of the
3-phase differential leakage current	 ✓ 	 ✓
Touch leakage current	 ✓ 	 Image: A set of the set of the
Polarity test	✓	 ✓
Active polarity test	✓	 ✓
3-phase polarity test / 3-phase active polarity test	✓	 ✓
Clamp current test	V	 ✓
P/RCD test	✓	 ✓
3-phase P/RCD test	 ✓ 	 ✓
Power / functional test	 ✓ 	V
3-phase power / functional test	 ✓ 	V
Continuity test (according to IEC/ EN 60974-4)	 ✓ 	V
Insulation resistance (according to IEC/ EN 60974-4)	 ✓ 	V
Leakage current (according to IEC/ EN 60974-4)	V	 ✓
No load voltage (according to IEC/ EN 60974-4)	 ✓ 	V

KEY FEATURES:

- Testing of Open-Circuit Voltage at ARC Welding Units in accordance to EN 60974-4.
- All tests on 3-phase electrical equipment can be carried out including live leakage test, power, polarity, RCD and Active polarity.
- Simple connection to the PAT/MACHINE tester with automatic detection.
- Simple test procedures, identical to single-phase equipment.
- Test sequence for 3-phase tests are automatically set based on entered test codes and input voltages.
- Built-in CEE 3-phase/32 A 5-pin, CEE 3-phase/16 A 5-pin and CEE 1-phase/16 A 3-pin test sockets.
- Instrument comes complete with all accessories necessary for comfortable measurements and is kept in a robust waterproof case.

APPLICATION:

- Testing of single and 3-phase ARC Welding equipment.
- Professional 3-phase portable appliance testing.
- Professional 3-phase machine testing.

STANDARDS APPLIED

Electromagnetic compatibility (EMC): EN 61326-1 Safety (LVD): EN 61010-1; EN 61010-031 Functionality: EN 60974-4; VDE 0544-4; VDE 0404-1; VDE 0404-2; VDE 0544-4; VDE 0404-1; VDE 0404-2; VDE 0701-0702; EN 60204-1 Ed.5; EN 60439; EN 61439-1; AS / NZS 3760; NEN 3140



Technical specifications

Differential leakage current (230/400 VAC or 120/208 VAC)

Differential leakage current rea			
Range	Resolution	Accuracy	
0.00 mA ÷ 9.99 mA	0.01 mA	±(5 % of reading + 5 digits)	
Power / Functional test (230/ Apparent power readout	/400 VAC or 120/208 VAC)		
Range	Resolution	Accuracy	
0.00 kVA ÷ 24.00 kVA	0.01 kVA	±(5 % of reading + 5 digits)	
Active power readout			
Range	Resolution	Accuracy	
0.00 kW ÷ 24.00 kW	0.01 kW	±(5 % of reading + 5 digits)	
Reactive power readout			
Range	Resolution	Accuracy	
0.00 kW ÷ 24.00 kVAr	0.01 kVAr	±(5 % of reading + 5 digits)	
Power factor readout			
Range	Resolution	Accuracy	
0.00 ÷ 1.00	0.01	±(5 % of reading + 5 digits)	
3-phase RCD / Test current (1 Portable RCD trip-out time rea			
Range	Resolution	Accuracy	
0 ms ÷ 300 ms (½ x ΙΔΝ, ΙΔΝ			
0 ms ÷ 150 ms (2 x I∆N)	1 ms	±3 ms	
0 ms ÷ 40 ms (5 x I∆N)	1 ms		
Portable RCD trip-out current r	readout (B type PRCD)		
Range	Resolution	Accuracy	
0.2 x ΙΔΝ ÷ 2.2 x ΙΔΝ	0.05 x IΔN	±0.1 x ΙΔΝ	
Continuity of the protective	-		
Range	Resolution		
$0.00 \Omega \div 1.99 \Omega$	0.01 Ω	±(5 % of reading + 3 digits)	
2.00 Ω ÷ 19.99 Ω	0.01 Ω	±10 %	
Test current set to 200 mA			
Test current set to 200 MA			
Range	Resolution	Accuracy	
Range 0.00 Ω ÷ 1.99 Ω	0.01 Ω	Accuracy ±(5 % of reading + 3 digits)	
Range 0.00 Ω ÷ 1.99 Ω 2.00 Ω ÷ 9.99 Ω	0.01 Ω 0.01 Ω		
$\begin{array}{l} \text{Range} \\ 0.00 \ \Omega \div 1.99 \ \Omega \\ 2.00 \ \Omega \div 9.99 \ \Omega \\ 10.0 \ \Omega \div 19.9 \ \Omega \\ \end{array}$	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circu circuit to welding circuit; E readout; LN-W readout:	±(5 % of reading + 3 digits) ±10 % it); (welding circuit to protective circuit); (according to IEC/ EN 60974-4)	
$\begin{array}{l} \text{Range} \\ 0.00 \ \Omega \div 1.99 \ \Omega \\ 2.00 \ \Omega \div 9.99 \ \Omega \\ 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline \end{array}$	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circu circuit to welding circuit; E readout; LN-W readout: Resolution	±(5 % of reading + 3 digits) ±10 % it); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy	
Range 0.00 Ω ÷ 1.99 Ω 2.00 Ω ÷ 9.99 Ω 10.0 Ω ÷ 19.9 Ω Insulation resistance (supply (Insulation resistance supply Insulation LN-PE readout; W-P Range 0.000 ΜΩ ÷ 0.500 ΜΩ	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuit circuit to welding circuit; E readout; LN-W readout: Resolution 0.001 MΩ	±(5 % of reading + 3 digits) ±10 % it); (welding circuit to protective circuit); (according to IEC/ EN 60974-4)	
$\begin{array}{l} \mbox{Range} \\ 0.00 \ \Omega \div 1.99 \ \Omega \\ 2.00 \ \Omega \div 9.99 \ \Omega \\ 10.0 \ \Omega \div 19.9 \ \Omega \\ \mbox{Insulation resistance (supply (Insulation resistance supply insulation LN-PE readout; W-P Range \\ 0.000 \ M\Omega \div 0.500 \ M\Omega \\ 0.501 \ M\Omega \div 1.999 \ M\Omega \end{array}$	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circu circuit to welding circuit; E readout; LN-W readout: Resolution	±(5 % of reading + 3 digits) ±10 % it); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits)	
$\begin{array}{l} \mbox{Range} \\ 0.00 \ \Omega + 1.99 \ \Omega \\ 2.00 \ \Omega + 9.99 \ \Omega \\ 10.0 \ \Omega + 19.9 \ \Omega \\ \mbox{insulation resistance (supply insulation resistance supply insulation LN-PE readout; W-P \\ \mbox{Range} \\ 0.000 \ M\Omega + 0.500 \ M\Omega \\ 0.501 \ M\Omega + 1.999 \ M\Omega \\ 2.00 \ M\Omega + 19.99 \ M\Omega \end{array}$	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuccircuit to welding circuit; E readout; LN-W readout: Resolution 0.01 MΩ 0.001 MΩ	±(5 % of reading + 3 digits) ±10 % it); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy	
$\begin{array}{l} \mbox{Range} \\ 0.00 \ \Omega \div 1.99 \ \Omega \\ 2.00 \ \Omega \div 9.99 \ \Omega \\ 10.0 \ \Omega \div 19.9 \ \Omega \\ \mbox{Insulation resistance (supply insulation resistance supply insulation LN-PE readout; W-P \\ \mbox{Range} \\ 0.000 \ M\Omega \div 0.500 \ M\Omega \\ 0.501 \ M\Omega \div 1.999 \ M\Omega \\ 2.00 \ M\Omega \div 19.99 \ M\Omega \\ 20.0 \ M\Omega \div 19.99 \ M\Omega \\ \mbox{Insulation resistance (supply circular)} \\ \mbox{Insulation resistance (supply circular)} \\ \mbox{Insulation resistance (supply circular)} \\ \mbox{Insulation LN-P readout:} \\ \mbox{Insulation resistance (supply circular)} \\ \mbox{Insulation LN-P readout:} \\ Insulation L$	$\begin{array}{c} 0.01 \ \Omega \\ 0.01 \ \Omega \\ 0.1 \ \Omega \\ \hline 0.01 \ M\Omega \\ \hline 0.001 \ M\Omega \\ \hline 0.001 \ M\Omega \\ \hline 0.001 \ M\Omega \\ \hline 0.01 \ M\Omega \\ \hline 0.01 \ M\Omega \\ \hline 0.1 \ M\Omega \\ \hline $	±(5 % of reading + 3 digits) ±10 % it); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4)	
$\begin{array}{l} \label{eq:result} \hline Range \\ \hline 0.00 \ \Omega \div 1.99 \ \Omega \\ \hline 2.00 \ \Omega \div 9.99 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline Insulation resistance (supply (Insulation LN-PE readout; W-P Range \\ \hline 0.000 \ M\Omega \div 0.500 \ M\Omega \\ \hline 0.501 \ M\Omega \div 19.99 \ M\Omega \\ \hline 2.00 \ M\Omega \div 19.99 \ M\Omega \\ \hline 20.0 \ M\Omega \div 19.99 \ M\Omega \\ \hline Insulation resistance (supply circular) \\ Insulation resistance (supply circular) \\ Insulation LN-P readout: \\ \hline Range \\ \hline Ran$	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuit circuit circuit to welding circuit; readout; LN-W readout: Resolution 0.001 MΩ 0.01 MΩ 0.01 MΩ 0.01 MΩ 0.11 MΩ	±(5 % of reading + 3 digits) ±10 % iit); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(5 % of conding to IEC/ EN 60974-4) Accuracy	
$\begin{array}{l} \mbox{Range} \\ \hline 0.00 \ \Omega \div 1.99 \ \Omega \\ \hline 2.00 \ \Omega \div 9.99 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 0.500 \ M\Omega \\ \hline 0.000 \ M\Omega \div 0.500 \ M\Omega \\ \hline 0.501 \ M\Omega \div 1.999 \ M\Omega \\ \hline 2.00 \ M\Omega \div 1.999 \ M\Omega \\ \hline 2.00 \ M\Omega \div 199.9 \ M\Omega \\ \hline 10.001 \ \Omega \times 19.99 \ M\Omega \\ \hline 10.001 \ \Omega \times 19.99 \ M\Omega \\ \hline 10.001 \ \Omega \times 19.99 \ M\Omega \\ \hline 10.001 \ \Omega \times 19.99 \ M\Omega \\ \hline 10.001 \ \Omega \times 19.99 \ M\Omega \\ \hline 10.001 \ \Omega \times 19.99 \ M\Omega \\ \hline 10.001 \ \Omega \times 19.90 \ M\Omega \\ \hline 10.001 \ \Omega \times 19.90 \ M\Omega \\ \hline 10.000 \ \Omega \times 19.000 \ \Omega \times 10.000 \ \Omega \\ \hline 10.000 \ M\Omega \times 0.500 \ M\Omega \\ \hline 10.000 \ M\Omega \times 0.500 \ M\Omega \\ \hline 0.000 \ M\Omega \times 0.500 \ M\Omega \ $	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuit covelding circuit; readout; LN-W readout: Resolution 0.001 MΩ 0.01 MΩ	±(5 % of reading + 3 digits) ±10 % it); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4)	
$\begin{array}{l} \mbox{Range} \\ \hline 0.00 \ \Omega \div 1.99 \ \Omega \\ \hline 2.00 \ \Omega \div 9.99 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \oplus 1.999 \ M\Omega \\ \hline 0.501 \ M\Omega \div 1.999 \ M\Omega \\ \hline 2.00 \ M\Omega \div 19.99 \ M\Omega \\ \hline 2.00 \ M\Omega \div 19.99 \ M\Omega \\ \hline 10.001 \ \Omega \oplus 1.999 \ M\Omega \\ \hline 10.001 \ \Omega \oplus 1.999 \ M\Omega \\ \hline 10.001 \ \Omega \oplus 1.999 \ M\Omega \\ \hline 10.000 \ M\Omega \div 0.500 \ M\Omega \\ \hline 10.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 10.000 \ M\Omega \div 0.500 \ M\Omega \\ \hline 0.501 \ M\Omega \div 1.999 \ M\Omega \\ \hline 10.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 10.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 10.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 10.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 0.501 \ M\Omega \div 1.999 \ M\Omega \hline 0.501 \ M\Omega \div 1.999 \ M\Omega \\ \hline 0.501 \ M\Omega \div 1.999 \ M\Omega \hline 0.501 \$	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuit circuit to welding circuit; E readout; LN-W readout: Resolution 0.01 MΩ 0.01 MΩ 0.1 MΩ 0.01 MΩ 0.01 MΩ 0.001 MΩ 0.001 MΩ 0.001 MΩ 0.001 MΩ	±(5 % of reading + 3 digits) ±10 % iit); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 5 digits) ±(10 % of reading to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits)	
Range 0.00 Ω ÷ 1.99 Ω 2.00 Ω ÷ 9.99 Ω 10.0 Ω ÷ 19.9 Ω Insulation resistance (supply (Insulation LN-PE readout; W-P Range 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 19.99 MΩ sulation LN-PE readout; W-P Range 0.000 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 19.99 MΩ sulation resistance (supply circu nsulation LN-P readout; Range 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 1.999 MΩ 0.501 MΩ ÷ 1.999 MΩ 0.501 MΩ ÷ 1.999 MΩ 0.000 MΩ ÷ 1.999 MΩ 0.501 MΩ ÷ 1.999 MΩ 0.000 MΩ ÷ 1.999 MΩ	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuit circuit to welding circuit; readout; LN-W readout: Resolution 0.01 MΩ 0.001 MΩ	±(5 % of reading + 3 digits) ±10 % it); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 5 digits) ±(5 % of reading + 3 digits)	
Range 0.00 Ω ÷ 1.99 Ω 2.00 Ω ÷ 9.99 Ω 10.0 Ω ÷ 19.9 Ω Insulation resistance (supply (Insulation LN-PE readout; W-P Range 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 19.99 MΩ 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 199.9 MΩ 0.000 MΩ ÷ 0.500 MΩ 0.000 MΩ ÷ 1.999 MΩ 2.0.00 MΩ ÷ 1.999 MΩ 0.000 MΩ ÷ 1.999 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 1.999 MΩ 0.400 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 1.999 MΩ Welding circuit leakage curren	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuit circuit; readout; LN-W readout: Resolution 0.01 MΩ 0.001 MΩ 0.01 MΩ	±(5 % of reading + 3 digits) ±10 % it); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 5 digits) ±(5 % of reading + 3 digits)	
Range 0.00 Ω ÷ 1.99 Ω 2.00 Ω ÷ 9.99 Ω 10.0 Ω ÷ 19.9 Ω Insulation resistance (supply (Insulation resistance supply Insulation LN-PE readout; W-P Range 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 1.999 MΩ 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 1.999 MΩ Welding circuit leakage curren Welding circuit leakage curren Range	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuc circuit to welding circuit; readout; LN-W readout: Resolution 0.01 MΩ 0.001 MΩ 0.01 MΩ	±(5 % of reading + 3 digits) ±10 % iit); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 10 digits) ±(10 digit	
Range 0.00 Ω ÷ 1.99 Ω 2.00 Ω ÷ 9.99 Ω 10.0 Ω ÷ 19.9 Ω Insulation resistance (supply (Insulation resistance supply Insulation LN-PE readout; W-P Range 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 1.999 MΩ 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 19.99 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 19.99 MΩ 0.000 MΩ ÷ 19.99 MΩ 0.000 MΩ ÷ 19.99 MΩ Welding circuit leakage curren Range 0.000 MΩ ÷ 19.99 MΩ Welding circuit leakage curren Range 0.000 MA ÷ 14.99 mA	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circu: circuit to welding circuit; readout; LN-W readout: Resolution 0.01 MΩ 0.001 MΩ 0.01 MΩ	±(5 % of reading + 3 digits) ±10 % it); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 5 digits) ±(5 % of reading + 3 digits)	
Range 0.00 Ω ÷ 1.99 Ω 2.00 Ω ÷ 9.99 Ω 10.0 Ω ÷ 19.9 Ω Insulation resistance (supply (Insulation LN-PE readout; W-P Range 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ 20.0 MΩ ÷ 19.99 MΩ 20.00 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 20.00 MΩ ÷ 0.500 MΩ 0.500 MΩ ÷ 0.500 MΩ 0.500 MΩ ÷ 0.500 MΩ 0.500 MΩ ÷ 0.500 MΩ 0.000 MΩ ÷ 0.500 MΩ 0.500 MΩ ÷ 0.500 MΩ 0.000 MΩ ÷ 19.99 MΩ Welding circuit leakage current Range 0.00 mA ÷ 14.99 mA No load voltage (acc. to IEC/ No load voltage readout: (AC p	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuit corrective circuit to welding circuit; E readout; LN-W readout: Resolution 0.001 MΩ 0.01 MΩ 0.001 MΩ 0.001 MΩ 0.001 MΩ 0.001 MΩ 0.01 MΩ ent; Primary leakage currective; readout; Primary leakage Resolution 0.01 mA EN 60974-4) peak or DC peak)	±(5 % of reading + 3 digits) ±10 % iit); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 5 digits) ±(5 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 3 digits) urrent readout: Accuracy ±(5 % of reading + 5 digits)	
Range 0.00 Ω ÷ 1.99 Ω 2.00 Ω ÷ 9.99 Ω 10.0 Ω ÷ 19.9 Ω Insulation resistance (supply (Insulation LN-PE readout; W-P Range 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 19.99 MΩ 1nsulation resistance (supply circu insulation LN-P readout: Range 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 1.999 MΩ 0.000 MΩ ÷ 1.999 MΩ No load voltage (acc. to IEC/ No load voltage readout: (AC p Range	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuit covelding circuit; readout; LN-W readout: Resolution 0.01 MΩ 0.001 MΩ 0.001 MΩ 0.001 MΩ 0.001 MΩ 0.001 MΩ 0.01 MΩ 0.02 0.03 MΩ 0.04 MΩ 0.05 MΩ Resolution 0.01 mA EN 60974-4) Deak or DC peak) Resolution	±(5 % of reading + 3 digits) ±10 % iit); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(5 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) urrent readout: Accuracy ±(5 % of reading + 3 digits) urrent readout: Accuracy ±(5 % of reading + 5 digits) Accuracy ±(5 % of reading + 5 digits)	
$\begin{array}{l} \mbox{Range} \\ \hline 0.00 \ \Omega \div 1.99 \ \Omega \\ \hline 2.00 \ \Omega \div 9.99 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \div 19.9 \ \Omega \\ \hline 10.0 \ \Omega \oplus 19.9 \ \Omega \\ \hline 10.000 \ M\Omega \div 0.500 \ M\Omega \\ \hline 0.501 \ M\Omega \div 1.999 \ M\Omega \\ \hline 2.00 \ M\Omega \div 19.99 \ M\Omega \\ \hline 2.00 \ M\Omega \div 19.99 \ M\Omega \\ \hline 2.00 \ M\Omega \div 19.99 \ M\Omega \\ \hline 10.000 \ M\Omega \div 19.99 \ M\Omega \\ \hline 10.000 \ M\Omega \div 19.99 \ M\Omega \\ \hline 10.000 \ M\Omega \div 19.99 \ M\Omega \\ \hline 10.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 10.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 10.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 10.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 0.501 \ M\Omega \div 1.999 \ M\Omega \\ \hline 0.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 0.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 0.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 0.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 0.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline 0.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline \hline 0.000 \ M\Omega \div 1.999 \ M\Omega \\ \hline \hline No \ load \ voltage \ (rcuit \ leakage \ curren \ Range \\ \hline 0.00 \ mA \div 14.99 \ mA \\ \hline No \ load \ voltage \ (readout: \ (AC \ P \ Range \\ \hline 0.0 \ V \div 199.9 \ V \\ \hline \hline \ 0.00 \ V \div 199.9 \ V \\ \hline \hline \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \ \$	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuit corrective circuit to welding circuit; readout; LN-W readout: Resolution 0.01 MΩ 0.02 ent; Primary leakage currective readout; Primary leakage c	±(5 % of reading + 3 digits) ±10 % iit); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 1 digits) ±(5 % of reading + 2 digits) ±(5 % of reading + 3 digits) urrent readout: Accuracy ±(5 % of reading + 5 digits) ±(5 % of reading + 5 digits)	
Range 0.00 Ω ÷ 1.99 Ω 2.00 Ω ÷ 9.99 Ω 10.0 Ω ÷ 19.9 Ω Insulation resistance (supply (Insulation LN-PE readout; W-P Range 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ Station resistance (supply circu insulation LN-P readout: Range 0.000 MΩ ÷ 0.500 MΩ 0.501 MΩ ÷ 1.999 MΩ 2.00 MΩ ÷ 19.99 MΩ 2.00 MΩ ÷ 19.99 MΩ 0.000 MΩ ÷ 1.999 MΩ 0.000 MΩ ÷ 1.999 MΩ 0.000 MΩ ÷ 19.99 MΩ Noload voltage current Range 0.00 mA ÷ 14.99 mA No load voltage (acc. to IEC/ No load voltage readout: (AC p Range 0.0 V ÷ 199.9 V	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuit corrective circuit to welding circuit; readout; LN-W readout: Resolution 0.01 MΩ 0.02 ent; Primary leakage currective readout; Primary leakage c	±(5 % of reading + 3 digits) ±10 % iit); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(5 % of reading + 3 digits) ±(5 % of reading to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) urrent readout: Accuracy ±(5 % of reading + 3 digits) urrent readout: Accuracy ±(5 % of reading + 5 digits) Accuracy ±(5 % of reading + 5 digits)	
$\begin{array}{l} \mbox{Range} \\ \mbox{0.00} \ \Omega \div 1.99 \ \Omega \\ \mbox{2.00} \ \Omega \div 9.99 \ \Omega \\ \mbox{10.0} \ \Omega \div 19.9 \ \Omega \\ \mbox{Insulation resistance (supply (Insulation resistance supply Insulation LN-PE readout; W-P \\ \mbox{Range} \\ \mbox{0.000} \ M\Omega \div 0.500 \ M\Omega \\ \mbox{0.501} \ M\Omega \div 1.999 \ M\Omega \\ \mbox{2.00} \ M\Omega \div 1.999 \ M\Omega \\ \mbox{2.00} \ M\Omega \div 19.99 \ M\Omega \\ \mbox{2.00} \ M\Omega \div 19.99 \ M\Omega \\ Insulation resistance (supply circules of the second $	0.01 Ω 0.01 Ω 0.1 Ω circuit to protective circuit corrective circuit to welding circuit; readout; LN-W readout: Resolution 0.01 MΩ 0.02 ent; Primary leakage currective readout; Primary leakage c	±(5 % of reading + 3 digits) ±10 % iit); (welding circuit to protective circuit); (according to IEC/ EN 60974-4) Accuracy ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 3 digits) ±(5 % of reading + 1 digits) ±(5 % of reading + 2 digits) ±(10 % of reading + 5 digits) ±(5 % of reading + 3 digits) accuracy ±(5 % of reading + 5 digits) Accuracy ±(5 % of reading + 5 digits) Accuracy ±(5 % of reading + 5 digits)	

Polarity test Standard test (<60 VAC and DC) Polarity test Active (Mains supply voltage, over-current protection)



Measuring and Regulation Equipment Manufacturer METREL d.d. Ljubljanska 77 SI-1354 Horjul Tel: + 386 (0)1 75 58 200 Fax: + 386 (0)1 75 49 226 E-mail: metrel@metrel.si http://www.metrel.si



- Bag for accessories
- Measuring / Connection cable betwen Adapter and Instrument
- ٠ 3-phase mains cable 16 A male / 32 A female, 5-pin, 2 m
- RS232 cable
- Instruction manual, short instruction manual
- Calibration certificate •

Optional accessories:

Photo	Order No.	Description
	A 1373	3-phase mains cable / adapter 32 A male / 32 A female, 5 pin, 2 m
\mathbf{P}	A 1375	1-phase mains cable / adapter 32 A / 16 A Schuko, 3 pin, 2 m
	A 1376	3-phase adapter 16 A male / 16 A female, 5 pin, 2 m
\bigcirc	A 1394	1-phase adapter 16 A male / 16 A female, 3-pin, 2 m
0	A 1418	1-phase adapter 16 A, 3-pin female / 16 A Schuko male, 2 m
0	A 1419	1-phase adapter 16 A, 3-pin male / 16 A Schuko female, 2 m
/	A 1423	Adapter for welding equipment
-	A 1424	Adapter for welding equipment
-	A 1425	Adapter for welding equipment

General data

Supply voltage 1-phase: Supply voltage 3-phase:

230 V ±10 % 230/400 V ±10 % 120/208 V ±10 % 32 A, 40 A max (10 min) Maximum test current:

CAT II / 300 V

Overvoltage category: Protection classification: Pollution degree: Protection degree:

Case: Dimensions (w x h x l): Weight:

2 IP 65 (closed and locked cover) IP 20 (connectors) Shock proof plastic, portable 335 x 160 x 335 mm 7.2 kg

Operation conditions: Working temperature range: 0 °C ÷ 40 °C Maximum relative humidity: 85 %RH (0 °C ÷ 40 °C)

Note! Photographs in this catalogue may slightly differ from the instruments at the time of delivery. Subject to technical change without notice.