



Stereo A/V Switch

model
627A

Specifications

Isolation:

> 60 dBmV @ 750 MHz
> 50 dBmV @ 950 MHz

Frequency Response:

± 1 dBmV 0 to 950 MHz

Control Input:

10 mA maximum to ground

Stereo Audio:

DPDT w/screw terminals

Power Requirement for External Power Supply:

117 VAC $\pm 10\%$, 50/60 Hz. (240 VAC Available)

Physical:

1.5" H x 2.75" W x 5.25" D
Weight: 1 lb.

Features

- Video Switch works from 0 to 950 MHz
- Small size
- 'F' connectors
- Unused signals terminated in 75 Ω
- Includes 12 VDC power pack
- Flanged enclosure for easy mounting



Description

Monroe Electronics' Model 627A Stereo Audio/Video Switch module provides 2x1 (AB) balanced stereo audio follow video switching.

The 2x1 switch will respond to a contact closure or a transistor switch to ground or a compatible logic level. The control input is buffered to eliminate high output current drive requirements of the controlling device.

The 627A can be controlled by Monroe Electronics program timers, remote controls or CATV Cue Tone receivers.