



Dual Program Timer jr. model R157A dual

Specifications

Video:

>70 dBmV @ 100 MHz

IF/RF:

>52 dBmV @ 750 MHz

Stereo Audio:

DPDT w/screw terminals

Clock Accuracy:

±1 sec per day @ 20° C

Power Requirements:

for External Power Supply 117VAC
±10%, 50/60 Hz (240 available)

Physical Size:

19.0" W x 3.5" H x 4.0" D

Weight:

4 lbs.

Features

- Two separate timed A/V switches with LCD displays
- Small Size
- "F" connectors
- Unused video terminated to 75Ω
- Balanced stereo audio
- Six on/off commands per day, per timer
- Block programming Monday - Friday
- Battery backup of clock on power loss (1 AA)
- Includes power pack
- Standard 19 inch rack mount
- May be used for IF/RF switching, A/V, or composite A/V



Description

The R157A DUAL Program Timer Jr. provides two 2x1 (AB) balanced stereo audio follow video switches, with separate timed commands.

The model R157A DUAL has been designed to be as simple as possible to program. Setting the time of day, programming of individual days, or an entire weekly schedule is accomplished with only five keystrokes. Manual override of output is accomplished with a single key stroke.

Four selectable block program variations allow for quick and simple programming:

Monday through Friday
Monday through Saturday
Monday through Sunday
Saturday/Sunday

This configuration gives you either two (2) separate timed switches, or allows you to have up to twelve (12) timed switches per signal.