



# Stereo A/V or IF/RF Switch

model  
R164

## Specifications

**Isolation:**

> 42 dBmV @ 950 Mhz

**Frequency Response:**

± 2 dBmV 0 to 950 MHz

**Control Input:**

1 mA maximum to ground

**Stereo Audio:**

DPDT w/screw terminals

**Power Requirement for External Power Supply:**

117 VAC ± 10 %, 50/60 Hz  
(240 VAC available)

**Physical:**

1.75" H X 19" W X 7" D

Weight: 2 lbs.

## Features

- Video Switch works from 0 to 750 MHz
- BNC connectors
- Unused signals terminated in 75 Ω
- Includes power pack
- Standard 19 inch rack size



## Description

Monroe Model R164 Stereo Audio/Video Switch module provides 2x1 (AB) balanced stereo audio follow video or IF/RF switching.

The 2x1 switch will respond to a contact closure, a transistor switch to ground or a compatible logic level. The control input is buffered to eliminate high output current drive requirements of the controlling device.

The R-164 can be controlled by Monroe Electronics' program timers, remote controls or CATV Cue Tone receivers.