

# **Programme's After Market Services NME-3 Series Transceivers**

## **Parts Lists**

**CONTENTS**

	<b>Page No</b>
Transceiver (radio Unit) .....	
System Module GM8B_06 .....	3
System Module GM8B_07 .....	19
Handset .....	
AH89 .....	34

## Transceiver (radio Unit)

### GM8B\_06 (0201346)

(EDMS V 7.0)

Item	Code	Description / Value / Type
R001	1430142	CHIPRES 0W06 4R7 J 0603
R002	1430142	CHIPRES 0W06 4R7 J 0603
R003	1430035	CHIPRES 0W06 1K0 J 0603
R004	1430142	CHIPRES 0W06 4R7 J 0603
R005	1430167	CHIPRES 0W06 47R J 0603
R006	1430167	CHIPRES 0W06 47R J 0603
R007	1430151	CHIPRES 0W1 10R J 0603
R008	1430167	CHIPRES 0W06 47R J 0603
R009	1430151	CHIPRES 0W1 10R J 0603
R010	1430167	CHIPRES 0W06 47R J 0603
R011	1430144	CHIPRES JUMPER 0R0 0603
R012	1430151	CHIPRES 0W1 10R J 0603
R013	1430167	CHIPRES 0W06 47R J 0603
R014	1430151	CHIPRES 0W1 10R J 0603
R015	1430167	CHIPRES 0W06 47R J 0603
R016	1430151	CHIPRES 0W1 10R J 0603
R017	1430167	CHIPRES 0W06 47R J 0603
R018	1430151	CHIPRES 0W1 10R J 0603
R019	1430167	CHIPRES 0W06 47R J 0603
R020	1430159	CHIPRES 0W06 22R J 0603
R021	1430159	CHIPRES 0W06 22R J 0603
R022	1430159	CHIPRES 0W06 22R J 0603
R023	1430159	CHIPRES 0W06 22R J 0603
R024	1430035	CHIPRES 0W06 1K0 J 0603
R080	1430159	CHIPRES 0W06 22R J 0603
R081	1430159	CHIPRES 0W06 22R J 0603
R082	1430159	CHIPRES 0W06 22R J 0603
R083	1430159	CHIPRES 0W06 22R J 0603
R084	1430159	CHIPRES 0W06 22R J 0603
R085	1430159	CHIPRES 0W06 22R J 0603
R086	1430159	CHIPRES 0W06 22R J 0603
R087	1430159	CHIPRES 0W06 22R J 0603
R100	1430001	CHIPRES 0W06 100R J 0603
R101	1430163	CHIPRES 0W06 33R J 0603
R102	1620035	RES NETWORK 0W06 2X10R J 0404
R103	1620019	RES NETWORK 0W06 2X10K J 0404
R104	1430045	CHIPRES 0W06 2K7 J 0603
R105	1430013	CHIPRES 0W06 330R J 0603
R106	1430017	CHIPRES 0W06 390R J 0603
R107	1620019	RES NETWORK 0W06 2X10K J 0404
R108	1430015	CHIPRES 0W06 470R J 0603
R109	1430055	CHIPRES 0W06 6K8 J 0603

## Parts Lists

## Technical Documentation

R110	1430069	CHIPRES 0W06 18K J	0603
R111	1430039	CHIPRES 0W06 1K5 J	0603
R112	1430005	CHIPRES 0W06 150R J	0603
R113	1430001	CHIPRES 0W06 100R J	0603
R114	1430007	CHIPRES 0W06 180R J	0603
R115	1620031	RES NETWORK 0W06	0404
R116	1430013	CHIPRES 0W06 330R J	0603
R117	1430039	CHIPRES 0W06 1K5 J	0603
R118	1430087	CHIPRES 0W06 100K J	0603
R119	1430151	CHIPRES 0W1 10R J	0603
R120	1430009	CHIPRES 0W06 220R J	0603
R121	1430063	CHIPRES 0W06 12K J	0603
R122	1430087	CHIPRES 0W06 100K J	0603
R123	1430063	CHIPRES 0W06 12K J	0603
R124	1430063	CHIPRES 0W06 12K J	0603
R125	1430067	CHIPRES 0W06 15K J	0603
R126	1430087	CHIPRES 0W06 100K J	0603
R127	1430063	CHIPRES 0W06 12K J	0603
R128	1430065	CHIPRES 0W06 10K J	0603
R129	1430007	CHIPRES 0W06 180R J	0603
R200	1430045	CHIPRES 0W06 2K7 J	0603
R201	1430151	CHIPRES 0W1 10R J	0603
R202	1430151	CHIPRES 0W1 10R J	0603
R203	1430151	CHIPRES 0W1 10R J	0603
R204	1620019	RES NETWORK 0W06	0404
R205	1430151	CHIPRES 0W1 10R J	0603
R250	1430095	CHIPRES 0W06 220K J	0603
R251	1430043	CHIPRES 0W06 2K2 J	0603
R252	1430087	CHIPRES 0W06 100K J	0603
R253	1430043	CHIPRES 0W06 2K2 J	0603
R254	1430051	CHIPRES 0W06 4K7 J	0603
R255	1430067	CHIPRES 0W06 15K J	0603
R256	1430087	CHIPRES 0W06 100K J	0603
R257	1430063	CHIPRES 0W06 12K J	0603
R258	1430103	CHIPRES 0W06 470K J	0603
R259	1430071	CHIPRES 0W06 22K J	0603
R260	1430071	CHIPRES 0W06 22K J	0603
R261	1430079	CHIPRES 0W06 47K J	0603
R262	1430073	CHIPRES 0W06 27K J	0603
R263	1430089	CHIPRES 0W06 120K J	0603
R264	1430101	CHIPRES 0W06 390K J	0603
R265	1430067	CHIPRES 0W06 15K J	0603
R266	1430069	CHIPRES 0W06 18K J	0603
R267	1430049	CHIPRES 0W06 3K9 J	0603
R268	1430067	CHIPRES 0W06 15K J	0603
R269	1430071	CHIPRES 0W06 22K J	0603
R270	1430151	CHIPRES 0W1 10R J	0603
R271	1430001	CHIPRES 0W06 100R J	0603
R272	1430001	CHIPRES 0W06 100R J	0603

R273	1620019	RES NETWORK 0W06	0404
R274	1430087	CHIPRES 0W06 100K J	0603
R275	1430007	CHIPRES 0W06 180R J	0603
R276	1430035	CHIPRES 0W06 1K0 J	0603
R277	1430069	CHIPRES 0W06 18K J	0603
R278	1430005	CHIPRES 0W06 150R J	0603
R279	1430057	CHIPRES 0W06 8K2 J	0603
R280	1430171	CHIPRES 0W06 68R J	0603
R281	1430171	CHIPRES 0W06 68R J	0603
R300	1430163	CHIPRES 0W06 33R J	0603
R301	1430057	CHIPRES 0W06 8K2 J	0603
R302	1430071	CHIPRES 0W06 22K J	0603
R303	1430067	CHIPRES 0W06 15K J	0603
R304	1430011	CHIPRES 0W06 270R J	0603
R305	1430151	CHIPRES 0W1 10R J	0603
R306	1430169	CHIPRES 0W06 56R J	0603
R307	1430163	CHIPRES 0W06 33R J	0603
R308	1430035	CHIPRES 0W06 1K0 J	0603
R311	1430047	CHIPRES 0W06 3K3 J	0603
R312	1430075	CHIPRES 0W06 33K J	0603
R313	1430043	CHIPRES 0W06 2K2 J	0603
R314	1430043	CHIPRES 0W06 2K2 J	0603
R315	1430073	CHIPRES 0W06 27K J	0603
R316	1430075	CHIPRES 0W06 33K J	0603
R317	1430159	CHIPRES 0W06 22R J	0603
R318	1430053	CHIPRES 0W06 5K6 J	0603
R319	1430055	CHIPRES 0W06 6K8 J	0603
R320	1430011	CHIPRES 0W06 270R J	0603
R321	1430013	CHIPRES 0W06 330R J	0603
R322	1430057	CHIPRES 0W06 8K2 J	0603
R323	1430009	CHIPRES 0W06 220R J	0603
R324	1430009	CHIPRES 0W06 220R J	0603
R400	1430031	CHIPRES 0W06 100K F	0603
R401	1430105	CHIPRES 0W06 560K J	0603
R402	1430087	CHIPRES 0W06 100K J	0603
R403	1430079	CHIPRES 0W06 47K J	0603
R409	1620019	RES NETWORK 0W06	0404
R410	1430179	CHIPRES 0W06 210K F 100PPM	0603
R411	1430179	CHIPRES 0W06 210K F 100PPM	0603
R412	1430079	CHIPRES 0W06 47K J	0603
R413	1430113	CHIPRES 0W06 348K F 50PPM	0603
R414	1430031	CHIPRES 0W06 100K F	0603
R415	1430031	CHIPRES 0W06 100K F	0603
R416	1430181	CHIPRES 0W06 30K9 F 100PPM	0603
R417	1430095	CHIPRES 0W06 220K J	0603
R418	1430039	CHIPRES 0W06 1K5 J	0603
R419	1430113	CHIPRES 0W06 348K F 50PPM	0603
R420	1430051	CHIPRES 0W06 4K7 J	0603
R421	1430311	CHIPRES 0W06 45K3 F 100PPM	0603

## Parts Lists

## Technical Documentation

R422	1430321	CHIPRES 0W06 261K F	0603
R423	1430079	CHIPRES 0W06 47K J	0603
R424	1430183	CHIPRES 0W06 110K F 100PPM	0603
R425	1430087	CHIPRES 0W06 100K J	0603
R426	1430069	CHIPRES 0W06 18K J	0603
R427	1430035	CHIPRES 0W06 1K0 J	0603
R450	1430065	CHIPRES 0W06 10K J	0603
R451	1430065	CHIPRES 0W06 10K J	0603
R452	1430043	CHIPRES 0W06 2K2 J	0603
R453	1430065	CHIPRES 0W06 10K J	0603
R454	1430071	CHIPRES 0W06 22K J	0603
R455	1430069	CHIPRES 0W06 18K J	0603
R456	1430065	CHIPRES 0W06 10K J	0603
R457	1430051	CHIPRES 0W06 4K7 J	0603
R458	1430051	CHIPRES 0W06 4K7 J	0603
R459	1430065	CHIPRES 0W06 10K J	0603
R460	1430065	CHIPRES 0W06 10K J	0603
R461	1430051	CHIPRES 0W06 4K7 J	0603
R500	1415632	MELFRES 0W25 33K0 F	0204
R501	1430075	CHIPRES 0W06 33K J	0603
R502	1415632	MELFRES 0W25 33K0 F	0204
R503	1416160	MELFRES 0W25 100K F	0204
R504	1416001	MELFRES 0W25 39K0 F	0204
R505	1430015	CHIPRES 0W06 470R J	0603
R506	1416001	MELFRES 0W25 39K0 F	0204
R507	1416160	MELFRES 0W25 100K F	0204
R508	1416160	MELFRES 0W25 100K F	0204
R509	1416001	MELFRES 0W25 39K0 F	0204
R510	1430015	CHIPRES 0W06 470R J	0603
R511	1416001	MELFRES 0W25 39K0 F	0204
R512	1416160	MELFRES 0W25 100K F	0204
R513	1430005	CHIPRES 0W06 150R J	0603
R514	1416160	MELFRES 0W25 100K F	0204
R515	1430005	CHIPRES 0W06 150R J	0603
R516	1416160	MELFRES 0W25 100K F	0204
R517	1620029	RES NETWORK 0W06 2X4K7 J	0404
R518	1620101	RES NETWORK 0W06 2X470R J	0404
R519	1416160	MELFRES 0W25 100K F	0204
R520	1416160	MELFRES 0W25 100K F	0204
R522	1620025	RES NETWORK 0W06 2X100K J	0404
R600	1430065	CHIPRES 0W06 10K J	0603
R601	1430051	CHIPRES 0W06 4K7 J	0603
R602	1620025	RES NETWORK 0W06 2X100K J	0404
R603	1430051	CHIPRES 0W06 4K7 J	0603
R604	1430087	CHIPRES 0W06 100K J	0603
R605	1620025	RES NETWORK 0W06 2X100K J	0404
R606	1430051	CHIPRES 0W06 4K7 J	0603
R607	1430015	CHIPRES 0W06 470R J	0603
R608	1430144	CHIPRES JUMPER 0R0	0603

R609	1430001	CHIPRES 0W06 100R J	0603
R610	1430051	CHIPRES 0W06 4K7 J	0603
R611	1620025	RES NETWORK 0W06 2X100K J	0404
R612	1430087	CHIPRES 0W06 100K J	0603
R614	1620023	RES NETWORK 0W06 2X47K J	0404
R615	1620017	RES NETWORK 0W06 2X100R J	0404
R617	1430095	CHIPRES 0W06 220K J	0603
R618	1430015	CHIPRES 0W06 470R J	0603
R619	1430079	CHIPRES 0W06 47K J	0603
R700	1620025	RES NETWORK 0W06 2X100K J	0404
R701	1430144	CHIPRES JUMPER 0R0	0603
R702	1430144	CHIPRES JUMPER 0R0	0603
R703	1430065	CHIPRES 0W06 10K J	0603
R704	1430079	CHIPRES 0W06 47K J	0603
R705	1430325	CHIPRES 0W06 2M2 J	0603
R706	1430079	CHIPRES 0W06 47K J	0603
R707	1430107	CHIPRES 0W06 680K J	0603
R709	1430144	CHIPRES JUMPER 0R0	0603
R710	1620017	RES NETWORK 0W06 2X100R J	0404
R711	1620011	RES NETWORK 0W06 4X100K J	1206
R712	1430065	CHIPRES 0W06 10K J	0603
R713	1430065	CHIPRES 0W06 10K J	0603
R714	1620025	RES NETWORK 0W06 2X100K J	0404
R715	1430065	CHIPRES 0W06 10K J	0603
R716	1430111	CHIPRES 0W06 1M0 J	0603
R717	1430095	CHIPRES 0W06 220K J	0603
R718	1430079	CHIPRES 0W06 47K J	0603
R719	1620025	RES NETWORK 0W06 2X100K J	0404
R720	1430075	CHIPRES 0W06 33K J	0603
R721	1430075	CHIPRES 0W06 33K J	0603
R722	1620025	RES NETWORK 0W06 2X100K J	0404
R723	1430075	CHIPRES 0W06 33K J	0603
R726	1430065	CHIPRES 0W06 10K J	0603
R727	1430144	CHIPRES JUMPER 0R0	0603
R728	1430325	CHIPRES 0W06 2M2 J	0603
R750	1430039	CHIPRES 0W06 1K5 J	0603
R751	1430087	CHIPRES 0W06 100K J	0603
R800	1620025	RES NETWORK 0W06 2X100K J	0404
R801	1430035	CHIPRES 0W06 1K0 J	0603
R802	1430151	CHIPRES 0W1 10R J	0603
R809	1620107	RES NETWORK 0W06 2X22K J	0404
R810	1620101	RES NETWORK 0W06 2X470R J	0404
R812	1430151	CHIPRES 0W1 10R J	0603
A300	9517012	SMD RF SHIELD DMC00422	HD940 UP8
B701	4510237	CRYSTAL 32.768KHZ+-20PPM	12.5PF
C001	2320099	CHIPCAP X7R 4N7 J 50V	0603
C002	2320107	CHIPCAP X7R 10N J 50V	0603
C003	2320063	CHIPCAP NP0 150P J 50V	0603
C004	2320099	CHIPCAP X7R 4N7 J 50V	0603

## Parts Lists

## Technical Documentation

C005	2320779	CHIPCAP X7R 100N K 16V	0603
C006	2320099	CHIPCAP X7R 4N7 J 50V	0603
C007	2320107	CHIPCAP X7R 10N J 50V	0603
C008	2320063	CHIPCAP NP0 150P J 50V	0603
C009	2320107	CHIPCAP X7R 10N J 50V	0603
C010	2320043	CHIPCAP NP0 22P J 50V	0603
C011	2320079	CHIPCAP X7R 680P J 50V	0603
C012	2320043	CHIPCAP NP0 22P J 50V	0603
C013	2320083	CHIPCAP X7R 1N0 J 50V	0603
C014	2320779	CHIPCAP X7R 100N K 16V	0603
C015	2320043	CHIPCAP NP0 22P J 50V	0603
C016	2320043	CHIPCAP NP0 22P J 50V	0603
C017	2320043	CHIPCAP NP0 22P J 50V	0603
C018	2315011	CHIP ARRAY NP0 4X22P K 16V	0612
C019	2315011	CHIP ARRAY NP0 4X22P K 16V	0612
C020	2315011	CHIP ARRAY NP0 4X22P K 16V	0612
C021	2315011	CHIP ARRAY NP0 4X22P K 16V	0612
C022	2320043	CHIPCAP NP0 22P J 50V	0603
C023	2320083	CHIPCAP X7R 1N0 J 50V	0603
C024	2320083	CHIPCAP X7R 1N0 J 50V	0603
C025	2320107	CHIPCAP X7R 10N J 50V	0603
C026	2320083	CHIPCAP X7R 1N0 J 50V	0603
C027	2320043	CHIPCAP NP0 22P J 50V	0603
C028	2320083	CHIPCAP X7R 1N0 J 50V	0603
C029	2320083	CHIPCAP X7R 1N0 J 50V	0603
C030	2320107	CHIPCAP X7R 10N J 50V	0603
C031	2320043	CHIPCAP NP0 22P J 50V	0603
C032	2320083	CHIPCAP X7R 1N0 J 50V	0603
C033	2320083	CHIPCAP X7R 1N0 J 50V	0603
C034	2320107	CHIPCAP X7R 10N J 50V	0603
C035	2320083	CHIPCAP X7R 1N0 J 50V	0603
C036	2320043	CHIPCAP NP0 22P J 50V	0603
C037	2320083	CHIPCAP X7R 1N0 J 50V	0603
C038	2320083	CHIPCAP X7R 1N0 J 50V	0603
C039	2320107	CHIPCAP X7R 10N J 50V	0603
C040	2320043	CHIPCAP NP0 22P J 50V	0603
C041	2320083	CHIPCAP X7R 1N0 J 50V	0603
C042	2320083	CHIPCAP X7R 1N0 J 50V	0603
C043	2320107	CHIPCAP X7R 10N J 50V	0603
C044	2320083	CHIPCAP X7R 1N0 J 50V	0603
C045	2320043	CHIPCAP NP0 22P J 50V	0603
C046	2320083	CHIPCAP X7R 1N0 J 50V	0603
C047	2320083	CHIPCAP X7R 1N0 J 50V	0603
C048	2320107	CHIPCAP X7R 10N J 50V	0603
C049	2320063	CHIPCAP NP0 150P J 50V	0603
C050	2320043	CHIPCAP NP0 22P J 50V	0603
C051	2320063	CHIPCAP NP0 150P J 50V	0603
C052	2320043	CHIPCAP NP0 22P J 50V	0603
C053	2320063	CHIPCAP NP0 150P J 50V	0603



C054	2340014	CHIPCAP X7R 47N K 25V	0805
C055	2320043	CHIPCAP NP0 22P J 50V	0603
C056	2320043	CHIPCAP NP0 22P J 50V	0603
C057	2320779	CHIPCAP X7R 100N K 16V	0603
C058	2320063	CHIPCAP NP0 150P J 50V	0603
C059	2320091	CHIPCAP X7R 2N2 J 50V	0603
C060	2340014	CHIPCAP X7R 47N K 25V	0805
C061	2312411	CHIPCAP X5R 1U0 M 25V	1206
C062	2320059	CHIPCAP NP0 100P J 50V	0603
C063	2320043	CHIPCAP NP0 22P J 50V	0603
C064	2340014	CHIPCAP X7R 47N K 25V	0805
C065	2320063	CHIPCAP NP0 150P J 50V	0603
C066	2320091	CHIPCAP X7R 2N2 J 50V	0603
C067	2320063	CHIPCAP NP0 150P J 50V	0603
C068	2320083	CHIPCAP X7R 1N0 J 50V	0603
C069	2320043	CHIPCAP NP0 22P J 50V	0603
C070	2320063	CHIPCAP NP0 150P J 50V	0603
C071	2320091	CHIPCAP X7R 2N2 J 50V	0603
C072	2340014	CHIPCAP X7R 47N K 25V	0805
C073	2340014	CHIPCAP X7R 47N K 25V	0805
C074	2320063	CHIPCAP NP0 150P J 50V	0603
C075	2320091	CHIPCAP X7R 2N2 J 50V	0603
C076	2320063	CHIPCAP NP0 150P J 50V	0603
C077	2320091	CHIPCAP X7R 2N2 J 50V	0603
C078	2340014	CHIPCAP X7R 47N K 25V	0805
C079	2320043	CHIPCAP NP0 22P J 50V	0603
C080	2320059	CHIPCAP NP0 100P J 50V	0603
C081	2320059	CHIPCAP NP0 100P J 50V	0603
C082	2320059	CHIPCAP NP0 100P J 50V	0603
C083	2320059	CHIPCAP NP0 100P J 50V	0603
C084	2320059	CHIPCAP NP0 100P J 50V	0603
C085	2320059	CHIPCAP NP0 100P J 50V	0603
C086	2320059	CHIPCAP NP0 100P J 50V	0603
C087	2320059	CHIPCAP NP0 100P J 50V	0603
C088	2320043	CHIPCAP NP0 22P J 50V	0603
C089	2320043	CHIPCAP NP0 22P J 50V	0603
C090	2320043	CHIPCAP NP0 22P J 50V	0603
C091	2320043	CHIPCAP NP0 22P J 50V	0603
C092	2320043	CHIPCAP NP0 22P J 50V	0603
C093	2320043	CHIPCAP NP0 22P J 50V	0603
C094	2320043	CHIPCAP NP0 22P J 50V	0603
C095	2320043	CHIPCAP NP0 22P J 50V	0603
C096	2320043	CHIPCAP NP0 22P J 50V	0603
C100	2320047	CHIPCAP NP0 33P J 50V	0603
C101	2320057	CHIPCAP NP0 82P J 50V	0603
C102	2320120	CHIPCAP X7R 22N K 25V	0603
C103	2320083	CHIPCAP X7R 1N0 J 50V	0603
C104	2320464	CHIPCAP NP0 180P J 50V	0603
C105	2320057	CHIPCAP NP0 82P J 50V	0603

## Parts Lists

## Technical Documentation

C106	2320057	CHIPCAP NP0 82P J 50V	0603
C107	2320047	CHIPCAP NP0 33P J 50V	0603
C108	2320464	CHIPCAP NP0 180P J 50V	0603
C109	2320059	CHIPCAP NP0 100P J 50V	0603
C110	2320039	CHIPCAP NP0 15P J 50V	0603
C111	2320019	CHIPCAP NP0 2P2 C 50V	0603
C112	2320039	CHIPCAP NP0 15P J 50V	0603
C113	2320057	CHIPCAP NP0 82P J 50V	0603
C114	2320057	CHIPCAP NP0 82P J 50V	0603
C115	2320029	CHIPCAP NP0 5P6 C 50V	0603
C116	2320075	CHIPCAP X7R 470P J 50V	0603
C117	2320075	CHIPCAP X7R 470P J 50V	0603
C118	2312401	CHIPCAP X5R 1U0 K 10V	0805
C119	2320045	CHIPCAP NP0 27P J 50V	0603
C120	2320083	CHIPCAP X7R 1N0 J 50V	0603
C121	2320045	CHIPCAP NP0 27P J 50V	0603
C122	2320045	CHIPCAP NP0 27P J 50V	0603
C123	2320057	CHIPCAP NP0 82P J 50V	0603
C124	2320059	CHIPCAP NP0 100P J 50V	0603
C125	2320107	CHIPCAP X7R 10N J 50V	0603
C126	2320107	CHIPCAP X7R 10N J 50V	0603
C127	2312401	CHIPCAP X5R 1U0 K 10V	0805
C128	2320083	CHIPCAP X7R 1N0 J 50V	0603
C129	2312401	CHIPCAP X5R 1U0 K 10V	0805
C130	2320053	CHIPCAP NP0 56P J 50V	0603
C131	2320083	CHIPCAP X7R 1N0 J 50V	0603
C132	2320091	CHIPCAP X7R 2N2 J 50V	0603
C133	2320057	CHIPCAP NP0 82P J 50V	0603
C134	2320053	CHIPCAP NP0 56P J 50V	0603
C135	2310417	CHIPCAP NP0 82P J 50V	0805
C200	2320047	CHIPCAP NP0 33P J 50V	0603
C201	2320047	CHIPCAP NP0 33P J 50V	0603
C202	2320047	CHIPCAP NP0 33P J 50V	0603
C203	2320031	CHIPCAP NP0 6P8 C 50V	0603
C204	2320029	CHIPCAP NP0 5P6 C 50V	0603
C205	2320031	CHIPCAP NP0 6P8 C 50V	0603
C206	2320031	CHIPCAP NP0 6P8 C 50V	0603
C207	2320017	CHIPCAP NP0 1P8 C 50V	0603
C208	2320039	CHIPCAP NP0 15P J 50V	0603
C209	2320059	CHIPCAP NP0 100P J 50V	0603
C210	2320059	CHIPCAP NP0 100P J 50V	0603
C211	2320059	CHIPCAP NP0 100P J 50V	0603
C212	2312401	CHIPCAP X5R 1U0 K 10V	0805
C213	2320047	CHIPCAP NP0 33P J 50V	0603
C214	2320047	CHIPCAP NP0 33P J 50V	0603
C215	2320083	CHIPCAP X7R 1N0 J 50V	0603
C250	2320779	CHIPCAP X7R 100N K 16V	0603
C251	2320779	CHIPCAP X7R 100N K 16V	0603
C252	2320779	CHIPCAP X7R 100N K 16V	0603

C253	2320107	CHIPCAP X7R 10N J 50V	0603
C254	2320039	CHIPCAP NP0 15P J 50V	0603
C255	2320053	CHIPCAP NP0 56P J 50V	0603
C256	2320057	CHIPCAP NP0 82P J 50V	0603
C257	2320057	CHIPCAP NP0 82P J 50V	0603
C258	2320047	CHIPCAP NP0 33P J 50V	0603
C259	2320059	CHIPCAP NP0 100P J 50V	0603
C260	2320107	CHIPCAP X7R 10N J 50V	0603
C261	2320043	CHIPCAP NP0 22P J 50V	0603
C262	2320083	CHIPCAP X7R 1N0 J 50V	0603
C263	2320057	CHIPCAP NP0 82P J 50V	0603
C264	2320057	CHIPCAP NP0 82P J 50V	0603
C265	2320059	CHIPCAP NP0 100P J 50V	0603
C266	2320057	CHIPCAP NP0 82P J 50V	0603
C267	2320045	CHIPCAP NP0 27P J 50V	0603
C268	2320107	CHIPCAP X7R 10N J 50V	0603
C269	2320107	CHIPCAP X7R 10N J 50V	0603
C270	2320019	CHIPCAP NP0 2P2 C 50V	0603
C271	2320029	CHIPCAP NP0 5P6 C 50V	0603
C272	2517801	ELCAP CHIP 330U M 25V 105°C 10X10	
C273	2517801	ELCAP CHIP 330U M 25V 105°C 10X10	
C274	2517801	ELCAP CHIP 330U M 25V 105°C 10X10	
C275	2517801	ELCAP CHIP 330U M 25V 105°C 10X10	
C300	2320107	CHIPCAP X7R 10N J 50V	0603
C301	2320107	CHIPCAP X7R 10N J 50V	0603
C302	2312401	CHIPCAP X5R 1U0 K 10V	0805
C303	2320083	CHIPCAP X7R 1N0 J 50V	0603
C304	2320083	CHIPCAP X7R 1N0 J 50V	0603
C305	2320107	CHIPCAP X7R 10N J 50V	0603
C306	2320107	CHIPCAP X7R 10N J 50V	0603
C307	2320107	CHIPCAP X7R 10N J 50V	0603
C308	2320107	CHIPCAP X7R 10N J 50V	0603
C309	2320057	CHIPCAP NP0 82P J 50V	0603
C310	2320107	CHIPCAP X7R 10N J 50V	0603
C311	2610003	CHIPTCAP 10U M 10V 3.2X1.6X1.6	
C312	2610003	CHIPTCAP 10U M 10V 3.2X1.6X1.6	
C313	2312401	CHIPCAP X5R 1U0 K 10V	0805
C314	2320083	CHIPCAP X7R 1N0 J 50V	0603
C315	2320057	CHIPCAP NP0 82P J 50V	0603
C316	2320059	CHIPCAP NP0 100P J 50V	0603
C317	2320019	CHIPCAP NP0 2P2 C 50V	0603
C318	2320023	CHIPCAP NP0 3P3 C 50V	0603
C319	2320047	CHIPCAP NP0 33P J 50V	0603
C320	2320083	CHIPCAP X7R 1N0 J 50V	0603
C321	2320029	CHIPCAP NP0 5P6 C 50V	0603
C322	2320057	CHIPCAP NP0 82P J 50V	0603
C323	2320039	CHIPCAP NP0 15P J 50V	0603
C324	2320019	CHIPCAP NP0 2P2 C 50V	0603
C325	2320053	CHIPCAP NP0 56P J 50V	0603

## Parts Lists

## Technical Documentation

C326	2312215	CHIPCAP NP0 2N2 J 50V	0805
C327	2320063	CHIPCAP NP0 150P J 50V	0603
C328	2320107	CHIPCAP X7R 10N J 50V	0603
C329	2320047	CHIPCAP NP0 33P J 50V	0603
C400	2320107	CHIPCAP X7R 10N J 50V	0603
C401	2309517	CHIPCAP X7R 100N K 50V	1206
C402	2320107	CHIPCAP X7R 10N J 50V	0603
C403	2320779	CHIPCAP X7R 100N K 16V	0603
C404	2611685	CHIPTCAP 22U M 35V 7.3X4.3X4.1	
C405	2517801	ELCAP CHIP 330U M 25V 105'C 10X10	
C406	2517801	ELCAP CHIP 330U M 25V 105'C 10X10	
C407	2517801	ELCAP CHIP 330U M 25V 105'C 10X10	
C408	2320083	CHIPCAP X7R 1N0 J 50V	0603
C409	2312411	CHIPCAP X5R 1U0 M 25V	1206
C410	2517801	ELCAP CHIP 330U M 25V 105'C 10X10	
C411	2309517	CHIPCAP X7R 100N K 50V	1206
C412	2320043	CHIPCAP NP0 22P J 50V	0603
C413	2309517	CHIPCAP X7R 100N K 50V	1206
C414	2312401	CHIPCAP X5R 1U0 K 10V	0805
C415	2611713	CHIPTCAP 68U K 25V 7.0X6.0X3.6	
C417	2320779	CHIPCAP X7R 100N K 16V	0603
C419	2517803	ELCAP CHIP 100U M 16V 105'C 8X6.3	
C420	2320779	CHIPCAP X7R 100N K 16V	0603
C421	2320059	CHIPCAP NP0 100P J 50V	0603
C422	2312296	CHIPCAP Y5V 10U Z 16V	1210
C423	2611713	CHIPTCAP 68U K 25V 7.0X6.0X3.6	
C424	2309517	CHIPCAP X7R 100N K 50V	1206
C425	2320779	CHIPCAP X7R 100N K 16V	0603
C426	2610105	CHIPTCAP 100U M 10V 7.3X4.3X2.9	
C427	2320779	CHIPCAP X7R 100N K 16V	0603
C428	2320083	CHIPCAP X7R 1N0 J 50V	0603
C429	2320043	CHIPCAP NP0 22P J 50V	0603
C430	2320107	CHIPCAP X7R 10N J 50V	0603
C431	2320779	CHIPCAP X7R 100N K 16V	0603
C432	2517680	ELCAP CHIP 4U7 M 35V 4.5X4.5X5.5	
C433	2320043	CHIPCAP NP0 22P J 50V	0603
C434	2320043	CHIPCAP NP0 22P J 50V	0603
C435	2320779	CHIPCAP X7R 100N K 16V	0603
C436	2312401	CHIPCAP X5R 1U0 K 10V	0805
C437	2517850	ELCAP CHIP 220U M 35V 105'C 10X10	
C450	2312401	CHIPCAP X5R 1U0 K 10V	0805
C451	2312401	CHIPCAP X5R 1U0 K 10V	0805
C500	2320120	CHIPCAP X7R 22N K 25V	0603
C501	2320079	CHIPCAP X7R 680P J 50V	0603
C502	2320120	CHIPCAP X7R 22N K 25V	0603
C503	2517803	ELCAP CHIP 100U M 16V 105'C 8X6.3	
C504	2320779	CHIPCAP X7R 100N K 16V	0603
C505	2320067	CHIPCAP X7R 220P J 50V	0603
C506	2320131	CHIPCAP X7R 33N K 16V	0603

C507	2610003	CHIPTCAP 10U M 10V	3.2X1.6X1.6
C508	2320131	CHIPCAP X7R 33N K 16V	0603
C509	2320067	CHIPCAP X7R 220P J 50V	0603
C510	2320067	CHIPCAP X7R 220P J 50V	0603
C511	2320131	CHIPCAP X7R 33N K 16V	0603
C512	2610003	CHIPTCAP 10U M 10V	3.2X1.6X1.6
C513	2320131	CHIPCAP X7R 33N K 16V	0603
C514	2320067	CHIPCAP X7R 220P J 50V	0603
C515	2320120	CHIPCAP X7R 22N K 25V	0603
C516	2320043	CHIPCAP NP0 22P J 50V	0603
C517	2320107	CHIPCAP X7R 10N J 50V	0603
C518	2517803	ELCAP CHIP 100U M 16V	105'C 8X6.3
C519	2320120	CHIPCAP X7R 22N K 25V	0603
C520	2320067	CHIPCAP X7R 220P J 50V	0603
C521	2320779	CHIPCAP X7R 100N K 16V	0603
C522	2320779	CHIPCAP X7R 100N K 16V	0603
C523	2320779	CHIPCAP X7R 100N K 16V	0603
C524	2517850	ELCAP CHIP 220U M 35V	105'C 10X10
C525	2610003	CHIPTCAP 10U M 10V	3.2X1.6X1.6
C600	2604093	CHIPTCAP 2U2 M 35V	6.0X3.2X2.5
C601	2320779	CHIPCAP X7R 100N K 16V	0603
C603	2320067	CHIPCAP X7R 220P J 50V	0603
C604	2320043	CHIPCAP NP0 22P J 50V	0603
C605	2320043	CHIPCAP NP0 22P J 50V	0603
C606	2320107	CHIPCAP X7R 10N J 50V	0603
C607	2320107	CHIPCAP X7R 10N J 50V	0603
C608	2320107	CHIPCAP X7R 10N J 50V	0603
C609	2320107	CHIPCAP X7R 10N J 50V	0603
C610	2320107	CHIPCAP X7R 10N J 50V	0603
C611	2320107	CHIPCAP X7R 10N J 50V	0603
C612	2320107	CHIPCAP X7R 10N J 50V	0603
C613	2320107	CHIPCAP X7R 10N J 50V	0603
C614	2320107	CHIPCAP X7R 10N J 50V	0603
C615	2320107	CHIPCAP X7R 10N J 50V	0603
C616	2320107	CHIPCAP X7R 10N J 50V	0603
C617	2320107	CHIPCAP X7R 10N J 50V	0603
C618	2320107	CHIPCAP X7R 10N J 50V	0603
C619	2320107	CHIPCAP X7R 10N J 50V	0603
C620	2320107	CHIPCAP X7R 10N J 50V	0603
C621	2320107	CHIPCAP X7R 10N J 50V	0603
C622	2320107	CHIPCAP X7R 10N J 50V	0603
C623	2320107	CHIPCAP X7R 10N J 50V	0603
C624	2320107	CHIPCAP X7R 10N J 50V	0603
C625	2320107	CHIPCAP X7R 10N J 50V	0603
C626	2320107	CHIPCAP X7R 10N J 50V	0603
C627	2320107	CHIPCAP X7R 10N J 50V	0603
C628	2315011	CHIP ARRAY NP0 4X22P K 16V	0612
C650	2310781	CHIPCAP X7R 220N K 16V	0805
C651	2310781	CHIPCAP X7R 220N K 16V	0805

## Parts Lists

## Technical Documentation

C652	2310781	CHIPCAP X7R 220N K 16V	0805
C653	2310781	CHIPCAP X7R 220N K 16V	0805
C654	2310781	CHIPCAP X7R 220N K 16V	0805
C655	2310781	CHIPCAP X7R 220N K 16V	0805
C700	2611689	CHIPTCAP 470U M 10V L 7.3X4.3X4.1	
C701	2312401	CHIPCAP X5R 1U0 K 10V	0805
C702	2312401	CHIPCAP X5R 1U0 K 10V	0805
C703	2320107	CHIPCAP X7R 10N J 50V	0603
C704	2610003	CHIPTCAP 10U M 10V 3.2X1.6X1.6	
C705	2320779	CHIPCAP X7R 100N K 16V	0603
C706	2312401	CHIPCAP X5R 1U0 K 10V	0805
C707	2320107	CHIPCAP X7R 10N J 50V	0603
C708	2320131	CHIPCAP X7R 33N K 16V	0603
C709	2320779	CHIPCAP X7R 100N K 16V	0603
C710	2610003	CHIPTCAP 10U M 10V 3.2X1.6X1.6	
C711	2312401	CHIPCAP X5R 1U0 K 10V	0805
C712	2312403	CHIPCAP X5R 2U2 K 10V	1206
C713	2610003	CHIPTCAP 10U M 10V 3.2X1.6X1.6	
C714	2312401	CHIPCAP X5R 1U0 K 10V	0805
C715	2312401	CHIPCAP X5R 1U0 K 10V	0805
C716	2320033	CHIPCAP NP0 8P2 C 50V	0603
C717	2320047	CHIPCAP NP0 33P J 50V	0603
C718	2312401	CHIPCAP X5R 1U0 K 10V	0805
C720	2610003	CHIPTCAP 10U M 10V 3.2X1.6X1.6	
C723	2312401	CHIPCAP X5R 1U0 K 10V	0805
C724	2320779	CHIPCAP X7R 100N K 16V	0603
C725	2312401	CHIPCAP X5R 1U0 K 10V	0805
C727	2320011	CHIPCAP NP0 1P0 C 50V	0603
C728	2320011	CHIPCAP NP0 1P0 C 50V	0603
C729	2312403	CHIPCAP X5R 2U2 K 10V	1206
C730	2312401	CHIPCAP X5R 1U0 K 10V	0805
C731	2320779	CHIPCAP X7R 100N K 16V	0603
C732	2320107	CHIPCAP X7R 10N J 50V	0603
C733	2320107	CHIPCAP X7R 10N J 50V	0603
C734	2310781	CHIPCAP X7R 220N K 16V	0805
C735	2312401	CHIPCAP X5R 1U0 K 10V	0805
C736	2320083	CHIPCAP X7R 1N0 J 50V	0603
C737	2320107	CHIPCAP X7R 10N J 50V	0603
C738	2320107	CHIPCAP X7R 10N J 50V	0603
C739	2312401	CHIPCAP X5R 1U0 K 10V	0805
C750	2320053	CHIPCAP NP0 56P J 50V	0603
C800	2320107	CHIPCAP X7R 10N J 50V	0603
C801	2320059	CHIPCAP NP0 100P J 50V	0603
C802	2320131	CHIPCAP X7R 33N K 16V	0603
C803	2320131	CHIPCAP X7R 33N K 16V	0603
C804	2312401	CHIPCAP X5R 1U0 K 10V	0805
C807	2610003	CHIPTCAP 10U M 10V 3.2X1.6X1.6	
C809	2320131	CHIPCAP X7R 33N K 16V	0603
C810	2320059	CHIPCAP NP0 100P J 50V	0603

C812	2320131	CHIPCAP X7R 33N K 16V	0603
C814	2320059	CHIPCAP NP0 100P J 50V	0603
C816	2610003	CHIPTCAP 10U M 10V 3.2X1.6X1.6	
C818	2320107	CHIPCAP X7R 10N J 50V	0603
C819	2320107	CHIPCAP X7R 10N J 50V	0603
C820	2320107	CHIPCAP X7R 10N J 50V	0603
C821	2320107	CHIPCAP X7R 10N J 50V	0603
C822	2320107	CHIPCAP X7R 10N J 50V	0603
C823	2320107	CHIPCAP X7R 10N J 50V	0603
C824	2320107	CHIPCAP X7R 10N J 50V	0603
C828	2320120	CHIPCAP X7R 22N K 25V	0603
D600	4370551	MAD2 ROM4 V25 F731929E C07 TQFP	
D601	4342264	EEPROM 8KX8 SER 2.7-5.5V SO8S	
D602	4340509	FLASH 1MX16 120NS 2.7V TSOP48	
D603	4340397	SRAM 128KX8 120NS 2.3-3.3V STSOP3	
D700	4340687	SN74LVC08A 4X 2-INPUT AND SO14	
D701	4340575	74HC123A 2XRETRIG.MULTIVIBR SO16S	
D702	4340156	74LV74 2XD-FF +EDGE-TR.+RES.SO14S	
G300	4510213	VCTCXO 13MHZ+-5PPM 2.8V GSM/PCN	
G301	4350125	VCO 1006-1031MHZ 2.8V 10MA GSM ET	
L001	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L002	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L003	3641282	CHIP COIL 2U2 J Q30/7.96MHZ 1008	
L005	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L006	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L007	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L008	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L009	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L010	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L011	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L012	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L013	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L014	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L015	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L016	3641262	FERRITE BEAD 30R/100MHZ 2A 1206	
L100	3641622	CHIP COIL 220N J Q30/100MHZ 0805	
L101	3641546	CHIP COIL 82N K Q40/150MHZ 0805	
L102	3645031	CHIP COIL 330NH K Q20/25MHZ 0805	
L104	3641548	CHIP COIL 100N K Q40/150MHZ 0805	
L105	3641560	CHIP COIL 220N K Q30/100MHZ 0805	
L106	3643039	CHIP COIL 220NH J Q35/100MHZ 0805	
L107	3641548	CHIP COIL 100N K Q40/150MHZ 0805	
L108	3645131	CHIP COIL 8N2 J Q8/100M 0603	
L109	3645031	CHIP COIL 330NH K Q20/25MHZ 0805	
L200	3640051	CHIP COIL 12N J Q45/250MHZ 0805	
L201	3641526	CHIP COIL 12N K Q45/250MHZ 0805	
L202	3641526	CHIP COIL 12N K Q45/250MHZ 0805	
L203	3645031	CHIP COIL 330NH K Q20/25MHZ 0805	
L204	3645031	CHIP COIL 330NH K Q20/25MHZ 0805	

L250	3641521	CHIP COIL 6N8 J Q50/250MHZ	0805
L251	3645123	CHIP COIL 10NH J Q31/800M	0603
L252	3645001	CHIP COIL 4N7 K Q10/100MHZ	0603
L300	3645121	CHIP COIL 6N8 J Q32/800M	0603
L301	3641540	CHIP COIL 47N M Q40/200MHZ	0805
L302	3641542	CHIP COIL 56N K Q40/200MHZ	0805
L303	3640053	CHIP COIL 4N7 +--0N3 Q8/100	0603
L400	3643067	CHIP COIL 100UH J Q15/796KHZ	1008
L500	3643067	CHIP COIL 100UH J Q15/796KHZ	1008
L702	3641282	CHIP COIL 2U2 J Q30/7.96MHZ	1008
N100	4350085	SLM-090A MIXER 700-1000MHZ	
N101	4370273	PLUSSA TXMOD+RXIF+2PLL	TQFP64
N200	4370253	CRFU1A RX+TX UHF GSM V5	SOT401-1
N250	4340647	MC33074D 4XOPAMP 3-44V 4.5M	SO14
N254	4350151	PW AMP 890-915MHZ 23W 12V	GSM
N400	4340067	LP2951 REG LD 3.3V 100MA 1%	SO8
N401	4340641	LM2937 REG LDO 8V 500MA	TO263
N402	4340067	LP2951 REG LD 3.3V 100MA 1%	SO8
N403	4340028	TLC393 2XCOMPARAT.DIFF.VOLT.	SO8S
N500	4340677	TPA1517 AUDIO POWER 6W/C AMP	SO20
N501	4340693	TS922 2X OP AMP 80MA 2.7-12V	SO8
N502	4301182	LM2902 4XOP.AMP -40/+105C	SO14S
N600	4340067	LP2951 REG LD 3.3V 100MA 1%	SO8
N650	4340501	MAX3237EAI RS232 5TX3RX	SSOP28
N700	4370479	CCONT2I WFD163KT64T	TQFP64
N701	4340071	LP2980 REG LD 3V 50MA	SSO5
N800	4370363	COBBA_GJ B09 BB ASIC	TQFP64
S250	4340085	TC7S66F 1XBILATERAL SWITCH	SSO5
S251	4340085	TC7S66F 1XBILATERAL SWITCH	SSO5
U001	2610003	CHIPTCAP 10U M 10V	3.2X1.6X1.6
V001	4113915	TVS DI SM5S26A 26V86A3K6W	DO218AA
V002	4110396	ZDI BZX84 3.0V 5% 0.3W	SOT23
V100	4210074	TR BFP420 N 4.5V35MA 20GHZ	SOT343
V101	4219922	TRX2 UMZ1 N&P 40V 0.1A >120	UM6
V102	4210074	TR BFP420 N 4.5V35MA 20GHZ	SOT343
V250	4100285	DIX2 BAV99 70V 200MA IN SER.	SOT23
V251	4200917	TR BC848B/BCW32 N 30V 100MA	SOT23
V252	4110014	SCHDIX2 BAS70-07 70V 15MA	SOT143
V253	4219922	TRX2 UMZ1 N&P 40V 0.1A >120	UM6
V254	4210010	BFP183 N 12V 65MA 8GHZ	SOT143
V300	4210010	BFP183 N 12V 65MA 8GHZ	SOT143
V301	4210066	TR BFR93AW N 12V 35MA 5GHZ	SOT323
V302	4110018	CAP.DI BB135 30V 2.1/21PF	SOD323
V303	4210010	BFP183 N 12V 65MA 8GHZ	SOT143
V400	4211601	MFET X2 NDS8947 P 30V4A 0R065	SO8
V401	4110028	TVS DI 16V 600W 23A	DO214AA
V402	4115811	SCH DI RB491D 20V 1A VF<0.45	SC59
V403	4200917	TR BC848B/BCW32 N 30V 100MA	SOT23
V404	4210096	TR BCP54 N 45V 1.5A 130MHZ	SOT223



V405	4110014	SCHDIX2 BAS70-07 70V 15MA SOT143
V406	4200917	TR BC848B/BCW32 N 30V 100MA SOT23
V407	4200917	TR BC848B/BCW32 N 30V 100MA SOT23
V408	4200917	TR BC848B/BCW32 N 30V 100MA SOT23
V450	4108639	DIX2 BAS28 75V 250MA SOT143
V451	4200836	TR BCX19 N 50V 0.5A 200MHZ SOT23
V452	4200917	TR BC848B/BCW32 N 30V 100MA SOT23
V453	4200909	TR BC858B/BCW30 P 30V 100MA SOT23
V454	4200603	TR BCX17 P 45V 500MA 100MHZ SOT23
V455	4200917	TR BC848B/BCW32 N 30V 100MA SOT23
V456	4100278	DIX2 BAV70 70V 200MA COMCAT.SOT23
V457	4101653	DI BYD17D 200V 1.5A PEAK20A SOD87
V458	4101653	DI BYD17D 200V 1.5A PEAK20A SOD87
V600	4100278	DIX2 BAV70 70V 200MA COMCAT.SOT23
V601	4110014	SCHDIX2 BAS70-07 70V 15MA SOT143
V602	4200909	TR BC858B/BCW30 P 30V 100MA SOT23
V603	4200917	TR BC848B/BCW32 N 30V 100MA SOT23
V701	4210215	TR MMBT589 P 30V 1A 0.3W 80 SOT23
V702	4110067	SCH DI MBR0520L 20V 0.5A SOD123
V703	4113651	TVS DI QUAD 6V ESDA6V1SC5 SOT23-5
V704	4200917	TR BC848B/BCW32 N 30V 100MA SOT23
V705	4110014	SCHDIX2 BAS70-07 70V 15MA SOT143
V706	4110014	SCHDIX2 BAS70-07 70V 15MA SOT143
V707	4200917	TR BC848B/BCW32 N 30V 100MA SOT23
V708	4200917	TR BC848B/BCW32 N 30V 100MA SOT23
V750	4102998	LED GRN >5MCD/20MA 2.2V 1206
V751	4102998	LED GRN >5MCD/20MA 2.2V 1206
X001	5400141	CONN 2X16 HEADER P2.54 90DEGREE
X080	5430009	D9 CONN F 90DEG BOARDLOCKUNC4-40
X240	5420011	CONNECTOR MINI UHF 90'DEG <2.5GHZ
X750	5400033	SIM CARD READER CCM04-5003 6POL
X914	5431718	FLEXFOIL CONNECT 1X30 0.5MM SMD
Z001	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z002	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z004	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z005	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z006	3648808	CHIP COIL 10U K Q50 1206
Z080	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z081	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z082	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z083	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z084	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z085	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z086	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z087	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z088	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z100	4512001	DUPL 890-915/935-960MHZ 39.7X14.8
Z101	4511017	SAW FILT 947.5+-12.5MHZ/3.8DB 4X4
Z102	4510137	SAW FILT 71+-0.09MHZ 14.2X8.4

Z103	4510009	CER.FILT 13+-0.09MHZ	7.2X3.2
Z250	4511015	SAW FILT 902.5+-12.5MHZ/3.8DB	4X4
Z650	3648808	CHIP COIL 10U K Q50	1206

**GM8B\_07 (0201346)**

(EDMS V 10.0)

Item	Code	Description / Value / Type
R	504 506 509 511	
R001	1430142	CHIP RESISTOR 4.7 5 % 0.063 W 0603
R002	1430142	CHIP RESISTOR 4.7 5 % 0.063 W 0603
R003	1430035	CHIP RESISTOR 1.0 K 5 % 0.063 W 0603
R004	1430142	CHIP RESISTOR 4.7 5 % 0.063 W 0603
R005	1430167	CHIP RESISTOR 47 5 % 0.063 W 0603
R006	1430167	CHIP RESISTOR 47 5 % 0.063 W 0603
R007	1430151	CHIP RESISTOR 10 5 % 0.1 W 0603
R008	1430167	CHIP RESISTOR 47 5 % 0.063 W 0603
R009	1430151	CHIP RESISTOR 10 5 % 0.1 W 0603
R010	1430167	CHIP RESISTOR 47 5 % 0.063 W 0603
R011	1430144	CHIP JUMPER 0603
R012	1430151	CHIP RESISTOR 10 5 % 0.1 W 0603
R013	1430167	CHIP RESISTOR 47 5 % 0.063 W 0603
R014	1430151	CHIP RESISTOR 10 5 % 0.1 W 0603
R015	1430167	CHIP RESISTOR 47 5 % 0.063 W 0603
R016	1430151	CHIP RESISTOR 10 5 % 0.1 W 0603
R017	1430167	CHIP RESISTOR 47 5 % 0.063 W 0603
R018	1430151	CHIP RESISTOR 10 5 % 0.1 W 0603
R019	1430167	CHIP RESISTOR 47 5 % 0.063 W 0603
R020	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R021	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R022	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R023	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R024	1430035	CHIP RESISTOR 1.0 K 5 % 0.063 W 0603
R080	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R081	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R082	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R083	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R084	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R085	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R086	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R087	1430159	CHIP RESISTOR 22 5 % 0.063 W 0603
R100	1430001	CHIP RESISTOR 100 5 % 0.063 W 0603
R101	1430163	CHIP RESISTOR 33 5 % 0.063 W 0603
R102	1620035	RES NETWORK 0W06 2X10R J 0404
R103	1620019	RES NETWORK 0W06 2X10K J 0404
R104	1430045	CHIP RESISTOR 2.7 K 5 % 0.063 W 0603
R105	1430013	CHIP RESISTOR 330 5 % 0.063 W 0603
R106	1430017	CHIP RESISTOR 390 5 % 0.063 W 0603
R107	1620019	RES NETWORK 0W06 2X10K J 0404
R108	1430015	CHIP RESISTOR 470 5 % 0.063 W 0603
R109	1430055	CHIP RESISTOR 6.8 K 5 % 0.063 W 0603

## Parts Lists

## Technical Documentation

R110	1430069	CHIP RESISTOR	18 K	5 % 0.063 W 0603
R111	1430039	CHIP RESISTOR	1.5 K	5 % 0.063 W 0603
R112	1430005	CHIP RESISTOR	150	5 % 0.063 W 0603
R113	1430001	CHIP RESISTOR	100	5 % 0.063 W 0603
R114	1430007	CHIP RESISTOR	180	5 % 0.063 W 0603
R115	1620031	RES NETWORK 0W06 2X1K0 J	0404	
R116	1430013	CHIP RESISTOR	330	5 % 0.063 W 0603
R117	1430039	CHIP RESISTOR	1.5 K	5 % 0.063 W 0603
R118	1430087	CHIP RESISTOR	100 K	5 % 0.063 W 0603
R119	1430151	CHIP RESISTOR	10	5 % 0.1 W 0603
R120	1430009	CHIP RESISTOR	220	5 % 0.063 W 0603
R121	1430063	CHIP RESISTOR	12 K	5 % 0.063 W 0603
R122	1430087	CHIP RESISTOR	100 K	5 % 0.063 W 0603
R123	1430063	CHIP RESISTOR	12 K	5 % 0.063 W 0603
R124	1430063	CHIP RESISTOR	12 K	5 % 0.063 W 0603
R125	1430067	CHIP RESISTOR	15 K	5 % 0.063 W 0603
R126	1430087	CHIP RESISTOR	100 K	5 % 0.063 W 0603
R127	1430063	CHIP RESISTOR	12 K	5 % 0.063 W 0603
R128	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R129	1430007	CHIP RESISTOR	180	5 % 0.063 W 0603
R200	1430045	CHIP RESISTOR	2.7 K	5 % 0.063 W 0603
R201	1430151	CHIP RESISTOR	10	5 % 0.1 W 0603
R202	1430151	CHIP RESISTOR	10	5 % 0.1 W 0603
R203	1430151	CHIP RESISTOR	10	5 % 0.1 W 0603
R204	1620019	RES NETWORK 0W06 2X10K J	0404	
R205	1430151	CHIP RESISTOR	10	5 % 0.1 W 0603
R250	1430095	CHIP RESISTOR	220 K	5 % 0.063 W 0603
R251	1430043	CHIP RESISTOR	2.2 K	5 % 0.063 W 0603
R252	1430087	CHIP RESISTOR	100 K	5 % 0.063 W 0603
R253	1430043	CHIP RESISTOR	2.2 K	5 % 0.063 W 0603
R254	1430051	CHIP RESISTOR	4.7 K	5 % 0.063 W 0603
R255	1430067	CHIP RESISTOR	15 K	5 % 0.063 W 0603
R256	1430087	CHIP RESISTOR	100 K	5 % 0.063 W 0603
R257	1430063	CHIP RESISTOR	12 K	5 % 0.063 W 0603
R258	1430103	CHIP RESISTOR	470 K	5 % 0.063 W 0603
R259	1430071	CHIP RESISTOR	22 K	5 % 0.063 W 0603
R260	1430071	CHIP RESISTOR	22 K	5 % 0.063 W 0603
R261	1430079	CHIP RESISTOR	47 K	5 % 0.063 W 0603
R262	1430073	CHIP RESISTOR	27 K	5 % 0.063 W 0603
R263	1430089	CHIP RESISTOR	120 K	5 % 0.063 W 0603
R264	1430099	CHIP RESISTOR	330 K	5 % 0.063 W 0603
R265	1430067	CHIP RESISTOR	15 K	5 % 0.063 W 0603
R266	1430069	CHIP RESISTOR	18 K	5 % 0.063 W 0603
R267	1430049	CHIP RESISTOR	3.9 K	5 % 0.063 W 0603
R268	1430067	CHIP RESISTOR	15 K	5 % 0.063 W 0603
R269	1430071	CHIP RESISTOR	22 K	5 % 0.063 W 0603
R270	1430151	CHIP RESISTOR	10	5 % 0.1 W 0603
R271	1430001	CHIP RESISTOR	100	5 % 0.063 W 0603
R272	1430001	CHIP RESISTOR	100	5 % 0.063 W 0603

R273	1620019	RES NETWORK 0W06 2X10K J 0404		
R274	1430087	CHIP RESISTOR	100 K	5 % 0.063 W 0603
R275	1430007	CHIP RESISTOR	180	5 % 0.063 W 0603
R276	1430035	CHIP RESISTOR	1.0 K	5 % 0.063 W 0603
R277	1430069	CHIP RESISTOR	18 K	5 % 0.063 W 0603
R278	1430005	CHIP RESISTOR	150	5 % 0.063 W 0603
R279	1430057	CHIP RESISTOR	8.2 K	5 % 0.063 W 0603
R280	1430171	CHIP RESISTOR	68	5 % 0.063 W 0603
R281	1430171	CHIP RESISTOR	68	5 % 0.063 W 0603
R300	1430163	CHIP RESISTOR	33	5 % 0.063 W 0603
R301	1430057	CHIP RESISTOR	8.2 K	5 % 0.063 W 0603
R302	1430071	CHIP RESISTOR	22 K	5 % 0.063 W 0603
R303	1430067	CHIP RESISTOR	15 K	5 % 0.063 W 0603
R304	1430011	CHIP RESISTOR	270	5 % 0.063 W 0603
R305	1430151	CHIP RESISTOR	10	5 % 0.1 W 0603
R306	1430169	CHIP RESISTOR	56	5 % 0.063 W 0603
R307	1430163	CHIP RESISTOR	33	5 % 0.063 W 0603
R308	1430035	CHIP RESISTOR	1.0 K	5 % 0.063 W 0603
R311	1430047	CHIP RESISTOR	3.3 K	5 % 0.063 W 0603
R312	1430075	CHIP RESISTOR	33 K	5 % 0.063 W 0603
R313	1430043	CHIP RESISTOR	2.2 K	5 % 0.063 W 0603
R314	1430043	CHIP RESISTOR	2.2 K	5 % 0.063 W 0603
R315	1430073	CHIP RESISTOR	27 K	5 % 0.063 W 0603
R316	1430075	CHIP RESISTOR	33 K	5 % 0.063 W 0603
R317	1430159	CHIP RESISTOR	22	5 % 0.063 W 0603
R318	1430053	CHIP RESISTOR	5.6 K	5 % 0.063 W 0603
R319	1430055	CHIP RESISTOR	6.8 K	5 % 0.063 W 0603
R320	1430011	CHIP RESISTOR	270	5 % 0.063 W 0603
R321	1430013	CHIP RESISTOR	330	5 % 0.063 W 0603
R322	1430057	CHIP RESISTOR	8.2 K	5 % 0.063 W 0603
R323	1430009	CHIP RESISTOR	220	5 % 0.063 W 0603
R324	1430009	CHIP RESISTOR	220	5 % 0.063 W 0603
R400	1430031	CHIP RESISTOR	100 K	1 % 0.063 W 0603
R401	1430105	CHIP RESISTOR	560 K	5 % 0.063 W 0603
R402	1430087	CHIP RESISTOR	100 K	5 % 0.063 W 0603
R403	1430079	CHIP RESISTOR	47 K	5 % 0.063 W 0603
R409	1620019	RES NETWORK 0W06 2X10K J 0404		
R410	1430179	CHIP RESISTOR	210 K	1 % 0.063 W 0603
R411	1430179	CHIP RESISTOR	210 K	1 % 0.063 W 0603
R412	1430079	CHIP RESISTOR	47 K	5 % 0.063 W 0603
R413	1430113	CHIP RESISTOR	348 K	1 % 0.063 W 0603
R414	1430031	CHIP RESISTOR	100 K	1 % 0.063 W 0603
R415	1430031	CHIP RESISTOR	100 K	1 % 0.063 W 0603
R416	1430181	CHIP RESISTOR	30.9 K	1 % 0.063 W 0603
R417	1430095	CHIP RESISTOR	220 K	5 % 0.063 W 0603
R418	1430039	CHIP RESISTOR	1.5 K	5 % 0.063 W 0603
R419	1430113	CHIP RESISTOR	348 K	1 % 0.063 W 0603
R420	1430051	CHIP RESISTOR	4.7 K	5 % 0.063 W 0603
R421	1430311	CHIP RESISTOR	45.3 K	1 % 0.063 W 0603

## Parts Lists

## Technical Documentation

R422	1430321	CHIP RESISTOR	261 K	1 % 0.063 W 0603
R423	1430079	CHIP RESISTOR	47 K	5 % 0.063 W 0603
R424	1430183	CHIP RESISTOR	110 K	1 % 0.063 W 0603
R425	1430087	CHIP RESISTOR	100 K	5 % 0.063 W 0603
R426	1430069	CHIP RESISTOR	18 K	5 % 0.063 W 0603
R427	1430035	CHIP RESISTOR	1.0 K	5 % 0.063 W 0603
R450	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R451	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R452	1430043	CHIP RESISTOR	2.2 K	5 % 0.063 W 0603
R453	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R454	1430071	CHIP RESISTOR	22 K	5 % 0.063 W 0603
R455	1430069	CHIP RESISTOR	18 K	5 % 0.063 W 0603
R456	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R457	1430051	CHIP RESISTOR	4.7 K	5 % 0.063 W 0603
R458	1430051	CHIP RESISTOR	4.7 K	5 % 0.063 W 0603
R459	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R460	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R461	1430051	CHIP RESISTOR	4.7 K	5 % 0.063 W 0603
R500	1415632	MELFRES 0W25 33K0 F		0204
R501	1430075	CHIPRES 0W06 33K J		0603
R502	1415632	MELFRES 0W25 33K0 F		0204
R503	1416160	MELFRES 0W25 100K F		0204
R504	1416001	MELFRES 0W25 39K0 F		0204
R505	1430015	CHIP RESISTOR	470	5 % 0.063 W 0603
R506	1416001	MELFRES 0W25 39K0 F		5 % 0.063 W 0603
R506	1416001	MELFRES 0W25 39K0 F		0204
R507	1416160	MELFRES 0W25 100K F		0204
R508	1416160	MELFRES 0W25 100K F		0204
R509	1416001	MELFRES 0W25 39K0 F		0204
R510	1430015	CHIP RESISTOR	470	5 % 0.063 W 0603
R511	1416001	MELFRES 0W25 39K0 F		0204
R513	1430011	CHIP RESISTOR	270	5 % 0.063 W 0603
R515	1430013	CHIP RESISTOR	330	5 % 0.063 W 0603
R517	1620029	RES NETWORK 0W06 2X4K7 J		0404
R518	1620101	RES NETWORK 0W06 2X470R J		0404
R522	1620025	RES NETWORK 0W06 2X100K J		0404
R600	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R601	1430051	CHIP RESISTOR	4.7 K	5 % 0.063 W 0603
R602	1620025	RES NETWORK 0W06 2X100K J		0404
R603	1430051	CHIP RESISTOR	4.7 K	5 % 0.063 W 0603
R604	1430087	CHIP RESISTOR	100 K	5 % 0.063 W 0603
R605	1620025	RES NETWORK 0W06 2X100K J		0404
R606	1430051	CHIP RESISTOR	4.7 K	5 % 0.063 W 0603
R607	1430015	CHIP RESISTOR	470	5 % 0.063 W 0603
R608	1430144	CHIP JUMPER		0603
R609	1430001	CHIP RESISTOR	100	5 % 0.063 W 0603
R610	1430051	CHIP RESISTOR	4.7 K	5 % 0.063 W 0603
R611	1620025	RES NETWORK 0W06 2X100K J		0404
R612	1430087	CHIP RESISTOR	100 K	5 % 0.063 W 0603

R614	1620023	RES NETWORK 0W06 2X47K J	0404	
R615	1620017	RES NETWORK 0W06 2X100R J	0404	
R617	1430095	CHIP RESISTOR	220 K	5 % 0.063 W 0603
R618	1430015	CHIP RESISTOR	470	5 % 0.063 W 0603
R619	1430079	CHIP RESISTOR	47 K	5 % 0.063 W 0603
R700	1620025	RES NETWORK 0W06 2X100K J	0404	
R701	1430144	CHIP JUMPER		0603
R702	1430144	CHIP JUMPER		0603
R703	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R704	1430079	CHIP RESISTOR	47 K	5 % 0.063 W 0603
R705	1430325	CHIP RESISTOR	2.2 M	5 % 0.063 W 0603
R706	1430079	CHIP RESISTOR	47 K	5 % 0.063 W 0603
R707	1430107	CHIP RESISTOR	680 K	5 % 0.063 W 0603
R709	1430144	CHIP JUMPER		0603
R710	1620017	RES NETWORK 0W06 2X100R J	0404	
R711	1620011	RES NETWORK 0W06 4X100K J	1206	
R712	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R713	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R714	1620025	RES NETWORK 0W06 2X100K J	0404	
R715	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R716	1430111	CHIP RESISTOR	1.0 M	5 % 0.063 W 0603
R717	1430095	CHIP RESISTOR	220 K	5 % 0.063 W 0603
R718	1430079	CHIP RESISTOR	47 K	5 % 0.063 W 0603
R719	1620025	RES NETWORK 0W06 2X100K J	0404	
R720	1430075	CHIP RESISTOR	33 K	5 % 0.063 W 0603
R721	1430075	CHIP RESISTOR	33 K	5 % 0.063 W 0603
R722	1620025	RES NETWORK 0W06 2X100K J	0404	
R723	1430075	CHIP RESISTOR	33 K	5 % 0.063 W 0603
R726	1430065	CHIP RESISTOR	10 K	5 % 0.063 W 0603
R727	1430144	CHIP JUMPER		0603
R728	1430325	CHIP RESISTOR	2.2 M	5 % 0.063 W 0603
R750	1430039	CHIP RESISTOR	1.5 K	5 % 0.063 W 0603
R751	1430087	CHIP RESISTOR	100 K	5 % 0.063 W 0603
R800	1620025	RES NETWORK 0W06 2X100K J	0404	
R801	1430035	CHIP RESISTOR	1.0 K	5 % 0.063 W 0603
R802	1430151	CHIP RESISTOR	10	5 % 0.1 W 0603
R809	1620107	RES NETWORK 0W06 2X22K J	0404	
R810	1620101	RES NETWORK 0W06 2X470R J	0404	
R812	1430151	CHIP RESISTOR	10	5 % 0.1 W 0603
C001	2320099	CERAMIC CAP.	4.7 N	5 % 50 V 0603
C002	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C003	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C004	2320099	CERAMIC CAP.	4.7 N	5 % 50 V 0603
C005	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C006	2320099	CERAMIC CAP.	4.7 N	5 % 50 V 0603
C007	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C008	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C009	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C010	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603

## Parts Lists

## Technical Documentation

C011	2320079	CERAMIC CAP.	680 P	5 % 50 V 0603
C012	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C013	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C014	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C015	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C016	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C017	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C018	2315011	CHIP ARRAY NP0 4X22P K 16V	0612	
C019	2315011	CHIP ARRAY NP0 4X22P K 16V	0612	
C020	2315011	CHIP ARRAY NP0 4X22P K 16V	0612	
C021	2315011	CHIP ARRAY NP0 4X22P K 16V	0612	
C022	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C023	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C024	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C025	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C026	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C027	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C028	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C029	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C030	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C031	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C032	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C033	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C034	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C035	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C036	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C037	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C038	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C039	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C040	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C041	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C042	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C043	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C044	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C045	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C046	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C047	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C048	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C049	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C050	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C051	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C052	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C053	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C054	2340014	CERAMIC CAP.	47 N	10 % 25 V 0805
C055	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C056	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C057	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C058	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C059	2320091	CERAMIC CAP.	2.2 N	5 % 50 V 0603



C060	2340014	CERAMIC CAP.	47 N	10 % 25 V 0805
C061	2312411	CERAMIC CAP.	1.0 U	20 % 25 V 1206
C062	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C063	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C064	2340014	CERAMIC CAP.	47 N	10 % 25 V 0805
C065	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C066	2320091	CERAMIC CAP.	2.2 N	5 % 50 V 0603
C067	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C068	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C069	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C070	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C071	2320091	CERAMIC CAP.	2.2 N	5 % 50 V 0603
C072	2340014	CERAMIC CAP.	47 N	10 % 25 V 0805
C073	2340014	CERAMIC CAP.	47 N	10 % 25 V 0805
C074	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C075	2320091	CERAMIC CAP.	2.2 N	5 % 50 V 0603
C076	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C077	2320091	CERAMIC CAP.	2.2 N	5 % 50 V 0603
C078	2340014	CERAMIC CAP.	47 N	10 % 25 V 0805
C079	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C080	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C081	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C082	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C083	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C084	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C085	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C086	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C087	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C088	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C089	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C090	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C091	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C092	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C093	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C094	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C095	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C096	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C099	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C100	2320047	CERAMIC CAP.	33 P	5 % 50 V 0603
C101	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C102	2320120	CERAMIC CAP.	22 N	10 % 25 V 0603
C103	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C104	2320464	CERAMIC CAP.	180 P	5 % 50 V 0603
C105	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C106	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C107	2320047	CERAMIC CAP.	33 P	5 % 50 V 0603
C108	2320464	CERAMIC CAP.	180 P	5 % 50 V 0603
C109	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C110	2320039	CERAMIC CAP.	15 P	5 % 50 V 0603

## Parts Lists

## Technical Documentation

C111	2320019	CERAMIC CAP.	2.2 P	0.25 % 50 V 0603
C112	2320039	CERAMIC CAP.	15 P	5 % 50 V 0603
C113	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C114	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C115	2320029	CERAMIC CAP.	5.6 P	0.25 % 50 V 0603
C116	2320075	CERAMIC CAP.	470 P	5 % 50 V 0603
C117	2320075	CERAMIC CAP.	470 P	5 % 50 V 0603
C118	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C119	2320045	CERAMIC CAP.	27 P	5 % 50 V 0603
C120	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C121	2320045	CERAMIC CAP.	27 P	5 % 50 V 0603
C122	2320045	CERAMIC CAP.	27 P	5 % 50 V 0603
C123	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C124	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C125	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C126	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C127	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C128	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C129	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C130	2320053	CERAMIC CAP.	56 P	5 % 50 V 0603
C131	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C132	2320091	CERAMIC CAP.	2.2 N	5 % 50 V 0603
C133	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C134	2320053	CERAMIC CAP.	56 P	5 % 50 V 0603
C135	2310417	CERAMIC CAP.	82 P	5 % 50 V 0805
C200	2320047	CERAMIC CAP.	33 P	5 % 50 V 0603
C201	2320047	CERAMIC CAP.	33 P	5 % 50 V 0603
C202	2320047	CERAMIC CAP.	33 P	5 % 50 V 0603
C203	2320021	CERAMIC CAP.	2.7 P	0.25 % 50 V 0603
C204	2320029	CERAMIC CAP.	5.6 P	0.25 % 50 V 0603
C205	2320031	CERAMIC CAP.	6.8 P	0.25 % 50 V 0603
C206	2320031	CERAMIC CAP.	6.8 P	0.25 % 50 V 0603
C207	2320017	CERAMIC CAP.	1.8 P	0.25 % 50 V 0603
C208	2320039	CERAMIC CAP.	15 P	5 % 50 V 0603
C209	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C210	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C211	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C212	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C213	2320047	CERAMIC CAP.	33 P	5 % 50 V 0603
C214	2320047	CERAMIC CAP.	33 P	5 % 50 V 0603
C215	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C250	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C251	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C252	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C253	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C254	2320039	CERAMIC CAP.	15 P	5 % 50 V 0603
C255	2320053	CERAMIC CAP.	56 P	5 % 50 V 0603
C256	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C257	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603

C258	2320047	CERAMIC CAP.	33 P	5 % 50 V 0603
C259	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C260	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C261	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C262	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C263	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C264	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C265	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C266	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C267	2320045	CERAMIC CAP.	27 P	5 % 50 V 0603
C268	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C269	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C270	2320019	CERAMIC CAP.	2.2 P	0.25 % 50 V 0603
C271	2320029	CERAMIC CAP.	5.6 P	0.25 % 50 V 0603
C272	2517801	ELECTROL. CAP.	330 U	20 % 25 V 10X10
C273	2517801	ELECTROL. CAP.	330 U	20 % 25 V 10X10
C274	2517801	ELECTROL. CAP.	330 U	20 % 25 V 10X10
C275	2517801	ELECTROL. CAP.	330 U	20 % 25 V 10X10
C300	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C301	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C302	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C303	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C304	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C305	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C306	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C307	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C308	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C309	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C310	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C311	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C312	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C313	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C314	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C315	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C316	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C317	2320019	CERAMIC CAP.	2.2 P	0.25 % 50 V 0603
C318	2320023	CERAMIC CAP.	3.3 P	0.25 % 50 V 0603
C319	2320047	CERAMIC CAP.	33 P	5 % 50 V 0603
C320	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C321	2320029	CERAMIC CAP.	5.6 P	0.25 % 50 V 0603
C322	2320057	CERAMIC CAP.	82 P	5 % 50 V 0603
C323	2320039	CERAMIC CAP.	15 P	5 % 50 V 0603
C324	2320019	CERAMIC CAP.	2.2 P	0.25 % 50 V 0603
C325	2320053	CERAMIC CAP.	56 P	5 % 50 V 0603
C326	2312215	CERAMIC CAP.	2.2 N	5 % 50 V 0805
C327	2320063	CERAMIC CAP.	150 P	5 % 50 V 0603
C328	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C329	2320047	CERAMIC CAP.	33 P	5 % 50 V 0603
C400	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603

## Parts Lists

## Technical Documentation

C401	2309517	CERAMIC CAP.	100 N	10 % 50 V 1206
C402	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C403	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C404	2611685	TANTALUM CAP.	22 U	20 % 35 V 7.3X4.3X4.1
C405	2517801	ELECTROL. CAP.	330 U	20 % 25 V 10X10
C406	2517801	ELECTROL. CAP.	330 U	20 % 25 V 10X10
C407	2517801	ELECTROL. CAP.	330 U	20 % 25 V 10X10
C408	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C409	2312411	CERAMIC CAP.	1.0 U	20 % 25 V 1206
C410	2517801	ELECTROL. CAP.	330 U	20 % 25 V 10X10
C411	2309517	CERAMIC CAP.	100 N	10 % 50 V 1206
C412	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C413	2309517	CERAMIC CAP.	100 N	10 % 50 V 1206
C414	2310784	CERAMIC CAP.	100 N	10 % 25 V 0805
C415	2611713	TANTALUM CAP.	68 U	10 % 25 V 7.0X6.0X3.6
C417	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C419	2517803	ELECTROL. CAP.	100 U	20 % 16 V 8X6.3
C420	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C421	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C422	2312296	CERAMIC CAP.		Y5 V 1210
C423	2611713	TANTALUM CAP.	68 U	10 % 25 V 7.0X6.0X3.6
C424	2309517	CERAMIC CAP.	100 N	10 % 50 V 1206
C425	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C426	2610105	TANTALUM CAP.	100 U	20 % 10 V 7.3X4.3X2.9
C427	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C428	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C429	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C430	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C431	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C432	2517680	ELECTROL. CAP.	4.7 U	20 % 35 V 4.5X4.5X5.5
C433	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C434	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C435	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C436	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C437	2517850	ELECTROL. CAP.	220 U	20 % 35 V 10X10
C450	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C451	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C500	2320120	CERAMIC CAP.	22 N	10 % 25 V 0603
C501	2320079	CERAMIC CAP.	680 P	5 % 50 V 0603
C502	2320120	CERAMIC CAP.	22 N	10 % 25 V 0603
C503	2517803	ELECTROL. CAP.	100 U	20 % 16 V 8X6.3
C504	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C505	2320067	CERAMIC CAP.	220 P	5 % 50 V 0603
C506	2320131	CERAMIC CAP.	33 N	10 % 16 V 0603
C507	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C508	2320131	CERAMIC CAP.	33 N	10 % 16 V 0603
C509	2320067	CERAMIC CAP.	220 P	5 % 50 V 0603
C510	2320067	CERAMIC CAP.	220 P	5 % 50 V 0603
C511	2320131	CERAMIC CAP.	33 N	10 % 16 V 0603

C512	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C513	2320131	CERAMIC CAP.	33 N	10 % 16 V 0603
C514	2320067	CERAMIC CAP.	220 P	5 % 50 V 0603
C515	2320120	CERAMIC CAP.	22 N	10 % 25 V 0603
C516	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C517	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C518	2517803	ELECTROL. CAP.	100 U	20 % 16 V 8X6.3
C519	2320120	CERAMIC CAP.	22 N	10 % 25 V 0603
C520	2320067	CERAMIC CAP.	220 P	5 % 50 V 0603
C521	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C522	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C523	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C524	2517850	ELECTROL. CAP.	220 U	20 % 35 V 10X10
C525	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C600	2604093	TANTALUM CAP.	2.2 U	20 % 35 V 6.0X3.2X2.5
C601	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C603	2320067	CERAMIC CAP.	220 P	5 % 50 V 0603
C604	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C605	2320043	CERAMIC CAP.	22 P	5 % 50 V 0603
C606	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C607	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C608	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C609	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C610	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C611	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C612	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C613	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C614	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C615	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C616	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C617	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C618	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C619	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C620	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C621	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C622	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C623	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C624	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C625	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C626	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C627	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C628	2315011	CHIP ARRAY NP0 4X22P K 16V	0612	
C650	2310781	CERAMIC CAP.	220 N	10 % 16 V 0805
C651	2310781	CERAMIC CAP.	220 N	10 % 16 V 0805
C652	2310781	CERAMIC CAP.	220 N	10 % 16 V 0805
C653	2310781	CERAMIC CAP.	220 N	10 % 16 V 0805
C654	2310781	CERAMIC CAP.	220 N	10 % 16 V 0805
C655	2310781	CERAMIC CAP.	220 N	10 % 16 V 0805
C700	2611689	TANTALUM CAP.	470 U	20 % 10 V 7.3X4.3X4.1

## Parts Lists

## Technical Documentation

C701	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C702	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C703	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C704	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C705	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C706	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C707	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C708	2320131	CERAMIC CAP.	33 N	10 % 16 V 0603
C709	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C710	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C711	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C712	2312403	CERAMIC CAP.	2.2 U	10 % 10 V 1206
C713	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C714	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C715	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C716	2320033	CERAMIC CAP.	8.2 P	0.25 % 50 V 0603
C717	2320047	CERAMIC CAP.	33 P	5 % 50 V 0603
C718	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C720	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C723	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C724	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C725	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C727	2320011	CERAMIC CAP.	1.0 P	0.25 % 50 V 0603
C728	2320011	CERAMIC CAP.	1.0 P	0.25 % 50 V 0603
C729	2312403	CERAMIC CAP.	2.2 U	10 % 10 V 1206
C730	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C731	2320779	CERAMIC CAP.	100 N	10 % 16 V 0603
C732	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C733	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C734	2310781	CERAMIC CAP.	220 N	10 % 16 V 0805
C735	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C736	2320083	CERAMIC CAP.	1.0 N	5 % 50 V 0603
C737	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C738	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C739	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C750	2320053	CERAMIC CAP.	56 P	5 % 50 V 0603
C800	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C801	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C802	2320131	CERAMIC CAP.	33 N	10 % 16 V 0603
C803	2320131	CERAMIC CAP.	33 N	10 % 16 V 0603
C804	2312401	CERAMIC CAP.	1.0 U	10 % 10 V 0805
C807	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C809	2320131	CERAMIC CAP.	33 N	10 % 16 V 0603
C810	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C812	2320131	CERAMIC CAP.	33 N	10 % 16 V 0603
C814	2320059	CERAMIC CAP.	100 P	5 % 50 V 0603
C816	2610003	TANTALUM CAP.	10 U	20 % 10 V 3.2X1.6X1.6
C818	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C819	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603

C820	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C821	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C822	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C823	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C824	2320107	CERAMIC CAP.	10 N	5 % 50 V 0603
C828	2320120	CERAMIC CAP.	22 N	10 % 25 V 0603
L001	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L003	3641282	CHIP COIL	2. Q U	5 % Q=30/7.96 MHZ
L005	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L006	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L007	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L008	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L009	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L010	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L011	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L012	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L013	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L014	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L015	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L016	3641262	FERRITE BEAD 30R/100MHZ 2A	1206	
L100	3641622	CHIP COIL	220 N	5 % Q=30/100 MHZ
L101	3641546	CHIP COIL	82.Q N	10 % Q=40/150 MHZ
L102	3645031	CHIP COIL	330 N	10 % Q=20/25 MHZ
L104	3641548	CHIP COIL	100 N	10 % Q=40/150 MHZ
L105	3641560	CHIP COIL	220 N	10 % Q=30/100 MHZ
L106	3643039	CHIP COIL	220 N	5 % Q=35/100 MHZ
L107	3641548	CHIP COIL	100 N	10 % Q=40/150 MHZ
L108	3645131	CHIP COIL	8. Q N	5 % Q=8/100M 0603
L109	3645031	CHIP COIL	330 N	10 % Q=20/25 MHZ
L200	3640051	CHIP COIL	12.Q N	5 % Q=45/250 MHZ
L201	3643061	CHIP COIL	1.0N N	Q=88/1700M 0805
L202	3643061	CHIP COIL	1.0N N	Q=88/1700M 0805
L203	3645031	CHIP COIL	330 N	10 % Q=20/25 MHZ
L204	3645031	CHIP COIL	330 N	10 % Q=20/25 MHZ
L250	3641521	CHIP COIL	6. Q N	5 % Q=50/250 MHZ
L251	3645123	CHIP COIL	10 N	5 % Q=31/800M 0603
L252	3645001	CHIP COIL	4. Q N	10 % Q=10/100 MHZ
L300	3645121	CHIP COIL	6. Q N	5 % Q=32/800M 0603
L301	3641540	CHIP COIL	47.Q N	20 % Q=40/200 MHZ
L302	3641542	CHIP COIL	56.Q N	10 % Q=40/200 MHZ
L303	3640053	CHIP COIL	4.-0 N	Q=8/100 0603
L400	3643067	CHIP COIL	100 U	5 % Q=15/796 KHZ
L500	3643067	CHIP COIL	100 U	5 % Q=15/796 KHZ
L702	3641282	CHIP COIL	2. Q U	5 % Q=30/7.96 MHZ
B701	4510237	CRYSTAL	32.768 K	+/-20PPM 12.5PF
G300	4510247	VCTCXO 13.0 M	+/-5PPM 2.8V GSM	
G301	4350125	VCO 1006-1031MHZ 2.8V 10MA GSM ET		
Z001	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603		
Z002	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603		

## Parts Lists

## Technical Documentation

Z004	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z005	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z006	3648808	CHIP COIL 10.Q U 10 % Q=50 1206
Z080	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z081	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z082	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z083	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z084	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z085	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z086	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z087	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z088	3640035	FILT Z>450R/100M 0R7MAX 0.2A 0603
Z100	4512001	DUPL 890-915/935-960MHZ
Z101	4511017	SAW FILTER
Z102	4510137	SAW FILTER
Z103	4510009	CER.FILT 13+-0.09MHZ
Z250	4511015	SAW FILTER
Z650	3648808	CHIP COIL 10.Q U 10 % Q=50 1206
V001	4113915	TRANS. SUPR.
V002	4110396	ZENER DIODE
V100	4210074	TRANSISTOR
V101	4219922	TRANSISTOR X 2
V102	4210074	TRANSISTOR BFP420 NPN 4. V SOT343
V250	4100285	DIODE X 2BAV99 70 V 200 MA SER.SOT23
V251	4200917	TRANSISTOR BC848B/BCW32NPN 30 V 100 MA
V252	4110014	SCH. DIODE X 2BAS70-07 70V 15MA
V253	4219922	TRANSISTOR X 2
V254	4210010	TRANSISTOR BFP183 NPN 12V 65MA
V300	4210010	TRANSISTOR BFP183 NPN 12V 65MA
V301	4210066	TRANSISTOR BFR93AW NPN 12V 35MA
V302	4110018	CAP. DIODE BB135 30V SOD323
V303	4210010	TRANSISTOR BFP183 NPN 12V 65MA
V400	4211601	MOSFET X2 NDS8947 P-CH 30V 30V4 A SO8
V401	4110028	TRANS. SUPR. 16V 23A 600W DO214AA
V402	4115811	SCHOTTKY DIODE RB491D 20V 1A SC59
V403	4200917	TRANSISTOR BC848B/BCW32 NPN 30V 100 MA
V404	4210096	TRANSISTOR BCP54 NPN 45V 1.5A SOT223
V405	4110014	SCH. DIODE X 2 BAS70-07 70V 15MA SOT143
V406	4200917	TRANSISTOR BC848B/BCW32 NPN 30V 100MA
V407	4200917	TRANSISTOR BC848B/BCW32 NPN 30V 100MA
V408	4200917	TRANSISTOR BC848B/BCW32 NPN 30V 100MA
V450	4108639	DIODE X 2 BAS28 75V 250MA
V451	4200836	TRANSISTOR BCX19 NPN 50V 0.5A
V452	4200917	TRANSISTOR BC848B/BCW32 NPN 30V 100MA
V453	4200909	TRANSISTOR BC858B/BCW30 PNP 30V 100MA
V454	4200603	TRANSISTOR BCX17 PNP 45V 500MA
V455	4200917	TRANSISTOR BC848B/BCW32 NPN 30V 100MA
V456	4100278	DIODE X 2 BAV70 70V 200MA COMCAT.SOT23
V457	4101653	DIODE BYD17D 20V 1.5A SOD87



V458	4101653	DIODE	BYD17D	200V 1.5A	SOD87
V600	4100278	DIODE X 2	BAV70	70V 200MA	COMCAT
V601	4110014	SCH. DIODE X 2	BAS70-07	70V 15MA	SOT143
V602	4200909	TRANSISTOR	BC858B/BC W30	PNP 30V 100MA	
V603	4200917	TRANSISTOR	BC848B/BCW32	NPN 30 V 100 MA	
V701	4210215	TRANSISTOR	MMBT589	PNP 30V 1A	
V702	4110067	SCHOTTKY DIODE	MBR0520L	20V 0.5A	SOD123
V703	4113651	TRANS. SUPR.	QUAD	6V	SOT23-5
V704	4200917	TRANSISTOR	BC848B/BCW32	NPN 30V 100MA	
V705	4110014	SCH. DIODE X 2	BAS70-07	70V 15MA	
V706	4110014	SCH. DIODE X 2	BAS70-07	70V 15MA	
V707	4200917	TRANSISTOR	BC848B/BCW32	NPN 30V 10MA	
V708	4200917	TRANSISTOR	BC848B/BCW32	NPN 30V 10 MA	
V750	4102998	LED	GREEN	2.2 V	1206
V751	4102998	LED	GREEN	2.2 V	1206
D600	4370551	MAD2 ROM4	V27 F731929H	C07	TQFP
D601	4342264	IC, EEPROM			
D602	4340509	IC, FLASH MEM.			
D603	4340397	IC, SRAM			
D700	4340687	SN74LVC08A	4X 2-INPUT	AND	
D701	4340575	IC, 2XRETRIG.	MULTIVIBR		
D702	4340156	IC, 2XD-FF	+EDGE-TR.+RES.	SO1	
N100	4350085	SLM-090A	MIXER	700-1000MHZ	
N101	4370273	PLUSSA5	WFD146ET64T		
N200	4370253	CRFU1A	RX+TX UHF	GSM V5	
N250	4340647	IC, 4XOPAMP	3-44V	4.5M	
N254	4350037	IC, POW.AMP.	12V 23W	GSM	
N400	4340067	IC, REGULATOR	LP2951	3.3 V 100MA	
N401	4340641	IC, REGULATOR	LM2937	8 V 500MA	
N402	4340067	IC, REGULATOR	LP2951	3.3V 100MA	
N403	4340028	IC, 2 X COMP.	TLC393	SO8S	
N500	4340677	TPA1517	AUDIO POWER	6W/C AMP	
N501	4340693	TS922	2X OP AMP	80MA 2.7-12V	
N502	4301182	IC, 2 X OP.AMP.	LM2902	SO14S	
N600	4340067	IC, REGULATOR	LP2951	3.3 V 100 MA	
N650	4340501	MAX3237EAI	RS232	5TX3RX	
N700	4370479	CCONT2I	WFD163KT64T		TQFP64
N701	4340071	IC, REGULATOR	LP2980	3V 50MA	SSO5
N800	4370363	COBBA_GJ	B09 BB ASIC		TQFP64
S250	4340085	IC, 1XBILATERAL	SWITCH	SSO5	
S251	4340085	IC, 1XBILATERAL	SWITCH	SSO5	
X001	5400141	CONN 2X16	HEADER	P2.54	90DEGREE
X080	5430009	D9 CONN	F 90DEG	BOARDLOCK	UNC4-40
X240	5420011	CONNECTOR	MINI UHF	90'DEG	<2.5GHZ
X750	5400033	SIM CARD	READER	CCM04-5003	6POL
X914	5431718	FLEXFOIL	CONNECT	1X30	0.5MM SMD
A300	9517012	SM, D RF	SHIELD	DMC00422	HD940 UP8
	9854379	PCB	GM8B	106.5X165.0X1.75	M8 1/PA

## Handset

### AH89 (0201345)

(EDMS V 6.0)

Item	Code	Description	Value	Type
R101	1430065	Chip resistor	10 k	5 % 0.063 W 0603
R102	1430065	Chip resistor	10 k	5 % 0.063 W 0603
R103	1430167	Chip resistor	47	5 % 0.063 W 0603
R104	1430087	Chip resistor	100 k	5 % 0.063 W 0603
R105	1430061	Chip resistor	511 k	1 % 0.063 W 0603
R106	1430219	Chip resistor	68 k	1 % 0.063 W 0603
R107	1430051	Chip resistor	4.7 k	5 % 0.063 W 0603
R108	1430065	Chip resistor	10 k	5 % 0.063 W 0603
R109	1430331	Chip resistor	26.1 k	1 % 0.063 W 0603
R110	1430085	Chip resistor	82 k	5 % 0.063 W 0603
R111	1430031	Chip resistor	100 k	1 % 0.063 W 0603
R112	1430031	Chip resistor	100 k	1 % 0.063 W 0603
R200	1430167	Chip resistor	47	5 % 0.063 W 0603
R201	1430167	Chip resistor	47	5 % 0.063 W 0603
R202	1415230	Melf resistor	11 k	1 % 0.2 W 0204
R204	1825001	Chip varistor vwm18v vc40v		0603
R205	1430159	Chip resistor	22	5 % 0.063 W 0603
R206	1620017	Res network 0w06 2x100r j		0404
R207	1825001	Chip varistor vwm18v vc40v		0603
R208	1825001	Chip varistor vwm18v vc40v		0603
R209	1430167	Chip resistor	47	5 % 0.063 W 0603
R211	1415230	Melf resistor	11 k	1 % 0.2 W 0204
R212	1430167	Chip resistor	47	5 % 0.063 W 0603
R213	1430095	Chip resistor	220 k	5 % 0.063 W 0603
R214	1430159	Chip resistor	22	5 % 0.063 W 0603
R215	1430095	Chip resistor	220 k	5 % 0.063 W 0603
R216	1416160	Melf resistor	100 k	1 % 0.2 W 0204
R217	1430039	Chip resistor	1.5 k	5 % 0.063 W 0603
R218	1430159	Chip resistor	22	5 % 0.063 W 0603
R219	1430167	Chip resistor	47	5 % 0.063 W 0603
R220	1430013	Chip resistor	330	5 % 0.063 W 0603
R221	1825001	Chip varistor vwm18v vc40v		0603
R222	1430087	Chip resistor	100 k	5 % 0.063 W 0603
R223	1825001	Chip varistor vwm18v vc40v		0603
R224	1430071	Chip resistor	22 k	5 % 0.063 W 0603
R225	1430129	Chip resistor	5.6 k	1 % 0.063 W 0603
R226	1825001	Chip varistor vwm18v vc40v		0603
R227	1430087	Chip resistor	100 k	5 % 0.063 W 0603
R228	1430013	Chip resistor	330	5 % 0.063 W 0603
R229	1430159	Chip resistor	22	5 % 0.063 W 0603
R230	1430167	Chip resistor	47	5 % 0.063 W 0603
R231	1430039	Chip resistor	1.5 k	5 % 0.063 W 0603

R232	1416160	Melf resistor	100 k	1 % 0.2 W 0204
R300	1430065	Chip resistor	10 k	5 % 0.063 W 0603
R301	1620019	Res network 0w06	2x10k j	0404
R302	1430001	Chip resistor	100	5 % 0.063 W 0603
R303	1620023	Res network 0w06	2x47k j	0404
R304	1620019	Res network 0w06	2x10k j	0404
R305	1430001	Chip resistor	100	5 % 0.063 W 0603
R306	1620041	Res network 0w03	4x10k j	0804
R307	1430001	Chip resistor	100	5 % 0.063 W 0603
R308	1430065	Chip resistor	10 k	5 % 0.063 W 0603
R309	1430001	Chip resistor	100	5 % 0.063 W 0603
R310	1430001	Chip resistor	100	5 % 0.063 W 0603
R311	1620003	Res network 0w03	4x100r j	0804
R312	1620003	Res network 0w03	4x100r j	0804
R313	1620003	Res network 0w03	4x100r j	0804
R400	1620025	Res network 0w06	2x100k j	0404
R401	1430087	Chip resistor	100 k	5 % 0.063 W 0603
R402	1620019	Res network 0w06	2x10k j	0404
R403	1620019	Res network 0w06	2x10k j	0404
R404	1430087	Chip resistor	100 k	5 % 0.063 W 0603
R405	1825001	Chip varistor vwm18v	vc40v	0603
R406	1430087	Chip resistor	100 k	5 % 0.063 W 0603
R407	1620019	Res network 0w06	2x10k j	0404
R408	1620019	Res network 0w06	2x10k j	0404
R409	1430151	Chip resistor	10	5 % 0.1 W 0603
R410	1825001	Chip varistor vwm18v	vc40v	0603
R411	1825001	Chip varistor vwm18v	vc40v	0603
R414	1430151	Chip resistor	10	5 % 0.1 W 0603
R415	1430065	Chip resistor	10 k	5 % 0.063 W 0603
R416	1430001	Chip resistor	100	5 % 0.063 W 0603
R417	1430001	Chip resistor	100	5 % 0.063 W 0603
R418	1430065	Chip resistor	10 k	5 % 0.063 W 0603
R419	1430001	Chip resistor	100	5 % 0.063 W 0603
R420	1430035	Chip resistor	1.0 k	5 % 0.063 W 0603
R421	1430035	Chip resistor	1.0 k	5 % 0.063 W 0603
R422	1620023	Res network 0w06	2x47k j	0404
R423	1430159	Chip resistor	22	5 % 0.063 W 0603
R424	1430159	Chip resistor	22	5 % 0.063 W 0603
R425	1430013	Chip resistor	330	5 % 0.063 W 0603
R426	1430013	Chip resistor	330	5 % 0.063 W 0603
R430	1430122	Chip resistor	4.7 M	5 % 0.063 W 0603
C100	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C101	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C102	2320801	Ceramic cap.		Y5 V 0603
C103	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C104	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C105	2340014	Ceramic cap.	47 n	10 % 25 V 0805
C106	2312296	Ceramic cap.		Y5 V 1210
C107	2320107	Ceramic cap.	10 n	5 % 50 V 0603

## Parts Lists

## Technical Documentation

C108	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C109	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C110	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C111	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C112	2610103	Tantalum cap.	100 u	20 % 16 V 7.3x4.3x4.1
C113	2610103	Tantalum cap.	100 u	20 % 16 V 7.3x4.3x4.1
C114	2312401	Ceramic cap.	1.0 u	10 % 10 V 0805
C115	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C116	2310003	Ceramic cap.	470 n	10 % 16 V 0805
C117	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C118	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C119	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C120	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C121	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C122	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C123	2611697	Tantalum cap.	33 u	20 % 10 V 6.0x3.2x2.6
C124	2312401	Ceramic cap.	1.0 u	10 % 10 V 0805
C200	2320083	Ceramic cap.	1.0 n	5 % 50 V 0603
C201	2310781	Ceramic cap.	220 n	10 % 16 V 0805
C202	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C203	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C204	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C205	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C206	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C207	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C208	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C209	2320059	Ceramic cap.	100 p	5 % 50 V 0603
C210	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C211	2610003	Tantalum cap.	10 u	20 % 10 V 3.2x1.6x1.6
C212	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C213	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C214	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C215	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C216	2340014	Ceramic cap.	47 n	10 % 25 V 0805
C217	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C218	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C219	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C220	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C221	2320059	Ceramic cap.	100 p	5 % 50 V 0603
C222	2310781	Ceramic cap.	220 n	10 % 16 V 0805
C223	2320083	Ceramic cap.	1.0 n	5 % 50 V 0603
C224	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C225	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C226	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C227	2611697	Tantalum cap.	33 u	20 % 10 V 6.0x3.2x2.6
C228	2610003	Tantalum cap.	10 u	20 % 10 V 3.2x1.6x1.6
C229	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C230	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C231	2611697	Tantalum cap.	33 u	20 % 10 V 6.0x3.2x2.6

C232	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C233	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C234	2312403	Ceramic cap.	2.2 u	10 % 10 V 1206
C235	2320120	Ceramic cap.	22 n	10 % 25 V 0603
C236	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C237	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C238	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C239	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C240	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C241	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C242	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C243	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C244	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C245	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C246	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C247	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C248	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C249	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C250	2320091	Ceramic cap.	2.2 n	5 % 50 V 0603
C251	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C252	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C253	2320120	Ceramic cap.	22 n	10 % 25 V 0603
C254	2312403	Ceramic cap.	2.2 u	10 % 10 V 1206
C255	2320063	Ceramic cap.	150 p	5 % 50 V 0603
C256	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C300	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C301	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C302	2320059	Ceramic cap.	100 p	5 % 50 V 0603
C303	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C304	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C305	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C306	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C307	2312401	Ceramic cap.	1.0 u	10 % 10 V 0805
C308	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C309	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C310	2312401	Ceramic cap.	1.0 u	10 % 10 V 0805
C311	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C312	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C313	2312401	Ceramic cap.	1.0 u	10 % 10 V 0805
C314	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C315	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C316	2312401	Ceramic cap.	1.0 u	10 % 10 V 0805
C317	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C318	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C319	2312401	Ceramic cap.	1.0 u	10 % 10 V 0805
C320	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C321	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C322	2312401	Ceramic cap.	1.0 u	10 % 10 V 0805
C323	2320043	Ceramic cap.	22 p	5 % 50 V 0603

## Parts Lists

## Technical Documentation

C324	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C325	2312401	Ceramic cap.	1.0 u	10 % 10 V 0805
C400	2320801	Ceramic cap.		Y5 V 0603
C402	2320801	Ceramic cap.		Y5 V 0603
C403	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C404	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C405	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C406	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C407	2320083	Ceramic cap.	1.0 n	5 % 50 V 0603
C408	2320059	Ceramic cap.	100 p	5 % 50 V 0603
C409	2320059	Ceramic cap.	100 p	5 % 50 V 0603
C410	2320049	Ceramic cap.	39 p	5 % 50 V 0603
C411	2320801	Ceramic cap.		Y5 V 0603
C412	2320107	Ceramic cap.	10 n	5 % 50 V 0603
C413	2309570	Ceramic cap.		Y5 V 1206
C414	2309570	Ceramic cap.		Y5 V 1206
C415	2320801	Ceramic cap.		Y5 V 0603
C416	2320801	Ceramic cap.		Y5 V 0603
C417	2320801	Ceramic cap.		Y5 V 0603
C418	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C419	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C420	2320043	Ceramic cap.	22 p	5 % 50 V 0603
C421	2320059	Ceramic cap.	100 p	5 % 50 V 0603
C422	2320801	Ceramic cap.		Y5 V 0603
L100	3203705	Ferrite bead 0.015r 42r/100m		0805
L101	3203705	Ferrite bead 0.015r 42r/100m		0805
L200	3641282	Chip coil 2. Q u	5 % Q=30/7.96 MHz	1008
L201	3640459	Choke 3. u	20 % 1.2 A SMD	
L202	3641282	Chip coil 2. Q u	5 % Q=30/7.96 MHz	1008
B300	4510155	Crystal 14.7456 M		+/-50PPM
Z100	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z101	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z102	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z103	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z104	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z200	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z201	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z202	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z203	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z204	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z205	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z300	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z301	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z302	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z303	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z304	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z305	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z306	3640035	Filt z>450r/100m 0r7max 0.2a		0603
Z307	3640035	Filt z>450r/100m 0r7max 0.2a		0603

Z400	3640035	Filt z>450r/100m 0r7max 0.2a 0603		
H400	485R003	Gd42 lcd module 84x48 fulldotmx		
V100	4210096	TransistorBCP54 npn 45V 1. A SOT223		
V101	4200909	TransistorBC858B/BCW30 pnp 30V 100mA SOT23		
V300	4219902	Transistor x 2	SOT363	
V301	4219902	Transistor x 2	SOT363	
V400	4219914	Transistor x 2	SOT363	
V401	4211231	MosFet	SOT23	
V402	4110014	Sch. diode x 2	BAS70-07 70V 15mA SOT143	
V403	4110014	Sch. diode x 2	BAS70-07 70V 15mA SOT143	
V404	4860005	Led	Green	0603
V405	4860005	Led	Green	0603
V406	4860005	Led	Green	0603
V407	4864388	Led	Green	0603
V408	4864388	Led	Green	0603
V409	4864388	Led	Green	0603
V410	4860005	Led	Green	0603
V411	4860005	Led	Green	0603
V412	4860005	Led	Green	0603
V413	4864388	Led	Green	0603
V414	4864388	Led	Green	0603
V415	4864388	Led	Green	0603
V416	4860005	Led	Green	0603
V417	4860005	Led	Green	0603
V418	4860005	Led	Green	0603
V419	4864388	Led	Green	0603
V420	4864388	Led	Green	0603
V421	4864388	Led	Green	0603
V422	4217070	Transistor x 2		IMD
V423	4217070	Transistor x 2		IMD
D300	4370541	IC, MCU	TQFP120	
D301	4346010	IC, SRAM	32kx8 bit 70 ns TSOP28	
D400	4340547	Sn74ahc125 quad bus buff	TSSOP14	
D401	4340549	Sn74ahc244 octal buff/dri	TSSOP20	
N100	4301062	IC, regulator	LP2951AC	SO8S
N101	4309664	555 timer analog 2-18v cmos	SO8	
N102	4340691	IC, comp 2.7-5v	LMV331M5X	SOT23-5
N103	4340097	S-81230sg reg 3.0v 2% 100ma	SSO5	
N200	4340331	IC, Power amp.	LM4862 P W	SO8S
N201	4301199	IC, 2 x op.amp.	LM2904	SO8S
N202	4340693	Ts922 2x op amp 80ma 2.7-12v	SO8	
N400	4340699	IC, e6779 hall sw 14mt	TLE4905G	SOT89
X200	540Y114	Use code 5409115		
	9854369	PCB AH89 154.6X45.5X1.0 M6 3/PA		