

No	Terminal Name	I/O	Description	P.OFF	P.Failure	Reset/ Release												
82	EX.FF/REW (L)	O	<p>Control signal filter select terminal in FF/REW mode. *During FF/REW: Hi-Z *Except FF/REW: Low</p> <div><p>VR MODE POSITION PNO</p><table><tr><td>STOP</td><td>FF/REW</td><td>STOP</td><td>PLAY</td></tr><tr><td>STOP</td><td>FF/REW</td><td>STOP</td><td>PLAY</td></tr><tr><td>00</td><td>21 00 26</td><td>27 28</td><td>00</td></tr></table><p>EX.FF/REW(L) Hi-Z Low Hi-Z</p><p>VTR MODE</p></div> <p>*Refer to FF/REW (Hi-z) output timing of the Z-mechanism regarding to control spec. of this terminal. *When the unit becomes into FF/REW mode , the input is set. *In STOP mode, the setting is released after shift to STOP3 for control of STOP. However, if the CTL amp gain is 5 (=60dB) or 7 (=70dB) when starting of FF/REW, Low is output compulsorily automatically.</p>	STOP	FF/REW	STOP	PLAY	STOP	FF/REW	STOP	PLAY	00	21 00 26	27 28	00	Low	Low	Low
STOP	FF/REW	STOP	PLAY															
STOP	FF/REW	STOP	PLAY															
00	21 00 26	27 28	00															
83	A.DUB (H)	O	A.DUB or A.DUB PAUSE: High is output Other Than Above: Low is output	Low	Low	Low												
84	FULL ERASE	O	FULL ERASE HEAD ON/OFF control terminal. During REC: Low is output Other than above: High is output	In	In	In												
85	GND	I	Low fix.	In	In	In												
86	FG.AMP.OUT	O	Output terminal for the Capstan FG AMP signal.	Out	Out	Out												
87	FG.AMP.IN	I	Input terminal for the Capstan FG AMP signal.	In	In	In												
88	GND(A)	-	GND for Analogue circuit.	-	-	-												
89	NC	I	Connected to GND.	In	In	In												
90	CYL.PFG	I	Input terminal for the Cylinder PG/FG.	In	In	In												
91	OREF	O	1/2 VDD reference voltage output terminal for the Analogue AMP.	Out	Out	Out												
92	IREF	I	1/2 VDD reference voltage input terminal for the Analogue AMP.	In	In	In												
93	GND	I	GND	In	In	In												
94	CTL.HEAD(-)	I/O	I/O terminal for the Control head (-)	In/Out	In/Out	In/Out												
95	CTL.HEAD(+)	I/O	I/O terminal for the Control head (+)	In/Out	In/Out	In/Out												
96	CTL.AMP.REF	I	Capacitor connection terminal for reference of the control AMP.	In	In	In												
97	PB.CTL.OUT	O	Output terminal for the Control AMP.	Out	Out	Out												
98	5V(A)	-	Power supply terminal for Analogue AMP.	-	-	-												
99	5V(AD)	-	Reference power supply terminal for the AD/8bit DA	-	-	-												
100	NORM/SERV/T2/TEST	O	<p>Factory mode/ Service mode setting terminal.</p> <table><tr><td>Input Voltage</td><td>Mode</td></tr><tr><td>Over 4.0V</td><td>Normal</td></tr><tr><td>Over 2.0V and less than 4.0V</td><td>Service</td></tr><tr><td>Over 1.0V and less than 2.5V</td><td>Test 2</td></tr><tr><td>Less than 1.0V</td><td>Test 1</td></tr></table>	Input Voltage	Mode	Over 4.0V	Normal	Over 2.0V and less than 4.0V	Service	Over 1.0V and less than 2.5V	Test 2	Less than 1.0V	Test 1	In	In	In		
Input Voltage	Mode																	
Over 4.0V	Normal																	
Over 2.0V and less than 4.0V	Service																	
Over 1.0V and less than 2.5V	Test 2																	
Less than 1.0V	Test 1																	