

Pin No.	In/Out	Port Name	Function																
1	I	P.FAIL.IN(L)	Power failure detection input.																
2	O	SP(L)	This port supplies low during SP mode.																
3	I	S.REEL.PULSE	Supply reel pulse input.																
4	I	T.REEL.PULSE	Take-up reel pulse input.																
5	I	I.R.	Remote Controller pulse input.																
6	O	OSD REC1	OSD REC control output.																
7	O	OSD REC1	OSD REC control output.																
8	O	FM MUTE(H)	Hi-Fi audio mute control output.																
9	O	VIDEO EE(H)	EE:Low VV:High																
10	O	FL DRV CS(L)	FIP driver chip selection.																
11	O	SQ PB(H)	This port is high during S-VHS playback mode.																
12	O	VTR(H)/TV(L)	VTR/TV mode switching control.																
13	O	CH H/L	Channel switching control.																
14	O	IC.CLK	FIP driver serial clock output.																
15	I	IC.LSN	FIP driver serial data input.																
16	O	IC.TLK	FIP driver serial data output.																
17	O	IIC.TALK/LSN	IIC serial data in/output																
18	O	IIC.CLK	IIC serial clock output																
19	I	N.C.	Not used																
20	O	HALF WAVE(H)	Capstan torque switching control. 1. FF/REW Mode Capstan rotation speed is 1300 rpm or more without VHS-C cassette:High Capstan rotation speed is less than 1300 rpm without VHS-C cassette:High impedance VHS-C cassette:High imedance 2. Except FF/REW Mode:High impedance																
21	O	CURRENT LIMIT	Capstan motor current limitter output.																
22	O	CAP R/F	Capstan rotation direction control. Reverse : High Forward : Low																
23	O	VIDEO H.SW	Video head switching signal output.																
24	O	ART V/H/N	This port supplies artificial vertical sync signal to stabilize the picture in special playback mode.																
25	I	RESET(L)	This port is low during reset.																
26	O	D.A.REC(H)	Audio signal recording on/off control.																
27	O	D.REC(H)	Video signal recording on/off control.																
28	O	CUR. EMPH(H)	This port supplies high during a certain time from starting the recording. <table border="1"> <thead> <tr> <th>REC MODE</th><th>OUTPUT TIMING</th><th>REC MODE</th><th>OUTPUT TIMING</th></tr> </thead> <tbody> <tr> <td>NTSC 2H</td><td>6 sec</td><td>PAL 3H</td><td>9 sec</td></tr> <tr> <td>NTSC 4H</td><td>12 sec</td><td>---</td><td>---</td></tr> <tr> <td>NTSC 6H</td><td>18 sec</td><td>PAL 6H</td><td>18 sec</td></tr> </tbody> </table>	REC MODE	OUTPUT TIMING	REC MODE	OUTPUT TIMING	NTSC 2H	6 sec	PAL 3H	9 sec	NTSC 4H	12 sec	---	---	NTSC 6H	18 sec	PAL 6H	18 sec
REC MODE	OUTPUT TIMING	REC MODE	OUTPUT TIMING																
NTSC 2H	6 sec	PAL 3H	9 sec																
NTSC 4H	12 sec	---	---																
NTSC 6H	18 sec	PAL 6H	18 sec																
29	O	128Hz	Oscillator output for main clock adjustment.																
30	O	FULL ERASE(L)	Full erase on/off control. ON:Low OFF:High																
31	O	BIAS(L)	Audio signal recording on/off control.																
32	O	A H SW	Audio head switching signal output.																
33	O	CAP ET	Capstan torque control.																
34	O	CYL ET	Cylinder torque control.																
35	I	N.C.	Not used																