

SYSTEM CONTROL & SERVO ICs DC VOLTAGE CHART (SP MODE)

Ref. No. MODE	IC2501																			
	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16				
STOP	15.1	15.1	15.3	1.0	5.0	1.1	1.1	0.5	2.5	1.4	0	3.8	3.8	3.8	0	15.1				
PLAY	15.0	15.0	15.3	1.0	5.0	1.1	1.1	0.5	2.4	1.4	0	3.8	3.8	3.8	0	15.0				
REC	15.0	15.0	15.3	1.0	5.0	1.1	1.1	0.5	2.4	1.4	0	3.8	3.8	3.8	0	15.0				
F.F	14.7	14.7	15.1	1.0	5.0	1.1	1.1	0.5	2.4	1.4	0	3.8	3.8	3.8	0	14.7				
REW	14.7	14.7	15.1	1.0	5.0	1.1	1.1	0.5	2.4	1.4	0	3.8	3.8	3.8	0	14.7				
Ref. No. MODE	IC6001																			
	1	2	3	4	5	6	7	8	9	10	11	12	13	14	15	16	17	18	19	20
STOP	5.0	0	5.2	3.9	5.0	5.0	0	0.2	5.0	3.4	0	0	0	4.7	4.5	4.5	3.9	3.9	0	0
PLAY	5.0	0	2.5	2.5	5.0	5.0	0	0.2	0	3.1	0	0	0	4.6	4.4	4.4	3.9	3.8	0	0.4
REC	5.0	0	2.5	2.5	5.0	5.0	0	0.2	5.0	3.1	0	0	0	4.6	4.4	4.4	3.8	3.8	0	0.4
F.F	5.0	0	2.5	2.5	5.0	5.0	0	0.2	5.0	2.7	0	0	0	4.6	4.2	4.2	3.7	3.6	0	4.8
REW	5.0	0	2.5	2.5	5.0	5.0	0	0.2	5.0	2.7	0	0	0	4.6	4.2	4.2	3.7	3.6	0	4.8
Ref. No. MODE	IC6001																			
	21	22	23	24	25	26	27	28	29	30	31	32	33	34	35	36	37	38	39	40
STOP	0	0	2.5	0	5.0	0	0	0	2.5	5.0	5.0	0	0	2.5	0	5.0	2.6	2.6	0	2.6
PLAY	4.0	0	2.5	0	5.0	0	0	0	2.5	5.0	5.0	0	2.5	2.4	0	5.0	2.6	2.6	0	2.6
REC	4.0	0	2.5	0	5.0	4.9	5.0	0	2.5	0.2	0.2	0	2.5	2.4	0	5.0	2.6	2.6	0	2.6
F.F	4.9	0	2.5	0	5.0	0	0	0	2.5	5.0	5.0	0	5.0	2.4	0	5.0	2.6	2.6	0	2.6
REW	4.9	5.0	2.5	0	5.0	0	0	0	2.5	5.0	5.0	0	5.0	2.4	0	5.0	2.6	2.6	0	2.5
Ref. No. MODE	IC6001																			
	41	42	43	44	45	46	47	48	49	50	51	52	53	54	55	56	57	58	59	60
STOP	2.7	5.0	0	0	0	5.0	1.9	0	1.9	1.7	5.1	2.5	2.6	0.7	0.1	0	0	0	4.3	0
PLAY	2.7	5.0	0	0	0	5.0	1.9	0	1.9	2.3	5.1	2.5	2.6	1.1	0.1	0	0	0	4.3	0
REC	2.7	5.0	0	0	0	5.0	1.9	0	1.9	1.7	5.1	2.5	2.6	1.2	0.1	0	0	0	4.3	0
F.F	2.7	5.0	0	0	0	5.0	1.9	0	1.9	2.1	5.1	2.5	2.6	0.9	0.3	0	0	0	3.8	0
REW	2.7	5.0	0	0	0	5.0	1.9	0	1.9	2.1	5.1	2.5	2.6	0.4	0.2	0	0	0	3.8	0
Ref. No. MODE	IC6001																			
	61	62	63	64	65	66	67	68	69	70	71	72	73	74	75	76	77	78	79	80
STOP	0	0.1	0	0	1.0	0	2.5	2.5	2.5	2.5	0	2.5	5.0	2.5	2.5	2.5	0	4.9	1.6	0
PLAY	5.0	0.1	0	0	1.0	0	2.5	2.5	2.5	2.5	0	2.5	5.0	2.5	2.5	2.5	0	4.9	1.6	0
REC	0	0.1	0	0	1.0	0	2.5	2.5	2.5	2.5	0	2.5	5.0	2.9	2.5	2.5	0	4.9	1.6	0
F.F	0	0.1	0	0	1.0	0	2.5	2.5	2.5	2.5	0	2.5	5.0	2.5	2.5	2.5	0	0	1.6	0
REW	0	0.1	0	0	1.0	0	2.5	2.5	2.5	2.5	0	2.5	5.0	2.5	2.5	2.5	0	0	1.6	0
Ref. No. MODE	IC6001																			
	81	82	83	84	85	86	87	88	89	90	91	92	93	94	95	96	97	98	99	100
STOP	0	0	0	0	5.0	4.8	5.0	2.4	1.6	5.0	0	0	0	0	0	0	5.0	0	0	1.7
PLAY	0	0	0	0	5.0	4.8	5.0	2.4	4.0	5.0	0	0	0	0	0	0	5.0	2.5	0	5.0
REC	0	0	0	0	5.0	4.7	5.0	2.4	2.2	5.0	0	0	0	0	0	0	5.0	2.5	0	0
F.F	0	0	0	0	5.0	4.8	5.0	2.4	1.0	5.0	5.0	0	0	0	0	0	5.0	0	0	2.6
REW	0	0	0	0	5.0	4.8	5.0	2.4	3.3	5.0	5.0	0	0	0	0	0	5.0	0	0	3.7
Ref. No. MODE	IC6002										IC6003									
	1	2	3	4							1	2	3	4						
STOP	1.1	2.3	5.2	0							0	1.1	3.9	0						
PLAY	1.1	2.3	2.5	0							0	1.1	2.5	0						
REC	1.1	2.3	2.5	0							0	1.1	2.5	0						
F.F	1.1	2.3	2.5	0							0	1.1	2.5	0						
REW	1.1	2.3	2.5	0							0	1.1	2.5	0						
Ref. No. MODE	IC6004										IC6005									
	1	2	3								1	2	3	4	5					
STOP	5.0	0	5.0								5.0	5.0	0	0	0					
PLAY	5.0	0	5.0								5.0	5.0	0	0	0					
REC	5.0	0	5.0								5.0	5.0	0	0	0					
F.F	5.0	0	5.0								5.0	5.0	0	0	0					
REW	5.0	0	5.0								5.0	5.0	0	0	0					

SYSTEM CONTROL & SERVO TRs DC VOLTAGE CHART (SP MODE)

Ref. No. MODE	Q6001			Q6002			Q7701			QR6001										
	E	C		E	C		E	C	B	E	C	B								
STOP	4.6	0		5.0	0		2.6	0	1.9	0	12.9	0								
PLAY	4.8	0		5.0	0		2.6	0	1.9	0	12.8	0								
REC	4.6	0		5.0	0		2.6	0	1.9	0	12.8	0								
F.F	4.7	0		5.0	0		2.6	0	1.9	0	12.8	0								
REW	4.7	0		5.0	0		2.6	0	1.9	0	12.0	0								