

5-2 ELECTRICAL REPLACEMENT PARTS LIST

Note: 1. Be sure to make your orders of replacement parts according to this list.
 2. IMPORTANT SAFETY NOTICE: Components identified with the mark (!) have the special characteristics for safety. When replacing any of these components, use only the same type.
 3. Unless otherwise specified, All resistors are in OHMS, K-1,000 OHMS. All capacitors are in MICRO-FARADS(uf), P-uuf.
 4. The P.C. Board units marked with ' show below the main assembled parts.
 5. The marking (RTL) indicates the retention time is limited for this item. After the discontinuation of this assembly in production, it will no longer be available.

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
*****	NV-HD70AM			
	NV-HD77AM			
	NV-HD90EE			
	VEPO3A86J	MAIN C.B.A. (Page:5-8)	1	(RTL)NV-HD70AM INCLUDED IN THE LUMINANCE & CHROMINANCE PACK C.B.A. (VEPO3975C), HI-FI AUDIO PACK C.B.A. (VEPO4447PJ), TV DEMODULATOR PACK C.B.A. (VEPO7723F), RECORDER PACK C.B.A. (VEPO7725A).
	VEPO3975C	LUMINANCE & CHROMINANCE PACK C.B.A.	1	(RTL)NV-HD70AM INCLUDED IN MAIN C.B.A. (VEPO3A86J). INCLUDING THE NTSC REC PACK C.B.A. (VEPO3888C).
	VEPO3888C	NTSC REC PACK C.B.A.	1	(RTL)NV-HD70AM INCLUDED IN LUMINANCE & CHROMINANCE PACK C.B.A. (VEPO3975C).
	VEPO4447PJ	HI-FI AUDIO PACK C.B.A.	1	(RTL)NV-HD70AM INCLUDED IN MAIN C.B.A. (VEPO3A86J).
	VEPO7723F	TV DEMODULATOR PACK C.B.A.	1	(RTL)NV-HD70AM INCLUDED IN MAIN C.B.A. (VEPO3A86J).
	VEPO7725A	RECORDER PACK C.B.A.	1	(RTL)NV-HD70AM INCLUDED IN MAIN C.B.A. (VEPO3A86J).
	VEPO3A86L	MAIN C.B.A. (Page:5-14)	1	(RTL)NV-HD77AM INCLUDING THE LUMINANCE & CHROMINANCE PACK C.B.A. (VEPO3975C), HI-FI AUDIO PACK C.B.A. (VEPO4447PJ), TV DEMODULATOR PACK C.B.A. (VEPO7723F), RECORDER PACK C.B.A. (VEPO7725B).
	VEPO3975C	LUMINANCE & CHROMINANCE PACK C.B.A.	1	(RTL)NV-HD77AM INCLUDED IN MAIN C.B.A. (VEPO3A86L). INCLUDING THE NTSC REC C.B.A. (VEPO3888C).
	VEPO3888C	NTSC REC C.B.A.	1	(RTL)NV-HD77AM INCLUDED IN LUMINANCE & CHROMINANCE PACK C.B.A. (VEPO3975C).
	VEPO4447PJ	HI-FI AUDIO PACK C.B.A.	1	(RTL)NV-HD77AM

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
				INCLUDED IN MAIN C.B.A. (VEPO3A86L).
	VEPO7723F	TV DEMODULATOR PACK C.B.A.	1	(RTL)NV-HD77AM INCLUDED IN MAIN C.B.A. (VEPO3A86L).
	VEPO7725B	RECORDER PACK C.B.A.	1	(RTL)NV-HD77AM INCLUDED IN MAIN C.B.A. (VEPO3A86L).
	VEPO3A86H	MAIN C.B.A. (Page:5-21)	1	(RTL)NV-HD90EE INCLUDING THE LUMINANCE & CHROMINANCE PACK C.B.A. (VEPO3975F), HI-FI AUDIO PACK C.B.A. (VEPO4447PH), TV DEMODULATOR PACK C.B.A. (VEPO7645Z), RECORDER PACK C.B.A. (VEPO7743A).
	VEPO3975F	LUMINANCE & CHROMINANCE PACK C.B.A.	1	(RTL)NV-HD90EE INCLUDED IN MAIN C.B.A. (VEPO3A86H). INCLUDING THE DDR C.B.A. (VEPO3A02A).
	VEPO3A02A	DDR C.B.A.	1	(RTL)NV-HD90EE INCLUDED IN LUMINANCE & CHROMINANCE PACK C.B.A. (VEPO3975F).
	VEPO4447PH	HI-FI AUDIO PACK C.B.A.	1	(RTL)NV-HD90EE INCLUDED IN MAIN C.B.A. (VEPO3A86H).
	VEPO7645Z	TV DEMODULATOR PACK C.B.A.	1	(RTL)NV-HD90EE INCLUDED IN MAIN C.B.A. (VEPO3A86H).
	VEPO7743A	RECORDER PACK C.B.A.	1	(RTL)NV-HD90EE INCLUDED IN MAIN C.B.A. (VEPO3A86H).
	VEX0128	CYLINDER DRIVE C.B.A. (Page:5-27)	1	(RTL)
	VEPO5176C	HEAD AMP C.B.A. (Page:5-28)	1	(RTL)
	VEPO6931B	OPERATION C.B.A. (Page:5-28)	1	(RTL)
	VEPO7675C	NICAM RECORDER C.B.A. (Page:5-28)	1	(RTL)NV-HD77AM
	VEPO7752N	TIMER C.B.A. (Page:5-29)	1	(RTL)NV-HD70AM
	VEPO7752Q	TIMER C.B.A. (Page:5-30)	1	(RTL)NV-HD77AM
	VEPO7752M	TIMER C.B.A. (Page:5-31)	1	(RTL)NV-HD90EE
	VEPO1587F	POWER C.B.A. (Page:5-32)	1	(RTL) (!) NV-HD70AM/HD77AM
	VEPO1587D	POWER C.B.A. (Page:5-32)	1	(RTL) (!) NV-HD90EE
	-----	MECHANISM CONNECTION C.B.A.	1	NOT SUPPLIED AS

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
		(Page:5-33)		C.B.A. (C.B. IS LISTED ON MECHANICAL PARTS LIST)	C797-99	ECUX1H103ZJV	C.CAPACITOR CH 50V 0.01U	3	
					C805	ECEAJK221	E.CAPACITOR 6.3V 220	1	
					C806	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	1	
					C807	ECUM1H181JCN	C.CAPACITOR CH 50V 180P	1	
					C808	ECUM1H270JCN	C.CAPACITOR CH 50V 27P	1	
		MOTOR C.B.A.	1	C.B.A. IS INCLUDED IN LOADING MOTOR (1) UNIT(VER0427).	C809	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1	
		(Page:5-33)			C812-14	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	3	
					C815	ECUM1H560JCN	C.CAPACITOR CH 50V 56P	1	
	ENC17992A	RF CONVERTER	1	<!>NV-HD70AM/HD77AM	C816	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1	
					C817	ECUM1H560JCN	C.CAPACITOR CH 50V 56P	1	
	ENC17991A	RF CONVERTER	1	<!>NV-HD90EE	C818	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1	
					C819	ECUM1H470JCN	C.CAPACITOR CH 50V 47P	1	
					C820-25	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	6	
					C826	ECEAJK101	E.CAPACITOR 6.3V 100U	1	
	EWV590BH3	TUNER	1	<!>	C827	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1	
					C828	ECUM1H470JCN	C.CAPACITOR CH 50V 47P	1	
					C829	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1	
F1101	YBA2C16TD0	FUSE	1	<!>	C830	ECEA1HKOR1	E.CAPACITOR 50V 0.1U	1	
					C831	ECQB1H332JH	P.CAPACITOR 50V 0.27U	1	
					C832	ECUM1H331JCN	C.CAPACITOR CH 50V 330P	1	
					C838	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	1	
	VEF03A86J	MAIN C.B.A.		(RTL)NV-HD70AM	C839	ECUM1H100DCN	C.CAPACITOR CH 50V 10P	1	
					C841	ECUM1H102KBN	C.CAPACITOR CH 50V 1000P	1	
					C842	ECEAJK101	E.CAPACITOR 6.3V 100U	1	
C305	ECUM1H470JCN	C.CAPACITOR CH 50V 47P	1		C843	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	1	
C306,07	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	2		C845	ECEA1HK010	E.CAPACITOR 50V 1U	1	
C308	ECEA1EK4R7	E.CAPACITOR 25V 4.7U	1		C846	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1	
C310	ECEA1CK220	E.CAPACITOR 16V 22U	1		C848-50	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	3	
C311	ECEAJK101	E.CAPACITOR 6.3V 100U	1		C1001	ECEA1EM101	E.CAPACITOR 25V 100U	1	
C312	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	1		C1002	ECEA1AFS221	E.CAPACITOR 10V 220U	1	
C313,14	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	2		C1003	ECEAJKA330	E.CAPACITOR 6.3V 33U	1	
C315	ECUM1H560JCN	C.CAPACITOR CH 50V 56P	1		C1004	ECEA1KA330	E.CAPACITOR 16V 33U	1	
C319	ECEAJK101	E.CAPACITOR 6.3V 100U	1		C1005	ECEA1KA100	E.CAPACITOR 16V 10U	1	
C320	ECUM1H620JCN	C.CAPACITOR CH 50V 82P	1		C1006	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1	
C321	ECUM1H33KBN	C.CAPACITOR CH 50V 0.033U	1		C2001	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	1	
C701,02	ECEA1CK100	E.CAPACITOR 16V 10U	2		C2002	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1	
C705	ECEA1CK220	E.CAPACITOR 16V 22U	1		C2003	ECEA1KA470	E.CAPACITOR 16V 47U	1	
C706	ECQV1H104JH	E.CAPACITOR 50V 0.1U	1		C2004	ECEA1KA101	E.CAPACITOR 16V 100U	1	
C707	ECEA1HQR47	E.CAPACITOR 50V 0.47U	1		C2005,06	ECEA1HQR47	E.CAPACITOR 50V 0.47U	2	
C708	ECEA1CK220	E.CAPACITOR 16V 22U	1		C2007	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1	
C709	ECEA1CK100	E.CAPACITOR 16V 10U	1		C2008	ECEA1HKA2R2	E.CAPACITOR 50V 2.2U	1	
C710	ECUX1H103ZJV	C.CAPACITOR CH 50V 0.01U	1		C2009,10	ECUM1H680JCN	C.CAPACITOR CH 50V 68P	2	
C711	ECEA1CK100	E.CAPACITOR 16V 10U	1		C2011,12	ECUM1H33KBN	C.CAPACITOR CH 50V 0.033U	2	
C712	ECQB1H822JH	P.CAPACITOR 50V 8200P	1		C2013	ECQV1H334JM	P.CAPACITOR 50V 0.33U	1	
C713	ECQV1H333JZ	P.CAPACITOR 50V 0.033U	1		C2014	ECUM1H33KBN	C.CAPACITOR CH 50V 0.033U	1	
C714	ECUX1H103ZJV	C.CAPACITOR CH 50V 0.01U	1		C2015,16	ECEA1HKA2R2	E.CAPACITOR 50V 2.2U	2	
C715	ECUM1H151JCN	C.CAPACITOR CH 50V 150P	1		C2017	ECEA1HQR22	E.CAPACITOR 50V 0.22U	1	
C716	ECUM1H331JCN	C.CAPACITOR CH 50V 330P	1		C2018,19	ECUM1H33KBN	C.CAPACITOR CH 50V 0.033U	2	
C717	ECEA1HKOR1	E.CAPACITOR 50V 0.1U	1		C2020	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1	
C718-20	ECUX1H103ZJV	C.CAPACITOR CH 50V 0.01U	3		C2021	ECAOJM221	E.CAPACITOR 6.3V 220U	1	
C721	ECEA1CK470	E.CAPACITOR 16V 47U	1		C2022	ECEA1KA470	E.CAPACITOR 16V 47U	1	
C722	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1		C2023	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	1	
C723	ECUM1H120JCN	C.CAPACITOR CH 50V 12P	1		C2024	ECEA1KA100	E.CAPACITOR 16V 10U	1	
C724	ECUM1H470JFN	C.CAPACITOR CH 50V 47P	1		C2025,26	ECUM1C105ZFN	C.CAPACITOR CH 16V 1U	2	
C725	ECQV1H473JZ	P.CAPACITOR 50V 0.047U	1		C2027	ECEA1HKA3R3	E.CAPACITOR 50V 3.3U	1	
C726	ECUX1H103ZJV	C.CAPACITOR CH 50V 0.01U	1		C2028	ECEA1HKNR3	E.CAPACITOR 50V 3.3U	1	
C727	ECUM1H270JCN	C.CAPACITOR CH 50V 27P	1		C2029	ECUM1H471JCN	C.CAPACITOR CH 50V 470P	1	
C728	ECEA1HQR47	E.CAPACITOR 50V 0.47U	1		C2030	ECUM1H222KBN	C.CAPACITOR CH 50V 2200P	1	
C729	ECUX1H390JCV	C.CAPACITOR CH 50V 39P	1		C2031	ECUM1H392KBN	C.CAPACITOR CH 50V 3900P	1	
C730-32	ECUX1H103ZJV	C.CAPACITOR CH 50V 0.01U	3		C2032	ECUM1H223KBN	C.CAPACITOR CH 50V 0.022U	1	
C733	ECEA1HK2R2	E.CAPACITOR 50V 2.2U	1		C2033	ECAOJM221	E.CAPACITOR 6.3V 220U	1	
C734	ECQV1H104JM	P.CAPACITOR 50V 0.1U	1		C2034	ECEA1KA100	E.CAPACITOR 16V 10U	1	
C735	ECEA1CK470	E.CAPACITOR 16V 47U	1		C2035	ECEA1HKA3R3	E.CAPACITOR 50V 3.3U	1	
C736-42	ECUX1H103ZJV	C.CAPACITOR CH 50V 0.01U	7		C2036	ECEAJKA220	E.CAPACITOR 6.3V 22U	1	
C752	ECUX1H820JCV	C.CAPACITOR CH 50V 82P	1		C2037	ECUM1H103ZFN	C.CAPACITOR CH 50V 0.01U	1	
C754,55	ECUX1H103ZJV	C.CAPACITOR CH 50V 0.01U	2		C2038	ECUM1H104ZFN	C.CAPACITOR CH 50V 0.1U	1	
C756	ECEA1CK470	E.CAPACITOR 16V 47U	1		C2039	ECEA1HQR47	E.CAPACITOR 50V 4.7U	1	
C757	ECUX1H470JCV	C.CAPACITOR CH 50V 47P	1		C2040	ECUM1H222KBN	C.CAPACITOR CH 50V 2200P	1	
C758,59	ECUX1H103ZJV	C.CAPACITOR CH 50V 0.01U	2		C2041	ECUM1H333KBN	C.CAPACITOR CH 50V 0.033U	1	
C760	ECEA1HKOR1	E.CAPACITOR 50V 0.1U	1		C2042	ECQV1H683JM	P.CAPACITOR 50V 0.068U	1	
C761	ECUX1H103ZJV	C.CAPACITOR CH 50V 0.01U	1		C2043	ECEA1KA470	E.CAPACITOR 16V 47U	1	
C762	ECEA1CK100	E.CAPACITOR 16V 10U	1		C2044	ECEA1HKA010	E.CAPACITOR 50V 1U	1	
C763-67	ECUX1H103ZJV	C.CAPACITOR CH 50V 0.01U	5		C2045	ECEA1KA470	E.CAPACITOR 16V 47U	1	
C790	ECUX1H100DCV	C.CAPACITOR CH 50V 10P	1		C2046	ECEA1HQR47	E.CAPACITOR 50V 0.47U	1	
C796	ECUX1H150JCV	C.CAPACITOR CH 50V 15P	1		C2047	ECQV1H603JM	P.CAPACITOR 50V 0.060U	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
C2048	ECEA1CKA470	E. CAPACITOR 16V 47U	1		C4545	ECUX1H102JCV	C. CAPACITOR CH 50V 1000P	1	
C2049	ECEA0JKA470	E. CAPACITOR 6.3V 47U	1		C4551	EQQB1H223JA	P. CAPACITOR 50V 0.022U	1	
C2050	ECUM1H101JCN	C. CAPACITOR CH 50V 100P	1		C4556	ECEA1CU100	E. CAPACITOR 16V 10U	1	
C2051	ECUM1H1042FN	C. CAPACITOR CH 50V 0.1U	1		C4558	ECEA1EKN4R7	E. CAPACITOR 25V 4.7U	1	
C2052	ECA0JM101	E. CAPACITOR 6.3V 100P	1		C4559	ECEA1AU470	E. CAPACITOR 10V 47U	1	
C3001	ECUM1H102KBN	C. CAPACITOR CH 50V 1000P	1		C4560	EQQB1H103JA	P. CAPACITOR 50V 0.01U	1	
C3002, 03	ECUM1H1042FN	C. CAPACITOR CH 50V 0.1U	2		C4561	EQQB1H332JA	P. CAPACITOR 50V 3300P	1	
C3004	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1		C4562	ECUX1H561JV	C. CAPACITOR CH 50V 560P	1	
C3005	ECUM1H1042FN	C. CAPACITOR CH 50V 0.1U	1		C4563	ECUX1H681JV	C. CAPACITOR CH 50V 680P	1	
C3006	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1		C4564	ECUX1H561JV	C. CAPACITOR CH 50V 560P	1	
C3007	ECEA0JKA221	E. CAPACITOR 6.3V 220U	1		C4565	ECEA1EU4R7	E. CAPACITOR 25V 4.7U	1	
C3008	ECEA1CA100	E. CAPACITOR 16V 10U	1		C4567	ECEA1AU101	E. CAPACITOR 10V 100U	1	
C3009	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1		C4568	ECUX1C1042FV	C. CAPACITOR CH 16V 0.1U	1	
C3010	ECEA0JKA470	E. CAPACITOR 6.3V 47U	1		C4572	ECEA1HU3R3	E. CAPACITOR 50V 3.3U	1	
C3011	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1		C4576	ECUM1E473KBN	C. CAPACITOR CH 25V 0.047U	1	
C3012	ECUM1H620JCN	C. CAPACITOR CH 50V 62P	1		C4583	ECEA1AU330	E. CAPACITOR 10V 33U	1	
C3013	ECUM1H333JCN	C. CAPACITOR CH 50V 33P	1		C4585, 86	ECEA1AU101	E. CAPACITOR 10V 100U	2	
C3014	ECUM1H683JCN	C. CAPACITOR CH 50V 68P	1		C4591	ECUX1C1042FV	C. CAPACITOR CH 16V 0.1U	1	
C3015	ECUM1H220JCN	C. CAPACITOR CH 50V 22P	1		C4592	ECUX1H152KBN	C. CAPACITOR CH 50V 1500P	1	
C3016	ECUM1H151JCN	C. CAPACITOR CH 50V 150P	1		C4593	ECUX1H221JCV	C. CAPACITOR CH 50V 220P	1	
C3017	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1		C4594, 95	ECUX1H101JCV	C. CAPACITOR CH 50V 100P	2	
C3019	ECUM1H220JCN	C. CAPACITOR CH 50V 22P	1		C4596	ECEA1CU100	E. CAPACITOR 16V 10U	1	
C3020	ECUM1H100JCN	C. CAPACITOR CH 50V 18P	1		C4597	ECUX1H330JCV	C. CAPACITOR CH 50V 33P	1	
C3021	ECA0JM471	E. CAPACITOR 6.3V 470	1		C4604	ECUM1H182JCN	C. CAPACITOR CH 50V 1800P	1	
C3022	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1		C4605	ECEA0JKA470	E. CAPACITOR 6.3V 47U	1	
C3023	ECEA1CA470	E. CAPACITOR 16V 47U	1		C4611	EQQB1H562JZ	P. CAPACITOR 50V 5600P	1	
C3024	ECUM1H1042FN	C. CAPACITOR CH 50V 0.1U	1		C4616	ECUX1H102JCV	C. CAPACITOR CH 50V 1000P	1	
C3025	ECEA0JKA470	E. CAPACITOR 6.3V 47U	1		C4617	ECEA10M22	E. CAPACITOR 10V 22U	1	
C3026, 27	ECEA1CA100	E. CAPACITOR 16V 10U	2		C4618	EQQB1H222JZ	P. CAPACITOR 50V 8200P	1	
C3028, 29	ECUM1H332KBN	C. CAPACITOR CH 50V 3300P	2		C4621	ECEA0JKA101	E. CAPACITOR 6.3V 100U	1	
C3030	ECEA1CA100	E. CAPACITOR 16V 10U	1		C4629	EQQB1H123JZ	E. CAPACITOR 50V 0.012U	1	
C3031	ECUM1H102KBN	C. CAPACITOR CH 50V 1000P	1		C4636	ECUX1H151JCV	C. CAPACITOR CH 50V 150P	1	
C3032	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1		C4638	EQQB1H272JZ	P. CAPACITOR 50V 2700P	1	
C3033	ECUM1H681JCN	C. CAPACITOR 50V 680P	1		C4652, 53	ECUX1C1052FN	C. CAPACITOR CH 16V 1U	2	
C3034	ECUM1H1042FN	C. CAPACITOR CH 50V 0.1U	1		C6001	ECUM1H1042FN	C. CAPACITOR CH 50V 0.1U	1	
C3035	ECUM1H181JCN	C. CAPACITOR CH 50V 180P	1		C6002	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1	
C3036	ECUM1H220JCN	C. CAPACITOR CH 50V 22P	1		C6003	ECEA1H82R2	E. CAPACITOR 50V 2.2U	1	
C3038	ECEA1AFS221	E. CAPACITOR 10V 220U	1		C6004	ECUM1H221JCN	C. CAPACITOR CH 50V 220P	1	
C3905, 06	ECUM1H821JCN	C. CAPACITOR CH 50V 820P	2		C6005	ECUM1H223KBN	C. CAPACITOR CH 50V 0.022U	1	
C3911	ECEA1CA100	E. CAPACITOR 16V 10U	1		C6006	ECUM1H472KBN	C. CAPACITOR CH 50V 4700P	1	
C3914, 15	ECUX1C1052FN	C. CAPACITOR CH 16V 1U	2		C6007, 08	ECUM1H220JCN	C. CAPACITOR CH 50V 22P	2	
C4001	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1		C6009	ECEA0JKA220	E. CAPACITOR 6.3V 22U	1	
C4002	EQCB2H331HB	C. CAPACITOR 500V 330P	1		C6010	ECQV1H104JM	P. CAPACITOR 50V 0.1U	1	
C4003	EQP1332JZ	P. CAPACITOR 50V 3300P	1		C6011	ECUM1H392KBN	C. CAPACITOR CH 50V 3900P	1	
C4004	EQQB1H102JZ	P. CAPACITOR 50V 1000P	1		C6012	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1	
C4005	EQQB1H153JZ	P. CAPACITOR 50V 0.015U	1		C6013	ECUM1H1042FN	C. CAPACITOR CH 50V 0.1U	1	
C4006	ECEA1GM33	E. CAPACITOR 16V 33U	1		C6014	ECEA0JKA220	E. CAPACITOR 6.3V 22U	1	
C4007	ECUM1H221JCN	C. CAPACITOR CH 50V 220P	1		C6015, 16	ECUM1H271JCN	C. CAPACITOR CH 50V 270P	2	
C4008	ECUM1H681JCN	C. CAPACITOR 50V 680P	1		C6017	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1	
C4010	ECUM1H683JCN	C. CAPACITOR CH 50V 0.068U	1		C6018	ECUM1H102KBN	C. CAPACITOR CH 50V 1000P	1	
C4034	ECEA1HKA010	E. CAPACITOR 50V 1U	1		C6019	ECEA1CA100	E. CAPACITOR 16V 10U	1	
C4503	ECUX1H152KBN	C. CAPACITOR CH 50V 1500P	1		C6025-28	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	4	
C4504, 05	ECEA1CU470	E. CAPACITOR 16V 47U	2		C7005	ECUX1C1052FN	C. CAPACITOR CH 16V 1U	1	
C4506	ECEA1CU100	E. CAPACITOR 16V 10U	1		C7006	ECEA1AKN100	E. CAPACITOR 10V 10U	1	
C4507	EQQB1H223JA	P. CAPACITOR 50V 0.022U	1		C7007	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1	
C4508	ECEA1EKN4R7	E. CAPACITOR 25V 4.7U	1		C7010	ECEA1CA100	E. CAPACITOR 16V 10U	1	
C4509	ECEA1AU470	E. CAPACITOR 10V 47U	1		C7011	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1	
C4510	EQQB1H103JA	P. CAPACITOR 50V 0.01U	1		C7012	ECUM1H1042FN	C. CAPACITOR CH 50V 0.1U	1	
C4511	EQQB1H332JA	P. CAPACITOR 50V 3300P	1		C7302	ECEA1CKN100	E. CAPACITOR 16V 10U	1	
C4512	ECUX1H561JV	C. CAPACITOR CH 50V 560P	1		C7303	ECQV1H393JZ	P. CAPACITOR 50V 0.039U	1	
C4513	ECUX1H681JV	C. CAPACITOR CH 50V 680P	1		C7304	ECEA1CKN100	E. CAPACITOR 16V 10U	1	
C4514	ECUX1H561JV	C. CAPACITOR CH 50V 560P	1		C7305	ECQV1H473JZ	P. CAPACITOR 50V 0.047U	1	
C4515	ECEA1EU4R7	E. CAPACITOR 25V 4.7U	1		C7306	EQQB1H102KZ	P. CAPACITOR 50V 1000P	1	
C4517	ECEA1AU101	E. CAPACITOR 10V 100U	1		C7307	EQQB1H822KZ	P. CAPACITOR 50V 8200P	1	
C4518	ECUX1C1042FV	C. CAPACITOR CH 16V 0.1U	1		C7308	EQQB1H102KZ	P. CAPACITOR 50V 1000P	1	
C4521	ECUM1E473KBN	C. CAPACITOR CH 25V 0.047U	1		C7309	EQQB1H152KZ	P. CAPACITOR 50V 1500P	1	
C4522	ECEA1HU3R3	E. CAPACITOR 50V 3.3U	1		C7310	ECEA1CK100	E. CAPACITOR 16V 10U	1	
C4524	ECEA1AU101	E. CAPACITOR 10V 100U	1		C7311	ECEA1HKR47	E. CAPACITOR 50V 0.47U	1	
C4528	ECUX1C1042FV	C. CAPACITOR CH 16V 0.1U	1		C7312	ECQV1H224JM	P. CAPACITOR 50V 0.22U	1	
C4530	ECEA0JU470	E. CAPACITOR 6.3V 47U	1		C7313	ECQV1H104JM	P. CAPACITOR 50V 0.1U	1	
C4533	ECEA1AU330	E. CAPACITOR 10V 33U	1		C7314	ECQV1H224JM	P. CAPACITOR 50V 0.22U	1	
C4537	ECUX1H102JCV	C. CAPACITOR CH 50V 1000P	1		C7315	ECQV1H104JM	P. CAPACITOR 50V 0.1U	1	
C4538	ECEA1HUR47	E. CAPACITOR 50V 0.47U	1		C7316	ECQV1H224JM	P. CAPACITOR 50V 0.22U	1	
C4539	ECUX1C224ZJF	C. CAPACITOR CH 16V 0.22U	1		C7317	ECEA1CK101	E. CAPACITOR 16V 100U	1	
C4541	ECUX1C1042FV	C. CAPACITOR CH 16V 0.1U	1		C7318	ECUX1H1032FV	C. CAPACITOR CH 50V 0.01U	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
C7319	ECEA1CK470	E. CAPACITOR 16V 47U	1	
C7320, 21	ECEA1CK100	E. CAPACITOR 16V 10U	2	
C7323, 24	ECQV1H393JZ	P. CAPACITOR 50V 0.039U	2	
C7331	ECQV1H474JM	P. CAPACITOR 50V 0.47U	1	
C7332, 33	ECUX1H102KBV	C. CAPACITOR CH 50V 1000P	2	
C7334	ECUX1H1032FV	C. CAPACITOR CH 50V 0.01U	1	
C7335	ECEA1CK470	E. CAPACITOR 16V 47U	1	
C7336	ECUX1H1032FV	C. CAPACITOR CH 50V 0.01U	1	
C7337	ECUX1H680JCV	C. CAPACITOR CH 50V 68P	1	
C7339	ECUX1H1032FV	C. CAPACITOR CH 50V 0.01U	1	
C7340	ECUM1H390JFN	C. CAPACITOR CH 50V 39P	1	
C7341	ECUX1H070DCV	C. CAPACITOR CH 50V 7P	1	
C7343	ECEA1CK100	E. CAPACITOR 16V 10U	1	
C7345	ECUX1H1032FV	C. CAPACITOR CH 50V 0.01U	1	
C7346	ECUM1H390JFN	C. CAPACITOR CH 50V 39P	1	
C7347	ECUX1H070DCV	C. CAPACITOR CH 50V 7P	1	
C7348	ECQV1H393JZ	P. CAPACITOR 50V 0.039U	1	
C7349, 50	ECUX1H221JCV	C. CAPACITOR CH 50V 220P	2	
C7351, 52	ECUX1H1032FV	C. CAPACITOR CH 50V 0.01U	2	
C7353	ECEA1CK470	E. CAPACITOR 16V 47U	1	
C7354	ECEA1CK220	E. CAPACITOR 16V 22U	1	
C7355	ECEA1CK100	E. CAPACITOR 16V 10U	1	
C7356	ECEA1CK100	E. CAPACITOR 16V 10U	1	
C7357	ECEA1CK100	E. CAPACITOR 16V 10U	1	
C7661	ECUM1H104KBM	C. CAPACITOR CH 50V 0.1U	1	
C7662	ECUM1H683KBM	C. CAPACITOR CH 50V 0.068U	1	
C7663	ECUM1H823KBM	C. CAPACITOR CH 50V 0.082U	1	
C7664	ECUM1H273KBM	C. CAPACITOR CH 50V 0.027U	1	
C7665, 66	ECUX1H1032FV	C. CAPACITOR CH 50V 0.01U	2	
C7667	ECEA1HKA100	E. CAPACITOR 50V 10U	1	
C7670, 71	ECUX1H1032FV	C. CAPACITOR CH 50V 0.01U	2	
C7673	ECUX1H1032FV	C. CAPACITOR CH 50V 0.01U	1	
C7675	ECEA1HKN010	E. CAPACITOR 50V 1U	1	
C7676, 77	ECUX1H1032FV	C. CAPACITOR CH 50V 0.01U	2	
C7679	ECEA1HKN010	E. CAPACITOR 50V 1U	1	
C7681	ECEA1CK220	E. CAPACITOR 16V 22U	1	
C8001	ECUM1C4742FN	C. CAPACITOR 16V 0.47U	1	
C8002-04	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	3	
C8006	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1	
C8007	ECEA1AKS330	E. CAPACITOR 10V 33U	1	
C8008	ECUM1H220JCN	C. CAPACITOR CH 50V 22P	1	
C8009	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1	
C8010-12	ECEA1AKS330	E. CAPACITOR 10V 33U	3	
C8013	ECUM1H1032FN	C. CAPACITOR CH 50V 0.01U	1	
C8014	ECUM1H561KBN	C. CAPACITOR CH 50V 560P	1	
C8015	ECUM1H221JCN	C. CAPACITOR CH 50V 220P	1	
C8019	ECUM1H680JCN	C. CAPACITOR CH 50V 68P	1	
C8020	ECUM1H470JCN	C. CAPACITOR CH 50V 47P	1	
D302	1SS283	DIODE	1	
D303	MA151A	DIODE	1	
D304	1SS254	DIODE	1	
D701-07	MA77	DIODE	7	
D708	MA3100L	DIODE	1	
D709	MA77	DIODE	1	
D771	MA141WK	DIODE	1	
D772, 73	MA141K	DIODE	2	
D801, 02	1SS254	DIODE	2	
D804	1SS254	DIODE	1	
D2001	1SS254	DIODE	1	
D2002	MA153	DIODE	1	
D2003, 04	1SS254	DIODE	2	
D2007, 08	1SS254	DIODE	2	
D2009	MA151WK	DIODE	1	
D2010	MA151K	DIODE	1	
D3001	MA151K	DIODE	1	
D3002, 03	1SS254	DIODE	2	
D4001	MA151K	DIODE	1	
D4003	MA151WK	DIODE	1	
D4004	MA723VT	DIODE	1	
D4005	MA151K	DIODE	1	
D4501-04	MA141K	DIODE	4	
D6001	1SS254	DIODE	1	
D6002	MA151K	DIODE	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
D6003	1SS254	DIODE	1	
D6005, 06	1SS254	DIODE	2	
D6007	MA4075-L	DIODE	1	
D7002	MA723VT	DIODE	1	
D7003	1SS254	DIODE	1	
D7004-06	11ES1	DIODE	3	
D7007	1SS254	DIODE	1	
D7304	MA3100L	DIODE	1	
D7601	MA141K	DIODE	1	
D7602	MA3082M	DIODE	1	
DL801	VLD0198	DELAY LINE	1	
FE	VJS1141	CONNECTOR (FEMALE)	1	
FL8001	ELB4N055	FILTER	1	
FL8002	ELB4L149	FILTER	1	
IC301	VERH29D	IC	1	
IC701	LA7577	IC	1	
IC702	LA7975	IC	1	
IC801	NJM2233BMA	IC	1	
IC802	M52352FP	IC	1	
IC2001	XRA6887-V3	IC	1	
IC2002	BA6871	IC	1	
IC2004	LM358PS	IC	1	
IC3001	NJM2233BL	IC	1	
IC3002	BA7004	IC	1	
IC4501	XIH7773KS	IC	1	
IC4601	BA7755AF	IC	1	
IC6001	MN67434VRSR	IC	1	
IC7301	TDA3803A	IC	1	
IC7302	TA8721SN	IC	1	
IC7303	TC4W66F	IC	1	
IC7652	AN5043SC	IC	1	
IC8001	BA7049FS	IC	1	
J3901, 02	VJJO348	JACK	2	
L303	ELESQ220KA	COIL 22UH	1	
L304	ELESQ101KA	COIL 100UH	1	
L305	ELESQ121JA	COIL	1	
L306	ELESQ390KA	COIL 39UH	1	
L701	ELESQ680KA	COIL 68UH	1	
L711	ELJNAR39KF	COIL	1	
L712-16	ELJFA151KB	COIL 150UH	5	
L718	ELJNAROJF	COIL H	1	
L719	ELESQ5R6KA	COIL 5.6UH	1	
L721	ELJFA151KB	COIL 150UH	1	
L723	ELJFA151KB	COIL 150UH	1	
L724	ELJNAR27KF	COIL	1	
L751	ELJFA100KB	COIL	1	
L752	ELESQ270KA	COIL 27UH	1	
L770	ELESQ680KA	COIL 68UH	1	
L803	ELESQ5R6KA	COIL 5.6UH	1	
L804	ELESQ101KA	COIL 100UH	1	
L805	ELESQ270KA	COIL 27UH	1	
L807, 08	VLQ0540J150	COIL 15UH	2	
L809	ELESQ101KA	COIL 100UH	1	
L811, 12	ELESQ101KA	COIL 100UH	2	
L2001	VLPO074	COIL	1	
L2002	ELESE10ZKA	COIL 1000UH	1	
L2003, 04	VLQ0599J680	COIL	2	
L2005	VLPO083	COIL	1	
L2006	VLQ0599J680	COIL	1	
L3001	VLQ0599J680	COIL	1	
L3002	VLQ0599J151	COIL 150UH	1	
L3003	VLQ0599J820	COIL H	1	
L3005	VLQ0599J680	COIL	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
L3006	VLQ0599J101	COIL 100UH	1		Q3004,05	MSD601-R	TRANSISTOR	2	
L3007,08	VLQ0599J680	COIL	2		Q3006	MSC2295	TRANSISTOR	1	
L3009	VLQ0599J120	COIL H	1		Q3007	MSB709-R	TRANSISTOR	1	
L3010	VLQ0599J6R8	COIL H	1		Q3008	MSC2295	TRANSISTOR	1	
L3011	VLQ0599J680	COIL	1		Q3010	2SB709	TRANSISTOR	1	
L3012	VLQ0599J270	COIL 27UH	1		Q4002	2SD602A-R	TRANSISTOR	1	
L3013	VLQ0599J680	COIL	1		Q4003	MSD601	TRANSISTOR	1	
L4001,02	ERJ6GMZOR00	M.RESISTOR 1/10W 0	2		Q4501	2SD655	TRANSISTOR	1	
L4501,02	ELESE101KA	COIL 100UH	2		Q4551	2SB561	TRANSISTOR	1	
L4601	VLQEL07F153J	COIL 15MH	1		Q4552	2SD1819A	TRANSISTOR	1	
L6001	VLP0074	COIL	1		Q4601	2SD1819A	TRANSISTOR	1	
L6005	VLQ0599J331	COIL H	1		Q6001	2SD1991A	TRANSISTOR	1	
L7003	VLQ0599J1R0	COIL 1UH	1		Q6002	MSB709-R	TRANSISTOR	1	
L7004	VLQ0599J680	COIL	1		Q6004,05	2SB1321-R	TRANSISTOR	2	
L7005	VLQ0599J1R0	COIL 1UH	1		Q7301	2SD1820-S	TRANSISTOR	1	
L7006	VLQ0599J680	COIL	1		Q7304	2SD1820	TRANSISTOR	1	
L7301	ELESQ102KA	COIL 1000UH	1		Q7305	MSD601	TRANSISTOR	1	
L8002	ELESQ101KA	COIL 100UH	1		Q7306	2SC2404-C	TRANSISTOR	1	
L8003	ELESQ221KA	COIL 220UH	1						
L8004	VLQ0188J470	COIL 47UH	1						
P1001	VJS3537A010G	CONNECTOR (FEMALE) 10P	1		QR303	MNR2404	TRANSISTOR-RESISTOR	1	
P2001	VJP1232T	CONNECTOR (MALE) 5P	1		QR306	MNR1404	TRANSISTOR-RESISTOR	1	
P2001	VJS1738T	CONNECTOR (FEMALE)	1		QR701-03	UN5213	TRANSISTOR-RESISTOR	3	
P2002	VJS3537A015G	CONNECTOR (FEMALE) 15P	1		QR704,05	XN4212	TRANSISTOR-TRANSISTOR	2	
P2003	VJP3502	CONNECTOR (MALE)	1		QR706	DTC363EK	TRANSISTOR-RESISTOR	1	
P2503	VJS3482	CONNECTOR (FEMALE)	1		QR707-09	XN4213	TRANSISTOR-RESISTOR	3	
P2902	VJS1738T	CONNECTOR (FEMALE)	1		QR711,12	UN5213	TRANSISTOR-RESISTOR	2	
P3001	VJS3537A020G	CONNECTOR (FEMALE) 20P	1		QR715	UN5213	TRANSISTOR-RESISTOR	1	
P4001	VJS2331	CONNECTOR (FEMALE)	1		QR717	UN5213	TRANSISTOR-RESISTOR	1	
P4002	VJP1230T	CONNECTOR (MALE) 3P	1		QR804	MNR2404	TRANSISTOR-RESISTOR	1	
P4002	VJS1230T	CONNECTOR (FEMALE)	1		QR805,06	MNR1404	TRANSISTOR-RESISTOR	2	
P6001	VJS3537A025G	CONNECTOR (FEMALE) 25P	1		QR2001	UN2113T	TRANSISTOR-RESISTOR	1	
P6002	VJS3537A012G	CONNECTOR (FEMALE) 12P	1		QR2002	UN2114	TRANSISTOR-RESISTOR	1	
P6003	VJP1242T	CONNECTOR (MALE) 2P	1		QR2003	XN1213	TRANSISTOR-TRANSISTOR	1	
P6004	VJS3537A013G	CONNECTOR (FEMALE) 13P	1		QR2004	UN2112T	TRANSISTOR-RESISTOR	1	
					QR3001	UN2111T	TRANSISTOR-RESISTOR	1	
					QR3002,03	DTC363EK	TRANSISTOR-RESISTOR	2	
					QR3005	UN2212T	TRANSISTOR-RESISTOR	1	
					QR4001,02	UN2213T	TRANSISTOR-RESISTOR	2	
FK4001-03	VJR0757B018T	CONNECTOR	3		QR4508,09	UN5113	TRANSISTOR-RESISTOR	2	
					QR4510	UN5212	TRANSISTOR-RESISTOR	1	
					QR4602	UN5111	TRANSISTOR-RESISTOR	1	
PP801	VJP3043A005W	CONNECTOR (MALE) 5P	1		QR4603	UN5213	TRANSISTOR-RESISTOR	1	
PP802	VJP3043A003W	CONNECTOR (MALE) 3P	1		QR6001	XN1211	TRANSISTOR-RESISTOR	1	
PP803	VJP3043A007W	CONNECTOR (MALE) 7P	1		QR6003	UN2211T	TRANSISTOR-RESISTOR	1	
PP3001	VJP3044G009W	CONNECTOR (MALE) 9P	1		QR6004	UN2212T	TRANSISTOR-RESISTOR	1	
PP3002	VJP3044G012W	CONNECTOR (MALE) 12P	1		QR7301,02	UN5213	TRANSISTOR-RESISTOR	2	
PP3003	VJP3044G006W	CONNECTOR (MALE) 6P	1		QR7312-14	UN5211	TRANSISTOR-RESISTOR	3	
PP7001	VJP3043A007W	CONNECTOR (MALE) 7P	1		QR7315,16	UN5213	TRANSISTOR-RESISTOR	2	
PP7002-04	VJP3043A005W	CONNECTOR (MALE) 5P	3		QR7317	XN4213	TRANSISTOR-RESISTOR	1	
PP7005	VJP3043A006W	CONNECTOR (MALE) 6P	1		QR7601	UN5213	TRANSISTOR-RESISTOR	1	
PS301	VJS3044F009W	CONNECTOR (FEMALE) 9P	1		R304	ERJ6GMZOR00	M.RESISTOR 1/10W 0	1	
PS302	VJS3044F012W	CONNECTOR (FEMALE) 12P	1		R307	ERJ6GEYJ472	M.RESISTOR CH 1/10W 4.7K	1	
PS303	VJS3044F006W	CONNECTOR (FEMALE) 6P	1		R308	ERJ6GMJ472	M.RESISTOR CH 1/10W 4.7K	1	
PS701-03	VJS3043B005W	CONNECTOR (FEMALE) 5P	3		R310	ERJ6GMJ272	M.RESISTOR CH 1/10W 2.7K	1	
PS704	VJS3043B007W	CONNECTOR (FEMALE) 7P	1		R312	ERJ6GMJ473	M.RESISTOR CH 1/10W 47K	1	
PS801	VJS3043B005W	CONNECTOR (FEMALE) 5P	1		R315	ERJ6GMJ393	M.RESISTOR CH 1/10W 39K	1	
PS802	VJS3043B003W	CONNECTOR (FEMALE) 3P	1		R316	ERJ6GMJ392	M.RESISTOR CH 1/10W 3.9K	1	
PS803	VJS3043B007W	CONNECTOR (FEMALE) 7P	1		R318,19	ERJ6GMJ103	M.RESISTOR CH 1/10W 10K	2	
PS7301,02	VJR0477	PACK PIN	2		R322	ERJ6GMJ332	M.RESISTOR CH 1/10W 3.3K	1	
					R327	ERJ6GEYK125	M.RESISTOR CH 1/10W 1.25K	1	
Q703	MSD601-S	TRANSISTOR	1		R701	ERJ3GEYJ682	M.RESISTOR CH 1/16W 6.8K	1	
Q712	2SD1996-R	TRANSISTOR	1		R702	ERJ3GEYJ222	M.RESISTOR CH 1/16W 2.2K	1	
Q713	2SD1979-S	TRANSISTOR	1		R703	ERJ3GEYJ183	M.RESISTOR CH 1/16W 18K	1	
Q714	2SD1210-R	TRANSISTOR	1		R704	ERJ3GEYJ152	M.RESISTOR CH 1/16W 1.5K	1	
Q715	2SD1820	TRANSISTOR	1		R705	ERJ3GEYJ222	M.RESISTOR CH 1/16W 2.2K	1	
Q716	2SC3931-C	TRANSISTOR	1		R706	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	1	
Q717	2SC2377	TRANSISTOR	1		R707	ERJ3GEYJ272	M.RESISTOR CH 1/16W 2.7K	1	
Q771	MSD601-S	TRANSISTOR	1		R709	ERJ3GEYJ183	M.RESISTOR CH 1/16W 18K	1	
Q1001	MSD1320	TRANSISTOR	1		R710	ERJ3GEYJ122	M.RESISTOR CH 1/16W 1.2K	1	
Q3001,02	MSD601-R	TRANSISTOR	2		R712	ERJ3GEYJ105	M.RESISTOR CH 1/16W 1M	1	
Q3003	MSB709-R	TRANSISTOR	1		R713	ERJ3GEYJ104	M.RESISTOR CH 1/16W 180K	1	
					R714	ERJ3GEYJ154	M.RESISTOR CH 1/16W 150K	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks	Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
R715	ERJ3GEYJ101	M.RESISTOR CH 1/16W 100	1		R2003	ERX1S1R8	M.RESISTOR 1W 1.8	1	
R716	ERJ6GEYJ102	M.RESISTOR CH 1/10W 1K	1		R2004-06	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	3	
R717	ERJ3GEYJ121	M.RESISTOR CH 1/16W 120	1		R2007,08	ERJ6GMYJ392	M.RESISTOR CH 1/10W 3.9K	2	
R718	ERJ3GEYJ470	M.RESISTOR CH 1/16W 47	1		R2009	ERX12SJR47	M.RESISTOR 1/12W 0.47U	1	
R720	ERJ3GEYJ102	M.RESISTOR CH 1/16W 1K	1		R2010	ERDS2TJ560	C.RESISTOR 1/4W 56	1	
R721-23	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	3		R2011,12	ERJ6GMYJ105	M.RESISTOR CH 1/10W 1M	2	
R724	VRE0040E471	M.RESISTOR CH 1/10W 470	1		R2013	ERDS2TJ681	C.RESISTOR 1/4W 680	1	
R725	ERJ3GEYJ271	M.RESISTOR CH 1/16W 270	1		R2014	ERJ6GMYG821	M.RESISTOR CH 1/10W 820	1	
R726	ERJ6GEYJ102	M.RESISTOR CH 1/10W 1K	1		R2015,16	ERDS2TJ560	C.RESISTOR 1/4W 56	2	
R727	ERJ3GEYJ101	M.RESISTOR CH 1/16W 100	1		R2017	ERDS1TJ561	C.RESISTOR 1/2W 560	1	
R728	ERJ3GEYJ152	M.RESISTOR CH 1/16W 1.5K	1		R2018	ERJ6GMYJ222	M.RESISTOR CH 1/10W 2.2K	1	
R729-32	ERJ3GEYJ223	M.RESISTOR CH 1/16W 22K	4		R2019	ERJ6GMYG432	M.RESISTOR CH 1/10W 4.3K	1	
R733	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	1		R2020	ERJ6GMYG473	M.RESISTOR CH 1/10W 47K	1	
R734	ERJ3GEYJ562	M.RESISTOR CH 1/16W 5.6K	1		R2021	ERJ6GMYJ104	M.RESISTOR CH 1/10W 100K	1	
R735	ERJ3GEYJ223	M.RESISTOR CH 1/16W 22K	1		R2022	ERJ6GMYJ683	M.RESISTOR CH 1/10W 68K	1	
R736	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	1		R2023	ERJ6GMYJ333	M.RESISTOR CH 1/10W 33K	1	
R737	ERJ3GEYJ223	M.RESISTOR CH 1/16W 22K	1		R2024	ERJ6GMYJ563	M.RESISTOR CH 1/10W 56K	1	
R738	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	1		R2025	ERJ6GMYJ682	M.RESISTOR CH 1/10W 6.8K	1	
R748	VRE0040E151	M.RESISTOR CH 1/10W 150	1		R2026	ERJ6GMYJ684	M.RESISTOR CH 1/10W 680K	1	
R751,52	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	2		R2027,28	ERJ6GMYJ223	M.RESISTOR CH 1/10W 22K	2	
R753	ERJ3GEYJ223	M.RESISTOR CH 1/16W 22K	1		R2029	ERJ6GMYJ272	M.RESISTOR CH 1/10W 2.7K	1	
R756	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	1		R2031	ERJ6GMYJ244	M.RESISTOR CH 1/10W 220K	1	
R758	ERJ3GEYJ102	M.RESISTOR CH 1/16W 1K	1		R2032	ERJ6GMYG103	M.RESISTOR CH 1/10W 10K	1	
R759	ERJ3GEYJ222	M.RESISTOR CH 1/16W 2.2K	1		R2033	ERJ6GMYG133	M.RESISTOR CH 1/10W 13K	1	
R760	ERJ3GEYJ562	M.RESISTOR CH 1/16W 5.6K	1		R2034	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	1	
R761	ERJ3GEYJ472	M.RESISTOR CH 1/16W 4.7K	1		R2035	ERJ6GMYJ105	M.RESISTOR CH 1/10W 1M	1	
R763,64	ERJ3GEYJ272	M.RESISTOR CH 1/16W 2.7K	2		R2036,37	ERJ6GMYJ472	M.RESISTOR CH 1/10W 4.7K	2	
R765	ERJ3GEYJ682	M.RESISTOR CH 1/16W 6.8K	1		R2038	ERJ6GMYJ683	M.RESISTOR CH 1/10W 68K	1	
R766	ERJ3GEYJ152	M.RESISTOR CH 1/16W 1.5K	1		R2039	ERJ6GMYJ472	M.RESISTOR CH 1/10W 4.7K	1	
R767	ERJ3GEYJ332	M.RESISTOR CH 1/16W 3.3K	1		R2040	ERJ6GMYJ332	M.RESISTOR CH 1/10W 3.3K	1	
R768	ERJ3GEYJ122	M.RESISTOR CH 1/16W 1.2K	1		R2041	ERJ6GMYJ221	M.RESISTOR CH 1/10W 220	1	
R769	ERJ3GEYJ681	M.RESISTOR CH 1/16W 680	1		R2042,43	ERJ6GMYJ223	M.RESISTOR CH 1/10W 22K	2	
R770,71	ERJ3GEYJ223	M.RESISTOR CH 1/16W 22K	2		R2044	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	1	
R772	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	1		R2045	ERJ6GMYJ104	M.RESISTOR CH 1/10W 100K	1	
R773	ERJ3GEYJ472	M.RESISTOR CH 1/16W 4.7K	1		R2046	ERJ6GMYG273	M.RESISTOR CH 1/10W 27K	1	
R774	ERJ3GEYJ562	M.RESISTOR CH 1/16W 5.6K	1		R2047	ERJ6GMYJ104	M.RESISTOR CH 1/10W 100K	1	
R775	ERJ3GEYJ101	M.RESISTOR CH 1/16W 100	1		R2048	ERJ6GMYG124	M.RESISTOR CH 1/10W 120K	1	
R776	ERJ3GEYJ472	M.RESISTOR CH 1/16W 4.7K	1		R2050	ERJ6GMYJ683	M.RESISTOR CH 1/10W 68K	1	
R777	ERJ6GEYJ821	M.RESISTOR CH 1/10W 820	1		R2051	ERJ6GMYJ392	M.RESISTOR CH 1/10W 3.9K	1	
R778	ERJ6GEYJ122	M.RESISTOR CH 1/10W 1.2K	1		R2053,54	ERJ6GMYJ222	M.RESISTOR CH 1/10W 2.2K	2	
R779	ERJ3GEYJ181	M.RESISTOR CH 1/16W 180	1		R2055	ERJ6GMYJ471	M.RESISTOR CH 1/10W 470	1	
R792	ERJ3GEYJ120	M.RESISTOR CH 1/16W 12	1		R2056,57	ERJ6GMYJ822	M.RESISTOR CH 1/10W 8.2K	2	
R793	ERJ3GEYJ102	M.RESISTOR CH 1/16W 1K	1		R2060	ERDS2TJ332	C.RESISTOR 1/4W 3.3K	1	
R794	ERJ6GEYJ392	M.RESISTOR CH 1/10W 3.9K	1		R3001	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	1	
R813	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	1		R3002	ERJ6GMYJ222	M.RESISTOR CH 1/10W 2.2K	1	
R814	ERJ6GMYJ393	M.RESISTOR CH 1/10W 39K	1		R3003	ERJ6GMYJ103	M.RESISTOR CH 1/10W 10K	1	
R815	ERJ6GMYJ821	M.RESISTOR CH 1/10W 820	1		R3004	ERJ6GMYJ272	M.RESISTOR CH 1/10W 2.7K	1	
R816	ERJ6GMYJ471	M.RESISTOR CH 1/10W 470	1		R3005	ERJ6GMYJ332	M.RESISTOR CH 1/10W 3.3K	1	
R817	ERJ6GMYJ182	M.RESISTOR CH 1/10W 1.8K	1		R3006	ERDS2TJ471	C.RESISTOR 1/4W 470	1	
R818	ERJ6GMYJ681	M.RESISTOR CH 1/10W 680	1		R3007	ERJ6GMYJ222	M.RESISTOR CH 1/10W 2.2K	1	
R819	ERJ6GMYJ272	M.RESISTOR CH 1/10W 2.7K	1		R3008	ERJ6GMYJ681	M.RESISTOR CH 1/10W 680	1	
R820,21	ERJ6GMYJ122	M.RESISTOR CH 1/10W 1.2K	2		R3009	ERJ6GMYJ222	M.RESISTOR CH 1/10W 2.2K	1	
R822	ERJ6GMYJ103	M.RESISTOR CH 1/10W 10K	1		R3010	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	1	
R823,24	ERJ6GMYJ152	M.RESISTOR CH 1/10W 1.5K	2		R3011	ERJ6GMYJ561	M.RESISTOR CH 1/10W 560	1	
R827	ERJ6GMYJ122	M.RESISTOR CH 1/10W 1.2K	1		R3012,13	ERJ6GMYJ473	M.RESISTOR CH 1/10W 47K	2	
R828	ERJ6GMYJ271	M.RESISTOR CH 1/10W 270	1		R3014	ERJ6GMYJ223	M.RESISTOR CH 1/10W 22K	1	
R829	ERJ6GMYJ122	M.RESISTOR CH 1/10W 1.2K	1		R3015,16	ERJ6GMYJ561	M.RESISTOR CH 1/10W 560	2	
R830	ERJ6GMYJ271	M.RESISTOR CH 1/10W 270	1		R3017	ERJ6GMYJ391	M.RESISTOR CH 1/10W 390	1	
R831	ERJ6GMYJ681	M.RESISTOR CH 1/10W 680	1		R3018	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	1	
R832	ERJ6GMYJ154	M.RESISTOR CH 1/10W 150K	1		R3019,20	ERJ6GMYJ821	M.RESISTOR CH 1/10W 820	2	
R833	ERJ6GMYJ204	M.RESISTOR CH 1/10W 200K	1		R3021	ERJ6GMYJ122	M.RESISTOR CH 1/10W 1.2K	1	
R834	ERJ6GMYJ153	M.RESISTOR CH 1/10W 15K	1		R3022	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	1	
R835	ERJ6GMYJ103	M.RESISTOR CH 1/10W 10K	1		R3023	ERJ6GMYJ103	M.RESISTOR CH 1/10W 10K	1	
R836	ERJ6GMYJ154	M.RESISTOR CH 1/10W 150K	1		R3024	ERJ6GMYJ332	M.RESISTOR CH 1/10W 3.3K	1	
R848	ERJ6GMYJ222	M.RESISTOR CH 1/10W 2.2K	1		R3025	ERJ6GMYJ152	M.RESISTOR CH 1/10W 1.5K	1	
R849	ERJ6GMYJ473	M.RESISTOR CH 1/10W 47K	1		R3026,27	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	2	
R850	ERJ6GMYJ563	M.RESISTOR CH 1/10W 56K	1		R3028	ERJ6GMYJ471	M.RESISTOR CH 1/10W 470	1	
R853	ERJ6GMYJ473	M.RESISTOR CH 1/10W 47K	1		R3029	ERDS2TJ103	C.RESISTOR 1/4W 10K	1	
R855	ERJ6GMYJ152	M.RESISTOR CH 1/10W 1.5K	1		R3030	ERJ6GMYJ103	M.RESISTOR CH 1/10W 10K	1	
R857	ERJ6GMYJ101	M.RESISTOR CH 1/10W 100	1		R3031	ERJ6GMYJ152	M.RESISTOR CH 1/10W 1.5K	1	
R858	ERJ6GMYJ561	M.RESISTOR CH 1/10W 560	1		R3032	ERJ6GMYJ561	M.RESISTOR CH 1/10W 560	1	
R859	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	1		R3033	ERJ6GMYJ223	M.RESISTOR CH 1/10W 22K	1	
R1001	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	1		R3035,36	ERJ6GMYJ223	M.RESISTOR CH 1/10W 22K	2	
R2001	ERJ6GMYG512	M.RESISTOR CH 1/10W 5.1K	1		R3037	ERJ6GMYJ222	M.RESISTOR CH 1/10W 2.2K	1	
R2002	ERJ6GMYG913	M.RESISTOR CH 1/10W 91K	1		R3038	ERJ6GMYJ102	M.RESISTOR CH 1/10W 1K	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
R3906	ERJ6GMJ750	M.RESISTOR CH 1/10W 75	1	
R3907	ERJ6GMJ102	M.RESISTOR CH 1/10W 1K	1	
R3909	ERDS2TJ393	C.RESISTOR 1/4W 39K	1	
R3912	ERDS2TJ393	C.RESISTOR 1/4W 39K	1	
R3913	ERJ6GMJ391	M.RESISTOR CH 1/10W 390	1	
R3914	ERJ6GMJ102	M.RESISTOR CH 1/10W 1K	1	
R3915	ERJ6GMJ750	M.RESISTOR CH 1/10W 75	1	
R3917	ERJ6GMZOR00	M.RESISTOR 1/10W 0	1	
R3919	ERJ6GMJ391	M.RESISTOR CH 1/10W 390	1	
R3920	ERJ6GMZOR00	M.RESISTOR 1/10W 0	1	
R4001	ERJ6GMJ332	M.RESISTOR CH 1/10W 3.3K	1	
R4002	ERJ6GMJ223	M.RESISTOR CH 1/10W 22K	1	
R4003	ERJ6GMJ392	M.RESISTOR CH 1/10W 3.9K	1	
R4004	ERJ6GMJ183	M.RESISTOR CH 1/10W 18K	1	
R4005	ERJ6GMJ823	M.RESISTOR CH 1/10W 82K	1	
R4006	ERJ6GMJ273	M.RESISTOR CH 1/10W 27K	1	
R4007	ERJ6GMJ683	M.RESISTOR CH 1/10W 68K	1	
R4008	ERJ6GMJ823	M.RESISTOR CH 1/10W 82K	1	
R4009	ERJ6GMJ100	M.RESISTOR CH 1/10W 10	1	
R4010,11	ERJ6GMJ823	M.RESISTOR CH 1/10W 82K	2	
R4014	ERJ6GMJ562	M.RESISTOR CH 1/10W 5.6K	1	
R4018	ERJ6GMJ333	M.RESISTOR CH 1/10W 33K	1	
R4501,02	ERJ3GEYOR00	M.RESISTOR CH 1/16W 0	2	
R4503	VRE0071E36C	M.RESISTOR CH 1/10W	1	
R4506,07	ERJ3GEYJ473	M.RESISTOR CH 1/16W 47K	2	
R4508	ERJ3GEYG224	M.RESISTOR CH 1/16W 220K	1	
R4509	VRE0071E622	M.RESISTOR CH 1/10W	1	
R4511	ERJ3GEY273	M.RESISTOR CH 1/16W 27K	1	
R4512	VRE0071E153	M.RESISTOR CH 1/10W	1	
R4513	ERJ3GEYG103	M.RESISTOR CH 1/16W 10K	1	
R4514	ERJ3GEYJ223	M.RESISTOR CH 1/16W 22K	1	
R4518,19	ERJ3GEYOR00	M.RESISTOR CH 1/16W 0	2	
R4522	ERJ3GEYJ225	M.RESISTOR CH 1/16W 2.2M	1	
R4527	VRE0071E333	M.RESISTOR CH 1/10W	1	
R4528	VRE0071E153	M.RESISTOR CH 1/10W	1	
R4529	ERJ3GEYG562	M.RESISTOR CH 1/16W 5.6K	1	
R4530	ERJ3GEYJ334	M.RESISTOR CH 1/16W 330K	1	
R4534	ERJ3GEYJ472	M.RESISTOR CH 1/16W 4.7K	1	
R4535	ERJ3GEYJ104	M.RESISTOR CH 1/16W 100K	1	
R4539	ERJ3GEYJ104	M.RESISTOR CH 1/16W 100K	1	
R4541	ERJ3GEYJ152	M.RESISTOR CH 1/16W 1.5K	1	
R4542	ERJ3GEYJ222	M.RESISTOR CH 1/16W 2.2K	1	
R4543	ERJ3GEYJ472	M.RESISTOR CH 1/16W 4.7K	1	
R4551,52	ERJ3GEYJ393	M.RESISTOR CH 1/16W 39K	2	
R4553,54	ERJ3GEYJ273	M.RESISTOR CH 1/16W 27K	2	
R4558	ERJ3GEYG224	M.RESISTOR CH 1/16W 220K	1	
R4561	ERJ3GEYG273	M.RESISTOR CH 1/16W 27K	1	
R4562	VRE0034E123	M.RESISTOR CH 1/10W 12K	1	
R4563	ERJ3GEYG272	M.RESISTOR CH 1/16W 2.7K	1	
R4568,69	ERJ3GEYJ273	M.RESISTOR CH 1/16W 27K	2	
R4572	ERJ3GEYJ473	M.RESISTOR CH 1/16W 47K	1	
R4573	ERJ3GEYJ152	M.RESISTOR CH 1/16W 1.5K	1	
R4577	ERJ3GEYJ473	M.RESISTOR CH 1/16W 47K	1	
R4578	VRE0071E473	M.RESISTOR CH 1/10W 47K	1	
R4581	ERJ3GEYJ104	M.RESISTOR CH 1/16W 100K	1	
R4583	ERJ3GEYJ102	M.RESISTOR CH 1/16W 1K	1	
R4584	ERJ3GEYJ152	M.RESISTOR CH 1/16W 1.5K	1	
R4585	ERJ3GEYOR00	M.RESISTOR CH 1/16W 0	1	
R4586	ERJ3GEYJ152	M.RESISTOR CH 1/16W 1.5K	1	
R4587,88	ERJ3GEYJ273	M.RESISTOR CH 1/16W 27K	2	
R4591	ERJ3GEYJ473	M.RESISTOR CH 1/16W 47K	1	
R4592	ERJ3GEYJ563	M.RESISTOR CH 1/16W 56K	1	
R4593	ERJ3GEYJ472	M.RESISTOR CH 1/16W 4.7K	1	
R4594	ERJ3GEYJ473	M.RESISTOR CH 1/16W 47K	1	
R4596	ERJ3GEYG473	M.RESISTOR CH 1/16W 47K	1	
R4597	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	1	
R4598,99	ERJ3GEYG104	M.RESISTOR CH 1/16W 100K	2	
R4603	ERJ3GEY183	M.RESISTOR CH 1/16W 18K	1	
R4606	VRE0071E562	M.RESISTOR	1	
R4610	ERJ3GEYJ473	M.RESISTOR CH 1/16W 47K	1	
R4611	ERJ3GEYJ101	M.RESISTOR CH 1/16W 100	1	
R4612	VRE0071E331	M.RESISTOR CH 1/10W	1	
R4613	ERJ3GEYG394	M.RESISTOR CH 1/16W 390K	1	
R4615	VRE0071E133	M.RESISTOR CH 1/10W	1	
R4616	ERJ3GEYJ105	M.RESISTOR CH 1/16W 1M	1	

Ref.No.	Part No.	Part Name & Description	Pcs	Remarks
R4649	ERJ3GEYJ470	M.RESISTOR CH 1/16W 47	1	
R4651	ERJ3GEYJ471	M.RESISTOR CH 1/16W 470	1	
R4653	ERJ3GEYJ821	M.RESISTOR CH 1/16W 820	1	
R4654	ERJ3GEYJ223	M.RESISTOR CH 1/16W 22K	1	
R4655	ERJ3GEYJ562	M.RESISTOR CH 1/16W 5.6K	1	
R4656	ERJ3GEYG243	M.RESISTOR CH 1/16W 24K	1	
R4657	ERJ3GEYJ392	M.RESISTOR CH 1/16W 3.9K	1	
R4666	ERJ3GEYJ471	M.RESISTOR CH 1/16W 470	1	
R4670	ERJ3GEYJ822	M.RESISTOR CH 1/16W 8.2K	1	
R4671	ERJ3GEYOR00	M.RESISTOR CH 1/16W 0	1	
R6001	ERJ6GMJ103	M.RESISTOR CH 1/10W 10K	1	
R6002	ERJ6GMVG272	M.RESISTOR CH 1/10W 2.7K	1	
R6004	ERJ6GMJ102	M.RESISTOR CH 1/10W 1K	1	
R6005-07	ERJ6GMJ333	M.RESISTOR CH 1/10W 33K	3	
R6008	ERJ6GMJ272	M.RESISTOR CH 1/10W 2.7K	1	
R6009-11	ERJ6GMJ102	M.RESISTOR CH 1/10W 1K	3	
R6012	ERJ6GMJ272	M.RESISTOR CH 1/10W 2.7K	1	
R6013	EROS2CHG2000	M.RESISTOR 1/4W 200	1	
R6014,15	ERJ6GMVG223	M.RESISTOR CH 1/10W 22K	2	
R6016	ERJ6GMJ103	M.RESISTOR CH 1/10W 10K	1	
R6017	ERJ6GMJ271	M.RESISTOR CH 1/10W 270	1	
R6018	ERJ6GMJ683	M.RESISTOR CH 1/10W 68K	1	
R6019	ERJ6GMJ103	M.RESISTOR CH 1/10W 10K	1	
R6020	ERJ6GMJ222	M.RESISTOR CH 1/10W 2.2K	1	
R6021	ERJ6GMJ103	M.RESISTOR CH 1/10W 10K	1	
R6022	ERJ6GMJ101	M.RESISTOR CH 1/10W 100	1	
R6023	ERJ6GMJ104	M.RESISTOR CH 1/10W 100K	1	
R6024-29	ERJ6GMJ102	M.RESISTOR CH 1/10W 1K	6	
R6030,31	ERJ6GMJ103	M.RESISTOR CH 1/10W 10K	2	
R6032,33	ERJ6GMJ272	M.RESISTOR CH 1/10W 2.7K	2	
R6034,35	ERJ6GMJ221	M.RESISTOR CH 1/10W 220	2	
R6036	ERJ6GMJ104	M.RESISTOR CH 1/10W 100K	1	
R6037	ERJ6GMJ224	M.RESISTOR CH 1/10W 220K	1	
R6038	ERJ6GMJ223	M.RESISTOR CH 1/10W 22K	1	
R6039	ERJ6GMJ183	M.RESISTOR CH 1/10W 18K	1	
R6040	ERJ6GMJ333	M.RESISTOR CH 1/10W 33K	1	
R6042	ERJ6GMJ103	M.RESISTOR CH 1/10W 10K	1	
R6043	ERJ6GMJ332	M.RESISTOR CH 1/10W 3.3K	1	
R6044	ERJ6GMJ222	M.RESISTOR CH 1/10W 2.2K	1	
R6048	ERJ6GMJ332	M.RESISTOR CH 1/10W 3.3K	1	
R6049	ERJ6GMJ152	M.RESISTOR CH 1/10W 1.5K	1	
R6050	ERJ6GMJ332	M.RESISTOR CH 1/10W 3.3K	1	
R6051	ERJ6GMJ472	M.RESISTOR CH 1/10W 4.7K	1	
R7001,02	ERJ6GMJ151	M.RESISTOR CH 1/10W 150	2	
R7004	ERJ6GMJ472	M.RESISTOR CH 1/10W 4.7K	1	
R7302	ERJ3GEYJ392	M.RESISTOR CH 1/16W 3.9K	1	
R7303	ERJ3GEYJ182	M.RESISTOR CH 1/16W 1.8K	1	
R7304	ERJ3GEYJ392	M.RESISTOR CH 1/16W 3.9K	1	
R7305	ERJ3GEYJ822	M.RESISTOR CH 1/16W 8.2K	1	
R7306	ERJ3GEYJ471	M.RESISTOR CH 1/16W 470	1	
R7307	ERJ3GEYJ104	M.RESISTOR CH 1/16W 100K	1	
R7308	ERJ3GEYJ273	M.RESISTOR CH 1/16W 27K	1	
R7309	ERDS2TJ102	C.RESISTOR 1/4W 1K	1	
R7310	ERJ3GEYJ474	M.RESISTOR CH 1/16W 470K	1	
R7311	ERJ3GEYJ562	M.RESISTOR CH 1/16W 5.6K	1	
R7312	ERJ3GEYJ563	M.RESISTOR CH 1/16W 56K	1	
R7313	ERJ3GEYJ824	M.RESISTOR CH 1/16W 820K	1	
R7314,15	ERJ3GEYJ224	M.RESISTOR CH 1/16W 220K	2	
R7316	ERJ3GEYJ473	M.RESISTOR CH 1/16W 47K	1	
R7317	ERJ3GEYJ393	M.RESISTOR CH 1/16W 39K	1	
R7318	ERJ3GEYJ153	M.RESISTOR CH 1/16W 15K	1	
R7321	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	1	
R7322	ERJ3GEYJ102	M.RESISTOR CH 1/16W 1K	1	
R7323	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	1	
R7324,25	ERJ3GEYJ271	M.RESISTOR CH 1/16W 270	2	
R7329	ERJ3GEYJ102	M.RESISTOR CH 1/16W 1K	1	
R7330	ERJ3GEYJ332	M.RESISTOR CH 1/16W 3.3K	1	
R7334-37	ERJ3GEYJ471	M.RESISTOR CH 1/16W 470	4	
R7338	ERJ3GEYJ182	M.RESISTOR CH 1/16W 1.8K	1	
R7339	ERJ3GEYJ330	M.RESISTOR CH 1/16W 33	1	
R7340	ERJ3GEYJ152	M.RESISTOR CH 1/16W 1.5K	1	
R7341	ERJ3GEYJ681	M.RESISTOR CH 1/16W 680	1	
R7342	ERJ3GEYJ103	M.RESISTOR CH 1/16W 10K	1	
R7345	ERJ3GEYJ182	M.RESISTOR CH 1/16W 1.8K	1	
R7346	ERJ3GEYJ221	M.RESISTOR CH 1/16W 220	1	