

12 REPLACEMENT PARTS LISTS

BEFORE REPLACING PARTS, READ THE FOLLOWING:

12.1. REPLACEMENT NOTES

12.1.1. General Notes

1. Use only original replacement parts:

To maintain original function and reliability of repaired units, use only original replacement parts which are listed with their part numbers in the parts list.

2. IMPORTANT SAFETY NOTICE

Components identified by the sign \triangle have special characteristics important for safety. When replacing any of these components, use only the specified parts.

3. SPECIAL NOTE

All integrated circuits and many other semiconductor devices are electrostatically sensitive and therefore require the special handling techniques described under the "ELECTROSTATICALLY SENSITIVE (ES) DEVICES" section of this service manual.

4. Parts with no Ref. No. in "EXPLODED VIEW" are not supplied. And some Ref. No. will be skipped. Be sure to make your orders of replacement parts according to the parts list.

5. Parts different in shape or size may be used. However, only interchangeable parts will be supplied as service replacement parts.

6. Parts with mark "VED" in the Remarks column are supplied from VED. Others are supplied from MKE.

12.1.2. Mechanical Replacement Notes

1. Section No. of parts shown in Exploded Views are indicated in the Remarks column.

2. Abbreviation

RTL: Retention Time Limited

This indicates that the retention time is limited for this item. After the discontinuation of this item in production, it will no longer be available.

3. Cut Washers (Ref No. 409, 411, and 419) are not reusable. If removed, install a new one.

4. Head Amp C.B.A. which is located on the Lower Cylinder is supplied as a Cylinder Unit only.

However, IC3501 (AN3365SB-E1 or AN3368SB-E1) is available separately as a replacement part.

5. After replacing Mechanism Chassis Ass'y (Ref. No. 49) or Mechanism Chassis Sub Ass'y (Ref. No. 213), perform the Tape Interchangeability Adjustment procedures. Refer to "TAPE INTERCHANGEABILITY ADJUSTMENT."

12.1.3. Electrical Replacement Notes

1. Item numbers with capital letter E (Example: E1, E2,...) in the Ref. No. column are shown in the exploded views.

2. The parts with "■" mark are supplied as an unit, and their individual parts are also supplied separately.

3. Unless otherwise specified;

All resistors are in Ω , 1/4 W, $\pm 5\%$, carbon, K = 1 000 Ω , M = 1 000 k Ω .

All capacitors are in μF , P = $\mu\mu\text{F}$, $\pm 10\%$.

All coils are in μH , M = 1 000 μH , $\pm 10\%$.

4. Abbreviation

RTL: Retention Time Limited

This indicates that the retention time is limited for this item. After the discontinuation of this item in production, it will no longer be available.

NR: Non Repairable Board Ass'y

MGF CHIP: Metal Glaze Film Chip

C CHIP: Ceramic Chip

COMPLX CMP: Complex Component

W FLMPRF: Wirewound Flameproof

C.B.A.: Circuit Board Assembly

P.C.B.: Printed Circuit Board

E.S.D.: Electrostatically Sensitive Devices

5. SERVICE OF CHIP PARTS

When servicing chip parts, please use a soldering iron of less than 30 watts. Refer to "IC, TRANSISTOR AND CHIP PART INFORMATION" page.

6. The parts with "●" are 0 Ω resistor. When replacing, a wire can be substituted for a 0 Ω resistor.

7. Lamp Kit (E41) replacement note:

Lamp is supplied as a Lamp Kit only (Kit No. VULS0001) which contains Lamp, Cushions, and Explanation Sheet.

8. IC306 replacement note:

When replacing this IC, be sure to write the initial data with PC-EVR Adjustment Program.

COMPARISON CHART OF MODELS & MARKS

MODEL	MARK
PV-L750	A
-----	B
PV-L780	C
PV-L850	D

12.2. MECHANICAL REPLACEMENT PARTS LIST

12.2.1. MECHANISM PARTS ON CHASSIS

Ref. No.	Part No.	Part Name & Description	Remarks
7	VDGW0072	TAKE GEAR	1
9		CYLINDER UNIT	
	VEGS0438	(A,B)	1
	VEGS0439	(C,D)	1
10	VGLW0088	TALLY LED PANEL	3
11		UPPER CYLINDER UNIT	
	VEHW0032	(A,B)	1
	VEHW0033	(C,D)	1
12	VEMS0337	CAPSTAN UNIT	1
13	LSEM0028	FOCUS MOTOR UNIT	2
15	VFBW0085	HAND STRAP,NYLON	2
16		OPTICAL FILTER	
	VFLW0414	(A,B,C)	2
	VFLW0448	(D)	2
17	VKFW0067	EVR COVER	3
22	VMAW0642	SPRING SUPPORTER	2
23	VMBS0717	PRE-LOAD SPRING	1
29	VMDW0341	BACK UP COVER	3
30	LSEQ0551	BATTERY CATCHER UNIT	3
31	VMGW0213	FILTER RUBBER	2
32	VEMW0078	LOADING MOTOR UNIT,2W	1
33	VMAW0745	P.C.B. ANGLE	1
37	VMAW0744	MECHANISM SUPPORT ANGLE	1
40	VXYS1369	CASSETTE UP UNIT	1
44	VXDW0196	TAKEUP POST UNIT	1
45	VXDW0187	SUPPLY POST UNIT	1
48		LENS UNIT	
	VXNW0018	(A,B,C)	2
	VXNW0019	(D)	2
49	VXKS0900	MECHANISM CHASSIS ASS'Y	1 RTL
50		VCR MECHANISM CHASSIS ASS'Y	
	VXKS0897	(A,B)	2 RTL
	VXKS0899	(C,D)	2 RTL
51	VXLW0080	TENSION UNIT	1
52	VXLW0082	PINCH ARM UNIT	1
54	VXLS1124	IDLER ARM UNIT	1
55	VXPW0025	REEL TABLE UNIT	1
56	VXPW0024	REV CLUTCH	1
58	VXLW0078	TAKEUP LOADING ARM UNIT	1
59	VXLW0077	SUPPLY LOADING ARM UNIT	1
61		ELECTRONIC VIEWFINDER UNIT	
	LSYK0331	(A,C)	2
	LSYK0233	(D)	2
		COLOR ELECTRONIC VIEWFINDER UNIT	
	LSYK0369	(B)	2
67		CASSETTE COVER UNIT	
	LSYK0250	(A,B,C)	3
	LSYK0252	(D)	3
71	LSJA0276	PC CONNECTION CABLE W/PLUG	5
74		INFRARED REMOTE CONTROL UNIT	
	VSQW0038	(A,D)	5
75	LSFT0193	DRIVER SOFTWARE FD FOR WINDOWS 95/98	5
77		INSTRUCTION BOOK	
	LSQT0203	(A)	5
	LSQT0225	(B)	5
	LSQT0226	(C)	5
	LSQT0204	(D)	5
78	LSFA0009	CF CARD	5
81	VJAW0029	DC CABLE W/PLUG,6V	5
	OR VJAW0030	DC CABLE W/PLUG,6V	5
82	VJAW0039	AUDIO/VIDEO CABLE W/PLUG,0V	5
83	VPNW0050	CUSHION,PAPER	5
84	VFPW0049	BAG,POLYETHYLENE	5
85		PACKING CASE,PAPER	
	LSPG0758	(A)	5

Ref. No.	Part No.	Part Name & Description	Remarks
	LSPG0836	(B)	5
	LSPG0839	(C)	5
	LSPG0759	(D)	5
86	VPNW0051	ACCESSORY CUSHION,PAPER	5
87	VPGW0755	ACCESSORY PAD	5
88		FAN BAG	
	LSQF0203	(A)	5
	LSQF0225	(B)	5
	LSQF0226	(C)	5
	LSQF0204	(D)	5
89	VSBW0004	BATTERY UNIT	3,5
90		REMOTE CONTROL HOLDER	
	VGQ6893	(A,D)	5
92	VYCW0225	SHOULDER STRAP,POLYPROPYLENE	5
93	VYMW0009	CASSETTE ADAPTOR	5
100	VEQW0279	VCR OPERATION UNIT	4
106	VGLW0090	POWER LED PANEL	2
107	VGTW0575	EJECT KNOB	3
109	VGTW0603	TAPE CHANGE KNOB	2
111	LSGU0136	DISPLAY BUTTON	3
114		EVF DUST COVER	
	LSDL0083	(A,C,D)	4
115		SIDE CASE L,ABS RESIN	
	LSKM0351	(A)	△ 2
	LSKM0407	(B,C)	△ 2
	LSKM0352	(D)	△ 2
117	VMAW0749	TRIPOD FRAME	2
118		EVF PLATE,STEEL	
	LSMA0416	(A,C,D)	4
	VMAW0677	(B)	4
119	VMAW0750	EVF ANGLE	2
122	VMZW0685	BARRIER	3
128		MICROPHONE UNIT	
	LSXM0007	(A)	3
	LSXM0005	(B,C)	3
	LSXM0006	(D)	3
129		LIQUID CRYSTAL DISPLAY PANEL	
	LCX032AKB-8	(B)	4
130	LSEQ0555	TOP OPERATION UNIT	3
131	LSEQ0557	SIDE L FLEXIBLE PRINTED CIRCUIT UNIT	2
137		LOCK KNOB	
	VGTW0547	(B)	4
138		TOP OPERATION BUTTON	
	LSGU0138	(A,B,C)	3
	VGUW0194	(D)	3
140		LCD MASK	
	LSKF0288	(B)	4
148		EVF CASE A,ABS RESIN	
	LSKM0267	(A,C)	△ 4
	LSKM0353	(B)	△ 4
	LSKM0303	(D)	△ 4
149		EVF CASE B,ABS RESIN	
	LSKM0268	(A,C)	△ 4
	LSKM0354	(B)	△ 4
	LSKM0305	(D)	△ 4
151		SIDE CASE R,ABS RESIN	
	LSKM0346	(A,B,C)	△ 3
	LSKM0347	(D)	△ 3
156		LOCK SPRING	
	VMBW0235	(B)	4
161		CAUTION LABEL	
	LSQL0878	(A,C,D)	4
163		ESD PLATE,STEEL	
	LSSC0324	(A,C,D)	4
	VSCW0869	(B)	4
164		CAUTION LABEL	
	VQLS3464	(A,C,D)	2
170	LSGU0125	EIS BUTTON	3
182	VQLW2037	LENS LABEL	2
183	VMDW0510	ARM HOLDER	2
184	LSXA0287	SENSOR SHIELD CASE UNIT,STEEL	2
185		INFRARED PANEL	

Ref. No.	Part No.	Part Name & Description	Remarks
	VGLW0089	(A,D)	2
186	VGFW0020	LIGHT PROTECTOR	3
187	VMDW0509	HINGE R	3
188	VMRW0025	LIGHT REFLECTOR	3
192	VSCW0935	LIGHT SHEET,AL	3
194		DIGITAL SELECT KNOB	
	LSGT0038	(A,B,C)	3
	VGTW0604	(D)	3
196		EVF LABEL	
	VQLW1735	(B)	4
200	VGTW0605	PHOTO SELECT KNOB	3
203	LSXY0157	LAMP UNIT	△ 3
206	VMAW0752	STRAP ANGLE A	3
207	VMAW0753	STRAP ANGLE B	3
209	VMAW0754	GRIP ANGLE	2
211		LIQUID CRYSTAL DISPLAY PANEL UNIT	
	VXYW0210	(A,C,D)	3
	LSXY0178	(B)	3
212	LSXY0177	LEAD LIGHT PANEL UNIT	3
213	VKKS0895	MECHANISM CHASSIS SUB ASS'Y	1
214	LSMZ0213	TAPE GUIDE	3
215	LSMZ0210	GUIDE COVER	3
216	LSMZ0214	PROTECTOR	3
218	LSEK0376	CF CARD CONNECTOR UNIT	3
219	LSYK0237	LENS RING UNIT	2
221	VEMW0085	ZOOM MOTOR UNIT,300MW	2
228		BULGE CHIP	
	VMDW0357	(A,B)	1
	VMDW0374	(C,D)	1
229	VMBW0333	TAPE GUIDE SPRING	3
234	VMTW0023	LENS RUBBER	2
235		EVF LENS COVER B	
	VMDW0451	(B)	4
236		PROTECT PLATE,STEEL	
	LSKG0007	(B)	4
237		EVF LENS COVER A	
	VMDW0450	(B)	4
239	VKFS1021	BATTERY COMPARTMENT LID	5
242		LCD CUSHION	
	VMGW0204-Y	(B)	4
245	VDVW0003	CAPSTAN BELT	1
250		LIGHT CAUTION LABEL	
	LSQL0880	(A,B,C)	△ 2
	LSQL0881	(D)	△ 2
268		EYE CAP UNIT	
	LSYK0238	(A,C,D)	4
	VYKW2901	(B)	4
273	VXYW0195	REDUCTION GEARUNIT	1
274	VDGW0063	REDUCTION GEAR A	1
275	VDGW0064	REDUCTION GEAR B	1
277	VXYW0194	MAIN CAM UNIT	1
284	VEQW0294	MANUAL FOCUS VARIABLE RESISTOR UNIT	2
286	LSGT0037	LIGHT KNOB	3
290	VSCW0951	ESD PLATE L,STEEL	2
295	VMBW0306	SHUTTER SPRING	3
297	VMDW0512	LENS PIECE	2
300	VMDW0494	OPENER	1
301	LSML0126	ARM	2
305	LSWZ0008	TUBE	1
307	LSSC0329	LENS ESD PLATE,STEEL	2
309	VMDW0486	PINCH TAPE GUIDE	1
310	VXJW0095	IMPEDANCE ROLLER UNIT	1
312	VEHS0588	AUDIO CONTROL HEAD UNIT	1
313	VMLW0083	PINCH TOGGLE	1
314	VXLW0081	P5 ARM UNIT	1
316	VXLS1125	REV BRAKE ARM UNIT	1
320		MICROPHONE CASE UNIT,ABS RESIN	
	VYKW3139	(A,B,C)	3
	LSYK0351	(D)	3
321	VKFW0065	WING	3
335		LCD CASE B,ABS RESIN	

Ref. No.	Part No.	Part Name & Description	Remarks
	VKMW1798	(A,C,D)	△ 3
	LSKM0424	(B)	△ 3
352	VSCW0957	LCD SHIELD CASE,STEEL	3
355		LCD CASE A UNIT,ABS RESIN	
	LSYK0267	(A,B)	3
	LSYK0374	(C)	3
	LSYK0268	(D)	3
365	LSMP0225	CASSETTE FRAME	3
366		LCD SHAFT UNIT	
	LSXA0301	(A,B,C)	3
	LSXA0302	(D)	3
371	LSSA0002	EARTH CONTACT	1
372	LSMB0168	CONTACT SPRING	1
373	LSMA0336	CONTACT PLATE,STEINLESS	1
374		EVF PIECE	
	LSKM0270	(A,C)	4
	LSKM0301	(D)	4
375	VDGW0059	MOTOR GEAR	1
376	VSCW0873	ALUMINUM FOIL	3
377	VSCW0872	ALUMINUM FOIL	3
381		TV TUNER UNIT	
	LSSQ0184	(D)	5 RTL
382		BAG,POLYETHYLENE	
	VVPF0043	(D)	5
383		TUNER PACKING CASE,PAPER	
	LSPG0783	(D)	5

12.2.2. SCREWS AND WASHERS

Ref. No.	Part No.	Part Name & Description	Remarks
404	XQN2+BF3FXK	SCREW,STEEL	3
407	XQN16+A32	SCREW,STEEL	1
408	VHDW0124	SCREW W/WASHER,STEEL	1
409	VMXW0217	CUT WASHER,STEEL	1
410	XWGV15Z32G	POLY SLIDER WASHER	1
411	VMXW0213	CUT WASHER,STEEL	1
412	XQN2+B35	SCREW,STEEL	1
413	XQN2+A22	SCREW,STEEL	1
414	XQN14+A32	SCREW,STEEL	1
415	XQN2+B22	SCREW,STEEL	1
416	XQN14+BJ25FZ	SCREW,STEEL	1
417	XQN2+B2	SCREW,STEEL	1
419	VMX2026	CUT WASHER,STEEL	1
421	XQN16+BF4FN	SCREW,STEEL	2
423	XQN16+B3FN	SCREW,STEEL	1
469	XQN2+BF4FXK	SCREW,STEEL	3
472	VHDW0102	SCREW,STEEL	3
473	VHDW0100	SCREW,STEEL	2
481	VMBW0253	WASHER,STEEL	2
482	XQN2+CJ12FXK	SCREW,STEEL	4
483	XQN2+BJ4FXK	SCREW,STEEL	2, 4
501	XQN16+CJ5FY	SCREW,STEEL	2
502	XQN16+CJ6	SCREW,STEEL	2
504	XQN2+CF3	SCREW,STEEL	2
533	XQN2+BF5FXK	SCREW,STEEL	2, 3
586	XQN2+BJ5FXK	SCREW,STEEL	2, 3
604	XQN2+BJ8FXK	SCREW,STEEL	3
617	XQN2+BJ10FXK	SCREW,STEEL	3
620	XQN2+BJ6FXK	SCREW,STEEL	3
628	XQN16+B3FU	SCREW,STEEL	1
630	VMXW0175	WASHER,NYLON	2
632	XQN14+B3	SCREW,STEEL	1
635	XQN16+C5FU	SCREW,STEEL	1
637	XQN2+CF10FU	SCREW,STEEL	2
639	LSHD0049	SCREW,STEEL	2
640	LSHD0054	SCREW,STEEL	1

12.2.3. SERVICE FIXTURE AND TOOLS

Ref. No.	Part No.	Part Name & Description	Remarks
	VFKS002	LIGHT BOX W/CHARTS SET	
	VFKS002A	GLAY SCALE CHART	
	VFKS002B	COLOR BAR CHART	
	VFKS002C	REGISTRATION CHART	
	VFKS002D	RESOLUTION CHART	
	VFKS002Y	LIGHT BOX	
	VFKS003-N	REFLECTION CHART SET	
	VFKS003A	GLAY SCALE CHART	
	VFKS003B	COLOR BAR CHART	
	VFKS003C	REGISTRATION CHART	
	VFKS003D	RESOLUTION CHART	
	VFK1164TFWC2	WHITE CHART	VED
	VFK1164TFGS2	GRAY SCALE CHART	VED
	VFK1164TFCB2	COLOR BAR CHART	VED
	VFK1164TFCT2	CONVERSION FILTER	VED
	VFK1164LBX1	LIGHT BOX	VED
	VFK1164TCM02	COLLIMATOR (INFINITY LENS) (WITH FOCUS CHART)	VED
	VFK1164TLA01	LAMP	VED
	VFK1164TAR58	ATTACHMENT RING (58mm)	VED
	VFK1164TAR55	ATTACHMENT RING (55mm)	VED
	VFK1164TAR52	ATTACHMENT RING (52mm)	VED
	VFK1164TAR49	ATTACHMENT RING (49mm)	VED
	VFK1164TAR46	ATTACHMENT RING (46mm)	VED
	VFK1164TAR43	ATTACHMENT RING (43mm)	VED
	VFK1164TAR37	ATTACHMENT RING (37mm)	VED
	VFK1164TAR3A	ATTACHMENT RING (30.5mm)	VED
	VFK1164TAR27	ATTACHMENT RING (27mm)	VED
	VFMS0004H6C	VHS-C ALIGNMENT TAPE	
	VFMW0001C	VHS-C ALIGNMENT TAPE	
	VFK27	HEAD CLEANING STICK	
	VFKS0081	GREASE	
	LSUQ0002	GREASE	
	VFK1024	MOLYBDENE GREASE	
	VUVS0007	EXTENSION CABLE 12P	
	LSUA0020	EXTENSION CABLE 20P	
	VUVS0012	EXTENSION CABLE 22P	
	VUVS0015	EXTENSION CABLE 28P	
		TP BOARD KIT	
	LSUP0005A	TP ADJUSTMENT CABLE 40P	
	VFKW0123B	TP ADJUSTMENT PCB 40P	
	LSUP0005C	TP CLIP 36P	
	VFKW0066	A.W.B. ADJUSTMENT FIXTURE	
	VFKW0116	COLOR CHIP CHART	
	VJAW0032	AUDIO VIDEO CABLE	
	VFKW1000	CAAS KIT	
	VFKW1000A	INTERFACE BOX	
	VFKW1000B	CAMERA CONNECTING CABLE	
	VFKW1000C	9PIN RS-232C CABLE	
	VFKW1000D	25PIN RS-232C CABLE	
	VHDW0125	LOCK SCREW	
	LSEQ0557	SIDE L FPC UNIT	
	LSEQ0551	BATTERY CATCHER UNIT	
		EVF UNIT	
	LSYK0232	(A,C,D)	
		COLOR EVF UNIT	
	LSYK0234	(B)	
	LSEP8033A1	RELAY C.B.A.	

12.3. ELECTRICAL REPLACEMENT PARTS LIST

PRINTED CIRCUIT BOARD ASSEMBLY

Ref. No.	Part No.	Part Name & Description	Remarks
E1	LSEP8026A1	MAIN C.B.A.	■ E.S.D. RTL
	(A)		
E1	LSEP8026F1	MAIN C.B.A.	■ E.S.D. RTL
	(B)		
E1	LSEP8026E1	MAIN C.B.A.	■ E.S.D. RTL
	(C)		
E1	LSEP8026B1	MAIN C.B.A.	■ E.S.D. RTL
	(D)		
E8	LSEP8050A1	PC JACK C.B.A.	■ RTL
E9	LSEP8051A1	TV TUNER JACK C.B.A.	■ RTL
	(D)		
E2	LSEQ0548	CCD C.B.A.	■ E.S.D. RTL
	(A,B,C)		
E2	LSEQ0571	CCD C.B.A.	■ E.S.D. RTL
	(D)		
E3	LSEQ0558	ELECTRONIC VIEWFINDER C.B.A.	■ RTL
	(A,C,D)		
E4	LSEP8035A1	COLOR ELECTRONIC VIEWFINDER A C.B.A.	■ RTL
	(B)		
E5	VEPW1671A1	COLOR ELECTRONIC VIEWFINDER B C.B.A.	■ RTL
	(B)		
E52	LSEP8031A1	LIQUID CRYSTAL DISPLAY C.B.A.	■ RTL
	(A,B,C)		
E52	LSEP8031B1	LIQUID CRYSTAL DISPLAY C.B.A.	■ E.S.D. RTL
	(D)		
E53	LSEP8033A1	RELAY C.B.A.	■

12.3.1. MAIN C.B.A. ■

INTEGRATED CIRCUITS

Ref. No.	Part No.	Part Name & Description	Remarks
IC301	MN67324	IC, LOGIC DIGITAL SIGNAL PROCESSOR	E.S.D.
IC302	ZA4035H	IC, 2.7M D RAM FIELD MEMORY	E.S.D.
IC304	SNAHC2G240HT	IC, CMOS STANDARD LOGIC BUFFER	E.S.D.
	OR TC7W240FU	IC, CMOS STANDARD LOGIC BUFFER	E.S.D.
IC306	BR9040FV-DE2	IC, 4K EEP ROM	E.S.D.
IC309	BA10324AFVE1	IC, LINEAR HALL/IRIS AMP	
	OR LM324DB	IC, LINEAR HALL/IRIS AMP	
IC310	HD74HC244TEL	IC, CMOS STANDARD LOGIC BUFFER	E.S.D.
	OR SN74HC244PWR	IC, CMOS STANDARD LOGIC BUFFER	E.S.D.
IC311	HD74HC244TEL	IC, CMOS STANDARD LOGIC BUFFER	E.S.D.
	OR SN74HC244PWR	IC, CMOS STANDARD LOGIC BUFFER	E.S.D.
IC503	ADM3202ARU	IC, RS232C DRIVER	
IC504	MN103004KEA	IC, 32BIT MICROCONTROLLER	E.S.D.
	(A,B,C)		
	MN103004KEC	IC, 32BIT MICROCONTROLLER	E.S.D.
	(D)		
IC602	MN5293-1	IC, CMOS GATE ARRAYS TIMING GENERATOR	E.S.D.

Ref. No.	Part No.	Part Name & Description	Remarks
IC603	MN3112SA-E1	IC, CMOS STANDARD LOGIC CCD V DRIVE	E.S.D.
IC605	AN2109NFHQ	IC, LINEAR SAMPLING HOLD	
IC606	TC7S08FTE85L	IC, CMOS STANDARD LOGIC NAND GATE	E.S.D.
	OR TC7S08FTE85R	IC, CMOS STANDARD LOGIC NAND GATE	E.S.D.
	(A,B,C)		
IC701	LB1837M-TE-L	IC, LINEAR MOTOR DRIVE	
	OR LB1837MLTEL3	IC, LINEAR MOTOR DRIVE	
	OR LB1837MTEL3	IC, LINEAR MOTOR DRIVE	
IC702	LB1837M-TE-L	IC, LINEAR MOTOR DRIVE	
	OR LB1837MLTEL3	IC, LINEAR MOTOR DRIVE	
	OR LB1837MTEL3	IC, LINEAR MOTOR DRIVE	
IC1001	BA9710KV	IC, LINEAR POWER CONTROL	
IC2001	AN3897FH	IC, LINEAR CYLINDER/CAPSTAN MOTOR DRIVE CONTROL	
IC2002	UN224-TX	IC, LINER POWER TRANSISTOR MOTOR DRIVE	
IC2003	UN224-TX	IC, LINER POWER TRANSISTOR MOTOR DRIVE	
IC3001	AN2401NFH	IC, LINEAR Y/C REC/PB PROCESS	
IC3002	MN38663S	IC, CCD 1H DELAY	E.S.D.
IC3003	NUJ4053BV	IC, CMOS STANDARD LOGIC SWITCHING	E.S.D.
	OR SNLV4053APW	IC, CMOS STANDARD LOGIC SWITCHING	E.S.D.
	(D)		
IC4001	BA7757BK	IC, LINEAR AUDIO REC/PB PROCESS	
IC6001	MN101D02FWD1	IC, 8BIT MICROCONTROLLER	E.S.D.
IC6002	R3111Q391ATR	IC, LINEAR RESET	
	OR S80839ANNPT2	IC, LINEAR RESET	
	OR XC61CN3902NR	IC, LINEAR RESET	
IC6005	S3510AEFJTB	IC, PERIPHERAL MCU CLOCK IN	E.S.D.
IC6006	RH5RE45AA-T1	IC, PERIPHERAL MCU +4.5V REGULATOR	E.S.D.
	OR XC62FP4502PR	IC, PERIPHERAL MCU +4.5V REGULATOR	E.S.D.
IC6007	BA6288FS-E2	IC, LINEAR LOADING MOTOR DRIVE	
IC6203	CNB10010RL	TAKEUP REEL SENSOR	

TRANSISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
Q301	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q302	2SC3931	CHIP	
Q303	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q305	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q306	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q307	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q310	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q311	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q617	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q703	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q1001	DTA114EU	CHIP	
	OR UN5111	CHIP	
Q1002	DTA144EU	CHIP	
	OR UN5113	CHIP	
Q1003	DTA114TU	CHIP	
	OR UN5115	CHIP	

Ref. No.	Part No.	Part Name & Description	Remarks
Q1005	2SB1628-T1ZX	CHIP	
	OR 2SB1628-T1ZY	CHIP	
Q1006	MPL1-TL	CHIP	
Q1007	2SB1424T100P	CHIP	
	OR 2SB1424T100Q	CHIP	
Q1008	MPL1-TL	CHIP	
Q1009	MPL1-TL	CHIP	
Q1010	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q1011	IMX1T108	COMPLX CMP SI NPN CHIP	
	OR XN4501	COMPLX CMP SI NPN CHIP	
Q1012	2SB1073	CHIP	
	OR 2SB1386T100Q	CHIP	
	OR 2SB1386T100R	CHIP	
	(A,B)		
Q1013	2SB1585	CHIP	
	OR 2SB970	CHIP	
	(C,D)		
Q1014	2SB1073	CHIP	
	OR 2SB1386T100Q	CHIP	
	OR 2SB1386T100R	CHIP	
Q1015	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q1020	2SB1073	CHIP	
	OR 2SB1386T100Q	CHIP	
	OR 2SB1386T100R	CHIP	
Q1021	DTC124EU	CHIP	
	OR UN5212	CHIP	
Q1022	2SB1585	CHIP	
	OR 2SB970	CHIP	
Q1023	IMX1T108	COMPLX CMP SI NPN CHIP	
	OR XN4501	COMPLX CMP SI NPN CHIP	
Q1101	2SA2014-TD	CHIP	
Q1102	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q1103	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q1104	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q1105	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q1106	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q3003	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q3004	2SC3931	CHIP	
Q3005	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q3021	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q3022	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q3027	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q3028	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q3029	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q3030	DTA144EU	CHIP	
	OR UN5113	CHIP	
	(D)		
Q3031	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
	(D)		
Q4002	IMZ1T108	COMPLX CMP SI NPN/PNP CHIP	
	OR XN4601	COMPLX CMP SI NPN/PNP CHIP	
Q4003	2SC4081T106R	CHIP	

Ref. No.	Part No.	Part Name & Description	Remarks
	OR 2SD1819A	CHIP	
Q4004	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q4007	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q4008	2SD2432(R)	CHIP	
	OR 2SD602(R)	CHIP	
	OR 2SD602A(R)	CHIP	
Q4009	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q4010	2SB1585	CHIP	
	OR 2SB970	CHIP	
Q4011	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q6004	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q6005	DTC124TU	CHIP	
	OR UN5217	CHIP	
Q6006	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
	(A,D)		
Q6008	DTC124TU	CHIP	
	OR UN5217	CHIP	
Q6009	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q6010	DTC124EU	CHIP	
	OR UN5212	CHIP	
Q6011	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q6012	2SK1958	F.E.T. CHIP	
Q6013	2SC2412K1	CHIP	
	OR 2SD601A	CHIP	
Q6018	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q6021	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q6022	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	

DIODES

Ref. No.	Part No.	Part Name & Description	Remarks
D503	RD12S-T1B	ZENER CHIP 12V	
	(D)		
D504	RD12S-T1B	ZENER CHIP 12V	
	(D)		
D505	RD12S-T1B	ZENER CHIP 12V	
	(D)		
D506	RD12S-T1B	ZENER CHIP 12V	
	(D)		
D1001	RD12S-T1B	ZENER CHIP 12V	
D1002	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D1004	EP10QY03TE8L	CHIP	
D1005	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D1006	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D1007	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D1008	MA728	CHIP	
D1101	RD12S-T1B	ZENER CHIP 12V	
D1102	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D4001	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D4002	MA3120WA	ZENER CHIP 12V	
D6001	DAN202UT	CHIP	

Ref. No.	Part No.	Part Name & Description	Remarks
	OR MA142WK	CHIP	
D6005	DAP202UT	CHIP	
	OR MA142WA	CHIP	
D6008	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D6015	DA204U	CHIP	
	OR MA143	CHIP	
D6019	MA111	CHIP	
	OR 1SS355TE-17	CHIP	

RESISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
R301	ERJ3GEYJ122V	MGF CHIP 1/16W 1.2K	
R302	VRJSD3D6800	MGF CHIP +-0.5% 1/16W 680	
R303	ERJ3GEYG102V	MGF CHIP +-2% 1/16W 1K	
R304	VRJSD3D2201	MGF CHIP +-0.5% 1/16W 2.2K	
R305	VRJSD3D2201	MGF CHIP +-0.5% 1/16W 2.2K	
R306	ERJ3GEYJ391V	MGF CHIP 1/16W 390	
R307	ERJ3GEYG103V	MGF CHIP +-2% 1/16W 10K	
R308	ERJ3GEYG391V	MGF CHIP +-2% 1/16W 390	
R309	ERJ3GEYG102V	MGF CHIP +-2% 1/16W 1K	
R310	ERJ3GEYG102V	MGF CHIP +-2% 1/16W 1K	
R314	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R315	ERJ3GEYG181V	MGF CHIP +-2% 1/16W 180	
R316	ERJ3GEYJ121V	MGF CHIP 1/16W 120	
R317	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R318	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R319	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R320	ERJ3GEYJ561X	MGF CHIP 1/16W 560	
R321	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R322	ERJ3GEYJ272X	MGF CHIP 1/16W 2.7K	
R323	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R324	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R327	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R332	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R333	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(A,B,C)		
R336	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R340	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R342	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R343	ERJ3GEYJ221V	MGF CHIP 1/16W 220	
R344	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R345	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R346	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R347	ERJ3GEYJ123X	MGF CHIP 1/16W 12K	
R348	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R349	ERJ3GEYJ563V	MGF CHIP 1/16W 56K	
R350	ERJ3GEYJ822V	MGF CHIP 1/16W 8.2K	
R351	ERJ3GEYJ154V	MGF CHIP 1/16W 150K	
R352	ERJ3GEYJ823V	MGF CHIP 1/16W 82K	
R353	ERJ3GEYJ562X	MGF CHIP 1/16W 5.6K	
R355	ERJ3GEYJ334V	MGF CHIP 1/16W 330K	
R356	ERJ3GEYJ394V	MGF CHIP 1/16W 390K	
R357	ERJ3GEYJ474V	MGF CHIP 1/16W 470K	
R358	ERJ3GEYJ123X	MGF CHIP 1/16W 12K	
R359	ERJ3GEYJ123X	MGF CHIP 1/16W 12K	
R360	ERJ3GEYJ331X	MGF CHIP 1/16W 330	
R361	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R362	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R363	ERJ3GEYJ123X	MGF CHIP 1/16W 12K	
R364	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R365	ERJ3GEYK225V	MGF CHIP +-10% 1/16W 2.2M	
R366	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R367	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R368	ERJ3GEYJ273V	MGF CHIP 1/16W 27K	
R369	ERJ3GEYJ393V	MGF CHIP 1/16W 39K	
R370	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R372	ERJ3GEYJ393V	MGF CHIP 1/16W 39K	
R373	ERJ3GEYJ303V	MGF CHIP 1/16W 30K	
R374	ERJ3GEYJ822V	MGF CHIP 1/16W 8.2K	

Ref. No.	Part No.	Part Name & Description	Remarks
R375	ERJ3GEYJ333X	MGF CHIP 1/16W 33K	
R376	ERJ3GEYJ822V	MGF CHIP 1/16W 8.2K	
R377	ERJ3GEYJ333X	MGF CHIP 1/16W 33K	
R378	ERJ3GEYJ333X	MGF CHIP 1/16W 33K	
R379	ERJ3GEYJ822V	MGF CHIP 1/16W 8.2K	
R380	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R381	ERJ3GEYJ272X	MGF CHIP 1/16W 2.7K	
R382	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R383	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R384	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R385	ERJ3GEYJ221V	MGF CHIP 1/16W 220	
R386	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R387	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R388	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R389	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R390	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R391	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R393	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R394	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R395	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R397	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R402	ERJ3GEYJ472V	MGF CHIP +-2% 1/16W 4.7K	
R410	EXB24V331JX	CHIP ARRAY 330	
R411	EXB24V331JX	CHIP ARRAY 330	
R412	EXB24V331JX	CHIP ARRAY 330	
R413	EXB24V331JX	CHIP ARRAY 330	
R414	EXB24V331JX	CHIP ARRAY 330	
R415	EXB24V331JX	CHIP ARRAY 330	
R427	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R430	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R431	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R432	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R433	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R434	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R436	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R437	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R438	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R441	ERJ3GEYJ331X	MGF CHIP 1/16W 330	
R450	EXB24V473JX	CHIP ARRAY 47K	
R451	EXB24V473JX	CHIP ARRAY 47K	
R452	EXB24V473JX	CHIP ARRAY 47K	
R453	EXB24V473JX	CHIP ARRAY 47K	
R454	EXB24V473JX	CHIP ARRAY 47K	
R455	EXB24V473JX	CHIP ARRAY 47K	
R462	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R470	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R471	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R472	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R473	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R474	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R475	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R476	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R477	EXB24V473JX	CHIP ARRAY 47K	
R479	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R480	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R501	ERJ3GEYJ151V	MGF CHIP 1/16W 150	
R502	ERJ3GEYJ151V	MGF CHIP 1/16W 150	
R503	ERJ3GEYJ151V	MGF CHIP 1/16W 150	
R504	ERJ3GEYJ151V	MGF CHIP 1/16W 150	
R505	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R506	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R507	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R508	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R509	ERJ3GEYJ331X	MGF CHIP 1/16W 330	
R510	ERJ3GEYJ331X	MGF CHIP 1/16W 330	
R512	ERJ3GEYJ331X	MGF CHIP 1/16W 330	
R513	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R516	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R517	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R522	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R523	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R524	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R525	ERJ3GEYJ101X	MGF CHIP 1/16W 100	

Ref. No.	Part No.	Part Name & Description	Remarks
R526	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R527	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R528	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R529	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R530	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R531	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R532	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R533	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R534	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R535	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R536	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R537	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R538	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R539	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R540	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R541	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R542	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R543	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R544	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R545	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R546	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R548	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R549	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R550	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R551	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R552	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R553	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R554	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R555	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R556	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R557	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R558	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R559	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R560	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R561	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R562	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R563	ERJ3GEYJ151V	MGF CHIP 1/16W 150	
R564	ERJ3GEYJ151V	MGF CHIP 1/16W 150	
R565	ERJ3GEYJ151V	MGF CHIP 1/16W 150	
R566	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R567	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R568	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R569	ERJ3GEYJ151V	MGF CHIP 1/16W 150	
R571	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R572	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R573	ERJ6GEY0R00V	MGF CHIP 1/10W 0	●
	(D)		
R574	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R575	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R576	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R577	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R578	ERJ6GEY0R00V	MGF CHIP 1/10W 0	●
	(D)		
R579	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
	(D)		
R580	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
	(D)		
R581	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
	(A,B,C)		
R582	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R583	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(A,B,C)		
R585	ERJ3GEYJ181V	MGF CHIP 1/16W 180	
	(D)		
R603	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R605	ERJ3GEYJ331X	MGF CHIP 1/16W 330	
	(A,B,C)		
	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		

Ref. No.	Part No.	Part Name & Description	Remarks
R608	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R609	ERJ3GEYJ821X	MGF CHIP 1/16W 820	
	(A,B,C)		
	ERJ3GEYJ681X	MGF CHIP 1/16W 680	
	(D)		
R610	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R611	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R613	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(A,B,C)		
R614	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R615	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R616	ERJ3GEYJ105V	MGF CHIP 1/16W 1M	
	(A,B,C)		
R617	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(A,B,C)		
R618	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R619	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R620	ERJ3GEYJ182V	MGF CHIP 1/16W 1.8K	
	(A,B,C)		
R623	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R625	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R626	ERJ3GEYJ183X	MGF CHIP 1/16W 18K	
R630	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R634	ERJ3GEYJ153V	MGF CHIP 1/16W 15K	
	(D)		
R635	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R639	ERJ3GEYJ105V	MGF CHIP 1/16W 1M	
R641	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R643	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R644	ERJ3GEYJ330V	MGF CHIP 1/16W 33	
R645	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R646	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R650	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R653	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R654	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
	(A,B,C)		
R656	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R659	ERJ3GEYJ562X	MGF CHIP 1/16W 5.6K	
R662	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R677	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R680	ERJ3GEYJ331X	MGF CHIP 1/16W 330	
R683	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R684	ERJ3GEYJ105V	MGF CHIP 1/16W 1M	
R685	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
	(A,B,C)		
R686	ERJ3GEYJ392X	MGF CHIP 1/16W 3.9K	
	(D)		
R687	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(A,B,C)		
R689	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
	(A,B,C)		
R690	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R691	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R692	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R694	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R701	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R702	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R703	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R704	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R705	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R706	ERJ3GEYJ393V	MGF CHIP 1/16W 39K	
R707	ERJ8GEYJ101V	MGF CHIP 1/8W 100	
R708	ERJ3GEYJ393V	MGF CHIP 1/16W 39K	
R709	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R710	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R711	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R712	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R713	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	

Ref. No.	Part No.	Part Name & Description	Remarks
R714	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R715	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R718	ERJ3GEYJ562X	MGF CHIP 1/16W 5.6K	
R719	ERJ3GEYJ183X	MGF CHIP 1/16W 18K	
R720	ERJ3GEYJ114V	MGF CHIP 1/16W 110K	
R721	ERJ3GEYJ183X	MGF CHIP 1/16W 18K	
R722	ERJ3GEYJ114V	MGF CHIP 1/16W 110K	
R723	ERJ3GEYJ363V	MGF CHIP 1/16W 36K	
R724	ERJ3GEYJ363V	MGF CHIP 1/16W 36K	
R726	ERJ3GEYJ562X	MGF CHIP 1/16W 5.6K	
R730	ERJ3GEYJ562X	MGF CHIP 1/16W 5.6K	
R732	ERJ3GEYJ562X	MGF CHIP 1/16W 5.6K	
R735	ERJ3GEYJ363V	MGF CHIP 1/16W 36K	
R736	ERJ3GEYJ363V	MGF CHIP 1/16W 36K	
R737	ERJ3GEYJ114V	MGF CHIP 1/16W 110K	
R738	ERJ3GEYJ183X	MGF CHIP 1/16W 18K	
R739	ERJ3GEYJ114V	MGF CHIP 1/16W 110K	
R740	ERJ3GEYJ183X	MGF CHIP 1/16W 18K	
R744	ERJ8GEYJ3R9V	MGF CHIP 1/8W 3.9	
R745	ERJ8GEYJ3R9V	MGF CHIP 1/8W 3.9	
R746	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R747	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R748	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R749	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R750	ERJ3GEYJ105V	MGF CHIP 1/16W 1M	
R751	ERJ3GEYJ105V	MGF CHIP 1/16W 1M	
R752	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R754	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R755	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R1003	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R1004	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R1006	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R1007	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R1008	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R1009	VRJSD3D1801	MGF CHIP +-0.5% 1/16W 1.8K	
R1010	VRJSD3D1801	MGF CHIP +-0.5% 1/16W 1.8K	
R1011	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R1012	VRJSD3D5101	MGF CHIP +-0.5% 1/16W 5.1K	
R1013	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R1014	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R1015	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R1016	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R1017	ERJ3GEYJ333X	MGF CHIP 1/16W 33K	
R1019	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R1020	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R1021	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R1022	ERJ3GEYJ270V	MGF CHIP 1/16W 27	
R1023	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R1024	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R1025	ERJ3GEYJ681X	MGF CHIP 1/16W 680	
R1026	ERJ3GEYJ470V	MGF CHIP 1/16W 47	
R1027	ERJ3GEYJ470V	MGF CHIP 1/16W 47	
R1028	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R1029	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R1030	ERJ3GEYJ470V	MGF CHIP 1/16W 47	
R1031	VRJSD3D6801	MGF CHIP +-0.5% 1/16W 6.8K	
R1032	VRJSD3D2401	MGF CHIP +-0.5% 1/16W 2.4K	
R1033	VRJSD3D22R0	MGF CHIP +-0.5% 1/16W 22	
R1034	VRJSD3D5601	MGF CHIP +-0.5% 1/16W 5.6K	
R1035	VRJSD3D2701	MGF CHIP +-0.5% 1/16W 2.7K	
R1036	VRJSD3D68R0	MGF CHIP +-0.5% 1/16W 68	
R1037	VRJSD3D2702	MGF CHIP +-0.5% 1/16W 27K	
R1038	VRJSD3D1001	MGF CHIP +-0.5% 1/16W 1K	
R1039	VRJSD3D2401	MGF CHIP +-0.5% 1/16W 2.4K	
R1040	VRJSD3D6801	MGF CHIP +-0.5% 1/16W 6.8K	
R1041	VRJSD3D2201	MGF CHIP +-0.5% 1/16W 2.2K	
R1043	VRJSD3D1500V	MGF CHIP +-0.5% 1/16W 150	
R1044	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R1045	ERJ6GEYJ331V	MGF CHIP 1/10W 330	
R1046	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R1047	ERJ6GEYJ101V	MGF CHIP 1/10W 100	
	(A,B,C)		
	ERJ6GEYJ330V	MGF CHIP 1/10W 33	

Ref. No.	Part No.	Part Name & Description	Remarks
	(D)		
R1056	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R1058	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R1059	ERJ3GEYJ681X	MGF CHIP 1/16W 680	
R1060	ERJ3GEYJ821X	MGF CHIP 1/16W 820	
R1061	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R1062	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R1064	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R1065	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
	(A,B)		
	ERJ3GEYJ392X	MGF CHIP 1/16W 3.9K	
	(C,D)		
R1067	VRJSD3D1801	MGF CHIP +-0.5% 1/16W 1.8K	
R1068	VRJSD3D1801	MGF CHIP +-0.5% 1/16W 1.8K	
R1069	VRJSD3D33R0	MGF CHIP +-0.5% 1/16W 33	
R1073	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R1075	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R1076	ERJ3GEYJ392X	MGF CHIP 1/16W 3.9K	
R1078	VRJSD3D1801	MGF CHIP +-0.5% 1/16W 1.8K	
R1079	VRJSD3D1801	MGF CHIP +-0.5% 1/16W 1.8K	
R1080	VRJSD3D33R0	MGF CHIP +-0.5% 1/16W 33	
R1101	ERJ8GEYJR56V	MGF CHIP 1/8W 0.56	
R1102	ERJ8GEYJR56V	MGF CHIP 1/8W 0.56	
R1103	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R1104	ERJ3GEYJ680V	MGF CHIP 1/16W 68	
R1105	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R1106	ERJ3GEYJ681X	MGF CHIP 1/16W 680	
R1107	ERJ3GEYJ562X	MGF CHIP 1/16W 5.6K	
R1108	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R1109	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R1110	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R1111	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R1112	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R1113	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R1114	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R1601	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R1602	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R1603	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R1604	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
	(B)		
R1605	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
	(B)		
R1606	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
	(B)		
R2001	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R2003	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R2004	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R2008	ERJ8GEYJR33V	MGF CHIP 1/8W 0.33	
R2010	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R2011	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R2012	ERJ3GEYJ184V	MGF CHIP 1/16W 180K	
R2013	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R2014	ERJ3GEYJ684V	MGF CHIP 1/16W 680K	
R2015	ERJ3GEYJ682V	MGF CHIP 1/16W 6.8K	
R2016	ERJ3GEYJ684V	MGF CHIP 1/16W 680K	
R2021	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R2022	ERJ3GEYJ221V	MGF CHIP 1/16W 220	
R2023	ERJ8GEYJR33V	MGF CHIP 1/8W 0.33	
R2025	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R2026	ERJ3GEYJ820V	MGF CHIP 1/16W 82	
R2027	ERJ3GEYJ471X	MGF CHIP 1/16W 470	
R2028	ERJ3GEYJ391V	MGF CHIP 1/16W 390	
R2029	ERJ3GEYJ391V	MGF CHIP 1/16W 390	
R2030	ERJ3GEYJ471X	MGF CHIP 1/16W 470	
R2031	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R2032	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R3002	ERJ3GEYJ154V	MGF CHIP 1/16W 150K	
R3003	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R3004	ERJ3GEYJ270V	MGF CHIP 1/16W 27	
R3005	ERJ3GEYJ221V	MGF CHIP 1/16W 220	
R3006	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R3008	ERJ3GEYJ122V	MGF CHIP 1/16W 1.2K	
R3009	ERJ3GEYJ392X	MGF CHIP 1/16W 3.9K	

Ref. No.	Part No.	Part Name & Description	Remarks
R3010	ERJ3GEYJ122V	MGF CHIP 1/16W 1.2K	
R3011	ERJ3GEYJ271V	MGF CHIP 1/16W 270	
R3015	ERJ3GEYJ393V	MGF CHIP 1/16W 39K	
R3016	ERJ3GEYJ821X	MGF CHIP 1/16W 820	
R3017	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R3018	ERJ3GEYJ471X	MGF CHIP 1/16W 470	
R3022	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R3023	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R3024	ERJ6GEYJ560V	MGF CHIP 1/10W 56	
R3025	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R3026	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R3031	ERJ3GEYJ821X	MGF CHIP 1/16W 820	
R3032	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R3033	ERJ3GEYJ182V	MGF CHIP 1/16W 1.8K	
R3034	ERJ3GEYJ821X	MGF CHIP 1/16W 820	
R3035	ERJ3GEYJ182V	MGF CHIP 1/16W 1.8K	
R3036	ERJ3GEYJ471X	MGF CHIP 1/16W 470	
R3037	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R3038	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R3039	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R3040	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R3041	ERJ3GEYJ681X	MGF CHIP 1/16W 680	
R3044	ERJ3GEYJ681X	MGF CHIP 1/16W 680	
R3045	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R3048	ERJ3GEYJ681X	MGF CHIP 1/16W 680	
R3050	ERJ3GEYJ821X	MGF CHIP 1/16W 820	
R3129	ERJ3GEYJ391V	MGF CHIP 1/16W 390	
R3130	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R3140	ERJ3GEYJ122V	MGF CHIP 1/16W 1.2K	
R3150	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R3151	ERJ3GEYJ183X	MGF CHIP 1/16W 18K	
R3152	ERJ3GEYJ821X	MGF CHIP 1/16W 820	
R3153	ERJ3GEYJ272X	MGF CHIP 1/16W 2.7K	
R3154	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R3167	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R3169	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R3173	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(C,D)		
R3174	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(A,B)		
R3176	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R3180	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R3181	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R3182	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R3183	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R3184	ERJ3GEYJ821X	MGF CHIP 1/16W 820	
R3185	ERJ3GEYJ182V	MGF CHIP 1/16W 1.8K	
R3186	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R3187	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R3188	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R3190	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R3191	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(A,B,C)		
R3192	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(A,B,C)		
R3201	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
	(D)		
R3202	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
	(D)		
R3203	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R3206	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R3207	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R3208	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R3209	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
	(D)		
R3212	ERJ3GEYJ105V	MGF CHIP 1/16W 1M	
	(D)		
R4001	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R4002	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R4004	ERJ3GEYJ123X	MGF CHIP 1/16W 12K	
R4005	ERJ3GEYJ333X	MGF CHIP 1/16W 33K	

Ref. No.	Part No.	Part Name & Description	Remarks
R4006	ERJ3GEYJ105V	MGF CHIP 1/16W 1M	
R4007	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R4008	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R4009	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R4010	ERJ3GEYJ221V	MGF CHIP 1/16W 220	
R4011	ERJ3GEYJ561X	MGF CHIP 1/16W 560	
R4012	ERJ3GEYJ163V	MGF CHIP 1/16W 16K	
R4013	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R4014	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R4015	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R4016	ERJ3GEYJ183X	MGF CHIP 1/16W 18K	
R4017	ERJ3GEYJ100V	MGF CHIP 1/16W 10	
R4018	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R4019	ERJ3GEYJ682V	MGF CHIP 1/16W 6.8K	
R4020	ERJ3GEYJ334V	MGF CHIP 1/16W 330K	
R4021	ERJ3GEYJ122V	MGF CHIP 1/16W 1.2K	
R4024	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R4025	ERJ3GEYJ682V	MGF CHIP 1/16W 6.8K	
R4027	ERJ3GEYJ153V	MGF CHIP 1/16W 15K	
R4029	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R4030	ERJ3GEYJ680V	MGF CHIP 1/16W 68	
R4031	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R4032	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R4033	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R4034	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R4035	ERJ3GEYJ101X	MGF CHIP 1/16W 100	
R4037	ERJ3GEYJ561X	MGF CHIP 1/16W 560	
R4046	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R4060	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R4061	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R4062	ERJ3GEYJ333X	MGF CHIP 1/16W 33K	
R4063	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R4064	ERJ3GEYJ391V	MGF CHIP 1/16W 390	
	(D)		
R4065	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
	(D)		
R6004	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R6006	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R6007	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6008	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R6009	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6010	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6011	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R6012	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
	(A,D)		
R6013	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
	(A,D)		
R6014	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6015	ERJ3GEYJ393V	MGF CHIP 1/16W 39K	
R6016	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6017	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6019	ERJ3GEYJ474V	MGF CHIP 1/16W 470K	
R6020	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6021	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6022	ERJ6GEY0R00V	MGF CHIP 1/10W 0	●
R6023	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
	(D)		
R6024	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R6025	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6026	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6027	ERJ3GEYJ272X	MGF CHIP 1/16W 2.7K	
R6028	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R6029	ERJ3GEYJ332X	MGF CHIP 1/16W 3.3K	
R6030	ERJ3GEYJ272X	MGF CHIP 1/16W 2.7K	
R6031	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R6034	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R6037	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6038	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R6039	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R6040	ERJ3GEYJ561X	MGF CHIP 1/16W 560	
R6041	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6042	ERJ3GEYJ124V	MGF CHIP 1/16W 120K	
R6043	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	

Ref. No.	Part No.	Part Name & Description	Remarks
R6044	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R6045	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R6046	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6047	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6048	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6049	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6050	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6051	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6052	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6053	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
	(D)		
R6054	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R6056	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6058	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6060	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6061	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6062	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6063	ERJ3GEYJ563V	MGF CHIP 1/16W 56K	
R6064	ERJ3GEYJ563V	MGF CHIP 1/16W 56K	
R6066	ERJ3GEYJ682V	MGF CHIP 1/16W 6.8K	
R6068	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R6070	ERJ3GEYJ683V	MGF CHIP 1/16W 68K	
R6072	ERJ3GEYJ392X	MGF CHIP 1/16W 3.9K	
R6073	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R6074	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R6075	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R6077	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R6079	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6080	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6081	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6082	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6083	ERJ3GEYJ681X	MGF CHIP 1/16W 680	
R6084	ERJ3GEYJ561X	MGF CHIP 1/16W 560	
R6085	ERJ3GEYJ561X	MGF CHIP 1/16W 560	
R6086	ERJ3GEYJ561X	MGF CHIP 1/16W 560	
R6087	ERJ3GEYJ561X	MGF CHIP 1/16W 560	
R6088	ERJ3GEYJ561X	MGF CHIP 1/16W 560	
R6089	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6090	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6091	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6092	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6093	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6094	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6095	ERJ3GEYJ563V	MGF CHIP 1/16W 56K	
R6096	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
R6097	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6098	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6099	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R6100	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
	(A,D)		
R6101	ERJ3GEYJ104X	MGF CHIP 1/16W 100K	
	(B,C)		
R6102	VRJSD3D1802	MGF CHIP +-0.5% 1/16W 18K	
R6103	ERJ3GEYJ272X	MGF CHIP 1/16W 2.7K	
R6104	VRJSD3D1002	MGF CHIP +-0.5% 1/16W 10K	
R6108	ERJ3GEYJ564V	MGF CHIP 1/16W 560K	
R6110	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6111	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6112	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6113	ERJ3GEYJ272X	MGF CHIP 1/16W 2.7K	
R6114	ERJ3GEYJ154V	MGF CHIP 1/16W 150K	
R6115	ERJ3GEYJ393V	MGF CHIP 1/16W 39K	
R6116	ERJ3GEYJ393V	MGF CHIP 1/16W 39K	
R6119	ERJ8GEYJ101V	MGF CHIP 1/8W 100	
R6120	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6129	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R6131	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R6132	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R6133	ERJ3GEYJ223X	MGF CHIP 1/16W 22K	
R6135	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●
R6143	ERJ3GEYJ271V	MGF CHIP 1/16W 270	
R6144	ERJ3GEYJ271V	MGF CHIP 1/16W 270	
R6145	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	

Ref. No.	Part No.	Part Name & Description	Remarks
R6146	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R6147	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R6148	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6149	ERJ3GEYJ472X	MGF CHIP 1/16W 4.7K	
R6152	ERJ3GEYJ473X	MGF CHIP 1/16W 47K	
R6162	ERJ3GEYJ102X	MGF CHIP 1/16W 1K	
R6191	ERJ3GEYJ222X	MGF CHIP 1/16W 2.2K	
R6201	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R6202	ERJ3GEYJ103X	MGF CHIP 1/16W 10K	
R6209	ERJ3GEYJ225V	MGF CHIP 1/16W 2.2M	
R6210	ERJ3GEYJ561X	MGF CHIP 1/16W 560	
R6215	ERJ3GEYJ132V	MGF CHIP 1/16W 1.3K	
R6217	ERJ3GEYJ392V	MGF CHIP 1/16W 3.9K	
R6226	ERJ3GEY0R00X	MGF CHIP 1/16W 0	●

CAPACITORS

Ref. No.	Part No.	Part Name & Description	Remarks
C301	ECUV1H330JCV	C CHIP +-5% 50V 33P	
C302	ECUV1H560JCV	C CHIP +-5% 50V 56P	
C305	ECUV1H470JCV	C CHIP +-5% 50V 47P	
C306	ECST0JY106	TANTALUM CHIP 6.3V 10	
C307	ECUE1C104ZFV	C CHIP +80%-20% 16V 0.1	
C308	ECUV1H102KBV	C CHIP 50V 1000P	
	(D)		
C309	ECST0JY106	TANTALUM CHIP 6.3V 10	
C310	ECST1CY105	TANTALUM CHIP 16V 1	
C311	ECST1CY105	TANTALUM CHIP 16V 1	
C312	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C314	ECST0JY106	TANTALUM CHIP 6.3V 10	
C315	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C316	ECST0JY106	TANTALUM CHIP 6.3V 10	
C317	ECST0JY106	TANTALUM CHIP 6.3V 10	
C318	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C319	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C320	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C321	ECST0JX226	TANTALUM CHIP 6.3V 22	
C323	ECST0JY106	TANTALUM CHIP 6.3V 10	
C326	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C327	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C329	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C330	ECVE0JA220S	ELECTROLYTIC CHIP 6.3V 22	
C337	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C338	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C339	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C340	ECUE1H103KBV	C CHIP 50V 0.01	
C341	ECUV1H102KBV	C CHIP 50V 1000P	
C342	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C345	ECUV1H471KBV	C CHIP 50V 470P	
C346	ECUV1H471KBV	C CHIP 50V 470P	
C350	ECST0JY106	TANTALUM CHIP 6.3V 10	
C351	ECST0JY106	TANTALUM CHIP 6.3V 10	
C353	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C354	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C355	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C356	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C357	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C358	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C402	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C406	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C501	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C502	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C503	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C504	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C505	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C506	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C507	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C508	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C509	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C510	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C511	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C512	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C513	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C514	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	

Ref. No.	Part No.	Part Name & Description	Remarks
C515	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C519	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C521	ECST0JY106	TANTALUM CHIP 6.3V 10	
C522	ECUV1C104KBV	C CHIP 16V 0.1	
C523	ECUV1C104KBV	C CHIP 16V 0.1	
C524	ECUV1C104KBV	C CHIP 16V 0.1	
C525	ECUV1C104KBV	CCHIP 16V 0.1	
C526	ECST0JY106	TANTALUM CHIP 6.3V 10	
C527	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C528	ECUE1H103ZFB	C CHIP +80%-20% 50V 0.01	
C529	ECUE1H103ZFB	C CHIP +80%-20% 50V 0.01	
C530	ECUE1H103ZFB	C CHIP +80%-20% 50V 0.01	
C531	ECUE1H103ZFB	C CHIP +80%-20% 50V 0.01	
C532	ECUV1H040CCV	C CHIP +-0.25P 50V 4P	
	(D)		
C533	ECUV1H040CCV	C CHIP +-0.25P 50V 4P	
	(D)		
C534	ECUE1H103ZFB	C CHIP +80%-20% 50V 0.01	
C535	ECUE1H103ZFB	C CHIP +80%-20% 50V 0.01	
C604	ECUV1H150JCV	C CHIP +-5% 50V 15P	
	(A,B,C)		
C605	ECST0JX226	TANTALUM CHIP 6.3V 22	
C606	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C607	ECUV1H150JCV	C CHIP +-5% 50V 15P	
C610	ECRJA010A11B	TRIMMER CHIP 100V 10P	
	(A,B,C)		
C611	ECUV1H150JCV	C CHIP +-5% 50V 15P	
	(A,B,C)		
C613	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C614	ECUV1C474KBM	C CHIP 16V 0.47	
C615	ECUE1H103ZFB	C CHIP +80%-20% 50V 0.01	
C616	ECUV1C104KBV	C CHIP 16V 0.1	
C617	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C618	ECUE1H103ZFB	C CHIP +80%-20% 50V 0.01	
C623	ECEV1CA100S	ELECTROLYTIC CHIP 16V 10	
C633	ECST1CY225	TANTALUM CHIP 16V 2.2	
C634	ECST1CY225	TANTALUM CHIP 16V 2.2	
C636	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C638	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C639	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C640	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C641	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C642	ECST0JX226	TANTALUM CHIP 6.3V 22	
C643	ECST0JY106	TANTALUM CHIP 6.3V 10	
C644	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C645	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C646	ECST0JY106	TANTALUM CHIP 6.3V 10	
C647	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C651	ECUV1H102KBV	C CHIP 50V 1000P	
	(A,B,C)		
C663	ECUV1H100DCV	C CHIP +-0.5P 50V 10P	
	(A,B,C)		
C701	ECUV1H392KBV	C CHIP 50V 3900P	
C702	ECUV1H392KBV	C CHIP 50V 3900P	
C703	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C704	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C706	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C707	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C708	ECEV1CA470S	ELECTROLYTIC CHIP 16V 47	
C709	ECUE1H103ZFB	C CHIP +80%-20% 50V 0.01	
C1002	ECUV1E223KBV	C CHIP 25V 0.022	
C1003	ECUV1E223KBV	C CHIP 25V 0.022	
C1004	ECST1AY475N	TANTALUM CHIP 10V 4.7	
C1005	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C1006	VCUSTBC334KB	C CHIP 16V 0.33	
C1007	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C1008	ECUV1H331JCV	C CHIP +-5% 50V 330P	
C1009	ECUV1A105KBN	C CHIP 10V 1	
C1010	ECUV1E223KBV	C CHIP 25V 0.022	
C1011	ECUV1H472KBV	C CHIP 50V 4700P	
C1012	ECUV1H472KBV	C CHIP 50V 4700P	
C1014	ECUV1H221KBV	C CHIP 50V 220P	
C1015	ECUV1H221KBV	C CHIP 50V 220P	

Ref. No.	Part No.	Part Name & Description	Remarks
C1016	ECUV1H221KBV	C CHIP 50V 220P	
C1017	ECUV1H221KBV	C CHIP 50V 220P	
C1018	ECUE1H103KBV	C CHIP 50V 0.01	
C1019	ECUE1H103KBV	C CHIP 50V 0.01	
C1020	VCUSQBC105KB	C CHIP 16V 1	
C1021	ECEV1CA470S	ELECTROLYTIC CHIP 16V 47	
C1022	VCUSQFC475MB	C CHIP +-20% 16V 4.7	
C1023	VCUSQAA335KB	C CHIP 10V 3.3	
C1025	ECUV1H471KBV	C CHIP 50V 470P	
C1026	VCUSQAC225KB	C CHIP 16V 2.2	
C1027	ECEV0GA470S	ELECTROLYTIC CHIP 4V 47	
C1028	ECUV1H221KBV	C CHIP 50V 220P	
C1029	VCUSQAC105KB	C CHIP 16V 1	
C1030	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C1031	ECEV1CA100S	ELECTROLYTIC CHIP 16V 10	
C1032	VCUSQAC105KB	C CHIP 16V 1	
C1033	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C1034	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C1035	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C1036	ECUV1H101JCV	C CHIP +-5% 50V 100P	
C1037	VCUSQAC105KB	C CHIP 16V 1	
C1038	ECEV1CA220S	ELECTROLYTIC CHIP 16V 22	
C1039	ECUV1H331KBV	C CHIP 50V 330P	
C1040	VCUSQAC105ZF	C CHIP +80%-20% 16V 1	
C1041	ECEV1CS100S	ELECTROLYTIC CHIP 16V 10	
C1042	ECEV0JA470S	ELECTROLYTIC CHIP 6.3V 47	
C1044	ECUV1A105KBN	C CHIP 10V 1	
C1045	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C1046	VCUSQAC105KB	C CHIP 16V 1	
C1047	ECEV1CA100S	ELECTROLYTIC CHIP 16V 10	
C1050	ECUV1H222KBV	C CHIP 50V 2200P	
C1051	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C1053	ECUV1E104KBN	C CHIP 25V 0.1	
	(A,B)		
	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
	(C,D)		
C1054	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
	(A,B)		
C1055	ECUV1A105KBN	C CHIP 10V 1	
C1057	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C1058	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C1059	ECST0JY106	TANTALUM CHIP 6.3V 10	
C1060	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C1101	ECUV0J225KBN	C CHIP 6.3V 2.2	
C1102	ECUV1H102KBV	C CHIP 50V 1000P	
C1103	ECUE1C104ZFB	C CHIP +80%-20% 16V 0.1	
C2001	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C2002	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C2003	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C2007	ECEV0JA220S	ELECTROLYTIC CHIP 6.3V 22	
C2008	ECUV1E333KBN	C CHIP 25V 0.033	
C2010	ECUV1E683KBN	C CHIP 25V 0.068	
C2011	VCUSQAC334KB	C CHIP 16V 0.33	
C2012	ECUV1E473KBN	C CHIP 25V 0.047	
C2013	ECUV1E473KBN	C CHIP 25V 0.047	
C2015	ECUV1H152KBV	C CHIP 50V 1500P	
C2016	ECUV1H331KBV	C CHIP 50V 330P	
C2017	VCUSQAC105KB	C CHIP 16V 1	
C2021	ECUV1E473ZFB	C CHIP +80%-20% 25V 0.047	
C2022	ECUV1E473ZFN	C CHIP +80%-20% 25V 0.047	
C2023	ECUV1C104KBV	C CHIP 16V 0.1	
C2024	VCUSQAC105KB	C CHIP 16V 1	
C2025	ECUV1E103KBN	C CHIP 25V 0.01	
C2030	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C2031	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C2032	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C2040	ECEV1CA100S	ELECTROLYTICCHIP 16V 10	
C3001	VCUSQAA335KB	C CHIP 10V 3.3	
C3002	ECUE1H103ZFB	C CHIP +80%-20% 50V 0.01	
C3003	ECST0JX226	TANTALUM CHIP 6.3V 22	
C3005	ECUV1H220JCV	C CHIP +-5% 50V 22P	
C3006	ECUV1H332KBV	C CHIP 50V 3300P	
C3007	ECUV1H104ZFN	C CHIP +80%-20% 50V 0.1	

Ref. No.	Part No.	Part Name & Description	Remarks
C3008	ECUE1H103KBV	C CHIP 50V 0.01	
C3009	ECUV1H104ZFN	C CHIP +80%-20% 50V 0.1	
C3010	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3011	ECUV1H221JCV	C CHIP +-5% 50V 220P	
C3012	ECUV1H821KBV	C CHIP 50V 820P	
C3013	ECUV1H560JCV	C CHIP +-5% 50V 56P	
C3014	ECUV1H331JCV	C CHIP +-5% 50V 330P	
C3015	ECUV1H561JCV	C CHIP +-5% 50V 560P	
C3017	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3018	MCUV1E104KBN	C CHIP 25V 0.1	
C3019	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3021	ECST0JX226	TANTALUM CHIP 6.3V 22	
C3023	ECUV1E473KBN	C CHIP 25V 0.047	
C3024	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C3025	ECUE1H103KBV	C CHIP 50V 0.01	
C3028	ECUE1H103KBV	C CHIP 50V 0.01	
C3029	ECUE1H103KBV	C CHIP 50V 0.01	
C3030	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3031	ECUV1C224KBN	C CHIP 16V 0.22	
C3032	ECUV1H332KBV	C CHIP 50V 3300P	
C3033	ECST1CY225	TANTALUM CHIP 16V 2.2	
C3034	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C3036	ECST1AY475N	TANTALUM CHIP 10V 4.7	
C3038	ECUV1H560JCV	C CHIP +-5% 50V 56P	
C3039	ECUV1H150JCV	C CHIP +-5% 50V 15P	
C3040	ECUV1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3042	ECST0JX226	TANTALUM CHIP 6.3V 22	
C3043	ECST0JX226	TANTALUM CHIP 6.3V 22	
C3045	ECST0JY335	TANTALUM CHIP 6.3V 3.3	
C3046	ECEV0GA221S	ELECTROLYTIC CHIP 4V 220	
C3047	VCUSQBA105KB	C CHIP 10V 1	
C3048	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3053	ECUV1H390JCV	C CHIP +-5% 50V 39P	
C3054	ECUV1H101JCV	C CHIP +-5% 50V 100P	
C3055	ECUV1H181JCV	C CHIP +-5% 50V 180P	
C3057	ECUV1H180JCV	C CHIP +-5% 50V 18P	
C3058	ECUV1H120JCV	C CHIP +-5% 50V 12P	
C3059	ECUV1H100DCV	C CHIP +-0.5P 50V 10P	
C3060	ECUV1H120JCV	C CHIP +-5% 50V 12P	
C3061	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3068	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3070	ECUE1C104ZFV	C CHIP +80%-20% 16V 0.1	
C3072	ECUE1H103KBV	C CHIP 50V 0.01	
C3073	ECUE1C104ZFV	C CHIP +80%-20% 16V 0.1	
C3074	ECST0JX226	TANTALUM CHIP 6.3V 22	
C3075	ECUE1H103KBV	C CHIP 50V 0.01	
C3077	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3078	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3079	ECUV1H102KBV	C CHIP 50V 1000P	
C3080	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3081	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3085	ECUV1E104ZFN	C CHIP +80%-20% 25V 0.1	
C3098	ECUV1E104ZFN	C CHIP +80%-20% 25V 0.1	
C3107	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3132	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C3135	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3139	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3150	ECUE1H103ZFV	C CHIP +80%-20% 50V 0.01	
C3152	ECUV1H681KBV	C CHIP 50V 680P	
C3153	ECUV1H681KBV	C CHIP 50V 680P	
C3157	ECUV1H103ZFV	C CHIP +80%-20% 50V 0.01	
	(D)		
C4002	ECST0JX226	TANTALUM CHIP 6.3V 22	
C4004	ECST0JY106	TANTALUM CHIP 6.3V 10	
C4005	ECEV0JA220S	ELECTROLYTIC CHIP 6.3V 22	
C4006	ECST0JX226	TANTALUM CHIP 6.3V 22	
C4007	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C4008	ECUV1E273KBN	C CHIP 25V 0.027	
C4009	ECUV1H822KBV	C CHIP 50V 8200P	
C4010	ECUV1H221KBV	C CHIP 50V 220P	
C4011	ECST1CY105	TANTALUM CHIP 16V 1	
C4012	ECUV1H152KBV	C CHIP 50V 1500P	
C4013	ECUV1H222KBV	C CHIP 50V 2200P	

Ref. No.	Part No.	Part Name & Description	Remarks
C4015	VCUSQBA105KB	C CHIP 10V 1	
C4016	ECEV1HA3R3S	ELECTROLYTIC CHIP 50V 3.3	
C4017	ECST0JX226	TANTALUM CHIP 6.3V 22	
C4018	ECUV1H103KBN	C CHIP 50V 0.01	
C4019	ECST1AY475N	TANTALUM CHIP 10V 4.7	
C4020	ECUV1H470JCV	C CHIP +-5% 50V 47P	
C4021	ECUV1H102KBV	C CHIP 50V 1000P	
C4022	ECUT2A472JCV	C CHIP +-5% 100V 4700P	
C4023	ECUV1H682KBN	C CHIP 50V 6800P	
C4024	ECUV1E223KBV	C CHIP 25V 0.022	
C4025	VCUSQBA105KB	C CHIP 10V 1	
C4026	ECST0JX226	TANTALUM CHIP 6.3V 22	
C4027	ECUV1H104ZFN	C CHIP +80%-20% 50V 0.1	
C4041	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C4043	VCUSQBA105KB	C CHIP 10V 1	
	(D)		
C6001	ECUV1H330JCV	C CHIP +-5% 50V 33P	
C6002	ECUV1C224KBN	C CHIP 16V 0.22	
C6004	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C6006	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C6007	ECUV1H120JCV	C CHIP +-5% 50V 12P	
C6008	ECUV1H100DCV	C CHIP +-0.5P 50V 10P	
C6009	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C6011	ECUE1H103ZFN	C CHIP +80%-20% 50V 0.01	
C6013	ECUV1E104ZFN	C CHIP +80%-20% 25V 0.1	
C6014	ECUE1H103ZFN	C CHIP +80%-20% 50V 0.01	
C6017	ECUV1E104KBN	C CHIP 25V 0.1	
C6018	ECUV1A105KBN	C CHIP 10V 1	
C6020	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C6022	ECUE1H103ZFN	C CHIP +80%-20% 50V 0.01	
C6023	ECUV1H102KBV	C CHIP 50V 1000P	
C6025	ECEV0JA470S	ELECTROLYTIC CHIP 6.3V 47	
C6028	ECUV1H0R5CCV	C CHIP +-0.25P 50V 0.5P	
C6029	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C6031	ECUE1H103KBV	C CHIP 50V 0.01	
C6032	ECUE1H103KBV	C CHIP 50V 0.01	
C6044	ECUE1C104ZFN	C CHIP +80%-20% 16V 0.1	
C6201	ECUV1C104KBV	C CHIP 16V 0.1	
C6202	ECUV1C104KBV	C CHIP 16V 0.1	
C6207	ECUE1H121JCV	C CHIP +-5% 50V 120P	
C6208	ECUV1C224ZFN	C CHIP +80%-20% 16V 0.22	
C6214	ECUV1H102KBV	C CHIP 50V 1000P	
C6220	TCUV1C155ZFM	C CHIP +80%-20% 16V 1.5	
C6221	ECUV1H392KBV	C CHIP 50V 3900P	
C6222	VCUSQAC105KB	C CHIP 16V 1	
C6223	ECST0JX226	TANTALUM CHIP 6.3V 22	
C6225	ECUV1H102KBV	C CHIP 50V 1000P	

FILTERS

Ref. No.	Part No.	Part Name & Description	Remarks
FL3001	VLFW0041		

COILS

Ref. No.	Part No.	Part Name & Description	Remarks
L302	VLQ0163K470	CHIP 47	
L303	VLQ0163K330	CHIP 33	
L304	ELJFA150KF2	15	
L305	VLQ0426J3R9	CHIP 3.9	
L307	ELJFA101KF2	CHIP 100	
L308	VLQ0319K100	CHIP 10	
L310	VLQ0319M4R7	CHIP	
L312	ELJFA101KF2	CHIP 100	
L313	VLQ0163K181	CHIP 180	
L503	BK1608HM102	FERRITE CORE	
L504	BK1608HM102	FERRITE CORE	
L505	BK1608HM102	FERRITE CORE	
L506	VLQ0163K150	CHIP 15	
L601	VLQ0163K470	CHIP 47	
L602	VLQ0426J150	CHIP +-5% 15	
L605	VLQ0163K150	CHIP 15	
L1001	NP05DA100M	+-20% 10	
L1002	NP05DA100M	+-20% 10	

Ref. No.	Part No.	Part Name & Description	Remarks
L1003	NP05DA330M	+ -20% 33	
L1004	NP05DA330M	+ -20% 33	
L1005	N05DA100K	10	
L1006	VLQ0319K100	CHIP 10	
L1007	VLJW3TC100KT	CHIP 10	
L1008	N05DA100K	10	
L1009	VLQ0426J470	CHIP +-5% 47	
L1010	VLQ0426J470	CHIP +-5% 47	
L1011	VLQ0426J470	CHIP +-5% 47	
L1012	VLQ0319K100	CHIP 10	
L1013	VLQ0319K101	CHIP 100	
L1014	LSLJCMAR7MF	CHIP +-20% 4.7	
L1015	LSLJDJA100KF	CHIP 10	
L1016	VLQ0319K100	CHIP 10	
L3001	VLJW3TC470KT	CHIP 47	
L3002	VLJW3TC470KT	CHIP 47	
L3003	VLJW3TC470KT	CHIP 47	
L3004	VLJW3TC470KT	CHIP 47	
L3006	VLJW3TC470KT	CHIP 47	
L3009	VLQ0426J820	CHIP +-5% 82	
L3011	VLQ0426J470	CHIP +-5% 47	
L3012	VLQ0426J120	CHIP +-5% 12	
L3013	VLQ0163J331	CHIP +-5% 330	
L3014	VLQ0426J180	CHIP +-5% 18	
L3015	VLQ0163J331	CHIP +-5% 330	
L3016	VLQ0426J470	CHIP +-5% 47	
L3017	VLQ0163J331	CHIP +-5% 330	
L3030	VLJW3TC470KT	CHIP 47	
L4001	VLQ0319K221	CHIP 220	

CRYSTAL OSCILLATOR

Ref. No.	Part No.	Part Name & Description	Remarks
X501	LSSX0042		
	(D)		
X601	VSXW0096		
	(A,B,C)		
X3001	VSXW0080		
X6001	VSXW0093		
X6002	LSSX0030		

PIN HEADERS

Ref. No.	Part No.	Part Name & Description	Remarks
B2	VJFPW0262	BOARD TO BOARD 18P	
P2	VJFPW0242	CONNECTOR 13P	
P3	VJFPW0254	CONNECTOR 5P	
	(A,C,D)		
	VJFPW0255	CONNECTOR 12P	
	(B)		
P38	VJFPW0264	CONNECTOR 3P	
	(A,B,C)		
	LSJP03AE009	CONNECTOR 9P	
	(D)		

FPC CONNECTOR

Ref. No.	Part No.	Part Name & Description	Remarks
FP1	LSJSRF28DGA	CONNECTOR 28P	
FP3	LSJSQG26DG	CONNECTOR 26P	
FP4	VJFPW501MP06	CONNECTOR 6P	
FP6	LSJS01EC039	CONNECTOR 39P	
FP7	VJFPW501MP14	CONNECTOR 14P	
FP8	VJFPW501MP12	CONNECTOR 12P	
FP9	VJFPW501MP20	CONNECTOR 20P	
FP11	LSJSQG13DG	CONNECTOR 13P	
FP13	VJFPW501MP42	CONNECTOR 42P	

FUSE & PROTECTOR

Ref. No.	Part No.	Part Name & Description	Remarks
F1001	LSSF008C30T	FUSE CHIP 32V 3A	△
	OR VSWF0011	FUSE CHIP 32V 3A	△
F1002	LSSF008F15T	FUSE CHIP 63V 1.5A	△
	OR VSWF0010	FUSE CHIP 63V 1.5A	△

Ref. No.	Part No.	Part Name & Description	Remarks
F1003	LSSF008F15T	FUSE CHIP 63V 1.5A	△
	OR VSWF0010	FUSE CHIP 63V 1.5A	△
	(D)		

TRANSFORMER

Ref. No.	Part No.	Part Name & Description	Remarks
T1001	VTPW0003A		
T1002	VTPW0004		
T4001	EQQ6QT001T		

12.3.2. PC JACK C.B.A. ■

JACKS

Ref. No.	Part No.	Part Name & Description	Remarks
JK1	LSJJ0137	MINI JACK SOCKET	

12.3.3. TV TUNER JACK C.B.A. (D) ■

JACKS

Ref. No.	Part No.	Part Name & Description	Remarks
JK7001	LSJS0099	TV TUNER JACK SOCKET	

12.3.4. CCD C.B.A. (A,B,C) ■

INTEGRATED CIRCUITS

Ref. No.	Part No.	Part Name & Description	Remarks
IC601	MN371132FT-M	IC, CCD	E.S.D.

TRANSISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
Q601	2SC3931	CHIP	

RESISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
R601	ERJ3GEYJ332V	MGF CHIP 1/16W 3.3K	
R602	ERJ8GEYJ470V	MGF CHIP 1/8W 47	
R661	ERJ3GEYJ101V	MGF CHIP 1/16W 100	

CAPACITORS

Ref. No.	Part No.	Part Name & Description	Remarks
C603	ECUV1C104ZV	C CHIP +80%-20% 16V 0.1	
C664	ECUV1C104ZV	C CHIP +80%-20% 16V 0.1	

MISCELLANEOUS

Ref. No.	Part No.	Part Name & Description	Remarks
E16	VMDW0430	CCD SURFACE PLATE, POLYESTER	

12.3.5. CCD C.B.A. (D) ■

INTEGRATED CIRCUITS

Ref. No.	Part No.	Part Name & Description	Remarks
IC601	MN39241FT	IC, CCD	E.S.D.

TRANSISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
Q601	2SC3931	CHIP	

RESISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
R601	ERJ3GEYJ332V	MGF CHIP 1/16W 3.3K	
R602	ERJ8GEYJ470V	MGF CHIP 1/8W 47	
R661	ERJ3GEYJ101V	MGF CHIP 1/16W 100	

CAPACITORS

Ref. No.	Part No.	Part Name & Description	Remarks
C603	ECUV1C104ZV	C CHIP +80%-20% 16V 0.1	

Ref. No.	Part No.	Part Name & Description	Remarks
C664	ECUV1C104ZFV	C CHIP +80%-20% 16V 0.1	

MISCELLANEOUS

Ref. No.	Part No.	Part Name & Description	Remarks
E16	VMDW0515	CCD SURFACE PLATE,POLYESTER	

12.3.6. ELECTRONIC VIEWFINDER C.B.A. (A,C,D) ■

INTEGRATED CIRCUITS

Ref. No.	Part No.	Part Name & Description	Remarks
IC901	AN2515NS	IC, LINEAR EVF DRIVE	

TRANSISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
Q901	2SD968A(S)	CHIP	△
Q902	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	

DIODES

Ref. No.	Part No.	Part Name & Description	Remarks
D901	SFPL-52V	CHIP	

RESISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
R901	ERJ3GEYJ4R7V	MGF CHIP 1/16W 4.7	
R902	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R903	VRJSD3D1302V	MGF CHIP +-0.5% 1/16W 13K	
R904	VRJSD3D1203V	MGF CHIP +-0.5% 1/16W 120K	
R905	ERJ3GEYJ514V	MGF CHIP 1/16W 510K	
R906	ERJ3GEYJ242V	MGF CHIP 1/16W 2.4K	
R907	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R908	VRJSD3D3302	MGF CHIP +-0.5% 1/16W 33K	
R911	ERJ3GEYJ3R9V	MGF CHIP 1/16W 3.9	
R912	ERJ3GEYJ222V	MGF CHIP 1/16W 2.2K	
R913	ERJ3GEYJ471V	MGF CHIP 1/16W 470	
R914	ERJ3GEYJ272V	MGF CHIP 1/16W 2.7K	
R915	ERJ3GEYJ153V	MGF CHIP 1/16W 15K	
R916	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R917	ERJ3GEYJ222V	MGF CHIP 1/16W 2.2K	
R918	ERJ3GEYJ105V	MGF CHIP 1/16W 1M	
R919	ERJ3GEYJ100V	MGF CHIP 1/16W 10	
R920	ERJ6GEYJ105V	MGF CHIP 1/10W 1M	
R921	ERJ6GEYJ106V	MGF CHIP 1/10W 10M	
R922	ERJ6GEYJ106V	MGF CHIP 1/10W 10M	
R923	ERJ6GEYJ185V	MGF CHIP 1/10W 1.8M	
R925	ERJ6GEYJ684V	MGF CHIP 1/10W 680K	
R926	ERJ6GEYJ225V	MGF CHIP 1/10W 2.2M	
R927	ERJ6GEYJ185V	MGF CHIP 1/10W 1.8M	
R929	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
VR901	EVM7JSX30BE2	VARIABLE CHIP 220	
VR902	VRVW0028	VARIABLE CHIP 5M	
VR903	EVM7ESX30B26	VARIABLE CHIP 2M	

CAPACITORS

Ref. No.	Part No.	Part Name & Description	Remarks
C902	ECUV1H123KBV	C CHIP 50V 0.012	
C903	VCUSQBA105KB	C CHIP 10V 1	
C904	EEAFC0J101H	ELECTROLYTIC 6.3V 100	
C905	VCUSQBA105KB	C CHIP 10V 1	
C906	ECQV1H104JM	POLTESTER +-5% 50V 0.1	
C907	ECUV1C104KBV	C CHIP 16V 0.1	
C908	EEAFC0J101H	ELECTROLYTIC 6.3V 100	
C909	ECUV1H151JCV	C CHIP +-5% 50V 150P	
C910	MCUV2A332JUM	C CHIP +-5% 100V 3300P	△
C911	EEAFC0J470H	ELECTROLYTIC 6.3V 47	
C912	EEAFC1C470H	ELECTROLYTIC 16V 47	
C913	ECUV1C104KBV	C CHIP 16V 0.1	
C914	ECUV1C104KBV	C CHIP 16V 0.1	

Ref. No.	Part No.	Part Name & Description	Remarks
C915	DE405B151K1K	CERAMIC 1KV 150P	△
C916	ECEA1HKS010	ELECTROLYTIC 50V 1	
C917	ECKD2H331KB5	CERAMIC 500V 330P	△

COILS

Ref. No.	Part No.	Part Name & Description	Remarks
L901	VLQ0319K330	CHIP 33	
L902	VLQ0426J220	CHIP +-5% 22	
L903	ELH5L3105	LINEALITY	△

PIN HEADERS

Ref. No.	Part No.	Part Name & Description	Remarks
P902	VJFPW0254	CONNECTOR 5P	
P903	VJFPW0004N1	CONNECTOR 4P	

FPC CONNECTOR

Ref. No.	Part No.	Part Name & Description	Remarks
FP901	VJFPW501MP06	CONNECTOR 6P	

TRANSFORMER

Ref. No.	Part No.	Part Name & Description	Remarks
T901	ETF08L204A		△

MISCELLANEOUS

Ref. No.	Part No.	Part Name & Description	Remarks
E18	VEKW1639	CRT SOCKET UNIT	
E27	ELY05V583A1	DEFLECTION YOKE	△
E33	M01LSX07WB01	CRT	△
E34	VMZW0606	INSULATION SHEET,PLASTIC	
E37	LSEK0375	EVF CABLE W/PLUG,DC5V	

12.3.7. COLOR ELECTRONIC VIEWFINDER A C.B.A. (B) ■

INTEGRATED CIRCUITS

Ref. No.	Part No.	Part Name & Description	Remarks
IC901	AN2536FHQ	IC, LINEAR EVF DRIVE	

TRANSISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
Q902	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q903	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q904	IMX1T108	COMPLX CMP SI NPN CHIP	
	OR XN4501	COMPLX CMP SI NPN CHIP	
Q905	2SA1037K146R	CHIP	
	OR 2SB709A	CHIP	

DIODES

Ref. No.	Part No.	Part Name & Description	Remarks
D901	MA8033-H	ZENER CHIP 3.3V	

RESISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
R901	ERJ3GEYJ222V	MGF CHIP 1/16W 2.2K	
R902	ERJ3GEYJ102V	MGF CHIP 1/16W 1K	
R903	ERJ3GEYJ102V	MGF CHIP 1/16W 1K	
R904	ERJ3GEYJ102V	MGF CHIP 1/16W 1K	
R905	ERJ3GEYJ221V	MGF CHIP 1/16W 220	
R906	ERJ3GEYJ102V	MGF CHIP 1/16W 1K	
R907	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R908	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R909	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R910	ERJ3GEYJ271V	MGF CHIP 1/16W 270	
R911	ERJ3GEYJ153V	MGF CHIP 1/16W 15K	
R912	ERJ3GEYJ113V	MGF CHIP 1/16W 11K	
R913	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●

Ref. No.	Part No.	Part Name & Description	Remarks
R915	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R916	ERJ3GEYJ122V	MGF CHIP 1/16W 1.2K	
R917	ERJ3GEYJ681V	MGF CHIP 1/16W 680	
R918	ERJ3GEYJ101V	MGF CHIP 1/16W 100	
R919	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R920	VRJSD3D2702	MGF CHIP +-0.5% 1/16W 27K	
R921	VRJSD3D4701	MGF CHIP +-0.5% 1/16W 4.7K	
R922	VRJSD3D2202	MGF CHIP +-0.5% 1/16W 22K	
R928	VRJSD3D1802	MGF CHIP +-0.5% 1/16W 18K	
R929	VRJSD3D1102	MGF CHIP +-0.5% 1/16W 11K	
R930	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R931	ERJ3GEYJ392V	MGF CHIP 1/16W 3.9K	
R935	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R936	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R938	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R939	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R942	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●

CAPACITORS

Ref. No.	Part No.	Part Name & Description	Remarks
C905	ECEV1EA4R7S	ELECTROLYTIC CHIP 25V 4.7	
C908	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C910	ECUV1H152KBV	C CHIP 50V 1500P	
C911	ECUV1A105ZFB	C CHIP +80%-20% 10V 1	
C912	NMA0J226MTR	ELECTROLYTIC CHIP 6.3V 22	
C913	ECUV1C104KBV	C CHIP 16V 0.1	
C914	ECUV1C104KBV	C CHIP 16V 0.1	
C915	VCUSJBJ225KB	C CHIP 6.3V 2.2	
C916	ECUV1H152KBV	C CHIP 50V 1500P	
C917	ECST0JY475	TANTALUM CHIP 6.3V 4.7	
C918	VCUSJBJ225KB	C CHIP 6.3V 2.2	
C919	ECUV1C104KBV	C CHIP 16V 0.1	
C920	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C922	ECEV1CA470S	ELECTROLYTIC CHIP 16V 47	
C923	VCUSJBJ225KB	C CHIP 6.3V 2.2	
C924	VCUSJBJ225KB	C CHIP 6.3V 2.2	
C925	ECUV1C104KBV	C CHIP 16V 0.1	
C926	VCUSQAC225KB	C CHIP 16V 2.2	
C927	ECUV1C104KBN	C CHIP 16V 0.1	
C931	ECUV1E104ZFN	C CHIP +80%-20% 25V 0.1	
C933	ECUV1C104KBV	C CHIP 16V 0.1	
C934	VCUSQBC105KB	C CHIP 16V 1	
C935	VCUSQBA105KB	C CHIP 10V 1	
C936	ECUV1H103KBV	C CHIP 50V 0.01	
C937	MCUV1E104KBN	C CHIP 25V 0.1	

COILS

Ref. No.	Part No.	Part Name & Description	Remarks
L902	VLQ0426J150	CHIP +-5% 15	
L903	VLQ0319K100	CHIP 10	
L905	VLQ0426J150	CHIP +-5% 15	

PIN HEADERS

Ref. No.	Part No.	Part Name & Description	Remarks
P901	VJFPW0255	CONNECTOR 12P	

FPC CONNECTOR

Ref. No.	Part No.	Part Name & Description	Remarks
FP901	VJFPW501MP06	CONNECTOR 6P	
FP902	VJFPW501MP16	CONNECTOR 16P	

MISCELLANEOUS

Ref. No.	Part No.	Part Name & Description	Remarks
E36	VEKW1781	EVF CABLE W/PLUG,DC15V	

12.3.8. COLOR ELECTRONIC VIEWFINDER B C.B.A. (B) ■

TRANSISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
Q901	2SK1299STL	F.E.T.	△

CAPACITORS

Ref. No.	Part No.	Part Name & Description	Remarks
C903	VCUSQFA106KE	C CHIP 10V 10	

COILS

Ref. No.	Part No.	Part Name & Description	Remarks
L901	SLF6028T101M	CHOKE +-20% 100	△

LAMP

Ref. No.	Part No.	Part Name & Description	Remarks
PL901	VLLW0010	LCD LAMP	△
	OR VLLW0011	LCD LAMP	△

TRANSFORMER

Ref. No.	Part No.	Part Name & Description	Remarks
T901	ETJ09K30AM		△
	OR VLTW0044		△

12.3.9. LIQUID CRYSTAL DISPLAY C.B.A. ■

INTEGRATED CIRCUITS

Ref. No.	Part No.	Part Name & Description	Remarks
IC1201	BA9746FV-E2	IC, LINEAR POWER CONTROL	
IC9001	AN2545FHQ	IC, LINEAR RGB SIGNAL PROCESS	
IC9002	TA758558F85L	IC, LINEAR OP.AMP.	
IC9003	M52684BFP	IC, LINEAR V/H SYNC SEPARATION	
	(D)		
IC9004	TC7W04FTE12L	IC, CMOS STANDARD LOGIC INVERTER	E.S.D.
	(D)		

TRANSISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
Q1202	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q1203	DTA124EU	CHIP	
	OR UN5112	CHIP	
Q1204	DTA124EU	CHIP	
	OR UN5112	CHIP	
Q1205	DTA124EU	CHIP	
	OR UN5112	CHIP	
Q1206	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q1207	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q1208	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q1209	IMX1T108	COMPLX CMP SI NPN CHIP	
	OR XN4501	COMPLX CMP SI NPN CHIP	
Q1210	2SB1073	CHIP	
	OR 2SB1386T100Q	CHIP	
	OR 2SB1386T100R	CHIP	
Q1211	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q1212	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q1213	DTC124EU	CHIP	
	OR UN5212	CHIP	
Q1214	2SK1958	F.E.T. CHIP	
Q1215	DTC124EU	CHIP	

Ref. No.	Part No.	Part Name & Description	Remarks
	OR UN5212	CHIP	
Q1216	DTC124EU	CHIP	
	OR UN5212	CHIP	
Q1217	CPH3215-TL	CHIP	
Q1218	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q1219	IMX1T108	COMPLX CMP SI NPN CHIP	
	OR XN4501	COMPLX CMP SI NPN CHIP	
Q1220	2SA1576A106R	CHIP	
	OR 2SB1218A	CHIP	
Q1221	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q1222	2SC4081T106R	CHIP	
	OR 2SD1819A	CHIP	
Q9001	DTC124EU	CHIP	
	OR UN5212	CHIP	
Q9002	DTA114YU	COMPLX CMP SI NPN/PNP CHIP	
	OR UN5114	COMPLX CMP SI NPN/PNP CHIP	
Q9101	2SD1119	CHIP	△
	OR 2SD2150T100R	CHIP	△
Q9102	2SD1119	CHIP	△
	OR 2SD2150T100R	CHIP	△

DIODES

Ref. No.	Part No.	Part Name & Description	Remarks
D1201	DAN202UT	CHIP	
	OR MA142WK	CHIP	
D1203	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D1204	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D1205	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D1206	MA8068-M	ZENER CHIP 6.8V	
D9001	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D9002	MA111	CHIP	
	OR 1SS355TE-17	CHIP	
D9003	MA111	CHIP	
	OR 1SS355TE-17	CHIP	

RESISTORS

Ref. No.	Part No.	Part Name & Description	Remarks
R1203	ERJ3GEYJ273V	MGF CHIP 1/16W 27K	
R1204	ERJ3GEYJ683V	MGF CHIP 1/16W 68K	
R1205	ERJ3GEYJ472V	MGF CHIP 1/16W 4.7K	
R1206	ERJ3GEYJ472V	MGF CHIP 1/16W 4.7K	
R1207	ERJ3GEYJ183V	MGF CHIP 1/16W 18K	
R1208	ERJ3GEYJ824V	MGF CHIP 1/16W 820K	
R1209	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R1210	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R1211	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R1212	ERJ3GEYJ473V	MGF CHIP 1/16W 47K	
R1213	ERJ3GEYJ473V	MGF CHIP 1/16W 47K	
R1214	ERJ3GEYJ223V	MGF CHIP 1/16W 22K	
R1215	ERJ3GEYJ473V	MGF CHIP 1/16W 47K	
R1216	ERJ3GEYJ473V	MGF CHIP 1/16W 47K	
R1217	VRJSD3D1002	MGF CHIP +-0.5% 1/16W 10K	
R1218	VRJSD3D1002	MGF CHIP +-0.5% 1/16W 10K	
R1219	ERJ3GEYJ562V	MGF CHIP 1/16W 5.6K	
R1220	ERJ3GEYJ472V	MGF CHIP 1/16W 4.7K	
R1221	VRJSD3D1002	MGF CHIP +-0.5% 1/16W 10K	
R1222	VRJSD3D3302	MGF CHIP +-0.5% 1/16W 33K	
R1223	ERJ3GEYJ223V	MGF CHIP 1/16W 22K	
R1224	ERJ3GEYJ391V	MGF CHIP 1/16W 390	
R1225	ERJ3GEYJ101V	MGF CHIP 1/16W 100	

Ref. No.	Part No.	Part Name & Description	Remarks
R1226	ERJ3GEYJ101V	MGF CHIP 1/16W 100	
R1227	ERJ3GEYJ223V	MGF CHIP 1/16W 22K	
R1228	ERJ3GEYJ472V	MGF CHIP 1/16W 4.7K	
R1229	ERJ3GEYJ223V	MGF CHIP 1/16W 22K	
R1230	ERJ3GEYJ105V	MGF CHIP 1/16W 1M	
R1231	VRJSD3D2702	MGF CHIP +-0.5% 1/16W 27K	
R1232	VRJSD3D3001	MGF CHIP +-0.5% 1/16W 3K	
R1233	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R1234	ERJ3GEYJ152V	MGF CHIP 1/16W 1.5K	
R1235	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R1237	ERJ3GEYJ331V	MGF CHIP 1/16W 330	
R1238	VRJSD3D3301	MGF CHIP +-0.5% 1/16W 3.3K	
R1239	ERJ3GEYJ100V	MGF CHIP 1/16W 10	
	(A, B, C)		
	ERJ3GEYJ470V	MGFCHIP 1/16W 47	
	(D)		
R1240	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R1241	ERJ3GEYJ223V	MGF CHIP 1/16W 22K	
R1242	VRJSD3D4702	MGF CHIP +-0.5% 1/16W 47K	
R1243	VRJSD3D3302	MGF CHIP +-0.5% 1/16W 33K	
R1244	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R1245	ERJ3GEYJ272V	MGF CHIP 1/16W 2.7K	
R1246	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R1247	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R1248	ERJ3GEYJ223V	MGF CHIP 1/16W 22K	
R1249	ERJ3GEYJ561V	MGF CHIP 1/16W 560	
R1250	ERJ3GEYJ562V	MGF CHIP 1/16W 5.6K	
R9001	ERJ3GEYJ472V	MGF CHIP 1/16W 4.7K	
R9003	ERJ3GEYJ472V	MGF CHIP 1/16W 4.7K	
R9004	ERJ3GEYJ102V	MGF CHIP 1/16W 1K	
R9005	ERJ3GEYJ102V	MGF CHIP 1/16W 1K	
R9006	ERJ3GEYJ102V	MGF CHIP 1/16W 1K	
R9007	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R9008	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R9009	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R9011	ERJ3GEYJ101V	MGF CHIP 1/16W 100	
R9012	ERJ3GEYJ101V	MGF CHIP 1/16W 100	
R9013	ERJ3GEYJ561V	MGF CHIP 1/16W 560	
	(A, B, C)		
R9014	ERJ3GEYJ153V	MGF CHIP 1/16W 15K	
R9015	ERJ3GEYJ123X	MGF CHIP 1/16W 12K	
R9016	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R9017	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R9018	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R9019	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
R9020	ERJ3GEYJ101V	MGF CHIP 1/16W 100	
R9021	ERJ3GEYJ101V	MGF CHIP 1/16W 100	
R9022	ERJ3GEYJ101V	MGF CHIP 1/16W 100	
R9023	ERJ3GEYJ303V	MGF CHIP 1/16W 30K	
R9024	ERJ3GEYJ104V	MGF CHIP 1/16W 100K	
R9025	ERJ3GEYJ682V	MGF CHIP 1/16W 6.8K	
R9026	ERJ3GEYJ473V	MGF CHIP 1/16W 47K	
R9027	ERJ3GEYJ473V	MGF CHIP 1/16W 47K	
R9028	ERJ3GEYJ223V	MGF CHIP 1/16W 22K	
R9029	ERJ3GEYJ473V	MGF CHIP 1/16W 47K	
R9030	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R9031	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
R9032	ERJ3GEYJ104V	MGF CHIP 1/16W 100K	
R9033	ERJ3GEYJ333V	MGF CHIP 1/16W 33K	
R9037	ERJ3GEYJ823V	MGF CHIP 1/16W 82K	
	(D)		
R9038	ERJ3GEYJ471V	MGF CHIP 1/16W 470	
	(D)		
R9039	ERJ3GEYJ103V	MGF CHIP 1/16W 10K	
	(D)		
R9040	ERJ3GEYJ271V	MGF CHIP 1/16W 270	
	(D)		
R9041	ERJ3GEYJ272V	MGF CHIP 1/16W 2.7K	
	(D)		
R9045	ERJ3GEY0R00V	MGF CHIP 1/16W 0	●
	(D)		
R9046	ERJ3GEYJ272V	MGF CHIP 1/16W 2.7K	
	(D)		

Ref. No.	Part No.	Part Name & Description	Remarks
R9048	ERJ3GEYJ102V (D)	MGF CHIP 1/16W 1K	
R9049	ERJ3GEYJ102V (D)	MGF CHIP 1/16W 1K	
R9050	ERJ3GEYJ302V (D)	MGF CHIP 1/16W 3K	
R9051	ERJ3GEYJ302V (D)	MGF CHIP 1/16W 3K	
R9052	ERJ3GEYJ102V (D)	MGF CHIP 1/16W 1K	
R9053	ERJ3GEYJ101V	MGF CHIP 1/16W 100	
R9054	ERJ3GEY0R00V (A,B,C)	MGF CHIP 1/16W 0	●
R9055	ERJ3GEY0R00V (D)	MGF CHIP 1/16W 0	●
R9101	ERJ3GEYJ102V	MGF CHIP 1/16W 1K	
R9102	ERJ8GEY0R00V	MGF CHIP 1/8W 0	●
VR9001	VRVW0024 (A,B,C)	VARIABLE 10K	
	VRVW0026 (D)	VARIABLE 10K	

CAPACITORS

Ref. No.	Part No.	Part Name & Description	Remarks
C1201	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C1202	ECUV1C104KBV	C CHIP 16V 0.1	
C1203	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C1204	ECUV1A105KBN	C CHIP 10V 1	
C1205	ECUV1C104KBN	C CHIP 16V 0.1	
C1206	ECUV1H102KBV	C CHIP 50V 1000P	
C1207	ECST0JY106	TANTALUM CHIP 6.3V 10	
C1208	ECUV1H102KBV	C CHIP 50V 1000P	
C1209	ECUV1C224KBN	C CHIP 16V 0.22	
C1210	ECUV1A105KBN	C CHIP 10V 1	
C1211	ECUV0J225KBN	C CHIP 6.3V 2.2	
C1212	VCUSJEA224KB	C CHIP 10V 0.22	
C1213	ECUV1A105ZFB	C CHIP +80%-20% 10V 1	
C1214	ECUV1H101JCV	C CHIP +-5% 50V 100P	
C1216	ECUV1H472KBV	C CHIP 50V 4700P	
C1217	ECUE1H121JCV	C CHIP +-5% 50V 120P	
C1218	VCUSQAC225KB	C CHIP 16V 2.2	
C1219	VCUSQAC105KB	C CHIP 16V 1	
C1220	VCUSQBC105KB	C CHIP 16V 1	
C1221	ECUV1A105KBN (A,B,C)	C CHIP 10V 1	
	ECUV0J225KBN (D)	C CHIP 6.3V 2.2	
C1223	ECUV1C105ZFN	C CHIP +80%-20% 16V 1	
C1224	ECUV1E105KBM	C CHIP 25V 1	
C1225	VCUSQAE105ZF	C CHIP +80%-20% 25V 1	
C1226	ECUV1C104KBN	C CHIP 16V 0.1	
C1227	ECUV1C104KBN	C CHIP 16V 0.1	
C1228	ECUV1E103KBV	C CHIP 25V 0.01	
C9003	ECST0JX226 (A,B,C)	TANTALUM CHIP 6.3V 22	
C9005	ECST0JY106	TANTALUM CHIP 6.3V 10	
C9007	ECUV1C104KBV	C CHIP 16V 0.1	
C9008	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C9009	NMA0J226MTR	ELECTROLYTIC CHIP 6.3V 22	
C9010	ECUV1H681KBV (A,B,C)	C CHIP 50V 680P	
C9011	ECUV1C104KBV	C CHIP 16V 0.1	
C9012	ECUV1C104KBV	C CHIP 16V 0.1	
C9013	VCUSJBJ225KB	C CHIP 6.3V 2.2	
C9014	ECUV1H152KBV	C CHIP 50V 1500P	
C9015	ECST0JY475	TANTALUM CHIP 6.3V 4.7	
C9016	NMA0J226MTR	ELECTROLYTIC CHIP 6.3V 22	
C9017	VCUSJBJ225KB	C CHIP 6.3V 2.2	
C9018	ECUV1C104KBV	C CHIP 16V 0.1	
C9019	ECST1CX106	TANTALUM CHIP 16V 10	
C9020	VCUSJBJ225KB	C CHIP 6.3V 2.2	
C9021	VCUSJBJ225KB	C CHIP 6.3V 2.2	
C9022	VCUSJBJ225KB	C CHIP 6.3V 2.2	

Ref. No.	Part No.	Part Name & Description	Remarks
C9023	ECST1DX106R	TANTALUM CHIP 20V 10	
C9024	VCUSJBJ225KB	C CHIP 6.3V 2.2	
C9025	ECUV1H151JCV	C CHIP +-5% 50V 150P	
C9026	VCUSJBJ225KB	C CHIP 6.3V 2.2	
C9027	ECUV1C104KBV	C CHIP 16V 0.1	
C9028	VCUSQBC105KB	C CHIP 16V 1	
C9029	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C9030	ECST0JY106	TANTALUM CHIP 6.3V 10	
C9031	ECST0JY106	TANTALUM CHIP 6.3V 10	
C9032	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C9033	ECST0JX226 (D)	TANTALUM CHIP 6.3V 22	
C9035	VCUSQBA105KB (D)	C CHIP 10V 1	
C9037	ECUV1H152KBV (D)	C CHIP 50V 1500P	
C9038	ECUV1H270JCV (D)	C CHIP +-5% 50V 27P	
C9039	ECUV1H103ZFB (D)	C CHIP +80%-20% 50V 0.01	
C9040	ECUV1E273ZFB (D)	C CHIP +80%-20% 25V 0.027	
C9041	VCUSQBA105KB (D)	C CHIP 10V 1	
C9042	ECUV1H102KBV (D)	C CHIP 50V 1000P	
C9043	ECUV1E103KBV (D)	C CHIP 25V 0.01	
C9044	ECUV1C104ZFB	C CHIP +80%-20% 16V 0.1	
C9046	ECUV1H102KBV (D)	C CHIP 50V 1000P	
C9047	ECUV1C104ZFB (D)	C CHIP +80%-20% 16V 0.1	
C9048	ECUV1C104KBV (D)	C CHIP 16V 0.1	
C9049	ECUV1C104KBV (D)	C CHIP 16V 0.1	
C9050	ECUV1H103ZFB (D)	C CHIP +80%-20% 50V 0.01	
C9101	EEFCD0J220R	TANTALUM CHIP 6.3V 22	
C9102	ECHU1H393JB5	C CHIP +-5% 50V 0.039	
C9103	VCCW0008	C CHIP	

COILS

Ref. No.	Part No.	Part Name & Description	Remarks
L1201	VLQ0319K100	CHIP 10	
L1202	NP05DB100M	+ -20% 10	
L1203	VLJW3TC100KT	CHIP 10	
L1204	VLQ0426J470	CHIP +-5% 47	
L1205	VLQ0426J470	CHIP +-5% 47	
L1206	VLQ0426J470 (A,B,C)	CHIP +-5% 47	
	VLQ0426J150 (D)	CHIP +-5% 15	
L1207	VLQ0426J150	CHIP +-5% 15	
L9001	VLQ0464K150	CHIP 15	
L9002	VLQ0464K150	CHIP 15	
L9003	VLQ0163J150	CHIP +-5% 15	
L9004	VLQ0464K150	CHIP 15	
L9005	VLQ0426J150	CHIP +-5% 15	
L9006	VLQ0464K150	CHIP 15	
L9007	VLQ0426J150	CHIP +-5% 15	
L9008	VLQ0464K150 (D)	CHIP 15	
L9101	SLF6028T680M	CHOKE +-20% 68	△

CRYSTAL OSCILLATOR

Ref. No.	Part No.	Part Name & Description	Remarks
X9001	LSSX0031 (D)		

FPC CONNECTOR

Ref. No.	Part No.	Part Name & Description	Remarks
FP1201	LSJS01EC021	CONNECTOR 21P	
FP9001	LSJSQG24DG	CONNECTOR 24P	

TRANSFORMER

Ref. No.	Part No.	Part Name & Description	Remarks
T1202	LSTP0094		
T9101	LSLT0030		△

MISCELLANEOUS

Ref. No.	Part No.	Part Name & Description	Remarks
E44	VMZW0650	INSULATION SHEET, PLASTIC	

12.3.10. RELAY C.B.A. ■

PIN HEADERS

Ref. No.	Part No.	Part Name & Description	Remarks
P9001	VJPW0242	CONNECTOR 13P	

FPC CONNECTOR

Ref. No.	Part No.	Part Name & Description	Remarks
FP9002	LSJSQG18DG	CONNECTOR 18P	

Ref. No.	Part No.	Part Name & Description	Remarks
E9	LSEP8051A1	TV TUNER JACK C.B.A.	RTL
E16	VMDW0430	CCD SURFACE PLATE, POLYESTER	
E16	VMDW0515	CCD SURFACE PLATE, POLYESTER	
E18	VEKW1639	CRT SOCKET UNIT	
E22	VJBW1626F	CYLINDER CABLE W/OUT PLUG, DC5V	
E27	ELY05V583A1	DEFLECTION YOKE	△
E33	M01LSX07WB01	CRT	△
E34	VMZW0606	INSULATION SHEET, PLASTIC	
E37	LSEK0375	EVF CABLE W/PLUG, DC5V	
E36	VEKW1781	EVF CABLE W/PLUG, DC15V	
E41	VULS0001	LAMP KIT	△
E44	VMZW0650	INSULATION SHEET, PLASTIC	
E46	VEKW1791	PC JACK CABLE W/PLUG	
E46	LSEK0363	PC/TV TUNER JACK CABLE W/PLUG	
E47	LSLP0064	FERRITE CORE	
E48	LSMA0417	FIXING ANGLE	
E49	XQN2+BF3FXK	SCREW, STEEL	
E52	LSEP8031A1	LIQUID CRYSTAL DISPLAY C.B.A.	RTL
E52	LSEP8031B1	LIQUID CRYSTAL DISPLAY C.B.A.	RTL
E53	LSEP8033A1	RELAY C.B.A.	
E64	VEKW1782	LCD CABLE W/PLUG, DC5V	

12.3.11. ELECTRICAL PARTS LOCATED ON CHASSIS

Ref. No.	Part No.	Part Name & Description	Remarks
IC3501	AN3365SB-E1	IC, LINEAR HEAD AMP	
	(A, B)		
IC3501	AN3368SB-E1	IC, LINEAR HEAD AMP	
	(C, D)		
E6	LSEQ0540	MECHANISM FLEXIBLE PRINTED CIRCUIT UNIT	
E22	VJBW1626F	CYLINDER CABLE W/OUT PLUG, DC5V	
E41	VULS0001	LAMP KIT	△
E46	VEKW1791	PC JACK CABLE W/PLUG	
	(A, B, C)		
E46	LSEK0363	PC/TV TUNER JACK CABLE W/PLUG	
	(D)		
E47	LSLP0064	FERRITE CORE	
	(D)		
E48	LSMA0417	FIXING ANGLE	
	(D)		
E49	XQN2+BF3FXK	SCREW, STEEL	
	(D)		
E64	VEKW1782	LCD CABLE W/PLUG, DC5V	

12.3.12. SUMMARY OF "E" ITEM NUMBERS

REFER TO ELECTRICAL PARTS LIST FOR MODEL INFORMATION

Ref. No.	Part No.	Part Name & Description	Remarks
E1	LSEP8026A1	MAIN C.B.A.	RTL
E1	LSEP8026F1	MAIN C.B.A.	RTL
E1	LSEP8026E1	MAIN C.B.A.	RTL
E1	LSEP8026B1	MAIN C.B.A.	RTL
E2	LSEQ0548	CCD C.B.A.	RTL
E2	LSEQ0571	CCD C.B.A.	RTL
E3	LSEQ0558	ELECTRONIC VIEWFINDER C.B.A.	RTL
E4	LSEP8035A1	COLOR ELECTRONIC VIEWFINDER A C.B.A.	RTL
E5	VEPW1671A1	COLOR ELECTRONIC VIEWFINDER B C.B.A.	RTL
E6	LSEQ0540	MECHANISM FLEXIBLE PRINTED CIRCUIT UNIT	
E8	LSEP8050A1	PC JACK C.B.A.	RTL