

STRICTLY CONFIDENTIAL
 For Philips
 Service Dealers only
 Copyright

Published by
 THE CENTRAL SERVICE DIVISION
 N.V. Philips' Gloeilampenfabrieken
 Eindhoven

PHILIPS

SERVICE NOTES

A3 768 85

(FM TUNER)

Range, alcance, bereik, gamme, Bereich	87,5-100 Mc/s (3,43-3m)
I.F. F.I. M.F. M.F. Z.F.	10,7 Mc/s
Dimensions, dimensiones, afmetingen, dimensions, Abmessungen	85x58x93 mm

Parts list, lista de piezas, lijst van onderdelen, liste de pièces, Ersatzteilliste.

S50)		A3 803 74	C80	13 pF	904/12E
S51)			C81	1500 pF	904/1K5
S52)			C82	2,2 pF	904/P2E2
S53)		A3 119 79	C83	33 pF	904/33E
S54)			C84)		
S55)			C92)		49 002 23
S58)		A3 127 82	C85	12 pF	904/12E
S59)			C86	6 pF	908/10E
R60	180 Ω	900/180E	C87	220 pF	904/220E
R61	56 Ω	900/56E	C88	12 pF	904/12E
R62	1 MΩ	900/1M	C89	6 pF	908/10E
R63	2200 Ω	E 001 A3/A2K2	C90	100 pF	904/100E
R64	10000 Ω	E 001 A3/A10K	C91	.933 pF	B1 513 23
			C93	10000 pF	904/10K
			C94	12 pF	904/12E
			C95	2200 pF	B1 664 25
			C96	2200 pF	B1 664 25
			C97	2200 pF	B1 664 25
			C98	24 pF	905/24E

ALIGNMENT, ALINEACION, AFREGELLEN, REGLAGE, ABGLEICH

Pointer to	Unmodulated signal	Connect oscillator to	Trim	Indication diode-voltmeter
Aguja de	Señal no modulado	Oscilador de servicio	Ajústese	Indicación voltímetro a diode
Wijzer op	Ongemoduleerd signaal	Oscillator aan	Afregelen	Aanwijzing diode-voltmeter
Aiguille à	Signal non-modulé	Relier oscilateur à	Régler	Consigne volt-mètre à diode
Zeiger auf	Unmoduliertes signal	Oszillator an	Abgleichen	Anweisung Diodenvoltmeter
87,5 Mc/s	10,7 Mc/s	⌊ ⚡	S58	Max.
87,5 Mc/s	87,5 Mc/s	⌊ ⚡	S55 S56-57	Max.
100 Mc/s	100 Mc/s	⌊ ⚡	C86 C89	Max.





