

Network Management Of:

- ▶ Powerware 9170
- ▶ FERRUPS®
- ▶ UNITY/1 Three Phase
- ▶ UNITY/I® Single-Phase
- ▶ Axxium Pro
- ▶ Axxium™ Rackmount
- ▶ Best® 610
- ▶ Fortress®
- ▶ Patriot® Pro II

BestLink™ SNMP/ WEB Adapter

Hardware for remote management.



Improved Remote Power Management

Best Power's BestLink SNMP/WEB Adapter is a network adapter for Uninterruptible Power Systems that provides both SNMP and HTTP compatibility. This allows you to easily monitor, manage and, if necessary, safely shut down remote UPS-protected servers, routers, hubs, and other key inter-networking devices in a controlled manner. BestLink SNMP/WEB Adapters provide a self-contained link between the Best Power UPS and an Ethernet LAN/WAN, allowing your UPS to be remotely monitored and controlled from the next room, the next building, or the next state...with no additional overhead on any server. These dedicated adapters provide the essential network connection and pathway between UPS and any industry-standard network management platform or popular Web browser. BestLink also controls automatic shutdown of protected computer systems with the use of NetWatch client software.

Expanded Network Communication

By utilizing the supplied MIB (Management Information Base) for UPSs, real-time monitoring and control of power protection across your LAN or WAN is achievable by using third-party network management software. The same network management software used to manage your other SNMP-compatible devices such as SunNet Manager, Novell Manage Wise, HP-OpenView, NetView 6000, and others,

may be used to manage the UPS. And even if your protected device goes down, the UPS can still communicate with you via the BestLink SNMP/WEB Adapter. You may even be able to use the UPS to reboot the device. You can also remotely change UPS-related parameters, tailoring them to your specific requirements, as well as display 176 MIB variables such as line voltage and frequency, battery voltage, UPS load, and various alarms.

Easier Network Management

Best Power's BestLink SNMP/WEB Adapters expand your control and visibility throughout the network, and allow you to track power-related problems anywhere on the network. Along with managing the servers, routers, hubs, and other network devices, the UPS can also be monitored and controlled. BestLink's HTTP compatibility means that you can simplify your management process by using a web browser such as Netscape® or Internet Explorer®.

BestLink™ SNMP/ WEB Adapter

| Model | BestLink™ SNMP/WEB Adapter | | | SNMP-3 |
|--|---|-------------------------------|---|--|
| Part No. | IPK-0318 | IPK-0319 | IPK-0320 | IPK-0033 |
| Description | Provides both SNMP and HTTP compatibility to UPS applications. External UnitInternal Card | | | Supporting UPS-to-Ethernet integration for three-phase UPS applications. |
| Network Connections | Ethernet 10BaseT | | | One Ethernet 10BaseT, one 10Base2. |
| UPS Compatibility | Patriot® Pro II, all Fortress® models, Powerware 9170, all FERRUPS® models, Axxium™ Pro, Axxium™ Rackmount, Best® 610*, UNITY/I® Three-Phase, UNITY/I® Single-Phase | | All Fortress models, Powerware 9170, Axxium Rackmount, Axxium Pro, Best 610, FERRUPS 800 Series | UNITY/I Three-Phase |
| Network Protocol | SNMP over UDP/IP, HTTP over TCP/IP, ARP, RARP and TFTP | | | SNMP over UDP/IP |
| Supported MIB | MIB_II, BestLink_MIB (bestpwr2.mib) | | | Best Power |
| OS Supported for Shutdown | Microsoft Windows 9x, 2000 & NT, Various UNIX versions, Novell NetWare | | | None |
| Operating Temperature | 0 to 40° C | | | |
| Operating Humidity | 10 to 80%, non-condensing | | | |
| Power Input | 120V AC 60Hz | 115V or 230V AC 50 to 60Hz | 12V DC | 120V AC 60Hz |
| Power Consumption | 9.5 Watts | | | |
| Dimensions (inches) | 5.3 x 3.4 x 1.1 | | 5.3 x 3.2 x 1.3 | 6.0 x 3.5 x 1.25 |
| LxWxH (mm) | 134 x 86 x 27 | | 134 x 81 x 33 | 152.4 x 88.9 x 31.75 |
| Weight | 7 oz. | | | |
| Regulatory | FCC class A, UL, CUL, CE | | | FCC Part 15, UL, CSA |
| All specifications subject to change without notice. | | | | |

* Requires INT-0073 Interface Cable.

Invensys Power Systems
8609 Six Forks Road
Raleigh, NC 27615 U.S.A.
Toll Free: 1.877.797.9273
or 919.872.3020
Fax: 1.800.753.9433
www.invensys-power.com

Best Power
P.O. Box 280
Necedah, WI 54646 USA
1-800-356-5794
www.bestpower.com

LTP-0267
Reprint 5/01
Revision 12/00

