



# TT-10188 Digital Pulse Distribution Amplifier



## Key Features

- DC – 20 MHz Frequency Range
- 16 digital outputs
- Can be used as a 1 pps distribution amplifier
- Alarm indicators for each channel
- Output level TTL or 2.5 V p-p into 50  $\Omega$ .
- Input Impedance adjustable from 50  $\Omega$  to 2 k $\Omega$
- Output to output skew < 150 ps
- AC and DC power supplies

## General Description

The TT-10188 is a digital distribution amplifier designed for digital signals. An input signal is distributed to sixteen output channels. The outputs channels are all isolated from each other, as well as protecting the input signal from any shorts or load changes applied to the outputs. The frequency range extends down to DC. Thus this amplifier is ideal for 1 pps (pulse per second) signals. It can be used to synchronize up to sixteen instruments to a frequency reference input. The reference input will typically be a 1 pps signal or an OXCO, Rubidium, Caesium or Hydrogen Maser Frequency Standard. Typical frequencies are 1 pps, 5 and 10 MHz, but any frequency from DC to 20 MHz can be used.

## Alarms

Every output has LED alarm monitoring. Should the RF level drop on any output, a LED alarm will be raised.

## Applications

The TT-10188 Distribution Amplifier is ideal for use in calibration or standard laboratories, space research, satellite systems, communication systems or anywhere where good performance is needed.

## Miscellaneous Information

The TT-10188 is a highly reliable unit. The TT-10188 is housed in a fully screened 19" rack mount case and operates from a 115 / 230 VAC supply. The TT-10188 is CE marked for sale within the EEC.

## Matched Propagation Delay times

The TT-10188 is ideal for pulse distribution since every output is matched to each other to within a 150 ps variance. So the TT-10188 can be used in timing distribution with the satisfaction of knowing the timing parameters will be preserved.

## Fast Rise / Fall Times

TT-10188 has very fast rise and fall times of < 1 ns. The TT-10188 will improve the rise time of slow rise-time inputs. For example an input rise time of 25 ns will result in output rise times of < 1 ns (800 ps).

## Other Distribution Amplifiers

Precision Test Systems also manufactures the PTS50 and DA series of distribution amplifiers operating from 1 to 100 MHz. The series includes our ultra low phase noise DA1-100-10 distribution amplifier.

### TT-10188 SPECIFICATIONS

Specification Parameter	Specification	Comments
<b>Input</b>		
Frequency	DC to 20 MHz	1 pps signals accepted
Impedance	50 $\Omega$ to 2 k $\Omega$ adjustable	
Input Level	0VDC min, 10 VDC max	
Trigger level	Adjustable from 0.6 V to 5V	+ve trigger. -ve trigger on request
<b>Sinewave Outputs</b>		
Number of outputs	16	BNC Sockets
Output Level	TTL (unloaded), 2.5 V p-p (50 $\Omega$ )	
Output Impedance	50 $\Omega$	
Significant Slope	Signal is non-inverted	
Pulse Duration	Same as input, nominal 20 $\mu$ s	
Rise / Fall Time	< 1 ns	<800 ps typical
Output to Output Time Matching	< 150 ps	< 100 ps typical
Delay Variation	< 3 ps	
Overall propagation delay	20 $\pm$ 2 ns	
Temperature Coefficient	10 ps / $^{\circ}$ C	10 $^{\circ}$ C to 50 $^{\circ}$ C
<b>General</b>		
Power (AC)	100 - 240 VAC (usable 90 - 260 VAC)	15 Watts max
Power DC	18 to 36 VDC isolated	AC Supply is dominant. Auto switchover
Size and weight	483 x 448 x 44 mm and 2.8 kg	Width x Depth x Height
Ambient Operating Temperature	-10 $^{\circ}$ C to +50 $^{\circ}$ C	
Alarm Output	Alarm LEDs on front panel	
<b>Precision Test Systems</b>		
<b>Head Office - UK</b>	<b>South Africa</b>	<b>USA</b>
Precision Test Systems LTD 40 Holkham Avenue, South Woodham Ferrers Essex, CM3 7AU, England Tel: +44 (0) 845 052 0920 Fax: +44 (0) 870 135 4973 Email: uksales@ptsyst.com Web: www.ptsyst.com	Precision Test Systems cc P.O Box 1344 Witkoppen 2068 South Africa Tel: +27 (0) 11 464 3778 Email: sasales@ptsyst.com Web: www.ptsyst.com	Precision Test Systems 14781 Memorial Dr, Suite # 981 Houston Texas, 77079, USA Tel: 1 888 876 4804 Fax: 1 760 923 6354 Email: usasales@ptsyst.com Web: www.ptsyst.com

Full specifications available from [www.ptsyst.com](http://www.ptsyst.com). Specifications and features subject to change without notice (200607)