


## 7. Electric Parts List

### 7-1 CB5320T5X (CB5020T5X AND CB5320T5X Dissimilar Parts)

| Loc. No.              | Code No.    | Description ; Specification                  | Remark  | Loc. No.                               | Code No. | Description ; Specification                           | Remark |
|-----------------------|-------------|--|---|--|----------|---|--------|
| <b>ASSY-PCB,MAIN</b>  |             |  |   | <b>ASSY-CRT</b>                        |          |   |        |
|                       |             | BUYER : AMFO                                 |   |  |          | AA03-10031E CRT-COLOR;- ,A51EERX131X,+400MG,21,90DEG  |        |
| *                     | HA94-100141 | ASSY-PCB,MAIN:CB5320T5X/AMF,S15A             |  |  |          | AA27-50005G DEFLECTION-YOKE;- ,DST-21944(2),21/A51EE  |        |
|                       |             | BUYER : AUTRONIC                             |   | <b>ASSY-CABINET OPTION (CB5320T5X)</b> |          |   |        |
| *                     | HA94-100142 | ASSY-PCB,MAIN:CB5320T5X/AUT,S15A             |   |  |          | HA91-100008 ASSY-CABINET,FRONT:5320,HITRON BLACK      |        |
|                       |             | BUYER : EUROPARTRAD                          |   |  |          | HA64-300010 CABINET-FRONT:DP,5320,- ,HIPS,HB,BLK,-,-  |        |
| *                     | HA94-100143 | ASSY-PCB,MAIN:CB5320T5X/EUP,S15A             |   |  |          | AA65-30019A CLAMP-D,COIL;- ,NYLON,V0,NTR,DADH-460     |        |
|                       |             | BUYER : INTRADE                              |   |  |          | HA60-020002 SCREW-TAPPING:DP,RH,+ ,2,M4,L15,ZPC(BLK), |        |
| *                     | HA94-100144 | ASSY-PCB,MAIN:CB5320T5X/INT,S15A             |   |  |          | AA63-50303A GRILLE-WOOFER:DP,AA63-50193A,5320         |        |
|                       |             | BUYER : SECOSA                               |   |  |          |   |        |
| *                     | HA94-100114 | ASSY-PCB,MAIN:CB5320T5X/XEC,S15A             |   |  |          |   |        |
|                       |             | BUYER : SESAB                                |   |  |          |   |        |
| *                     | HA94-100146 | ASSY-PCB,MAIN:CB5320T5X/XEE,S15A             |   |  |          |   |        |
|                       |             | BUYER : SEP                                  |   |  |          |   |        |
| *                     | HA99-100118 | ASSY-PCB,MAIN:CB5320T5X/XEP,S15A             |   |  |          |   |        |
|                       |             | BUYER : SEI                                  |   |  |          |   |        |
| *                     | HA94-100149 | ASSY-PCB,MAIN:CB5320T5X/XET,S15A             |   |  |          |   |        |
| C409                  | 2306-000253 | C-FILM,MPPF;7.2NF,5% 1.6KV 28.5X18.5X20      |   |  |          |   |        |
| C410                  | 2201-000406 | C-CERAMIC,DISC;270PF,10%,2KV,Y5P8X5.5TP      |   |  |          |   |        |
| C419                  | 2201-000984 | C-CERAMIC,DISC;680PF,10%,2KV,Y5P,TP,11X      |   |  |          |   |        |
| CN802                 | AA27-20003Z | COIL-DEGAUSSING;- ,21,13.5OHM,25T,L2380      |   |  |          |   |        |
|                       |             | BUYER : INTRADE (ONLY)                       |   |  |          |   |        |
| L801                  | AA29-30002K | FILTER-LINE;- ,80MH,-084A,- (INTRADE)        |   |  |          |   |        |
| LW01                  | AA27-40001N | COIL-HORIZ,WIDTH;- ,90/260UH,SB-5S620,PIO    |   |  |          |   |        |
| R301                  | 2004-000869 | R-METAL;3KOHM,1%,1/8W,AA,TP,1.8X3.2MM        |   |  |          |   |        |
| R305                  | 2001-001048 | R-CARBON(S);1.2OHM,5%,1/2W,AB,TP,2.4X6.4     |   |  |          |   |        |
| R307                  | 2003-001026 | R-METAL,OXIDE(S);180OHM,5%,2W,AF,TP,3.9X     |   |  |          |   |        |
| <b>ASSY-ACCESSORY</b> |             |  |   |  |          |   |        |
|                       |             | BUYER : AMFO (ONLY)                          |   |  |          |   |        |
|                       | HA68-100050 | MANUAL-USERS;- ,A/P 80(G),ENG,GER,DAN,FRA    |   |  |          |   |        |
|                       |             | BUYER : AUTRONIC (ONLY)                      |   |  |          |   |        |
|                       | AA68-11264A | MANUAL-USERS:S15A,GERMANY,TTX,B5,W/P         |   |  |          |   |        |
|                       | AA68-11266A | MANUAL-USERS:S15A,ITALY,TTX,B5,W/P           |   |  |          |   |        |
|                       | AA68-11288A | MANUAL-USERS:S15A,FRE(SEF),TTX,B5,W/P        |   |  |          |   |        |
|                       |             | BUYER : EUROPARTRAD / INTRADE (ONLY)         |   |  |          |   |        |
|                       | AA68-11262A | MANUAL-USERS:S15A,ENGLISH,TTX,B5,W/P         |   |  |          |   |        |
|                       | AA68-11264A | MANUAL-USERS:S15A,GERMANY,TTX,B5,W/P         |   |  |          |   |        |
|                       |             | BUYER : SECOSA (ONLY)                        |   |  |          |   |        |
|                       | AA68-11274A | MANUAL-USERS:S15A,SPANISH,TTX,B5,W/P         |   |  |          |   |        |
|                       |             | BUYER : SESAB (ONLY)                         |   |  |          |   |        |
|                       | HA68-100054 | MANUAL-USER:A/P 80(G),SWE,FIN,NOR,CB5        |   |  |          |   |        |
|                       |             | BUYER : SEI / SEP (ONLY)                     |   |  |          |   |        |
|                       | HA68-100052 | MANUAL-USERS;- ,A/P 80(G),ITA,SPA,POR,CB5073 |   |  |          |   |        |
|                       | AA68-20052A | MANUAL-S/D:S15A,W/P 100(G)-,ITALIAN,-,-      |   |  |          |   |        |




## 7-2 CB5020T5X Parts List

| Loc. No.             | Code No.    | Description ; Specification                       | Remark | Loc. No. | Code No.    | Description ; Specification                       | Remark |
|----------------------|-------------|---|--------|----------|-------------|---|--------|
| <b>ASSY-PCB,MAIN</b> |             |   |        | C414     | 2301-001065 | C-FILM,MPPF:47NF,5%,630V,TP,19X15.5X7,7.5         |        |
|                      |             | BUYER : SEI                                       |        | C415     | 2401-000560 | C-AL:1UF,20%,160V,GP,TP,6.3*11.5MM                |        |
| *                    | HA94-100210 | ASSY-PCB,MAIN:CB5020T5X/XET,S15A                  |        | C416     | 2306-000204 | C-FILM,MPPF:430NF,5%,400V,-,20MM,TP               |        |
|                      |             | BUYER : AMFO                                      |        | C417     | 2201-000556 | C-CERAMIC,DISC:470PF,10%,500V,Y5P,6X3.5MM,5MM     |        |
| *                    | HA94-100202 | ASSY-PCB,MAIN:CB5020T5X/AMF,S15A                  |        | C418     | 2401-000384 | C-AL:10UF,20%,100V,GP,TP,6.3X11.5MM               |        |
|                      |             | BUYER : AUTRONIC                                  |        | C419     | 2201-000983 | C-CERAMIC,DISC:1NF,10%,2KV,Y5P,8X5,5,TP           |        |
| *                    | HA94-100203 | ASSY-PCB,MAIN:CB5020T5X/AUT,S15A                  |        | C502     | 2301-000213 | C-FILM,PEF:220NF,5%,250V,21.5X11MM,17.5MM         |        |
|                      |             | BUYER : EUROPARTRAD                               |        | C503     | 2201-002063 | C-CERAMIC,DISC:10NF,-20,+80%,3KV,Y5V,TP,16X5,     |        |
| *                    | HA94-100204 | ASSY-PCB,MAIN:CB5020T5X/EUP,S15A                  |        | C504     | 2401-001232 | C-AL:4.7UF,20%,250V,GP,10X12.5MM,5M               |        |
|                      |             | BUYER : SESOSA                                    |        | C506     | 2401-000430 | C-AL:10UF,20%,250V,GP,TP,10X16MM,5M               |        |
| *                    | HA94-100108 | ASSY-PCB,MAIN:CB5020T5X/XEC,S15A                  |        | C601     | 2202-000210 | C-CERAMIC,MLC-AXIAL:270PF,10%,50V,Y5P,-,7.5MM,TP  |        |
|                      |             | BUYER : SEP                                       |        | C602     | 2401-000939 | C-AL:22UF,20%,25V,GP,TP,5X11MM,5                  |        |
| *                    | HA94-100209 | ASSY-PCB,MAIN:CB5020T5X/XEP,S15A                  |        | C603     | 2301-000108 | C-FILM,PEF:1.5NF,5%,50V,6.5X3.0X5.5MM,5MM         |        |
|                      |             | BUYER : INTRADE                                   |        | C604     | 2401-001323 | C-AL:470NF,20%,50V,BP,6X11MM,5MM,TP               |        |
| *                    | HA94-100206 | ASSY-PCB,MAIN:CB5020T5X/INT,S15A                  |        | C610     | 2401-001998 | C-AL:1000UF,20%,25V,GP,TP,10X20,5MM               |        |
| C101                 | 2401-000939 | C-AL:22UF,20%,25V,GP,TP,5X11MM,5                  |        | C611     | 2301-000108 | C-FILM,PEF:1.5NF,5%,50V,6.5X3.0X5.5MM,5MM         |        |
| C102                 | 2401-001082 | C-AL:330NF,20%,50V,GP,5X11MM,5MM,TP               |        | C612     | 2401-001323 | C-AL:470NF,20%,50V,BP,6X11MM,5MM,TP               |        |
| C103                 | 2401-001363 | C-AL:470UF,20%,16V,GP,TP,10X12.5MM,               |        | C613     | 2202-000796 | C-CERAMIC,MLC-AXIAL:1NF,10%,50V,Y5P,TP,5.5X19,-   |        |
| C201                 | 2306-000122 | C-FILM,MPPF:100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        | C614     | 2202-000210 | C-CERAMIC,MLC-AXIAL:270PF,10%,50V,Y5P,-,7.5MM,TP  |        |
| C203                 | 2401-000660 | C-AL:2.2 UF 20% 50V GP 5X11.5 TP                  |        | C702     | 2202-000263 | C-CERAMIC,MLC-AXIAL:470PF,10%,50V,Y5P,TP,3.5X19,- |        |
| C204                 | 2401-000603 | C-AL:1UF,20%,50V,GP,5X11MM,5MM,TP                 |        | C704     | 2202-000121 | C-CERAMIC,MLC-AXIAL:100PF,10%,50V,Y5P,1.9X3.5MM,- |        |
| C205                 | 2305-000411 | C-FILM,MPEF:470NF,5%,50V,7.3X4.8X5.5MM,5MM        |        | C705     | 2401-001264 | C-AL:4.7UF,20%,50V,BP,6X11MM,5MM,TP               |        |
| C206                 | 2305-000411 | C-FILM,MPEF:470NF,5%,50V,7.3X4.8X5.5MM,5MM        |        | C706     | 2401-001264 | C-AL:4.7UF,20%,50V,BP,6X11MM,5MM,TP               |        |
| C207                 | 2305-000196 | C-FILM,MPEF:150NF,5%,63V,TP,-,5MM                 |        | C800     | 2306-000320 | C-FILM,MPPF:470NF,20%,250V,TP,-,20MM              |        |
| C208                 | 2401-000027 | C-AL:4.7UF,20%,50V,GP,TP,5X11MM,5MM               |        | C801     | 2401-000534 | C-AL:150UF,20%,400V,GP,25X30,10,ST                |        |
| C209                 | 2202-000794 | C-CERAMIC,MLC-AXIAL:18PF,5%,50V,CH,TP,3.5X19MM    |        | C802     | 2401-002284 | C-AL:33UF,20%,50V,GP,TP,5X11MM,5MM                |        |
| C210                 | 2301-000108 | C-FILM,PEF:1.5NF,5%,50V,6.5X3.0X5.5MM,5MM         |        | C803     | 2301-000224 | C-FILM,PEF:22NF,5%,50V,7.4X3.9X13MM,5MM,T         |        |
| C211                 | 2305-000665 | C-FILM,MPEF:100NF,5%,63V,7.5X4.0X5.0MM,5MM        |        | C804     | 2301-000310 | C-FILM,PEF:68NF,5%,50V,8.0X8.5X4.0X5.5MM,         |        |
| C212                 | 2202-000796 | C-CERAMIC,MLC-AXIAL:1NF,10%,50V,Y5P,TP,5.5X19,-   |        | C805     | 2303-000163 | C-FILM,PPF:2.2NF,5%,800V,-,-,TP                   |        |
| C213                 | 2201-000273 | C-CERAMIC,DISC:18PF,5%,50V,NPO,5.0*3.0,2.5MM,     |        | C806     | 2201-000446 | C-CERAMIC,DISC:3.3NF,20%,400V,Y5U,TP,18X8,10M     |        |
| C214                 | 2301-000285 | C-FILM,PEF:47NF,5%,50V,7.5X4.0X6.5,5MM,TP         |        | C807     | 2201-000991 | C-CERAMIC,DISC:560PF 10% 2KV Y5P 8X5.5 TP         |        |
| C215                 | 2301-000380 | C-FILM,PEF:10NF,5%,50V,6.5X3MM,5MM,TP             |        | C808     | 2401-000262 | C-AL:100UF,20%,160V,GP,16X25MM,5MM,               |        |
| C216                 | 2305-000288 | C-FILM,MPEF:220NF,5%,50V,7.3X4.8X5.5MM,5MM        |        | C809     | 2401-002290 | C-AL:47UF,20%,160V,GP,TP,13X20MM,5M               |        |
| C217                 | 2301-000192 | C-FILM,PEF:1NF,5%,50V,5.3X10MM,5MM,TP             |        | C810     | 2201-000991 | C-CERAMIC,DISC:560PF 10% 2KV Y5P 8X5.5 TP         |        |
| C219                 | 2401-000603 | C-AL:1UF,20%,50V,GP,5X11MM,5MM,TP                 |        | C811     | 2401-003141 | C-AL:2200UF,20%,25V,WT,TP,13X25,5MM               |        |
| C221                 | 2202-000821 | C-CERAMIC,MLC-AXIAL:560PF,10%,50V,Y5P,TP,3.5X19,- |        | C814     | 2301-000192 | C-FILM,PEF:1NF,5%,50V,5.3X10MM,5MM,TP             |        |
| C222                 | 2401-000440 | C-AL:10UF,20%,25V,GP,5X11MM,5MM,TP                |        | C815     | 2401-000808 | C-AL:220UF,20%,16V,GP,8X11MM,5MM,TP               |        |
| C226                 | 2301-000224 | C-FILM,PEF:22NF,5%,50V,7.4X3.9X13MM,5MM,T         |        | C816     | 2401-000603 | C-AL:1UF,20%,50V,GP,5X11MM,5MM,TP                 |        |
| C228                 | 2201-000247 | C-CERAMIC,DISC:15PF,5%,50V,CH,TP,5X3,5            |        | C818     | 2401-001495 | C-AL:47UF,20%,16V,GP,5X11MM,5MM,TP                |        |
| C230                 | 2401-001495 | C-AL:47UF,20%,16V,GP,5X11MM,5MM,TP                |        | C819     | 2401-001840 | C-AL:100UF,20%,16V,GP,TP,8X11.5MM,5               |        |
| C231                 | 2401-000416 | C-AL:10UF,20%,16V,GP,TP,5X11,5MM                  |        | C901     | 2401-001840 | C-AL:100UF,20%,16V,GP,TP,8X11.5MM,5               |        |
| C232                 | 2401-001840 | C-AL:100UF,20%,16V,GP,TP,8X11.5MM,5               |        | C902     | 2202-000796 | C-CERAMIC,MLC-AXIAL:1NF,10%,50V,Y5P,TP,5.5X19,-   |        |
| C238                 | 2401-001495 | C-AL:47UF,20%,16V,GP,5X11MM,5MM,TP                |        | C904     | 2202-000796 | C-CERAMIC,MLC-AXIAL:1NF,10%,50V,Y5P,TP,5.5X19,-   |        |
| C239                 | 2305-000288 | C-FILM,MPEF:220NF,5%,50V,7.3X4.8X5.5MM,5MM        |        | C905     | 2401-001333 | C-AL:0.47UF 20% 50V,GP 5X11,5 TP                  |        |
| C247                 | 2202-002037 | C-CERAMIC,MLC-AXIAL:100NF,80-20%,50V,Y5P,TP,2.2X3 |        | C907     | 2201-000119 | C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,8X5MM,5M     |        |
| C248                 | 2309-000138 | C-FILM,PE-PPF:100NF,5%,50V,16X7MM,7.5MM,TP        |        | C908     | 2201-000980 | C-CERAMIC,DISC:30PF,5%,50V,NPO,5.0X3.0,5MM        |        |
| C249                 | 2401-000603 | C-AL:1UF,20%,50V,GP,5X11MM,5MM,TP                 |        | C909     | 2201-000980 | C-CERAMIC,DISC:30PF,5%,50V,NPO,5.0X3.0,5MM        |        |
| C250                 | 2301-000224 | C-FILM,PEF:22NF,5%,50V,7.4X3.9X13MM,5MM,T         |        | C910     | 2306-000122 | C-FILM,MPPF:100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        |
| C251                 | 2301-000204 | C-FILM,PEF:2.7NF,5%,50V,7.4X3.9X13MM,5MM,         |        | C911     | 2401-002235 | C-AL:10UF,20%,16V,GP,TP,5X11MM,5MM                |        |
| C252                 | 2301-000192 | C-FILM,PEF:1NF,5%,50V,5.3X10MM,5MM,TP             |        | C912     | 2201-000234 | C-CERAMIC,DISC:150PF,5%,50V,NPO,10X3.5MM,5MM,     |        |
| C253                 | 2306-000122 | C-FILM,MPPF:100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        | C913     | 2301-000108 | C-FILM,PEF:1.5NF,5%,50V,6.5X3.0X5.5MM,5MM         |        |
| C254                 | 2306-000122 | C-FILM,MPPF:100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        | C914     | 2306-000122 | C-FILM,MPPF:100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        |
| C255                 | 2306-000122 | C-FILM,MPPF:100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        | C915     | 2306-000122 | C-FILM,MPPF:100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        |
| C301                 | 2202-000253 | C-CERAMIC,MLC-AXIAL:4.7NF,20%,16V,Y5R,TP,1.9X3.5, |        | C916     | 2301-000108 | C-FILM,PEF:1.5NF,5%,50V,6.5X3.0X5.5MM,5MM         |        |
| C302                 | 2202-000253 | C-CERAMIC,MLC-AXIAL:4.7NF,20%,16V,Y5R,TP,1.9X3.5, |        | C917     | 2202-002037 | C-CERAMIC,MLC-AXIAL:100NF,80-20%,50V,Y5P,TP,2.2X3 |        |
| C303                 | 2401-003028 | C-AL:100UF,20%,25V,WT,TP,6.3X11.5MM               |        | C920     | 2401-000480 | C-AL:10UF,20%,50V,GP,5X11MM,5MM,TP                |        |
| C304                 | 2401-000903 | C-AL:22UF,20%,160V,WT,TP,10X20MM,5M               |        | C923     | 2202-002037 | C-CERAMIC,MLC-AXIAL:100NF,80-20%,50V,Y5P,TP,2.2X3 |        |
| C305                 | 2305-000178 | C-FILM,MPEF:10NF,5%,100V,-,5MM,TP                 |        | C924     | 2202-002037 | C-CERAMIC,MLC-AXIAL:100NF,80-20%,50V,Y5P,TP,2.2X3 |        |
| C306                 | 2305-000285 | C-FILM,MPEF:220NF,5%,100V,-,5MM,TP                |        | C926     | 2202-000796 | C-CERAMIC,MLC-AXIAL:1NF,10%,50V,Y5P,TP,5.5X19,-   |        |
| C307                 | 2305-000708 | C-FILM,MPEF:150NF,5%,100V,TP,16.5X10.3X5.7        |        | C928     | 2305-000412 | C-FILM,MPEF:470NF,5%,63V,-,5MM,TP                 |        |
| C308                 | 2305-000450 | C-FILM,MPEF:56NF,5%,100V,TP,-,5MM                 |        | CA01     | 2401-001264 | C-AL:4.7UF,20%,50V,BP,6X11MM,5MM,TP               |        |
| C401                 | 2301-000380 | C-FILM,PEF:10NF,5%,50V,6.5X3MM,5MM,TP             |        | CN501    | AA39-20109B | LEAD-CONNECTOR,ASSY:-,YBNH025-08,S,8P,500,1007#26 |        |
| C402                 | 2201-000599 | C-CERAMIC,DISC:560PF 10% 500V Y5P 6X4MM,5MM       |        | CN601    | 3711-002642 | CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGHT,SN      |        |
| C403                 | 2201-000556 | C-CERAMIC,DISC:470PF,10%,500V,Y5P,6X3.5MM,5MM     |        | CN602    | 3711-002643 | CONNECTOR-HEADER:BOX,4P,1R,2.5MM,STRAIGHT         |        |
| C404                 | 2401-001998 | C-AL:1000UF,20%,25V,GP,TP,10X20,5MM               |        | CN701    | 3711-000628 | CONNECTOR-HEADER:BOX,11P,1R,2.5MM,STRAIGHT        |        |
| C408                 | 2401-001530 | C-AL:47UF,20%,25V,GP,5X11MM,5MM,TP                |        | CN703    | 3711-002648 | CONNECTOR-HEADER:BOX,9P,1R,2.5MM,STRAIGHT         |        |
| C409                 | 2306-000355 | C-FILM,MPPF:7.4NF,5%,1.6KV,28.5X18.5X12.20        |        | CN802    | AA27-20003Y | COIL-DEGAUSSING:-,20,15,20HM,28T,L2170,E          |        |
| C410                 | 2201-000983 | C-CERAMIC,DISC:1NF,10%,2KV,Y5P,8X5,5,TP           |        | CT01     | 2202-002037 | C-CERAMIC,MLC-AXIAL:100NF,80-20%,50V,Y5P,TP,2.2X3 |        |
| C411                 | 2401-000927 | C-AL:22UF,20%,250V,GP,13X20MM,5MM,T               |        | CT02     | 2202-002037 | C-CERAMIC,MLC-AXIAL:100NF,80-20%,50V,Y5P,TP,2.2X3 |        |
| C413                 | 2305-000382 | C-FILM,MPEF:4.7NF,5%,400V,TP,-,5MM                |        | CT03     | 2401-001495 | C-AL:47UF,20%,16V,GP,5X11MM,5MM,TP                |        |
|                      |             |   |        | CT04     | 2202-002037 | C-CERAMIC,MLC-AXIAL:100NF,80-20%,50V,Y5P,TP,2.2X3 |        |
|                      |             |   |        | CT05     | 2202-000154 | C-CERAMIC,MLC-AXIAL:150PF,10%,50V,Y5P,TP          |        |
|                      |             |   |        | CT06     | 2202-002037 | C-CERAMIC,MLC-AXIAL:100NF,80-20%,50V,Y5P,TP,2.2X3 |        |

| Loc. No. | Code No.    | Description ; Specification                      | Remark | Loc. No. | Code No.    | Description ; Specification                    | Remark |
|----------|-------------|--|--------|----------|-------------|--|--------|
| CT07     | 2401-001495 | C-AL:47UF,20%,16V,GP,5X11MM,5MM,TP               |        | J176     | 2001-000857 | R-CARBON:560OHM 5% 1/8W AA TP 1.8X3.2MM        |        |
| CW901    | 2503-000156 | C-NETWORK:100PFX4,20%50V                         |        | J178     | 2001-000857 | R-CARBON:560OHM 5% 1/8W AA TP 1.8X3.2MM        |        |
| D201     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | J185     | 2701-000114 | INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM              |        |
| D202     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | JS701    | 3722-000183 | JACK-RCA:21P,4MM,-,SN                          |        |
| D205     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | L102     | 2701-000212 | INDUCTOR-AXIAL:68UH,10%,2.8X7MM                |        |
| D208     | 2001-000633 | R-CARBON:30KOHM,5%,1/8W,AA,TP,1.8X3.2MM          |        | L103     | 2701-000114 | INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM              |        |
| D209     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | L202     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| D210     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | L206     | 2701-000114 | INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM              |        |
| D211     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | L301     | 2701-000114 | INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM              |        |
| D401     | 0402-000132 | DIODE-RECTIFIER:1N4004,400V,1A,DO-41             |        | L302     | 2701-000114 | INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM              |        |
| D402     | 0402-000132 | DIODE-RECTIFIER:1N4004,400V,1A,DO-41             |        | L304     | 2701-000159 | INDUCTOR-AXIAL:22UH,10%,4.2X9.8MM              |        |
| D403     | 0402-001105 | DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP       |        | L305     | 2701-000116 | INDUCTOR-AXIAL:10 UH 10% 4.2X9.8MM             |        |
| D404     | 0402-000534 | DIODE-RECTIFIER:RG10V,400V,1.2A                  |        | L306     | 2701-000115 | INDUCTOR-AXIAL:10UH,10%,2.8X7MM                |        |
| D405     | 0402-001105 | DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP       |        | L401     | AA27-30001B | COIL-LINEARITY:-,195UH,QIC1010,PIO.4,4.5X21.5  |        |
| D406     | 0402-001105 | DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP       |        | L402     | 2901-000297 | FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-           |        |
| D501     | 0402-000216 | DIODE-RECTIFIER:ERC24-06,600V,1.0A,DO-204        |        | L601     | 2701-000146 | INDUCTOR-AXIAL:2.2UH,10%,2.5X3.4MM             |        |
| D502     | 0402-001105 | DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP       |        | L702     | 2701-000184 | INDUCTOR-AXIAL:4.7UH,                          |        |
| D503     | 0402-001105 | DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP       |        | L703     | 2701-000184 | INDUCTOR-AXIAL:4.7UH,                          |        |
| D504     | 0402-001105 | DIODE-RECTIFIER:ERB43-04SV1,400V,1.0A,-,TP       |        | L704     | 2701-000184 | INDUCTOR-AXIAL:4.7UH,                          |        |
| D701     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | L706     | 2701-000184 | INDUCTOR-AXIAL:4.7UH,                          |        |
| D800     | 1405-000152 | VARISTOR:560V,2500A,14X8,5MM,TP                  |        | L801     | AA29-30001G | FILTER-LINE:-,27MH,-,-,BUYER : INTRADE (ONLY)  |        |
| D801     | 0402-000102 | DIODE-BRIDGE:D2SB60,600V,1.5A,-                  |        | L801     | AA29-30002K | FILTER-LINE:-,80MH,-,084A,- (INTRADE)          |        |
| D802     | 0402-000540 | DIODE-RECTIFIER:RU20A,600V,1.5A,-                |        | L804     | 3301-000287 | CORE-FERRITE BEAD:AA,3.5X1.0X6.0MM,1500,2400G  |        |
| D803     | 0402-000430 | DIODE-RECTIFIER:FML-G02S,200V,2.5A,TO-220F       |        | L805     | 2901-000297 | FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-           |        |
| D804     | 0402-000213 | DIODE-RECTIFIER:ERB12-06,600V, 1A                |        | L807     | 2901-000297 | FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-           |        |
| D809     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | L809     | 2701-001032 | INDUCTOR-AXIAL:100UH,10%,5X14MM                |        |
| D810     | 0402-000216 | DIODE-RECTIFIER:ERC24-06,600V,1.0A,DO-204        |        | L810     | 2701-001032 | INDUCTOR-AXIAL:100UH,10%,5X14MM                |        |
| D901     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | L902     | 2701-000189 | INDUCTOR-AXIAL:470NH,10%,2.5X3.4MM             |        |
| D903     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | LD901    | AA96-30007A | ASSY-LED,GUIDE:-,AA61-50055A,DL-67GA, GREEN    |        |
| D905     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM           |        | LT01     | 2901-000297 | FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-           |        |
| D910     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | LT02     | 2901-000297 | FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-           |        |
| D911     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | LT03     | 2701-000114 | INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM              |        |
| DA01     | 0401-000005 | DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP        |        | NT801    | 1404-000187 | THERMISTOR-NTC:4.7 OHM,15% 2800K,27,2MMW/C,TP  |        |
| DZ201    | 0403-000355 | DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500mW       |        | P801     | 1404-001048 | THERMISTOR-PTC:70HM,30%,200/220V,270V,19A,-,B  |        |
| DZ202    | 0403-000551 | DIODE-ZENER:MTZ3.9B,3.9V,3.89-4.16V,500MW,       |        | PC801    | 0604-001038 | PHOTO-COUPLER:TR,130-260%,200MW,DIP-4,ST       |        |
| DZ203    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | Q201     | 0501-002183 | TR-SMALL SIGNAL:KTC9014,NPN,625MW,TO-92,TP,100 |        |
| DZ204    | 2001-000812 | R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M          |        | Q202     | 0501-002183 | TR-SMALL SIGNAL:KTC9014,NPN,625MW,TO-92,TP,100 |        |
| DZ205    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | Q204     | 0501-002183 | TR-SMALL SIGNAL:KTC9014,NPN,625MW,TO-92,TP,100 |        |
| DZ208    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | Q401     | 0502-001115 | TR-POWER:KSC5386,NPN,50W,TO-3PF,ST-8           |        |
| DZ301    | 0403-000660 | DIODE-ZENER:MTZ22A 22V 20 15-21 2V 500MW         |        | Q402     | 0501-000369 | TR-SMALL SIGNAL:KSC2331-Y NPN 80V 60V 700MA    |        |
| DZ302    | 0403-001039 | DIODE-ZENER:MA2560,56V,52-60,1W,DO-4             |        | Q701     | 0501-002183 | TR-SMALL SIGNAL:KTC9014,NPN,625MW,TO-92,TP,100 |        |
| DZ401    | 0403-000296 | DIODE-ZENER:MTZ 5.6B                             |        | Q703     | 0501-000283 | TR-SMALL SIGNAL:KSA539 PNP 60V 45V 200MA 40    |        |
| DZ501    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | Q901     | 0501-002183 | TR-SMALL SIGNAL:KTC9014,NPN,625MW,TO-92,TP,100 |        |
| DZ502    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | Q902     | 0501-002183 | TR-SMALL SIGNAL:KTC9014,NPN,625MW,TO-92,TP,100 |        |
| DZ503    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | Q903     | 0501-002183 | TR-SMALL SIGNAL:KTC9014,NPN,625MW,TO-92,TP,100 |        |
| DZ504    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | Q904     | 0504-000123 | TR-DIGITAL:KSR1010,NPN,300MW,10K,TO-92,TP      |        |
| DZ701    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | Q905     | 0504-000123 | TR-DIGITAL:KSR1010,NPN,300MW,10K,TO-92,TP      |        |
| DZ702    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | Q906     | 0504-000123 | TR-DIGITAL:KSR1010,NPN,300MW,10K,TO-92,TP      |        |
| DZ703    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | Q907     | 0504-000125 | TR-DIGITAL:KSR1012,NPN,300MW,47K,TO-92,TP      |        |
| DZ704    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | Q908     | 0504-000123 | TR-DIGITAL:KSR1010,NPN,300MW,10K,TO-92,TP      |        |
| DZ705    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | QA01     | 0501-002183 | TR-SMALL SIGNAL:KTC9014,NPN,625MW,TO-92,TP,100 |        |
| DZ802    | 0403-000297 | DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500MW,       |        | QT02     | 0501-002183 | TR-SMALL SIGNAL:KTC9014,NPN,625MW,TO-92,TP,100 |        |
| DZ803    | 1203-001217 | IC-POS:ADJUST REG:431,TO-92,3P,4.58MIL,PLASTIC,2 |        | QT03     | 0504-000123 | TR-DIGITAL:KSR1010,NPN,300MW,10K,TO-92,TP      |        |
| DZ804    | 2001-001170 | R-CARBON(S):6.8OHM,5%,1/2W,AA,TP,2.4X6.4MM       |        | R200     | 2001-000780 | R-CARBON:470 OHM 5% 1/8W AATP 1.8X3.2MM        |        |
| DZ806    | 0403-000355 | DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500mW       |        | R201     | 2001-000005 | R-CARBON:390OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| DZ808    | 0403-000300 | DIODE-ZENER:MTZ8.2B,7.78-8.19V,500MW,DO-34       |        | R202     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| DZ809    | 0403-000296 | DIODE-ZENER:MTZ 5.6B                             |        | R203     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| DZ901    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,       |        | R204     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| DZ902    | 0403-000296 | DIODE-ZENER:MTZ 5.6B                             |        | R205     | 2001-000793 | R-CARBON:470HM,5%,1/8W,AA,TP,1.8X3.2MM         |        |
| DZ903    | 1203-000451 | IC-VOLTAGE REGULATOR:33 TO 92.3P PLASTIC-31/35   |        | R207     | 2001-000008 | R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| DZ905    | 0403-000296 | DIODE-ZENER:MTZ 5.6B                             |        | R208     | 2001-000005 | R-CARBON:390OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| DZ907    | 0403-000296 | DIODE-ZENER:MTZ 5.6B                             |        | R209     | 2701-000114 | INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM              |        |
| DZ909    | 0403-000551 | DIODE-ZENER:MTZ3.9B,3.9V,3.89-4.16V,500MW,       |        | R210     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM         |        |
| F801     | 3601-000261 | FUSE-FERRULE:3.15A 250V                          |        | R211     | 2001-000331 | R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| F801A    | 3602-000114 | FUSE-HOLDER:-,30MOHM                             |        | R212     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| F801B    | 3602-000114 | FUSE-HOLDER:-,30MOHM                             |        | R213     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| F802     | 3601-001086 | FUSE-FERRULE:125V,5A,QUICK,CERAMIC               |        | R214     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| IC201    | 1204-001373 | IC-VIDEO PROCESS:TDA8841,DIP56P,PLASTIC,8.0V     |        | R215     | 2004-001995 | R-METAL:9.1KOHM,5%,1/8W,AA,TP,1.8X3.2M         |        |
| IC301    | 1204-000441 | IC-IF CIRCUIT:TDA8356,SIP,9P,-,PLASTIC,40V       |        | R216     | 2001-000490 | R-CARBON:200OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| IC501    | 1201-001159 | IC-VIDEO AMP:6107,ZIP,9P,300MIL,SINGLE,-,PL      |        | R217     | 2001-000449 | R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M        |        |
| IC602    | 1201-000537 | IC-AUDIO AMP:7057,ZIP,13P,-,DUAL,40DB,PLAS       |        | R218     | 2001-000591 | R-CARBON:3.3 KOHM 5% 1/8W AATP 1.8X3.2MM       |        |
| IC801    | 1203-001494 | IC-PWM CONTROLLER:3S0680RF,TO3PF-5L,5,210,PLASTI |        | R219     | 2001-000008 | R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| IC802    | 1203-000644 | IC-POS:FIXED REG:7630,SIP,10P,-,PLASTIC,5.1/8V,  |        | R220     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| IC901    | AA13-30019P | IC-MCU:SAA5291PS-098,8BIT,SDIP,175EE             |        | R221     | 2001-000290 | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM        |        |
| IC902    | 1103-001105 | IC-EEPROM:24C040,512X8BIT,DIP8P,300MIL,          |        | R223     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |
| J149     | 2701-000114 | INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM                |        | R224     | 2001-000563 | R-CARBON:27 KOHM 5% 1/8W AATP 1.8X3.2MM        |        |
| J175     | 2001-000857 | R-CARBON:560OHM 5% 1/8W AA TP 1.8X3.2MM          |        |          |             |  |        |

## Electric Parts List

| Loc. No. | Code No.    | Description ; Specification                  | Remark | Loc. No. | Code No.  | Description ; Specification                  | Remark |
|----------|-------------|--|--------|----------|---|--|--------|
| R225     | 2001-000554 | R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        | R815     | 2008-000267   | R-FUSIBLE(S):2.40OHM,5%,2W,AA,TP,3.9X10MM    |        |
| R226     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        | R815     | 2008-000189   | R-FUSIBLE:0.47 OHM 10%2W AA TP 6X15          |        |
| R227     | 2004-001234 | R-METAL:75KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R816     | 2004-004089   | R-METAL:123KOHM,1%,1/2W,AA,TP,2.5X6.5M       |        |
| R229     | 2001-000890 | R-CARBON:6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | R817     | 2004-001983   | R-METAL:2.49KOHM,1%,1/2W,AA,TP,2.4X6.4       |        |
| R230     | 2001-000793 | R-CARBON:47OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R818     | 2004-001371   | R-METAL(S):1.5KOHM,1%,1/2W,AA,TP,2.4X6.4M    |        |
| R231     | 2001-000563 | R-CARBON:27 KOHM 5% 1/8W AATP 1.8X3.2MM      |        | R819     | 2004-001390   | R-METAL(S):1KOHM,2%,1/2W,AA,TP,2.4X6.4MM     |        |
| R232     | 2001-000356 | R-CARBON:150KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | R820     | 2008-001062   | R-FUSIBLE:39 OHM,2W                          |        |
| R234     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        | R822     | 2001-001150   | R-CARBON(C):470KOHM,5%,1/2W,AA,TP,2.4X6.4M   |        |
| R236     | 2003-000634 | R-METAL OXIDE(S):3.9KOHM,5%,1W,AA,TP,3.3X9MM |        | R823     | 2001-001150   | R-CARBON(C):470KOHM,5%,1/2W,AA,TP,2.4X6.4M   |        |
| R236     | 2003-000634 | R-METAL OXIDE(S):3.9KOHM,5%,1W,AA,TP,3.3X9MM |        | R825     | 2003-001040   | R-METAL OXIDE(S):47KOHM,5%,2W,AF,TP,3.9X10MM |        |
| R237     | 2001-000793 | R-CARBON:47OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R901     | 2001-000832   | R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2M       |        |
| R238     | 2001-000739 | R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | R902     | 2001-000734   | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R239     | 2001-000739 | R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | R903     | 2001-000281   | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| R240     | 2001-000832 | R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X2.3M       |        | R904     | 2001-000281   | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| R241     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | R905     | 2001-000241   | R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R242     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | R906     | 2001-000290   | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM      |        |
| R250     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R907     | 2001-000449   | R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R251     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R908     | 2001-000449   | R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R252     | 2004-001914 | R-METAL:39KOHM,2%,1/8W,AA,TP,1.8X3.5MM       |        | R909     | 2001-000591   | R-CARBON:3.3 KOHM 5% 1/8W AATP1.8X3.2MM      |        |
| R262     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R912     | 2001-000924   | R-CARBON:680ohm,5%,1/8W,AA,TP,1.8x3.2mm      |        |
| R301     | 2004-001983 | R-METAL:2.49KOHM,1%,1/2W,AA,TP,2.4X6.4       |        | R919     | 2001-000290   | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM      |        |
| R302     | 2008-001033 | R-FUSIBLE:10 OHM 5% 2W AF TP 10X3.9MM        |        | R921     | 2001-001062   | R-CARBON(S):10MOHM,5%,1/2W,AA,TP,2.4X6.4MM   |        |
| R303     | 2001-000273 | R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | R922     | 2001-000281   | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| R305     | 2004-001370 | R-METAL(S):1.3OHM,1%,1/2W,AA,TP,2.4X6.4MM    |        | R923     | 2001-000281   | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| R306     | 2008-000254 | R-FUSIBLE(S):0.68 OHM 5% 2T AF TP 3.9X10MM   |        | R924     | 2001-000449   | R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R402     | 2003-000664 | R-METAL OXIDE(S):33OHM,5%,2W,AF,TP,4X12MM    |        | R925     | 2001-000449   | R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R403     | 2001-001114 | R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4MM   |        | R926     | 2001-000290   | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM      |        |
| R404     | 2008-000294 | R-FUSIBLE(S):33ohm,5%,2W,AF,TO,3.9X10MM      |        | R927     | 2001-000290   | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM      |        |
| R405     | 2001-001410 | R-CARBON(S):43 OHM 5%1/2W,AA,TP,2.4X6.4MM    |        | R928     | 2001-000066   | R-CARBON(S):10 KOHM 5% 1/2W AATP 2.4X6.4MM   |        |
| R406     | 2001-000037 | R-CARBON(S):330OHM,5%,1/2W,AA,TP,2.4X6.4MM   |        | R929     | 2004-000253   | R-METAL:11KOHM,1%,1/8W,AA,TP,1.8X3.2MM       |        |
| R407     | 2001-001037 | R-CARBON(S):0.39OHM,5%,1/2W,AA,TP,2.4X6.4M   |        | R930     | 2004-000218   | R-METAL:10KOHM,1%,1/8W,AA,TP,1.8X3.2MM       |        |
| R408     | 2001-000022 | R-CARBON(S):33OHM,5%,1/2W,AA,TP,2.4X6.4MM    |        | R931     | 2004-000218   | R-METAL:10KOHM,1%,1/8W,AA,TP,1.8X3.2MM       |        |
| R409     | 2008-000204 | R-FUSIBLE(S):0.22OHM,10%,1/2W,AF,TP,2.5X6.5  |        | R932     | 2001-000734   | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R412     | 2003-000664 | R-METAL OXIDE(S):33OHM,5%,2W,AF,TP,4X12MM    |        | R933     | 2001-000786   | R-CARBON:47 KOHM 5% 1.8W AATP 1.8X3.2MM      |        |
| R413     | 2003-000784 | R-METAL OXIDE(S):7.5KOHM,5%,2W,AD,TP,4X12MM  |        | R936     | 2001-000734   | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R414     | 2003-000540 | R-METAL OXIDE(S):1KOHM,5%,2W,AD,TP,4X12MM    |        | R937     | 2001-000734   | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R415     | 2008-000206 | R-FUSIBLE(S):1OHM,5%,1/2W,AF,TP,2.5X6.5MM    |        | R939     | 2001-000006   | R-CARBON:2.4 KOHM 5% 1/8W AATP 1.8X3.2M      |        |
| R416     | 2008-000277 | R-FUSIBLE:68OHM,5%,1/2W,AA,TP,4.7X11MM       |        | R940     | 2001-000660   | R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| R417     | 2008-000265 | R-FUSIBLE(S):1OHM,5%,2W,AA,TP,3.9X10MM       |        | R944     | 2001-000006   | R-CARBON:2.4 KOHM 5% 1/8W AATP 1.8X3.2M      |        |
| R420     | 2004-001377 | R-METAL(S):120 KOHM 1/2W 1% AA TP 2.4X6.4M   |        | R946     | 2001-000429   | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        |
| R501H    | 2002-001008 | R-COMPOSITION:1.8KOHM,5%,1/2W,AA,TP,3.7X9MM  |        | R951     | 2001-000734   | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R502H    | 2002-001008 | R-COMPOSITION:1.8KOHM,5%,1/2W,AA,TP,3.7X9MM  |        | R952     | 2001-000281   | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| R503     | 2002-001008 | R-COMPOSITION:1.8KOHM,5%,1/2W,AA,TP,3.7X9MM  |        | R954     | 2001-000006   | R-CARBON:2.4 KOHM 5% 1/8W AATP 1.8X3.2M      |        |
| R504     | 2001-001062 | R-CARBON(S):10MOHM,5%,1/2W,AA,TP,2.4X6.4MM   |        | R956     | 2001-000429   | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        |
| R505     | 2008-001011 | R-FUSIBLE(S):0.18OHM,10%,2W,AF,TP,3.9X10MM   |        | R958     | 2001-000780   | R-CARBON:470 OHM 5% 1/8W AATP 1.8X3.2MM      |        |
| R510     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        | R959     | 2001-000800   | R-CARBON:5.1 KOHM 5% 1/8W AATP 1.08X3.2      |        |
| R511     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        | R960     | 2001-000290   | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM      |        |
| R512     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        | R962     | 2001-000273   | R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R603     | 2001-000241 | R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | RA01     | 2001-000924   | R-CARBON:680ohm,5%,1/8W,AA,TP,1.8x3.2mm      |        |
| R604     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | RA02     | 2001-000241   | R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R605     | 2001-000563 | R-CARBON:27 KOHM 5% 1/8W AATP 1.8X3.2MM      |        | RA03     | 2001-000734   | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R606     | 2001-000591 | R-CARBON:3.3 KOHM 5% 1/8W AATP1.8X3.2MM      |        | RA04     | 2001-000734   | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R610     | 2001-000563 | R-CARBON:27 KOHM 5% 1/8W AATP 1.8X3.2MM      |        | RL901    | AA59-60001U MODULE-REMOCON:-,ORC-50VF,38KHZ,940NM,MESH,V, |  |        |
| R611     | 2001-000591 | R-CARBON:3.3 KOHM 5% 1/8W AATP1.8X3.2MM      |        | RT01     | 2001-000563   | R-CARBON:27 KOHM 5% 1/8W AATP 1.8X3.2MM      |        |
| R701     | 2001-000281 | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        | RT02     | 2001-000577   | R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        |
| R702     | 2001-000969 | R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | RT03     | 2001-000958   | R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| R703     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | RT03     | 2001-000252   | R-CARBON:1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R705     | 2001-000003 | R-CARBON:330 OHM 5% 1/8W AATP 1.8X3.2MM      |        | RT04     | 2008-001062   | R-FUSIBLE:39 OHM,2W                          |        |
| R706     | 2001-000221 | R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | RT05     | 2001-000864   | R-CARBON:56KOHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| R713     | 2001-000812 | R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | RT06     | 2001-000362   | R-CARBON:150 OHM 5% 1/8W AATP 1.8X3.2MM      |        |
| R714     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | RT07     | 2001-000429   | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        |
| R715     | 2001-000812 | R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | RT08     | 2001-000003   | R-CARBON:330 OHM 5% 1/8W AATP 1.8X3.2MM      |        |
| R717     | 2001-000812 | R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | RT09     | 2001-000734   | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R801     | 2003-000994 | R-METAL OXIDE(S):33KOHM,5%,2W,AF,TP,3.9X10MM |        | RT13     | 2001-000734   | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R802     | 2003-000994 | R-METAL OXIDE(S):33KOHM,5%,2W,AF,TP,3.9X10MM |        | RW701    | 2011-001133   | R-NETWORK:33K/24K/75X3,1/8W                  |        |
| R803     | 2001-001178 | R-CARBON(S):680OHM,5%,1/2W,AA,TP,2.4X6.4MM   |        | RW702    | 2011-001098   | R-NETWORK:75/75/1K,75OHM,5%,--P              |        |
| R805     | 2003-001023 | R-METAL OXIDE(S):120OHM,5%,2W,AA,TP,3.9X10MM |        | RW901    | 2011-000531   | R-NETWORK:4.7KOHM,5%,1/8W,AA,SIP8B,PTP       |        |
| R806     | 2002-001011 | R-COMPOSITION:3.3MOHM,10%1/2W,AA,TP,3        |        | RX801    | 2002-001011   | R-COMPOSITION:3.3MOHM,10%1/2W,AA,TP,3        |        |
| R807     | 2002-001011 | R-COMPOSITION:3.3MOHM,10%1/2W,AA,TP,3        |        | SFN02    | 2904-001070   | FILTER-SAW AV:37.4MHZ,SIP5K,TP,14.5DB,PAL-B/ |        |
| R808     | 2001-000022 | R-CARBON(S):33OHM,5%,1/2W,AA,TP,2.4X6.4MM    |        | SW801    | 3403-001020   | SWITCH-PUSH:250V,5A,DPST,OFF ON-OFF          |        |
| R809     | 2001-000622 | R-CARBON:300KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        | SW901    | 3404-000244   | SWITCH-TACT:15V,20MA,90-170GF,7.5X7MM,SPST   |        |
| R810     | 2003-000527 | R-METAL OXIDE(S):18KOHM,5%,2W,AA,TP,4X12MM   |        | SW902    | 3404-000244   | SWITCH-TACT:15V,20MA,90-170GF,7.5X7MM,SPST   |        |
| R812     | 2003-000455 | R-METAL OXIDE(S):100OHM,5%,2W,AA,TP,4X12MM   |        | SW903    | 3404-000244   | SWITCH-TACT:15V,20MA,90-170GF,7.5X7MM,SPST   |        |
| R814     | 2008-000189 | R-FUSIBLE:0.47 OHM 10%2W AA TP 6X15          |        | SW904    | 3404-000244   | SWITCH-TACT:15V,20MA,90-170GF,7.5X7MM,SPST   |        |
| R814     | 2008-000267 | R-FUSIBLE(S):2.40HM,5%,2W,AA,TP,3.9X10MM     |        | SW905    | 3404-000244   | SWITCH-TACT:15V,20MA,90-170GF,7.5X7MM,SPST   |        |
| R814     | 2008-000189 | R-FUSIBLE:0.47 OHM 10%2W AA TP 6X15          |        | T401     | AA26-50001B HORIZ.DRIVE:-,7.1MH,102UH,10-20UH,YL081,ST    |  |        |
| R815     | 2008-000189 | R-FUSIBLE:0.47 OHM 10%2W AA TP 6X15          |        | T444     | AA26-30001Y TRANS-FLYBACK:-,FSV-20A001,20,125V            |  |        |

| Loc. No.  | Code No. | Description ; Specification                                 | Remark | Loc. No. | Code No. | Description ; Specification | Remark |
|---|----------|---|--------|----------|----------|-----------------------------|--------|
|  | T801     | AA26-20007Q TRANS-SWITCHING;- ,180-260V,125V/12.5V,EN,EER28 |        |          |          |                             |        |
|  | TU01     | AA40-10006Q TUNER-V/S;TELE4-125A,PAL-B/G,TR,181CH           |        |          |          |                             |        |
|  | V999     | 3704-001090 SOCKET-CRT:9P;15.24PI,26.5PI,SN,-               |        |          |          |                             |        |
|   | X202     | 2801-000226 CRYSTAL-UNIT;3.579545MHZ,20PPM,28-AAM,15PF,     |        |          |          |                             |        |
|   | X203     | 2801-000274 CRYSTA-UNIT;4.433618MHZ,30PPM,28AAM,20PF        |        |          |          |                             |        |
|   | X901     | 2801-001476 CRYSTAL-UNIT;12 MHZ 50PPM 28-ABQ S 300HM        |        |          |          |                             |        |
|   | Z202     | 2903-001019 FILTER-SAW;TR,5,5/5,742MHZ,-,-,-TP              |        |          |          |                             |        |
|   | Z204     | 2903-000184 FILTER-CERAMIC;BP;5.5MHZ                        |        |          |          |                             |        |
|   | Z206     | 2903-000184 FILTER-CERAMIC;BP;5.5MHZ                        |        |          |          |                             |        |

## ASSY-PCB,A/V FRONT

|      |             |   |  |
|------|-------------|---|--|
| *    | HA95-900001 | ASSY-PCB,A/V FRONT;- ,20,S15A,CE,11P,-              |  |
| CE01 | 2401-001840 | C-AL:100UF,20%,16V,GP,TP8X11.5MM,5                  |  |
| CE03 | 2401-001264 | C-AL:4.7UF,20%,50V,BP6X11MM,5MM,TP                  |  |
| CE06 | 2202-000862 | C-CERAMIC,MLC-AXIAL:390PF,10%50V,Y5P,3.5X1.9TP      |  |
| CE07 | 2202-000222 | C-CERAMIC,MLC-AXIAL:3.3NF,20%,16V,Y5P;- ,7.5MM,TP   |  |
| LE01 | 2701-000158 | INDUCTOR-AXIAL:22 UH 10% 2.5X3.4MM                  |  |
| QE01 | 0501-000283 | TR-SMALL SIGNAL:KSA539 PNP 60V 45V 200MA 40         |  |
| RE01 | 2001-001153 | R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4MM           |  |
| RE02 | 2001-001153 | R-CARBON(S);47OHM,5%,1/2W,AA,TP,2.4X6.4MM           |  |
| RE03 | 2001-000010 | R-CARBON(S);68KOHM,5%,1/8W,AA,TP,1.8X3.2MM          |  |
| RE04 | 2001-000429 | R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM              |  |
| RE05 | 2001-000009 | R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM             |  |
|      | AA39-20461C | LEAD-CONNECTOR, ASSY;- ,YBNH250-11,67096-011,11,300 |  |
|      | 3722-000143 | JACK-PHONE:1P,3.4MM,MBAG,BLACK                      |  |
|      | 3722-000507 | JACK-RCA;2P 3.6MM;- ,AG                             |  |

## REMOCON

|   |             |  |  |
|---|-------------|--|--|
| * | AA59-10101T | REMOCON;DP,TM59,-,-,-,-,-,AA59-10107C, |  |
|---|-------------|--|--|



## ASSY-HOLDER,SPK

|   |             |                                   |  |
|---|-------------|-----------------------------------|--|
| * | AA91-60028A | ASSY-HOLDER,SPK;ABS 8 OHM 5W,5085 |  |
|---|-------------|-----------------------------------|--|

## ASSY-POWER,CORD

|   |        |             |                        |  |
|---|--------|-------------|------------------------|--|
|  | P/CORD | AA96-20077B | ASSY-POWER,CORD;SCT11D |  |
|---|--------|-------------|------------------------|--|


## ASSY-CRT

|   |  |             |  |  |
|---|--|-------------|--|--|
|  |  | AA03-10031D | CRT-COLOR;- ,A48ECR141X,+400MG,20,90DEG        |  |
|  |  | AA27-50005H | DEFLECTION-YOKE;- ,DSE-2093BL,20/A48ECR141X,ST |  |
|   |  | AA27-60001D | MAGNET-CONVERGENCE;- ,JH-291-(JH-8210),29.1mm  |  |
|   |  | AA63-60028A | SPACER-DY;NEOPRENE,- ,BLK,V0 W12,-,-           |  |

## ASSY-ACCESSORY

|  |                                      |  |
|--|--------------------------------------|--|
|  | BUYER : SEI / SEP (ONLY)             |  |
|  | HA68-100052                          | MANUAL-USERS;- ,A/P 80(G),ITA,SPA,POR,CB5073 |
|  | AA68-20052A                          | MANUAL-S/D:S15A,W/P 100(G);- ,ITALIAN,-,-    |
|  | BUYER : AMFO (ONLY)                  |  |
|  | HA68-100050                          | MANUAL-USERS;- ,A/P 80(G),ENG,GER,DAN,FRA    |
|  | BUYER : AUTRONIC (ONLY)              |  |
|  | AA68-11264A                          | MANUAL-USERS:S15A,GERMANY,TTX,B5,W/P         |
|  | AA68-11266A                          | MANUAL-USERS:S15A,ITALY,TTX,B5,W/P           |
|  | AA68-11288A                          | MANUAL-USERS:S15A,FRE(SEF),TTX,B5,W/P        |
|  | BUYER : EUROPARTRAD / INTRADE (ONLY) |  |
|  | AA68-11262A                          | MANUAL-USERS:S15A,ENGLISH,TTX,B5,W/P         |
|  | AA68-11264A                          | MANUAL-USERS:S15A,GERMANY,TTX,B5,W/P         |
|  | BUYER : SECOSA (ONLY)                |  |
|  | AA68-11274A                          | MANUAL-USERS:S15A,SPANISH,TTX,B5,W/P         |

## 7-3 CB5320Z5X (CB5020Z5X AND CB5320Z5X Dissimilar Parts)

| Loc. No.   | Code No. | Description ; Specification | Remark | Loc. No.   | Code No. | Description ; Specification | Remark |
|--|----------|-----------------------------|--------|--|----------|-----------------------------|--------|
| <b>ASSY-PCB,MAIN</b><br>BUYER : SECOSA<br><br>* HA94-100115 ASSY-PCB,MAIN:CB5320Z5X/XEC,S15A<br><br>C409 2306-000253 C-FILM,MPPF:7.2NF,5%,1.6KV 28.5X18.5X20<br>C410 2201-000406 C-CERAMIC,DISC:270PF,10%,2KV,Y5P,8X5.5TP<br>C419 2201-000984 C-CERAMIC,DISC:680PF,10%,2KV,Y5P,TP,11X<br>CN802 AA27-20003Z COIL-DEGAUSSING:-,21,13.5OHM,25T,L2380<br>LW01 AA27-40001N COIL-HORIZ,WIDTH:-,90/260UH,SB-5S620,PI0<br>R301 2004-000869 R-METAL:3KOHM,1%,1/8W,AA,TP,1.8X3.2MM |          |                             |        | <b>ASSY-CABINET OPTION (CB5320Z5X)</b><br><br>HA91-100008 ASSY-CABINET,FRONT:5320,HITRON BLACK<br>HA64-300010 CABINET-FRONT:DP:5320,-,HIPS,HB,BLK,-,-<br>AA65-30019A CLAMP-D,COIL:-,NYLON,V0,NTR,DADH-460<br>HA60-020002 SCREW-TAPPING:DP,RH,+,2,M4,L15,ZPC(BLK),<br>AA63-50303A GRILLE-WOOFER:DP,AA63-50193A,5320 |          |                             |        |
| <b>ASSY-CRT</b><br><br> AA03-10031E CRT-COLOR:-,A51EERX131X,+400MG,21,90DEG<br>AA27-50005G DEFLECTION-YOKE:-,DST-21944(2),21/A51EE  |          |                             |        |  |          |                             |        |

## 7-4 CB5020Z5X Parts List

| Loc. No.   | Code No.    | Description ; Specification                       | Remark | Loc. No. | Code No.    | Description ; Specification                       | Remark |
|--|-------------|---|--------|----------|-------------|---|--------|
| <b>ASSY-PCB,MAIN</b><br><br>BUYER : SECOSA<br>* HA94-100109 ASSY-PCB,MAIN:CB5020Z5X/XEC,S15A<br>BUYER : AMFO<br>* HA94-100211 ASSY-PCB,MAIN:CB5020Z5X/AMF,S15A |             |   |        |          |             |   |        |
| C101   | 2401-000939 | C-AL:22UF,20%,25V,GP,TP,5X11MM,5                  |        | C255     | 2306-000122 | C-FILM,MPPF:100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        |
| C102   | 2401-001082 | C-AL:330NF,20%,50V,GP,5X11MM,5MM,TP               |        | C301     | 2202-000253 | C-CERAMIC,MLC-AXIAL:4.7NF,20%,16V,Y5R,TP,1.9X3.5  |        |
| C103   | 2401-001363 | C-AL:470UF,20%,16V,GP,TP,10X12.5MM,               |        | C302     | 2202-000253 | C-CERAMIC,MLC-AXIAL:4.7NF,20%,16V,Y5R,TP,1.9X3.5  |        |
| C201   | 2306-000122 | C-FILM,MPPF:100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        | C303     | 2401-003028 | C-AL:100UF,20%,25V,WT,TP,6.3X11.5MM               |        |
| C203   | 2401-000660 | C-AL:2.2 UF 20% 50V GP 5X11.5 TP                  |        | C304     | 2401-000903 | C-AL:22UF,20%,160V,WT,TP,10X20MM,5M               |        |
| C204   | 2401-000603 | C-AL:1UF,20%,50V,GP,5X11MM,5MM,TP                 |        | C305     | 2305-000178 | C-FILM,MPEF:10NF,5%,100V,-,5MM,TP                 |        |
| C205   | 2305-000411 | C-FILM,MPEF:470NF,5%,50V,7.3X4.8X5.5MM,5MM        |        | C306     | 2305-000285 | C-FILM,MPEF:220NF,5%,100V,-5MM,TP                 |        |
| C206   | 2305-000411 | C-FILM,MPEF:470NF,5%,50V,7.3X4.8X5.5MM,5MM        |        | C307     | 2305-000149 | C-FILM,MPEF:100NF,5% 100V,7.5X4.05.0MM            |        |
| C207   | 2305-000196 | C-FILM,MPEF:150NF,5%,63V,TP,-,5MM                 |        | C308     | 2305-000450 | C-FILM,MPEF:56NF,5%,100V,TP,-,5MM                 |        |
| C208   | 2401-000027 | C-AL:4.7UF,20%,50V,GP,TP,5X11MM,5MM               |        | C401     | 2301-000380 | C-FILM,PEF:10NF,5%,50V,6.5X3MM,5MM,TP             |        |
| C209   | 2202-000794 | C-CERAMIC,MLC-AXIAL:18PF,5%,50V,CH,TP,3.5X19MM    |        | C402     | 2201-000599 | C-CERAMIC,DISC:560PF 10% 500V Y5P 6X4MM,5MM       |        |
| C210   | 2301-000264 | C-FILM,PEF:4.7NF,5%,50V,6.5X5.5X3.0X5.5MM         |        | C403     | 2201-000556 | C-CERAMIC,DISC:470PF,10%,500V,Y5P,6X3.5MM,5MM     |        |
| C211   | 2305-000665 | C-FILM,MPEF:100NF,5%,63V,7.5X4.0X5.0MM,5MM        |        | C404     | 2401-001998 | C-AL:1000UF,20%,25V,GP,TP,10X20,5MM               |        |
| C212   | 2202-000796 | C-CERAMIC,MLC-AXIAL:1NF,10%,50V,Y5P,TP,5.5X19,-   |        | C408     | 2401-001530 | C-AL:47UF,20%,25V,GP,5X11MM,5MM,TP                |        |
| C213   | 2201-000273 | C-CERAMIC,DISC:18PF,5%,50V,NPO,5.0*3.0,2.5MM,     |        | C409     | 2306-000355 | C-FILM,MPPF:7.4NF,5%,1.6KV,28.5X18.5X12.20        |        |
| C214   | 2301-000285 | C-FILM,PEF:47NF,5%,50V,7.5X4.0X6.5.5MM,TP         |        | C410     | 2201-000983 | C-CERAMIC,DISC:1NF,10%,2KV,Y5P,8X5.5,TP           |        |
| C215   | 2301-000380 | C-FILM,PEF:10NF,5%,50V,6.5X3MM,5MM,TP             |        | C411     | 2401-000927 | C-AL:22UF,20%,250V,GP,13X20MM,5MM,T               |        |
| C216   | 2305-000288 | C-FILM,MPEF:220NF,5%,50V,7.3X4.8X5.5MM,5MM        |        | C413     | 2305-000382 | C-FILM,MPEF:4.7NF,5%,400V,TP,-,5MM                |        |
| C217   | 2301-000192 | C-FILM,PEF:1NF,5%,50V,5.3X10MM,5MM,TP             |        | C414     | 2301-001065 | C-FILM,MPPF:47NF,5%,630V,TP,19X15.5X7.7.5         |        |
| C219   | 2401-000603 | C-AL:1UF,20%,50V,GP,5X11MM,5MM,TP                 |        | C415     | 2401-000560 | C-AL:1UF,20%,160V,GP,TP,6.3*11.5MM                |        |
| C221   | 2202-000821 | C-CERAMIC,MLC-AXIAL:560PF,10%,50V,Y5P,TP,3.5X19,- |        | C416     | 2306-000204 | C-FILM,MPPF:430NF,5%,400V,-,20MM,TP               |        |
| C222   | 2401-000440 | C-AL:10UF,20%,25V,GP,5X11MM,5MM,TP                |        | C417     | 2201-000556 | C-CERAMIC,DISC:470PF,10%,500V,Y5P,6X3.5MM,5MM     |        |
| C226   | 2301-000224 | C-FILM,PEF:22NF,5%,50V,7.4X3.9X13MM,5MM,T         |        | C418     | 2401-000384 | C-AL:10UF,20%,100V,GP,TP,6.3X11.5MM               |        |
| C230   | 2401-001495 | C-AL:47UF,20%,16V,GP,5X11MM,5MM,TP                |        | C419     | 2201-000984 | C-CERAMIC,DISC:680PF,10%,2KV,Y5P,TP,11X6.7.5      |        |
| C231   | 2401-000416 | C-AL:10UF,20%,16V,GP,TP,5X11.5MM                  |        | C502     | 2301-000213 | C-FILM,PEF:220NF,5%,250V,21.5X11MM,17.5MM         |        |
| C232   | 2401-001840 | C-AL:100UF,20%,16V,GP,TP,8X11.5MM,5               |        | C503     | 2201-002063 | C-CERAMIC,DISC:10NF,-20,+80%,3KV,Y5V,TP,16X5,     |        |
| C238   | 2401-001495 | C-AL:47UF,20%,16V,GP,5X11MM,5MM,TP                |        | C504     | 2401-001232 | C-AL:4.7UF,20%,250V,GP,10X12.5MM,5M               |        |
| C239   | 2305-000288 | C-FILM,MPEF:220NF,5%,50V,7.3X4.8X5.5MM,5MM        |        | C506     | 2401-000430 | C-AL:10UF,20%,250V,GP,TP,10X16MM,5M               |        |
| C247   | 2202-002037 | C-CERAMIC,MLC-AXIAL:100NF,80-20%,50V,Y5P,TP,2.2X3 |        | C601     | 2202-000210 | C-CERAMIC,MLC-AXIAL:270PF,10%,50V,Y5P,-,7.5MM,TP  |        |
| C248   | 2309-000138 | C-FILM,PE-PF:100NF,5%,50V,16X7MM,7.5MM,TP         |        | C602     | 2401-000939 | C-AL:22UF,20%,25V,GP,TP,5X11MM,5                  |        |
| C249   | 2401-000603 | C-AL:1UF,20%,50V,GP,5X11MM,5MM,TP                 |        | C603     | 2301-000264 | C-FILM,PEF:4.7NF,5%,50V,6.5X5.5X3.0X5.5MM         |        |
| C250   | 2301-000224 | C-FILM,PEF:22NF,5%,50V,7.4X3.9X13MM,5MM,T         |        | C604     | 2401-001323 | C-AL:470NF,20%,50V,BP,6X11MM,5MM,TP               |        |
| C251   | 2301-000204 | C-FILM,PEF:2.7NF,5%,50V,7.4X3.9X13MM,5MM,         |        | C610     | 2401-001998 | C-AL:1000UF,20%,25V,GP,TP,10X20,5MM               |        |
| C252   | 2301-000192 | C-FILM,PEF:1NF,5%,50V,5.3X10MM,5MM,TP             |        | C611     | 2301-000264 | C-FILM,PEF:4.7NF,5%,50V,6.5X5.5X3.0X5.5MM         |        |
| C253   | 2306-000122 | C-FILM,MPPF:100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        | C612     | 2401-001323 | C-AL:470NF,20%,50V,BP,6X11MM,5MM,TP               |        |
| C254   | 2306-000122 | C-FILM,MPPF:100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        | C613     | 2202-000796 | C-CERAMIC,MLC-AXIAL:1NF,10%,50V,Y5P,TP,5.5X19,-   |        |
|  |             |   |        | C614     | 2202-000210 | C-CERAMIC,MLC-AXIAL:270PF,10%,50V,Y5P,-,7.5MM,TP  |        |
|  |             |   |        | C702     | 2202-000263 | C-CERAMIC,MLC-AXIAL:470PF,10%,50V,Y5P,TP,3.5X19,- |        |
|  |             |   |        | C704     | 2202-000121 | C-CERAMIC,MLC-AXIAL:100PF,10%,50V,Y5P,1.9X3.5MM,- |        |
|  |             |   |        | C705     | 2401-001264 | C-AL:4.7UF,20%,50V,BP,6X11MM,5MM,TP               |        |
|  |             |   |        | C706     | 2401-001264 | C-AL:4.7UF,20%,50V,BP,6X11MM,5MM,TP               |        |
|  |             |   |        | C800     | 2306-000320 | C-FILM,MPPF:470NF,20%,250V,TP,-,20MM              |        |
|  |             |   |        | C801     | 2401-000534 | C-AL:150UF,20%,400V,GP,25X30,10,ST                |        |
|  |             |   |        | C802     | 2401-002284 | C-AL:33UF,20%,50V,GP,TP,5X11MM,5MM                |        |

| Loc. No. | Code No.    | Description ; Specification                       | Remark | Loc. No. | Code No.                                      | Description ; Specification                        | Remark |
|----------|-------------|---|--------|----------|---|--|--------|
| C803     | 2301-000224 | C-FILM,PEF;22NF,5%,50V,7.4X3.9X13MM,5MM,T         |        | DZ204    | 2001-000812                                   | R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M            |        |
| C804     | 2301-000310 | C-FILM,PEF;68NF,5%,50V,8.0X8.5X4.0X5.5MM,         |        | DZ205    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C805     | 2303-000163 | C-FILM,PPF;2.2NF,5%,800V,-,-,TP                   |        | DZ208    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C806     | 2201-000446 | C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,18X8,10M     |        | DZ301    | 0403-000660                                   | DIODE-ZENER:MTZ22A 22V 20 15-21 2V 500MW           |        |
| C807     | 2201-000991 | C-CERAMIC,DISC;560PF 10% 2KV Y5P 8X5.5 TP         |        | DZ302    | 0403-001039                                   | DIODE-ZENER:MA2560,56V,52-60,1W,DO-4               |        |
| C808     | 2401-000262 | C-AL;100UF,20%,160V,GP,16X25MM,5MM,               |        | DZ401    | 0403-000296                                   | DIODE-ZENER:MTZ 5.6B                               |        |
| C809     | 2401-000290 | C-AL;47UF,20%,160V,GP,TP,13X20MM,5M               |        | DZ501    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C810     | 2201-000991 | C-CERAMIC,DISC;560PF 10% 2KV Y5P 8X5.5 TP         |        | DZ502    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C811     | 2401-003141 | C-AL;220UF,20%,25V,WT,TP,13X25.5MM                |        | DZ503    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C814     | 2301-000192 | C-FILM,PEF;1NF,5%,50V,5.3X10MM,5MM,TP             |        | DZ504    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C815     | 2401-000808 | C-AL;220UF,20%,16V,GP,8X11MM,5MM,TP               |        | DZ701    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C816     | 2401-000603 | C-AL;1UF,20%,50V,GP,5X11MM,5MM,TP                 |        | DZ702    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C818     | 2401-001495 | C-AL;47UF,20%,16V,GP,5X11MM,5MM,TP                |        | DZ703    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C819     | 2401-001840 | C-AL;100UF,20%,16V,GP,TP8X11.5MM,5                |        | DZ704    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C901     | 2401-001840 | C-AL;100UF,20%,16V,GP,TP8X11.5MM,5                |        | DZ705    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C902     | 2202-000796 | C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP5.5X19,-    |        | DZ802    | 0403-000297                                   | DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500MW,         |        |
| C904     | 2202-000796 | C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP5.5X19,-    |        | DZ803    | 1203-001217                                   | IC-POS.I,ADJUST REG;431,TO-92,3P,4.58MIL,PLASTIC,2 |        |
| C905     | 2401-001333 | C-AL;0.47UF 20% 50V,GP 5X11.5 TP                  |        | DZ804    | 2001-001170                                   | R-CARBON(S);6.8OHM,5%,1/2W,AA,TP,2.4X6.4MM         |        |
| C907     | 2201-000119 | C-CERAMIC,DISC;100NF,+80-20%,50V,Y5V,8X5MM,5M     |        | DZ808    | 0403-000300                                   | DIODE-ZENER:MTZ8.2B,7.78-8.19V,500MW,DO-34         |        |
| C908     | 2201-000193 | C-CERAMIC,DISC;10PF,0.25PF,50V,NPO,-,5MM,TP       |        | DZ809    | 0403-000296                                   | DIODE-ZENER:MTZ 5.6B                               |        |
| C909     | 2201-000193 | C-CERAMIC,DISC;10PF,0.25PF,50V,NPO,-,5MM,TP       |        | DZ901    | 0403-000563                                   | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,         |        |
| C910     | 2306-000122 | C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        | DZ902    | 0403-000296                                   | DIODE-ZENER:MTZ 5.6B                               |        |
| C911     | 2401-000235 | C-AL;10UF,20%,16V,GP,TP,5X11MM,5MM                |        | DZ903    | 1203-000451                                   | IC-VOLTAGE REGULATOR;33 TO 92.3P PLASTIC-31/35     |        |
| C912     | 2201-000234 | C-CERAMIC,DISC;150PF,5%,50V,NPO,10X3.5MM,5MM,     |        | DZ905    | 0403-000296                                   | DIODE-ZENER:MTZ 5.6B                               |        |
| C913     | 2301-000108 | C-FILM,PEF;1.5NF,5%,50V,6.5X3.0X5.5MM,5MM         |        | DZ907    | 0403-000296                                   | DIODE-ZENER:MTZ 5.6B                               |        |
| C914     | 2306-000122 | C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        | DZ909    | 0403-000551                                   | DIODE-ZENER:MTZ3.9B,3.9V,3.89-4.16V,500MW,         |        |
| C915     | 2306-000122 | C-FILM,MPPF;100NF,5%,50V,7.3X4.0X5.0MM,5MM        |        | △ F801   | 3601-000261                                   | FUSE-FERRULE;3.15A 250V                            |        |
| C916     | 2301-000264 | C-FILM,PEF;4.7NF,5%,50V,6.5X5.5X3.0X5.5MM         |        | F801A    | 3602-000114                                   | FUSE-HOLDER;-,-,30MOHM                             |        |
| C917     | 2202-002037 | C-CERAMIC,MLC-AXIAL;100NF,80-20%,50V,Y5P,TP,2.2X3 |        | F801B    | 3602-000114                                   | FUSE-HOLDER;-,-,30MOHM                             |        |
| C919     | 2202-000796 | C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP5.5X19,-    |        | △ F802   | 3601-001086                                   | FUSE-FERRULE;125V,5A,QUICK,CERAMIC                 |        |
| C920     | 2401-000480 | C-AL;10UF,20%,50V,GP,5X11MM,5MM,TP                |        | △ IC201  | 1204-001373                                   | IC-VIDEO PROCESS;TDA8841,DIP,56P,-,PLASTIC,8.0V    |        |
| C922     | 2201-000573 | C-CERAMIC,DISC;47PF,5%,50V,NPO,6.5X3.0,5MM,TP     |        | △ IC301  | 1204-000441                                   | IC-IF CIRCUIT;TDA8356,SIP,9P,-,PLASTIC,40V         |        |
| C923     | 2202-002037 | C-CERAMIC,MLC-AXIAL;100NF,80-20%,50V,Y5P,TP,2.2X3 |        | △ IC501  | 1201-001159                                   | IC-VIDEO AMP;6107,ZIP,9P,300MIL,SINGLE,-,PL        |        |
| C924     | 2202-002037 | C-CERAMIC,MLC-AXIAL;100NF,80-20%,50V,Y5P,TP,2.2X3 |        | △ IC602  | 1201-000537                                   | IC AUDIO AMP;7057,ZIP,13P,-,DUAL,40DB,PLAS         |        |
| C926     | 2202-000796 | C-CERAMIC,MLC-AXIAL;1NF,10%,50V,Y5P,TP5.5X19,-    |        | △ IC801  | 1203-001494                                   | IC-PWM CONTROLLER;3S0680RF,TO3PF-5L,5,210,PLASTI   |        |
| C927     | 2201-000573 | C-CERAMIC,DISC;47PF,5%,50V,NPO,6.5X3.0,5MM,TP     |        | △ IC802  | 1203-001531                                   | IC-POS.I,FIXED REG;7630,SIP,10P,-,PLASTIC          |        |
| CA01     | 2401-001264 | C-AL;4.7UF,20%,50V,BP,6X11MM,5MM,TP               |        | △ IC901  | AA13-30020NIC-MCU;Z90234-R3816,8BIT,SZM-173EW |  |        |
| CN501    | AA39-20109B | LEAD-CONNECTOR,ASSY;-YBNH025-08,S,8P,500,1007#26  |        | △ IC902  | 1103-001105                                   | IC-EEPROM;24C040,512X8BIT,DIP,8P,300MIL,           |        |
| CN602    | 3711-002643 | CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGHT         |        | J185     | 2701-000114                                   | INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM                  |        |
| CN701    | 3711-000628 | CONNECTOR-HEADER;BOX 11P,1R,2.5MM,STRAIGHT        |        | JS701    | 3722-000183                                   | JACK-RCA;21P4MM,-,SN                               |        |
| CN802    | AA27-20003Y | COIL-DEGAUSSING;-20,15.2OHM,28T,L2170,E           |        | L102     | 2701-000212                                   | INDUCTOR-AXIAL;68UH,10%,2.8X7MM                    |        |
| CW901    | 2503-000156 | C-NETWORK;100PFX4,20%50V                          |        | L103     | 2701-000114                                   | INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM                  |        |
| D202     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | L202     | 2001-000281                                   | R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM            |        |
| D205     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | L206     | 2701-000114                                   | INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM                  |        |
| D208     | 2001-000633 | R-CARBON:30KOHM,5%,1/8W,AA,TP,1.8X3.2MM           |        | L301     | 2701-000114                                   | INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM                  |        |
| D209     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | L302     | 2701-000114                                   | INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM                  |        |
| D210     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | L304     | 2701-000159                                   | INDUCTOR-AXIAL;22UH,10%,4.2X9.8MM                  |        |
| D211     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | L305     | 2701-000116                                   | INDUCTOR-AXIAL;10 UH 10% 4.2X9.8MM                 |        |
| D401     | 0402-000132 | DIODE-RECTIFIER;1N4004,400V,1A,DO-41              |        | L306     | 2701-000115                                   | INDUCTOR-AXIAL;10UH,10%,2.8X7MM                    |        |
| D402     | 0402-000132 | DIODE-RECTIFIER;1N4004,400V,1A,DO-41              |        | L401     | AA27-30001B                                   | COIL-LINEARITY;-195UH,QIC1010,PIO,4,4.5X21.5       |        |
| D403     | 0402-001105 | DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP        |        | L402     | 2901-000297                                   | FILTER-EMI ON BOARD;-3A,-,-,3.5X5,TP-              |        |
| D404     | 0402-000534 | DIODE-RECTIFIER;RG10V,400V,1.2A                   |        | L601     | 2701-000146                                   | INDUCTOR-AXIAL;2.2UH,10%,2.5X3.4MM                 |        |
| D405     | 0402-001105 | DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP        |        | L702     | 2701-000184                                   | INDUCTOR-AXIAL;4.7UH,                              |        |
| D406     | 0402-001105 | DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP        |        | L703     | 2701-000184                                   | INDUCTOR-AXIAL;4.7UH,                              |        |
| D501     | 0402-000216 | DIODE-RECTIFIER;ERC24-06,600V,1.0A,DO-204         |        | L704     | 2701-000184                                   | INDUCTOR-AXIAL;4.7UH,                              |        |
| D502     | 0402-001105 | DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP        |        | L706     | 2701-000184                                   | INDUCTOR-AXIAL;4.7UH,                              |        |
| D503     | 0402-001105 | DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP        |        | L801     | AA29-30001G                                   | FILTER-LINE;-27MH,-,-,-                            |        |
| D504     | 0402-001105 | DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP        |        | L804     | 3301-000287                                   | CORE-FERRITE BEAD;AA,3.5X1.0X6.0MM,1500,2400G      |        |
| D701     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | L805     | 2901-000297                                   | FILTER-EMI ON BOARD;-3A,-,-,3.5X5,TP-              |        |
| D800     | 1405-000152 | VARIATOR;560V,2500A,14X8,5MM,TP                   |        | L807     | 2901-000297                                   | FILTER-EMI ON BOARD;-3A,-,-,3.5X5,TP-              |        |
| D801     | 0402-000102 | DIODE-BRIDGE;D2SB60,600V,1.5A,-                   |        | L809     | 2701-001032                                   | INDUCTOR-AXIAL;100UH,10%,5X14MM                    |        |
| D802     | 0402-000540 | DIODE-RECTIFIER;RU20A,600V,1.5A,-                 |        | L810     | 2701-001032                                   | INDUCTOR-AXIAL;100UH,10%,5X14MM                    |        |
| D803     | 0402-000430 | DIODE-RECTIFIER;FML-G02S,200V,2.5A,TO-220F        |        | L902     | 2701-000189                                   | INDUCTOR-AXIAL;470NH,10%,2.5X3.4MM                 |        |
| D804     | 0402-000213 | DIODE-RECTIFIER;ERB12-06,600V,1A                  |        | L904     | 2701-000299                                   | INDUCTOR-AXIAL;13UH,10%,2.5X3.4MM                  |        |
| D809     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | NT801    | 1404-000187                                   | THERMISTOR-NTC;4.7 OHM,15% 2800K,27.2MW/C,TP       |        |
| D810     | 0402-000216 | DIODE-RECTIFIER;ERC24-06,600V,1.0A,DO-204         |        | P801     | 1404-001048                                   | THERMISTOR-PTC;70OHM,30%,200/220V,270V,19A,-,B     |        |
| D901     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | PC801    | 0604-001038                                   | PHOTO-COUPLER;TR,130-260%,200MW,DIP-4,ST           |        |
| D903     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | Q201     | 0501-002183                                   | TR-SMALL SIGNAL;KTC9014,NPN,625MW,TO-92,TP,100     |        |
| D905     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | Q202     | 0501-002183                                   | TR-SMALL SIGNAL;KTC9014,NPN,625MW,TO-92,TP,100     |        |
| D906     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | Q204     | 0501-002183                                   | TR-SMALL SIGNAL;KTC9014,NPN,625MW,TO-92,TP,100     |        |
| D907     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | △ Q401   | 0502-001115                                   | TR-POWER;KSC5386,NPN,50W,TO-3PF,ST,8-              |        |
| D908     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | △ Q402   | 0501-000369                                   | TR-SMALL SIGNAL;KSC2331-Y NPN 80V 60V 700MA        |        |
| D910     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M           |        | Q701     | 0501-002183                                   | TR-SMALL SIGNAL;KTC9014,NPN,625MW,TO-92,TP,100     |        |
| DA01     | 0401-000005 | DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP         |        | Q703     | 0501-000283                                   | TR-SMALL SIGNAL;KSA539 PNP 60V 45V 200MA 40        |        |
| DZ201    | 0403-000295 | DIODE-ZENER:MTZ5.1B 5.1V 4.94 5.20V 500MW         |        | Q901     | 0501-002183                                   | TR-SMALL SIGNAL;KTC9014,NPN,625MW,TO-92,TP,100     |        |
| DZ202    | 0403-000551 | DIODE-ZENER:MTZ3.9B,3.9V,3.89-4.16V,500MW,        |        | Q902     | 0501-002183                                   | TR-SMALL SIGNAL;KTC9014,NPN,625MW,TO-92,TP,100     |        |
| DZ203    | 0403-000563 | DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500MW,        |        | Q903     | 0501-002183                                   | TR-SMALL SIGNAL;KTC9014,NPN,625MW,TO-92,TP,100     |        |

## Electric Parts List

| Loc. No. | Code No.    | Description ; Specification                    | Remark | Loc. No. | Code No.    | Description ; Specification                  | Remark |
|----------|-------------|--|--------|----------|-------------|--|--------|
| Q904     | 0504-000123 | TR-DIGITAL:KSR1010,NPN,300MW,10K,TO-92,TP      |        | R606     | 2001-000591 | R-CARBON:3.3 KOHM 5% 1/8W AATP1.8X3.2MM      |        |
| Q905     | 0504-000123 | TR-DIGITAL:KSR1010,NPN,300MW,10K,TO-92,TP      |        | R610     | 2001-000563 | R-CARBON:27 KOHM 5% 1/8W AATP 1.8X3.2MM      |        |
| Q906     | 0504-000123 | TR-DIGITAL:KSR1010,NPN,300MW,10K,TO-92,TP      |        | R611     | 2001-000591 | R-CARBON:3.3 KOHM 5% 1/8W AATP1.8X3.2MM      |        |
| Q907     | 0504-000125 | TR-DIGITAL:KSR1012,NPN,300MW,47K,TO-92,TP      |        | R701     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM     |        |
| Q908     | 0504-000123 | TR-DIGITAL:KSR1010,NPN,300MW,10K,TO-92,TP      |        | R702     | 2001-000969 | R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| QA01     | 0501-002183 | TR-SMALL SIGNAL:KTC9014,NPN,625MW,TO-92,TP,100 |        | R703     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        |
| R200     | 2001-000780 | R-CARBON:470 OHM 5% 1/8W AATP 1.8X3.2MM        |        | R705     | 2001-000003 | R-CARBON:330 OHM 5% 1/8W AATP 1.8X3.2MM      |        |
| R201     | 2001-000005 | R-CARBON:390OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        | R706     | 2001-000221 | R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R202     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R713     | 2001-000812 | R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R203     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R714     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        |
| R204     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R715     | 2001-000812 | R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R207     | 2001-000008 | R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM        |        | R717     | 2001-000812 | R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R208     | 2001-000005 | R-CARBON:390OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        | R801     | 2003-000994 | R-METAL OXIDE(S):33KOHM,5%,2W,AF,TP,3.9X10MM |        |
| R209     | 2701-000114 | INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM              |        | R802     | 2003-000994 | R-METAL OXIDE(S):33KOHM,5%,2W,AF,TP,3.9X10MM |        |
| R210     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM         |        | R803     | 2001-001178 | R-CARBON(S):680OHM,5%,1/2W,AA,TP,2.4X6.4MM   |        |
| R211     | 2001-000331 | R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM        |        | R805     | 2003-001023 | R-METAL OXIDE(S):120OHM,5%,2W,AA,TP,3.9X10MM |        |
| R212     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R806     | 2002-001011 | R-COMPOSITION:3.3MOHM,10%/1/2W,AA,TP,3       |        |
| R213     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R807     | 2002-001011 | R-COMPOSITION:3.3MOHM,10%/1/2W,AA,TP,3       |        |
| R214     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R808     | 2001-000022 | R-CARBON(S):330OHM,5%,1/2W,AA,TP,2.4X6.4MM   |        |
| R215     | 2004-001995 | R-METAL:9.1KOHM,5%,1/8W,AA,TP,1.8X3.2M         |        | R809     | 2001-000622 | R-CARBON:300KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R216     | 2001-000490 | R-CARBON:200OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        | R810     | 2003-000527 | R-METAL OXIDE(S):18KOHM,5%,2W,AA,TP,4X12MM   |        |
| R217     | 2001-000449 | R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M        |        | R812     | 2003-000455 | R-METAL OXIDE(S):100OHM,5%,2W,AA,TP,4X12MM   |        |
| R218     | 2001-000591 | R-CARBON:3.3 KOHM 5% 1/8W AATP1.8X3.2MM        |        | R814     | 2008-000189 | R-FUSIBLE:0.47 OHM 10%2W AA TP 6X15          |        |
| R219     | 2001-000008 | R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM        |        | R815     | 2008-000189 | R-FUSIBLE:0.47 OHM 10%2W AA TP 6X15          |        |
| R221     | 2001-000290 | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM        |        | R816     | 2004-004089 | R-METAL:123KOHM,1%,1/2W,AA,TP,2.5X6.5M       |        |
| R223     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R817     | 2001-001983 | R-METAL:2.49KOHM,1%,1/2W,AA,TP,2.4X6.4       |        |
| R224     | 2001-000563 | R-CARBON:27 KOHM 5% 1/8W AATP 1.8X3.2MM        |        | R818     | 2004-001371 | R-METAL(S):1.5KOHM,1%,1/2W,AA,TP,2.4X6.4M    |        |
| R225     | 2001-000554 | R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        | R819     | 2004-001390 | R-METAL(S):1KOHM,2%,1/2W,AA,TP,2.4X6.4MM     |        |
| R226     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R820     | 2008-000299 | R-FUSIBLE:47 OHM 5% 2T AP TP 3.9X10MM        |        |
| R227     | 2004-001234 | R-METAL:75KOHM,5%,1/8W,AA,TP,1.8X3.2MM         |        | R821     | 2008-000266 | R-FUSIBLE(S):10HM,5%,2W,AF,TP,3.9X10MM       |        |
| R229     | 2001-000890 | R-CARBON:6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M        |        | R822     | 2001-001150 | R-CARBON(C):470KOHM,5%,1/2W,AA,TP,2.4X6.4M   |        |
| R230     | 2001-000793 | R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        | R823     | 2001-001150 | R-CARBON(C):470KOHM,5%,1/2W,AA,TP,2.4X6.4M   |        |
| R231     | 2001-000563 | R-CARBON:27 KOHM 5% 1/8W AATP 1.8X3.2MM        |        | R825     | 2003-001040 | R-METAL OXIDE(S):47KOHM,5%,2W,AF,TP,3.9X10MM |        |
| R232     | 2001-000356 | R-CARBON:150KOHM,5%,1/8W,AA,TP,1.8X3.2M        |        | R901     | 2001-000832 | R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X2.3M       |        |
| R234     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R902     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R236     | 2003-000634 | R-METAL OXIDE(S):3.9KOHM,5%,1W,AA,TP,3.3X9MM   |        | R903     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM     |        |
| R237     | 2001-000793 | R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM        |        | R904     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM     |        |
| R238     | 2001-000739 | R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M        |        | R905     | 2001-000241 | R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R239     | 2001-000739 | R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M        |        | R906     | 2001-000472 | R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R240     | 2001-000832 | R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X2.3M         |        | R907     | 2001-000995 | R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| R241     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M        |        | R908     | 2001-000232 | R-CARBON:1.3KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R242     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M        |        | R909     | 2001-000605 | R-CARBON:3.6KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R251     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM         |        | R910     | 2001-000290 | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM      |        |
| R252     | 2004-001914 | R-METAL:39KOHM,2%,1/8W,AA,TP,1.8X3.5MM         |        | R912     | 2004-001193 | R-METAL:680OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        |
| R262     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM         |        | R916     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM     |        |
| R301     | 2004-001983 | R-METAL:2.49KOHM,1%,1/2W,AA,TP,2.4X6.4         |        | R917     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM     |        |
| R302     | 2008-001033 | R-FUSIBLE:10 OHM 5% 2W AF TP 10X3.9MM          |        | R918     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM     |        |
| R303     | 2001-000273 | R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M        |        | R919     | 2001-000290 | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM      |        |
| R305     | 2004-001370 | R-METAL(S):1.3OHM,1%,1/2W,AA,TP,2.4X6.4MM      |        | R920     | 2001-000864 | R-CARBON:56KOHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| R306     | 2008-000254 | R-FUSIBLE(S):0.68 OHM 5% 2T AF TP 3.9X10MM     |        | R921     | 2001-001062 | R-CARBON(S):10MOHM,5%,1/2W,AA,TP,2.4X6.4MM   |        |
| R307     | 2003-001026 | R-METAL OXIDE(S):180OHM,5%,2W,AF,TP,3.9X       |        | R922     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM     |        |
| R402     | 2003-000664 | R-METAL OXIDE(S):33OHM,5%,2W,AF,TP,4X12MM      |        | R923     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM     |        |
| R403     | 2001-001114 | R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4MM     |        | R924     | 2001-000449 | R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R404     | 2008-000294 | R-FUSIBLE(S):33ohm,5%,2W,AF,TP,3.9X10MM        |        | R925     | 2001-000449 | R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R405     | 2001-001410 | R-CARBON(S):43 OHM 5% 1/2W,AA,TP,2.4X6.4MM     |        | R926     | 2001-000290 | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM      |        |
| R406     | 2001-000037 | R-CARBON(S):330OHM,5%,1/2W,AA,TP,2.4X6.4MM     |        | R927     | 2001-000290 | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM      |        |
| R407     | 2001-001037 | R-CARBON(S):0.39OHM,5%,1/2W,AA,TP,2.4X6.4M     |        | R928     | 2001-000066 | R-CARBON(S):10 KOHM 5% 1/2W AATP 2.4X6.4MM   |        |
| R408     | 2001-000022 | R-CARBON(S):33OHM,5%,1/2W,AA,TP,2.4X6.4MM      |        | R929     | 2004-000253 | R-METAL:11KOHM,1%,1/8W,AA,TP,1.8X3.2MM       |        |
| R409     | 2008-000204 | R-FUSIBLE(S):0.22OHM,10%,1/2W,AF,TP,2.5X6.5    |        | R930     | 2004-000218 | R-METAL:10KOHM,1%,1/8W,AA,TP,1.8X3.2MM       |        |
| R412     | 2003-000664 | R-METAL OXIDE(S):33OHM,5%,2W,AF,TP,4X12MM      |        | R931     | 2004-000218 | R-METAL:10KOHM,1%,1/8W,AA,TP,1.8X3.2MM       |        |
| R413     | 2003-000784 | R-METAL OXIDE(S):7.5KOHM,5%,2W,AD,TP,4X12MM    |        | R934     | 2001-000449 | R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R414     | 2003-000540 | R-METAL OXIDE(S):1KOHM,5%,2W,AD,TP,4X12MM      |        | R936     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R415     | 2008-000206 | R-FUSIBLE(S):1OHM,5%,1/2W,AF,TP,2.5X6.5MM      |        | R937     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R416     | 2008-000277 | R-FUSIBLE:68OHM,5%,1/2W,AA,TP,4.7X11MM         |        | R938     | 2001-000472 | R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R417     | 2008-000265 | R-FUSIBLE(S):1OHM,5%,2W,AA,TP,3.9X10MM         |        | R940     | 2001-000660 | R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM      |        |
| R420     | 2004-001377 | R-METAL(S):120 KOHM 1/2W 1% AA TP 2.4X6.4      |        | R946     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        |
| R501H    | 2002-001008 | R-COMPOSITION:1.8KOHM,5%,1/2W,AA,TP,3.7X9MM    |        | R948     | 2001-000241 | R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R502H    | 2002-001008 | R-COMPOSITION:1.8KOHM,5%,1/2W,AA,TP,3.7X9MM    |        | R951     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R503     | 2002-001008 | R-COMPOSITION:1.8KOHM,5%,1/2W,AA,TP,3.7X9MM    |        | R952     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM     |        |
| R504     | 2001-001062 | R-CARBON(S):10MOHM,5%,1/2W,AA,TP,2.4X6.4MM     |        | R954     | 2001-000006 | R-CARBON:2.4 KOHM 5% 1/8W AATP 1.8X3.2M      |        |
| R505     | 2008-001011 | R-FUSIBLE(S):0.18OHM,10%,2W,AF,TP,3.9X10MM     |        | R955     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        |
| R510     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R956     | 2001-000429 | R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM       |        |
| R511     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R960     | 2001-000290 | R-CARBON:10KOHM 5% 1/8W AATP 1.8X3.2 MM      |        |
| R512     | 2001-000281 | R-CARBON:1000OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        | R962     | 2001-000273 | R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R603     | 2001-000241 | R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M        |        | RA01     | 2004-001193 | R-METAL:680OHM,5%,1/8W,AA,TP,1.8X3.2MM       |        |
| R604     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M        |        | RA02     | 2001-000241 | R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |
| R605     | 2001-000563 | R-CARBON:27 KOHM 5% 1/8W AATP 1.8X3.2MM        |        | RA03     | 2001-000734 | R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M      |        |



| Loc. No.                  | Code No. | Description ; Specification                                   | Remark | Loc. No. | Code No. | Description ; Specification | Remark |
|---------------------------|----------|---|--------|----------|----------|-----------------------------|--------|
|                           | RA04     | 2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M           |        |          |          |                             |        |
|                           | RL901    | AA59-60001U MODULE-REMOCON:-,ORC-50VF,38KHZ,940NM,MESH,V,     |        |          |          |                             |        |
|                           | RT03     | 2001-000252 R-CARBON:1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M           |        |          |          |                             |        |
|                           | RW701    | 2011-001133 R-NETWORK:33K/24K/75X3,1/8W                       |        |          |          |                             |        |
|                           | RW702    | 2011-001098 R-NETWORK:75/75/1K,75OHM,5%,--P                   |        |          |          |                             |        |
|                           | RX801    | 2002-001011 R-COMPOSITION:3.3MOHM,10%1/2W,AA,TP,3             |        |          |          |                             |        |
|                           | SFN02    | 2904-001070 FILTER-SAW AV:37.4MHZ,SIP5K,TP,14.5DB,PAL-B/      |        |          |          |                             |        |
|                           | SW801    | 3403-001020 SWITCH-PUSH:250V,5A,DPST,OFF ON-OFF               |        |          |          |                             |        |
|                           | SW901    | 3404-000244 SWITCH-TACT:15V,20MA,90-170GF,7.5X7MM,SPST        |        |          |          |                             |        |
|                           | SW902    | 3404-000244 SWITCH-TACT:15V,20MA,90-170GF,7.5X7MM,SPST        |        |          |          |                             |        |
|                           | SW903    | 3404-000244 SWITCH-TACT:15V,20MA,90-170GF,7.5X7MM,SPST        |        |          |          |                             |        |
|                           | SW904    | 3404-000244 SWITCH-TACT:15V,20MA,90-170GF,7.5X7MM,SPST        |        |          |          |                             |        |
|                           | SW905    | 3404-000244 SWITCH-TACT:15V,20MA,90-170GF,7.5X7MM,SPST        |        |          |          |                             |        |
| △                         | T401     | AA26-50001B HORIZ,DRIVE:-,7.1MH,102UH,10-20UH,YL081,ST        |        |          |          |                             |        |
| △                         | T444     | AA26-30001Y TRANS-FLYBACK:-,FSV-20A001,20,125V                |        |          |          |                             |        |
| △                         | T801     | AA26-200070 TRANS-SWITCHING:-,180-260V,125V/12.5V,EN,EER28    |        |          |          |                             |        |
| △                         | TU01     | AA40-10006Q TUNER-V/S;TELE4-125A,PAL-B/G,TR,181CH             |        |          |          |                             |        |
| △                         | V999     | 3704-001090 SOCKET-CRT:9P,15.24PI,26.5PI,SN,-                 |        |          |          |                             |        |
|                           | X203     | 2801-000274 CRYSTA-UNIT:4.433618MHZ,30PPM,28AAM,20PF          |        |          |          |                             |        |
|                           | X901     | 2801-000724 CRYSTAL-UNIT:6MHZ,50PPM,28-AAM,20PF,40OHM,T       |        |          |          |                             |        |
|                           | Z202     | 2903-001019 FILTER-SAW:TR,5.5/5,742MHZ,--,-,TP                |        |          |          |                             |        |
|                           | Z204     | 2903-000184 FILTER-CERAMIC:BP,5.5MHZ                          |        |          |          |                             |        |
|                           | Z206     | 2903-000184 FILTER-CERAMIC:BP,5.5MHZ                          |        |          |          |                             |        |
| <b>ASSY-PCB,A/V FRONT</b> |          |   |        |          |          |                             |        |
| *                         |          | HA99-200002 ASSY-PCB,A/V FRONT(ACI):20,SCT13B,S15A            |        |          |          |                             |        |
|                           | L-CON    | AA39-20461C LEAD-CONNECTOR,ASSY:-,YBNH250-11,67096-011,11,300 |        |          |          |                             |        |
|                           | QE01     | 0501-000283 TR-SMALL SIGNAL:KSA539 PNP 60V 45V 200MA 40       |        |          |          |                             |        |
|                           | RE05     | 2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM           |        |          |          |                             |        |
|                           | RE03     | 2001-000010 R-CARBON(S):68KOHM,5%,1/8W,AA,TP,1.8X3.2MM        |        |          |          |                             |        |
|                           | RE04     | 2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM            |        |          |          |                             |        |
|                           | RE01     | 2001-001153 R-CARBON(S):47OHM,5%,1/2W,AA,TP,2.4X6.4MM         |        |          |          |                             |        |
|                           | RE02     | 2001-001153 R-CARBON(S):47OHM,5%,1/2W,AA,TP,2.4X6.4MM         |        |          |          |                             |        |
|                           | CE07     | 2202-000222 C-CERAMIC,MLC-AXIAL:3.3NF,20%,16V,Y5P,-,7.5MM,TP  |        |          |          |                             |        |
|                           | CE06     | 2202-000862 C-CERAMIC,MLC-AXIAL:390PF,10%50V,Y5P,3.5X1.9TP    |        |          |          |                             |        |
|                           | CE03     | 2401-001264 C-AL:4.7UF,20%,50V,BP,6X11MM,5MM,TP               |        |          |          |                             |        |
|                           | CE01     | 2401-001840 C-AL:100UF,20%,16V,GP,TP,8X11.5MM,5               |        |          |          |                             |        |
|                           | LE01     | 2701-000158 INDUCTOR-AXIAL:22 UH 10% 2.5X3.4MM                |        |          |          |                             |        |
|                           | J-PHONE  | 3722-000143 JACK-PHONE:1P,3.4MM,MBAG,BLACK                    |        |          |          |                             |        |
|                           | J-RCA    | 3722-000507 JACK-RCA:2P 3.6MM:-,AG                            |        |          |          |                             |        |
| <b>REMOCON</b>            |          |   |        |          |          |                             |        |
| *                         |          | AA59-10101Q REMOCON:DP,TM59,AA59-10095W                       |        |          |          |                             |        |
| <b>ASSY-HOLDER,SPK</b>    |          |   |        |          |          |                             |        |
| *                         |          | AA91-60028A ASSY-HOLDER,SPK:ABS 8 OHM 5W,5085                 |        |          |          |                             |        |
| <b>ASSY-POWER,CORD</b>    |          |   |        |          |          |                             |        |
| △                         | P/CORD   | AA96-20077B ASSY-POWER,CORD:SCT11D                            |        |          |          |                             |        |
| <b>ASSY-CRT</b>           |          |   |        |          |          |                             |        |
| △                         | CRT      | AA03-10031D CRT-COLOR:-,A48ECR141X,+400MG,20,90DEG            |        |          |          |                             |        |
| △                         | D-YOKE   | AA27-50005H DEFLECTION-YOKE:-,DSE-2093BL,20/A48ECR141X,ST     |        |          |          |                             |        |
|                           | S-DY     | AA63-60028A SPACER-DY:NEOPRENE,-,BLK,V0 W12,-,-               |        |          |          |                             |        |
| <b>ASSY-ACCESSORY</b>     |          |   |        |          |          |                             |        |
|                           |          | BUYER : SECOSA (ONLY)   |        |          |          |                             |        |
| M-USE                     |          | AA68-11273A MANUAL-USERS:S15A,SPANISH,W/O TTX,B5,W/P 10       |        |          |          |                             |        |
|                           |          | BUYER : AMFO (ONLY)   |        |          |          |                             |        |
|                           |          | HA68-100051 MANUAL-USERS:-,A/P,80(G),ENG,GER,DAN,FRA          |        |          |          |                             |        |