

7. Electric Parts List

7-1 CK20H1Z5X/XEH (CK20H1T5X AND CK20H1Z5X Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN							
BUYER : SEH							
*	HA94-100439	ASSY-PCB,MAIN:CK20H1Z5X/XEH,S15A	LOCAL	R906	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C208	2401-000939	C-AL:22uF,20%,25V,GP,TP,5x11,5		R907	2001-000995	R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C301	2202-000253	C-CERAMIC,MLC-AXIAL:4.7nF,20%,16V,Y5R,TP,1.9x3.5,7		R908	2001-000232	R-CARBON:1.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C506	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		R909	2001-000605	R-CARBON:3.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C908	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,5		R910	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C909	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,5		R916	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C916	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		R917	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C918	2003-001030	R-METAL OXIDE(S):2.4Kohm,5%,1W,AF,TP,2.5x6.5mm		R918	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C919	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		R920	2001-000864	R-CARBON:56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C922	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3,0,5		R934	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C927	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3,0,5		R938	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
D204	2001-001155	R-CARBON(S):5.6Kohm,5%,1/2W,AA,TP,2.4x6.4m		R948	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
D905	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		R955	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
D906	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		RT03	2001-000252	R-CARBON:1.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
D907	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		X901	2801-000724	CRYSTAL-UNIT:6MHz,50ppm,28-AAM,20pF,40ohm,T	
D908	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		REMOCON			
D910	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		*	AA59-10101WREMOCON:DP,TM59,-,-,-,-,-,AA59-10107N,		
DZ202	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M		ASSY-ACCESSORY			
DZ909	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M		USER/M	HA68-100049	MANUAL-USERS-,A/P 80(G),HUN,CK5073Z5X/	LOCAL
⚠ IC802	1203-000575	IC-POSI.ADJUST.REG:8133,SIP9P,-,PLASTIC,5/5,2V,-					
⚠ IC901	AA13-30020GIC-MCU:-,Z90234-R3782,8BIT,SDIP,CS-53						
J198	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP					
L904	2701-000299	INDUCTOR-AXIAL:13UH,10%,2.5X3.4MM					
Q203	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,TP,120-					
R228	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R820	2008-000299	R-FUSIBLE(S):47ohm,5%,2W,AF,TP,3.9x10mm					
R821	2008-000266	R-FUSIBLE(S):10HM,5%,2W,AF,TP,3.9X10MM					

7-2 CK21H1T5X/XEO (CK20H1T5X AND CK21H1T5X Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN				ASSY-ACCESSORY			
BUYER : SEPOL							
*	HA94-100505	ASSY-PCB,MAIN:CK21H1T5X/XEO,S15A	LOCAL	USER/M	HA68-100060	MANUAL-USERS-,A/P 80(G),POL,CK5073T5X/	LOCAL
C301	2202-000253	C-CERAMIC,MLC-AXIAL:4.7nF,20%,16V,Y5R,TP,1.9x3.5,7		ASSY-CABINET;21H1			
C416	2306-000195	C-FILM,MPPF:360nF,5%,400V,TP,26x19x11.5,20		*	HA91-100021	ASSY-CABINET,FRONT:21H1LOCAL	
CN802	AA27-20003Z	COIL-DEGAUSSING:-,21,13.5ohm,25T,L2380,E		FRONT	HA64-31352A	CABINET-FRONT:-,21H1,BK708P,HIPS,HB,BLK,-,-	LOCAL
DZ806	0403-000355	DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500mW					
LD901	AA96-30001B	ASSY-LED,GUIDE:-,AA61-50055A,DL-G5RGA,-					
LW01	AA27-40001N	COIL-HORIZ.WIDTH:-,90/260uH,SB-5S620,PI0.8,-					
R301	2004-000869	R-METAL:3KOHM,1%,1/8W,AA,TP,1.8X3.2MM					
R305	2001-001048	R-CARBON(S):1.2ohm,5%,1/2W,AA,TP,2.4x6.4mm					
R913	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT03	2001-000958	R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM					
ASSY-CRT							
⚠ CRT	AA03-10031E	CRT-COLOR:-,A51EER131X,+400mG,21,90deg,					
D/Y	AA27-50005G	DEFLECTION-YOKE:-,DST-21944(2),21/A51EER131XS					

7-3 CK21H1Z5X/XEH (CK20H1T5X AND CK21H1Z5X Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN				R820	2008-000299	R-FUSIBLE(S);47ohm,5%,2W,AF,TP,3.9x10mm	
BUYER : SEH				R821	2008-000266	R-FUSIBLE(S);10HM,5%,2W,AF,TP,3.9X10MM	
*	HA94-100442	ASSY-PCB,MAIN:CK21H1Z5X/XEH,S15A	LOCAL	R906	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C208	2401-000939	C-AL:22uF,20%,25V,GP,TP,5x11,5		R907	2001-000995	R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C301	2202-000253	C-CERAMIC,MLC-AXIAL:4.7nF,20%,16V,Y5R,TP,1.9x3.5,7		R908	2001-000232	R-CARBON:1.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C416	2306-000195	C-FILM,MPPF:360nF,5%,400V,TP,26x19x11.5,20		R909	2001-000605	R-CARBON:3.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C908	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,5		R910	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C909	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,5		R916	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C916	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		R917	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C918	2003-001030	R-METAL OXIDE(S);2.4Kohm,5%,1W,AF,TP,2.5x6.5mm		R918	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C919	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		R920	2001-000864	R-CARBON:56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C922	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0,5		R934	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C927	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0,5		R938	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CN802	AA27-20003Z	COIL-DEGAUSSING:-,21,13.5ohm,25T,L2380,E		R948	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
D204	2001-001155	R-CARBON(S);5.6Kohm,5%,1/2W,AA,TP,2.4x6.4m		R955	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
D905	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		X901	2801-000724	CRYSTAL-UNIT:6MHz,50ppm,28-AAM,20pF,40ohm,T	
D906	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		ASSY-CRT			
D907	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		△ CRT	AA03-10031E	CRT-COLOR:-,A51EER131X,+400mG,21,90deg,	
D908	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		D/Y	AA27-50005G	DEFLECTION-YOKE:-,DST-21944(2),21/A51EER131XS	
D910	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		ASSY-ACCESSORY			
DZ202	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M		USER/M	HA68-100049	MANUAL-USERS:-,A/P 80(G),HUN,CK5073Z5X/	LOCAL
DZ909	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M		ASSY-CABINET;21H1			
△ IC802	1203-000575	IC-POSI.ADJUST.REG:8133,SIP,9P,-,PLASTIC,5/5,2V,-		*	HA91-100021	ASSY-CABINET,FRONT;21H1	LOCAL
△ IC901	AA13-30020G	IC-MCU:-,Z90234-R3782,8BIT,SDIP,CS-53		FRONT	HA64-31352A	CABINET-FRONT:-,21H1,BK708P,HIPS,HB,BLK,-,-	LOCAL
J198	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP					
L904	2701-000299	INDUCTOR-AXIAL:13UH,10%,2.5X3.4MM					
LW01	AA27-40001N	COIL-HORIZ.WIDTH:-,90/260uH,SB-5S620,PIO.8,-					
Q203	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,TP,120-					
R228	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R301	2004-000869	R-METAL:3KOHM,1%,1/8W,AA,TP,1.8X3.2MM					
R305	2001-001048	R-CARBON(S);1.2ohm,5%,1/2W,AA,TP,2.4x6.4mm					

7-4 CK20H1T5X/XEH Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN				C224	2202-000295	C-CERAMIC,MLC-AXIAL:68PF,5%,50V,SL,3.5X19,-,TP	
BUYER : SEH				C226	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m	
*	HA94-100440	ASSY-PCB,MAIN:CK20H1T5X/XEH,S15A	LOCAL	C227	2401-001495	C-AL:47uF,20%,16V,GP,5x11mm,5mm,TP	
C101	2401-000939	C-AL:22uF,20%,25V,GP,TP,5x11,5		C228	2201-000247	C-CERAMIC,DISC:15PF,5%,50V,CH,TP,5X3,5	
C102	2401-001082	C-AL:330nF,20%,50V,GP,TP,5x11,5		C230	2401-001495	C-AL:47uF,20%,16V,GP,5x11mm,5mm,TP	
C103	2401-002463	C-AL:470uF,20%,16V,GP,TP,8x11.5,5		C231	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C201	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		C232	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
C202	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		C238	2401-001495	C-AL:47uF,20%,16V,GP,5x11mm,5mm,TP	
C203	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5		C239	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C204	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C240	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5X4.0X5.0MM,	
C205	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5mm,		C247	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C206	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5mm,		C248	2309-000138	C-FILM,PE-PPF:100nF,5%,50V,TP,20x16x8.5,7.5m	
C207	2305-000196	C-FILM,MPEF:150nF,5%,63V,TP,-,5MM		C249	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
C208	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5		C250	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m	
C209	2202-000794	C-CERAMIC,MLC-AXIAL:18pF,5%,50V,CH,TP,3.5x19mm,-		C251	2301-000204	C-FILM,PEF:2.7nF,5%,50V,TP,7.4x3.9x13mm,5	
C210	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm		C252	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm	
C211	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5X4.0X5.0MM,		C253	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C212	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		C254	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C213	2201-000273	C-CERAMIC,DISC:18pF,5%,50V,CH,TP,5x3mm,5		C255	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C214	2301-000356	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5mm		C301	2202-000210	C-CERAMIC,MLC-AXIAL:270PF,10%,50V,Y5P,TP,1.9X3.5,7	
C215	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm		C302	2202-000253	C-CERAMIC,MLC-AXIAL:4.7nF,20%,16V,Y5R,TP,1.9x3.5,7	
C216	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		C303	2401-003028	C-AL:100uF,20%,25V,WT,TP,6.3x11,5	
C217	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		C304	2401-000903	C-AL:22UF,20%,160V,WT,TP,10X20MM,5M	
C219	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C305	2305-000178	C-FILM,MPEF:10nF,5%,100V,TP,-,5mm	
C221	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP,1.9x3.5,-		C306	2305-000285	C-FILM,MPEF:220nF,5%,100V,TP,20x18x11.5,15	
C222	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		C307	2305-000708	C-FILM,MPEF:150nF,5%,100V,TP,16.5x10.3x5.7	
				C308	2305-000450	C-FILM,MPEF:56nF,5%,100V,TP,-,5MM	
				C401	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm	
				C402	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4,5	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C403	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4,5		CW901	2503-000156	C-NETWORK;100pFx4,20%,50V	
C404	2401-001998	C-AL:1000UF,20%,25V,GP,TP,10X20,5MM		D201	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C408	2401-001530	C-AL:47uF,20%,25V,GP,TP,5x11,5		D205	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C409	2306-000253	C-FILM,MPPF:7.2nF,5%,1.6KV,TP,28.5x18.5x12		D209	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C410	2201-000984	C-CERAMIC,DISC:680pF,10%,2KV,Y5P,TP,11x6,7,5mm		D210	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C411	2401-000927	C-AL:22UF,20%,250V,GP,TP,13X20MM,5M		D211	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C413	2305-000382	C-FILM,MPEF:4.7nF,5%,400V,TP,-,5MM		D213	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C414	2301-001065	C-FILM,MPPF:47nF,5%,630V,TP,19x15.5x7,7,5		D401	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
C415	2401-000560	C-AL:1uF,20%,160V,GP,TP,6.3x11,5		D402	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
C416	2306-000204	C-FILM,MPPF:430nF,5%,400V,TP,26x20.5x12.		D403	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C417	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4,5		D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,TP	
C418	2401-000384	C-AL:10UF,20%,100V,GP,TP,6.3X11,5MM		D405	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C419	2201-000984	C-CERAMIC,DISC:680pF,10%,2KV,Y5P,TP,11x6,7,5mm		D406	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C502	2301-000213	C-FILM,PEF:220nF,5%,250V,TP,21.5x11,7,5		D501	0402-000216	DIODE-RECTIFIER;ERC24-06,600V,1.0A,DO-204	
C503	2201-002063	C-CERAMIC,DISC:10nF,+80-20%,3KV,Y5V,TP,16x5,7		D502	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C504	2401-001232	C-AL:4.7uF,20%,250V,GP,TP,10x12,5,5		D503	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C506	2401-000430	C-AL:10UF,20%,250V,GP,TP,10X16MM,5M		D504	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C601	2202-000210	C-CERAMIC,MLC-AXIAL:270PF,10%,50V,Y5P,TP,1.9X3.5,7		D701	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C602	2401-000939	C-AL:22uF,20%,25V,GP,TP,5x11,5		D800	1405-000187	VARISTOR:750V,1250A,12.5x7mm,TP	
C603	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm		D801	0402-000102	DIODE-BRIDGE:D2SB60,600V,1.5A,-	
C604	2401-001323	C-AL:470nF,20%,50V,BP,TP,5x11,5mm		D802	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
C610	2401-001998	C-AL:1000UF,20%,25V,GP,TP,10X20,5MM		D803	0402-000430	DIODE-RECTIFIER;FML-G02S,200V,3.0A,TO-220F,BK	
C613	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		D804	0402-000213	DIODE-RECTIFIER;FML-12C,600V,1.0A,DO-41,TP	
C614	2202-000210	C-CERAMIC,MLC-AXIAL:270PF,10%,50V,Y5P,TP,1.9X3.5,7		D809	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C702	2202-000263	C-CERAMIC,MLC-AXIAL:470pF,10%,50V,Y5P,TP,3.5x19,-		D810	0402-000216	DIODE-RECTIFIER;ERC24-06,600V,1.0A,DO-204	
C704	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP,1.9x3.5,-		D901	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C705	2401-001264	C-AL:4.7uF,20%,50V,BP,TP,5x11,5		D903	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C706	2401-001264	C-AL:4.7uF,20%,50V,BP,TP,5x11,5		D905	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C800	2306-000321	C-FILM,MPPF:470nF,5%,275V,TP,-,22.5mm		D910	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C801	2401-000534	C-AL:150uF,20%,400V,GP,ST,25x30,10		D911	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C802	2401-002284	C-AL:33uF,20%,50V,GP,TP,5x11,5		DA01	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C803	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m		DT01	2001-000252	R-CARBON:1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C804	2301-000310	C-FILM,PEF:68nF,5%,50V,TP,8.0X8.5X4.0X5,5		DT02	2001-000252	R-CARBON:1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C805	2303-000163	C-FILM,PPF:2.2nF,5%,800V,TP,15x13x8.5,7,5		DT03	2001-000252	R-CARBON:1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C806	2201-000446	C-CERAMIC,DISC:3.3nF,20%,400V,Y5U,TP,18x8,10mm		DZ201	0403-000355	DIODE-ZENER;UZ5.1BSB,5.1V,4.97-5.18V,500mW	
C807	2201-000991	C-CERAMIC,DISC:560pF,10%,2KV,Y5P,TP,13x7,7,5		DZ203	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C808	2401-000262	C-AL:100uF,20%,160V,HR,TP,16x25,7,5		DZ204	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C809	2401-002290	C-AL:47uF,20%,160V,GP,TP,13x20,5		DZ205	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C810	2201-000991	C-CERAMIC,DISC:560pF,10%,2KV,Y5P,TP,13x7,7,5		DZ208	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C811	2401-003141	C-AL:2200UF,20%,25V,WT,TP,13X25,5MM		DZ301	0403-000660	DIODE-ZENER;MTZ22A,22V,20.15-21.2V,500mW,D	
C814	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		DZ302	0403-001039	DIODE-ZENER;MA2560,5.6V,5.2-6.0V,1W,DO-41,TP	
C815	2401-000808	C-AL:220uF,20%,16V,GP,TP,8x11,5,5		DZ401	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW	
C816	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		DZ501	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C818	2401-001495	C-AL:47uF,20%,16V,GP,5x11mm,5mm,TP		DZ502	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C819	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		DZ503	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C901	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		DZ504	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C902	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		DZ701	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C904	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		DZ702	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C905	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11,5		DZ703	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C907	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,8x3.5		DZ704	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C908	2201-000980	C-CERAMIC,DISC:30pF,5%,50V,CH,TP,5.0x3.0,5mm		DZ705	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C909	2201-000980	C-CERAMIC,DISC:30pF,5%,50V,CH,TP,5.0x3.0,5mm		DZ802	0403-000297	DIODE-ZENER;MTZ6.2B,6.2V,5.96-6.27V,500mW	
C910	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		DZ803	1203-001217	IC-POS.I.ADJUST REG.:431,TO-92,3P,4.58MIL,PLASTIC,2	
C911	2401-002235	C-AL:10UF,20%,16V,GP,TP,5X11MM,5MM		DZ804	2001-001170	R-CARBON(S):6.8ohm,5%,1/2W,AA,TP,2.4x6.4mm	
C912	2201-000234	C-CERAMIC,DISC:150pF,5%,50V,CH,TP,9.5x3,5		DZ806	0403-000295	DIODE-ZENER;MTZ5.1B,5.1V,4.94-5.20V,500mW	
C913	2301-000108	C-FILM,PEF:1.5nF,5%,50V,TP,6.5x3.0x5.5mm,		DZ808	0403-000300	DIODE-ZENER;MTZ8.2B,8.2V,7.78-8.19V,500mW	
C914	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		DZ809	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW	
C915	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		DZ901	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C916	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		DZ902	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW	
C917	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ903	1203-000451	IC-VOLTAGE REGULATOR:33,TO-92,3P,-,PLASTIC,31/35V,	
C920	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		DZ905	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW	
C923	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ907	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW	
C924	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		△ F801	3601-000261	FUSE-FERRULE:250V,3.15A,TIME LAG,GLASS,5x20	
C926	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		F801A	3602-000114	FUSE-HOLDER:-,30MOHM	
C928	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,-,5mm		F801B	3602-000114	FUSE-HOLDER:-,30MOHM	
CA01	2401-001264	C-AL:4.7uF,20%,50V,BP,TP,5x11,5		△ F802	3601-001086	FUSE-FERRULE:125V,5A,FA,GLASS,2.4x7.5mm	
CN501	AA39-20109B	LEAD-CONNECTOR,ASSY:-,YBNH025-08,S,8P,500,1007#26		△ IC201	1204-001440	IC-VIDEO SYSTEM;TDA8842,DIP,56P,300MIL,PLASTIC	
CN603	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5mm,STRAIGHT,SN		△ IC301	1204-000441	IC-IF CIRCUIT;TDA8356,SIP,9P,-,PLASTIC,40V,-	
CN703	3711-002648	CONNECTOR-HEADER;BOX,9P,1R,2.5mm,STRAIGHT,SN		△ IC501	1201-001159	IC-VIDEO AMP;6107,ZIP,9P,300MIL,SINGLE,-,PL	
CN802	AA27-20003Y	COIL-DEGAUSSING:-,20,15,2ohm,28T,12170,E		△ IC601	1201-001147	IC-AUDIO AMP;7056P,SIP,9P,-,SINGLE,41.5DB,P	
CT01	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		△ IC801	1203-001494	IC-PWM CONTROLLER;S30680RF,TO3PF-5L,5,210,PLASTI	
CT02	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		△ IC802	1203-000644	IC-POS.FIXED REG.;7630,SIP,10P,-,PLASTIC,5.1/8V,	
CT03	2401-001495	C-AL:47uF,20%,16V,GP,5x11mm,5mm,TP		△ IC901	AA13-30019P	IC-MCU;-,SAA5291PS-098,8BIT,SDIP,CK-5	
CT04	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		△ IC902	1103-001105	IC-EEPROM;24C040,4KX1BIT,DIP,8P,300MIL,1	
CT05	2202-000154	C-CERAMIC,MLC-AXIAL:150PF,10%,50V,Y5P,TP		J149	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM	
CT06	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		J175	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CT07	2401-001495	C-AL:47uF,20%,16V,GP,5x11mm,5mm,TP		J176	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Electric Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
J178	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		R227	2004-001234	R-METAL:75KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
J185	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R230	2001-000793	R-CARBON:470HM,5%,1/8W,AA,TP,1.8X3.2MM	
JS701	3722-000183	JACK-SCART:21P,4mm,SN,BLK,NO		R231	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L102	2701-000212	INDUCTOR-AXIAL:68UH,10%,2.8X7MM		R232	2001-000356	R-CARBON:150KOHM,5%,1/8W,AA,TP,1.8X3.2M	
L103	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R234	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L202	2701-000168	INDUCTOR-AXIAL:3.3uH,5%,2.5X3.4mm		R236	2003-000634	R-METAL OXIDE(S):3.9Kohm,5%,1W,AA,TP,3.3x9mm	
L206	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R237	2001-000793	R-CARBON:470HM,5%,1/8W,AA,TP,1.8X3.2MM	
L301	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R238	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
L302	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R239	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
L304	2701-000159	INDUCTOR-AXIAL:22UH,10%,4.2X9.8MM		R240	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L305	2701-000116	INDUCTOR-AXIAL:10uH,10%,4.2x9.8mm		R241	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
L306	2701-000115	INDUCTOR-AXIAL:10UH,10%,2.8X7MM		R242	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
L401	AA27-30001B	COIL-LINEARITY:-,195UH,QIC1010,PIO.4,4.5X21.5		R250	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L402	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-		R251	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L601	2701-000146	INDUCTOR-AXIAL:2.2UH,10%,2.5X3.4MM		R252	2004-001914	R-METAL:39KOHM,2%,1/8W,AA,TP,1.8X3.5MM	
L702	2701-000184	INDUCTOR-AXIAL:4.7UH,10%,2.5X3.4MM		R301	2004-001983	R-METAL:2.49KOHM,1%,1/2W,AA,TP,2.4X6.4	
L703	2701-000184	INDUCTOR-AXIAL:4.7UH,10%,2.5X3.4MM		R302	2008-001033	R-FUSIBLE(S):10ohm,5%,2W,AF,TP,3.9x10mm	
L704	2701-000184	INDUCTOR-AXIAL:4.7UH,10%,2.5X3.4MM		R303	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
L706	2701-000184	INDUCTOR-AXIAL:4.7UH,10%,2.5X3.4MM		R305	2004-001370	R-METAL(S):1.3ohm,1%,1/2W,AA,TP,2.4x6.4mm	
L801	AA29-30001G	FILTER-LINE:-,27mH,0.6A,-,-		R306	2008-000254	R-FUSIBLE(S):0.68ohm,5%,2W,AF,TP,3.9x10mm	
L804	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400G		R307	2003-001026	R-METAL OXIDE(S):180OHM,5%,2W,AF,TP,3.9X	
L805	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-		R402	2003-000664	R-METAL OXIDE(S):33OHM,5%,2W,AF,TP,4X12MM	
L807	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-		R403	2001-001114	R-CARBON(S):270ohm,5%,1/2W,AA,TP,2.4x6.4mm	
L809	2701-001032	INDUCTOR-AXIAL:100UH,10%,5X14MM		R404	2008-000294	R-FUSIBLE(S):33ohm,5%,2W,AF,TP,3.9x10mm	
L810	2701-001032	INDUCTOR-AXIAL:100UH,10%,5X14MM		R405	2001-001410	R-CARBON(S):430HM,5%,1/2W,AA,TP,2.4x6.4MM	
L902	2701-000189	INDUCTOR-AXIAL:470NH,10%,2.5X3.4MM		R406	2001-000037	R-CARBON(S):330ohm,5%,1/2W,AA,TP,2.4x6.4mm	
LD901	AA96-30007A	ASSY-LED,GUIDE:-,AA61-50055A,DL-G7GA,GREEN		R407	2001-001037	R-CARBON(S):0.39ohm,5%,1/2W,AA,TP,2.4x6.4m	
LT01	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-		R408	2001-000022	R-CARBON(S):33ohm,5%,1/2W,AA,TP,2.4x6.4mm	
LT02	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-		R409	2008-000204	R-FUSIBLE(S):0.22ohm,10%,1/2W,AF,TP,2.5x6.5	
LT03	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R412	2003-000664	R-METAL OXIDE(S):33OHM,5%,2W,AF,TP,4X12MM	
NT801	1404-000187	THERMISTOR-NTC:4.7ohm,15%,2800K,27.2mW/C,TP		R413	2003-000784	R-METAL OXIDE(S):7.5Kohm,5%,2W,AF,TP,4x12mm	
P801	1404-001048	THERMISTOR-PTC:7ohm,30%,200/220V,270V,19A,-,B		R414	2003-000540	R-METAL OXIDE(S):1KOHM,5%,2W,AF,TP,4X12MM	
PC801	0604-001038	PHOTO-COUPLER:TR,130-260%,200MW,DIP-4,ST		R415	2008-000206	R-FUSIBLE(S):1ohm,5%,1/2W,AF,TP,2.5x6.5mm	
Q201	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R416	2008-000277	R-FUSIBLE:680HM,5%,1/2W,AA,TP,4.7X11MM	
Q202	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R417	2008-000265	R-FUSIBLE(S):10HM,5%,2W,AA,TP,3.9X10MM	
Q204	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R501H	2002-001008	R-COMPOSITION:1.8Kohm,5%,1/2W,AA,TP,3.7x9mm	
Q251	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R502H	2002-001008	R-COMPOSITION:1.8Kohm,5%,1/2W,AA,TP,3.7x9mm	
Q401	0502-001115	TR-POWER:KSC5386,NPN,50W,TO-3PF,ST,8-		R503	2002-001008	R-COMPOSITION:1.8Kohm,5%,1/2W,AA,TP,3.7x9mm	
Q402	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L,-,120-		R504	2001-001062	R-CARBON(S):10Mohm,5%,1/2W,AA,TP,2.4x6.4mm	
Q701	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R505	2008-001011	R-FUSIBLE(S):0.18ohm,10%,1/2W,AF,TP,3.9x10mm	
Q703	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,TP,120-		R510	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q901	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R511	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q902	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R512	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q903	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R603	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
Q904	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R604	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
Q905	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R610	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q906	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R611	2001-000723	R-CARBON:4.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
Q907	0504-000125	TR-DIGITAL:KSR1012,NPN,300mW,47K,TO-92,TP		R701	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q908	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R702	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM	
QA01	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R703	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
QT02	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R705	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,1.8X3.2MM	
QT03	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R706	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R200	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM		R713	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R201	2001-000005	R-CARBON:390OHM,5%,1/8W,AA,TP,1.8X3.2MM		R714	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R202	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R715	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R203	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R717	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R204	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R801	2003-000994	R-METAL OXIDE(S):33Kohm,5%,2W,AF,TP,3.9x10mm	
R205	2001-000793	R-CARBON:470HM,5%,1/8W,AA,TP,1.8X3.2MM		R802	2003-000994	R-METAL OXIDE(S):33Kohm,5%,2W,AF,TP,3.9x10mm	
R207	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R803	2001-001178	R-CARBON(S):680ohm,5%,1/2W,AA,TP,2.4x6.4mm	
R208	2001-000005	R-CARBON:390OHM,5%,1/8W,AA,TP,1.8X3.2MM		R805	2003-001023	R-METAL OXIDE(S):120ohm,0.05,2W,AF,TP,3.9x10mm	
R209	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R806	2002-001011	R-COMPOSITION:3.3Mohm,10%,1/2W,AA,TP,3.7x9mm	
R210	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R807	2002-001011	R-COMPOSITION:3.3Mohm,10%,1/2W,AA,TP,3.7x9mm	
R211	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R808	2001-000022	R-CARBON(S):33ohm,5%,1/2W,AA,TP,2.4x6.4mm	
R212	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R809	2001-000622	R-CARBON:300KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R213	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R810	2003-000527	R-METAL OXIDE(S):18Kohm,5%,2W,AA,TP,4x12mm	
R214	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R812	2003-000455	R-METAL OXIDE(S):100ohm,5%,2W,AA,TP,4x12mm	
R215	2004-001995	R-METAL:9.1KOHM,5%,1/8W,AA,TP,1.8X3.2M		R815	2008-001002	R-FUSIBLE(S):0.18ohm,5%,2W,AA,TP,3.9x10mm	
R216	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP,1.8X3.2MM		R816	2004-004089	R-METAL:123KOHM,1%,1/2W,AA,TP,2.5x6.5M	
R217	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		R817	2004-001983	R-METAL:2.49KOHM,1%,1/2W,AA,TP,2.4X6.4	
R218	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		R818	2004-001371	R-METAL(S):1.5Kohm,1%,1/2W,AA,TP,2.4x6.4m	
R219	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R819	2004-001390	R-METAL(S):1KOHM,2%,1/2W,AA,TP,2.4x6.4MM	
R220	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R820	2008-001062	R-FUSIBLE:39ohm,5%,2W,AF,TP,3.9x10mm	
R221	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R822	2001-001150	R-CARBON(S):470Kohm,5%,1/2W,AA,TP,2.4x6.4m	
R223	2001-000938	R-CARBON:68ohm,5%,1/8W,AA,TP,1.8x3.2mm		R823	2001-001150	R-CARBON(S):470Kohm,5%,1/2W,AA,TP,2.4x6.4m	
R224	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R825	2003-001040	R-METAL OXIDE(S):47Kohm,5%,2W,AF,TP,3.9x10mm	
R225	2001-000554	R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM		R901	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R226	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R902	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	

