

7. Electrical Parts List

7-1 CK28C7VD3X/XEH Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN				C409	2201-000551	C-CERAMIC,DISC:470pF,10%,1KV,Y5P,TP,8x5,5	
BUYER : SEH				C410	2401-001397	C-AL:470uF,20%,25V,GP,10x16mm,5mm,T	
*				C411	2305-000178	C-FILM,MPEF:10nF,5%,100V,TP,-,5mm	
HA94-100445 ASSY-PCB,MAIN:28C7VD3X,S51A,THMINV				C412	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4,5	
C102	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11,5,5		C413	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,5	
C103	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		C414	2306-000354	C-FILM,MPPF:7.2nF,5%,1.6KV,BK,31x18.5x12mm	
C104	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		C415	2306-000237	C-FILM,MPPF:6.3nF,5%,1.6KV,TP,28.5x18x11.5	
C105	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		C416	2303-001026	C-FILM,PPF:33nF,10%,400V,TP,20x15x8,7,5	
C106	2401-001082	C-AL:330nF,20%,50V,GP,TP,5x11,5		C417	2306-001017	C-FILM,MPPF:680nF,5%,400V,TP,26X14.5X24MM,	
C107	2401-000914	C-AL:22uF,20%,16V,GP,TP,5x11,5		C418	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4,5	
C109	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		C419	2401-001397	C-AL:470uF,20%,25V,GP,10x16mm,5mm,T	
C207	2401-001026	C-AL:3.3uF,20%,50V,GP,TP,5x11mm,5mm		C421	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,5	
C210	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		C422	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C211	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,5		C423	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4,5	
C213	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m		C424	2401-001527	C-AL:47uF,20%,250V,HR,TP,13x25mm,5m	
C214	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5		C425	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11.5	
C215	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,-,5mm		C427	2201-000406	C-CERAMIC,DISC:270pF,10%,2KV,Y5P,TP,8x6,7,5	
C216	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		C504	2202-000862	C-CERAMIC,MLC-AXIAL:390pF,10%,50V,Y5P,TP,3.5x11.9,-	
C217	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5X4.0X5.0MM,		C506	2301-000213	C-FILM,PEF:220nF,5%,250V,TP,21.5x11,7,5	
C218	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5mm,		C510	2401-000430	C-AL:10uF,20%,250V,GP,TP,10X16MM,5M	
C219	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		C520	2401-001232	C-AL:4.7uF,20%,250V,GP,TP,10x12,5,5	
C220	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		C530	2201-002063	C-CERAMIC,DISC:10nF,+80-20%,3KV,Y5V,TP,16x5,7	
C221	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		C601	2401-001914	C-AL:1uF,20%,50V,BP,TP,5x11,5	
C222	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,-,5mm		C602	2301-000310	C-FILM,PEF:68nF,5%,50V,TP,8.0X8.5X4.0X5,5	
C223	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		C603	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11,5	
C224	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		C604	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm	
C225	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		C605	2401-001914	C-AL:1uF,20%,50V,BP,TP,5x11,5	
C226	2401-000939	C-AL:22uF,20%,25V,GP,TP,5x11,5		C606	2301-000310	C-FILM,PEF:68nF,5%,50V,TP,8.0X8.5X4.0X5,5	
C226	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		C607	2401-001998	C-AL:1000UF,20%,25V,GP,TP,10X20,5MM	
C227	2201-000986	C-CERAMIC,DISC:12pF,5%,50V,NPO,TP,5x3mm,2.5mm		C701	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C228	2201-000273	C-CERAMIC,DISC:18pF,5%,50V,CH,TP,5x3mm,5		C702	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
C229	2301-000356	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5mm		C703	2202-000243	C-CERAMIC,MLC-AXIAL:33pF,5%,50V,SL,3.5X19,-,TP	
C230	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		C704	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C231	2202-000183	C-CERAMIC,MLC-AXIAL:2.2nF,20%,16V,Y5R,TP,3.5x19,-		C705	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C232	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		C707	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C233	2309-000138	C-FILM,PE-PPF:100nF,5%,50V,TP,20x16x8.5,7.5mm		C709	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C234	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		C710	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C235	2202-000849	C-CERAMIC,MLC-AXIAL:18pF,5%,50V,CH,TP,3.5x1,9,-		C711	2401-002235	C-AL:10uF,20%,16V,GP,TP,5X11MM,5MM	
C236	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		C712	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C237	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5X4.0X5.0MM,		C713	2301-000247	C-FILM,PEF:33nF,5%,50V,TP,8.1x4.5x13mm,5m	
C238	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm		C714	2301-000289	C-FILM,PEF:5.6nF,5%,50V,TP,7x6x3,5	
C239	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm		C715	2401-001991	C-AL:2.2uF,20%,50V,GP,TP,5x11,5	
C240	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		C716	2401-001991	C-AL:2.2uF,20%,50V,GP,TP,5x11,5	
C241	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C717	2301-000289	C-FILM,PEF:5.6nF,5%,50V,TP,7x6x3,5	
C242	2202-000806	C-CERAMIC,MLC-AXIAL:220PF,10%,50V,Y5P,TP,3.5*19,-		C718	2301-000247	C-FILM,PEF:33nF,5%,50V,TP,8.1x4.5x13mm,5m	
C243	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C719	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C244	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m		C720	2401-002235	C-AL:10uF,20%,16V,GP,TP,5X11MM,5MM	
C245	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5X4.0X5.0MM,		C721	2301-000175	C-FILM,PEF:15nF,5%,50V,TP,7.1x3.5x13mm,5m	
C301	2301-000254	C-FILM,PEF:39nF,5%,50V,TP,7.5x3.5x6.5mm,5		C722	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C302	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,5		C723	2301-000175	C-FILM,PEF:15nF,5%,50V,TP,7.1x3.5x13mm,5m	
C303	2201-000259	C-CERAMIC,DISC:180pF,10%,500V,Y5P,TP,6x4,5		C725	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C304	2301-000212	C-FILM,PEF:220nF,5%,100V,BK,16.0x10.0x24.		C727	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C305	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5,5		C730	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP,3.5x19,-	
C306	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m		C731	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP,3.5x19,-	
C307	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,5		C732	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP,3.5x19,-	
C308	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		C733	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP,3.5x19,-	
C309	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		C801	2306-000321	C-FILM,MPPF:470nF,5%,275V,TP,-,22.5mm	
C403	2401-000901	C-AL:22uF,20%,160V,GP,TP,10x20,5		C802	2306-000321	C-FILM,MPPF:470nF,5%,275V,TP,-,22.5mm	
C404	2201-000291	C-CERAMIC,DISC:1nF,10%,500V,Y5P,TP,8.5x5MM,5		C804	2201-000332	C-CERAMIC,DISC:2.2nF,20%,250VAC,Y5U,TP,11x7,7	
C405	2401-002268	C-AL:2.2uF,20%,250V/LZ,TP,8X11,5		C805	2201-000332	C-CERAMIC,DISC:2.2nF,20%,250VAC,Y5U,TP,11x7,7	
C406	2306-000204	C-FILM,MPPF:430nF,5%,400V,TP,26x20.5x12.		C806	2401-001140	C-AL:330uF,20%,400V,GP,BK,35x45,10	
C407	2201-000984	C-CERAMIC,DISC:680pF,10%,2KV,Y5P,TP,11x6,7,5mm		C807	2303-000163	C-FILM,PPF:2.2nF,5%,800V,TP,15x13x8.5,7,5	
C408	2305-000382	C-FILM,MPEF:4.7nF,5%,400V,TP,-,5MM		C808	2401-002292	C-AL:47uF,20%,25V,WVT,TP,8X11,5	
				C809	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m	
				C811	2301-000310	C-FILM,PEF:68nF,5%,50V,TP,8.0X8.5X4.0X5,5	

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C812	2201-000446	C-CERAMIC,DISC:3.3nF,20%,400V,Y5U,TP,18x8,10m		D210	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C814	2201-000683	C-CERAMIC,DISC:850pF,10%,1KV,Y5P,TP,10x5,5		D217	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C815	2401-003026	C-AL:330uF,20%,200V,GP,ST,22x35,10		D301	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,TP	
C816	2401-000293	C-AL:100uF,+30-10%,200V,HR,TP,16x25		D302	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C817	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4,5		D303	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C818	2401-000722	C-AL:2200uf,20%,25V,WT,TP,16x25,7.5		D304	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C819	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4,5		D401	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L,TP	
C820	2401-000722	C-AL:2200uf,20%,25V,WT,TP,16x25,7.5		D402	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
C821	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m		D403	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
C822	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4,5		D404	0402-001012	DIODE-RECTIFIER:FMP-3FU,1500V,5A,TO-3PF	
C823	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		D406	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,TP	
C824	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		D407	0402-000216	DIODE-RECTIFIER:ERC24-06,600V,1.0A,DO-204	
C825	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		D410	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L,TP	
C826	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		D507	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,TP	
C827	2401-002235	C-AL:100uF,20%,16V,GP,TP,5X11MM,5MM		D508	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,TP	
C828	2401-000493	C-AL:10uF,20%,50V,LZ,TP,5x11mm,5mm		D509	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,TP	
C829	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		D520	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
C830	2305-000665	C-FILM,MPEF:100NF,5%,63V,TP,7.5X4.0X5.0MM,		D601	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,	
C831	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		D602	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C832	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		D801	0402-000213	DIODE-RECTIFIER:ERB12-06,600V,1.0A,DO-41,TP	
C833	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		D802	0402-001160	DIODE-BRIDGE:D5SB60,600V,2.8A,SIP-4,ST	
C834	2201-000370	C-CERAMIC,DISC:220pF,10%,50V,Y5P,TP,4.0X4.0,5		D803	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,TP	
C835	2401-000142	C-AL:1000uF,20%,16V,WT,TP,10x20,5		D804	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C901	2201-000234	C-CERAMIC,DISC:150pF,5%,50V,CH,TP,9.5x3,5		D805	0402-001230	DIODE-FMG-G2CS	
C902	2301-000108	C-FILM,PEF:1.5nF,5%,50V,TP,6.5x3.0x5,5mm,		D806	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L,TP	
C903	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,8x3.5		D807	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	
C904	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		D808	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
C905	2305-000665	C-FILM,MPEF:100NF,5%,63V,TP,7.5X4.0X5.0MM,		D809	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C906	2305-000665	C-FILM,MPEF:100NF,5%,63V,TP,7.5X4.0X5.0MM,		D810	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C907	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		D813	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L,TP	
C908	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		D901	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C909	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		D906	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C910	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		D907	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C911	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		DE01	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,TP	
C913	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm		DT02	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C914	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		DT05	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP	
C916	2201-000980	C-CERAMIC,DISC:30pF,5%,50V,CH,TP,5.0x3.0,5mm		DV801	1405-000187	VARIABLE:750V,1250A,12.5x7mm,TP	
C917	2201-000980	C-CERAMIC,DISC:30pF,5%,50V,CH,TP,5.0x3.0,5mm		DV802	1405-000187	VARIABLE:750V,1250A,12.5x7mm,TP	
C919	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ201	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500mW,	
C920	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		DZ203	0403-000298	DIODE-ZENER:MTZ6.8C,6.8V,6.66-7.01V,500mW,	
C921	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		DZ204	0403-000662	DIODE-ZENER:MTZ3.0B,3.0V,3.01-3.22V,500mW,	
C923	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ205	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C924	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		DZ302	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,	
C925	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ303	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,	
C926	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ304	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,	
C927	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ305	0403-000494	DIODE-ZENER:MTZ39,39V,35.36-37.2V,500mW,DO	
CE01	2401-002597	C-AL:220uF,20%,35V,GP,TP,10x12,5,5		DZ306	0403-000700	DIODE-ZENER:TZP33A,33V,31-35V,1W,DO-41,TP	
CE02	2305-000665	C-FILM,MPEF:100NF,5%,63V,TP,7.5X4.0X5.0MM,		DZ402	0403-000300	DIODE-ZENER:MTZ8.2B,8.2V,7.78-8.19V,500mW,	
CE03	2305-000470	C-FILM,MPEF:68nF,5%,100V,TP,-,5mm		DZ403	0403-000698	DIODE-ZENER:TZP12A,12V,11.4-12.6V,1W,DO-41	
CN501B	AA39-20604ALEAD	CONNECTOR-ASSY:-YBNH250-09,YBNH05/04,5/4P,5		DZ505	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,	
CN502	3711-002643	CONNECTOR-HEADER:BOX,4P,1R,2.5mm,STRAIGHT,SN		DZ601	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,	
CN602	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5MM,STRAIGHT,SN		DZ602	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,	
CN701	3711-002647	CONNECTOR-HEADER:BOX,8P,1R,2.5mm,STRAIGHT,SN		DZ603	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,	
CN802	AA27-20004K	COIL-DEGAUSSING:-29,19.0ohm,45T,3000mm,E		DZ604	0403-000545	DIODE-ZENER:MTZ24B,24V,22.61-23.77V,500mW,	
CN901	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGHT,SN		DZ701	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,	
CN901A	3711-002643	CONNECTOR-HEADER:BOX,4P,1R,2.5mm,STRAIGHT,SN		DZ702	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,	
CN902	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5MM,STRAIGHT,SN		DZ703	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,	
CND01	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGHT,SN		DZ704	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,	
CNS01	3711-002702	CONNECTOR-HEADER:NOWALL,4P,1R,2.5mm,ANGLE,SN		DZ705	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,	
CNS02	3711-002703	CONNECTOR-HEADER:NOWALL,5P,1R,2.5mm,ANGLE,SN		DZ801	0403-000300	DIODE-ZENER:MTZ8.2B,8.2V,7.78-8.19V,500mW,	
CNS03	AA39-20052F	LEAD CONNECTOR-ASSY:-YBNH025-04,YSH025-04,4P,200		DZ802	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,	
CT01	2305-000665	C-FILM,MPEF:100NF,5%,63V,TP,7.5X4.0X5.0MM,		DZ803	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,	
CT02	2401-000242	C-AL:100uF,20%,10V,GP,TP,6x11,5MM		DZ804	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,	
CT03	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ805	1203-001217	IC-POS.ADJUST.REG.:431,TO-92,3P,4.58MIL,PLASTIC,2	
CT04	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ807	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,	
CT05	2202-000164	C-CERAMIC,MLC-AXIAL:180PF,10%,50V,Y5P,TP,3.5x19,-,TP		DZ808	0403-000562	DIODE-ZENER:MTZ7.5B,7.5V,7.07-7.45V,500mW,	
CT06	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		DZ901	1203-000451	IC-VOLTAGE REGULATOR:33,TO-92,3P,-,PLASTIC,31/35V,	
CT08	2401-001914	C-AL:1uF,20%,50V,BP,TP,5x11,5		DZ904	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500mW,	
CT11	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ905	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500mW,	
CW701	2503-000161	C-NETWORK:331*8		F801	3601-000281	FUSE-FERRULE:250V,4A,TIME LAG,GLASS,5x20mm	
CW901	2503-000156	C-NETWORK:100pFx4,20%,50V		F801A	3602-000114	FUSE-HOLDER:-,30MOHM	
D201	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		F801B	3602-000114	FUSE-HOLDER:-,30MOHM	
D202	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		F802	3601-001086	FUSE-FERRULE:125V,5A,FA,GLASS,2.4x7.5mm	
D203	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		F803	3601-001086	FUSE-FERRULE:125V,5A,FA,GLASS,2.4x7.5mm	
D204	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		GT404	AA39-20010D	LEAD-CONNECTOR,ASSY:-,YFH800-01,S,1P,400,1617#22	
D207	0401-000005	DIODE-SWITCHING:1N4148,75V,300MA,DO-35,TP		GT804-	AA39-20010B	LEAD-CONNECTOR,ASSY:-,YFH800-01,S,1P,500,1617#22	
D209	0402-000216	DIODE-RECTIFIER:ERC24-06,600V,1.0A,DO-204		H001	AA61-10068A	BRACKET-PCB:-,M2160,SPT,TO,3,-,-,-	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
△	HC101	AA13-20004WIC-HYBRID;-PAP103T,SIP,6PPRE-AMP,TP		O905	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
△	IC201	0904-001294 IC-BUS CONTROLLER:8844,-,DIP,56P,600MIL,3.58MHz,		O907	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
△	IC301	1204-000517 IC-VERTICAL DEF.:LA7845,SIP,7P,-,PLASTIC,40V,11		O908	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
△	IC501	1201-001330 IC-VIDEO AMP:6108,ZSIP,9P,-,SINGLE,-,PLASTI		QE01	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,TP,120-	
△	IC601	1201-001064 IC-POWER AMP:7297,ZIP,15P,-,DUAL,32DB,PLAST		QT01	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-	
△	IC701	1204-000473 IC-AUDIO PROCESSOR:TDA9859,DIP,32P,-,PLASTIC,-,-,		QT02	0504-000125	TR-DIGITAL:KSR1012,NPN,300mW,47K,TO-92,TP	
△	IC801	1203-001482 IC-PWM CONTROLLER:3S1265R,TO-3P,5P,210,PLASTIC,6		R201	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△	IC802	0604-001038 PHOTO-COUPLER:TR,130-260%,200MW,DIP-4,ST		R202	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△	IC803	1203-001006 IC-VOLTAGE REGULATOR:78R05,TO-220F,4P,-,PLASTIC,4.		R203	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△	IC804	1203-000644 IC-POSI.FIXED REG.:7630,SIP,10P,-,PLASTIC,5.1/8V,		R204	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
△	IC901	AA09-00001AIC-MCU:SAA5553M3A-0059,52P,ST,8BIT,-,		R212	2001-000005	R-CARBON:390OHM,5%,1/8W,AA,TP,1.8X3.2MM	
△	IC902	1103-001043 IC-EEPROM:24C16,2Kx8BIT,DIP,8P,300MIL,10		R214	2001-000793	R-CARBON:470HM,5%,1/8W,AA,TP,1.8X3.2MM	
△	IC903	1203-001752 IC-POSI.FIXED REG.:LF33CV,TO-220,3P,-,PL		R215	2001-000780	R-CARBON:470HM,5%,1/8W,AA,TP,1.8X3.2MM	
△	ICE01	1201-000191 IC-OP AMP:4558,DIP,8P,300MIL,DUAL,20V/mV		R218	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
△	ICS01	1001-000223 IC-VIDEO SWITCH:TEA5114A,-,DIP,16P,334MIL,SING		R219	2001-000343	R-CARBON:130ohm,5%,1/8W,AA,TP,1.8x3.2mm	
J206	3301-000287 CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400G		R220	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
J961	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R221	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
JA701	3722-000195 JACK-SCART:42P,-,SN,BLK,NO		R222	2701-000142	INDUCTOR-AXIAL:1UH,10%,2.5X3.4MM		
L101	2701-000326 INDUCTOR-AXIAL:560nH,10%,2.3x3.4mm		R223	2001-000617	R-CARBON:3.9Mohm,5%,1/8W,AA,TP,1.8x3.2m		
L102	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R224	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L103	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R225	2001-001026	R-CARBON:910ohm,5%,1/8W,AA,TP,1.8x3.2mm		
L202	2701-000197 INDUCTOR-AXIAL:5.6UH,10%,2.5X3.4MM		R226	2001-000793	R-CARBON:470HM,5%,1/8W,AA,TP,1.8X3.2MM		
L205	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R230	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L206	2701-000142 INDUCTOR-AXIAL:1UH,10%,2.5X3.4MM		R233	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM		
L207	2701-000142 INDUCTOR-AXIAL:1UH,10%,2.5X3.4MM		R234	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM		
L208	2701-000142 INDUCTOR-AXIAL:1UH,10%,2.5X3.4MM		R235	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM		
L303	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R236	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM		
L401	AA27-40003H COIL-HORIZ.WIDTH:-,2MH,DR15X20,2UEW0.35,ST		R237	2001-000605	R-CARBON:3.6KOHM,5%,1/8W,AA,TP,1.8X3.2M		
L402	AA27-30001F COIL-LINEARITY:-,22uH,DR1011,PI0.45,25.5,-,20		R238	2004-001993	R-METAL:750KOHM,5%,1/8W,AA,TP,1.8X3.2M		
L403	3301-000287 CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400G		R241	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L404	AA27-40003L COIL-HORIZ.WIDTH:-,1.0MH,DR14X20,2UEW0.45,ST		R245	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M		
L501	2901-000297 FILTER-EMI ON BOARD:-,3A,-,-,3.5X5,TP-		R246	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M		
L601	3301-000287 CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400G		R247	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
L603	3301-000287 CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400G		R248	2001-000793	R-CARBON:470HM,5%,1/8W,AA,TP,1.8X3.2MM		
L701	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R249	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L702	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R250	2001-000938	R-CARBON:68ohm,5%,1/8W,AA,TP,1.8x3.2mm		
L703	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R251	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
L704	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R252	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L705	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R253	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		
L706	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R255	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L707	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R256	2004-001234	R-METAL:75KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L708	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R257	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L709	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R258	2004-001914	R-METAL:39KOHM,2%,1/8W,AA,TP,1.8X3.5MM		
L710	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R259	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
L801	AA29-30001O FILTER-LINE:-,20MH,1.26A,-,BSF3050		R260	2001-001015	R-CARBON:9.1Kohm,5%,1/8W,AA,TP,1.8x3.2m		
L802	3301-000287 CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400G		R261	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L803	3301-000287 CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400G		R262	2001-001015	R-CARBON:9.1Kohm,5%,1/8W,AA,TP,1.8x3.2m		
L804	2901-000299 FILTER-EMI ON BOARD:-,6A,UL/CSA,-,9x7.5,TP-		R301	2001-001049	R-CARBON(S):1.3Kohm,5%,1/2W,AA,TP,2.4x6.4m		
L805	2701-001032 INDUCTOR-AXIAL:10UH,10%,5X14MM		R302	2001-001049	R-CARBON(S):1.3Kohm,5%,1/2W,AA,TP,2.4x6.4m		
L806	2901-000297 FILTER-EMI ON BOARD:-,3A,-,-,3.5X5,TP-		R303	2001-000016	R-CARBON(S):10HM,5%,1/2W,AA,TP,2.4x6.4MM		
L807	3301-000287 CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400G		R304	2008-000254	R-FUSIBLE(S):0.68ohm,5%,2W,AF,TP,3.9x10mm		
L808	3301-000287 CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400G		R305	2003-000998	R-METAL OXIDE:300ohm,5%,2W,AF,TP,3.9x10mm		
L901	2701-000189 INDUCTOR-AXIAL:470NH,10%,2.5X3.4MM		R307	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L903	2701-000197 INDUCTOR-AXIAL:5.6UH,10%,2.5X3.4MM		R309	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L904	2701-000211 INDUCTOR-AXIAL:68uH,10%,2.5x3.4mm		R310	2001-000387	R-CARBON:16Kohm,5%,1/8W,AA,TP,1.8x3.2mm		
L905	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R311	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L906	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R312	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
L907	2701-000114 INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R313	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
L908	2901-000299 FILTER-EMI ON BOARD:-,6A,UL/CSA,-,9x7.5,TP-		R314	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		
Q201	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-		R315	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
Q202	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-		R316	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		
Q204	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-		R317	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		
Q207	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-		R404	2008-000254	R-FUSIBLE(S):0.68ohm,5%,2W,AF,TP,3.9x10mm		
Q209	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,TP,120-		R405	2001-001138	R-CARBON(S):390ohm,5%,1/2W,AA,TP,2.4x6.4mm		
Q210	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-		R406	2003-002008	R-METAL OXIDE(S):18Kohm,5%,2W,AF,TP,3.9x10mm		
Q301	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-		R407	2003-001025	R-METAL OXIDE(S):15Kohm,5%,2W,AF,TP,3.9x10mm		
Q302	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-		R409	2008-000264	R-FUSIBLE(S):10HM,5%,1W,AF,TP,3.9X10MM		
△	Q401	0502-000298 TR-POWER:KSD73,NPN,30W,TO-220,-,120-240		R410	2001-001114	R-CARBON(S):270ohm,5%,1/2W,AA,TP,2.4x6.4mm	
△	Q402	0502-001007 TR-POWER:KSC2073-H2,NPN,25W,TO-220,ST,6		R411	2001-001199	R-CARBON(S):91ohm,5%,1/2W,AA,TP,2.4x6.4mm	
△	Q403	0502-001136 TR-POWER:KSD5703,NPN,70W,TO-3PF,ST,8-		R412	2001-000020	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4mm	
Q701	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-		R413	2008-000251	R-FUSIBLE(S):0.27ohm,10%,2W,AF,TP,3.9x10mm		
Q702	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-		R414	2008-000278	R-FUSIBLE(S):82ohm,5%,2W,AA,TP,3.9x10mm		
Q801	0501-000369 TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L,-,120-		R415	2008-001011	R-FUSIBLE(S):0.18ohm,10%,2W,AF,TP,3.9x10mm		
Q901	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,TP,120-		R417	2001-001152	R-CARBON(S):47Kohm,5%,1/2W,AA,TP,2.4x6.4mm		
Q902	0504-000123 TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R418	2001-001152	R-CARBON(S):47Kohm,5%,1/2W,AA,TP,2.4x6.4mm		
Q903	0504-000123 TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R419	2004-001390	R-METAL(S):1KOHM,2%,1/2W,AA,TP,2.4X6.4MM		
Q904	0504-000123 TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R420	2001-001114	R-CARBON(S):270ohm,5%,1/2W,AA,TP,2.4x6.4mm		

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R421	2001-001043	R-CARBON(S):00HM,5%,1/2W,AA,TP,2.4X6.4MM		R820	2008-000294	R-FUSIBLE(S):33ohm,5%,2W,AF,TP,3.9x10mm	
R422	2008-000254	R-FUSIBLE(S):0.68ohm,5%,2W,AF,TP,3.9x10mm		R821	2008-000271	R-FUSIBLE(S):3.30HM,5%,2W,AA,TP,3.9X10MM	
R424	2001-001043	R-CARBON(S):00HM,5%,1/2W,AA,TP,2.4X6.4MM		R822	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R425	2001-001043	R-CARBON(S):00HM,5%,1/2W,AA,TP,2.4X6.4MM		R823	2901-000297	FILTER-EMI ON BOARD:-3A,-,3.5X5,TP-	
R428	2001-001043	R-CARBON(S):00HM,5%,1/2W,AA,TP,2.4X6.4MM		R824	2001-001125	R-CARBON(S):300Kohm,5%,1/2W,AA,TP,2.4x6.4m	
R429	2001-001043	R-CARBON(S):00HM,5%,1/2W,AA,TP,2.4X6.4MM		R826	2001-001153	R-CARBON(S):47OHM,5%,1/2W,AA,TP,2.4X6.4MM	
R430	2001-001043	R-CARBON(S):00HM,5%,1/2W,AA,TP,2.4X6.4MM		R828	2001-000022	R-CARBON(S):33ohm,5%,1/2W,AA,TP,2.4x6.4mm	
R501	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R901	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R502	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R902	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R503	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R903	2001-000066	R-CARBON(S):10Kohm,5%,1/2W,AA,TP,2.4x6.4mm	
R505	2008-000266	R-FUSIBLE(S):10HM,5%,2W,AF,TP,3.9X10MM		R904	2004-000218	R-METAL:10KOHM,1%,1/8W,AA,TP,1.8X3.2MM	
R506	2008-000299	R-FUSIBLE(S):47ohm,5%,2W,AF,TP,3.9x10mm		R905	2004-000218	R-METAL:10KOHM,1%,1/8W,AA,TP,1.8X3.2MM	
R507	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP,1.8X3.2MM		R906	2004-000218	R-METAL:10KOHM,1%,1/8W,AA,TP,1.8X3.2MM	
R508	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP,1.8X3.2MM		R908	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R509	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP,1.8X3.2MM		R909	2004-001126	R-METAL:6.2KOHM,1%,1/8W,AA,TP,1.8X3.2M	
R510	2002-001009	R-COMPOSITION:2.7Kohm,10%,1/2W,AA,TP,3.7X9.0		R913	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R517	2002-001009	R-COMPOSITION:2.7Kohm,10%,1/2W,AA,TP,3.7X9.0		R914	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R518	2002-001009	R-COMPOSITION:2.7Kohm,10%,1/2W,AA,TP,3.7X9.0		R918	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R519	2002-001009	R-COMPOSITION:2.7Kohm,10%,1/2W,AA,TP,3.7X9.0		R919	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R520	2001-001062	R-CARBON(S):10Mohm,5%,1/2W,AA,TP,2.4x6.4mm		R920	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R601	2008-001002	R-FUSIBLE(S):0.18ohm,5%,2W,AA,TP,3.9x10mm		R921	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R602	2008-001002	R-FUSIBLE(S):0.18ohm,5%,2W,AA,TP,3.9x10mm		R922	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R603	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R923	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R604	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R924	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R605	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R925	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R606	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R926	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R607	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R927	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM	
R701	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R928	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM	
R702	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R929	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM	
R703	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM		R930	2001-000628	R-CARBON:300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R704	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM		R932	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R705	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R933	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R706	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R934	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R707	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM		R935	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R708	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM		R936	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R709	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM		R937	2001-001062	R-CARBON(S):10Mohm,5%,1/2W,AA,TP,2.4x6.4mm	
R712	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R941	0403-000551	DIODE-ZENER:MTZ3.9B,3.9V,3.89-4.16V,500mW,	
R713	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM		R942	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R714	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R945	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R715	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM		R948	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R716	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R951	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R717	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R953	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R718	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM		R954	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R719	2001-000527	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM		R955	2001-000605	R-CARBON:3.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R720	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RE01	2004-001390	R-METAL(S):1KOHM,2%,1/2W,AA,TP,2.4x6.4MM	
R721	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RE02	2004-001914	R-METAL:39KOHM,2%,1/8W,AA,TP,1.8X3.5MM	
R722	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RE03	2001-000066	R-CARBON(S):10Kohm,5%,1/2W,AA,TP,2.4x6.4mm	
R723	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RE04	2001-001142	R-CARBON(S):3kohm,5%,1/2W,AA,TP,2.4x6.4mm	
R724	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RE05	2001-000052	R-CARBON(S):3.3Kohm,5%,1/2W,AA,TP,2.4x6.4m	
R725	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM		RE06	2004-001390	R-METAL(S):1KOHM,2%,1/2W,AA,TP,2.4x6.4MM	
R728	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		RE07	2003-002069	R-METAL OXIDE:470ohm,5%,2W,AF,TP,3.9x10mm	
R729	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		RE08	2001-001120	R-CARBON(S):3.3ohm,5%,1/2W,AA,TP,2.4x6.4mm	
R732	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RE09	2001-001125	R-CARBON(S):300Kohm,5%,1/2W,AA,TP,2.4x6.4m	
R733	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM		RE10	2001-001125	R-CARBON(S):300Kohm,5%,1/2W,AA,TP,2.4x6.4m	
R734	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM		RL801	3501-001040	RELAY-POWER:12VDC,500mW,10A,1FormA,15mS,5m	
R735	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM		RP802	1404-001045	THERMISTOR-NTC:4.70HM,15%,2900K,35.0MW,T	
R736	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RP803	1404-001087	THERMISTOR-PTC:7ohm,30%,220V,270V,19A,-,ST	
R740	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		RT01	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R741	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		RT02	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R801	2002-001011	R-COMPOSITION:3.3Mohm,10%,1/2W,AA,TP,3.7x9mm		RT03	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R802	2003-000994	R-METAL OXIDE(S):33Kohm,5%,2W,AF,TP,3.9x10mm		RT04	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R803	2003-000994	R-METAL OXIDE(S):33Kohm,5%,2W,AF,TP,3.9x10mm		RT05	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R804	2001-001150	R-CARBON(S):470Kohm,5%,1/2W,AA,TP,2.4x6.4m		RT06	2001-000539	R-CARBON:24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R805	2001-001150	R-CARBON(S):470Kohm,5%,1/2W,AA,TP,2.4x6.4m		RT07	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R806	2003-000458	R-METAL OXIDE(S):100ohm,5%,2W,AF,TP,4x12mm		RT17	2202-000825	C-CERAMIC,MLC-AXIAL-680pf,10%,50V,Y5P,TP,3.5x19,-	
R807	2001-001178	R-CARBON(S):680ohm,5%,1/2W,AA,TP,2.4x6.4mm		RT18	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R808	2002-001011	R-COMPOSITION:3.3Mohm,10%,1/2W,AA,TP,3.7x9mm		RT19	2001-000232	R-CARBON:1.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R809	2002-001013	R-COMPOSITION:4.7Mohm,10%,1/2W,AA,TP,3.7x9mm		RT20	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R810	2003-000487	R-METAL OXIDE(S):12Kohm,5%,2W,AA,TP,4x12mm		RT22	2001-000628	R-CARBON:300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R811	2003-000510	R-METAL OXIDE(S):15Kohm,5%,2W,AA,TP,4x12mm		RT23	2001-000628	R-CARBON:300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R813	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RT24	2001-000628	R-CARBON:300OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R814	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		RT25	2001-000007	R-CARBON:3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R815	2004-004364	R-METAL(S):152Kohm,1%,1/2W,AA,TP,2.4x6.4m		RW901	2011-000157	R-NETWORK:10K,5%,1/8W,AA,SIP6,TP	
R816	2004-001983	R-METAL:2.49KOHM,1%,1/2W,AA,TP,2.4X6.4		SF101	2904-000302	FILTER-SAW AV:38.90MHz,-,ST,13.9dB,PAL-B/G,-	
R817	2001-001153	R-CARBON(S):47OHM,5%,1/2W,AA,TP,2.4X6.4MM		T401	AA26-50001R	TRANS-HORIZ DRIVE,-,80MH,580UH,4UH,G11A E19,ST	
R818	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		T444	AA26-30005V	TRANS-FLYBACK,-,FUH-29A00A,29.155V	
R819	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		T801	AA26-20007X	TRANS-SWITCHING,-,90-260,155/15.5/12/8V,VDE,SE	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
△	TU101	AA40-00007A TUNER-V/S;TECC0949VG29A(S),PAL-B/G,-,181					
△	V999	3704-001105 SOCKET-CRT;11P,20P,26.5P,NL,-					
X202	2801-003726	CRYSTAL-UNIT;4.433619MHz,20ppm,28-AAM,20pF,					
X203	2801-000226	CRYSTAL-UNIT;3.579545MHz,20ppm,28-AAM,15pF,					
XT01	2801-003433	CRYSTAL-UNIT;12MHz,30ppm,28-AAA,30pF,30ohm,					
Z208	2903-000181	FILTER-CERAMIC;TR,5.5MHz,-,-,-,TP,TPS5.5MB-TF					
ASSY-PCB,CONTROL				ASSY-SOUND			
*	HA95-00156A	ASSY-PCB,CONTROL;-S51A,28C7		*	AA95-00232A	ASSY-SOUND-DP;WS28W6,S51A,-,NICAM,STEREO,	
CC01	2401-001495	C-AL;47uF,20%,16V,GP,5x11mm,5mm,TP		CD01	2203-000979	C-CERAMIC,CHIP;47NF,10%,50V,X7R,TP,2012	
CC02	2202-000720	C-CERAMIC,MLC-AXIAL;8.2NF,20%,16V,Y5R,3.5X19,-,TP		CD02	2203-000495	C-CERAMIC,CHIP;2.2NF,10%,50V,X7R,TP,2012	
CC03	2202-000720	C-CERAMIC,MLC-AXIAL;8.2NF,20%,16V,Y5R,3.5X19,-,TP		CD03	2203-000495	C-CERAMIC,CHIP;2.2NF,10%,50V,X7R,TP,2012	
CC04	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP,1.9x3.5,-		CD04	2203-000979	C-CERAMIC,CHIP;47NF,10%,50V,X7R,TP,2012	
CC05	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP,1.9x3.5,-		CD05	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
CC06	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		CD06	2203-000979	C-CERAMIC,CHIP;47NF,10%,50V,X7R,TP,2012	
CC07	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		CD07	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
CDZ01	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW,		CD08	2203-000979	C-CERAMIC,CHIP;47NF,10%,50V,X7R,TP,2012	
CH01	3722-001061	JACK-PHONE;1P,3.6mm,AG,BLK,N		CD09	2203-001158	C-CERAMIC,CHIP;0.068nF,5%,50V,NPO,TP,201	
CL01	2701-000180	INDUCTOR-AXIAL;33UH,5%,2.5X3.4MM		CD10	2203-000979	C-CERAMIC,CHIP;47NF,10%,50V,X7R,TP,2012	
CL02	2701-000180	INDUCTOR-AXIAL;33UH,5%,2.5X3.4MM		CD11	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
CL03	2701-000114	INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM		CD12	2401-001496	C-AL;47uF,20%,16V,GP,TP,5x7,5	
CL04	2701-000114	INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM		CD13	2203-001158	C-CERAMIC,CHIP;0.068nF,5%,50V,NPO,TP,201	
CLD01	0601-000198	LED-ROUND,RED/GRN,5.0mm,630/565nm		CD14	2401-001496	C-AL;47uF,20%,16V,GP,TP,5x7,5	
CNC01	AA39-20005B	LEAD CONNECTOR-ASSY;-YBNH025-03,67096-003,3P,300		CD15	2203-000609	C-CERAMIC,CHIP;22NF,10%,50V,X7R,TP,2012	
CNC02	AA39-20069D	LEAD CONNECTOR-ASSY;-YBNH025-05,67096-005,5P,300,		CD16	2203-000979	C-CERAMIC,CHIP;47NF,10%,50V,X7R,TP,2012	
CNC03	AA39-20068E	LEAD CONNECTOR-ASSY;-YBNH025-08,67096-0		CD17	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
CNC05	AA39-20069C	LEAD CONNECTOR-ASSY;-YBNH025-05,67096-005,5P,400,		CD18	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
CNC06	AA39-20499B	LEAD CONNECTOR-ASSY;-YBNH025-04,SMP025-04,4P,200		CD19	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
CR01	2001-000793	R-CARBON;47OHM,5%,1/8W,AA,TP,1.8X3.2MM		CD20	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
CR02	2001-000924	R-CARBON;680OHM,5%,1/8W,AA,TP,1.8X3.2MM		CD21	2203-000142	C-CERAMIC,CHIP;1.5NF,10%,50V,X7R,TP,2012	
CR03	2001-000214	R-CARBON;1.1KOHM,5%,1/8W,AA,TP,1.8X3.2M		CD22	2203-000142	C-CERAMIC,CHIP;1.5NF,10%,50V,X7R,TP,2012	
CR04	2001-000449	R-CARBON;2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		CD23	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-	
CR06	2001-000522	R-CARBON;22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CD24	2401-000914	C-AL;22uF,20%,16V,GP,TP,5x11,5	
CR07	2001-000028	R-CARBON(S);100ohm,5%,1/2W,AA,TP,2.4x6.4mm		CD25	2404-000235	C-TA,CHIP;4.7uF,20%,16V,-,TP,3528,1.4	
CR08	2001-000028	R-CARBON(S);100ohm,5%,1/2W,AA,TP,2.4x6.4mm		CD26	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,	
CSW01	3404-000176	SWITCH-TACT;12V,50mA,90-150gf,6x6mm		CD27	2203-000274	C-CERAMIC,CHIP;10pF,0.25pF,50V,NPO,TP,20	
CSW02	3404-000176	SWITCH-TACT;12V,50mA,90-150gf,6x6mm		CD28	2203-000274	C-CERAMIC,CHIP;10pF,0.25pF,50V,NPO,TP,20	
CSW03	3404-000176	SWITCH-TACT;12V,50mA,90-150gf,6x6mm		CD29	2401-002594	C-AL;220uF,20%,16V,GP,TP,8x11.5,5	
CSW04	3404-000176	SWITCH-TACT;12V,50mA,90-150gf,6x6mm		CD30	2404-000151	C-TA,CHIP;1uF,20%,16V,-,TP,3216,-	
CSW05	3404-000176	SWITCH-TACT;12V,50mA,90-150gf,6x6mm		CD31	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
GT801-	AA39-20041B	LEAD CONNECTOR-ASSY;-YFH800-02,S,2P,300,1617#22		CD32	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
GUIDE	AA61-50032A	GUIDE-LED;6201,ABS,HB,BLK,-,-,-		CD33	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
PA01	AA59-60003J	MODULE-REMOCON;-ORC-06H2,38KHZ,940NM,ME		CD34	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
SW801	3403-000179	SWITCH-PUSH;250V,5A,DPST,-,-,JPW-2104B		CD35	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
ASSY-R/G/B,SWITCHING				ASSY-SOUND			
*	HA95-90009S	ASSY-R/G/B,SWITCHING;-,-,S51A,PHILIPS MICOM ALL,-,-		CD36	2401-003028	C-AL;100uF,20%,25V,WT,TP,6.3x11,5	
CS01	2401-002619	C-AL;47uF,20%,25V,GP,TP,5x11,5		CN01	2203-000260	C-CERAMIC,CHIP;10NF,10%,50V,X7R,TP,2012	
CS02	2305-000665	C-FILM,MPEF;100NF,5%,63V,TP,7.5X4.0X5.0MM,		CN02	2203-000260	C-CERAMIC,CHIP;10NF,10%,50V,X7R,TP,2012	
CS03	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.		CN03	2203-000891	C-CERAMIC,CHIP;4.7NF,10%,50V,X7R,TP,2012	
CS04	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.		CN04	2203-002392	C-CERAMIC,CHIP;220nF,+80-20%,50V,Y5V,TP,	
CS05	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.		CN05	2401-000620	C-AL;2.2uF,10%,50V,GP,TP,5x11,5	
CS06	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.		CN06	2401-000030	C-AL;22uF,20%,25V,GP,TP,5x11,5	
CS07	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.		CN07	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,	
CS08	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.		CN08	2203-001002	C-CERAMIC,CHIP;0.047nF,5%,50V,NPO,TP,201	
DS01	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP		CN09	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,	
RS01	2001-000003	R-CARBON;330OHM,5%,1/8W,AA,TP,1.8X3.2MM		CN10	2203-000260	C-CERAMIC,CHIP;10NF,10%,50V,X7R,TP,2012	
RS04	2001-000003	R-CARBON;330OHM,5%,1/8W,AA,TP,1.8X3.2MM		CN11	2404-000167	C-TA,CHIP;2.2uF,20%,16V,-,TP,3216,-	
RS06	2001-000003	R-CARBON;330OHM,5%,1/8W,AA,TP,1.8X3.2MM		CN12	2203-000784	C-CERAMIC,CHIP;330pF,5%,50V,NPO,TP,2012,	
RS07	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CN13	2203-000784	C-CERAMIC,CHIP;330pF,5%,50V,NPO,TP,2012,	
RS08	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CN14	2401-000404	C-AL;10uF,20%,16V,BP,TP,5x11,5	
RS09	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CN15	2401-000404	C-AL;10uF,20%,16V,BP,TP,5x11,5	
RS10	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CN16	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
RS11	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CN17	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
RS12	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CN18	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
RS13	2001-000003	R-CARBON;330OHM,5%,1/8W,AA,TP,1.8X3.2MM		CN19	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
RS14	2001-000003	R-CARBON;330OHM,5%,1/8W,AA,TP,1.8X3.2MM		CN20	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
RS15	2001-000003	R-CARBON;330OHM,5%,1/8W,AA,TP,1.8X3.2MM		CN21	2203-000802	C-CERAMIC,CHIP;33NF,10%,50V,X7R,TP,2012	
RS16	2001-000003	R-CARBON;330OHM,5%,1/8W,AA,TP,1.8X3.2MM		CN22	2203-002442	C-CERAMIC,CHIP;330NF,+80-20%,25V,Y5V,TP,	
RS17	2001-000003	R-CARBON;330OHM,5%,1/8W,AA,TP,1.8X3.2MM		CN23	2203-000389	C-CERAMIC,CHIP;15pF,5%,50V,NPO,TP,2012,-	
RS18	2001-000003	R-CARBON;330OHM,5%,1/8W,AA,TP,1.8X3.2MM		CN24	2203-000818	C-CERAMIC,CHIP;0.033nF,5%,50V,NPO,TP,201	
				CN25	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
				CN26	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,	
				CN27	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
				CN28	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
				CN29	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
				CN30	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
				CN31	2203-000925	C-CERAMIC,CHIP;470NF,+80-20%,50V,Y5V,TP,	
				CN32	2401-000471	C-AL;10uF,20%,50V,GP,TP,5x11,5mm	
				CN33	2203-000260	C-CERAMIC,CHIP;10NF,10%,50V,X7R,TP,2012	
				CN34	2203-000260	C-CERAMIC,CHIP;10NF,10%,50V,X7R,TP,2012	
				CN35	2203-000701	C-CERAMIC,CHIP;2pF,0.25pF,50V,NPO,TP,201	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
CN36	2401-000242	C-AL:100uF,20%,10V,GP,TP,5x11,5		RN13	2007-000308	R-CHIP:100HM,5%,1/10W,DA,TP,2012	
CN37	2404-000167	C-TA,CHIP:2.2uF,20%,16V,-,TP,3216,-		RN14	2007-000881	R-CHIP:4.70HM,5%,1/10W,DA,TP,2012	
CND01	AA39-20467A	LEAD CONNECTOR-ASSY:-,YBNH250-03,67096-0		RN15	2007-000830	R-CHIP:39KOHM,5%,1/10W,DA,TP,2012	
CNN01	3711-002704	CONNECTOR-HEADER:NOWALL,6P,1R,2.5mm,ANGL		RN16	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
CNN02	3711-002705	CONNECTOR-HEADER:NOWALL,7P,1R,2.5mm,ANGL		RN17	2007-000830	R-CHIP:39KOHM,5%,1/10W,DA,TP,2012	
DN01	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP		RN18	2007-001177	R-CHIP:8.2KOHM,5%,1/10W,DA,TP,2012	
DN02	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP		RN19	2007-000308	R-CHIP:100HM,5%,1/10W,DA,TP,2012	
DN03	0405-000108	DIODE-VARACTOR:BB405B,28V,10nA,D		RN20	2007-000308	R-CHIP:100HM,5%,1/10W,DA,TP,2012	
DZD01	0403-000663	DIODE-ZENER:MTZ3.3B,3.3V,3.32-3.53V,500m		RN21	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
HN01	AA61-10068A	BRACKET-PCB:-,M2160,SPT,TO.3,-,-,-		RN22	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
ICD01	0904-001352	IC-DSP:7712H,20BIT,QFP,80P,-,18.432MH		RN23	2007-000881	R-CHIP:4.70HM,5%,1/10W,DA,TP,2012	
ICD02	1002-001054	IC-A/D CONVERTER:SAA7367,1BIT,SOJ,24P,30		RN25	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
ICD03	1201-000541	IC-OP AMP:062.SOP,8P,153MIL,DUAL,6V/mV,P		RN26	2007-000308	R-CHIP:100HM,5%,1/10W,DA,TP,2012	
ICN01	1209-000218	IC-PLL:TDA9814T,SOP,28P,-,PLASTIC,5.5		RN27	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012	
ICN02	1209-001113	IC-ETC, LINEAR:TDA9874H,QFP,44P,-,PLASTI		RN28	2007-000774	R-CHIP:33KOHM,5%,1/10W,DA,TP,2012	
LD01	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		RN29	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012	
LD02	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		RN30	2007-000774	R-CHIP:33KOHM,5%,1/10W,DA,TP,2012	
LD03	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		SFN01	2904-000301	FILTER-SAW AV:38.90MHz,SIP5K,ST,14.5dB,P	
LD04	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		SFN02	2904-000259	FILTER-SAW AV:38.9MHz,SIP5P,ST,15dB,PAL-	
LD05	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		TN01	AA26-10004E	TRANS-IF:-,7MG,VLF,-,7mm,8pF,116.7MHz,S	
LN01	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		XD01	2801-003452	CRYSTAL-UNIT:11.2896MHz,30ppm,28-AAM,10p	
LN02	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		XN01	2801-003316	CRYSTAL-UNIT:24.576MHZ,30PPM,28-AAM,20PF	
LN03	2701-000168	INDUCTOR-AXIAL:3.3uH,5%,2.5x3.4mm					
LN04	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-					
LN05	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-					
LN06	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm					
LN07	2701-000326	INDUCTOR-AXIAL:560nH,10%,2.3x3.4mm					
QN01	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,					
QN02	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,					
QN03	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,					
QN04	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,					
QN05	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,					
RD01	2007-000947	R-CHIP:470HM,5%,1/10W,DA,TP,2012					
RD02	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012					
RD03	2007-000029	R-CHIP:00HM,5%,1/10W,DA,TP,2012					
RD04	2007-000757	R-CHIP:330KOHM,5%,1/10W,DA,TP,2012					
RD05	2007-000457	R-CHIP:18KOHM,5%,1/10W,DA,TP,2012					
RD06	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012					
RD08	2007-000947	R-CHIP:470HM,5%,1/10W,DA,TP,2012					
RD09	2007-000774	R-CHIP:33KOHM,5%,1/10W,DA,TP,2012					
RD10	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012					
RD11	2007-000757	R-CHIP:330KOHM,5%,1/10W,DA,TP,2012					
RD12	2007-000457	R-CHIP:18KOHM,5%,1/10W,DA,TP,2012					
RD13	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012					
RD14	2007-000642	R-CHIP:270OHM,5%,1/10W,DA,TP,2012					
RD15	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012					
RD16	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012					
RD17	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012					
RD18	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012					
RD19	2007-000881	R-CHIP:4.70HM,5%,1/10W,DA,TP,2012					
RD20	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012					
RD21	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012					
RD22	2007-000947	R-CHIP:470HM,5%,1/10W,DA,TP,2012					
RD23	2007-000947	R-CHIP:470HM,5%,1/10W,DA,TP,2012					
RD24	2007-000947	R-CHIP:470HM,5%,1/10W,DA,TP,2012					
RD25	2007-000947	R-CHIP:470HM,5%,1/10W,DA,TP,2012					
RD26	2003-000592	R-METAL OXIDE(S):22ohm,5%,2W,AF,TP,4x12mm					
RD27	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012					
RD28	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012					
RD29	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012					
RD30	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012					
RD31	2007-000024	R-CHIP:1.3KOHM,5%,1/10W,DA,TP,2012					
RD32	2007-000546	R-CHIP:20KOHM,5%,1/10W,DA,TP,2012					
RD34	2007-000546	R-CHIP:20KOHM,5%,1/10W,DA,TP,2012					
RD35	2007-000024	R-CHIP:1.3KOHM,5%,1/10W,DA,TP,2012					
RN01	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012					
RN02	2007-001071	R-CHIP:6.8KOHM,5%,1/10W,DA,TP,2012					
RN03	2007-000774	R-CHIP:33KOHM,5%,1/10W,DA,TP,2012					
RN04	2007-001071	R-CHIP:6.8KOHM,5%,1/10W,DA,TP,2012					
RN05	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012					
RN06	2007-001071	R-CHIP:6.8KOHM,5%,1/10W,DA,TP,2012					
RN07	2007-000981	R-CHIP:5.6KOHM,5%,1/10W,DA,TP,2012					
RN08	2007-000030	R-CHIP:560OHM,5%,1/10W,DA,TP,2012					
RN09	2007-000766	R-CHIP:330OHM,5%,1/10W,DA,TP,2012					
RN10	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012					
RN11	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012					
RN12	2007-000308	R-CHIP:100HM,5%,1/10W,DA,TP,2012					

REMOCON

AA59-10117A REMOCON:DP,TM59,-,-,-,-,AA59-10116A,

ASSY-SPEAKER

3001-001038 SPEAKER:6W,160HM,92DB,140HZ
AA39-20583B LEAD CONNECTOR-ASSY:-,SMH025-04,REC,REC,4P,400,800

ASSY-POWER,CORD

AA96-00175A ASSY-POWER,CORD:-,CP2/NO(4.0),H/C450,KKJ1004A,

ASSY-CRT

AA03-00030A CRT-COLOR:-,A66EGW83X381,+380MG,-,110,42
AA39-20519A LEAD CONNECTOR-ASSY:-,YFH806-06,-,6(4)P,500MM,1617

ASSY-ACCESSORY

HA68-00330A MANUAL-USERS:S51A,HUN,ROM,POL,-,-,A/P100(G)