

7. Electric Parts List

7-1 CK531FZ5X (CK501FT5X/XEH AND CK531FZ5X Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
		ASSY-PCB,MAIN					
		BUYER : SEH		R938	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				TUBE	AA39-20567A	LEAD-CONNECTOR-ASSY:-,TUBE,7ΔfjA,-,25mm,	
				X901	2801-000724	CRYSTAL-UNIT:6MHz,50ppm,28-AAM,20pf,40oh	
*	HA94-100199	ASSY-PCB,MAIN:CK531FZ5X/XMO,S15A				ASSY-CRT	
C410	2201-000406	C-CERAMIC,DISC:270pf,10%,2KV,Y5P,TP,8x6,				AA03-10031E	CRT-COLOR:-,A51EER131X,+400mG,21,90deg,
C416	2306-000195	C-FILM,MPPF:360nf,5%,400V,TP,26x19x11.5,		△		AA27-50005G	DEFLECTION-YOKE:-,DST-21944(2),21/A51EE
C801	2401-002213	C-AL:150uF,+30-10%,450V,GP,BK,25x35		△			
C908	2201-000193	C-CERAMIC,DISC:10pf,0.3pf,50V,CH,TP,5x3,					
C909	2201-000193	C-CERAMIC,DISC:10pf,0.3pf,50V,CH,TP,5x3,					
C922	2201-000573	C-CERAMIC,DISC:47pf,5%,50V,CH,TP,6.5x3.0					
C927	2201-000573	C-CERAMIC,DISC:47pf,5%,50V,CH,TP,6.5x3.0					
CN802	AA27-20003Z	COIL-DEGAUSSING:-,21,13.5ohm,25T,L2380,		*	AA59-10101W	REMOCON:DP,TM59,-,-,-,-,-,AA59-10107N,	
△	IC802	IC-POSIFIXEDREG:7630,SIP,10P,-,PLASTI				ASSY-ACCESSORY	
△	IC901	AA13-30020G	IC-MCU:-,Z90234-R3782,8BIT,SDIP,CS-53			HA68-100049	MANUAL-USERS:-,A/P,80(G),HUN,CK5073Z5X
L904	2701-000299	INDUCTOR-AXIAL:13UH,10%,2.5X3.4MM					
LD901	AA96-30007A	ASSY-LED,GUIDE:-,AA61-50055A,DL-G7GA,GRE					
LW01	AA27-40001N	COIL-HORIZ.WIDTH:-,90/260uH,SB-5S620,PI0					
R301	2004-000869	R-METAL:3KOHM,1%,1/8W,AA,TP,1.8X3.2MM					
R305	2001-001048	R-CARBON(S):1.2OHM,5%,1/2W,AA,TP,2.4X6.4					
R820	2008-000299	R-FUSIBLE(S):47ohm,5%,2W,AF,TP,3.9x10mm					
R821	2008-000266	R-FUSIBLE(S):1OHM,5%,2W,AF,TP,3.9X10MM					
R906	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		*	HA91-100017	ASSY-CABINET,FRONT:531F	
R907	2001-000995	R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM			HA64-300007	CABINET-FRONT:531F,HIPS,-,BLK	
R908	2001-000232	R-CARBON:1.3KOHM,5%,1/8W,AA,TP,1.8X3.2M			HA64-300006	CABINET-BACK:-,531,HIPS,V2,BLK,-,-	
R909	2001-000605	R-CARBON:3.6KOHM,5%,1/8W,AA,TP,1.8X3.2M			AA65-30018A	CLAMP-WIRE:NYLON-66,-,-,DATL-600,DONG-A,	

7-2 CK531FT5X (CK501FT5X/XEH AND CK501FT5X Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
		ASSY-PCB,MAIN					
		BUYER : SEH / OMAXTRADE /SEPOL					
*	HA94-100198	ASSY-PCB,MAIN:CK531FT5X/XEH,S15A				HA68-100060	MANUAL-USERS:-,A/P,80(G),POL,CK5073T5X
C410	2201-000406	C-CERAMIC,DISC:270pf,10%,2KV,Y5P,TP,8x6,					
C416	2306-000195	C-FILM,MPPF:360nf,5%,400V,TP,26x19x11.5,					
CN802	AA27-20003Z	COIL-DEGAUSSING:-,21,13.5ohm,25T,L2380,					
LW01	AA27-40001N	COIL-HORIZ.WIDTH:-,90/260uH,SB-5S620,PI0					
R301	2004-000869	R-METAL:3KOHM,1%,1/8W,AA,TP,1.8X3.2MM					
R305	2001-001048	R-CARBON(S):1.2OHM,5%,1/2W,AA,TP,2.4X6.4					
		ASSY-CRT					
△		AA03-10031E	CRT-COLOR:-,A51EER131X,+400mG,21,90deg,				
△		AA27-50005G	DEFLECTION-YOKE:-,DST-21944(2),21/A51EE				
		ASSY-ACCESSORY					
		BUYER : SEH					
	HA68-100048	MANUAL-USERS:-,A/P,80(G),HUN,CK5073T5X/...					
		BUYER : OMAXTRADE					
	HA68-100068	MANUAL-USERS:-,A/P,80(G)BOL,CK5073T5X					
		BUYER : SEPOL					
						ASSY-CABINET(OPTION);CK531FT5X	
				*	HA91-100017	ASSY-CABINET,FRONT:531F	
					HA64-300007	CABINET-FRONT:531F,HIPS,-,BLK	
					HA64-300006	CABINET-BACK:-,531,HIPS,V2,BLK,-,-	
					AA65-30018A	CLAMP-WIRE:NYLON-66,-,-,DATL-600,DONG-A,	

7-3 CK501FZ5X (CK501FT5X/XEH AND CK501FZ5X Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB,MAIN							
		BUYER : SEH		R908	2001-000214	R-CARBON:1.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
*	HA94-100375	ASSY-PCB,MAIN:CK501FZ5X/XEH,S15A		R944	2004-001201	R-METAL:68Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
		BUYER : MAKMEDIA		TUBE	AA39-20567A	LEAD-CONNECTOR-ASSY:-,TUBE,7,-,25mm,	
*	HA94-100408	ASSY-PCB,MAIN:CK501FZ5S/BOM,S15A		X901	2801-003224	CRYSTAL-UNIT:32.768KHZ,20PPM,28-AA,Y,12.5	
		BUYER : SCSC					
*	HA94-100402	ASSY-PCB,MAIN:CK501FZ5S/XEK,S15A					
		BUYER : SCSC(ONLY)		C801	2401-002213	C-AL:150uF,+30-10%,450V,GP,BK,25x35	
C908	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,		△ IC901	AA13-30020F	IC-MCU:-,Z90203-R3787,8BIT,SDIP,CS-53	
C909	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,		TUBE	AA39-20567A	LEAD-CONNECTOR-ASSY:-,TUBE,7,-,25mm,	
C922	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0		REMOCON			
C927	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0					
△ IC802	1203-001531	IC-POSIFIXED REG.:7630,SIP,10P,-,PLASTI		*	AA59-10101W	REMOCON:DP,TM59,-,-,-,-,AA59-10107N,	
△ IC901	AA13-30020G	IC-MCU:-,Z90234-R3782,8BIT,SDIP,CS-53		ASSY-ACCESSORY			
L904	2701-000299	INDUCTOR-AXIAL:13UH,10%,2.5X3.4MM					
LD901	AA96-30007A	ASSY-LED,GUIDE:-,AA61-50055A,DL-G7GA,GRE					
R820	2008-000299	R-FUSIBLE(S):47ohm,5%,2W,AF,TP,3.9x10mm					
R821	2008-000266	R-FUSIBLE(S):10HM,5%,2W,AF,TP,3.9X10MM					
R906	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R907	2001-000995	R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R908	2001-000232	R-CARBON:1.3KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R908	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R909	2001-000605	R-CARBON:3.6KOHM,5%,1/8W,AA,TP,1.8X3.2M					
X901	2801-000724	CRYSTAL-UNIT:6MHz,50ppm,28-AAM,20pF,40oh					

7-4 CK501FT5X/XEH Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-PCB MAIN							
		BUYER : SEH/SEPOL		C230	2401-001495	C-AL:47uF,20%,16V,GP,5x11mm,5mm,TP	
*	HA94-100268	ASSY-PCB MAIN:CK501FT5X/XEH,S15A		C231	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
		BUYER : MAKMEDIA		C232	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
*	HA94-100407	ASSY-PCB,MAIN:CK501FT5S/BOM,S15A		C238	2401-001495	C-AL:47uF,20%,16V,GP,5x11mm,5mm,TP	
		BUYER : MAKMEDIA		C239	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C101	2401-000939	C-AL:22uF,20%,25V,GP,TP,5x11,5		C240	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5X4.0X5.0MM,	
C102	2401-001082	C-AL:330nF,20%,50V,GP,TP,5x11,5		C247	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V,TP,2.2x3.	
C103	2401-002463	C-AL:470uF,20%,16V,GP,TP,8x11,5,5		C248	2309-000138	C-FILM,PE-PFF:100nF,5%,50V,TP,20x16x8.5,7.5mm	
C201	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,		C249	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
C202	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		C250	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m	
C203	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5		C251	2301-000204	C-FILM,PEF:2.7nF,5%,50V,TP,7.4x3.9x13mm,5	
C204	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C252	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm	
C205	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5mm,		C253	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C206	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5mm,		C254	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C207	2305-000196	C-FILM,MPEF:150nF,5%,63V,TP,-,5MM		C255	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0mm,	
C208	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5		C301	2202-000253	C-CERAMIC,MLC-AXIAL:4.7nF,20%,16V,Y5R,TP,1.9x3.5,7	
C209	2202-000794	C-CERAMIC,MLC-AXIAL:18pF,5%,50V,CH,TP,3.5x19mm,-		C302	2202-000253	C-CERAMIC,MLC-AXIAL:4.7nF,20%,16V,Y5R,TP,1.9x3.5,7	
C210	2301-000108	C-FILM,PEF:1.5nF,5%,50V,TP,6.5x3.0x5.5mm,		C303	2401-003028	C-AL:100uF,20%,25V,WT,TP,6.3x11,5	
C211	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5X4.0X5.0MM,		C304	2401-000903	C-AL:22uF,20%,160V,WT,TP,10X20MM,5M	
C212	2202-000796	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,3.5x19,-		C305	2305-000178	C-FILM,MPEF:10nF,5%,100V,TP,-,5mm	
C213	2201-000273	C-CERAMIC,DISC:18pF,5%,50V,CH,TP,5x3mm,5		C306	2305-000285	C-FILM,MPEF:220nF,5%,100V,TP,20x18x11.5,15	
C214	2301-000285	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5mm		C307	2305-000708	C-FILM,MPEF:150nF,5%,100V,TP,16.5x10.3x5.7	
C215	2301-000380	C-FILM,PEF:10nF,5%,50V,TP,6.5x3mm,5mm		C308	2305-000450	C-FILM,MPEF:56nF,5%,100V,TP,-,5MM	
C216	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		C401	2301-000380	C-FILM,PEF:10nF,5%,50V,TP,6.5x3mm,5mm	
C217	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		C402	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4,5	
C219	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C403	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4,5	
C221	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP,1.9x3.5,-		C404	2401-001998	C-AL:1000uF,20%,25V,GP,TP,10X20,5MM	
C222	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		C408	2401-001530	C-AL:47uF,20%,25V,GP,TP,5x11,5	
C224	2202-000295	C-CERAMIC,MLC-AXIAL:68PF,5%,50V,SL,3.5X19,-,TP		C409	2306-000253	C-FILM,MPPF:7.2nF,5%,1.6KV,TP,28.5x18.5x12	
C226	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5m		c410	2201-000984	C-CERAMIC,DISC:680pF,10%,2KV,Y5P,TP,11x6,7,5mm	
C227	2401-001495	C-AL:47uF,20%,16V,GP,5x11mm,5mm,TP		C411	2401-000927	C-AL:22uF,20%,250V,GP,TP,13X20MM,5M	
C228	2201-000247	C-CERAMIC,DISC:15PF,5%,50V,CH,TP,5X3,5		C413	2305-000382	C-FILM,MPEF:4.7nF,5%,400V,TP,-,5MM	
				C414	2301-001065	C-FILM,MPPF:47nF,5%,630V,TP,19x15.5x7,7,5	
				C415	2401-000560	C-AL:1uF,20%,160V,GP,TP,6.3x11,5	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C416	2306-000204	C-FILM,MPPF;430nF,5%,400V,TP,26x20.5x12.		D401	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
C417	2201-000556	C-CERAMIC,DISC;470pF,10%,500V,Y5P,TP,7x4,5		D402	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
C418	2401-000384	C-AL;10uF,20%,100V,GP,TP,6.3X11,5MM		D403	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C419	2201-000984	C-CERAMIC,DISC;680pF,10%,2KV,Y5P,TP,11x6,7.5mm		D404	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,TP	
C502	2301-000213	C-FILM,PEF;220nF,5%,250V,TP,21.5x11,7.5		D405	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C503	2201-002063	C-CERAMIC,DISC;10nF,+80-20%,3KV,Y5V,TP,16x5,7		D406	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C504	2401-001232	C-AL;4.7uF,20%,250V,GP,TP,10x12.5,5		D501	0402-000216	DIODE-RECTIFIER;ERC24-06,600V,1.0A,DO-204	
C506	2401-000430	C-AL;10uF,20%,250V,GP,TP,10X16MM,5M		D502	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C601	2202-000210	C-CERAMIC,MLC-AXIAL;270PF,10%,50V,Y5P,TP,1.9X3.5,7		D503	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C602	2401-000939	C-AL;22uF,20%,25V,GP,TP,5x11,5		D504	0402-001105	DIODE-RECTIFIER;ERB43-04SV1,400V,1.0A,-,TP	
C603	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm,		D701	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C604	2401-001323	C-AL;470nF,20%,50V,BP,TP,5x11,5mm		D800	1405-000152	VARISTOR;560V,2500A,14X8.5MM,TP	
C610	2401-001998	C-AL;1000uF,20%,25V,GP,TP,10X20,5MM		D801	0402-000102	DIODE-BRIDGE;D2SB60,600V,1.5A,-	
C613	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-		D802	0402-000540	DIODE-RECTIFIER;RU20A,600V,1.5A,-,TP	
C614	2202-000210	C-CERAMIC,MLC-AXIAL;270PF,10%,50V,Y5P,TP,1.9X3.5,7		D804	0402-000213	DIODE-RECTIFIER;ERB12-06,600V,1.0A,DO-41,TP	
C702	2202-000263	C-CERAMIC,MLC-AXIAL;470pF,10%,50V,Y5P,TP,3.5x19,-		D805	0402-000534	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,TP	
C704	2202-000121	C-CERAMIC,MLC-AXIAL;100pF,10%,50V,Y5P,TP,1.9x3.5,-		D809	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C705	2401-001264	C-AL;4.7uF,20%,50V,BP,TP,5x11,5		D810	0402-000216	DIODE-RECTIFIER;ERC24-06,600V,1.0A,DO-204	
C706	2401-001264	C-AL;4.7uF,20%,50V,BP,TP,5x11,5		D901	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C800	2306-000320	C-FILM,MPPF;470nF,20%,250V,TP,-,20MM		D903	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C801	2401-000534	C-AL;150uF,20%,400V,GP,ST,25x30,10		D905	2001-000429	R-CARBON;1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C802	2401-002284	C-AL;33uF,20%,50V,GP,TP,5x11,5		D910	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C803	2301-000224	C-FILM,PEF;22nF,5%,50V,TP,7.4x3.9x13mm,5m		D911	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C804	2301-000310	C-FILM,PEF;68nF,5%,50V,TP,8.0X8.5X4.0X5.5		DA01	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP	
C805	2303-000163	C-FILM,PPF;2.2nF,5%,800V,TP,15x13x8.5,7.5		DT01	2001-000252	R-CARBON;1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C806	2201-000446	C-CERAMIC,DISC;3.3nF,20%,400V,Y5U,TP,18x8,10mm		DT02	2001-000252	R-CARBON;1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C807	2201-000991	C-CERAMIC,DISC;560pF,10%,2KV,Y5P,TP,13x7,7.5		DT03	2001-000252	R-CARBON;1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C808	2401-000262	C-AL;100uF,20%,160V,HR,TP,16x25,7.5		DZ201	0403-000355	DIODE-ZENER;UZ5.1BSB,5.1V,4.97-5.18V,500mW	
C809	2401-002290	C-AL;47uF,20%,160V,GP,TP,13x20,5		DZ202	0403-000551	DIODE-ZENER;MTZ3.9B,3.9V,3.89-4.16V,500mW	
C810	2201-000991	C-CERAMIC,DISC;560pF,10%,2KV,Y5P,TP,13x7,7.5		DZ203	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C811	2401-003141	C-AL;2200uF,20%,25V,WT,TP,13X25,5MM		DZ204	2001-000812	R-CARBON;5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C814	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm		DZ205	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C815	2401-000808	C-AL;220uF,20%,16V,GP,TP,8x11,5,5		DZ208	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C816	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5		DZ301	0403-000660	DIODE-ZENER;MTZ22A,22V,20.15-21.2V,500mW,D	
C818	2401-001495	C-AL;47uF,20%,16V,GP,5x11mm,5mm,TP		DZ302	0403-001039	DIODE-ZENER;MA2560,56V,52-60V,1W,DO-41,TP	
C819	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		DZ401	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW	
C901	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		DZ501	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C902	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-		DZ502	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C904	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-		DZ503	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C905	2401-001333	C-AL;470nF,20%,50V,GP,TP,5x11,5		DZ504	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C907	2201-000119	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5P,TP,8x3.5		DZ701	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C908	2201-000980	C-CERAMIC,DISC;30pF,5%,50V,CH,TP,5.0x3.0,5mm		DZ702	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C909	2201-000980	C-CERAMIC,DISC;30pF,5%,50V,CH,TP,5.0x3.0,5mm		DZ703	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C910	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0mm,		DZ704	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C911	2401-002235	C-AL;10uF,20%,16V,GP,TP,5X11MM,5MM		DZ705	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C912	2201-000234	C-CERAMIC,DISC;150pF,5%,50V,CH,TP,9.5x3,5		DZ802	0403-000297	DIODE-ZENER;MTZ6.2B,6.2V,5.96-6.27V,500mW	
C913	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm,		DZ803	1203-001217	IC-POSI.ADJUST REG.;431,TO-92,3P,4.58MIL,PLASTIC,2	
C914	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0mm,		DZ804	2001-001170	R-CARBON(S);6.8ohm,5%,1/2W,AA,TP,2.4x6.4mm	
C915	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0mm,		DZ806	0403-000295	DIODE-ZENER;MTZ5.1B,5.1V,4.94-5.20V,500mW	
C916	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm,		DZ808	0403-000300	DIODE-ZENER;MTZ8.2B,8.2V,7.78-8.19V,500mW	
C917	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ809	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW	
C920	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5		DZ901	0403-000563	DIODE-ZENER;MTZ9.1B,9.1V,8.57-9.01V,500mW	
C923	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ902	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW	
C924	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.		DZ903	1203-000451	IC-VOLTAGE REGULATOR;33,TO-92,3P,-,PLASTIC,31/35V	
C926	2202-000796	C-CERAMIC,MLC-AXIAL;1nF,10%,50V,Y5P,TP,3.5x19,-		DZ905	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW	
C928	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm		DZ907	0403-000296	DIODE-ZENER;MTZ5.6B,5.6V,5.45-5.73V,500mW	
CA01	2401-001264	C-AL;4.7uF,20%,50V,BP,TP,5x11,5		DZ909	0403-000551	DIODE-ZENER;MTZ3.9B,3.9V,3.89-4.16V,500mW	
CN501	AA39-20109B	LEAD-CONNECTOR,ASSY;-YBNH025-08,S,8P500,1007#26	△	F801	3601-000261	FUSE-FERRULE;250V,3.15A,TIME LAG,GLASS,5x20	
CN601	3711-002642	CONNECTOR-HEADER;BOX,3P,1R,2.5MM,STRAIGHT,SN	△	F801A	3602-000114	FUSE-HOLDER;-,-,30MOHM	
CN703	3711-002648	CONNECTOR-HEADER;BOX,9P,1R,2.5mm,STRAIGHT,SN	△	F801B	3602-000114	FUSE-HOLDER;-,-,30MOHM	
CN802	AA27-20003Y	COIL-DEGAUSSING;-20,15.2ohm,2BT,L2170.E	△	F802	3601-001086	FUSE-FERRULE;125V,5A,FA,GLASS,2.4x7.5mm	
CT01	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.	△	IC201	1204-001386	IC-VIDEO SYSTEM;TDA8842,DIP,56P,300MIL,PLASTIC	
CT02	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.	△	IC301	1204-000441	IC-IF CIRCUIT;TDA8356,SIP,9P,-,PLASTIC,40V,-	
CT03	2401-001495	C-AL;47uF,20%,16V,GP,5x11mm,5mm,TP	△	IC501	1201-001159	IC-VIDEO AMP;6107,ZIP,9P,300MIL,SINGLE,-,PL	
CT04	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.	△	IC601	1201-001147	IC-AUDIO AMP;7056B,SIP,9P,-,SINGLE,41.5DB,P	
CT05	2202-000154	C-CERAMIC,MLC-AXIAL;150PF,10%,50V,Y5P,TP	△	IC801	1203-001494	IC-PWM CONTROLLER;3S0680RF,TO3PF-5L,5,210,PLASTI	
CT06	2202-002037	C-CERAMIC,MLC-AXIAL;100nF,80-20%,50V,Y5V,TP,2.2x3.	△	IC802	1203-000644	IC-POSI.FIXED REG.;7630,SIP,10P,-,PLASTIC,5.1/8V	
CT07	2401-001495	C-AL;47uF,20%,16V,GP,5x11mm,5mm,TP	△	IC901	AA13-30019P	IC-MCU;-SAA5291PS-098,8BIT,SDIP,CK-5	
CW901	2503-000156	C-NETWORK;100PFx4,20%,50V	△	IC902	1103-001105	IC-EEPROM;24C040,4KX1BIT,DIP,8P,300MIL,1	
D201	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP		J149	2701-000114	INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM	
D202	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP		J175	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
D205	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP		J176	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
D208	2001-000633	R-CARBON;30KOHM,5%,1/8W,AA,TP,1.8X3.2MM		J178	2001-000857	R-CARBON;560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
D209	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP		J185	2701-000114	INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM	
D210	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP		JS701	3722-000183	JACK-SCART;21P,4mm,SN,BLK,NO	
D211	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP		L102	2701-000212	INDUCTOR-AXIAL;68UH,10%,2.8X7MM	
D213	0401-000005	DIODE-SWITCHING;1N4148,75V,300MA,DO-35,TP		L103	2701-000114	INDUCTOR-AXIAL;10UH,10%,2.5X3.4MM	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
L202	2701-000168	INDUCTOR-AXIAL:3.3uH,5%,2.5x3.4mm		R234	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L206	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R236	2003-000634	R-METAL OXIDE(S):3.9Kohm,5%,1W,AA,TP,3.3x9mm	
L301	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R237	2001-000793	R-CARBON:470HM,5%,1/8W,AA,TP,1.8X3.2MM	
L302	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R238	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
L304	2701-000159	INDUCTOR-AXIAL:22UH,10%,4.2X9.8MM		R239	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M	
L305	2701-000116	INDUCTOR-AXIAL:10uH,10%,4.2x9.8mm		R240	2001-000832	R-CARBON:5100HM,5%,1/8W,AA,TP,1.8X3.2MM	
L306	2701-000115	INDUCTOR-AXIAL:10UH,10%,2.8X7MM		R241	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L401	AA27-30001B	COIL-LINEARITY:-,195UH,QIC1010,PIO,4.4,5X21.5		R242	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
L402	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-		R250	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L601	2701-000146	INDUCTOR-AXIAL:2.2UH,10%,2.5X3.4MM		R251	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L702	2701-000184	INDUCTOR-AXIAL:4.7UH,10%,2.5X3.4MM		R252	2004-001914	R-METAL:39KOHM,2%,1/8W,AA,TP,1.8X3.5MM	
L703	2701-000184	INDUCTOR-AXIAL:4.7UH,10%,2.5X3.4MM		R262	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L704	2701-000184	INDUCTOR-AXIAL:4.7UH,10%,2.5X3.4MM		R301	2004-001983	R-METAL:2.49KOHM,1%,1/2W,AA,TP,2.4X6.4	
L706	2701-000184	INDUCTOR-AXIAL:4.7UH,10%,2.5X3.4MM		R302	2008-001033	R-FUSIBLE(S):10ohm,5%,2W,AF,TP,3.9x10mm	
L801	AA29-30001G	FILTER-LINE:-,27mH,0.6A,-,-		R303	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
L804	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400G		R305	2004-001370	R-METAL(S):1.3ohm,1%,1/2W,AA,TP,2.4x6.4mm	
L805	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-		R306	2008-000254	R-FUSIBLE(S):0.68ohm,5%,2W,AF,TP,3.9x10mm	
L807	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-		R307	2003-001026	R-METAL OXIDE(S):180OHM,5%,2W,AF,TP,3.9X	
L809	2701-001032	INDUCTOR-AXIAL:100UH,10%,5X14MM		R402	2003-000664	R-METAL OXIDE(S):33OHM,5%,2W,AF,TP,4X12MM	
L810	2701-001032	INDUCTOR-AXIAL:100UH,10%,5X14MM		R403	2001-001114	R-CARBON(S):270ohm,5%,1/2W,AA,TP,2.4x6.4mm	
L902	2701-000189	INDUCTOR-AXIAL:470NH,10%,2.5X3.4MM		R404	2008-000294	R-FUSIBLE(S):33ohm,5%,2W,AF,TP,3.9x10mm	
LD901	AA96-30001B	ASSY-LED,GUIDE:-,AA61-50055A,DL-G5RGA,-		R405	2001-001410	R-CARBON(S):430HM,5%,1/2W,AA,TP,2.4X6.4MM	
LT01	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-		R406	2001-000037	R-CARBON(S):330ohm,5%,1/2W,AA,TP,2.4x6.4mm	
LT02	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5X5,TP-		R407	2001-001037	R-CARBON(S):0.39ohm,5%,1/2W,AA,TP,2.4x6.4m	
LT03	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R408	2001-000022	R-CARBON(S):33ohm,5%,1/2W,AA,TP,2.4x6.4mm	
NT801	1404-000187	THERMISTOR-NTC:4.7ohm,15%,2800K,27.2mW/C,TP		R409	2008-000204	R-FUSIBLE(S):0.22ohm,10%,1/2W,AF,TP,2.5x6.5	
P801	1404-001048	THERMISTOR-PTC:7ohm,30%,200/220V,270V,19A,-B		R412	2003-000664	R-METAL OXIDE(S):33OHM,5%,2W,AF,TP,4X12MM	
PC801	0604-001038	PHOTO-COUPLER:TR,130-260%,200MW,DIP-4,ST		R413	2003-000784	R-METAL OXIDE(S):7.5Kohm,5%,2W,AF,TP,4X12mm	
Q201	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R414	2003-000540	R-METAL OXIDE(S):1KOHM,5%,2W,AF,TP,4X12MM	
Q202	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R415	2008-000206	R-FUSIBLE(S):1ohm,5%,1/2W,AF,TP,2.5x6.5mm	
Q204	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R416	2008-000277	R-FUSIBLE:680HM,5%,1/2W,AA,TP,4.7X11MM	
Q251	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R417	2008-000265	R-FUSIBLE(S):10HM,5%,2W,AA,TP,3.9X10MM	
Q401	0502-001115	TR-POWER:KSC5386,NPN,50W,TO-3PF,ST,8-		R420	2004-001377	R-METAL(S):120Kohm,1%,1/2W,AA,TP,2.4x6.4m	
Q402	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L,-,120-		R501H	2002-001008	R-COMPOSITION:1.8Kohm,5%,1/2W,AA,TP,3.7x9mm	
Q701	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R502H	2002-001008	R-COMPOSITION:1.8Kohm,5%,1/2W,AA,TP,3.7x9mm	
Q703	0501-002183	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,TP,120-		R503	2002-001008	R-COMPOSITION:1.8Kohm,5%,1/2W,AA,TP,3.7x9mm	
Q901	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R504	2001-001062	R-CARBON(S):10Mohm,5%,1/2W,AA,TP,2.4x6.4mm	
Q902	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R505	2008-001011	R-FUSIBLE(S):0.18ohm,10%,2W,AF,TP,3.9x10mm	
Q903	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R510	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q904	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R511	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q905	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R512	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q906	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R603	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
Q907	0504-000125	TR-DIGITAL:KSR1012,NPN,300mW,47K,TO-92,TP		R604	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
Q908	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R610	2001-000347	R-CARBON:13KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
QA01	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R611	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
QT02	0501-002183	TR-SMALL SIGNAL:KTC9014,NPN,625mW,TO-92,TP,100		R701	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
QT03	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,TP		R702	2001-000969	R-CARBON:750HM,5%,1/8W,AA,TP,1.8X3.2MM	
R200	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM		R703	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R201	2001-000005	R-CARBON:390OHM,5%,1/8W,AA,TP,1.8X3.2MM		R705	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R202	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R706	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R203	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R713	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R204	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R714	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R205	2001-000793	R-CARBON:470HM,5%,1/8W,AA,TP,1.8X3.2MM		R715	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R207	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R717	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R208	2001-000005	R-CARBON:390OHM,5%,1/8W,AA,TP,1.8X3.2MM		R801	2003-000994	R-METAL OXIDE(S):33Kohm,5%,2W,AF,TP,3.9x10mm	
R209	2701-000114	INDUCTOR-AXIAL:10UH,10%,2.5X3.4MM		R802	2003-000994	R-METAL OXIDE(S):33Kohm,5%,2W,AF,TP,3.9x10mm	
R210	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R803	2001-001178	R-CARBON(S):680ohm,5%,1/2W,AA,TP,2.4x6.4mm	
R211	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R805	2003-001023	R-METAL OXIDE(S):120ohm,0.05,2W,AF,TP,3.9x10mm	
R212	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R806	2002-001011	R-COMPOSITION:3.3Mohm,10%,1/2W,AA,TP,3.7x9mm	
R213	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R807	2002-001011	R-COMPOSITION:3.3Mohm,10%,1/2W,AA,TP,3.7x9mm	
R214	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R808	2001-000022	R-CARBON(S):33ohm,5%,1/2W,AA,TP,2.4x6.4mm	
R215	2004-001995	R-METAL:9.1KOHM,5%,1/8W,AA,TP,1.8X3.2M		R809	2001-000622	R-CARBON:300KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R216	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP,1.8X3.2MM		R810	2003-000527	R-METAL OXIDE(S):18Kohm,5%,2W,AA,TP,4x12mm	
R217	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		R812	2003-000455	R-METAL OXIDE(S):100ohm,5%,2W,AA,TP,4x12mm	
R218	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		R814	2008-000267	R-FUSIBLE(S):2.4OHM,5%,2W,AA,TP,3.9X10MM	
R219	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R815	2008-000267	R-FUSIBLE(S):2.4OHM,5%,2W,AA,TP,3.9X10MM	
R220	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R816	2004-004089	R-METAL:123KOHM,1%,1/2W,AA,TP,2.5X6.5M	
R221	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R817	2004-001983	R-METAL:2.49KOHM,1%,1/2W,AA,TP,2.4X6.4	
R223	2001-000938	R-CARBON:68ohm,5%,1/8W,AA,TP,1.8x3.2mm		R818	2004-001371	R-METAL(S):1.5Kohm,1%,1/2W,AA,TP,2.4x6.4m	
R224	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R819	2004-001390	R-METAL(S):1KOHM,2%,1/2W,AA,TP,2.4X6.4MM	
R225	2001-000554	R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM		R820	2008-001062	R-FUSIBLE:39ohm,5%,2W,AF,TP,3.9x10mm	
R226	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R822	2001-001150	R-CARBON(S):470Kohm,5%,1/2W,AA,TP,2.4x6.4m	
R227	2004-001234	R-METAL:75KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R823	2001-001150	R-CARBON(S):470Kohm,5%,1/2W,AA,TP,2.4x6.4m	
R229	2001-000890	R-CARBON:6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		R825	2003-001040	R-METAL OXIDE(S):47Kohm,5%,2W,AF,TP,3.9x10mm	
R230	2001-000793	R-CARBON:470HM,5%,1/8W,AA,TP,1.8X3.2MM		R901	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R231	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R902	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R232	2001-000356	R-CARBON:150KOHM,5%,1/8W,AA,TP,1.8X3.2M		R903	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R904	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		Z210	2903-000200	FILTER-CERAMIC;BP;6.5MHz,+70KHz,6dB,-,TP,-	
R905	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R906	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R907	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R908	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R909	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R912	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R913	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R913	2004-001193	R-METAL:680OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R919	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R921	2001-001062	R-CARBON(S);10Mohm,5%,1/2W,AA,TP,2.4x6.4mm					
R922	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R923	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		*	AA59-10101T	REMOCON;DP;TM59,-,-,-,-,-,AA59-10107C,	
R924	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R925	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R926	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R927	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R928	2001-000066	R-CARBON(S);10Kohm,5%,1/2W,AA,TP,2.4x6.4mm					
R929	2004-000253	R-METAL:11KOHM,1%,1/8W,AA,TP,1.8X3.2MM					
R930	2004-000218	R-METAL:10KOHM,1%,1/8W,AA,TP,1.8X3.2MM					
R931	2004-000218	R-METAL:10KOHM,1%,1/8W,AA,TP,1.8X3.2MM					
R932	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R933	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R935	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R936	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R937	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R939	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R940	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R944	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R946	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R947	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R951	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R952	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R954	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R956	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R958	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R959	2001-000800	R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R960	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R962	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M					
RA01	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM					
RA02	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M					
RA03	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
RA04	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
RL901	AA59-60001U	MODULE-REMOCON;-ORC-50VF/SR-12V,38KHz,940nm,					
RT01	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT02	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT03	2001-000252	R-CARBON:1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M					
RT04	2008-001062	R-FUSIBLE:39ohm,5%,2W,AF,TP,3.9x10mm					
RT05	2001-000864	R-CARBON:56KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT06	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT07	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT08	2001-000003	R-CARBON:330OHM,5%,1/8W,AA,TP,1.8X3.2MM					
RT09	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
RT13	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M					
RW701	2011-001133	R-NETWORK:33K/24K/75x3,5%,1/8W,X,SIP,6P,					
RW702	2011-001098	R-NETWORK:75/75/1K/75ohm,5%,-,PLCC,5P,					
RW901	2011-000531	R-NETWORK:4.7KOHM,5%,1/8W,A,SIP,8PTP					
RX801	2002-001011	R-COMPOSITION:3.3Mohm,10%,1/2W,AA,TP,3.7x9mm					
SFN02	2904-001063	FILTER-SAW AV;38.9MHz,SIP5K,TP,17dB,PAL-B/G,					
SW801	3403-001020	SWITCH-PUSH:250V,5A,DPST,OFF-ON-OFF					
SW901	3404-000244	SWITCH-TACT:12V,50mA,100-160gf,8.4x22.6mm,					
SW902	3404-000244	SWITCH-TACT:12V,50mA,100-160gf,8.4x22.6mm,					
SW903	3404-000244	SWITCH-TACT:12V,50mA,100-160gf,8.4x22.6mm,					
SW904	3404-000244	SWITCH-TACT:12V,50mA,100-160gf,8.4x22.6mm,					
SW905	3404-000244	SWITCH-TACT:12V,50mA,100-160gf,8.4x22.6mm,					
T401	AA26-50001B	HORIZ.DRIVE;-7.1MH,102UH,10-20UH,YL081,ST					
T444	AA26-30001Y	TRANS-FLYBACK;-FSV-20A001,20,125V					
T801	AA26-20007Q	TRANS-SWITCHING;-180-260V,125V/12.5V,EN,EER28					
TU01	AA40-10006P	TUNER-V/S;TECC0949VG28B(S),PAL-B/G,TR,18					
V999	3704-001090	SOCKET-CRT;9P,15.24PI,26.5PI,SN,-					
X202	2801-000226	CRYSTAL-UNIT;3.579545MHz,20ppm,28-AAM,15pF,					
X203	2801-000274	CRYSTAL-UNIT;4.433619MHz,30PPM,28-AAM,20PF,					
X901	2801-001476	CRYSTAL-UNIT;12.0MHz,50ppm,28-ABQ,S,30ohm,T					
Z201	2903-000199	FILTER-CERAMIC;TR,6.5MHz,70KHz,-,TP,-					
Z202	2903-000181	FILTER-CERAMIC;TR,5.5MHz,-,-,TP,TPS5.5MB-TF					
Z205	2903-000202	FILTER-CERAMIC;BP;6.5MHz,+80KHz,6dB,-,TP,-					
Z206	2903-000184	FILTER-CERAMIC;BP;5.5MHz,+60KHz,6dB,-,TP,-					