

You can search for the updated part code through ITSELF web site.
 URL : http://itself.sec.samsung.co.kr

7. Electrical Parts List

7-1 HCN4226WX/XAA

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark		
ASSY COVER FRONT									
1	M0001	BP90-00152A	ASSY COVER FRONT;P55A				S.N.A		
..2	T0081	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A	...	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
..2	T0081	6003-001339	SCREW-TAPTITE;HH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A	...	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
..2	HC+CW	6005-001003	SCREW-WOOD;HH,+,M4,L19,ZPC(BLK),SWRCH18AS.N.A	S.N.A	...	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR	
..2	HC+CW	6005-001003	SCREW-WOOD;HH,+,M4,L19,ZPC(BLK),SWRCH18AS.N.A	S.N.A	...	AA61-01132A	VELCRO-A;COMMANDO,BST1 1/4H	S.N.A	
..2	HC+CW	6005-001003	SCREW-WOOD;HH,+,M4,L19,ZPC(BLK),SWRCH18AS.N.A	S.N.A	...	CIS7	AA61-60003A	SPRING ETC-CS;-SUS304,-,OD7,N7,OD7,-,	S.N.A
..2	BCM+W06006-001094	SCREW-ASS'Y WOOD;WW,HH,+,M7,L32,ZPC(YEL)	S.N.A	BP61-00272A	HOLDER-PCB POWER;42W8,ABS,SMOG,6G	S.N.A	
..2	T0118	AA26-00101A	TRANS FBT-H/V DISTRIBUTOR;FWZ50A001E/FFA	S.N.A	...	BP61-00273A	HOLDER-RING;42W8,ABS,GRAY,AL	S.N.A	
..2	AA60-00072B	SPACER-SCREEN;DUST;43,54,62J9,SPONGE 94HF	S.N.A	BP64-00230A	CABINET FRONT-BOT;42W8,HIPS V0,GRAY,SV70	S.N.A	
..2	T0081	AA60-10011A	SCREW-TAPTITE-;SWRCH18A,M4,L12,HH,+,PC,	S.N.A	...	T0023	BP64-00231A	KNOB POWER;42W8,ABS,HB,GRAY,AL	S.N.A
..2	T0081	AA60-10011A	SCREW-TAPTITE-;SWRCH18A,M4,L12,HH,+,PC,	S.N.A	BP64-00232A	WINDOW-RMC;42W8,ABS,HB,CLEAR	S.N.A
..2	T0081	AA60-10011A	SCREW-TAPTITE-;SWRCH18A,M4,L12,HH,+,PC,	S.N.A	...	T0022	BP64-00233A	KNOB CONTROL;42W8,ABS,HB,GRAY,SVM1132	S.N.A
..2	T0115	AA61-00475B	BRACKET-CRT,MAIN;54,SECC,T1.6,-,-,-	S.N.A	AA61-20129A	HOLDER-WIRE-;NYLON-66,-,-,-,NTR,DAFC-25	S.N.A
..2	AA61-00618C	GUIDE-FLOW;54J8,J7,ABS,IVORY,V0	S.N.A	..2	...	BH73-60304C	RUBBER-SUPPORT;DP15LT,CR V0,GRAY,-,14*7*	S.N.A	
..2	AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A	ASSY COVER REAR					
..2	T0056	AA67-00193A	SCREEN-TINT;42W,958*550,T=0.7,P	1	M0002	BP90-00155A	ASSY COVER REAR;P55A	S.N.A	
..2	T0053	AA67-00193B	SCREEN FRESNEL;42W,960*552,T=2.0	..2	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A	
..2	T0052	AA67-00207A	SCREEN-FILTER;T=82%,9,G=110,AG	..2	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A	
..2	T0076	BP39-00009A	LEAD CONNECTOR-ASSY;P54A/SVP-42W5,UL2547	..2	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A	
..2	BP61-00023E	BRACKET-SCREEN,ASSY(TOP);42W5,SECC,T1.0	S.N.A	..2	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A	
..3	T0069	AA60-00091J	SPACER-FELT;-FELT,330X10,-,-,BLK,TO.5,-	..2	T0081	6003-001026	SCREW-TAPTITE;RH,+,B,M4,L15,ZPC(BLK),SWR	S.N.A	
..3	T0254	AA61-01121A	BRACKET-SCREEN,TB;42W5,SECC,T1.0	..2	HC+CW	6005-001003	SCREW-WOOD;HH,+,M4,L19,ZPC(BLK),SWRCH18AS.N.A	S.N.A	
..3	BP61-00043B	HOLDER-SENSOR;W9,PC HB, VIOLET	S.N.A	..2	HC+CW	6005-001003	SCREW-WOOD;HH,+,M4,L19,ZPC(BLK),SWRCH18AS.N.A	S.N.A	
..3	BP61-00052A	HOLDER-WIRE;PJT,NYLON,66,NATURAL	S.N.A	..2	T0081	AA60-10011A	SCREW-TAPTITE-;SWRCH18A,M4,L12,HH,+,PC,	S.N.A	
..3	BP61-00024E	BRACKET-SCREEN,ASSY(BOT);42W5,SECC,T1.0,	S.N.A	..2	T0081	AA60-10011A	SCREW-TAPTITE-;SWRCH18A,M4,L12,HH,+,PC,	S.N.A	
..3	T0069	AA60-00091J	SPACER-FELT;-FELT,330X10,-,-,BLK,TO.5,-	..2	T0081	AA60-10011A	SCREW-TAPTITE-;SWRCH18A,M4,L12,HH,+,PC,	S.N.A	
..3	AA65-00020A	CLAMPER CORE-WIRE;55W9,NYLON 66	S.N.A	..2	T0081	AA60-10011A	SCREW-TAPTITE-;SWRCH18A,M4,L12,HH,+,PC,	S.N.A	
..3	BP61-00043B	HOLDER-SENSOR;W9,PC HB, VIOLET	S.N.A	..2	T0112	AA64-02728A	CABINET-BACK,TOP;42W5,HIPS,HB,G4309	S.N.A	
..3	BP61-00052A	HOLDER-WIRE;PJT,NYLON,66,NATURAL	S.N.A	..2	T0112	AA64-02729B	CABINET-BACK,BOT;42W5,HIPS,V0,G4309	S.N.A	
..3	T0254	AA61-01121A	BRACKET-SCREEN,TB;42W5,SECC,T1.0	..2	AA64-60449B	INLAY-COVER;SP-434JMF,PS,TO.5,149.3X69.5	S.N.A		
..2	BP61-00025D	BRACKET-SCREEN,ASSY(R);42W5,SECC,T1.0,NE	S.N.A	..2	AA65-30008A	CLAMPER CORE-CORD;-PE,HB,-,BLK,-	S.N.A		
..3	T0056	AA61-01122A	BRACKET-SCREEN,RL;42W5,SECC,T1.0	..2	AA67-00204A	MIRROR-FRONT;42W5,FSM,870*633*446	S.N.A		
..3	BP61-00043B	HOLDER-SENSOR;W9,PC HB, VIOLET	S.N.A	..2	T0068	BP61-00008A	BRACKET-MIRROR,ASSY;42W5,SECC,T1.0,01123	S.N.A	
..3	BP61-00052A	HOLDER-WIRE;PJT,NYLON,66,NATURAL	S.N.A	..3	AA61-01123A	BRACKET-MIRROR;42W5,SECC,T1.0	S.N.A		
..2	BP61-00026D	BRACKET-SCREEN,ASSY(L);42W5,SECC,T1.0,NE	S.N.A	..3	BP60-00005A	SPACER-SPONGE;42W5,RUBBER-SPONGE,T3	S.N.A		
..3	T0056	AA61-01122A	BRACKET-SCREEN,RL;42W5,SECC,T1.0	..2	T0092	BP96-00038H	ASSY COVER P-TERMINAL,ANT;WIDE PJT,HIPS	S.N.A	
..3	BP61-00043B	HOLDER-SENSOR;W9,PC HB, VIOLET	S.N.A	..3	AA64-02836J	INLAY-TERMINAL,NT;WIDE PJT,PS SHEET,TO.5	S.N.A		
..3	AA65-00020A	CLAMPER CORE-WIRE;55W9,NYLON 66	S.N.A	..3	AA65-00023A	TERMINAL-BOARD,ANT;HIPS V0,BLK	S.N.A		
..3	BP61-00052A	HOLDER-WIRE;PJT,NYLON,66,NATURAL	S.N.A	..2	AA64-60421C	INLAY-COVER;-PS,TO.3,-,-,BLK,SEA	S.N.A		
..2	BP64-00029A	INLAY-SUPPORT;42W5,PS SHEET,TO.5,94V0	S.N.A	ASSY PRT					
..2	T0102	BP73-00004A	RUBBER-CAP;42W5,SILICONE,WHT,RUBBER	1	BP91-00423A	ASSY PRT;HCM4215WX/XAA,P55A,ASSY-PRT	S.N.A		
..2	T0257	BP91-00005D	ASSY-CABINET,WOOD;WOOD,MJU,42W5	..2	T0026	BP91-00420A	ASSY CPT-R;0	S.N.A	
..3	T0082	3001-001107	SPEAKER;20W,80HM,95DB,1300HZ	..3	AA03-00200A	CRT MONO;P16LSG03RJA,FREE,3.30mH,2.20mH	S.N.A		
..3	T0076	AA39-00086A	LEAD CONNECTOR-ASSY;2.2UF,200MM,REC,REC	..3	T0117	AA26-30006F	TRANS FBT-ANODE CAP ASS'Y;-FWZ-50A001C,	S.N.A	
..3	HC+CW	AA60-10051A	SCREW-WOOD;-SWRCH18A,M4,L16,PH,+,-,-,ZP	..3	T0078	AA27-00249A	DEFLECTION YOKE;-DPD-5292AA,S/S,7,29.1	S.N.A	
..3	AA61-00097A	HOLDER-WIRE-;NYLON 6/6,-,-,-,NTR,-	S.N.A	..3	T0079	AA33-00016A	MAGNET CONVERGENCE;JH 92LT - 29F,-,29.1M	S.N.A	
..3	AA61-00506B	HOLDER-CRT,MAIN;43,54,62J8,HIPS,-,-,-,BL	S.N.A	..3	T0076	AA39-00018A	LEAD CONNECTOR-ASSY;UL1015#22,UL/CSA,1P	S.N.A	
..3	AA61-00508D	HOLDER-JERSEY;W3,ABS V0,GRAY,G4309	S.N.A	..3	AA60-00126B	SPACER-CAP;PROJ,EPDM,BLK	S.N.A		
..3	AA61-00533B	BRACKET-GRILLE;43,54,62J8,SECC-1,TO.5,-	S.N.A	..3	AA60-00127B	SPACER-LENS;PROJ,SILICONE,D/GRAY	S.N.A		
..3	AA64-02724A	CABINET-WOOD;42W5,WOOD,SDE8336R	S.N.A	..3	AA60-00128B	SPACER-CRT;PROJ(J65),SILICONE,D/GRAY	S.N.A		
..3	AA98-00049A	ASSY-LEAD,CON;-LEAD-CON,CORE,AA39-20505	S.N.A	..3	T0081	AA60-10011A	SCREW-TAPTITE-;SWRCH18A,M4,L12,HH,+,PC,	S.N.A	
....4	T0121	3301-001201	CORE-FERRITE;AE,21x11x32mm,1500,280G	..3	...	AA61-00056B	BRACKET-LENS;PROJECTION,SECC,T1.6,-,-,-,	S.N.A	
..3	BP61-00019A	HOLDER-PALLET;42W5,HIPS,HB,BLK	S.N.A	..3	...	AA61-00806B	CASE-COUPLER,R;PROJ,ALDC,T8,BLK	S.N.A	
..3	BP61-00035A	BRACKET-GRILLE;42W5,SECC-1,T1.0	S.N.A	..3	T0114	AA61-00810B	HOLDER-CAP;PROJ,PC,CLR	S.N.A	
..3	AA61-00094C	HOLDER-RAIL;PCJ533R,ABS,-,-,-,BLK,HB,480	S.N.A	..3	T0109	AA67-00187A	LENS-ASSY;DELTA71,CLEAR A/B	S.N.A	
..3	T0082	3001-001353	SPEAKER;25W,80HM,90DB+/-3DB,60HZ+/-12HZ	..3	T0051	AA67-00188A	LENS-DELTA71,RED C ELEMENT	S.N.A	
..2	T0004	BP91-00006G	ASSY-FRONT MASK;42W8,SV012P,HIPS,HB,GRY,	..3	T0107	AA91-00722A	ASSY-BRKT,CRT;SECC T1.6,PROJ	S.N.A	
..3	T0081	6003-001019	SCREW-TAPTITE;RH,+,B,M4,L12,ZPC(BLK),SWR4	T0072	AA61-00473B	BRACKET-CRT;53,SECC,T1.6,-,-,-,-	S.N.A	
..3	AA61-01133A	VELCRO-B;COMMANDO,BST1 1/4H	S.N.A						
..3	T0017	AA64-02727R	CABINET-FRONT MASK;42W8,HIPS,HB,GRY,SV01						
..3	T0057	BP64-00199A	BADGE-BRAND;PJLDC,AL,T1.5,72,12.5,-,DGN-S						
..3	T0102	BP73-00004A	RUBBER-CAP;42W5,SILICONE,WHT,RUBBER						
..2	T0071	BP96-00285A	ASSY COVER P-FRONT BOT;42W8,HIPS,V0,G430						

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark		
....4	AA61-00615B	BRACKET-EARTH:54J8,PBS,TO.5,-,-,-,-	S.N.A4	R125	2001-000554	R-CARBON:2700HM,5%,1/8W,AA,TP,1.8X3.2MM		
....4	AA61-00812A	SPRING ETC-WIRE-PROJ,STS,3,6	S.N.A4	R125	2001-000666	R-CARBON:330HM,5%,1/8W,AA,TP,1.8X3.2MM		
....3	BP61-00091A	HOLDER-CRT:PJTV,PCABS GF20%,BLUE	S.N.A4	R125	2001-000832	R-CARBON:5100HM,5%,1/8W,AA,TP,1.8X3.2MM		
....3	BP61-00079A	HOLDER-DY:,PJT,V,TO.5,NYLON66 V2	S.N.A4	RZ110	2001-001100	R-CARBON(S):2.70HM,5%,1/2W,AA,TP,2.4X6.4		
....3	AA63-00076B	SPACER-LENS:FELT,W7,BLK,TO.8	S.N.A4	RZ104	2001-001100	R-CARBON(S):2.70HM,5%,1/2W,AA,TP,2.4X6.4		
..2	T0027	BP91-00421A	ASSY CPT-G-04	RZ105	2001-001139	R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4		
....3	AA03-00201A	CRT MONO:P16LSG03HKA,FREE,3.30mH,2.20mH,	S.N.A4	RZ106	2001-001139	R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4		
....3	T0117	AA26-30006F	TRANS FBT-ANODE CAP ASS'Y:-,FWZ-50A001C,4	RZ114	2003-000532	R-METAL OXIDE(S):180hm,5%,2W,AF,TP,4x12m		
....3	T0078	AA27-00249A	DEFLECTION YOKE:-,DPD-5292AA,S/S,7,29.14	RZ103	2003-000713	R-METAL OXIDE(S):47ohm,5%,2W,AF,TP,4x12m		
....3	T0076	AA39-00018A	LEAD CONNECTOR-ASSY:,UL1015#22,UL/CSA,TP4	RZ111	2003-000713	R-METAL OXIDE(S):47ohm,5%,2W,AF,TP,4x12m		
....3	AA60-00125B	SPACER-CRT:PROJ,SILICONE,D/GRAY	S.N.A4	RZ123	2003-002157	R-METAL OXIDE:2200HM,5%,2W,AG,TP,6X16MM		
....3	AA60-00126B	SPACER-CAP:PROJ,EPDM,BLK	S.N.A4	RZ113	2003-002157	R-METAL OXIDE:2200HM,5%,2W,AG,TP,6X16MM		
....3	AA60-00127B	SPACER-LENS-PROJ,SILICONE,D/GRAY	S.N.A4	RZ112	2003-002157	R-METAL OXIDE:2200HM,5%,2W,AG,TP,6X16MM		
....3	T0081	AA60-10011A	SCREW-TAPTITE:-,SWRCH18A,M4,L12,HH,+PC,4	RFZ101	2008-001086	R-FUSIBLE(S):3.3ohm,5%,2W,AG,TP,3.9x12mm		
....3	AA61-00056B	BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,-	S.N.A4	C598	2201-000193	C-CERAMIC,DISC:0.01NF,0.25PF,50V,COG,TP,		
....3	AA61-00807B	CASE-COUPLER,G:PROJ,ALDC,T8,BLK	S.N.A4	C598	2201-000193	C-CERAMIC,DISC:0.01NF,0.25PF,50V,COG,TP,		
....3	AA61-00809B	HOLDER-CRT:PROJ,PC/ABS GF 20%,BLK	S.N.A4	C598	2201-000516	C-CERAMIC,DISC:4.7NF,+100-0%,500V,Y5U,TP		
....3	T0114	AA61-00810B	HOLDER-CAP:PROJ,PC,CLR4	C598	2201-000516	C-CERAMIC,DISC:4.7NF,+100-0%,500V,Y5U,TP		
....3	T0109	AA67-00187A	LENS-ASSY:DELTA71,CLEAR A/B4	C598	2201-000604	C-CERAMIC,DISC:0.056NF,+100-0%,500V,SL,T		
....3	T0051	AA67-00189A	LENS:DELTA71,GREEN C ELEMENT4	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11.5		
....3	T0107	AA91-00722A	ASSY-BRKT,CRT:,SECC T1.6,PROJ4	C701	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11.5,5		
....4	T0072	AA61-00473B	BRACKET-CRT:53,SECC,T1.6,-,-,-,-	S.N.A4	C701	2401-001157	C-AL:33uF,20%,160V,GP,TP,12.5x20.5	
....4	AA61-00615B	BRACKET-EARTH:54J8,PBS,TO.5,-,-,-,-	S.N.A4	C701	2401-001220	C-AL:4.7uF,20%,160V,GP,TP,8x11.5,5		
....4	AA61-00812A	SPRING ETC-WIRE-PROJ,STS,3,6	S.N.A4	C701	2401-001220	C-AL:4.7uF,20%,160V,GP,TP,8x11.5,5		
....3	BP61-00079A	HOLDER-DY:,PJT,V,TO.5,NYLON66 V2	S.N.A4	C701	2401-001513	C-AL:47uF,20%,16V,WT,TP,5x11.5		
....3	AA63-00076B	SPACER-LENS:FELT,W7,BLK,TO.8	S.N.A4	C701	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11.5		
..2	T0028	BP91-00422A	ASSY CPT-B-04	LZ101	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm		
....3	AA03-00202A	CRT MONO:P16LSG03BMB,FREE,3.30mH,2.20mH,	S.N.A4	CN906	3711-002642	CONNECTOR-HEADER:BOX,3P1R,2.5mm,STRAIGH		
....3	T0117	AA26-30006F	TRANS FBT-ANODE CAP ASS'Y:-,FWZ-50A001C,4	CN906	3711-002642	CONNECTOR-HEADER:BOX,3P1R,2.5mm,STRAIGH		
....3	T0078	AA27-00249A	DEFLECTION YOKE:-,DPD-5292AA,S/S,7,29.14	CN906	3711-002642	CONNECTOR-HEADER:BOX,3P1R,2.5mm,STRAIGH		
....3	T0079	AA33-00018A	MAGNET CONVERGENCE:JH 92LT - 36F,-,29.1M4	PCB	AA41-00611A	PCB-VM:HCM4215W,FR-1,1L,A,1,6T,245X245,P	S.N.A	
....3	T0076	AA39-00018A	LEAD CONNECTOR-ASSY:,UL1015#22,UL/CSA,TP	..3	OZ101	AA96-00243M	ASSY H/S:-,AMP,AA62-000450A,2SC2344,HERC	S.N.A	
....3	AA60-00126B	SPACER-CAP:PROJ,EPDM,BLK	S.N.A4		0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A	
....3	AA60-00127B	SPACER-LENS:PROJ,SILICONE,D/GRAY	S.N.A4	T0090	0502-000131	TR-POWER:2SA1011-D,NPN,1.2W,TO-220,-,60		
....3	AA60-00128B	SPACER-CRT:PROJ(65),SILICONE,D/GRAY	S.N.A4	T0081	6003-000335	SCREW-TAPTITE:RH,+2S,M3,L8,ZPC(YEL),SWR	S.N.A	
....3	T0081	AA60-10011A	SCREW-TAPTITE:-,SWRCH18A,M4,L12,HH,+PC,4		AA62-00045A	HEAT SINK-PS:-,T1.0,-,-,DREAM,-,-,-,-	S.N.A	
....3	AA61-00056B	BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,-	S.N.A	..3	OZ102	AA96-00243L	ASSY H/S:-,CRT,AA62-000450A,2SC2344,HERC	S.N.A	
....3	AA61-00808B	CASE-COUPLER,B:PROJ,ALDC,T8,BLK	S.N.A4		0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A	
....3	T0114	AA61-00810B	HOLDER-CAP:PROJ,PC,CLR4	T0090	0502-000153	TR-POWER:2SC2344-D,NPN,1.2W,TO-220,-,60		
....3	T0109	AA67-00187A	LENS-ASSY:DELTA71,CLEAR A/B4	T0081	6003-000335	SCREW-TAPTITE:RH,+2S,M3,L8,ZPC(YEL),SWR	S.N.A	
....3	T0051	AA67-00190A	LENS:DELTA71,CLEAR C ELEMENT4		AA62-00045A	HEAT SINK-PS:-,T1.0,-,-,DREAM,-,-,-,-	S.N.A	
....3	T0107	AA91-00722A	ASSY-BRKT,CRT:,SECC T1.6,PROJ	..3		0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A	
....4	T0072	AA61-00473B	BRACKET-CRT:53,SECC,T1.6,-,-,-,-	S.N.A	..3	T0121	3301-001201	CORE-FERRITE:AE,21x11x32mm,1500,280G	
....4	AA61-00615B	BRACKET-EARTH:54J8,PBS,TO.5,-,-,-,-	S.N.A	..3	T0079	AA33-00017A	MAGNET CONVERGENCE:JH 92LT - 29G,-,29.1M		
....4	AA61-00812A	SPRING ETC-WIRE-PROJ,STS,3,6	S.N.A	..3	T0081	6003-001023	SCREW-TAPTITE:RW,+,B,M3,L10,ZPC(YEL),SW	S.N.A	
....3	BP61-00091A	HOLDER-CRT:PJTV,PCABS GF20%,BLUE	S.N.A	..3	T0076	AA39-20055C	LEAD CONNECTOR-ASSY:,6P,500,YBNH025-06,6		
....3	BP61-00079A	HOLDER-DY:,PJT,V,TO.5,NYLON66 V2	S.N.A	..2	T0105	AA94-08270A	ASSY PCB MISC-DY JACK:COMMANDO		
....3	AA63-00076B	SPACER-LENS:FELT,W7,BLK,TO.8	S.N.A	..3		AA97-07230N	ASSY AUTO:COMMANDO	S.N.A	

ASSY CHASSIS

1	M0017	BP91-00771L	ASSY CHASSIS:HCM4226WX/XAA,P55A	S.N.A4	R301	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4		
..2	T0098	AA94-08268A	ASSY PCB MISC-VM:COMMANDO	4	R302	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4		
....3	RZ120	2008-001097	R-FUSIBLE(S):330HM,5%,1/2W,AC,BK,2.5X6.5	4	R303	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4		
....3	AA97-07230M	ASSY AUTO-VM:COMMANDO	S.N.A4	PCB	AA41-00632A	PCB-DY CONNECTION:HCM4215W,FR-1,1L,A,1,6	S.N.A		
....4	DZ106	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		..3		0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A	
....4	DZ105	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		..3	GT01	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5,-NYLON66	S.N.A	
....4	DZ102	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		..3	GT05	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5,-NYLON66	S.N.A	
....4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		..3	GT09	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5,-NYLON66	S.N.A	
....4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		..3	GT13	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5,-NYLON66	S.N.A	
....4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		..2	T0097	AA94-08574A	ASSY PCB MISC-PWR-DEF, ,HCM4215W,P55A		
....4	OZ103	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		..3		0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A	
....4	OZ106	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		..3	T0083	0402-000236	DIODE-RECTIFIER:GI824,400V,5A,-,TP		
....4	OZ105	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		..3	T0083	0402-000250	DIODE-RECTIFIER:RG4C,1000V,1A,-		
....4	OZ104	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		..3		NT801S	1404-001195	THERMISTOR-NTC:5.1ohm,15%,2900,27mW/C,BK	
....4	RZ122	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M		..3		CX802S	2306-000112	C-FILM,MPPF:100nF,20%,250V,BK,-,15mm	
....4	R125	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		CX801S	2306-000112	C-FILM,MPPF:100nF,20%,250V,BK,-,15mm	
....4	R125	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		C701	2401-000701	C-AL:2200uF,20%,250V,GP,-,35x70mm,1	
....4	R125	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		C701	2401-000701	C-AL:2200uF,20%,250V,GP,-,35x70mm,1	
....4	R125	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		C701	2401-002251	C-AL:470uF,20%,200V,GP,BK,25x40mm,1	
....4	R125	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		C701	2401-003076	C-AL:3300UF,20%,50V,WT,BK,18X35.5MM,7.5	
....4	R125	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		C701	2401-003076	C-AL:3300UF,20%,50V,WT,BK,18X35.5MM,7.5	
....4	R125	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		C701	2401-003076	C-AL:3300UF,20%,50V,WT,BK,18X35.5MM,7.5	
....4	R125	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		FP801S	3601-000300	FUSE-CARTRIDGE:250V,6.3A,SLOW-BLOW,GLASS	
....4	R125	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		T481	AA26-00091A	TRANS-HV-STORAGE:4mH,-,14P,830uH,180V,10	
....4	R125	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		T444S	AA26-00100A	TRANS FBT:FFA97513L,CT29A7DR,0.3mH,-,-,-	
....4	R125	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		T431	AA26-50001U	TRANS-HORIZ.DRIVE:-,-,-,28mH,-,-,105uH,-	
....4	R125	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		T461	AA26-50001V	TRANS-HORIZ.DRIVE:-,-,-,6.0mH,-,-,113uH,-	
....4	R125	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		..3		LR401S	AA27-30003M	COIL LINEARITY:-,5uH,OVA14x15,USRC0.1x60	

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark
....4	R125	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-001031	R-CARBON:91KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	RS807	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
....4	R854	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
....4	R839	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
....4	R413	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
⚠	RR401S	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
....4	R434	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
....4	R837	2001-001108	R-CARBON(S):22KOHM,5%,1/2W,AA,TP,2.4X6.4
....4	R468	2001-001122	R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.4
....4	RS802	2001-001124	R-CARBON(S):3.9OHM,5%,1/2W,AA,TP,2.4X6.4
....4	R433	2001-001155	R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.4
....4	R410	2001-001155	R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.4
....4	RS806	2001-001168	R-CARBON(S):6.8KOHM,5%,1/2W,AA,TP,2.4X6.4
....4	R459	2001-001192	R-CARBON(S):820OHM,5%,1/2W,AA,TP,2.4X6.4
....4	R851	2001-001196	R-CARBON(S):9.1KOHM,5%,1/2W,AA,TP,2.4X6.4
⚠	RY801S	2002-001010	R-COMPOSITION:1.8Mohm,5%,1/2W,AA,TP,3.7x
⚠	RP801S	2002-001013	R-COMPOSITION:4.7Mohm,5%,1/2W,AA,TP,3.7x
....4	R428	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9
....4	R428A	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9
....4	R429	2003-000586	R-METAL OXIDE(S):22Kohm,5%,2W,AF,TP,4x12
....4	R430	2003-000586	R-METAL OXIDE(S):22Kohm,5%,2W,AF,TP,4x12
....4	R463	2003-001024	R-METAL OXIDE(S):150ohm,5%,2W,AF,TP,3.9x
....4	R310	2003-001024	R-METAL OXIDE(S):150ohm,5%,2W,AF,TP,3.9x
....4	R460	2003-002044	R-METAL OXIDE(S):100ohm,5%,1W,AF,TP,2.5x
....4	R426	2003-002153	R-METAL OXIDE:4.7OHM,5%,2W,AG,TP,6X16MM
....4	R443A	2003-002156	R-METAL OXIDE:560OHM,5%,2W,AG,TP,6X16MM
....4	R443	2003-002156	R-METAL OXIDE:560OHM,5%,2W,AG,TP,6X16MM
....4	R464	2003-002158	R-METAL OXIDE:0.68OHM,5%,1W,AG,TP,4.3X12
....4	R421	2003-002159	R-METAL OXIDE:150OHM,5%,1W,AG,TP,4.3X12M
....4	R024	2004-001369	R-METAL(S):1.2Kohm,1%,1/2W,AA,TP,2.4x6.4
....4	R024	2004-001386	R-METAL(S):16.9Kohm,1%,1/2W,AA,TP,2.4x6.4
....4	R024	2004-001395	R-METAL(S):330Kohm,2%,1/2W,AA,TP,2.4x6.4
....4	R024	2004-001408	R-METAL(S):91Kohm,1%,1/2W,AA,TP,2.4x6.4m
....4	R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5
....4	R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5
....4	R024	2004-001897	R-METAL(S):43.2Kohm,1%,1/2W,AA,TP,2.5x6.5
....4	R024	2004-001897	R-METAL(S):43.2Kohm,1%,1/2W,AA,TP,2.5x6.5
....4	R024	2004-001984	R-METAL(S):26.7Kohm,1%,1/2W,AA,TP,2.4x6.4
....4	R024	2004-001984	R-METAL(S):26.7Kohm,1%,1/2W,AA,TP,2.4x6.4
....4	R024	2004-001984	R-METAL(S):26.7Kohm,1%,1/2W,AA,TP,2.4x6.4
....4	R024	2004-002011	R-METAL(S):110Kohm,1%,1/2W,AA,TP,2.4x6.4
....4	R024	2004-004001	R-METAL(S):180Kohm,1%,1/2W,AA,TP,2.5x6.5
....4	R024	2004-004046	R-METAL(S):430Kohm,1%,1/2W,AA,TP,2.5x6.5
....4	R024	2004-004046	R-METAL(S):430Kohm,1%,1/2W,AA,TP,2.5x6.5
....4	R024	2004-004366	R-METAL(S):1.3Kohm,1%,1/2W,AA,TP,2.5x6.5
....4	R472	2008-000252	R-FUSIBLE(S):0.47ohm,10%,1/2W,AF,TP,2.5x
....4	R465	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
....4	R449	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
....4	R445	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
....4	R442	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
....4	R441	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
....4	R447	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
....4	R442A	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
....4	R307	2008-000290	R-FUSIBLE(S):2.4ohm,5%,2W,AF,TP,3.9x10mm
....4	R486	2008-001018	R-FUSIBLE(S):0.47ohm,10%,2W,AF,TP,3.9x10
....4	R838	2008-001053	R-FUSIBLE:22ohm,5%,1/2W,AF,TP,2.5x6.5mm
....4	R437	2008-001087	R-FUSIBLE(S):1.8ohm,5%,2W,AG,TP,3.9x12mm
....4	R485	2008-001137	R-FUSIBLE(S):3.3ohm,5%,1W,AF,TP,3.9x10mm
....4	R405	2009-001109	R-TEMPERATURE:240ohm,5%,1/4W,AA,TP,2.3x6
⚠	RR471S	2103-001024	VR-SEMI:50Kohm,25%,0.3W,TOP
⚠	RR402S	2103-001086	VR-SEMI:100KOHM,25%,0.3W,TOP
....4	C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP,
....4	C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP,
....4	C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP,
....4	C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP,
....4	C598	2201-000132	C-CERAMIC,DISC:0.1NF,10%,500V,Y5P,TP,6.5
....4	C598	2201-000132	C-CERAMIC,DISC:0.1NF,10%,500V,Y5P,TP,6.5
....4	C598	2201-000132	C-CERAMIC,DISC:0.1NF,10%,500V,Y5P,TP,6.5
....4	C598	2201-000132	C-CERAMIC,DISC:0.1NF,10%,500V,Y5P,TP,6.5
....4	C598	2201-000132	C-CERAMIC,DISC:0.1NF,10%,500V,Y5P,TP,6.5
....4	C598	2201-000138	C-CERAMIC,DISC:0.1NF,10%,50V,Y5P,TP,4X4M
....4	C598	2201-000146	C-CERAMIC,DISC:0.1NF,5%,50V,SL,TP,5X3.5M
....4	C598	2201-000146	C-CERAMIC,DISC:0.1NF,5%,50V,SL,TP,5X3.5M
....4	C598	2201-000180	C-CERAMIC,DISC:10NF,10%,50V,Y5V,TP,7X3MM
....4	C598	2201-000180	C-CERAMIC,DISC:10NF,10%,50V,Y5V,TP,7X3MM
....4	C598	2201-000017	C-CERAMIC,DISC:1NF,10%,50V,Y5P,TP,5X3.5M

Loc. No.	Code No.	Description ; Specification	Remark
....4	C598	2201-000017	C-CERAMIC,DISC:1NF,10%,50V,Y5P,TP,5X3.5M
....4	C598	2201-000017	C-CERAMIC,DISC:1NF,10%,50V,Y5P,TP,5X3.5M
....4	C598	2201-000332	C-CERAMIC,DISC:2.2NF,20%,250V,Y5U,TP,9X4
....4	C598	2201-000332	C-CERAMIC,DISC:2.2NF,20%,250V,Y5U,TP,9X4
....4	C598	2201-000332	C-CERAMIC,DISC:2.2NF,20%,250V,Y5U,TP,9X4
....4	C598	2201-000370	C-CERAMIC,DISC:0.22NF,10%,50V,Y5P,TP,4X3
....4	C598	2201-000406	C-CERAMIC,DISC:0.27NF,10%,2KV,Y5P,TP,6.3
....4	C598	2201-000551	C-CERAMIC,DISC:0.47NF,10%,1KV,Y5P,TP,6.3
....4	C598	2201-000551	C-CERAMIC,DISC:0.47NF,10%,1KV,Y5P,TP,6.3
....4	C598	2201-000551	C-CERAMIC,DISC:0.47NF,10%,1KV,Y5P,TP,6.3
....4	C598	2201-000551	C-CERAMIC,DISC:0.47NF,10%,1KV,Y5P,TP,6.3
....4	C598	2201-000558	C-CERAMIC,DISC:0.47NF,10%,50V,Y5P,TP,5X3
....4	C478	2301-000020	C-FILM,PEF:27nF,5%,100V,TP,7.3x4x12.5mm,
....4	C479	2301-000200	C-FILM,PEF:2.2nF,5%,200V,TP,11.0x6.0x9.0
....4	C477	2301-000213	C-FILM,PEF:220nF,5%,250V,TP,21.5x11.7,5
....4	CS801	2301-000356	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5m
....4	C493	2301-000356	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5m
....4	C412	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm
....4	C831	2301-001216	C-FILM,PPF:47nF,5%,630V,TP,20x14.5x22.7,
....4	C460	2303-000331	C-FILM,PPF:4.7nF,5%,630V,TP,19.5x12x7.7,
....4	C311	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5
....4	C487	2305-000178	C-FILM,MPEF:10nF,5%,100V,TP,5mm
....4	C309	2305-000285	C-FILM,MPEF:220NF,5%,100V,TP,10.5X5.5X15
....4	C838	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,5mm
....4	C865	2305-000427	C-FILM,MPEF:47nF,5%,100V,TP,7.5x12.5x3.5
....4	C303	2305-000427	C-FILM,MPEF:47nF,5%,100V,TP,7.5x12.5x3.5
....4	C301	2305-000427	C-FILM,MPEF:47nF,5%,100V,TP,7.5x12.5x3.5
....4	C429	2305-000704	C-FILM,MPEF:100nF,5%,250V,TP,16.5x10.3x5
....4	C428	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m
....4	C480	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m
....4	C701	2401-000164	C-AL:100uF,20%,25V,WT,TP,12.5x20.5
....4	C701	2401-000262	C-AL:100uF,20%,160V,HR,TP,16x25,7.5
....4	C701	2401-000262	C-AL:100uF,20%,160V,HR,TP,16x25,7.5
....4	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11.5
....4	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11.5
....4	C701	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5
....4	C701	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5
....4	C701	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12.5mm,
....4	C701	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12.5mm,
....4	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11.5
....4	C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,2
....4	C701	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5X11,5
....4	C701	2401-000703	C-AL:2200uF,20%,25V,GP,TP,12.5x25mm,
....4	C701	2401-001026	C-AL:3.3UF,20%,50V,GP,TP,5X11,5
....4	C701	2401-001026	C-AL:3.3UF,20%,50V,GP,TP,5X11,5
....4	C701	2401-001192	C-AL:33uF,20%,50V,GP,TP,6.3x11.5
....4	C701	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5
....4	C701	2401-001428	C-AL:470uF,20%,50V,GP,TP,10x20,5
....4	C701	2401-001527	C-AL:47uF,20%,250V,HR,TP,13x25mm,5mm
....4	C701	2401-001622	C-AL:6.8uF,20%,50V,BP,TP,16x25mm,7.
....4	C701	2401-000025	C-AL:100uF,20%,16V,GP,TP,6.3x11,5
....4	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5
....4	C701	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5
....4	C701	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5
....4	C701	2401-002216	C-AL:2200uF,20%,35V,GP,TP,16x25,7.5
....4	C701	2401-002216	C-AL:2200uF,20%,35V,GP,TP,16x25,7.5
....4	C701	2401-000050	C-AL:10uF,20%,16V,GP,TP,5x11,2.5
....4	C701	2401-002288	C-AL:470uF,20%,25V,WT,TP,10x20,5
....4	C701	2401-002288	C-AL:470uF,20%,25V,WT,TP,10x20,5
....4	C701	2401-002300	C-AL:47uF,20%,50V,GP,TP,6.3x11,5
....4	C701	2401-002463	C-AL:470uF,20%,16V,GP,TP,8x11.5,5
....4	C701	2401-003114	C-AL:4.7uF,20%,250V,WT,TP,10x16,5
....4	L431	2701-000116	INDUCTOR-AXIAL:10uH,10%,4.2x9.8mm
....4	F101	2901-000297	FILTER-EMI ON BOARD:-3A,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-3A,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-3A,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-3A,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-3A,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-3A,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-3A,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-3A,-,3.5x5,TP,-
....4	F101	2901-000297	FILTER-EMI ON BOARD:-3A,-,3.5x5,TP,-
....4	F101	2901-000299	FILTER-EMI ON BOARD:-6A,UL/CSA,-,9x7.5,
....4	G101	3301-000287	CORE-FERRITE BEAD-AA,3.5x1.0x6.0mm,1500,
....4	G101	3301-000287	CORE-FERRITE BEAD-AA,3.5x1.0x6.0mm,1500,

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
....4	EY59	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	CIS	BH73-00028A SILICON/RUBBER-HS-CDT ALL,SILICON,26*33*	S.N.A
....4	EY58	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	CIS	0205-001027 OIL-SILICON;G746,-,-	S.N.A
....4	EY57	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△3	TS801S BP26-00001A TRANS SWITCHING-POWER;19B012,P55A,HCM421	
....4	EY56	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△3	PC801S 0604-001032 PHOTO-COUPLER;TR,170-260%,300mW,DIP-4,ST	
....4	EL08	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△3	PC811S 0604-001032 PHOTO-COUPLER;TR,170-260%,300mW,DIP-4,ST	
....4	EL07	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A3	DU410	1201-000191 IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV	
....4	EL06	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A3	T0086	1203-000610 IC-PWM CONTROLLER;494,DIP,16P,300MIL,PLA	
....4	EL05	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A3	IC851	1203-001400 IC-POWER PRESCALER;SE110N,TO-220(SIP),3P	
....4	EL04	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A3	C598	2201-000446 C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
....4	EL03	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A3	C598	2201-000446 C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
....4	EL02	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A3	C598	2201-000446 C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
....4	EL01	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A3	C598	2201-000446 C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	
....4	EY39	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△3	CR471S 2301-001091 C-FILM,MPPF;470nF,5%,400V,TP,26x21.5x14.	
....4	EL16	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△3	CR436S 2306-000235 C-FILM,MPPF;560nF,5%,400V,TP,26*22.5*14.	
....4	EL15	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A3	C491	2306-000322 C-FILM,MPPF;12nF,5%,1.6KV,TP,29x20.5x13.	
....4	EL14	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△3	CR473S 2306-000322 C-FILM,MPPF;12nF,5%,1.6KV,TP,29x20.5x13.	
....4	EL10	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△3	CR474S 2306-000326 C-FILM,MPPF;4.7nF,5%,1.6KV,ST,5x16x9mm	
....4	EL11	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A3	L862	AA27-10001C COIL CHOKE;-100uH,K,-,5.0A,ST,700UH-K(R	
....4	EL12	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A3	L863	AA27-10001C COIL CHOKE;-100uH,K,-,5.0A,ST,700UH-K(R	
....4	EL13	6042-000001 EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△3	LX801S AA29-30002L FILTER LINE NOISE;-10mHMIN,5A,AC90-260V	
....4	GT35	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A3	LX802S AA29-30002M FILTER LINE NOISE;-1mHMIN,5A,AC90-260V		
....4	GT34	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A	△3	LX803S AA29-30002M FILTER LINE NOISE;-1mHMIN,5A,AC90-260V	
....4	GT33	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A	△3	LX804S AA29-30002M FILTER LINE NOISE;-1mHMIN,5A,AC90-260V	
....4	GT404	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A3	C701	2401-000142 C-AL;1000uF,20%,16V,WT,TP,10x20.5	
....4	GT801	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A3	L864	AA27-10002L COIL CHOKE;-24uH,K,-,2A,-,24UH-K,10x10mm	
....4	GT802	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A3	T0086	1203-002177 IC-PWM CONTROLLER;VIPER12ADIP,DIP,8P,300	
....4	GT810	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A3	IC421	AA96-00475B ASSY H/S;SILICON-OIL,FMLG-12S(4),AA62-00	S.N.A
....4	GT811	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A4	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
....4	GT14	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A4	T0083	0402-000233 DIODE-RECTIFIER;FML-G12S,200V,5A,-,-	
....4	GT15	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A4	IC012	1203-000165 IC-POSI.ADJUST REG.;78R12,TO-220,4P,-,PL	
....4	GT16	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A4	T0081	6003-000334 SCREW-TAPTITE;RH,+,2S,M3,L6,ZPC(YEL),SWR	
....4	GT17	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A4	AA62-00066B	HEAT SINK;D2,D3,AL,1T1.0,89,70,-,AA62-00	S.N.A
....4	GT807	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A3	C814	2301-001041 C-FILM,PPF;15nF,5%,1.6KV,TP,29x14x21.5,2	
....4	GT433	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A3	DZS801	0406-001007 DIODE-TVS;P6KE180A,171/180/189V,600W,CAS	
....4	T0083	0402-001286 DIODE-RECTIFIER;RP1H,2000V,1A,-,TP	△3	T801S	BP26-00002A TRANS SWITCHING;EER5345,P55A,160V-280V,P	
....4	R024	2004-001893 R-METAL(S);22Kohm,1%,1/2W,AA,TP,2.5x6.5mm	△3	CR430S	2301-001343 C-FILM,MPPF;3.9nF,5%,2KV,TP,29x9.5x16mm,	
....4	R024	2004-001402 R-METAL(S);6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	△3	CR431S	2301-001343 C-FILM,MPPF;3.9nF,5%,2KV,TP,29x9.5x16mm,	
....4	R462	2008-001145 R-FUSIBLE;4.70HM,5%,1/2W,AF,TP,2.5X6.5MM	△3	T432	AA26-00053A TRANS;-,-,1.2mH,-,-,-,-,-,31.5KHZ,-,	
....4	R125	2001-000745 R-CARBON;4.70HM,5%,1/8W,AA,TP,1.8X3.2MM	3	T0076	BP39-00014A LEAD CONNECTOR-ASSY;P55A/HCM4215W,UL1007	
....4	C701	2401-002619 C-AL;47uF,20%,25V,GP,TP,5x11.5	3	T0121	3301-001201 CORE-FERRITE;AE,21x11x32mm,1500,280G	
....4	C701	2401-001655 C-AL;680uF,20%,25V,GP,TP,10x20.5	3	T0090	0502-000405 TR-POWER;-NPN,70W,TO-220,BK,10	
....4	C871	2305-000289 C-FILM,MPEF;220nF,5%,63V,TP,-,5mm	3	T0123	1203-001006 IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-,	
....4	C701	2401-001486 C-AL;47uF,20%,160V,HR,TP,13x20mm,5m	3	BP39-00017A	LEAD CONNECTOR;P55A/HCM4215W,UL1617#22,U	
....4	R431	2001-001153 R-CARBON(S);470HM,5%,1/2W,AA,TP,2.4X6.4MM	4	T0121	3301-001201 CORE-FERRITE;AE,21x11x32mm,1500,280G	
....4	G101	3301-000287 CORE-FERRITE BEAD;AA,3.5x1.0x6.0mm,1500,	3	GT01	AA60-40012D PIN-GT,ASSY;T1,6.6-12.5,-,NYLON66	S.N.A
....4	R833	2009-000017 R-METAL PLATE;0.1ohm,10%,5W,CL,TP,5x14x1	3	CN906	3711-003043 CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH	
....4	C701	2401-001625 C-AL;6.8uF,20%,50V,GP,TP,5x11.5	3	C598	2201-000963 C-CERAMIC,DISC;1nF,20%,400V,Y5U,TP,9.5X6	
△	FD802S	3601-001228 FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	3	C598	2201-000963 C-CERAMIC,DISC;1nF,20%,400V,Y5U,TP,9.5X6	
△	FD855S	3601-001228 FUSE-AXIAL LEAD;125V,10A,FAST-ACTING,EPO	3	IC012	1203-000162 IC-POSI.ADJUST REG.;317,TO-220,3P,-,PLAS	
....4	R306	2008-001076 R-FUSIBLE(S);1.8ohm,5%,2W,AF,TP,3.9x10mm	3	C701	2401-000787 C-AL;220uF,20%,160V,GP,TP,16x31.5mm	
....4	R125	2001-000554 R-CARBON;2700HM,5%,1/8W,AA,TP,1.8X3.2MM		△3	VX801S 1405-000187 VARISTOR;750V,1250A,12.5x7mm,TP	
....4	R427	2003-002152 R-METAL OXIDE;10HM,5%,2W,AG,TP,6X16MM	3	C832	2301-001418 C-FILM,MPPF;1.5nF,5%,2KV,TP,29x7x13.5mm,	
....4	R427A	2003-002152 R-METAL OXIDE;10HM,5%,2W,AG,TP,6X16MM	3	L432	AA27-00056A COIL HORIZ. WIDTH:-,600uH,YL9N 15x27.5 C	
....4	C701	2401-000698 C-AL;220uF,20%,16V,WT,TP,12.5x25.5	3	R384	2002-001079 R-COMPOSITION;470Kohm,5%,1/2W,AA,TP,4x10	
....4	R424	2008-000289 R-FUSIBLE(S);1ohm,5%,1W,AA,TP,3.9x10mm	3	Q473	BP96-00006B ASSY HEAT SINK P-HS,SCREW,IRF640B,2SC412	S.N.A
....4	C432	2303-000002 C-FILM,PPF;8.2nF 5% 400V TP 19X18X7,7.5m	4	CIS	0205-001027 OIL-SILICON;G746,-,-	S.N.A
....4	C438	2303-000002 C-FILM,PPF;8.2nF 5% 400V TP 19X18X7,7.5m	4	T0090	0502-001100 TR-POWER;2SC4125,NPN,70W,TO-3PML,BK,8-	
....4	R440	2008-000282 R-FUSIBLE;0.47ohm,5%,1W,AA,TP,3.9x12mm	4	Q409	0505-001722 FET-SILICON;IRFS640B,N,200V,18A,0.180HM,	
....4	R831	2003-000512 R-METAL OXIDE(S);15Kohm,5%,3W,AA,TP,6x16	4	T0081	6003-000333 SCREW-TAPTITE;RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
....4	R832	2003-000512 R-METAL OXIDE(S);15Kohm,5%,3W,AA,TP,6x16	4	CIS	AA60-30001A WASHER-PLATE;M3,JD3.5,15X8.5,T1.0,SBHG	S.N.A
....4	R425	2003-000417 R-METAL OXIDE(S);1.2Kohm,5%,3W,AA,TP,6x1	4	CIS	BP62-00001A HEAT SINK;COMMANDO,A1050P,T2.0,W62.0,H50	S.N.A
....4	R853	2008-001152 R-FUSIBLE(S);1.3KOHM,5%,1/2W,AA,TP,2.5X6	2	T0099	AA94-08582A ASSY PCB MISC-CRT;COMMANDO,C2	
....4	0	AA41-00598D PCB-SUB;HCM4215W,CEM-1,1L,D,1.6T,330X245	S.N.A3	0202-000187	SOLDER-WIRE FLUX;-RS60S,D1.2,63Sn/37Pb	S.N.A
....4	R024	2004-005051 R-METAL(S);2.2KOHM,1%,1/2W,AA,TP,2.4X6.4	3	VR501	2101-000321 VR-ROTARY;1Mohm,-,0.6W,SIDE	
△	RS801S	3601-000102 FUSE-AXIAL LEAD;125V,1A,FAST-ACTING,GLAS	3	VR531	2101-000321 VR-ROTARY;1Mohm,-,0.6W,SIDE	
....4	R840	2001-001045 R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.	3	VR561	2101-000321 VR-ROTARY;1Mohm,-,0.6W,SIDE	
....4	R841	2003-002102 R-METAL OXIDE(S);68Kohm,5%,2W,AF,TP,4x12	3	V561	3704-001019 SOCKET-CRT;10P,29.1PI,35.5PI,AU30U,-	
....4	R024	2004-004029 R-METAL(S);10Kohm,1%,1/2W,AA,TP,2.5X6.5m	3	V531	3704-001019 SOCKET-CRT;10P,29.1PI,35.5PI,AU30U,-	
....4	R801	2003-002285 R-METAL OXIDE(S);1.5KOHM,5%,2W,AF,TP,6X1	3	V501	3704-001019 SOCKET-CRT;10P,29.1PI,35.5PI,AU30U,-	
....4	DZ016	0403-000698 DIODE-ZENER;TZP12A,12V,11.4-12.6V,1W,DO-	3	CN906	3711-003052 CONNECTOR-HEADER;BOX,10P,1R,2.5MM,STRAIG	
....4	Q409	0505-001723 FET-SILICON;FOP630TSTU,N,200V,9A,0.40HM,	3	CN906	3711-003052 CONNECTOR-HEADER;BOX,10P,1R,2.5MM,STRAIG	
....4	Q409	0505-001723 FET-SILICON;FOP630TSTU,N,200V,9A,0.40HM,	3	CN906	3711-003973 CONNECTOR-HEADER;BOX,11P,1R,2.5mm,STRAIG	
....3	Q431	BH99-00033H ASSY HEAT/SINK;BH62-00038A,SPRING,F,UL692	S.N.A3	CN906	3711-003973 CONNECTOR-HEADER;BOX,11P,1R,2.5mm,STRAIG	
....4	T0083	0402-001286 DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	3	SG301	4715-001050 SURGE ABSORBER;2.4KV,20%,1500A,-,DISC-RA	
....4	T0060	BH61-70003A SPRING ETC;CVT4857,STS304-W1/2H,W3.8,-,L	S.N.A3	SG562	AA27-00084A COIL;S-23,-,-,-,-,-,S-23,5000Mohm MIN,	
....4	T0090	0502-001230 TR-POWER;FJL6920YDTU,N,200000MW,TO-264 F	3	SG532	AA27-00084A COIL;S-23,-,-,-,-,-,S-23,5000Mohm MIN,	
....4	CIS	BH62-00038B HEAT SINK-FBT;COMMANDO,A1050S,T2.0,85*80	S.N.A3	SG502	AA27-00084A COIL;S-23,-,-,-,-,-,S-23,5000Mohm MIN,	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
...3	Q371	AA96-00244H ASSY H/S;SCREW,2SC4636(2),CRT,SLICON-OIL	S.N.A	...4	R125	2001-001015 R-CARBON:9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A	...4	R581	2001-001052 R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0090	0502-000442 TR-POWER:2SC4636RB,NPN,2W,TO-220,ST,10-		...4	R551	2001-001052 R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0081	6003-000335 SCREW-TAPTITE:RH,+.2S,M3,L8,ZPC(YEL),SWR	S.N.A	...4	R521	2001-001052 R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	AA62-00046A	HEAT SINK-PS-,-,T1.0,-,D1(DREAM) 60X25X	S.N.A	...4	R371	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...3	IC561	AA96-50311L ASSY H/S;- ,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A	...4	R370	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...3	IC531	AA96-50311L ASSY H/S;- ,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A	...4	R369A	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...3	IC501	AA96-50311L ASSY H/S;- ,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A	...4	R367	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0074	1201-001131 IC-VIDEO AMP:6111,SIP,9P,-,SINGLE,-,PLAS		...4	R368	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0081	6003-000334 SCREW-TAPTITE:RH,+.2S,M3,L6,ZPC(YEL),SWR		...4	R369	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	AA62-30175D	HEAT SINK-PS-;SECC,T1.0,-,33X15X30 FT-2	S.N.A	...4	R567	2001-001088 R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
...3	AA97-07608A	ASSY AUTO-CRT:HCM4215W	S.N.A	...4	R537	2001-001088 R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
...4	D372	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...4	R507	2001-001088 R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
...4	D504	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...4	R381	2001-001088 R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
...4	D509	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...4	R361	2001-001097 R-CARBON(S):2.4KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	D361	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...4	R374	2001-001110 R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	D362	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...4	R373	2001-001110 R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	D371	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...4	R372	2001-001110 R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	D510	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...4	R377	2001-001110 R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0083	0402-000493 DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L		...4	R375	2001-001113 R-CARBON(S):270KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0083	0402-000493 DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L		...4	R365	2001-001120 R-CARBON(S):3.30HM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0083	0402-000493 DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L		...4	R574	2001-001122 R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		...4	R544	2001-001122 R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		...4	R514	2001-001122 R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		...4	R583	2002-001006 R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7	
...4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		...4	R582	2002-001006 R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7	
...4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		...4	R553	2002-001006 R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7	
...4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		...4	R552	2002-001006 R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7	
...4	DZ016	0403-000508 DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500		...4	R523	2002-001006 R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7	
...4	DZ016	0403-000508 DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500		...4	R522	2002-001006 R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7	
...4	DZ016	0403-000508 DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500		...4	R589	2002-001015 R-COMPOSITION:47Kohm,5%,1/2W,AA,TP,3.7x9	
...4	DZ016	0403-000708 DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500		...4	R559	2002-001015 R-COMPOSITION:47Kohm,5%,1/2W,AA,TP,3.7x9	
...4	DZ016	0403-000708 DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500		...4	R529	2002-001015 R-COMPOSITION:47Kohm,5%,1/2W,AA,TP,3.7x9	
...4	DZ016	0403-000708 DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500		...4	R575	2002-001017 R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9	
...4	DZ016	0403-000708 DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500		...4	R545	2002-001017 R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9	
...4	Q563	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		...4	R515	2002-001017 R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9	
...4	Q534	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		...4	R579	2002-001021 R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X	
...4	Q533	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		...4	R578	2002-001021 R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X	
...4	Q504	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		...4	R549	2002-001021 R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X	
...4	Q361	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		...4	R518	2002-001021 R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X	
...4	Q362	0501-000366 TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L,		...4	R519	2002-001021 R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X	
...4	Q502	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		...4	R548	2002-001021 R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X	
...4	T0090	0502-000006 TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-		...4	R588	2003-000738 R-METAL OXIDE(S):56Kohm,5%,2W,AA,TP,4x12	
...4	T0090	0502-000006 TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-		...4	R538	2003-000738 R-METAL OXIDE(S):56Kohm,5%,2W,AA,TP,4x12	
...4	T0090	0502-000006 TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-		...4	R508	2003-000738 R-METAL OXIDE(S):56Kohm,5%,2W,AA,TP,4x12	
...4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	R024	2004-001892 R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5	
...4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	R024	2004-001892 R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5	
...4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	R024	2004-001892 R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5	
...4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	R573	2008-001129 R-FUSIBLE(S):1.5ohm,5%,1/2W,AF,TP,2.5x6.4	
...4	R584	2001-000028 R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4		...4	R543	2008-001129 R-FUSIBLE(S):1.5ohm,5%,1/2W,AF,TP,2.5x6.4	
...4	R554	2001-000028 R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4		...4	R513	2008-001129 R-FUSIBLE(S):1.5ohm,5%,1/2W,AF,TP,2.5x6.4	
...4	R524	2001-000028 R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4		...4	C598	2201-000119 C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP,	
...4	R580	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4		...4	C598	2201-000119 C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP,	
...4	R550	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4		...4	C598	2201-000119 C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP,	
...4	R520	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4		...4	C598	2201-000556 C-CERAMIC,DISC:0.47NF,10%,500V,Y5P,TP,5.	
...4	R577	2001-000085 R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4		...4	C598	2201-000723 C-CERAMIC,DISC:4.7NF,20%,3KV,Y5U,TP,16X5	
...4	R547	2001-000085 R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4		...4	C598	2201-000723 C-CERAMIC,DISC:4.7NF,20%,3KV,Y5U,TP,16X5	
...4	R517	2001-000085 R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4		...4	C598	2201-000723 C-CERAMIC,DISC:4.7NF,20%,3KV,Y5U,TP,16X5	
...4	R366	2001-000109 R-CARBON(S):470OHM,5%,1/2W,AA,TP,2.4X6.4		...4	C598	2201-000983 C-CERAMIC,DISC:1NF,10%,2KV,Y5P,TP,9X5MM,	
...4	R125	2001-000290 R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C598	2201-000983 C-CERAMIC,DISC:1NF,10%,2KV,Y5P,TP,9X5MM,	
...4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C598	2201-000983 C-CERAMIC,DISC:1NF,10%,2KV,Y5P,TP,9X5MM,	
...4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C565	2305-000149 C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5	
...4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C535	2305-000149 C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5	
...4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C505	2305-000149 C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5	
...4	R125	2001-000539 R-CARBON:24KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C507	2305-000154 C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11	
...4	R125	2001-000577 R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C537	2305-000154 C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11	
...4	R125	2001-000613 R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C567	2305-000154 C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11	
...4	R125	2001-000660 R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C361	2306-000122 C-FILM,MPEF:100nF,5%,50V,TP,7.3x4.0x5.0m	
...4	R125	2001-000723 R-CARBON:4.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C701	2401-002075 C-AL:4.7uF,20%,50V,GP,TP,5x11,5	
...4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C701	2401-002075 C-AL:4.7uF,20%,50V,GP,TP,5x11,5	
...4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C701	2401-000133 C-AL:1000uF,20%,16V,GP,TP,10x20,5	
...4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C701	2401-000302 C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
...4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C701	2401-000302 C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
...4	R125	2001-000938 R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C701	2401-000430 C-AL:10uF,20%,250V,GP,TP,10x16mm,5m	
...4	R125	2001-000995 R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C701	2401-000430 C-AL:10uF,20%,250V,GP,TP,10x16mm,5m	
...4	R125	2001-000995 R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C701	2401-000430 C-AL:10uF,20%,250V,GP,TP,10x16mm,5m	

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM
....4	C701	2401-001621	C-AL:8.6uF,20%,450V,GP,TP,13x20.54	L561	2701-000168	INDUCTOR-AXIAL:3.3uH,5%,2.5x3.4mm
....4	L531	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm4	R382	2002-001014	R-COMPOSITION:6.8Kohm,10%,1/2W,AA,TP,3.7
....4	L501	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm4	PCB	AA41-00600E	PCB-CRT:HCM4215W,FR,1,1L,E,1.6T,245X197(S.N.A
....4	SG561	4715-001036	SURGE ABSORBER:500V,20%,--,TP4	T0083	0402-000243	DIODE-RECTIFIER:RC2-V1,2000V,0.2A,DO-201
....4	SG563	4715-001036	SURGE ABSORBER:500V,20%,--,TP3	T0076	BP39-00004B	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239
....4	SG533	4715-001036	SURGE ABSORBER:500V,20%,--,TP3	T0076	BP39-00004C	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239
....4	SG501	4715-001036	SURGE ABSORBER:500V,20%,--,TP3	T0076	BP39-00004C	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239
....4	SG503	4715-001036	SURGE ABSORBER:500V,20%,--,TP3	T0076	AA39-00112A	LEAD CONNECTOR-ASSY,UL1007#26,UL/CSA,10
....4	SG531	4715-001036	SURGE ABSORBER:500V,20%,--,TP3	T0076	AA39-20031D	LEAD CONNECTOR-ASSY,9P500,67096-009,S
....4	EL06	6042-000002	EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H3	CN906	3711-002648	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,STRAIGH
....4	EL03	6042-000002	EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H3	T0103	BP59-00005A	MODULE-FOCUS PACK ASSY:PJT,TV,F301-P03A
....4	EL563	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	T0076	AA39-00198D	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL1617
....4	EL537	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	T0076	AA39-20010D	LEAD CONNECTOR-ASSY,1P,400,YFH800-01,S
....4	EL536	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	T0076	AA39-20010D	LEAD CONNECTOR-ASSY,1P,400,YFH800-01,S
....4	EL535	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	T0076	AA39-00120F	LEAD CONNECTOR-ASSY:SIR-1165,UL1007#26,U
....4	EL564	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	T0076	AA39-20027B	LEAD CONNECTOR-ASSY,6P,400,67096-006,S
....4	EL565	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	T0121	3301-001201	CORE-FERRITE:AE,21x11x32mm,1500,280G
....4	EL566	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	T0076	AA39-20010B	LEAD CONNECTOR-ASSY,1P,500,YFH800-01,S
....4	EL567	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	CN906	3711-002645	CONNECTOR-HEADER:BOX,6P,1R,2.5mm,STRAIGH
....4	EL534	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	T0076	AA39-20010C	LEAD CONNECTOR-ASSY,1P,600,YFH800-01,S
....4	EL01	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11.5
....4	EL02	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	AA63-10002A	BAND-TIE-NYLON66 V2,L100,NTR	S.N.A
....4	EL04	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H2	T0094	AA95-02002A	ASSY SUB-PCB,CG AMP;COMMANDO
....4	EL05	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H3	AA97-07418A	ASSY AUTO:HCM4215WX/AA,P55A	S.N.A
....4	EL533	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H4	R125	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	EL505	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H4	R125	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	EL504	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H4	R125	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	EL503	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H4	R125	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT537	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT561	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT536	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT535	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT534	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT562	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT568	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT567	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000857	R-CARBON:5600HM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT564	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000857	R-CARBON:5600HM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT563	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000857	R-CARBON:5600HM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT503	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000857	R-CARBON:5600HM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT502	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000857	R-CARBON:5600HM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT501	AA60-40014A	PIN-GT,ASSY:AUTO4	R125	2001-000857	R-CARBON:5600HM,5%,1/8W,AA,TP,1.8X3.2MM
....4	GT373	AA60-40014A	PIN-GT,ASSY:AUTO4	RZ109	2001-001114	R-CARBON(S):2700HM,5%,1/2W,AA,TP,2.4X6.4
....4	GT372	AA60-40014A	PIN-GT,ASSY:AUTO4	RZ108	2001-001114	R-CARBON(S):2700HM,5%,1/2W,AA,TP,2.4X6.4
....4	GT371	AA60-40014A	PIN-GT,ASSY:AUTO4	RZ107	2001-001114	R-CARBON(S):2700HM,5%,1/2W,AA,TP,2.4X6.4
....4	GT504	AA60-40014A	PIN-GT,ASSY:AUTO4	RZ106	2001-001114	R-CARBON(S):2700HM,5%,1/2W,AA,TP,2.4X6.4
....4	GT533	AA60-40014A	PIN-GT,ASSY:AUTO4	RZ105	2001-001114	R-CARBON(S):2700HM,5%,1/2W,AA,TP,2.4X6.4
....4	GT532	AA60-40014A	PIN-GT,ASSY:AUTO4	RZ104	2001-001114	R-CARBON(S):2700HM,5%,1/2W,AA,TP,2.4X6.4
....4	GT531	AA60-40014A	PIN-GT,ASSY:AUTO4	R857	2001-001155	R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.
....4	GT506	AA60-40014A	PIN-GT,ASSY:AUTO4	R856	2001-001155	R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.
....4	GT374	AA60-40014A	PIN-GT,ASSY:AUTO4	RZ142	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	GT375	AA60-40014A	PIN-GT,ASSY:AUTO4	RZ143	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	R125	2001-000362	R-CARBON:1500HM,5%,1/8W,AA,TP,1.8X3.2MM4	RZ144	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	R125	2001-000362	R-CARBON:1500HM,5%,1/8W,AA,TP,1.8X3.2MM4	RZ145	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	R125	2001-000362	R-CARBON:1500HM,5%,1/8W,AA,TP,1.8X3.2MM4	RZ146	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	DZ016	0403-000334	DIODE-ZENER:U22.7BSA,2.7V,2.54-2.75V,5004	RZ147	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	DZ016	0403-000334	DIODE-ZENER:U22.7BSA,2.7V,2.54-2.75V,5004	RZ123	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	DZ016	0403-000334	DIODE-ZENER:U22.7BSA,2.7V,2.54-2.75V,5004	RZ124	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	R566	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.4	RZ125	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	R536	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.4	RZ128	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	R506	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.4	RZ127	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	R125	2001-000007	R-CARBON:3KOHM,5%,1/8W,AA,TP,1.8X3.2MM4	RZ126	2003-002148	R-METAL OXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M
....4	R125	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM4	RZ132	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	C598	2201-000599	C-CERAMIC,DISC:0.56NF,10%,500V,Y5P,TP5.4	RZ132A	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	C598	2201-000599	C-CERAMIC,DISC:0.56NF,10%,500V,Y5P,TP5.4	RZ148	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	C598	2201-000599	C-CERAMIC,DISC:0.56NF,10%,500V,Y5P,TP5.4	RZ148A	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	C701	2401-001571	C-AL:47uF,+20%-0%,50V,GP,TP,8x11.5,4	RZ149	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	C701	2401-001571	C-AL:47uF,+20%-0%,50V,GP,TP,8x11.5,4	RZ149A	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	C701	2401-001571	C-AL:47uF,+20%-0%,50V,GP,TP,8x11.5,4	RZ129	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	R125	2001-000319	R-CARBON:120KOHM,5%,1/8W,AA,TP,1.8X3.2MM4	RZ129A	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	R125	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM4	RZ130	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	R125	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM4	RZ131A	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	R125	2001-000232	R-CARBON:1.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM4	RZ131	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM4	RZ130A	2003-002171	R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x
....4	R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM4	RFZ50	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9X10mm

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5	R979	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	C120	2203-000748	C-CERAMIC,CHIP:0.03NF,5%,50V,COG,TP,2012
.....5	R940	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	C120	2203-000748	C-CERAMIC,CHIP:0.03NF,5%,50V,COG,TP,2012
.....5	R909	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	C120	2203-001048	C-CERAMIC,CHIP:0.56NF,10%,50V,COG,TP,201
.....5	R916	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	C120	2203-005809	C-CERAMIC,CHIP:1000nF,10%,16V,X7R,TP,201
.....5	R918	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	C950	2402-000179	C-AL,SMD:47uF,20%,16V,GP,TP,6.6x6.6x5.4
.....5	R939	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	C936	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4
.....5	R923	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	C921	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4
.....5	R922	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	C918	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4
.....5	R907	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	C915	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4
.....5	R917	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	C913	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4
.....5	R911	2007-000076	R-CHIP:330ohm,5%,1/10W,TP,16085	C938	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4
.....5	R963	2007-000077	R-CHIP:470ohm,5%,1/10W,TP,16085	C917	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4
.....5	R901	2007-000077	R-CHIP:470ohm,5%,1/10W,TP,16085	C912	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4
.....5	R930	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	C911	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4
.....5	R933	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	L905	2703-001245	INDUCTOR-SMD:8.2uH,10%,2x1.25x1.25mm
.....5	R936	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	G101	3301-001324	CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,
.....5	R974	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	G101	3301-001324	CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,
.....5	R905	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	G101	3301-001324	CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,
.....5	R921	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	G101	3301-001324	CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,
.....5	R924	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	G101	3301-001324	CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,
.....5	R925	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	G101	3301-001324	CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,
.....5	R915	2007-000081	R-CHIP:2.7Kohm,5%,1/10W,TP,16085	R949	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
.....5	R913	2007-000081	R-CHIP:2.7Kohm,5%,1/10W,TP,16085	R950	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
.....5	R912	2007-000081	R-CHIP:2.7Kohm,5%,1/10W,TP,16085	R951	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
.....5	R978	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16085	R945	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
.....5	R976	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16085	R946	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
.....5	R971	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16085	R948	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
.....5	R958	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16085	R966	2007-000931	R-CHIP:470ohm,5%,1/8W,TP,2012
.....5	R980	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16085	PCB	AA41-00599B	PCB-MICOM:HCM4215W,FR-4,2L,B,1.6T,180X24
.....5	R982	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16085		0202-001167	SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SN S.N.A
.....5	R985	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16084	IC902	1102-001130	IC-EPRM:M27W201-80F6,256KX8BIT,DIP,32P,
.....5	R986	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16084		0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb
.....5	R903	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16083	IC801	AA96-00475C	ASSY H/S:SILICON-OIL,KA278R09,KA7808,AA6
.....5	R904	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16084		0205-000129	GREASE-SILICON:SC102,JAPAN
.....5	R906	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16084	T0087	1203-000293	IC-POSIFIXED REG.:7808,TO-220,3P,-,PLAS
.....5	R908	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16084	T0123	1203-002003	IC-VOLTAGE REGULATOR:278R09,TO-220,4P,-,
.....5	R955	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16084	T0081	6003-000334	SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR
.....5	R954	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16084		AA62-00066B	HEAT SINK:D2,D3,AL,T1.0,89,70,-,AA62-00
.....5	R928	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16084	T0123	1203-001978	IC-VOLTAGE REGULATOR:KA278RA05,TO-220F,4
.....5	R927	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16083	IC601	AA96-00623E	ASSY H/S:SCREW,MAIN,AA62-00056A,TDAT265,
.....5	R983	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16084		0205-000129	GREASE-SILICON:SC102,JAPAN
.....5	R934	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,16084	T0124	1201-001026	IC-POWER AMP:7265,ZIP,11P,19.6MIL,DUAL,1
.....5	R987	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,16084	T0081	6003-000334	SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR
.....5	R957	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,16084		AA62-00056A	HEAT SINK-PS:-,T1.0,-,41*35*70,D2,-,
.....5	R944	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,16083		BP63-00030A	SHIELD CASE:COMMANDO,SPT,TO.5,W26.0,L13
.....5	R926	2007-000097	R-CHIP:47Kohm,5%,1/10W,TP,16083	T0093	BP95-00146C	ASSY SUB PCB-CONV MOD.;P55A,CG MOD
.....5	R975	2007-000121	R-CHIP:820ohm,5%,1/10W,TP,16084		0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb
.....5	R942	2007-000123	R-CHIP:1.5Kohm,5%,1/10W,TP,16084	L01	2701-001030	INDUCTOR-AXIAL:43uH,10%,5x14mm
.....5	R941	2007-000123	R-CHIP:1.5Kohm,5%,1/10W,TP,16084	CN01	3703-001124	CONNECTOR-BACK PANEL:32P,2R,MALE,ANGLE,A
.....5	R914	2007-000123	R-CHIP:1.5Kohm,5%,1/10W,TP,16084	CN906	3711-003601	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,ANGLE,
.....5	R988	2007-000290	R-CHIP:100ohm,5%,1/8W,TP,20124		BP97-00513D	ASSY SMD.;P55A,CG MOD
.....5	R962	2007-000583	R-CHIP:22Kohm,1%,1/10W,TP,16085	D13	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	R961	2007-000939	R-CHIP:47Kohm,1%,1/10W,TP,16085	D12	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D11	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D10	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D14	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D15	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D16	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D17	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D18	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D01	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D02	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D03	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D04	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D05	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000189	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	D09	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,32165	D08	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,16085	D07	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,16085	D06	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP
.....5	C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,16085	DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-
.....5	C120	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,20125	DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-
.....5	C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,16085	Q02	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23
.....5	C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-5	Q03	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23
.....5	C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-5	Q10	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-
.....5	C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-5	Q04	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-
.....5	C120	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-5	Q409	0505-000110	FET-SILICON:2N7002,N.60V,115MA,7.5OHM,0.

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5	Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.5	R69	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608
.....5	Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.5	R51	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608
.....5	IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P,45	R57	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608
.....5	IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P,45	R63	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608
.....5	IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P,45	R109	2007-000082	R-CHIP:3.3Kohm,5%,1/10W,TP,1608
.....5	IC08	1001-000164	IC-ANALOG MULTIPLEX:74HC4052,CMOS,SOP165	R66	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	IC13	1001-001155	IC-ANALOG MULTIPLEX:NC7S3157P6X,CMOS,SC5	R61	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	IC112	1103-001195	IC-EEPROM:24C64,8Kx8Bit,SOP,8P,150MIL,105	R60	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	DU410	1201-001135	IC-OP AMP:324,SOPST,14P,150MIL,QUAD,1005	R55	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	DU410	1201-001504	IC-OP AMP:072,SOP8P,150MIL,DUAL,-,PLAST5	R54	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	DU410	1201-001504	IC-OP AMP:072,SOP8P,150MIL,DUAL,-,PLAST5	R79	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	DU410	1201-001504	IC-OP AMP:072,SOP8P,150MIL,DUAL,-,PLAST5	R78	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	DU410	1201-001504	IC-OP AMP:072,SOP8P,150MIL,DUAL,-,PLAST5	R73	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	T0074	1201-001520	IC-VIDEO AMP:EL2250CS,SOIC,8P,150MIL,DUA5	R72	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	IC03	1203-001824	IC-VOL. DETECTOR:7042,SOT-89,3P,-,PLASTI5	R67	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	T0087	1203-002302	IC-POSI.FIXED REG.:78RM33D,D-PAK,3P,-,PL5	R49	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	IC17	1209-001163	IC-PLL:TLC2932PWLE,SOP,14P,-,PLASTIC5	R08	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	R36	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,20125	R07	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	R35	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,20125	R06	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	R31	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,20125	R04	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	R30	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,20125	R01	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	R143	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,16085	R48	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	R144	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,16085	R133	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	R25	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,16085	R121	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	R122	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,16085	R119	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	R123	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,16085	R118	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....5	R141	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,16085	R86	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....5	R136	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,16085	R92	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....5	R15	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,16085	R93	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....5	R24	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,16085	R96	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....5	R45	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,16085	R97	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....5	R46	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,16085	R85	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....5	R09	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,16085	R113	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....5	R10	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,16085	R114	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....5	R129	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,16085	R115	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....5	R134	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,16085	R83	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....5	R135	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,16085	R84	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....5	R59	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	R125	2007-000091	R-CHIP:12Kohm,5%,1/10W,TP,1608
.....5	R65	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	R05	2007-000102	R-CHIP:100Kohm,5%,1/10W,TP,1608
.....5	R71	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	R127	2007-000109	R-CHIP:1Mohm,5%,1/10W,TP,1608
.....5	R77	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	R100	2007-000118	R-CHIP:390ohm,5%,1/10W,TP,1608
.....5	R91	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	R32	2007-000119	R-CHIP:560ohm,5%,1/10W,TP,1608
.....5	R53	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	R34	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608
.....5	R02	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	R29	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608
.....5	R16	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	R28	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608
.....5	R17	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	R117	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608
.....5	R20	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	R107	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608
.....5	R47	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,16085	R33	2007-000124	R-CHIP:2.2Kohm,5%,1/10W,TP,1608
.....5	R62	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R120	2007-000124	R-CHIP:2.2Kohm,5%,1/10W,TP,1608
.....5	R64	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R90	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608
.....5	R68	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R89	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608
.....5	R58	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R88	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608
.....5	R56	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R87	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608
.....5	R52	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R108	2007-000381	R-CHIP:13Kohm,5%,1/10W,TP,1608
.....5	R70	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R139	2007-000402	R-CHIP:150ohm,5%,1/10W,TP,1608
.....5	R98	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R138	2007-000402	R-CHIP:150ohm,5%,1/10W,TP,1608
.....5	R94	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R137	2007-000402	R-CHIP:150ohm,5%,1/10W,TP,1608
.....5	R82	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R99	2007-000704	R-CHIP:3.6Kohm,5%,1/16W,DA,TP,1608
.....5	R80	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R95	2007-000704	R-CHIP:3.6Kohm,5%,1/16W,DA,TP,1608
.....5	R76	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R126	2007-000857	R-CHIP:4.3Kohm,1%,1/16W,DA,TP,1608
.....5	R74	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R27	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
.....5	R38	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R26	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
.....5	R37	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	R116	2007-001179	R-CHIP:8.2Kohm,5%,1/10W,TP,1608
.....5	R110	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	RN04	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP8P,TP
.....5	R11	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	RN05	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP8P,TP
.....5	R101	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	RN06	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP8P,TP
.....5	R03	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	RN01	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP8P,TP
.....5	R39	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	RN02	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP8P,TP
.....5	R50	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	RN03	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP8P,TP
.....5	R44	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP
.....5	R43	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP
.....5	R42	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP
.....5	R41	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP
.....5	R40	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,16085	C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP
.....5	R128	2007-000079	R-CHIP:1.8Kohm,5%,1/10W,TP,16085	C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP
.....5	R81	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,16085	C120	2203-000041	C-CERAMIC,CHIP:0.01NF,0.25PF,50V,COG,TP
.....5	R75	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,16085	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	C80	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	OSCO1	2804-001479	OSCILLATOR-CLOCK:24MHZ,100PPM,50PF,TP5V
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	F103	2901-000226	FILTER-EMI SMD:25V,0.3A,-,100pf,3.2x1.25
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	F103	2901-000226	FILTER-EMI SMD:25V,0.3A,-,100pf,3.2x1.25
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	F103	2901-000229	FILTER-EMI SMD:50V,0.3A,-,22000pf,4.5x3.
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	F103	2901-000229	FILTER-EMI SMD:50V,0.3A,-,22000pf,4.5x3.
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	T0119	AA09-00032A	IC MICOM;TSC8725IG2D-OTP,4.5 TO 5.5V,-, S.N.A
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	1	AA41-00717D	PCB (FR 4) 4L(AU);CONVERGENCE,FR-4,4,1,6 S.N.A
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	IC125	BP13-00003A	IC ASIC;SDC12,128,-0.3 TO +3.8,0 TO 70,0
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5		0202-001167	SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SN,S.N.A
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,3	IC808	BP96-00020G	ASSY HEAT SINK P-AA62-00045B,TAPTITE,SI- S.N.A
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	CIS	0205-000129	GREASE-SILICON:SC102,JAPAN S.N.A
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	T0081	6003-000334	SCREW-TAPTITE,RH,+2S,M3,L6,ZPC(YEL),SWR
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	CIS	AA62-00045B	HEAT SINK:COMMANDO,AL1050,T1.0,H45.0 S.N.A
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	IC012	1203-000203	IC-POSI.ADJUST REG.;3050,TO-220,5P,-,PLA
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,3		BP97-00511F	ASSY AUTO:0 S.N.A
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	D607	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	D608	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	D609	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	D601	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	D604	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	D605	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	DZ016	0403-000700	DIODE-ZENER:TZP33A,33V,31-35V,1W,DO-41,T
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	DZ016	0403-001039	DIODE-ZENER:MA2560,56V,52-60V,1W,DO-41,T
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	DZ016	0403-001319	DIODE-ZENER:MTZJ4.7C,4.68-4.93V,500mW,DO
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	DZ016	0403-001325	DIODE-ZENER:MTZJ15C,14.35-15.09V,500mW,D
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	Q603	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	Q602	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	Q601	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	R125	2001-000007	R-CARBON:3KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	R810	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	R808	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	R125	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	R125	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	R125	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,4	R125	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,16084	R125	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,16084	R125	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,16084	R125	2001-000508	R-CARBON:220KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,16084	R125	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,16084	R125	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,16084	R125	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,16084	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,16084	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-4	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000575	C-CERAMIC,CHIP:220nF,10%,25V,X7R,TP,20124	R125	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000575	C-CERAMIC,CHIP:220nF,10%,25V,X7R,TP,20124	R125	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000975	C-CERAMIC,CHIP:47nF,10%,25V,X7R,TP,1608,4	R125	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000975	C-CERAMIC,CHIP:47nF,10%,25V,X7R,TP,1608,4	R125	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-000975	C-CERAMIC,CHIP:47nF,10%,25V,X7R,TP,1608,4	R125	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,1604	R125	2001-000780	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,1604	R125	2001-000780	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,1604	R125	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,1604	R125	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,1604	R125	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,1604	R125	2001-001000	R-CARBON:82KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	C120	2203-001071	C-CERAMIC,CHIP:0.056nF,5%,50V,COG,TP,1604	R801	2001-001077	R-CARBON(S):150OHM,5%,1/2W,AA,TP,2.4X6.4
.....5	C120	2203-001083	C-CERAMIC,CHIP:0.005nF,0.1pf,50V,NPO,TP,4	R674	2001-001103	R-CARBON(S):20KOHM,5%,1/2W,AA,TP,2.4X6.4
.....5	C120	2203-001083	C-CERAMIC,CHIP:0.005nF,0.1pf,50V,NPO,TP,4	R677	2001-001103	R-CARBON(S):20KOHM,5%,1/2W,AA,TP,2.4X6.4
.....5	C120	2203-001083	C-CERAMIC,CHIP:0.005nF,0.1pf,50V,NPO,TP,4	R682	2001-001146	R-CARBON(S):4.7OHM,5%,1/2W,AA,TP,2.4X6.4
.....5	C120	2203-001083	C-CERAMIC,CHIP:0.005nF,0.1pf,50V,NPO,TP,4	R681	2001-001146	R-CARBON(S):4.7OHM,5%,1/2W,AA,TP,2.4X6.4
.....5	C120	2203-001245	C-CERAMIC,CHIP:0.082nF,5%,50V,NPO,TP,2014	R811	2001-001182	R-CARBON(S):7.5KOHM,5%,1/2W,AA,TP,2.4X6.4
.....5	C38	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.44	R814	2003-001098	R-METAL OXIDE(S):22Kohm,5%,3W,AA,TP,6x16
.....5	C40	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.44	R805	2004-000970	R-METAL:470ohm,1%,1/4W,AA,TP,2.4x6.4mm
.....5	C70	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.44	R024	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm
.....5	C84	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.44	R024	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm
.....5	C14	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.44	R024	2004-001970	R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.5
.....5	C06	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.44	R024	2004-001970	R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.5
.....5	C03	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.44	R024	2004-001970	R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.5
.....5	C01	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.44	R024	2004-001970	R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.5

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20125	0202-001167	SOLDER-CREAM;RX3603-2330HO,S45A,PASTE,SNS,N.A	
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20123	T0095	BP95-00142N	ASSY SUB PCB-PRO SCAN;HCN4727WX/XAA,P55A
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	0202-000187	SOLDER-WIRE FLUX;-RS60S,D1.2,63Sn/37Pb	S.N.A
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	FC48	2305-000011	C-FILM,MPEF;470nF,5%,250V,TP,21.5X13.0X7
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	FC59	2305-000704	C-FILM,MPEF;100nF,5%,250V,TP,16.5x10.3x5
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	FC58	2309-000138	C-FILM,PE-PPF;100nF,5%,50V,TP,20x16x8.5,
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	EX01	2801-004019	CRYSTAL-UNIT;20.25MHz,30ppm,28-AAM,13pF,
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	T0122	2802-001177	RESONATOR-CERAMIC;2.696MHZ,0.4%,BK,10X4.
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	T0122	2802-001179	RESONATOR-CERAMIC;4MHZ,0.5%,BK,8X3X5.5MM
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	CN02	3703-001124	CONNECTOR-BACK PANEL;32P,2R,MALE,ANGLE,A
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	CN01	3703-001124	CONNECTOR-BACK PANEL;32P,2R,MALE,ANGLE,A
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	CN906	3711-001164	CONNECTOR-HEADER-BOX;9P,1R,2.5mm,ANGLE,-
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	CN906	3711-003601	CONNECTOR-HEADER-BOX;12P,1R,2.5mm,ANGLE,-
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20124	BP97-00169A	ASSY SMD;HCM4215WJ/XAA,P55A	S.N.A
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20125	FD13	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20125	FD14	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
....5	C120	2203-000206	C-CERAMIC,CHIP;100nF,10%,50V,X7R,TP,20125	FD15	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	FD16	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	FD17	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	FD10	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	FD01	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	FD02	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	FD07	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	FD08	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	FD09	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	DZ016	0403-000746	DIODE-ZENER;RLZ3.9B,3.89-4.16V,500mW,LL-
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	DZ016	0403-001016	DIODE-ZENER;RLZ6.2B,5.96-6.27V,500mW,LL-
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	DZ016	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	DZ016	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	DZ016	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	DZ016	0403-001117	DIODE-ZENER;RLZ12B,5%,500mW,LL-34,TP
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	SQ01	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23
....5	C120	2203-000236	C-CERAMIC,CHIP;0.1nF,5%,50V,COG,TP,16085	FQ13	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23
....5	C120	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,16085	FQ04	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23
....5	C120	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,16085	FQ03	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23
....5	C120	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,16085	FQ02	0501-000280	TR-SMALL SIGNAL;KSA1182,PNP,150mW,SOT-23
....5	C120	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,16085	FQ08	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
....5	C120	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,16085	FQ09	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
....5	C120	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,16085	FQ12	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
....5	C120	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,16085	PQ01	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
....5	C120	2203-000332	C-CERAMIC,CHIP;0.012nF,5%,50V,COG,TP,1605	FQ06	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
....5	C120	2203-000332	C-CERAMIC,CHIP;0.012nF,5%,50V,COG,TP,1605	FQ05	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
....5	C120	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-5	EQ15	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
....5	C120	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-5	EQ14	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
....5	C120	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-5	EQ13	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
....5	C120	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-5	FQ07	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,
....5	C120	2203-001071	C-CERAMIC,CHIP;0.056nF,5%,50V,COG,TP,1605	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.
....5	C120	2203-001071	C-CERAMIC,CHIP;0.056nF,5%,50V,COG,TP,1605	Q409	0505-000110	FET-SILICON;2N7002,N,60V,115MA,7.5OHM,0.
....5	C120	2203-001071	C-CERAMIC,CHIP;0.056nF,5%,50V,COG,TP,1605	IC104	0801-000662	IC-CMOS LOGIC;74HC123,MULTIVIBRATOR,SOP,1
....5	C120	2203-001211	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,16085	IC106	1001-001082	IC-VIDEO SWITCH;BA7657F,-SOP,24P,300MIL
....5	C120	2203-001211	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,16085	IC06	1203-001211	IC-VOL. DETECTOR;7027,SOT-89,3P,-PLASTI
....5	C120	2203-001211	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,16085	T0087	1203-002186	IC-POSIFIXED REG.;18,DPAK,3P,240MIL,PLA
....5	C120	2203-001211	C-CERAMIC,CHIP;8.2nF,10%,50V,X7R,TP,16085	T0087	1203-002302	IC-POSIFIXED REG.;78RM33D,D-PAK,3P,-PL
....5	C120	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,5	IC02	1204-001814	IC-SELECTOR;CXA2151Q,QFP,48P,144MIL,PLAS
....5	C120	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,5	IC01A	1204-001938	IC-DECODER;VSP9407B-B11,MQFP,80P,14X14MM
....5	C120	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,5	IC118	1204-001989	IC-VIDEO PROCESS;CXA2165Q,QFP,64P,20X14MM
....5	C120	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,5	SR08	2007-000052	R-CHIP;10kOhm,1%,1/10W,TP,1608
....5	C120	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,5	FR80	2007-000052	R-CHIP;10kOhm,1%,1/10W,TP,1608
....5	C120	2203-001652	C-CERAMIC,CHIP;470nF,+80-20%,16V,Y5V,TP,5	FR79	2007-000052	R-CHIP;10kOhm,1%,1/10W,TP,1608
....5	C120	2203-005590	C-CERAMIC,CHIP;330nF,10%,16V,X7R,TP,20125	FR78	2007-000052	R-CHIP;10kOhm,1%,1/10W,TP,1608
....5	C120	2203-005590	C-CERAMIC,CHIP;330nF,10%,16V,X7R,TP,20125	FR57	2007-000052	R-CHIP;10kOhm,1%,1/10W,TP,1608
....5	C120	2203-005590	C-CERAMIC,CHIP;330nF,10%,16V,X7R,TP,20125	FR35	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	C120	2203-005590	C-CERAMIC,CHIP;330nF,10%,16V,X7R,TP,20125	FR07	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	C120	2203-005590	C-CERAMIC,CHIP;330nF,10%,16V,X7R,TP,20125	ER90	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	L701	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm5	FR76	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	L707	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm5	FR96	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	L708	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm5	SR09	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	L901	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm5	SR22	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	L902	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm5	ER29	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	L604	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm5	ER04	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	L125	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm5	ER05	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	L126	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm5	ER06	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	L601	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm5	ER13	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	L602	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm5	ER19	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	L603	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm5	ER18	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	G101	3301-001324	CORE-FERRITE BEAD;AB,150OHM,2X1.25X0.9MM,5	ER17	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
....5	PCB	AA41-00597F	PCB-MAIN;HCM4215W,FR-4,2L,F,1.6T,245X2455	SR03	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
....4	C120	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608				
....4	C120	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608				
....4	C120	2203-000257	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,1608				
....4	C120	2203-000440	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,1608,-				
....4	C120	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,COG,TP,160				
....4	C120	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,COG,TP,160				
....4	C120	2203-000626	C-CERAMIC,CHIP;0.022NF,5%,50V,COG,TP,160				
....4	C120	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,COG,TP,160				
....4	C120	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,COG,TP,160				
....4	C120	2203-000998	C-CERAMIC,CHIP;0.047NF,5%,50V,COG,TP,160				
....4	C120	2203-005437	C-CERAMIC,CHIP;10000nF,+80-20%,10V,Y5V,T				
....4	C120	2203-005437	C-CERAMIC,CHIP;10000nF,+80-20%,10V,Y5V,T				
....4	C120	2203-005437	C-CERAMIC,CHIP;10000nF,+80-20%,10V,Y5V,T				
....4	C120	2203-005437	C-CERAMIC,CHIP;10000nF,+80-20%,10V,Y5V,T				
....4	C120	2203-005437	C-CERAMIC,CHIP;10000nF,+80-20%,10V,Y5V,T				
....4	C120	2203-005437	C-CERAMIC,CHIP;10000nF,+80-20%,10V,Y5V,T				
....4	C120	2203-005437	C-CERAMIC,CHIP;10000nF,+80-20%,10V,Y5V,T				
....4	DC420	2402-000165	C-AL,SMD;47uF,20%,6.3V,GP,TP5.3x5.3x5.				
....4	DC417	2402-000165	C-AL,SMD;47uF,20%,6.3V,GP,TP5.3x5.3x5.				
....4	DC413	2402-000165	C-AL,SMD;47uF,20%,6.3V,GP,TP5.3x5.3x5.				
....4	DC410	2402-000165	C-AL,SMD;47uF,20%,6.3V,GP,TP5.3x5.3x5.				
....4	DC407	2402-000165	C-AL,SMD;47uF,20%,6.3V,GP,TP5.3x5.3x5.				
....4	DC406	2402-000165	C-AL,SMD;47uF,20%,6.3V,GP,TP5.3x5.3x5.				
....4	DC404	2402-000165	C-AL,SMD;47uF,20%,6.3V,GP,TP5.3x5.3x5.				
....4	DC402	2402-001129	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM				
....4	DC706	2402-001155	C-AL,SMD;47UF,20%,16V,WT,TP,6.3X5.2MM				
....4	DC701	2404-001020	C-TA,CHIP;10uF,20%,10V,GP,TP,3216,3.2				
....4	DL701	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm				
....4	DL409	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm				
....4	DL408	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm				
....4	DL406	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm				
....4	DL404	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm				
....4	DL401	2703-000398	INDUCTOR-SMD;10uH,10%,3.2x2.5x2.2mm				
....4	G101	3301-001202	CORE-FERRITE BEAD;AB,120ohm,4.5x3.2x1.3m				
....4	T0119	BP09-00004A	IC MICOM:T89C51IC2-SLSCM,44,5V,32KBYTE,P				
....4	CR501	2402-000108	C-AL,SMD;10uF,20%,16V,WT,TP,4.3x4.3x5.4				
....4	G101	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M				
....4	G101	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M				
....4	G101	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M				
....4	G101	3301-001593	CORE-FERRITE BEAD;AB,200OHM,2.0X1.2X1.3M				
....4	DR705	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608				
....4	DR708	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608				
....4	DR503	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608				
....4	DR505	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608				
....4	DR507	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608				
....4	DR521	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608				
....4	DR522	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608				
....4	0	AA41-00793B	PCB;HCN473,PCB-DVI,2L,1.6T,245*180,P55A,	S.N.A			
....4	0202-001167	SOLDER-CREAM;RX3603-2330HO,S45A,PASTE,SN	S.N.A				
....3	CN906	3711-003641	CONNECTOR-HEADER-BOX,12P,1R,2.5mm,STRAIG				
....3	T0121	3301-001201	CORE-FERRITE;AE,21x11x32mm,1500,280G				
....3	AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A				
....3	IC112	1103-001211	IC-EEPROM;24C16-PC27 C,2048x8Bit,DIP,8P,				
....3	T0076	AA39-20032B	LEAD CONNECTOR-ASSY;,12P,300,67096-012,S				
....3	PL1	3701-001173	CONNECTOR-DSUB;24P,3R,FEMALE,ANGLE,AUF				

ASSY ACCESSORY

1	M0016	BP92-00512C	ASSY ACCESSORY;HCN553WX/XAA,P55A,DVI	S.N.A
..2	6902-000018	BAG PE;LDPE,TO.1,W280,L400,GRY,8,2-	S.N.A	
..2	T0116	AA39-00006A	CABLE RCA;,3000MM	
..2	T0074	AA59-00262A	REMOCON;,TM63,COMMONDO,48,G6671B,EX,S/S	
..3	T0122	2802-000194	RESONATOR-CERAMIC;8MHz,1.0%,TP,8.5x4.5x5	
..3	T0119	AA09-00275A	IC MICOM;Z86L8808SSC-R51PX,SOP,ST,SZTM-8	
..2	T0113	AA61-20126A	HOLDER-LEG;-ABS,-,-,BLK,HB	
..2	AA68-00371C	CARD WARRANTY-01;,SEA,W/P100(G),1 YEAR	S.N.A	
..2	AA68-40065B	CARD-REGISTRATION;,SEA,A5,ENG,A/P220,2P(S.N.A	
..2	AA69-30009C	BAG-SHEET;LDPE,TO.08,W150,L120,-,-,-	S.N.A	
..2	CIS	BP68-00054A	MANUAL USERS;HCM473WJX,ENG,W/P100G,P55A,	

ASSY P/MATERIAL

1	BP92-00542A	ASSY P/MATERIAL;,P55A	S.N.A
..2	AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A
..2	AA61-20285A	HOLDER-BOX;3456,PP,-,-,WHT,VO	S.N.A
..2	AA63-10007C	BAND-PP;W18,CLEA,1G	S.N.A
..2	AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
..2	AA69-00744L	BAG-SHEET;-HDPE PE FOAM,TO.015,W1650,H1	S.N.A

ASSY FIXING

1	BP91-00833Q	ASSY FIXING;HCN436WX/XAA,P55A	S.N.A	
..2	T0081	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
..2	T0081	6003-001023	SCREW-TAPTITE;RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
..2	T0076	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,500,YFH800-01,S,	
..2	T0076	AA39-20010B	LEAD CONNECTOR-ASSY;,1P,500,YFH800-01,S,	
..2	T0070	AA61-01127A	HOLDER-CHASSIS;COMMANDO,HIPS V0,G4309	S.N.A
..2	AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A	
..2	AA65-30018A	CLAMPER CORE-WIRE-DONG-A,NYLON-66,-,-,-,	S.N.A	
..2	AA65-30111A	CLAMPER CORE-WIRE;ALL MODEL,NYLON,V0,-,-,S.N.A		
..2	T0066	AA96-00156A	ASSY POWER CORD;-EP2/YES(US),H/C100MM,K	
..3	3811-000401	WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A	
..3	T0077	AA39-10007Y	CBF POWER CORD;-EP2/YES,SPT-2 18AWGx2C,	
..3	AA61-20284A	HOLDER-P-CORD,PP,-,-,BLK,VO,KE-002	S.N.A	
..3	AA63-10002B	BAND-TIE;NYLON66 V2,L140,NTR	S.N.A	
..3	T0121	3301-001201	CORE-FERRITE;AE,21x11x32mm,1500,280G	
..2	BP39-00047A	LEAD CONNECTOR;P55A/HCM4215W,UL2547#26,U		

You can search for the updated part code through ITSELF web site.
 URL : http://itself.sec.samsung.co.kr

7-2 HCN4226W3S/XAA

Loc. No.	Code No.	Description ; Specification	Remark
ASSY SKD PART			
1	AA92-07170A	ASSY SKD PART;HCN653WSC/XAA,P55A	S.N.A
..2	T0118	AA26-00101A TRANS FBT-H/V DISTRIBUTOR;FWZ50A001E/FFA	
..2		AA63-10002A BAND-TIE:NYLON66 V2,L100,NTR	S.N.A
..2		AA65-30018A CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	S.N.A
..2		AA65-30104C CLAMPER CORE-WIRE:ALL MODEL,NYLON 66,V2,S.N.A	S.N.A
△..2	T0066	AA96-00156A ASSY POWER CORD;-EP2/YES(US),H/C100MM,K	
...3		3811-000401 WIRE-PVC CU-BCWA,300V,ROLL,17/0.16mm,#22	S.N.A
...3	T0077	AA39-10007Y CBF POWER CORD;-EP2/YES,SPT-2 18AWGx2C,	
...3		AA61-20284A HOLDER;P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A
...3		AA63-10002B BAND-TIE:NYLON66 V2,L140,NTR	S.N.A
...3	T0121	3301-001201 CORE-FERRITE;AE,21x11x32mm,1500,280G	

ASSY K/D-SKD P/MATERIAL

1	AA98-01629A	ASSY K/D-SKD P/MATERIAL;SKD FORMAT-3	S.N.A
..2	AA69-00305A	BAG AIR;ALL,LDPE,1000,500,CLR,	S.N.A
..2	AA69-00306A	BAG AIR;LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
..2	AA69-90001A	CHEMICALS-SILICAGEL;-,-,-,-,-,M2,5GR,-,-	S.N.A
..2	AA60-40006A	PIN-STAPLE;AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A
..2	WOODENA63-10007C	BAND-PP;W18,CLEA,1G	S.N.A

ASSY COVER FRONT

1	M0001	BP90-00152B	ASSY COVER FRONT;HCN4226W3S/XAA,P55A	S.N.A
..2	T0081	6003-001023	SCREW-TAPTITE;RWH,+B,M3,L10,ZPC(YEL),SW	S.N.A
..2	T0081	6003-001339	SCREW-TAPTITE;HH,+B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	HC+CW	6005-001003	SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18AS.N.A	S.N.A
..2	HC+CW	6005-001003	SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18AS.N.A	S.N.A
..2	HC+CW	6005-001003	SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18AS.N.A	S.N.A
..2	BCM+W06	6006-001094	SCREW-ASS'Y WOOD;WWW,HH,+M7,L32,ZPC(YEL),S.N.A	S.N.A
..2	T0118	AA26-00101A	TRANS FBT-H/V DISTRIBUTOR;FWZ50A001E/FFA	
..2		AA60-00072B	SPACER-COVER;DUST;43,54,62J9,SPONGE 94HF	S.N.A
..2	T0069	AA60-00091J	SPACER-FELT;-FELT,330X10,-,-,BLK,TO,5,-	S.N.A
..2	T0081	AA60-10011A	SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A
..2	T0081	AA60-10011A	SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A
..2	T0081	AA60-10011A	SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A
..2	T0115	AA61-00475B	BRACKET-CRT;MAIN;54,SECC,T1,6,-,-,-,-	
..2		AA61-00618C	GUIDE-FLOW;54J8,J7,ABS,IVORY,VO	S.N.A
..2		AA63-10002A	BAND-TIE:NYLON66 V2,L100,NTR	S.N.A
..2		AA65-00020A	CLAMPER CORE-WIRE;55W9,NYLON 66	S.N.A
..2	T0056	AA67-00193A	SCREEN-TINT;42W,958*550,T=0.7,P	
..2	T0053	AA67-00193B	SCREEN FRESNEL;42W,960*552,T=2.0	
..2	T0052	AA67-00207A	SCREEN-FILTER;T=82%,9,G=110,AG	
..2		BH73-60304C	RUBBER-SUPPORT;DP15LT,CR VO,GRAY,-,14*7*	S.N.A
..2	T0076	BP39-00009A	LEAD CONNECTOR-ASSY;P54A/SVP-42W5,UL2547	
..2	T0254	BP61-00010A	BRACKET-SCREEN,TB;DP,42W5,AA61-01121A,26	S.N.A
...3	T0254	AA61-01121A	BRACKET-SCREEN,TB;42W5,SECC,T1,0	S.N.A
..2	T0056	BP61-00011A	BRACKET-SCREEN,RL;DP,42W5,AA61-01122A,13	S.N.A
...3	T0056	AA61-01122A	BRACKET-SCREEN,RL;42W5,SECC,T1,0	S.N.A
..2		BP61-00043B	HOLDER-SENSOR;W9,PC HB,VIOLET	S.N.A
..2		BP61-00052A	HOLDER-WIRE;PJT,V,NYLON,66,NATURAL	S.N.A
..2		BP64-00029A	INLAY-SUPPORT;42W5,PS SHEET,TO,5,94V0	S.N.A
..2	T0102	BP73-00004A	RUBBER-CAP;42W5,SILICONE,WHT,RUBBER	
..2		BP98-00189A	ASSY K/D-FRONT MASK;42W8	S.N.A
...3	T0081	6003-001019	SCREW-TAPTITE;RH,+B,M4,L12,ZPC(BLK),SWR	S.N.A
...3		AA61-01133A	VELCRO-B-COMMANDO,BST1 1/4H	S.N.A
...3	T0017	AA64-02727R	CABINET-FRONT MASK;42W8,HIPS,HB,GRY,SV01	
...3	T0057	BP64-00199A	BADGE-BRAND;PJLCD,AL,T1,5,72,12,5,-,DGN-S	S.N.A
...3	T0102	BP73-00004A	RUBBER-CAP;42W5,SILICONE,WHT,RUBBER	S.N.A
..2		BP98-00190A	ASSY K/D-FRONT BOT;42W8	S.N.A
...3	T0081	6003-001019	SCREW-TAPTITE;RH,+B,M4,L12,ZPC(BLK),SWR	

Loc. No.	Code No.	Description ; Specification	Remark	
...3	T0081	6003-001019	SCREW-TAPTITE;RH,+B,M4,L12,ZPC(BLK),SWR	
...3	T0081	6003-001019	SCREW-TAPTITE;RH,+B,M4,L12,ZPC(BLK),SWR	
...3		AA61-01132A	VELCRO-A-COMMANDO,BST1 1/4H	S.N.A
...3		AA61-20129A	HOLDER-WIRE;-NYLON-66,-,-,-,NTR,DAFC-25	S.N.A
...3	CIS7	AA61-60003A	SPRING ETC-CS;-SUS304,-,-,OD7,N7,OD7,-,	S.N.A
...3		BP61-00272A	HOLDER-PCB POWER;42W8,ABS,SMOG,6G	S.N.A
...3		BP61-00273A	HOLDER-RING;42W8,ABS,GRAY,AL	S.N.A
...3		BP64-00230A	CABINET FRONT-BOT;42W8,HIPS VO,GRAY,SV70	S.N.A
...3	T0023	BP64-00231A	KNOB POWER;42W8,ABS,HB,GRAY,AL	S.N.A
...3		BP64-00232A	WINDOW-RMC;42W8,ABS,HB,CLEAR	S.N.A
...3	T0022	BP64-00233A	KNOB CONTROL;42W8,ABS,HB,GRAY,SVM1132	S.N.A
..2		BP98-00191A	ASSY K/D-WOOD;42W8,WOOD	S.N.A
...3	T0082	3001-001107	SPEAKER;20W,80HM,95DB,1300HZ	
...3	T0082	3001-001353	SPEAKER;25W,80HM,90DB+,-,3DB,60HZ+/-12HZ	
...3	T0076	AA39-00086A	LEAD CONNECTOR-ASSY;2.2UF,200MM,REC,REC	
...3	HC+CW	AA60-10051A	SCREW-WOOD;-SWRCH18A,M4,L16,PH,+,-,-,ZP	S.N.A
...3		AA61-00094C	HOLDER-RAIL;PCJ533R,ABS,-,-,-,BLK,HB,480	S.N.A
...3		AA61-00097A	HOLDER-WIRE;-NYLON 6/6,-,-,-,NTR,-	S.N.A
...3		AA61-00508D	HOLDER-JERSEY;W3,ABS VO,GRAY,G4309	S.N.A
...3		AA61-00533B	BRACKET-GRILLE;43,54,62J8,SECC-1,TO,5,-	S.N.A
...3		AA61-00616B	HOLDER-CRT;MAIN;54J7,DP,-,-,-,AA61-005	S.N.A
...4		AA61-00506B	HOLDER-CRT;MAIN;43,54,62J8,HIPS,-,-,-,BL	S.N.A
...3		AA64-02724A	CABINET-WOOD;42W5,WOOD,SDE8336R	S.N.A
...3		AA98-00049A	ASSY-LEAD,CON;-LEAD-CON,CORE,AA39-20505	S.N.A
...4	T0121	3301-001201	CORE-FERRITE;AE,21x11x32mm,1500,280G	
...3		BP61-00019A	HOLDER-PALLET;42W5,HIPS HB,BLK	S.N.A
...3		BP61-00035A	BRACKET-GRILLE;42W5,SECC-1,T1,0	S.N.A

ASSY COVER REAR

1	M0002	BP90-00155B	ASSY COVER REAR;HCN4226W3S/XAA,P55A	S.N.A
..2	T0081	6003-001026	SCREW-TAPTITE;RH,+B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	T0081	6003-001026	SCREW-TAPTITE;RH,+B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	T0081	6003-001026	SCREW-TAPTITE;RH,+B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	T0081	6003-001026	SCREW-TAPTITE;RH,+B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	T0081	6003-001026	SCREW-TAPTITE;RH,+B,M4,L15,ZPC(BLK),SWR	S.N.A
..2	HC+CW	6005-001003	SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18	S.N.A
..2	HC+CW	6005-001003	SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18AS.N.A	S.N.A
..2	T0081	AA60-10011A	SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A
..2	T0081	AA60-10011A	SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A
..2	T0081	AA60-10011A	SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A
..2	T0081	AA60-10011A	SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A
..2	T0112	AA64-02728A	CABINET-BACK,TOP;42W5,HIPS,HB,G4309	
..2	T0112	AA64-02729B	CABINET-BACK,BOT;42W5,HIPS,VO,G4309	
..2		AA64-60421C	INLAY-COVER;-PS,TO,3,-,-,BLK,SEA	S.N.A
..2		AA64-60449B	INLAY-COVER;SP-434JMF,PS,TO,5,149.3X69.5	S.N.A
..2		AA65-30008A	CLAMPER CORE-CORD;-PE,HB,-,BLK,-	S.N.A
..2		AA67-00204A	MIRROR-FRONT;42W5,FSM,870*633*446	
..2		BP61-00012A	BRACKET-MIRROR;DP,42W5,AA61-01123A,11.8K	S.N.A
..2		AA61-01123A	BRACKET-MIRROR;42W5,SECC,T1,0	S.N.A
..2		BP60-00005A	SPACER-SPONGE;42W5,RUBBER-SPONGE,T3	S.N.A
..2	T0092	BP96-00077L	ASSY COVER P-TERMINAL,ANT;DP WIDE PJT,HI	
..2	T0092	BP96-00038H	ASSY COVER P-TERMINAL,ANT;WIDE PJT,HIPS	
...4		AA64-02836J	INLAY-TERMINAL,NT;WIDE PJT,PS SHEET,TO,5	S.N.A
...4		AA65-00023A	TERMINAL-BOARD,ANT;HIPS VO,BLK	S.N.A

ASSY CHASSIS

1	M0017	BP91-00935A	ASSY CHASSIS;HCN4226WS,P55A,KAWA	S.N.A
..2		BP91-00801Y	ASSY MISC-CHASSIS PACK;HCN4226W,P55A,KAW	
..2	S.N.A			
...3	T0081	6003-001023	SCREW-TAPTITE;RWH,+B,M3,L10,ZPC(YEL),SW	S.N.A
...3	T0081	6003-001023	SCREW-TAPTITE;RWH,+B,M3,L10,ZPC(YEL),SW	S.N.A
...3	T0070	AA61-01127A	HOLDER-CHASSIS;COMMANDO,HIPS VO,G4309	S.N.A
...3	T0097	AA94-08574A	ASSY PCB MISC-PWR-DEF;-H,HCMA215W,P55A	

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark
.....5	R125	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000613	R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000613	R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000761	R-CARBON:4300HM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000761	R-CARBON:4300HM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000761	R-CARBON:4300HM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000761	R-CARBON:4300HM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000761	R-CARBON:4300HM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000800	R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000800	R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-000924	R-CARBON:6800HM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	R125	2001-001031	R-CARBON:91KOHM,5%,1/8W,AA,TP,1.8X3.2MM
.....5	RS807	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	R854	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	R839	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	R413	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	RR401S	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	R434	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	R837	2001-001108	R-CARBON(S):22KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	R468	2001-001122	R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	RS802	2001-001124	R-CARBON(S):3.9OHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	R433	2001-001155	R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	R410	2001-001155	R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	RS806	2001-001168	R-CARBON(S):6.8KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	R459	2001-001192	R-CARBON(S):8200HM,5%,1/2W,AA,TP,2.4X6.4M
.....5	R851	2001-001196	R-CARBON(S):9.1KOHM,5%,1/2W,AA,TP,2.4X6.4M
.....5	RP801S	2002-001010	R-COMPOSITION:1.8Mohm,5%,1/2W,AA,TP,3.7x
.....5	RY801S	2002-001013	R-COMPOSITION:4.7Mohm,5%,1/2W,AA,TP,3.7x
.....5	R428	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9
.....5	R428A	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9
.....5	R429	2003-000586	R-METAL OXIDE(S):22Kohm,5%,2W,AF,TP,4x12
.....5	R430	2003-000586	R-METAL OXIDE(S):22Kohm,5%,2W,AF,TP,4x12
.....5	R463	2003-001024	R-METAL OXIDE(S):150ohm,5%,2W,AF,TP,3.9x
.....5	R310	2003-001024	R-METAL OXIDE(S):150ohm,5%,2W,AF,TP,3.9x
.....5	R460	2003-002044	R-METAL OXIDE(S):100ohm,5%,1W,AF,TP,2.5x
.....5	R426	2003-002153	R-METAL OXIDE:4.70HM,5%,2W,AG,TP,6X16MM
.....5	R443A	2003-002156	R-METAL OXIDE:5600HM,5%,2W,AG,TP,6X16MM
.....5	R443	2003-002156	R-METAL OXIDE:5600HM,5%,2W,AG,TP,6X16MM
.....5	R464	2003-002158	R-METAL OXIDE:0.680HM,5%,1W,AG,TP,4.3X12
.....5	R421	2003-002159	R-METAL OXIDE:1500HM,5%,1W,AG,TP,4.3X12M
.....5	R024	2004-001369	R-METAL(S):1.2Kohm,1%,1/2W,AA,TP,2.4x6.4
.....5	R024	2004-001386	R-METAL(S):16.9Kohm,1%,1/2W,AA,TP,2.4x6.4
.....5	R024	2004-001395	R-METAL(S):330Kohm,2%,1/2W,AA,TP,2.4x6.4
.....5	R024	2004-001408	R-METAL(S):91Kohm,1%,1/2W,AA,TP,2.4x6.4m
.....5	R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5
.....5	R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5
.....5	R024	2004-001897	R-METAL(S):43.2Kohm,1%,1/2W,AA,TP,2.5x6.5
.....5	R024	2004-001897	R-METAL(S):43.2Kohm,1%,1/2W,AA,TP,2.5x6.5
.....5	R024	2004-001984	R-METAL(S):26.7Kohm,1%,1/2W,AA,TP,2.4x6.4
.....5	R024	2004-001984	R-METAL(S):26.7Kohm,1%,1/2W,AA,TP,2.4x6.4
.....5	R024	2004-002011	R-METAL(S):110Kohm,1%,1/2W,AA,TP,2.4x6.4
.....5	R024	2004-004001	R-METAL(S):180Kohm,1%,1/2W,AA,TP,2.5x6.5
.....5	R024	2004-004046	R-METAL(S):430Kohm,1%,1/2W,AA,TP,2.5x6.5
.....5	R024	2004-004046	R-METAL(S):430Kohm,1%,1/2W,AA,TP,2.5x6.5
.....5	R024	2004-004366	R-METAL(S):1.3Kohm,1%,1/2W,AA,TP,2.5x6.5
.....5	R472	2008-000252	R-FUSIBLE(S):0.47ohm,10%,1/2W,AF,TP,2.5x
.....5	R465	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
.....5	R449	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
.....5	R445	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
.....5	R442	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
.....5	R441	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
.....5	R447	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
.....5	R442A	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m
.....5	R307	2008-000290	R-FUSIBLE(S):2.4ohm,5%,2W,AF,TP,3.9x10mm
.....5	R486	2008-001018	R-FUSIBLE(S):0.47ohm,10%,2W,AF,TP,3.9x10
.....5	R838	2008-001053	R-FUSIBLE:22ohm,5%,1/2W,AF,TP,2.5x6.5mm
.....5	R437	2008-001087	R-FUSIBLE(S):1.8ohm,5%,2W,AG,TP,3.9x12mm
.....5	R485	2008-001137	R-FUSIBLE(S):3.3ohm,5%,1W,AF,TP,3.9x10mm



Loc. No.	Code No.	Description ; Specification	Remark
.....5	R405	2009-001109	R-TEMPERATURE:240ohm,5%,1/4W,AA,TP,2.3x6
.....5	RR471S	2103-001024	VR-SEMI:50Kohm,25%,0.3W,TOP
.....5	RR402S	2103-001086	VR-SEMI:100KOHM,25%,0.3W,TOP
.....5	C598	2201-000119	C-CERAMIC, DISC:100NF,+80-20%,50V,Y5V,TP,
.....5	C598	2201-000119	C-CERAMIC, DISC:100NF,+80-20%,50V,Y5V,TP,
.....5	C598	2201-000119	C-CERAMIC, DISC:100NF,+80-20%,50V,Y5V,TP,
.....5	C598	2201-000119	C-CERAMIC, DISC:100NF,+80-20%,50V,Y5V,TP,
.....5	C598	2201-000132	C-CERAMIC, DISC:0.1NF,10%,500V,Y5P,TP,6.5
.....5	C598	2201-000132	C-CERAMIC, DISC:0.1NF,10%,500V,Y5P,TP,6.5
.....5	C598	2201-000132	C-CERAMIC, DISC:0.1NF,10%,500V,Y5P,TP,6.5
.....5	C598	2201-000132	C-CERAMIC, DISC:0.1NF,10%,500V,Y5P,TP,6.5
.....5	C598	2201-000138	C-CERAMIC, DISC:0.1NF,10%,50V,Y5P,TP,4X4M
.....5	C598	2201-000146	C-CERAMIC, DISC:0.1NF,5%,50V,SL,TP,5X3.5M
.....5	C598	2201-000146	C-CERAMIC, DISC:0.1NF,5%,50V,SL,TP,5X3.5M
.....5	C598	2201-000180	C-CERAMIC, DISC:10NF,10%,50V,Y5V,TP,7X3MM
.....5	C598	2201-000180	C-CERAMIC, DISC:10NF,10%,50V,Y5V,TP,7X3MM
.....5	C598	2201-000180	C-CERAMIC, DISC:10NF,10%,50V,Y5V,TP,7X3MM
.....5	C598	2201-000017	C-CERAMIC, DISC:1NF,10%,50V,Y5P,TP,5X3.5M
.....5	C598	2201-000017	C-CERAMIC, DISC:1NF,10%,50V,Y5P,TP,5X3.5M
.....5	C598	2201-000332	C-CERAMIC, DISC:2.2NF,20%,250V,Y5U,TP,9X4
.....5	C598	2201-000332	C-CERAMIC, DISC:2.2NF,20%,250V,Y5U,TP,9X4
.....5	C598	2201-000332	C-CERAMIC, DISC:2.2NF,20%,250V,Y5U,TP,9X4
.....5	C598	2201-000370	C-CERAMIC, DISC:0.22NF,10%,50V,Y5P,TP,4X3
.....5	C598	2201-000406	C-CERAMIC, DISC:0.22NF,10%,2KV,Y5P,TP,6.3
.....5	C598	2201-000551	C-CERAMIC, DISC:0.47NF,10%,1KV,Y5P,TP,6.3
.....5	C598	2201-000551	C-CERAMIC, DISC:0.47NF,10%,1KV,Y5P,TP,6.3
.....5	C598	2201-000551	C-CERAMIC, DISC:0.47NF,10%,1KV,Y5P,TP,6.3
.....5	C598	2201-000551	C-CERAMIC, DISC:0.47NF,10%,1KV,Y5P,TP,6.3
.....5	C598	2201-000551	C-CERAMIC, DISC:0.47NF,10%,1KV,Y5P,TP,6.3
.....5	C478	2301-000020	C-FILM,PEF:27nF,5%,100V,TP,7.3x4x12.5mm,
.....5	C479	2301-000200	C-FILM,PEF:2.2nF,5%,200V,TP,11.0x6.0x9.0
.....5	C477	2301-000213	C-FILM,PEF:220nF,5%,250V,TP,21.5x11.7,5
.....5	CS801	2301-000356	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5m
.....5	C493	2301-000356	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5m
.....5	C412	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm
.....5	C831	2301-001216	C-FILM,PPF:47nF,5%,630V,TP,20x14.5x22.7,
.....5	C460	2303-000331	C-FILM,PPF:4.7nF,5%,630V,TP,19.5x12x7.7,
.....5	C311	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5
.....5	C487	2305-000178	C-FILM,MPEF:10nF,5%,100V,TP,-5mm
.....5	C309	2305-000285	C-FILM,MPEF:220nF,5%,100V,TP,10.5x5.5x15
.....5	C838	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,-5mm
.....5	C865	2305-000427	C-FILM,MPEF:47nF,5%,100V,TP,7.5x12.5x3.5
.....5	C303	2305-000427	C-FILM,MPEF:47nF,5%,100V,TP,7.5x12.5x3.5
.....5	C301	2305-000427	C-FILM,MPEF:47nF,5%,100V,TP,7.5x12.5x3.5
.....5	C429	2305-000704	C-FILM,MPEF:100nF,5%,250V,TP,16.5x10.3x5
.....5	C428	2306-000122	C-FILM,MPPF:100nF,5%,630V,TP,20x14.5x22.7,
.....5	C480	2306-000122	C-FILM,MPPF:100nF,5%,630V,TP,20x14.5x22.7,
.....5	C701	2401-000164	C-AL:100uF,20%,25V,WT,TP,12.5x20.5
.....5	C701	2401-000262	C-AL:100uF,20%,160V,HR,TP,16x25,7.5
.....5	C701	2401-000262	C-AL:100uF,20%,160V,HR,TP,16x25,7.5
.....5	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5
.....5	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5
.....5	C701	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5
.....5	C701	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5
.....5	C701	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12.5mm,
.....5	C701	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12.5mm,
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5
.....5	C701	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,2
.....5	C701	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5
.....5	C701	2401-000703	C-AL:2200uF,20%,25V,GP,-12.5x25mm,
.....5	C701	2401-001026	C-AL:3.3uF,20%,50V,GP,TP,5x11,5
.....5	C701	2401-001026	C-AL:3.3uF,20%,50V,GP,TP,5x11,5
.....5	C701	2401-001192	C-AL:33uF,20%,160V,HR,TP,6.3x11,5
.....5	C701	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5
.....5	C701	2401-001428	C-AL:470uF,20%,50V,GP,TP,10x20,5
.....5	C701	2401-001527	C-AL:47uF,20%,250V,HR,TP,13x25mm,5m
.....5	C701	2401-001622	C-AL:6.8uF,20%,50V,BP,TP,16x25mm,7.
.....5	C701	2401-000025	C-AL:100uF,20%,16V,GP,TP,6.3x11,5
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5
.....5	C701	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5
.....5	C701	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5
.....5	C701	2401-002216	C-AL:2200uF,20%,35V,GP,TP,16x25,7.5
.....5	C701	2401-002216	C-AL:2200uF,20%,35V,GP,TP,16x25,7.5
.....5	C701	2401-000050	C-AL:10uF,20%,16V,GP,TP,5x11,2,5
.....5	C701	2401-002288	C-AL:470uF,20%,25V,WT,TP,10x20,5

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5	EY130	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A5	R832	2003-000512 R-METAL OXIDE(S):15Kohm,5%,3W,AA,TP,6x16	
.....5	EY83	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A5	R425	2003-000417 R-METAL OXIDE(S):1.2Kohm,5%,3W,AA,TP,6x1	
.....5	EY84	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A5	R853	2008-001152 R-FUSIBLE(S):1.3KOHM,5%,1/2W,AA,TP,2.5X6	
.....5	EY32	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A5	0	AA41-00598D PCB-SUB:HCM4215W,CEM-1,1L,D,1.6T,330X245	S.N.A
.....5	EY37	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A5	R024	2004-005051 R-METAL(S):2.2KOHM,1%,1/2W,AA,TP,2.4X6.4	
.....5	EY38	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A	△	RS801S	3601-000102 FUSE-AXIAL LEAD:125V,1A,FAST-ACTING,GLAS	
.....5	EY52	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	R840	2001-001045 R-CARBON(S):1.2KOHM,5%,1/2W,AA,TP,2.4X6.	
.....5	EY53	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	R841	2003-002102 R-METAL OXIDE(S):68Kohm,5%,2W,AF,TP,4x12	
.....5	EY54	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	R024	2004-004029 R-METAL(S):10Kohm,1%,1/2W,AA,TP,2.5x6.5m	
.....5	EY55	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	R801	2003-002285 R-METAL OXIDE(S):1.5KOHM,5%,2W,AF,TP,6X1	
.....5	EY51	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	DZ016	0403-000698 DIODE-ZENER:TZP12A,12V,11.4-12.6V,1W,DO-	
.....5	EY42	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	Q409	0505-001723 FET-SILICON:FQP630TSTU,N,200V,9A,0.40OHM,	
.....5	EY41	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	Q409	0505-001723 FET-SILICON:FQP630TSTU,N,200V,9A,0.40OHM,	
.....5	EY40	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	Q431	BH99-00033H ASSY HEAT/SINK:BH62-00038A,SPRING,FJL692	S.N.A
.....5	EY63	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	T0083	0402-001296 DIODE-RECTIFIER:FMP-3FU,1.5KV,5A,TO-3PF,	
.....5	EY62	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	T0060	BH61-70003A SPRING ETC:CVT4857,STS304-W1/2H,W3.8,-L	S.N.A
.....5	EY61	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	T0090	0502-001230 TR-POWER:FJL6920YDTU,N,200000MV,TO-264 F	
.....5	EY60	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	CIS	BH62-00038B HEAT SINK-FBT-COMMANDO,A1050S,T2.0,85*80	S.N.A
.....5	EY59	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	CIS	BH73-00028A SILICON/RUBBER-HS:CDT ALL,SILICON,26*33*	S.N.A
.....5	EY58	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A5	CIS	0205-001027 OIL-SILICON:G746,-,-	S.N.A
.....5	EY57	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△	TS801S	BP26-00001A TRANS SWITCHING-POWER:19B012,P55A,HCM421	
.....5	EY56	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△	PC801S	0604-001032 PHOTO-COUPLER:TR,170-260%,300mW,DIP-4,ST	
.....5	EL08	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△	PC811S	0604-001032 PHOTO-COUPLER:TR,170-260%,300mW,DIP-4,ST	
.....5	EL07	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	DU410	1201-000191 IC-OP AMP:4558,DIP,8P,300ML,DUAL,20V/mv	
.....5	EL06	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	T0086	1203-000610 IC-PWM CONTROLLER:494,DIP,16P,300ML,PLA	
.....5	EL05	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	IC851	1203-001400 IC-POWER PRESCALER:SE110N,TO-220(SIP),3P	
.....5	EL04	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	C598	2201-000446 C-CERAMIC,DISC:3.3NF,20%,400V,Y5U,TP,15X	
.....5	EL03	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	C598	2201-000446 C-CERAMIC,DISC:3.3NF,20%,400V,Y5U,TP,15X	
.....5	EL02	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	C598	2201-000446 C-CERAMIC,DISC:3.3NF,20%,400V,Y5U,TP,15X	
.....5	EL01	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	C598	2201-000446 C-CERAMIC,DISC:3.3NF,20%,400V,Y5U,TP,15X	
.....5	EY39	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△	CR471S	2301-001091 C-FILM,MPPF:470nF,5%,400V,TP,26x21.5x14.	
.....5	EL16	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△	CR436S	2306-000235 C-FILM,MPPF:560nF,5%,400V,TP,26*22.5*14,	
.....5	EL15	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	C491	2306-000322 C-FILM,MPPF:12nF,5%,1.6KV,TP,29x20.5x13,	
.....5	EL14	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△	CR473S	2306-000322 C-FILM,MPPF:12nF,5%,1.6KV,TP,29x20.5x13,	
.....5	EL10	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△	CR474S	2306-000326 C-FILM,MPPF:4.7nF,5%,1.6KV,TP,28.5x16x9m	
.....5	EL11	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	L862	AA27-10001C COIL CHOKE,-,100uH,K,-,5.0A,ST,700UH-K(R	
.....5	EL12	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A4	L863	AA27-10001C COIL CHOKE,-,100uH,K,-,5.0A,ST,700UH-K(R	
.....5	EL13	6042-000001 EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A	△	LX801S	AA29-30002L FILTER LINE NOISE:-,10mHMIN,5A,AC90-260V	
.....5	GT35	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A	△	LX802S	AA29-30002M FILTER LINE NOISE:-,1mHMIN,5A,AC90-260V,	
.....5	GT34	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A	△	LX803S	AA29-30002M FILTER LINE NOISE:-,1mHMIN,5A,AC90-260V,	
.....5	GT33	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A	△	LX804S	AA29-30002M FILTER LINE NOISE:-,1mHMIN,5A,AC90-260V,	
.....5	GT404	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A4	C701	2401-000142 C-AL:1000uF,20%,16V,WT,TP,10x20.5	
.....5	GT801	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A4	L864	AA27-10002L COIL CHOKE,-,24uH,K,-,2A,-,24UH-K,10x10mm	
.....5	GT802	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A4	T0086	1203-002177 IC-PWM CONTROLLER:VIPER12ADIP,DIP,8P,300	
.....5	GT810	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A	△	IC421	AA96-00475B ASSY H/S:SILICON-OIL,FMLG-12S(4),AA62-00	S.N.A
.....5	GT811	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A5	0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A
.....5	GT14	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A5	T0083	0402-000233 DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	
.....5	GT15	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A5	IC012	1203-000165 IC-POSI.ADJUST REG:-78R12,TO-220,4P,-,PL	
.....5	GT16	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A5	T0081	6003-000334 SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR	
.....5	GT17	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A5	AA62-00066B	HEAT SINK:D2,D3,AL, T1.0,89,70,-,AA62-00	S.N.A
.....5	GT807	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A4	C814	2301-001041 C-FILM,PPF:15nF,5%,1.6KV,TP,29x14x21.5.2	
.....5	GT433	AA60-40014A PIN-GT,ASSY:AUTO	S.N.A4	DZS801	0406-001007 DIODE-TVS:P6KE180A,171/180/189V,600W,CAS	
.....5	T0083	0402-001286 DIODE-RECTIFIER:RP1H,2000V,1A,-,TP	S.N.A	△	T801S	BP26-00002A TRANS SWITCHING:EER5345,P55A,160V-280V,P	
.....5	R024	2004-001893 R-METAL(S):22Kohm,1%,1/2W,AA,TP,2.5x6.5m		△	CR430S	2301-001343 C-FILM,MPPF:3.9nF,5%,2KV,TP,29x9.5x16mm,	
.....5	R024	2004-001402 R-METAL(S):6.8Kohm,1%,1/2W,AA,TP,2.4x6.4		△	CR431S	2301-001343 C-FILM,MPPF:3.9nF,5%,2KV,TP,29x9.5x16mm,	
.....5	R462	2008-001145 R-FUSIBLE:4.7OHM,5%,1/2W,AF,TP,2.5X6.5MM		△	T432	AA26-00053A TRANS:-,-,1.2mH,-,-,-,-,-,31.5KHZ,-,	
.....5	R125	2001-000745 R-CARBON:4.7OHM,5%,1/8W,AA,TP,1.8X3.2MM	4	T0076	BP39-00014A LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL1007	
.....5	C701	2401-002619 C-AL:47uF,20%,25V,GP,TP,5x11,5	4	T0121	3301-001201 CORE-FERRITE:AE,21x11x32mm,1500,280G	
.....5	C701	2401-001655 C-AL:680uF,20%,25V,GP,TP,10x20,5	4	T0090	0502-000405 TR-POWER:-,NPN,70W,TO-220,BK,10	
.....5	C871	2305-000289 C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	4	T0123	1203-001006 IC-VOLTAGE REGULATOR:78R05,TO-220F,4P,-,	
.....5	C701	2401-001486 C-AL:47uF,20%,160V,HR,TP,13x20mm,5m	5	BP39-00017A	LEAD CONNECTOR:P55A/HCM4215W,UL1617#22,U	
.....5	R431	2001-001153 R-CARBON(S):47OHM,5%,1/2W,AA,TP,2.4X6.4MM	5	T0121	3301-001201 CORE-FERRITE:AE,21x11x32mm,1500,280G	
.....5	G101	3301-000287 CORE-FERRITE BEAD-AA,3.5x1.0x6.0mm,1500,	4	GT01	AA60-40012D PIN-GT,ASSY:T1,6.6-12.5,-,NYLON66	S.N.A
.....5	R833	2009-000017 R-METAL PLATE:0.1ohm,10%,5W,CL,TP,5x14x1	4	CN906	3711-003043 CONNECTOR-HEADER:BOX,4P,1R,2.5MM,STRAIGH	
.....5	C701	2401-001625 C-AL:6.8uF,20%,50V,GP,TP,5x11,5	4	C598	2201-000963 C-CERAMIC,DISC:1NF,20%,400V,Y5U,TP,9.5X6	
.....5	FD802S	3601-001228 FUSE-AXIAL LEAD:125V,10A,FAST-ACTING,EPO	4	C598	2201-000963 C-CERAMIC,DISC:1NF,20%,400V,Y5U,TP,9.5X6	
.....5	FD855S	3601-001228 FUSE-AXIAL LEAD:125V,10A,FAST-ACTING,EPO	4	IC012	1203-000162 IC-POSI.ADJUST REG:-317,TO-220,3P,-,PLAS	
.....5	R306	2008-000107 R-FUSIBLE(S):1.8ohm,5%,2W,AF,TP,3.9x10mm	4	C701	2401-000787 C-AL:220uF,20%,160V,GP,TP,16x31.5mm	
.....5	R125	2001-000554 R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM		△	VX801S	1405-000187 VARISTOR:750V,1250A,12.5x7mm,TP	
.....5	R427	2003-002152 R-METAL OXIDE:10HM,5%,2W,AG,TP,6X16MM	4	C832	2301-001418 C-FILM,MPPF:1.5nF,5%,2KV,TP,29x7x13.5mm,	
.....5	R427A	2003-002152 R-METAL OXIDE:10HM,5%,2W,AG,TP,6X16MM	4	L432	AA27-00056A COIL HORIZ. WIDTH:-,600uH,YL9N 15x27.5 C	
.....5	C701	2401-000698 C-AL:2200uF,20%,16V,WT,TP,12.5x25,5	4	R384	2002-001079 R-COMPOSITION:470Kohm,5%,1/2W,AA,TP,4x10	
.....5	R424	2008-000289 R-FUSIBLE(S):1ohm,5%,1W,AA,TP,3.9x10mm	4	Q473	BP96-00006B ASSY HEAT SINK P:HS,SCREW,IRF640B,2SC412	S.N.A
.....5	C432	2303-000002 C-FILM,PPF:8.2nF 5% 400V TP 19X18X7,7.5m	5	CIS	0205-001027 OIL-SILICON:G746,-,-	S.N.A
.....5	C438	2303-000002 C-FILM,PPF:8.2nF 5% 400V TP 19X18X7,7.5m	5	T0090	0502-001100 TR-POWER:2SC4125,NPN,70W,TO-3PML,BK,8-	
.....5	R440	2008-000282 R-FUSIBLE:0.47ohm,5%,1W,AA,TP,3.9x12mm	5	Q409	0505-001722 FET-SILICON:IRFS640B,N,200V,18A,0.18OHM,	
.....5	R831	2003-000512 R-METAL OXIDE(S):15kohm,5%,3W,AA,TP,6x16	5	T0081	6003-000333 SCREW-TAPTITE:RH,+2S,M3,L10,ZPC(YEL),SW	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark
.....6	C120	2203-000236 C-CERAMIC,CHIP:0.1NF,5%,50V,COG,TP,1608	
.....6	C120	2203-000260 C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012	
.....6	C120	2203-000357 C-CERAMIC,CHIP:0.15NF,5%,50V,COG,TP,1608	
.....6	C120	2203-000440 C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-	
.....6	C120	2203-000440 C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-	
.....6	C120	2203-000440 C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-	
.....6	C120	2203-000444 C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
.....6	C120	2203-000748 C-CERAMIC,CHIP:0.03NF,5%,50V,COG,TP,2012	
.....6	C120	2203-001048 C-CERAMIC,CHIP:0.56NF,10%,50V,COG,TP,201	
.....6	C120	2203-005809 C-CERAMIC,CHIP:1000nF,10%,16V,X7R,TP,201	
.....6	C950	2402-000179 C-AL,SMD:47uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	C936	2402-001042 C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	C921	2402-001042 C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	C918	2402-001042 C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	C915	2402-001042 C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	C913	2402-001042 C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	C938	2402-001042 C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	
.....6	C917	2402-001049 C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	C912	2402-001049 C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	C911	2402-001049 C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4	
.....6	L905	2703-001245 INDUCTOR-SMD:8.2uH,10%,2x1.25x1.25mm	
.....6	G101	3301-001324 CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,	
.....6	G101	3301-001324 CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,	
.....6	G101	3301-001324 CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,	
.....6	G101	3301-001324 CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,	
.....6	G101	3301-001324 CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,	
.....6	G101	3301-001324 CORE-FERRITE BEAD:AB,150OHM,2X1.25X0.9MM,	
.....6	R949	2007-001167 R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6	R950	2007-001167 R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6	R951	2007-001167 R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6	R945	2007-001167 R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6	R946	2007-001167 R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6	R948	2007-001167 R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6	R966	2007-000931 R-CHIP:470ohm,5%,1/8W,TP,2012	
.....6	PCB	AA41-00599B PCB-MICOM:HCM4215W,FR-4,2L,B,1.6T,180X24	S.N.A
.....6		0202-001167 SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SNS.N.A	
.....5	IC902	1102-001130 IC-EPROM:M27W201-80F6,256KX8BIT,DIP,32P	
.....5	IC	0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1,2.63Sn/37Pb	S.N.A
.....4	IC801	AA96-00475C ASSY H/S:SILICON-OIL,KA278R09,KA7808,AA6	S.N.A
.....5		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A
.....5	T0087	1203-000293 IC-POSI.FIXED REG.:7808,TO-220,3P,-,PLAS	
.....5	T0123	1203-002003 IC-VOLTAGE REGULATOR:278R09,TO-220,4P,-	
.....5	T0081	6003-000334 SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR	
.....5		AA62-00066B HEAT SINK:D2,D3,AL,T1.0,89,70,-,AA62-00	S.N.A
.....5	T0123	1203-001978 IC-VOLTAGE REGULATOR:KA278RA05,TO-220F,4	
.....4	IC601	AA96-00623E ASSY H/S:SCREW,MAIN,AA62-00065A,TDA7265,S.N.A	
.....5		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A
.....5	T0124	1201-001026 IC-POWER AMP:7265,ZIP,11P,19.6MIL,DUAL,1	
.....5	T0081	6003-000334 SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR	
.....5		AA62-00056A HEAT SINK-PS:-,T1.0,-,41*35*70,D2,-, S.N.A	
.....4		BP39-00036A LEAD CONNECTOR:J54A/SP42W5HP,UL2547#26,U	
.....4		BP63-00030A SHIELD CASE:COMMANDO,SPT,TO.5,W26.0,113	S.N.A
.....4	T0095	BP95-00142N ASSY SUB PCB-PRO SCAN:HCM4272WX/XAA,P55A	
.....5		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1,2.63Sn/37Pb	S.N.A
.....5	FC48	2305-000011 C-FILM,MPEF:470nF,5%,250V,TP,21.5X13.0X7	
.....5	FC59	2305-000704 C-FILM,MPEF:100nF,5%,250V,TP,16.5x10.3x5	
.....5	FC58	2309-000138 C-FILM,PE-PPF:100nF,5%,50V,TP,20x16x8.5,	
.....5	EX01	2801-004019 CRYSTAL-UNIT:20.25MHz,30ppm,28-AAM,13pF,	
.....5	T0122	2802-001177 RESONATOR-CERAMIC:2.696MHZ,0.4%,BK,10X4,	
.....5	T0122	2802-001179 RESONATOR-CERAMIC:4MHZ,0.5%,BK,8X3X5.5MM	
.....5	CN02	3703-001124 CONNECTOR-BACK PANEL:32P,2R,MALE,ANGLE,A	
.....5	CN01	3703-001124 CONNECTOR-BACK PANEL:32P,2R,MALE,ANGLE,A	
.....5	CN906	3711-001164 CONNECTOR-HEADER:BOX,9P,1R,2.5mm,ANGLE,-	
.....5	CN906	3711-003601 CONNECTOR-HEADER:BOX,12P,1R,2.5mm,ANGLE,	
.....5		BP97-00169A ASSY SMD:HCM4215WJX/XAA,P55A	S.N.A
.....6	FD13	0401-000133 DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	FD14	0401-000133 DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	FD15	0401-000133 DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	FD16	0401-000133 DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	FD17	0401-000133 DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	FD10	0401-000133 DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	FD01	0401-000133 DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	FD02	0401-000133 DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	FD07	0401-000133 DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	FD08	0401-000133 DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	FD09	0401-000133 DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	

Loc. No.	Code No.	Description ; Specification	Remark
.....6	DZ016	0403-000746 DIODE-ZENER:RLZ3.9B,3.89-4.16V,500MW,LL-	
.....6	DZ016	0403-001016 DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....6	DZ016	0403-001117 DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....6	DZ016	0403-001117 DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....6	DZ016	0403-001117 DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....6	DZ016	0403-001117 DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....6	SO01	0501-000280 TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6	FQ13	0501-000280 TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6	FQ04	0501-000280 TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6	FQ03	0501-000280 TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6	FQ02	0501-000280 TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6	FQ08	0501-000344 TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	FQ09	0501-000344 TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	FQ12	0501-000344 TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	PQ01	0501-000344 TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	FQ06	0501-000344 TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	FQ05	0501-000344 TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	EQ15	0501-000344 TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	EQ14	0501-000344 TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	EQ13	0501-000344 TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	FQ07	0501-000727 TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
.....6	Q409	0505-000110 FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0,	
.....6	Q409	0505-000110 FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0,	
.....6	IC104	0801-000662 IC-CMOS LOGIC:74HC123,MULTIVIBRATOR,SOP,1	
.....6	IC106	1001-001087 IC-VIDEO SWITCH:BA7657F,-,SOP,24P,300MIL	
.....6	IC06	1203-001211 IC-VOL. DETECTOR:7027,SOT-89,3P,-,PLASTI	
.....6	T0087	1203-002186 IC-POSI.FIXED REG.:18,DPAK,3P,240MIL,PLA	
.....6	T0087	1203-002302 IC-POSI.FIXED REG.:78RM333D,D-PAK,3P,-,PL	
.....6	IC02	1204-001814 IC-SELECTOR:CXA2151Q,OFF,48P,144MIL,PLAS	
.....6	IC01A	1204-001938 IC-DECODER:VSP9407B-B11,MOFF,80P,14X14MM	
.....6	IC118	1204-001989 IC-VIDEO PROCESS:CXA2165Q,OFF,64P,20X14MM	
.....6	SR08	2007-000052 R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6	FR80	2007-000052 R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6	FR79	2007-000052 R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6	FR78	2007-000052 R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6	FR57	2007-000052 R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6	FR35	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	FR07	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	ER90	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	FR76	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	FR96	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	SR09	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	SR22	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	ER29	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	ER04	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	ER05	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	ER06	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	ER13	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	ER19	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	ER18	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	ER17	2007-000070 R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	SR03	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR04	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR05	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR06	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR10	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR11	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR02	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	FR71	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	FR74	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	FR75	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	FR81	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	FR82	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR01	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR49	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR53	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR75	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	YR43	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	YR44	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	YR45	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	YR48	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR31	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR32	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR33	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR34	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR35	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6	SR47	2007-000074 R-CHIP:100ohm,5%,1/10W,TP,1608	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....6	IC13	1001-001155	IC-ANALOG MULTIPLEX;NC7SB3157P6X,CMOS,SC6	R61	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	IC112	1103-001195	IC-EEPROM;24C64,8Kx8Bit,SOP,8P,150MIL,106	R60	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	DU410	1201-001135	IC-OP AMP;324,SOP,ST,14P,150MIL,QUAD,1006	R55	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	DU410	1201-001504	IC-OP AMP;072,SOP,8P,150MIL,DUAL,-,PLAST6	R54	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	DU410	1201-001504	IC-OP AMP;072,SOP,8P,150MIL,DUAL,-,PLAST6	R79	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	DU410	1201-001504	IC-OP AMP;072,SOP,8P,150MIL,DUAL,-,PLAST6	R78	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	DU410	1201-001504	IC-OP AMP;072,SOP,8P,150MIL,DUAL,-,PLAST6	R73	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	T0074	1201-001520	IC-VIDEO AMP;EL2250CS,SOIC,8P,150MIL,DUA6	R72	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	IC03	1203-001824	IC-VOL. DETECTOR;7042,SOT-89,3P,-,PLASTI6	R67	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	T0087	1203-002302	IC-POS.FIXED REG.;78RM33D,D-PAK,3P,-,PL6	R49	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	IC17	1209-001163	IC-PLL;TLC2932IPWLE,SOP,14P,-,PLASTIC6	R08	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	R36	2007-000028	R-CHIP;39ohm,5%,1/8W,TP,20126	R07	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	R35	2007-000028	R-CHIP;39ohm,5%,1/8W,TP,20126	R06	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	R31	2007-000028	R-CHIP;39ohm,5%,1/8W,TP,20126	R04	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	R30	2007-000028	R-CHIP;39ohm,5%,1/8W,TP,20126	R01	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	R143	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,16086	R48	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	R144	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,16086	R133	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	R25	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,16086	R121	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	R122	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,16086	R119	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	R123	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,16086	R118	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....6	R141	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,16086	R86	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608
.....6	R136	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,16086	R92	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608
.....6	R15	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,16086	R93	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608
.....6	R24	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,16086	R96	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608
.....6	R45	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,16086	R97	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608
.....6	R46	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,16086	R85	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608
.....6	R09	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,16086	R113	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608
.....6	R10	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,16086	R114	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608
.....6	R129	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,16086	R115	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608
.....6	R134	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,16086	R83	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608
.....6	R135	2007-000072	R-CHIP;47ohm,5%,1/10W,TP,16086	R84	2007-000090	R-CHIP;10Kohm,5%,1/10W,TP,1608
.....6	R59	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,16086	R125	2007-000091	R-CHIP;12Kohm,5%,1/10W,TP,1608
.....6	R65	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,16086	R05	2007-000102	R-CHIP;100Kohm,5%,1/10W,TP,1608
.....6	R71	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,16086	R127	2007-000109	R-CHIP;1Mohm,5%,1/10W,TP,1608
.....6	R77	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,16086	R100	2007-000118	R-CHIP;390ohm,5%,1/10W,TP,1608
.....6	R91	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,16086	R32	2007-000119	R-CHIP;560ohm,5%,1/10W,TP,1608
.....6	R53	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,16086	R34	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608
.....6	R02	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,16086	R29	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608
.....6	R16	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,16086	R28	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608
.....6	R17	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,16086	R117	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608
.....6	R20	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,16086	R107	2007-000122	R-CHIP;1.2Kohm,5%,1/10W,TP,1608
.....6	R47	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,16086	R33	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608
.....6	R62	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R120	2007-000124	R-CHIP;2.2Kohm,5%,1/10W,TP,1608
.....6	R64	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R90	2007-000133	R-CHIP;330Kohm,5%,1/10W,TP,1608
.....6	R68	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R89	2007-000133	R-CHIP;330Kohm,5%,1/10W,TP,1608
.....6	R58	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R88	2007-000133	R-CHIP;330Kohm,5%,1/10W,TP,1608
.....6	R56	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R87	2007-000133	R-CHIP;330Kohm,5%,1/10W,TP,1608
.....6	R52	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R108	2007-000381	R-CHIP;13Kohm,5%,1/10W,TP,1608
.....6	R70	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R139	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608
.....6	R98	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R138	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608
.....6	R94	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R137	2007-000402	R-CHIP;150ohm,5%,1/10W,TP,1608
.....6	R82	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R99	2007-000704	R-CHIP;3.6Kohm,5%,1/16W,DA,TP,1608
.....6	R80	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R95	2007-000704	R-CHIP;3.6Kohm,5%,1/16W,DA,TP,1608
.....6	R76	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R126	2007-000857	R-CHIP;4.3Kohm,1%,1/16W,DA,TP,1608
.....6	R74	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R27	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608
.....6	R38	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R26	2007-001167	R-CHIP;75ohm,5%,1/10W,TP,1608
.....6	R37	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	R116	2007-001179	R-CHIP;8.2Kohm,5%,1/10W,TP,1608
.....6	R110	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	RN04	2011-000585	R-NETWORK;470HM,5%,1/16W,L,CHIP,8P,TP
.....6	R11	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	RN05	2011-000585	R-NETWORK;470HM,5%,1/16W,L,CHIP,8P,TP
.....6	R101	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	RN06	2011-000585	R-NETWORK;470HM,5%,1/16W,L,CHIP,8P,TP
.....6	R03	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	RN01	2011-000585	R-NETWORK;470HM,5%,1/16W,L,CHIP,8P,TP
.....6	R39	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	RN02	2011-000585	R-NETWORK;470HM,5%,1/16W,L,CHIP,8P,TP
.....6	R50	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	RN03	2011-000585	R-NETWORK;470HM,5%,1/16W,L,CHIP,8P,TP
.....6	R44	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	C120	2203-000041	C-CERAMIC,CHIP;0.01nF,0.25PF,50V,COG,TP
.....6	R43	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	C120	2203-000041	C-CERAMIC,CHIP;0.01nF,0.25PF,50V,COG,TP
.....6	R42	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	C120	2203-000041	C-CERAMIC,CHIP;0.01nF,0.25PF,50V,COG,TP
.....6	R41	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	C120	2203-000041	C-CERAMIC,CHIP;0.01nF,0.25PF,50V,COG,TP
.....6	R40	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,16086	C120	2203-000041	C-CERAMIC,CHIP;0.01nF,0.25PF,50V,COG,TP
.....6	R128	2007-000079	R-CHIP;1.8Kohm,5%,1/10W,TP,16086	C120	2203-000041	C-CERAMIC,CHIP;0.01nF,0.25PF,50V,COG,TP
.....6	R81	2007-000080	R-CHIP;2Kohm,5%,1/10W,TP,16086	C120	2203-000041	C-CERAMIC,CHIP;0.01nF,0.25PF,50V,COG,TP
.....6	R75	2007-000080	R-CHIP;2Kohm,5%,1/10W,TP,16086	C120	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP
.....6	R69	2007-000080	R-CHIP;2Kohm,5%,1/10W,TP,16086	C120	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP
.....6	R51	2007-000080	R-CHIP;2Kohm,5%,1/10W,TP,16086	C120	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP
.....6	R57	2007-000080	R-CHIP;2Kohm,5%,1/10W,TP,16086	C120	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP
.....6	R63	2007-000080	R-CHIP;2Kohm,5%,1/10W,TP,16086	C120	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP
.....6	R109	2007-000082	R-CHIP;3.3Kohm,5%,1/10W,TP,16086	C120	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP
.....6	R66	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,16086	C120	2203-000181	C-CERAMIC,CHIP;100nF,+80-20%,25V,Y5V,TP

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5	C701	2401-000025	C-AL:100uF,20%,16V,GP,TP,6.3x11,55	L105	2701-000106	INDUCTOR-AXIAL:1.5uH,10%,3x7mm
.....5	C701	2401-000025	C-AL:100uF,20%,16V,GP,TP,6.3x11,55	L119	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000025	C-AL:100uF,20%,16V,GP,TP,6.3x11,55	L120	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000039	C-AL:1000uF,20%,16V,GP,TP,10x16,55	L121	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000039	C-AL:1000uF,20%,16V,GP,TP,10x16,55	L122	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7,55	L123	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7,55	L124	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,55	L107	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,55	L108	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,55	L111	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,55	L114	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000471	C-AL:10uF,20%,50V,BP,TP,5x11,5mm5	L113	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L112	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L703	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L106	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L104	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L103	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L101	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L706	2701-001030	INDUCTOR-AXIAL:43uH,10%,5x14mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L705	2701-001030	INDUCTOR-AXIAL:43uH,10%,5x14mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L102	2701-001040	INDUCTOR-AXIAL:10uH,10%,4.5x14mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	G101	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	G101	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	G101	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	CN906	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	CN906	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	CN906	3711-002643	CONNECTOR-HEADER:BOX,4P,1R,2.5mm,STRAIGH
.....5	C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,25	CN906	3711-002645	CONNECTOR-HEADER:BOX,6P,1R,2.5mm,STRAIGH
.....5	C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,25	GT01	AA60-40014A	PIN-GT,ASSY:AUTO S.N.A
.....5	C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,25	GT02	AA60-40014A	PIN-GT,ASSY:AUTO S.N.A
.....5	C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,25	GT03	AA60-40014A	PIN-GT,ASSY:AUTO S.N.A
.....5	C701	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11,5,55		BP97-005130	ASSY SMD:HCN4226WX/XAA,P55A S.N.A
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-000314	DIODE-ZENER:RLZJ9,1B,8.80-9.30V,500MW,LL
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-000314	DIODE-ZENER:RLZJ9,1B,8.80-9.30V,500MW,LL
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-000314	DIODE-ZENER:RLZJ9,1B,8.80-9.30V,500MW,LL
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-000314	DIODE-ZENER:RLZJ9,1B,8.80-9.30V,500MW,LL
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-000314	DIODE-ZENER:RLZJ9,1B,8.80-9.30V,500MW,LL
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001016	DIODE-ZENER:RLZ6,2B,5.96-6.27V,500MW,LL-
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001016	DIODE-ZENER:RLZ6,2B,5.96-6.27V,500MW,LL-
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001016	DIODE-ZENER:RLZ6,2B,5.96-6.27V,500MW,LL-
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001016	DIODE-ZENER:RLZ6,2B,5.96-6.27V,500MW,LL-
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP
.....5	C701	2401-001192	C-AL:33uF,20%,50V,GP,TP,6.3x11,56	Q703	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,56	Q704	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001513	C-AL:47uF,20%,16V,WT,TP,5x11,56	Q707	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	Q708	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	Q709	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	Q710	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	Q101	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	Q103	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	Q106	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,56	IC106	1001-001177	IC-VIDEO SWITCH:TEA6425D,VIDEO SWITCH,S
.....5	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,56	IC106	1001-001177	IC-VIDEO SWITCH:TEA6425D,VIDEO SWITCH,S
.....5	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,56	IC605	1001-001178	IC-AUDIO SWITCH:TEA6422D,AUDIO SWITCH,S
.....5	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,56	IC704	1002-001048	IC-A/D&D/A CONVERTER:PCF8591T,8BIT,SOP,1
.....5	C701	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,56	IC705	1002-001048	IC-A/D&D/A CONVERTER:PCF8591T,8BIT,SOP,1
.....5	C701	2401-002300	C-AL:47uF,20%,50V,GP,TP,6.3x11,56	DU410	1201-000541	IC-OP AMP:062,SOP,8P,153MIL,DUAL,6V/mV,P
.....5	C701	2401-002300	C-AL:47uF,20%,50V,GP,TP,6.3x11,56	IC602	1204-002002	IC-SOUND PROCESSOR:MSP3420G-B11,PQFP,80P
.....5	C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,56	R789	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,56	R788	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,56	R777	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,56	R776	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,56	R775	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,56	R791	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002463	C-AL:470uF,20%,16V,GP,TP,8x11,5,56	R97C	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002463	C-AL:470uF,20%,16V,GP,TP,8x11,5,56	R904	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11,5,56	R79B	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,56	R795	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,56	R794	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,56	R729	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,56	R145	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....5	C701	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,56	R143	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608

Loc. No.	Code No.	Description ; Specification	Remark
....4	CZ114	2202-000561 C-CERAMIC,MLC-RADIAL:0.68NF,5%,50V,COG,T	
....4	C701	2401-000183 C-AL:1000uF,20%,35V,WT,TP,12.5x25.5	
....4	C701	2401-000183 C-AL:1000uF,20%,35V,WT,TP,12.5x25.5	
....4	C701	2401-000962 C-AL:22uF,20%,50V,GP,TP5x11.5	
....4	C701	2401-000962 C-AL:22uF,20%,50V,GP,TP5x11.5	
....4	LZ112	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
....4	LZ111	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
....4	LZ110	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
....4	LZ109	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
....4	LZ108	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
....4	LZ107	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
....4	FD102S	3601-001065 FUSE-AXIAL LEAD:125V,3.5A,FAST-ACTING,CE	
....4	FD101S	3601-001065 FUSE-AXIAL LEAD:125V,3.5A,FAST-ACTING,CE	
....4	ELZ01	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	ELZ02	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	ELZ03	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
....4	R125	2001-000800 R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	0	AA41-00601C PCB:HCM4215W,PCB,CEM-1,1L,C,1.6,245X245,	S.N.A
....4	SGZ101	4715-000106 SURGE ABSORBER:300V,210-390V,-,AXIAL	S.N.A
....3	T0076	BP39-00005A LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL2547	
....3	T0076	BP39-00015A LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL1185	
....3		BP61-00076A HOLDER-PUSH,A:42W5,NYLON6.6,NATURAL	S.N.A
....3		BP61-00077A HOLDER-PUSH,B:42W5,NYLON6.6,NATURAL	S.N.A
....3	CZ101	BP96-00005A ASSY HEAT SINK P:BP62-00002A,SCREW,STK39	S.N.A
....4	T0081	6003-001021 SCREW-TAPTITE:RH,+2S,M3,L15,ZPC(YEL),SWR	S.N.A
....4	CIS	BP62-00002A HEAT SINK:COMMANDO,A1050P,T2.0,W62.0,H14	S.N.A
....4	CIS	BP62-00008A HEAT SINK:COMMANDO CG AMP,AL6063,T2.0,W	S.N.A
....4	CIS	BP73-00002A SILICON/RUBBER:COMMANDO CG AMP,SILICON ,N.A	
....4	T0074	1201-001225 IC-VIDEO AMP:392,SIP,22P,-,TRIPLE,-,PLAS	
....2	T0099	BP94-00234A ASSY PCB MISC-CRT:DP,HCM4215W3S/XAA,P55A	
....3		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37PB	S.N.A
....3	VR561	2101-000321 VR-ROTARY:1Mohm,-,0.6W,SIDE	
....3	VR531	2101-000321 VR-ROTARY:1Mohm,-,0.6W,SIDE	
....3	VR501	2101-000321 VR-ROTARY:1Mohm,-,0.6W,SIDE	
....3	T0121	3301-001201 CORE-FERRITE:AE,21x11x32mm,1500,280G	
....3	V561	3704-001019 SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	
....3	V531	3704-001019 SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	
....3	V501	3704-001019 SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	
....3	CN906	3711-002645 CONNECTOR-HEADER:BOX,6P,1R,2.5mm,STRAIGH	
....3	CN906	3711-002648 CONNECTOR-HEADER:BOX,9P,1R,2.5mm,STRAIGH	
....3	CN906	3711-003052 CONNECTOR-HEADER:BOX,10P,1R,2.5MM,STRAIG	
....3	CN906	3711-003052 CONNECTOR-HEADER:BOX,10P,1R,2.5MM,STRAIG	
....3	CN906	3711-003973 CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIG	
....3	CN906	3711-003973 CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIG	
....3	SG301	4715-001050 SURGE ABSORBER:2.4kV,20%,1500A,-,DISC-RA	
....3	SG562	AA27-00084A COIL:S-23,-,S-23,5000Mohm MIN,	
....3	SG532	AA27-00084A COIL:S-23,-,S-23,5000Mohm MIN,	
....3	SG502	AA27-00084A COIL:S-23,-,S-23,5000Mohm MIN,	
....3	T0076	AA39-00112A LEAD CONNECTOR-ASSY,UL1007#26,UL/CSA,10	
....3	T0076	AA39-00120F LEAD CONNECTOR-ASSY:SIR-T165,UL1007#26,U	
....3	T0076	AA39-00198D LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL1617	
....3	T0076	AA39-20010B LEAD CONNECTOR-ASSY:,1P,500,YFH800-01,S,	
....3	T0076	AA39-20010D LEAD CONNECTOR-ASSY:,1P,400,YFH800-01,S,	
....3	T0076	AA39-20010D LEAD CONNECTOR-ASSY:,1P,400,YFH800-01,S,	
....3	T0076	AA39-20027B LEAD CONNECTOR-ASSY:,6P,400,67096-006,S,	
....3	T0076	AA39-20031D LEAD CONNECTOR-ASSY:,9P,500,67096-009,S,	
....3		AA69-01396A BAG PE:SKD CHASSIS,LDPE,TO.03,240,180,NO	S.N.A
....3	Q371	AA96-00244H ASSY H/S:SCREW,2SC4636(2),CRT,SILICON-OIL	S.N.A
....4		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A
....4	T0090	0502-000442 TR-POWER:2SC4636RB,NPN,2W,TO-220,ST,10-	
....4	T0081	6003-000335 SCREW-TAPTITE:RH,+2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00046A HEAT SINK-PS:-,T1.0,-,D1(DREAM) 60X25X	S.N.A
....3	IC561	AA96-50311L ASSY H/S:-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....3	IC531	AA96-50311L ASSY H/S:-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....3	IC501	AA96-50311L ASSY H/S:-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....4	T0074	1201-001131 IC-VIDEO AMP:6111,SIP,9P,-,SINGLE,-,PLAS	

Loc. No.	Code No.	Description ; Specification	Remark
....4	T0081	6003-000334 SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR	
....4		AA62-30175D HEAT SINK-PS:-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
....3		AA97-07608A ASSY AUTO-CRT:HCM4215W	S.N.A
....4	D372	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D504	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D509	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D361	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D362	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D371	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D510	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	T0083	0402-000493 DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
....4	T0083	0402-000493 DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
....4	T0083	0402-000493 DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
....4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
....4	DZ016	0403-000508 DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508 DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508 DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000708 DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
....4	DZ016	0403-000708 DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
....4	DZ016	0403-000708 DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
....4	Q563	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
....4	Q534	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
....4	Q533	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
....4	Q504	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
....4	Q361	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
....4	Q362	0501-000366 TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L	
....4	Q502	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
....4	T0090	0502-000006 TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-	
....4	T0090	0502-000006 TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-	
....4	T0090	0502-000006 TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-	
....4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R584	2001-000028 R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R554	2001-000028 R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R524	2001-000028 R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R580	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R550	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R520	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R577	2001-000085 R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R547	2001-000085 R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R517	2001-000085 R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R366	2001-000109 R-CARBON(S):470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R125	2001-000290 R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000539 R-CARBON:24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000577 R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000613 R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000613 R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000660 R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000723 R-CARBON:4.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000938 R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000995 R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-001015 R-CARBON:9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R581	2001-001052 R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R551	2001-001052 R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R521	2001-001052 R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R371	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R370	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R369A	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R367	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R368	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.4	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark	
....4	R369	2001-001065	R-CARBON(S);110KOHM,5%,1/2W,AA,TP,2.4X6.4	SG501	4715-001036	SURGE ABSORBER;500V,20%,--,TP	
....4	R567	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M4	SG503	4715-001036	SURGE ABSORBER;500V,20%,--,TP	
....4	R537	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M4	SG531	4715-001036	SURGE ABSORBER;500V,20%,--,TP	
....4	R507	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M4	EL06	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	R381	2001-001088	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M4	EL03	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	R361	2001-001097	R-CARBON(S);2.4KOHM,5%,1/2W,AA,TP,2.4X6.4	EL563	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R374	2001-001110	R-CARBON(S);240KOHM,5%,1/2W,AA,TP,2.4X6.4	EL537	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R373	2001-001110	R-CARBON(S);240KOHM,5%,1/2W,AA,TP,2.4X6.4	EL536	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R372	2001-001110	R-CARBON(S);240KOHM,5%,1/2W,AA,TP,2.4X6.4	EL535	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R377	2001-001110	R-CARBON(S);240KOHM,5%,1/2W,AA,TP,2.4X6.4	EL564	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R375	2001-001113	R-CARBON(S);270KOHM,5%,1/2W,AA,TP,2.4X6.4	EL565	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R365	2001-001120	R-CARBON(S);3.30HM,5%,1/2W,AA,TP,2.4X6.44	EL566	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R574	2001-001122	R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.4	EL567	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R544	2001-001122	R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.4	EL534	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R514	2001-001122	R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.4	EL01	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R583	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.74	EL02	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R582	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.74	EL04	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R553	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.74	EL05	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R552	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.74	EL533	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R523	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.74	EL505	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R522	2002-001006	R-COMPOSITION;4.7KOHM,15%,1/2W,AA,TP,3.74	EL504	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R589	2002-001015	R-COMPOSITION;47Kohm,5%,1/2W,AA,TP,3.7x94	EL503	6042-000001	EYELET;ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R559	2002-001015	R-COMPOSITION;47Kohm,5%,1/2W,AA,TP,3.7x94	GT537	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R529	2002-001015	R-COMPOSITION;47Kohm,5%,1/2W,AA,TP,3.7x94	GT561	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R575	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x94	GT536	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R545	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x94	GT535	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R515	2002-001017	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x94	GT534	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R579	2002-001021	R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X4	GT562	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R578	2002-001021	R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X4	GT568	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R549	2002-001021	R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X4	GT567	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R518	2002-001021	R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X4	GT564	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R519	2002-001021	R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X4	GT563	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R548	2002-001021	R-COMPOSITION;560KOHM,5%,1/2W,AA,TP,3.7X4	GT503	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R588	2003-000738	R-METAL OXIDE(S);56Kohm,5%,2W,AA,TP,4x124	GT502	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R538	2003-000738	R-METAL OXIDE(S);56Kohm,5%,2W,AA,TP,4x124	GT501	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R508	2003-000738	R-METAL OXIDE(S);56Kohm,5%,2W,AA,TP,4x124	GT373	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R024	2004-001892	R-METAL(S);162Kohm,1%,1/2W,AA,TP,2.5x6.54	GT372	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R024	2004-001892	R-METAL(S);162Kohm,1%,1/2W,AA,TP,2.5x6.54	GT371	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R024	2004-001892	R-METAL(S);162Kohm,1%,1/2W,AA,TP,2.5x6.54	GT504	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R573	2008-001129	R-FUSIBLE(S);1.5ohm,5%,1/2W,AF,TP,2.5x6.4	GT533	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R543	2008-001129	R-FUSIBLE(S);1.5ohm,5%,1/2W,AF,TP,2.5x6.4	GT532	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	R513	2008-001129	R-FUSIBLE(S);1.5ohm,5%,1/2W,AF,TP,2.5x6.4	GT531	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	C598	2201-000119	C-CERAMIC,DISC;100NF,+80-20%,50V,Y5V,TP,4	GT506	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	C598	2201-000119	C-CERAMIC,DISC;100NF,+80-20%,50V,Y5V,TP,4	GT374	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	C598	2201-000119	C-CERAMIC,DISC;100NF,+80-20%,50V,Y5V,TP,4	GT375	AA60-40014A	PIN-GT,ASSY/AUTO	S.N.A
....4	C598	2201-000556	C-CERAMIC,DISC;0.47NF,10%,500V,Y5P,TP,5.4	R125	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C598	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X54	R125	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C598	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X54	R125	2001-000362	R-CARBON;150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C598	2201-000723	C-CERAMIC,DISC;4.7NF,20%,3KV,Y5U,TP,16X54	DZ016	0403-000334	DIODE-ZENER;U2.7BSA,2.7V,2.54-2.75V,500	
....4	C598	2201-000983	C-CERAMIC,DISC;1NF,10%,2KV,Y5P,TP,9X5MM,4	DZ016	0403-000334	DIODE-ZENER;U2.7BSA,2.7V,2.54-2.75V,500	
....4	C598	2201-000983	C-CERAMIC,DISC;1NF,10%,2KV,Y5P,TP,9X5MM,4	DZ016	0403-000334	DIODE-ZENER;U2.7BSA,2.7V,2.54-2.75V,500	
....4	C598	2201-000983	C-CERAMIC,DISC;1NF,10%,2KV,Y5P,TP,9X5MM,4	R566	2001-001049	R-CARBON(S);1.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	C565	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.54	R536	2001-001049	R-CARBON(S);1.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	C535	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.54	R506	2001-001049	R-CARBON(S);1.3KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	C505	2305-000149	C-FILM,MPEF;100nF,5%,100V,TP,12x12.5x6.54	R125	2001-000007	R-CARBON;3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C507	2305-000154	C-FILM,MPEF;100nF,5%,400V,TP,21.5x6.5x114	R125	2001-000006	R-CARBON;2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C537	2305-000154	C-FILM,MPEF;100nF,5%,400V,TP,21.5x6.5x114	C598	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C567	2305-000154	C-FILM,MPEF;100nF,5%,400V,TP,21.5x6.5x114	C598	2201-000599	C-CERAMIC,DISC;0.56NF,10%,500V,Y5P,TP,5.	
....4	C361	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m4	C701	2401-001571	C-AL;47uF,+20%-0%,50V,GP,TP,8x11.5.	
....4	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11.54	C701	2401-001571	C-AL;47uF,+20%-0%,50V,GP,TP,8x11.5.	
....4	C701	2401-002075	C-AL;4.7uF,20%,50V,GP,TP,5x11.54	C701	2401-001571	C-AL;47uF,+20%-0%,50V,GP,TP,8x11.5.	
....4	C701	2401-000133	C-AL;1000uF,20%,16V,GP,TP,10x20,54	R125	2001-000319	R-CARBON;120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11.54	R125	2001-000472	R-CARBON;2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11.54	R125	2001-000563	R-CARBON;27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000232	R-CARBON;1.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000908	R-CARBON;62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL;10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000281	R-CARBON;100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-001621	C-AL;6.8uF,20%,450V,GP,TP,13x20,54	L561	2701-000168	INDUCTOR-AXIAL;3.3uH,5%,2.5x3.4mm	
....4	L531	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm4	R382	2002-001014	R-COMPOSITION;6.8Kohm,10%,1/2W,AA,TP,3.7	
....4	L501	2701-000114	INDUCTOR-AXIAL;10uH,10%,2.5x3.4mm4	PCB	AA41-00600E	PCB-CRT;HCM4215W,FR-1,1L,E,1.6T,245X197(S.N.A
....4	SG561	4715-001036	SURGE ABSORBER;500V,20%,--,TP4	T0083	0402-000243	DIODE-RECTIFIER;RC2-V1,2000V,0.2A,DO-201	
....4	SG563	4715-001036	SURGE ABSORBER;500V,20%,--,TP3	T0076	BP39-00004B	LEAD CONNECTOR-ASSY;P55A/HCM4215W,UL3239	
....4	SG533	4715-001036	SURGE ABSORBER;500V,20%,--,TP3	T0076	BP39-00004C	LEAD CONNECTOR-ASSY;P55A/HCM4215W,UL3239	

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
...3	T0076	BP39-00004C LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239		...3	GT09	AA60-40012D PIN-GT,ASSY:T1.6,6-12.5-.NYLON66	S.N.A
...3	T0103	BP59-00005A MODULE-FOCUS PACK ASS:Y:PJT TV,F301-P03A		...3	GT05	AA60-40012D PIN-GT,ASSY:T1.6,6-12.5-.NYLON66	S.N.A
...3	T0076	AA39-20010C LEAD CONNECTOR-ASSY:,TP,600,YFH800-01,S,		...3	GT01	AA60-40012D PIN-GT,ASSY:T1.6,6-12.5-.NYLON66	S.N.A
...3	C701	2401-000480 C-AL:10uF,20%,50V,GP,TP,5x11,5		...3		AA61-01197A HOLDER-PCB,DY:COMANDO,ABS V0,BLK	S.N.A
...3		AA63-10002A BAND-TIE:NYLON66 V2,L100,NTR	S.N.A	...3		AA97-07230N ASSY AUTO-COMMANDO	S.N.A
...3		6902-000395 BAG PE:LDPE,TO,05,W200,L140,...	S.N.A	...4	R301	2001-001107 R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
...2	T0098	BP94-000238A ASSY PCB MISC-VM:DPHCM4215W3S/XAA,P55A		...4	R302	2001-001107 R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
...3		0202-000187 SOLDER-WIRE FLUX:;,RS60S,D1.2,63Sn/37Pb	S.N.A	...4	R303	2001-001107 R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
...3	RZ120	2008-001097 R-FUSIBLE(S):330HM,5%,1/2W,AC,BK,2.5X6.5		...4	PCB	AA41-00632A PCB-DY CONNECTION:HCM4215W,FR-1,1L,A,1.6	S.N.A
...3	T0121	3301-001201 CORE-FERRITE:AE,21x11x32mm,1500,280G		...2	T0098	BP94-00517Z ASSY PCB MISC-CONTROL:DPHCN4226W,P55A,K	
...3	T0079	AA33-00017A MAGNET CONVERGENCE:JH 92LT - 29G,-.29.1M		...3		0202-000187 SOLDER-WIRE FLUX:;,RS60S,D1.2,63Sn/37Pb	S.N.A
...3	T0076	AA39-20055C LEAD CONNECTOR-ASSY:,6P,500,YBNH025-06,6		...3	T0121	3301-001201 CORE-FERRITE:AE,21x11x32mm,1500,280G	
...3	OZ102	AA96-00243L ASSY H/S:;CRT,AA62-000450A,2SC2344,HERC	S.N.A	...3	SWY08	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A	...3	SWY07	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4	T0090	0502-000153 TR-POWER:25C2344-D,NPN,1.2W,TO-220,-.60		...3	SWY06	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4	T0081	6003-000335 SCREW-TAPTITE:RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A	...3	SWY05	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4		AA62-00045A HEAT SINK-PS:;,T1.0,;,DREAM:;,;,;	S.N.A	...3	SWY04	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...3	OZ101	AA96-00243M ASSY H/S:;AMP,AA62-000450A,2SA1011,HERC	S.N.A	...3	SWY03	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A	...3	SWY01	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4	T0090	0502-000131 TR-POWER:25A1011-D,PNP,1.2W,TO-220,-.60		...3	CN906	3711-000447 CONNECTOR-HEADER:BOX,3P,1R,2.5MM,ANGLE,-	
...4	T0081	6003-000335 SCREW-TAPTITE:RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A	...3	CN906	3711-000479 CONNECTOR-HEADER:BOX,5P,1R,2.5mm,ANGLE,-	
...4		AA62-00045A HEAT SINK-PS:;,T1.0,;,DREAM:;,;,;	S.N.A	...3	CN906	3711-003353 CONNECTOR-HEADER:BOX,11P,1R,2.5mm,ANGLE,	
...3		AA97-07230M ASSY AUTO-VM:COMMANDO	S.N.A	...3	RMY01	AA32-00012A MODULE REMOCON:ORC-50HF2,38KHZ,940NM,MES	
...4	DZ106	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...3	T0076	AA39-00223C LEAD CONNECTOR-ASSY:P55A/SVP-42W5HD,UL10	
...4	DZ105	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...3	CN902	AA39-00259B LEAD CONNECTOR-SVP-43W6,UL1007#26,UL/CSA	
...4	DZ102	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		...3	T0076	AA39-20020D LEAD CONNECTOR-ASSY:,5P,600,67096-005,S,	
...4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		...3		BP97-00511H ASSY AUTO-HCN4226WX/XAA,P55A	S.N.A
...4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		...4	DZ016	0403-000510 DIODE-ZENER:MTZJ6.2B,6.2V,5.96-6.27V,500	
...4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		...4	DZ016	0403-000510 DIODE-ZENER:MTZJ6.2B,6.2V,5.96-6.27V,500	
...4	OZ103	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		...4	OY01	0504-000123 TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T	
...4	OZ106	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		...4	RY07	2001-000020 R-CARBON(S):220OHM,5%,1/2W,AA,TP,2.4X6.4MM	
...4	OZ105	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		...4	RY09	2001-000109 R-CARBON(S):470OHM,5%,1/2W,AA,TP,2.4X6.4	
...4	OZ104	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		...4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	RZ122	2001-000019 R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4MM		...4	R125	2001-000832 R-CARBON:5100HM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	R125	2001-000221 R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	R125	2001-000832 R-CARBON:5100HM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	R125	2001-000221 R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	R125	2001-000832 R-CARBON:5100HM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	R125	2001-000241 R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	R125	2001-000924 R-CARBON:6800HM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	R125	2001-000258 R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	RY08	2001-001108 R-CARBON(S):22KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	R125	2001-000258 R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C701	2401-002009 C-AL:100uF,20%,16V,GP,TP,6.3x7.5	
...4	R125	2001-000331 R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	PCB	BP41-00023A PCB:SVP-43W8,PCB-CONTROL,1L,1.6T,330*245	S.N.A
...4	R125	2001-000331 R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...2	T0100	BP94-00559A ASSY PCB MISC-A/V FRONT:DPHCN4226W,P55A	
...4	R125	2001-000554 R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM		...3		0202-000187 SOLDER-WIRE FLUX:;,RS60S,D1.2,63Sn/37Pb	S.N.A
...4	R125	2001-000666 R-CARBON:330OHM,5%,1/8W,AA,TP,1.8X3.2MM		...3	SW101	3404-000208 SWITCH-TACT:12V,50mA,120gf,6x6mm,SPST	
...4	R125	2001-000832 R-CARBON:5100HM,5%,1/8W,AA,TP,1.8X3.2MM		...3	CN906	3711-000447 CONNECTOR-HEADER:BOX,3P,1R,2.5MM,ANGLE,-	
...4	RZ110	2001-001100 R-CARBON(S):2.7OHM,5%,1/2W,AA,TP,2.4X6.4		...3	CN906	3711-003601 CONNECTOR-HEADER:BOX,12P,1R,2.5mm,ANGLE,-	
...4	RZ104	2001-001100 R-CARBON(S):2.7OHM,5%,1/2W,AA,TP,2.4X6.4		...3	JK101	3722-000544 JACK-VHS:4P,11.5mm,AG,BLK,N	
...4	RZ105	2001-001139 R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4		...3	JK102	3722-001164 JACK-PIN:3P,4mm,SN,WH:YE:RE,#16-22	
...4	RZ106	2001-001139 R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4		...3	T0081	6003-001023 SCREW-TAPTITE:RW,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...4	RZ114	2003-000532 R-METAL OXIDE(S):18ohm,5%,2W,AF,TP,4x12m		...3	T0076	AA39-00257C LEAD CONNECTOR-ASSY:P55A/SVP-42W5HD,UL25	
...4	RZ103	2003-000713 R-METAL OXIDE(S):47ohm,5%,2W,AF,TP,4x12m		...3	T0076	AA39-00260A LEAD CONNECTOR-ASSY:,UL1007#26,UL/CSA,3P	
...4	RZ111	2003-000713 R-METAL OXIDE(S):47ohm,5%,2W,AF,TP,4x12m		...3		AA63-10002A BAND-TIE:NYLON66 V2,L100,NTR	S.N.A
...4	RZ123	2003-002157 R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM		...4	R125	AA97-07429A ASSY AUTO-A/V FRONT:HCM4215WX/XAA,P55A	S.N.A
...4	RZ113	2003-002157 R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM		...4	PCB	2001-000006 R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	RZ112	2003-002157 R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM		...3	T0105	BP96-00007G ASSY COVER P/SVP:JACK:42W5,ABS HB G3676	
...4	RFZ101	2008-001086 R-FUSIBLE(S):3.3ohm,5%,2W,AG,TP,3.9x12mm		...4		AA61-01128C HOLDER-SIDE AV:42W5,ABS HB G3676,SV-704P	S.N.A
...4	C598	2201-000193 C-CERAMIC,DISC:0.01NF,0.25PF,50V,C0G,TP,		...4		AA64-02086S INLAY-AV:42W5,PS SHEET,TO,5,P55A,S/PG	S.N.A
...4	C598	2201-000193 C-CERAMIC,DISC:0.01NF,0.25PF,50V,C0G,TP,		...4	T0150	AA64-02780C DOOR-AV:42W5,ABS HB G3676,SV-704P	
...4	C598	2201-000516 C-CERAMIC,DISC:4.7NF,+100-0%,500V,Y5U,TP		...2	CIS	BP94-00564C ASSY PCB MISC-POWER S/W:DP, HCN4226W,P55	
...4	C598	2201-000516 C-CERAMIC,DISC:4.7NF,+100-0%,500V,Y5U,TP		...3	LEDY04	0601-001381 LED-ROUND,RED/GRN,5.0MM,650/563NM	
...4	C598	2201-000604 C-CERAMIC,DISC:0.056NF,+100-0%,500V,SL,T		...3	LEDY03	0601-001381 LED-ROUND,RED/GRN,5.0MM,650/563NM	
...4	C701	2401-000480 C-AL:10uF,20%,50V,GP,TP,5x11,5		...3	LEDY02	0601-001381 LED-ROUND,RED/GRN,5.0MM,650/563NM	
...4	C701	2401-000832 C-AL:220uF,20%,25V,GP,TP,8x11.5,5		...3	LEDY01	0601-001381 LED-ROUND,RED/GRN,5.0MM,650/563NM	
...4	C701	2401-001157 C-AL:33uF,20%,160V,GP,TP,12,5x20,5		...3	SWY02	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4	C701	2401-001220 C-AL:4.7uF,20%,160V,GP,TP,8x11.5,5		...3	CN906	3711-000479 CONNECTOR-HEADER:BOX,5P,1R,2.5mm,ANGLE,-	
...4	C701	2401-001220 C-AL:4.7uF,20%,160V,GP,TP,8x11.5,5		...3		AA61-01140E CASE-PS BOX:ANTISTATIC,PS,295,295,32	S.N.A
...4	C701	2401-001513 C-AL:47uF,20%,16V,WT,TP,5x11,5		...3	PCB	BP41-00022A PCB:SVP-43W8,PCB-MASTER-S/W,1L,1.6T,245*	S.N.A
...4	C701	2401-002144 C-AL:47uF,20%,16V,GP,TP,5x11,5		...2	T0096	BP95-00075A ASSY SUB-DVI:DPHCM4215WJ/XAA,P55A,DVI	
...4	LZ101	2701-000002 INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm		...3		0202-000187 SOLDER-WIRE FLUX:;,RS60S,D1.2,63Sn/37Pb	S.N.A
...4	CN906	3711-002642 CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH		...3	Q409	0505-000109 FET-SILICON:2N7000,N,60V,200mA,5ohm,400m	
...4	CN906	3711-002642 CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH		...3	Q409	0505-000109 FET-SILICON:2N7000,N,60V,200mA,5ohm,400m	
...4	CN906	3711-002642 CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH		...3	DX301	2801-001385 CRYSTAL-UNIT:14.31818MHz,30ppm,28-AAA,16	
...4	PCB	AA41-00611A PCB-VM:HCM4215W,FR-1,1L,A,1.6T,245X245,P	S.N.A	...3	DX701	2801-001385 CRYSTAL-UNIT:14.31818MHz,30ppm,28-AAA,16	
...3	T0081	6003-001023 SCREW-TAPTITE:RW,+,B,M3,L10,ZPC(YEL),SW	S.N.A	...3	CN906	3711-002643 CONNECTOR-HEADER:BOX,4P,1R,2.5mm,STRAIGH	
...2	T0105	BP94-00239A ASSY PCB MISC-DY-JACK:DPHCM4215W3S/XAA,		...3		AA69-01396B BAG PE:SKD CHASSIS,LDPE,TO,03,130,130,NO	S.N.A
...3		0202-000187 SOLDER-WIRE FLUX:;,RS60S,D1.2,63Sn/37Pb	S.N.A	...3		BP97-00166A ASSY SMD:HCM4215WJ/XAA,DVI-AUTO,P55A	S.N.A
...3	GT13	AA60-40012D PIN-GT,ASSY:T1.6,6-12.5-.NYLON66	S.N.A	...4	DD512	0401-000133 DIODE-SWITCHING:RLS4148,100V,200mA,SOD-8	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
...4	DD511	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD510	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD509	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD513	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD514	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD515	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD516	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD501	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD502	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD503	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD504	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD508	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD507	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD506	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD505	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DD901	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,
...4	DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	...4	C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,1608
...4	IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P,4	...4	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608
...4	IC01	1002-001333	IC-A/D&D/A CONVERTER;GM7030,10BIT,POFP,1	...4	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608
...4	IC112	1103-000180	IC-EEPROM:24C16,2Kx8Bit,SOP8P,150MIL,10	...4	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608
...4	T0123	1203-001419	IC-VOLTAGE REGULATOR:4931,TO-252,3P,6.6x	...4	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608
...4	IC05	1203-001824	IC-VOL. DETECTOR:7042,SOT-89,3P,-PLASTI	...4	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608
...4	T0123	1203-002351	IC-VOLTAGE REGULATOR:LF25C,DPAK,3P,240MI	...4	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608
...4	DR514	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	...4	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608
...4	DR515	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	...4	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608
...4	DR516	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	...4	C120	2203-000257	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,1608
...4	DR517	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	...4	C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-
...4	DR501	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	...4	C120	2203-000626	C-CERAMIC,CHIP:0.022nF,5%,50V,COG,TP,160
...4	DR502	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	...4	C120	2203-000626	C-CERAMIC,CHIP:0.022nF,5%,50V,COG,TP,160
...4	DR504	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	...4	C120	2203-000626	C-CERAMIC,CHIP:0.022nF,5%,50V,COG,TP,160
...4	DR504	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	...4	C120	2203-000998	C-CERAMIC,CHIP:0.047nF,5%,50V,COG,TP,160
...4	DR506	2007-000071	R-CHIP:22ohm,5%,1/10W,TP,1608	...4	C120	2203-000998	C-CERAMIC,CHIP:0.047nF,5%,50V,COG,TP,160
...4	DR513	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	...4	C120	2203-000998	C-CERAMIC,CHIP:0.047nF,5%,50V,COG,TP,160
...4	DR512	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	...4	C120	2203-005437	C-CERAMIC,CHIP:10000nF,+80-20%,10V,Y5V,T
...4	DR510	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	...4	C120	2203-005437	C-CERAMIC,CHIP:10000nF,+80-20%,10V,Y5V,T
...4	DR109	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	...4	C120	2203-005437	C-CERAMIC,CHIP:10000nF,+80-20%,10V,Y5V,T
...4	DR301	2007-000079	R-CHIP:1.8Kohm,5%,1/10W,TP,1608	...4	C120	2203-005437	C-CERAMIC,CHIP:10000nF,+80-20%,10V,Y5V,T
...4	DR901	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	...4	C120	2203-005437	C-CERAMIC,CHIP:10000nF,+80-20%,10V,Y5V,T
...4	DR519	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	...4	C120	2203-005437	C-CERAMIC,CHIP:10000nF,+80-20%,10V,Y5V,T
...4	DR518	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	...4	C120	2203-005437	C-CERAMIC,CHIP:10000nF,+80-20%,10V,Y5V,T
...4	DR511	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	...4	DC420	2402-000165	C-AL,SMD:47uF,20%,6.3V,GP,TP,5.3x5.3x5.5
...4	DR508	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	...4	DC417	2402-000165	C-AL,SMD:47uF,20%,6.3V,GP,TP,5.3x5.3x5.5
...4	DR701	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DC413	2402-000165	C-AL,SMD:47uF,20%,6.3V,GP,TP,5.3x5.3x5.5
...4	DR520	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DC410	2402-000165	C-AL,SMD:47uF,20%,6.3V,GP,TP,5.3x5.3x5.5
...4	DR509	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DC407	2402-000165	C-AL,SMD:47uF,20%,6.3V,GP,TP,5.3x5.3x5.5
...4	DR210	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DC406	2402-000165	C-AL,SMD:47uF,20%,6.3V,GP,TP,5.3x5.3x5.5
...4	DR702	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DC404	2402-000165	C-AL,SMD:47uF,20%,6.3V,GP,TP,5.3x5.3x5.5
...4	DR703	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DC402	2402-001129	C-AL,SMD:47UF,20%,16V,WT,TP,6.3X5.2MM
...4	DR704	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DC706	2402-001155	C-AL,SMD:47UF,20%,16V,WT,TP,6.3X5.2MM
...4	DR706	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DC701	2404-001020	C-TA,CHIP:10uF,20%,10V,GP,TP,3216,3.2
...4	DR707	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DL701	2703-000398	INDUCTOR-SMD:10uH,10%,3.2x2.5x2.2mm
...4	DR201	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DL409	2703-000398	INDUCTOR-SMD:10uH,10%,3.2x2.5x2.2mm
...4	DR202	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DL408	2703-000398	INDUCTOR-SMD:10uH,10%,3.2x2.5x2.2mm
...4	DR203	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DL406	2703-000398	INDUCTOR-SMD:10uH,10%,3.2x2.5x2.2mm
...4	DR204	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DL404	2703-000398	INDUCTOR-SMD:10uH,10%,3.2x2.5x2.2mm
...4	DR205	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	DL401	2703-000398	INDUCTOR-SMD:10uH,10%,3.2x2.5x2.2mm
...4	DR209	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	G101	3301-001202	CORE-FERRITE BEAD:AB,120ohm,4.5x3.2x1.3m
...4	DR208	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	T0119	BP09-00004A	IC MICOM:T89C51C2-SLSCM,44,5V,32KBYTE,P
...4	DR207	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	CR501	2402-000108	C-AL,SMD:10uF,20%,16V,WT,TP,4.3x4.3x5.4
...4	DR206	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	...4	G101	3301-001593	CORE-FERRITE BEAD:AB,2000HM,2.0X1.2X1.3M
...4	DR902	2007-000102	R-CHIP:100Kohm,5%,1/10W,TP,1608	...4	G101	3301-001593	CORE-FERRITE BEAD:AB,2000HM,2.0X1.2X1.3M
...4	C120	2203-000041	C-CERAMIC,CHIP:0.01nF,0.25PF,50V,COG,TP,	...4	G101	3301-001593	CORE-FERRITE BEAD:AB,2000HM,2.0X1.2X1.3M
...4	C120	2203-000041	C-CERAMIC,CHIP:0.01nF,0.25PF,50V,COG,TP,	...4	G101	3301-001593	CORE-FERRITE BEAD:AB,2000HM,2.0X1.2X1.3M
...4	C120	2203-000041	C-CERAMIC,CHIP:0.01nF,0.25PF,50V,COG,TP,	...4	DR705	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
...4	C120	2203-000041	C-CERAMIC,CHIP:0.01nF,0.25PF,50V,COG,TP,	...4	DR708	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	...4	DR503	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	...4	DR505	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	...4	DR507	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	...4	DR521	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	...4	DR522	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608
...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	...4	0	AA41-00793B	PCB:HCHN473,PCB-DVI,2L,1.6T,245*180,P55A,
...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	...4		0202-001167	SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SNS.N.A
...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	...3	CN906	3711-003641	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG
...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	...3	T0121	3301-001201	CORE-FERRITE-AE,21x11x32mm,1500,280G
...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	...3		AA63-10002A	BAND-TIE-NYLON66 V2,L100,NTR
...4	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	...3	IC112	1103-001211	IC-EEPROM:24C16-PC27,C,2048x8Bit,DIP8P,

Loc. No.	Code No.	Description ; Specification	Remark
...3	T0076	AA39-20032B LEAD CONNECTOR-ASSY; 12P,300,67096-012,S	
...3	PL1	3701-001173 CONNECTOR-DSUB:24P,3R,FEMALE,ANGLE,AUF	
..2		BP95-00147D ASSY SUB PCB-SENSOR:DP,54A,SENSOR	
...3		0202-000187 SOLDER-WIRE FLUX;- ,RS60S,D1.2,63Sn/37Pb	S.N.A
...3		AA69-01808B BAG-SHEET;LDPE(ANTISTATIC),TO.05,800,50	S.N.A
...3		BP97-00208A ASSY SMD-0	S.N.A
....4	Q01	0501-000342 TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
....4	PCB	AA41-00853A PCB-SEROR-SVP-42W5HRC,FR-4,2L,A,1.6T,24	S.N.A
....4	D01	BP32-00001A SENSOR PHOTO:BCS5030G1,-40 TO +85,0.42 U	
....4	R01	2007-000305 R-CHIP:10Mohm,5%,1/10W,TP,1608	
....4	R02	2007-000109 R-CHIP:1Mohm,5%,1/10W,TP,1608	
....4	R03	2007-000109 R-CHIP:1Mohm,5%,1/10W,TP,1608	
....4		0202-001167 SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SNS.N.A	
...3	CN906	3711-000447 CONNECTOR-HEADER:BOX,3P,1R,2.5MM,ANGLE,-	

ASSY P/MATERIAL

1	BP92-00542C	ASSY P/MATERIAL:HCN4226W5S/XAA,P55A	S.N.A
..2	AA60-40006A	PIN-STAPLE:AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A
..2	AA61-00049B	HOLDER-BOX;-PP,-,-,NTR,VO,AA61-20285A	S.N.A
...3	AA61-20285A	HOLDER-BOX:3456,PP,-,-,WHT,VO	S.N.A
..2	AA63-10007C	BAND-PP:W18,CLEA,1G	S.N.A
..2	AA69-00305A	BAG AIR:ALL,LDPE,1000,500,CLR,	S.N.A
..2	AA69-00744L	BAG-SHEET;-HDPE PE FOAM,TO.015,W1650,H1	S.N.A

ASSY ACCESSORY

1	M0016	BP92-00577Q ASSY ACCESSORY:0	S.N.A
..2	6902-000018	BAG PE:LDPE,TO.1,W280,L400,GRY,8,2-	S.N.A
..2	T0116	AA39-00006A CABLE RCA;3000MM	
..2	T0074	AA59-00262A REMOCON;TM63,COMMONDO,48,G6671B,EX,S/S	
...3	T0122	2802-000194 RESONATOR-CERAMIC:8MHz,1.0%,TP,8.5x4.5x5	
...3	T0119	AA09-00275A IC MICOM:Z86L8808SSC-R51PX,SOP,ST,SZTM-8	
..2	T0113	AA61-20126A HOLDER-LEG;-ABS,-,-,BLK,HB	
..2	AA68-00371C	CARD WARRANTY-01;-SEA,W/P100(G),1 YEAR	S.N.A
..2	AA68-0065B	CARD-REGISTRATION;-SEA,A5,ENG,A/P220,2P(S.N.A
..2	AA69-30009C	BAG-SHEET:LDPE,TO.08,W150,L120,-,-,-	S.N.A
..2	CIS	BP68-00054A MANUAL USERS:HCM473WJX,ENG,W/P100G,P55A,	

ASSY K/D-ASSY,CRT

1	BP98-00091A	ASSY K/D-ASSY,CRT:HCM4215W3S/XAA,P55A	S.N.A
..2	T0262	BP98-00084A ASSY K/D-CRT-R:HCM4215W3S/XAA	
...3	AA03-00200A	CRT MONO:P16LSG03RJA,FREE,3.30mH,2.20mH,	S.N.A
...3	T0079	AA33-00016A MAGNET CONVERGENCE:JH 92LT - 29F,-29.1M	
...3	T0076	AA39-00018A LEAD CONNECTOR-ASSY;UL1015#22,UL/CSA,1P	
...3		AA60-00126B SPACER-CAP:PROJ,EPDM,BLK	S.N.A
...3		AA60-00127B SPACER-LENS:PROJ,SILICONE,D/GRAY	S.N.A
...3		AA60-00128B SPACER-CRT:PROJ(65),SILICONE,D/GRAY	S.N.A
...3	T0081	AA60-10011A SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A
...3		AA61-00056B BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,	S.N.A
...3	T0114	AA61-00810B HOLDER-CAP:PROJ,PC,CLR	
...3		AA61-00845A CASE-COUPLER,R:DP,PROJ,AA61-00806B	S.N.A
....4		AA61-00806B CASE-COUPLER,R:PROJ,ALDC,T8,BLK	S.N.A
....4		AA63-10007C BAND-PP:W18,CLEA,1G	S.N.A
...3		AA63-00076A SPACER-LENS:PROJECTION,FELT,-,-,-,BROWN	S.N.A
...3	T0109	AA67-00187A LENS-ASSY:DELTA71,CLEAR A/B	
...3	T0051	AA67-00188A LENS:DELTA71,RED C ELEMENT	
...3	T0107	AA91-00735B ASSY-BRKT,CRT:DP,AA91-00722A,PROJ	
....4	T0107	AA91-00722A ASSY-BRKT,CRT;SECC T1.6,PROJ	
....5	T0072	AA61-00473B BRACKET-CRT:53,SECC,T1.6,-,-,-,-	S.N.A
....5		AA61-00615B BRACKET-EARTH:54J8,PBS,TO.5,-,-,-,-	S.N.A
....5		AA61-00812A SPRING ETC-WIRE:PROJ,STS,3.6	S.N.A
...3		BP61-00091A HOLDER-CRT:PJT,PCABS GF20%,BLUE	S.N.A
...3		BP61-00079A HOLDER-DY;PJT,TO.5,NYLON66 V2	S.N.A
...3	T0078	AA27-00249A DEFLECTION YOKE;-DPD-5292AA,S/S,7,29.1	
...3	T0117	AA26-30006F TRANS FBT-ANODE CAP ASS'Y;-FWZ-50A001C,	
..2	T0261	BP98-00085A ASSY K/D-CRT-G:HCM4215W3S/XAA	
...3		AA03-00201A CRT MONO:P16LSG03HKA,FREE,3.30mH,2.20mH,	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark
...3	T0076	AA39-00018A LEAD CONNECTOR-ASSY;UL1015#22,UL/CSA,1P	
...3		AA60-00125B SPACER-CRT:PROJ,SILICONE,D/GRAY	S.N.A
...3		AA60-00126B SPACER-CAP:PROJ,EPDM,BLK	S.N.A
...3		AA60-00127B SPACER-LENS:PROJ,SILICONE,D/GRAY	S.N.A
...3	T0081	AA60-10011A SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A
...3		AA61-00056B BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,	S.N.A
...3		AA61-00809B HOLDER-CRT:PROJ,PC/ABS GF 20%,BLK	S.N.A
...3	T0114	AA61-00810B HOLDER-CAP:PROJ,PC,CLR	
...3		AA61-00846A CASE-COUPLER,G:DP,PROJ,AA61-00807B	S.N.A
....4		AA61-00807B CASE-COUPLER,G:PROJ,ALDC,T8,BLK	S.N.A
....4		AA63-10007C BAND-PP:W18,CLEA,1G	S.N.A
...3		AA63-00076A SPACER-LENS:PROJECTION,FELT,-,-,-,BROWN	S.N.A
...3	T0109	AA67-00187A LENS-ASSY:DELTA71,CLEAR A/B	
...3	T0051	AA67-00188A LENS:DELTA71,GREEN C ELEMENT	
...3	T0107	AA91-00735B ASSY-BRKT,CRT:DP,AA91-00722A,PROJ	
....4	T0107	AA91-00722A ASSY-BRKT,CRT;SECC T1.6,PROJ	
....5	T0072	AA61-00473B BRACKET-CRT:53,SECC,T1.6,-,-,-,-	S.N.A
....5		AA61-00615B BRACKET-EARTH:54J8,PBS,TO.5,-,-,-,-	S.N.A
....5		AA61-00812A SPRING ETC-WIRE:PROJ,STS,3.6	S.N.A
...3		BP61-00091A HOLDER-CRT:PJT,PCABS GF20%,BLUE	S.N.A
...3		BP61-00079A HOLDER-DY;PJT,TO.5,NYLON66 V2	S.N.A
...3	T0078	AA27-00249A DEFLECTION YOKE;-DPD-5292AA,S/S,7,29.1	
...3	T0117	AA26-30006F TRANS FBT-ANODE CAP ASS'Y;-FWZ-50A001C,	

You can search for the updated part code through ITSELF web site.
URL : <http://itself.sec.samsung.co.kr>

7-3 ST54T8PCS/XAX

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY SKD PART							
1	AA92-07172A	ASSY SKD PART:ST54T8PCS/XAX,P55A	S.N.A	...	AA61-20129A	HOLDER-WIRE:-,NYLON-66,-,-,NTR,DAFC-25	S.N.A
..2	T0118	AA26-00101A TRANS FBT-H/V DISTRIBUTOR:FWZ50A001E/FFA		...	AA61-01132A	VELCRO-A-COMMANDO BST1 1/4H	S.N.A
..2		AA63-10002A BAND-TIE:NYLON66 V2,L100,NTR	S.N.A	..2	BP96-00340A	ASSY COVER P-DOOR RACK:DP,BP64-00154A,54	S.N.A
..2		AA65-30018A CLAMPER CORE-WIRE:DONG-A,NYLON-66,-,-,-	S.N.A	..3	T0081	6003-001323 SCREW-TAPTITE:RH,+B,M4,L12,NI PLT,SWRCH	S.N.A
..2		AA65-30104B CLAMPER CORE-WIRE:ALL MODEL,NYLON 66,V2,	S.N.A	..3	T0081	6003-001374 SCREW-TAPTITE:FH,+B,M4,L12,NI PLT,SWRCH	
..2		AA65-30111A CLAMPER CORE-WIRE:ALL MODEL,NYLON,V0,-,W	S.N.A	..3	CIS1	BP64-00154A CABINET-DOOR,RACK:54T8,HIPS,HB,GRAY	S.N.A
..2	T0066	AA96-20112C ASSY POWER CORD:-,EP2/NO,H/C250,KJ10,THA	S.N.A	..3		BP64-00208A WINDOW-DOOR RACK:54T8,GLASS,T3.0,...,BR,	S.N.A
..3		3811-000401 WIRE-PVC CU:BCWA,300V,ROLL,17/0.16mm,#22	S.N.A	..2		BP96-00341A ASSY MISC P-BRKT SCREEN TB:DP,BP61-00189	S.N.A
..3	T0077	AA39-10006K CBF POWER CORD:-,KJ-10,SPT-2.2/18AWG,240	S.N.A	..3	T0254	BP61-00189A BRACKET-SCREEN,TB:54T8,SECC,T1.0,SCREEN	S.N.A
..3		AA61-20284A HOLDER:P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A	..2		BP96-00342A ASSY MISC P-BRKT SCREEN RL:DP,BP61-00190	S.N.A
ASSY K/D-SKD P/MATERIAL							
1	AA98-01629A	ASSY K/D-SKD P/MATERIAL:SKD FORMAT-3	S.N.A	..3	T0056	BP61-00190A BRACKET-SCREEN,RL:54T8,SECC,T1.0,SCREEN	S.N.A
..2		AA69-00305A BAG AIR:ALL,LDPE,1000,500,CLR,	S.N.A	..2		BP98-00192A ASSY K/D-WOOD:54T8,WOOD	S.N.A
..2		AA69-00306A BAG AIR:LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A	..3		AA61-00094C HOLDER-RAIL:PCJ533R,ABS,-,-,-,BLK,HB,480	S.N.A
..2		AA69-90001A CHEMICALS-SILICAGEL:-,-,-,-,M2.5GR,-,-	S.N.A	..3		AA61-00458C CASTER:,URETHANE,OD40,BLK,H47,95'	S.N.A
..2		AA60-40006A PIN-STAPLE:AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A	..3		AA61-00507B HOLDER-CABINET,WOOD:43,54,62J8,ABS,-,-,-	S.N.A
..2	WO	AA63-10007C BAND-PP:W18,CLEA,1G	S.N.A	..3		AA61-00616B HOLDER-CRT,MAIN:54J7,DP,-,-,-,AA61-005	S.N.A
ASSY COVER FRONT							
1	M0001	BP90-00142H ASSY COVER FRONT:ST54T8PCS/XAX,P55A	S.N.A	..3		AA61-00506B HOLDER-CRT,MAIN:43,54,62J8,HIPS,-,-,-,BL	S.N.A
..2	HC+CW	6009-001296 SCREW-SPECIAL:BH,+,-,M4,L12(11),ZPC(BLK)		..3		AA61-01115A HOLDER-VENT:55W9,HIPS HB,BLK	S.N.A
..2	T0076	AA39-00284A LEAD CONNECTOR-ASSY:SVP-47W3HD,UL2547#26		..3		AA63-00384A COVER-DUCT:DP 54J8,-,-,-,HB,-,AA63-003	S.N.A
..2		AA60-00072B SPACER-COVER,DUST:43,54,62J9,SPONGE 94HF	S.N.A	..3		AA63-00348B COVER-DUCT:54,62J8,HIPS,-,-,-,HB,BLK,-	S.N.A
..2	T0069	AA60-00091N SPACER-FELT:-,FELT,70X10,-,-,BLK,T1.0,-,	S.N.A	..3		AA64-02859A CABINET-BOSS,RACK:55W9,HIPS,HB,NTR	S.N.A
..2		AA61-00618C GUIDE-FLOW:54J8,J7,ABS,IVORY,V0	S.N.A	..3		BP61-00075A HOLDER-JERSEY,ASSY:W3,ABS V0,GRAY,63-000	S.N.A
..2	T0069	AA63-60002V SPACER-FELT:-,FELT,-,-,-,BLK,T0.3,-,60X4	S.N.A	..3	T0069	AA63-00099C SPACER-FELT:47W3,FELT,BLK,T0.35,30*30	S.N.A
..2		AA63-60002V SPACER-FELT:-,FELT,-,-,-,BLK,T0.3,-,60X4	S.N.A	..3		AA61-00508D HOLDER-JERSEY:W3,ABS V0,GRAY,G4309	S.N.A
..2	T0069	AA63-60131A SPACER-FELT:SVP403J,FELT,-,-,-,BLK,T0.5,	S.N.A	..3		BP61-00191A HOLDER-MASK,TOP:54T8,ABS HB,BLK	S.N.A
..2		AA65-00016A CLAMPER CORE-CABLE:PJTV,NYLON,NTR,6/6	S.N.A	..3		BP61-00191B HOLDER-MASK SIDE:54T8,ABS,HB,...,BLK,	S.N.A
..2		AA98-00333M ASSY K/D-SPEAKER:20W(3001-001107),8 OHM	S.N.A	..3		BP64-00207A CABINET-WOOD:54T8,WOOD,...,SILVER(SDE833	S.N.A
..3	T0082	3001-001107 SPEAKER:20W,8OHM,95DB,1300HZ		..3	HC+CW	AA60-10051A SCREW-WOOD:-,SWRCH18A,M4,L16,PH,+,-,-,ZP	S.N.A
..3	T0082	3001-001134 SPEAKER:30W,8OHM,93DB,60HZ		..3		AA61-00097A HOLDER-WIRE:-,NYLON 6/6,-,-,-,NTR,-	S.N.A
..3	T0076	AA39-00042A LEAD CONNECTOR-ASSY:2.2UF,200MM,REC,REC		..3		AA61-01133A VELCRO-B-COMMANDO,BST1 1/4H	S.N.A
..3		AA98-00049A ASSY-LEAD,CON:-,LEAD-CON,CORE,AA39-20505	S.N.A	..3	HC+CW	AA60-10051B SCREW-WOOD:-,SWRCH18A,M3.5,L11,RH,+,-,-,	S.N.A
..4	T0121	3301-001201 CORE-FERRITE:AE,21x11x32mm,1500,280G		..3		BP61-00284A HOLDER-MASK CORNER:54T8,ABS HB,BLK	S.N.A
..2		BP61-00043B HOLDER-SENSOR:W9,PC HB,VIOLET	S.N.A	..3		AA61-00856B BRACKET-DOOR:47W3,SECC,T1.0,BLK	S.N.A
..2		BP65-00004N CLAMPER CORE-WIRE:5207,NYLON	S.N.A	..2	T0115	AA61-00617B BRACKET-CRT,MAIN:DP:54J7,AA61-00475B	S.N.A
..2	T0064	BP65-00005A CLAMPER CORE:5207,NYLON	S.N.A	..3	T0115	AA61-00475B BRACKET-CRT,MAIN:54,SECC,T1.6,-,-,-,-	
..2	T0102	BP73-00004A RUBBER-CAP:42W5,SILICONE,WHT,RUBBER		..3		AA63-10007C BAND-PP:W18,CLEA,1G	S.N.A
..2	T0076	BP96-00338B ASSY COVER P-FRONT MASK:DP,BP64-00164E,5	S.N.A	..2	T0053	AA67-00116B SCREEN FRESNEL:53,1125*854,T2	
..3		AA65-00020A CLAMPER CORE-WIRE:55W9,NYLON 66	S.N.A	..2	T0110	AA67-00130A SUN SCREEN-AG:54J8,1125*853",T=82%,G=110	
..3	T0017	BP64-00164E CABINET-FRONT MASK:54T8,HIPS,HB,G4309,SV	S.N.A	..2	T0056	AA67-00199A SCREEN-TINT:54,1123*852,P=0.5,DNP	
..3	T0102	BP73-00004A RUBBER-CAP:42W5,SILICONE,WHT,RUBBER		..2	T0069	AA60-00091A SPACER-FELT:-,FELT,150X10,-,-,BLK,T0.35,	S.N.A
..3		BP61-00285A HOLDER-MASK SNAP:54T8,HIPS HB,BLK	S.N.A	ASSY COVER REAR			
..2	T0071	BP96-00339B ASSY COVER P-FRONT BOT:DP,BP64-00151D,54	S.N.A	1	M0002	BP90-00143E ASSY COVER REAR:ST54T8PCS/XAX,P55A	S.N.A
..3	T0081	6003-001019 SCREW-TAPTITE:RH,+B,M4,L12,ZPC(BLK),SWR		..2	T0081	6002-000522 SCREW-TAPPING:TH,+2,M4,L15,ZPC(BLK),SWR	
..3	T0081	6003-001019 SCREW-TAPTITE:RH,+B,M4,L12,ZPC(BLK),SWR		..2	T0081	6002-000522 SCREW-TAPPING:TH,+2,M4,L15,ZPC(BLK),SWR	
..3		AA61-01104A HOLDER-LOCK:Z7,ABS	S.N.A	..2	T0081	6002-000522 SCREW-TAPPING:TH,+2,M4,L15,ZPC(BLK),SWR	
..3		BP60-00004A SPACER-BUMPON:55W9,RUBBER,5MM	S.N.A	..2	T0081	6002-000522 SCREW-TAPPING:TH,+2,M4,L15,ZPC(BLK),SWR	
..3		BP61-00108A GUIDE-KONB,CONTROL:42W4,G3676,42W4,ABS HS,N.A		..2	T0081	6002-000522 SCREW-TAPPING:TH,+2,M4,L15,ZPC(BLK),SWR	
..3		BP64-00078A WINDOW REMOCON-LED:42W4,PC,42W4,PC,CLEAS,N.A		..2	T0081	6002-000522 SCREW-TAPPING:TH,+2,M4,L15,ZPC(BLK),SWR	
..3		BP64-00151D CABINET FRONT-BOT:54T8,HIPS,HB,G4309,SV0	S.N.A	..2	T0081	6002-000522 SCREW-TAPPING:TH,+2,M4,L15,ZPC(BLK),SWR	
..3	T0022	BP64-00165A KNOB CONTROL:54T8,ABS,HB,GRAY,G3676		..2	T0081	6002-000522 SCREW-TAPPING:TH,+2,M4,L15,ZPC(BLK),SWR	
..3	T0023	BP64-00166A KNOB POWER:54T8,ABS,HB,GRAY,G3676		..2	T0081	6002-000522 SCREW-TAPPING:TH,+2,M4,L15,ZPC(BLK),SWR	
..3	T0057	BP64-00178A BADGE-BRAND:ALL,AL,T1.5,78,13.0,BLK,SIL	S.N.A	..2	T0081	6002-000522 SCREW-TAPPING:TH,+2,M4,L15,ZPC(BLK),SWR	
..3	T0081	6003-001019 SCREW-TAPTITE:RH,+B,M4,L12,ZPC(BLK),SWR		..2	HC+CW	6005-001003 SCREW-WOOD:HH,+M4,L19,ZPC(BLK),SWRCH18 S.N.A	
..3	CIS7	AA61-60003J SPRING ETC-CS:-,SUS304,-,-,OD6,N7,OD6,-,	S.N.A	..2	HC+CW	6005-001003 SCREW-WOOD:HH,+M4,L19,ZPC(BLK),SWRCH18AS.N.A	
				..2	HC+CW	6005-001003 SCREW-WOOD:HH,+M4,L19,ZPC(BLK),SWRCH18AS.N.A	
				..2	HC+CW	6005-001003 SCREW-WOOD:HH,+M4,L19,ZPC(BLK),SWRCH18AS.N.A	
				..2	HC+CW	6005-001003 SCREW-WOOD:HH,+M4,L19,ZPC(BLK),SWRCH18AS.N.A	
				..2		AA61-01134A HOLDER-MIRROR,BOT:43,54T6,HIPS HB,BLK	S.N.A
				..2	T0112	AA64-01379B CABINET-BACK,TOP:54J8,HIPS,-,-,-,HB,BLK,	
				..3		0103-001229 RESIN-HIPS:HR-1360,GRY,C7425,HB	S.N.A
				..2	CBT	AA64-60449B INLAY-COVER:SP-434JMF,PS,T0.5,149.3X69.5	S.N.A
				..2		AA65-30008A CLAMPER CORE-CORD:-,PE,HB,-,BLK,-	S.N.A
				..3	T0068	AA91-00661A ASSY-BRKT,MIRROR:DP:91-00489B 22KG,54J9	S.N.A
				..3	T0068	AA91-00489B ASSY-BRKT,MIRROR:-,SECC-1 T1.0,54J8	
				..4	T0069	AA60-00073A SPACER-FELT:54J8,FELT,-,-,-,T1.0,-,210	S.N.A
				..4		AA61-00512B BRACKET-MIRROR:43,53,61J8,SECC-1,T1.0,-,	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark	
...2	AA91-00887A	ASSY-HOLDER,MIRROR(R);HIPS HB BLK,INLAY	S.N.A	△...4	T432	AA26-00053A	TRANS-;...;1.2mH;...;31.5KHZ;-	
...3	AA61-00873A	HOLDER-MIRROR,R;54J8,HIPS HB,BLK	S.N.A	△...4	T481	AA26-00091A	TRANS-HV-STORAGE;4mH;-;14P,830uH,180V,10	
...3	AA64-00263H	INLAY-FORM;54J8,PVC FORM,T2.0,BLK,220X7	S.N.A	△...4	T444S	AA26-00100A	TRANS FBT;FFA97513L,CT29A7DR,0.3mH,-;-	
...2	AA91-00887B	ASSY-HOLDER,MIRROR(L);HIPS HB BLK,INLAY	S.N.A	△...4	T431	AA26-50001U	TRANS-HORIZ.DRIVE;-;-;28mH;-;-;105uH,-	
...3	AA61-00873B	HOLDER-MIRROR,L;54J8,HIPS HB,BLK	S.N.A	△...4	T461	AA26-50001V	TRANS-HORIZ.DRIVE;-;-;6.0mH;-;-;113uH,-	
...3	AA64-00263H	INLAY-FORM;54J8,PVC FORM,T2.0,BLK,220X7	S.N.A	...4	L432	AA27-00056A	COIL HORIZ. WIDTH;-;600uH,YL9N 15x27.5 C	
...2	T0062	BP61-00180C	HOLDER-POWER:HIPS,T8,O7,V0,BLK	S.N.A	...4	L862	AA27-10001C	COIL CHOKE;-;100uH,K;-;5.0A,ST,700UH-K(R
...2	T0015	BP64-00262A	CABINET BACK-BOT;DP;BP64-00152A,54T8,HIP	S.N.A	...4	L863	AA27-10001C	COIL CHOKE;-;100uH,K;-;5.0A,ST,700UH-K(R
...3	T0112	BP64-00152A	CABINET-BACK,BOT;54T8,HIPS,HB,BLK	S.N.A	...4	L864	AA27-10002L	COIL CHOKE;-;24uH,K;-;2A;-;24UH-K,10x10m
...2	BP64-00263A	CABINET BACK-SIDE R;DP;BP64-00153A,54T8,	S.N.A	△...4	LR401S	AA27-30003M	COIL LINEARITY;-;5uH,OWA14x15,USRC0.1x60	
...3	T0014	BP64-00153A	CABINET-BACK,SIDE R;54T8,HIPS,HB,BLK	S.N.A	△...4	LX801S	AA29-30002L	FILTER LINE NOISE;-;10mHMIN,5A,AC90-260V
...2	BP64-00264A	CABINET BACK-SIDE L;DP;BP64-00153B,54T8,	S.N.A	△...4	LX804S	AA29-30002M	FILTER LINE NOISE;-;1mHMIN,5A,AC90-260V,	
...3	T0015	BP64-00153B	CABINET-BACK SIDE L;54T8,HIPS,HB,BLK,	S.N.A	△...4	LX803S	AA29-30002M	FILTER LINE NOISE;-;1mHMIN,5A,AC90-260V,
...2	T0092	BP96-00077E	ASSY COVER P-TERMINAL,ANT;DP;42W5,HIPS,V	S.N.A	△...4	LX802S	AA29-30002M	FILTER LINE NOISE;-;1mHMIN,5A,AC90-260V,
...3	T0092	BP96-00038A	ASSY COVER P-TERMINAL,ANT;42W5,HIPS VO,B	S.N.A	...4	T0076	AA39-00180A	LEAD CONNECTOR-ASSY,14P,100MM,YBNH250-1
...4	AA64-02836B	INLAY-TERMINAL,NT;42W5,PS SHEET,T0.5,BLK	S.N.A	...4	GT01	AA60-40012D	PIN-GT,ASSY;T1.6,6-12.5,-NYLON66	
...4	AA65-00023A	TERMINAL-BOARD,ANT;HIPS VO,BLK	S.N.A	...4	D856	AA96-00243E	ASSY H/S;-;SOUND,AA62-00045A,FMG-G26S	
...2	T0108	AA67-00080A	MIRROR-BACK;54J8,GLASS,940.5*684.5*674.5	S.N.A	...4	D855	AA96-00243E	ASSY H/S;-;SOUND,AA62-00045A,FMG-G26S

ASSY CHASSIS

1	M0017	BP91-00926A	ASSY CHASSIS;ST54T8PCS/XAX,P55A	S.N.A	...5	T0083	0402-000231	DIODE-RECTIFIER;FMG-G26S,600V,4A,TO-220F	S.N.A
...2	BP91-00801T	ASSY MISC-CHASSIS PACK;ST54T8PCS/XAX,P55	S.N.A	...5	T0081	6003-000335	SCREW-TAPTITE;RH,+2S,M3,L8,ZPC(YEL),SWR	S.N.A	
...3	T0081	6003-001023	SCREW-TAPTITE;RWH,+B,M3,L10,ZPC(YEL),SW	S.N.A	...5	AA62-00045A	HEAT SINK-PS;-;T1.0;-;DREAM;-;-;-	S.N.A	
...3	T0081	6003-001023	SCREW-TAPTITE;RWH,+B,M3,L10,ZPC(YEL),SW	S.N.A	△...4	Q433	AA96-00243H	ASSY H/S;-;POWER,AA62-00045A,KSD73Y,C17A	
...3	T0070	AA61-01127A	HOLDER-CHASSIS;COMMANDO,HIPS VO,G4309	S.N.A	...5	T0090	0205-000129	GREASE-SILICON;SC102,JAPAN	S.N.A
...3	AA98-01177B	ASSY K/D-P/MATERIAL:P.JTV(COMANDO),P55A	S.N.A	...5	T0081	6003-000335	SCREW-TAPTITE;RH,+2S,M3,L8,ZPC(YEL),SWR	S.N.A	
...4	AA63-10007C	BAND-PP;W18,CLEA,1G	S.N.A	...5	T0081	6003-000334	SCREW-TAPTITE;RH,+2S,M3,L6,ZPC(YEL),SWR	S.N.A	
...4	AA69-01808A	BAG-SHEET,LDPE(ANTISTATIC),TO.05,950,90	S.N.A	...5	CIS	AA62-00051A	HEAT SINK-PS;-;SILVER,HOLE 31mm,ALL,	S.N.A	
...4	AA69-01403A	WRAP VINYL-PACKING;SKD CHASSIS,LDPE,TO.0	S.N.A	...5	CIS	AA62-30177A	HEAT SINK-PN;-;CUS-1,T1.0;-;KCVC12D;-;-;1	S.N.A	
...3	T0097	BP94-00518S	ASSY PCB MISC-PWR DEF;ST54T8PCX/XAX,P55A	S.N.A	...5	IC063	BP13-00004A	IC HYBRID;STR-X6459A,COMMANDO,7,-20 TO +	
...4	0202-000187	SOLDER-WIRE FLUX;-;RS60S,D1.2,63Sn/37Pb	S.N.A	△...4	D811S	AA96-00276A	ASSY H/S;-;BRIDGE,AA62-00052A,RBV606,WAS	S.N.A	
...4	T0083	0402-000236	DIODE-RECTIFIER;G1824,400V,5A,-;TP	S.N.A	...5	T0083	0402-000549	DIODE-BRIDGE;RBV606,600V,6A,-;BK	S.N.A
...4	T0083	0402-000250	DIODE-RECTIFIER;RG4C,1000V,1A,-	S.N.A	...5	T0081	6003-000335	SCREW-TAPTITE;RH,+2S,M3,L8,ZPC(YEL),SWR	S.N.A
...4	DZS801	0406-001007	DIODE-TVS;P6KE180A,171/180/189V,600W,CAS	S.N.A	...5	AA60-30003A	WASHER;T1.5,SBHG-1	S.N.A	
...4	T0090	0502-000405	TR-POWER;-;NPN,70W,TO-220,BK,10	S.N.A	△...4	IC421	AA96-00475B	ASSY H/S;SILICON-OIL,FMLG-12S(4),AA62-00	S.N.A
△...4	PC811S	0604-001032	PHOTO-COUPLER;TR,170-260%,300mW,DIP-4,ST	S.N.A	...5	T0083	0402-000233	DIODE-RECTIFIER;FML-G12S,200V,5A,-;-	S.N.A
△...4	PC801S	0604-001032	PHOTO-COUPLER;TR,170-260%,300mW,DIP-4,ST	S.N.A	...5	IC012	1203-000165	IC-POSI,ADJUST REG;-;78R12,TO-220,4P,-;PL	S.N.A
...4	DJ410	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV	S.N.A	...5	T0081	6003-000334	SCREW-TAPTITE;RH,+2S,M3,L6,ZPC(YEL),SWR	S.N.A
...4	IC012	1203-000162	IC-POSI,ADJUST REG;-;317,TO-220,3P,-;PLAS	S.N.A	...5	AA62-00066B	HEAT SINK;D2,D3,AL,T1.0,89,70,-;AA62-00	S.N.A	
...4	T0086	1203-000610	IC-PWM CONTROLLER;494,DIP,16P,300MIL,PLA	S.N.A	...4	IC301	AA96-00623A	ASSY H/S;-;POWER,AA62-00056A,LA7845	S.N.A
...4	T0123	1203-001006	IC-VOLTAGE REGULATOR;78R05,TO-220F,4P,-	S.N.A	...5	T0088	1204-000517	IC-VERTICAL DEF;LA7845,SIP,7P,-;PLASTIC	S.N.A
...4	IC851	1203-001400	IC-POWER PRECALER;SE110N,TO-220(SIP),3P	S.N.A	...5	T0081	6003-000334	SCREW-TAPTITE;RH,+2S,M3,L6,ZPC(YEL),SWR	S.N.A
...4	T0086	1203-002177	IC-PWM CONTROLLER;VIPER12ADIP,DIP,8P,300	S.N.A	...5	AA62-00056A	HEAT SINK-PS;-;T1.0,-;41*35*70,D2,-;-	S.N.A	
△...4	NT801S	1404-001195	THERMISTOR-NTC;5.1ohm,15%,2900,27mW/C,BK	S.N.A	...4	Q431	BH99-00033H	ASSY HEAT/SINK;BH62-00038A,SPRING,FJL692	S.N.A
△...4	VX801S	1405-000187	VARISTOR;750V,1250A,12.5x7mm,TP	S.N.A	...5	T0083	0402-001296	DIODE-RECTIFIER;FMP-3FU,1.5KV,5A,TO-3PF,	S.N.A
...4	R384	2002-001079	R-COMPOSITION;470kohm,5%,1/2W,AA,TP,4x10	S.N.A	...5	T0060	BH61-70003A	SPRING ETC;CVT4857,STS304-W1/2H,W3,8,-;L	S.N.A
...4	C598	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	S.N.A	...5	T0090	0502-001230	TR-POWER;FJL6920YDTU,N,20000MMW,TO-264 F	S.N.A
...4	C598	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	S.N.A	...5	CIS	BH62-00038B	HEAT SINK-FBT;COMMANDO,A1050S,T2.0,85*80	S.N.A
...4	C598	2201-000446	C-CERAMIC,DISC;3.3NF,20%,400V,Y5U,TP,15X	S.N.A	...5	CIS	BH73-00028A	SILICON/RUBBER-HS;CDT ALL,SILICON,26*33*	S.N.A
...4	C598	2201-000963	C-CERAMIC,DISC;1NF,20%,400V,Y5U,TP,9.5X6	S.N.A	△...4	TS801S	BP26-00001A	TRANS SWITCHING-POWER;19B012,P55A,HCM421	S.N.A
△...4	CR471S	2301-001091	C-FILM,MPPF;470nF,5%,400V,TP,26x21.5x14.	S.N.A	△...4	T801S	BP26-00006A	TRANS SWITCHING;EERS345,P55A,HCM4215W,80	S.N.A
△...4	CR431S	2301-001343	C-FILM,MPPF;3.9nF,5%,2kV,TP,29x9.5x16mm,	S.N.A	...4	T0076	BP39-00014A	LEAD CONNECTOR-ASSY;P55A/HCM4215W,UL1007	S.N.A
△...4	CR430S	2301-001343	C-FILM,MPPF;3.9nF,5%,2kV,TP,29x9.5x16mm,	S.N.A	...4	Q473	BP39-00084A	LEAD CONNECTOR;HCL4715WB,UL1617#22,UL/CS	S.N.A
△...4	CX801S	2306-000112	C-FILM,MPPF;100nF,20%,250V,BK,-;15mm	S.N.A	...5	CIS	0205-001027	OIL-SILICON;G746,-;-	S.N.A
△...4	CX802S	2306-000112	C-FILM,MPPF;100nF,20%,250V,BK,-;15mm	S.N.A	...5	T0090	0502-001100	TR-POWER;2SC4125,NPN,70W,TO-3PML,BK,8-	S.N.A
△...4	CR436S	2306-000235	C-FILM,MPPF;560nF,5%,400V,TP,26*22.5*14.	S.N.A	...5	Q409	0505-001722	FET-SILICON;IRFS640B,N,200V,18A,0.180HM,	S.N.A
...4	C491	2306-000322	C-FILM,MPPF;12nF,5%,1.6KV,TP,29x20.5x13,	S.N.A	...5	T0081	6003-000333	SCREW-TAPTITE;RH,+2S,M3,L10,ZPC(YEL),SW	S.N.A
...4	CR473S	2306-000322	C-FILM,MPPF;12nF,5%,1.6KV,TP,29x20.5x13,	S.N.A	...5	CIS	AA60-30001A	WASHER-PLATE;M3,JD3.5,15X8.5,T1.0,SBHG	S.N.A
...4	C832	2306-000323	C-FILM,MPPF;2.2nF,5%,1.6KV,TP,28.5x15.5x	S.N.A	...5	CIS	BP62-00001A	HEAT SINK;COMMANDO,A1050P,T2.0,W62.0,H50	S.N.A
△...4	CR474S	2306-000326	C-FILM,MPPF;4.7nF,5%,1.6KV,TP,28.5x16x9m	S.N.A	...4	D477	BP97-00511P	ASSY AUTO;ST54T8PCX/XAX,P55A	S.N.A
...4	C701	2401-000142	C-AL;1000uF,20%,16V,WT,TP,10x20.5,	S.N.A	...5	D478	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	S.N.A
...4	C701	2401-000701	C-AL;2200uF,20%,250V,GP,-;35x70mm,1	S.N.A	...5	D479	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	S.N.A
...4	C701	2401-000701	C-AL;2200uF,20%,250V,GP,-;35x70mm,1	S.N.A	△...5	DR401S	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	S.N.A
...4	C701	2401-000787	C-AL;220uF,20%,160V,GP,TP,16x31.5mm	S.N.A	△...5	DR402S	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	S.N.A
...4	C701	2401-002251	C-AL;470uF,20%,200V,GP,BK,25x40mm,1	S.N.A	...5	D301	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	S.N.A
...4	C701	2401-003076	C-AL;3300UF,20%,50V,WT,BK,18X35.5MM,7.5	S.N.A	...5	D385	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	S.N.A
...4	C701	2401-003076	C-AL;3300UF,20%,50V,WT,BK,18X35.5MM,7.5	S.N.A					
...4	C701	2401-003076	C-AL;3300UF,20%,50V,WT,BK,18X35.5MM,7.5	S.N.A					
...4	T0121	3301-001201	CORE-FERRITE;AE,21x11x32mm,1500,280G	S.N.A					
△...4	FP801S	3601-000300	FUSE-CARTRIDGE;250V,6.3A,SLOW-BLOW,GLASS	S.N.A					
...4	CN906	3711-003043	CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH	S.N.A					

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5	D436	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	5	RS804	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	D442	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	5	R855	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	D443	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	5	RS803	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	DS804	DIODE-SWITCHING;BAV21,250V,250mA,DO-35,T	5	R814	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	DS802	DIODE-SWITCHING;BAV21,250V,250mA,DO-35,T	5	R813	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	T0083	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	5	R812	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	T0083	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	5	R811	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	T0083	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	5	R439	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	T0083	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	5	R438	R-CARBON(S);100KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	T0083	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	5	R834	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	T0083	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	5	R125	R-CARBON-1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	T0083	DIODE-RECTIFIER;RGP10J,600V,1A,DO-41,TP	5	R125	R-CARBON-1.8MOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	T0083	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	5	R125	R-CARBON-100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	T0083	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	5	R125	R-CARBON-100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	T0083	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	5	R125	R-CARBON-10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	T0083	DIODE-RECTIFIER;RG10V,400V,1.2A,DO-201,T	5	R125	R-CARBON-10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	T0083	DIODE-RECTIFIER;RH1A,600V,0.6A,DO-204AC	5	R125	R-CARBON-10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	T0083	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	5	R125	R-CARBON-150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	T0083	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	5	R125	R-CARBON-1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	T0083	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	5	R125	R-CARBON-1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	T0083	DIODE-RECTIFIER;TVR10G,400V,1.0A,DO-41,T	5	R125	R-CARBON-1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	T0083	DIODE-RECTIFIER;RP1H,2000V,1A,-,TP	5	R125	R-CARBON-2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;TZP12A,12V,11.4-12.6V,1W,DO-	5	R125	R-CARBON-220KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;TZP7.5B,7.5V,7.5-8.4V,1W,DO-	5	R125	R-CARBON-220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ4.7B,4.7V,4.55-4.8V,500m	5	R125	R-CARBON-22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	5	R125	R-CARBON-270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	5	R125	R-CARBON-2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ9.1B,9.1V,8.57-9.01V,500	5	R125	R-CARBON-2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;TZP15B,15V,14.7-16.5V,1W,DO-	5	R125	R-CARBON-2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ30D,30V,29.02-30.51V,500	5	R125	R-CARBON-3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ3.0A,2.85-3.07V,500mW,DO	5	R125	R-CARBON-3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	5	R125	R-CARBON-4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ4.7C,4.68-4.93V,500mW,DO	5	R125	R-CARBON-4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	5	R125	R-CARBON-4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	5	R125	R-CARBON-4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	5	R125	R-CARBON-4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ15C,14.35-15.09V,500mW,D	5	R125	R-CARBON-4.70OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	5	R125	R-CARBON-4.70OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	5	R125	R-CARBON-430OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ18A,16.22-17.06V,500mW,D	5	R125	R-CARBON-430OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ22A,20.15-21.20V,500mW,D	5	R125	R-CARBON-430OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	5	R125	R-CARBON-430OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	5	R125	R-CARBON-430OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ24B,22.61-23.77V,500mW,D	5	R125	R-CARBON-430OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ30A,26.99-28.39V,500mW,D	5	R125	R-CARBON-47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DZ016	DIODE-ZENER;MTZJ30A,26.99-28.39V,500mW,D	5	R125	R-CARBON-5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	DS805	DIODE-SCHOTTKY;RK16,60V,1.5A,DO-204AC,TP	5	R125	R-CARBON-5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	QR401S	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	5	R125	R-CARBON-680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	Q482	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	5	R125	R-CARBON-91KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	Q432	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	5	R840	R-CARBON(S);1.2KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	Q461	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	RS807	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	Q471	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	RR401S	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	Q474	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	R854	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	Q481	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	R839	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	Q851	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	R434	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	QS801	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	R413	R-CARBON(S);1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	QS802	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	R837	R-CARBON(S);22KOHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	Q301	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	R468	R-CARBON(S);3.9KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	Q381	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	RS802	R-CARBON(S);3.9OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	Q382	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	R431	R-CARBON(S);470OHM,5%,1/2W,AA,TP,2.4X6.4M	
.....5	Q401	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	R433	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	Q402	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	R410	R-CARBON(S);5.6KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	Q421	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	RS806	R-CARBON(S);6.8KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	Q451	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	5	R459	R-CARBON(S);820OHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	Q409	FET-SILICON;FQP630TSTU,N,200V,9A,0.4OHM,	5	R851	R-CARBON(S);9.1KOHM,5%,1/2W,AA,TP,2.4X6.4	
.....5	Q409	FET-SILICON;FQP630TSTU,N,200V,9A,0.4OHM,	5	RP801S	R-COMPOSITION;1.8Mohm,5%,1/2W,AA,TP,3.7x	
.....5	IC012	IC-POSI.ADJUST REG. .431,TO-92,3P,4.58MIL	5	RY801S	R-COMPOSITION;4.7Mohm,5%,1/2W,AA,TP,3.7x	
.....5	VP801S	VARIABLE;560V,2500A,14x8.5mm,TP	5	R428A	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
.....5	R125	R-CARBON;390ohm,5%,1/8W,AA,TP,1.8X3.2mm	5	R428	R-COMPOSITION;1Kohm,10%,1/2W,AA,TP,3.7x9	
.....5	R125	R-CARBON;2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	5	R425	R-METAL OXIDE(S);1.2Kohm,5%,3W,AA,TP,6x1	
.....5	R125	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	5	R832	R-METAL OXIDE(S);15Kohm,5%,3W,AA,TP,6x16	
.....5	R125	R-CARBON;20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	5	R831	R-METAL OXIDE(S);15Kohm,5%,3W,AA,TP,6x16	
.....5	R308	R-CARBON(S);10HM,5%,1/2W,AA,TP,2.4X6.4MM	5	R430	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R470	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	5	R429	R-METAL OXIDE(S);22Kohm,5%,2W,AF,TP,4x12	
.....5	R422	R-CARBON(S);100OHM,5%,1/2W,AA,TP,2.4X6.4	5	R310	R-METAL OXIDE(S);150ohm,5%,2W,AF,TP,3.9x	
.....5	R493	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.4	5	R463	R-METAL OXIDE(S);150ohm,5%,2W,AF,TP,3.9x	
.....5	R836	R-CARBON(S);3.3KOHM,5%,1/2W,AA,TP,2.4X6.4	5	R460	R-METAL OXIDE(S);100ohm,5%,1W,AF,TP,2.5x	
.....5	RS808	R-CARBON(S);10KOHM,5%,1/2W,AA,TP,2.4X6.4					

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark
.....5 R841	2003-002102	R-METAL OXIDE(S):68Kohm,5%,2W,AF,TP,4x12	
.....5 R427	2003-002152	R-METAL OXIDE:10HM,5%,2W,AG,TP,6X16MM	
.....5 R427A	2003-002152	R-METAL OXIDE:10HM,5%,2W,AG,TP,6X16MM	
.....5 R426	2003-002153	R-METAL OXIDE:4.70HM,5%,2W,AG,TP,6X16MM	
.....5 R443A	2003-002156	R-METAL OXIDE:560OHM,5%,2W,AG,TP,6X16MM	
.....5 R443	2003-002156	R-METAL OXIDE:560OHM,5%,2W,AG,TP,6X16MM	
.....5 R464	2003-002158	R-METAL OXIDE:0.680HM,5%,1W,AG,TP,4.3X12	
.....5 R421	2003-002159	R-METAL OXIDE:150OHM,5%,1W,AG,TP,4.3X12MM	
.....5 R801	2003-002285	R-METAL OXIDE(S):1.5KOHM,5%,2W,AF,TP,6X1	
.....5 R408	2004-000531	R-METAL:20Kohm,1%,1/2W,AA,TP,3.3x9mm	
.....5 R024	2004-001369	R-METAL(S):1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5 R024	2004-001386	R-METAL(S):16.9Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5 R024	2004-001395	R-METAL(S):330Kohm,2%,1/2W,AA,TP,2.4x6.4	
.....5 R024	2004-001402	R-METAL(S):6.8Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5 R024	2004-001408	R-METAL(S):91Kohm,1%,1/2W,AA,TP,2.4x6.4m	
.....5 R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5 R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5 R024	2004-001897	R-METAL(S):43.2Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5 R024	2004-001897	R-METAL(S):43.2Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5 R024	2004-001984	R-METAL(S):26.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5 R024	2004-001984	R-METAL(S):26.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5 R024	2004-001984	R-METAL(S):26.7Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5 R024	2004-002011	R-METAL(S):110Kohm,1%,1/2W,AA,TP,2.4x6.4	
.....5 R024	2004-004001	R-METAL(S):180Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5 R024	2004-004029	R-METAL(S):10Kohm,1%,1/2W,AA,TP,2.5x6.5m	
.....5 R024	2004-004046	R-METAL(S):430Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5 R024	2004-004046	R-METAL(S):430Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5 R024	2004-004366	R-METAL(S):1.3Kohm,1%,1/2W,AA,TP,2.5x6.5	
.....5 R024	2004-005051	R-METAL(S):2.2KOHM,1%,1/2W,AA,TP,2.4X6.4	
.....5 R472	2008-000252	R-FUSIBLE(S):0.47ohm,10%,1/2W,AF,TP,2.5x	
.....5 R465	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m	
.....5 R449	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m	
.....5 R447	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m	
.....5 R445	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m	
.....5 R441	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m	
.....5 R442	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m	
.....5 R442A	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x10m	
.....5 R440	2008-000282	R-FUSIBLE:0.47ohm,5%,1W,AA,TP,3.9x12mm	
.....5 R424	2008-000289	R-FUSIBLE(S):1ohm,5%,1W,AA,TP,3.9x10mm	
.....5 R307	2008-000290	R-FUSIBLE(S):2.4ohm,5%,2W,AF,TP,3.9x10mm	
.....5 R486	2008-001018	R-FUSIBLE(S):0.47ohm,10%,2W,AF,TP,3.9x10	
.....5 R838	2008-001053	R-FUSIBLE:22ohm,5%,1/2W,AF,TP,2.5x6.5mm	
.....5 R306	2008-001076	R-FUSIBLE(S):1.8ohm,5%,2W,AF,TP,3.9x10mm	
.....5 R437	2008-001087	R-FUSIBLE(S):1.8ohm,5%,2W,AG,TP,3.9x12mm	
.....5 R485	2008-001137	R-FUSIBLE(S):3.3ohm,5%,1W,AF,TP,3.9x10mm	
.....5 R462	2008-001145	R-FUSIBLE:4.70HM,5%,1/2W,AF,TP,2.5X6.5MM	
.....5 R853	2008-001152	R-FUSIBLE(S):1.3KOHM,5%,1/2W,AA,TP,2.5X6.5	
.....5 R833	2009-001096	R-METAL PLATE:0.07ohm,5%,5W,CL,BK,5x14x1	
.....5 R405	2009-001109	R-TEMPERATURE:240ohm,5%,1/4W,AA,TP,2.3x6	
.....5 RR471S	2103-001024	VR-SEMI:50Kohm,25%,0.3W,TOP	
.....5 RR402S	2103-001086	VR-SEMI:100KOHM,25%,0.3W,TOP	
.....5 C598	2201-000017	C-CERAMIC,DISC:1NF,10%,50V,Y5P,TP,5X3.5M	
.....5 C598	2201-000017	C-CERAMIC,DISC:1NF,10%,50V,Y5P,TP,5X3.5M	
.....5 C598	2201-000017	C-CERAMIC,DISC:1NF,10%,50V,Y5P,TP,5X3.5M	
.....5 C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP,	
.....5 C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP,	
.....5 C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP,	
.....5 C598	2201-000132	C-CERAMIC,DISC:0.1NF,10%,500V,Y5P,TP,6.5	
.....5 C598	2201-000132	C-CERAMIC,DISC:0.1NF,10%,500V,Y5P,TP,6.5	
.....5 C598	2201-000132	C-CERAMIC,DISC:0.1NF,10%,500V,Y5P,TP,6.5	
.....5 C598	2201-000132	C-CERAMIC,DISC:0.1NF,10%,500V,Y5P,TP,6.5	
.....5 C598	2201-000138	C-CERAMIC,DISC:0.1NF,10%,50V,Y5P,TP,4X4M	
.....5 C598	2201-000146	C-CERAMIC,DISC:0.1NF,5%,50V,SL,TP,5X3.5M	
.....5 C598	2201-000146	C-CERAMIC,DISC:0.1NF,5%,50V,SL,TP,5X3.5M	
.....5 C598	2201-000180	C-CERAMIC,DISC:10NF,10%,50V,Y5V,TP,7X3MM	
.....5 C598	2201-000180	C-CERAMIC,DISC:10NF,10%,50V,Y5V,TP,7X3MM	
.....5 C598	2201-000332	C-CERAMIC,DISC:2.2NF,20%,250V,Y5U,TP,9X4	
.....5 C598	2201-000332	C-CERAMIC,DISC:2.2NF,20%,250V,Y5U,TP,9X4	
.....5 C598	2201-000332	C-CERAMIC,DISC:2.2NF,20%,250V,Y5U,TP,9X4	
.....5 C598	2201-000370	C-CERAMIC,DISC:0.22NF,10%,50V,Y5P,TP,4X3	
.....5 C598	2201-000406	C-CERAMIC,DISC:0.27NF,10%,2KV,Y5P,TP,6.3	
.....5 C598	2201-000551	C-CERAMIC,DISC:0.47NF,10%,1KV,Y5P,TP,6.3	
.....5 C598	2201-000551	C-CERAMIC,DISC:0.47NF,10%,1KV,Y5P,TP,6.3	
.....5 C598	2201-000551	C-CERAMIC,DISC:0.47NF,10%,1KV,Y5P,TP,6.3	
.....5 C598	2201-000551	C-CERAMIC,DISC:0.47NF,10%,1KV,Y5P,TP,6.3	



Loc. No.	Code No.	Description ; Specification	Remark
.....5 C598	2201-000551	C-CERAMIC,DISC:0.47NF,10%,1KV,Y5P,TP,6.3	
.....5 C598	2201-000558	C-CERAMIC,DISC:0.47NF,10%,50V,Y5P,TP,5X3	
.....5 C478	2301-000020	C-FILM,PEF:27nf,5%,100V,TP,7.3x4x12.5mm,	
.....5 C479	2301-000200	C-FILM,PEF:2.2nf,5%,200V,TP,11.0x6.0x9.0	
.....5 C477	2301-000213	C-FILM,PEF:220f,5%,250V,TP,21.5x11.7,5	
.....5 C493	2301-000356	C-FILM,PEF:47nf,5%,50V,TP,7.5x4.0x6.5,5m	
.....5 CS801	2301-000356	C-FILM,PEF:47nf,5%,50V,TP,7.5x4.0x6.5,5m	
.....5 C412	2301-000383	C-FILM,PEF:10nf,5%,60V,TP,6x7x3.2mm,5mm	
.....5 C831	2301-001216	C-FILM,PPF:47nf,5%,50V,TP,20x14.5x22.7,	
.....5 C438	2303-000002	C-FILM,PPF:8.2nf 5% 400V TP 19X18X7,7.5m	
.....5 C432	2303-000002	C-FILM,PPF:8.2nf 5% 400V TP 19X18X7,7.5m	
.....5 C460	2303-000331	C-FILM,PPF:4.7nf,5%,630V,TP,19.5x12x7,7.	
.....5 C311	2305-000149	C-FILM,MPEF:100nf,5%,100V,TP,12x12.5x6.5	
.....5 C487	2305-000178	C-FILM,MPEF:10nf,5%,100V,TP,-,5mm	
.....5 C309	2305-000285	C-FILM,MPEF:220NF,5%,100V,TP,10.5X5.5X15	
.....5 C871	2305-000289	C-FILM,MPEF:220nf,5%,63V,TP,-,5mm	
.....5 C838	2305-000412	C-FILM,MPEF:47nf,5%,63V,TP,-,5mm	
.....5 C865	2305-000427	C-FILM,MPEF:47nf,5%,100V,TP,7.5x12.5x3.5	
.....5 C303	2305-000427	C-FILM,MPEF:47nf,5%,100V,TP,7.5x12.5x3.5	
.....5 C301	2305-000427	C-FILM,MPEF:47nf,5%,100V,TP,7.5x12.5x3.5	
.....5 C429	2305-000704	C-FILM,MPEF:100nf,5%,250V,TP,16.5x10.3x5	
.....5 C480	2306-000122	C-FILM,MPF:100nf,5%,50V,TP,7.3x4.0x5.0m	
.....5 C428	2306-000122	C-FILM,MPF:100nf,5%,50V,TP,7.3x4.0x5.0m	
.....5 C701	2401-000025	C-AL:100uf,20%,16V,GP,TP,6.3x11,5	
.....5 C701	2401-000050	C-AL:10uf,20%,16V,GP,TP,5x11,2,5	
.....5 C701	2401-000164	C-AL:1000uf,20%,25V,WT,TP,12.5x20,5	
.....5 C701	2401-000262	C-AL:100uf,20%,160V,HR,TP,16x25,7.5	
.....5 C701	2401-000262	C-AL:100uf,20%,160V,HR,TP,16x25,7.5	
.....5 C701	2401-000302	C-AL:100uf,20%,25V,GP,TP,6.3x11,5	
.....5 C701	2401-000302	C-AL:100uf,20%,25V,GP,TP,6.3x11,5	
.....5 C701	2401-000360	C-AL:100uf,20%,50V,GP,TP,8x11,5,5	
.....5 C701	2401-000360	C-AL:100uf,20%,50V,GP,TP,8x11,5,5	
.....5 C701	2401-000365	C-AL:100uf,20%,50V,WT,TP,10x12.5mm,	
.....5 C701	2401-000365	C-AL:100uf,20%,50V,WT,TP,10x12.5mm,	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	
.....5 C701	2401-000603	C-AL:1uF,20%,50V,GP,TP,5X11,2	
.....5 C701	2401-000660	C-AL:2.2uf,20%,50V,GP,TP,5x11,5	
.....5 C701	2401-000698	C-AL:2200uf,20%,16V,WT,TP,12.5x25,5	
.....5 C701	2401-000703	C-AL:2200uf,20%,25V,GP,-,12.5x25mm,	
.....5 C701	2401-001026	C-AL:3.3UF,20%,50V,GP,TP,5X11,5	
.....5 C701	2401-001026	C-AL:3.3UF,20%,50V,GP,TP,5X11,5	
.....5 C701	2401-001192	C-AL:33uf,20%,50V,GP,TP,6.3x11,5	
.....5 C701	2401-001397	C-AL:470uf,20%,25V,GP,TP,10x16,5	
.....5 C701	2401-001428	C-AL:470uf,20%,50V,GP,TP,10x20,5	
.....5 C701	2401-001486	C-AL:47uf,20%,16V,HR,TP,13x20mm,5m	
.....5 C701	2401-001527	C-AL:47uf,20%,250V,HR,TP,13x25mm,5m	
.....5 C701	2401-001622	C-AL:6.8uf,20%,50V,BP,TP,16x25mm,7.	
.....5 C701	2401-001625	C-AL:6.8UF,20%,50V,GP,TP,5X11,5	
.....5 C701	2401-001655	C-AL:680uf,20%,25V,GP,TP,10x20,5	
.....5 C701	2401-001989	C-AL:4.7uf,20%,50V,BP,TP,5x11,5	
.....5 C701	2401-002144	C-AL:47uf,20%,16V,GP,TP,5x11,5	
.....5 C701	2401-002144	C-AL:47uf,20%,16V,GP,TP,5x11,5	
.....5 C701	2401-002216	C-AL:2200uf,20%,35V,GP,TP,16x25,7.5	
.....5 C701	2401-002216	C-AL:2200uf,20%,35V,GP,TP,16x25,7.5	
.....5 C701	2401-002288	C-AL:470uf,20%,50V,GP,TP,10x20,5	
.....5 C701	2401-002288	C-AL:470uf,20%,50V,GP,TP,10x20,5	
.....5 C701	2401-002300	C-AL:47uf,20%,50V,GP,TP,6.3x11,5	
.....5 C701	2401-002463	C-AL:470uf,20%,16V,GP,TP,8x11,5,5	
.....5 C701	2401-002619	C-AL:47uf,20%,25V,GP,TP,5x11,5	
.....5 C701	2401-003114	C-AL:4.7uf,20%,250V,WT,TP,10x16,5	
.....5 L431	2701-000116	INDUCTOR-AXIAL:10uH,10%,4.2x9.8mm	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 F101	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP-	
.....5 G101	3301-000287	CORE-FERRITE BEAD-AA,3.5x1.0x6.0mm,1500,	
.....5 G101	3301-000287	CORE-FERRITE BEAD-AA,3.5x1.0x6.0mm,1500,	
.....5 G101	3301-000287	CORE-FERRITE BEAD-AA,3.5x1.0x6.0mm,1500,	
.....5 G101	3301-000287	CORE-FERRITE BEAD-AA,3.5x1.0x6.0mm,1500,	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5	EY152	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A5	AA97-07275A	ASSY SMD;SVP-47W3HRT,P55A, , , S.N.A
.....5	EY151	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6D905	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
.....5	EY150	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6D906	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
.....5	EY15	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6D920	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
.....5	EY149	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6D923	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
.....5	EY13	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6D602	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
.....5	EY129	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6D901	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
.....5	EY128	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6D902	0401-000133	DIODE-SWITCHING;RLS4148,100V,200MA,SOD-8
.....5	EY127	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6DZ016	0403-001375	DIODE-ZENER;RLZ3.6B,3.6-3.845V,500mW,LL-
.....5	EY126	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6DZ016	0403-001375	DIODE-ZENER;RLZ3.6B,3.6-3.845V,500mW,LL-
.....5	EY125	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6DZ016	0403-001375	DIODE-ZENER;RLZ3.6B,3.6-3.845V,500mW,LL-
.....5	EY124	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6DZ016	0403-001375	DIODE-ZENER;RLZ3.6B,3.6-3.845V,500mW,LL-
.....5	EY123	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6DZ016	0403-001375	DIODE-ZENER;RLZ3.6B,3.6-3.845V,500mW,LL-
.....5	EY137	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6DZ016	0403-001375	DIODE-ZENER;RLZ3.6B,3.6-3.845V,500mW,LL-
.....5	EY136	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6DZ016	0403-001375	DIODE-ZENER;RLZ3.6B,3.6-3.845V,500mW,LL-
.....5	EY135	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6Q915	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
.....5	EY134	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6Q916	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
.....5	EY130	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6Q917	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
.....5	EY131	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6Q920	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
.....5	EY132	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6Q914	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
.....5	EY133	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A6Q913	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
.....5	0	AA41-00598D	PCB-SUB;HCM4215W,CEM-1,1L,D,1.6T,330X245	S.N.A6Q910	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
.....5	GT404	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6Q908	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
.....5	GT433	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6C102	0501-000344	TR-SMALL SIGNAL;KSC1623-G,NPN,200mW,SOT-
.....5	GT801	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6I912	1103-000180	IC-EEPROM;24C16,2Kx8Bit,SOP,8P,150MIL,10
.....5	GT802	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6T0087	1203-002302	IC-POSI.FIXED REG.;78RM33D,D-PAK,3P,-,PL
.....5	GT807	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6IC901	1204-001912	IC-DECODER;SDA5550M,P-MOFF,100P,-,PLASTI
.....5	GT810	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6R981	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
.....5	GT811	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6R964	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
.....5	GT14	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6R960	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
.....5	GT15	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6R959	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
.....5	GT16	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6R965	2007-000070	R-CHIP;0ohm,5%,1/10W,TP,1608
.....5	GT17	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6R956	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....5	GT33	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6R953	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....5	GT34	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6R952	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....5	GT35	AA60-40014A	PIN-GT,ASSY,AUTO	S.N.A6R969	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....3	T0073	BP94-00519A	ASSY PCB MAIN;ST54T8PCS/XAX,P55A,MEXICO	6R970	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	IC802	0202-000187	SOLDER-WIRE FLUX;-RS60S,D1.2,63Sn/37Pb	S.N.A6R972	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	IC012	1203-000119	IC-NEGA.FIXED REG.;7905,TO-220,3P,-,PLAS	6R979	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	C701	1203-000165	IC-POSTI.ADJUST REG.;78R12,TO-220,4P,-,PL	6R940	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	C701	2401-000737	C-AL;2200uf,20%,50V,GP,TP,18x35.5,7	6R909	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	C701	2401-001068	C-AL;3300uf,20%,50V,GP,BK,22x40,10	6R916	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	X601	2801-004020	CRYSTAL-UNIT;18.432MHz,30ppm,28-AAM,12pF	6R918	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	CNZ01	3703-001150	CONNECTOR-BACK PANEL;32P,2R,FEMALE,STRAI	6R939	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	CNW02	3703-001150	CONNECTOR-BACK PANEL;32P,2R,FEMALE,STRAI	6R923	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	CNW01	3703-001150	CONNECTOR-BACK PANEL;32P,2R,FEMALE,STRAI	6R922	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	CN901	3703-001187	CONNECTOR-BACK PANEL;64P,2R,FEMALE,STRAI	6R907	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	CN906	3711-003046	CONNECTOR-HEADER;BOX,9P,1R,2.5MM,STRAIG	6R917	2007-000074	R-CHIP;100ohm,5%,1/10W,TP,1608
.....4	CN906	3711-003641	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG	6R911	2007-000076	R-CHIP;330ohm,5%,1/10W,TP,1608
.....4	CN906	3711-003973	CONNECTOR-HEADER;BOX,11P,1R,2.5mm,STRAIG	6R963	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608
.....4	CN906	3711-003975	CONNECTOR-HEADER;BOX,14P,1R,2.5mm,STRAIG	6R901	2007-000077	R-CHIP;470ohm,5%,1/10W,TP,1608
.....4	CN906	3711-004946	CONNECTOR-HEADER;BOX,15P,1R,2.5MM,STRAIG	6R930	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608
.....4	JA703	3722-001163	JACK-VHS;4P,12mm,AU,BLK,N	6R933	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608
.....4	JA701	3722-001426	JACK-PIN;9P,3.4mm,NI,BLK,-	6R936	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608
.....4	JA704	3722-001870	JACK-PIN;5P(10P),8.3MM,NI,GRN/BLU/RED/WH	6R974	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608
.....4	JA702	3722-001871	JACK-PIN;5P(9P),8.3MM,NI,GRN/BLU/RED/WH	6R905	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608
.....4	L802	AA27-10001C	COIL CHOKE;-100uH,K,-,5.0A,ST,700UH-K/R	6R921	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608
.....4	L801	AA29-00004A	FILTER LINE NOISE;-20UH,3A,AC80-260V,TQ	6R924	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608
.....4	T0076	AA39-20010B	LEAD CONNECTOR-ASSY;1P,500,YFH800-01,S,	6R925	2007-000078	R-CHIP;1Kohm,5%,1/10W,TP,1608
.....4	T0076	AA39-20010B	LEAD CONNECTOR-ASSY;1P,500,YFH800-01,S,	6R915	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608
.....4	TU04	AA40-00049A	TUNER;TCPN3081PC19C(S),TCPN3081PC19C(S),	6R913	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608
.....4	TU02	AA40-00049A	TUNER;TCPN3081PC19C(S),TCPN3081PC19C(S),	6R912	2007-000081	R-CHIP;2.7Kohm,5%,1/10W,TP,1608
.....4	TU01	AA59-00164A	MODULE-RF,SPLITTER;-UMX-NT-005,-,2IN/3O	6R978	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....4	AA63-00396B	SHIELD CASE-TOP;PRJT,P54A,SPT,TO.5,-,-,	S.N.A6R976	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
.....4	AA63-00397B	SHIELD CASE-BOT;PRJT,P54A,SPT,TO.5,-,-,	S.N.A6R971	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
.....4	AA63-00608A	SHIELD CASE;HERCULES TOP,SPT,TO.5,W140,	S.N.A6R958	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
.....4	AA63-00610A	SHIELD CASE;COMMANDO,SPT,TO.5,W141.5,H1	S.N.A6R980	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
.....4	AA63-10002A	BAND-TIE;NYLON66 V2,L100,NTR	S.N.A6R982	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
.....4	AA65-30018A	CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-,	S.N.A6R985	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
.....4	AA65-30111A	CLAMPER CORE-WIRE;ALL MODEL,NYLON,V0,-,WS,N.A	S.N.A6R986	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608	
.....4	T0104	AA95-02001K	ASSY SUB-PCB MICOM;C2	6R903	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....5	T0083	0402-000274	DIODE-RECTIFIER;UF4004,400V,1A,DO-41,TP	6R904	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....5	Q409	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	6R906	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....5	Q409	0505-000109	FET-SILICON;2N7000,N,60V,200mA,5ohm,400m	6R908	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....5	IC904	1203-001943	IC-VOL. DETECTOR;7025,TO-92,3P,-,PLASTIC	6R955	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....5	X901	2801-004071	CRYSTAL-UNIT;6MHZ,30PPM,28-AAM,20PF,40OH	6R954	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608
.....5	CN901	3703-001175	CONNECTOR-BACK PANEL;64P,2R,MALE,ANGLE,A	6R928	2007-000084	R-CHIP;4.7Kohm,5%,1/10W,TP,1608

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....6R927	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	4 IC601	AA96-00623E	ASSY H/S:SCREW,MAIN,AA62-00056A,TDA7265, S.N.A	
.....6R983	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	5	0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A
.....6R934	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	5 T0124	1201-001026	IC-POWER AMP:7265,ZIP,11P,19.6ML,DUAL,1	
.....6R987	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	5 T0081	6003-000334	SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR	
.....6R957	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	5	AA62-00056A	HEAT SINK-PS-,-,T1.0,-,41*35*70.D2,-,-, S.N.A	
.....6R944	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	4	BP39-00047A	LEAD CONNECTOR:P55A/HCM4215W,UL2547#26,U	
.....6R926	2007-000097	R-CHIP:47Kohm,5%,1/10W,TP,1608	4 T0095	BP95-00077A	ASSY SUB-PRO SCAN:HCM4215WJX/XAA,P55A,DV	
.....6R975	2007-000121	R-CHIP:820ohm,5%,1/10W,TP,1608	5	0202-000187	SOLDER-WIRE FLUX:,-,RS60S,D1.2.63Sn/37Pb	S.N.A
.....6R942	2007-000123	R-CHIP:1.5Kohm,5%,1/10W,TP,1608	5 FC48	2305-000011	C-FILM,MPEF:470nF,5%,250V,TP,21.5X13.0X7	
.....6R941	2007-000123	R-CHIP:1.5Kohm,5%,1/10W,TP,1608	5 EX01	2801-004019	CRYSTAL-UNIT:20.25MHz,30ppm,28-AAAM,13pF,	
.....6R914	2007-000123	R-CHIP:1.5Kohm,5%,1/10W,TP,1608	5 T0122	2802-001177	RESONATOR-CERAMIC:2.696MHZ,0.4%,BK,10X4.	
.....6R988	2007-000290	R-CHIP:100ohm,5%,1/8W,TP,2012	5 T0122	2802-001179	RESONATOR-CERAMIC:4MHZ,0.5%,BK,8X3X5.5MM	
.....6R962	2007-000583	R-CHIP:22Kohm,1%,1/10W,TP,1608	5 CN02	3703-001124	CONNECTOR-BACK PANEL:32P,2R,MALE,ANGLE,A	
.....6R961	2007-000939	R-CHIP:47Kohm,1%,1/10W,TP,1608	5 CN01	3703-001124	CONNECTOR-BACK PANEL:32P,2R,MALE,ANGLE,A	
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	5 CN906	3711-001164	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,ANGLE,-	
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	5	BP97-00169A	ASSY SMD:HCM4215WJX/XAA,P55A	S.N.A
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	6FD13	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	6FD14	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	6FD15	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	6FD16	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	6FD17	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	6FD10	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	6FD01	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	6FD02	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	6FD07	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	6FD08	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6C120	2203-000189	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,	6FD09	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6C120	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216	6DZ016	0403-000746	DIODE-ZENER:RLZ3.9B,3.89-4.16V,500MW,LL-	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,1608	6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,1608	6DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,1608	6DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....6C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,1608	6DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....6C120	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012	6DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....6C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,1608	6SQ01	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-	6FQ13	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-	6FQ04	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-	6FQ03	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6C120	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	6FQ02	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6C120	2203-000748	C-CERAMIC,CHIP:0.03nF,5%,50V,COG,TP,2012	6FQ08	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6C120	2203-000748	C-CERAMIC,CHIP:0.03nF,5%,50V,COG,TP,2012	6FQ09	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6C120	2203-001048	C-CERAMIC,CHIP:0.56nF,10%,50V,COG,TP,201	6FQ12	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6C120	2203-005809	C-CERAMIC,CHIP:1000nF,10%,16V,X7R,TP,201	6PQ01	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6C950	2402-000179	C-AL,SMD:47uF,20%,16V,GP,TP,6.6x6.6x5.4	6FQ06	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6C936	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	6FQ05	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6C921	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	6EQ15	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6C918	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	6EQ14	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6C915	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	6EQ13	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6C913	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	6FQ07	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
.....6C938	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.4	6Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
.....6C917	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4	6Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
.....6C912	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4	6IC104	0801-000662	IC-CMOS LOGIC:74HC123,MULTIVIBRATOR,SOP,1	
.....6C911	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.4	6IC106	1001-001082	IC-VIDEO SWITCH:BA7657F,-,SOP,24P,300MIL	
.....6L905	2703-001245	INDUCTOR-SMD:8.2uH,10%,2x1.25x1.25mm	6IC06	1203-001211	IC-VOL. DETECTOR:7027,SOT-89,3P,-PLASTI	
.....6G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,	6T0087	1203-002186	IC-POSI.FIXED REG:-,18,DPAK,3P,240MIL,PLA	
.....6G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,	6T0087	1203-002302	IC-POSI.FIXED REG:-,78RM33D,D-PAK,3P,-PL	
.....6G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,	6IC02	1204-001814	IC-SELECTOR:CXA2151Q,QFP,48P,144MIL,PLAS	
.....6G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,	6IC01A	1204-001938	IC-DECODER:VSP9407B-B11,MOFP,80P,14X14MM	
.....6G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,	6IC118	1204-001989	IC-VIDEO PROCESS:CXA2165Q,QFP,64P,20X14MM	
.....6R949	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	6SR08	2007-000052	R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6R950	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	6FR80	2007-000052	R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6R951	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	6FR78	2007-000052	R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6R945	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	6FR57	2007-000052	R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6R946	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	6FR35	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6R948	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	6FR07	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6R966	2007-000931	R-CHIP:470ohm,5%,1/8W,TP,2012	6ER90	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6PCB	AA41-00599B	PCB-MICOM:HCM4215W,FR-4,2L,B,1.6T,180X24	S.N.A6FR76	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6	0202-001167	SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,S.N.S.N.A	6FR96	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 IC902	1102-001130	IC-EPROM:M27W201-80F6,256KX8BIT,DIP,32P,	6SR09	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	0202-000187	SOLDER-WIRE FLUX:,-,RS60S,D1.2.63Sn/37Pb	S.N.A6SR22	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
....4 IC801	AA96-00475C	ASSY H/S:SILICON-OIL,KA278R09,KA7808,AA6	S.N.A6ER29	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A6ER04	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 T0087	1203-000293	IC-POSI.FIXED REG:-,7808,TO-220,3P,-PLAS	6ER05	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 T0123	1203-002003	IC-VOLTAGE REGULATOR:278R09,TO-220,4P,-	6ER06	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 T0081	6003-000334	SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR	6ER13	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	AA62-00066B	HEAT SINK:D2,D3,AL,T1.0,89,70,-,AA62-00	S.N.A6ER19	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5 T0123	1203-001978	IC-VOLTAGE REGULATOR:KA278RA05,TO-220F,4	6ER18	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	

Loc. No.	Code No.	Description ; Specification	Remark
.....6D10	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D14	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D15	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D16	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D17	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D18	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D01	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D02	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D03	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D04	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D05	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D09	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D08	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D07	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6D06	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....6Q02	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6Q03	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6Q10	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
.....6Q04	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
.....6Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
.....6Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
.....6Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
.....6IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P,4	
.....6IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P,4	
.....6IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P,4	
.....6IC08	1001-000164	IC-ANALOG MULTIPLEX:74HC4052,CMOS,SOP,16	
.....6IC13	1001-001155	IC-ANALOG MULTIPLEX:NCT5B3157P6X,CMOS,SC	
.....6IC112	1103-001195	IC-EEPROM:24C64,8Kx8Bit,SOP,8P,150MIL,10	
.....6DU410	1201-001135	IC-OP AMP:324,SOP,ST,14P,150MIL,QUAD,100	
.....6DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST	
.....6DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST	
.....6DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST	
.....6DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST	
.....6T0074	1201-001520	IC-VIDEO AMP:EL2250CS,SOIC,8P,150MIL,DUA	
.....6IC03	1203-001824	IC-VOL DETECTOR:7042,SOT-89,3P,-,PLASTI	
.....6T0087	1203-002302	IC-POSI.FIXED REG.:78RM33D,D-PAK,3P,-,PL	
.....6IC17	1209-001163	IC-PLL:TLC2932PWLE,SOP,14P,-,PLASTIC	
.....6R36	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012	
.....6R35	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012	
.....6R31	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012	
.....6R30	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012	
.....6R143	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6R144	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6R25	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6R122	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6R123	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6R141	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6R136	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6R15	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6R24	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6R45	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6R46	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6R09	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6R10	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6R129	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6R134	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6R135	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6R59	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6R65	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6R71	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6R77	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6R91	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6R53	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6R02	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6R16	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6R17	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6R20	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6R47	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6R62	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R64	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R68	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R58	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R56	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R52	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	

Loc. No.	Code No.	Description ; Specification	Remark
.....6R70	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R98	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R94	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R82	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R80	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R76	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R74	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R38	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R37	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R110	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R11	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R101	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R03	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R39	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R50	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R44	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R43	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R42	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R41	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R40	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6R128	2007-000079	R-CHIP:1.8Kohm,5%,1/10W,TP,1608	
.....6R81	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6R75	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6R69	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6R51	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6R57	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6R63	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6R109	2007-000082	R-CHIP:3.3Kohm,5%,1/10W,TP,1608	
.....6R66	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R61	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R60	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R55	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R54	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R79	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R78	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R73	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R72	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R67	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R49	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R08	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R07	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R06	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R04	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R01	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R48	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R133	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R121	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R119	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R118	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6R86	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R92	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R93	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R96	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R97	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R85	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R113	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R114	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R115	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R83	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R84	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6R125	2007-000091	R-CHIP:12Kohm,5%,1/10W,TP,1608	
.....6R05	2007-000102	R-CHIP:100Kohm,5%,1/10W,TP,1608	
.....6R127	2007-000109	R-CHIP:1Mohm,5%,1/10W,TP,1608	
.....6R100	2007-000118	R-CHIP:390ohm,5%,1/10W,TP,1608	
.....6R32	2007-000119	R-CHIP:560ohm,5%,1/10W,TP,1608	
.....6R34	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....6R29	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....6R28	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....6R117	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....6R107	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....6R33	2007-000124	R-CHIP:2.2Kohm,5%,1/10W,TP,1608	
.....6R120	2007-000124	R-CHIP:2.2Kohm,5%,1/10W,TP,1608	
.....6R90	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....6R89	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....6R88	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....6R87	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....6R108	2007-000381	R-CHIP:13Kohm,5%,1/10W,TP,1608	

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5 R125	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	5 C701	2401-001397	C-AL:470uf,20%,25V,GP,TP,10x16,5	
.....5 R125	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	5 C701	2401-001513	C-AL:47uf,20%,16V,WT,TP5x11,5	
.....5 R125	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2MM	5 C701	2401-000025	C-AL:100uf,20%,16V,GP,TP,6.3x11,5	
.....5 R125	2001-000780	R-CARBON:4700HM,5%,1/8W,AA,TP,1.8X3.2MM	5 C701	2401-000025	C-AL:100uf,20%,16V,GP,TP,6.3x11,5	
.....5 R125	2001-000780	R-CARBON:4700HM,5%,1/8W,AA,TP,1.8X3.2MM	5 C701	2401-000025	C-AL:100uf,20%,16V,GP,TP,6.3x11,5	
.....5 R125	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	5 C701	2401-001989	C-AL:4.7uf,20%,50V,BP,TP5x11,5	
.....5 R125	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	5 C701	2401-001989	C-AL:4.7uf,20%,50V,BP,TP5x11,5	
.....5 R125	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	5 C701	2401-001989	C-AL:4.7uf,20%,50V,BP,TP5x11,5	
.....5 R125	2001-001000	R-CARBON:82KOHM,5%,1/8W,AA,TP,1.8X3.2MM	5 C701	2401-001989	C-AL:4.7uf,20%,50V,BP,TP5x11,5	
.....5 R811	2001-001071	R-CARBON(S):12KOHM,5%,1/2W,AA,TP,2.4X6.4	5 C701	2401-001989	C-AL:4.7uf,20%,50V,BP,TP5x11,5	
.....5 R801	2001-001077	R-CARBON(S):150OHM,5%,1/2W,AA,TP,2.4X6.4	5 C701	2401-001989	C-AL:4.7uf,20%,50V,BP,TP5x11,5	
.....5 R677	2001-001103	R-CARBON(S):20KOHM,5%,1/2W,AA,TP,2.4X6.4	5 C701	2401-001989	C-AL:4.7uf,20%,50V,BP,TP5x11,5	
.....5 R674	2001-001103	R-CARBON(S):20KOHM,5%,1/2W,AA,TP,2.4X6.4	5 C701	2401-002144	C-AL:47uf,20%,16V,GP,TP5x11,5	
.....5 R681	2001-001146	R-CARBON(S):4.7OHM,5%,1/2W,AA,TP,2.4X6.4	5 C701	2401-002300	C-AL:47uf,20%,50V,GP,TP,6.3x11,5	
.....5 R682	2001-001146	R-CARBON(S):4.7OHM,5%,1/2W,AA,TP,2.4X6.4	5 C701	2401-002300	C-AL:47uf,20%,50V,GP,TP,6.3x11,5	
.....5 R814	2003-001098	R-METAL OXIDE(S):22Kohm,5%,3W,AA,TP,6x16	5 C701	2401-002459	C-AL:220uf,20%,25V,LZ,TP,10x16,5	
.....5 R805	2004-000970	R-METAL:470ohm,1%,1/4W,AA,TP,2.4x6.4mm	5 C701	2401-002459	C-AL:220uf,20%,25V,LZ,TP,10x16,5	
.....5 R024	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	5 C701	2401-002459	C-AL:220uf,20%,25V,LZ,TP,10x16,5	
.....5 R024	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	5 C701	2401-002459	C-AL:220uf,20%,25V,LZ,TP,10x16,5	
.....5 R024	2004-001970	R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.5	5 C701	2401-002459	C-AL:220uf,20%,25V,LZ,TP,10x16,5	
.....5 R024	2004-001970	R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.5	5 C701	2401-002463	C-AL:470uf,20%,16V,GP,TP8x11.5,5	
.....5 R024	2004-001970	R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.5	5 C701	2401-002463	C-AL:470uf,20%,16V,GP,TP8x11.5,5	
.....5 C695	2301-000192	C-FILM,PEF:1nf,5%,50V,TP,5.3x10mm,5mm	5 C701	2401-002594	C-AL:220uf,20%,16V,GP,TP8x11.5,5	
.....5 C694	2301-000192	C-FILM,PEF:1nf,5%,50V,TP,5.3x10mm,5mm	5 C701	2401-002619	C-AL:47uf,20%,25V,GP,TP5x11,5	
.....5 C689	2305-000665	C-FILM,MPEF:100nf,5%,63V,TP,7.5x4.0x5.0m	5 C701	2401-002619	C-AL:47uf,20%,25V,GP,TP5x11,5	
.....5 C687	2305-000665	C-FILM,MPEF:100nf,5%,63V,TP,7.5x4.0x5.0m	5 C701	2401-002619	C-AL:47uf,20%,25V,GP,TP5x11,5	
.....5 C682	2305-000665	C-FILM,MPEF:100nf,5%,63V,TP,7.5x4.0x5.0m	5 C701	2401-002619	C-AL:47uf,20%,25V,GP,TP5x11,5	
.....5 C701	2401-002075	C-AL:4.7uf,20%,50V,GP,TP5x11,5	5 C701	2401-002619	C-AL:47uf,20%,25V,GP,TP5x11,5	
.....5 C701	2401-002075	C-AL:4.7uf,20%,50V,GP,TP5x11,5	5 L105	2701-000106	INDUCTOR-AXIAL:1.5uH,10%,3x7mm	
.....5 C701	2401-002075	C-AL:4.7uf,20%,50V,GP,TP5x11,5	5 L119	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-002075	C-AL:4.7uf,20%,50V,GP,TP5x11,5	5 L120	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000039	C-AL:1000uf,20%,16V,GP,TP,10x16,5	5 L121	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000039	C-AL:1000uf,20%,16V,GP,TP,10x16,5	5 L122	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000192	C-AL:1000uf,20%,50V,GP,TP,16x25,7,5	5 L123	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000192	C-AL:1000uf,20%,50V,GP,TP,16x25,7,5	5 L124	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000302	C-AL:100uf,20%,25V,GP,TP,6.3x11,5	5 L107	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000302	C-AL:100uf,20%,25V,GP,TP,6.3x11,5	5 L108	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000360	C-AL:100uf,20%,50V,GP,TP,8x11.5,5	5 L111	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000360	C-AL:100uf,20%,50V,GP,TP,8x11.5,5	5 L114	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000471	C-AL:10uf,20%,50V,BP,TP,5x11,5mm	5 L113	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 L112	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 L703	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 L106	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 L104	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 L103	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 L101	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 L706	2701-001030	INDUCTOR-AXIAL:43uH,10%,5x14mm	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 L705	2701-001030	INDUCTOR-AXIAL:43uH,10%,5x14mm	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 L102	2701-001040	INDUCTOR-AXIAL:10uH,10%,4.5x14mm	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 G101	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 G101	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 G101	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 CN906	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 CN906	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH	
.....5 C701	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11,5	5 CN906	3711-002643	CONNECTOR-HEADER:BOX,4P,1R,2.5mm,STRAIGH	
.....5 C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,2	5 CN906	3711-002645	CONNECTOR-HEADER:BOX,6P,1R,2.5mm,STRAIGH	
.....5 C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,2	5 GT03	AA60-40014A	PIN-GT,ASSY:AUTO	S,N,A
.....5 C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,2	5 GT02	AA60-40014A	PIN-GT,ASSY:AUTO	S,N,A
.....5 C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,2	5 GT01	AA60-40014A	PIN-GT,ASSY:AUTO	S,N,A
.....5 C701	2401-000832	C-AL:220uf,20%,25V,GP,TP,8x11.5,5	5	AA97-07233J	ASSY SMD:HCM4215WX/XAA,P55A	S,N,A
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....5 C701	2401-000962	C-AL:22uf,20%,50V,GP,TP,5x11,5	6DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....5 C701	2401-001192	C-AL:33uf,20%,50V,GP,TP,6.3x11,5	6Q703	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark	
...4	RFZ52	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	...3	SG301	4715-001050	SURGE ABSORBER:2.4kV,20%,1500A,-DISC-RA	
...4	RFZ53	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	...3	SG562	AA27-00084A	COIL:S-23,-----,S-23,5000Mohm MIN,	
...4	RFZ19	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	...3	SG532	AA27-00084A	COIL:S-23,-----,S-23,5000Mohm MIN,	
...4	RFZ20	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	...3	SG502	AA27-00084A	COIL:S-23,-----,S-23,5000Mohm MIN,	
...4	RFZ21	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	...3	T0076	AA39-00112A	LEAD CONNECTOR-ASSY;UL1007#26,UL/CSA,10	
...4	RFZ22	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	...3	T0076	AA39-00120F	LEAD CONNECTOR-ASSY:SIR-T165,UL1007#26,U	
...4	C598	2201-000327	C-CERAMIC,DISC:2.2NF,10%,50V,Y5V,TP,6.5X	...3	T0076	AA39-00198D	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL1617	
...4	C598	2201-000327	C-CERAMIC,DISC:2.2NF,10%,50V,Y5V,TP,6.5X	...3	T0076	AA39-20010B	LEAD CONNECTOR-ASSY;1P,500,YFH800-01,S,	
...4	C598	2201-000327	C-CERAMIC,DISC:2.2NF,10%,50V,Y5V,TP,6.5X	...3	T0076	AA39-20010D	LEAD CONNECTOR-ASSY;1P,400,YFH800-01,S,	
...4	C598	2201-000327	C-CERAMIC,DISC:2.2NF,10%,50V,Y5V,TP,6.5X	...3	T0076	AA39-20010D	LEAD CONNECTOR-ASSY;1P,400,YFH800-01,S,	
...4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pf,10%,50V,Y5P,TP	...3	T0076	AA39-20027B	LEAD CONNECTOR-ASSY;6P,400,67096-006,S,	
...4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pf,10%,50V,Y5P,TP	...3	T0076	AA39-20031D	LEAD CONNECTOR-ASSY;9P,500,67096-009,S,	
...4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pf,10%,50V,Y5P,TP	...3	AA69-01396A	BAG PE:SKD CHASSIS,LDPE,TO.03,240,180,NO	S.N.A	
...4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pf,10%,50V,Y5P,TP	...3	Q371	AA96-00244H	ASSY H/S:SCREW,2SC4636(2),CRT,SLICON-OIL	S.N.A
...4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pf,10%,50V,Y5P,TP	...4	0205-000129	0205-000129	GREASE-SILICON:SC102 JAPAN	S.N.A
...4	C689	2202-000121	C-CERAMIC,MLC-AXIAL:100pf,10%,50V,Y5P,TP	...4	T0090	0502-000442	TR-POWER:2SC4636RB,NPN,2W,TO-220,ST,10-	
...4	C689	2202-000205	C-CERAMIC,MLC-AXIAL:22pf,5%,50V,SL,TP,1.	...4	T0081	6003-000335	SCREW-TAPTITE:RH,+2S,M3,L8,ZPC(YEL),SWR	S.N.A
...4	C689	2202-000205	C-CERAMIC,MLC-AXIAL:22pf,5%,50V,SL,TP,1.	...4	AA62-00046A	AA62-00046A	HEAT SINK-PS-,-,T1.0,-,D1(DREAM) 60X25X	S.N.A
...4	C689	2202-000205	C-CERAMIC,MLC-AXIAL:22pf,5%,50V,SL,TP,1.	...3	IC561	AA96-50311L	ASSY H/S;-AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...4	C689	2202-000205	C-CERAMIC,MLC-AXIAL:22pf,5%,50V,SL,TP,1.	...3	IC531	AA96-50311L	ASSY H/S;-AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...4	C689	2202-000205	C-CERAMIC,MLC-AXIAL:22pf,5%,50V,SL,TP,1.	...3	IC501	AA96-50311L	ASSY H/S;-AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
...4	CZ113	2202-000561	C-CERAMIC,MLC-RADIAL:0.68NF,5%,50V,COG,T	...4	T0074	1201-001131	IC-VIDEO AMP:6111,SIP,9P,-,SINGLE,-,PLAS	
...4	CZ114	2202-000561	C-CERAMIC,MLC-RADIAL:0.68NF,5%,50V,COG,T	...4	T0081	6003-000334	SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR	
...4	C701	2401-000183	C-AL:1000uF,20%,35V,WT,TP,12.5x25,5	...4	AA62-30175D	AA62-30175D	HEAT SINK-PS-;SECC,T1.0,-,33X15X30 FT-2	S.N.A
...4	C701	2401-000183	C-AL:1000uF,20%,35V,WT,TP,12.5x25,5	...3	AA97-07608A	AA97-07608A	ASSY AUTO-CRT:HCM4215W	S.N.A
...4	C701	2401-000962	C-AL:22uF,20%,50V,GPT,5x11,5	...4	D372	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
...4	C701	2401-000962	C-AL:22uF,20%,50V,GPT,5x11,5	...4	D504	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
...4	LZ112	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	...4	D509	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
...4	LZ111	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	...4	D361	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
...4	LZ110	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	...4	D362	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
...4	LZ109	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	...4	D371	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
...4	LZ108	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	...4	D510	0401-000005	DIODE-SWITCHING;1N4148,100V,200mA,DO-35,	
...4	LZ107	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	...4	T0083	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
...4	FD102S	3601-001065	FUSE-AXIAL LEAD:125V,3.5A,FAST-ACTING,CE	...4	T0083	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
...4	FD101S	3601-001065	FUSE-AXIAL LEAD:125V,3.5A,FAST-ACTING,CE	...4	T0083	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
...4	ELZ01	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A	...4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T
...4	ELZ02	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A	...4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T
...4	ELZ03	6042-000002	EYELET;ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A	...4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T
...4	C689	2202-000825	C-CERAMIC,MLC-AXIAL:680pf,10%,50V,Y5P,TP	...4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
...4	C689	2202-000825	C-CERAMIC,MLC-AXIAL:680pf,10%,50V,Y5P,TP	...4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
...4	C689	2202-000825	C-CERAMIC,MLC-AXIAL:680pf,10%,50V,Y5P,TP	...4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
...4	C689	2202-000825	C-CERAMIC,MLC-AXIAL:680pf,10%,50V,Y5P,TP	...4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
...4	C689	2202-000825	C-CERAMIC,MLC-AXIAL:680pf,10%,50V,Y5P,TP	...4	DZ016	0403-000508	DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500	
...4	C689	2202-000825	C-CERAMIC,MLC-AXIAL:680pf,10%,50V,Y5P,TP	...4	DZ016	0403-000508	DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500	
...4	C689	2202-000863	C-CERAMIC,MLC-AXIAL:560pf,10%,50V,Y5P,TP	...4	DZ016	0403-000708	DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
...4	C689	2202-000863	C-CERAMIC,MLC-AXIAL:560pf,10%,50V,Y5P,TP	...4	DZ016	0403-000708	DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
...4	C689	2202-000863	C-CERAMIC,MLC-AXIAL:560pf,10%,50V,Y5P,TP	...4	DZ016	0403-000708	DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
...4	C689	2202-000863	C-CERAMIC,MLC-AXIAL:560pf,10%,50V,Y5P,TP	...4	DZ016	0403-000708	DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
...4	C689	2202-000863	C-CERAMIC,MLC-AXIAL:560pf,10%,50V,Y5P,TP	...4	DZ016	0403-000708	DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
...4	R125	2001-000800	R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	Q563	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
...4	0	AA41-00601C	PCB:HCM4215W,PCB,CEM-1,1L,C,1.6,245X245,	S.N.A	...4	Q534	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T
...4	SGZ101	4715-000106	SURGE ABSORBER:300V,210-390V,-,AXIAL	S.N.A	...4	Q533	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T
...3	T0076	BP39-00005A	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL2547	S.N.A	...4	Q504	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T
...3	T0076	BP39-00015A	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL1185	S.N.A	...4	Q361	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T
...3	BP61-00076A	BP61-00076A	HOLDER-PUSH,A:42W5,NYLON6.6,NATURAL	S.N.A	...4	Q362	0501-000366	TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L,
...3	BP61-00077A	BP61-00077A	HOLDER-PUSH,B:42W5,NYLON6.6,NATURAL	S.N.A	...4	Q502	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,15W,TO-220,TP,120-
...3	CZ101	BP96-00005A	ASSY HEAT SINK P:BP62-00002A,SCREW,STK39	S.N.A	...4	T0090	0502-000006	TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-
...4	T0081	6003-001021	SCREW-TAPTITE:RH,+B,M3,L15,ZPC(YEL),SWR	S.N.A	...4	T0090	0502-000006	TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-
...4	CIS	BP62-00002A	HEAT SINK;COMMANDO,A1050P,T2.0,W62.0,H14	S.N.A	...4	R125	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM
...4	CIS	BP62-00008A	HEAT SINK;COMMANDO CG AMP;AL6063,T2.0,W15	S.N.A	...4	R125	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM
...4	CIS	BP73-00002A	SILICON/RUBBER;COMMANDO CG AMP;SILICON	S.N.A	...4	R125	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM
...4	T0074	1201-001225	IC-VIDEO AMP:392,SIP,22P,-,TRIPLE,-,PLAS	S.N.A	...4	R125	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM
...2	T0099	BP94-00234A	ASSY PCB MISC-CRT:DP:HCM4215W3S/XAA,P55A	S.N.A	...4	R584	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4
...3	VR561	2101-000321	VR-ROTARY:1Mohm,-,0.6W,SIDE	S.N.A	...4	R554	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4
...3	VR531	2101-000321	VR-ROTARY:1Mohm,-,0.6W,SIDE	S.N.A	...4	R524	2001-000028	R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4
...3	VR501	2101-000321	VR-ROTARY:1Mohm,-,0.6W,SIDE	S.N.A	...4	R580	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4
...3	T0121	3301-001201	CORE-FERRITE:AE,21x11x32mm,1500,280G	S.N.A	...4	R550	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4
...3	V561	3704-001019	SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	S.N.A	...4	R520	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4
...3	V531	3704-001019	SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	S.N.A	...4	R577	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4
...3	V501	3704-001019	SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	S.N.A	...4	R547	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4
...3	CN906	3711-002645	CONNECTOR-HEADER:BOX,6P,1R,2.5mm,STRAIGH	S.N.A	...4	R517	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4
...3	CN906	3711-002648	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,STRAIGH	S.N.A	...4	R366	2001-000109	R-CARBON(S):470OHM,5%,1/2W,AA,TP,2.4X6.4
...3	CN906	3711-003052	CONNECTOR-HEADER:BOX,10P,1R,2.5MM,STRAIG	S.N.A	...4	R125	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM
...3	CN906	3711-003052	CONNECTOR-HEADER:BOX,10P,1R,2.5MM,STRAIG	S.N.A	...4	R125	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
...3	CN906	3711-003973	CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIG	S.N.A	...4	R125	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
...3	CN906	3711-003973	CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIG	S.N.A	...4	R125	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark
....4	R125	2001-000539	R-CARBON:24KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000613	R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000613	R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000723	R-CARBON:4.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000938	R-CARBON:680HM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000995	R-CARBON:8200HM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000995	R-CARBON:8200HM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-001015	R-CARBON:9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R581	2001-001052	R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.
....4	R551	2001-001052	R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.
....4	R521	2001-001052	R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.
....4	R371	2001-001065	R-CARBON(S):2.4KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R370	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R369A	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R367	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R368	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R369	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R567	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
....4	R537	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
....4	R507	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
....4	R381	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M
....4	R361	2001-001097	R-CARBON(S):2.4KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R374	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R373	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R372	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R377	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R375	2001-001113	R-CARBON(S):270KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R365	2001-001120	R-CARBON(S):3.30HM,5%,1/2W,AA,TP,2.4X6.4
....4	R574	2001-001122	R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R544	2001-001122	R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R514	2001-001122	R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R583	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7
....4	R582	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7
....4	R553	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7
....4	R552	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7
....4	R523	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7
....4	R522	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.7
....4	R589	2002-001015	R-COMPOSITION:47Kohm,5%,1/2W,AA,TP,3.7x9
....4	R559	2002-001015	R-COMPOSITION:47Kohm,5%,1/2W,AA,TP,3.7x9
....4	R529	2002-001015	R-COMPOSITION:47Kohm,5%,1/2W,AA,TP,3.7x9
....4	R575	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9
....4	R545	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9
....4	R515	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9
....4	R579	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X
....4	R578	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X
....4	R549	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X
....4	R518	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X
....4	R519	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X
....4	R548	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X
....4	R588	2003-000738	R-METAL OXIDE(S):56Kohm,5%,2W,AA,TP,4x12
....4	R538	2003-000738	R-METAL OXIDE(S):56Kohm,5%,2W,AA,TP,4x12
....4	R508	2003-000738	R-METAL OXIDE(S):56Kohm,5%,2W,AA,TP,4x12
....4	R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5
....4	R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5
....4	R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5
....4	R573	2008-001129	R-FUSIBLE(S):1.5ohm,5%,1/2W,AF,TP,2.5x6.
....4	R543	2008-001129	R-FUSIBLE(S):1.5ohm,5%,1/2W,AF,TP,2.5x6.
....4	R513	2008-001129	R-FUSIBLE(S):1.5ohm,5%,1/2W,AF,TP,2.5x6.
....4	C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP
....4	C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP
....4	C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP
....4	C598	2201-000556	C-CERAMIC,DISC:0.47NF,10%,500V,Y5P,TP,5
....4	C598	2201-000723	C-CERAMIC,DISC:4.7NF,20%,3KV,Y5U,TP,16X5
....4	C598	2201-000723	C-CERAMIC,DISC:4.7NF,20%,3KV,Y5U,TP,16X5
....4	C598	2201-000723	C-CERAMIC,DISC:4.7NF,20%,3KV,Y5U,TP,16X5
....4	C598	2201-000983	C-CERAMIC,DISC:1NF,10%,2KV,Y5P,TP,9X5MM
....4	C598	2201-000983	C-CERAMIC,DISC:1NF,10%,2KV,Y5P,TP,9X5MM
....4	C598	2201-000983	C-CERAMIC,DISC:1NF,10%,2KV,Y5P,TP,9X5MM
....4	C565	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5
....4	C535	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5
....4	C505	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5

Loc. No.	Code No.	Description ; Specification	Remark
....4	C507	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11
....4	C537	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11
....4	C567	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11
....4	C361	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m
....4	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,5
....4	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,5
....4	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,5
....4	C701	2401-000133	C-AL:1000uF,20%,16V,GP,TP,10x20,5
....4	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5
....4	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m
....4	C701	2401-001621	C-AL:6.8uF,20%,450V,GP,TP,13x20,5
....4	L531	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
....4	L501	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
....4	SG561	4715-001036	SURGE ABSORBER:500V,20%,--,-,TP
....4	SG563	4715-001036	SURGE ABSORBER:500V,20%,--,-,TP
....4	SG533	4715-001036	SURGE ABSORBER:500V,20%,--,-,TP
....4	SG501	4715-001036	SURGE ABSORBER:500V,20%,--,-,TP
....4	SG503	4715-001036	SURGE ABSORBER:500V,20%,--,-,TP
....4	SG531	4715-001036	SURGE ABSORBER:500V,20%,--,-,TP
....4	EL06	6042-000002	EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H
....4	EL03	6042-000002	EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H
....4	EL563	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL537	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL536	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL535	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL564	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL565	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL566	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL567	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL534	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL01	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL02	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL04	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL05	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL533	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL505	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL504	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	EL503	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H
....4	GT537	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT561	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT536	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT535	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT534	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT562	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT567	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT564	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT563	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT502	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT501	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT373	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT372	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT371	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT504	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT533	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT532	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT531	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT506	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT374	AA60-40014A	PIN-GT,ASSY:AUTO
....4	GT375	AA60-40014A	PIN-GT,ASSY:AUTO
....4	R125	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	R125	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM
....4	DZ016	0403-000334	DIODE-ZENER:UZ2.7BSA,2.7V,2.54-2.75V,500
....4	DZ016	0403-000334	DIODE-ZENER:UZ2.7BSA,2.7V,2.54-2.75V,500
....4	DZ016	0403-000334	DIODE-ZENER:UZ2.7BSA,2.7V,2.54-2.75V,500
....4	R566	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R536	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R506	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.
....4	R125	2001-000007	R-CARBON:3KOHM,5%,1/8W,AA,TP,1.8X3.2MM

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark	
...4	R125	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	RFZ101	2008-001086	R-FUSIBLE(S):3.3ohm,5%,2W,AG,TP,3.9x12mm	
...4	C598	2201-000599	C-CERAMIC,DISC:0.56NF,10%,500V,Y5P,TP,5.	...4	C598	2201-000193	C-CERAMIC,DISC:0.01NF,0.25PF,50V,COG,TP,	
...4	C598	2201-000599	C-CERAMIC,DISC:0.56NF,10%,500V,Y5P,TP,5.	...4	C598	2201-000193	C-CERAMIC,DISC:0.01NF,0.25PF,50V,COG,TP,	
...4	C598	2201-000599	C-CERAMIC,DISC:0.56NF,10%,500V,Y5P,TP,5.	...4	C598	2201-000516	C-CERAMIC,DISC:4.7NF,+100-0%,500V,Y5U,TP	
...4	C701	2401-001571	C-AL:47uF,+20%-0%,50V,GP,TP,8x11.5,	...4	C598	2201-000516	C-CERAMIC,DISC:4.7NF,+100-0%,500V,Y5U,TP	
...4	C701	2401-001571	C-AL:47uF,+20%-0%,50V,GP,TP,8x11.5,	...4	C598	2201-000604	C-CERAMIC,DISC:0.056NF,+100-0%,500V,SL,T	
...4	C701	2401-001571	C-AL:47uF,+20%-0%,50V,GP,TP,8x11.5,	...4	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11.5	
...4	R125	2001-000319	R-CARBON:120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	C701	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11.5,5	
...4	R125	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	C701	2401-001157	C-AL:33uF,20%,160V,GP,TP,12.5x20.5	
...4	R125	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	C701	2401-001220	C-AL:4.7uF,20%,160V,GP,TP,8x11.5,5	
...4	R125	2001-000232	R-CARBON:1.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	C701	2401-001220	C-AL:4.7uF,20%,160V,GP,TP,8x11.5,5	
...4	R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	C701	2401-001513	C-AL:47uF,20%,16V,WT,TP,5x11.5	
...4	R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	C701	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11.5	
...4	R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	LZ101	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm	
...4	R125	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	CN906	3711-002642	CONNECTOR-HEADER-BOX,3P,1R,2.5mm,STRAIGH	
...4	R125	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	CN906	3711-002642	CONNECTOR-HEADER-BOX,3P,1R,2.5mm,STRAIGH	
...4	L561	2701-000168	INDUCTOR-AXIAL:3.3uH,5%,2.5x3.4mm	...4	CN906	3711-002642	CONNECTOR-HEADER-BOX,3P,1R,2.5mm,STRAIGH	
...4	R382	2002-001014	R-COMPOSITION:6.8Kohm,10%,1/2W,AA,TP,3.7	...4	PCB	AA41-00611A	PCB-VM:HCM4215W,FR-1,1L,E,1.6T,245X245,P	
...4	PCB	AA41-00600E	PCB-CRT:HCM4215W,FR-1,1L,E,1.6T,245X197(S.N.A	...3	T0081	6003-001023	SCREW-TAPTITE:RWH,+B,M3,L10,ZPC(YEL),SW
...4	T0083	0402-000243	DIODE-RECTIFIER:RC2-V1,2000V,0.2A,DO-201	...2	T0105	BP94-00239A	ASSY PCB MISC-DY:JACK-DP:HCM4215W3S/XAA,	
...3	T0076	BP39-00004B	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239	...3	0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1,2.63Sn/37Pb	S.N.A	
...3	T0076	BP39-00004C	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239	...3	GT13	AA60-40012D	PIN-GT,ASSY:T1,6.6-12.5,-NYLON66	
...3	T0076	BP39-00004C	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239	...3	GT09	AA60-40012D	PIN-GT,ASSY:T1,6.6-12.5,-NYLON66	
...3	T0103	BP59-00005A	MODULE-FOCUS PACK ASS'Y:PJT TV,F301-P03A	...3	GT05	AA60-40012D	PIN-GT,ASSY:T1,6.6-12.5,-NYLON66	
...3	T0076	AA39-20010C	LEAD CONNECTOR-ASSY:TP,600,YFH800-01,S,	...3	GT01	AA60-40012D	PIN-GT,ASSY:T1,6.6-12.5,-NYLON66	
...3	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11.5	...3	AA61-01197A	HOLDER-PCB,DY:COMANDO,ABS V0,BLK		
...3	AA63-10002A	BAND-TIE:NYLON66 V2,L100,NTR	S.N.A	...3	AA97-07230N	ASSY AUTO-COMMANDO		
...3	6902-000395	BAG PE:LDP,TO.05,W200,L140,...	S.N.A	...4	R301	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
...2	T0098	BP94-00238A	ASSY PCB MISC-VM:DP:HCM4215W3S/XAA,P55A	...4	R302	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
...3	0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1,2.63Sn/37Pb	S.N.A	...4	R303	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
...3	RZ120	2008-001097	R-FUSIBLE(S):330HM,5%,1/2W,AC,BK,2.5X6.5	...4	PCB	AA41-00632A	PCB-DY CONNECTION:HCM4215W,FR-1,1L,A,1.6	
...3	T0121	3301-001201	CORE-FERRITE:AE,21x11x32mm,1500,280G	...2	T0098	BP94-00517Q	ASSY PCB MISC-CONTROL-DP,ST54T8PCS/XAX,	
...3	T0079	AA33-00017A	MAGNET CONVERGENCE:JH 92LT - 29G,-,29.1M	...3	0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1,2.63Sn/37Pb		
...3	T0076	AA39-20055C	LEAD CONNECTOR-ASSY:6P,500,YBNH025-06,6	...3	LEDY01	0601-001381	LED-ROUND,RED/GRN,5.0MM,650/563NM	
...3	OZ102	AA96-00243L	ASSY H/S:-,CRT,AA62-000450A,2SC2344,HERC	...3	T0121	3301-001201	CORE-FERRITE:AE,21x11x32mm,1500,280G	
...4	0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A	...3	SWY08	3404-001006	SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4	T0090	0502-000153	TR-POWER:2SC2344-D,NPN,1.2W,TO-220,-,60	...3	SWY07	3404-001006	SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4	T0081	6003-000335	SCREW-TAPTITE:RH,+2S,M3,L8,ZPC(YEL),SWR	...3	SWY06	3404-001006	SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4	AA62-00045A	HEAT SINK-PS:-,T1,0,-,DREAM,-,-,-,-,	S.N.A	...3	SWY05	3404-001006	SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...3	OZ101	AA96-00243M	ASSY H/S:-,AMP,AA62-000450A,2SA1011,HERC	...3	SWY01	3404-001006	SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4	0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A	...3	SWY02	3404-001006	SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4	T0090	0502-000131	TR-POWER:2SA1011-D,NPN,1.2W,TO-220,-,60	...3	SWY03	3404-001006	SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4	T0081	6003-000335	SCREW-TAPTITE:RH,+2S,M3,L8,ZPC(YEL),SWR	...3	SWY04	3404-001006	SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST	
...4	AA62-00045A	HEAT SINK-PS:-,T1,0,-,DREAM,-,-,-,-,	S.N.A	...3	CN906	3711-000447	CONNECTOR-HEADER-BOX,3P,1R,2.5MM,ANGLE,-	
...3	AA97-07230M	ASSY AUTO-VM:COMMANDO	S.N.A	...3	CN906	3711-003353	CONNECTOR-HEADER-BOX,11P,1R,2.5mm,ANGLE,	
...4	DZ106	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	...3	RMV01	AA32-00012A	MODULE REMOCON:ORC-50HF2,38KHZ,940NM,MES	
...4	DZ105	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	...3	T0076	AA39-00223A	LEAD CONNECTOR-ASSY:11P,800MM,6.7096-011	
...4	DZ102	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	...3	T0076	AA39-00259A	LEAD CONNECTOR-ASSY:UL1007#26,UL/CSA,3P	
...4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	...3	BP97-00511J	ASSY AUTO-CONTROL:ST54T8,P55A		
...4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	...4	DZ016	0403-000510	DIODE-ZENER:MTZJ6.2B,6.2V,5.96-6.27V,500	
...4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	...4	DZ016	0403-000510	DIODE-ZENER:MTZJ6.2B,6.2V,5.96-6.27V,500	
...4	OZ103	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	...4	OY01	0504-000123	TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T	
...4	OZ106	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	...4	RY07	2001-000020	R-CARBON(S):220HM,5%,1/2W,AA,TP,2.4X6.4M	
...4	OZ105	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	...4	RY09	2001-000109	R-CARBON(S):470OHM,5%,1/2W,AA,TP,2.4X6.4	
...4	OZ104	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	...4	R125	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	RZ122	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M	...4	R125	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	R125	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	R125	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	R125	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	R125	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	R125	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	R125	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	R125	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	RY08	2001-001108	R-CARBON(S):22KOHM,5%,1/2W,AA,TP,2.4X6.4	
...4	R125	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	C701	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7.5	
...4	R125	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...4	BP41-00040A	PCB CONTROL:ST54T8,CONTROL,1L,1.6T,245*2		
...4	R125	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...2	T0100	BP94-00564F	ASSY PCB MISC-A/V FRONT:ST54T8PCS/XAX,P5	
...4	R125	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	...3	0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1,2.63Sn/37Pb		
...4	R125	2001-000554	R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM	...3	SW101	3404-000208	SWITCH-TACT:12V,50mA,120gf,6x6mm,SPST	
...4	R125	2001-000666	R-CARBON:330OHM,5%,1/8W,AA,TP,1.8X3.2MM	...3	CN906	3711-000447	CONNECTOR-HEADER-BOX,3P,1R,2.5MM,ANGLE,-	
...4	R125	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	...3	CN906	3711-003601	CONNECTOR-HEADER-BOX,12P,1R,2.5mm,ANGLE,	
...4	RZ110	2001-001100	R-CARBON(S):2.7OHM,5%,1/2W,AA,TP,2.4X6.4	...3	JK101	3722-000544	JACK-VHS:4P,11.5mm,AG,BLK,N	
...4	RZ104	2001-001100	R-CARBON(S):2.7OHM,5%,1/2W,AA,TP,2.4X6.4	...3	JK102	3722-001164	JACK-PIN:3P,3.4mm,SN,WH:YE:RE,#16-22	
...4	RZ105	2001-001139	R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4	...3	T0081	6003-001023	SCREW-TAPTITE:RWH,+B,M3,L10,ZPC(YEL),SW	
...4	RZ106	2001-001139	R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4	...3	T0076	AA39-00260A	LEAD CONNECTOR-ASSY:UL1007#26,UL/CSA,3P	
...4	RZ114	2003-000532	R-METAL OXIDE(S):18ohm,5%,2W,AF,TP,4x12m	...3	AA63-10002A	BAND-TIE:NYLON66 V2,L100,NTR		
...4	RZ103	2003-000713	R-METAL OXIDE(S):47ohm,5%,2W,AF,TP,4x12m	...3	T0147	AA91-00762U	ASSY-JACK SIDE:54/62T8,SV704P,XAX	
...4	RZ111	2003-000713	R-METAL OXIDE(S):47ohm,5%,2W,AF,TP,4x12m	...4	AA61-00793E	HOLDER-SIDE AV:47H1,ABS HB,GRAY,SV-704P		
...4	RZ123	2003-002157	R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM	...4	T0150	AA64-02085F	DOOR-AV:H1,ABS HB,GRAY,SV-704P	
...4	RZ113	2003-002157	R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM	...4	AA64-02086F	INLAY-AV:W3,PS SHEET,TO.5,P54A XAC		
...4	RZ112	2003-002157	R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM	...3	AA97-07429A	ASSY AUTO-A/V FRONT:HCM4215W/XAA,P55A		

Loc. No.	Code No.	Description ; Specification	Remark
....4	R125	2001-000006 R-CARBON;2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	PCB	AA41-00499B PCB-FRONT A/V-SVP-54T6SR,FR-1,1L,A,1.6T, S.N.A	
....3	CNW01A	BP39-00016B LEAD CONNECTOR:HCL4715WB,UL2547#26,UL/CS	
..2		BP95-00147D ASSY SUB PCB-SENSOR:DPP54A,SENSOR	
....3		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb S.N.A	
....3		AA69-01808B BAG-SHEET;LDPE(ANTISTATIC),TO.05,800,50 S.N.A	
....3		BP97-00208A ASSY SMD;0 S.N.A	
....4	Q01	0501-000342 TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
....4	PCB	AA41-00853A PCB-SERSOR:SVP-42W5HRC,FR-4,2L,A,1.6T,24 S.N.A	
....4	D01	BP32-00001A SENSOR PHOTO:BCS5030G1,-40 TO +85,0.42 U	
....4	R01	2007-000305 R-CHIP:10Mohm,5%,1/10W,TP,1608	
....4	R02	2007-000109 R-CHIP:1Mohm,5%,1/10W,TP,1608	
....4	R03	2007-000109 R-CHIP:1Mohm,5%,1/10W,TP,1608	
....4		0202-001167 SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SNS,N.A	
....3	CN906	3711-000447 CONNECTOR-HEADER:BOX,3P,1R,2.5MM,ANGLE,-	

ASSY P/MATERIAL

1	BP92-00526B	ASSY P/MATERIAL:ST54T8PCS/XAX,J54A	S.N.A
..2	AA60-40006A	PIN-STAPLE:AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A
..2	AA61-00049B	HOLDER-BOX:-,PP,-,-,NTR,VO,AA61-20285A	S.N.A
....3	AA61-20285A	HOLDER-BOX:3456,PP,-,-,WHT,VO	S.N.A
..2	AA63-10007C	BAND-PP:W18,CLEA,1G	S.N.A
..2	AA69-00305A	BAG AIR:ALL,LDPE,1000,500,CLR,	S.N.A
..2	AA69-00306A	BAG AIR:LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
..2	AA69-00744L	BAG-SHEET:-,HDPE PE FOAM,TO.015,W1650,H1	S.N.A

ASSY ACCESSORY

1	M0016	BP92-00577F	ASSY ACCESSORY:ST54T8PCS/XAX,P55A	S.N.A
..2		6902-000018	BAG PE:LDPE,TO.1,W280,L400,GRY,8,2-	S.N.A
..2	T0116	AA39-00006A	CABLE RCA:,3000MM	S.N.A
..2	T0074	AA59-00262A	REMOCON;-;TM63,COMMONDO,48,G6671B,EX,S/S	S.N.A
..2	T0122	2802-000194	RESONATOR-CERAMIC:8MHz,1.0%,TP8.5x4.5x5	S.N.A
....3	T0119	AA09-00275A	IC MICOM:Z86L8808SSC-R51PX,SOP,STZTM-8	S.N.A
..2	T0113	AA61-20126A	HOLDER-LEG:-,ABS,-,-,BLK,HB	S.N.A
..2	W/C	AA68-00559C	CARD WARRANTY:-,W/P150(G)-,138X212,-,	S.N.A
..2		AA68-00560A	CARD-SVC NETWORK:-,W/P100(G)-,SEM,1',	S.N.A
..2		AA69-30009C	BAG-SHEET:LDPE,TO.08,W150,L120,-,-,-	S.N.A
..2	CIS	BP68-00056B	MANUAL USERS:ST47W3PC,ENG,W/P 100g,P55A,S,N.A	S.N.A
..2	CIS	BP68-00057B	MANUAL USERS:ST47W3PC,SPA,W/P 100g,P55A,S,N.A	S.N.A

ASSY K/D-CPT

1	BP98-00180A	ASSY K/D-CPT:ST54T8PCS/XAX,P55A	S.N.A	
..2	T0026	BP98-00181A	ASSY K/D-CPT R:ST54T8PCS/XAX,P55A	S.N.A
....3	AA03-00200A	CRT MONO:P16LSG03RJA,FREE,3.30mH,2.20mH,	S.N.A	
....3	T0117	AA26-30006F	TRANS FBT-ANODE CAP ASS'Y:-,FWZ-50A001C,	S.N.A
....3	T0078	AA27-00249A	DEFLECTION YOKE:-,DPD-5292AA,S/S,7,29.1	S.N.A
....3	T0079	AA33-00016A	MAGNET CONVERGENCE:JH 92LT - 29F,-,29.1M	S.N.A
....3	T0076	AA39-00018A	LEAD CONNECTOR-ASSY;UL1015#22,UL/CSA,1P	S.N.A
....3		AA60-00125B	SPACER-CRT:PROJ,SILICONE,D/GRAY	S.N.A
....3		AA60-00126B	SPACER-CAP:PROJ,EPDM,BLK	S.N.A
....3		AA60-00127B	SPACER-LENS:PROJ,SILICONE,D/GRAY	S.N.A
....3	T0081	AA60-10011A	SCREW-TAPTITE:-,SWRCH18A,M4,L12,HH,+PC,	S.N.A
....3		AA61-00056B	BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,	S.N.A
....3		AA61-00809B	HOLDER-CRT:PROJ,PC/ABS GF 20%,BLK	S.N.A
....3	T0114	AA61-00810B	HOLDER-CAP:PROJ,PC,CLR	S.N.A
....3		AA63-00076A	SPACER-LENS:PROJECTION,FELT,-,-,-,BROWN	S.N.A
....3	T0109	AA67-00147A	LENS-ASSY;DELTA 78,CLEAR A/B	S.N.A
....3	T0051	AA67-10007A	LENS:-,DELTA,CLEAR,PJT,-,77,79,-	S.N.A
....3		BP61-00079A	HOLDER-DY;PJT,TO.5,NYLON66 V2	S.N.A
....3		AA61-00845A	CASE-COUPLER,R:DP,PROJ,AA61-00806B	S.N.A
....4		AA61-00806B	CASE-COUPLER,R:PROJ,ALDC,T8,BLK	S.N.A
....4		AA63-10007C	BAND-PP:W18,CLEA,1G	S.N.A
....3	T0107	AA91-00735A	ASSY-BRKT,CRT:DP,AA91-00722A,PROJ	S.N.A
....4	T0107	AA91-00722A	ASSY-BRKT,CRT;SECC T1.6,PROJ	S.N.A
....5	T0072	AA61-00473B	BRACKET-CRT;53,SECC,T1.6,-,-,-,-	S.N.A
....5		AA61-00615B	BRACKET-EARTH:54J8,PBS,TO.5,-,-,-,-	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark	
....5	AA61-00812A	SPRING ETC-WIRE:PROJ,STS,3.6	S.N.A	
..2	T0027	BP98-00182A	ASSY K/D-CPT G:ST54T8PCS/XAX,P55A	S.N.A
....3	AA03-00201A	CRT MONO:P16LSG03HKA,FREE,3.30mH,2.20mH,	S.N.A	
....3	T0117	AA26-30006F	TRANS FBT-ANODE CAP ASS'Y:-,FWZ-50A001C,	S.N.A
....3	T0078	AA27-00249A	DEFLECTION YOKE:-,DPD-5292AA,S/S,7,29.1	S.N.A
....3	T0076	AA39-00018A	LEAD CONNECTOR-ASSY;UL1015#22,UL/CSA,1P	S.N.A
....3		AA60-00125B	SPACER-CRT:PROJ,SILICONE,D/GRAY	S.N.A
....3		AA60-00126B	SPACER-CAP:PROJ,EPDM,BLK	S.N.A
....3		AA60-00127B	SPACER-LENS:PROJ,SILICONE,D/GRAY	S.N.A
....3	T0081	AA60-10011A	SCREW-TAPTITE:-,SWRCH18A,M4,L12,HH,+PC,	S.N.A
....3		AA61-00056B	BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-,	S.N.A
....3		AA61-00809B	HOLDER-CRT:PROJ,PC/ABS GF 20%,BLK	S.N.A
....3	T0114	AA61-00810B	HOLDER-CAP:PROJ,PC,CLR	S.N.A
....3		AA63-00076A	SPACER-LENS:PROJECTION,FELT,-,-,-,BROWN	S.N.A
....3	T0109	AA67-00147A	LENS-ASSY;DELTA 78,CLEAR A/B	S.N.A
....3	T0051	AA67-10007A	LENS:-,DELTA,CLEAR,PJT,-,77,79,-	S.N.A
....3		BP61-00079A	HOLDER-DY;PJT,TO.5,NYLON66 V2	S.N.A
....3	T0107	AA91-00735A	ASSY-BRKT,CRT:DP,AA91-00722A,PROJ	S.N.A
....4	T0107	AA91-00722A	ASSY-BRKT,CRT;SECC T1.6,PROJ	S.N.A
....5	T0072	AA61-00473B	BRACKET-CRT;53,SECC,T1.6,-,-,-,-	S.N.A
....5		AA61-00615B	BRACKET-EARTH:54J8,PBS,TO.5,-,-,-,-	S.N.A
....5		AA61-00812A	SPRING ETC-WIRE:PROJ,STS,3.6	S.N.A
....3		AA61-00847A	CASE-COUPLER,B:DP,PROJ,AA61-00808B	S.N.A
....4		AA61-00808B	CASE-COUPLER,B:PROJ,ALDC,T8,BLK	S.N.A
....4		AA63-10007C	BAND-PP:W18,CLEA,1G	S.N.A

You can search for the updated part code through ITSELF web site.
 URL : http://itself.sec.samsung.co.kr

7-4 HCN4727W5S/XAA

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY SKD PART							
1	AA92-07174A	ASSY SKD PART;HCN4727W5S/XAA,P55A	S.N.A	...	BP61-00075A	HOLDER-JERSEY,ASSY;W3,ABS V0,GRAY,63-000	S.N.A
..2	T0121	3301-001201 CORE-FERRITE;AE,21x11x32mm,1500,280G		...4	T0069	AA63-00099C SPACER-FELT;47W3,FELT,BLK,TO.35,30*30	S.N.A
..2	T0118	AA26-00101A TRANS FBT-H/V DISTRIBUTOR;FWZ50A001E/FFA		...4		AA61-00508D HOLDER-JERSEY;W3,ABS V0,GRAY,G4309	S.N.A
..2		AA63-10002A BAND-TIE;NYLON66 V2,L100,NTR	S.N.A	...		BP61-00207A HOLDER-FOOT;47W7,HIPS HB BLK,....	S.N.A
..2		AA65-30018A CLAMPER CORE-WIRE;DONG-A,NYLON-66,-,-,-	S.N.A	...		BP61-00210A HOLDER-WOOD,TOP;55W7,ABS HB BLK,....	S.N.A
..2		AA65-30104C CLAMPER CORE-WIRE;ALL MODEL,NYLON 66,V2,	S.N.A	...		BP64-00237A CABINET-WOOD;47W7,WOOD,DE8326 D/GRY	S.N.A
△	T0066	AA96-00156A ASSY POWER CORD;-EP2/YES(US),H/C100MM,K		...		AA61-00097A HOLDER-WIRE;-NYLON 6/6,-,-,-,NTR,-	S.N.A
...		3811-000401 WIRE-PVC CU;BCWA,300V,ROLL,17/0.16mm,#22	S.N.A	...		AA61-00458B CASTER;-TP4020-05 PLY,-,OH56,-,-,SR44.4	S.N.A
...	T0077	AA39-10007Y CBF POWER CORD;-EP2/YES,SPT-2 18AWGx2C,		...		AA61-00858C BRACKET-FRAME;SECC,T2,0,NO-R PJTV	S.N.A
...		AA61-20284A HOLDER-P-CORD,PP,-,-,-,BLK,VO,KE-002	S.N.A	...	HC+CW	AA60-10051B SCREW-WOOD;-SWRCH18A,M3.5,L11,RH,+,-,-	S.N.A
...		AA63-10002B BAND-TIE;NYLON66 V2,L140,NTR	S.N.A	...		AA60-00078B SPACER-DUAL,LOCK;W3,#250,19*40	S.N.A
...	T0121	3301-001201 CORE-FERRITE;AE,21x11x32mm,1500,280G		...		BP61-00210B HOLDER-WOOD,SIDE;ABS,47W7,HB,650,BLK	S.N.A
ASSY COVER FRONT				...		AA61-20129D HOLDER-WIRE;NYLON NTR,W7	S.N.A
1	M0001	BP90-00150B ASSY COVER FRONT;P55A	S.N.A	..2		BP98-00185A ASSY K/D-FRONT MASK;47W7,XAA	S.N.A
..2	T0081	6002-000522 SCREW-TAPPING;TH,+2,M4,L15,ZPC(BLK),SWR		...	T0057	BP64-00177A BADGE-BRAND;ALL,AL,T1.5,70,11.3, BLK,SIL	S.N.A
..2	T0081	6003-001023 SCREW-TAPTITE;RWH,+B,M3,L10,ZPC(YEL),SW	S.N.A	...	T0017	BP64-00201A CABINET FRONT-MASK;47W7,HIPS HB,GRY,DGM1	S.N.A
..2	T0081	6003-001026 SCREW-TAPTITE;RH,+B,M4,L15,ZPC(BLK),SWR	S.N.A	...	T0102	BP73-00004A RUBBER-CAP;42W5,SILICONE,WHIT,RUBBER	S.N.A
..2	T0081	6003-001026 SCREW-TAPTITE;RH,+B,M4,L15,ZPC(BLK),SWR	S.N.A	...	T0067	BP60-00032A SPACER-SCREEN;47W7,EVA SPONGE,600,BLK,T1	S.N.A
..2	T0081	6003-001026 SCREW-TAPTITE;RH,+B,M4,L15,ZPC(BLK),SWR	S.N.A	...	T0067	BP60-00032B SPACER-SCREEN;47W7,EVA SPONGE,1000,BLK,T	S.N.A
..2	T0081	6003-001026 SCREW-TAPTITE;RH,+B,M4,L15,ZPC(BLK),SWR	S.N.A	..2		BP98-00188A ASSY K/D-FRONT BOT;HCN4727W5SXAA	S.N.A
..2	T0081	6003-001026 SCREW-TAPTITE;RH,+B,M4,L15,ZPC(BLK),SWR	S.N.A	...	T0081	6003-001019 SCREW-TAPTITE;RH,+B,M4,L12,ZPC(BLK),SWR	S.N.A
..2	T0081	6003-001026 SCREW-TAPTITE;RH,+B,M4,L15,ZPC(BLK),SWR	S.N.A	...	T0081	6003-001019 SCREW-TAPTITE;RH,+B,M4,L12,ZPC(BLK),SWR	S.N.A
..2	HC+CW	6005-001003 SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18A	S.N.A	...	T0069	AA60-00091R SPACER-FELT;FELT,250X10,-,BLK,TO.5,-	S.N.A
..2	HC+CW	6005-001003 SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18A	S.N.A	...	CIS7	AA61-60003J SPRING ETC-CS;-SUS304,-,-,OD6,N7,OD6,-,	S.N.A
..2	HC+CW	6005-001003 SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18A	S.N.A	...		BP60-00031A SPACER-DUAL LOCK;W7,20.6,3463	S.N.A
..2	HC+CW	6005-001003 SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18A	S.N.A	...		BP64-00202A CABINET FRONT-BOT;47W7,HIPS V0,G4309,SV0	S.N.A
..2	HC+CW	6005-001003 SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18A	S.N.A	...	T0023	BP64-00204A KNOB POWER;47W7,ABS HB,G3676,SVM3132	S.N.A
..2	HC+CW	6005-001003 SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18A	S.N.A	...	T0022	BP64-00205A KNOB CONTROL;47W7,ABS HB,G3676,SVM3132	S.N.A
..2	HC+CW	6005-001003 SCREW-WOOD;HH,+M4,L19,ZPC(BLK),SWRCH18A	S.N.A	...		BP64-00206A WINDOW REMOCON-LED;47W7,ABS HB,....CLR,	S.N.A
..2	BCM+CW	6006-001094 SCREW-ASS'Y WOOD;WW,HH,+M7,L32,ZPC(YEL)	S.N.A	..2	T0053	AA67-00119B SCREEN FRESNEL;47W,1072*614,T	S.N.A
..2	T0076	AA39-00284A LEAD CONNECTOR-ASSY;SVP-47W3HD,UL2547#26		..2	T0056	AA67-00196A SCREEN-TINT;47W,1070*612,T=0.7,P	S.N.A
..2		AA60-00072B SPACER-COVER,DUST;43,54,62J9,SPONGE 94HF	S.N.A	..2		BP61-00350A HOLDER-SCREEN TOP ASSY;HIPS,47W7,HB,BLK,	S.N.A
..2	T0081	AA60-10011A SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A	..2	T0081	6003-001019 SCREW-TAPTITE;RH,+B,M4,L12,ZPC(BLK),SWR	S.N.A
..2	T0081	AA60-10011A SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A	...		BP61-00158A HOLDER-SENSOR;52Q7,PC,VIOLET	S.N.A
..2	T0081	AA60-10011A SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A	...		BP61-00211A HOLDER-SCREEN TB;47W7,HIPS HB BLK,....	S.N.A
..2	T0081	AA60-10011A SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+PC,	S.N.A	...	T0069	AA60-00091U SPACER-FELT;W7,L1035,BLK,TO.35,W10	S.N.A
..2	T0115	AA61-00617B BRACKET-CRT,MAIN;DP;54J7,AA61-00475B	S.N.A	..2		BP61-00350B HOLDER-SCREEN BOT ASSY;HIPS,47W7,HB,BLK,	S.N.A
..3	T0115	AA61-00475B BRACKET-CRT,MAIN;54,SECC,T1.6,-,-,-		...	T0081	6003-001019 SCREW-TAPTITE;RH,+B,M4,L12,ZPC(BLK),SWR	S.N.A
..3		AA63-10007C BAND-PP;W18,CLEA,1G	S.N.A	...		BP61-00158A HOLDER-SENSOR;52Q7,PC,VIOLET	S.N.A
..3		AA61-00618C GUIDE-FLOW;54J8,J7,ABS,IVORY,V0	S.N.A	...	T0064	BP65-00005A CLAMPER CORE;52Q7,NYLON	S.N.A
..3	T0069	AA63-60002V SPACER-FELT;-FELT,-,-,-,BLK,TO.3,-,60X4	S.N.A	...	T0069	AA60-00091U SPACER-FELT;W7,L1035,BLK,TO.35,W10	S.N.A
..3	T0110	AA67-00136A SUN SCREEN-AG;47W,1072*614*,T=82%,G=110		..2		BP61-00352A HOLDER-SCREEN SIDE ASSY;HIPS,47/55W7,HB,	S.N.A
..3		AA98-00333M ASSY K/D-SPEAKER;20W(3001-001107),8 OHM	S.N.A	...	T0081	6003-001019 SCREW-TAPTITE;RH,+B,M4,L12,ZPC(BLK),SWR	S.N.A
..3	T0082	3001-001107 SPEAKER;20W,8OHM,95DB,1300HZ		...		BP61-00158A HOLDER-SENSOR;52Q7,PC,VIOLET	S.N.A
..3	T0082	3001-001134 SPEAKER;30W,8OHM,93DB,60HZ		...		BP61-00209A HOLDER-SCREEN SIDE;55W7,HIPS HB BLK,....	S.N.A
..3	T0076	AA39-00042A LEAD CONNECTOR-ASSY;2.2UF,200MM,REC,REC		...	T0069	AA60-00091T SPACER-FELT;W7,L635,BLK,TO.35,W10	S.N.A
..3		AA98-00049A ASSY-LEAD,CON;-LEAD-CON,CORE,AA39-20505	S.N.A	ASSY COVER REAR			
...4	T0121	3301-001201 CORE-FERRITE;AE,21x11x32mm,1500,280G		1	M0002	BP90-00153B ASSY COVER REAR;P55A	S.N.A
..2	T0064	BP65-00005A CLAMPER CORE;52Q7,NYLON	S.N.A	..2	DVI+TB	6006-001095 SCREW-ASS'Y TAPT;WP,BH,+M4,L12,ZPC(YEL)	S.N.A
..2		BP98-00184A ASSY K/D-WOOD;47W7,XAA	S.N.A	..2	T0069	AA60-00091N SPACER-FELT;-FELT,70X10,-,-,BLK,T1.0,-	S.N.A
..3	HC+CW	AA60-10051A SCREW-WOOD;-SWRCH18A,M4,L16,PH,+,-,-,ZP	S.N.A	..2		AA61-01134A HOLDER-MIRROR,BOT;43,54T6,HIPS HB,BLK	S.N.A
..3	HC+CW	AA60-10051A SCREW-WOOD;-SWRCH18A,M4,L16,PH,+,-,-,ZP	S.N.A	..2		AA64-60421C INLAY-COVER;-PS,TO.3,-,-,BLK,SEA	S.N.A
..3	HC+CW	AA60-10051A SCREW-WOOD;-SWRCH18A,M4,L16,PH,+,-,-,ZP	S.N.A	..2		AA64-60449B INLAY-COVER;SP-434JMF,PS,TO.5,149.3X69.5	S.N.A
..3	HC+CW	AA60-10051A SCREW-WOOD;-SWRCH18A,M4,L16,PH,+,-,-,ZP	S.N.A	..2		AA65-30008A CLAMPER CORE-CORD;-PE,HB,-,BLK,-	S.N.A
..3	HC+CW	AA60-10051A SCREW-WOOD;-SWRCH18A,M4,L16,PH,+,-,-,ZP	S.N.A	..2	T0106	AA91-00751A ASSY-BRACKER,MIRROR;47W3	S.N.A
..3		AA61-00094C HOLDER-RAIL;PCJ533R,ABS,-,-,-,BLK,HB,480	S.N.A	..3	T0069	AA60-00073G SPACER-FELT;PJT,FELT,1.0,800*7	S.N.A
..3		AA61-00507B HOLDER-CABINET,WOOD;43,54,62J8,ABS,-,-,-	S.N.A	...		AA61-00783B BRACKET-MIRROR;47W3,SECC,T1.0	S.N.A
..3		AA61-00616B HOLDER-CRT,MAIN;54J7,DP,-,-,-,AA61-005	S.N.A	..2		AA91-00921A ASSY-HOLDER,MIRROR;HIPS HB BLK,47W3	S.N.A
...4		AA61-00506B HOLDER-CRT,MAIN;43,54,62J8,HIPS,-,-,-,BL	S.N.A	..3	T0069	AA60-00091A SPACER-FELT;-FELT,150X10,-,-,BLK,TO.35,	S.N.A
..3		AA61-10247A BRACKET-FOCUS;S46DS,SECC,T1.0,-,-,-	S.N.A	...		AA61-00879A HOLDER-MIRROR,SIDE(R);47W3,HIPS HB,BLK	S.N.A
..3		AA63-00384A COVER-DUCT;DP 54J8,-,-,-,HB,-,AA63-003	S.N.A	..2		AA91-00921B ASSY-HOLDER,MIRROR;HIPS HB BLK,47W3	S.N.A
...4		AA63-00348B COVER-DUCT;54,62J8,HIPS,-,-,-,HB,BLK,-	S.N.A	..3	T0069	AA60-00091A SPACER-FELT;-FELT,150X10,-,-,BLK,TO.35,	S.N.A
..3		AA64-02536B CABINET-HANDLE WOOD;47W7,HIPS,HB,GRY,DG7	S.N.A	...		AA61-00879B HOLDER-MIRROR,SIDE(L);47W3,HIPS HB,BLK	S.N.A
..3				..2	T0015	BP64-00203A CABINET BACK-BOT;47W7,HIPS V0,BLK	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark
...3	0103-000161	RESIN-HIPS-BASFK456M,BLK,-,V0	S.N.A
..2 T0092	BP96-00077L	ASSY COVER P-TERMINAL,ANT:DP WIDE PJT,HI	
...3 T0092	BP96-00038H	ASSY COVER P-TERMINAL,ANT:WIDE PJT,HIPS	
....4	AA64-02836J	INLAY-TERMINAL,NT:WIDE PJT,PS SHEET,TO.5	S.N.A
....4	AA65-00023A	TERMINAL-BOARD,ANT:,HIPS V0,BLK	S.N.A
..2 T0112	AA64-02061B	CABINET-BACK, TOP:47W3,HIPS HB,BLK,DO	
..2 T0111	AA64-02065C	CABINET-BACK, SIDE:47.55W3,HIPS V0,BLK	
..2 T0108	AA67-00181A	MIRROR-BACK:47W3, GLASS,861*677*421,T3.0	

ASSY CHASSIS

1	M0017	BP91-00917A	ASSY CHASSIS:HCN4727WSC/XAA,P55A	S.N.A
..2		BP91-00801R	ASSY MISC-CHASSIS PACK:DP,HCN4727WSC/XAAS.N.A	
...3	T0081	6003-001023	SCREW-TAPTITE:RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...3	T0081	6003-001023	SCREW-TAPTITE:RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
...3	T0070	AA61-01127A	HOLDER-CHASSIS:COMMANDO,HIPS V0,G4309	S.N.A
...3		AA98-01177B	ASSY K/D-P/MATERIAL:PJT(VCOMANDO),P55A	S.N.A
....4		AA63-10007C	BAND-PP:W18,CLEA,1G	S.N.A
....4		AA69-01808A	BAG-SHEET,LDPE(ANTISTATIC),TO.05,950,90	S.N.A
....4		AA69-01403A	WRAP VINYL-PACKING:SKD CHASSIS,LDPE,TO.0	S.N.A
...3	T0073	BP94-00500C	ASSY PCB MAIN:HCN4727WSC/XAA,P55A	
....4		0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
....4	IC802	1203-000119	IC-NEGA.FIXED REG.:7905,TO-220,3P,-,PLAS	
....4	IC012	1203-000165	IC-POSI.ADJUST REG.:78R12,TO-220,4P,-,PL	
....4	C701	2401-000737	C-AL:2200uF,20%,50V,GP,TP,18x35.5,7	
....4	C701	2401-001068	C-AL:3300uF,20%,50V,GP,BK,22x40,10	
....4	X601	2801-004020	CRYSTAL-UNIT:18.432MHz,30ppm,28-AAM,12pF	
....4	CNW01	3703-001150	CONNECTOR-BACK PANEL:32P,2R,FEMALE,STRAI	
....4	CNW02	3703-001150	CONNECTOR-BACK PANEL:32P,2R,FEMALE,STRAI	
....4	CNZ01	3703-001150	CONNECTOR-BACK PANEL:32P,2R,FEMALE,STRAI	
....4	CN901	3703-001187	CONNECTOR-BACK PANEL:64P,2R,FEMALE,STRAI	
....4	CN906	3711-003046	CONNECTOR-HEADER:BOX,9P,1R,2.5MM,STRAIGH	
....4	CN906	3711-003641	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG	
....4	CN906	3711-003973	CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIG	
....4	CN906	3711-003975	CONNECTOR-HEADER:BOX,14P,1R,2.5mm,STRAIG	
....4	CN906	3711-004946	CONNECTOR-HEADER:BOX,15P,1R,2.5MM,STRAIG	
....4	JA703	3722-001163	JACK-VHS:4P,12mm,AU,BLK,N	
....4	JA701	3722-001426	JACK-PIN:9P,3.4mm,NI,BLK,-	
....4	JA704	3722-001796	JACK-PIN:7P(10P)-,NI,RD/RD/WH/WH/RD/BL/	
....4	JA702	3722-001871	JACK-PIN:5P(9P),8.3MM,NI,GRN/BLU/RED/WHIT	
....4	L802	AA27-10001C	COIL CHOKE:-,100uH,K,-,5.0A,ST,700UH-K/R	
....4	L801	AA29-00004A	FILTER LINE NOISE:-,20UH,3A,AC80-260V,TO	
....4	T0076	AA39-20010B	LEAD CONNECTOR-ASSY:1P,500,YFH800-01,S,	
....4	T0076	AA39-20010B	LEAD CONNECTOR-ASSY:1P,500,YFH800-01,S,	
....4	TU02	AA40-00049A	TUNER:TCPN3081PC19C(S),TCPN3081PC19C(S),	
....4	TU04	AA40-00049A	TUNER:TCPN3081PC19C(S),TCPN3081PC19C(S),	
....4	TU01	AA59-00164A	MODULE-RF,SPLITTER:-,UMX-NT-005,-,2IN/3O	
....4		AA63-00396B	SHIELD CASE-TOP:PRJT,P54A,SPT,TO.5,-,-,	S.N.A
....4		AA63-00397B	SHIELD CASE-BOT:PRJT,P54A,SPT,TO.5,-,-,	S.N.A
....4		AA63-00610A	SHIELD CASE:COMMANDO,SPT,TO.5,W141.5,H1	S.N.A
....4		AA63-10002A	BAND-TIE-NYLON66 V2,L100,NTR	S.N.A
....4		AA65-30018A	CLAMPER CORE-WIRE:DONG-A,NYLON-66,-,-,-,	S.N.A
....4		AA65-30111A	CLAMPER CORE-WIRE:ALL MODEL,NYLON,V0,-,V	S.N.A
....4	T0104	AA95-02001K	ASSY SUB-PCB MICOM:,C2	
....5	T0083	0402-000274	DIODE-RECTIFIER:UF4004,400V,1A,DO-41,TP	
....5	Q409	0505-000109	FET-SILICON:2N7000,N,60V,200mA,5ohm,400m	
....5	Q409	0505-000109	FET-SILICON:2N7000,N,60V,200mA,5ohm,400m	
....5	IC904	1203-001943	IC-VOL. DETECTOR:7025,TO-92,3P,-,PLASTIC	
....5	X901	2801-004071	CRYSTAL-UNIT:6MHZ,30PPM,28-AAM,20PF,400H	
....5	CN901	3703-001175	CONNECTOR-BACK PANEL:64P,2R,MALE,ANGLE,A	
....5		AA97-07275A	ASSY SMD:SVP-47W3HRT,P55A, , ,	S.N.A
....6	D905	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
....6	D906	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
....6	D920	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
....6	D923	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
....6	D602	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
....6	D901	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
....6	D902	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
....6	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
....6	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
....6	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
....6	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
....6	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	
....6	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-	

Loc. No.	Code No.	Description ; Specification	Remark
.....6	DZ016	0403-001375	DIODE-ZENER:RLZ3.6B,3.6-3.845V,500mW,LL-
.....6	R0915	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....6	R0916	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....6	R0917	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....6	R0920	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....6	R0914	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....6	R0913	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....6	R0910	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....6	R0908	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....6	R0902	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....6	IC112	1103-000180	IC-EEPROM:24C16,2Kx8Bit,SOP,8P,150MIL,10
.....6	T0087	1203-002302	IC-POSI.FIXED REG.:78RM33D,D-PAK,3P,-,PL
.....6	R901	1204-001912	IC-DECODER:SDA5550M,P-MOFF,100P,-,PLASTI
.....6	R981	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....6	R964	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....6	R960	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....6	R959	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....6	R965	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608
.....6	R956	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R953	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R952	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R969	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R970	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R972	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R979	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R940	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R909	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R916	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R918	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R939	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R923	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R922	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R907	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R917	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608
.....6	R911	2007-000076	R-CHIP:330ohm,5%,1/10W,TP,1608
.....6	R963	2007-000077	R-CHIP:470ohm,5%,1/10W,TP,1608
.....6	R901	2007-000077	R-CHIP:470ohm,5%,1/10W,TP,1608
.....6	R930	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608
.....6	R933	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608
.....6	R936	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608
.....6	R974	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608
.....6	R905	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608
.....6	R921	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608
.....6	R924	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608
.....6	R925	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608
.....6	R915	2007-000081	R-CHIP:2.7Kohm,5%,1/10W,TP,1608
.....6	R913	2007-000081	R-CHIP:2.7Kohm,5%,1/10W,TP,1608
.....6	R912	2007-000081	R-CHIP:2.7Kohm,5%,1/10W,TP,1608
.....6	R978	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R976	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R971	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R958	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R980	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R982	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R985	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R986	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R903	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R904	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R906	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R908	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R955	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R954	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R928	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R927	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R983	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R934	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608
.....6	R987	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....6	R957	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....6	R944	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608
.....6	R926	2007-000097	R-CHIP:47Kohm,5%,1/10W,TP,1608
.....6	R975	2007-000121	R-CHIP:820ohm,5%,1/10W,TP,1608
.....6	R942	2007-000123	R-CHIP:1.5Kohm,5%,1/10W,TP,1608
.....6	R941	2007-000123	R-CHIP:1.5Kohm,5%,1/10W,TP,1608
.....6	R914	2007-000123	R-CHIP:1.5Kohm,5%,1/10W,TP,1608
.....6	R988	2007-000290	R-CHIP:100ohm,5%,1/8W,TP,2012
.....6	R962	2007-000583	R-CHIP:22Kohm,1%,1/10W,TP,1608
.....6	R961	2007-000939	R-CHIP:47Kohm,1%,1/10W,TP,1608

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark	
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	T0122	2802-001179	RESONATOR-CERAMIC:4MHZ,0.5%,BK,8X3X5.5MM	
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	CN02	3703-001124	CONNECTOR-BACK PANEL:32P,2R,MALE,ANGLE,A	
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	CN01	3703-001124	CONNECTOR-BACK PANEL:32P,2R,MALE,ANGLE,A	
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	CN906	3711-001164	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,ANGLE,-	
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	CN906	3711-003601	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,ANGLE,	
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,5	CN906	BP97-00169A	ASSY SMD:HCM4215WJX/XAA,P55A	S.N.A
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,6	FD13	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,6	FD14	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,6	FD15	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,6	FD16	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,6	FD17	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	C120	2203-000181	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,6	FD10	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	C120	2203-000189	C-CERAMIC,CHIP:100nF,+80-20%,25V,Y5V,TP,6	FD01	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	C120	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,32166	FD02	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,16086	FD07	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,16086	FD08	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,16086	FD09	0401-000133	DIODE-SWITCHING:RLS4148,100V,200MA,SOD-8	
.....6	C120	2203-000236	C-CERAMIC,CHIP:0.1nF,5%,50V,COG,TP,16086	DZ016	0403-000746	DIODE-ZENER:RLZ3.9B,3.89-4.16V,500MW,LL-	
.....6	C120	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,20126	DZ016	0403-001016	DIODE-ZENER:RLZ2.2B,5.96-6.27V,500MW,LL-	
.....6	C120	2203-000357	C-CERAMIC,CHIP:0.15nF,5%,50V,COG,TP,16086	DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....6	C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-6	DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....6	C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,1608,-6	DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP	
.....6	C120	2203-000440	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-6	S001	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6	C120	2203-000748	C-CERAMIC,CHIP:0.03nF,5%,50V,COG,TP,20126	FQ13	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6	C120	2203-000748	C-CERAMIC,CHIP:0.03nF,5%,50V,COG,TP,20126	FQ04	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6	C120	2203-001048	C-CERAMIC,CHIP:0.56nF,10%,50V,COG,TP,2016	FQ03	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6	C120	2203-005809	C-CERAMIC,CHIP:1000nF,10%,16V,X7R,TP,2016	FQ02	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6	C950	2402-000179	C-AL,SMD:47uF,20%,16V,GP,TP,6.6x6.6x5.46	FQ08	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	C936	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.46	FQ09	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	C921	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.46	FQ12	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	C918	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.46	P001	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	C915	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.46	FQ06	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	C913	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.46	FQ05	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	C938	2402-001042	C-AL,SMD:100uF,20%,16V,GP,TP,6.6x6.6x5.46	EQ15	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	C917	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.46	EQ14	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	C912	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.46	EQ13	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
.....6	C911	2402-001049	C-AL,CHIP:10uF,20%,16V,GP,TP,3.3x3.3x5.46	FQ07	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
.....6	L905	2703-001245	INDUCTOR-SMD:8.2uH,10%,2x1.25x1.25mm6	Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
.....6	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,6	Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
.....6	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,6	IC104	0801-000662	IC-CMOS LOGIC:74HC123,MULTIVIBRATOR,SOP,1	
.....6	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,6	IC106	1001-001082	IC-VIDEO SWITCH:BA7657F,-,SOP,24P,300MIL	
.....6	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,6	IC06	1203-001211	IC-VOL. DETECTOR:7027,SOT-89,3P,-,PLASTI	
.....6	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,6	T0087	1203-002186	IC-POSI.FIXED REG.:18,DPAK,3P,240MIL,PLA	
.....6	G101	3301-001324	CORE-FERRITE BEAD:AB,150HM,2X1.25X0.9MM,6	T0087	1203-002302	IC-POSI.FIXED REG.:78RM33D,D-PAK,3P,-,PL	
.....6	R949	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,16086	IC02	1204-001814	IC-SELECTOR:CXA2151Q,QFP,48P,144MIL,PLAS	
.....6	R950	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,16086	IC01A	1204-001938	IC-DECODER:VSP9407B-B11,MOPF,80P,14X14MM	
.....6	R951	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,16086	IC118	1204-001989	IC-VIDEO PROCESS:CXA2165Q,QFP,64P,20X14MM	
.....6	R945	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,16086	SR08	2007-000052	R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6	R946	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,16086	FR80	2007-000052	R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6	R948	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,16086	FR79	2007-000052	R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6	R966	2007-000931	R-CHIP:470ohm,5%,1/8W,TP,20126	FR78	2007-000052	R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6	PCB	AA41-00599B	PCB-MICOM:HCM4215W,FR-4,2L,B,1.6T,180X246	FR57	2007-000052	R-CHIP:10Kohm,1%,1/10W,TP,1608	
.....6	IC902	0202-001167	SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SN6	FR35	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	IC902	1102-001130	IC-EEPROM:M27W201-80F6,256KX8BIT,DIP,326	FR07	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	IC801	0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1,2.63Sn/37Pb6	ER90	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....4	IC801	AA96-00475C	ASSY H/S:SILICON-OIL,KA278R09,KA7808,AA66	FR76	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	T0087	0205-000129	GREASE-SILICON:SC102,JAPAN6	FR96	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	T0123	1203-000293	IC-POSI.FIXED REG.:7808,TO-220,3P,-,PLAS6	SR09	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	T0123	1203-002003	IC-VOLTAGE REGULATOR:278R09,TO-220,4P,-6	SR22	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	T0081	6003-000334	SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR6	ER29	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	T0123	AA62-00066B	HEAT SINK:D2,D3,AL,T1,0.89,70,-,AA62-006	ER04	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....4	IC601	1203-001978	IC-VOLTAGE REGULATOR:KA278RA05,TO-220F,46	ER05	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....4	IC601	AA96-00623E	ASSY H/S:SCREW,MAIN,AA62-00056A,TA7265,6	ER06	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	T0124	0205-000129	GREASE-SILICON:SC102,JAPAN6	ER13	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	T0124	1201-001026	IC-POWER AMP:7265,ZIP,1P,19.6MIL,DUAL,16	ER19	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	T0081	6003-000334	SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR6	ER18	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....5	T0081	AA62-00056A	HEAT SINK-PS:-,T1,0,-,41*35*70,D2,-,6	ER17	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....4	T0095	BP39-00036A	LEAD CONNECTOR:J54A/SP42W5HP,UL2547#26,U6	SR03	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....4	T0095	BP63-00030A	SHIELD CASE:COMMANDO,SPT,TO,5,W26,0,L136	SR04	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....4	T0095	BP95-00142N	ASSY SUB PCB-PRO SCAN:HCN4727WX/XAA,P55A6	SR05	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....5	FC48	2305-000011	SOLDER-WIRE FLUX:-,RS60S,D1,2.63Sn/37Pb6	SR06	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....5	FC59	2305-000704	C-FILM,MPEF:470nF,5%,250V,TP,21.5X13.0X76	SR10	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....5	FC58	2305-000704	C-FILM,MPEF:100nF,5%,250V,TP,16.5X10.3X56	SR11	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....5	EX01	2801-004019	C-FILM,PE-PPF:100nF,5%,50V,TP,20x16x8.56	SR02	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....5	T0122	2802-001177	CRYSTAL-UNIT:20.25MHz,30ppm,28-AAM,13pF,6	FR71	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....5	T0122	2802-001177	RESONATOR-CERAMIC:2.696MHZ,0.4%,BK,10X4.6	FR74	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	

Loc. No.	Code No.	Description ; Specification	Remark
.....6 D08	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6 D07	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6 D06	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
.....6 DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....6 DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....6 DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-	
.....6 Q02	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6 Q03	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
.....6 Q10	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
.....6 Q04	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
.....6 Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
.....6 Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
.....6 Q409	0505-000110	FET-SILICON:2N7002,N,60V,115MA,7.5OHM,0.	
.....6 IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P4	
.....6 IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P4	
.....6 IC104	0801-002345	IC-CMOS LOGIC:7S04,INVERTER,SOT-353,5P4	
.....6 IC08	1001-000164	IC-ANALOG MULTIPLEX:74HC4052,CMOS,SOP,16	
.....6 IC13	1001-001155	IC-ANALOG MULTIPLEX:NC7SB3157P6X,CMOS,S6	
.....6 IC112	1103-001195	IC-EEPROM:24C64,8Kx8BIT,SOP,8P,150MIL,10	
.....6 DU410	1201-001135	IC-OP AMP:324,SOP,ST,14P,150MIL,QUAD,100	
.....6 DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST	
.....6 DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST	
.....6 DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST	
.....6 DU410	1201-001504	IC-OP AMP:072,SOP,8P,150MIL,DUAL,-,PLAST	
.....6 T0074	1201-001520	IC-VIDEO AMP:EL2250CS,SOIC,8P,150MIL,DUA	
.....6 IC03	1203-001824	IC-VOL. DETECTOR:7042,SOT-89,3P,-,PLASTI	
.....6 T0087	1203-002302	IC-POSI.FIXED REG.:78RM33D,D-PAK,3P,-,PL	
.....6 IC17	1209-001163	IC-PLL:TLC2932PWLE,SOP,14P,-,PLASTIC	
.....6 R36	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012	
.....6 R35	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012	
.....6 R31	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012	
.....6 R30	2007-000028	R-CHIP:39ohm,5%,1/8W,TP,2012	
.....6 R143	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6 R144	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6 R25	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6 R122	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6 R123	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6 R141	2007-000070	R-CHIP:0ohm,5%,1/10W,TP,1608	
.....6 R136	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6 R15	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6 R24	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6 R45	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6 R46	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6 R09	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6 R10	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6 R129	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6 R134	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6 R135	2007-000072	R-CHIP:47ohm,5%,1/10W,TP,1608	
.....6 R59	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6 R65	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6 R71	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6 R77	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6 R91	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6 R53	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6 R02	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6 R16	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6 R17	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6 R20	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6 R47	2007-000074	R-CHIP:100ohm,5%,1/10W,TP,1608	
.....6 R62	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R64	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R68	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R58	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R56	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R52	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R70	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R98	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R94	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R82	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R80	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R76	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R74	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R38	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R37	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R110	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R11	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R101	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	

Loc. No.	Code No.	Description ; Specification	Remark
.....6 R03	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R39	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R50	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R44	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R43	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R42	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R41	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R40	2007-000078	R-CHIP:1Kohm,5%,1/10W,TP,1608	
.....6 R128	2007-000079	R-CHIP:1.8Kohm,5%,1/10W,TP,1608	
.....6 R81	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6 R75	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6 R69	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6 R51	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6 R57	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6 R63	2007-000080	R-CHIP:2Kohm,5%,1/10W,TP,1608	
.....6 R109	2007-000082	R-CHIP:3.3Kohm,5%,1/10W,TP,1608	
.....6 R66	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R61	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R60	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R55	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R54	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R79	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R78	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R73	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R72	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R67	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R49	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R08	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R07	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R06	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R04	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R01	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R48	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R133	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R121	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R119	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R118	2007-000084	R-CHIP:4.7Kohm,5%,1/10W,TP,1608	
.....6 R86	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6 R92	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6 R93	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6 R96	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6 R97	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6 R85	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6 R113	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6 R114	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6 R115	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6 R83	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6 R84	2007-000090	R-CHIP:10Kohm,5%,1/10W,TP,1608	
.....6 R125	2007-000091	R-CHIP:12Kohm,5%,1/10W,TP,1608	
.....6 R05	2007-000102	R-CHIP:100Kohm,5%,1/10W,TP,1608	
.....6 R127	2007-000109	R-CHIP:1Mohm,5%,1/10W,TP,1608	
.....6 R100	2007-000118	R-CHIP:390ohm,5%,1/10W,TP,1608	
.....6 R32	2007-000119	R-CHIP:560ohm,5%,1/10W,TP,1608	
.....6 R34	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....6 R29	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....6 R28	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....6 R117	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....6 R107	2007-000122	R-CHIP:1.2Kohm,5%,1/10W,TP,1608	
.....6 R33	2007-000124	R-CHIP:2.2Kohm,5%,1/10W,TP,1608	
.....6 R120	2007-000124	R-CHIP:2.2Kohm,5%,1/10W,TP,1608	
.....6 R90	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....6 R89	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....6 R88	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....6 R87	2007-000133	R-CHIP:330Kohm,5%,1/10W,TP,1608	
.....6 R108	2007-000381	R-CHIP:13Kohm,5%,1/10W,TP,1608	
.....6 R139	2007-000402	R-CHIP:150ohm,5%,1/10W,TP,1608	
.....6 R138	2007-000402	R-CHIP:150ohm,5%,1/10W,TP,1608	
.....6 R137	2007-000402	R-CHIP:150ohm,5%,1/10W,TP,1608	
.....6 R99	2007-000704	R-CHIP:3.6Kohm,5%,1/16W,DA,TP,1608	
.....6 R95	2007-000704	R-CHIP:3.6Kohm,5%,1/16W,DA,TP,1608	
.....6 R126	2007-000857	R-CHIP:4.3Kohm,1%,1/16W,DA,TP,1608	
.....6 R27	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6 R26	2007-001167	R-CHIP:75ohm,5%,1/10W,TP,1608	
.....6 R116	2007-001179	R-CHIP:8.2Kohm,5%,1/10W,TP,1608	
.....6 RN04	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP,8P,TP	
.....6 RN05	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP,8P,TP	
.....6 RN06	2011-000585	R-NETWORK:470HM,5%,1/16W,L,CHIP,8P,TP	

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
.....5	R682	2001-001146	R-CARBON(S):4.7OHM,5%,1/2W,AA,TP,2.4X6.45	C701	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11.5
.....5	R681	2001-001146	R-CARBON(S):4.7OHM,5%,1/2W,AA,TP,2.4X6.45	C701	2401-002300	C-AL:47uF,20%,50V,GP,TP,6.3x11.5
.....5	R811	2001-001182	R-CARBON(S):7.5KOHM,5%,1/2W,AA,TP,2.4X6.5	C701	2401-002300	C-AL:47uF,20%,50V,GP,TP,6.3x11.5
.....5	R814	2003-001098	R-METAL OXIDE(S):22Kohm,5%,3W,AA,TP,6x165	C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,5
.....5	R805	2004-000970	R-METAL:470ohm,1%,1/4W,AA,TP,2.4x6.4mm5	C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,5
.....5	R024	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm5	C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,5
.....5	R024	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm5	C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,5
.....5	R024	2004-001970	R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.55	C701	2401-002459	C-AL:220uF,20%,25V,LZ,TP,10x16,5
.....5	R024	2004-001970	R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.55	C701	2401-002463	C-AL:470uF,20%,16V,GP,TP,8x11.5,5
.....5	R024	2004-001970	R-METAL(S):1.8Kohm,1%,1/2W,AA,TP,6.5x2.55	C701	2401-002463	C-AL:470uF,20%,16V,GP,TP,8x11.5,5
.....5	C695	2301-000192	C-FILM,PEF:1nf,5%,50V,TP,5.3x10mm,5mm5	C701	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11.5,5
.....5	C694	2301-000192	C-FILM,PEF:1nf,5%,50V,TP,5.3x10mm,5mm5	C701	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11.5
.....5	C689	2305-000665	C-FILM,MPEF:100nf,5%,63V,TP,7.5x4.0x5.0m5	C701	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11.5
.....5	C687	2305-000665	C-FILM,MPEF:100nf,5%,63V,TP,7.5x4.0x5.0m5	C701	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11.5
.....5	C682	2305-000665	C-FILM,MPEF:100nf,5%,63V,TP,7.5x4.0x5.0m5	C701	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11.5
.....5	C701	2401-000025	C-AL:100uF,20%,16V,GP,TP,6.3x11.55	C701	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11.5
.....5	C701	2401-000025	C-AL:100uF,20%,16V,GP,TP,6.3x11.55	L105	2701-000106	INDUCTOR-AXIAL:1.5uH,10%,3x7mm
.....5	C701	2401-000025	C-AL:100uF,20%,16V,GP,TP,6.3x11.55	L119	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000025	C-AL:100uF,20%,16V,GP,TP,6.3x11.55	L120	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000039	C-AL:1000uF,20%,16V,GP,TP,10x16,55	L121	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000039	C-AL:1000uF,20%,16V,GP,TP,10x16,55	L122	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7.55	L123	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7.55	L124	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11.55	L107	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11.55	L108	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,55	L111	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,55	L114	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000471	C-AL:10uF,20%,50V,BP,TP,5x11,5mm5	L113	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L112	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L703	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L106	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L104	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L103	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L101	2701-000115	INDUCTOR-AXIAL:10uH,10%,3x7mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L706	2701-001030	INDUCTOR-AXIAL:43uH,10%,5x14mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L705	2701-001030	INDUCTOR-AXIAL:43uH,10%,5x14mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	L102	2701-001040	INDUCTOR-AXIAL:10uH,10%,4.5x14mm
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	G101	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	G101	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	G101	3301-000287	CORE-FERRITE BEAD:AA,3.5x1.0x6.0mm,1500,
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	CN906	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	CN906	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH
.....5	C701	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,55	CN906	3711-002643	CONNECTOR-HEADER:BOX,4P,1R,2.5mm,STRAIGH
.....5	C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,25	CN906	3711-002645	CONNECTOR-HEADER:BOX,6P,1R,2.5mm,STRAIGH
.....5	C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,25	GT01	AA60-40014A	PIN-GT,ASSY:AUTO S.N.A
.....5	C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,25	GT02	AA60-40014A	PIN-GT,ASSY:AUTO S.N.A
.....5	C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,25	GT03	AA60-40014A	PIN-GT,ASSY:AUTO S.N.A
.....5	C701	2401-000603	C-AL:1UF,20%,50V,GP,TP,5X11,25		BP97-00513Q	ASSY SMD:HCN4226WX/XAA,P55A S.N.A
.....5	C701	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11.5,56	DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-000314	DIODE-ZENER:RLZJ9.1B,8.80-9.30V,500MW,LL
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001016	DIODE-ZENER:RLZ6.2B,5.96-6.27V,500MW,LL-
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP
.....5	C701	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,56	DZ016	0403-001117	DIODE-ZENER:RLZ12B,5%,500mW,LL-34,TP
.....5	C701	2401-001192	C-AL:33uF,20%,50V,GP,TP,6.3x11,56	0703	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,56	0704	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001513	C-AL:47uF,20%,16V,WVT,TP,5x11,56	0707	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	0708	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	0709	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	0710	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	0101	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	0103	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,56	0106	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-
.....5	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,56	IC106	1001-001177	IC-VIDEO SWITCH:TEA6425D,VIDEO SWITCH ,S
.....5	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,56	IC106	1001-001177	IC-VIDEO SWITCH:TEA6425D,VIDEO SWITCH ,S
.....5	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,56	IC605	1001-001178	IC-AUDIO SWITCH:TEA6422D,AUDIO SWITCH ,S
.....5	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,56	IC704	1002-001048	IC-A/D&D/A CONVERTER:PCF8591T,8BIT,SOP,1

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark		
.....5	EY107	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	R841	2003-002102	R-METAL OXIDE(S):68Kohm,5%,2W,AF,TP,4x12	
.....5	EY106	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	R024	2004-004029	R-METAL(S):10Kohm,1%,1/2W,AA,TP,2.5x6.5mm	
.....5	EY121	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	R801	2003-002285	R-METAL OXIDE(S):1.5KOHM,5%,2W,AF,TP,6x1	
.....5	EY120	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	DZ016	0403-000698	DIODE-ZENER:TZP12A,12V,11.4-12.6V,1W,DO-	
.....5	EY12	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	Q409	0505-001723	FET-SILICON:FQP630TSTU,N,200V,9A,0.40HMM,	
.....5	EY119	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	Q409	0505-001723	FET-SILICON:FQP630TSTU,N,200V,9A,0.40HMM,	
.....5	EY118	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	Q473	BP96-00006B	ASSY HEAT SINK P-HS,SCREW,IRF640B,2SC412	S.N.A
.....5	EY117	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	CIS	0205-001027	OIL-SILICON:G746,-,-	S.N.A
.....5	EY116	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	T0090	0502-001100	TR-POWER:2SC4125,NPN,70W,TO-3PML,BK,8-	
.....5	EY115	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	Q409	0505-001722	FET-SILICON:IRF5640B,N,200V,18A,0.180HMM,	
.....5	EY08	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	T0081	6003-000333	SCREW-TAPTITE:RH,+,2S,M3,L10,ZPC(YEL),SW	S.N.A
.....5	EY07	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	CIS	AA60-30001A	WASHER-PLATE:M3,1D3.5,15X8.5,T1.0,SBHG	S.N.A
.....5	EY06	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A5	CIS	BP62-00001A	HEAT SINK:COMMANDO,A1050P,T2.0,W62.0,H50	S.N.A
.....5	EY05	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	T0121	3301-001201	CORE-FERRITE:AE,21x11x32mm,1500,280G	
.....5	EY04	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A2	T0105	BP94-00239A	ASSY PCB MISC-DY:JACK:DPHCM4215W3S/XAA,	
.....5	EY03	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3		0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
.....5	EY02	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	GT13	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5,-,NYLON66	S.N.A
.....5	EY01	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	GT09	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5,-,NYLON66	S.N.A
.....5	EY105	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	GT05	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5,-,NYLON66	S.N.A
.....5	EY104	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	GT01	AA60-40012D	PIN-GT,ASSY:T1.6,6-12.5,-,NYLON66	S.N.A
.....5	EY103	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3		AA61-01197A	HOLDER-PCB,DY:COMANDO,ABS V0,BLK	S.N.A
.....5	EY102	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3		AA97-07230N	ASSY AUTO:COMMANDO	S.N.A
.....5	EY101	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	R301	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
.....5	EY100	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	R302	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
.....5	EY10	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	R303	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
.....5	EY09	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	PCB	AA41-00632A	PCB-DY CONNECTION:HCM4215W,FR,1,1L,A,1.6	S.N.A
.....5	EY122	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A2	T0100	BP94-00338A	ASSY PCB MISC-A/V FRONT:DPHCM473W3S/XAA	
.....5	EY148	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3		0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
.....5	EY147	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	SW101	3404-000208	SWITCH-TACT:12V,50mA,120gf,6x6mm,SPST	
.....5	EY142	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	CN906	3711-000447	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,ANGLE,-	
.....5	EY141	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	CN906	3711-003601	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,ANGLE,	
.....5	EY140	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	JK101	3722-000544	JACK-VHS:4P,11.5mm,AG,BLK,N	
.....5	EY14	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	JK102	3722-001164	JACK-PIN:3P,4mm,SN,WH:YE:RE,#16-22	
.....5	EY139	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	T0081	6003-001023	SCREW-TAPTITE:RWH,+,B,M3,L10,ZPC(YEL),SW	S.N.A
.....5	EY138	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	T0076	AA39-00260A	LEAD CONNECTOR-ASSY,UL1007#26,UL/CSA,3P	
.....5	EY155	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3		AA63-10002A	BAND-TIE:NYLON66 V2,L100,NTR	S.N.A
.....5	EY154	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	T0014	AA91-00762D	ASSY-JACK,SIDE:P54A PAL XAA,W30	
.....5	EY153	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4		AA61-00793C	HOLDER-JACK:W3,ABS HB,BLK,DG703P	S.N.A
.....5	EY152	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	T0150	AA64-02085D	DOOR-AV:W3,ABS HB,BLK,DG703P	S.N.A
.....5	EY151	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4		AA64-02086E	INLAY-AV:W3,PS SHEET,T0.5,P55A	S.N.A
.....5	EY150	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3		AA97-07429A	ASSY AUTO-A/V FRONT:HCM4215WX/XAA,P55A	S.N.A
.....5	EY15	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	R125	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	EY149	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	PCB	AA41-00499B	PCB-FRONT A/V:SVP-54T6SR,FR,1,1L,A,1.6T,	S.N.A
.....5	EY13	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	CNW01A	BP39-00016B	LEAD CONNECTOR:HCL4715WB,UL2547#26,UL/CS	
.....5	EY129	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A2	T0098	BP94-00346A	ASSY PCB MISC-VM:DPHCM5525J3S/XAA,P55A	
.....5	EY128	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3		0202-000187	SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A
.....5	EY127	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	RZ120	2008-001097	R-FUSIBLE(S):330HM,5%,1/2W,AC,BK,2.5X6.5	
.....5	EY126	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	T0121	3301-001201	CORE-FERRITE:AE,21x11x32mm,1500,280G	
.....5	EY125	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	T0079	AA33-00017A	MAGNET CONVERGENCE:JH 92LT - 29G,-,29.1M	
.....5	EY124	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	T0076	AA39-20055F	LEAD CONNECTOR-ASSY,6P,700MM,YBNH250-06	
.....5	EY123	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	OZ102	AA96-00243L	ASSY H/S:-,CRT,AA62-000450A,2SC2344,HERC	S.N.A
.....5	EY137	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4		0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A
.....5	EY136	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	T0090	0502-000153	TR-POWER:2SC2344-D,NPN,1.2W,TO-220,-,60	
.....5	EY135	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	T0081	6003-000335	SCREW-TAPTITE:RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
.....5	EY134	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4		AA62-00045A	HEAT SINK-PS:-,T1.0,-,-,DREAM,-,-,-,-,-	S.N.A
.....5	EY130	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A3	OZ101	AA96-00243M	ASSY H/S:-,AMP,AA62-000450A,2SA1011,HERC	S.N.A
.....5	EY131	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4		0205-000129	GREASE-SILICON:SC102,JAPAN	S.N.A
.....5	EY132	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	T0090	0502-000131	TR-POWER:2SA1011-D,PNP,1.2W,TO-220,-,60	
.....5	EY133	6042-000002	EYELET:ID1.5,OD2,L2.8,NH+SN,BSP3-1/2H	S.N.A4	T0081	6003-000335	SCREW-TAPTITE:RH,+,2S,M3,L8,ZPC(YEL),SWR	S.N.A
.....5	GT404	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4		AA62-00045A	HEAT SINK-PS:-,T1.0,-,-,DREAM,-,-,-,-,-	S.N.A
.....5	GT433	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A3		AA97-07230M	ASSY AUTO-VM:COMMANDO	S.N.A
.....5	GT801	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	DZ106	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
.....5	GT802	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	DZ105	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
.....5	GT807	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	DZ102	0401-000005	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
.....5	GT810	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
.....5	GT811	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
.....5	GT14	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	T0083	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
.....5	GT15	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	OZ103	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
.....5	GT16	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	OZ106	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
.....5	GT17	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	OZ105	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
.....5	GT33	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	OZ104	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
.....5	GT34	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	RZ122	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4MM	
.....5	GT35	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A4	R125	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	0	AA41-00598D	PCB-SUB:HCM4215W,CEM-1,1L,D,1.6T,330X245	S.N.A4	R125	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R024	2004-005051	R-METAL(S):2.2KOHM,1%,1/2W,AA,TP,2.4X6.4	S.N.A4	R125	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	RS801S	3601-000102	FUSE-AXIAL LEAD:125V,1A,FAST-ACTING,GLAS	4	R125	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
.....5	R840	2001-001045	R-CARBON(S):1.2KOHM,5%,1/2W,AA,TP,2.4X6.4	4	R125	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	



Loc. No.	Code No.	Description ; Specification	Remark
....4	R125	2001-000258 R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000331 R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000331 R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000554 R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000666 R-CARBON:33OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000832 R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	RZ110	2001-001100 R-CARBON(S):2.70HM,5%,1/2W,AA,TP,2.4X6.4	
....4	RZ104	2001-001100 R-CARBON(S):2.70HM,5%,1/2W,AA,TP,2.4X6.4	
....4	RZ105	2001-001139 R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RZ106	2001-001139 R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	RZ114	2003-000532 R-METAL OXIDE(S):18ohm,5%,2W,AF,TP,4x12m	
....4	RZ103	2003-000713 R-METAL OXIDE(S):47ohm,5%,2W,AF,TP,4x12m	
....4	RZ111	2003-000713 R-METAL OXIDE(S):47ohm,5%,2W,AF,TP,4x12m	
....4	RZ123	2003-002157 R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM	
....4	RZ113	2003-002157 R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM	
....4	RZ112	2003-002157 R-METAL OXIDE:220OHM,5%,2W,AG,TP,6X16MM	
....4	RFZ101	2008-001086 R-FUSIBLE(S):3.3ohm,5%,2W,AG,TP,3.9x12mm	
....4	C598	2201-000193 C-CERAMIC,DISC:0.01NF,0.25PF,50V,COG,TP,	
....4	C598	2201-000193 C-CERAMIC,DISC:0.01NF,0.25PF,50V,COG,TP,	
....4	C598	2201-000516 C-CERAMIC,DISC:4.7NF,+100-0%,500V,Y5U,TP	
....4	C598	2201-000516 C-CERAMIC,DISC:4.7NF,+100-0%,500V,Y5U,TP	
....4	C598	2201-000604 C-CERAMIC,DISC:0.056NF,+100-0%,500V,SL,T	
....4	C701	2401-000480 C-AL:10uF,20%,50V,GP,TP,5x11,5	
....4	C701	2401-000832 C-AL:220uF,20%,25V,GP,TP,8x11,5,5	
....4	C701	2401-001157 C-AL:33uF,20%,160V,GP,TP,12,5x20,5	
....4	C701	2401-001220 C-AL:4.7uF,20%,160V,GP,TP,8x11,5,5	
....4	C701	2401-001220 C-AL:4.7uF,20%,160V,GP,TP,8x11,5,5	
....4	C701	2401-001513 C-AL:47uF,20%,16V,WT,TP,5x11,5	
....4	C701	2401-002144 C-AL:47uF,20%,16V,GP,TP,5x11,5	
....4	LZ101	2701-000002 INDUCTOR-AXIAL:100uH,10%,4,2x9.8mm	
....4	CN906	3711-002642 CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH	
....4	CN906	3711-002642 CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH	
....4	CN906	3711-002642 CONNECTOR-HEADER:BOX,3P,1R,2.5mm,STRAIGH	
....4	PCB	AA41-00611A PCB-VM:HCM4215W,FR-1,1L,A,1.6T,245X245,P	S.N.A
....4	T0081	6003-001023 SCREW-TAPTITE:RWH,+B,M3,L10,ZPC(YEL),SW	S.N.A
..2	T0099	BP94-00503R ASSY PCB CRT-PCB EMI:DP,HCM4727WSC/XAA,P	
....3		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1,2.63Sn/37Pb	S.N.A
....3	VR501	2101-000321 VR-ROTARY:1Mohm,-,0.6W,SIDE	
....3	VR531	2101-000321 VR-ROTARY:1Mohm,-,0.6W,SIDE	
....3	VR561	2101-000321 VR-ROTARY:1Mohm,-,0.6W,SIDE	
....3	C701	2401-000480 C-AL:10uF,20%,50V,GP,TP,5x11,5	
....3	T0121	3301-001201 CORE-FERRITE:AE,21x11x32mm,1500,280G	
....3	T0121	3301-001502 CORE-FERRITE:AE,16.5*ø7*ø30MM,-,-	
....3	V501	3704-001019 SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	
....3	V531	3704-001019 SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	
....3	V561	3704-001019 SOCKET-CRT:10P,29.1PI,35.5PI,AU30U,-	
....3	CN906	3711-002645 CONNECTOR-HEADER:BOX,6P,1R,2.5mm,STRAIGH	
....3	CN906	3711-002648 CONNECTOR-HEADER:BOX,9P,1R,2.5mm,STRAIGH	
....3	CN906	3711-003052 CONNECTOR-HEADER:BOX,10P,1R,2.5MM,STRAIG	
....3	CN906	3711-003052 CONNECTOR-HEADER:BOX,10P,1R,2.5MM,STRAIG	
....3	CN906	3711-003973 CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIG	
....3	CN906	3711-003973 CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIG	
....3	SG301	4715-001050 SURGE ABSORBER:2.4kV,20%,1500A,-,DISC-RA	
....3		6902-000395 BAG PE:LDPE,TO.05,W200,L140,,	S.N.A
....3	SG562	AA27-00084A COIL:S-23,-,-,-,-,-,S-23,5000Mohm MIN,	
....3	SG532	AA27-00084A COIL:S-23,-,-,-,-,-,S-23,5000Mohm MIN,	
....3	SG502	AA27-00084A COIL:S-23,-,-,-,-,-,S-23,5000Mohm MIN,	
....3	T0076	AA39-00112A LEAD CONNECTOR-ASSY:UL1007#26,UL/CSA,10	
....3	T0076	AA39-00120F LEAD CONNECTOR-ASSY:SIR-T165,UL1007#26,U	
....3	T0076	AA39-00198A LEAD CONNECTOR-ASSY:3P,900/600MM,YFH800	
....3	T0076	AA39-20010D LEAD CONNECTOR-ASSY:,1P,400,YFH800-01,S,	
....3	T0076	AA39-20010D LEAD CONNECTOR-ASSY:,1P,400,YFH800-01,S,	
....3	T0076	AA39-20010E LEAD CONNECTOR-ASSY:,1P,800,YFH800-01,S,	
....3	T0076	AA39-20010F LEAD CONNECTOR-ASSY:,1P,700,YFH800-01,S,	
....3	T0076	AA39-20027H LEAD CONNECTOR-ASSY:,6P,700MM,67096-006,	
....3	T0076	AA39-20031G LEAD CONNECTOR-ASSY:,9P,800,67096-009,S,	
....3		AA63-10002A BAND-TIE:NYLON66 V2,L100,NTR	S.N.A
....3		AA69-01396A BAG PE:SKD CHASSIS,LDPE,TO.03,240,180,NO	S.N.A
....3	Q371	AA96-00244H ASSY H/S:SCREW,2SC4636(2),CRT,SLICON-OIL	S.N.A
....4		0205-000129 GREASE-SILICON:SC102,JAPAN	S.N.A
....4	T0090	0502-000442 TR-POWER:2SC4636RB,NPN,2W,TO-220,ST,10-	
....4	T0081	6003-000335 SCREW-TAPTITE:RH,+2S,M3,L8,ZPC(YEL),SWR	S.N.A
....4		AA62-00046A HEAT SINK-PS:-,T1.0,-,D1(DREAM) 60X25X	S.N.A
....3	IC501	AA96-50311L ASSY H/S:-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....3	IC531	AA96-50311L ASSY H/S:-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....3	IC561	AA96-50311L ASSY H/S:-,AMP,AA62-30175D ,TDA6111Q,HE	S.N.A
....4	T0074	1201-001131 IC-VIDEO AMP:6111,SIP,9P,-,SINGLE,-,PLAS	

Loc. No.	Code No.	Description ; Specification	Remark
....4	T0081	6003-000334 SCREW-TAPTITE:RH,+2S,M3,L6,ZPC(YEL),SWR	
....4		AA62-30175D HEAT SINK-PS:-,SECC,T1.0,-,33X15X30 FT-2	S.N.A
....3		AA97-07608A ASSY AUTO-CRT:HCM4215W	S.N.A
....4	D372	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D504	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D509	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D361	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D362	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D371	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	D510	0401-000005 DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
....4	T0083	0402-000493 DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
....4	T0083	0402-000493 DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
....4	T0083	0402-000493 DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
....4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
....4	T0083	0402-000546 DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
....4	DZ016	0403-000508 DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508 DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000508 DIODE-ZENER:MTZJ5.6B,5.6V,5.45-5.73V,500	
....4	DZ016	0403-000708 DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
....4	DZ016	0403-000708 DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
....4	DZ016	0403-000708 DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
....4	DZ016	0403-000708 DIODE-ZENER:MTZJ13B,13V,12.55-13.21V,500	
....4	Q563	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
....4	Q534	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
....4	Q533	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
....4	Q504	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
....4	Q361	0501-000283 TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
....4	Q362	0501-000366 TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L,	
....4	Q502	0501-000389 TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
....4	T0090	0502-000006 TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-	
....4	T0090	0502-000006 TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-	
....4	T0090	0502-000006 TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-	
....4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000009 R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R584	2001-000028 R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R554	2001-000028 R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R524	2001-000028 R-CARBON(S):100OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R580	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R550	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R520	2001-000066 R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R577	2001-000085 R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R547	2001-000085 R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R517	2001-000085 R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R366	2001-000109 R-CARBON(S):470OHM,5%,1/2W,AA,TP,2.4X6.4	
....4	R125	2001-000290 R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000539 R-CARBON:24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000577 R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000613 R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000613 R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000660 R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000723 R-CARBON:4.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000734 R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000938 R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000995 R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-000995 R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R125	2001-001015 R-CARBON:9.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	R581	2001-001052 R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R551	2001-001052 R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R521	2001-001052 R-CARBON(S):1.5MOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R371	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R370	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R369A	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R367	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.	
....4	R368	2001-001065 R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.	

Electrical Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark	
....4	R369	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.44	SG501	4715-001036	SURGE ABSORBER:500V,20%,--,TP	
....4	R567	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M4	SG503	4715-001036	SURGE ABSORBER:500V,20%,--,TP	
....4	R537	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M4	SG531	4715-001036	SURGE ABSORBER:500V,20%,--,TP	
....4	R507	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M4	EL06	6042-000002	EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	R381	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M4	EL03	6042-000002	EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
....4	R361	2001-001097	R-CARBON(S):2.4KOHM,5%,1/2W,AA,TP,2.4X6.44	EL563	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R374	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.44	EL537	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R373	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.44	EL536	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R372	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.44	EL535	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R377	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.44	EL564	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R375	2001-001113	R-CARBON(S):270KOHM,5%,1/2W,AA,TP,2.4X6.44	EL565	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R365	2001-001120	R-CARBON(S):3.30HM,5%,1/2W,AA,TP,2.4X6.44	EL566	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R574	2001-001122	R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.44	EL567	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R544	2001-001122	R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.44	EL534	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R514	2001-001122	R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.44	EL01	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R583	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.74	EL02	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R582	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.74	EL04	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R553	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.74	EL05	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R552	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.74	EL533	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R523	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.74	EL505	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R522	2002-001006	R-COMPOSITION:4.7KOHM,15%,1/2W,AA,TP,3.74	EL504	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R589	2002-001015	R-COMPOSITION:47Kohm,5%,1/2W,AA,TP,3.7x94	EL503	6042-000001	EYELET:ID2.2,OD2.7,L3.1,NI+SN,BSP3-1/2H	S.N.A
....4	R559	2002-001015	R-COMPOSITION:47Kohm,5%,1/2W,AA,TP,3.7x94	GT537	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R529	2002-001015	R-COMPOSITION:47Kohm,5%,1/2W,AA,TP,3.7x94	GT561	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R575	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x94	GT536	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R545	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x94	GT535	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R515	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x94	GT534	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R579	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X4	GT562	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R578	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X4	GT568	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R549	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X4	GT567	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R518	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X4	GT564	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R519	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X4	GT563	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R548	2002-001021	R-COMPOSITION:560KOHM,5%,1/2W,AA,TP,3.7X4	GT503	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R588	2003-000738	R-METAL OXIDE(S):56Kohm,5%,2W,AA,TP,4x124	GT501	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R538	2003-000738	R-METAL OXIDE(S):56Kohm,5%,2W,AA,TP,4x124	GT373	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R508	2003-000738	R-METAL OXIDE(S):56Kohm,5%,2W,AA,TP,4x124	GT372	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.54	GT371	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.54	GT371	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R024	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.54	GT504	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R573	2008-001129	R-FUSIBLE(S):1.5ohm,5%,1/2W,AF,TP,2.5x6.54	GT533	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R543	2008-001129	R-FUSIBLE(S):1.5ohm,5%,1/2W,AF,TP,2.5x6.54	GT532	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	R513	2008-001129	R-FUSIBLE(S):1.5ohm,5%,1/2W,AF,TP,2.5x6.54	GT531	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP4	GT506	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP4	GT374	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000119	C-CERAMIC,DISC:100NF,+80-20%,50V,Y5V,TP4	GT375	AA60-40014A	PIN-GT,ASSY:AUTO	S.N.A
....4	C598	2201-000556	C-CERAMIC,DISC:0.47NF,10%,500V,Y5P,TP,54	R125	2001-000362	R-CARBON:1500HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C598	2201-000723	C-CERAMIC,DISC:4.7NF,20%,3KV,Y5U,TP,16X54	R125	2001-000362	R-CARBON:1500HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C598	2201-000723	C-CERAMIC,DISC:4.7NF,20%,3KV,Y5U,TP,16X54	R125	2001-000362	R-CARBON:1500HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C598	2201-000723	C-CERAMIC,DISC:4.7NF,20%,3KV,Y5U,TP,16X54	DZ016	0403-000334	DIODE-ZENER:UZ2.7BSA,2.7V,2.54-2.75V,500	
....4	C598	2201-000983	C-CERAMIC,DISC:1NF,10%,2KV,Y5P,TP,9X5MM4	DZ016	0403-000334	DIODE-ZENER:UZ2.7BSA,2.7V,2.54-2.75V,500	
....4	C598	2201-000983	C-CERAMIC,DISC:1NF,10%,2KV,Y5P,TP,9X5MM4	R566	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	C565	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.54	R536	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	C535	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.54	R506	2001-001049	R-CARBON(S):1.3KOHM,5%,1/2W,AA,TP,2.4X6.4	
....4	C505	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.54	R125	2001-000007	R-CARBON:3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C507	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x114	R125	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C537	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x114	C598	2201-000599	C-CERAMIC,DISC:0.56NF,10%,500V,Y5P,TP,5	
....4	C567	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x114	C598	2201-000599	C-CERAMIC,DISC:0.56NF,10%,500V,Y5P,TP,5	
....4	C361	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m4	C598	2201-000599	C-CERAMIC,DISC:0.56NF,10%,500V,Y5P,TP,5	
....4	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,54	C701	2401-001571	C-AL:47uF,+20%-0%,50V,GP,TP,8x11.5	
....4	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,54	C701	2401-001571	C-AL:47uF,+20%-0%,50V,GP,TP,8x11.5	
....4	C701	2401-002075	C-AL:4.7uF,20%,50V,GP,TP,5x11,54	C701	2401-001571	C-AL:47uF,+20%-0%,50V,GP,TP,8x11.5	
....4	C701	2401-000133	C-AL:1000uF,20%,16V,GP,TP,10x20,54	R125	2001-000319	R-CARBON:120KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,54	R125	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,54	R125	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000232	R-CARBON:1.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000908	R-CARBON:62KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m4	R125	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
....4	C701	2401-001621	C-AL:6.8uF,20%,450V,GP,TP,13x20,54	L561	2701-000168	INDUCTOR-AXIAL:3.3uH,5%,2.5x3.4mm	
....4	L531	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm4	R382	2002-001014	R-COMPOSITION:6.8Kohm,10%,1/2W,AA,TP,3.7	
....4	L501	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm4	PCB	AA41-00060E	PCB-CRT:HCM4215W,FR-1,1L,E,1.6T,245X197	S.N.A
....4	SG561	4715-001036	SURGE ABSORBER:500V,20%,--,TP4	T0083	0402-000243	DIODE-RECTIFIER:RC2-V1,2000V,0.2A,DO-201	
....4	SG563	4715-001036	SURGE ABSORBER:500V,20%,--,TP3	T0076	BP39-00004B	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239	
....4	SG533	4715-001036	SURGE ABSORBER:500V,20%,--,TP3	T0076	BP39-00004C	LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
...3	T0076	BP39-00004C LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL3239		...4	RZ128	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M	
...3	T0103	BP59-00005A MODULE-FOCUS PACK ASSY:PJT TV,F301-P03A		...4	RZ127	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M	
...2	T0098	BP94-00517C ASSY PCB MISC-CONTROL:DP,HCN4727WSC/XAA,		...4	RZ126	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M	
...3		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A	...4	RZ132	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	LEDY01	0601-001381 LED:ROUND,RED/GRN,5.0MM,650/563NM		...4	RZ132A	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	T0121	3301-001201 CORE-FERRITE:AE,21x11x32mm,1500,280G		...4	RZ148	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	SWY08	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST		...4	RZ148A	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	SWY07	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST		...4	RZ149	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	SWY06	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST		...4	RZ149A	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	SWY05	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST		...4	RZ129	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	SWY04	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST		...4	RZ129A	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	SWY03	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST		...4	RZ130	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	SWY02	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST		...4	RZ131A	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	SWY01	3404-001006 SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST		...4	RZ131	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	CN906	3711-000447 CONNECTOR-HEADER-BOX,3P,1R,2.5MM,ANGLE,-		...4	RZ130A	2003-002171 R-METAL OXIDE(S):150ohm,5%,2W,AG,TP,3.9x	
...3	CN906	3711-003353 CONNECTOR-HEADER-BOX,11P,1R,2.5mm,ANGLE,		...4	RFZ50	2008-000261 R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
...3	RMY01	AA32-00012A MODULE REMOCON:ORC-50HF2,38KHZ,940NM,MES		...4	RFZ51	2008-000261 R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
...3	T0076	AA39-00223C LEAD CONNECTOR-ASSY:P54A/SVP-42W5HD,UL10		...4	RFZ52	2008-000261 R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
...3	T0076	AA39-00259A LEAD CONNECTOR-ASSY:UL1007#26,UL/CSA,3P		...4	RFZ53	2008-000261 R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
...3		BP97-00503K ASSY AUTO:HCM4727WX,P55A	S.N.A	...4	RFZ19	2008-000261 R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
...4	DZ016	0403-000510 DIODE-ZENER:MTZJ6.2B,6.2V,5.96-6.27V,500		...4	RFZ20	2008-000261 R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
...4	DZ016	0403-000510 DIODE-ZENER:MTZJ6.2B,6.2V,5.96-6.27V,500		...4	RFZ21	2008-000261 R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
...4	QY01	0504-000123 TR-DIGITAL:KSR1010,NPN,300mW,10K,TO-92,T		...4	RFZ22	2008-000261 R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
...4	RY07	2001-000020 R-CARBON(S):220HM,5%,1/2W,AA,TP,2.4X6.4M		...4	C598	2201-000327 C-CERAMIC,DISC:2.2NF,10%,50V,Y5V,TP,6.5X	
...4	RY09	2001-000109 R-CARBON(S):4700HM,5%,1/2W,AA,TP,2.4X6.4		...4	C598	2201-000327 C-CERAMIC,DISC:2.2NF,10%,50V,Y5V,TP,6.5X	
...4	R125	2001-000429 R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C598	2201-000327 C-CERAMIC,DISC:2.2NF,10%,50V,Y5V,TP,6.5X	
...4	R125	2001-000832 R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C598	2201-000327 C-CERAMIC,DISC:2.2NF,10%,50V,Y5V,TP,6.5X	
...4	R125	2001-000832 R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C689	2202-000121 C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
...4	R125	2001-000832 R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C689	2202-000121 C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
...4	R125	2001-000924 R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C689	2202-000121 C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
...4	RY08	2001-001108 R-CARBON(S):22KOHM,5%,1/2W,AA,TP,2.4X6.4		...4	C689	2202-000121 C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
...4	C701	2401-002009 C-AL:100uF,20%,16V,GP,TP,6.3x7.5		...4	C689	2202-000121 C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
...4	0	BP41-00025B PCB CONTROL:HCM4727W,CONTROL,1L,1.6T,245	S.N.A	...4	C689	2202-000121 C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
...3		AA69-01396A BAG PE,SKD CHASSIS,LDPE,TO.03,240,180,NO	S.N.A	...4	C689	2202-000205 C-CERAMIC,MLC-AXIAL:22pF,5%,50V,SL,TP,1.	
...2	T0094	BP94-00517D ASSY PCB MISC-CG AMP:DP,HCM4727WSC/XAA,P		...4	C689	2202-000205 C-CERAMIC,MLC-AXIAL:22pF,5%,50V,SL,TP,1.	
...3		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb	S.N.A	...4	C689	2202-000205 C-CERAMIC,MLC-AXIAL:22pF,5%,50V,SL,TP,1.	
...3	CN906	3711-003043 CONNECTOR-HEADER-BOX,4P,1R,2.5MM,STRAIGH		...4	C689	2202-000205 C-CERAMIC,MLC-AXIAL:22pF,5%,50V,SL,TP,1.	
...3	CN906	3711-003043 CONNECTOR-HEADER-BOX,4P,1R,2.5MM,STRAIGH		...4	C689	2202-000205 C-CERAMIC,MLC-AXIAL:22pF,5%,50V,SL,TP,1.	
...3	CN906	3711-003043 CONNECTOR-HEADER-BOX,4P,1R,2.5MM,STRAIGH		...4	CZ113	2202-000561 C-CERAMIC,MLC-RADIAL:0.68NF,5%,50V,COG,T	
...3	CN906	3711-003043 CONNECTOR-HEADER-BOX,4P,1R,2.5MM,STRAIGH		...4	CZ114	2202-000561 C-CERAMIC,MLC-RADIAL:0.68NF,5%,50V,COG,T	
...3	CN906	3711-003046 CONNECTOR-HEADER-BOX,9P,1R,2.5MM,STRAIGH		...4	C701	2401-000183 C-AL:1000uF,20%,35V,WT,TP,12.5x25.5	
...3		AA65-30110A CLAMPER CORE-WIRE:ALL MODEL,NYLON 66,V2,	S.N.A	...4	C701	2401-000183 C-AL:1000uF,20%,35V,WT,TP,12.5x25.5	
...3		AA97-07418A ASSY AUTO:HCM4215WX/XAA,P55A	S.N.A	...4	C701	2401-000962 C-AL:22uF,20%,50V,GP,TP,5x11,5	
...4	R125	2001-000563 R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C701	2401-000962 C-AL:22uF,20%,50V,GP,TP,5x11,5	
...4	R125	2001-000563 R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	LZ112	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
...4	R125	2001-000563 R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	LZ111	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
...4	R125	2001-000563 R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	LZ110	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
...4	R125	2001-000563 R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	LZ109	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	LZ108	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	LZ107	2701-000142 INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	FD102S	3601-001065 FUSE-AXIAL LEAD:125V,3.5A,FAST-ACTING,CE	
...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	FD101S	3601-001065 FUSE-AXIAL LEAD:125V,3.5A,FAST-ACTING,CE	
...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	ELZ01	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	ELZ02	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...4	R125	2001-000591 R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	ELZ03	6042-000002 EYELET:ID1.5,OD2,L2.8,NI+SN,BSP3-1/2H	S.N.A
...4	R125	2001-000857 R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
...4	R125	2001-000857 R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
...4	R125	2001-000857 R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
...4	R125	2001-000857 R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
...4	R125	2001-000857 R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
...4	R125	2001-000857 R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		...4	C689	2202-000825 C-CERAMIC,MLC-AXIAL:680pF,10%,50V,Y5P,TP	
...4	RZ109	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4		...4	C689	2202-000863 C-CERAMIC,MLC-AXIAL:560pF,10%,50V,Y5P,TP	
...4	RZ108	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4		...4	C689	2202-000863 C-CERAMIC,MLC-AXIAL:560pF,10%,50V,Y5P,TP	
...4	RZ107	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4		...4	C689	2202-000863 C-CERAMIC,MLC-AXIAL:560pF,10%,50V,Y5P,TP	
...4	RZ106	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4		...4	C689	2202-000863 C-CERAMIC,MLC-AXIAL:560pF,10%,50V,Y5P,TP	
...4	RZ105	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4		...4	C689	2202-000863 C-CERAMIC,MLC-AXIAL:560pF,10%,50V,Y5P,TP	
...4	RZ104	2001-001114 R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4		...4	C689	2202-000863 C-CERAMIC,MLC-AXIAL:560pF,10%,50V,Y5P,TP	
...4	R857	2001-001155 R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.4		...4	C689	2202-000863 C-CERAMIC,MLC-AXIAL:560pF,10%,50V,Y5P,TP	
...4	R856	2001-001155 R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.4		...4	R125	2001-000800 R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	RZ142	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		...4	R125	2001-000800 R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
...4	RZ143	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		...4	0	AA41-00601C PCB:HCM4215W,PCB,CEM-1,1L,C.1.6,245X245,	S.N.A
...4	RZ144	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		...3	SGZ101	4715-000106 SURGE ABSORBER:300V,210-390V,-,AXIAL	S.N.A
...4	RZ145	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		...3	T0076	BP39-00015A LEAD CONNECTOR-ASSY:P55A/HCM4215W,UL1185	
...4	RZ146	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		...3		BP61-00076A HOLDER-PUSH,A:42W5,NYLON6.6,NATURAL	S.N.A
...4	RZ147	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		...3		BP61-00077A HOLDER-PUSH,B:42W5,NYLON6.6,NATURAL	S.N.A
...4	RZ148	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		...3	CZ101	BP96-00005A ASSY HEAT SINK P:BP62-00002A,SCREW,STK39	S.N.A
...4	RZ149	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		...4	T0081	6003-001021 SCREW-TAPTITE:RH,+B,M3,L15,ZPC(YEL),SWR	S.N.A
...4	RZ123	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		...4	CIS	BP62-00002A HEAT SINK:COMMANDO,A1050P,T2.0,W62.0,H14	S.N.A
...4	RZ124	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		...4	CIS	BP62-00008A HEAT SINK:COMMANDO CG AMP,AL6063,T2.0,W1	S.N.A
...4	RZ125	2003-002148 R-METAL OXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		...4	CIS	BP73-00002A SILICON/RUBBER:COMMANDO CG AMP,SILICON ,	S.N.A

Loc. No.	Code No.	Description ; Specification	Remark
...4	DR708	2007-000070 R-CHIP;0ohm,5%,1/10W,TP,1608	
...4	DR503	2007-001167 R-CHIP;75ohm,5%,1/10W,TP,1608	
...4	DR505	2007-001167 R-CHIP;75ohm,5%,1/10W,TP,1608	
...4	DR507	2007-001167 R-CHIP;75ohm,5%,1/10W,TP,1608	
...4	DR521	2007-001167 R-CHIP;75ohm,5%,1/10W,TP,1608	
...4	DR522	2007-001167 R-CHIP;75ohm,5%,1/10W,TP,1608	
...4	0	AA41-00793B PCB:HCN473,PCB-DVI,2L,1.6T,245*180,P55A, S.N.A	
...4		0202-001167 SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SN S.N.A	
...3	CN906	3711-003641 CONNECTOR-HEADER:BOX,12P1R,2.5mm,STRAIG	
...3	T0121	3301-001201 CORE-FERRITE:AE,21x11x32mm,1500,280G	
...3		AA63-10002A BAND-TIE:NYLON66 V2,L100,NTR S.N.A	
...3	IC112	1103-001211 IC-EEPROM:24C16-PC27 C,2048x8Bit,DIP8P,	
...3	T0076	AA39-20032B LEAD CONNECTOR-ASSY;,12P,300,67096-012,S	
...3	PL1	3701-001173 CONNECTOR-DSUB;24P,3R,FEMALE,ANGLE,AUF	
...2		BP95-00147D ASSY SUB PCB-SENSOR:DP954A,SENSOR	
...3		0202-000187 SOLDER-WIRE FLUX:-,RS60S,D1.2,63Sn/37Pb S.N.A	
...3		AA69-01808B BAG-SHEET;LDPE(ANTISTATIC),TO.05,800,50 S.N.A	
...3		BP97-00208A ASSY SMD:0 S.N.A	
...4	Q01	0501-000342 TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
...4	PCB	AA41-00853A PCB-SERSON:VSP-42W5HRC,FR,4,2L,A,1.6T,24 S.N.A	
...4	D01	BP32-00001A SENSOR PHOTO:BCC5030G1,-40 TO +85,0.42 U	
...4	R01	2007-000305 R-CHIP;10Mohm,5%,1/10W,TP,1608	
...4	R02	2007-000109 R-CHIP;1Mohm,5%,1/10W,TP,1608	
...4	R03	2007-000109 R-CHIP;1Mohm,5%,1/10W,TP,1608	
...4		0202-001167 SOLDER-CREAM:RX3603-2330HO,S45A,PASTE,SN S.N.A	
...3	CN906	3711-000447 CONNECTOR-HEADER:BOX,3P,1R,2.5MM,ANGLE,-	

ASSY ACCESSORY

1	M0016	BP92-00577B ASSY ACCESSORY:HCN4727WSC/XAA,P55A	S.N.A
..2		6902-000018 BAG PE-LDPE,TO.1,W280,L400,GRY,8,2-	S.N.A
..2	T0116	AA39-00006A CABLE RCA;,3000MM	
..2	T0074	AA59-00262A REMOCON;TM63,COMMONDO,48,G6671B,EX,S/S	
...3	T0122	2802-000194 RESONATOR-CERAMIC:8MHz,1.0%,TP,8.5x4.5x5	
...3	T0119	AA09-00275A IC MICOM:Z86L8808SSC-R51PX,SOP,ST,SZTM-8	
..2	T0113	AA61-20126A HOLDER-LEG;-ABS,-,-,-,BLK,HB	
..2		AA68-00371C CARD WARRANTY-01;,SEA,W/P100(G),1 YEAR S.N.A	
..2		AA68-40065B CARD-REGISTRATION;,SEA,A5,ENG,A/P220,2P(S.N.A	
..2		AA69-30009C BAG-SHEET;LDPE,TO.08,W150,L120,-,-,- S.N.A	
..2	CIS	BP68-00054A MANUAL USERS:HCM473WJX,ENG,W/P100G,P55A,	

ASSY K/D-CRT

1		BP98-00173A ASSY K/D-CRT ASSY:HCN4727WSC/XAA,P55A	S.N.A
..2	T0026	BP98-00174A ASSY K/D-CRT R:HCN4727WSC/XAA,P55A	
...3		AA03-00200A CRT MONO:P16LSG03RJA,FREE,3.30mH,2.20mH, S.N.A	
...3	T0117	AA26-30006F TRANS FBT-ANODE CAP ASS'Y;-FWZ-50A001C,	
...3	T0078	AA27-00249A DEFLECTION YOKE;-DPD-5292AA,S/S,7,29.1	
...3	T0079	AA33-00016A MAGNET CONVERGENCE:JH 92LT - 29F,-,29.1M	
...3	T0076	AA39-00018A LEAD CONNECTOR-ASSY;,UL1015#22,UL/CSA,1P	
...3		AA60-00125B SPACER-CRT:PROJ,SILICONE,D/GRAY S.N.A	
...3		AA60-00126B SPACER-CAP:PROJ,EPDM,BLK S.N.A	
...3		AA60-00127B SPACER-LENS:PROJ,SILICONE,D/GRAY S.N.A	
...3	T0081	AA60-10011A SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+,PC, S.N.A	
...3		AA61-00056B BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-, S.N.A	
...3		AA61-00809B HOLDER-CRT:PROJ,PC/ABS GF 20%,BLK S.N.A	
...3	T0114	AA61-00810B HOLDER-CAP:PROJ,PC,CLR	
...3		AA63-00076A SPACER-LENS:PROJECTION,FELT,-,-,-,BROWN S.N.A	
...3	T0109	AA67-00147A LENS-ASSY;,DELTA 78,CLEAR A/B	
...3	T0051	AA67-10008A LENS;-DELTA,RED,PJT,-,77,79,- S.N.A	
...3		BP61-00079A HOLDER-DY;,PJT,TO.5,NYLON66 V2 S.N.A	
...3		AA61-00845A CASE-COUPLER,R:DP,PROJ,AA61-00806B S.N.A	
...4		AA61-00806B CASE-COUPLER,R:PROJ,ALDC,T8,BLK S.N.A	
...4		AA63-10007C BAND-PP;W18,CLEA,1G S.N.A	
...3	T0107	AA91-00735A ASSY-BRKT,CRT;DP,AA91-00722A,PROJ	
...4	T0107	AA91-00722A ASSY-BRKT,CRT;,SECC T1.6,PROJ	
...5	T0072	AA61-00473B BRACKET-CRT:53,SECC,T1.6,-,-,-, S.N.A	
...5		AA61-00615B BRACKET-EARTH:54J8,PBS,TO.5,-,-,-, S.N.A	
...5		AA61-00812A SPRING ETC-WIRE:PROJ,STS,3.6 S.N.A	
..2	T0027	BP98-00175A ASSY K/D-CRT G:HCN4727WSC/XAA,P55A	
...3		AA03-00201A CRT MONO:P16LSG03HKA,FREE,3.30mH,2.20mH, S.N.A	

Loc. No.	Code No.	Description ; Specification	Remark
...3	T0117	AA26-30006F TRANS FBT-ANODE CAP ASS'Y;-FWZ-50A001C,	
...3	T0078	AA27-00249A DEFLECTION YOKE;-DPD-5292AA,S/S,7,29.1	
...3	T0076	AA39-00018A LEAD CONNECTOR-ASSY;,UL1015#22,UL/CSA,1P	
...3		AA60-00125B SPACER-CRT:PROJ,SILICONE,D/GRAY S.N.A	
...3		AA60-00126B SPACER-CAP:PROJ,EPDM,BLK S.N.A	
...3		AA60-00127B SPACER-LENS:PROJ,SILICONE,D/GRAY S.N.A	
...3	T0081	AA60-10011A SCREW-TAPTITE;-SWRCH18A,M4,L12,HH,+,PC, S.N.A	
...3		AA61-00056B BRACKET-LENS:PROJECTION,SECC,T1.6,-,-,-, S.N.A	
...3		AA61-00809B HOLDER-CRT:PROJ,PC/ABS GF 20%,BLK S.N.A	
...3	T0114	AA61-00810B HOLDER-CAP:PROJ,PC,CLR	
...3		AA63-00076A SPACER-LENS:PROJECTION,FELT,-,-,-,BROWN S.N.A	
...3	T0109	AA67-00147A LENS-ASSY;,DELTA 78,CLEAR A/B	
...3	T0051	AA67-10007A LENS;-DELTA,CLEAR,PJT,-,77,79,- S.N.A	
...3		BP61-00079A HOLDER-DY;,PJT,TO.5,NYLON66 V2 S.N.A	
...3	T0107	AA91-00735A ASSY-BRKT,CRT;DP,AA91-00722A,PROJ	
...4	T0107	AA91-00722A ASSY-BRKT,CRT;,SECC T1.6,PROJ	
...5	T0072	AA61-00473B BRACKET-CRT:53,SECC,T1.6,-,-,-, S.N.A	
...5		AA61-00615B BRACKET-EARTH:54J8,PBS,TO.5,-,-,-, S.N.A	
...5		AA61-00812A SPRING ETC-WIRE:PROJ,STS,3.6 S.N.A	
...3		AA61-00847A CASE-COUPLER,B:DP,PROJ,AA61-00808B S.N.A	
...4		AA61-00808B CASE-COUPLER,B:PROJ,ALDC,T8,BLK S.N.A	
...4		AA63-10007C BAND-PP;W18,CLEA,1G S.N.A	

ASSY K/D-SKD P/MATERIAL

1		AA98-01629A ASSY K/D-SKD P/MATERIAL:SKD FORMAT-3	S.N.A
..2		AA69-00305A BAG AIR:ALL,LDPE,1000,500,CLR,	S.N.A
..2		AA69-00306A BAG AIR:LDPE,-,1800,1000,CLR,ASSY,ALL,-	S.N.A
..2		AA69-90001A CHEMICALS-SILICAGEL;-,-,-,-,M2,5GR,-,-	S.N.A
..2		AA60-40006A PIN-STAPLE:AUTO,33X17.8X2.4,H18,33X17.8X	S.N.A
..2	WOODEN	AA63-10007C BAND-PP;W18,CLEA,1G	S.N.A

MEMO