

7. Electrical Parts List

7-1 PCJ612RX/XAA (PCJ522RX/XAA and PCJ612RX/XAA Dissimilar Parts)

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ASSY-CABINET				ASSY-CABINET,MIDDLE			
		*AA90-00186ASSY-CABINET:612R,PCJ612RX/XAA				* AA91-00207AASSY-CABINET,MIDDLE:-,WOOD,-,PCJ612R	
SPC	AA60-00027	BSPACER-COVER,DUST:SPONGE,T2.0,-,612R,-		AL	2401-003493	C-AL:1.75uF,10%,100V,BP,BK,10x13mm,5	
HDR	AA61-00079	BHOLDER-SCREEN:-,PCJ613R,ABS,HB,BLK,L1255		BCKT	AA61-10247	ABRACKET-FOCUS:-,S46DS,SECC,T1.0,-,-	
HDR	AA61-00079	BHOLDER-SCREEN:-,PCJ613R,ABS,HB,BLK,L945		BF+CM	AA60-10051	ASCREW-WOOD:PH,+M4,L16,ZPC(BLK),SWRCH18A,	
COVM	AA63-00082	ACOVER-MIRROR,WOOD:-,PCJ613R,-,WOOD,-,-,-,-		CABMID	AA64-00514	ACABINET-MIDDLE:-,PCJ612R,-,WOOD,-,BLK,-,-	
COVF	AA63-00183	ACOVER-FRONT,WOOD:-,PCJ612R,JERSEY,WOOD,-,-,-,-		CABMID	3001-000153	SPEAKER:20W,8ohm,93dB,1.3KHz	
SPA	AA63-60131	ESPACER-FELT:FELT,T0.5,BLK,520X200,PCJ612R,-		CABMID	3001-000176	SPEAKER:30W,80HM,93DB+-2DB,65HZ	
BACK	AA64-00625	ACABINET-BACK,BOARD:-,613R,-,HIPS,VO,BLK,T3.0,-		CABMID	AA61-00030	ACASTER:SVP-614JM,POLYURETHANE,-,50,23,-,H63,-	
BACK	AA64-31213	BCABINET-BACK,TOP:-,555J,-,HIPS,HB,BLK,-,-		CABMID	AA61-00080	BHOLDER-MASK:-,PCJ613R,ABS,HB,NTR,L80	
MIRB	AA67-00020	AMIRROR-BACK:613,GLASS,T3.0,-,-,1160*754*806,BSM,-		CABMID	AA63-00105	ASPACER-FELT:FELT,T2.0,BLK,32X878,PCJ613R,-	
SUN	AA67-00022	ASUN-SCREEN:-,61,H/C,A/S,PMMA,T=82%,T2.0,1283*973,-		CABMID	AA63-00105	BSPACER-FELT:FELT,T2.0,BLK,32X1211,PCJ613R,-	
SCRN	AA67-70056	ASCREEN-TINT:0.515,61',DNP,896-985,TINT10%,2.7,1283*973,		HDRP	AA61-00146	AHOLDER-PIN,LOCKER:-,PRJT,ABS,HB,BLK,WOOD	
AC+BCM	AA60-10011	ASCREW-TAPTITE:HH,+PC,M4,L12,ZPC(BLK),SWRCH1		LEAD	AA39-20609	ALEAD CONNECTOR-ASSY:-,SMH250-02,REC,2P,400mm,1007#	
ACB+CM	AA60-10050	SCREW-WOOD:W/H,+M4,20,ZPC(BLK),SWRCH18A,		SPA	AA63-00066	BSPACER-DUAL,LOCK:#250,-,-,11X25,PROJECTION,-	
AV+CFB	AA60-10002	ASCREW-TAPPING:RH,+M4,L12,ZPC(YEL)-,OD14		SPAF	AA63-60126	ASPACER-FELT:FELT,T2,BLK,1160X15,PRJT43,52,	
BCM	AA63-60040	BSPACER-DIECAST:PU,-,-,225X23,S4388,-		SPAF	AA63-60126	DSPACER-FELT:FELT,T2,-,400X15,PRJ61,-	
BCM+CM	AA60-00015	ASCREW-ASSY:-,WP,-,M8,L25,SCM30C,-,-		SPK	AA39-20505	RLEAD CONNECTOR-ASSY:-,YSH250-04,REC,4P,1400,900,1007#22	
CMW	AA60-10050	SCREW-WOOD:W/H,+M4,20,ZPC(BLK),SWRCH18A,		ASSY-CRT-(R)			
CMW+CM	6005-001001	SCREW-WOOD:TH,+M4,L28,BLK,SWRCH18A				* AA94-01676AASSY-CRT-(R):P16LNM07RJA,+380MG,7,BARE,PCJ612R,-	
CP+CFB	AA60-10002	ASCREW-TAPPING:RH,+M4,L12,ZPC(YEL)-,OD14		LENS	AA67-10066	ALENS-ASSY:DELTA 37,-,-,CLEAR A/B,-,-,-	
FP+BF	6003-001023	SCREW-TAPTITE:RWH,+B,M3,L10,ZPC(YEL),SWRCH1		ASSY-CRT-(G)			
HC+CM	AA60-10050	SCREW-WOOD:W/H,+M4,20,ZPC(BLK),SWRCH18A,				* AA94-01677AASSY-CRT-(G):P16LNM07HKA,+380MG,7,BARE,PCJ612R,-	
HS+CM	AA60-00021	ASCREW-WOOD:RH,+M3.5,L22,ZPC(BLK),SWRCH18,-		LENS	AA67-10066	ALENS-ASSY:DELTA 37,-,-,CLEAR A/B,-,-,-	
HSS+CM	AA60-00021	ASCREW-WOOD:RH,+M3.5,L22,ZPC(BLK),SWRCH18,-		ASSY-CRT-(B)			
HV+BCM	6003-001024	SCREW-TAPTITE:RWH,+B,M4,L12,ZPC(YEL),SWRCH1				* AA94-01678AASSY-CRT-(B):P16LNM07BMB,+380MG,7,BARE,PCJ612R,-	
RNGBCM	6003-001024	SCREW-TAPTITE:RWH,+B,M4,L12,ZPC(YEL),SWRCH1		LENS	AA67-10066	ALENS-ASSY:DELTA 37,-,-,CLEAR A/B,-,-,-	
TBACBW	6003-001024	SCREW-TAPTITE:RWH,+B,M4,L12,ZPC(YEL),SWRCH1		ASSY-PCB,CRT			
VBW+CM	AA60-10050	SCREW-WOOD:W/H,+M4,20,ZPC(BLK),SWRCH18A,				* AA95-00344DASSY-PCB,CRT:-,P51A,-,USA,PCJ612R	
ASSY-CABINET,BOT							
		* AA91-00014GASSY-CABINET,BOT:-,VO,DG707M ALL,PCJ612R		BDW-GND	AA39-20009	KLEAD CONNECTOR-ASSY:-,YFH800-01,-,1P,1617#22,1000MM	
BADGE	AA64-00406	EBADGE-BRAND:AL,DG-707M SAMSUNG,SILVER,72,FORG		CNW401	AA39-20027	DLEAD-CONNECTOR,ASSY:-,67096-006,S,6P,600,1007#26	
CAFRBOT	AA61-30001	ALATCH-DOOR:-,-,KIFUCO LA701,-		CNW501	AA39-20030	DLEAD-CONNECTOR,ASSY:-,67096-008,S,8P,600,1007#26	
CAFRBOT	AA61-60005	ASPRING-CS:-,SUS304,0.6,OD10.7,H10,N4,-,-		GDW-GND	AA39-20009	GLEAD-CONNECTOR,ASSY:-,YFH800-01,-,1P,700,1617#22	
CAFRBOT	AA64-10764	BKNOB-CONTROL:-,-,CHAMPAINE GOLD+UV,ABS,HB,NTR		RDW-GND	AA39-20009	CLEAD CONNECTOR-ASSY:-,YFH800-01,-,1P,400,1617#22	
CAFRBOT	AA64-40494	AWINDOW-REMOCON:-,SVP-434J,-,PC,-,VIOLET,-		ASSY-CABINET,MASK			
DOOR	AA64-00090	DDOOR-A/V:-,PCJ612R,DG707M ALL,ABS,HB,BLK,-,-				* AA91-00140EASSY-CABINET,MASK:-,HB,BLK,DG902+BK901	
FRONT	AA64-00088	JCABINET-FRONT,BOT:-,PCJ612R,DG707M				SEA,PCJ612R	
KC+CFB	6003-001022	SCREW-TAPTITE:RH,+B,M3,L12,ZPC(BLK),SWRCH18		FRONT	AA64-00257	BCABINET-FRONT,MASK:-,PCJ613R,L1251,ABS,HB,BLK,-,-	
LAB	AA68-00046	CLABEL-DOOR,A,V:TETRON MAT P,E,PCJ533R,P51A EL,-,-,-		FRONT	AA64-00257	CCABINET-FRONT,SIDE:-,PCJ613R,L941,ABS,HB,BLK,-,-	
WIN	AA64-40493	AINDICATOR-LED:-,SVP-434JA,-,ABS,-,CLR,-		HDC	AA61-00078	BHOLDER-CORNER:-,PCJ613R,ABS,HB,BLK,-	
WR+CFB	6003-001022	SCREW-TAPTITE:RH,+B,M3,L12,ZPC(BLK),SWRCH18		SPA	AA63-00063	ASPACER-DUAL,LOCK:#400,-,-,19X19,SVP-614J,-	

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
ASSY-CRT-(B)				CNW401	AA39-20027DLEAD-CONNECTOR,ASSY;-	.67096-006,S,6P,600,1007#26	
* AA94-01678AASSY-CRT-(B);P16LNM07BMB,+380MG,7,BARE,PCJ612R,-				CNW501	AA39-20030DLEAD-CONNECTOR,ASSY;-	.67096-008,S,8P,600,1007#26	
LENS	AA67-10066ALENS-ASSY:DELTA 37,-,-,CLEAR A/B,-,-,-			GDW-GND	AA39-20009GLEAD-CONNECTOR,ASSY;-	YFH800-01,-,1P,700,1617#22	
ASSY-PCB,CRT				RDW-GND	AA39-20009CLEAD CONNECTOR,ASSY;-	YFH800-01,-,1P,400,1617#22	
* AA95-00344DASSY-PCB,CRT;-P51A,-,USA,PCJ612R							
BDW-GND	AA39-20009KLEAD CONNECTOR,ASSY;-	YFH800-01,-,1P,1617#22,1000MM					

7-4 PCJ522RX/XAA

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
ASSY-PCB,MAIN(OPT)				C538	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
* AA94-01636AASSY-PCB,MAIN(OPT);PCJ522RX/XAA,P51A,U,S				C539	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
C101	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5		C540	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm	
C102	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5		C543	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5	
C103	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		C544	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
C104	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12.5,5		C545	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0	
C105	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,5		C547	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0	
C106	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5		C549	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11.5,5	
C107	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C550	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
C108	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5		C551	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5	
C109	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		C552	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
C110	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12.5,5		C639	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5	
C112	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5		C640	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
C113	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5		C664	2401-001068	C-AL:3300uF,20%,50V,GP,BK,22x40,10	
C114	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		C665	2401-000737	C-AL:2200uF,20%,50V,GP,TP,18x35.5,7,5	
C116	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C666	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm	
C117	2301-000310	C-FILM,PEF:68nF,5%,50V,TP,8.0x8.5x4.0x5,		C667	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
C118	2201-000180	C-CERAMIC,DISC:10nF,10%,50V,Y5V,TP,6.5*3		C668	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
C119	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C669	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,5	
C121	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C670	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
C125	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C671	2401-001537	C-AL:47uF,20%,25V,GP,TP,6.3x7mm,5mm	
C126	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		C672	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5	
C129	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5		C676	2401-001192	C-AL:33uF,20%,50V,GP,TP,6.3x11,5	
C130	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		C686	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm	
C132	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C687	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm	
C133	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12.5,5		C688	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7,5	
C180	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5		C689	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm	
C185	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12.5,5		C690	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm	
C191	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,5		C691	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7,5	
C193	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		C701	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5	
C195	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,5		C801	2401-002300	C-AL:47uF,20%,50V,GP,TP,6.3x11,5	
C501	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C901	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5	
C502	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5		C904	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V	
C503	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C905	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5	
C504	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11.5,5		C906	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5	
C505	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C907	2301-000111	C-FILM,PEF:1.8nF,5%,50V,TP,6.5x3.0x5.5mm	
C506	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11.5,5		C908	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5	
C507	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C909	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5	
C508	2401-002286	C-AL:470uF,20%,16V,WT,TP,10x12.5,5		C910	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5	
C513	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11.5,5		C911	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
C514	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C912	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
C515	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0		C913	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,	
C516	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0		C914	2201-000573	C-CERAMIC,DISC:47pF,5%,50V,CH,TP,6.5x3.0	
C517	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11.5,5		C915	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
C518	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C916	2401-002042	C-AL:220uF,20%,10V,GP,TP,6.3x11,5	
C519	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C917	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
C520	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11.5,5		C918	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
C521	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C919	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C522	2401-002286	C-AL:470uF,20%,16V,WT,TP,10x12.5,5		C920	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
C537	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C925	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
				C926	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CLAMPF	AA65-30109ACLAMP-FBT-NYLON-66,V2,BLK,-,-,-		
				CLAMPW	AA65-30105BCLAMP-WIRE-NYLON 66,V2,NTR,25MM,ALL MODE		

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
CLAMPW	AA65-30013	ACLAMP-WIRE:NYLON-66,VO,NTR,DAWH-45N,-,-		DZ913	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m	
CLAMPW	AA65-30018	ACLAMP-WIRE:NYLON-66,-,-,DATL-600,DONG-A,		DZ914	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
CN201	3711-002647	CONNECTOR-HEADER:BOX,8P,1R,2.5mm,STRAIGH		DZ915	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
CN202	3711-002641	CONNECTOR-HEADER:BOX,10P,1R,2.54mm,STRAI		DZ916	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
CN501	3711-002647	CONNECTOR-HEADER:BOX,8P,1R,2.5mm,STRAIGH		DZ917	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
CN601	3711-002643	CONNECTOR-HEADER:BOX,4P,1R,2.5MM,STRAIGH		DZ918	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
CN801	3711-003641	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG		F101	2903-000135	FILTER-CERAMIC:BP,4.5MHz,+60KHz,6dB,-,T	
CNT01	3710-001208	CONNECTOR-SOCKET:32P,2R,2.54mm,STRAIGHT,		F102	2903-000129	FILTER-CERAMIC:TR,4.5M/4.72MHz,-,-,TP	
CNT02	3710-001208	CONNECTOR-SOCKET:32P,2R,2.54mm,STRAIGHT,		F901	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
CNY01	3711-000628	CONNECTOR-HEADER:-,11P,1R,2.5mm,STRAIGHT		H001	AA40-10005	RTUNER-F/S,LNA:TECC1070PG30A(S),NTSC/USA,	
CS801	2201-000332	C-CERAMIC,DISC:2.2nF,20%,250VAC,Y5U,TP,1		H002	AA40-10005	UTUNER-F/S:TCNP9082PC27A(S),NTSC/USA,TR,1	
CS802	2201-000332	C-CERAMIC,DISC:2.2nF,20%,250VAC,Y5U,TP,1		H003	AA59-400030	MODULE-MTS:-,MZ-201,ZENITH,US,43X54,-	
CS803	2401-000366	C-AL:10uF,20%,450V,GP,TP,13x20mm,5m		H004	AA59-00028A	MODULE-IF:-,SP-222,NTSC,USA,74X54,-	
CS804	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		△IC101	1204-001435	IC-IFSYSTEM:LA7565B,DIP,24P,300MIL,PLAS	
CS805	2401-001101	C-AL:330uF,20%,16V,GP,TP,10x11.5,5		△IC101	1204-001204	IC-DECODER:TDA9850,DIP,32P,4000MIL,PLAST	
CS807	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		△IC101	1203-000577	IC-VOLTAGE REGULATOR:3090,ZIP,5P,-,PLASTI	H/SINK
CS808	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12.5,5		△IC102	1203-000203	IC-POSITIVE ADJUST REG.:3050,TO-220,5P,-,PLA	H/SINK
CS809	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4		△IC501	1203-000165	IC-POSITIVE ADJUST REG.:78R12,TO-220,3P,-,-	H/SINK
CS810	2201-000446	C-CERAMIC,DISC:3.3nF,20%,400V,Y5U,TP,18x		△IC502	1203-000203	IC-POSITIVE ADJUST REG.:3050,TO-220,5P,-,PLA	H/SINK
CS811	2201-000446	C-CERAMIC,DISC:3.3nF,20%,400V,Y5U,TP,18x		△IC504	1203-000203	IC-POSITIVE ADJUST REG.:3050,TO-220,5P,-,PLA	H/SINK
CS812	2201-002076	C-CERAMIC,DISC:0.068nF,5%,1kV,SL,TP,8x4m		△IC506	1203-000006	IC-POSITIVE FIXED REG.:7808,TO-220,3P,-,PLAS	
D501	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		△IC665	1201-001026	IC-POWER AMP:7265,ZIP,11P,19.6MIL,DUAL,1	H/SINK
D502	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		△IC807	1203-000274	IC-POSITIVE FIXED REG.:7805,TO-220,3P,-,PLAS	H/SINK
D664	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		△IC901	AA13-00054A	IC-MCU:-,Z9035112PSC-OTP,16BIT,SDIP,C	
D665	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		△IC902	1103-001105	IC-EEPROM:24C040,4Kx1BIT,DIP,8P,300MIL,1	
D666	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		△IC903	1203-0001274	IC-VOL. DETECTOR:7545,TO-92,3P,-,PLASTIC	
D667	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		△IC904	1203-000515	IC-VOL. DETECTOR:7042,TO-92,3P,177MIL,PL	
D668	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		△ICS801	AA13-00024A	IC-HYBRID:-,TNY253P,-,BPN,-,-	
D669	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		△ICS802	0604-001032	PHOTO-COUPLER:TR,170-260%,300mW,DIP-4,ST	
D671	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		IF	AA39-30007A	IF-CABLE:-,T,100mm,1365#26	
D672	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		J244	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
D701	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		J317	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
D702	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		L101	2701-001040	INDUCTOR-AXIAL:10uH,10%,14X4.5MM	
D703	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		L102	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
D901	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		L103	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
D902	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		L104	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
D903	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m		L106	2701-001040	INDUCTOR-AXIAL:10uH,10%,14X4.5MM	
D904	0403-000546	DIODE-ZENER:MTZ3.6B,3.6V,3.6-3.845V,500m		L107	2701-000116	INDUCTOR-AXIAL:10uH,10%,4.2x9.8mm	
D905	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		L108	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
DS801	0402-000102	DIODE-BRIDGE:D2SB60,600V,1.5A,-		L201	AA27-10001C	COIL-CHOKER:-,100uH,K,-,5.0A,ST,700UH-K(R	
DS802	1405-001036	VARISTOR:430V,2500A,14x8.5mm,TP		L502	2701-000116	INDUCTOR-AXIAL:10uH,10%,4.2x9.8mm	
DS803	0403-000300	DIODE-ZENER:MTZ8.2B,8.2V,7.78-8.19V,500m		L505	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
DS804	0403-000294	DIODE-ZENER:MTZ4.7B,4.7V,4.55-4.80V,500m		L506	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
DS805	0402-000534	DIODE-RECTIFIER:RG10V,400V,1.2A,DO-201,T		L507	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
DS806	1405-001030	VARISTOR:120V,2500A,14x8.5mm,TP		L509	2701-001040	INDUCTOR-AXIAL:10uH,10%,14X4.5MM	
DS807	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		L510	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
DS808	1405-001036	VARISTOR:430V,2500A,14x8.5mm,TP		L511	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
DS810	1405-001036	VARISTOR:430V,2500A,14x8.5mm,TP		L512	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
DZ107	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		L514	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
DZ108	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		L516	2701-001040	INDUCTOR-AXIAL:10uH,10%,14X4.5MM	
DZ109	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		L601	AA29-00004A	FILTER-LINE:-,20UH,3A,AC80-260V,TQ20 20U	
DZ110	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		L902	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
DZ501	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		L903	2701-001040	INDUCTOR-AXIAL:10uH,10%,14X4.5MM	
DZ502	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		L909	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
DZ503	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m		L910	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
DZ504	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m		L912	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
DZ505	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m		LEADC	AA39-00025A	LEAD CONNECTOR-ASSY:-,YFH800-02,YFH800-0	
DZ506	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m		LEADC	AA39-20577A	LEAD CONNECTOR-ASSY:-,YFH806-06,-,6(3)P,	
DZ507	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		LS801	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-	
DZ508	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		LS802	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-	
DZ510	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		LS803	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
DZ665	0403-001039	DIODE-ZENER:MA2560,56V,52-60V,1W,DO-41,T		MDLF	AA59-40003P	MODULE-FOCUS,PACK:-,F300,NTSC,43,64x62,	
DZ666	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m		PCB	AA41-11053C	PCB-MAIN:P51A,1L,FR-1,330x245x1.6T,1A,-	
DZ667	0403-000355	DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500		PCBM	AA41-11040A	PCB-MTS MODULE:PLT51A,1L,FR-1,245x245x1.	
DZ701	0403-000289	DIODE-ZENER:MTZ10C,10V,9.7-10.2V,500mW,D		Q501	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ801	0403-000700	DIODE-ZENER:TZP33A,33V,31-35V,1W,DO-41,T		Q502	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ901	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		Q503	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ902	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		Q665	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ903	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		Q666	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ904	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		Q667	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ905	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		Q701	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ906	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		Q702	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ907	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		Q901	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ909	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		Q902	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ910	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		Q909	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
DZ911	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m		Q910	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
DZ912	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m		QS801	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L,	

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
R121	2008-000266	R-FUSIBLE(S):1ohm,5%,2W,AF,TP,3.9x10mm		R914	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R123	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R915	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R125	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R916	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R126	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R917	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R128	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R918	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R129	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R919	2001-000411	R-CARBON:18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R130	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R920	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R131	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M		R921	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R132	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M		R922	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R133	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		R923	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R134	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		R924	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R143	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R925	2001-001050	R-CARBON(S):1.5KOHM,5%,1/2W,AA,TP,2.4X6.4	
R144	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R926	2001-001050	R-CARBON(S):1.5KOHM,5%,1/2W,AA,TP,2.4X6.4	
R501	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4		R927	2001-001050	R-CARBON(S):1.5KOHM,5%,1/2W,AA,TP,2.4X6.4	
R502	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R928	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R503	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R929	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R504	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R930	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R505	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R931	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R506	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM		R932	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R507	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM		R933	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R508	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R934	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R510	2008-000266	R-FUSIBLE(S):1ohm,5%,2W,AF,TP,3.9x10mm		R935	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R511	2008-001088	R-FUSIBLE(S):1ohm,5%,2W,AG,TP,3.9x12mm		R936	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R512	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm		R941	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R513	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R942	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R515	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R943	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R516	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R944	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R524	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M		R945	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R525	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M		R946	2001-000290	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R528	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R947	2001-000290	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R531	2001-000739	R-CARBON:4.7MOHM,5%,1/8W,AA,TP,1.8X3.2M		R948	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R532	2001-000037	R-CARBON(S):330OHM,5%,1/2W,AA,TP,2.4X6.4		R949	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R626	2001-000411	R-CARBON:18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R950	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R627	2001-000411	R-CARBON:18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R951	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R661	2004-001970	R-METAL:1.8Kohm,1%,1/2W,AA,TP,6.5x2.5m		R952	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R662	2004-001970	R-METAL:1.8Kohm,1%,1/2W,AA,TP,6.5x2.5m		R953	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R665	2001-000052	R-CARBON(S):3.3KOHM,5%,1/2W,AA,TP,2.4X6.4		R954	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R666	2001-000052	R-CARBON(S):3.3KOHM,5%,1/2W,AA,TP,2.4X6.4		R955	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R668	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM		R958	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R669	2001-001144	R-CARBON(S):4.7KOHM,5%,1/2W,AA,TP,2.4X6.4		R959	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R670	2001-000085	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4		R960	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R671	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4		R961	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R672	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4		R962	2001-000864	R-CARBON:56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R673	2001-001086	R-CARBON(S):18KOHM,5%,1/2W,AA,TP,2.4X6.4		R963	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R673A	2001-001144	R-CARBON(S):4.7KOHM,5%,1/2W,AA,TP,2.4X6.4		R964	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R674	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM		R965	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R675	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4		R967	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R676	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M		R968	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R677	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R970	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R678	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R971	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R679	2001-001071	R-CARBON(S):12KOHM,5%,1/2W,AA,TP,2.4X6.4		R974	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
R680	2001-001000	R-CARBON:82KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R976	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R681	2004-001970	R-METAL:1.8Kohm,1%,1/2W,AA,TP,6.5x2.5m		R977	2001-001062	R-CARBON(S):10MOHM,5%,1/2W,AA,TP,2.4X6.4	
R682	2004-002019	R-METAL(S):33Kohm,1%,1/2W,AA,TP,2.5x6.5m		R978	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R683	2004-002019	R-METAL(S):33Kohm,1%,1/2W,AA,TP,2.5x6.5m		R981	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R684	2004-001970	R-METAL:1.8Kohm,1%,1/2W,AA,TP,6.5x2.5m		R982	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R685	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm		R983	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R686	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm		RF802	2008-000294	R-FUSIBLE(S):33ohm,5%,2W,AF,TP,3.9x10mm	
R687	2001-001146	R-CARBON(S):4.7OHM,5%,1/2W,AA,TP,2.4X6.4		RL801	3501-001053	RELAY-POWER:5VDC,530MMW,10A,1FORMA,15MS,5	
R689	2001-001146	R-CARBON(S):4.7OHM,5%,1/2W,AA,TP,2.4X6.4		RS801	2001-001093	R-CARBON(S):2.2KOHM,5%,1/2W,AA,TP,2.4X6.4	
R701	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RS803	2001-001159	R-CARBON(S):510OHM,5%,1/2W,AA,TP,2.4X6.4	
R702	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RS804	2001-001182	R-CARBON(S):7.5KOHM,5%,1/2W,AA,TP,2.4X6.4	
R703	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RS805	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4	
R704	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		RS806	2001-001159	R-CARBON(S):510OHM,5%,1/2W,AA,TP,2.4X6.4	
R801	2003-002161	R-METALOXIDE(S):22KOHM,5%,3W,AG,TP,6X16		RS807	2001-001192	R-CARBON(S):820OHM,5%,1/2W,AA,TP,2.4X6.4	
R802	1404-000187	THERMISTOR-NTC:4.7ohm,15%,2800K,27.2mW/C		SF01	2904-000288	FILTER-SAW AV:45.75MHz,SIP5P,ST,13.7dB,N	
R901	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		SHIELD	AA63-40027	ASHIELD-CASE,T,-,SPTE,TO.25 ACT51A,K1025,	
R903	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		TS801	AA26-00019	ATRANS-SWITCHING,-,AC80-260V,-,US,-,4MH,B	
R904	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		X101	2802-001054	RESONATOR-CERAMIC:514.5KHZ,1.5KHZ,BK,7.0	
R905	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		X901	2801-003224	CRYSTAL-UNIT:32.768KHZ,20PPM,28-AAV,12.5	
R906	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R907	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R908	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R909	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R910	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R912	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm					
R913	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM					

Loc. No.	Code No.	Description : Specification	Remark
		ASSY-CHASSIS,PART	
		* AA90-30220F ASSY-CHASSIS,PART:P51A,PCJ522R	
CON+HC	6003-001023	SCREW-TAPTITE:RWH,+B,M3,L10,ZPC(YEL),SW	
DF+FBT	6003-001023	SCREW-TAPTITE:RWH,+B,M3,L10,ZPC(YEL),SW	
DF+HC	6003-001023	SCREW-TAPTITE:RWH,+B,M3,L10,ZPC(YEL),SW	
HDRC	AA61-00051BHOLDER-CHASSIS:-,PCJ533R,ABS,VO,GRAYE-2		
HV	AA61-10149ABRACKET-HV:-,S4388,SECC,T1.0,-,-,-		
HV+BH	6003-001023	SCREW-TAPTITE:RWH,+B,M3,L10,ZPC(YEL),SW	
PM+HC	6003-001023	SCREW-TAPTITE:RWH,+B,M3,L10,ZPC(YEL),SW	
TBA+AV	6002-000522	SCREW-TAPPING:TH,+2,M4,L15,ZPC(BLK),SWR	
TBA+HC	6003-001023	SCREW-TAPTITE:RWH,+B,M3,L10,ZPC(YEL),SW	

Loc. No.	Code No.	Description : Specification	Remark
		ASSY-CABINET,FRONT	
		* AA90-70139V ASSY-CABINET:524J,PCJ522RX/XAA	
		* AA91-10419M ASSY-CABINET,FRONT:-,PCJ523R,DG703P+BK70	
ABCKET	AA91-00241A ASSY-BRACKET,MAIN:-,SECC T1.6 7.53J5		
AV+CFT	AA60-10011ASCREW-TAPTITE:HH,+PC,M4,L12,ZPC(BLK),SW		
BACKT	AA64-30714ACABINET-BACK, TOP:-,HIPS,HB,-,BLK,-,SVP52		
BACKW	AA64-00501ACABINET-BACK,WOOD:-,PCJ522R,HARD BOARD,H		
BADGE	AA64-00406ABADGE-BRAND AL FORGING,SAMSUNG,DG-703P,S		
BCKETM	AA61-10242ABRACKET-MIRROR,C:-,S5288,SECC-1,T1.0,-,-		
BCKETM	AA61-10361ABRACKET-MIRROR,-,S5288,SECC-1,T1.0,-,-,-		
BCKETM	AA61-00153B BRACKET-MAIN, SIDE:-,7 PROJECTION,SECC,-		
BCKTM	AA61-00152B BRACKET-MAIN,MID:-,7 PROJECTION,SECC,-		
BCM+CM	AA60-10001ASCREW-ASSY:WP,-,+M6,L20,SCM30C,-,ZPC(YE		
BH+ABM	AA60-10011ASCREW-TAPTITE:HH,+PC,M4,L12,ZPC(BLK),SW		
BM+CBT	6003-001026	SCREW-TAPTITE:RH,+B,M4,L15,ZPC(BLK),SWR	
BM5BMM	AA60-10011ASCREW-TAPTITE:HH,+PC,M4,L12,ZPC(BLK),SW		
BOSSC	AA61-40012ABOSS-CABINET:S5288,HIPS,HB,NTR,-,-		
BOSSC	AA61-40026ABOSS-CABINET:S4388,5288,HIPS,HB,NTR,-,-		
BS+CFT	AA60-10011ASCREW-TAPTITE:HH,+PC,M4,L12,ZPC(BLK),SW		
CBB+CM	AA60-10011ASCREW-TAPTITE:HH,+PC,M4,L12,ZPC(BLK),SW		
CBB+TB	AA60-10011ASCREW-TAPTITE:HH,+PC,M4,L12,ZPC(BLK),SW		
CBT+CM	AA60-10050WSCREW-WOOD:W/H,+M4,20,ZPC(BLK),SWRCH18A		
CFB+CM	AA60-10011ASCREW-TAPTITE:HH,+PC,M4,L12,ZPC(BLK),SW		
CFT+CM	AA60-10050WSCREW-WOOD:W/H,+M4,20,ZPC(BLK),SWRCH18A		
CLAMPC	AA65-30008ACLAMP-CORD:PE,HB,BLK,-,-,-		
CRTABM	AA60-10011ASCREW-TAPTITE:HH,+PC,M4,L12,ZPC(BLK),SW		
FOC+CM	AA60-10050WSCREW-WOOD:W/H,+M4,20,ZPC(BLK),SWRCH18A		
FRONT	AA64-31357ACABINET-FRONT,BOT:-,SVP-524J,DG-703P,PIC		
FRONT	AA64-31356MCABINET-FRONT, TOP:-,524J,D703+B702NO-PE		
HDRBOX	AA61-20285AHOLDER-BOX:-,3456,PP,VO,WHT,-		
HDRS	AA61-00081BHOLDER-SCREEN, SIDE:-,524J,A6063 EXTR,-,-,		
HDRS	AA61-00081CHOLDER-SCREEN:-,524J,A6063 EXTR,-,-,WHT,L		
INLAY	AA64-60449BINLAY-COVER:SP-434JMF,-,PS,TO.5,BLK,149.		
INLAY	AA64-60440EINLAY-A/V, SIDE:PCJ533R,E2,PS,TO.3,GRY,-		
KC+CFT	6003-001022	SCREW-TAPTITE:RH,+B,M3,L12,ZPC(BLK),SWR	
KNOBC	AA64-10764BKNOB-CONTROL:-,CHAMPAINNE GOLD+UV,ABS,-		
KNOBP	AA64-10765FKNOB-POWER:-,CHAMPAINNE GOLD+UV,ABS,-,HB		
LED	AA64-40493AINDICATOR-LED:-,SVP-434JA,-,ABS,-,CLR,-		
MBACK	AA67-20026AMIRROR-BACK SURFACE:52' GLASS,3.0,BSM,-,		
PC+CFT	AA60-10002ASCREW-TAPPING:RH,+M4,L12,ZPC(YEL),-OD1		
SCREEN	AA67-70065ASCREEN-TINT:-,52',DNP,-,-,-,1087,815		
SPA	AA60-00027ASPACER-COVER,DUST-SPONGE,T2.0,-,-,-,43J5,-		
SPAM	AA63-00021CSPACER-MIRROR:PVC,-,BLK,L970,SP-524JMF,-		
SPAM	AA63-00021DSPACER-MIRROR:PVC,-,BLK,L678,SP-524JMF,-		
SPAM	AA63-00021GSPACER-MIRROR:PVC,-,BLK,L420,524J,434J,-		
SPRING	AA61-60005ASPRING-CS:-,SUS304,0.6,OD10.7,H10,N4,-,-		
SUN	AA67-70048ASUN-SCREEN:-,52,H/C, A/S,PMMA,TRAN=82%,		
WR+CFT	6003-001022	SCREW-TAPTITE:RH,+B,M3,L12,ZPC(BLK),SWR	
WRMC	AA64-40494AWINDOW-REMOCON:-,SVP-434J,-,PC,-,VIOLETT,		

Loc. No.	Code No.	Description : Specification	Remark
		ASSY-TERMINAL,BOARD	
		* AA91-00158H ASSY-TERMINAL,BOARD:-,HIPS,VO,BLK,NO-PC,	
TEMB	AA63-00045BTERMINAL-BOARD ANT:-,HIPS,-,PCJ533R,-		
INLAY	AA64-00182JINLAY-BACK:PCJ612R,NO-PC,NO-DOLBY,PS SHE		

Loc. No.	Code No.	Description : Specification	Remark
		ASSY-ACCESSORY	
		* AA94-01638A ASSY-ACCESSORY:PCJ522RX/XAA,P51A,U.S.A,S	
HDRLEG	AA61-20126AHOLDER-LEG:-,-,ABS,HB,BLK,-		
IB	AA68-00532AMANUAL-USERS:P51A,W/P100(G),-ENG,-,-,B5		

Loc. No.	Code No.	Description : Specification	Remark
		ASSY-CRT-(R)	
		* AA94-01640A ASSY-CRT-(R):P16LNM07RJA,+380MG,7,BARE,	
AWIRE	AA91-00103CASSY-WIRE,CRT:-,-,7CRT,PROJECTION		
BCKETC	AA61-00055CBRACKET-CRT,WIRE:-,PJT,SUS304 1/8H,-,-,-		
BCKETE	AA61-00054B BRACKET-EARTH:-,PROJECTION,PBS,-,-,-,-		
BCKETL	AA61-00056B BRACKET-LENS:-,PROJECTION,SECC,T1.6,-,-,-		
BCKETVW	AA61-00053B BRACKET-WIRE:-,PROJECTION,SECC-1,T1.6,-,-		
CASE	AA64-00206BCASE-COUPLER,RED:-,PROJECTION,-,ALDC8,-,		
CRTM	AA03-10026UCRT-MONO:-,P16LNM07RJA,-,7INCH,90deg,90		
△DY	AA27-50005LDEFLECTION-YOKE:-,DPD-5292AL(S),7/PJT C		
HDRC	AA61-00057CHOLDER-CAP:-,7 PROJECTION,PC,-,CLEAR,-		
LEAD	AA39-00018ALEAD CONNECTOR-ASSY:-,YFH800-01,YRH187RH		
LENZA	AA67-10005ALENS-ASSY:-,DELTA,CLEAR,S4388,-,77,-		
LENZA	AA67-10008ALENS:-,DELTA,RED,PJT,-,77,79,-		
MAGN	AA27-00003BMAGNET-CONVERGENCE:-,JH92LT-029,29.1MM		
SCREW	AA60-10011ASCREW-TAPTITE:HH,+PC,M4,L12,ZPC(BLK),SW		
SPAC	AA63-00091BSPACER-CLENS:EPDM,-,BLK,-,PROJECTION,-		
SPACAP	AA63-00061BSPACER-CAP:EPDM,-,BLK,-,PROJECTION,-		
SPACRT	AA63-00060BSPACER-CRT:EPDM,-,BLK,7,PROJECTION,-		
SPADY	AA63-60025ASPACER-DY:NEOPRENE,-,BLK,VO,S4388,-		
SPAF	AA63-00099ASPACER-FELT:FELT,T1.0,BLK,-,PJT,-		
SPAL	AA63-00076ASPACER-LENS:FELT,T1.0,BROWN,7CRT,PROJE		

Loc. No.	Code No.	Description : Specification	Remark
		ASSY-CRT-(G)	
		* AA94-01641A ASSY-CRT-(G):P16LNM07HKA,+380MG,7,BARE,	
AWIRE	AA91-00103CASSY-WIRE,CRT:-,-,7CRT,PROJECTION		
CASE	AA64-00207BCASE-COUPLER,GREEN:-,PROJECTION,7,ALDC8		
CRTB	AA61-00055CBRACKET-CRT,WIRE:-,PJT,SUS304 1/8H,-,-,-		
CRTM	AA03-10026VCR T-MONO:-,P16LNM07HKA,-,7INCH,90deg,90		
DY	AA27-50005LDEFLECTION-YOKE:-,DPD-5292AL(S),7/PJT C		
EARB	AA61-00054B BRACKET-EARTH:-,PROJECTION,PBS,-,-,-,-		
HDRCAP	AA61-00057CHOLDER-CAP:-,7 PROJECTION,PC,-,CLEAR,-		
LEAD	AA39-00018ALEAD CONNECTOR-ASSY:-,YFH800-01,YRH187RH		
LENZA	AA67-10005ALENS-ASSY:-,DELTA,CLEAR,S4388,-,77,-		
LENSB	AA61-00056B BRACKET-LENS:-,PROJECTION,SECC,T1.6,-,-,-		
LENSD	AA67-10071ALENS-DELTA 77 79:-,GREEN,C ELEMENT,		
MAGNET	AA27-00003BMAGNET-CONVERGENCE:-,JH92LT-029,29.1MM		
SCREW	AA60-10011ASCREW-TAPTITE:HH,+PC,M4,L12,ZPC(BLK),SW		
SPACAP	AA63-00061BSPACER-CAP:EPDM,-,BLK,-,PROJECTION,-		
SPACL	AA63-00091BSPACER-CLENS:EPDM,-,BLK,-,PROJECTION,-		
SPACRT	AA63-00060BSPACER-CRT:EPDM,-,BLK,7,PROJECTION,-		
SPADY	AA63-60025ASPACER-DY:NEOPRENE,-,BLK,VO,S4388,-		
SPAF	AA63-00099ASPACER-FELT:FELT,T1.0,BLK,-,PJT,-		
SPALEN	AA63-00076ASPACER-LENS:FELT,T1.0,BROWN,7CRT,PROJE		
WIREB	AA61-00053B BRACKET-WIRE:-,PROJECTION,SECC-1,T1.6,-,-		

Loc. No.	Code No.	Description : Specification	Remark
		ASSY-CRT-(B)	
		* AA94-01642A ASSY-CRT-(B):P16LNM07BMB,+380MG,7,BARE,	
ALENS	AA67-10005ALENS-ASSY:-,DELTA,CLEAR,S4388,-,77,-		
AWRE	AA91-00103CASSY-WIRE,CRT:-,-,7CRT,PROJECTION		
BCKETC	AA61-00055CBRACKET-CRT,WIRE:-,PJT,SUS304 1/8H,-,-,-		
BCKETE	AA61-00054B BRACKET-EARTH:-,PROJECTION,PBS,-,-,-,-		
BCKETVW	AA61-00053B BRACKET-WIRE:-,PROJECTION,SECC-1,T1.6,-,-		
CAPS	AA63-00061BSPACER-CAP:EPDM,-,BLK,-,PROJECTION,-		
CASEC	AA64-00208BCASE-COUPLER,BLUE:-,PROJECTION,7,ALDC,-		
CLENS	AA63-00091BSPACER-CLENS:EPDM,-,BLK,-,PROJECTION,-		
CRTM	AA03-10026WCRT-MONO:-,P16LNM07BMB,-,7INCH,90deg,90		
CRTS	AA63-00060BSPACER-CRT:EPDM,-,BLK,7,PROJECTION,-		
△DY	AA27-50005LDEFLECTION-YOKE:-,DPD-5292AL(S),7/PJT C		
DYS	AA63-60025ASPACER-DY:NEOPRENE,-,BLK,VO,S4388,-		
FELTS	AA63-00099ASPACER-FELT:FELT,T1.0,BLK,-,PJT,-		

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
F804A	3602-000114	FUSE-HOLDER:-,30mohm		R427A	2003-001031	R-METALOXIDE(S):2.4ohm,5%,2W,AF,TP,3.9x	
F804B	3602-000114	FUSE-HOLDER:-,30mohm		R428	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9	
F805	3601-001065	FUSE-FERRULE:125V,3.5A,FA,CERAMIC,2.4X7.		R428A	2002-001017	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.7x9	
F806	3601-001065	FUSE-FERRULE:125V,3.5A,FA,CERAMIC,2.4X7.		R429	2003-000586	R-METALOXIDE(S):22Kohm,5%,2W,AF,TP,4x12	
F807	3601-001065	FUSE-FERRULE:125V,3.5A,FA,CERAMIC,2.4X7.		R430	2003-000586	R-METALOXIDE(S):22Kohm,5%,2W,AF,TP,4x12	
F854	3601-001086	FUSE-FERRULE:125V,5A,FA,GLASS,2.4x7.5mm		R433	2001-001155	R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.5x6.4	
F855	3601-001064	FUSE-FERRULE:125V,4A,FA,GLASS,2.4x7.5mm		R434	2001-001093	R-CARBON(S):2.2KOHM,5%,1/2W,AA,TP,2.4X6.	
F871	3601-001065	FUSE-FERRULE:125V,3.5A,FA,CERAMIC,2.4X7.		R440	2008-001091	R-FUSIBLE(S):0.470HM,10%,1/2W,AC,BK,2.5X	
FETS	0505-001202	FET-SILICON-IRFS640A,N,200V,9.8A,0.18ohm		R441	2008-000282	R-FUSIBLE:0.47ohm,5%,1W,AA,TP,3.9x12mm	
△ IC301	1204-000517	IC-VERTICAL DEF.:LA7845,SIP,7P,-,PLASTICH/SINK		R442	2008-001091	R-FUSIBLE(S):0.470HM,10%,1/2W,AC,BK,2.5X	
△ IC421	1203-000165	IC-POSI.ADJUSTREG.:78R12,TO-220,3P,-,-		R444	2003-000995	R-METALOXIDE(S):3.3Kohm,5%,2W,AF,TP,3.9	
△ IC431	1201-000191	IC-OPAMP:4558,DIP,8P,300MIL,DUAL,20V/mV		R462	2008-001033	R-FUSIBLE(S):10ohm,5%,2W,AF,TP,3.9x10mm	
△ IC801	AA13-00018AIC-HYBRID:-,STR-F6656,LF1351,5PIN,-,-	H/SINK		R463	2003-000502	R-METALOXIDE(S):150ohm,5%,2W,AA,TP,4x12	
△ IC802	AA13-00033AIC-HYBRID:-,SVD001,-,7PIN,-,-			R464	2003-002158	R-METALOXIDE:0.680HM,5%,1W,AG,TP,4.3X12	
△ IC804	AA13-20002LIC-HYBRID:-,SE125N,SIP,3P,ERROR AMP			R465	2008-001091	R-FUSIBLE(S):0.470HM,10%,1/2W,AC,BK,2.5X	
△ IC806	0604-001032	PHOTO-COUPLER:TR,170-260%,300mW,DIP-4,ST		R466	2004-002019	R-METAL(S):33Kohm,1%,1/2W,AA,TP,2.5x6.5m	
L431	AA27-30003SCOIL-LINERITY:-,54uH,YL81DR14x15,0.12mmx			R467	2004-002019	R-METAL(S):33Kohm,1%,1/2W,AA,TP,2.5x6.5m	
L432	AA27-40001FCOIL-HORIZ.WIDTH:-,1mH,DR1520,PI0,4,-			R468	2001-001122	R-CARBON(S):3.9KOHM,5%,1/2W,AA,TP,2.4X6.	
L481	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R469	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
L482	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R470	2001-000028	R-CARBON(S):1000HM,5%,1/2W,AA,TP,2.4X6.4	
L483	2901-000299	FILTER-EMI ON BOARD:-,6A,UL/CSA,-,9x7.5,		R471	2004-002011	R-METAL(S):110Kohm,1%,1/2W,AA,TP,2.4x6.4	
L492	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		R472	2008-000252	R-FUSIBLE(S):0.47ohm,10%,1/2W,AF,TP,2.5x	
△ L800	AA29-30002PFILTER-LINE NOISE:-,3MH,5A,AC100-260V,35			R473	2004-001395	R-METAL(S):330Kohm,2%,1/2W,AA,TP,2.4x6.4	
△ L801	AA29-30002MFILTER-LINE NOISE:-,1mHMIN,5A,AC90-260V,			R486	2003-002014	R-METALOXIDE(S):0.60HM,5%,2W,AF,TP,3.9X	
L803	AA29-30002MFILTER-LINE NOISE:-,1mHMIN,5A,AC90-260V,			R488	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L806	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R808	2001-000002	R-CARBON(S):200KOHM,5%,1/2W,AA,TP,6.4X2.	
L807	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R809	2001-000002	R-CARBON(S):200KOHM,5%,1/2W,AA,TP,6.4X2.	
L808	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R812	2003-002151	R-METALOXIDE:18KOHM,5%,2W,AG,TP,6X16MM	
L810	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R814	2003-002151	R-METALOXIDE:18KOHM,5%,2W,AG,TP,6X16MM	
L811	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R815	2003-002162	R-METALOXIDE(S):15KOHM,5%,3W,AG,TP,6X16	
L812	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R815A	2003-002162	R-METALOXIDE(S):15KOHM,5%,3W,AG,TP,6X16	
L813	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R817	2009-001096	R-METAL PLATE:0.070HM,5%,5W,-,BK,13X5.X1	
L814	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R825	2002-001010	R-COMPOSITION:1.8Mohm,5%,1/2W,AA,TP,3.7x	
L815	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R832	2001-001178	R-CARBON(S):680OHM,5%,1/2W,AA,TP,2.4X6.4	
L816	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R833	2003-001024	R-METALOXIDE(S):150ohm,5%,2W,AF,TP,3.9x	
L831	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R834	2001-001097	R-CARBON(S):2.4KOHM,5%,1/2W,AA,TP,2.4X6.	
L832	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R838	2001-001144	R-CARBON(S):4.7KOHM,5%,1/2W,AA,TP,2.4X6.	
L851	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R840	2003-002020	R-METALOXIDE(S):56Kohm,5%,2W,AF,TP,3.9x	
L854	AA27-10001CCOIL-CHOKE:-,100uH,K,-,5.0A,ST,700UH-K(R			R841	2008-001096	R-FUSIBLE(S):3.3OHM,5%,1/2W,AC,BK,2.5X6.	
L857	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R842	2001-001150	R-CARBON(S):470KOHM,5%,1/2W,AA,TP,2.4X6.	
L859	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R844	2003-002020	R-METALOXIDE(S):56Kohm,5%,2W,AF,TP,3.9x	
L860	AA27-10001CCOIL-CHOKE:-,100uH,K,-,5.0A,ST,700UH-K(R			R845	2003-002020	R-METALOXIDE(S):56Kohm,5%,2W,AF,TP,3.9x	
L862	AA27-10001CCOIL-CHOKE:-,100uH,K,-,5.0A,ST,700UH-K(R			R846	2003-002020	R-METALOXIDE(S):56Kohm,5%,2W,AF,TP,3.9x	
L872	AA27-10001CCOIL-CHOKE:-,100uH,K,-,5.0A,ST,700UH-K(R			R847	2003-002020	R-METALOXIDE(S):56Kohm,5%,2W,AF,TP,3.9x	
L874	AA27-10002LCOIL-CHOKE:-,24UH,K,-,2A,-,24UH-K,10X10M			R848	2001-000114	R-CARBON(S):180KOHM,5%,1/2W,AA,TP,2.4X6.	
PCB	AA41-00013BPCB-SUB-P51A,1L,CEM-1,330X245X1,6T,1A,			R849	2001-000114	R-CARBON(S):180KOHM,5%,1/2W,AA,TP,2.4X6.	
Q301	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R855	2001-001196	R-CARBON(S):9.1KOHM,5%,1/2W,AA,TP,2.4X6.	
△ Q411	0502-000258	TR-POWER:KSC1983,NPN,30W,TO-220,-,500		R856	2001-001155	R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
△ Q431	0502-000450	TR-POWER:2SD1887YD,NPN,1500V,800V,10A,7	H/SINK	R857	2001-001155	R-CARBON(S):5.6KOHM,5%,1/2W,AA,TP,2.4X6.	
△ Q432	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R871	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
△ Q433	0502-000298	TR-POWER:KSD73,NPN,30W,TO-220,-,120-240	H/SINK	R872	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4MM	
△ Q441	0502-001104	TR-POWER:2SD921,NPN,80W,TO-3P,BK,700-	H/SINK	R891	2002-001013	R-COMPOSITION:4.7Mohm,5%,1/2W,AA,TP,3.7x	
△ Q472	0502-001118	TR-POWER:KSC2335,NPN,40W,TO-220,ST,30-6		RL802	3501-001040	RELAY-POWER:12VDC,500mW,10A,1FormA,15mS,	
△ Q473	0502-001100	TR-POWER:2SC4125,NPN,70W,TO-3PNVL,BK,8-	H/SINK	△ T431	AA26-50001UTRANS-HORIZ DRIVE:-,28mH,105uH,4uH,ER28x		
R301	2004-001897	R-METAL(S):43.2Kohm,1%,1/2W,AA,TP,2.5x6.		△ T432	AA26-00033ATRANS-DUMMY:-,-,PL-5 EER4445,BK,5.5M		
R302	2004-001897	R-METAL(S):43.2Kohm,1%,1/2W,AA,TP,2.5x6.		△ T444	AA26-00032ATRANS-FLYBACK:-,FWZ-50A002,50,125V		
R303	2004-001984	R-METAL(S):26.7Kohm,1%,1/2W,AA,TP,2.4x6.		△ T461	AA26-50001VTRANS-HORIZ DRIVE:-,6.0mH,113uH,4uH,EI19		
R305	2004-001984	R-METAL(S):26.7Kohm,1%,1/2W,AA,TP,2.4x6.		△ T481	AA26-50001WTRANS-HORIZ DRIVE:-,830uH,23uH,4uH,EI-30		
R306	2003-002070	R-METALOXIDE:1ohm,5%,2W,AF,TP,3.9x10mm		△ T802	AA26-00034ATRANS-SWITCHING:-,-,AC90-260V,-,UL/CSA		
R307	2003-000436	R-METALOXIDE(S):1.5ohm,5%,1W,AF,TP,3.3x		VR471	2103-001024	VR-SEMI:50Kohm,25%,0.3W,TOP	
R308	2001-000016	R-CARBON(S):10HM,5%,1/2W,AA,TP,2.4X6.4MM					
R310	2003-002150	R-METALOXIDE:270OHM,5%,2W,AG,TP,6X16MM					
R312	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R313	2001-000761	R-CARBON:430OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R314	2001-000761	R-CARBON:430OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R332	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4					
R333	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4					
R334	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4					
R406	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm					
R407	2004-001897	R-METAL(S):43.2Kohm,1%,1/2W,AA,TP,2.5x6.					
R408	2004-002016	R-METAL(S):15Kohm,1%,1/2W,AA,TP,2.5x6.5m					
R409	2004-001394	R-METAL(S):2Kohm,1%,1/2W,AA,TP,2.4x6.4mm					
R410	2001-000109	R-CARBON(S):470OHM,5%,1/2W,AA,TP,2.4X6.4					
R419	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R424	2008-000299	R-FUSIBLE(S):47ohm,5%,2W,AF,TP,3.9x10mm					
R426	2003-002153	R-METALOXIDE:4.7OHM,5%,2W,AG,TP,6X16MM					
R427	2003-001031	R-METALOXIDE(S):2.4ohm,5%,2W,AF,TP,3.9x					
				BKZ01	AA61-10068ABRACKET-PCB:-,M2160,SPTE,TO.3,-,-,-		
				BKZ02	AA61-10068ABRACKET-PCB:-,M2160,SPTE,TO.3,-,-,-		
				CN401	3711-002705	CONNECTOR-HEADER:NOWALL,7P,1R,2.5mm,ANGL	
				CN402	3711-000447	CONNECTOR-HEADER:3WALL,3P,1R,2.5mm,ANGLE	
				△ CN403	3711-000447	CONNECTOR-HEADER:3WALL,3P,1R,2.5mm,ANGLE	
				△ CN404	3711-000447	CONNECTOR-HEADER:3WALL,3P,1R,2.5mm,ANGLE	
				CZ144	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11.5	
				CZ146	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11.5.5	
				CZ147	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,	
				CZ148	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,	
				CZ149	2201-000516	C-CERAMIC,DISC:4.7nF,+100-0%,500V,Y5U,TP	

ASSY-PCB,V/M

* AA95-00054AASSY-PCB,V/M:-,PCJ533RX/XAA,P51A,-,-,-

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
CZ150	2201-000516	C-CERAMIC,DISC:4.7nF,+100-0%,500V,Y5U,TP		CZ121	2201-000764	C-CERAMIC,DISC:82pF,5%,50V,NPO,TP,8x3.5,	
CZ151	2401-001513	C-AL:47uF,20%,16V,WT,TP,5x11.5		CZ126	2201-000499	C-CERAMIC,DISC:390pF,5%,50V,SL,TP,8.0x3.	
CZ152	2401-001157	C-AL:33uF,20%,160V,GP,TP,12.5x20.5		CZ127	2201-000499	C-CERAMIC,DISC:390pF,5%,50V,SL,TP,8.0x3.	
CZ153	2401-001513	C-AL:47uF,20%,16V,WT,TP,5x11.5		CZ128	2201-000499	C-CERAMIC,DISC:390pF,5%,50V,SL,TP,8.0x3.	
CZ155	2201-000604	C-CERAMIC,DISC:56pF,+100-0%,500V,SL,TP,7		CZ132	2201-000976	C-CERAMIC,DISC:22pF,5%,50V,CH,TP,5.0x3.0	
CZ167	2401-001220	C-AL:4.7uF,20%,160V,GP,TP,8x11.5,5		CZ133	2201-000863	C-CERAMIC,DISC:680pF,10%,50V,Y5P,TP,5x3,	
CZ167A	2401-001220	C-AL:4.7uF,20%,160V,GP,TP,8x11.5,5		CZ135	2201-000863	C-CERAMIC,DISC:680pF,10%,50V,Y5P,TP,5x3,	
DZ116	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		CZ136	2201-000976	C-CERAMIC,DISC:22pF,5%,50V,CH,TP,5.0x3.0	
DZ117	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		CZ137	2201-000863	C-CERAMIC,DISC:680pF,10%,50V,Y5P,TP,5x3,	
DZ118	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		CZ138	2201-000327	C-CERAMIC,DISC:2.2nF,10%,50V,Y5V,TP,6.5x	
DZ119	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		CZ139	2201-000327	C-CERAMIC,DISC:2.2nF,10%,50V,Y5V,TP,6.5x	
DZ120	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		CZ144	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11.5	
DZ121	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		CZ145	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
LZ112	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm		CZ146	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11.5	
LZ114	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		CZ147	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
LZ115	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		CZ151	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
LZ116	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		CZ152	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
PCB	AA41-00018APCB-V/M MODULE:P15A,1L,FR,1.245X245X1.6T			CZ153	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
OZ103	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		CZ154	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
OZ104	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		CZ155	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
OZ105	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		CZ156	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP	
OZ106	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		D453	0402-001286	DIODE-RECTIFIER:RP1H,2000V,1A,-,TP	
OZ107	0502-000131	TR-POWER:2SA1011-D,PNP,1.2W,TO-220,-,60	H/SINK	D501	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
OZ108	0502-000153	TR-POWER:2SC2344-D,NPN,1.2W,TO-220,-,60	H/SINK	DZ120	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
RZ154	2003-000532	R-METALOXIDE(S):18ohm,5%,2W,AF,TP,4x12m		DZ121	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
RZ156	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM		DZ123	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
RZ165	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		DZ126	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
RZ166	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		DZ127	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
RZ167	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		DZ128	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
RZ167A	2001-000554	R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM		△ICZ101	1203-000284	IC-POSI.FIXED REG.:7806,TO-220,3P,-,PLAS	H/SINK
RZ168	2003-002157	R-METALOXIDE:220OHM,5%,2W,AG,TP,6X16MM		△ICZ102	1203-000121	IC-NEGA.FIXED REG.:7906,TO-220,3P,-,PLAS	
RZ169	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M		△ICZ103	1201-001512	IC-VIDEO AMP:392,SIP,22P,-,THREE,-,PLAST	H/SINK
RZ170	2001-000666	R-CARBON:330HM,5%,1/8W,AA,TP,1.8X3.2MM		△ICZ104	1201-001512	IC-VIDEO AMP:392,SIP,22P,-,THREE,-,PLAST	H/SINK
RZ171	2001-000666	R-CARBON:330HM,5%,1/8W,AA,TP,1.8X3.2MM		LZ101	2701-001030	INDUCTOR-AXIAL:43UH,10%,14X4.5MM	
RZ172	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		LZ102	2701-001030	INDUCTOR-AXIAL:43UH,10%,14X4.5MM	
RZ173	2001-001139	R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4		LZ107	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
RZ174	2001-001139	R-CARBON(S):39KOHM,5%,1/2W,AA,TP,2.4X6.4		LZ108	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
RZ175	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		LZ109	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
RZ176	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		LZ110	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
RZ177	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		LZ111	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
RZ178	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2M		LZ112	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
RZ179	2003-000713	R-METALOXIDE(S):47ohm,5%,2W,AF,TP,4x12m		PCB	AA41-00135APCB-CONVERGENCE:P15A,1L,CEM-1,330X245X1.		
RZ180	2001-001100	R-CARBON(S):2.70HM,5%,1/2W,AA,TP,2.4X6.4		R382	2002-001006	R-COMPOSITION:4.7Kohm,5%,1/2W,AA,TP,3.7x	
RZ181	2001-001100	R-CARBON(S):2.70HM,5%,1/2W,AA,TP,2.4X6.4		R476	2004-004046	R-METAL(S):430Kohm,1%,1/2W,AA,TP,2.5x6.5	
RZ182	2003-000713	R-METALOXIDE(S):47ohm,5%,2W,AF,TP,4x12m		R476A	2004-004001	R-METAL(S):180Kohm,1%,1/2W,AA,TP,2.5x6.5	
RZ183	2003-001018	R-METALOXIDE(S):220ohm,5%,2W,AF,TP,3.9x		R476B	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5	
				R476C	2004-004046	R-METAL(S):430Kohm,1%,1/2W,AA,TP,2.5x6.5	
				R478	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5	
				R501	2004-002016	R-METAL(S):15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
				R502	2004-001369	R-METAL(S):1.2Kohm,1%,1/2W,AA,TP,2.4x6.4	
				RFZ19	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
				RFZ20	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
				RFZ21	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
				RFZ22	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
				RFZ50	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
				RFZ51	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
				RFZ52	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
				RFZ53	2008-000261	R-FUSIBLE(S):150ohm,5%,1W,AF,TP,3.9x10mm	
CZ101	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20.5		RZ104	2001-001114	R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
CZ102	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20.5		RZ105	2001-001114	R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
CZ103	2401-000689	C-AL:2200uF,20%,16V,GP,TP,13x25.5		RZ106	2001-001114	R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
CZ105	2401-000689	C-AL:2200uF,20%,16V,GP,TP,13x25.5		RZ107	2001-001114	R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
CZ106	2201-000180	C-CERAMIC,DISC:10nF,10%,50V,Y5V,TP,6.5*3		RZ108	2001-001114	R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
CZ107	2201-000180	C-CERAMIC,DISC:10nF,10%,50V,Y5V,TP,6.5*3		RZ109	2001-001114	R-CARBON(S):270OHM,5%,1/2W,AA,TP,2.4X6.4	
CZ108	2201-000499	C-CERAMIC,DISC:390pF,5%,50V,SL,TP,8.0x3		RZ110	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CZ109	2201-000499	C-CERAMIC,DISC:390pF,5%,50V,SL,TP,8.0x3		RZ111	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CZ110	2201-000499	C-CERAMIC,DISC:390pF,5%,50V,SL,TP,8.0x3		RZ112	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CZ111	2201-000976	C-CERAMIC,DISC:22pF,5%,50V,CH,TP,5.0x3.0		RZ113	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
CZ112	2201-000863	C-CERAMIC,DISC:680pF,10%,50V,Y5P,TP,5x3,		RZ114	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CZ113	2201-000976	C-CERAMIC,DISC:22pF,5%,50V,CH,TP,5.0x3.0		RZ115	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
CZ114	2201-000863	C-CERAMIC,DISC:680pF,10%,50V,Y5P,TP,5x3,		RZ116	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CZ115	2201-000976	C-CERAMIC,DISC:22pF,5%,50V,CH,TP,5.0x3.0		RZ117	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
CZ116	2201-000863	C-CERAMIC,DISC:680pF,10%,50V,Y5P,TP,5x3,		RZ118	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CZ117	2201-000327	C-CERAMIC,DISC:2.2nF,10%,50V,Y5V,TP,6.5x		RZ119	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
CZ118	2201-000327	C-CERAMIC,DISC:2.2nF,10%,50V,Y5V,TP,6.5x		RZ120	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CZ119	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		RZ121	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CZ120	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		RZ123	2003-002148	R-METALOXIDE:3.9OHM,2%,2W,AF,TP,3.9X10M	

ASSY-PCB,CONVERGENCE

* AA95-00055EASSY-PCB,CONVERGENCE-;PCJ522RX/XAA,P51A

C491	2306-000322	C-FILM,MPPF:12nF,5%,1.6KV,TP,29x20.5x13,	
CN203	AA39-20067GLEAD CONNECTOR-ASSY:-,YBNH250-10,67096-0		
CN401	AA39-20068ALEAD-CONNECTOR,ASSY:-,YBNH025-08,67096-0		
CN402	AA39-20071BLEAD-CONNECTOR,ASSY:-,YBNH025-12,67096-0		
CN403	3711-002643 CONNECTOR-HEADER:BOX,4P,1R,2.5MM,STRAIGH		
CN802	AA39-20068ALEAD-CONNECTOR,ASSY:-,YBNH025-08,67096-0		

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
RZ124	2003-002148	R-METALOXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		C493	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP	
RZ125	2003-002148	R-METALOXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		C494	2201-000471	C-CERAMIC,DISC:0.33nF,10%,50V,Y5P,TP,4x3	
RZ126	2003-002148	R-METALOXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		C495	2301-000204	C-FILM,PEF:2.7nF,5%,50V,TP,7.4x3.9x13mm,	
RZ127	2003-002147	R-METALOXIDE:3.30HM,2%,2W,AF,TP,3.9X10M		C496	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11.5,5	
RZ128	2003-002147	R-METALOXIDE:3.30HM,2%,2W,AF,TP,3.9X10M		CN401	3711-001049	CONNECTOR-HEADER BOX,6P,1R,2.5mm,ANGLE,-	
RZ129	2003-001024	R-METALOXIDE(S):150ohm,5%,2W,AF,TP,3.9x		CN402	3711-002709	CONNECTOR-HEADER NOWALL,12P,1R,2.5MM,ANG	
RZ130	2003-001024	R-METALOXIDE(S):150ohm,5%,2W,AF,TP,3.9x		CN403	AA39-20052ALEAD-CONNECTOR,ASSY:-,YBNH025-04,YSH025-		
RZ131	2003-001024	R-METALOXIDE(S):150ohm,5%,2W,AF,TP,3.9x		CN404	3711-001283	CONNECTOR-HEADER NOWALL,14P,1R,2.5mm,ANG	
RZ132	2003-001024	R-METALOXIDE(S):150ohm,5%,2W,AF,TP,3.9x		D342	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ133	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		D343	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ134	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		D344	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ135	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		D352	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ136	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		D353	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ137	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		D355	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
RZ138	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		D363	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ139	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		D364	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ140	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		D371	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ141	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		D372	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ142	2003-002147	R-METALOXIDE:3.30HM,2%,2W,AF,TP,3.9X10M		D373	0402-000243	DIODE-RECTIFIER:RC2-V1,200V,0.2A,DO-201	
RZ143	2003-002147	R-METALOXIDE:3.30HM,2%,2W,AF,TP,3.9X10M		D384	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ144	2003-002148	R-METALOXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		D385	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ145	2003-002148	R-METALOXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		D386	0403-000663	DIODE-ZENER:MTZ3.3B,3.3V,3.32-3.53V,500m	
RZ146	2003-002148	R-METALOXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		D395	0403-000355	DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500	
RZ147	2003-002148	R-METALOXIDE:3.90HM,2%,2W,AF,TP,3.9X10M		D442	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ148	2003-001024	R-METALOXIDE(S):150ohm,5%,2W,AF,TP,3.9x		D443	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
RZ149	2003-001024	R-METALOXIDE(S):150ohm,5%,2W,AF,TP,3.9x		D451	0402-000216	DIODE-RECTIFIER:ERC2-06,600V,1.0A,DO-20	
SG303	AA27-90001BCOIL-SPARK,GAP:S-23,1.5KV,-,-,-		D456	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		
VR472	2103-001086	VR-SEMI:100KOHM,25%,0.3W,TOP		D457	0403-000551	DIODE-ZENER:MTZ3.9B,3.9V,3.89-4.16V,500m	
VR491	2103-000669	VR-SEMI:10Kohm,25%,1/5W,TOP		D474	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m	
				D475	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
				D476	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
				D477	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
				D478	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
				D479	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
				D480	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
				D482	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
				D483	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				D491	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
				D492	0403-000666	DIODE-ZENER:MTZ5.1A,5.1V,4.81-5.07V,500m	
				△IC471	1203-000610	IC-PWMCONTROLLER:494,DIP,16P,300MIL,PLA	
				△IC481	1203-001217	IC-POS:ADJUST REG.:431,TO-92,3P,4.58MIL	
				△IC491	0801-000659	IC-CMOSLOGIC:74HC123,MULTIVIBATOR,DIP,1	
				L341	2701-000116	INDUCTOR-AXIAL:10uH,10%,4.2x9.8mm	
				L351	AA27-10003MCOIL-CHOKE:-,6100uH,J,40,34mA,TP,EL6067R		
				PCB	AA41-00021APCB-HV MODULE:P51A,1L,FR,1.330X245X1.6T,		
				Q342	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q343	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q344	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
				Q350	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q351	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
				Q352	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q353	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q354	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
				Q355	0501-000366	TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L,	
				Q371	0502-000442	TR-POWER:2SC4636RB,NPN,2W,TO-220,ST,10-	H/SINK
				Q381	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q382	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q401	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q402	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q421	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				△Q422	0502-001118	TR-POWER:KSC2335,NPN,40W,TO-220,ST,30-6	
				Q451	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q452	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q453	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q454	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
				Q461	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q471	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q473	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q481	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				Q482	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
				Q483	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
				Q491	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
R339	2001-000613	R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M		R340	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R340	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		R341	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R341	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R342	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R342	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,1.8X3.2M		R343	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	

ASSY-PCB,H/V MDL

* AA95-00056DASSY-PCB,H/V MDL:-,PCJ522RX/XAA,P51A,-,-,-

BK01	AA61-10068ABRACKET-PCB:-,M2160,SPT,TO,3,-,-,-
BK02	AA61-10068ABRACKET-PCB:-,M2160,SPT,TO,3,-,-,-
BK03	AA61-10068ABRACKET-PCB:-,M2160,SPT,TO,3,-,-,-
C341	2401-001914 C-AL:1uF,20%,50V,BP,TP,5x11,5
C342	2401-000962 C-AL:22uF,20%,50V,GP,TP,5x11,5
C351	2305-000443 C-FILM,MPEF:51nF,5%,100V,TP,-,5mm
C352	2401-000480 C-AL:10uF,20%,50V,GP,TP,5x11,5
C353	2201-000863 C-CERAMIC,DISC:680pF,10%,50V,Y5P,TP,5x3,
C354	2301-000261 C-FILM,PEF:4.7nF,5%,100V,TP,10.5x12.5x6.
C355	2401-000480 C-AL:10uF,20%,50V,GP,TP,5x11,5
C356	2201-000180 C-CERAMIC,DISC:10nF,10%,50V,Y5V,TP,6.5*3
C357	2401-001989 C-AL:4.7uF,20%,50V,BP,TP,5x11,5
C358	2401-000471 C-AL:10uF,20%,50V,BP,TP,5x11,5mm
C360	2305-000355 C-FILM,MPEF:330nF,5%,63V,TP,-,5mm
C361	2306-000122 C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m
C362	2305-000149 C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5
C371	2401-000302 C-AL:100uF,20%,25V,GP,TP,6.3x11,5
C372	2401-000480 C-AL:10uF,20%,50V,GP,TP,5x11,5
C373	2401-000302 C-AL:100uF,20%,25V,GP,TP,6.3x11,5
C374	2401-001621 C-AL:6.8uF,20%,450V,GP,TP,13x20,5
C405	2201-000558 C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,
C406	2201-000370 C-CERAMIC,DISC:220pF,10%,50V,Y5P,TP,4.0X
C421	2401-000302 C-AL:100uF,20%,25V,GP,TP,6.3x11,5
C422	2301-000289 C-FILM,PEF:5.6nF,5%,50V,TP,7x6x3,5
C429	2305-000704 C-FILM,MPEF:100nF,5%,250V,TP,16.5x10.3x5
C454	2303-000331 C-FILM,PPF:4.7nF,5%,630V,TP,19.5x12x7.7.
C455	2401-001527 C-AL:47uF,20%,250V,HR,TP,13x25mm,5m
C456	2201-000132 C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4
C461	2201-000600 C-CERAMIC,DISC:560pF,10%,50V,Y5P,TP,5x3,
C462	2301-000246 C-FILM,PEF:33nF,5%,100V,TP,7x5.0x9.5mm,5
C466	2305-001023 C-FILM,MPEF:680nF,10%,63V,TP,7.5x5.5x14.
C480	2306-000122 C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m
C481	2401-000914 C-AL:22uF,20%,16V,GP,TP,5x11,5
C482	2305-000178 C-FILM,MPEF:10nF,5%,100V,TP,-,5mm
C484	2401-001026 C-AL:3.3uF,20%,50V,GP,TP,5x11,5
C485	2201-000146 C-CERAMIC,DISC:100pF,5%,50V,SL,TP,5x3,5
C486	2201-000146 C-CERAMIC,DISC:100pF,5%,50V,SL,TP,5x3,5
C487	2401-001026 C-AL:3.3uF,20%,50V,GP,TP,5x11,5
C488	2401-002144 C-AL:47uF,20%,16V,GP,TP,5x11,5
C489	2401-001840 C-AL:100uF,20%,16V,GP,TP,6.3x11,5
C490	2201-000119 C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP
C492	2401-002144 C-AL:47uF,20%,16V,GP,TP,5x11,5

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
R344	2001-000890	R-CARBON:6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		R460	2003-002159	R-METALOXIDE:150OHM,5%,1W,AG,TP,4.3X12M	
R345	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M		R461	2001-000302	R-CARBON:100HM,5%,1/8W,AA,TP,1.8X3.2MM	
R345A	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R464	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R346	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R471	2001-001146	R-CARBON(S):4.7OHM,5%,1/2W,AA,TP,2.4X6.4	
R347	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M		R472	2001-000800	R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R348	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		R473	2001-000800	R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R349	2001-000252	R-CARBON:1.6KOHM,5%,1/8W,AA,TP,1.8X3.2M		R474	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R350	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2M		R474A	2001-000508	R-CARBON:220KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R351	2001-001178	R-CARBON(S):680OHM,5%,1/2W,AA,TP,2.4X6.4		R475	2001-000977	R-CARBON:8.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R352	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm		R475A	2001-000411	R-CARBON:18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R353	2001-000890	R-CARBON:6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		R475B	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R354	2001-000890	R-CARBON:6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		R477	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R355	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		R479	2001-000005	R-CARBON:390ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R357	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R480	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R358	2001-000837	R-CARBON:51KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R481	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R359	2001-000766	R-CARBON:43KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R482	2001-001031	R-CARBON:91KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R360	2001-000857	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		R483	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R361	2001-001191	R-CARBON(S):820KOHM,5%,1/2W,AA,TP,2.4X6.		R484	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R362	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R485	2008-001096	R-FUSIBLE(S):3.3OHM,5%,1/2W,AC,BK,2.5X6.	
R363	2001-000723	R-CARBON:4.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		R487	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R364	2001-000938	R-CARBON:68OHM,5%,1/8W,AA,TP,1.8X3.2MM		R489	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R365	2001-001120	R-CARBON(S):3.3OHM,5%,1/2W,AA,TP,2.4X6.4		R490	2001-000723	R-CARBON:4.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R366	2001-000109	R-CARBON(S):470OHM,5%,1/2W,AA,TP,2.4X6.4		R491	2001-001178	R-CARBON(S):680OHM,5%,1/2W,AA,TP,2.4X6.4	
R367	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.		R492	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R368	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.		R493	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R369	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.		R494	2001-000066	R-CARBON(S):10KOHM,5%,1/2W,AA,TP,2.4X6.4	
R369A	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.		R495	2001-000037	R-CARBON(S):330OHM,5%,1/2W,AA,TP,2.4X6.4	
R370	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.		R496	2001-000347	R-CARBON:13KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R371	2001-001065	R-CARBON(S):110KOHM,5%,1/2W,AA,TP,2.4X6.		R497	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R372	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.		R498	2001-001165	R-CARBON(S):560OHM,5%,1/2W,AA,TP,2.4X6.4M	
R373	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.					
R374	2001-001110	R-CARBON(S):240KOHM,5%,1/2W,AA,TP,2.4X6.					
R375	2001-001113	R-CARBON(S):270KOHM,5%,1/2W,AA,TP,2.4X6.					
R376	2001-000613	R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R377	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5					
R378	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5					
R379	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5					
R380	2004-001892	R-METAL(S):162Kohm,1%,1/2W,AA,TP,2.5x6.5		CNP01	3711-002704	CONNECTOR-HEADER:NOWALL,6P,1R,2.5mm,ANGL	
R381	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M		CNT01	3711-002702	CONNECTOR-HEADER:NOWALL,4P,1R,2.5mm,ANGL	
R384	2001-001150	R-CARBON(S):470KOHM,5%,1/2W,AA,TP,2.4X6.		CNT02	3711-002703	CONNECTOR-HEADER:NOWALL,5P,1R,2.5mm,ANGL	
R385	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CNT03	3711-002705	CONNECTOR-HEADER:NOWALL,7P,1R,2.5mm,ANGL	
R386	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CP01	2401-000404	C-AL:10uF,20%,16V,BP,TP,5x11.5	
R387	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CP02	2401-000404	C-AL:10uF,20%,16V,BP,TP,5x11.5	
R388	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CP03	2401-000404	C-AL:10uF,20%,16V,BP,TP,5x11.5	
R389	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CP04	2203-002392	C-CERAMIC,CHIP:220nF,+80-20%,50V,Y5V,TP	
R395	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		CP05	2203-002392	C-CERAMIC,CHIP:220nF,+80-20%,50V,Y5V,TP	
R397	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CP06	2203-002392	C-CERAMIC,CHIP:220nF,+80-20%,50V,Y5V,TP	
R412	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M		CP07	2203-002392	C-CERAMIC,CHIP:220nF,+80-20%,50V,Y5V,TP	
R413	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM		CP08	2203-002392	C-CERAMIC,CHIP:220nF,+80-20%,50V,Y5V,TP	
R414	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CP09	2203-002392	C-CERAMIC,CHIP:220nF,+80-20%,50V,Y5V,TP	
R415	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M		CP10	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11.5	
R416	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2M		CP11	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP	
R420	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		CP12	2203-000323	C-CERAMIC,CHIP:12nF,10%,50V,X7R,TP,2012	
R421	2003-002159	R-METALOXIDE:150OHM,5%,1W,AG,TP,4.3X12M		CP13	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP	
R422	2001-001163	R-CARBON(S):560OHM,5%,1/2W,AA,TP,2.4X6.4		CP14	2401-001513	C-AL:47uF,20%,16V,WT,TP,5x11.5	
R423	2001-000869	R-CARBON:560OHM,5%,1/8W,AA,TP,1.8X3.2MM		CP15	2203-000716	C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012	
R425	2003-002163	R-METALOXIDE(S):1.2KOHM,5%,3W,AG,TP,6X1		CP16	2203-002442	C-CERAMIC,CHIP:330nF,+80-20%,25V,Y5V,TP	
R437	2008-001087	R-FUSIBLE(S):1.8ohm,5%,2W,AG,TP,3.9x1.2mm		CP19	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP	
R438	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.		CP20	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP	
R439	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.		CP21	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP	
R442	2008-000253	R-FUSIBLE(S):0.47ohm,5%,1W,AF,TP,3.9x1.0m		CP22	2203-001105	C-CERAMIC,CHIP:6.8nF,10%,50V,X7R,TP,2012	
R442A	2008-000204	R-FUSIBLE(S):0.22ohm,10%,1/2W,AF,TP,2.5x		CP23	2203-000609	C-CERAMIC,CHIP:22nF,10%,50V,X7R,TP,2012	
R443	2003-002156	R-METALOXIDE:560OHM,5%,2W,AG,TP,6X16MM		CP24	2203-000192	C-CERAMIC,CHIP:120nF,+80-20%,50V,Y5V,TP	
R443A	2003-002156	R-METALOXIDE:560OHM,5%,2W,AG,TP,6X16MM		CP25	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012	
R445	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		CP26	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11.5	
R446	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CP27	2203-000429	C-CERAMIC,CHIP:0.018nF,5%,50V,NPO,TP,201	
R447	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M		CP28	2203-000429	C-CERAMIC,CHIP:0.018nF,5%,50V,NPO,TP,201	
R448	2001-000411	R-CARBON:18KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CP29	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11.5	
R449	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CP30	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP	
R450	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CP31	2401-000242	C-AL:100uF,20%,10V,GP,TP,5x11.5	
R451	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M		CP32	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP	
R452	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		CP33	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012	
R454	2001-000761	R-CARBON:430OHM,5%,1/8W,AA,TP,1.8X3.2MM		CP34	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11.5	
R455	2001-000761	R-CARBON:430OHM,5%,1/8W,AA,TP,1.8X3.2MM		CP35	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP	
R456	2001-000761	R-CARBON:430OHM,5%,1/8W,AA,TP,1.8X3.2MM		CP36	2203-000609	C-CERAMIC,CHIP:22nF,10%,50V,X7R,TP,2012	
R458	2001-000577	R-CARBON:2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CP37	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11.5	
R459	2001-001192	R-CARBON(S):820OHM,5%,1/2W,AA,TP,2.4X6.4		CP38	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012	
				CP39	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP	

ASSY-PCB,PIP

* AA95-00151BASSY-PCB,PIP,-,PCJ522R,P51A,-,-,TDA8601

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
C237	2401-002299	C-AL:4.7uF,20%,50V,GP,TP,5x7.5		R215	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
C238	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11.5		R216	2004-001983	R-METAL(S):2.49Kohm,1%,1/2W,AA,TP,2.4x6.	
C239	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,		R217	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C240	2201-000247	C-CERAMIC,DISC:15pF,5%,50V,CH,TP,5x3.5		R219	2001-000028	R-CARBON(S):1000HM,5%,1/2W,AA,TP,2.4X6.4	
C241	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		R220	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm	
C242	2401-001537	C-AL:47uF,20%,25V,GP,TP,6.3x7mm,5mm		R221	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
C243	2401-000311	C-AL:100uF,20%,25V,GP,TP,8x9mm,5mm		R222	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
C244	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		R223	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
C245	2401-000404	C-AL:10uF,20%,16V,BP,TP,5x11.5		R224	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
C246	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3.5		R225	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C247	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		R226	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C248	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		R229	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
C249	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm		R230	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C250	2401-001537	C-AL:47uF,20%,25V,GP,TP,6.3x7mm,5mm		R231	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C251	2401-001537	C-AL:47uF,20%,25V,GP,TP,6.3x7mm,5mm		R232	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
C254	2401-001537	C-AL:47uF,20%,25V,GP,TP,6.3x7mm,5mm		R233	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C255	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		R234	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C256	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		R235	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
C257	2401-001537	C-AL:47uF,20%,25V,GP,TP,6.3x7mm,5mm		R236	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
C258	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3.5		R237	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C259	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3.5		R238	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CN201	3711-003543	CONNECTOR-HEADER:NOWALL,16P,1R,2.54MM,ANG		R239	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
CN202	3711-001283	CONNECTOR-HEADER:NOWALL,14P,1R,2.5mm,ANG		R240	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
CN203	3711-001283	CONNECTOR-HEADER:NOWALL,14P,1R,2.5mm,ANG		R241	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CN204	3711-001283	CONNECTOR-HEADER:NOWALL,14P,1R,2.5mm,ANG		R243	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
D202	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R244	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
D203	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R245	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
D204	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R246	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
D205	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R247	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
D206	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R248	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
D207	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R249	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
D208	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R250	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
D209	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R251	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
D210	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R252	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
D211	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R253	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
D212	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R254	2001-000411	R-CARBON:18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
D215	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		R255	2004-001970	R-METAL:1.8Kohm,1%,1/2W,AA,TP,6.5x2.5m	
DZ201	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m		R256	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ202	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R257	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ203	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		R258	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ204	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		R259	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ206	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		R260	2001-000761	R-CARBON:430OHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ207	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		R261	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ208	0403-000655	DIODE-ZENER:MTZ13A,13V,12.11-12.75V,500m		R262	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ209	0403-000655	DIODE-ZENER:MTZ13A,13V,12.11-12.75V,500m		R263	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
DZ210	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		R264	2004-002016	R-METAL(S):15Kohm,1%,1/2W,AA,TP,2.5x6.5m	
△ IC201	1204-001207	IC-CHROMA,CXA2095S,DIP,48P,-,PLASTIC,12V		R265	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
△ IC202	1204-001142	IC-VIDEO SYSTEM:TDA9177,DIP,24P,-,PLASTI		R266	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
△ IC203	1201-001522	IC-VIDEOAMP:2210,DIP,8P,-,DUAL,-,PLASTI		R267	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
△ IC204	0801-000961	IC-CMOSLOGIC:4053,MUTIPLEXER,DIP,16P,30		R268	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
△ IC206	0801-000961	IC-CMOSLOGIC:4053,MUTIPLEXER,DIP,16P,30		R269	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
L201	2701-000116	INDUCTOR-AXIAL:10uH,10%,4.2x9.8mm		R270	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
L203	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		R271	2001-000995	R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
PCB	AA41-00134APCB-CHROMA MOL:P51A,2L,FR-4,245X245X1.6T			R272	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q201	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R273	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q202	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R274	2001-000633	R-CARBON:30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q203	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R275	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
Q205	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R276	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
Q206	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R277	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
Q207	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R278	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q208	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R279	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q209	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R285	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
Q210	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R290	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R201	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM		R291	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R202	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM		R292	2001-000947	R-CARBON:7.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R203	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM		SHIELD	AA63-00100ASHIELD-CASE:-,SPTE,0.5,SCAN-MODULE,FCC		
R204	2001-000214	R-CARBON:1.1KOHM,5%,1/8W,AA,TP,1.8X3.2M		X201	2801-000226	CRYSTAL-UNIT:3.579545MHz,20ppm,28-AAM,15	
R205	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M		X202	2802-000169	RESONATOR-CERAMIC:500KHz,2KHz,BK,7.0x3.5	
R206	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R207	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R208	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R209	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM					
R210	2001-000645	R-CARBON:330KOHM,5%,1/8W,AA,TP,1.8X3.2M					
R211	2004-002016	R-METAL(S):15Kohm,1%,1/2W,AA,TP,2.5x6.5m					
R212	2004-004045	R-METAL(S):390ohm,1%,1/2W,AA,TP,2.5x6.5m					
R213	2001-000890	R-CARBON:6.8KOHM,5%,1/8W,AA,TP,1.8X3.2M		BKV01	AA61-10068ABRACKET-PCB:-,M2160,SPTE,TO.3,-,-,-		
R214	2001-000262	R-CARBON:1.8MOHM,5%,1/8W,AA,TP,1.8X3.2M		CNV01	3711-002706	CONNECTOR-HEADER:NOWALL,8P,1R,2.5mm,ANGL	
				CV01	2401-000444	C-AL:10uF,20%,25V,GP,TP,5x5mm,5mm	

ASSY-PCB,H/V BLK

* AA95-00441AASSY-PCB,H/V BLK:-,PCJ522R,P51A,-,-,-

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
CV02	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm		C155	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
CV03	2401-001914	C-AL:1uF,20%,50V,BP,TP,5x11,5		C156	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
CV04	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X		C157	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
CV05	2301-000247	C-FILM,PEF:33nF,5%,50V,TP,8.1x4.5x13mm,5		C158	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
CV06	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		C159	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
DZV01	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m		C160	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
△ICV01	0801-000659	IC-CMOSLOGIC:74HC123,MULTIVIBATOR,DIP,1		C161	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Z5U,TP,2012	
LV01	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		C162	2203-001077	C-CERAMIC,CHIP:0.056nF,5%,50V,NPO,TP,201	
LV02	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm		C163	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm	
LV03	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		C164	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
PCB	AA41-00190	PCB-H/V, BLK:P51A, 1L,FR-1,245x245x1.6T,20		C165	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
QV01	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		C166	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm	
RV01	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C167	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
RV02	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C168	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
RV03	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2M		C169	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Z5U,TP,2012	
RV04	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C170	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm	
RV05	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C171	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
RV06	2001-000563	R-CARBON:27KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C172	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
RV07	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C173	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm	
RV09	2001-000904	R-CARBON:620OHM,5%,1/8W,AA,TP,1.8X3.2MM		C174	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
RV11	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C175	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
RV12	2004-000218	R-METAL:10Kohm,1%,1/8W,AA,TP,1.8x3.2mm		C176	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm	
RV13	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C177	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
				C178	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
				C179	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm	
				C180	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
				C181	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
				C182	2203-001077	C-CERAMIC,CHIP:0.056nF,5%,50V,NPO,TP,201	
				C183	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
				C184	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
				C185	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
				C186	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
				C187	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Z5U,TP,2012	
				C188	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
				C189	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
				C190	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Z5U,TP,2012	
				C191	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
				C192	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
				C193	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm	
				C194	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Z5U,TP,2012	
				C195	2404-000275	C-TA,CHIP:100UF,10%,10V,GP,TP,7343	
				C196	2203-000634	C-CERAMIC,CHIP:0.022nF,5%,50V,NPO,TP,201	
				C197	2203-000634	C-CERAMIC,CHIP:0.022nF,5%,50V,NPO,TP,201	
				C198	2203-000634	C-CERAMIC,CHIP:0.022nF,5%,50V,NPO,TP,201	
				C199	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5	
				C201	2404-000256	C-TA,CHIP:47UF,20%,16V,GP,TP,7343	
				C202	2203-000683	C-CERAMIC,CHIP:0.027nF,5%,50V,NPO,TP,201	
				C203	2203-000429	C-CERAMIC,CHIP:0.018nF,5%,50V,NPO,TP,201	
				C204	2203-001002	C-CERAMIC,CHIP:0.047nF,5%,50V,NPO,TP,201	
				C205	2203-001002	C-CERAMIC,CHIP:0.047nF,5%,50V,NPO,TP,201	
				C206	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm	
				C207	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Z5U,TP,2012	
				C208	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
				C210	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm	
				C220	2203-001002	C-CERAMIC,CHIP:0.047nF,5%,50V,NPO,TP,201	
				C301	2203-000634	C-CERAMIC,CHIP:0.022nF,5%,50V,NPO,TP,201	
				C302	2203-000634	C-CERAMIC,CHIP:0.022nF,5%,50V,NPO,TP,201	
				C303	2203-000634	C-CERAMIC,CHIP:0.022nF,5%,50V,NPO,TP,201	
				CN001	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG	
				CN002	3711-002708	CONNECTOR-HEADER:NOWALL,10P,1R,2.5MM,ANG	
				CP101	2901-000233	FILTER-EMISMD:50V,300mA,-,330pF,4.5x1.8	
				CP102	2901-000233	FILTER-EMISMD:50V,300mA,-,330pF,4.5x1.8	
				CP103	2901-000229	FILTER-EMISMD:50V,300mA,-,22nF,4.5x1.8x	
				CP104	2901-000229	FILTER-EMISMD:50V,300mA,-,22nF,4.5x1.8x	
				CP105	2901-000229	FILTER-EMISMD:50V,300mA,-,22nF,4.5x1.8x	
				CP106	2901-000229	FILTER-EMISMD:50V,300mA,-,22nF,4.5x1.8x	
				CP107	2901-000229	FILTER-EMISMD:50V,300mA,-,22nF,4.5x1.8x	
				CP108	2901-000232	FILTER-EMISMD:50V,300mA,-,10nF,4.5x1.8x	
				CP109	2901-000232	FILTER-EMISMD:50V,300mA,-,10nF,4.5x1.8x	
				CP110	2901-000232	FILTER-EMISMD:50V,300mA,-,10nF,4.5x1.8x	
				CP120	2901-000226	FILTER-EMISMD:25V,200mA,-,100pF,3.2x1.2	
				CP121	2901-000226	FILTER-EMISMD:25V,200mA,-,100pF,3.2x1.2	
				CP122	2901-000226	FILTER-EMISMD:25V,200mA,-,100pF,3.2x1.2	
				CP123	2901-000226	FILTER-EMISMD:25V,200mA,-,100pF,3.2x1.2	
				CP124	2901-000226	FILTER-EMISMD:25V,200mA,-,100pF,3.2x1.2	
				CP125	2901-000226	FILTER-EMISMD:25V,200mA,-,100pF,3.2x1.2	
				CP126	2901-000226	FILTER-EMISMD:25V,200mA,-,100pF,3.2x1.2	

ASSY-PCB,CONV MDL

* AA95-90027 VASSY-PCB,CONV MDL-;SVP524JA,KPT51A,PAL-

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
CP127	2901-000226	FILTER-EMISMD:25V,200mA,-,100pF,3.2x1.2		Q130	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D100	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q131	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT	
D101	0405-000128	DIODE-VARACTOR:1SV214,30V,10nA,USC,TP		Q132	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D104	0403-000689	DIODE-ZENER-DTZ5.1A,5.1V,4.84-5.04V,200m		Q133	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT	
D106	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q134	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D110	0401-000008	DIODE-SWITCHING:DAN217,80V,100mA,SOT-23,		Q135	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT	
D111	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q136	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D112	0401-000008	DIODE-SWITCHING:DAN217,80V,100mA,SOT-23,		Q137	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D113	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q138	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D114	0401-000008	DIODE-SWITCHING:DAN217,80V,100mA,SOT-23,		Q139	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D115	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q140	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D116	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q141	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D117	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q142	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D200	0403-000689	DIODE-ZENER-DTZ5.1A,5.1V,4.84-5.04V,200m		Q143	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D201	0403-000689	DIODE-ZENER-DTZ5.1A,5.1V,4.84-5.04V,200m		Q144	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D203	0403-000689	DIODE-ZENER-DTZ5.1A,5.1V,4.84-5.04V,200m		Q145	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
△ IC104	1001-000105	IC-ANALOG SWITCH:CD4066BM,BILATERAL CMOS		Q146	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
△ IC106	1201-000167	IC-OPAMP:358,SOP,8P,150MIL,DUAL,100V/mV		Q200	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT	
△ IC112	AA13-30006BIC-MCU-,AT89C52-24,-,DIP,-,40P,600MI		Q201	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT		
△ IC113	1002-000131	IC-A/D&D/ACONVERTER:PCM55HP,16BIT,SOP,2		Q202	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT	
△ IC114	1002-000131	IC-A/D&D/ACONVERTER:PCM55HP,16BIT,SOP,2		Q203	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT	
△ IC115	1002-000131	IC-A/D&D/ACONVERTER:PCM55HP,16BIT,SOP,2		Q204	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT	
△ IC132	0801-001156	IC-CMOS LOGIC:74HC4066,BILATERAL SWITCH,		Q205	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT	
△ IC133	0801-001156	IC-CMOS LOGIC:74HC4066,BILATERAL SWITCH,		R100	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012	
△ IC135	1001-000105	IC-ANALOG SWITCH:CD4066BM,BILATERAL CMOS		R101	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012	
△ IC136	1001-000105	IC-ANALOG SWITCH:CD4066BM,BILATERAL CMOS		R102	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
△ IC141	1103-000139	IC-EEPROM:24C16,2KX8BIT,DIP,8P,300MIL,10		R103	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
△ IC142	1201-000480	IC-VIDEOAMP:14577,SOP,8P,150MIL,DUAL,7d		R104	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
△ IC143	AA13-10001XIC-ASIC-,DCS04,QFP,160P,CONV CONTROL		R105	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012		
L100	AA26-10001YTRANS-IF-,5CA,IF,10uH,5mm,-,2.52MHz,ST		R106	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012		
L102	2703-000248	INDUCTOR-SMD 820uH,5%,4.5x3.2x3.2mm		R107	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
L103	2703-000248	INDUCTOR-SMD 820uH,5%,4.5x3.2x3.2mm		R108	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
L104	2703-000248	INDUCTOR-SMD 820uH,5%,4.5x3.2x3.2mm		R109	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
L105	2703-000248	INDUCTOR-SMD 820uH,5%,4.5x3.2x3.2mm		R110	2007-000409	R-CHIP:15KOHM,5%,1/10W,DA,TP,2012	
L106	2703-000248	INDUCTOR-SMD 820uH,5%,4.5x3.2x3.2mm		R111	2007-000572	R-CHIP:220OHM,5%,1/10W,DA,TP,2012	
L107	2703-000248	INDUCTOR-SMD 820uH,5%,4.5x3.2x3.2mm		R112	2007-000409	R-CHIP:15KOHM,5%,1/10W,DA,TP,2012	
L108	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R113	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
L109	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R114	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
L110	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R115	2007-000830	R-CHIP:39KOHM,5%,1/10W,DA,TP,2012	
L111	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R116	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
L112	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R118	2007-000830	R-CHIP:39KOHM,5%,1/10W,DA,TP,2012	
L113	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R119	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
L121	2901-000297	FILTER-EMI ON BOARD-,3A,-,3.5x5,TP,-		R120	2007-000415	R-CHIP:150OHM,5%,1/10W,DA,TP,2012	
L122	2703-000392	INDUCTOR-SMD:10uH,5%,4.5x3.2x2.2mm		R121	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
L123	2703-000392	INDUCTOR-SMD:10uH,5%,4.5x3.2x2.2mm		R122	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
L124	2703-000392	INDUCTOR-SMD:10uH,5%,4.5x3.2x2.2mm		R123	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012	
PCB	AA41-10897PBCB-CONV:KPT51A,2L,FR-4,245x180x1.6T,A2		R125	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012		
Q100	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R130	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q101	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R131	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q102	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R132	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q103	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R133	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q104	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R134	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q105	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R135	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q106	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R136	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q107	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R137	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q108	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R138	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q109	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R139	2007-000267	R-CHIP:1.8KOHM,5%,1/10W,DA,TP,2012	
Q110	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R140	2007-000304	R-CHIP:10MOHM,5%,1/10W,DA,TP,2012	
Q111	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R141	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q112	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R150	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
Q113	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R151	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q114	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R152	2007-000493	R-CHIP:2.2KOHM,5%,1/10W,DA,TP,2012	
Q115	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R153	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q116	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R154	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
Q117	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R155	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q118	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R157	2007-001166	R-CHIP:750OHM,5%,1/10W,DA,TP,2012	
Q119	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R158	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
Q120	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R159	2007-000221	R-CHIP:1.2KOHM,5%,1/10W,DA,TP,2012	
Q121	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R160	2007-000300	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012	
Q122	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R161	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q123	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R162	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q124	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R163	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q125	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R164	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
Q126	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R165	2007-000380	R-CHIP:13KOHM,5%,1/10W,DA,TP,2012	
Q127	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R168	2007-000653	R-CHIP:27KOHM,5%,1/10W,DA,TP,2012	
Q128	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R170	2007-000029	R-CHIP:0OHM,5%,1/10W,DA,TP,2012	
Q129	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT		R172	2007-000029	R-CHIP:0OHM,5%,1/10W,DA,TP,2012	

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
HDRM	AA61-20101	BHOLDER-MASK,AL,-,S4388,ABS,HB,BLK,-		CV10	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
HDRM	AA61-20124	AHOLDER-MASK,B,-,S4388,ABS,HB,BLK,-		CV11	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
HDRR	AA61-00094	BHOLDER-RAIL,-,PCJ533R,ABS,HB,BLK,240		CV12	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
HDRR	AA61-00094	CHOLDER-RAIL,-,PCJ533R,ABS,HB,BLK,480		CV13	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
LEAD	AA39-00005	BLEAD CONNECTOR-ASSY,-,YSH250-04,REC,REC,		CV14	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
SPK	3001-000176	SPEAKER:30W,80HM,93DB+2DB,65HZ		CV15	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
SPK	3001-001107	SPEAKER:20W,80HM,95+2DB,1300HZ		CV16	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
SPK+CM	AA60-10051	ASCREW-WOOD:PH,+,M4,L16,ZPC(BLK),SWRCH18A		CV17	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
WOOD	AA64-00263	FINLAY-FORM:SP53J2,WOOD,PVC FORM,T2,BLK,W		CV18	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV19	2401-001840	C-AL:100uF,20%,16V,GP,TP,6,3x11,5	
				CV20	2201-000180	C-CERAMIC,DISC:10nF,10%,50V,Y5V,TP,6,5*3	
				CV22	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV24	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV25	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV26	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV27	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5	
				CV28	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5	
				CV29	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5	
				CV31	2401-000471	C-AL:10uF,20%,50V,BP,TP,5x11,5mm	
				CV32	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV33	2401-000471	C-AL:10uF,20%,50V,BP,TP,5x11,5mm	
				CV34	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV35	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV36	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV37	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV38	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV39	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
				CV40	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7mm,5mm	
				CV41	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7mm,5mm	
				CV42	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6	
				CV49	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
				DZ601	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
				DZ602	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
				DZ603	0403-000701	DIODE-ZENER:TZP5,1A,5,1V,4.8-5,4V,1W,DO-	
				DZV01	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				DZV04	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				DZV07	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				DZV09	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				DZV11	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				DZV13	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				DZV15	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				DZV17	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				DZV19	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				DZV23	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				DZV24	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				DZV25	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
				△IC601	1204-001222	IC-AUDIOPROCESSOR:TDA7429,DIP,44P,-,PLA	
				△IC602	1201-000191	IC-OPAMP:4558,DIP,8P,300MIL,DUAL,20V/mV	
				△IC905	0904-000121	IC-I/O SUPPORT CHIP:8574,8BIT,DIP,16P,30	
				△ICV01	1001-000212	IC-VIDEOSWITCH:TA8851AN,-,DIP,54P,-,-	
				△ICV02	0801-000961	IC-CMOSLOGIC:4053,MULTIPLEXER,DIP,16P,30	
				△ICV03	0801-000961	IC-CMOSLOGIC:4053,MULTIPLEXER,DIP,16P,30	
				L601	2701-000115	INDUCTOR-AXIAL:10uH,10%,2,8x7mm	
				LV01	2701-000116	INDUCTOR-AXIAL:10uH,10%,4,2x9.8mm	
				PCB	AA41-00020	PCB-TERMINAL:P51A,2L,FR-4,180X245X1.6T,1	
				QV01	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				QV02	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
				QV05	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				QV06	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				QV07	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
				R601	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R602	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R603	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R604	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R605	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R606	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R609	2001-000878	R-CARBON:6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R610	2001-000878	R-CARBON:6.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R611	2001-001102	R-CARBON(S):200OHM,5%,1/2W,AA,TP,2.4X6.4	
				R612	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R613	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R614	2001-000313	R-CARBON:11KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R615	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4	
				R616	2001-001187	R-CARBON(S):75OHM,5%,1/2W,AA,TP,2.4X6.4MM	
				R617	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R618	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
				R619	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	

REMOCON

* AA59-00096AREMOCON-AMERICA, TM57, KS88P0416S, 45, L/G

△ ICMCU
RESONAA13-00062AIC-MCU,-,SZM-828(R4385),16BIT,SOP,E-2
2802-000194 RESONATOR-CERAMIC:8MHz,1.0%,TP,8.5x4.5x5

ASSY-PCB,TERMINAL

* AA95-00057DASSY-PCB,TERMINAL,-,PCJ522R/XAA,P51A,-,-

C601	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C602	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5	
C603	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5	
C604	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm	
C605	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m	
C606	2301-000104	C-FILM,PEF:1.2nF,5%,50V,TP,6.5x3.0x5.5mm	
C607	2301-000289	C-FILM,PEF:5.6nF,5%,50V,TP,7x6x3,5	
C608	2305-001023	C-FILM,MPEF:680nF,10%,63V,TP,7.5x5.5x14.	
C609	2401-000647	C-AL:2.2uF,20%,50V,BP,TP,5x11,5	
C610	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5	
C611	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5	
C612	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m	
C613	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m	
C614	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,5	
C615	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m	
C616	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m	
C617	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5	
C618	2301-000395	C-FILM,PEF:18nF,5%,50V,TP,6.5x12.5x3.5mm	
C619	2301-000224	C-FILM,PEF:22nF,5%,50V,TP,7.4x3.9x13mm,5	
C620	2301-000395	C-FILM,PEF:18nF,5%,50V,TP,6.5x12.5x3.5mm	
C621	2301-000289	C-FILM,PEF:5.6nF,5%,50V,TP,7x6x3,5	
C622	2301-000289	C-FILM,PEF:5.6nF,5%,50V,TP,7x6x3,5	
C623	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C624	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C625	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5	
C626	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5	
C627	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5	
C628	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5	
C629	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C630	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C631	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m	
C632	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12,5,5	
C633	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm	
C634	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C635	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C636	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C637	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C638	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm	
C707	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
C930	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7mm,5mm	
C931	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6	
CLAMPW	AA65-30105	BCLAMP-WIRE:NYLON 66,V2,NTR,25MM,ALL MODE	
CNT01	3711-003630	CONNECTOR-HEADER:BOX,32P,2R,2.54mm,ANGLE	
CNT02	3711-003630	CONNECTOR-HEADER:BOX,32P,2R,2.54mm,ANGLE	
CNY02	3711-003601	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,ANGLE,	
CV01	2401-002009	C-AL:100uF,20%,16V,GP,TP,6,3x7,5	
CV02	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6	
CV03	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12,5,5	
CV04	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
CV05	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
CV06	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
CV07	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
CV08	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
CV09	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	

Loc. No.	Code No.	Description : Specification	Remark
R620	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R621	2001-001187	R-CARBON(S):75OHM,5%,1/2W,AA,TP,2.4X6.4M	
R622	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
R623	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R624	2001-000313	R-CARBON:11KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R625	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R985	2001-001102	R-CARBON(S):2000HM,5%,1/2W,AA,TP,2.4X6.4M	
R986	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R987	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R988	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R990	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R992	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R993	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R994	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RN902	2011-000160	R-NETWORK:10K,5%,1/8W,A,SIP,9P,TP	
RV01	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RV02	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
RV03	2001-001066	R-CARBON(S):110OHM,5%,1/2W,AA,TP,2.4X6.4M	
RV04	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
RV05	2001-000117	R-CARBON(S):680HM,5%,1/2W,AA,TP,2.4X6.4M	
RV06	2001-001050	R-CARBON(S):1.5KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV07	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M	
RV08	2001-001187	R-CARBON(S):75OHM,5%,1/2W,AA,TP,2.4X6.4M	
RV09	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV10	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV11	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M	
RV12	2001-001187	R-CARBON(S):75OHM,5%,1/2W,AA,TP,2.4X6.4M	
RV13	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV14	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV15	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M	
RV16	2001-001187	R-CARBON(S):75OHM,5%,1/2W,AA,TP,2.4X6.4M	
RV17	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV18	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M	
RV19	2001-001187	R-CARBON(S):75OHM,5%,1/2W,AA,TP,2.4X6.4M	
RV20	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV21	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M	
RV22	2001-001187	R-CARBON(S):75OHM,5%,1/2W,AA,TP,2.4X6.4M	
RV23	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV24	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M	
RV25	2001-001187	R-CARBON(S):75OHM,5%,1/2W,AA,TP,2.4X6.4M	
RV26	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV27	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M	
RV28	2001-001187	R-CARBON(S):75OHM,5%,1/2W,AA,TP,2.4X6.4M	
RV30	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M	
RV32	2001-000019	R-CARBON(S):100HM,5%,1/2W,AA,TP,2.4X6.4M	
RV34	2001-001185	R-CARBON(S):750OHM,5%,1/2W,AA,TP,2.4X6.4M	
RV35	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV36	2001-001185	R-CARBON(S):750OHM,5%,1/2W,AA,TP,2.4X6.4M	
RV37	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV38	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
RV39	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
RV40	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
RV41	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
RV46	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RV47	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
RV48	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RV49	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
RV50	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
RV51	2001-000281	R-CARBON:1000HM,5%,1/8W,AA,TP,1.8X3.2MM	
RV53	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV54	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV55	2001-000085	R-CARBON(S):100KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV65	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV66	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV67	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV68	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV69	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV70	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV71	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV80	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	
RV81	2001-001088	R-CARBON(S):1KOHM,5%,1/2W,AA,TP,2.4X6.4M	

ASSY-PCB,CRT

* AA95-00129DASSY-PCB,CRT,-,P51A,PCJ522R,USA,-

Loc. No.	Code No.	Description : Specification	Remark
BCKTR	AA61-10060	ABRACKET-TR,-,-,CUS-1 1/2H,T0.5,-,-,-	
BDW-GN	AA39-20009	GLEAD-CONNECTOR,ASSY:-,YFH800-01,-,1P,700	
C501	2201-000961	C-CERAMIC,DISC:10pF,0.5pF,50V,RH,TP,5x3mm	
C502	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11.5	
C503	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
C504	2401-001537	C-AL:47uF,20%,25V,GP,TP,6.3x7mm,5mm	
C505	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5	
C506	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5mm	
C507	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11	
C510	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5mm	
C511	2201-000969	C-CERAMIC,DISC:10nF,+80-20%,3KV,Y5V,TP,-	
C512	2401-000133	C-AL:1000uF,20%,16V,GP,TP,10x20.5	
C513	2201-000983	C-CERAMIC,DISC:1nF,10%,2KV,Y5P,TP,13x6.7	
C514	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4	
C531	2201-000961	C-CERAMIC,DISC:10pF,0.5pF,50V,RH,TP,5x3mm	
C532	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11.5	
C533	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
C534	2401-001537	C-AL:47uF,20%,25V,GP,TP,6.3x7mm,5mm	
C535	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5	
C536	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5mm	
C537	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11	
C540	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5mm	
C541	2201-000969	C-CERAMIC,DISC:10nF,+80-20%,3KV,Y5V,TP,-	
C542	2201-000983	C-CERAMIC,DISC:1nF,10%,2KV,Y5P,TP,13x6.7	
C543	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4	
C561	2201-000247	C-CERAMIC,DISC:15pF,5%,50V,CH,TP,5x3,5	
C562	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11.5	
C563	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,	
C564	2401-001537	C-AL:47uF,20%,25V,GP,TP,6.3x7mm,5mm	
C565	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5	
C566	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5mm	
C567	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11	
C570	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5mm	
C571	2201-000969	C-CERAMIC,DISC:10nF,+80-20%,3KV,Y5V,TP,-	
C572	2201-000983	C-CERAMIC,DISC:1nF,10%,2KV,Y5P,TP,13x6.7	
C573	2201-000599	C-CERAMIC,DISC:560pF,10%,500V,Y5P,TP,7x4	
CFILM	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0mm	
CN401	3711-002645	CONNECTOR-HEADER BOX,6P,1R,2.5MM,STRAIGH	
CN501	3711-002647	CONNECTOR-HEADER BOX,8P,1R,2.5mm,STRAIGH	
CN502	3711-002641	CONNECTOR-HEADER BOX,10P,1R,2.54mm,STRAI	
CN502B	3711-002641	CONNECTOR-HEADER BOX,10P,1R,2.54mm,STRAI	
CN503	3711-002641	CONNECTOR-HEADER BOX,10P,1R,2.54mm,STRAI	
CN503B	3711-002641	CONNECTOR-HEADER BOX,10P,1R,2.54mm,STRAI	
CNW401	AA39-20027	BLEAD-CONNECTOR,ASSY:-,67096-006,S,6P,400	
CNW501	AA39-20030	BLEAD-CONNECTOR,ASSY:-,67096-008,S,8P,400	
CNW502	AA39-20025	CLEAD-CONNECTOR,ASSY:-,67096-010,S,10P,30	
CNW503	AA39-20025	CLEAD-CONNECTOR,ASSY:-,67096-010,S,10P,30	
CORE	3301-001201	CORE-FERRITE-AE,230.5x10.25x36mm,1500,28	
D501	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D502	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D503	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
D504	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
D509	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
D510	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,	
D531	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D532	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D533	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
D561	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D562	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
D563	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
DZ501	0403-000546	DIODE-ZENER:MTZ3.6B,3.6V,3.6-3.845V,500m	
DZ502	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m	
DZ503	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m	
DZ531	0403-000546	DIODE-ZENER:MTZ3.6B,3.6V,3.6-3.845V,500m	
DZ532	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m	
DZ533	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m	
DZ561	0403-000546	DIODE-ZENER:MTZ3.6B,3.6V,3.6-3.845V,500m	
DZ562	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m	
DZ563	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m	
FOCUS-	AA39-20115	ALEAD-CONNECTOR,ASSY:-,BUSHING,-,1P,500,3	
FOCUS-	AA39-20111	ALEAD-CONNECTOR,ASSY:-,BUSHING,-,1P,500,3	
FOCUS-	AA39-20115	ALEAD-CONNECTOR,ASSY:-,BUSHING,-,1P,700MM	

Loc. No.	Code No.	Description : Specification	Remark	Loc. No.	Code No.	Description : Specification	Remark
CD29	2203-000818	C-CERAMIC,CHIP:0.033nF,5%,50V,NP0,TP,201		QD21	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-	
CD30	2203-000634	C-CERAMIC,CHIP:0.022nF,5%,50V,NP0,TP,201		QD22	0501-000280	TR-SMALLSIGNAL:KSA1182,PNP,150mW,SOT-23	
CD31	2203-000609	C-CERAMIC,CHIP:22nF,10%,50V,X7R,TP,2012		QD23	0501-000280	TR-SMALLSIGNAL:KSA1182,PNP,150mW,SOT-23	
CD32	2401-001250	C-AL:4.7uF,20%,35V,GP,TP,4x5,5		RD08	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
CD33	2401-000215	C-AL:100nF,20%,50V,GP,TP,4x7mm,5mm		RD09	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
CD34	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012		RD10	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
CD35	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD11	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
CD36	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD12	2007-001141	R-CHIP:7.5KOHM,5%,1/10W,DA,TP,2012	
CD37	2203-000839	C-CERAMIC,CHIP:0.39nF,5%,50V,NP0,TP,2012		RD13	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
CD38	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD14	2007-000030	R-CHIP:560OHM,5%,1/10W,DA,TP,2012	
CD39	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD15	2007-000030	R-CHIP:560OHM,5%,1/10W,DA,TP,2012	
CD41	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD16	2007-000981	R-CHIP:5.6KOHM,5%,1/10W,DA,TP,2012	
CD42	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD17	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
CD43	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD18	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
CD44	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD19	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
CD45	2401-002212	C-AL:10uF,20%,25V,WT,TP,5x11,5.0mm		RD20	2007-000221	R-CHIP:1.2KOHM,5%,1/10W,DA,TP,2012	
CD46	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD22	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
CD47	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD23	2007-000030	R-CHIP:560OHM,5%,1/10W,DA,TP,2012	
CD50	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD25	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
CD51	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD26	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
CD52	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD28	2007-000518	R-CHIP:2.7KOHM,5%,1/10W,DA,TP,2012	
CD53	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD29	2007-000642	R-CHIP:270OHM,5%,1/10W,DA,TP,2012	
CD54	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD30	2007-001177	R-CHIP:8.2KOHM,5%,1/10W,DA,TP,2012	
CD55	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012		RD31	2007-000241	R-CHIP:1.5KOHM,5%,1/10W,DA,TP,2012	
CD56	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD32	2007-000493	R-CHIP:2.2KOHM,5%,1/10W,DA,TP,2012	
CD57	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD33	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012	
CD58	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD34	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012	
CD59	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD35	2007-000572	R-CHIP:220OHM,5%,1/10W,DA,TP,2012	
CD60	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD36	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012	
CD62	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD37	2007-000572	R-CHIP:220OHM,5%,1/10W,DA,TP,2012	
CD63	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD40	2007-000493	R-CHIP:2.2KOHM,5%,1/10W,DA,TP,2012	
CD64	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD41	2007-000931	R-CHIP:470OHM,5%,1/10W,DA,TP,2012	
CD66	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD42	2007-000593	R-CHIP:220OHM,5%,1/10W,DA,TP,2012	
CD67	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD43	2007-000931	R-CHIP:470OHM,5%,1/10W,DA,TP,2012	
CD68	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD44	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
CD69	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD45	2007-001001	R-CHIP:510OHM,5%,1/10W,DA,TP,2012	
CD71	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD46	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
CD72	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD47	2007-000477	R-CHIP:1MOHM,5%,1/10W,DA,TP,2012	
CD73	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD48	2007-000931	R-CHIP:470OHM,5%,1/10W,DA,TP,2012	
CD74	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD51	2007-000401	R-CHIP:150OHM,5%,1/10W,DA,TP,2012	
CD75	2203-000634	C-CERAMIC,CHIP:0.022nF,5%,50V,NP0,TP,201		RD52	2007-000221	R-CHIP:1.2KOHM,5%,1/10W,DA,TP,2012	
CD77	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD53	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
CD78	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		RD54	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
CD79	2401-001496	C-AL:47uF,20%,16V,GP,TP,5x7,5		RD55	2007-000401	R-CHIP:150OHM,5%,1/10W,DA,TP,2012	
CD80	2203-000661	C-CERAMIC,CHIP:0.27nF,5%,50V,NP0,TP,2012		RD56	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
CON01	3711-002705	CONNECTOR-HEADER-NOWALL,7P,1R,2.5mm,ANGL		RD57	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
CON02	3711-002703	CONNECTOR-HEADER-NOWALL,5P,1R,2.5mm,ANGL		RD58	2007-000267	R-CHIP:1.8KOHM,5%,1/10W,DA,TP,2012	
DD01	0403-000355	DIODE-ZENER-UZ5.1BSB,5.1V,4.97-5.18V,500		RD59	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012	
DD02	0403-000355	DIODE-ZENER-UZ5.1BSB,5.1V,4.97-5.18V,500		RD61	2007-000380	R-CHIP:13KOHM,5%,1/10W,DA,TP,2012	
DD03	0401-000005	DIODE-SWITCHING:1N4148,100V,200MA,DO-35,		RD62	2007-001071	R-CHIP:6.8KOHM,5%,1/10W,DA,TP,2012	
FD01	2909-001051	FILTER-LC:6MHz,6MHz,1.0dB,TP,5dB/6.0MHz,		RD63	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
FD02	2909-001052	FILTER-LC:3.58MHz,3MHz,1.5dB,TP,11dB/1.0		RD64	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
FD03	2909-001051	FILTER-LC:6MHz,6MHz,1.0dB,TP,5dB/6.0MHz,		RD65	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
△ IC01	1204-001210	IC-SEPARATOR:6488,QFP,100P,-,PLASTIC,5.0		RD66	2007-000738	R-CHIP:30KOHM,5%,1/10W,DA,TP,2012	
△ IC02	1209-001075	IC-PLL-UPC1862GS,SOP,36P,300MIL,PLAST		RD67	2007-001071	R-CHIP:6.8KOHM,5%,1/10W,DA,TP,2012	
△ IC03	1109-001083	IC-ETC. MEMORY:5412222,256Kx12BIT,TSOP,4		RD68	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
△ IC04	1203-001419	IC-VOLTAGEREGULATOR:4931,TO-252,3P,6.6x		RD69	2007-000931	R-CHIP:470OHM,5%,1/10W,DA,TP,2012	
LD01	2701-000184	INDUCTOR-AXIAL:4.7uH,10%,2.5x3.4mm		RD70	2007-000931	R-CHIP:470OHM,5%,1/10W,DA,TP,2012	
LD02	2701-000136	INDUCTOR-AXIAL:18uH,10%,2.5x3.4mm		RD71	2007-000267	R-CHIP:1.8KOHM,5%,1/10W,DA,TP,2012	
LD03	2701-000180	INDUCTOR-AXIAL:33uH,5%,2.5x3.4mm		RD72	2007-000931	R-CHIP:470OHM,5%,1/10W,DA,TP,2012	
LD04	2701-000180	INDUCTOR-AXIAL:33uH,5%,2.5x3.4mm		RD73	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
LD05	2701-000136	INDUCTOR-AXIAL:18uH,10%,2.5x3.4mm		RD74	2007-000493	R-CHIP:2.2KOHM,5%,1/10W,DA,TP,2012	
LD06	2701-000136	INDUCTOR-AXIAL:18uH,10%,2.5x3.4mm		RD75	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
LD07	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		RD81	2007-000380	R-CHIP:13KOHM,5%,1/10W,DA,TP,2012	
LD08	2701-000136	INDUCTOR-AXIAL:18uH,10%,2.5x3.4mm		RD82	2007-000710	R-CHIP:3.9KOHM,5%,1/10W,DA,TP,2012	
PCB	AA41-10956BPCB-3D COMB:P51A,2L,FR-4,180X245X1.6T,6A		RD83	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012		
QD09	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-		RD84	2007-000030	R-CHIP:560OHM,5%,1/10W,DA,TP,2012	
QD10	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-		RD85	2007-000981	R-CHIP:5.6KOHM,5%,1/10W,DA,TP,2012	
QD11	0501-000280	TR-SMALLSIGNAL:KSA1182,PNP,150mW,SOT-23		RD86	2007-000931	R-CHIP:470OHM,5%,1/10W,DA,TP,2012	
QD12	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-		RD87	2007-000931	R-CHIP:470OHM,5%,1/10W,DA,TP,2012	
QD13	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-		RD88	2007-000210	R-CHIP:1.1KOHM,5%,1/10W,DA,TP,2012	
QD15	0501-000280	TR-SMALLSIGNAL:KSA1182,PNP,150mW,SOT-23		RD89	2007-000781	R-CHIP:330OHM,5%,1/10W,DA,TP,2012	
QD16	0501-000280	TR-SMALLSIGNAL:KSA1182,PNP,150mW,SOT-23		RD90	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
QD17	0501-000344	TR-SMALL SIGNAL:KSC1623-G,NPN,200mW,SOT-		RD91	2007-000493	R-CHIP:2.2KOHM,5%,1/10W,DA,TP,2012	
QD18	0501-000280	TR-SMALLSIGNAL:KSA1182,PNP,150mW,SOT-23		RD92	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
QD19	0501-000280	TR-SMALLSIGNAL:KSA1182,PNP,150mW,SOT-23		RD99	2007-000029	R-CHIP:0OHM,5%,1/10W,DA,TP,2012	
QD20	0501-000280	TR-SMALLSIGNAL:KSA1182,PNP,150mW,SOT-23		XTAL01	2802-000165	RESONATOR-CERAMIC:500KHZ,0.5%,BK,10.0X5.	
				XTAL02	2801-000151	CRYSTAL-UNIT:14.31818MHz,30ppm,28-AAA,30	