

## 8. Areas and Option Specification

### 8-1 Local Specification & BOM option

Area	Country	Buyer	Model Name	Local Specification & Bom Option							Safety - Standard	Special Specification	Others	Introduction
				IF	Power ASSY	Power Code ASSY	MIC	TTX	I/B	MICOM				
S O U T H E A S T  A S I A	CHINA	SEHK	SPM5288PF/HKX	AA95-90012B	AA95-10002H L802-4:10mH L848-9:10mH	AA96-20074A CP2	APPLIED (AA95-90001V)	AA95-90003U ENG FLOP	AA68-10761A CHI	RM130ECP (ENG/CHI)	SACI	GAUSS:300mg LATING:100-260V 50/60Hz, MIC PLUG-CONV	PB1209	
	INDONESIA	SME	SPM5288PF/SMEK	AA95-90003V	AA95-10008P L802-4:2mH L848-9:10mH (2902-001001)	AA96-20074A CP2	NOT APPLIED	AA95-90003U ENG FLOF	AA68-10759A ENG AA68-10766A IND	RM130ETP (ENG/TAI/M AL/IND)		GAUSS:-200mG RATING:100-260V 50/60Hz	PB1206	OCT, 96
	SINGAPORE	S'PORE	SPM4388PF/SAPX SPM5288PF/SAPX	AA95-90003V	AA95-10002H L802-4:10mH L848-9:10mH	AA96-20074A CP2	NOT APPLIED	AA95-90003U ENG FLOF	AA68-10759A ENG	RM130ECP (ENG/CHI)	SISIR	GAUSS:-150mG LATING:230V 50Hz	PB1267 PB1208	OCT, 96
	MYANMAR	MUR	SPM5288PF/MURX	AA95-90003V	AA95-10008P L802-4:2mH L848-9:2mH (2902-001001)	AA96-20074A CP2	NOT APPLIED	AA9590003U ENG FLOF	AA68-10759A ENG	RM130ETP (ENG/TAI/ MAL/IND)		GAUSS:100mG LATING:100-260V 50/60Hz W/C, CP2	PB1207	OCT, 96
	MALAYSIA	SMARINA	SPM5288PF/MARX	AA95-90003V	AA95-10002H L802-4:10mH L848-9:10mH	AA96-20074A CP2	NOT APPLIED	AA95-90003U ENG FLOF	AA68-10759A ENG	RM130ETP (ENG/TAI/ MAL/IND)	SSIR	GAUSS:-100mG LATING:230V50Hz Same Specification as Singapore	PB1243	
	THAILAND	TSE	SPM5288PF/TSEX	AA95-90003V	AA95-10008P L802-4:2mH L848-9:2mH (2902-001001)	AA96-20052C	NOT APPLIED	AA95-90003U ENG FLOP	AA68-10759A ENG	RM130ETP (ENG/TAI/ MAL/IND)		GAUSS:100mG LATING:100-260V 50/60Hz W/C, EP2-NO	PB1244	NOV,96
	VIETNAM	SAVINA	SPM5288PF/SVIX	AA95-90003V	AA95-10008P L802-4:2mH L848-9:2mH (2902-001001)	AA96-20074A CP2	NOT APPLIED	AA95-90003U ENG FLOF	AA68-10759A ENG	RM130ETP (ENG/TAI/ MAL/IND)		GAUSS:100mG LATING:100-260V 50/60Hz W/C	PB1241	NOV,96
	INDIA	SIEL	SPM5288PF/SIX	AA95-90003V	AA95-10008P L802-4:2mH L848-9:2mH (2902-001001)	AA96-20054C	NOT APPLIED	AA95-90003U FLOP	AA68-10759A ENG	RM130ETP ENG		GAUSS:100mG LATING:100-260V 50/60Hz	PB1246	NOV,96
M I D D L E	SAUDI-A	ZAMA	SPM4388PF/ZAX SPM5288PF/ZAX	AA95-90003V	AA95-10002H L802-4:10mH L848-9:10mH	AA96-20074A	NOT APPLIED	AA95-90003U ENG FLOF	AA68-10759A ENG AA68-10760A ARAB	RM130EAP ENG/ARAB	SASO Non- forced Stan- dard	GAUSS:200mG LATING:100-260V (WARRANTY CARD) 50/60Hz	PB1265 PB1042	SEP, 96
	U.A.E	SGE	SPM4388PF/SGEX SPM5288PF/SGEX	AA95-90003V	AA95-10008P L802-4:2mH L848-9:2mH (2902-001001)	AA96-20074A	NOT APPLIED	AA95-90003U ENG FLOF	AA68-10759A ENG AA68-10760A ARAB	RM130EAP ENG/ARAB		GAUSS:200mG LATING:100-260V 50/60Hz	PB1266 PB1042	SEP, 96

### 8-1 Local Specification & BOM option (Continued)

Area	Country	Buyer	Model Name	Local Specification & Bom Option							Safety - Standard	Special Specification	Others	Introduction
				IF	Power ASSY	Power Code ASSY	MIC	TTX	I/B	MICOM				
S O U T H E A S T  A S I A	CHINA	SEHK	SPM5288PF/HKX	AA95-90012B	AA95-10002H L802-4:10mH L848-9:10mH	AA96-20074A CP2	APPLIED (AA95-90001V)	AA95-90003U ENG FLOP	AA68-10761A CHI	RM130ECP (ENG/CHI)	SACI	GAUSS:300mg LATING:100-260V 50/60Hz, MIC PLUG-CONV	PB1209	
	INDONESIA	SME	SPM5288PF/SMEX	AA95-90003V	AA95-10008P L802-4:2mH L848-9:10mH (2902-001001)	AA96-20074A CP2	NOT APPLIED	AA95-90003U ENG FLOP	AA68-10759A ENG AA68-10766A IND	RM130ETP (ENG/TAI/M AL/IND)		GAUSS:-200mG RATING:100-260V 50/60Hz	PB1206	OCT, 96
	SINGAPORE	S'PORE	SPM4388PF/SAPX SPM5288PF/SAPX	AA95-90003V	AA95-10002H L802-4:10mH L848-9:10mH	AA96-20074A CP2	NOT APPLIED	AA95-90003U ENG FLOP	AA68-10759A ENG	RM130ECP ENG/CHI)	SISIR	GAUSS:-150mG LATING:230V 50Hz	PB1267 PB1208	OCT, 96
	MYANMAR	MUR	SPM5288PF/MURX	AA95-90003V	AA95-10008P L802-4:2mH L848-9:2mH (2902-001001)	AA96-20074A CP2	NOT APPLIED	AA9590003U ENG FLOP	AA68-10759A ENG	RM130ETP (ENG/TAI/ MAL/IND)		GAUSS:100mG LATING:100-260V 50/60Hz W/C, CP2	PB1207	OCT, 96
	MALAYSIA	SMARINA	SPM5288PF/MARX	AA95-90003V	AA95-10002H L802-4:10mH L848-9:10mH	AA96-20074A CP2	NOT APPLIED	AA95-90003U ENG FLOP	AA68-10759A ENG	RM130ETP (ENG/TAI/ MAL/IND)	SSIR	GAUSS:-100mG LATING:230V50Hz Same Specification as Singapore	PB1243	
	THAILAND	TSE	SPM5288PF/TSEX	AA95-90003V	AA95-10008P L802-4:2mH L848-9:2mH (2902-001001)	AA96-20052C	NOT APPLIED	AA95-90003U ENG FLOP	AA68-10759A ENG	RM130ETP (ENG/TAI/ MAL/IND)		GAUSS:100mG LATING:100-260V 50/60Hz W/C, EP2-NO	PB1244	NOV,96
	VIETNAM	SAVINA	SPM5288PF/SVIX	AA95-90003V	AA95-10008P L802-4:2mH L848-9:2mH (2902-001001)	AA96-20074A CP2	NOT APPLIED	AA95-90003U ENG FLOP	AA68-10759A ENG	RM130ETP (ENG/TAI/ MAL/IND)		GAUSS:100mG LATING:100-260V 50/60Hz W/C	PB1241	NOV,96
	INDIA	SIEL	SPM5288PF/SIX	AA95-90003V	AA95-10008P L802-4:2mH L848-9:2mH (2902-001001)	AA96-20054C	NOT APPLIED	AA95-90003U FLOP	AA68-10759A ENG	RM130ETP ENG		GAUSS:100mG LATING:100-260V 50/60Hz	PB1246	NOV,96
M I D D L E	SAUDI-A	ZAMA	SPM4388PF/ZAX SPM5288PF/ZAX	AA95-90003V	AA95-10002H L802-4:10mH L848-9:10mH	AA96-20074A	NOT APPLIED	AA95-90003U ENG FLOP	AA68-10759A ENG AA68-10760A ARAB	RM130EAP ENG/ARAB	SASO Non- forced Stand- ard	GAUSS:200mG LATING:100-260V (WARRANTY CARD) 50/60Hz	PB1265 PB1042	SEP, 96
	U.A.E	SGE	SPM4388PF/SGEX SPM5288PF/SGEX	AA95-90003V	AA95-10008P L802-4:2mH L848-9:2mH (2902-001001)	AA96-20074A	NOT APPLIED	AA95-90003U ENG FLOP	AA68-10759A ENG AA68-10760A ARAB	RM130EAP ENG/ARAB		GAUSS:200mG LATING:100-260V 50/60Hz	PB1266 PB1042	SEP, 96

## 8-1 Local Specification &amp; BOM option (Continued)

Area	Country	Buyer	Model Name	Local Specification & Bom Option							Safety - Standard	Special Specification	Others	Introduction
				IF	Power ASSY	Power Code ASSY	MIC	TTX	I/B	MICOM				
AFRICA	GHANA	AFKO	SPM5288PF/AMEX	AA95-90003V	AA95-10008P L802~4:2mH L848~9:2mH	AA96-20074A	NOT APPLIED	AA95-90003U FLOP	AA68-10759A ENG	RM130EAP ENG/ ARAB	NONE	GAUSS:500mg LATING:100~260V 50/60Hz	PB1374	MAR,96
S O U T H E A S T  A S I A	AUSTRALIA	SEAU	SPM4388PF/SEUX SPM5288PF/SEUX	AA95-90003V	AA95-10008P L802~4:10mH L848~9:10mH	AA96-20055C	NOT APPLIED	AA95-90003U LIST	AA68-10759A ENG	RM130ECP ENG/CHI		GAUSS:-500mG RATING:240V 50/60Hz, AP2	PB1415 PB1415	
	TAHITI	SAM	SPM5288PF/TAHX	AA95-90003V	AA95-10002H L802~4:10mH L848~9:10mH	AA96-20074A	NOT APPLIED	AA95-90003U FLOF	AA68-10759A ENG	RM130EAP ENG		GAUSS:-500mG LATING:220V 60Hz	PB1417	OCT, 96
	BANGLADESH	ELECTRA	SPM4388PF/ELHX SPM5288PF/ELHX	AA95-90003V	AA95-10008H L802~4:2mH L848~9:2mH	AA96-20074A	NOT APPLIED	AA95-90003U FLOF	AA68-10759A ENG	RM130EAP ENG/ ARAB		GAUSS:100mG LATING:100~260V 50/60Hz	PB1435 PB1434	
	CHINA	SEHK	SPM4388PF/HKX	AA95-90012B	AA95-10002H L802~4:10mH L848~9:10mH	AA96-20074A CP2	APPLIED (AA95- 90001V)	AA95-90003U ENG FLOP	AA68-10761A CHI	RM130ECP (ENG/CHI)	SACI	GAUSS:300mG LATING:100~220V 50/60Hz, MIC PLUG-CONV.	PB1436	

\* Dissimilar Potion Specification (among assays)

1. Audio: AA95-40004L NICAM(for all SPT51A models)  
AA95-40004Q No NICAM
2. IF :AA95-90003V All (excepting Czecho, China)  
AA95-90004E Czecho (SFE 6.25MC Ceramic Filter used)  
AA95-90012B China
3. PIP : AA95-90003W for 2 tuner  
AA95-90004R for 1 tuner
4. TTX : AA95-90003U English-TTX countries  
AA95-90003Y eastern Europe

5. MICOM

RM130EAP (English/ Arabian)

RM130ECP (English/ Chinese)

RM130ERP (English/ Russian)

RM130ETP (English/ Thai/ Malay/ Indonesian)

RM130EUP (English/ Yugo/ Czecho/ Rumania/ Croatia)

## 9. Electric Parts List

### 9-1. SPM4388PF

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
<b>ASSY-PCB,MAIN</b>							
*	AA94-10088	LASSY-PCB,MAIN(OPT);SPM4388PF/SGEX,SPT51A		C238	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
BRKT	AA61-10360	ABRACKET-MODULE;-,-,CUS-1 1/2H,T0.5,-,SCT		C239	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C1001	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C240	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C1002	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m		C241	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C1003	2401-000962	C-AL;22uF,20%,50V,GP,TP,5x11,5		C242	2305-000354	C-FILM,MPEF;330NF,5%,50V,TP,7.3x4.8x5.5M	
C1004	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m		C243	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C1005	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C244	2401-001668	C-AL;68uF,20%,16V,GP,TP,5x11,5	
C1006	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C245	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
C1007	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		C246*	2201-000273	C-CERAMIC,DISC;18pF,5%,50V,CH,TP,5x3mm,5	
C1008	2201-000982	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,TP,6		C247*	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C1009	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C248	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C1015	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C249	2305-000355	C-FILM,MPEF;330nF,5%,63V,TP,-5mm	
C1016	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C250	2301-000148	C-FILM,PEF;10nF,5%,100V,TP,7x3.2x7mm,5mm	
C200	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5		C251	2301-000148	C-FILM,PEF;10nF,5%,100V,TP,7x3.2x7mm,5mm	
C201	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C252	2301-000148	C-FILM,PEF;10nF,5%,100V,TP,7x3.2x7mm,5mm	
C202	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C253	2301-000148	C-FILM,PEF;10nF,5%,100V,TP,7x3.2x7mm,5mm	
C203	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C254	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
C204	2309-000138	C-FILM,PE-PF;100nF,5%,50V,TP,20x16x8,5		C255	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C205	2201-000483	C-CERAMIC,DISC;33pF,5%,50V,CH,TP,5x3,5		C256	2301-000148	C-FILM,PEF;10nF,5%,100V,TP,7x3.2x7mm,5mm	
C206	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C257	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C207	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C258	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C208	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,		C259	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C209	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C260	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C210	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C261	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C2101	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm		C262	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C2102	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm		C265	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C2103	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm		C266	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C2104	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm		C268	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C2105	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm		C269	2401-000947	C-AL;22uF,20%,35V,GP,TP,5x11,5	
C2106	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm		C270	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C2107	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C271	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C2108	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C274	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
C2109	2201-000611	C-CERAMIC,DISC;56pF,5%,50V,CH,TP,6.5x3,5		C275	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C211	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C277	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C2110	2201-000234	C-CERAMIC,DISC;150pF,5%,50V,CH,TP,9.5x3,		C278	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
C2111	2201-000504	C-CERAMIC,DISC;39pF,5%,50V,SL,TP,-,5		C279	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C2112	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		C280	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C212	2305-000355	C-FILM,MPEF;330nF,5%,63V,TP,-5mm		C281	2401-000947	C-AL;22uF,20%,35V,GP,TP,5x11,5	
C213	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,		C282	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C214	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm		C283	2201-000375	C-CERAMIC,DISC;220pF,5%,50V,RH,TP,9.5x3.	
C215	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C284	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C216	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5		C285	2301-000261	C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6.	
C217	2201-000471	C-CERAMIC,DISC;330pF,10%,50V,Y5P,TP,5x3,		C286	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C218	2201-000375	C-CERAMIC,DISC;220pF,5%,50V,RH,TP,9.5x3.		C287	2401-001333	C-AL;470nF,20%,50V,GP,TP,5x11,5	
C219	2305-000354	C-FILM,MPEF;330NF,5%,50V,TP,7.3x4.8x5.5M		C288	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C220	2201-000375	C-CERAMIC,DISC;220pF,5%,50V,RH,TP,9.5x3.		C289	2201-000375	C-CERAMIC,DISC;220pF,5%,50V,RH,TP,9.5x3.	
C221	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5		C290	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C222	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C291	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C223	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C292	2201-000961	C-CERAMIC,DISC;10pF,0.5pF,50V,RH,TP,5x3m	
C224	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C293	2201-000961	C-CERAMIC,DISC;10pF,0.5pF,50V,RH,TP,5x3m	
C225	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C294	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C226	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		C295	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C227	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		C296	2201-000193	C-CERAMIC,DISC;10pF,0.3pF,50V,CH,TP,5x3,	
C228	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m		C297	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C229	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C298	2401-002289	C-AL;470uF,20%,35V,WT,TP,10x20,5	
C230	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm		C299	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5	
C231	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm		C601	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
C232	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-5mm		C602	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C233	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C603	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C234	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C605	2401-000471	C-AL;10uF,20%,50V,BP,TP,5x11,5mm	
C235	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C606	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C236	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C8001	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
C237	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C8002	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
				C8003	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
				C8004	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
				C8005	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
				C8006	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	

Electric Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C8008	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		CZ306	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C8009	2401-000832	C-AL:220uF,20%,25V,GP,TP,8x11.5,5		CZ307	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C8010	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11.5,5		CZ308	2305-000354	C-FILM,MPEF:330nF,5%,50V,TP,7.3x4.8x5.5M	
C8012	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		CZ310	2201-000281	C-CERAMIC,DISC:1nF,79.8,50V,Y5V,TP,4x3.5	
C8013	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5		CZ311	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m	
C8014	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		CZ312	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C8015	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		CZ313	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m	
C901	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5		CZ314	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C902	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		CZ315	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5	
C903	2201-000374	C-CERAMIC,DISC:220pF,5%,50V,CH,TP,12.5x3		CZ316	2401-000404	C-AL:10uF,20%,16V,BP,TP,5x11,5	
C904	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11.5,5		D202	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C909	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5		D203	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C910	2201-000281	C-CERAMIC,DISC:1nF,79.8,50V,Y5V,TP,4x3.5		D204	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C911	2201-000247	C-CERAMIC,DISC:15pF,5%,50V,CH,TP,5x3,5		D205	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C912	2201-000247	C-CERAMIC,DISC:15pF,5%,50V,CH,TP,5x3,5		D211	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C913	2201-000423	C-CERAMIC,DISC:27pF,5%,50V,NPO,TP,5x3,2		D212	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C914	2201-000423	C-CERAMIC,DISC:27pF,5%,50V,NPO,TP,5x3,2		D601	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C917	2201-000611	C-CERAMIC,DISC:56pF,5%,50V,CH,TP,6.5x3,5		D905	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C918	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11.5,5		D906	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C919	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		D907	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C920	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		D908	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C921	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		D909	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C922	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		D910	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C923	2201-000146	C-CERAMIC,DISC:100pF,5%,50V,SL,TP,5x3,5		D911	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C924	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		D912	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C925	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		D914	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C926	2301-000289	C-FILM,PEF:5.6nF,5%,50V,TP,7x6x3,5		D915	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
CC01	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		DL201	4711-000205	DELAY LINE:0.140uS,-,-,TR	
CC02	2401-002462	C-AL:33uF,20%,16V,GP,TP,5x11,5		DZ201	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
CC03	2401-002462	C-AL:33uF,20%,16V,GP,TP,5x11,5		DZ203	0403-000355	DIODE-ZENER:U25.1BSB,5.1V,4.97-5.18V,500	
CC04	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		DZ204	0403-000300	DIODE-ZENER:MTZ8.2B,8.2V,7.78-8.19V,500m	
CC05	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5		DZ206	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
CC06	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		DZ207	0403-000289	DIODE-ZENER:MTZ10C,10V,9.7-10.2V,500mW,D	
CC07	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m		DZ208	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m	
CC10	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5		DZ209	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m	
CC11	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5		DZ210	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m	
CC12	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		DZ901	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m	
CF01	AA29-10002A	FILTER-COMB:-,UGL-357KNT,NTSC,ST		DZ902	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
CN201	3711-002646	CONNECTOR-HEADER:BOX,7P,1R,2.5mm,STRAIGH		DZC01	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
CN202	3711-003641	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG		IC201	1204-000636	IC-PICTURE PROCESS:TDA4566,DIP,18P,300MI	
CN601	3711-002645	CONNECTOR-HEADER:BOX,6P,1R,2.5MM,STRAIGH		IC202	1204-000530	IC-PAL/NTSC DECODER:TDA9160A,DIP,32P,400	
CN601	AA39-20038D	LEAD-CONNECTOR,ASSY:-,67096-006,S,6P,300		IC203	1204-000464	IC-VIDEO PROCESS:TDA4780,DIP,28P,-,PLAST	
CN701	3710-001155	CONNECTOR-SOCKET:20P,2R,2.54MM,STRAIGHT,		IC204	1209-000214	IC-DELAY LINE:TDA4665,DIP,16P,300MIL,PLA	
CN702	3710-001155	CONNECTOR-SOCKET:20P,2R,2.54MM,STRAIGHT,		IC205	1204-000444	IC-PICTURE PROCESS:TDA9170,DIP,32P,-,PLA	
CN801	3711-000628	CONNECTOR-HEADER:-,11P,1R,2.5mm,STRAIGHT		IC206	1201-000501	IC-VIDEO AMP:14577,DIP,8P,300MIL,CMOS,-5	
CN801	AA39-20160E	LEAD-CONNECTOR,ASSY:-,67096-011,S,11P,14		IC207	1204-000471	IC-PICTURE PROCESS:AN5342K,DIP,30P,400MI	
CN901	3711-002641	CONNECTOR-HEADER:BOX,10P,1R,2.54mm,STRAI		IC208	1001-000223	IC-VIDEO SWITCH:TEA5114A,-,DIP,16P,334MI	
CN903	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH		IC8001	1203-000006	IC-POSI.FIXED REG.:7808,TO-220,3P,-,PLAS	H/SINK
CN904	3711-002648	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,STRAIGH		IC8002	1203-000274	IC-POSI.FIXED REG.:7805,TO-220,3P,-,PLAS	H/SINK
CN905	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH		IC8003	1203-000165	IC-POSI.ADJUST REG.:78R12,TO-220,3P	H/SINK
CN906	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH		IC8004	1203-000298	IC-POSI.FIXED REG.:7809,TO-220,3P,-,PLAS	H/SINK
CNH02	AA39-20113A	LEAD-CONNECTOR,ASSY:-,YFH806-06,-,6(2)P,		IC901	AA13-30002H	IC-MCU:-,CXP853P40S-1,8bit,SDIP,-,64P	
CNQ01	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH		IC902	1103-000118	IC-EEPROM:2408,1Kx8BIT,DIP,8P,300MIL,10m	
CNV01	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH		IC903	1202-000001	IC-VOLTAGE COMP.:7533,TO-92,3P,-,SINGLE,	
CNV01	AA39-20016D	LEAD-CONNECTOR,ASSY:-,67096-003,S,3P,500		ICC01	0801-000961	IC-CMOS LOGIC:4053B,MULTIPLEXER,DIP,16P,3	
CNX01	AA39-20010E	LEAD-CONNECTOR,ASSY:-,YFH800-01,S,1P,800		ICZ30	1001-000223	IC-VIDEO SWITCH:TEA5114A,-,DIP,16P,334MI	
CNZ01	3711-002648	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,STRAIGH		ICZ31	1001-000223	IC-VIDEO SWITCH:TEA5114A,-,DIP,16P,334MI	
CNZ01	AA39-20082C	LEAD-CONNECTOR,ASSY:-,67096-009,S,9P,400		IF-C	AA39-30007B	IF-CABLE:-,T,150mm,1365#26	
CP101	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,5		L1001	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CP1010	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		L1002	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CP102	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		L1003	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CP103	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		L1004	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP104	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		L1005	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
CP105	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm		L101	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
CP106	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		L201	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
CP107	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		L202	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
CP108	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		L203	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
CP109	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		L204	2701-000162	INDUCTOR-AXIAL:27uH,10%,2.5x3.4mm	
CW901	2503-000158	C-NETWORK:330PFx4,20%,50V,MCCB1H331MX4YT		L205	2701-000223	INDUCTOR-AXIAL:82uH,10%,2.5X3.4MM	
CW902	2503-000159	C-NETWORK:330PFx5,20%,50V,MCCB1H331MX5YT		L206	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CW903	2503-000161	C-NETWORK:330PFx8,20%,50V,MCCB1H331MX8YT		L207	2701-000162	INDUCTOR-AXIAL:27uH,10%,2.5x3.4mm	
CW904	2503-000158	C-NETWORK:330PFx4,20%,50V,MCCB1H331MX4YT		L209	2701-000207	INDUCTOR-AXIAL:56uH,5%,2.5x3.4mm	
CZ301	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5m		L602	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CZ302	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5m		L603	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CZ303	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5m		L604	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
CZ304	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		L902	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CZ305	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		L903	AA27-10003G	COIL-CHOKE:-,30uH,K,50,22.3mA,TEL0606R	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
L904	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		R2118	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
L906	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R2119	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LP101	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm		R212	2001-000977	R-CARBON:8.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
LP102	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		R2120	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LP103	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm		R2121	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LP104	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm		R2122	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LP105	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm		R2123	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LP106	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm		R2124	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LP108	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		R2126	2001-000490	R-CARBON:200ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LZ301	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R2127	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LZ302	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R2128	2001-000490	R-CARBON:200ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LZ303	2701-000111	INDUCTOR-AXIAL:100uH,10%,2.5x3.4mm		R2129	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LZ304	2701-000111	INDUCTOR-AXIAL:100uH,10%,2.5x3.4mm		R213	2001-000008	R-CARBON:15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
LZ305	2701-000111	INDUCTOR-AXIAL:100uH,10%,2.5x3.4mm		R2130	2001-000490	R-CARBON:200ohm,5%,1/8W,AA,TP,1.8x3.2mm	
M101	AA59-4003F	MODULE-LNA;-LNA1410AF(S),PAL,EU,TR TYPE		R2131	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	
MODULE	AA59-4003P	MODULE-FOCUS,PACK-,F300,NTSC,43,64x62,		R2133	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
Q1001	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R2134	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q201	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R2135	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q202	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R214	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
Q203	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R215	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
Q204	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R217	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q205	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R218	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q206	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R219	2001-001000	R-CARBON:82Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q207	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R220	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q208	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R2201	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q209	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R2202	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q210	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R221	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q211	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R222	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q212	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R223	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
Q213	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R224	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q601	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R225	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q602	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R226	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q901	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L,		R227	2008-000300	R-FUSIBLE:560ohm,5%,1/2W,AA,TP,4.7x11mm	
Q903	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R228	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q904	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R229	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q905	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R230	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q906	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R231	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q907	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R232	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q908	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R233	2001-000645	R-CARBON:330Kohm,5%,1/8W,AA,TP,1.8x3.2m	
Q909	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R234	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q910	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R235*	2001-001000	R-CARBON:82Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
QC01	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R236	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm	
QC02	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R237	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
QC03	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R238	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
QC04	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R239	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
QC05	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R240	2001-000890	R-CARBON:6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
QC06	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R241	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
QZ301	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R242	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1002	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		R243	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1003	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		R244	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1004	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		R245	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1005	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		R248	2001-000522	R-CARBON:22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1006	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		R249	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1007	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm		R250	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R201	2001-000008	R-CARBON:15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R251	2001-000832	R-CARBON:510ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R202	2001-001015	R-CARBON:9.1Kohm,5%,1/8W,AA,TP,1.8x3.2m		R252	2001-000472	R-CARBON:2.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R203	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R253	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R204	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R254	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R205	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		R255	2001-000633	R-CARBON:30Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R206	2001-000273	R-CARBON:100KOHM,5%,1/8W,AA,TP,-		R256	2001-000522	R-CARBON:22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R208	2001-000864	R-CARBON:56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R257	2001-000008	R-CARBON:15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R210	2001-000563	R-CARBON:27Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R258	2001-000977	R-CARBON:8.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2100	2001-000633	R-CARBON:30Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R259	2001-000800	R-CARBON:5.1Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2101	2001-000832	R-CARBON:510ohm,5%,1/8W,AA,TP,1.8x3.2mm		R260	2001-000723	R-CARBON:4.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2103	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		R261	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R2106	2001-000008	R-CARBON:15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R262	2001-000522	R-CARBON:22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2107	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R263	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,-	
R2108	2001-000568	R-CARBON:27ohm,5%,1/8W,AA,TP,1.8x3.2mm		R264	2001-000252	R-CARBON:1.6KOHM,5%,1/8W,AA,TP,-	
R2109	2001-000832	R-CARBON:510ohm,5%,1/8W,AA,TP,1.8x3.2mm		R265	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R211	2004-001914	R-METAL:39Kohm,2%,1/8W,AA,TP,1.8x3.5mm		R266	2001-000633	R-CARBON:30Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2110	2001-000568	R-CARBON:27ohm,5%,1/8W,AA,TP,1.8x3.2mm		R267	2001-000008	R-CARBON:15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2111	2001-000832	R-CARBON:510ohm,5%,1/8W,AA,TP,1.8x3.2mm		R268	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2112	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		R269	2001-000660	R-CARBON:33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2113	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R270	2001-000702	R-CARBON:39Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2114	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		R271	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R2115	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		R272	2001-000605	R-CARBON:3.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2116	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R273	2001-000613	R-CARBON:3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	

Electric Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R274	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R950	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R275	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R951	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R276	2001-001000	R-CARBON:82Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R952	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R277	2004-001089	R-METAL:560Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R953	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R278	2001-000890	R-CARBON:6.8Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R954	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,-	
R279	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		R955	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R281	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		R956	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R282	2001-000347	R-CARBON:13Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R958	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R284	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		R959	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R285	2001-000924	R-CARBON:680ohm,5%,1/8W,AA,TP,1.8x3.2mm		R960	2001-000660	R-CARBON:33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R286	2001-000591	R-CARBON:3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		R961	2001-000554	R-CARBON:270ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R287	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm		R962	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R288	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R963	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R289	2001-000554	R-CARBON:270ohm,5%,1/8W,AA,TP,1.8x3.2mm		R964	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R290	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		R965	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R291	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm		R966	2001-000591	R-CARBON:3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R292	2001-000362	R-CARBON:150ohm,5%,1/8W,AA,TP,1.8x3.2mm		R967	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,-	
R293	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		R968	2001-000325	R-CARBON:120ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R294	2008-000272	R-FUSIBLE:33ohm,5%,1/2W,AA,TP,2.5x6.5mm		R969	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R295	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R970	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R297	2001-001015	R-CARBON:9.1Kohm,5%,1/8W,AA,TP,1.8x3.2m		R971	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R298	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		R972	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R299	2001-000007	R-CARBON:3Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R973	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R601	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R974	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R602	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		R975	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R616	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R976	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R8001	2001-000066	R-CARBON(S):10Kohm,5%,1/2W,AA,TP,2.4x6.4		R977	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R8003	2003-000590	R-METAL OXIDE(S):22ohm,5%,2W,AA,TP,4x12m		R978	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R8004	2003-000744	R-METAL OXIDE(S):56ohm,5%,2W,AA,TP,4x12m		R979	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R901	2001-000117	R-CARBON(S):68ohm,5%,1/2W,AA,TP,2.4x6.4m		R980	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R902	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,-		R981	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R903	2001-000449	R-CARBON:2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		R982	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R904	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		R985	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R905	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		R986	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R906	2001-001093	R-CARBON(S):2.2Kohm,5%,1/2W,AA,TP,2.4x6.		R987	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R907	2001-001093	R-CARBON(S):2.2Kohm,5%,1/2W,AA,TP,2.4x6.		R988	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R908	2001-001093	R-CARBON(S):2.2Kohm,5%,1/2W,AA,TP,2.4x6.		R989	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R909	2001-001093	R-CARBON(S):2.2Kohm,5%,1/2W,AA,TP,2.4x6.		R990	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R910	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R991	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,-	
R911	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R992	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m	
R912	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		R993	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R913	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		R994	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R914	2001-000362	R-CARBON:150ohm,5%,1/8W,AA,TP,1.8x3.2mm		R995	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R915	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		R996	2001-001197	R-CARBON(S):910ohm,5%,1/2W,AA,TP,2.4x6.4	
R916	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		R999	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R917	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		RC01	2008-000272	R-FUSIBLE:33ohm,5%,1/2W,AA,TP,2.5x6.5mm	
R918	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		RC02	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R919	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC03	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R920	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		RC04	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R921	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		RC05	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R922	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		RC06	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R924	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		RC07	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R925	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		RC08	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R926	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC09	2001-000118	R-CARBON(S):180ohm,5%,1/2W,AA,TP,2.4x6.4	
R927	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		RC10	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R928	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		RC11	2001-000376	R-CARBON:15ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R929	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC12	2001-001077	R-CARBON(S):150ohm,5%,1/2W,AA,TP,2.4x6.4	
R930	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC13	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R931	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC14	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R932	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC15	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R933	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		RC16	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R934	2001-000241	R-CARBON:1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		RC17	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R935	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		RC18	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R936	2001-000947	R-CARBON:7.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		RC19	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R937	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		RC20	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R938	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		RC25	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R939	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RC26	2001-000605	R-CARBON:3.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R940	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RC27	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R941	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RP102	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R942	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RP103	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R943	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		RP104	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R944	2001-000449	R-CARBON:2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		RT101	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R945	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		RT102	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R946	2001-000449	R-CARBON:2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		RZ301	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R947	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		RZ302	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R948	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		RZ303	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
R949	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		RZ306	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	





Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
DZ502	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m		CY06	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5	
DZ503	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m		CY07	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
DZ501	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m		CY08	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5	
D531	0402-000536	DIODE-RECTIFIER:RH10F,1500V,0.8A,DO-204A		GUIDE	AA61-50033A	GUIDE-LED:-,PP,HB,BLK,-,-,-	
<b>ASSY-PCB,CRT(BLUE)</b>				JACK	3722-000540	JACK-VHS:4P,-,AG,BLK,N	
*	AA95-20002D	ASSY-PCB,CRT,-,SPT51A,52,BLUE,-		JHY01	3722-000148	JACK-PHONE:1P,3.6mm,MBAG,BLACK,-	
C561	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,		JSY01	3722-000191	JACK-RCA:3P(VHS),3.4mm,AG,BLU,NO	
C562	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12.5,5		LDY01	0601-000385	LED:ROUND,RED,3mm,700nm	
C563	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		LDY02	0601-000385	LED:ROUND,RED,3mm,700nm	
C564	2401-000922	C-AL:22uF,20%,16V,GP,TP,5x5,5		LDY03	0601-000385	LED:ROUND,RED,3mm,700nm	
C565	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		LDY04	0601-000385	LED:ROUND,RED,3mm,700nm	
C566	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m		LY01	2701-000101	INDUCTOR-AXIAL:1.2uH,10%,2.5x3.4mm	
C567	2201-000600	C-CERAMIC,DISC:560pF,10%,50V,Y5P,TP,5x3,		LY02	2701-000101	INDUCTOR-AXIAL:1.2uH,10%,2.5x3.4mm	
C568	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m		RY05	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
C569	2201-000969	C-CERAMIC,DISC:10nF,+80-20%,3KV,Y5V,TP,-		RY06	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C571	AA27-90001B	COIL-SPARK,GAP-S-23,1.5KV,-,-,-		RY07	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C575	AA27-90001B	COIL-SPARK,GAP-S-23,1.5KV,-,-,-		RY08	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
C576	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11		RY09	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4	
C577	2201-000611	C-CERAMIC,DISC:56pF,5%,50V,CH,TP,6.5x3,5		RY10	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4	
CN	AA39-20115A	LEAD-CONNECTOR,ASSY:-,BUSHING,-,1P,500,3		RY11	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4	
CN502	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH		RY12	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4	
CN5051	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH		RY13	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m	
CNH01	AA39-20116A	LEAD-CONNECTOR,ASSY:-,YFH800-03,-,3(2)P,		RY14	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m	
D502	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		RY15	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
D503	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		<b>ASSY-PCB,PRE AMP</b>			
D504	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		*	AA95-40002W	ASSY-PCB,PREAMP:-,SPM5288PF,SPT51A,PREAM	
D561	0402-000536	DIODE-RECTIFIER:RH10F,1500V,0.8A,DO-204A		RR01	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
DZ501	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m		CR01	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
DZ502	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m		LR01	2701-000112	INDUCTOR-AXIAL:100uH,10%,2.8x7mm	
DZ503	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m		CN905	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH	
IC561	1201-000539	IC-VIDEO AMP:6101,ZIP,9P,-,SINGLE,-,PLAS	H/SINK	CN905	AA39-20033J	LEAD-CONNECTOR,ASSY:-,67096-003,S,3P,700	
L561	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		RMR01	AA59-60001Z	MODULE-REMOCON:-,ORC-638V1/SR-5CP2,38KHz	
Q561	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		SCREW	AA60-10011A	SCREW-TAPTITE:HH,-,PC,M4,L12,ZPC(BLK),SW	
R561	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		BRKT	AA61-10042A	BRACKET-PCB,RMC:-,S4388,SECC,T1.0,-,-,-	
R562	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4		<b>ASSY-PCB,A/V S/W</b>			
R563	2001-000232	R-CARBON:1.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		*	AA95-40002X	ASSY-PCB,A/V S/W:-,SPM5288PF,SPT51A,A/V,	
R564	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		AV701	3722-000502	JACK-RCA:9P,3.6MM,-,SN	
R565	2001-001164	R-CARBON(S):56Kohm,5%,1/2W,AA,TP,2.4x6.4		AV702	3722-000498	JACK-SCART:21P,-,SN,BLK,NO	
R566	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		AV703	3722-000544	JACK-VHS:12P,11.5mm,AG,BLK,N	
R567	2003-000468	R-METAL OXIDE(S):10ohm,5%,1W,AA,TP,3.3x9		C701	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R568	2001-000085	R-CARBON(S):100Kohm,5%,1/2W,AA,TP,2.4x6.		C702	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R569	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4		C703	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
R570	2001-001122	R-CARBON(S):3.9Kohm,5%,1/2W,AA,TP,2.4x6.		C704	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R571	2001-000563	R-CARBON:27Kohm,5%,1/8W,AA,TP,1.8x3.2mm		C705	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X	
R572	2002-000119	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.5x9		C706	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R573	2001-001047	R-CARBON(S):1.2Mohm,5%,1/2W,AA,TP,2.4x6.		C707	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R574	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.		C708	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R575	2001-001150	R-CARBON(S):470Kohm,5%,1/2W,AA,TP,2.4x6.		C709	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
R576	2001-001113	R-CARBON(S):270Kohm,5%,1/2W,AA,TP,2.4x6.		C710	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R577	2001-000679	R-CARBON:36Kohm,5%,1/8W,AA,TP,1.8x3.2mm		C711	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R578	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.		C712	2401-000242	C-AL:100uF,20%,10V,GP,TP,5x11,5	
R579	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.		C713	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
V561	3704-001019	SOCKET-CRT:10P,29.1PI,35.5PI,AU30U		C714	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
VR561	2101-000321	VR-ROTARY:1Mohm,0.2,0.6W,-,-		C715	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
ZD561	0403-000664	DIODE-ZENER:MTZ3.6A,3.6V,3.455-3.695V,50		C716	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
<b>ASSY-PCB,JACK</b>				C717	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X	
*	AA95-30001M	ASSY-PCB,JACK:-,SPT51A,-,-		C718	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
CN602	3711-003641	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG		C719	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
CN602	AA39-20032C	LEAD-CONNECTOR,ASSY:-,67096-012,S,12P,40		C720	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
CN901	3711-002641	CONNECTOR-HEADER:BOX,10P,1R,2.54mm,STRAI		C722	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X	
CN901	AA39-20025F	LEAD-CONNECTOR,ASSY:-,67096-010,S,10P,50		C723	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
CN902	3711-000631	CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIG		C724	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
CN904	3711-002648	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,STRAIGH		C725	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
CN904	AA39-20096B	LEAD-CONNECTOR,ASSY:-,67096-009,S,9P,600		C726	2201-000423	C-CERAMIC,DISC:27pF,5%,50V,NPO,TP,5x3,2.	
CY01	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		C727	2201-000423	C-CERAMIC,DISC:27pF,5%,50V,NPO,TP,5x3,2.	
CY02	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,		C728	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
CY03	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,		C729	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
CY04	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		C730	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
CY05	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		C731	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C732	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		L709	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
C733	2201-000426	C-CERAMIC,DISC:27pF,5%,50V,SL,TP,5x3,5		L710	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
C734	2201-000426	C-CERAMIC,DISC:27pF,5%,50V,SL,TP,5x3,5		Q701	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C735	2201-000426	C-CERAMIC,DISC:27pF,5%,50V,SL,TP,5x3,5		Q702	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C736	2201-000426	C-CERAMIC,DISC:27pF,5%,50V,SL,TP,5x3,5		Q703	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C737	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X		Q704	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C738	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		Q705	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C742	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,		Q706	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C743	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		Q707	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C744	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X		Q708	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C745	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X		Q709	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C747	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		Q710	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C748	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		Q711	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C749	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5		Q712	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C750	2401-002299	C-AL:4.7uF,20%,50V,GP,TP,5x7,5		Q713	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C751	2401-002299	C-AL:4.7uF,20%,50V,GP,TP,5x7,5		Q714	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C754	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		Q715	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C755	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		Q716	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C756	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		Q717	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C757	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		R701	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C758	2401-000242	C-AL:100uF,20%,10V,GP,TP,5x11,5		R702	2001-000660	R-CARBON:33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C759	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		R703	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
C760	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		R704	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
C762	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		R705	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C763	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		R706	2001-000660	R-CARBON:33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C764	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5		R707	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
C765	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5		R708	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
C766	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		R709	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CN701	3711-003490	CONNECTOR-HEADER:BOX,20P,2R,2.54MM,ANGLE		R710	2001-000325	R-CARBON:120ohm,5%,1/8W,AA,TP,1.8x3.2mm	
CN702	3711-003490	CONNECTOR-HEADER:BOX,20P,2R,2.54MM,ANGLE		R711	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
D701	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R712	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D702	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R713	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
D703	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R714	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D704	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R715	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D705	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R716	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D706	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R717	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D707	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R718	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D708	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R719	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D709	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R720	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D710	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R721	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D711	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R722	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D712	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R723	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ706	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R724	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ707	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R725	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
DZ708	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R726	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ709	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R727	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ710	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R728	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ712	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R729	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ713	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R730	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ714	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R731	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ715	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R732	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ716	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R733	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ717	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R734	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DZ718	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R735	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DZ719	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R736	2001-001175	R-CARBON(S):62ohm,5%,1/2W,AA,TP,2.4x6.4m	
DZ720	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R737	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ721	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R738	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
DZ722	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R739	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
DZ723	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R740	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ724	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R742	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
DZ725	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R743	2001-000522	R-CARBON:22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ726	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R744	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
DZ727	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R745	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ728	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R746	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
DZ729	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R747	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
IC701	0801-000961	IC-CMOS LOGIC:4053B,MUTIPLEXER,DIP,16P3		R749	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-	
IC702	0801-000961	IC-CMOS LOGIC:4053B,MUTIPLEXER,DIP,16P3		R750	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
IC703	1001-000217	IC-AUDIO SWITCH:KA2192B,4-INPUT,DIP,30P,		R751	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
IC704	1001-000217	IC-AUDIO SWITCH:KA2192B,4-INPUT,DIP,30P,		R752	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
L701	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R753	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
L702	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R754	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
L703	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R756	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
L704	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R757	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
L705	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R758	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
L706	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R759	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
L707	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R760	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
L708	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R761	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R762	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		C689	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
R763	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm		C691	2203-001105	C-CERAMIC,CHIP:6.8nF,10%,50V,X7R,TP,2012	
R764	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		CJ01	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,-,5mm	
R765	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ02	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R766	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ03	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,	
R767	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ04	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,	
R768	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		CJ05	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,	
R769	2001-001015	R-CARBON:9.1Kohm,5%,1/8W,AA,TP,1.8x3.2m		CJ06	2203-000609	C-CERAMIC,CHIP:22nF,10%,50V,X7R,TP,2012,	
R771	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ07	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R772	2001-000591	R-CARBON:3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		CJ08	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
R773	2004-001126	R-METAL:6.2Kohm,1%,1/8W,AA,TP,1.8x3.2m		CJ09	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
R774	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ10	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R775	2001-000591	R-CARBON:3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		CJ11	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R776	2004-001126	R-METAL:6.2Kohm,1%,1/8W,AA,TP,1.8x3.2m		CJ12	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
R777	2001-000019	R-CARBON(S):10ohm,5%,1/2W,AA,TP,2.4x6.4m		CJ13	2203-000595	C-CERAMIC,CHIP:220pF,5%,50V,NPO,TP,2012,	
R778	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ14	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
R779	2001-001066	R-CARBON(S):110ohm,5%,1/2W,AA,TP,2.4x6.4		CJ15	2203-000274	C-CERAMIC,CHIP:10pF,0.25pF,50V,NPO,TP,20	
R780	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ16	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
R781	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		CJ17	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R782	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		CJ18	2203-000839	C-CERAMIC,CHIP:390pF,5%,50V,NPO,TP,2012,	
R783	2001-000241	R-CARBON:1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		CJ19	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R784	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4		CJ20	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
R785	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ21	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
R786	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		CJ22	2203-000979	C-CERAMIC,CHIP:47nF,10%,50V,X7R,TP,2012,	
R787	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		CJ23	2203-000578	C-CERAMIC,CHIP:220nF,20%,50V,Y5V,TP,3216	
R788	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,-		CJ24	2401-001569	C-AL:47uF,20%,50V,BP,TP,10x12.5mm,5	
R789	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ25	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
R790	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		CJ26	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R791	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ27	2401-001569	C-AL:47uF,20%,50V,BP,TP,10x12.5mm,5	
R792	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ28	2203-000578	C-CERAMIC,CHIP:390pF,5%,50V,Y5V,TP,3216	
R793	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-		CJ29	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R794	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ30	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
R795	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4		CJ31	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
R796	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ32	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5	
R798	2001-001187	R-CARBON(S):75ohm,5%,1/2W,AA,TP,2.4x6.4m		CJ33	2203-001223	C-CERAMIC,CHIP:820pF,10%,50V,X7R,TP,2012	
R799	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm		CJ34	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5	
RW701	2011-001098	R-NETWORK:75/75/1K/75ohm,5%,1/8W,-,SIP,5		CJ35	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
RW702	2011-001133	R-NETWORK:33K/24K/75x3,5%,1/8W,X,SIP,6P,		CJ36	2203-001223	C-CERAMIC,CHIP:820pF,10%,50V,X7R,TP,2012	

**ASSY-PCB,AUDIO**

\* AA95-40004L ASSY-PCB,AUDIO;-,CS7277PF/MVXT,SCT51A,-,

C	2201-000180	C-CERAMIC,DISC:10nF,10%,50V,Y5V,TP,6.5*3	
C653	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C654	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C655	2301-000320	C-FILM,PEF:82nF,5%,50V,TP,8.0x4.5x8.5mm,	
C656	2203-001132	C-CERAMIC,CHIP:680pF,5%,50V,NPO,TP,2012,	
C657	2401-000947	C-AL:22uF,20%,35V,GP,TP,5x11,5	
C658	2401-000947	C-AL:22uF,20%,35V,GP,TP,5x11,5	
C659	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
C660	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
C661	2203-001105	C-CERAMIC,CHIP:6.8nF,10%,50V,X7R,TP,2012	
C662	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
C663	2203-000609	C-CERAMIC,CHIP:22nF,10%,50V,X7R,TP,2012,	
C664	2203-000609	C-CERAMIC,CHIP:22nF,10%,50V,X7R,TP,2012,	
C665	2203-000495	C-CERAMIC,CHIP:2.2nF,10%,50V,X7R,TP,2012	
C666	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
C669	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
C670	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
C671	2401-001026	C-AL:3.3uF,20%,50V,GP,TP,5x11mm,5mm	
C672	2401-001026	C-AL:3.3uF,20%,50V,GP,TP,5x11mm,5mm	
C673	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C674	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
C675	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
C676	2201-000452	C-CERAMIC,DISC:3.9nF,10%,50V,Y5P,TP,8x3,	
C678	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5	
C679	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5	
C680	2203-000891	C-CERAMIC,CHIP:4.7nF,10%,50V,X7R,TP,2012	
C681	2401-002042	C-AL:220uF,20%,10V,GP,TP,6.3x11,5	
C682	2203-000891	C-CERAMIC,CHIP:4.7nF,10%,50V,X7R,TP,2012	
C684	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
C685	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
C686	2401-000242	C-AL:100uF,20%,10V,GP,TP,5x11,5	
C687	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,	
C688	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	

CN601	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG	
CN602	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG	
DJ01	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
DJ02	0405-000108	DIODE-VARACTOR:BB405B,28V,10nA,D	
IC602	0904-000004	IC-PERIPHERAL:1853,-,DIP,30P,-,-,ST,-,PL	
IC603	1204-000515	IC-SOUND PROCESSOR:TDA9840/V2,DIP,20P,32	
ICJ01	1204-000449	IC-DECODER:SAA7283ZP,DIP,52P,600MIL,PLAS	
ICJ02	1201-000191	IC-OP AMP:4558,DIP,8P,300MIL,DUAL,20V/mV	
L651	2702-000131	INDUCTOR-RADIAL:2.2mH,5%,6.2x7.4mm	
LJ01	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
LJ02	2701-000208	INDUCTOR-AXIAL:6.8uH,10%,2.5x3.4mm	
R650	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
R651	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
R652	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
R653	2007-001141	R-CHIP:7.5KOHM,5%,1/10W,DA,TP,2012	
R654	2007-001141	R-CHIP:7.5KOHM,5%,1/10W,DA,TP,2012	
R657	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
R658	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
R659	2007-000710	R-CHIP:3.9KOHM,5%,1/10W,DA,TP,2012	
R661	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
R662	2007-001141	R-CHIP:7.5KOHM,5%,1/10W,DA,TP,2012	
R663	2007-000029	R-CHIP:00HM,5%,1/10W,DA,TP,2012	
R664	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
R665	2007-001195	R-CHIP:820KOHM,5%,1/10W,DA,TP,2012	
R666	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
R667	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
RJ01	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
RJ02	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
RJ03	2007-001113	R-CHIP:680KOHM,5%,1/10W,DA,TP,2012	
RJ04	2007-000593	R-CHIP:220HM,5%,1/10W,DA,TP,2012	
RJ05	2007-000477	R-CHIP:1MOHM,5%,1/10W,DA,TP,2012	
RJ06	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
RJ07	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
RJ08	2001-001096	R-CARBON(S):2.2ohm,5%,1/2W,AA,TP,2.4x6.4	
RJ09	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
RJ10	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
RJ12	2007-000774	R-CHIP:33KOHM,5%,1/10W,DA,TP,2012	
RJ13	2007-000267	R-CHIP:1.8KOHM,5%,1/10W,DA,TP,2012	
RJ14	2007-000034	R-CHIP:1OHM,5%,1/8W,DA,TP,3216	



Electric Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R307	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4		RJ409	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R308	2001-001152	R-CARBON(S):47Kohm,5%,1/2W,AA,TP,2.4x6.4		RJ410	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R309	2001-001155	R-CARBON(S):5.6Kohm,5%,1/2W,AA,TP,2.4x6.4		RJ411	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R310	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4		RJ412	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R311	2001-001146	R-CARBON(S):4.7ohm,5%,1/2W,AA,TP,2.4x6.4		RJ413	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R312	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4		RJ414	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R313	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4		RJ415	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R314	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4		RJ416	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R315	2003-000606	R-METAL OXIDE(S):270ohm,5%,2W,AA,TP,4x12		RJ417	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R316	2003-000606	R-METAL OXIDE(S):270ohm,5%,2W,AA,TP,4x12		RJ418	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R317	2008-000190	R-FUSIBLE(S):1.2ohm,5%,2W,AA,TP,3.9x10mm		RJ419	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R401	2004-001989	R-METAL:620ohm,5%,1/8W,AA,TP,1.8x3.2mm		RJ420	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R402	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm		RJ421	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R403	2003-000683	R-METAL OXIDE(S):4.7Kohm,5%,1W,AA,TP,3.3		RJ422	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R404	2003-000417	R-METAL OXIDE(S):1.2Kohm,5%,3W,AA,TP,6x1		RJ423	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R405	2006-000319	R-CEMENT:3Kohm,5%,5W,CA,BK,9.5x25x9.5mm		RJ424	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R406	2001-000020	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4m		RJ425	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R407	2003-000522	R-METAL OXIDE(S):180ohm,5%,1W,AA,TP,3.3x		RJ428	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R408	2003-000634	R-METAL OXIDE(S):3.9Kohm,5%,1W,AA,TP,3.3		RJ429	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R409	2001-001143	R-CARBON(S):4.3Kohm,5%,1/2W,AA,TP,2.4x6.4		RJ433	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R410	2003-000561	R-METAL OXIDE(S):2.7Kohm,5%,2W,AA,TP,4x1		RJ434	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R411	2004-001989	R-METAL:620ohm,5%,1/8W,AA,TP,1.8x3.2mm		RJ436	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R412	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm		RJ438	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R413	2003-000650	R-METAL OXIDE(S):330ohm,5%,2W,AA,TP,4x12		RJ445	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R414	2008-000298	R-FUSIBLE:47ohm,5%,1/4W,AA,TP,-		RV01	2008-001005	R-FUSIBLE:0.47ohm,10%,1W,AA,TP,4.7x11.7m	
R415	2001-000020	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4m		RV02	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R416	2003-000561	R-METAL OXIDE(S):2.7Kohm,5%,2W,AA,TP,4x1		RV03	2001-001178	R-CARBON(S):680ohm,5%,1/2W,AA,TP,2.4x6.4	
R417	2008-001005	R-FUSIBLE:0.47ohm,10%,1W,AA,TP,4.7x11.7m		RV04	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,-	
R421	2003-000487	R-METAL OXIDE(S):12Kohm,5%,2W,AA,TP,4x12		RV05	2001-000890	R-CARBON:6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R423	2001-001099	R-CARBON(S):2.7Kohm,5%,1/2W,AA,TP,2.4x6.4		RV06	2001-000449	R-CARBON:2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R424	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m		RV07	2001-000449	R-CARBON:2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R425	2003-000752	R-METAL OXIDE(S):6.8Kohm,5%,2W,AA,TP,4x1		RV09	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R426	2001-001144	R-CARBON(S):4.7Kohm,5%,1/2W,AA,TP,2.4x6.4		RV10	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R441	2001-000591	R-CARBON:3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		RV11	2008-001005	R-FUSIBLE:0.47ohm,10%,1W,AA,TP,4.7x11.7m	
R444	2004-001185	R-METAL:680Kohm,5%,1/8W,AA,TP,1.8x3.2m		RV12	2001-001192	R-CARBON(S):820ohm,5%,1/2W,AA,TP,2.4x6.4	
R445	2004-001384	R-METAL(S):150Kohm,1%,1/2W,AA,TP,2.4x6.4		RV13	2001-000793	R-CARBON:47ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R446	2001-000109	R-CARBON(S):470ohm,5%,1/2W,AA,TP,2.4x6.4		RV14	2001-000118	R-CARBON(S):180ohm,5%,1/2W,AA,TP,2.4x6.4	
R447	2001-001086	R-CARBON(S):18Kohm,5%,1/2W,AA,TP,2.4x6.4		RV15	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,-	
R448	2001-001047	R-CARBON(S):1.2Mohm,5%,1/2W,AA,TP,2.4x6.4		RV16	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R449	2001-001142	R-CARBON(S):3Kohm,5%,1/2W,AA,TP,2.4x6.4m		RV17	2001-000660	R-CARBON:33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R450	2001-000007	R-CARBON:3Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RV18	2001-000793	R-CARBON:47ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R451	2001-000591	R-CARBON:3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		RV19	2001-000019	R-CARBON(S):10ohm,5%,1/2W,AA,TP,2.4x6.4m	
R452	2001-001131	R-CARBON(S):33Kohm,5%,1/2W,AA,TP,2.4x6.4		RV20	2001-001195	R-CARBON(S):82ohm,5%,1/2W,AA,TP,2.4x6.4m	
R453	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m		RV21	2001-001195	R-CARBON(S):82ohm,5%,1/2W,AA,TP,2.4x6.4m	
R454	2003-002046	R-METAL OXIDE(S):3.3KOHM,5%,3W,AA,TP,6x1		RV22	2001-001045	R-CARBON(S):1.2Kohm,5%,1/2W,AA,TP,2.4x6.4	
R455	2003-000538	R-METAL OXIDE(S):1Kohm,5%,2W,AA,TP,4x12m		RV23	2001-001050	R-CARBON(S):1.5Kohm,5%,1/2W,AA,TP,2.4x6.4	
R456	2003-000505	R-METAL OXIDE(S):150ohm,5%,3W,AA,TP,6x16		RV24	2001-001179	R-CARBON(S):68Kohm,5%,1/2W,AA,TP,2.4x6.4	
R457	2004-001390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm		RV25	2001-001179	R-CARBON(S):68Kohm,5%,1/2W,AA,TP,2.4x6.4	
R460	2001-001179	R-CARBON(S):68Kohm,5%,1/2W,AA,TP,2.4x6.4		RV26	2001-001050	R-CARBON(S):1.5Kohm,5%,1/2W,AA,TP,2.4x6.4	
R461	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m		RV27	2001-001045	R-CARBON(S):1.2Kohm,5%,1/2W,AA,TP,2.4x6.4	
R462	2001-001194	R-CARBON(S):82Kohm,5%,1/2W,AA,TP,2.4x6.4		RV28	2003-000744	R-METAL OXIDE(S):56ohm,5%,2W,AA,TP,4x12m	
R471	2008-000241	R-FUSIBLE:1.9ohm,5%,2W,CA,BK,6.3x18x6.3m		RV29	2001-001152	R-CARBON(S):47Kohm,5%,1/2W,AA,TP,2.4x6.4	
R472	2001-000085	R-CARBON(S):100Kohm,5%,1/2W,AA,TP,2.4x6.4		RV30	2003-000744	R-METAL OXIDE(S):56ohm,5%,2W,AA,TP,4x12m	
R473	2001-000085	R-CARBON(S):100Kohm,5%,1/2W,AA,TP,2.4x6.4		RV31	2001-001100	R-CARBON(S):2.7ohm,5%,1/2W,AA,TP,2.4x6.4	
R474	2008-000263	R-FUSIBLE:1ohm,5%,1/2W,AA,TP,4.7x11mm		RV32	2001-001100	R-CARBON(S):2.7ohm,5%,1/2W,AA,TP,2.4x6.4	
R475	2008-001005	R-FUSIBLE:0.47ohm,10%,1W,AA,TP,4.7x11.7m		RV33	2003-000578	R-METAL OXIDE(S):220ohm,5%,2W,AA,TP,4x12	
R476	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4		RV34	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,-	
R481	2001-001164	R-CARBON(S):56Kohm,5%,1/2W,AA,TP,2.4x6.4		T401	AA26-90001K TRANS-DUMMY:-.55MH,EEER404215,130/46/16.		
R482	2004-001379	R-METAL(S):12Kohm,1%,1/2W,AA,TP,2.4x6.4m		T402	AA26-50001A HORIZ.DRIVE:-.90MH,67UH,9.5UH,YL81,ST		
RJ301	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		T403	AA26-50001F HORIZ.DRIVE:-.55MH,594uH,4.0uH,EI19,-		
RJ302	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		T404	AA26-90001L TRANS-DUMMY:-.15mH,ER4042,-,-		
RJ303	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		T444	AA26-30001U TRANS-FLYBACK:-.FWZ-43B001,43,125V		
RJ304	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		VR401	2103-000670 VR-SEMI:1Kohm,25%,1/5W,TP		
RJ305	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD301	0403-000655 DIODE-ZENER:MTZ13A,13V,12.11-12.75V,500m		
RJ306	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD302	0403-000699 DIODE-ZENER:TZP27B,27V,27-30.8V,1W,DO-41		
RJ307	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD303	0403-000700 DIODE-ZENER:TZP33A,33V,31-35V,1W,DO-41,T		
RJ308	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD304	0403-000699 DIODE-ZENER:TZP27B,27V,27-30.8V,1W,DO-41		
RJ309	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD305	0403-000699 DIODE-ZENER:TZP27B,27V,27-30.8V,1W,DO-41		
RJ310	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD306	0403-000658 DIODE-ZENER:MTZ18A,18V,16.22-17.06V,500m		
RJ401	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD307	0403-000355 DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500m		
RJ402	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD308	0403-000699 DIODE-ZENER:TZP27B,27V,27-30.8V,1W,DO-41		
RJ403	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD401	0403-000300 DIODE-ZENER:MTZ8.2B,8.2V,7.78-8.19V,500m		
RJ404	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD402	0403-000654 DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		
RJ405	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD405	0403-000299 DIODE-ZENER:MTZ7.5C,7.5V,7.29-7.67V,500m		
RJ406	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD423	0403-000355 DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500m		
RJ407	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD424	0403-000294 DIODE-ZENER:MTZ4.7B,4.7V,4.55-4.80V,500m		
RJ408	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZDV01	0403-000655 DIODE-ZENER:MTZ13A,13V,12.11-12.75V,500m		

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
<b>ASSY-PCB,CONVERGENCE</b>							
*	AA95-90001S	ASSY-PCB,CONVERGENCE-;SPM5288F,SPT51A,P		CZ055	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
BT+HS	AA60-10008A	SCREW-TAPPING;TH,+,M3,L10,ZPC(YEL),SWRCH		CZ056	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C651	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm		CZ057	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C652	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11,5		CZ058	2401-000988	C-AL:3.3uF,20%,100V,BP,TP,5x11mm,5mm	
C653	2301-000192	C-FILM,PEF;1nF,5%,50V,TP,5.3x10mm,5mm		CZ059	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C654	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11,5		CZ060	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
C655	2201-002022	C-CERAMIC,DISC;5pF,0.25pF,500V,NPO,TP,5x		CZ061	2401-000988	C-AL:3.3uF,20%,100V,BP,TP,5x11mm,5mm	
C656	2201-002022	C-CERAMIC,DISC;5pF,0.25pF,500V,NPO,TP,5x		CZ062	2401-001914	C-AL:1uF,20%,50V,BP,TP,5x11,5	
C657	2301-000530	C-FILM,PEF;100nF,5%,100V,TP,11.5x12.5x6		CZ063	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C658	2301-000530	C-FILM,PEF;100nF,5%,100V,TP,11.5x12.5x6		CZ064	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C675	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5		CZ064A	2401-000711	C-AL:2200uF,20%,25V,GP,TP,16x25,7.5	
C676	2401-001661	C-AL:68uF,20%,100V,GP,TP,10x16,5		CZ065	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5	
C678	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5		CZ066	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5	
C679	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20,5		CZ067	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20,5	
C680	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5		CZ067A	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5	
C681	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20,5		CZ068	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20,5	
C682	2401-001661	C-AL:68uF,20%,100V,GP,TP,10x16,5		CZ069	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12.5mm,5	
C683	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11.5,5		CZ070	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12.5mm,5	
C684	2401-000773	C-AL:220uF,20%,10V,NP,TP,10x12.5,5mm		CZ071	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12.5mm,5	
C685	2401-000622	C-AL:2.2uF,20%,100V,BP,TP,13x25mm,5		CZ072	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12.5mm,5	
C686	2401-000622	C-AL:2.2uF,20%,100V,BP,TP,13x25mm,5		CZ073	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12.5mm,5	
CN401	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH		CZ074	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12.5mm,5	
CN401	AA39-20018A	LEAD-CONNECTOR,ASSY-;YSH025-04,S,4P,100		CZ075	2401-001570	C-AL:47uF,20%,50V,WT,TP,10x20MM,5MM	
CN601	3711-002645	CONNECTOR-HEADER;BOX,6P,1R,2.5MM,STRAIGH		CZ080	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
CN602	3711-003641	CONNECTOR-HEADER;BOX,12P,1R,2.5mm,STRAIG		D651	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CN603	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH		D652	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
CN604	3711-002643	CONNECTOR-HEADER;BOX,4P,1R,2.5MM,STRAIGH		DZ001	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CN802	3711-002644	CONNECTOR-HEADER;BOX,5P,1R,2.5mm,STRAIGH		DZ002	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CNZ02	3711-002646	CONNECTOR-HEADER;BOX,7P,1R,2.5mm,STRAIGH		DZ003	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CNZ02	AA39-20029K	LEAD CONNECTOR,ASSY-;67096-007,S,7P,400		DZ004	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CNZ03	3711-000445	CONNECTOR-HEADER;BOX,6P,1R,2.5MM,STRAIGH		DZ005	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
CNZ03	AA39-20027A	LEAD-CONNECTOR,ASSY-;67096-006,S,6P,300		DZ006	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
CZ001	2301-000310	C-FILM,PEF;68nF,5%,50V,TP,8.0x8.5x4.0X		DZ007	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ002	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m		DZ008	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ004	2201-000265	C-CERAMIC,DISC;180pF,5%,50V,RH,TP,8x3,5		DZ009	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ005	2301-000108	C-FILM,PEF;1.5nF,5%,50V,TP,6.5x3.0x5.5mm		DZ010	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ006	2301-000175	C-FILM,PEF;15nF,5%,50V,TP,7.1x3.5x13mm,5		DZ011	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ007	2301-000104	C-FILM,PEF;1.2nF,5%,50V,TP,6.5x3.0x5.5mm		DZ012	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ008	2201-000145	C-CERAMIC,DISC;100pF,5%,50V,RH,TP,8.0*3		DZ013	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ009	2201-000145	C-CERAMIC,DISC;100pF,5%,50V,RH,TP,8.0*3		DZ014	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ011	2301-000227	C-FILM,PEF;27nF,5%,50V,TP,7x3.5x6.5mm,5m		DZ015	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ012	2201-000982	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,TP,6		DZ016	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ013	2201-000982	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,TP,6		DZ017	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ014	2201-000556	C-CERAMIC,DISC;470pF,10%,500V,Y5P,TP,7x4		DZ018	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ015	2201-000138	C-CERAMIC,DISC;100pF,10%,50V,Y5P,TP,4.0X		DZ018	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ016	2201-000411	C-CERAMIC,DISC;270pF,10%,50V,Y5P,TP,5x3		DZ020	0403-000655	DIODE-ZENER;MT213A,13V,12.11-12.75V,500m	
CZ017	2201-000325	C-CERAMIC,DISC;2.2nF,10%,500V,Y5P,TP,8x4		DZ024	0403-000655	DIODE-ZENER;MT213A,13V,12.11-12.75V,500m	
CZ018	2201-000325	C-CERAMIC,DISC;2.2nF,10%,500V,Y5P,TP,8x4		HC651	AA13-20001WIC	HYBRID-;STK4142(2),SIP,18PAUDIO POW	
CZ019	2201-000472	C-CERAMIC,DISC;330pF,5%,50V,SL,TP,8x3.5		HCZ01	1203-000121	IC-NEGA.FIXED REG.;7906,TO-220,3P,-PLAS	H/SINK
CZ020	2201-000556	C-CERAMIC,DISC;470pF,10%,500V,Y5P,TP,7x4		HCZ02	1203-000284	IC-POSI.FIXED REG.;7806,TO-220,3P,-PLAS	H/SINK
CZ021	2201-000411	C-CERAMIC,DISC;270pF,10%,50V,Y5P,TP,5x3		HCZ03	AA13-20001V	IC-HYBRID-;STK391-020,SIP,15POP AMP	
CZ022	2201-000138	C-CERAMIC,DISC;100pF,10%,50V,Y5P,TP,4.0X		HCZ04	AA13-20001V	IC-HYBRID-;STK391-020,SIP,15POP AMP	
CZ023	2201-000556	C-CERAMIC,DISC;470pF,10%,500V,Y5P,TP,7x4		HCZ05	AA13-20001V	IC-HYBRID-;STK391-020,SIP,15POP AMP	
CZ024	2201-000411	C-CERAMIC,DISC;270pF,10%,50V,Y5P,TP,5x3		HETSIN	AA61-10183A	BRACKET-TR-;S4388,STS,TO.5,-,-,-	
CZ025	2201-000325	C-CERAMIC,DISC;2.2nF,10%,500V,Y5P,TP,8x4		ICZ01	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV	
CZ026	2201-000325	C-CERAMIC,DISC;2.2nF,10%,500V,Y5P,TP,8x4		ICZ02	0801-000659	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,DIP,1	
CZ027	2201-000472	C-CERAMIC,DISC;330pF,5%,50V,SL,TP,8x3.5		ICZ03	0801-000659	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,DIP,1	
CZ028	2201-000556	C-CERAMIC,DISC;470pF,10%,500V,Y5P,TP,7x4		LZ001	AA27-10001Z	COIL-CHOKE-;13UH,K,-,3A,-,14UH-K(3A),10	
CZ029	2201-000411	C-CERAMIC,DISC;270pF,10%,50V,Y5P,TP,5x3		LZ002	AA27-10001Z	COIL-CHOKE-;13UH,K,-,3A,-,14UH-K(3A),10	
CZ030	2201-000138	C-CERAMIC,DISC;100pF,10%,50V,Y5P,TP,4.0X		LZ003	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
CZ031	2201-000556	C-CERAMIC,DISC;470pF,10%,500V,Y5P,TP,7x4		LZ004	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
CZ032	2201-000411	C-CERAMIC,DISC;270pF,10%,50V,Y5P,TP,5x3		LZ005	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ033	2201-000325	C-CERAMIC,DISC;2.2nF,10%,500V,Y5P,TP,8x4		LZ006	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ034	2201-000325	C-CERAMIC,DISC;2.2nF,10%,500V,Y5P,TP,8x4		LZ007	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ035	2201-000472	C-CERAMIC,DISC;330pF,5%,50V,SL,TP,8x3.5		LZ008	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ036	2201-000556	C-CERAMIC,DISC;470pF,10%,500V,Y5P,TP,7x4		LZ009	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ037	2201-000411	C-CERAMIC,DISC;270pF,10%,50V,Y5P,TP,5x3		LZ010	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ038	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m		LZ011	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ051	2401-000471	C-AL:10uF,20%,50V,BP,TP,5x11,5mm		LZ012	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ052	2401-001569	C-AL:47uF,20%,50V,BP,TP,10x12.5mm,5		PCB+HS	6003-000335	SCREW-TAPTING;RH,+,2S,M3,L8,ZPC(YEL),SWR	
CZ053	2401-000934	C-AL:22uF,20%,25V,GP,TP,8x11.5,5		Q651	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
CZ054	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		Q652	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
				Q653	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L	
				QZ001	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
				QZ002	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
				QZ003	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
				QZ004	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
				QZ005	0502-000441	TR-POWER;2SC4635RB,NPN,2W,TO-220,ST,10-	H/SINK



Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
CT08	2201-000119	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,		CN166	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012,	
CT09	2201-000193	C-CERAMIC,DISC;10pF,0.3pF,50V,CH,TP,5x3,		CN101	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG	
CT10	2201-000247	C-CERAMIC,DISC;15pF,5%,50V,CH,TP,5x3,5		CN102	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG	
CT11	2201-000292	C-CERAMIC,DISC;1nF,10%,50V,Y5P,TP,5x3,5		D112	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
CT12	2201-000119	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,		D113	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
CT13	2201-000119	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,		D128	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CT17	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm		D161	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
CT18	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm		D164	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
CT19	2305-000412	C-FILM,MPEF;470nF,5%,63V,TP,-,5mm		D165	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
CT20	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5		DI161	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
ICT01	1204-000535	IC-PAL DECODER;SAA5281P/E,DIP,48P,-,PLAS		DI162	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
ICT02	1001-000223	IC-VIDEO SWITCH;TEA5114A,-,DIP,16P,334MI		DK161	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
LTO1	2701-000169	INDUCTOR-AXIAL;3.9uH,10%,2.5x3.4mm		DK162	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
RT01	2004-000971	R-METAL;470ohm,1%,1/8W,AA,TP,1.8x3.2mm		DK163	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
RT02	2004-000971	R-METAL;470ohm,1%,1/8W,AA,TP,1.8x3.2mm		DK164	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
RT03	2004-000971	R-METAL;470ohm,1%,1/8W,AA,TP,1.8x3.2mm		DN111	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
RT05	2001-000325	R-CARBON;120ohm,5%,1/8W,AA,TP,1.8x3.2mm		DN112	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
RT10	2001-000302	R-CARBON;10ohm,5%,1/8W,AA,TP,1.8x3.2mm		DN113	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
RT11	2001-000290	R-CARBON;10KOHM,5%,1/8W,AA,TP,-		DN161	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
RT13	2001-000812	R-CARBON;5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		DN162	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
RT14	2001-000591	R-CARBON;3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		DN163	0401-000160	DIODE-SWITCHING;ISS314,30V,100mA,USC,TP	
RT15	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		IC111	1204-000560	IC-DEMOMULATOR;TDA9815,DIP,32P,400MIL,PL	
RT16	2001-000563	R-CARBON;27Kohm,5%,1/8W,AA,TP,1.8x3.2mm		IC113	AA13-20003F	IC-HYBRID;-,PAP101,SIP,5P,PREAMPBK	
RT17	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		JL111	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
RT18	2001-000281	R-CARBON;100ohm,5%,1/8W,AA,TP,1.8x3.2mm		JL121	3812-000219	WIRE-NO SHEATH CU;TCWA,300V,52mm(TAPING)	
RT20	2004-000971	R-METAL;470ohm,1%,1/8W,AA,TP,1.8x3.2mm		L111	2701-000326	INDUCTOR-AXIAL;560nH,10%,2.3x3.4mm	
RT21	2004-000971	R-METAL;470ohm,1%,1/8W,AA,TP,1.8x3.2mm		L112	AA26-10004E	TRANS-IF,-,7MG,VIF,-,7mm,8pF,116.7MHz,S	
RT22	2004-000971	R-METAL;470ohm,1%,1/8W,AA,TP,1.8x3.2mm		L113	2701-000299	INDUCTOR-AXIAL;13uH,10%,2.5x3.4mm	
RT23	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		LN113	2701-000136	INDUCTOR-AXIAL;18uH,10%,2.5x3.4mm	
RT24	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		Q112	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
RT25	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		Q113	0501-002049	TR-SMALL SIGNAL;BC858,PNP,330mW,SOT-23,T	
RT26	2001-000734	R-CARBON;4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		Q161	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
RT28	2004-000971	R-METAL;470ohm,1%,1/8W,AA,TP,1.8x3.2mm		Q161	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
RT29	2004-000971	R-METAL;470ohm,1%,1/8W,AA,TP,1.8x3.2mm		QK161	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
RT30	2004-000971	R-METAL;470ohm,1%,1/8W,AA,TP,1.8x3.2mm		QN111	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
RT32	2001-000958	R-CARBON;750ohm,5%,1/8W,AA,TP,1.8x3.2mm		QN112	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
RT33	2001-000958	R-CARBON;750ohm,5%,1/8W,AA,TP,1.8x3.2mm		QN113	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
RT34	2001-000958	R-CARBON;750ohm,5%,1/8W,AA,TP,1.8x3.2mm		QN114	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
RT36	2001-000515	R-CARBON;220ohm,5%,1/8W,AA,TP,1.8x3.2mm		QN161	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
SHIELD	AA63-40014A	SHIELD-CASE,T,-,SPT,TO.5,SC151A,-		QN162	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
TT01	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T		QN163	0501-000727	TR-SMALL SIGNAL;BC848C,NPN,310mW,SOT-23,	
XT01	2801-000214	CRYSTAL-UNIT;27MHz,40ppm,28-AAM,S,40ohm,		R113	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
<b>ASSY-PCB,IF</b>							
*	AA95-90003V	ASSY-PCB,IF,-,CS2777PF/MVTX,SC151A,BG,DK		R114	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
C112	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012,		R115	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
C113	2401-000947	C-AL;22uF,20%,35V,GP,TP,5x11,5		R116	2001-000117	R-CARBON(S);68ohm,5%,1/2W,AA,TP,2.4x6.4m	
C114	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5		R117	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
C115	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,		R118	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
C116	2203-000938	C-CERAMIC,CHIP;470pF,5%,50V,NPO,TP,2012,		R119	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
C118	2203-002392	C-CERAMIC,CHIP;220nF,+80-20%,50V,Y5V,TP,		R120	2007-000738	R-CHIP;30KOHM,5%,1/10W,DA,TP,2012	
C122	2201-000692	C-CERAMIC,DISC;8pF,0.5pF,50V,UJ,TP,5x3,5		R121	2007-000328	R-CHIP;11KOHM,5%,1/10W,DA,TP,2012	
C123	2203-000444	C-CERAMIC,CHIP;1nF,10%,50V,X7R,TP,2012,-		R122	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012	
C124	2201-000692	C-CERAMIC,DISC;8pF,0.5pF,50V,UJ,TP,5x3,5		R126	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
C125	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5		R127	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
C126	2401-001082	C-AL;330nF,20%,50V,GP,TP,5x11,5		R128	2007-000572	R-CHIP;220OHM,5%,1/10W,DA,TP,2012	
C127	2401-000660	C-AL;2.2uF,20%,50V,GP,TP,5x11,5		R129	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012	
C128	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012,		R161	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
C161	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012,		R162	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
C164	2401-000947	C-AL;22uF,20%,35V,GP,TP,5x11,5		R163	2007-000710	R-CHIP;3.9KOHM,5%,1/10W,DA,TP,2012	
C165	2401-000947	C-AL;22uF,20%,35V,GP,TP,5x11,5		R164	2007-000710	R-CHIP;3.9KOHM,5%,1/10W,DA,TP,2012	
C166	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012,		R165	2007-000449	R-CHIP;180OHM,5%,1/10W,DA,TP,2012	
C167	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012,		R166	2007-000449	R-CHIP;180OHM,5%,1/10W,DA,TP,2012	
C181	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		R167	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
C182	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,		R168	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012	
C183	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		R169	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
C184	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,		R170	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012	
C185	2203-000192	C-CERAMIC,CHIP;100nF,+80-20%,50V,Y5V,TP,		R172	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
C186	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		R173	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
CL111	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012,		R174	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
CL112	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012,		R175	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
CN111	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012,		R176	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
CN164	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012,		R177	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
CN165	2203-000260	C-CERAMIC,CHIP;10nF,10%,50V,X7R,TP,2012,		R198	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
				R199	2007-000409	R-CHIP;15KOHM,5%,1/10W,DA,TP,2012	
				RI161	2007-000774	R-CHIP;33KOHM,5%,1/10W,DA,TP,2012	
				RI163	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012	
				RI166	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012	
				RI169	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012	



Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
RK161	2007-000030	R-CHIP:560OHM,5%,1/10W,DA,TP,2012		CP141	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,	
RK162	2007-000981	R-CHIP:5.6KOHM,5%,1/10W,DA,TP,2012		CP142	2401-000199	C-AL:1000uF,20%,6.3V,GP,TP,10x12.5,5	
RK163	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012		CP143	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,5	
RK164	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012		CP144	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216	
RK165	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012		CP145	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216	
RK166	2007-000030	R-CHIP:560OHM,5%,1/10W,DA,TP,2012		CP201	2203-000325	C-CERAMIC,CHIP:12nF,10%,50V,X7R,TP,3216,	
RL112	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2mm		CP203	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
RN111	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012		CP204	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216	
RN112	2007-000981	R-CHIP:5.6KOHM,5%,1/10W,DA,TP,2012		CP205	2401-001271	C-AL:4.7uF,20%,50V,GP,TP,4X7,5MM	
RN113	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012		CP206	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216	
RN114	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012		CP207	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5	
RN117	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		CP208	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216	
RN118	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012		CP209	2401-001914	C-AL:1uF,20%,50V,BP,TP,5x11,5	
RN119	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012		CP210	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
RN161	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012		CP211	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
RN162	2007-000030	R-CHIP:560OHM,5%,1/10W,DA,TP,2012		CP213	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
RN163	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012		CP214	2203-000578	C-CERAMIC,CHIP:220nF,20%,50V,Y5V,TP,3216	
RN164	2007-001071	R-CHIP:6.8KOHM,5%,1/10W,DA,TP,2012		CP215	2401-000603	C-AL:1uF,20%,50V,GP,TP,5x11,5	
RN165	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012		CP216	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216	
RN166	2007-001071	R-CHIP:6.8KOHM,5%,1/10W,DA,TP,2012		CP217	2203-000578	C-CERAMIC,CHIP:220nF,20%,50V,Y5V,TP,3216	
RN167	2007-000941	R-CHIP:47KOHM,5%,1/10W,DA,TP,2012		CP218	2203-002085	C-CERAMIC,CHIP:56nF,10%,50V,X7R,TP,2012,	
SHIELD	AA63-40014A	SHIELD-CASE,T,-,SPT,E,TO.5,SCT51A,-		CP219	2203-000495	C-CERAMIC,CHIP:2.2nF,10%,50V,X7R,TP,2012	
VR111	2103-000665	VR-SEMI:20Kohm,25%,1/5W,SIDE		CP220	2203-000578	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216	
Z111	2904-000253	FILTER-SAW AV:33.9MHZ,DIP10P,ST,17.1DB,P		CP221	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216	
Z112	2903-001019	FILTER-CERAMIC,TR:5.5/5.742MHZ,-,-,TP,		CP301	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5	
Z161	2904-000300	FILTER-SAW AV:38.90MHZ,SIP5K,ST,13.2dB,P		CP302	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216	
Z162	2904-000303	FILTER-SAW AV:38.90MHZ,-,ST,14.6dB,SECAM		CP303	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5	
Z163	2903-000185	FILTER-CERAMIC,BP:5.5MHZ,+75KHz,6dB,-,T		CP304	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216	
Z167	2903-000189	FILTER-CERAMIC,BP:5.74MHZ,+50KHz,8dB,-,T		CP305	2203-000389	C-CERAMIC,CHIP:15pF,5%,50V,NPO,TP,2012,-	
Z168	2903-000189	FILTER-CERAMIC,BP:5.74MHZ,+50KHz,8dB,-,T		CP306	2203-000389	C-CERAMIC,CHIP:15pF,5%,50V,NPO,TP,2012,-	
Z1611	2903-000277	FILTER-CERAMIC,BP:6.0MHZ,60KHz,6.0dB,-,T		CP308	2203-001245	C-CERAMIC,CHIP:82pF,5%,50V,NPO,TP,2012,-	
ZK163	2903-000202	FILTER-CERAMIC,BP:6.5MHZ,+80KHz,6dB,-,T		DP101	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
ZN111	2903-001022	FILTER-CERAMIC,TR:4.5MHZ,-,0.5dB,-,TP,-		DP103	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
ZN161	2903-000135	FILTER-CERAMIC,BP:4.5MHZ,+60KHz,6dB,-,T		DP105	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
ZN162	2903-000135	FILTER-CERAMIC,BP:4.5MHZ,+60KHz,6dB,-,T		DP201	0403-000662	DIODE-ZENER:MTZ3.0B,3.0V,3.01-3.22V,500m	
<b>ASSY-PCB,PIP</b>				ICP101	1204-000530	IC-PAL/NTSC DECODER:TDA9160A,DIP,32P,400	
*				ICP102	1204-000560	IC-DEMOMULATOR:TDA9815,DIP,32P,400MIL,PL	
AA95-90003WASSY-PCB,PIP,-,CS7277PF/MVTS,SCT51A,BG,D				ICP103	AA13-20003F	IC-HYBRID:-,PAP101,SIP,5PPREAMP,BK	
CNP01	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG		ICP105	1204-000635	IC-PICTURE PROCESS:SDA9189X,SOP,32P,350M	
CNP03	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG		ICP201	1002-000206	IC-A/D CONVERTER:SDA9187-2X,6BIT,SOP,28P	
CP101	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216		LP101	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP102	2401-000922	C-AL:22uF,20%,16V,GP,TP,5x5,5		LP102	2701-000219	INDUCTOR-AXIAL:820nH,10%,2.5x3.4mm	
CP103	2203-000429	C-CERAMIC,CHIP:18pF,5%,50V,NPO,TP,2012,-		LP103	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP104	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		LP104	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP105	2203-000717	C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,3216		LP105	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP106	2203-000612	C-CERAMIC,CHIP:22nF,10%,50V,X7R,TP,3216,		LP201	2701-000197	INDUCTOR-AXIAL:5.6uH,10%,2.5x3.4mm	
CP107	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216		LP202	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP108	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216		LP301	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP110	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216		LP302	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP111	2203-000716	C-CERAMIC,CHIP:3.3nF,10%,50V,X7R,TP,2012		OP101	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP112	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5		OP102	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP113	2203-000891	C-CERAMIC,CHIP:4.7nF,10%,50V,X7R,TP,2012		OP103	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
CP114	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216		OP104	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP115	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216		OP105	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP116	2203-000753	C-CERAMIC,CHIP:330nF,+80-20%,50V,Y5V,TP,		OP201	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP117	2401-002619	C-AL:47uF,20%,25V,GP,TP,5x11,5		OP202	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP118	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216		OP203	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
CP120	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216		OP204	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP121	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5		OP205	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP123	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		OP206	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP124	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5		OP302	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP125	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		OP303	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
CP126	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		OP304	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
CP127	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216		OP305	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
CP129	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		RC129	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
CP130	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,		RP101	2007-001208	R-CHIP:82KOHM,5%,1/10W,DA,TP,2012	
CP132	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,		RP103	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
CP133	2203-000221	C-CERAMIC,CHIP:100nF,20%,50V,Y5V,TP,3216		RP104	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
CP134	2401-001026	C-AL:3.3uF,20%,50V,GP,TP,5x11mm,5mm		RP105	2007-000328	R-CHIP:11KOHM,5%,1/10W,DA,TP,2012	
CP135	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		RP106	2007-000774	R-CHIP:33KOHM,5%,1/10W,DA,TP,2012	
CP136	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		RP107	2007-000409	R-CHIP:15KOHM,5%,1/10W,DA,TP,2012	
CP137	2203-000938	C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,		RP108	2007-000493	R-CHIP:2.2KOHM,5%,1/10W,DA,TP,2012	
CP139	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,		RP109	2007-000830	R-CHIP:39KOHM,5%,1/10W,DA,TP,2012	
CP140	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,		RP110	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
				RP111	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
				RP112	2007-000931	R-CHIP:470OHM,5%,1/10W,DA,TP,2012	



Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
D819	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		L865	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
D851	0402-000231	DIODE-RECTIFIER:FMG-G26S,600V,4A,TO-220F	H/SINK	L866	AA27-10001C	COIL-CHOKE:-,100uH,K,-,5.0A,ST,700UH-K(R	
D852	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L		L867	2701-000115	INDUCTOR-AXIAL:1.0uH,10%,2.8x7mm	
D853	0402-000544	DIODE-RECTIFIER:RU4Y,100V,2A,-		L870	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
D854	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	NT801	1404-001045	THERMISTOR-NTC:4.7OHM,15%,2900K,35.0MW,T	
D855	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		NT802	1404-001045	THERMISTOR-NTC:4.7OHM,15%,2900K,35.0MW,T	
D856	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	PC801	0604-001038	PHOTO-COUPLER:TR,130-260%,200mW,DIP-4,ST	
D857	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		PC802	0604-001038	PHOTO-COUPLER:TR,130-260%,200mW,DIP-4,ST	
D858	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		Q801	0503-000153	TR-DARLINGTON:TIP102,NPN,2W,TO-220,TP,10	
D859	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	Q802	0503-000153	TR-DARLINGTON:TIP102,NPN,2W,TO-220,TP,10	
D860	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	Q851	0502-000244	TR-POWER:KSA940,PNP,1.5W,TO-220,-,40-14	
D861	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	Q852	0501-000366	TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L,	
D862	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	Q853	0501-000366	TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L,	
D863	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		Q854	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L,	
D865	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		Q855	0501-000366	TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L,	
DZ801	0403-000299	DIODE-ZENER:MTZ7.5C,7.5V,7.29-7.67V,500m		R801	2006-000296	R-CEMENT:11ohm,5%,5W,CH,BK,9.5x27x9.5mm	
DZ802	0403-000299	DIODE-ZENER:MTZ7.5C,7.5V,7.29-7.67V,500m		R801A	2001-001078	R-CARBON(S):15Kohm,5%,1/2W,AA,TP,2.4x6.4	
DZ803	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m		R802	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4	
DZ804	0403-000662	DIODE-ZENER:MTZ3.0B,3.0V,3.01-3.22V,500m		R802A	2001-001066	R-CARBON(S):110ohm,5%,1/2W,AA,TP,2.4x6.4	
DZ805	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m		R803	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
DZ806	0403-000662	DIODE-ZENER:MTZ3.0B,3.0V,3.01-3.22V,500m		R804	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
DZ851	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m		R805	2001-001055	R-CARBON(S):1.8Kohm,5%,1/2W,AA,TP,2.4x6.	
DZ852	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m		R805A	2001-001143	R-CARBON(S):4.3Kohm,5%,1/2W,AA,TP,2.4x6.	
DZ853	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m		R806	2009-000026	R-METAL PLATE:0.15ohm,10%,5W,CL,TP,5x14x	
DZ857	1203-000451	IC-VOLTAGE REGULATOR:33,TO-92,3P,-,PLAST		R807	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
F801	3601-000461	FUSE-FERRULE:250V,6.3A,TIME-LAG,CERAMIC,		R808	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
F801A	3602-000114	FUSE-HOLDER:-,30mohm		R809	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
F801B	3602-000114	FUSE-HOLDER:-,30mohm		R810	2002-001010	R-COMPOSITION:1.8Mohm,10%,1/2W,AA,TP,3.7	
F851	3601-000399	FUSE-FERRULE:250V,1.6A,TL,GLASS,5.2x20mm		R812	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
F851A	3602-000114	FUSE-HOLDER:-,30mohm		R813	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
F851B	3602-000114	FUSE-HOLDER:-,30mohm		R814	2006-000296	R-CEMENT:11ohm,5%,5W,CH,BK,9.5x27x9.5mm	
F852	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R814A	2001-001078	R-CARBON(S):15Kohm,5%,1/2W,AA,TP,2.4x6.4	
F852A	3602-000114	FUSE-HOLDER:-,30mohm		R815	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
F852B	3602-000114	FUSE-HOLDER:-,30mohm		R816	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
F853	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R817	2001-001055	R-CARBON(S):1.8Kohm,5%,1/2W,AA,TP,2.4x6.	
F853A	3602-000114	FUSE-HOLDER:-,30mohm		R817A	2001-001143	R-CARBON(S):4.3Kohm,5%,1/2W,AA,TP,2.4x6.	
F853B	3602-000114	FUSE-HOLDER:-,30mohm		R818	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4	
F854	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R818A	2001-001066	R-CARBON(S):110ohm,5%,1/2W,AA,TP,2.4x6.4	
F854A	3602-000114	FUSE-HOLDER:-,30mohm		R819	2009-001011	R-METAL PLATE:0.18ohm,10%,5W,CL,TP,5x14x	
F854B	3602-000114	FUSE-HOLDER:-,30mohm		R820	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
F855	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R820A	2001-000107	R-CARBON(S):150Kohm,5%,1/2W,AA,TP,2.4x6.	
F855A	3602-000114	FUSE-HOLDER:-,30mohm		R821	2002-001012	R-COMPOSITION:8.2Mohm,10%,1/2W,AA,TP,3.7	
F855B	3602-000114	FUSE-HOLDER:-,30mohm		R825	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
F856	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R826	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
F856A	3602-000114	FUSE-HOLDER:-,30mohm		R827	2001-001096	R-CARBON(S):2.2ohm,5%,1/2W,AA,TP,2.4x6.4	
F856B	3602-000114	FUSE-HOLDER:-,30mohm		R830	2003-000706	R-METAL OXIDE(S):47Kohm,5%,2W,AA,TP,4.3x	
F857	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R830A	2003-000706	R-METAL OXIDE(S):47Kohm,5%,2W,AA,TP,4.3x	
F857A	3602-000114	FUSE-HOLDER:-,30mohm		R831	2001-000002	R-CARBON(S):200KOHM,5%,1/2W,AA,TP,-	
F857B	3602-000114	FUSE-HOLDER:-,30mohm		R832	2001-000002	R-CARBON(S):200KOHM,5%,1/2W,AA,TP,-	
HC801	AA13-20002K	IC-HYBRID:-,STR-S6709 LF953,SIP,9P,SMPS	H/SINK	R851	2003-000584	R-METAL OXIDE(S):22Kohm,5%,2W,AA,TP,4x12	
HC802	AA13-20002K	IC-HYBRID:-,STR-S6709 LF953,SIP,9P,SMPS	H/SINK	R852	2003-000777	R-METAL OXIDE(S):68ohm,5%,2W,AA,TP,4x12m	
HC851	1203-000580	IC-POWER PRESCALER:130,TO-220,3P,-,PLAST		R853	2001-001152	R-CARBON(S):47Kohm,5%,1/2W,AA,TP,2.4x6.4	
HC852	1203-000187	IC-POS.ADJUST REG.:431,TO-92,3P,-,PLAST		R854	2001-001135	R-CARBON(S):36Kohm,5%,1/2W,AA,TP,2.4x6.4	
L801	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R855	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4	
L801A	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R856	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4	
L802	2902-001001	FILTER-LINE:2mH,+3TURNS,0.233ohm		R857	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
L803	2902-001001	FILTER-LINE:2mH,+3TURNS,0.233ohm		R858	2001-001144	R-CARBON(S):4.7Kohm,5%,1/2W,AA,TP,2.4x6.	
L804	2902-001001	FILTER-LINE:2mH,+3TURNS,0.233ohm		R859	2001-000117	R-CARBON(S):68ohm,5%,1/2W,AA,TP,2.4x6.4	
L805	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R860	2001-001144	R-CARBON(S):4.7Kohm,5%,1/2W,AA,TP,2.4x6.	
L806	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R862	2001-000052	R-CARBON(S):3.3Kohm,5%,1/2W,AA,TP,2.4x6.	
L807	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R863	2001-000052	R-CARBON(S):3.3Kohm,5%,1/2W,AA,TP,2.4x6.	
L848	2902-001001	FILTER-LINE:2mH,+3TURNS,0.233ohm		R866	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4	
L849	2902-001001	FILTER-LINE:2mH,+3TURNS,0.233ohm		R867	2001-000109	R-CARBON(S):470ohm,5%,1/2W,AA,TP,2.4x6.4	
L851	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R870	2001-001103	R-CARBON(S):20Kohm,5%,1/2W,AA,TP,2.4x6.4	
L852	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R871	2001-001078	R-CARBON(S):15Kohm,5%,1/2W,AA,TP,2.4x6.4	
L853	AA27-10002L	COIL-CHOKE:-,24UH,K,-,2A,-,24UH-K,10X10M		R872	2004-001983	R-METAL:2.49Kohm,1%,1/2W,AA,TP,2.4x6.4	
L854	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R873	2008-000270	R-FUSIBLE:3.3ohm,5%,1/2W,AA,TP,4.7x11mm	
L855	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R890	2001-000052	R-CARBON(S):3.3Kohm,5%,1/2W,AA,TP,2.4x6.	
L856	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		R891	2001-000052	R-CARBON(S):3.3Kohm,5%,1/2W,AA,TP,2.4x6.	
L857	AA27-10001C	COIL-CHOKE:-,100uH,K,-,5.0A,ST,700UH-K(R		R896	2001-001126	R-CARBON(S):300ohm,5%,1/2W,AA,TP,2.4x6.4	
L858	AA27-10002L	COIL-CHOKE:-,24UH,K,-,2A,-,24UH-K,10X10M		RL801	3501-001040	RELAY-POWER:12VDC,500mW,10A,1FormA,15mS,	
L859	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400		T801	AA26-20004H	TRANS-SWITCHING:-,80-280V,-,EER534521,45	
L860	AA27-10001C	COIL-CHOKE:-,100uH,K,-,5.0A,ST,700UH-K(R		T802	AA26-20004G	TRANS-SWITCHING:-,90-260V,KS,EER534521,4	
L861	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400					
L862	AA27-10001C	COIL-CHOKE:-,100uH,K,-,5.0A,ST,700UH-K(R					
L863	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400					
L864	AA27-10001C	COIL-CHOKE:-,100uH,K,-,5.0A,ST,700UH-K(R					

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
<b>ASSY-CABINET,MASK</b>							
*	AA91-10132C	ASSY-CABINET,MASK;- ,HB,BLK,WP-1000,SVP-4		CASTER	AA60-10051A	SCREW-WOOD;PH,+ ,M4,L16,ZPC(BLK),SWRCH18A	
MASK	AA64-30512B	CABINET-MASK;- ,SVP431J,WP1000,HIPS,HB,BL		SPK+CM	AA60-10051A	SCREW-WOOD;PH,+ ,M4,L16,ZPC(BLK),SWRCH18A	
CABMAS	AA61-40025A	BOSS-CABINET;S4388,HIPS,HB,NTR,-,-		BB+CM	AA60-10051B	SCREW-WOOD;RH,+ ,M3.5,L12,ZPC(YEL),SWRCH1	
CABMAS	AA61-40026A	BOSS-CABINET;S4388.5288,HIPS,HB,NTR,-,-		BM+CM	AA60-10051B	SCREW-WOOD;RH,+ ,M3.5,L12,ZPC(YEL),SWRCH1	
BADGE	AA64-70105A	BADGE-BRAND;AL,SS FLAT,SILVER,L70,-,-,-		BBW+CM	AA60-10051B	SCREW-WOOD;RH,+ ,M3.5,L12,ZPC(YEL),SWRCH1	
				SCREW	AA60-10050X	SCREW-WOOD;FH,+ ,M3.5,L32,ZPC(YEL),SWRCH1	
				SPACER	AA63-60126C	SPACER-FELT;FELT,T2,BLK,938X15,PRJT43,-	
<b>ASSY-HOLDER,CONTROL</b>				<b>ASSY-CABINET</b>			
*	AA91-60049E	ASSY-HOLDER,CONTROL;-,-,-,-,WP1000 SPM43		*	AA90-70061G	ASSY-CABINET;S4388,SPM4388PF/SGEX	
DY01	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T		HV+BCM	AA60-10011A	SCREW-TAPTITE;HH,+ ,PC,M4,L12,ZPC(BLK),SW	
DY02	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T		CFB+CM	AA60-10011A	SCREW-TAPTITE;HH,+ ,PC,M4,L12,ZPC(BLK),SW	
DY03	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T		CBT+CM	AA60-10011A	SCREW-TAPTITE;HH,+ ,PC,M4,L12,ZPC(BLK),SW	
DY04	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T		CBB+CM	AA60-10011A	SCREW-TAPTITE;HH,+ ,PC,M4,L12,ZPC(BLK),SW	
ZDY01	0403-000654	DIODE-ZENER;MTZ12B,12V,11.44-12.03V,500m		BS+CFT	AA60-10011A	SCREW-TAPTITE;HH,+ ,PC,M4,L12,ZPC(BLK),SW	
ZDY02	0403-000654	DIODE-ZENER;MTZ12B,12V,11.44-12.03V,500m		AC+BCM	AA60-10011A	SCREW-TAPTITE;HH,+ ,PC,M4,L12,ZPC(BLK),SW	
ZDY03	0403-000654	DIODE-ZENER;MTZ12B,12V,11.44-12.03V,500m		FOCUS+	AA60-10050W	SCREW-	
ZDY04	0403-000654	DIODE-ZENER;MTZ12B,12V,11.44-12.03V,500m		WOOD;W/H,+ ,M4,20,ZPC(BLK),SWRCH18A			
SWY01	3404-000178	SWITCH-TACT;12V,50mA,90-150gf,6x6mm,SPST		CFT+CM	AA60-10050W	SCREW-	
SWY02	3404-000178	SWITCH-TACT;12V,50mA,90-150gf,6x6mm,SPST		WOOD;W/H,+ ,M4,20,ZPC(BLK),SWRCH18A			
SWY03	3404-000178	SWITCH-TACT;12V,50mA,90-150gf,6x6mm,SPST		CBT+CM	AA60-10050W	SCREW-	
SWY04	3404-000178	SWITCH-TACT;12V,50mA,90-150gf,6x6mm,SPST		WOOD;W/H,+ ,M4,20,ZPC(BLK),SWRCH18A			
SWY05	3404-000178	SWITCH-TACT;12V,50mA,90-150gf,6x6mm,SPST		BRKT	AA61-10361A	BRACKET-MIRROR;- ,S5288,SECC-1,T1.0,-,-,-	
SWY06	3404-000178	SWITCH-TACT;12V,50mA,90-150gf,6x6mm,SPST		BRKT	AA61-10366A	BRACKET-SCREEN,SIDE;- ,S4388,SECC-1,T1.0,-	
SWY07	3404-000178	SWITCH-TACT;12V,50mA,90-150gf,6x6mm,SPST		BRKT	AA61-10367A	BRACKET-SCREEN,BOT;- ,S4388,SECC-1,T1.0,-	
CN902	AA39-20045A	LEAD-CONNECTOR,ASSY;- ,35022-0011,S,11P,3		SPACER	AA63-60052C	SPACER-MIRROR;PVC,- ,BLK,HB SOFT,S5288,-	
SCREW	AA60-10008A	SCREW-TAPPING;TH,+ ,M3,L10,ZPC(YEL),SWRCH		SPACER	AA63-60052D	SPACER-MIRROR;PVC,- ,BLK,HB SOFT,S5288,-	
BRKT	AA61-10080A	BRACKET-HOLDER;- ,S4388,STS304L,T0.5,-,-,-		BACK-T	AA64-30433A	CABINET-BACK,T;- ,S4388,- ,HIPS,HB,BLK,-,-	
HOLCON	AA61-20102A	HOLDER-CONTROL;-,- ,ABS,HB,BLK,-		BACK-B	AA64-30434A	CABINET-BACK,BOT;- ,PRJT,- ,HIPS,VO,BLK,-,-	
HOLKEY	AA61-20114A	HOLDER-KEY;-,- ,ABS,HB,BLK,-		C-CORD	AA65-30008A	CLAMP-CORD;PE,HB,BLK,-,-,-	
L/DOOR	AA61-30001A	LATCH-DOOR;-,-,- ,KIFUCO LA701,-		MIRROR	AA67-20025A	MIRROR-BACK SURFACE;43,GLASS,3.0,- ,BSM,	
SPRING	AA61-60048A	SPRING-CS;- ,SUS304,0.8,OD9.6,H6,N5,-,-,-		SCREEN	AA67-70030A	SCREEN-TINT;- ,43 INCH,V,LENTI,PVMM,A,- ,T3,	
DAMPER	AA61-80005B	DAMPER-GEAR;-,-,- ,20G,- ,OIL,-		SPACER	AA63-60052E	SPACER-MIRROR;HARD PVC,- ,BLK,- ,SVP5288,-	
SPACER	AA63-60002V	SPACER-FELT;FELT,TO.3,BLK,60X40,-,-		BRKT	AA61-11008A	BRACKET-MIRROR,SIDE;- ,SPT431J,SECC,T1.0,-	
SPACER	AA63-60002W	SPACER-FELT;FELT,TO.5,BLK,30X10,-,-		BRKT	AA61-10380B	BRACKET-CRT,MAIN;- ,SVP-521JB,SECC,T1.6,N	
KNOCON	AA64-10214C	KNOB-CONTROL,ASSY;- ,SPM5288PF,- ,ABS,HB,B		SPACER	AA63-60119A	SPACER-COVER,BRACKET;FELT,TO.5,BLK,630X3	
DOOR-B	AA64-50082D	DOOR-BOTTOM;- ,SPM4388,WP1000,ABS,HB,BLK,		CBB+CM	AA60-10050W	SCREW-WOOD;W/H,+ ,M4,20,ZPC(BLK),SWRCH18A	
<b>ASSY-CABINET,BOT</b>							
*	AA91-10131H	ASSY-CABINET,BOT;- ,HIPS,VO,WP1000,SPM438		BCM+CM	AA60-10001A	SCREW-ASSY;WP,- ,M6,L20,SCM30C,- ,ZPC(YE	
BK+C/G	6002-000512	SCREW-TAPPING;RH,+ ,2,M4,L12,ZPC(BLK),SWR		BM+ACM	6003-000334	SCREW-TAPTITE;RH,+ ,2S,M3,L6,ZPC(YEL),SWR	
BRKT	AA61-10160A	BRACKET-MASK;- ,S4388,SBHG-1,T1.0,-,-,-		APAV+A	6003-001024	SCREW-TAPTITE;RWH,+ ,B,M4,L12,ZPC(YEL),SW	
SPRING	AA61-60003A	SPRING-CS;- ,SUS304,0.5,OD7.H16,N7,-,-,-		BM+CBT	6003-001026	SCREW-TAPTITE;RH,+ ,B,M4,L15,ZPC(BLK),SWR	
INDLED	AA64-40218A	INDICATOR-LED;- ,S4388,- ,PC,-,-,-		BRKT	AA61-11007B	BRACKET-MIRROR;- ,SVP-434JA,SECC,T1.0,BLK	
KNOPOW	AA64-10360D	KNOB-POWER;- ,SPM4388PF,WP-1000,ABS,HB,BL		CFT+AH	6003-001026	SCREW-TAPTITE;RH,+ ,B,M4,L15,ZPC(BLK),SWR	
BOTTOM	AA64-31070C	CABINET-BOTTOM;- ,SPM4388,WP1000,HIPS,VO,		<b>REMOCON</b>			
COVER	AA63-30054A	COVER-GRILLE;-,- ,SACHUL,HIPS,VO,BLK,-,-		*	AA59-10079T	REMOCON;- ,TM50,RM130,54,GOLD,SS	
BADGE	AA64-70114A	BADGE;AL,TITANUM,-,-,- ,SPM4388PF,-		<b>ASSY-CHASSIS,PART</b>			
<b>ASSY-CABINET,MID</b>							
*	AA91-10325A	ASSY-CABINET,MID;- ,SVP-431J(4388),WOOD,-		*	AA90-30113C	ASSY-CHASSIS,PART;- ,SPM5288PF	
BRKT	AA61-10049A	BRACKET-MODULE;- ,S4388,SECC,TO.6,-,-,-		PCB+BP	AA60-10011A	SCREW-TAPTITE;HH,+ ,PC,M4,L12,ZPC(BLK),SW	
BRKT	AA61-10165A	BRACKET-BOTTOM;- ,PRJT,SECC,T1.0,NTR,-,-		TBA+HC	AA60-10011A	SCREW-TAPTITE;HH,+ ,PC,M4,L12,ZPC(BLK),SW	
BRKT	AA61-10387A	BRACKET-GRILLE;- ,SVP-462J,SECC-1,TO.5,-		HC+HC	AA60-10011A	SCREW-TAPTITE;HH,+ ,PC,M4,L12,ZPC(BLK),SW	
HOLDER	AA61-20101A	HOLDER-MASK,AR;- ,S4388,ABS,HB,BLK,-		BCM+BP	AA60-10011A	SCREW-TAPTITE;HH,+ ,PC,M4,L12,ZPC(BLK),SW	
HOLDER	AA61-20101B	HOLDER-MASK,AL;- ,S4388,ABS,HB,BLK,-		TER/B	AA63-40138A	TERMINAL-BOARD,ANT;- ,HIPS,- ,VO,BLK,SPM52	
HOLDER	AA61-20124A	HOLDER-MASK,B;- ,S4388,ABS,HB,BLK,-		IN-B	AA64-60286A	INLAY-BACK;SPM5288PF,- ,PS,TO.5,BLK,-,-	
HOLDER	AA61-20136A	HOLDER-MASK,PIN;- ,S4388,NYLON,- ,BLK,#066		HOLD/C	AA61-20142B	HOLDER-CHASSIS;- ,SVP-462J,ABS,VO,GRY,-	
RAIL	AA61-70022A	RAIL-PCB;- ,S4388,ABS,VO,NTR,-,-		H-CORD	AA61-20135B	HOLDER-CORD;-,- ,HIPS,VO,BLK,-	
SPK	3001-000148	SPEAKER;20W,8ohm,90dB,2KHz		HV	AA61-10149A	BRACKET-HV;- ,S4388,SECC,T1.0,-,-,-	
SPK1	3001-000148	SPEAKER;20W,8ohm,90dB,2KHz		HOLCHA	AA65-30112A	CLAMP-WIRE-NYLON,VO,BLK,- ,PRJT,-	
SPK	3001-000279	SPEAKER;30W,8ohm,91dB,20Hz		TB+JAC	6003-001026	SCREW-TAPTITE;RH,+ ,B,M4,L15,ZPC(BLK),SWR	
SPK1	3001-000279	SPEAKER;30W,8ohm,91dB,20Hz		PCB+HC	6003-001023	SCREW-TAPTITE;RWH,+ ,B,M3,L10,ZPC(YEL),SW	
CN604	AA39-20507A	LEAD CONNECTOR-ASSY;- ,YSH025-04,REC,4P,7		HV+BH	6003-001023	SCREW-TAPTITE;RWH,+ ,B,M3,L10,ZPC(YEL),SW	
CN603	AA39-20507B	LEAD CONNECTOR-ASSY;- ,YSH025-04,REC,4P,1		DF+FBT	6003-001023	SCREW-TAPTITE;RWH,+ ,B,M3,L10,ZPC(YEL),SW	
MIDDLE	AA64-31069A	CABINET-MIDDLE;- ,SVP-431J,- ,WOOD,-,-,-,-		<b>ASSY-PCB,CONV MLD</b>			
SPACER	AA63-60001X	SPACER-FELT;FELT,TO.5,BLK,330X15,-,-		*	AA95-90037A	ASSY-PCB,CONV MDL;- ,SPM5288PF,SPT51A,PAL	
BRKT	AA61-11003A	BRACKET-BACK;- ,PROJ,SECC,T1.0,-,-,-		C103	2203-000239	C-CERAMIC,CHIP;100pf,5%,50V,NPO,TP,2012,	
SPACER	AA63-60126A	SPACER-FELT;FELT,T2,BLK,1160X15,PRJT43,5		C104	2203-001680	C-CERAMIC,CHIP;68nf,20%,50V,Y5V,TP,2012,	
NUT	AA60-20050A	NUT-INSERT;M6,L8,ZPC(WHT)- ,PROJECTION		C105	2203-000239	C-CERAMIC,CHIP;100pf,5%,50V,NPO,TP,2012,	

Electric Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C108	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		C187	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
C109	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,		C188	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm	
C110	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP		C189	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm	
C111	2203-000274	C-CERAMIC,CHIP:10pF,0.25pF,50V,NPO,TP,20		C190	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
C112	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		C191	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C113	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		C193	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP6032,2.9mm	
C114	2203-001002	C-CERAMIC,CHIP:47pF,5%,50V,NPO,TP,2012,-		C194	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
C115	2203-001002	C-CERAMIC,CHIP:47pF,5%,50V,NPO,TP,2012,-		C195	2404-000275	C-TA,CHIP:100uF,10%,10V,-,TP7343,7.3mm	
C116	2203-000374	C-CERAMIC,CHIP:15nF,10%,50V,X7R,TP,2012,		C196	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-	
C117	2404-000275	C-TA,CHIP:100uF,10%,10V,-,TP7343,7.3mm		C197	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-	
C118	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		C198	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-	
C119	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		C201	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP	
C121	2203-000495	C-CERAMIC,CHIP:2.2nF,10%,50V,X7R,TP,2012		C202	2203-000683	C-CERAMIC,CHIP:27pF,5%,50V,NPO,TP,2012,-	
C122	2203-000609	C-CERAMIC,CHIP:22nF,10%,50V,X7R,TP,2012,		C203	2203-000429	C-CERAMIC,CHIP:18pF,5%,50V,NPO,TP,2012,-	
C124	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		C204	2203-000683	C-CERAMIC,CHIP:27pF,5%,50V,NPO,TP,2012,-	
C125	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		C205	2203-001002	C-CERAMIC,CHIP:47pF,5%,50V,NPO,TP,2012,-	
C126	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		C207	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
C127	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		C208	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
C128	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		C209	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
C129	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		C210	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP6032,2.9mm	
C130	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		C220	2203-001002	C-CERAMIC,CHIP:47pF,5%,50V,NPO,TP,2012,-	
C131	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP		C301	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-	
C132	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		C302	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-	
C133	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		C303	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-	
C134	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP		C304	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP	
C135	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP		CNZ01	3711-001164	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,ANGLE,-	
C136	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		CNZ02	3711-001094	CONNECTOR-HEADER:BOX,7P,1R,2.5mm,ANGLE,-	
C137	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		CNZ03	3711-001049	CONNECTOR-HEADER:BOX,6P,1R,2.5mm,ANGLE,-	
C138	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP		CP101	2901-000233	FILTER-EMI SMD:50V,300mA,-,330pF,4.5x1.8	
C139	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP		CP102	2901-000233	FILTER-EMI SMD:50V,300mA,-,330pF,4.5x1.8	
C140	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		CP103	2901-000229	FILTER-EMI SMD:50V,300mA,-,22nF,4.5x1.8x	
C141	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		CP104	2901-000229	FILTER-EMI SMD:50V,300mA,-,22nF,4.5x1.8x	
C142	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP		CP105	2901-000229	FILTER-EMI SMD:50V,300mA,-,22nF,4.5x1.8x	
C143	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP6032,2.9mm		CP106	2901-000229	FILTER-EMI SMD:50V,300mA,-,22nF,4.5x1.8x	
C144	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		CP107	2901-000229	FILTER-EMI SMD:50V,300mA,-,22nF,4.5x1.8x	
C145	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,		CP108	2901-000232	FILTER-EMI SMD:50V,300mA,-,10nF,4.5x1.8x	
C146	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,		CP109	2901-000232	FILTER-EMI SMD:50V,300mA,-,10nF,4.5x1.8x	
C147	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		CP110	2901-000232	FILTER-EMI SMD:50V,300mA,-,10nF,4.5x1.8x	
C148	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,		CP120	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2	
C149	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,		CP121	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2	
C150	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		CP122	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2	
C151	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,		CP123	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2	
C152	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,		CP124	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2	
C153	2404-000275	C-TA,CHIP:100uF,10%,10V,-,TP,7343,7.3mm		CP125	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2	
C154	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP6032,2.9mm		CP126	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2	
C155	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012		CP127	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2	
C156	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012		D100	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,	
C157	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012		D101	0405-000128	DIODE-VARACTOR:1SV214,30V,10nA,USC,TP	
C158	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012		D104	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C159	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012		D105	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,	
C160	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012		D106	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,	
C161	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		D110	0401-000008	DIODE-SWITCHING:DAN217,80V,100mA,SOT-23,	
C162	2203-001077	C-CERAMIC,CHIP:56pF,5%,50V,NPO,TP,2012,-		D111	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,	
C163	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm		D112	0401-000008	DIODE-SWITCHING:DAN217,80V,100mA,SOT-23,	
C164	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012		D113	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,	
C165	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		D114	0401-000008	DIODE-SWITCHING:DAN217,80V,100mA,SOT-23,	
C166	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm		D115	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,	
C167	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012		D118	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C168	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		D119	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C169	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		D200	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C170	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm		D201	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C171	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012		D202	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C172	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		D203	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C173	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm		D204	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C174	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012		D205	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C175	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		D206	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C176	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm		D207	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m	
C177	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012		IC104	1001-000105	IC-ANALOG SWITCH:CD4066BM,BILATERAL CMOS	
C178	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		IC106	1201-000167	IC-OP AMP:358,SOP,8P,150MIL,DUAL,100V/mV	
C179	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm		IC112	AA13-30006B	IC-MCU:-,AT89C52-24,-,DIP,-,40P,600MI	
C180	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012		IC113	1002-000131	IC-A/D&D/A CONVERTER:PCM55HP,16BIT,SOP,2	
C181	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		IC114	1002-000131	IC-A/D&D/A CONVERTER:PCM55HP,16BIT,SOP,2	
C182	2203-001077	C-CERAMIC,CHIP:56pF,5%,50V,NPO,TP,2012,-		IC115	1002-000131	IC-A/D&D/A CONVERTER:PCM55HP,16BIT,SOP,2	
C183	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm		IC132	0801-001156	IC-CMOS LOGIC:74HC4066,BILATERAL SWITCH,	
C184	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm		IC133	0801-001156	IC-CMOS LOGIC:74HC4066,BILATERAL SWITCH,	
C185	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm		IC135	1001-000105	IC-ANALOG SWITCH:CD4066BM,BILATERAL CMOS	
C186	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP5054,1.5mm		IC136	1001-000105	IC-ANALOG SWITCH:CD4066BM,BILATERAL CMOS	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
IC141	1103-000139	IC-EEPROM:24C16,2KX8BIT,DIP,8P,300MIL,10		R108	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
IC143	AA13-10001X	IC-ASIC:-,DCS04,QFP,160P,CONV CONTROLL		R109	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
IC144	1203-000641	IC-RESET:7442,TO-92,3P,-,PLASTIC,-,0.3/7		R110	2007-000409	R-CHIP:15KOHM,5%,1/10W,DA,TP,2012	
L100	AA26-10001Y	TRANS-IF:-,5CA,IF,10uH,5mm,-,2.52MHz,ST		R111	2007-000572	R-CHIP:220OHM,5%,1/10W,DA,TP,2012	
L102	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm		R112	2007-000409	R-CHIP:15KOHM,5%,1/10W,DA,TP,2012	
L103	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm		R113	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
L104	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm		R114	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
L105	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm		R115	2007-000830	R-CHIP:39KOHM,5%,1/10W,DA,TP,2012	
L106	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm		R116	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
L107	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm		R118	2007-000830	R-CHIP:39KOHM,5%,1/10W,DA,TP,2012	
L108	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R119	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
L109	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R120	2007-000415	R-CHIP:15OHM,5%,1/10W,DA,TP,2012	
L110	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R121	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
L111	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R122	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
L112	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R123	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012	
L113	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm		R124	2103-000677	VR-SEMI:5Kohm,25%,1/5W,TOP	
L121	2901-000297	FILTER-EMI ON BOARD:-,3A,-,-,3.5x5,TP,-		R125	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012	
Q100	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R130	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q101	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R131	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q102	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R132	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q103	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R133	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q104	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R134	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q105	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R135	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q106	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R136	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q107	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R137	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
Q108	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R138	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q109	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R139	2007-001097	R-CHIP:62Kohm,5%,1/10W,DA,TP,2012	
Q110	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R140	2007-000304	R-CHIP:10Mohm,5%,1/10W,DA,TP,2012	
Q111	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R141	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q112	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R142	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
Q113	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R159	2007-000221	R-CHIP:1.2KOHM,5%,1/10W,DA,TP,2012	
Q114	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R160	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
Q115	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R162	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
Q116	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R163	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
Q117	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R164	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
Q118	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R165	2007-000380	R-CHIP:13KOHM,5%,1/10W,DA,TP,2012	
Q119	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R167	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q120	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R168	2007-000653	R-CHIP:27KOHM,5%,1/10W,DA,TP,2012	
Q121	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R169	2007-000029	R-CHIP:00HM,5%,1/10W,DA,TP,2012	
Q122	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R171	2007-000029	R-CHIP:00HM,5%,1/10W,DA,TP,2012	
Q123	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R181	2007-000221	R-CHIP:1.2KOHM,5%,1/10W,DA,TP,2012	
Q124	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R182	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q125	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R183	2007-000686	R-CHIP:3.3KOHM,5%,1/10W,DA,TP,2012	
Q126	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R184	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q127	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R185	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q128	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R186	2007-000221	R-CHIP:1.2KOHM,5%,1/10W,DA,TP,2012	
Q129	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R187	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q130	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R188	2007-000686	R-CHIP:3.3KOHM,5%,1/10W,DA,TP,2012	
Q131	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R189	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q132	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R190	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q133	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R191	2007-000221	R-CHIP:1.2KOHM,5%,1/10W,DA,TP,2012	
Q134	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R192	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q135	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R193	2007-000686	R-CHIP:3.3KOHM,5%,1/10W,DA,TP,2012	
Q136	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R194	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q137	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-		R195	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q138	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23		R196	2007-000300	R-CHIP:10KOHM,5%,1/10W,DA,TP,2012	
Q139	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23		R197	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
Q140	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23		R198	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q141	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23		R199	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
Q142	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23		R200	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q143	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23		R201	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
Q144	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23		R202	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q145	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23		R203	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
Q200	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-		R204	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q201	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-		R205	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
Q202	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-		R206	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q203	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-		R207	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
Q204	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-		R208	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012	
Q205	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-		R209	2003-002026	R-METAL OXIDE(S):4.7ohm,5%,1W,AF,TP,2.5x	
R100	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012		R210	2003-002026	R-METAL OXIDE(S):4.7ohm,5%,1W,AF,TP,2.5x	
R101	2007-000282	R-CHIP:100KOHM,5%,1/10W,DA,TP,2012		R211	2003-002026	R-METAL OXIDE(S):4.7ohm,5%,1W,AF,TP,2.5x	
R102	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012		R212	2007-000030	R-CHIP:560OHM,5%,1/10W,DA,TP,2012	
R103	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012		R213	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	
R104	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012		R214	2007-000981	R-CHIP:5.6KOHM,5%,1/10W,DA,TP,2012	
R105	2007-000586	R-CHIP:22KOHM,5%,1/10W,DA,TP,2012		R215	2007-000872	R-CHIP:4.7KOHM,5%,1/10W,DA,TP,2012	
R106	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012		R216	2007-000030	R-CHIP:560OHM,5%,1/10W,DA,TP,2012	
R107	2007-000468	R-CHIP:1KOHM,5%,1/10W,DA,TP,2012		R217	2007-000290	R-CHIP:100OHM,5%,1/10W,DA,TP,2012	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R218	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012		R295	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012	
R219	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012		R296	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012	
R220	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012		R297	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R221	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012		R301	2007-001113	R-CHIP;680KOHM,5%,1/10W,DA,TP,2012	
R222	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012		R302	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
R223	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012		R310	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R224	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012		R311	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R225	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012		R312	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R226	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012		R313	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R227	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012		R314	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R228	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012		R315	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012	
R229	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012		R316	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012	
R230	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012		R318	2007-000029	R-CHIP;0OHM,5%,1/10W,DA,TP,2012	
R231	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012		X1	2801-001476	CRYSTAL-UNIT;12.0MHz,50ppm,28-ABQ,S,30oh	
R232	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012		X2	2801-000226	CRYSTAL-UNIT;3.579545MHz,20ppm,28-AAAM,15	
R233	2007-000290	R-CHIP;100OHM,5%,1/10W,DA,TP,2012					
R234	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012					
R235	2007-000872	R-CHIP;4.7KOHM,5%,1/10W,DA,TP,2012					
R236	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012					
R237	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012					
R238	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012					
R239	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012					
R240	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012					
R241	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012					
R242	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012					
R243	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012					
R244	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012					
R245	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012					
R246	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012					
R247	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012					
R248	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012					
R249	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012					
R250	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012					
R251	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012					
R252	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012					
R253	2007-001039	R-CHIP;56KOHM,5%,1/10W,DA,TP,2012					
R254	2007-000030	R-CHIP;560OHM,5%,1/10W,DA,TP,2012					
R255	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012					
R256	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012					
R257	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012					
R258	2007-000586	R-CHIP;22KOHM,5%,1/10W,DA,TP,2012					
R259	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012					
R260	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012					
R261	2007-001118	R-CHIP;680OHM,5%,1/10W,DA,TP,2012					
R262	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012					
R263	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012					
R264	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012					
R265	2007-001118	R-CHIP;680OHM,5%,1/10W,DA,TP,2012					
R266	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012					
R267	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012					
R268	2007-001118	R-CHIP;680OHM,5%,1/10W,DA,TP,2012					
R269	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012					
R270	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012					
R271	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012					
R272	2007-001118	R-CHIP;680OHM,5%,1/10W,DA,TP,2012					
R273	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012					
R274	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012					
R275	2007-001118	R-CHIP;680OHM,5%,1/10W,DA,TP,2012					
R276	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012					
R277	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012					
R278	2007-000518	R-CHIP;2.7KOHM,5%,1/10W,DA,TP,2012					
R279	2007-001118	R-CHIP;680OHM,5%,1/10W,DA,TP,2012					
R280	2007-000981	R-CHIP;5.6KOHM,5%,1/10W,DA,TP,2012					
R281	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012					
R282	2007-000282	R-CHIP;100KOHM,5%,1/10W,DA,TP,2012					
R283	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012					
R284	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012					
R285	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012					
R286	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012					
R287	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012					
R288	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012					
R289	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012					
R290	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012					
R291	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012					
R292	2007-000300	R-CHIP;10KOHM,5%,1/10W,DA,TP,2012					
R293	2007-000355	R-CHIP;12KOHM,5%,1/10W,DA,TP,2012					
R294	2007-000468	R-CHIP;1KOHM,5%,1/10W,DA,TP,2012					

### ASSY-CRT-(R)

*	AA94-00089A	ASSY-CRT-(R);16LFM00REA,+380MG,7',BARE,S	
BHL+CR	6001-000059	SCREW-MACHINE;TH,+,M4,L10,ZPC(BLK),SWRCH	
LA+CR	6001-000059	SCREW-MACHINE;TH,+,M4,L10,ZPC(BLK),SWRCH	
CRT	AA03-10021K	CRT-MONO;-P16LFM00RFA(AU),-,7.90DEG,9	
D/Y	AA27-50003W	DEFLECTION-YOKE;-DPD-4274BL-A,46/PJT,-	
C/Y	AA27-60003C	MAGNET-CONVERGENCE;-JH92LTU-SC-20,29,1m	
SCREW	AA60-10050MS	SCREW-ASSY;-HH,+,M6,L16,SWRCH18A,ZPC(YE	
BRKT	AA61-10030A	BRACKET-LENS;-S4388,SECC,T1.6,-,-,-	
HOLDER	AA61-20125A	HOLDER-SPACER;-S43.5288,ABS,HB,BLK,HR-0	
SP-DY	AA63-60025A	SPACER-DY;NEOPRENE,-,BLK,V0,S4388,-	
SP/LEN	AA63-60039A	SPACER-LENS;SPONGE,T2.0,BLK,W110,S4388,-	
SPA	AA63-60059A	SPACER-FELT;FELT,TO.5,BLK,CRT,-,-	
SPA	AA63-60111A	SPACER-CRT;EPDM,-,-,-,S4388,5288,-	
SPA	AA63-60125A	SPACER-C,ELEMENT;EPDM,3.2,BLK,-,PROJECTI	
BRKT	AA61-10381A	BRACKET-CRT;-S4388,5288,SECC,T1.6,-,-,-	
LENS	AA67-10036A	LENS-ASSY;43INCH,SSM-75RS-43,-,SEKINOS,C	
LENS	AA67-10038A	LENS;43INCH,SSM-75RS-43,-,SEKINOS,R	
HOLDER	AA61-00009A	HOLDER—CAP;-PJT,-,-,BLK,-	
SPACER	AA63-00011A	SPACER—CAP;EPDM RUBBER,-,BLK,-,PJT,-	
CASE	AA64-00066A	CASE—COUPLER,R/B;-PJT,-,ALDC8,-,BLK,-,-	

### ASSY-CRT

*	AA94-00090A	ASSY-CRT;16LFM00HLA,+380MG,7',BARE,SPM-	
BHL+CR	6001-000059	SCREW-MACHINE;TH,+,M4,L10,ZPC(BLK),SWRCH	
LA+CR	6001-000059	SCREW-MACHINE;TH,+,M4,L10,ZPC(BLK),SWRCH	
CRT	AA03-10021L	CRT-MONO;-P16LFM00HLA(AU),-,7.90DEG,9	
D/Y	AA27-50003W	DEFLECTION-YOKE;-DPD-4274BL-A,46/PJT,-	
C/Y	AA27-60003C	MAGNET-CONVERGENCE;-JH92LTU-SC-20,29,1m	
SCREW	AA60-10050MS	SCREW-ASSY;-HH,+,M6,L16,SWRCH18A,ZPC(YE	
BRKT	AA61-10030A	BRACKET-LENS;-S4388,SECC,T1.6,-,-,-	
HOLDER	AA61-20125A	HOLDER-SPACER;-S43.5288,ABS,HB,BLK,HR-0	
SPA	AA63-60025A	SPACER-DY;NEOPRENE,-,BLK,V0,S4388,-	
SPA	AA63-60039A	SPACER-LENS;SPONGE,T2.0,BLK,W110,S4388,-	
SPA	AA63-60059A	SPACER-FELT;FELT,TO.5,BLK,CRT,-,-	
SPA	AA63-60111A	SPACER-CRT;EPDM,-,-,-,S4388,5288,-	
SPA	AA63-60125A	SPACER-C,ELEMENT;EPDM,3.2,BLK,-,PROJECTI	
BRKT	AA61-10381A	BRACKET-CRT;-S4388,5288,SECC,T1.6,-,-,-	
LENS	AA67-10036A	LENS-ASSY;43INCH,SSM-75RS-43,-,SEKINOS,C	
LENS	AA67-10039A	LENS;-SSM-75RS-43,-,GRN C-ELEMENT	
HOLDER	AA61-00009A	HOLDER—CAP;-PJT,-,-,BLK,-	
SPA	AA63-00011A	SPACER—CAP;EPDM RUBBER,-,BLK,-,PJT,-	
CASE	AA64-00065A	CASE—COUPLER,G;-PJT,-,ALDC8,-,BLK,-,-	

### ASSY-CRT

*	AA94-00088A	ASSY-CRT;16LFM00BMB,+380MG,7',BARE,SPM-	
BHL+CR	6001-000059	SCREW-MACHINE;TH,+,M4,L10,ZPC(BLK),SWRCH	
LA+CR	6001-000059	SCREW-MACHINE;TH,+,M4,L10,ZPC(BLK),SWRCH	
CRT	AA03-10021N	CRT-MONO;-P16LFM00BMB(U),-,7.90DEG,90	
D/Y	AA27-50003W	DEFLECTION-YOKE;-DPD-4274BL-A,46/PJT,-	
C/Y	AA27-60003C	MAGNET-CONVERGENCE;-JH92LTU-SC-20,29,1m	
SCREW	AA60-10050MS	SCREW-ASSY;-HH,+,M6,L16,SWRCH18A,ZPC(YE	
BRKT	AA61-10030A	BRACKET-LENS;-S4388,SECC,T1.6,-,-,-	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
HOLDER	AA61-20125A	HOLDER-SPACER;-;S43.5288,ABS,HB,BLK,HR-0					
SPA	AA63-60025A	SPACER-DY;NEOPRENE,-,BLK,V0,S4388,-					
SPA	AA63-60039A	SPACER-LENS;SPONGE,T2.0,BLK,W110,S4388,-					
SPA	AA63-60059A	SPACER-FELT;FELT,TO.5,BLK,CRT,-,-					
SPA	AA63-60111A	SPACER-CRT;EDPM,-,-,-,S4388,5288,-					
SPA	AA63-60125A	SPACER-C,ELEMENT;EPDM,3.2,BLK,-,PROJECTI					
BRKT	AA61-10381A	BRACKET-CRT;-;S4388,5288,SECC,T1.6,-,-,-					
LENS	AA67-10036A	LENS-ASSY;43INCH,SSM-75RS-43,-,SEKINOS,C					
LENS	AA67-10037A	LENS;43INCH,SSM-75RS-43,-,SEKINOS,C					
HOLDER	AA61-00009A	HOLDER—CAP;-;PJT,-,-,BLK,-					
CASE	AA64-00066A	CASE—COUPLER,R/B;-;PJT,-,ALDC8,-,BLK,-					
SPA	AA63-00011A	SPACER—CAP;EPDM RUBBER,-,BLK,-,PJT,-					
PCB	AA41-10421B	PCB-SIGNAL;SPT51A,1,FR-1,330x245x1.6T,-					
PCB	AA41-10431C	PCB-CRT(R);SPT51A,1,FR-1,330x245x1.6T,-					
PCB	AA41-10434A	PCB-CONTROL;SPT51A,1,FR-1,245X245X1.6T					
PCB	AA41-10436A	PCB-PREAMP;SPT51A,1,FR-1,245X245X1.6T					
PCB	AA41-10437B	PCB-A/V BACK;SPT51A,2L,FR-4,330x245x1.6T					
PWB	AA41-10371B	PCB-AUDIO;SCT51A,2L,FR-4,100x76x1.6T,-,-					
PCB	AA41-10424D	PCB-DEFLECTION;SPT51A,1,CEM-1,330x245x1.					
PCB	AA41-10479E	PCB-CONVERGENCE;SPT51A,1,CEM-1,330x245x1					
PCB	AA41-10438A	PCB-MASTER S/W;SPT51A,1,CEM-1,245X245X1.					
PWB	AA41-10330B	PCB-TTX;SCT51A,1L,FR-1,81x65x1.6T,-,-					
PWB	AA41-10323A	PCB-IF;SCT51A,2,FR-4,100X76X1.6T					
PWB	AA41-10321C	PCB-PIP;SCT51A,2L,FR-4,100x76x1.6T,-,-					
PCB	AA41-10581D	PCB-POWER;SPT51A,1L,CEM-1,330x245x1.6T,-					
PCB	AA41-10430A	PCB-CONTROL;SPT51A,1,FR-1,245X245X1.6T,-					
03LOT	AA41-10480D	PCB-MODULE;APT51A,2L,FR-4,191x123x1.6T,-					



9-2 SPM5288PF

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
<b>ASSY-PCB,MAIN</b>							
	* AA94-10150A	ASSY-PCB,MAIN(OPT);SP5288PFX/PIC,SPT51A,	PIIC	C242	2305-000354	C-FILM,MPEF;330NF,5%,50V,TP,7.3X4.8X5.5M	
	* AA94-10152D	ASSY-PCB,MAIN(OPT);SP5288PFX/XEH,SPT51A,	SEH	C243	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
BRKT	AA61-10360A	BRACKET-MODULE;-,-,CUS-1 1/2H,T0.5,-,SCT		C244	2401-001668	C-AL;68uF,20%,16V,GP,TP,5x11,5	
C1001	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C245	2301-000342	C-FILM,PEF;2.2nF,5%,50V,TP,7.4x3.9x13mm,	
C1002	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m		C246*	2201-000273	C-CERAMIC,DISC;18pF,5%,50V,CH,TP,5x3mm,5	
C1003	2401-000962	C-AL;22uF,20%,50V,GP,TP,5x11,5		C247*	2401-000603	C-AL;1uF,20%,50V,GP,TP,5x11,5	
C1004	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m		C248	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C1005	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C249	2305-000355	C-FILM,MPEF;330NF,5%,63V,TP,-,5mm	
C1006	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C250	2301-000148	C-FILM,PEF;10nF,5%,100V,TP,7x3.2x7mm,5mm	
C1007	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		C251	2301-000148	C-FILM,PEF;10nF,5%,100V,TP,7x3.2x7mm,5mm	
C1008	2201-000982	C-CERAMIC,DISC;10nF,+80-20%,50V,Y5V,TP,6		C252	2301-000148	C-FILM,PEF;10nF,5%,100V,TP,7x3.2x7mm,5mm	
C1009	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C253	2301-000148	C-FILM,PEF;10nF,5%,100V,TP,7x3.2x7mm,5mm	
C1015	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C254	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
C1016	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C255	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C200	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5		C256	2301-000148	C-FILM,PEF;10nF,5%,100V,TP,7x3.2x7mm,5mm	
C201	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C257	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C202	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C258	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C203	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C259	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C204	2309-000138	C-FILM,PE-PFF;100nF,5%,50V,TP,20x16x8,5,		C260	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C205	2201-000483	C-CERAMIC,DISC;33pF,5%,50V,CH,TP,5x3,5		C261	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C206	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C262	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C207	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C265	2401-000922	C-AL;22uF,20%,16V,GP,TP,5x5,5	
C208	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,		C266	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C209	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C268	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C210	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C269	2401-000947	C-AL;22uF,20%,35V,GP,TP,5x11,5	
C2101	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm		C270	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C2102	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm		C271	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C2103	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm		C274	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
C2104	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm		C275	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C2105	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm		C277	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C2106	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm		C278	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
C2107	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C279	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C2108	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C280	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C2109	2201-000611	C-CERAMIC,DISC;56pF,5%,50V,CH,TP,6.5x3,5		C281	2401-000947	C-AL;22uF,20%,35V,GP,TP,5x11,5	
C211	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C282	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C2110	2201-000234	C-CERAMIC,DISC;150pF,5%,50V,CH,TP,9.5x3,		C283	2201-000375	C-CERAMIC,DISC;220pF,5%,50V,RH,TP,9.5x3,	
C2111	2201-000504	C-CERAMIC,DISC;39pF,5%,50V,SL,TP,-,5		C284	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C2112	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		C285	2301-000261	C-FILM,PEF;4.7nF,5%,100V,TP,10.5x12.5x6,	
C212	2305-000355	C-FILM,MPEF;330NF,5%,63V,TP,-,5mm		C286	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C213	2301-000232	C-FILM,PEF;3.3nF,5%,50V,TP,8.1x4.5x13mm,		C287	2401-001333	C-AL;470nF,20%,50V,GP,TP,5x11,5	
C214	2301-000016	C-FILM,PEF;22nF,5%,100V,TP,7.2x4.5x9.0mm		C288	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C215	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C289	2201-000375	C-CERAMIC,DISC;220pF,5%,50V,RH,TP,9.5x3,	
C216	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5		C290	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C217	2201-000471	C-CERAMIC,DISC;330pF,10%,50V,Y5P,TP,5x3,		C291	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C218	2201-000375	C-CERAMIC,DISC;220pF,5%,50V,RH,TP,9.5x3,		C292	2201-000961	C-CERAMIC,DISC;10pF,0.5pF,50V,RH,TP,5x3mm	
C219	2305-000354	C-FILM,MPEF;330NF,5%,50V,TP,7.3X4.8X5.5M		C293	2201-000961	C-CERAMIC,DISC;10pF,0.5pF,50V,RH,TP,5x3mm	
C220	2201-000375	C-CERAMIC,DISC;220pF,5%,50V,RH,TP,9.5x3,		C294	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5	
C221	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5		C295	2301-000383	C-FILM,PEF;10nF,5%,50V,TP,6x7x3.2mm,5mm	
C222	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C296	2201-000193	C-CERAMIC,DISC;10pF,0.3pF,50V,CH,TP,5x3,	
C223	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C297	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m	
C224	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C298	2401-002231	C-AL;470uF,20%,50V,WT,TP,13x20mm,5m	
C225	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C299	2201-000144	C-CERAMIC,DISC;100pF,5%,50V,CH,TP,8x3,5	
C226	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		C601	2401-002144	C-AL;47uF,20%,16V,GP,TP,5x11,5	
C227	2401-000027	C-AL;4.7uF,20%,50V,GP,TP,5x11,5		C602	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C228	2306-000122	C-FILM,MPPF;100nF,5%,50V,TP,7.3x4.0x5.0m		C603	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C229	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5		C605	2401-000471	C-AL;10uF,20%,50V,BP,TP,5x11,5mm	
C230	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm		C606	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C231	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm		C8001	2401-000302	C-AL;100uF,20%,25V,GP,TP,6.3x11,5	
C232	2305-000289	C-FILM,MPEF;220nF,5%,63V,TP,-,5mm		C8002	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C233	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C8003	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C234	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C8004	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
C235	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C8005	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C236	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C8006	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
C237	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C8008	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C238	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C8009	2401-000832	C-AL;220uF,20%,25V,GP,TP,8x11.5,5	
C239	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C8010	2401-002594	C-AL;220uF,20%,16V,GP,TP,8x11.5,5	
C240	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C8012	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
C241	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m		C8013	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
				C8014	2401-001840	C-AL;100uF,20%,16V,GP,TP,6.3x11,5	
				C8015	2305-000665	C-FILM,MPEF;100nF,5%,63V,TP,7.5x4.0x5.0m	
				Q901	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16,5	
				Q902	2401-000480	C-AL;10uF,20%,50V,GP,TP,5x11,5	
				C903	2201-000374	C-CERAMIC,DISC;220pF,5%,50V,CH,TP,12.5x3	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C904	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11.5,5		D202	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C909	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5		D203	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C910	2201-000281	C-CERAMIC,DISC:1nF,79.8,50V,Y5V,TP,4x3.5		D204	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C911	2201-000247	C-CERAMIC,DISC:15pF,5%,50V,CH,TP,5x3,5		D205	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C912	2201-000247	C-CERAMIC,DISC:15pF,5%,50V,CH,TP,5x3,5		D211	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C913	2201-000423	C-CERAMIC,DISC:27pF,5%,50V,NPO,TP,5x3,2.		D212	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C914	2201-000423	C-CERAMIC,DISC:27pF,5%,50V,NPO,TP,5x3,2.		D601	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C917	2201-000611	C-CERAMIC,DISC:56pF,5%,50V,CH,TP,6.5x3,5		D905	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C918	2401-002594	C-AL:220uF,20%,16V,GP,TP,8x11.5,5		D906	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C919	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		D907	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C920	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		D908	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C921	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		D909	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C922	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		D910	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C923	2201-000146	C-CERAMIC,DISC:100pF,5%,50V,SL,TP,5x3,5		D911	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C924	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		D912	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C925	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		D914	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C926	2301-000289	C-FILM,MPEF:5.6nF,5%,50V,TP,7x6x3,5		D915	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
CC01	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		DL201	4711-000205	DELAY LINE:0.140uS,-,-,TR	
CC02	2401-002462	C-AL:33uF,20%,16V,GP,TP,5x11,5		DZ201	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
CC03	2401-002462	C-AL:33uF,20%,16V,GP,TP,5x11,5		DZ203	0403-000355	DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500	
CC04	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		DZ204	0403-000300	DIODE-ZENER:MTZ8.2B,8.2V,7.78-8.19V,500m	
CC05	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5		DZ206	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
CC06	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		DZ207	0403-000289	DIODE-ZENER:MTZ10C,10V,9.7-10.2V,500mW,D	
CC07	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m		DZ208	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m	
CC10	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5		DZ209	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m	
CC11	2401-000027	C-AL:4.7uF,20%,50V,GP,TP,5x11,5		DZ210	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m	
CC12	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		DZ901	0403-000296	DIODE-ZENER:MTZ5.6B,5.6V,5.45-5.73V,500m	
CF01	AA29-10002A	FILTER-COMB:-,UGL-357KNT,NTSC,ST		DZ902	0403-000297	DIODE-ZENER:MTZ6.2B,6.2V,5.96-6.27V,500m	
CN201	3711-002646	CONNECTOR-HEADER:BOX,7P,1R,2.5mm,STRAIGH		DZC01	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
CN202	3711-003641	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIG		IC201	1204-000636	IC-PICTURE PROCESS:TDA4566,DIP,18P,300MI	
CN601	3711-002645	CONNECTOR-HEADER:BOX,6P,1R,2.5MM,STRAIGH		IC202	1204-000530	IC-PAL/NTSC DECODER:TDA9160A,DIP,32P,400	
CN601	AA39-20038D	LEAD-CONNECTOR,ASSY:-,67096-006,S,6P,300		IC203	1204-000464	IC-VIDEO PROCESS:TDA4780,DIP,28P,-,PLAS	
CN701	3710-001155	CONNECTOR-SOCKET:20P,2R,2.54MM,STRAIGHT,		IC204	1209-000214	IC-DELAY LINE:TDA4665,DIP,16P,300MIL,PLA	
CN702	3710-001155	CONNECTOR-SOCKET:20P,2R,2.54MM,STRAIGHT,		IC205	1204-000444	IC-PICTURE PROCESS:TDA9170,DIP,32P,-,PLA	
CN801	3711-000628	CONNECTOR-HEADER:-,11P,1R,2.5mm,STRAIGHT		IC206	1201-000501	IC-VIDEO AMP:14577,DIP,8P,300MIL,CMOS,-5	
CN801	AA39-20160E	LEAD CONNECTOR ASSY:-,67096-011,S,11P,14		IC207	1204-000471	IC-PICTURE PROCESS:ANS5342K,DIP,30P,400MI	
CN901	3711-002641	CONNECTOR-HEADER:BOX,10P,1R,2.54mm,STRAI		IC208	1001-000223	IC-VIDEO SWITCH:TEA5114A,-,DIP,16P,334MI	
CN903	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH		IC8001	1203-000006	IC-POSI.FIXED REG.:7808,TO-220,3P,-,PLAS	H/SINK
CN904	3711-002648	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,STRAIGH		IC8002	1203-000274	IC-POSI.FIXED REG.:7805,TO-220,3P,-,PLAS	H/SINK
CN905	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH		IC8003	1203-000165	IC-POSI.ADJ REG.:78R12,TO-220,3P,-,-,	H/SINK
CN906	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH		IC8004	1203-000298	IC-POSI.FIXED REG.:7809,TO-220,3P,-,PLAS	H/SINK
CNH02	AA39-20113A	LEAD-CONNECTOR,ASSY:-,YFH806-06,-,(2)P,		IC901	AA13-30002HC-MCU:-,CXPH853P40S-1,8bit,SDIP,-,64P	PIIC	
CNQ01	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH		IC901	AA13-30005F	IC-MCU:SEH	
CNV01	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH		IC902	1103-000118	IC-EEPROM:2408,1Kx8BIT,DIP,8P,300MIL,10m	
CNV01	AA39-20016D	LEAD-CONNECTOR,ASSY:-,67096-003,S,3P,500		IC903	1202-000001	IC-VOLTAGE COMP:7533,TO-92,3P,-,SINGLE,	
CNX01	AA39-20010E	LEAD-CONNECTOR,ASSY:-,YFH800-01,S,1P,800		IC903	0801-000961	IC-CMOS LOGIC:4053B,MULTIPLEXER,DIP,16P,3	
CNZ01	3711-002648	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,STRAIGH		ICZ30	1001-000223	IC-VIDEO SWITCH:TEA5114A,-,DIP,16P,334MI	
CNZ01	AA39-20082C	LEAD-CONNECTOR,ASSY:-,67096-009,S,9P,400		ICZ31	1001-000223	IC-VIDEO SWITCH:TEA5114A,-,DIP,16P,334MI	
CP101	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,5		IF-C	AA39-30007B	IF-CABLE:-,T,150mm,1365#26	
CP1010	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		L1001	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CP102	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		L1002	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CP103	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		L1003	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CP104	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		L1004	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP105	2401-002235	C-AL:10uF,20%,16V,GP,TP,5x11mm,5mm		L1005	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
CP106	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		L101	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
CP107	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		L201	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
CP108	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		L202	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
CP109	2305-000665	C-FILM,MPEF:100nF,5%,63V,TP,7.5x4.0x5.0m		L203	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
CW901	2503-000158	C-NETWORK:330PFx4,20%,50V,MCCB1H331MX4YT		L204	2701-000162	INDUCTOR-AXIAL:27uH,10%,2.5x3.4mm	
CW902	2503-000159	C-NETWORK:330PFx5,20%,50V,MCCB1H331MX5YT		L205	2701-000223	INDUCTOR-AXIAL:82uH,10%,2.5x3.4MM	
CW903	2503-000161	C-NETWORK:330PFx8,20%,50V,MCCB1H331MX8YT		L206	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CW904	2503-000158	C-NETWORK:330PFx4,20%,50V,MCCB1H331MX4YT		L207	2701-000162	INDUCTOR-AXIAL:27uH,10%,2.5x3.4mm	
CZ301	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5m		L209	2701-000207	INDUCTOR-AXIAL:56uH,5%,2.5x3.4mm	
CZ302	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5m		L602	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CZ303	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5m		L603	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CZ304	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		L604	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
CZ305	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		L902	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CZ306	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		L903	AA27-10003G	COIL-CHOKE:-,30uH,K,50,22.3mA,TPELO606R	
CZ307	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		L904	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
CZ308	2305-000354	C-FILM,MPEF:330nF,5%,50V,TP,7.3x4.8x5.5M		L906	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CZ310	2201-000281	C-CERAMIC,DISC:1nF,79.8,50V,Y5V,TP,4x3.5		LP101	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CZ311	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m		LP102	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
CZ312	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		LP103	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CZ313	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m		LP104	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CZ314	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		LP105	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CZ315	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5		LP106	2701-000142	INDUCTOR-AXIAL:1uH,10%,2.5x3.4mm	
CZ316	2401-000404	C-AL:10uF,20%,16V,BP,TP,5x11,5		LP108	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
LZ301	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R2127	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LZ302	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R2128	2001-000490	R-CARBON:200ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LZ303	2701-000111	INDUCTOR-AXIAL:100uH,10%,2.5x3.4mm		R2129	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	
LZ304	2701-000111	INDUCTOR-AXIAL:100uH,10%,2.5x3.4mm		R213	2001-000008	R-CARBON:15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
LZ305	2701-000111	INDUCTOR-AXIAL:100uH,10%,2.5x3.4mm		R2130	2001-000490	R-CARBON:200ohm,5%,1/8W,AA,TP,1.8x3.2mm	
M101	AA59-40003F	MODULE-LNA:-,LNA1410AF(S),PAL,EU,TR TYPE		R2131	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	
MODULE	AA59-40003P	MODULE-FOCUS,PACK:-,F300,NTSC,43,64x62,		R2133	2001-000290	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q1001	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R2134	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q201	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R2135	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q202	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R214	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q203	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R215	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q204	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R217	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q205	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R218	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q206	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R219	2001-001000	R-CARBON:82Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q207	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R220	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q208	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R2201	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q209	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R2202	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q210	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R221	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q211	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R222	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q212	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R223	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q213	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R224	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q601	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R225	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q602	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R226	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q901	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L		R227	2008-000300	R-FUSIBLE:560ohm,5%,1/2W,AA,TP,4.7x11mm	
Q903	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R228	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q904	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R229	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q905	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R230	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q906	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R231	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q907	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R232	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q908	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R233	2001-000645	R-CARBON:330Kohm,5%,1/8W,AA,TP,1.8x3.2m	
Q909	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R234	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
Q910	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R235*	2001-001000	R-CARBON:82Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
QC01	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R236	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm	
QC02	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R237	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
QC03	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R238	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
QC04	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R239	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
QC05	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R240	2001-000890	R-CARBON:6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
QC06	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T		R241	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
QZ301	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R242	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1002	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		R243	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1003	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		R244	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1004	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		R245	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1005	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R248	2001-000522	R-CARBON:22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1006	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R249	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R1007	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm		R250	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R201	2001-000008	R-CARBON:15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R251	2001-000832	R-CARBON:510ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R202	2001-001015	R-CARBON:9.1Kohm,5%,1/8W,AA,TP,1.8x3.2m		R252	2001-000472	R-CARBON:2.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R203	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R253	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R204	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R254	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R205	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R255	2001-000633	R-CARBON:30Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R206	2001-000273	R-CARBON:100Kohm,5%,1/8W,AA,TP,1.8x3.2m		R256	2001-000522	R-CARBON:22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R208	2001-000864	R-CARBON:56Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R257	2001-000008	R-CARBON:15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R210	2001-000563	R-CARBON:27Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R258	2001-000977	R-CARBON:8.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2100	2001-000633	R-CARBON:30Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R259	2001-000800	R-CARBON:5.1Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2101	2001-000832	R-CARBON:510ohm,5%,1/8W,AA,TP,1.8x3.2mm		R260	2001-000723	R-CARBON:4.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2103	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		R261	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2106	2001-000008	R-CARBON:15Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R262	2001-000522	R-CARBON:22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2107	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R263	2001-000258	R-CARBON:1.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2108	2001-000568	R-CARBON:27ohm,5%,1/8W,AA,TP,1.8x3.2mm		R264	2001-000252	R-CARBON:1.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2109	2001-000832	R-CARBON:510ohm,5%,1/8W,AA,TP,1.8x3.2mm		R265	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R211	2004-001914	R-METAL:39Kohm,2%,1/8W,AA,TP,1.8x3.5mm		R266	2001-000633	R-CARBON:30Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2110	2001-000568	R-CARBON:27ohm,5%,1/8W,AA,TP,1.8x3.2mm		R267	2001-000008	R-CARBON:15Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2111	2001-000832	R-CARBON:510ohm,5%,1/8W,AA,TP,1.8x3.2mm		R268	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2112	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R269	2001-000660	R-CARBON:33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2113	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R270	2001-000702	R-CARBON:39Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2114	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R271	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2115	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R272	2001-000605	R-CARBON:3.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2116	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R273	2001-000613	R-CARBON:3.9Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2118	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm		R274	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2119	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm		R275	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R212	2001-000977	R-CARBON:8.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		R276	2001-001000	R-CARBON:82Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2120	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm		R277	2004-001089	R-METAL:560Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2121	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm		R278	2001-000890	R-CARBON:6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R2122	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm		R279	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2123	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm		R281	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2124	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm		R282	2001-000347	R-CARBON:13Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R2126	2001-000490	R-CARBON:200ohm,5%,1/8W,AA,TP,1.8x3.2mm		R284	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R285	2001-000924	R-CARBON:680ohm,5%,1/8W,AA,TP,1.8x3.2mm		R960	2001-000660	R-CARBON:33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R286	2001-000591	R-CARBON:3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		R961	2001-000554	R-CARBON:270ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R287	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm		R962	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R288	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R963	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R289	2001-000554	R-CARBON:270ohm,5%,1/8W,AA,TP,1.8x3.2mm		R964	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R290	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R965	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R291	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm		R966	2001-000591	R-CARBON:3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R292	2001-000362	R-CARBON:150ohm,5%,1/8W,AA,TP,1.8x3.2mm		R967	2001-000009	R-CARBON:20Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R293	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R968	2001-000325	R-CARBON:120ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R294	2008-000272	R-FUSIBLE:33ohm,5%,1/2W,AA,TP,2.5x6.5mm		R969	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R295	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R970	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R297	2001-001015	R-CARBON:9.1Kohm,5%,1/8W,AA,TP,1.8x3.2m		R971	2001-000995	R-CARBON:820ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R298	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		R972	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R299	2001-000007	R-CARBON:3Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R973	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R601	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R974	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R602	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R975	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R616	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		R976	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R8001	2001-000066	R-CARBON(S):10Kohm,5%,1/2W,AA,TP,2.4x6.4		R977	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R8003	2003-000590	R-METAL OXIDE(S):22ohm,5%,2W,AA,TP,4x12m		R978	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R8004	2003-000744	R-METAL OXIDE(S):56ohm,5%,2W,AA,TP,4x12m		R979	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R901	2001-000117	R-CARBON(S):68ohm,5%,1/2W,AA,TP,2.4x6.4m		R980	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R902	2001-000221	R-CARBON:1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		R981	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R903	2001-000449	R-CARBON:2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		R982	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R904	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R985	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R905	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R986	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R906	2001-001093	R-CARBON(S):2.2Kohm,5%,1/2W,AA,TP,2.4x6.4		R987	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R907	2001-001093	R-CARBON(S):2.2Kohm,5%,1/2W,AA,TP,2.4x6.4		R988	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R908	2001-001093	R-CARBON(S):2.2Kohm,5%,1/2W,AA,TP,2.4x6.4		R989	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R909	2001-001093	R-CARBON(S):2.2Kohm,5%,1/2W,AA,TP,2.4x6.4		R990	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R910	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R991	2001-000258	R-CARBON:1.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R911	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R992	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m	
R912	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R993	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R913	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R994	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R914	2001-000362	R-CARBON:150ohm,5%,1/8W,AA,TP,1.8x3.2mm		R995	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R915	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R996	2001-001197	R-CARBON(S):910ohm,5%,1/2W,AA,TP,2.4x6.4	
R916	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		R999	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R917	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC01	2008-000272	R-FUSIBLE:33ohm,5%,1/2W,AA,TP,2.5x6.5mm	
R918	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC02	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R919	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC03	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R920	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC04	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R921	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC05	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R922	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC06	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R924	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		RC07	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R925	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC08	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R926	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC09	2001-000118	R-CARBON(S):180ohm,5%,1/2W,AA,TP,2.4x6.4	
R927	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC10	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R928	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC11	2001-000376	R-CARBON:15ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R929	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC12	2001-001077	R-CARBON(S):150ohm,5%,1/2W,AA,TP,2.4x6.4	
R930	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC13	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R931	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC14	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R932	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC15	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R933	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC16	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R934	2001-000241	R-CARBON:1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		RC17	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R935	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC18	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R936	2001-000947	R-CARBON:7.5Kohm,5%,1/8W,AA,TP,1.8x3.2m		RC19	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R937	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RC20	2001-000837	R-CARBON:51Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R938	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		RC25	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R939	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RC26	2001-000605	R-CARBON:3.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R940	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RC27	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R941	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RP102	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R942	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RP103	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R943	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		RP104	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R944	2001-000449	R-CARBON:2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		RT101	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R945	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		RT102	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R946	2001-000449	R-CARBON:2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m		RZ301	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R947	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RZ302	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R948	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RZ303	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R949	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RZ306	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R950	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RZ307	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R951	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RZ308	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R952	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RZ310	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R953	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		RZ311	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R954	2001-000331	R-CARBON:12Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RZ312	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R955	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RZ313	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R956	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		RZ314	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R958	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RZ315	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R959	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RZ316	2001-001187	R-CARBON(S):75ohm,5%,1/2W,AA,TP,2.4x6.4m	

Loc. No.	Code No.	Description ; Specification	Remark
RZ317	2001-000405	R-CARBON:180ohm,5%,1/8W,AA,TP,1.8x3.2mm	
RZ318	2001-000857	R-CARBON:560ohm,5%,1/8W,AA,TP,1.8x3.2mm	
RZ319	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RZ320	2001-001187	R-CARBON(S):75ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RZ323	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RZ324	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4mm	
RZ330	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
RZ331	2001-001187	R-CARBON(S):75ohm,5%,1/2W,AA,TP,2.4x6.4mm	
TU101	AA40-10002NTUNER-F/S:-,TECC0889PA19C,PAL-MULTI,TR,1		
TUP01	AA40-10002NTUNER-F/S:-,TECC0889PA19C,PAL-MULTI,TR,1		
X201	2801-000235	CRYSTAL-UNIT:3.579545MHz,40ppm,28-AAAM,S	
X202	2801-000274	CRYSTAL-UNIT:4.433619MHz,30PPM,28-AAAM,20	
X901	2801-001480	CRYSTAL-UNIT:4.194304MHz,20ppm,28-ABQ,12	

**ASSY-ACCESSORY**

RCA/CA	AA39-40001B	CABLE-RCA:-,RCA,1500mm,0.12/10,RED/WHT/Y	
HOLDER	AA61-20126A	HOLDER-LEG:-,ABS,HB,BLK,-	
I/B	AA68-10759A	MANUAL-USERS:S/W120(G):-,ENG SPT51A,43	
I/B	AA68-10760A	MANUAL-USERS:S/W120(G):-,ARAB SPT51A,4	

**ASSY-CRT**

*	AA94-50015H	ASSY-CRT:16LFM00REA,+380MG,7,BARE,SVP-	
C/Y	AA27-60003C	MAGNET-CONVERGENCE:-,JH92LTU-SC-20,29,1m	
BHL+CR	6001-000059	SCREW-MACHINE:TH,+,M4,L10,ZPC(BLK),SWRCH	
LA+CR	6001-000059	SCREW-MACHINE:TH,+,M4,L10,ZPC(BLK),SWRCH	
SCREW	AA60-10050L	SCREW-MACHINE:-,M8,L16,-,STS304,SV	
HOLDER	AA61-20125A	HOLDER-SPACER:-,S43.5288,ABS,HB,BLK,HR-0	
SPACER	AA63-60039A	SPACER-LENS:SPONGE,T2.0,BLK,W110,S4388,-	
BRKT/A	AA91-40086A	ASSY-BRACKET,CRT:SECC,T1.6,S4388	
LENS	AA67-10008A	LENS:-,DELTA,RED,PJT,-,77,79,-	
LENS/A	AA67-10005A	LENS-ASSY:-,DELTA,CLEAR,S4388,-,77,-	
CASE-C	AA64-31028A	CASE-COUPLER,R/B:-,S4388,5288,-,ALDC8,-	
SPACER	AA63-60111A	SPACER-CRT:EDPM,-,-,S4388,5288,-	
SPACER	AA63-60059A	SPACER-FELT:FELT,TO.5,BLK,CRT,-	
SPACER	AA63-60046A	SPACER-OIL,RING:EPDM,-,-,S4388,-	
SP-DY	AA63-60025A	SPACER-DY:NEOPRENE,-,BLK,VO,S4388,-	
BRKT/A	AA61-10030A	BRACKET-LENS:-,S4388,SECC,T1.6,-,-	
CRT	AA03-10021K	CRT-MONO:-,P16LFM00RFA(AU)-,7,90DEG,9	
SCREW	AA60-10050M	SCREW-ASSY:-,HH,+,M6,L16,SWRCH18A,ZPC(YE	
SPACER	AA63-60125A	SPACER-C,ELEMENT:EPDM,3.2,BLK,-,PROJECTI	
D/Y	AA27-50003W	DEFLECTION-YOKE:-,DPD-4274BL-A,46/PJT,-	

**ASSY-CRT**

*	AA94-50015J	ASSY-CRT:16LFM00HLA,+380MG,7,BARE,SVP-	
C/Y	AA27-60003C	MAGNET-CONVERGENCE:-,JH92LTU-SC-20,29,1m	
BHL+CR	6001-000059	SCREW-MACHINE:TH,+,M4,L10,ZPC(BLK),SWRCH	
LA+CR	6001-000059	SCREW-MACHINE:TH,+,M4,L10,ZPC(BLK),SWRCH	
SPACER	AA63-60111A	SPACER-CRT:EDPM,-,-,S4388,5288,-	
SPACER	AA63-60059A	SPACER-FELT:FELT,TO.5,BLK,CRT,-	
SPACER	AA63-60046A	SPACER-OIL,RING:EPDM,-,-,S4388,-	
SPACER	AA63-60039A	SPACER-LENS:SPONGE,T2.0,BLK,W110,S4388,-	
SPACER	AA63-60025A	SPACER-DY:NEOPRENE,-,BLK,VO,S4388,-	
BRKT/A	AA91-40086A	ASSY-BRACKET,CRT:SECC,T1.6,S4388	
BRKT	AA61-10381A	BRACKET-CRT:-,S4388,5288,SECC,T1.6,-,-	
LENS	AA67-10007A	LENS:-,DELTA,CLEAR,PJT,-,77,79,-	
LENS/A	AA67-10006A	LENS-ASSY:-,DELTA,GREEN,S4388,-,77,-	
HOLDER	AA61-20125A	HOLDER-SPACER:-,S43.5288,ABS,HB,BLK,HR-0	
BRKT	AA61-10030A	BRACKET-LENS:-,S4388,SECC,T1.6,-,-	
SCREW	AA60-10050L	SCREW-MACHINE:-,M8,L16,-,STS304,SV	
CRT	AA03-10021L	CRT-MONO:-,P16LFM00HLA(AU)-,7,90DEG,9	
SCREW	AA60-10050M	SCREW-ASSY:-,HH,+,M6,L16,SWRCH18A,ZPC(YE	
SPACER	AA63-60125A	SPACER-C,ELEMENT:EPDM,3.2,BLK,-,PROJECTI	
D/Y	AA27-50003W	DEFLECTION-YOKE:-,DPD-4274BL-A,46/PJT,-	

**ASSY-CRT**

*	AA94-50015K	ASSY-CRT:16LFM00BMB,+380MG,7,BARE,SVP-	
CRT	AA03-10021N	CRT-MONO:-,P16LFM00BMB(U)-,7,90DEG,90	
C/Y	AA27-60003C	MAGNET-CONVERGENCE:-,JH92LTU-SC-20,29,1m	
BHL+CR	6001-000059	SCREW-MACHINE:TH,+,M4,L10,ZPC(BLK),SWRCH	
LA+CR	6001-000059	SCREW-MACHINE:TH,+,M4,L10,ZPC(BLK),SWRCH	

Loc. No.	Code No.	Description ; Specification	Remark
SPACER	AA63-60111A	SPACER-CRT:EDPM,-,-,S4388,5288,-	
SPACER	AA63-60059A	SPACER-FELT:FELT,TO.5,BLK,CRT,-	
SPACER	AA63-60046A	SPACER-OIL,RING:EPDM,-,-,S4388,-	
SPACER	AA63-60039A	SPACER-LENS:SPONGE,T2.0,BLK,W110,S4388,-	
SPACER	AA63-60025A	SPACER-DY:NEOPRENE,-,BLK,VO,S4388,-	
BRKT/A	AA91-40086A	ASSY-BRACKET,CRT:SECC,T1.6,S4388	
BRKT/A	AA61-10381A	BRACKET-CRT:-,S4388,5288,SECC,T1.6,-,-	
LENS	AA67-10007A	LENS:-,DELTA,CLEAR,PJT,-,77,79,-	
LENS	AA67-10005A	LENS-ASSY:-,DELTA,CLEAR,S4388,-,77,-	
HOLDER	AA61-20125A	HOLDER-SPACER:-,S43.5288,ABS,HB,BLK,HR-0	
BRKT	AA61-10030A	BRACKET-LENS:-,S4388,SECC,T1.6,-,-	
SCREW	AA60-10050L	SCREW-MACHINE:-,M8,L16,-,STS304,SV	
SCREW	AA60-10050M	SCREW-ASSY:-,HH,+,M6,L16,SWRCH18A,ZPC(YE	
SPACER	AA63-60125A	SPACER-C,ELEMENT:EPDM,3.2,BLK,-,PROJECTI	
D/Y	AA27-50003W	DEFLECTION-YOKE:-,DPD-4274BL-A,46/PJT,-	

**ASSY-PCB,POWER**

*	AA95-10008P	PASSY-PCB,POWER:SPM5288PF/SVIX,SPT51A,52	PIIC
*	AA95-10002H	PASSY-PCB,POWER:SPM5288PF,SPT51A,-,-,-	SEH

C801	2401-003031	C-AL:470uF,20%,450V,GP,BK,35x45mm,1	
C802	2401-003031	C-AL:470uF,20%,450V,GP,BK,35x45mm,1	
C803	2306-000323	C-FILM,MPPF:2.2nF,5%,1.6KV,TP,28.5x15.5x	
C804	2401-003065	C-AL:470uF,20%,50V,LZ,TP,13x25mm,5m	
C805	2401-002262	C-AL:10uF,20%,160V,WT,TP,10x20,5	
C806	2201-000281	C-CERAMIC,DISC:1nF,79.8,50V,Y5V,TP,4x3.5	
C807	2401-002274	C-AL:220uF,20%,35V,WT,TP,10x12.5,5	
C808	2306-000318	C-FILM,MPPF:220nF,20%,275V,TP,-,22.5mm	
C809	2306-000318	C-FILM,MPPF:220nF,20%,275V,TP,-,22.5mm	
C811	2201-000332	C-CERAMIC,DISC:2.2nF,20%,250VAC,Y5U,TP,1	
C812	2201-000332	C-CERAMIC,DISC:2.2nF,20%,250VAC,Y5U,TP,1	
C813	2401-002223	C-AL:220uF,20%,450V,GP,ST,30x40,10	
C814	2401-002274	C-AL:220uF,20%,35V,WT,TP,10x12.5,5	
C815	2306-000323	C-FILM,MPPF:2.2nF,5%,1.6KV,TP,28.5x15.5x	
C816	2401-003065	C-AL:470uF,20%,50V,LZ,TP,13x25mm,5m	
C817	2401-000045	C-AL:10uF,20%,160V,GP,TP,10x16,5	
C818	2201-000281	C-CERAMIC,DISC:1nF,79.8,50V,Y5V,TP,4x3.5	
C819	2201-000987	C-CERAMIC,DISC:2.2nF,20%,400V,Y5U,TP,15x	
C824	2201-000467	C-CERAMIC,DISC:330pF,10%,2KV,Y5P,TP,8x6	
C851	2201-000991	C-CERAMIC,DISC:560pF,10%,2KV,Y5P,TP,13x7	
C852	2401-002251	C-AL:470uF,20%,200V,GP,BK,25x40mm,1	
C853	2401-001482	C-AL:47uF,20%,160V,GP,TP,13x25,5	
C854	2401-003024	C-AL:220uF,20%,200V,WT,TP,22x35,10	
C855	2201-000132	C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4	
C856	2401-002215	C-AL:2200uF,20%,25V,WT,TP,13x25,5	
C857	2201-000132	C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4	
C858	2201-000132	C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4	
C859	2401-001068	C-AL:3300uF,20%,50V,GP,BK,22x40,10	
C860	2401-001998	C-AL:1000uF,20%,25V,GP,TP,10x20,5mm	
C861	2401-002216	C-AL:2200uF,20%,35V,GP,TP,16x25,7,5	
C862	2401-000133	C-AL:1000uF,20%,16V,GP,TP,10x20,5	
C863	2401-001998	C-AL:1000uF,20%,25V,GP,TP,10x20,5mm	
C864	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5mm	
C865	2401-001115	C-AL:330uF,20%,25V,GP,TP,10x12.5,5	
C866	2301-000356	C-FILM,PEF:47nF,5%,50V,TP,7.5x4.0x6.5,5m	
C867	2201-000132	C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4	
C868	2401-000737	C-AL:2200uF,20%,50V,GP,TP,18x35,5,7	
C869	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7,5	
C870	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7,5	
C871	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5	
C872	2401-000737	C-AL:2200uF,20%,50V,GP,TP,18x35,5,7	
C873	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7,5	
C874	2401-000192	C-AL:1000uF,20%,50V,GP,TP,16x25,7,5	
C875	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5	
C876	2201-000132	C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4	
C877	2201-000132	C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4	
C878	2401-000737	C-AL:2200uF,20%,50V,GP,TP,18x35,5,7	
C879	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20,5	
C880	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm	
C881	2201-000132	C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4	
C882	2305-000411	C-FILM,MPEF:470nF,5%,50V,TP,7.3x4.8x5.5mm	
C883	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm	
C884	2401-000737	C-AL:2200uF,20%,50V,GP,TP,18x35,5,7	
C885	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20,5	
C887	2401-000962	C-AL:22uF,20%,50V,GP,TP,5x11,5	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C888	2306-000122	C-FILM,MPPF;100nf,5%,50V,TP,7.3x4.0x5.0m		HC851	1203-000580	IC-POWER PRESCALER:130,TO-220,3P,-,PLAST	
C889	2201-000132	C-CERAMIC,DISC;100pF,10%,500V,Y5P,TP,6x4		HC852	1203-000187	IC-POS.ADJUST REG.;431,TO-92,3P,-,PLAST	
C894	2201-000991	C-CERAMIC,DISC;560pF,10%,2KV,Y5P,TP,13x7		L801	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
C895	2401-001397	C-AL;470uF,20%,25V,GP,TP,10x16.5		L801A	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
CN801	3711-000628	CONNECTOR-HEADER;-;11P,1R,2.5mm,STRAIGHT		L802	2902-001001	FILTER-LINE:2mH,+3TURNS,0.233ohm	PIIC
CN802	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH		L802	AA29-30001Z	FILTER-LINE:-;10mH,2.8A,-,SQE3535	SEH
CN802	AA39-20020H	LEAD-CONNECTOR,ASSY;-;67096-005,S,5P,140		L803	2902-001001	FILTER-LINE:2mH,+3TURNS,0.233ohm	PIIC
CN803	AA39-20165A	LEAD CONNECTOR-ASSY;-;YFH806-06,S,6P,130		L803	AA29-30001Z	FILTER-LINE:-;10mH,2.8A,-,SQE3535	SEH
CN804	AA39-20164A	LEAD CONNECTOR-ASSY;-;YFH806-05,S,5P,500		L804	2902-001001	FILTER-LINE:2mH,+3TURNS,0.233ohm	PIIC
D801	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		L804	AA29-30001Z	FILTER-LINE:-;10mH,2.8A,-,SQE3535	SEH
D802	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		L805	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D803	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		L806	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D804	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		L807	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D805	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		L848	2902-001001	FILTER-LINE:2mH,+3TURNS,0.233ohm	PIIC
D806	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L		L848	AA29-30001Z	FILTER-LINE:-;10mH,2.8A,-,SQE3535	SEH
D807	0402-000213	DIODE-RECTIFIER:ERB12-06,600V,1.0A,DO-41		L849	2902-001001	FILTER-LINE:2mH,+3TURNS,0.233ohm	PIIC
D808	0402-000549	DIODE-BRIDGE:RBV606,600V,6A,-,BK	H/SINK	L849	AA29-30001Z	FILTER-LINE:-;10mH,2.8A,-,SQE3535	SEH
D809	1405-000152	VARIATOR:560V,2500A,14x8.5mm,TP		L851	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D810	1405-000152	VARIATOR:560V,2500A,14x8.5mm,TP		L852	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D811	0402-000213	DIODE-RECTIFIER:ERB12-06,600V,1.0A,DO-41		L853	AA27-10002L	COIL-CHOKE:-;24UH,K,-,2A,-,24UH-K,10X10M	
D812	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		L854	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D813	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		L855	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D814	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		L856	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D815	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		L857	AA27-10001C	COIL-CHOKE:-;100uH,K,-,5.0A,ST,700UH-K(R	
D817	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L		L858	AA27-10002L	COIL-CHOKE:-;24UH,K,-,2A,-,24UH-K,10X10M	
D818	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		L859	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D819	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		L860	AA27-10001C	COIL-CHOKE:-;100uH,K,-,5.0A,ST,700UH-K(R	
D851	0402-000231	DIODE-RECTIFIER:FMG-G26S,600V,4A,TO-220F	H/SINK	L861	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D852	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L		L862	AA27-10001C	COIL-CHOKE:-;100uH,K,-,5.0A,ST,700UH-K(R	
D853	0402-000544	DIODE-RECTIFIER:RU4Y,100V,2A,-		L863	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D854	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	L864	AA27-10001C	COIL-CHOKE:-;100uH,K,-,5.0A,ST,700UH-K(R	
D855	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		L865	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D856	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	L866	AA27-10001C	COIL-CHOKE:-;100uH,K,-,5.0A,ST,700UH-K(R	
D857	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T		L867	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
D858	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		L870	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
D859	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	NT801	1404-001045	THERMISTOR-NTC:4.7OHM,15%,2900K,35.0MW,T	
D860	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	NT802	1404-001045	THERMISTOR-NTC:4.7OHM,15%,2900K,35.0MW,T	
D861	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	PC801	0604-001038	PHOTO-COUPLER:TR,130-260%,200mW,DIP-4,ST	
D862	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK	PC802	0604-001038	PHOTO-COUPLER:TR,130-260%,200mW,DIP-4,ST	
D863	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		Q801	0503-000153	TR-DARLINGTON:TIP102,NPN,2W,TO-220,TP,10	
D865	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		Q802	0503-000153	TR-DARLINGTON:TIP102,NPN,2W,TO-220,TP,10	
DZ801	0403-000299	DIODE-ZENER:MTZ7.5C,7.5V,7.29-7.67V,500m		Q851	0502-000244	TR-POWER:KSA940,PNP,1.5W,TO-220,-,40-14	
DZ802	0403-000299	DIODE-ZENER:MTZ7.5C,7.5V,7.29-7.67V,500m		Q852	0501-000366	TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L	
DZ803	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m		Q853	0501-000366	TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L	
DZ804	0403-000662	DIODE-ZENER:MTZ3.0B,3.0V,3.01-3.22V,500m		Q854	0501-000369	TR-SMALL SIGNAL:KSC2331-Y,NPN,1W,TO-92L	
DZ805	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m		Q855	0501-000366	TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L	
DZ806	0403-000662	DIODE-ZENER:MTZ3.0B,3.0V,3.01-3.22V,500m		R801	2006-000296	R-CEMENT:11ohm,5%,5W,CH,BK,9.5x27x9.5mm	
DZ851	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m		R801A	2001-001078	R-CARBON(S):15Kohm,5%,1/2W,AA,TP,2.4x6.4	
DZ852	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m		R802	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4	
DZ853	0403-000656	DIODE-ZENER:MTZ15C,15V,14.35-15.09V,500m		R802A	2001-001066	R-CARBON(S):110ohm,5%,1/2W,AA,TP,2.4x6.4	
DZ857	1203-000451	IC-VOLTAGE REGULATOR:33,TO-92,3P,-,PLAST		R803	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
F801	3601-000461	FUSE-FERRULE:250V,6.3A,TIME-LAG,CERAMIC,		R804	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
F801A	3602-000114	FUSE-HOLDER:-;30mohm		R805	2001-001055	R-CARBON(S):1.8Kohm,5%,1/2W,AA,TP,2.4x6.4	
F801B	3602-000114	FUSE-HOLDER:-;30mohm		R805A	2001-001143	R-CARBON(S):4.3Kohm,5%,1/2W,AA,TP,2.4x6.4	
F851	3601-000399	FUSE-FERRULE:250V,1.6A,TL,GLASS,5.2x20mm		R806	2009-000026	R-METAL PLATE:0.15ohm,10%,5W,CL,TP	
F851A	3602-000114	FUSE-HOLDER:-;30mohm		R807	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
F851B	3602-000114	FUSE-HOLDER:-;30mohm		R808	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
F852	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R809	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
F852A	3602-000114	FUSE-HOLDER:-;30mohm		R810	2002-001010	R-COMPOSITION:1.8Mohm,10%,1/2W,AA,TP,3.7	
F852B	3602-000114	FUSE-HOLDER:-;30mohm		R812	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
F853	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R813	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
F853A	3602-000114	FUSE-HOLDER:-;30mohm		R814	2006-000296	R-CEMENT:11ohm,5%,5W,CH,BK,9.5x27x9.5mm	
F853B	3602-000114	FUSE-HOLDER:-;30mohm		R814A	2001-001078	R-CARBON(S):15Kohm,5%,1/2W,AA,TP,2.4x6.4	
F854	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R815	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
F854A	3602-000114	FUSE-HOLDER:-;30mohm		R816	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
F854B	3602-000114	FUSE-HOLDER:-;30mohm		R817	2001-001055	R-CARBON(S):1.8Kohm,5%,1/2W,AA,TP,2.4x6.4	
F855	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R817A	2001-001143	R-CARBON(S):4.3Kohm,5%,1/2W,AA,TP,2.4x6.4	
F855A	3602-000114	FUSE-HOLDER:-;30mohm		R818	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4	
F855B	3602-000114	FUSE-HOLDER:-;30mohm		R818A	2001-001066	R-CARBON(S):110ohm,5%,1/2W,AA,TP,2.4x6.4	
F856	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R819	2009-001011	R-METAL PLATE:0.18ohm,10%,5W,CL,TP,5x14x	
F856A	3602-000114	FUSE-HOLDER:-;30mohm		R820	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4	
F856B	3602-000114	FUSE-HOLDER:-;30mohm		R820A	2001-000107	R-CARBON(S):150Kohm,5%,1/2W,AA,TP,2.4x6.4	
F857	3601-000281	FUSE-FERRULE:250V,4A,TL,GLASS,5.2x20mm		R821	2002-001012	R-COMPOSITION:8.2Mohm,10%,1/2W,AA,TP,3.7	
F857A	3602-000114	FUSE-HOLDER:-;30mohm		R825	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
F857B	3602-000114	FUSE-HOLDER:-;30mohm		R826	2003-000462	R-METAL OXIDE(S):10Kohm,5%,2W,AA,TP,4x12	
HC801	AA13-20002K	IC-HYBRID:-;STR-S6709 LF953,SIP,9P,SMPS	H/SINK	R827	2001-001096	R-CARBON(S):2.2ohm,5%,1/2W,AA,TP,2.4x6.4	
HC802	AA13-20002K	IC-HYBRID:-;STR-S6709 LF953,SIP,9P,SMPS	H/SINK	R830	2003-000706	R-METAL OXIDE(S):47Kohm,5%,2W,AA,TP,4.3x	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R830A	2003-000706	R-METAL OXIDE(S):47Kohm,5%,2W,AA,TP,4.3x		R515	2001-001150	R-CARBON(S):470Kohm,5%,1/2W,AA,TP,2.4x6.	
R831	2001-000002	R-CARBON(S):200Kohm,5%,1/2W,AA,TP,6.4x2.		R516	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.	
R832	2001-000002	R-CARBON(S):200Kohm,5%,1/2W,AA,TP,6.4x2.		R517	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.	
R851	2003-000584	R-METAL OXIDE(S):22Kohm,5%,2W,AA,TP,4x12		R518	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.	
R852	2003-000777	R-METAL OXIDE(S):68ohm,5%,2W,AA,TP,4x12m		R519	2001-000679	R-CARBON:36Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R853	2001-001152	R-CARBON(S):47Kohm,5%,1/2W,AA,TP,2.4x6.4		V501	3704-001019	SOCKET-CRT:10P,29.1PI,35.5PI,AU30U	
R854	2001-001135	R-CARBON(S):36Kohm,5%,1/2W,AA,TP,2.4x6.4		VR501	2101-000321	VR-ROTARY:1Mohm,0.2,0.6W,-,-	
R855	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m		ZD501	0403-000664	DIODE-ZENER:MTZ3.6A,3.6V,3.455-3.695V,50	
R856	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m					
R857	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4m					
R858	2001-001144	R-CARBON(S):4.7Kohm,5%,1/2W,AA,TP,2.4x6.					
R859	2001-000117	R-CARBON(S):68ohm,5%,1/2W,AA,TP,2.4x6.4m					
R860	2001-001144	R-CARBON(S):4.7Kohm,5%,1/2W,AA,TP,2.4x6.					
R862	2001-000052	R-CARBON(S):3.3Kohm,5%,1/2W,AA,TP,2.4x6.					
R863	2001-000052	R-CARBON(S):3.3Kohm,5%,1/2W,AA,TP,2.4x6.					
R866	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m					
R867	2001-000109	R-CARBON(S):470ohm,5%,1/2W,AA,TP,2.4x6.4					
R870	2001-001103	R-CARBON(S):20Kohm,5%,1/2W,AA,TP,2.4x6.4					
R871	2001-001078	R-CARBON(S):15Kohm,5%,1/2W,AA,TP,2.4x6.4					
R872	2004-001983	R-METAL:2.49Kohm,1%,1/2W,AA,TP,2.4x6.4					
R873	2008-000270	R-FUSIBLE:3.3ohm,5%,1/2W,AA,TP,4.7x11mm					
R890	2001-000052	R-CARBON(S):3.3Kohm,5%,1/2W,AA,TP,2.4x6.					
R891	2001-000052	R-CARBON(S):3.3Kohm,5%,1/2W,AA,TP,2.4x6.					
R896	2001-001126	R-CARBON(S):300ohm,5%,1/2W,AA,TP,2.4x6.4					
RL801	3501-001040	RELAY-POWER:12VDC,500mW,10A,1FormA,15mS,					
T801	AA26-20004H	TRANS-SWITCHING:-,80-280V,-,EER534521.45					
T802	AA26-20004G	TRANS-SWITCHING:-,90-260V,KS,EER534521.4					
<b>ASSY-PCB,CRT(RED)</b>							
*	AA95-20002B	ASSY-PCB,CRT,-,SPT51A,52,RED,-					
C501	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,					
C502	2401-001363	C-AL:470uf,20%,16V,GP,TP,10x12.5.5					
C503	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,					
C504	2401-000922	C-AL:22uf,20%,16V,GP,TP,5x5.5					
C505	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,					
C506	2401-000430	C-AL:10uf,20%,250V,GP,TP,10x16mm,5m					
C507	2201-000600	C-CERAMIC,DISC:560pf,10%,50V,Y5P,TP,5x3,					
C508	2401-000430	C-AL:10uf,20%,250V,GP,TP,10x16mm,5m					
C509	AA27-90001B	COIL-SPARK,GAP:S-23,1.5KV,-,-,-					
C510	AA27-90001B	COIL-SPARK,GAP:S-23,1.5KV,-,-,-					
C515	2201-000969	C-CERAMIC,DISC:10nF,+80-20%,3KV,Y5V,TP,-					
C516	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11					
C517	2201-000611	C-CERAMIC,DISC:56pf,5%,50V,CH,TP,6.5x3.5					
CN501	AA39-20163A	LEAD CONNECTOR-ASSY:-,YFH806-04,S,4P,500					
CN503	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH					
CN504	AA39-20020D	LEAD-CONNECTOR,ASSY:-,67096-005,S,5P,600					
CN505	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH					
D501	0402-000536	DIODE-RECTIFIER:RH10F,1500V,0.8A,DO-204A					
D502	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP					
D503	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP					
D504	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP					
DZ501	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m					
DZ502	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m					
DZ503	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m					
IC501	1201-000539	IC-VIDEO AMP:6101,ZIP9P,-,SINGLE,-,PLAS	H/SINK				
L501	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm					
LEAD/C	AA39-20115A	LEAD-CONNECTOR,ASSY:-,BUSHING,-,1P,500,3					
Q501	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T					
R480	2008-000267	R-FUSIBLE(S):2.4ohm,5%,2W,AA,TP,3.9x10mm					
R501	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm					
R502	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4					
R503	2001-000241	R-CARBON:1.5Kohm,5%,1/8W,AA,TP,1.8x3.2m					
R504	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm					
R505	2001-001164	R-CARBON(S):56Kohm,5%,1/2W,AA,TP,2.4x6.4					
R506	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm					
R507	2003-000468	R-METAL OXIDE(S):10ohm,5%,1W,AA,TP,3.3x9					
R508	2001-000085	R-CARBON(S):100Kohm,5%,1/2W,AA,TP,2.4x6.					
R509	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4					
R510	2001-001122	R-CARBON(S):3.9Kohm,5%,1/2W,AA,TP,2.4x6.					
R511	2001-000563	R-CARBON:27Kohm,5%,1/8W,AA,TP,1.8x3.2mm					
R512	2002-000119	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.5x9					
R513	2001-001047	R-CARBON(S):1.2Mohm,5%,1/2W,AA,TP,2.4x6.					
R514	2001-001113	R-CARBON(S):270Kohm,5%,1/2W,AA,TP,2.4x6.					
R515	2001-001150	R-CARBON(S):470Kohm,5%,1/2W,AA,TP,2.4x6.					
R516	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.					
R517	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.					
R518	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.					
R519	2001-000679	R-CARBON:36Kohm,5%,1/8W,AA,TP,1.8x3.2mm					
V501	3704-001019	SOCKET-CRT:10P,29.1PI,35.5PI,AU30U					
VR501	2101-000321	VR-ROTARY:1Mohm,0.2,0.6W,-,-					
ZD501	0403-000664	DIODE-ZENER:MTZ3.6A,3.6V,3.455-3.695V,50					
<b>ASSY-PCB,CRT(GREEN)</b>							
*	AA95-20002C	ASSY-PCB,CRT,-,SPT51A,52,GREEN,-					
C531	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,					
C532	2401-001363	C-AL:470uf,20%,16V,GP,TP,10x12.5.5					
C533	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,					
C534	2401-000922	C-AL:22uf,20%,16V,GP,TP,5x5.5					
C535	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,					
C536	2401-000430	C-AL:10uf,20%,250V,GP,TP,10x16mm,5m					
C537	2201-000600	C-CERAMIC,DISC:560pf,10%,50V,Y5P,TP,5x3,					
C538	2401-000430	C-AL:10uf,20%,250V,GP,TP,10x16mm,5m					
C539	AA27-90001B	COIL-SPARK,GAP:S-23,1.5KV,-,-,-					
C542	AA27-90001B	COIL-SPARK,GAP:S-23,1.5KV,-,-,-					
C545	2201-000969	C-CERAMIC,DISC:10nF,+80-20%,3KV,Y5V,TP,-					
C546	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11					
C547	2201-000611	C-CERAMIC,DISC:56pf,5%,50V,CH,TP,6.5x3.5					
CN201	3711-002644	CONNECTOR-HEADER:BOX,7P,1R,2.5mm,STRAIGH					
CN201	AA39-20029D	LEAD-CONNECTOR,ASSY:-,67096-007,S,7P,500					
CN502	AA39-20020D	LEAD-CONNECTOR,ASSY:-,67096-005,S,5P,600					
CN5021	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH					
CN5031	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH					
CN5041	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH					
CN505	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH					
CN505	AA39-20020D	LEAD-CONNECTOR,ASSY:-,67096-005,S,5P,600					
CN502	AA39-20016C	LEAD-CONNECTOR,ASSY:-,67096-003,S,3P,400					
CNV021	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH					
CNV03	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH					
CNV04	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH					
CNV05	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH					
D502	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP					
D503	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP					
D504	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP					
D531	0402-000536	DIODE-RECTIFIER:RH10F,1500V,0.8A,DO-204A					
D564	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP					
DZ501	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m					
DZ502	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m					
DZ503	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m					
IC531	1201-000539	IC-VIDEO AMP:6101,ZIP9P,-,SINGLE,-,PLAS	H/SINK				
L531	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm					
LEAD/C	AA39-20115A	LEAD-CONNECTOR,ASSY:-,BUSHING,-,1P,500,3					
Q531	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T					
R520	2001-000508	R-CARBON:220Kohm,5%,1/8W,AA,TP,1.8x3.2m					
R521	2001-000864	R-CARBON:56Kohm,5%,1/8W,AA,TP,1.8x3.2mm					
R531	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm					
R532	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4					
R533	2001-000221	R-CARBON:1.2Kohm,5%,1/8W,AA,TP,1.8x3.2m					
R534	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm					
R535	2001-001164	R-CARBON(S):56Kohm,5%,1/2W,AA,TP,2.4x6.4					
R536	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm					
R537	2003-000468	R-METAL OXIDE(S):10ohm,5%,1W,AA,TP,3.3x9					
R538	2001-000085	R-CARBON(S):100Kohm,5%,1/2W,AA,TP,2.4x6.					
R539	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4					
R540	2001-001122	R					

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
ZD531	0403-000664	DIODE-ZENER:MTZ3.6A,3.6V,3.455-3.695V,50		GUIDE	AA61-50033A	GUIDE-LED;-,PP,H,BL,K,-,-,-	
		<b>ASSY-PCB,CRT(BLUE)</b>		JHY01	3722-000148	JACK-PHONE:1P,3.6mm,MBAG,BLACK,-	
				JSY01	3722-000191	JACK-RCA:3P(VHS),3.4mm,AG,BLU,NO	
*	AA95-20002D	ASSY-PCB,CRT;-SPT51A,52,BLUE,-		LDY01	0601-000385	LED:ROUND,RED,3mm,700nm	
C561	2201-000193	C-CERAMIC,DISC;10pF,0.3pF,50V,CH,TP,5x3,		LDY02	0601-000385	LED:ROUND,RED,3mm,700nm	
C562	2401-001363	C-AL:470uF,20%,16V,GP,TP,10x12.5,5		LDY03	0601-000385	LED:ROUND,RED,3mm,700nm	
C563	2201-000119	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,		LDY04	0601-000385	LED:ROUND,RED,3mm,700nm	
C564	2401-000922	C-AL:22uF,20%,16V,GP,TP,5x5,5		LY01	2701-000101	INDUCTOR-AXIAL:1.2uH,10%,2.5x3.4mm	
C565	2201-000119	C-CERAMIC,DISC;100nF,+80-20%,50V,Y5V,TP,		LY02	2701-000101	INDUCTOR-AXIAL:1.2uH,10%,2.5x3.4mm	
C566	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m		RY05	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
C567	2201-000600	C-CERAMIC,DISC:560pF,10%,50V,Y5P,TP,5x3,		RY06	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C568	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m		RY07	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C569	2201-000969	C-CERAMIC,DISC;10nF,+80-20%,3KV,Y5V,TP,-		RY08	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
C571	AA27-90001B	COIL-SPARK,GAP:S-23,1.5KV,-,-,-		RY09	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4	
C575	AA27-90001B	COIL-SPARK,GAP:S-23,1.5KV,-,-,-		RY10	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4	
C576	2305-000154	C-FILM,MPEF:100nF,5%,400V,TP,21.5x6.5x11		RY11	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4	
C577	2201-000611	C-CERAMIC,DISC:56pF,5%,50V,CH,TP,6.5x3,5		RY12	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4	
CN502	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH		RY13	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m	
CN5051	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH		RY14	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m	
CNH01	AA39-20116A	LEAD-CONNECTOR,ASSY;-YFH800-03,-,3(2)P,		RY15	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
D502	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP				<b>ASSY-PCB,PREAMP</b>	
D503	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		*	AA95-40002W	ASSY-PCB,PREAMP;-SPM5288PF,SPT51A,PREAM	
D504	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP		RR01	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D561	0402-000536	DIODE-RECTIFIER:RH10F,1500V,0.8A,DO-204A		CR01	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11.5	
DZ501	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m		LR01	2701-000112	INDUCTOR-AXIAL:100uH,10%,2.8x7mm	
DZ502	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m		CN905	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH	
DZ503	0403-000531	DIODE-ZENER:MTZ13B,13V,12.55-13.21V,500m		CN905	AA39-20033J	LEAD-CONNECTOR,ASSY;-67096-003,S,3P,700	
IC561	1201-000539	IC-VIDEO AMP:6101,ZIP9P,-,SINGLE,-,PLAS	H/SINK	RMR01	AA59-60001Z	MODULE-REMOCON;-ORC-638V1/SR-5CP2,38KHz	
LEAD/C	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm		SCREW	AA60-10011A	SCREW-TAPTITE:HH,+PC,MA,L12,ZPC(BLK),SW	
Q561	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mV,TO-92,T		BRKT	AA61-10042A	BRACKET-PCB,RMC;-S4388,SECC,T1.0,-,-,-	
R561	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm				<b>ASSY-PCB,A/V SW</b>	
R562	2001-001159	R-CARBON(S):510ohm,5%,1/2W,AA,TP,2.4x6.4		*	AA95-40002X	ASSY-PCB,A/V S/W;-SPM5288PF,SPT51A,A/V,	
R563	2001-000232	R-CARBON:1.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		AV701	3722-000502	JACK-RCA:9P,3.6MM,-,SN	
R564	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm		AV702	3722-000498	JACK-SCART:21P,-,SN,BLK,NO	
R565	2001-001164	R-CARBON(S):56Kohm,5%,1/2W,AA,TP,2.4x6.4		AV703	3722-000544	JACK-VHS:12P,11.5mm,AG,BLK,N	
R566	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		C701	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R567	2003-000468	R-METAL OXIDE(S):10ohm,5%,1W,AA,TP,3.3x9		C702	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R568	2001-000085	R-CARBON(S):100Kohm,5%,1/2W,AA,TP,2.4x6.		C703	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
R569	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4		C704	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R570	2001-001122	R-CARBON(S):3.9Kohm,5%,1/2W,AA,TP,2.4x6.		C705	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X	
R571	2001-000563	R-CARBON:27Kohm,5%,1/8W,AA,TP,1.8x3.2mm		C706	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R572	2002-000119	R-COMPOSITION:1Kohm,10%,1/2W,AA,TP,3.5x9		C707	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R573	2001-001047	R-CARBON(S):1.2Mohm,5%,1/2W,AA,TP,2.4x6.		C708	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R574	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.		C709	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
R575	2001-001150	R-CARBON(S):470Kohm,5%,1/2W,AA,TP,2.4x6.		C710	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R576	2001-001113	R-CARBON(S):270Kohm,5%,1/2W,AA,TP,2.4x6.		C711	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R577	2001-000679	R-CARBON:36Kohm,5%,1/8W,AA,TP,1.8x3.2mm		C712	2401-000242	C-AL:100uF,20%,10V,GP,TP,5x11.5	
R578	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.		C713	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
R579	2001-001129	R-CARBON(S):330Kohm,5%,1/2W,AA,TP,2.4x6.		C714	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
V561	3704-001019	SOCKET-CRT:10P,29.1PI,35.5PI,AU30U		C715	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
VR561	2101-000321	VR-ROTARY:1Mohm,0.2,0.6W,-,-		C716	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
ZD561	0403-000664	DIODE-ZENER:MTZ3.6A,3.6V,3.455-3.695V,50		C717	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X	
		<b>ASSY-PCB,JACK</b>		C718	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
*	AA95-30001M	ASSY-PCB,JACK;-SPT51A,-,-		C719	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
CN602	3711-000661	CONNECTOR-HEADER:BOX,12P,1R,2.5m		C720	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
CN602	AA39-20032C	LEAD-CONNECTOR,ASSY;-67096-012,S,12P,40		C722	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X	
CN901	3711-002641	CONNECTOR-HEADER:BOX,10P,1R,2.54mm,STRAI		C723	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
CN901	AA39-20025F	LEAD-CONNECTOR,ASSY;-67096-010,S,10P,50		C724	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
CN902	3711-000631	CONNECTOR-HEADER:BOX,11P,1R,2.5mm,STRAIG		C725	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
CN904	3711-002648	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,STRAIGH		C726	2201-000423	C-CERAMIC,DISC:27pF,5%,50V,NPO,TP,5x3,2.	
CN904	AA39-20096B	LEAD-CONNECTOR,ASSY;-67096-009,S,9P,600		C727	2201-000423	C-CERAMIC,DISC:27pF,5%,50V,NPO,TP,5x3,2.	
CY01	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11.5		C728	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
CY02	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,		C729	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,	
CY03	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,		C730	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
CY04	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11.5		C731	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
CY05	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11.5		C732	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM	
CY06	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5		C733	2201-000426	C-CERAMIC,DISC:27pF,5%,50V,SL,TP,5x3,5	
CY07	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11.5		C734	2201-000426	C-CERAMIC,DISC:27pF,5%,50V,SL,TP,5x3,5	
CY08	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5		C735	2201-000426	C-CERAMIC,DISC:27pF,5%,50V,SL,TP,5x3,5	



Electric Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C736	2201-000426	C-CERAMIC,DISC:27pF,5%,50V,SL,TP,5x3,5		O703	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C737	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X		O704	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C738	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		O705	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C742	2201-000558	C-CERAMIC,DISC:470pF,10%,50V,Y5P,TP,5x3,		O706	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C743	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		O707	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C744	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X		O708	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C745	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X		O709	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C747	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		O710	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C748	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		O711	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C749	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5		O712	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C750	2401-002299	C-AL:4.7uF,20%,50V,GP,TP,5x7,5		O713	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C751	2401-002299	C-AL:4.7uF,20%,50V,GP,TP,5x7,5		O714	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C754	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		O715	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C755	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		O716	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C756	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		O717	0504-000116	TR-DIGITAL:KSR1001,NPN,300mW,4.7K-4.7K,T	
C757	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		R701	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C758	2401-000242	C-AL:100uF,20%,10V,GP,TP,5x11,5		R702	2001-000660	R-CARBON:33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C759	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		R703	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C760	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		R704	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
C762	2401-000455	C-AL:10UF,20%,35V,GP,TP,4X7MM,5MM		R705	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C763	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		R706	2001-000660	R-CARBON:33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C764	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5		R707	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
C765	2401-002009	C-AL:100uF,20%,16V,GP,TP,6.3x7,5		R708	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
C766	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		R709	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
CN701	3711-003490	CONNECTOR-HEADER:BOX,20P,2R,2.54MM,ANGLE		R710	2001-000325	R-CARBON:120ohm,5%,1/8W,AA,TP,1.8x3.2mm	
CN702	3711-003490	CONNECTOR-HEADER:BOX,20P,2R,2.54MM,ANGLE		R711	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D701	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R712	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D702	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R713	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
D703	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R714	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D704	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R715	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D705	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R716	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D706	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R717	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D707	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R718	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D708	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R719	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D709	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R720	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D710	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R721	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D711	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R722	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
D712	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T		R723	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ706	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R724	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ707	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R725	2001-000429	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ708	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R726	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ709	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R727	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ710	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R728	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ712	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R729	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ713	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R730	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ714	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R731	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ715	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R732	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ716	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R733	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ717	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R734	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DZ718	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R735	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
DZ719	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R736	2001-001175	R-CARBON(S):62ohm,5%,1/2W,AA,TP,2.4x6.4m	
DZ720	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R737	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ721	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R738	2001-000290	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ722	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R739	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ723	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R740	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ724	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R742	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ725	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R743	2001-000522	R-CARBON:22Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ726	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R744	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ727	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R745	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ728	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R746	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
DZ729	0403-000654	DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		R747	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
IC701	0801-000961	IC-CMOS LOGIC:4053B,MULTIPLEXER,DIP,16P,3		R749	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
IC702	0801-000961	IC-CMOS LOGIC:4053B,MULTIPLEXER,DIP,16P,3		R750	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
IC703	1001-000217	IC-AUDIO SWITCH:KA2192B,4-INPUT,DIP,30P,		R751	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
IC704	1001-000217	IC-AUDIO SWITCH:KA2192B,4-INPUT,DIP,30P,		R752	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
L701	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R753	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
L702	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R754	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
L703	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R756	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
L704	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R757	2001-000302	R-CARBON:10ohm,5%,1/8W,AA,TP,1.8x3.2mm	
L705	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R758	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
L706	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R759	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
L707	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R760	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
L708	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R761	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
L709	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R762	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
L710	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm		R763	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	
O701	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R764	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
O702	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T		R765	2001-000969	R-CARBON:75ohm,5%,1/8W,AA,TP,1.8x3.2mm	



Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
RJ20	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012		CV12	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,	
RJ21	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012		CV13	2401-001527	C-AL:47uF,20%,250V,HR,TP,13x25mm,5m	
RJ22	2007-001177	R-CHIP;8.2Kohm,5%,1/10W,DA,TP,2012		CV14	2401-001527	C-AL:47uF,20%,250V,HR,TP,13x25mm,5m	
RJ23	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012		CV15	2201-000604	C-CERAMIC,DISC:56pF,+100-0%,500V,SL,TP,7	
RJ24	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012		CV16	2401-000399	C-AL:10uF,20%,160V,HR,TP,10x20,5mm	
RJ25	2007-000738	R-CHIP;30Kohm,5%,1/10W,DA,TP,2012		CV17	2201-000441	C-CERAMIC,DISC:3.3nF,10%,500V,Y5P,TP,10x	
SHIELD	AA63-40023A	SHIELD-CASE-,SPT,TO.5,SCT51A,Z70,WZ74,		CV18	2301-000261	C-FILM,PEF:4.7nF,5%,100V,TP,10.5x12.5x6.	
X651	2801-000125	CRYSTAL-UNIT:10MHZ,20PPM,28-AAM,32PF,300		D301	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
XJ01	2801-000992	CRYSTAL-UNIT:8.192MHZ,30PPM,28-AAM,15PF,		D302	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
<b>ASSY-PCB,DEFLECTION</b>				D303	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
*	AA95-90001R	ASSY-PCB,DEFLECTION;-;SPM5288F,SPT51A,PA		D401	0402-000266	DIODE-RECTIFIER:RH4F,1500V,1.5A,-	
C301	2401-001661	C-AL:68uF,20%,100V,GP,TP,10x16,5		D402	0402-000542	DIODE-RECTIFIER:RU4AM,600V,2A,-	
C302	2401-002273	C-AL:220uF,20%,25V,HR,TP,10x20mm,5m		D403	0402-000536	DIODE-RECTIFIER:RH10F,1500V,0.8A,DO-204A	
C303	2401-002285	C-AL:470uF,20%,100V,GP,TP,16x25,7.5		D429	0402-000546	DIODE-RECTIFIER:TVR10G,400V,1.0A,DO-41,T	
C304	2401-001622	C-AL:6.8uF,20%,50V,BP,TP,16x25mm,7.		D430	0402-000536	DIODE-RECTIFIER:RH10F,1500V,0.8A,DO-204A	
C305	2401-002285	C-AL:470uF,20%,100V,GP,TP,16x25,7.5		D431	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C306	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		D432	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C308	2301-000383	C-FILM,PEF:10nF,5%,50V,TP,6x7x3.2mm,5mm		D433	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C310	2305-000178	C-FILM,MPEF:10nF,5%,100V,TP,-,5mm		D434	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C311	2305-000285	C-FILM,MPEF:220nF,5%,100V,TP,20x18x11.5,		D435	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C312	2201-000291	C-CERAMIC,DISC:1nF,10%,500V,Y5P,TP,8.5x5		D471	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
C313	2305-000285	C-FILM,MPEF:220nF,5%,100V,TP,20x18x11.5,		D472	0402-000493	DIODE-RECTIFIER:1R5GU41,400V,1.5A,DO-15L	
C314	2305-000149	C-FILM,MPEF:100nF,5%,100V,TP,12x12.5x6.5		D473	0402-000540	DIODE-RECTIFIER:RU20A,600V,1.5A,-,TP	
C315	2301-000148	C-FILM,PEF:10nF,5%,100V,TP,7x3.2x7mm,5mm		D474	0402-000233	DIODE-RECTIFIER:FML-G12S,200V,5A,-,-	H/SINK
C315	2305-000178	C-FILM,MPEF:10nF,5%,100V,TP,-,5mm		D475	0402-000250	DIODE-RECTIFIER:RG4C,1000V,1A,-	
C400	2401-000262	C-AL:100uF,20%,160V,HR,TP,16x25,7.5		D476	0402-000250	DIODE-RECTIFIER:RG4C,1000V,1A,-	
C401	2305-000308	C-FILM,MPEF:22nF,5%,250V,-,14.5x6.0x9.5m		DV01	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C402	2303-000110	C-FILM,PPF:100nF,5%,200V,BK,20.5x18.5x10		DV02	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
C404	2303-000128	C-FILM,PPF:12nF,5%,1.6KV,BK,31x21x14.25m		DV03	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
C405	2303-000186	C-FILM,PPF:22nF,5%,400V,BK,19.5x13.5x8.1		DV04	0402-000132	DIODE-RECTIFIER:1N4004,400V,1A,DO-41,TP	
C406	2306-000260	C-FILM,MPPF:720nF,5%,200V,BK,26x23.5x15,		IC301	1204-000426	IC-VERTICAL PROCESSOR:TDA83500/N4,SIP,13P	H/SINK
C407	2201-000441	C-CERAMIC,DISC:3.3nF,10%,500V,Y5P,TP,10x		IC401	1201-000191	IC-OP AMP:4558,DIP,8P,300MIL,DUAL,20V/mV	
C408	2401-001232	C-AL:4.7uF,20%,250V,GP,TP,10x12.5,5		L301	2701-001013	INDUCTOR-AXIAL:1uH,10%,4.5x14mm	
C411	2301-000198	C-FILM,PEF:2.2nF,5%,100V,TP,10.5x12.5x6.		L302	2701-001013	INDUCTOR-AXIAL:1uH,10%,4.5x14mm	
C412	2401-001571	C-AL:47uF,+20%-0%,50V,GP,TP,8x11.5,		L303	AA27-40001F	COIL-HORIZ WIDTH:-,1mH,DR1520,PIO,4,-	
C413	2201-000555	C-CERAMIC,DISC:470pF,10%,2KV,Y5P,BK,8x3.		L304	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C414	2303-001027	C-FILM,PPF:4.7nF,5%,1600V,BK,31x16x9,20		L305	2701-001043	INDUCTOR-AXIAL:10uH,10%,14x4.5mA	
C415	2306-000327	C-FILM,MPPF:6.3nF,3%,1.6KV,TP,28.5x18x10		L307	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
C416	2306-000004	C-FILM,MPPF:330nF,5%,250V,TP,20x18.5x10.		L308	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
C427	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		L309	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
C429	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		L401	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
C430	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		L402	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
C431	2401-000993	C-AL:3.3uF,20%,160V,GP,TP,8x11.5,5		L403	AA27-30001G	COIL-LINEARITY:-,21UH,DR1415,PIO,7.4.5X3	
C432	2201-000132	C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4		L471	2701-000115	INDUCTOR-AXIAL:10uH,10%,2.8x7mm	
C434	2301-000213	C-FILM,PEF:220nF,5%,250V,TP,21.5x11,7.5		LV01	AA27-10001E	COIL-CHOKE:-,1.0UH,K,25.2100A,T,SP0408-1	
C435	2201-000112	C-CERAMIC,DISC:1.5nF,10%,50V,Y5V,TP,5x3,		LV02	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
C437	2401-001157	C-AL:33uF,20%,160V,GP,TP,12.5x20,5		LV03	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
C438	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		LV04	3301-000287	CORE-FERRITE BEAD:AA,3.5x1x6mm,1500,2400	
C439	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		Q301	0502-000194	TR-POWER:2SD1267,NPN,2W,TO-220,ST,120-2	H/SINK
C471	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		Q302	0502-000242	TR-POWER:KSA614,PNP,25W,TO-220,TP,40-24	
C472	2201-000132	C-CERAMIC,DISC:100pF,10%,500V,Y5P,TP,6x4		Q401	0502-000006	TR-POWER:KSC1507,NPN,15W,TO-220,TP,120-	
C473	2401-000262	C-AL:100uF,20%,160V,HR,TP,16x25,7.5		Q402	0502-000450	TR-POWER:2SD1887YD,NPN,1500V,800V,10A,7	H/SINK
C474	2401-000262	C-AL:100uF,20%,160V,HR,TP,16x25,7.5		Q403	0502-000153	TR-POWER:2SC2344-D,NPN,1.2W,TO-220,-,60	
C475	2201-000551	C-CERAMIC,DISC:470pF,10%,1KV,Y5P,TP,8x5,		Q404	0502-000209	TR-POWER:2SD1880YD,NPN,70W,TO-3P,ST,8	H/SINK
C476	2401-002285	C-AL:470uF,20%,100V,GP,TP,16x25,7.5		Q426	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
C477	2201-000551	C-CERAMIC,DISC:470pF,10%,1KV,Y5P,TP,8x5,		Q427	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
C478	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20,5		Q428	0501-000366	TR-SMALL SIGNAL:KSC2330-Y,NPN,1W,TO-92L,	
C479	2306-000252	C-FILM,MPPF:68nF,5%,1.6KV,BK,41x28.5x22,		Q429	0502-000193	TR-POWER:2SD1090,NPN,80W,TO-3P,ST,500-2	H/SINK
CN202	AA39-20071B	LEAD-CONNECTOR,ASSY;-;YBNH025-12,67096-0		Q430	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
CN401	3711-002643	CONNECTOR-HEADER:BOX,4P,1R,2.5MM,STRAIGH		QV01	0501-000245	TR-SMALL SIGNAL:BC548C,NPN,500mW,TO-92,T	
CNV01	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH		QV02	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
CNV02	3711-002642	CONNECTOR-HEADER:BOX,3P,1R,2.5MM,STRAIGH		QV03	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
CV01	2401-002273	C-AL:220uF,20%,25V,HR,TP,10x20mm,5m		QV04	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
CV02	2201-000180	C-CERAMIC,DISC:10nF,10%,50V,Y5V,TP,6.5*3		QV05	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
CV03	2201-000180	C-CERAMIC,DISC:10nF,10%,50V,Y5V,TP,6.5*3		QV06	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
CV04	2201-000180	C-CERAMIC,DISC:10nF,10%,50V,Y5V,TP,6.5*3		QV07	0501-000283	TR-SMALL SIGNAL:KSA539,PNP,400mW,TO-92,T	
CV05	2301-000519	C-FILM,PEF:3.3nF,5%,100V,TP,5.8x3x12.5,5		QV08	0502-000131	TR-POWER:2SA1011-D,PNP,1.2W,TO-220,-,60	H/SINK
CV06	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5		QV09	0502-000153	TR-POWER:2SC2344-D,NPN,1.2W,TO-220,-,60	H/SINK
CV07	2201-000180	C-CERAMIC,DISC:10nF,10%,50V,Y5V,TP,6.5*3		QV10	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO-92,T	
CV08	2201-000180	C-CERAMIC,DISC:10nF,10%,50V,Y5V,TP,6.5*3		R301	2001-001117	R-CARBON(S):2Kohm,5%,1/2W,AA,TP,2.4x6.4m	
CV09	2201-000291	C-CERAMIC,DISC:1nF,10%,500V,Y5P,TP,8.5x5		R302	2001-000016	R-CARBON(S):1ohm,5%,1/2W,AA,TP,2.4x6.4mm	
CV10	2401-000430	C-AL:10uF,20%,250V,GP,TP,10x16mm,5m		R303	2001-000016	R-CARBON(S):1ohm,5%,1/2W,AA,TP,2.4x6.4mm	
CV11	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,		R304	2003-000606	R-METAL OXIDE(S):270ohm,5%,2W,AA,TP,4x12	
				R305	2003-000502	R-METAL OXIDE(S):150ohm,5%,2W,AA,TP,4x12	
				R306	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4	
				R307	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4	
				R308	2001-001152	R-CARBON(S):47Kohm,5%,1/2W,AA,TP,2.4x6.4	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R309	2001-001155	R-CARBON(S):5.6Kohm,5%,1/2W,AA,TP,2.4x6.4		RJ410	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R310	2001-000028	R-CARBON(S):100ohm,5%,1/2W,AA,TP,2.4x6.4		RJ411	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R311	2001-001146	R-CARBON(S):4.7ohm,5%,1/2W,AA,TP,2.4x6.4		RJ412	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R312	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4		RJ413	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R313	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4		RJ414	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R314	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4		RJ415	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R315	2003-000606	R-METAL OXIDE(S):270ohm,5%,2W,AA,TP,4x12		RJ416	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R316	2003-000606	R-METAL OXIDE(S):270ohm,5%,2W,AA,TP,4x12		RJ417	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R317	2008-000190	R-FUSIBLE(S):1.2ohm,5%,2W,AA,TP,3.9x10mm		RJ418	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R401	2004-001989	R-METAL:620ohm,5%,1/8W,AA,TP,1.8x3.2mm		RJ419	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R402	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm		RJ420	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R403	2003-000683	R-METAL OXIDE(S):4.7Kohm,5%,1W,AA,TP,3.3		RJ421	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R404	2003-000417	R-METAL OXIDE(S):1.2Kohm,5%,3W,AA,TP,6x1		RJ422	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R405	2006-000319	R-CEMENT:3Kohm,5%,5W,CA,BK,9.5x25x9.5mm		RJ423	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R406	2001-000020	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4m		RJ424	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R407	2003-000522	R-METAL OXIDE(S):180ohm,5%,1W,AA,TP,3.3x		RJ425	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R408	2003-000634	R-METAL OXIDE(S):3.9Kohm,5%,1W,AA,TP,3.3		RJ428	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R409	2001-001143	R-CARBON(S):4.3Kohm,5%,1/2W,AA,TP,2.4x6.4		RJ429	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R410	2003-000561	R-METAL OXIDE(S):2.7Kohm,5%,2W,AA,TP,4x1		RJ433	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R411	2004-001989	R-METAL:620ohm,5%,1/8W,AA,TP,1.8x3.2mm		RJ434	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R412	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm		RJ436	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R413	2003-000650	R-METAL OXIDE(S):330ohm,5%,2W,AA,TP,4x12		RJ438	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R414	2008-000298	R-FUSIBLE:47ohm,5%,1/4W,AA,TP-		RJ445	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R415	2001-000020	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4m		RV01	2008-001005	R-FUSIBLE:0.47ohm,10%,1W,AA,TP,4.7x11.7m	
R416	2003-000561	R-METAL OXIDE(S):2.7Kohm,5%,2W,AA,TP,4x1		RV02	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R417	2008-001005	R-FUSIBLE:0.47ohm,10%,1W,AA,TP,4.7x11.7m		RV03	2001-001178	R-CARBON(S):680ohm,5%,1/2W,AA,TP,2.4x6.4	
R421	2003-000487	R-METAL OXIDE(S):12Kohm,5%,2W,AA,TP,4x12		RV04	2001-000331	R-CARBON:12Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R423	2001-001099	R-CARBON(S):2.7Kohm,5%,1/2W,AA,TP,2.4x6.4		RV05	2001-000890	R-CARBON:6.8Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R424	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m		RV06	2001-000449	R-CARBON:2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R425	2003-000752	R-METAL OXIDE(S):6.8Kohm,5%,2W,AA,TP,4x1		RV07	2001-000449	R-CARBON:2.2Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R426	2001-001144	R-CARBON(S):4.7Kohm,5%,1/2W,AA,TP,2.4x6.4		RV09	2001-000780	R-CARBON:470ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R441	2001-000591	R-CARBON:3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		RV10	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R444	2004-001185	R-METAL:680Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RV11	2008-001005	R-FUSIBLE:0.47ohm,10%,1W,AA,TP,4.7x11.7m	
R445	2004-001384	R-METAL(S):150Kohm,1%,1/2W,AA,TP,2.4x6.4		RV12	2001-001192	R-CARBON(S):820ohm,5%,1/2W,AA,TP,2.4x6.4	
R446	2001-000109	R-CARBON(S):470ohm,5%,1/2W,AA,TP,2.4x6.4		RV13	2001-000793	R-CARBON:47ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R447	2001-001086	R-CARBON(S):18Kohm,5%,1/2W,AA,TP,2.4x6.4		RV14	2001-000118	R-CARBON(S):180ohm,5%,1/2W,AA,TP,2.4x6.4	
R448	2001-001047	R-CARBON(S):1.2Mohm,5%,1/2W,AA,TP,2.4x6.4		RV15	2001-000009	R-CARBON:20Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R449	2001-001142	R-CARBON(S):3Kohm,5%,1/2W,AA,TP,2.4x6.4m		RV16	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m	
R450	2001-000007	R-CARBON:3Kohm,5%,1/8W,AA,TP,1.8x3.2mm		RV17	2001-000660	R-CARBON:33Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R451	2001-000591	R-CARBON:3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		RV18	2001-000793	R-CARBON:47ohm,5%,1/8W,AA,TP,1.8x3.2mm	
R452	2001-001131	R-CARBON(S):33Kohm,5%,1/2W,AA,TP,2.4x6.4		RV19	2001-000019	R-CARBON(S):10ohm,5%,1/2W,AA,TP,2.4x6.4m	
R453	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m		RV20	2001-001195	R-CARBON(S):82ohm,5%,1/2W,AA,TP,2.4x6.4m	
R454	2003-000246	R-METAL OXIDE(S):3.3KOHM,5%,3W,AA,TP,6x1		RV21	2001-001195	R-CARBON(S):82ohm,5%,1/2W,AA,TP,2.4x6.4m	
R455	2003-000538	R-METAL OXIDE(S):1Kohm,5%,2W,AA,TP,4x12m		RV22	2001-001045	R-CARBON(S):1.2Kohm,5%,1/2W,AA,TP,2.4x6.4	
R456	2003-000505	R-METAL OXIDE(S):150ohm,5%,3W,AA,TP,6x1		RV23	2001-001050	R-CARBON(S):1.5Kohm,5%,1/2W,AA,TP,2.4x6.4	
R457	2004-0011390	R-METAL(S):1Kohm,2%,1/2W,AA,TP,2.4x6.4mm		RV24	2001-001179	R-CARBON(S):68Kohm,5%,1/2W,AA,TP,2.4x6.4	
R460	2001-001179	R-CARBON(S):68Kohm,5%,1/2W,AA,TP,2.4x6.4		RV25	2001-001179	R-CARBON(S):68Kohm,5%,1/2W,AA,TP,2.4x6.4	
R461	2001-001088	R-CARBON(S):1Kohm,5%,1/2W,AA,TP,2.4x6.4m		RV26	2001-001050	R-CARBON(S):1.5Kohm,5%,1/2W,AA,TP,2.4x6.4	
R462	2001-001194	R-CARBON(S):82Kohm,5%,1/2W,AA,TP,2.4x6.4		RV27	2001-001045	R-CARBON(S):1.2Kohm,5%,1/2W,AA,TP,2.4x6.4	
R471	2008-000241	R-FUSIBLE:1.9ohm,5%,2W,CA,BK,6.3x18x6.3m		RV28	2003-000744	R-METAL OXIDE(S):56ohm,5%,2W,AA,TP,4x12m	
R472	2001-000085	R-CARBON(S):100Kohm,5%,1/2W,AA,TP,2.4x6.4		RV29	2001-001152	R-CARBON(S):47Kohm,5%,1/2W,AA,TP,2.4x6.4	
R473	2001-000085	R-CARBON(S):100Kohm,5%,1/2W,AA,TP,2.4x6.4		RV30	2003-000744	R-METAL OXIDE(S):56ohm,5%,2W,AA,TP,4x12m	
R474	2008-000263	R-FUSIBLE:1ohm,5%,1/2W,AA,TP,4.7x11mm		RV31	2001-001100	R-CARBON(S):2.7ohm,5%,1/2W,AA,TP,2.4x6.4	
R475	2008-001005	R-FUSIBLE:0.47ohm,10%,1W,AA,TP,4.7x11.7m		RV32	2001-001100	R-CARBON(S):2.7ohm,5%,1/2W,AA,TP,2.4x6.4	
R476	2001-001107	R-CARBON(S):220ohm,5%,1/2W,AA,TP,2.4x6.4		RV33	2003-000578	R-METAL OXIDE(S):220ohm,5%,2W,AA,TP,4x12	
R481	2001-001164	R-CARBON(S):56Kohm,5%,1/2W,AA,TP,2.4x6.4		RV34	2001-000429	R-CARBON:1Kohm,5%,1/8W,AA,TP,1.8x3.2mm	
R482	2004-001379	R-METAL(S):12Kohm,1%,1/2W,AA,TP,2.4x6.4m		T401	AA26-90001K TRANS-DUMMY:-.55MH,EER404215,130/46/16		
RJ301	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		T402	AA26-50001A HORIZ.DRIVE:-.90MH,67UH,9.5UH,YL81,ST		
RJ302	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		T403	AA26-50001F HORIZ.DRIVE:-.50MH,594uH,4.0uH,E119,-		
RJ303	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		T404	AA26-90001L TRANS-DUMMY:-.15mH,ER4042,-		
RJ304	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		T444	AA26-30001U TRANS-FLYBACK:-FWZ-43B001,43,125V		
RJ305	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		VR401	2103-000670 VR-SEMI:1Kohm,25%,1/5W,TOP		
RJ306	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD301	0403-000655 DIODE-ZENER:MTZ13A,13V,12.11-12.75V,500m		
RJ307	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD302	0403-000699 DIODE-ZENER:TZP27B,27V,27-30.8V,1W,DO-41		
RJ308	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD303	0403-000700 DIODE-ZENER:TZP33A,33V,31-35V,1W,DO-41		
RJ309	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD304	0403-000699 DIODE-ZENER:TZP27B,27V,27-30.8V,1W,DO-41		
RJ310	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD305	0403-000699 DIODE-ZENER:TZP27B,27V,27-30.8V,1W,DO-41		
RJ311	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD306	0403-000658 DIODE-ZENER:MTZ18A,18V,16.22-17.06V,500m		
RJ401	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD307	0403-000355 DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500		
RJ402	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD308	0403-000699 DIODE-ZENER:TZP27B,27V,27-30.8V,1W,DO-41		
RJ403	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD401	0403-000300 DIODE-ZENER:MTZ8.2B,8.2V,7.78-8.19V,500m		
RJ404	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD402	0403-000654 DIODE-ZENER:MTZ12B,12V,11.44-12.03V,500m		
RJ405	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD405	0403-000299 DIODE-ZENER:MTZ7.5C,7.5V,7.29-7.67V,500m		
RJ406	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD423	0403-000355 DIODE-ZENER:UZ5.1BSB,5.1V,4.97-5.18V,500		
RJ407	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZD424	0403-000294 DIODE-ZENER:MTZ4.7B,4.7V,4.55-4.80V,500m		
RJ408	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm		ZDV01	0403-000655 DIODE-ZENER:MTZ13A,13V,12.11-12.75V,500m		
RJ409	2001-000210	R-CARBON:0ohm,5%,1/8W,AA,TP,1.8x3.2mm					

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
<b>ASSY-PCB,CONVERGENCE</b>							
*	AA95-90001S	ASSY-PCB,CONVERGENCE;- ,SPM5288F,SPT51A,P		CZ056	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
BT+HS	AA60-10008A	SCREW-TAPPING;TH+,M3,L10,ZPC(YEL),SWRCH		CZ057	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C651	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		CZ058	2401-000988	C-AL:3.3uF,20%,100V,BP,TP,5x11mm,5m	
C652	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11,5		CZ059	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C653	2301-000192	C-FILM,PEF:1nF,5%,50V,TP,5.3x10mm,5mm		CZ060	2401-000480	C-AL:100uF,20%,50V,GP,TP,5x11,5	
C654	2401-001333	C-AL:470nF,20%,50V,GP,TP,5x11,5		CZ061	2401-000988	C-AL:3.3uF,20%,100V,BP,TP,5x11mm,5m	
C655	2201-002022	C-CERAMIC,DISC:5pF,0.25pF,500V,NPO,TP,5x		CZ062	2401-001914	C-AL:1uF,20%,50V,BP,TP,5x11,5	
C656	2201-002022	C-CERAMIC,DISC:5pF,0.25pF,500V,NPO,TP,5x		CZ063	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C657	2301-000530	C-FILM,PEF:100nF,5%,100V,TP,11.5x12.5x6.		CZ064	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
C658	2301-000530	C-FILM,PEF:100nF,5%,100V,TP,11.5x12.5x6.		CZ064A	2401-000711	C-AL:2200uF,20%,25V,GP,TP,16x25,7,5	
C675	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,5		CZ065	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5	
C676	2401-001661	C-AL:68uF,20%,100V,GP,TP,10x16,5		CZ066	2401-001397	C-AL:470uF,20%,25V,GP,TP,10x16,5	
C678	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,5		CZ067	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20,5	
C679	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20,5		CZ067A	2401-001989	C-AL:4.7uF,20%,50V,BP,TP,5x11,5	
C680	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,5		CZ068	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20,5	
C681	2401-001429	C-AL:470uF,20%,50V,GP,TP,13x20,5		CZ069	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12,5mm,	
C682	2401-001661	C-AL:68uF,20%,100V,GP,TP,10x16,5		CZ070	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12,5mm,	
C683	2401-000360	C-AL:100uF,20%,50V,GP,TP,8x11,5,5		CZ071	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12,5mm,	
C684	2401-000773	C-AL:220uF,20%,10V,NP,TP,10x12,5,5m		CZ072	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12,5mm,	
C685	2401-000622	C-AL:2.2uF,20%,100V,BP,TP,13x25mm,5		CZ073	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12,5mm,	
C686	2401-000622	C-AL:2.2uF,20%,100V,BP,TP,13x25mm,5		CZ074	2401-000365	C-AL:100uF,20%,50V,WT,TP,10x12,5mm,	
CN401	3711-002643	CONNECTOR-HEADER:BOX,4P,1R,2.5MM,STRAIGH		CZ075	2401-001570	C-AL:47UF,20%,50V,WT,TP,10X20MM,5MM	
CN401	AA39-20018A	LEAD-CONNECTOR,ASSY;- ,YSH025-04,S,4P,100		CZ080	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5	
CN601	3711-002645	CONNECTOR-HEADER:BOX,6P,1R,2.5MM,STRAIGH		D651	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CN602	3711-003641	CONNECTOR-HEADER:BOX,12P,1R,2.5mm,STRAIGH		D652	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
CN603	3711-002643	CONNECTOR-HEADER:BOX,4P,1R,2.5MM,STRAIGH		DZ001	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CN604	3711-002643	CONNECTOR-HEADER:BOX,4P,1R,2.5MM,STRAIGH		DZ002	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CN802	3711-002644	CONNECTOR-HEADER:BOX,5P,1R,2.5mm,STRAIGH		DZ003	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CNZ02	3711-002646	CONNECTOR-HEADER:BOX,7P,1R,2.5mm,STRAIGH		DZ004	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CNZ03	AA39-20029K	LEAD CONNECTOR,ASSY;- ,67096-007,S,7P,400		DZ005	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
CNZ05	3711-002645	CONNECTOR-HEADER:BOX,6P,1R,2.5MM,STRAIGH		DZ006	0402-000132	DIODE-RECTIFIER;1N4004,400V,1A,DO-41,TP	
CNZ03	AA39-20027A	LEAD-CONNECTOR,ASSY;- ,67096-006,S,6P,300		DZ007	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ001	2301-000310	C-FILM,PEF:68nF,5%,50V,TP,8.0x8.5x4.0X		DZ008	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ002	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m		DZ009	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ004	2201-000265	C-CERAMIC,DISC:180pF,5%,50V,RH,TP,8x3,5		DZ010	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ005	2301-000108	C-FILM,PEF:1.5nF,5%,50V,TP,6.5x3.0x5.5mm		DZ011	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ006	2301-000175	C-FILM,PEF:15nF,5%,50V,TP,7.1x3.5x13mm,5		DZ012	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ007	2301-000104	C-FILM,PEF:1.2nF,5%,50V,TP,6.5x3.0x5.5mm		DZ013	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ008	2201-000145	C-CERAMIC,DISC:100pF,5%,50V,RH,TP,8.0*3.		DZ014	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ009	2201-000145	C-CERAMIC,DISC:100pF,5%,50V,RH,TP,8.0*3.		DZ015	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ011	2301-000227	C-FILM,PEF:27nF,5%,50V,TP,7x3.5x6.5mm,5m		DZ016	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ012	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		DZ017	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ013	2201-000982	C-CERAMIC,DISC:10nF,+80-20%,50V,Y5V,TP,6		DZ018	0401-000005	DIODE-SWITCHING;1N4148,75V,300mA,DO-35,T	
CZ014	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4		DZ020	0403-000655	DIODE-ZENER;MTZ13A,13V,12.11-12.75V,500m	
CZ015	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X		DZ024	0403-000655	DIODE-ZENER;MTZ13A,13V,12.11-12.75V,500m	
CZ016	2201-000411	C-CERAMIC,DISC:270pF,10%,50V,Y5P,TP,5x3,		HC651	AA13-20001WIC-HYBRID;- ,STK4142(2),SIP,18PAUDIO POW		
CZ017	2201-000325	C-CERAMIC,DISC:2.2nF,10%,500V,Y5P,TP,8x4		HCZ01	1203-000121	IC-NEGA.FIXED REG.;7906,TO-220,3P,-,PLAS	H/SINK
CZ018	2201-000325	C-CERAMIC,DISC:2.2nF,10%,500V,Y5P,TP,8x4		HCZ02	1203-000284	IC-POS.FIXED REG.;7806,TO-220,3P,-,PLAS	H/SINK
CZ019	2201-000472	C-CERAMIC,DISC:330pF,5%,50V,SL,TP,8x3.5,		HCZ03	AA13-20001V IC-HYBRID;- ,STK391-020,SIP,15P,OP AMP		
CZ020	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4		HCZ04	AA13-20001V IC-HYBRID;- ,STK391-020,SIP,15P,OP AMP		
CZ021	2201-000411	C-CERAMIC,DISC:270pF,10%,50V,Y5P,TP,5x3,		HCZ05	AA61-10183A BRACKET-TR;- ,S4388,STS,TO.5,-,-		
CZ022	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X		ICZ01	1201-000191	IC-OP AMP;4558,DIP,8P,300MIL,DUAL,20V/mV	
CZ023	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4		ICZ02	0801-000659	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,DIP,1	
CZ024	2201-000411	C-CERAMIC,DISC:270pF,10%,50V,Y5P,TP,5x3,		ICZ03	0801-000659	IC-CMOS LOGIC;74HC123,MULTIVIBATOR,DIP,1	
CZ025	2201-000325	C-CERAMIC,DISC:2.2nF,10%,500V,Y5P,TP,8x4		LZ001	AA27-10001Z COIL-CHOKE;- ,13UH,K,-,3A,-,14UH-K(3A),10		
CZ026	2201-000325	C-CERAMIC,DISC:2.2nF,10%,500V,Y5P,TP,8x4		LZ002	AA27-10001Z COIL-CHOKE;- ,13UH,K,-,3A,-,14UH-K(3A),10		
CZ027	2201-000472	C-CERAMIC,DISC:330pF,5%,50V,SL,TP,8x3.5,		LZ003	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
CZ028	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4		LZ004	3301-000287	CORE-FERRITE BEAD;AA,3.5x1x6mm,1500,2400	
CZ029	2201-000411	C-CERAMIC,DISC:270pF,10%,50V,Y5P,TP,5x3,		LZ005	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ030	2201-000138	C-CERAMIC,DISC:100pF,10%,50V,Y5P,TP,4.0X		LZ006	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ031	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4		LZ007	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ032	2201-000411	C-CERAMIC,DISC:270pF,10%,50V,Y5P,TP,5x3,		LZ008	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ033	2201-000325	C-CERAMIC,DISC:2.2nF,10%,500V,Y5P,TP,8x4		LZ009	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ034	2201-000325	C-CERAMIC,DISC:2.2nF,10%,500V,Y5P,TP,8x4		LZ010	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ035	2201-000472	C-CERAMIC,DISC:330pF,5%,50V,SL,TP,8x3.5,		LZ011	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ036	2201-000556	C-CERAMIC,DISC:470pF,10%,500V,Y5P,TP,7x4		LZ012	2701-000142	INDUCTOR-AXIAL;1uH,10%,2.5x3.4mm	
CZ037	2201-000411	C-CERAMIC,DISC:270pF,10%,50V,Y5P,TP,5x3,		PCB+HS	6003-000335	SCREW-TAPTITE;RH,+2S,M3,L8,ZPC(YEL),SWR	
CZ038	2306-000122	C-FILM,MPPF:100nF,5%,50V,TP,7.3x4.0x5.0m		Q651	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
CZ051	2401-000471	C-AL:10uF,20%,50V,BP,TP,5x11,5mm		Q652	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
CZ052	2401-001569	C-AL:47uF,20%,50V,BP,TP,10x12,5mm,5		Q653	0501-000369	TR-SMALL SIGNAL;KSC2331-Y,NPN,1W,TO-92L	
CZ053	2401-000934	C-AL:22uF,20%,25V,BP,TP,8x11,5,5		QZ001	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
CZ054	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		QZ002	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
CZ055	2401-000302	C-AL:100uF,20%,25V,GP,TP,6.3x11,5		QZ003	0501-000283	TR-SMALL SIGNAL;KSA539,PNP,400mW,TO-92,T	
				QZ004	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	
				QZ005	0502-000441	TR-POWER;2SC4635RB,NPN,2W,TO-220,ST,10-	H/SINK
				QZ006	0501-000389	TR-SMALL SIGNAL;KSC815,NPN,400mW,TO-92,T	



Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
CT07	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		CN111	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
CT08	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		CN164	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
CT09	2201-000193	C-CERAMIC,DISC:10pF,0.3pF,50V,CH,TP,5x3,		CN165	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
CT10	2201-000247	C-CERAMIC,DISC:15pF,5%,50V,CH,TP,5x3,5		CN166	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
CT11	2201-000292	C-CERAMIC,DISC:1nF,10%,50V,Y5P,TP,5x3,5		CN101	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG	
CT12	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		CN102	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG	
CT13	2201-000119	C-CERAMIC,DISC:100nF,+80-20%,50V,Y5V,TP,		D112	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
CT17	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,-,5mm		D113	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
CT18	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,-,5mm		D128	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
CT19	2305-000412	C-FILM,MPEF:470nF,5%,63V,TP,-,5mm		D161	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
CT20	2201-000144	C-CERAMIC,DISC:100pF,5%,50V,CH,TP,8x3,5		D164	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
ICT01	1204-000535	IC-PAL DECODER:SAAS5281P/E,DIP,48P,-,PLAS PIIC		D165	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
ICT01	1204-000536	IC-PAL DECODER:SAAS5281P/H,DIP,48P,-,PLASTIC SEH		D161	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
ICT02	1001-000223	IC-VIDEO SWITCH:TEA5114A,-,DIP,16P,334MI		D162	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
LT01	2701-000169	INDUCTOR-AXIAL:3.9uH,10%,2.5x3.4mm		DK161	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
RT01	2004-000971	R-METAL:470ohm,1%,1/8W,AA,TP,1.8x3.2mm		DK162	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
RT02	2004-000971	R-METAL:470ohm,1%,1/8W,AA,TP,1.8x3.2mm		DK163	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
RT03	2004-000971	R-METAL:470ohm,1%,1/8W,AA,TP,1.8x3.2mm		DK164	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
RT05	2001-000325	R-CARBON:120ohm,5%,1/8W,AA,TP,1.8x3.2mm		DN111	0401-000005	DIODE-SWITCHING:1N4148,75V,300mA,DO-35,T	
RT10	2001-000302	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		DN112	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
RT11	2001-000290	R-CARBON:10Kohm,5%,1/8W,AA,TP,1.8x3.2mm		DN113	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
RT13	2001-000812	R-CARBON:5.6Kohm,5%,1/8W,AA,TP,1.8x3.2m		DN161	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
RT14	2001-000591	R-CARBON:3.3Kohm,5%,1/8W,AA,TP,1.8x3.2m		DN162	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
RT15	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		DN163	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
RT16	2001-000563	R-CARBON:27Kohm,5%,1/8W,AA,TP,1.8x3.2mm		IC111	1204-000560	IC-DEMODULATOR:TDA9815,DIP,32P,400MIL,PL	
RT17	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		IC113	AA13-20003F	IC-HYBRID:-,PAP101,SIP,5PPREAMPK	
RT18	2001-000281	R-CARBON:100ohm,5%,1/8W,AA,TP,1.8x3.2mm		JL111	2007-000029	R-CHIP:0ohm,5%,1/10W,DA,TP,2012	
RT20	2004-000971	R-METAL:470ohm,1%,1/8W,AA,TP,1.8x3.2mm		JL121	3812-000219	WIRE-NO SHEATH CU-TICWA,300V,52mm(TAPING)	
RT21	2004-000971	R-METAL:470ohm,1%,1/8W,AA,TP,1.8x3.2mm		L111	2701-000326	INDUCTOR-AXIAL:560nH,10%,2.3x3.4mm	
RT22	2004-000971	R-METAL:470ohm,1%,1/8W,AA,TP,1.8x3.2mm		L112	AA26-10004E	TRANS-IF:-,7MG,VIF-,7mm,8pF,116.7MHz,S	
RT23	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		L113	2701-000299	INDUCTOR-AXIAL:13uH,10%,2.5x3.4mm	
RT24	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		LN113	2701-000136	INDUCTOR-AXIAL:18uH,10%,2.5x3.4mm	
RT25	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		Q112	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
RT26	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2m		Q113	0501-002049	TR-SMALL SIGNAL:BC858,PNP,330mW,SOT-23,T	
RT28	2004-000971	R-METAL:470ohm,1%,1/8W,AA,TP,1.8x3.2mm		Q161	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
RT29	2004-000971	R-METAL:470ohm,1%,1/8W,AA,TP,1.8x3.2mm		Q162	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
RT30	2004-000971	R-METAL:470ohm,1%,1/8W,AA,TP,1.8x3.2mm		QK161	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
RT32	2001-000958	R-CARBON:750ohm,5%,1/8W,AA,TP,1.8x3.2mm		QN111	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
RT33	2001-000958	R-CARBON:750ohm,5%,1/8W,AA,TP,1.8x3.2mm		QN112	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
RT34	2001-000958	R-CARBON:750ohm,5%,1/8W,AA,TP,1.8x3.2mm		QN113	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
RT36	2001-000515	R-CARBON:220ohm,5%,1/8W,AA,TP,1.8x3.2mm		QN114	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
SHIELD	AA63-40014A	SHIELD-CASE,T,-,SPT,E,TO.5, SCT51A,-,PIIC		QN161	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
SHIELD	AA63-40014A	SHIELD-CASE!T,-,SPT,E,TO.5, SCT51A,-,SEH		QN162	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
TT01	0501-000389	TR-SMALL SIGNAL:KSC815,NPN,400mW,TO.92,T		QN163	0501-000727	TR-SMALL SIGNAL:BC848C,NPN,310mW,SOT-23,	
XT01	2801-000214	CRYSTAL-UNIT:27MHz,40ppm,28-AAM,S,40ohm,		R113	2007-000774	R-CHIP:33Kohm,5%,1/10W,DA,TP,2012	
<b>ASSY-PCB,IF</b>				R114	2007-000774	R-CHIP:33Kohm,5%,1/10W,DA,TP,2012	
*	AA95-90003V	ASSY-PCB,IF:-,CS7277PF/MVXT,SCT51A,BG,DK		R115	2007-000300	R-CHIP:10Kohm,5%,1/10W,DA,TP,2012	
C112	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		R116	2001-000117	R-CARBON(S):68ohm,5%,1/2W,AA,TP,2.4x6.4m	
C113	2401-000947	C-AL:22uF,20%,35V,GP,TP,5x11,5		R117	2007-000029	R-CHIP:0ohm,5%,1/10W,DA,TP,2012	
C114	2401-000480	C-AL:10uF,20%,50V,GP,TP,5x11,5		R118	2007-000468	R-CHIP:1Kohm,5%,1/10W,DA,TP,2012	
C115	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R119	2007-001039	R-CHIP:56Kohm,5%,1/10W,DA,TP,2012	
C116	2203-000938	C-CERAMIC,CHIP:470pF,5%,50V,NPO,TP,2012,		R120	2007-000738	R-CHIP:30Kohm,5%,1/10W,DA,TP,2012	
C118	2203-002392	C-CERAMIC,CHIP:220nF,+80-20%,50V,Y5V,TP,		R121	2007-000328	R-CHIP:11Kohm,5%,1/10W,DA,TP,2012	
C122	2201-000692	C-CERAMIC,DISC:8pF,0.5pF,50V,UJ,TP,5x3,5		R122	2007-001039	R-CHIP:56Kohm,5%,1/10W,DA,TP,2012	
C123	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		R126	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012	
C124	2201-000692	C-CERAMIC,DISC:8pF,0.5pF,50V,UJ,TP,5x3,5		R127	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012	
C125	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5		R128	2007-000572	R-CHIP:220ohm,5%,1/10W,DA,TP,2012	
C126	2401-001082	C-AL:330nF,20%,50V,GP,TP,5x11,5		R129	2007-000030	R-CHIP:560ohm,5%,1/10W,DA,TP,2012	
C127	2401-000660	C-AL:2.2uF,20%,50V,GP,TP,5x11,5		R161	2007-000981	R-CHIP:5.6Kohm,5%,1/10W,DA,TP,2012	
C128	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		R162	2007-000981	R-CHIP:5.6Kohm,5%,1/10W,DA,TP,2012	
C161	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		R163	2007-000710	R-CHIP:3.9Kohm,5%,1/10W,DA,TP,2012	
C164	2401-000947	C-AL:22uF,20%,35V,GP,TP,5x11,5		R164	2007-000710	R-CHIP:3.9Kohm,5%,1/10W,DA,TP,2012	
C165	2401-000947	C-AL:22uF,20%,35V,GP,TP,5x11,5		R165	2007-000449	R-CHIP:180ohm,5%,1/10W,DA,TP,2012	
C166	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		R166	2007-000449	R-CHIP:180ohm,5%,1/10W,DA,TP,2012	
C167	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		R167	2007-000981	R-CHIP:5.6Kohm,5%,1/10W,DA,TP,2012	
C181	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		R168	2007-000030	R-CHIP:560ohm,5%,1/10W,DA,TP,2012	
C182	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R169	2007-000981	R-CHIP:5.6Kohm,5%,1/10W,DA,TP,2012	
C183	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		R170	2007-000030	R-CHIP:560ohm,5%,1/10W,DA,TP,2012	
C184	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R172	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012	
C185	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		R173	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012	
C186	2401-001840	C-AL:100uF,20%,16V,GP,TP,6.3x11,5		R174	2007-000300	R-CHIP:10Kohm,5%,1/10W,DA,TP,2012	
CL111	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		R175	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012	
CL112	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		R176	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012	
				R177	2007-000029	R-CHIP:0ohm,5%,1/10W,DA,TP,2012	
				R198	2007-000409	R-CHIP:15Kohm,5%,1/10W,DA,TP,2012	
				R199	2007-000409	R-CHIP:15Kohm,5%,1/10W,DA,TP,2012	
				R161	2007-000774	R-CHIP:33Kohm,5%,1/10W,DA,TP,2012	

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
RI163	2007-000981	R-CHIP:5.6Kohm,5%,1/10W,DA,TP,2012		CP139	2203-000239	C-CERAMIC,CHIP:100pf,5%,50V,NPO,TP,2012,	
RI166	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012		CP140	2203-000239	C-CERAMIC,CHIP:100pf,5%,50V,NPO,TP,2012,	
RI169	2007-000030	R-CHIP:560ohm,5%,1/10W,DA,TP,2012		CP141	2203-000239	C-CERAMIC,CHIP:100pf,5%,50V,NPO,TP,2012,	
RK161	2007-000030	R-CHIP:560ohm,5%,1/10W,DA,TP,2012		CP142	2401-000199	C-AL:1000uf,20%,6.3V,GP,TP,10x12.5,	
RK162	2007-000981	R-CHIP:5.6Kohm,5%,1/10W,DA,TP,2012		CP143	2401-002619	C-AL:47uf,20%,25V,GP,TP,5x11.5	
RK163	2007-000941	R-CHIP:47Kohm,5%,1/10W,DA,TP,2012		CP144	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216	
RK164	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012		CP145	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216	
RK165	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012		CP201	2203-000325	C-CERAMIC,CHIP:12nf,10%,50V,X7R,TP,3216,	
RK166	2007-000030	R-CHIP:560ohm,5%,1/10W,DA,TP,2012		CP203	2401-002144	C-AL:47uf,20%,16V,GP,TP,5x11.5	
RL112	2001-000734	R-CARBON:4.7Kohm,5%,1/8W,AA,TP,1.8x3.2mm		CP204	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216	
RN111	2007-000941	R-CHIP:47Kohm,5%,1/10W,DA,TP,2012		CP205	2401-001271	C-AL:4.7UF,20%,50V,GP,TP,4X7,5MM	
RN112	2007-000981	R-CHIP:5.6Kohm,5%,1/10W,DA,TP,2012		CP206	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216	
RN113	2007-000941	R-CHIP:47Kohm,5%,1/10W,DA,TP,2012		CP207	2401-000480	C-AL:10uf,20%,50V,GP,TP,5x11.5	
RN114	2007-000941	R-CHIP:47Kohm,5%,1/10W,DA,TP,2012		CP208	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216	
RN117	2001-000786	R-CARBON:47Kohm,5%,1/8W,AA,TP,1.8x3.2mm		CP209	2401-001914	C-AL:1uf,20%,50V,BP,TP,5x11.5	
RN118	2007-000282	R-CHIP:100Kohm,5%,1/10W,DA,TP,2012		CP210	2401-000603	C-AL:1uf,20%,50V,GP,TP,5x11.5	
RN119	2007-000282	R-CHIP:100Kohm,5%,1/10W,DA,TP,2012		CP211	2401-000603	C-AL:1uf,20%,50V,GP,TP,5x11.5	
RN161	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012		CP213	2401-000603	C-AL:1uf,20%,50V,GP,TP,5x11.5	
RN162	2007-000030	R-CHIP:560ohm,5%,1/10W,DA,TP,2012		CP214	2203-000578	C-CERAMIC,CHIP:220nf,20%,50V,Y5V,TP,3216	
RN163	2007-000941	R-CHIP:47Kohm,5%,1/10W,DA,TP,2012		CP215	2401-000603	C-AL:1uf,20%,50V,GP,TP,5x11.5	
RN164	2007-001071	R-CHIP:6.8Kohm,5%,1/10W,DA,TP,2012		CP216	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216	
RN165	2007-000941	R-CHIP:47Kohm,5%,1/10W,DA,TP,2012		CP217	2203-000578	C-CERAMIC,CHIP:220nf,20%,50V,Y5V,TP,3216	
RN166	2007-001071	R-CHIP:6.8Kohm,5%,1/10W,DA,TP,2012		CP218	2203-002085	C-CERAMIC,CHIP:56nf,10%,50V,X7R,TP,2012,	
RN167	2007-000941	R-CHIP:47Kohm,5%,1/10W,DA,TP,2012		CP219	2203-000495	C-CERAMIC,CHIP:2.2nf,10%,50V,X7R,TP,2012	
VR111	2103-000665	VR-SEMI:20Kohm,25%,1/5W,SIDE		CP220	2203-000578	C-CERAMIC,CHIP:220nf,20%,50V,Y5V,TP,3216	
Z111	2904-000253	FILTER-SAW AV:33.9MHZ,DIP10P,ST,17.1DB,P		CP221	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216	
Z112	2903-001019	FILTER-CERAMIC:TR,5.5/5.742MHZ,-,-,-,TP,		CP301	2401-001840	C-AL:100uf,20%,16V,GP,TP,6.3x11.5	
Z161	2904-000300	FILTER-SAW AV:38.90MHZ,SIP5K,ST,13.2dB,P		CP302	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216	
Z162	2904-000303	FILTER-SAW AV:38.90MHZ,-,ST,14.6dB,SECAM		CP303	2401-002144	C-AL:47uf,20%,16V,GP,TP,5x11.5	
Z163	2903-000185	FILTER-CERAMIC:BP,5.5MHZ,+75KHz,6dB,-,T		CP304	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216	
Z167	2903-000189	FILTER-CERAMIC:BP,5.74MHZ,+50KHz,8dB,-,		CP305	2203-000389	C-CERAMIC,CHIP:15pf,5%,50V,NPO,TP,2012,-	
Z168	2903-000189	FILTER-CERAMIC:BP,5.74MHZ,+50KHz,8dB,-,		CP306	2203-000389	C-CERAMIC,CHIP:15pf,5%,50V,NPO,TP,2012,-	
Z161	2903-000277	FILTER-CERAMIC:BP,6.0MHZ,60KHz,6.0dB,-,T		CP308	2203-001245	C-CERAMIC,CHIP:82pf,5%,50V,NPO,TP,2012,-	
ZK163	2903-000202	FILTER-CERAMIC:BP,6.5MHZ,+80KHz,6dB,-,T		DP101	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
ZN111	2903-001022	FILTER-CERAMIC:TR,4.5MHZ,-,0.5dB,-,TP,-		DP103	0403-000563	DIODE-ZENER:MTZ9.1B,9.1V,8.57-9.01V,500m	
ZN161	2903-000135	FILTER-CERAMIC:BP,4.5MHZ,+60KHz,6dB,-,T		DP105	0401-000160	DIODE-SWITCHING:ISS314,30V,100mA,USC,TP	
ZN162	2903-000135	FILTER-CERAMIC:BP,4.5MHZ,+60KHz,6dB,-,T		DP201	0403-000662	DIODE-ZENER:MTZ3.0B,3.0V,3.01-3.22V,500m	
<b>ASSY-PCB,PIP</b>							
*	AA95-90003	WASSY-PCB,PIP,-,CS7277PF/MVTX,SC751A,BG,D		ICP101	1204-000530	IC-PAL/NTSC DECODER:TDA9160A,DIP,32P,400	
CNP01	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG		ICP102	1204-000560	IC-DEMODULATOR:TDA9815,DIP,32P,400MIL,PL	
CNP03	3711-002709	CONNECTOR-HEADER:NOWALL,12P,1R,2.5MM,ANG		ICP103	AA13-20003F	IC-HYBRID:-,PAP101,SIP,5PPREAMPBK	
CP101	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216		ICP105	1204-000635	IC-PICTURE PROCESS:SDA9189X,SOP,32P,350M	
CP102	2401-000922	C-AL:22uf,20%,16V,GP,TP,5x5.5		ICP201	1002-000206	IC-A/D CONVERTER:SDA9187-2X,6BIT,SOP,28P	
CP103	2203-000429	C-CERAMIC,CHIP:18pf,5%,50V,NPO,TP,2012,-		LP101	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP104	2203-000192	C-CERAMIC,CHIP:100nf,+80-20%,50V,Y5V,TP,		LP102	2701-000219	INDUCTOR-AXIAL:820nH,10%,2.5x3.4mm	
CP105	2203-000717	C-CERAMIC,CHIP:3.3nf,10%,50V,X7R,TP,3216		LP103	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP106	2203-000612	C-CERAMIC,CHIP:22nf,10%,50V,X7R,TP,3216,		LP104	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP107	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216		LP105	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP108	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216		LP201	2701-000197	INDUCTOR-AXIAL:5.6uH,10%,2.5x3.4mm	
CP110	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216		LP202	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP111	2203-000716	C-CERAMIC,CHIP:3.3nf,10%,50V,X7R,TP,2012		LP301	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP112	2401-000660	C-AL:2.2uf,20%,50V,GP,TP,5x11.5		LP302	2701-000114	INDUCTOR-AXIAL:10uH,10%,2.5x3.4mm	
CP113	2203-000891	C-CERAMIC,CHIP:4.7nf,10%,50V,X7R,TP,2012		QP101	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP114	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216		QP102	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP115	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216		QP103	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
CP116	2203-000753	C-CERAMIC,CHIP:330nf,+80-20%,50V,Y5V,TP,		QP104	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP117	2401-002619	C-AL:47uf,20%,25V,GP,TP,5x11.5		QP105	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP118	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216		QP106	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP120	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216		QP201	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP121	2401-000660	C-AL:2.2uf,20%,50V,GP,TP,5x11.5		QP202	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP123	2203-000260	C-CERAMIC,CHIP:10nf,10%,50V,X7R,TP,2012,		QP203	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
CP124	2401-000660	C-AL:2.2uf,20%,50V,GP,TP,5x11.5		QP204	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP125	2203-000260	C-CERAMIC,CHIP:10nf,10%,50V,X7R,TP,2012,		QP205	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP126	2401-001840	C-AL:100uf,20%,16V,GP,TP,6.3x11.5		QP206	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP127	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216		QP302	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP129	2203-000260	C-CERAMIC,CHIP:10nf,10%,50V,X7R,TP,2012,		QP303	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
CP130	2203-000239	C-CERAMIC,CHIP:100pf,5%,50V,NPO,TP,2012,		QP304	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
CP132	2203-000239	C-CERAMIC,CHIP:100pf,5%,50V,NPO,TP,2012,		QP305	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
CP133	2203-000221	C-CERAMIC,CHIP:100nf,20%,50V,Y5V,TP,3216		RC129	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012	
CP134	2401-001026	C-AL:3.3uf,20%,50V,GP,TP,5x11mm,5mm		RP101	2007-001208	R-CHIP:82Kohm,5%,1/10W,DA,TP,2012	
CP135	2401-002144	C-AL:47uf,20%,16V,GP,TP,5x11.5		RP103	2007-000290	R-CHIP:100ohm,5%,1/10W,DA,TP,2012	
CP136	2203-000260	C-CERAMIC,CHIP:10nf,10%,50V,X7R,TP,2012,		RP104	2007-000468	R-CHIP:1Kohm,5%,1/10W,DA,TP,2012	
CP137	2203-000938	C-CERAMIC,CHIP:470pf,5%,50V,NPO,TP,2012,		RP105	2007-000328	R-CHIP:11Kohm,5%,1/10W,DA,TP,2012	
				RP106	2007-000774	R-CHIP:33Kohm,5%,1/10W,DA,TP,2012	
				RP107	2007-000409	R-CHIP:15Kohm,5%,1/10W,DA,TP,2012	
				RP108	2007-000493	R-CHIP:2.2Kohm,5%,1/10W,DA,TP,2012	
				RP109	2007-000830	R-CHIP:39Kohm,5%,1/10W,DA,TP,2012	
				RP110	2007-000300	R-CHIP:10Kohm,5%,1/10W,DA,TP,2012	



Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
RP111	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012		C105	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,	
RP112	2007-000931	R-CHIP;470ohm,5%,1/10W,DA,TP,2012		C108	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
RP113	2007-000774	R-CHIP:33Kohm,5%,1/10W,DA,TP,2012		C109	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,	
RP114	2007-000290	R-CHIP:100ohm,5%,1/10W,DA,TP,2012		C110	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP	
RP115	2007-000290	R-CHIP:100ohm,5%,1/10W,DA,TP,2012		C111	2203-000274	C-CERAMIC,CHIP:10pF,0.25pF,50V,NPO,TP,2012,-	
RP116	2007-000493	R-CHIP;2.2Kohm,5%,1/10W,DA,TP,2012		C112	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
RP117	2007-000241	R-CHIP:1.5Kohm,5%,1/10W,DA,TP,2012		C113	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
RP118	2001-000117	R-CARBON(S);68ohm,5%,1/2W,AA,TP,2.4x6.4mm		C114	2203-001002	C-CERAMIC,CHIP:47pF,5%,50V,NPO,TP,2012,-	
RP119	2007-000282	R-CHIP:100Kohm,5%,1/10W,DA,TP,2012		C115	2203-001002	C-CERAMIC,CHIP:47pF,5%,50V,NPO,TP,2012,-	
RP120	2007-000241	R-CHIP:1.5Kohm,5%,1/10W,DA,TP,2012		C116	2203-000374	C-CERAMIC,CHIP:15nF,10%,50V,X7R,TP,2012,	
RP121	2007-000258	R-CHIP:1.6Kohm,5%,1/10W,DA,TP,2012		C117	2404-000275	C-TA,CHIP:100uF,10%,10V,-,TP,7343,7.3mm	
RP122	2007-000300	R-CHIP:10Kohm,5%,1/10W,DA,TP,2012		C118	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
RP123	2007-000941	R-CHIP:47Kohm,5%,1/10W,DA,TP,2012		C119	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
RP124	2007-000941	R-CHIP:47Kohm,5%,1/10W,DA,TP,2012		C121	2203-000495	C-CERAMIC,CHIP:2.2nF,10%,50V,X7R,TP,2012	
RP125	2007-000401	R-CHIP:150ohm,5%,1/10W,DA,TP,2012		C122	2203-000609	C-CERAMIC,CHIP:22nF,10%,50V,X7R,TP,2012,	
RP126	2103-000665	VR-SEMI:20Kohm,25%,1/5W,SIDE		C124	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
RP127	2007-000822	R-CHIP:390ohm,5%,1/10W,DA,TP,2012		C125	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
RP128	2007-000941	R-CHIP:47Kohm,5%,1/10W,DA,TP,2012		C126	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
RP130	2007-000872	R-CHIP:4.7Kohm,5%,1/10W,DA,TP,2012		C127	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
RP131	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012		C128	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
RP132	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012		C129	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
RP133	2007-000872	R-CHIP:4.7Kohm,5%,1/10W,DA,TP,2012		C130	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
RP134	2007-000872	R-CHIP:4.7Kohm,5%,1/10W,DA,TP,2012		C131	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP	
RP135	2007-000468	R-CHIP:1Kohm,5%,1/10W,DA,TP,2012		C132	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
RP136	2007-000872	R-CHIP:4.7Kohm,5%,1/10W,DA,TP,2012		C133	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
RP137	2007-001039	R-CHIP:56Kohm,5%,1/10W,DA,TP,2012		C134	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP	
RP138	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012		C135	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP	
RP139	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012		C136	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
RP140	2007-000029	R-CHIP:0ohm,5%,1/10W,DA,TP,2012		C137	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
RP201	2007-001039	R-CHIP:56Kohm,5%,1/10W,DA,TP,2012		C138	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP	
RP202	2007-000401	R-CHIP:150ohm,5%,1/10W,DA,TP,2012		C139	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP	
RP203	2007-000703	R-CHIP:3.6Kohm,5%,1/10W,DA,TP,2012		C140	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
RP204	2007-000593	R-CHIP:22ohm,5%,1/10W,DA,TP,2012		C141	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,	
RP205	2007-000477	R-CHIP:1Mohm,5%,1/10W,DA,TP,2012		C142	2404-000160	C-TA,CHIP:1uF,20%,50V,-,6032,6mm,TP	
RP206	2007-000931	R-CHIP:470ohm,5%,1/10W,DA,TP,2012		C143	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm	
RP207	2007-001009	R-CHIP:51Kohm,5%,1/10W,DA,TP,2012		C144	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
RP208	2007-000774	R-CHIP:33Kohm,5%,1/10W,DA,TP,2012		C145	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,	
RP209	2007-000401	R-CHIP:150ohm,5%,1/10W,DA,TP,2012		C146	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,	
RP210	2007-000221	R-CHIP:1.2Kohm,5%,1/10W,DA,TP,2012		C147	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
RP211	2007-001001	R-CHIP:510ohm,5%,1/10W,DA,TP,2012		C148	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,	
RP212	2007-000931	R-CHIP:470ohm,5%,1/10W,DA,TP,2012		C149	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,	
RP213	2007-000872	R-CHIP:4.7Kohm,5%,1/10W,DA,TP,2012		C150	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
RP215	2007-000872	R-CHIP:4.7Kohm,5%,1/10W,DA,TP,2012		C151	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,	
RP216	2007-000872	R-CHIP:4.7Kohm,5%,1/10W,DA,TP,2012		C152	2203-000408	C-CERAMIC,CHIP:180pF,5%,50V,NPO,TP,2012,	
RP217	2007-000409	R-CHIP:15Kohm,5%,1/10W,DA,TP,2012		C153	2404-000275	C-TA,CHIP:100uF,10%,10V,-,TP,7343,7.3mm	
RP2301	2007-000290	R-CHIP:100ohm,5%,1/10W,DA,TP,2012		C154	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm	
RP303	2007-000468	R-CHIP:1Kohm,5%,1/10W,DA,TP,2012		C155	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
RP304	2007-000290	R-CHIP:100ohm,5%,1/10W,DA,TP,2012		C156	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
RP307	2007-000642	R-CHIP:270ohm,5%,1/10W,DA,TP,2012		C157	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
RP308	2007-000401	R-CHIP:150ohm,5%,1/10W,DA,TP,2012		C158	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
RP309	2007-000931	R-CHIP:470ohm,5%,1/10W,DA,TP,2012		C159	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
RP310	2007-000931	R-CHIP:470ohm,5%,1/10W,DA,TP,2012		C160	2203-000126	C-CERAMIC,CHIP:1.2nF,10%,50V,X7R,TP,2012	
RP311	2007-000931	R-CHIP:470ohm,5%,1/10W,DA,TP,2012		C161	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
RP312	2007-000300	R-CHIP:10Kohm,5%,1/10W,DA,TP,2012		C162	2203-001077	C-CERAMIC,CHIP:56pF,5%,50V,NPO,TP,2012,-	
RP313	2007-000710	R-CHIP:3.9Kohm,5%,1/10W,DA,TP,2012		C163	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
RP314	2007-000710	R-CHIP:3.9Kohm,5%,1/10W,DA,TP,2012		C164	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
RP315	2007-000710	R-CHIP:3.9Kohm,5%,1/10W,DA,TP,2012		C165	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
TP101	AA26-10004E	TRANS-IF,-,7MG,VIF,-,7mm,8pF,116.7MHz,S		C166	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
XP101	2801-000235	CRYSTAL-UNIT:3.579545MHz,40ppm,28-AAM,S		C167	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
XP102	2801-000276	CRYSTAL-UNIT:4.433619MHz,40ppm,28-AAM,20		C168	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
XP301	2802-000121	RESONATOR-CERAMIC:20.48MHZ,0.5%,TP,10.OX		C169	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,	
ZP102	2904-000253	FILTER-SAW AV:33.9MHZ,DIP10P,ST,17.1DB,P		C170	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
				C171	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
				C172	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
				C173	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
				C174	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
				C175	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
				C176	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
				C177	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
				C178	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
				C179	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
				C180	2203-001214	C-CERAMIC,CHIP:8.2nF,10%,50V,X7R,TP,2012	
				C181	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-	
				C182	2203-001077	C-CERAMIC,CHIP:56pF,5%,50V,NPO,TP,2012,-	
				C183	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
C103	2203-000239	C-CERAMIC,CHIP:100pF,5%,50V,NPO,TP,2012,		C184	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	
C104	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		C185	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm	

**ASSY-POWER,CORD**

\* AA96-20074A ASSY-POWER,CORD:-,CP2/NO(4.8),H/C250,VM0  
P-CORD AA39-10007B POWER-CORD:-,VM-0377,2X42/0.15,2.4MT,3P  
HOLDER AA61-20045A HOLDER-CORD:-,PP,V0,BLK,UL/CSA

**ASSY-PCB,CONV MDL**

\* AA95-90037A ASSY-PCB,CONV MDL:-,SPM5288PF,SPT51A,PAL

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
C186	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm		IC136	1001-000105	IC-ANALOG SWITCH:CD4066BM,BILATERAL CMOS	
C187	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		IC141	1103-000139	IC-EEPROM:24C16,2KX8BIT,DIP8P,300MIL,10	
C188	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm		IC143	AA13-10001X	IC-ASIC,-,DCS04,0FP,160P,CONV CONTROLL	
C189	2404-000125	C-TA,CHIP:10uF,20%,16V,-,TP,5054,1.5mm		IC144	1203-000641	IC-RESET:7442,TO-92,3P,-,PLASTIC,-,0.3/7	
C190	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		L100	AA26-10001Y	TRANS-IF,-,5CA,IF,10uH,5mm,-,2.52MHz,ST	
C191	2305-000289	C-FILM,MPEF:220nF,5%,63V,TP,-,5mm		L102	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm	
C193	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm		L103	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm	
C194	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		L104	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm	
C195	2404-000275	C-TA,CHIP:100uF,10%,10V,-,TP,7343,7.3mm		L105	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm	
C196	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-		L106	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm	
C197	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-		L107	2703-000248	INDUCTOR-SMD:820uH,5%,3.2x4.5x3.2mm	
C198	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-		L108	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm	
C201	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		L109	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm	
C202	2203-000683	C-CERAMIC,CHIP:27pF,5%,50V,NPO,TP,2012,-		L110	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm	
C203	2203-000429	C-CERAMIC,CHIP:18pF,5%,50V,NPO,TP,2012,-		L111	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm	
C204	2203-000683	C-CERAMIC,CHIP:27pF,5%,50V,NPO,TP,2012,-		L112	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm	
C205	2203-001002	C-CERAMIC,CHIP:47pF,5%,50V,NPO,TP,2012,-		L113	2703-000155	INDUCTOR-SMD:1mH,5%,3.2x4.5x3.2mm	
C207	2203-001680	C-CERAMIC,CHIP:68nF,20%,50V,Y5V,TP,2012,		L121	2901-000297	FILTER-EMI ON BOARD:-,3A,-,3.5x5,TP-	
C208	2203-000444	C-CERAMIC,CHIP:1nF,10%,50V,X7R,TP,2012,-		Q100	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
C209	2203-000260	C-CERAMIC,CHIP:10nF,10%,50V,X7R,TP,2012,		Q101	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
C210	2404-000123	C-TA,CHIP:10uF,20%,16V,-,TP,6032,2.9mm		Q102	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
C220	2203-001002	C-CERAMIC,CHIP:47pF,5%,50V,NPO,TP,2012,-		Q103	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
C301	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-		Q104	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
C302	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-		Q105	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
C303	2203-000634	C-CERAMIC,CHIP:22pF,5%,50V,NPO,TP,2012,-		Q106	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
C304	2203-000192	C-CERAMIC,CHIP:100nF,+80-20%,50V,Y5V,TP,		Q107	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CNZ01	3711-001164	CONNECTOR-HEADER:BOX,9P,1R,2.5mm,ANGLE,-		Q108	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CNZ02	3711-001094	CONNECTOR-HEADER:BOX,7P,1R,2.5mm,ANGLE,-		Q109	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CNZ03	3711-001049	CONNECTOR-HEADER:BOX,6P,1R,2.5mm,ANGLE,-		Q110	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP101	2901-000233	FILTER-EMI SMD:50V,300mA,-,330pF,4.5x1.8		Q111	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP102	2901-000233	FILTER-EMI SMD:50V,300mA,-,330pF,4.5x1.8		Q112	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP103	2901-000229	FILTER-EMI SMD:50V,300mA,-,22nF,4.5x1.8x		Q113	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP104	2901-000229	FILTER-EMI SMD:50V,300mA,-,22nF,4.5x1.8x		Q114	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP105	2901-000229	FILTER-EMI SMD:50V,300mA,-,22nF,4.5x1.8x		Q115	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP106	2901-000229	FILTER-EMI SMD:50V,300mA,-,22nF,4.5x1.8x		Q116	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP107	2901-000229	FILTER-EMI SMD:50V,300mA,-,22nF,4.5x1.8x		Q117	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP108	2901-000232	FILTER-EMI SMD:50V,300mA,-,10nF,4.5x1.8x		Q118	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP109	2901-000232	FILTER-EMI SMD:50V,300mA,-,10nF,4.5x1.8x		Q119	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP110	2901-000232	FILTER-EMI SMD:50V,300mA,-,10nF,4.5x1.8x		Q120	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP120	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2		Q121	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP121	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2		Q122	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP122	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2		Q123	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP123	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2		Q124	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP124	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2		Q125	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP125	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2		Q126	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP126	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2		Q127	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
CP127	2901-000226	FILTER-EMI SMD:25V,200mA,-,100pF,3.2x1.2		Q128	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D100	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q129	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D101	0405-000128	DIODE-VARACTOR:1SV214,30V,10nA,USC,TP		Q130	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D104	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m		Q131	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D105	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q132	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D106	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q133	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D110	0401-000008	DIODE-SWITCHING:DAN217,80V,100mA,SOT-23,		Q134	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D111	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q135	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D112	0401-000008	DIODE-SWITCHING:DAN217,80V,100mA,SOT-23,		Q136	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D113	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q137	0501-000342	TR-SMALL SIGNAL:KSC1623-Y,NPN,200mW,SOT-	
D114	0401-000008	DIODE-SWITCHING:DAN217,80V,100mA,SOT-23,		Q138	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D115	0401-000003	DIODE-SWITCHING:1SS193,80V,100mA,SOT-23,		Q139	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D118	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m		Q140	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D119	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m		Q141	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D200	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m		Q142	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D201	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m		Q143	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D202	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m		Q144	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D203	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m		Q145	0501-000280	TR-SMALL SIGNAL:KSA1182,PNP,150mW,SOT-23	
D204	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m		Q200	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-	
D205	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m		Q201	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-	
D206	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m		Q202	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-	
D207	0403-000689	DIODE-ZENER:DTZ5.1A,5.1V,4.84-5.04V,200m		Q203	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-	
IC104	1001-000105	IC-ANALOG SWITCH:CD4066BM,BILATERAL CMOS		Q204	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-	
IC106	1201-000167	IC-OP AMP:358,SOP,8P,150MIL,DUAL,100V/mV		Q205	0505-000257	FET-SILICON:2SK217,N,-,20mA,-,150mW,SOT-	
IC112	AA13-30006B	IC-MCU:-,AT89C52-24,-,DIP,-,40P,600MI		R100	2007-000282	R-CHIP:100Kohm,5%,1/10W,DA,TP,2012	
IC113	1002-000131	IC-A/D&D/A CONVERTER:PCM55HP,16BIT,SOP,2		R101	2007-000282	R-CHIP:100Kohm,5%,1/10W,DA,TP,2012	
IC114	1002-000131	IC-A/D&D/A CONVERTER:PCM55HP,16BIT,SOP,2		R102	2007-000468	R-CHIP:1Kohm,5%,1/10W,DA,TP,2012	
IC115	1002-000131	IC-A/D&D/A CONVERTER:PCM55HP,16BIT,SOP,2		R103	2007-000468	R-CHIP:1Kohm,5%,1/10W,DA,TP,2012	
IC132	0801-001156	IC-CMOS LOGIC:74HC4066,BILATERAL SWITCH,		R104	2007-000468	R-CHIP:1Kohm,5%,1/10W,DA,TP,2012	
IC133	0801-001156	IC-CMOS LOGIC:74HC4066,BILATERAL SWITCH,		R105	2007-000586	R-CHIP:22Kohm,5%,1/10W,DA,TP,2012	
IC135	1001-000105	IC-ANALOG SWITCH:CD4066BM,BILATERAL CMOS		R106	2007-000468	R-CHIP:1Kohm,5%,1/10W,DA,TP,2012	

Electric Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
R107	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R217	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012	
R108	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R218	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012	
R109	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012		R219	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012	
R110	2007-000409	R-CHIP;15Kohm,5%,1/10W,DA,TP,2012		R220	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012	
R111	2007-000572	R-CHIP;220ohm,5%,1/10W,DA,TP,2012		R221	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012	
R112	2007-000409	R-CHIP;15Kohm,5%,1/10W,DA,TP,2012		R222	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012	
R113	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R223	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012	
R114	2007-000586	R-CHIP;22Kohm,5%,1/10W,DA,TP,2012		R224	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012	
R115	2007-000830	R-CHIP;39Kohm,5%,1/10W,DA,TP,2012		R225	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012	
R116	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R226	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012	
R118	2007-000830	R-CHIP;39Kohm,5%,1/10W,DA,TP,2012		R227	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012	
R119	2007-000586	R-CHIP;22Kohm,5%,1/10W,DA,TP,2012		R228	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012	
R120	2007-000415	R-CHIP;15Kohm,5%,1/10W,DA,TP,2012		R229	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012	
R121	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012		R230	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012	
R122	2007-000586	R-CHIP;22Kohm,5%,1/10W,DA,TP,2012		R231	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012	
R123	2007-000282	R-CHIP;100Kohm,5%,1/10W,DA,TP,2012		R232	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012	
R124	2103-000677	VR-SEMI;5Kohm,25%,1/5W,TOP		R233	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012	
R125	2007-000586	R-CHIP;22Kohm,5%,1/10W,DA,TP,2012		R234	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012	
R130	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012		R235	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012	
R131	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012		R236	2007-000586	R-CHIP;22Kohm,5%,1/10W,DA,TP,2012	
R132	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012		R237	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012	
R133	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012		R238	2007-001039	R-CHIP;56Kohm,5%,1/10W,DA,TP,2012	
R134	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012		R239	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012	
R135	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012		R240	2007-000355	R-CHIP;12Kohm,5%,1/10W,DA,TP,2012	
R136	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012		R241	2007-001039	R-CHIP;56Kohm,5%,1/10W,DA,TP,2012	
R137	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012		R242	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012	
R138	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R243	2007-000355	R-CHIP;12Kohm,5%,1/10W,DA,TP,2012	
R139	2007-001097	R-CHIP;62Kohm,5%,1/10W,DA,TP,2012		R244	2007-001039	R-CHIP;56Kohm,5%,1/10W,DA,TP,2012	
R140	2007-000304	R-CHIP;10Mohm,5%,1/10W,DA,TP,2012		R245	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012	
R141	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R246	2007-000355	R-CHIP;12Kohm,5%,1/10W,DA,TP,2012	
R142	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012		R247	2007-001039	R-CHIP;56Kohm,5%,1/10W,DA,TP,2012	
R159	2007-000221	R-CHIP;1.2Kohm,5%,1/10W,DA,TP,2012		R248	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012	
R160	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012		R249	2007-000355	R-CHIP;12Kohm,5%,1/10W,DA,TP,2012	
R162	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012		R250	2007-001039	R-CHIP;56Kohm,5%,1/10W,DA,TP,2012	
R163	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012		R251	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012	
R164	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012		R252	2007-000355	R-CHIP;12Kohm,5%,1/10W,DA,TP,2012	
R165	2007-000380	R-CHIP;13Kohm,5%,1/10W,DA,TP,2012		R253	2007-001039	R-CHIP;56Kohm,5%,1/10W,DA,TP,2012	
R167	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R254	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012	
R168	2007-000653	R-CHIP;27Kohm,5%,1/10W,DA,TP,2012		R255	2007-000355	R-CHIP;12Kohm,5%,1/10W,DA,TP,2012	
R169	2007-000029	R-CHIP;0ohm,5%,1/10W,DA,TP,2012		R256	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012	
R171	2007-000029	R-CHIP;0ohm,5%,1/10W,DA,TP,2012		R257	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012	
R181	2007-000221	R-CHIP;1.2Kohm,5%,1/10W,DA,TP,2012		R258	2007-000586	R-CHIP;22Kohm,5%,1/10W,DA,TP,2012	
R182	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R259	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012	
R183	2007-000686	R-CHIP;3.3Kohm,5%,1/10W,DA,TP,2012		R260	2007-000518	R-CHIP;2.7Kohm,5%,1/10W,DA,TP,2012	
R184	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R261	2007-001118	R-CHIP;680ohm,5%,1/10W,DA,TP,2012	
R185	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R262	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012	
R186	2007-000221	R-CHIP;1.2Kohm,5%,1/10W,DA,TP,2012		R263	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012	
R187	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R264	2007-000518	R-CHIP;2.7Kohm,5%,1/10W,DA,TP,2012	
R188	2007-000686	R-CHIP;3.3Kohm,5%,1/10W,DA,TP,2012		R265	2007-001118	R-CHIP;680ohm,5%,1/10W,DA,TP,2012	
R189	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R266	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012	
R190	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R267	2007-000518	R-CHIP;2.7Kohm,5%,1/10W,DA,TP,2012	
R191	2007-000221	R-CHIP;1.2Kohm,5%,1/10W,DA,TP,2012		R268	2007-001118	R-CHIP;680ohm,5%,1/10W,DA,TP,2012	
R192	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R269	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012	
R193	2007-000686	R-CHIP;3.3Kohm,5%,1/10W,DA,TP,2012		R270	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012	
R194	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R271	2007-000518	R-CHIP;2.7Kohm,5%,1/10W,DA,TP,2012	
R195	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R272	2007-001118	R-CHIP;680ohm,5%,1/10W,DA,TP,2012	
R196	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012		R273	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012	
R197	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012		R274	2007-000518	R-CHIP;2.7Kohm,5%,1/10W,DA,TP,2012	
R198	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R275	2007-001118	R-CHIP;680ohm,5%,1/10W,DA,TP,2012	
R199	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012		R276	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012	
R200	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R277	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012	
R201	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012		R278	2007-000518	R-CHIP;2.7Kohm,5%,1/10W,DA,TP,2012	
R202	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R279	2007-001118	R-CHIP;680ohm,5%,1/10W,DA,TP,2012	
R203	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012		R280	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012	
R204	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R281	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012	
R205	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012		R282	2007-000282	R-CHIP;100Kohm,5%,1/10W,DA,TP,2012	
R206	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R283	2007-000355	R-CHIP;12Kohm,5%,1/10W,DA,TP,2012	
R207	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012		R284	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012	
R208	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012		R285	2007-000355	R-CHIP;12Kohm,5%,1/10W,DA,TP,2012	
R209	2003-002026	R-METAL OXIDE(S);4.7ohm,5%,1W,AF,TP,2.5x		R286	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012	
R210	2003-002026	R-METAL OXIDE(S);4.7ohm,5%,1W,AF,TP,2.5x		R287	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012	
R211	2003-002026	R-METAL OXIDE(S);4.7ohm,5%,1W,AF,TP,2.5x		R288	2007-000355	R-CHIP;12Kohm,5%,1/10W,DA,TP,2012	
R212	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012		R289	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012	
R213	2007-000290	R-CHIP;100ohm,5%,1/10W,DA,TP,2012		R290	2007-000355	R-CHIP;12Kohm,5%,1/10W,DA,TP,2012	
R214	2007-000981	R-CHIP;5.6Kohm,5%,1/10W,DA,TP,2012		R291	2007-000468	R-CHIP;1Kohm,5%,1/10W,DA,TP,2012	
R215	2007-000872	R-CHIP;4.7Kohm,5%,1/10W,DA,TP,2012		R292	2007-000300	R-CHIP;10Kohm,5%,1/10W,DA,TP,2012	
R216	2007-000030	R-CHIP;560ohm,5%,1/10W,DA,TP,2012		R293	2007-000355	R-CHIP;12Kohm,5%,1/10W,DA,TP,2012	



Electric Parts List

Loc. No.	Code No.	Description ; Specification	Remark	Loc. No.	Code No.	Description ; Specification	Remark
HOLDER	AA61-20102A	HOLDER-CONTROL;-,-,ABS,HB,BLK,-					
HOLDER	AA61-20114A	HOLDER-KEY;-,-,ABS,HB,BLK,-					
LATCH	AA61-30001A	LATCH-DOOR;-,-,KIFUCO LA701,-					
SPRING	AA61-60048A	SPRING-CS;-,-,SUS304,0.8,OD9.6,H6,N5,-,-,-					
DAMPER	AA61-80005B	DAMPER-GEAR;-,-,20G,-,OIL,-					
SPACER	AA63-60002V	SPACER-FELT;FELT,TO.3,BLK,60X40,-,-					
SPACER	AA63-60002W	SPACER-FELT;FELT,TO.5,BLK,30X10,-,-					
KNOCON	AA64-10214C	KNOB-CONTROL ASSY;-,-,SPM5288PF,-,ABS,HB,B					
DOOR-B	AA64-50082D	DOOR-BOTTOM;-,-,SPM4388,WP1000,ABS,HB,BLK,					
I-DOOR	AA64-60112B	INLAY-DOOR;SPM5288PF,-,PS,TO.5,BLK,-,-					
I-MIC	AA64-60244A	INLAY-MIC;-,-,PS,TO.3,BLK,-,-					
I-CON	AA64-60264B	INLAY-CONTROL,BOT;SPM5288PF,-,PS,TO.3,BL					
PCB	AA41-10421B	PCB-SIGNAL;SPT51A,1,FR-1,330x245x1.6T,-,-					
PCB	AA41-10581D	PCB-POWER;SPT51A,1L,CEM-1,330x245x1.6T,-					
PCB	AA41-10431C	PCB-CRT(R);SPT51A,1,FR-1,330x245x1.6T,-,-					
PCB	AA41-10434A	PCB-CONTROL;SPT51A,1,FR-1,245X245X1.6T					
PCB	AA41-10436A	PCB-PREAMP;SPT51A,1,FR-1,245X245X1.6T					
PCB	AA41-10437B	PCB-A/V BACK;SPT51A,2L,FR-4,330x245x1.6T					
PWB	AA41-10371B	PCB-AUDIO;SCT51A,2L,FR-4,100x76x1.6T,-,-					
PCB	AA41-10424D	PCB-DEFLECTION;SPT51A,1,CEM-1,330x245x1.					
PCB	AA41-10479E	PCB-CONVERGENCE;SPT51A,1,CEM-1,330x245x1					
PCB	AA41-10438A	PCB-MASTER S/W;SPT51A,1,CEM-1,245X245X1.					
PWB	AA41-10330B	PCB-TTX;SCT51A,1L,FR-1,81x65x1.6T,-,-					
PWB	AA41-10323A	PCB-IF;SCT51A,2,FR-4,100X76X1.6T					
PWB	AA41-10321C	PCB-PIP;SCT51A,2L,FR-4,100x76x1.6T,-,-					
O3LOT	AA41-10480D	PCB-MODULE;APT51A,2L,FR-4,191x123x1.6T,-					