

4. Electrical Parts List

Loc.No	Part No	Description ; Specification	Remark	Loc.No	Part No	Description ; Specification	Remark
-	-	ASSY PCB-MAIN	S.N.A.	R1SD16	2006-000273	R-CEMENT:27Kohm,5%,2W,CA,BK,6.4x27x6.4mm	SVR-2301 ONLY
S.M.P.S. PARTS				R1SD31	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
BD1SD1	AC27-92001M	INDUCTOR:70UH-M RT BFS3565R2F,-,-,-,-		R1SD31	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-2301 ONLY
BD1SF1	3301-000297	CORE-FERRITE BEAD:AA,3.6x1.2x5.7mm,1400,	SVR-2301 NOT USER	R1SD32	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
BD1SF3	AC27-92001M	INDUCTOR:70UH-M RT BFS3565R2F,-,-,-,-	SVR-2301 NOT USER	R1SD32	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-2301 ONLY
BD1SR1	3301-000297	CORE-FERRITE BEAD:AA,3.6x1.2x5.7mm,1400,	SVR-2301 ONLY	R1SF11	2001-000076	R-CARBON:47KOHM,5%,1/4W,AA,TP,2.4X6.4MM	SVR-2301 NOT USER
BD1SS3	AC27-92001M	INDUCTOR:70UH-M RT BFS3565R2F,-,-,-,-		R1SF15	2001-000591	R-CARBON:3.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-2301 NOT USER
C1SD03	2201-000828	C-CERAMIC,DISC:3.3nF,20%,400V,Y5U,TP,15x		R1SF19	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-2301 NOT USER
C1SD04	2201-000828	C-CERAMIC,DISC:3.3nF,20%,400V,Y5U,TP,15x		R1SF20	2003-000105	R-METAL OXIDE:0.33ohm,5%,2W,AD,TP,6x16mm	SVR-2301 NOT USER
C1SD11	2401-003303	C-AL:82uF,20%,400V,GP,BK,22X30,10		R1SF21	2001-000096	R-CARBON(S):1MOHM,5%,1/2W,AA,TP,2.4X6.4MM	SVR-2301 NOT USER
C1SD11	2401-003302	C-AL:47uF,20%,400V,GP,TP,18X31.5,7.	SVR-2301 ONLY	R1SR11	2003-000119	R-METAL OXIDE:0.68ohm,5%,2W,AE,TP,6x16mm	SVR-2301 ONLY
C1SD12	2305-001029	C-FILM,MPEF:10nF,10%,630V,TP,12x9x12.5,5		R1SR12	2003-000264	R-METAL OXIDE:300ohm,5%,1W,AD,TP,4.3x12mm	SVR-2301 ONLY
C1SD12	2201-000828	C-CERAMIC,DISC:3.3nF,20%,400V,Y5U,TP,15x	SVR-2301 ONLY	R1SR14	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8X3.2mm	SVR-2301 ONLY
C1SD13	2301-000361	C-FILM,PEF:1.2nF,10%,50V,TP,-,5mm	SVR-2301 ONLY	R1SS10	2006-000262	R-CEMENT:2.7ohm,10%,2W,CB,TP,7.5x11x20.	
C1SD13	2201-000376	C-CERAMIC,DISC:0.22nF,5%,50V,SL,TP,6.3x3		R1SS11	2003-000994	R-METAL OXIDE(S):33Kohm,5%,2W,AF,TP,3.9x	SVR-2301 NOT USER
C1SF12	2401-001200	C-AL:33uF,20%,50V,WT,TP,6.3x11,5	SVR-2301 NOT USER	R1SS13	2003-000148	R-METAL OXIDE:100OHM,5%,2W,AE,TP,6X16MM	
C1SR12	2401-000905	C-AL:22uF,20%,16V,BP,-,6x11,2.5mm	SVR-2301 ONLY	R1SS32	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C1SR14	2301-000445	C-FILM,PEF:4.7nF,5%,50V,TP,5.5x7x3mm,5mm	SVR-2301 ONLY	R1SS33	2004-000869	R-METAL:3Kohm,1%,1/8W,AA,TP,1.8x3.2mm	
C1SS01	2305-001021	C-FILM,MPEF:100nF,20%,275V,TP,17.5x7x13.	△	R1SS34	2004-000459	R-METAL:2.2Kohm,1%,1/8W,AA,TP,1.8x3.2m	
C1SS02	2305-001021	C-FILM,MPEF:100nF,20%,275V,TP,17.5x7x13.	△	VA1SS1	1405-001026	VARISTOR:470V,600A,9x7mm,TP	△
C1SS12	2201-000129	C-CERAMIC,DISC:0.1nF,10%,1KV,Y5P,TP,7x4,		ZD1SS1	0403-000571	DIODE-ZENER:UZP43B.43V,40-46V,1W,DO-41,T	SVR-2301 ONLY
C1SS31	2401-000385	C-AL:10uF,20%,100V,GP,TP,6.3x11,5		POWER DRIVE PARTS			
C1SS33	2401-001126	C-AL:330uF,20%,25V,WT,TP,10x12.5,5,5		C1P102	2401-001507	C-AL:47uF,20%,16V,GP,TP,6.3x5,5	
C1SS34	2401-003477	C-AL:330uF,20%,25V,LZ,TP,10X12.5MM,		C1P103	2401-001915	C-AL:1uF,20%,50V,GP,TP,3x5,5	
C1SS35	2401-003480	C-AL:1000uF,20%,10V,LZ,TP,10X16MM,5		C1P104	2401-002299	C-AL:4.7uF,20%,50V,GP,TP,5x7,5	
C1SS36	2401-003480	C-AL:1000uF,20%,10V,LZ,TP,10X16MM,5		C1P105	2401-001507	C-AL:47uF,20%,16V,GP,TP,6.3x5,5	
C1SS39	2301-000129	C-FILM,PEF:100nF,5%,50V,TP,10X9X4.3X5,5m		C1P106	2401-001915	C-AL:1uF,20%,50V,GP,TP,3x5,5	
CN1SS1	3711-000178	CONNECTOR-HEADER:1WALL,2P,1R,3.96mm,STRA		C1P107	2401-001507	C-AL:47uF,20%,16V,GP,TP,6.3x5,5	
D1SD11	0402-001195	DIODE-RECTIFIER:FT14,400V,1.0A,TS-1,TP		C1P108	2401-001507	C-AL:47uF,20%,16V,GP,TP,6.3x5,5	
D1SD31	0402-001195	DIODE-RECTIFIER:FT14,400V,1.0A,TS-1,TP		C1P115	2401-001915	C-AL:1uF,20%,50V,GP,TP,3x5,5	SVR-2301 ONLY
D1SF05	0402-001196	DIODE-RECTIFIER:1T5,600V,1A,TS-1,TP	SVR-2301 NOT USER	D1P101	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
D1SF12	0402-001195	DIODE-RECTIFIER:FT14,400V,1.0A,TS-1,TP	SVR-2301 NOT USER	D1P103	0402-000127	DIODE-RECTIFIER:1N4002,100V,1A,DO-41,TP	
D1SR11	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	SVR-2301 ONLY	D1P104	0402-000127	DIODE-RECTIFIER:1N4002,100V,1A,DO-41,TP	
D1SS01	0402-001196	DIODE-RECTIFIER:1T5,600V,1A,TS-1,TP		D1P106	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
D1SS02	0402-001196	DIODE-RECTIFIER:1T5,600V,1A,TS-1,TP		D1P108	0402-000127	DIODE-RECTIFIER:1N4002,100V,1A,DO-41,TP	
D1SS03	0402-001196	DIODE-RECTIFIER:1T5,600V,1A,TS-1,TP		D1P109	0402-000127	DIODE-RECTIFIER:1N4002,100V,1A,DO-41,TP	SVR-131 NOT USER
D1SS04	0402-001196	DIODE-RECTIFIER:1T5,600V,1A,TS-1,TP		D1P117	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
D1SS11	0402-000276	DIODE-RECTIFIER:UF4007,1KV,1A,DO-41,TP		D1P120	0402-000127	DIODE-RECTIFIER:1N4002,100V,1A,DO-41,TP	
D1SS32	0402-001194	DIODE-RECTIFIER:UG20,200V,2A,DO-204AC,TP		D1P121	0402-000127	DIODE-RECTIFIER:1N4002,100V,1A,DO-41,TP	
D1SS33	0402-000431	DIODE-RECTIFIER:FML-M02S,200V,2.5A,TO-22		Q1P101	0501-000616	TR-SMALL SIGNAL:KSC2328A-Y,NPN,1W,TO-92L	
F1SS01	3601-001208	FUSE-CARTRIDGE:250V,1.6A,TIME-LAG,GLASS	△	Q1P103	0501-000616	TR-SMALL SIGNAL:KSC2328A-Y,NPN,1W,TO-92L	
IC1SF1	1203-001802	IC-PWM CONTROLLER:STR-G6551,TO-220F,5P,-	SVR-2301 NOT USER	Q1P106	0504-000142	TR-DIGITAL:KSR2001,PNP,300MW,4.7Kx4.7K,T	
IC1SS1	0604-001028	PHOTO-COUPLER:TR.50-600% 250mW,DIP-4,ST	△	Q1P107	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	
IC1SS2	AC14-12006D	IC:KA431Z,TO-92,TAPING		Q1P108	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	
L1SS02	AC29-30050C	FILTER-LINE NOISE:-,25MH,0.35A,AC250V,BS	△	Q1P114	0501-000616	TR-SMALL SIGNAL:KSC2328A-Y,NPN,1W,TO-92L	
L1SS31	AC27-12001N	COIL-CHOKE:10UH-15%,RA,K-30,Q80,150KHZ,-		R1P101	2001-000855	R-CARBON:560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
L1SS32	AC27-12001N	COIL-CHOKE:10UH-15%,RA,K-30,Q80,150KHZ,-		R1P102	2001-000855	R-CARBON:560OHM,5%,1/4W,AA,TP,2.4X6.4MM	
PT1SD1	AC26-00001D	TRANS-SWITCHING:-,100V-240V,DEMCO,EE2821	△	R1P103	2001-000034	R-CARBON:220OHM,5%,1/4W,AA,TP,2.4X6.4MM	
PT1SD1	AC26-00001E	TRANS-SWITCHING:-,230V,DEMCO,EE2821,1.3M	△ SVR-2301 ONLY	R1P108	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2M	
Q1SR01	0502-001050	TR-POWER:2SC4517A,NPN,30W,TO-220,ST,10-	SVR-2301 ONLY	R1P115	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q1SR02	0501-000442	TR-SMALL SIGNAL:KTC3203-Y,NPN,400MW,TO-9	SVR-2301 ONLY	R1P116	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
R1SD11	2001-000305	R-CARBON:110KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-2301 ONLY	R1P117	2001-000554	R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD12	2001-000869	R-CARBON:56OHM,5%,1/8W,AA,TP,1.8X3.2MM		R1P118	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R1SD12	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm	SVR-2301 ONLY	ZD1P01	0403-001211	DIODE-ZENER:MTZJ12B,11.44-12.03V,500MW,D	
R1SD13	2001-000076	R-CARBON:47KOHM,5%,1/4W,AA,TP,2.4X6.4MM		ZD1P02	0403-000717	DIODE-ZENER:MTZJ5.1B,5.1V,4.9-5.2V,500m	
R1SD13	2001-000305	R-CARBON:110KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-2301 ONLY	ZD1P03	0403-000720	DIODE-ZENER:MTZJ9.1B,9.1V,8.57-9.01V,500	
R1SD14	2001-000076	R-CARBON:47KOHM,5%,1/4W,AA,TP,2.4X6.4MM					
R1SD14	2001-000305	R-CARBON:110KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-2301 ONLY				
R1SD15	2001-000076	R-CARBON:47KOHM,5%,1/4W,AA,TP,2.4X6.4MM					
R1SD15	2001-000305	R-CARBON:110KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-2301 ONLY				
R1SD16	2003-000994	R-METAL OXIDE(S):33Kohm,5%,2W,AF,TP,3.9x					

Electrical Parts List

Loc.No	Part No	Description ; Specification	Remark	Loc.No	Part No	Description ; Specification	Remark
SYSTEM CONTROL/SERVO PARTS				R641	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C601	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R642	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C602	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R644	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C603	2401-001545	C-AL:47uf,20%,25V,GP,TP,6.3x7mm,2.5		R650	2003-000259	R-METAL OXIDE:3.90HM,5%,2W,AE,TP,6X16MM	
C604	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		R651	2001-000010	R-CARBON:68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C605	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		R654	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C607	2401-000118	C-AL:1000uf,20%,10V,GP,TP,10x12.5,5	SVR-131 NOT USER	R655	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C609	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R656	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C610	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		R657	2001-000010	R-CARBON:68KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-131 NOT USER
C611	2301-000392	C-FILM,PEF:15nF,5%,50V,TP,6.5x8.5x3.2mm,		R660	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C614	2401-001507	C-AL:47uf,20%,16V,GP,TP,6.3x5,5		R661	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C615	2401-001507	C-AL:47uf,20%,16V,GP,TP,6.3x5,5		R666	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C618	2401-001545	C-AL:47uf,20%,25V,GP,TP,6.3x7mm,2.5		R667	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C619	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		R668	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C620	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		R669	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C621	2401-001545	C-AL:47uf,20%,25V,GP,TP,6.3x7mm,2.5		R670	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C622	2301-001006	C-FILM,PEF:68nF,5%,50V,TP,8x4x8.5mm,5mm		R671	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C623	2202-000807	C-CERAMIC,MLC-AXIAL:22nF,+80-20%,25V,Y5V		R672	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C624	2202-000205	C-CERAMIC,MLC-AXIAL:22pF,5%,50V,SL,TP,1.	SVR-131 NOT USER	R674	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C625	2202-000205	C-CERAMIC,MLC-AXIAL:22pF,5%,50V,SL,TP,1.	SVR-131 NOT USER	R675	2001-000032	R-CARBON:180OHM,5%,1/4W,AA,TP,2.4X6.4MM	
C626	2202-000205	C-CERAMIC,MLC-AXIAL:22pF,5%,50V,SL,TP,1.		R676	2001-000633	R-CARBON:30KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C627	2202-000205	C-CERAMIC,MLC-AXIAL:22pF,5%,50V,SL,TP,1.		R677	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C633	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		R678	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C634	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		R679	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C635	2202-000183	C-CERAMIC,MLC-AXIAL:2.2NF,20%,16V,Y5R,TP		R682	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C636	2202-000183	C-CERAMIC,MLC-AXIAL:2.2NF,20%,16V,Y5R,TP		R685	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C637	2202-000263	C-CERAMIC,MLC-AXIAL:470pF,10%,50V,Y5P,TP		R686	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C638	2401-000922	C-AL:22uf,20%,16V,GP,TP,5x5,5		R687	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C639	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP		R688	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C640	2401-001507	C-AL:47uf,20%,16V,GP,TP,6.3x5,5		R690	2001-000864	R-CARBON:56KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C641	2401-002165	C-AL:100uf,20%,16V,GP,TP,6.3x7,5		R691	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C644	2202-000806	C-CERAMIC,MLC-AXIAL:220pF,10%,50V,Y5P,TP		R692	2001-000568	R-CARBON:270HM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-131 NOT USER
C646	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R693	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C679	2202-000807	C-CERAMIC,MLC-AXIAL:22nF,+80-20%,25V,Y5V		R696	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C689	2202-000791	C-CERAMIC,MLC-AXIAL:150pF,10%,50V,Y5P,TP		RS601	AC34-20100B	SWITCH-REC:-,X-9,-	
C690	2301-001006	C-FILM,PEF:68nF,5%,50V,TP,8x4x8.5mm,5mm		S601	0603-001011	PHOTO-TR:NPN,35V,6V,50mA,75mW,BK	
C691	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		S602	0603-001011	PHOTO-TR:NPN,35V,6V,50mA,75mW,BK	
C693	2401-000118	C-AL:1000uf,20%,10V,GP,TP,10x12.5,5		SW601	AC34-20100A	SWITCH-MODE:-,X-9,-	
CN601	AC39-20817S	LEAD CONNECTOR-ASSY:DP,SMH200-02,YBH200-		W117	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CN602	3708-001163	CONNECTOR-FPC/FPC/PIC:5P,1.25mm,STRAIGHT,		W128	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
CN604	3711-003749	CONNECTOR-HEADER-BOX,8P,2R,2mm,STRAIGHT,		W173	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
D601	0402-000127	DIODE-RECTIFIER:1N4002,100V,1A,DO-41,TP		W174	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
D603	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		W250	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
D604	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		W300	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
D606	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		XT601	2801-003318	CRYSTAL-UNIT:32.768KHz,20ppm,28-AAP,12.5	SVR-131 NOT USER
D610	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		XT602	2801-003139	CRYSTAL-UNIT:8MHz,50ppm,28-AAA,22pF,80oh	
D612	0402-000127	DIODE-RECTIFIER:1N4002,100V,1A,DO-41,TP		AUDIO/VIDEO PARTS			
IC601	AC09-00089A	IC-MICOM:uPD784927GF-159-3BA,784927GF-1		C301	2401-001919	C-AL:2.2uf,20%,50V,-,TP,4x7mm,5	
IC601	AC09-00102A	IC-MICOM:uPD784927GF-153-3BA,784927GF-1	SVR-131 ONLY	C302	2301-000283	C-FILM,PEF:47nF,5%,100V,TP,7.3X7X3.2X5,5	
IC602	1003-001162	IC-MOTOR DRIVER:KA3082,SIP,10PIN,25MIL,D		C303	2401-001915	C-AL:1uf,20%,50V,GP,TP,3x5,5	
IC604	AC14-12006C	IC:KA7533,DIP,-		C304	2202-000216	C-CERAMIC,MLC-AXIAL:027NF,5%,50V,SL,TP,	
IC605	1103-001148	IC-EEPROM:24C021,2KBIT,DIP,8P,300MIL,10M		C305	2202-000164	C-CERAMIC,MLC-AXIAL:18NF,10%,50V,Y5P,TP	
IC608	1203-000515	IC-VOL. DETECTOR:7042,TO-92,3P,177MIL,PL	SVR-131 NOT USER	C306	2202-000231	C-CERAMIC,MLC-AXIAL:330pF,10%,50V,Y5P,TP	
L601	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm		C307	2202-000162	C-CERAMIC,MLC-AXIAL:015NF,5%,50V,SL,TP,	
L602	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm		C308	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,	
L603	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm		C309	2401-001915	C-AL:1uf,20%,50V,GP,TP,3x5,5	
L604	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm		C310	2401-000407	C-AL:10uf,20%,16V,GP,TP,3.5x5,2.5	
LD601	0601-000517	LED-IR-RECTANGULA,4x6.0mm,75mW,6V,950		C311	2401-000922	C-AL:22uf,20%,16V,GP,TP,5x5,5	
PT601	0604-001122	PHOTO-INTERRUPTER:TR,0.065%,150mW,DIP-4,		C313	2202-000173	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,1	
PT602	0604-001122	PHOTO-INTERRUPTER:TR,0.065%,150mW,DIP-4,		C314	2401-001775	C-AL:470nF,20%,50V,GP,TP,4x7,5	
O602	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T		C315	2401-000407	C-AL:10uf,20%,16V,GP,TP,3.5x5,2.5	
R608	2001-000864	R-CARBON:56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C316	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V	
R609	2001-000864	R-CARBON:56KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C318	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V	
R613	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-131 NOT USER	C320	2401-001915	C-AL:1uf,20%,50V,GP,TP,3x5,5	
R614	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C321	2401-000407	C-AL:10uf,20%,16V,GP,TP,3.5x5,2.5	

Loc.No	Part No	Description ; Specification	Remark	Loc.No	Part No	Description ; Specification	Remark
C322	2401-001915	C-AL:1uF,20%,50V,GP,TP,3x5,5		L303	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm	
C323	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		L304	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm	
C324	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		L306	2701-000119	INDUCTOR-AXIAL:120uH,5%,2.4x3.4mm	
C325	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		L307	2701-000122	INDUCTOR-AXIAL:12uH,5%,2.4x3.4mm	
C326	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		L3A01	2702-000120	INDUCTOR-RADIAL:15mH,5%,6.2x7.4mm	
C327	2401-001507	C-AL:47uF,20%,16V,GP,TP,6.3x5,5		L3A02	2702-000106	INDUCTOR-RADIAL:100uH,10%,6.2x7.4mm	
C328	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		L3A03	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm	
C329	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		L3A04	2702-000106	INDUCTOR-RADIAL:100uH,10%,6.2x7.4mm	
C330	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		Q302	0501-000303	TR-SMALL SIGNAL:KSA733,PNP,250mW,TO-92,T	
C331	2401-001507	C-AL:47uF,20%,16V,GP,TP,6.3x5,5		Q303	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	
C332	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		Q304	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	
C333	2401-001915	C-AL:1uF,20%,50V,GP,TP,3x5,5		Q308	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	
C334	2202-002055	C-CERAMIC,MLC-AXIAL:47nF,+80-20%,50V,Y5V		Q309	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	
C335	2401-001915	C-AL:1uF,20%,50V,GP,TP,3x5,5		Q3A01	0501-000303	TR-SMALL SIGNAL:KSA733,PNP,250mW,TO-92,T	
C336	2401-001915	C-AL:1uF,20%,50V,GP,TP,3x5,5		Q3A03	0501-000442	TR-SMALL SIGNAL:KTC3203-Y,NPN,400mW,TO-9	
C337	2202-000807	C-CERAMIC,MLC-AXIAL:22nF,+80-20%,25V,Y5V		Q3A04	0501-000442	TR-SMALL SIGNAL:KTC3203-Y,NPN,400mW,TO-9	
C338	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		Q3A05	0501-000442	TR-SMALL SIGNAL:KTC3203-Y,NPN,400mW,TO-9	
C339	2202-002055	C-CERAMIC,MLC-AXIAL:47nF,+80-20%,50V,Y5V		Q3A06	0501-000303	TR-SMALL SIGNAL:KSA733,PNP,250mW,TO-92,T	
C340	2202-000807	C-CERAMIC,MLC-AXIAL:22nF,+80-20%,25V,Y5V		R301	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C341	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		R302	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C342	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R303	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C343	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		R304	2001-000977	R-CARBON:8.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C345	2201-002031	C-CERAMIC,DISC:0.005nF,0.5pF,50V,NPO,TP,		R306	2001-000232	R-CARBON:1.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C346	2401-001507	C-AL:47uF,20%,16V,GP,TP,6.3x5,5		R308	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C347	2202-000286	C-CERAMIC,MLC-AXIAL:56pF,5%,50V,SL,TP,1.		R309	2001-000723	R-CARBON:4.3KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C348	2202-000286	C-CERAMIC,MLC-AXIAL:56pF,5%,50V,SL,TP,1.		R311	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C349	2202-000849	C-CERAMIC,MLC-AXIAL:18pF,5%,50V,CH,TP,3.		R312	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C350	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		R313	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C380	2202-000243	C-CERAMIC,MLC-AXIAL:33pF,5%,50V,SL,TP,1.		R314	2001-000924	R-CARBON:680OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C381	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		R315	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C390	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R316	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C391	2202-000121	C-CERAMIC,MLC-AXIAL:100pF,10%,50V,Y5P,TP		R317	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
C393	2202-000787	C-CERAMIC,MLC-AXIAL:10PF,5%,50V,Y5P,TP,3		R318	2001-000003	R-CARBON:330ohm,5%,1/8W,AA,TP,1.8x3.2mm	
C395	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R320	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C398	2202-000205	C-CERAMIC,MLC-AXIAL:22pF,5%,50V,SL,TP,1.		R321	2001-000009	R-CARBON:20KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A01	2401-002299	C-AL:4.7uF,20%,50V,GP,TP,5x7,5		R322	2001-000539	R-CARBON:24KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A02	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R325	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A04	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R326	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A07	2301-000392	C-FILM,PEF:15nF,5%,50V,TP,6.5x8.5x3.2mm,		R327	2001-000832	R-CARBON:510OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A08	2301-001014	C-FILM,PEF:6.8nF,5%,50V,TP,7x3x6,5mm		R328	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C3A09	2301-001014	C-FILM,PEF:6.8nF,5%,50V,TP,7x3x6,5mm		R329	2001-000472	R-CARBON:2.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	4H'D ONLY
C3A10	2301-000314	C-FILM,PEF:8.2nF,5%,50V,TP,6.5x3.0x5.5mm		R330	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C3A11	2301-000253	C-FILM,PEF:39nF,5%,100V,TP,7.5X4.5X12.5MM		R331	2001-000515	R-CARBON:220OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A12	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		R332	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A13	2301-000161	C-FILM,PEF:12nF,5%,50V,TP,6.5X5.5X3.0X5,		R333	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A14	2301-001014	C-FILM,PEF:6.8nF,5%,50V,TP,7x3x6,5mm		R334	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A15	2301-000381	C-FILM,PEF:10nF,5%,50V,TP,6.5x5.5x3mm,5m		R335	2001-000800	R-CARBON:5.1KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C3A16	2401-002299	C-AL:4.7uF,20%,50V,GP,TP,5x7,5		R336	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A17	2401-000922	C-AL:22uF,20%,16V,GP,TP,5x5,5		R337	2001-001000	R-CARBON:82KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A18	2301-000402	C-FILM,PEF:1nF,5%,50V,TP,5x7x2.8mm,5mm		R342	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C3A21	2301-000008	C-FILM,PEF:2.2nF,5%,50V,TP,5.5X7X3.5mm		R346	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C3A22	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R3A01	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A23	2401-001169	C-AL:33uF,20%,16V,GP,6.3x7,2.5mm		R3A04	2001-000241	R-CARBON:1.5KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C3A24	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R3A05	2001-000660	R-CARBON:33KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A25	2401-000922	C-AL:22uF,20%,16V,GP,TP,5x5,5		R3A06	2001-000325	R-CARBON:120OHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A29	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R3A07	2001-000645	R-CARBON:330KOHM,5%,1/8W,AA,TP,1.8X3.2M	
C3A30	2401-002144	C-AL:47uF,20%,16V,GP,TP,5x11,5		R3A08	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C3A31	2202-002037	C-CERAMIC,MLC-AXIAL:100nF,80-20%,50V,Y5V		R3A09	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2M	
CN301	3708-000395	CONNECTOR-FPC/FC/PIC:8P,1.25MM,STRAIGHT,		R3A10	2001-000429	R-CARBON:1KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
CN3A01	3708-001302	CONNECTOR-FPC/FC/PIC:7P,1.25mm,STRAIGHT,		R3A11	2001-000258	R-CARBON:1.8KOHM,5%,1/8W,AA,TP,1.8X3.2M	
CN3A02	3711-002445	CONNECTOR-HEADER:BOX,2P,2R,1.5MM,STRAIGH		R3A12	2001-000458	R-CARBON:2.20HM,5%,1/8W,AA,TP,1.8X3.2MM	
D302	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,		R3A13	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
FL3A01	AC27-80100A	COIL-OSC:126QN-K5272YHC-K,-,AM		R3A14	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
IC301	1204-001649	IC-VIDEO PROCESS:LA71598M,QFP,100P,-,PLA		R3A15	2001-000411	R-CARBON:18KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L301	2701-000206	INDUCTOR-AXIAL:56uH,5%,2.4x3.4mm		R3A16	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
L302	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm		R3A17	2001-000613	R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2M	

Electrical Parts List

Loc.No	Part No	Description ; Specification	Remark	Loc.No	Part No	Description ; Specification	Remark
R3A18	2001-000613	R-CARBON:3.9KOHM,5%,1/8W,AA,TP,1.8X3.2MM		INPUT-OUTPUT PARTS			
R3A19	2001-000405	R-CARBON:180OHM,5%,1/8W,AA,TP,1.8X3.2MM		C801	2401-002144	C-AL:47uf,20%,16V,GP,TP,5x11.5	
R3A21	2001-000904	R-CARBON:620OHM,5%,1/8W,AA,TP,1.8X3.2MM		C802	2401-001479	C-AL:470uf,20%,10V,GP,TP,-	
R3A22	2001-000006	R-CARBON:2.4KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C806	2202-000830	C-CERAMIC,MLC-AXIAL:82pf,10%,50V,Y5P,TP,	
R3A23	2001-000812	R-CARBON:5.6KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C809	2401-002299	C-AL:4.7uf,20%,50V,GP,TP,5x7.5	
R3A24	2001-000522	R-CARBON:22KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C810	2401-001074	C-AL:330nf,20%,50V,GP,TP,4x5.2.5mm	
R3A25	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C812	2202-000121	C-CERAMIC,MLC-AXIAL:100pf,10%,50V,Y5P,TP	
R3A26	2001-000331	R-CARBON:12KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C813	2202-000173	C-CERAMIC,MLC-AXIAL:1nf,10%,50V,Y5P,TP,1	
R3A27	2001-000947	R-CARBON:7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM		C814	2202-000121	C-CERAMIC,MLC-AXIAL:100pf,10%,50V,Y5P,TP	
R3A28	2001-000890	R-CARBON:6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM		JC801	AC37-20001H	JACK-RCA:DPAM,-4P,MONO,PI3.3	
R3A29	2001-000890	R-CARBON:6.8KOHM,5%,1/8W,AA,TP,1.8X3.2MM		L801	2701-000181	INDUCTOR-AXIAL:33uH,5%,2.4x3.4mm	
R3A30	2001-000454	R-CARBON:2.2MOHM,5%,1/8W,AA,TP,1.8X3.2MM		L802	2701-000181	INDUCTOR-AXIAL:33uH,5%,2.4x3.4mm	
R3A31	2001-000766	R-CARBON:43KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R801	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A32	2001-000766	R-CARBON:43KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R802	2001-000995	R-CARBON:820OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A33	2001-000766	R-CARBON:43KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R803	2001-000221	R-CARBON:1.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R3A37	2001-000947	R-CARBON:7.5KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R806	2001-000969	R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM	
XT301	2801-001397	CRYSTAL-UNIT:4.433619MHZ,HC-49/U-S 15PPM		R808	2001-000969	R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R324	2001-000554	R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 NOT USER	R809	2001-000969	R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM	
Q307	0504-000119	TR-DIGITAL:KSR1004,NPN,300MW,47K/47K,TO-	SVR-433 NOT USER	R810	2001-000554	R-CARBON:270OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R329	2001-000734	R-CARBON:4.7KOHM,5%,1/8W,AA,TP,1.8X3.2MM	2H D ONLY	FUNCTION MATRIX PARTS			
TM-BLOCK				CN703	3708-001163	CONNECTOR-FPC/FC/PIC:5P,1.25mm,STRAIGHT,	
C401	2401-002144	C-AL:47uf,20%,16V,GP,TP,5x11.5		CN708	3711-004013	CONNECTOR-HEADER:3WALL,10P,1R,2mm,STRAIG	
C402	2202-000807	C-CERAMIC,MLC-AXIAL:22nf,+80-20%,25V,Y5V		D701	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
C403	2401-002144	C-AL:47uf,20%,16V,GP,TP,5x11.5		D702	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
C404	2202-000807	C-CERAMIC,MLC-AXIAL:22nf,+80-20%,25V,Y5V		D703	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
C405	2401-001573	C-AL:47uf,20%,50V,GP,TP,6.3x11.2.5		D704	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
C406	2202-000807	C-CERAMIC,MLC-AXIAL:22nf,+80-20%,25V,Y5V		D705	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
C407	2401-001085	C-AL:330nf,20%,50V,GP,5x9,2mm		D706	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
D401	0402-000127	DIODE-RECTIFIER:1N4002,100V,1A,DO-41,TP		D708	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
L401	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm		D709	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
L402	2701-000002	INDUCTOR-AXIAL:100uH,10%,4.2x9.8mm		D720	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,	
R401	2001-000786	R-CARBON:47KOHM,5%,1/8W,AA,TP,1.8X3.2MM		Q701	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	
R402	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		Q702	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	
R403	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		Q703	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	
R404	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		Q704	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	
TM401	AC40-00001G	TM-BLOCK:TCMK0600PD11A,G/I/K(MONO),TCMK		Q705	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	
TM401	AC40-20100L	RF-MODULATOR:RMUP74055VC,VCP PAL	SVR-131 ONLY	Q708	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T	SVR-433 ONLY
ZD401	0403-000390	DIODE-ZENER:UZP33B,33V,31.4-34.6V,1W,DO-		Q711	0501-000290	TR-SMALL SIGNAL:KSA643-Y,PNP,500mW,TO-92	SVR-433 ONLY
O.S.D. PARTS				Q712	0501-000290	TR-SMALL SIGNAL:KSA643-Y,PNP,500mW,TO-92	SVR-433 ONLY
C6P01	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,		Q713	0501-000290	TR-SMALL SIGNAL:KSA643-Y,PNP,500mW,TO-92	SVR-433 ONLY
C6P02	2401-002144	C-AL:47uf,20%,16V,GP,TP,5x11.5		Q714	0501-000290	TR-SMALL SIGNAL:KSA643-Y,PNP,500mW,TO-92	SVR-433 ONLY
C6P03	2202-002037	C-CERAMIC,MLC-AXIAL:100nf,80-20%,50V,Y5V		Q715	0501-000290	TR-SMALL SIGNAL:KSA643-Y,PNP,500mW,TO-92	SVR-433 ONLY
C6P04	2202-000243	C-CERAMIC,MLC-AXIAL:33pf,5%,50V,SL,TP,3.		R701	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C6P05	2202-000216	C-CERAMIC,MLC-AXIAL:027NF,5%,50V,SL,TP,		R702	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C6P08	2202-000286	C-CERAMIC,MLC-AXIAL:56pf,5%,50V,SL,TP,1.		R703	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C6P09	2202-000145	C-CERAMIC,MLC-AXIAL:12NF,10%,50V,Y5P,TP		R704	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C6P10	2401-001915	C-AL:1uf,20%,50V,GP,TP,3x5.5		R705	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C6P11	2401-001915	C-AL:1uf,20%,50V,GP,TP,3x5.5		R706	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C6P12	2401-002144	C-AL:47uf,20%,16V,GP,TP,5x11.5		R707	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
C6P13	2202-002037	C-CERAMIC,MLC-AXIAL:100nf,80-20%,50V,Y5V		R708	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY
IC6P01	AC09-00078A	IC-OSD:LC74759JM-9785,LC74759JM-9785,		R711	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY
IC6P01	AC09-10458R	IC-MCU:LC74783JM-9745,24P,MFP,OSD IC,-	SVR-131 ONLY	R712	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY
L6P03	2701-000160	INDUCTOR-AXIAL:22uH,5%,2.4x3.4mm		R713	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY
L6P05	2702-001077	INDUCTOR-RADIAL:27uH,5%,5.5x5.5mm		R714	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY
Q6P01	0501-000303	TR-SMALL SIGNAL:KSA733,PNP,250mW,TO-92,T		R715	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY
Q6P02	0501-000303	TR-SMALL SIGNAL:KSA733,PNP,250mW,TO-92,T		R716	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY
R6P07	2001-000281	R-CARBON:100OHM,5%,1/8W,AA,TP,1.8X3.2MM		R718	2001-000969	R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY
R6P08	2001-000005	R-CARBON:390ohm,5%,1/8W,AA,TP,1.8x3.2mm		R718	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 NOT USER
R6P09	2001-000449	R-CARBON:2.2KOHM,5%,1/8W,AA,TP,1.8X3.2MM		R719	2001-000969	R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY
R6P10	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-131 NOT USER	R719	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 NOT USER
				R720	2001-000969	R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY
				R720	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 NOT USER
				R721	2001-000969	R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY
				R721	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 NOT USER
				R722	2001-000969	R-CARBON:750OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY

Loc.No	Part No	Description ; Specification	Remark	Loc.No	Part No	Description ; Specification	Remark
R722	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 NOT USER	R730	2001-000780	R-CARBON:470OHM,5%,1/8W,AA,TP,1.8X3.2MM	
R723	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY	R731	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM	
R723	2001-000362	R-CARBON:150OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 NOT USER	RM701	AC59-60060A	MODULE-REMOCON:GP1U281R,SHARP:38KHZ,-,-	
R724	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM	SVR-433 ONLY	-	-	ASSY-PCB-SUB:SHUTTLE	S.N.A.
R727	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		CN707	3708-001164	CONNECTOR-FPC/FC/PIC:5P,1.25MM,ANGLE,SN	
R728	2001-000008	R-CARBON:15KOHM,5%,1/8W,AA,TP,1.8X3.2MM		SH701	2101-000101	VR-ROTARY:100Kohm,20%,1/10W,SIDE	
SW701	3404-001076	SWITCH-TACT:12V,50mA,16gf+-50gf,6x6mm,SP					
SW703	3404-001076	SWITCH-TACT:12V,50mA,16gf+-50gf,6x6mm,SP					
SW706	3404-000165	SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST					
SW707	3404-000165	SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST					
SW708	3404-001076	SWITCH-TACT:12V,50mA,16gf+-50gf,6x6mm,SP					
SW709	3404-001076	SWITCH-TACT:12V,50mA,16gf+-50gf,6x6mm,SP					
SW711	3404-001076	SWITCH-TACT:12V,50mA,16gf+-50gf,6x6mm,SP					
SW712	3404-001076	SWITCH-TACT:12V,50mA,16gf+-50gf,6x6mm,SP					
SW713	3404-001076	SWITCH-TACT:12V,50mA,16gf+-50gf,6x6mm,SP					
SW714	3404-001076	SWITCH-TACT:12V,50mA,16gf+-50gf,6x6mm,SP					
SW715	3404-001076	SWITCH-TACT:12V,50mA,16gf+-50gf,6x6mm,SP					
SW716	3404-001076	SWITCH-TACT:12V,50mA,16gf+-50gf,6x6mm,SP					
SW718	3404-000165	SWITCH-TACT:12V,50mA,160gf,6x6mm,SPST					
FRONT AV JACK (SVR-433/233 ONLY)							
C704	2401-000407	C-AL:10uF,20%,16V,GP,TP,3.5x5.2,5					
C706	2202-000173	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,1					
CN709	3710-001385	CONNECTOR-SOCKET:10P,1R,2mm,ANGLE,SN					
D707	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,					
JK701	AC37-22002J	JACK-PIN:3.2mm,DPSE-9814,2P,13mm,S/W					
L703	2701-000181	INDUCTOR-AXIAL:33uH,5%,2.4x3.4mm					
Q706	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T					
Q707	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T					
R735	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM					
-	-	ASSY-PCB-F/TIMER:LED MODILE	S.N.A.				
C701	2401-002165	C-AL:100uF,20%,16V,GP,TP,6.3x7.5					
C702	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,					
C703	2202-000173	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,1					
CN705	3711-001198	CONNECTOR-HEADER:NOWALL,10P,1R,2mm,ANGLE					
CN706	3711-001198	CONNECTOR-HEADER:NOWALL,10P,1R,2mm,ANGLE					
DT701	0703-001096	LED DISPLAY:AMB,6,10,50x22.5mm					
Q709	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T					
Q710	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T					
Q716	0501-000290	TR-SMALL SIGNAL:KSA643-Y,PNP,500mW,TO-92					
R709	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R710	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R717	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R725	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R726	2001-000969	R-CARBON:75OHM,5%,1/8W,AA,TP,1.8X3.2MM					
R731	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
RM701	AC59-60060A	MODULE-REMOCON:GP1U281R,SHARP:38KHZ,-,-					
-	-	ASSY-PCB-F/TIMER:LED SINGLE	S.N.A.				
C701	2401-002165	C-AL:100uF,20%,16V,GP,TP,6.3x7.5					
C702	2202-000797	C-CERAMIC,MLC-AXIAL:10NF,30%,16V,Y5S,TP,					
C703	2202-000173	C-CERAMIC,MLC-AXIAL:1nF,10%,50V,Y5P,TP,1					
CN705	3711-001198	CONNECTOR-HEADER:NOWALL,10P,1R,2mm,ANGLE					
CN706	3711-001198	CONNECTOR-HEADER:NOWALL,10P,1R,2mm,ANGLE					
D711	0401-000101	DIODE-SWITCHING:1N4148,100V,200mA,DO-35,					
LD702	0601-001201	LED ROUND,RED,3mm,635nm					
LD703	0601-001408	LED:TAPG,-,-,-					
LD704	0601-001408	LED:TAPG,-,-,-					
LD705	0601-001408	LED:TAPG,-,-,-					
LD706	0601-001408	LED:TAPG,-,-,-					
LD707	0601-001408	LED:TAPG,-,-,-					
LD709	0601-001408	LED:TAPG,-,-,-					
Q710	0501-000398	TR-SMALL SIGNAL:KSC945,NPN,250mW,TO-92,T					
R710	2001-000290	R-CARBON:10KOHM,5%,1/8W,AA,TP,1.8X3.2MM					
R729	2001-000490	R-CARBON:200OHM,5%,1/8W,AA,TP,1.8X3.2MM					

MEMO