

100MS/s Single-Channel Arbitrary Waveform Generator

MODEL 8025



- Single-channel 100 MS/s waveform generator
- Multi-Instrument synchronization
- 14 Bit amplitude resolution, 18 Bit offset resolution
- 1 Meg word waveform memory, 4 Meg word memory, optional
- 1 ppm clock accuracy and stability
- Extensive modulation capabilities AM, FM, Arbitrary FM, FSK, Ramped FSK and Sweep
- Waveform sequencing with up to 4096 segments and sequences

- 10 Built-in popular standard waveforms
- DDS technology delivers extremely low phase noise signals
- GPIB and RS-232 interfaces
- ArbConnection software for easy waveform creation & control

The 8025 system breaks new ground in arbitrary waveform generator design. With its unprecedented combination of arbitrary generator and synthesizer, its versatility, its high resolution and wide frequency range, and its extremely good performance-to-price ratio, the 8025 offers a range of benefits that will facilitate work in many fields.

100 MS/s Sample Rate

The 100 MS/s sample rate allows the vertical accuracy to be converted into excellent performance at high frequencies. This opens up many applications in communication, video and television, telecommunication, radar, and ultrasonics, for example.

14 Bit Resolution

The 14-bit resolution provides 16,384 output levels. This means that even audio waveforms can be generated with excellent fidelity. It also allows video and other complex waveforms to be generated with small details superimposed on large signals, in order to test the response of receiving systems.

Bench Operation

Looking at the instrument as a simple function generator, there are eleven basic waveforms with adjustable parameters. These are sine, triangle, square, pulse, ramp, sinc, Gaussian, exponential up, exponential down, noise, as well as DC. All are accessible from the front panel.

4 Meg Memory

The 8025 offers 1 Meg word (4Meg word optional) memory for arbitrary waveforms. Given the 14-bit resolution, the generator offers enormous power. In addition, the memory can be divided into as many as 4096 segments, which can be looped and linked in many different ways. Using 1 Meg word at 25 MS/s to generate a video signal, for example, the duration is 0.04 s, 25 Hz, even without any looping of repetitive elements.

Sequence Generator

When the sequencing facilities are invoked, the 8025 becomes truly unique. The memory segments can be linked and repeated in any

combination both manually and under programmed control.

In the automatic advanced mode, the complete sequence runs continuously and automatically under the control of a pre-programmed table. In the stepped sequence-advance mode, the current segment is looped continuously until a trigger is received, when the next segment is invoked. The single sequence advance mode runs the current segment once only, and then idles until the next trigger is received. There is even a mixed sequence mode in which each segment can be preprogrammed to run under either automatic-advance mode or in stepped advance mode.



TABOR ELECTRONICS Ltd.

100MS/s Single-Channel Arbitrary Waveform Generator

Model 8025



Fast Data Transfer

Arbitrary waveform data may be quickly transferred to the 8025 via RS-232C or GPIB - IEEE 488.2 - using a very fast DMA mode.

Sample Clock Modulation

One of the many attractive features of the 8025 is the sample clock modulation function. In a normal arbitrary waveform generator, to make a frequency modulated sinewave, you have to enter the complete mathematical function. Not so with the 8025: all you need to do is to generate the carrier signal, and then modulate the clock to obtain the required result. The sample clock modulation can be done by internal waveforms - sine, square, triangle, and ramp. Using downloaded arbitrary modulating waveforms, you can generate signals that would be difficult or impossible to define using an equation.

Frequency Shift Keying

Frequency shift keying could be accomplished by using the facilities already mentioned, but the 8025 includes an FSK function to simplify operations. A TTL input is used to control the shifting.

As a further refinement, the 8025 offers a ramped FSK function, in which the rate of change of frequency is controlled by the ramp time parameter.

Linear Logarithmic Frequency Sweep

A linear or logarithmic frequency sweep is offered, and of course the FM functions can be used to define more complicated variations.

Triggering Facilities

However versatile the waveform generation systems are made, the need for external control of generation is vital. The triggering facilities of the 8025 match the generation functions in versatility.

In the simplest mode, signals are output continuously. The 8025 also offers the triggered mode, gated mode, external burst mode, and internal burst mode, all of which can use an external trigger signal or an internal trigger. The use of external sources to prompt the switching of segments has already been mentioned.

Any point in a wave can be designated as a start point. On receipt of a trigger, the wave starts at this point, runs to the end, restarts seamlessly at the beginning, and stops at the point before the trigger point.

Separate breakpoints are programmable in each channel, triggerable from SCPI commands via GPIB or RS-232C, or by signals at the trigger input.

ArbConnection

Unlimited Source of Arbitrary Waveforms. With the ArbConnection software you can control instruments functions, modes and features. You can also create virtually an unlimited variety of test waveforms. Freehand sketch allows you to draw your own custom waveform for quick analysis of analog signals. You can use the built-in equation editor to create your own exotic functions. Add or subtract components of a Fourier series to characterize digital or analog filters or, inject random noise into a signal to test immunity to auxiliary noise.



TABOR ELECTRONICS Ltd.

100MS/s Single-Channel Arbitrary Waveform Generator

Model 8025



Service and Support

Beyond providing precision Test & Measurement instruments, Tabor Electronics provides unparalleled service and support, and is continuously finding new ways to bring added value to its customers.

Our after-sales services are comprehensive. They include all types of repair and calibration, and a single point of contact that you can turn to whenever you need assistance. As part of our extensive support, we offer individualized, personal attention Help Desk, both online and offline, via e-mail, phone or fax.

Tabor Electronics maintains a complete repair and calibration lab as well as a standards laboratory in Israel and USA. Service is also available at regional authorized repair/calibration facilities.

Contact Tabor Electronics for the address of service facilities nearest you.

Applications

For expert technical assistance with your specific needs and objectives, contact your local sales representative or our in-house applications engineers.

Manuals, Drivers, and Software Support

Every instrument comes equipped with a dedicated manual, developer libraries, IVI drivers, and software. However, if your specific manual is lost or outdated, Tabor Electronics makes it possible to log-on to its Download Center and get the latest data "in a click".

Product Demonstrations

If your application requires that you evaluate an instrument before you purchase it, a hands-on demonstration can be arranged by contacting your local Tabor Electronics representative or the Sales Department at our Corporate Headquarters.

Three-year Warranty

Every Tabor Electronics instrument comes with a three-year warrantee. Each one has full test results, calibration certificate, and CD containing product's manual and complete software package. Our obligation under this warranty is to repair or replace any instrument or part thereof which, within three years after shipment, proves defective upon examination. To exercise this warranty, write or call your local Tabor representative, or contact Tabor Headquarters and you will be given prompt assistance and shipping instructions.

CORPORATE HEADQUARTERS

9 Hattiasia St. P.O.Box404,
Tel Hanan, Israel 20302
☎ +972 (4) 8213393
☎ +972 (4) 8213388
www.taborelec.com

EUROPE

Austria
UEI-Viena
☎ +43 15451 588
☎ +43 15451 464

Benelux (Belgium, The Netherlands and Luxembourg)
BFI Optilas B.V.
☎ +31 172 44 60 60
☎ +31 172 44 34 14

Bulgaria
New-Tek Ltd.
☎ +359 296 25286
☎ +359 268 7110

Cyprus
Sprel Ltd.
☎ +357 2237 7159
☎ +357 2237 7284

Czech Republic & Slovakia
Testovací Technika s.r.o.
☎ +420 2 7478 2237
☎ +420 2 7478 1285

Denmark
Atimco AS
☎ +45 8625 8899
☎ +45 8625 5889

France
Racal Instruments SAS
☎ +33 1 3923 2205
☎ +33 1 3923 2225

Germany
Compulless Elektronik GmbH
☎ +49 89 321501-0
☎ +49 89 321501-11

Greece
American Technical Enterprises S.A
☎ +30 210 5240 740
☎ +30 210 5249 995

Hungary
ProMet Meresteknika
☎ +36 24 521 240
☎ +36 24 521 253

Italy
LP Instruments srl
☎ +39 2 4840 1713
☎ +39 2 4840 1852

Norway
Nortelco AS
☎ +47 2257 6100
☎ +47 2257 6130

Poland
Helmar
☎ +48 22 436 3106
☎ +48 22 436 3110

Romania
InterNET SRL
☎ +40 21 312 1662
☎ +40 21 312 1663

Russia
CDIP
☎ +7 0959 56 2022
☎ +7 0959 56 2022

Spain & Portugal
Instrumentos De Media SL
☎ +34 91 300 0191
☎ +34 91 388 5433

Sweden & Finland
Ferner Elektronik AB
☎ +46 8 760 8360
☎ +46 8 760 8341

Switzerland
Elstar Elektronik AG
☎ +41 56 427 1888
☎ +41 56 427 1976

United Kingdom & Ireland
SEMATRON UK Ltd.
☎ +44 1256 812222
☎ +44 1256 812666

Yugoslavia (Bosnia, Croatia, Macedonia, Montenegro, Serbia, Slovenia)
Mechanic & Electronic Measurement
☎ +43 1943 4254
☎ +43 1943 4251

ASIA PACIFIC & JAPAN

Australia
Trio Test & Measurement Solutions
☎ +61 8 8234 0504
☎ +61 8 8234 0130

India
AIMIL Ltd.
☎ +91 11 2695 0001
☎ +91 11 2695 0011

Japan
TOYO Corporation
☎ +81 3 3279 0771
☎ +81 3 3246 0645

Korea
ITB Corporation
☎ +82 2 549 8501
☎ +82 2 549 8502

New Zealand
Electrotest Ltd.
☎ +64 9 448 2600
☎ +64 9 448 2611

Philippines
Sunley Inc.
☎ +63 2751 1216
☎ +63 2815 0730

Singapore, Thailand & Vietnam
Gold Lite Engineering Pte Ltd.
☎ +65 6273 0487
☎ +65 6273 5006

Taiwan, China & Hong Kong
Precision International Corp.

Taiwan
☎ +886 2 85124888
☎ +886 2 85124900

China & Hong Kong
☎ +86 21 64401300
☎ +86 21 64400524

AFRICA

South Africa
Channels Measurement
☎ +27 11 254 8362
☎ +27 11 254 8451

MIDDLE EAST
Israel
Dan-EI Technologies Ltd.
☎ +972 3 9271888
☎ +972 3 9271666

Turkey
Alfatek Test & Automation Ltd.
☎ +90 216 474 7355
☎ +90 216 474 7357

UNITED STATES US SALES & SUPPORT OFFICE

☎ +1 909 7970484
☎ +1 909 7974955

IL, IN, IA, KS, KY, MN, MO, NE, ND, SD, WI
Base Eight, Inc.
☎ +1 847 670 1680
☎ +1 847 670 1737

AZ, CO, ID, MT, NM, TX, EI Paso, UT, WY
Berry Technical Sales Inc.
☎ +1 303 665 9116
☎ +1 303 833 1294

AR, LA, OK, TX
Data Marketing Associates Inc.
☎ +1-972 661 0300
☎ +1 972 490 0836

OH, WV, PA, MI
Dytec EAST
☎ +1-330 405 8311
☎ +1 330 405 8313

DC, MD, VA
Eastern Instrumentation Corp.
☎ +1 410 884 7303
☎ +1 410 884 7306

PA, NJ
EI Philly
☎ +1 856 231 0668
☎ +1 856 231 9022

HAW, NV, CA
Sierra Technical Sales
☎ +1 510 713 9957
☎ +1 510 713 9958

NJ, NY
Tera Technologies Inc.
☎ +1 888 921-TERA
☎ +1 888 449 2799

CT, ME, MA, NH, RI, VT
Test-Rep Associates, Inc.
☎ +1 978 692 8000
☎ +1 407 839 0337

AL, FL, GA, MS, NC, SC, TN
W.A Brown Instruments
☎ +1 407 648 9660
☎ +1 407 839 0337

CA, NV
W5 Inc.
☎ +1 949 212 1199
☎ +1 714 281 0767

CANADA
Testforce Systems Inc.
☎ +1 514 856 0970
☎ +1 514 856 6983

LATIN AMERICAS SALES & SUPPORT OFFICE
☎ +1 440 543 7710
☎ +1 440 543 9681

Specification 100MS/s Single-Channel Arbitrary Waveform Generator

Model 8025



STANDARD WAVEFORMS

Waveforms: Sine, Triangle, Square, Pulse, Ramp, Sinc (Sine(x)/x), Gaussian Pulse, Exponential Fall, Rising Pulse, Noise, DC.

Frequency Range: Waveform dependent

Source: Internal synthesizer

SINE

Frequency Range: 100µHz to 50MHz

Band Flatness: 5% to 10MHz; 20%, to 50MHz

Programmable Parameters: Start phase, 0 to 360°

Harmonics and non-related spurious at 5Vp-p: <-55dBc for carrier frequencies 1MHz
<-45dBc for carrier frequencies 5MHz
<-40dBc for carrier frequencies 10MHz
<-22dBc for carrier frequencies 50MHz

Total Harmonic Distortion: 0.1% to 100kHz

TRIANGLE

Frequency Range: 100µHz to 12.5MHz

Start phase: 0 to 360°

SQUARE

Frequency Range: 100µHz to 50MHz

Duty cycle: 1% to 99%

Rise/Fall time: <10ns

Aberration: <5%

PULSE

Frequency Range: 100µHz to 6.25MHz

Adjustable Parameters:

| | |
|-----------|-----------------------|
| Delay | 0% to 99.9% of period |
| Rise Time | 0% to 99.9% of period |
| High Time | 0% to 99.9% of period |
| Fall Time | 0% to 99.9% of period |

Rise/Fall time: <10ns

Aberration: <5%

RAMP

Frequency Range: 100µHz to 12.5MHz

Adjustable Parameters:

| | |
|-----------|-----------------------|
| Delay | 0% to 99.9% of period |
| Rise Time | 0% to 99.9% of period |
| Fall Time | 0% to 99.9% of period |

SINC (SINE(x)/x)

Frequency Range: 100µHz to 3.125MHz

"0" Crossing: 4 to 100 cycles

GAUSSIAN PULSE

Frequency Range: 100µHz to 3.125MHz

Time Constant: 10 to 200

EXPONENTIAL FALL/RISING PULSE

Frequency Range: 100µHz to 6.25MHz

Time Constant: -20 to 20

NOISE

Bandwidth: 25MHz

DC

Range: -100% to 100% of amplitude

ARBITRARY WAVEFORMS

SAMPLE CLOCK SOURCE

INTERNAL

Range: 100mS/s to 100MS/s

EXTERNAL

Connector: Rear panel BNC

Range: DC to 100MHz

Level: ECL 100k compatible

Vertical Resolution: 14Bits

Waveform Memory: 1Meg points standard, 4Meg points optional

MEMORY SEGMENTATION

Number of Segments: 1 to 4096

Min Segment Size: 16 points

Memory Interleave: 4 (All trace lengths must be multiples of 4)

SEQUENCED ARBITRARY WAVEFORMS

Operation: Permits division of the memory bank into smaller segments. Segments may be linked, and repeated in user-selectable fashion to generate extremely long waveforms.

ADVANCE MODES

Automatic Sequence Advance: No triggers required to step from one segment to the next.

Sequence is repeated continuously through a pre-programmed sequence table

Stepped Sequence Advance:

Current segment is sampled continuously, external trigger advances to next programmed segment. Control input is TRIG IN connector.

Single Sequence Advance:

Current segment is sampled to the end of the segment including repeats and idles there. Next trigger advances to next segment. Control input is TRIG IN connector.

Mixed Sequence Advance:

Each step of a sequence can be programmed to advance either a) automatically (Automatic Sequence Advance), or b) with a trigger (Stepped Sequence Advance)

Advance Source: External, rear panel BNC; Internal; GPIB

Sequencer steps: From 1 to 4096

Segment loops: From 1 to 1Meg

Segment Duration: Minimum 1µs for more than one loop.

COMMON CHARACTERISTICS

MAIN OUTPUT

Connector: Front panel BNC

Stand-by: Output Off or Normal

Impedance: 50Ω, ±1%

Protection: Protected against temporary short to case ground

Frequency Resolution:

7 digits limited by 1µS/s

Accuracy:

1ppm

Stability:

1ppm

Reference:

Internal
0.0001% (1ppm TCXO) initial tolerance over a 19°C to 29°C temperature range; 1ppm/°C below 19°C and above 29°C; 1ppm/year aging rate

External
10MHz TTL, 50% ±2% duty cycle

Specification 100MS/s Single-Channel Arbitrary Waveform Generator

Model 8025



AMPLITUDE

| | |
|-------------------------|--|
| Range: | 10 mV to 10Vp-p, into 50Ω; Double into open circuit |
| Resolution: | 4 digits |
| Accuracy (1kHz): | |
| 1.000V to 10Vp-p | ±(1% + 25 mV) |
| 100 mV to 999.9 mVp-p | ±(1% + 5 mV) |
| 10 mV to 99.99 mVp-p | ±(1% + 2 mV) |

OFFSET

| | |
|--------------------|------------------------------------|
| Range: | 0 to ±4.5V, amplitude dependent |
| Resolution: | 2.2mV |
| Accuracy: | ±1% |

| | |
|----------------|----------------------------------|
| FILTERS | 50MHz Elliptic 25MHz Elliptic |
|----------------|----------------------------------|

SYNC/MARKER OUTPUT

| | |
|-----------------------|---|
| Connector: | Front panel BNC |
| Impedance: | 50Ω, ±1% |
| Level: | >2V into 50Ω, 4V nominal into 10kΩ |
| Protection: | Protected against temporary short to case ground |
| Validators: | BIT, LCOM |
| Position: | Point 0 to n, Programmable with 4-point resolution |
| Width Control: | Programmable |
| Range: | 4 to 100000 waveform points |
| Resolution: | 4 points |
| Source: | Main output |

SINEWAVE OUTPUT

| | |
|--|---|
| Connector: | Rear panel BNC |
| Impedance: | 50Ω, ±1% |
| Level: | 1V into 50Ω |
| Protection: | Protected against temporary short to case ground |
| Source: | Sample clock frequency |
| Frequency Range and Resolution: | Same as Sample clock |
| Total Harmonic Distortion: | 0.05% to 100kHz |
| Harmonics and non-related spurious: | < -30dBc |

INPUTS

TRIG INPUT

| | |
|-------------------|----------------|
| Connector: | Rear panel BNC |
| Impedance: | 10kΩ, ±5% |

| | |
|-------------------------|-------------------------------------|
| Threshold Level: | TTL |
| Min Pulse Width: | 20ns |
| Slope: | Positive or negative going edge. |

10 MHz REFERENCE INPUT

| | |
|---------------------------|--|
| Connector: | Rear panel BNC |
| Impedance: | 10kΩ, ±5% |
| Threshold Level: | TTL |
| Duty Cycle: | 50%, ±5% |
| AM Input | |
| Modulation Input: | Rear panel BNC |
| Impedance: | 1MΩ, ±5% |
| Max Input Voltage: | 12V |
| Sensitivity: | 0V to +5V (5Vp-p) produce 100% modulation |
| Source: | External |
| Modulation Range: | 0 to 100% |
| Bandwidth: | DC to 500kHz |

MODULATION

FM

| | |
|----------------------------|---|
| Waveform | |
| Modulation: | Sine, Triangle, Square, Pulse, Ramp, Sinc (Sine(x)/x), Gaussian Pulse, Exponential Fall, Rising Pulse, Noise, DC, Arb |
| Source: | Internal |
| Resolution: | 7 digits |
| Accuracy: | 0.1% |
| Frequency | |
| Distortion: | <0.1% |
| Deviation Range: | 100mS/s to 100MS/s |
| Trigger | |
| Advanced Mode: | Automatic, Triggered, Gated or Software Command |
| Marker | |
| Output & Level: | Same as SYNC output. |
| Position: | Programmable for selected frequency |

FM – BUILT-IN STANDARD WAVEFORMS

| | |
|---------------------------|------------------------------------|
| Carrier Waveforms: | Sine, Square, Triangle and Ramp |
|---------------------------|------------------------------------|

| | |
|-------------------------|----------------|
| Modulation | |
| Frequency Range: | 1mHz to 100kHz |

FM – DOWNLOADED ARBITRARY WAVEFORMS

| | |
|---------------------------|--|
| Modulation Source: | User waveform, any shape, 10 to 20000 waveform points |
| SCLK Range: | 1mS/s to 2MS/s |

FSK

| | |
|-------------------------|--|
| Carrier Sample | |
| Clock Range: | 100mS/s to 100MS/s |
| Source: | External, Rear panel Trigger input BNC. |
| Low level: | Carrier sample clock |
| High level: | Hop frequency |
| Frequency Range: | From 10MHz to DC |
| FSK Delay: | Minimum 1 waveform cycle + 50ns |

RAMPED FSK

| | |
|-------------------------|-----------------------------|
| Ramp Time Range: | 10μs to 1s, 3 digits, ±0.1% |
|-------------------------|-----------------------------|

SWEEP

| | |
|----------------------------|--|
| Carrier Waveforms: | Sine, Square, Triangle, Ramp, Arb |
| Type: | Linear or Logarithmic |
| Direction: | Up or down, depending on the start and stop setting |
| Sweep Time: | 1ms to 1000s, 7 digits, ±0.1% |
| Range: | 100mS/s to 100MS/s |
| Trigger | |
| Advanced Mode: | Automatic, Triggered, Gated or Software Command |
| Marker: | |
| Output & Level: | Same as SYNC output. |
| Position: | Programmable for selected frequency |

TRIGGERING CHARACTERISTICS

TRIGGER SOURCES

EXTERNAL

| | |
|-------------------|----------------------|
| Connector: | Rear panel BNC |
| Level: | TTL |
| Slope: | Positive or negative |
| Frequency: | DC to 2MHz |
| Impedance: | 10kΩ, DC coupled |

INTERNAL

| | |
|--------------------|----------------|
| Range: | 100mHz to 2MHz |
| Resolution: | 7 digits |
| Accuracy: | 0.1% |

MANUAL

Single trigger (front panel push-button) simulates an external trigger signal.

Specification 100MS/s Single-Channel Arbitrary Waveform Generator

Model 8025



TRIGGER START PHASE

Description: Waveform starts from point n and completes at point n-1.
Range: 0 to 999999 waveform points (1Meg, 4Meg optional)
Resolution: 4 points

START/STOP CONTROL (BREAKPOINT)

Range: 0 to 999999 waveform points (1Meg, 4Meg optional)
Source: External (Rear Panel Trigger Input BNC), Manual, or software command through RS232 or GPIB
Resolution: 4 points
Breakpoint Error: ± 4 points

SYSTEM DELAY

Trigger to waveform output: 1 Sample Clock+150ns

GATED MODE External signal enables generator. First output cyclesynchronous with the active slope of the triggering signal. Last cycle of output waveform always completed

BURST

Waveforms: Sine, Triangle, Square, Pulse, Ramp, Sinc (Sine(x)/x), Gaussian Pulse, Exponential Fall, Rising Pulse, Noise, DC, Arb

Number of cycles per burst: 1 to 1000000
Trigger source: Manual, External or Internal

MULTI-INSTRUMENT SYNCHRONIZATION

Description: Multiple instruments can be connected together and synchronized to provide multi-channel synchronization.

PHASE (LEADING EDGE) OFFSET

Description: Leading edge of master output trails the leading edge of the slave output by a programmable number of points. Each slave can be programmed to have individual offset.

Range: 0 to 999999 points (1Meg, 4Meg optional)

Resolution and Accuracy: 4 point
Initial Skew: $< \pm 15$ ns, depending on cable length and quality, typically with 1 meter coax cables

GENERAL

Power requirements: 90 to 264V, 47 to 63Hz, 50W max
Display: 4 lines, 80 characters, backlit LCD.

Operating temperature: 0 - 40°C
Humidity (non-condensing): 11°C to 30°C: 85 %
 31°C to 40°C: 75 %

Storage temperature: -40°C to + 70°C.
Interface: GPIB and RS232C standard
Language: IEEE-488.2 - SCPI - 1993.0
Dimensions: 212 x 88 x 415 mm (WxHxD)
Weight: Approx 4kg
Safety: EN61010-1
EMC: CE marked. Designed to meet VDE 0411/03.81 and UL 1244
Reliability: MTBF per MIL-HDBK-217E, 25°C, Ground Benign

Workmanship Standards: Conform to IPC-A-610D

Supplied Accessories: Power Cord, CD containing Operating Manual, ArbConnection software and developer libraries.
Warranty: 3 years standard

ORDERING INFORMATION

| MODEL | 8025 |
|---|------|
| 100MS/s Single-Channel Arbitrary Waveform Generator | |

OPTIONS

| | |
|------|--------------|
| 4Meg | 4 Meg Memory |
|------|--------------|

ACCESSORIES

| | |
|---------------------|---|
| Sync cable | Sync cable for multi instrument synchronization |
| S-Rack mount | 19" Single Rack Mounting Kit |
| D-Rack mount | 19" Dual Rack Mounting Kit |
| Case Kit: | Professional Carrying Bag |

Note: Options and Accessories must be specified at the time of your purchase.