




Anhang
Appendix
Annexe



Pegelmeßgerät
Transmission Measuring Set
Appareil de mesure de niveau

PMG-3



PEGELMESSGERÄT

PMG-3

für den Frequenzbereich 50 Hz bis 20 (110) kHz

TRANSMISSION MEASURING SET

PMG-3

for the frequency range 50 Hz to 20 (110) kHz

APPAREIL DE MESURE DE NIVEAU

PMG-3

pour la gamme de fréquence 50 Hz à 20 (110) kHz

Anhang/Appendix/Annexe

BN 9202/03

Serie A...

I.12.81 brt/Kh
0.1.12.81 2861


Anderungen vorbehalten
Printed in the Federal Republic of Germany



Subject to change without notice
Printed in the Federal Republic of Germany

Droits de modifications réservés
Imprimé en République Fédérale d'Allemagne

Wandel & Goltermann

ELEKTRONISCHE
PRÄZISIONSMESSGERÄTE





4-2 REQ'D
5-4 REQ'D

6-4 REQ'D



3-5 REQ'D

NUMBERING FOR
REFERENCE ONLY



REMOVE ALL SWITCH
BUTTONS BEFORE
FLOW SOLDERING



SWITCH BUTTON ROTATED AS
SHOWN FOR CLARITY ONLY. PLACE
BUTTON IN THIS POSITION BEFORE
INSERTING ON SHAFT
THIS IS NOT AN END VIEW OF THE
SWITCH ASSEMBLY

CIRCUIT BOARD NCs




NOTE:
1. ADD 1200 TO ALL COMPONENT
DESIGNATIONS EXCEPT CONNECTOR,
FOR PART NUMBER
2. DOT REMOVES P.N. I.C.S






Bestückungszeichnung 1:1 siehe Seite
 Component drawings are 1:1, see Page
 Disposition des composants en grandeur réelle, voir page

REVISION	DATE	BY	CHK
1.0	1970-10-10	J. B.	J. B.
2.0	1970-10-10	J. B.	J. B.
3.0	1970-10-10	J. B.	J. B.
4.0	1970-10-10	J. B.	J. B.
5.0	1970-10-10	J. B.	J. B.
6.0	1970-10-10	J. B.	J. B.
7.0	1970-10-10	J. B.	J. B.
8.0	1970-10-10	J. B.	J. B.
9.0	1970-10-10	J. B.	J. B.
10.0	1970-10-10	J. B.	J. B.




9/L 9202-76/3

DESIGNATION	ASSEMBLY C.W.S.	REV	1
SERIES	9202-7013-00/1	DATE	10/1
UNIT NO	9202-7013-00/1		




NOTES:
 1. ALL RESISTOR VALUES IN OHMS UNLESS OTHERWISE SPECIFIED
 2. ALL P1401 CONNECTIONS RUN VIA (18)




Bestückungszeichnung 1:1 siehe Seite
 Component drawings are 1:1, see Page
 Disposition des composants en grandeur réelle, voir page

- NOTES
1. COMPONENT DESIGNATOR SHOWN FOR REF ONLY. NOT ALL COMPONENTS ARE SHOWN.
 2. ADD "A007" TO ALL REF DESIGNATORS.
 3. DOT ON IC'S DENOTES PIN 1




BN 9202/03	PMG-3	PARTS LIST - 9202-764/PL
DESIGNATION	SCHEMATIC SECTION (14)	SERIES A...
DWG NO.	9202-7514-01/BB	DWG NO.
		PAGE 2 OF 3

SEE PAGE 1 FOR REV. #





BN 9202/03	PMG-3	PARTS LIST - 9202-764/PL
DESIGNATION	SCHEMATIC SECTION (14)	SERIES A...
DWG NO.	9202-7514-01/B	DWG NO.
		PAGE 3 OF 3

4w2



- NOTES
1. COMPONENT DESIGNATOR SHOWN FOR REF. ONLY - NOT MARKED ON COMPONENTS.
 2. ADD "1400" TO ALL REF. DESIGNATORS.
 3. DOT ON IC'S DENOTES PIN 1





NOTES:

1. S.A.T. DENOTES SELECT AT TEST COMPONENT
2. COMPONENT DESIGNATORS SHOWN FOR REFERENCE ONLY - NOT MARKED ON COMPONENTS.
3. ADD '300' TO COMPONENT DESIGNATORS EXCEPT CONNECTOR FOR PART NUMBERS
4. S.A.T. DENOTES 'SELECT AT TEST' COMPONENT
5. COMPONENT LOCATIONS

FOR PM3.3 (3000Hz-850Hz-420Hz) OPERATION:

- INSTALL R77 IN POSITION B-C
- INSTALL R76 IN POSITION B-F
- INSTALL R75 IN POSITION J-N
- R74 IS NOT USED

FOR PM3.3 (3000Hz-850Hz-420Hz) OPERATION:


- INSTALL R77 IN POSITION B-C
- INSTALL R76 IN POSITION Q-F
- INSTALL R75 IN POSITION J-L
- INSTALL R74 IN POSITION M-O

6. PADS MARKED g+h ARE NOT USED




7. THE FOLLOWING COMPONENTS ARE HARD-WIRED TO THE BOARD FOR SERIES A4B (REFER TO SCHEMATIC NO. 9202-7015-01) - C52, C53, C54, C55, R51, Q3

PL 9202-7615

BN 9202/3	PM 6-3	DESIGNATION		SERIAL NO.	REV
		ASSEMBLY		DWG NO	PAGE 1
		SYNTHESIZER BD		9202-7515-00/D	OF 1




NOTE:
1. COMPONENT DESIGNATORS SHOWN
FOR REFERENCE ONLY - NOT
MARKED ON COMPONENTS







BN 9202 / 03	PARTS LIST	9202-700 / 11	REV
DESIGNATION	SERIES	DWG NO	PAGE 1
ASSEMBLY DVS	9202-700 / 00 / 0	OF 1	
DISPLAY BOARD			

202-7016-00



NOTES:
1. ALL WIRES 22 GAUGE STRANDED.
2. MAX COMPONENT HEIGHT 40mm





ITEM QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
R1101	1	Resistor	Film 615 +.5% 4W	0008-0646
R1102	1	Resistor	Film 1255 +.5% 4W	0008-0665
R1103	1	Resistor	Film 615 +.5% 4W	0008-0646
R1104	1	Resistor	Film 1255 +.5% 4W	0008-0665
R1105	1	Resistor	MF 200 K 1% 1/2W	0008-0316
R1106	1	Resistor	MF 200 K 1% 1/2W	0008-0316
R1107	1	Resistor	MF 2.67 K 1% 1/2W	0008-0336
R1108	1	Resistor	MF 681 1% 1/2W	0008-0047
R1109	1	Resistor	CF 100 K 5% 1/2W	0008-0194
R1110	1	Resistor	MF 681 1% 1/2W	0008-0047
R1111	1	Resistor	CF 22 5% 1/2W	0008-0234
R1112	1	Resistor	MF 15 K 1% 1/2W	0008-0348
R1113	1	Resistor	MF 10 K 1% 1/2W	0008-0311
R1114	1	Resistor	MF 8.25 K 1% 1/2W	0008-0329
R1115	1	Resistor	MF 118 K 1% 1/2W	0008-0450
R1116				
R1117	1	Resistor	CF 22 5% 1/2W	0008-0234
R1118				
R1119				
R1120				
R1121	1	Resistor	CF 100 5% 1/2W	0008-0172
R1122	1	Resistor	CF 100 5% 1/2W	0008-0172
R1123	1	Resistor	CF 12 K 5% 1/2W	0008-0184
R1124	1	Resistor	CF 12 K 5% 1/2W	0008-0184

1) Select at Test.

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
R1125	1	Resistor	MF 82.5 1% 1/2W	0008-0276 1)
R1126	1	Resistor	MF 28.7 1% 1/2W	0008-0518
R1127	1	Resistor	MF 332 1% 1/2W	0008-0131 1)
R1128	1	Resistor	MF 30.1K 1% 1/2W	0008-0061
R1129	1	Resistor	MF 4.64K 1% 1/2W	0008-0324 1)
R1130	1	Resistor	MF 13 K 1% 1/2W	0008-0328 1)
R1131	1	Resistor	MF 30.1 K 1% 1/2W	0008-0061
R1132	1	Resistor	MF 4.32 K 1% 1/2W	0008-0327
R1133	1	Resistor	MF 3.92 K 1% 1/2W	0008-0274
R1134	1	Resistor	MF 23.7 K 1% 1/2W	0008-0059
R1135	1	Resistor	CF 100 5% 1/2W	0008-0172
R1136	1	Resistor	CF 100 5% 1/2W	0008-0172
R1137	1	Resistor	MF 13 K 1% 1/2W	0008-0328
R1138	1	Resistor	CF 27 K 5% 1/2W	0008-0186
R1139	1	Resistor	CF 27 K 5% 1/2W	0008-0186
R1140	1	Resistor	CF 27 K 5% 1/2W	0008-0186
R1141	1	Resistor	CF 27 K 5% 1/2W	0008-0186
R1142	1	Resistor	CF 51 5% 1/2W	0008-0004
R1143	1	Resistor	CF 7.5 K 5% 1/2W	0008-0362
R1144	1	Resistor	CF 4.7 K 5% 1/2W	0008-0182
R1145	1	Resistor	CF 100 K 5% 1/2W	0008-0194
R1146	1	Resistor	CF 330 K 5% 1/2W	0008-0403 1)
R1147	1	Resistor	CF 220 K 5% 1/2W	0008-0251
R1148	1	Resistor	CF 47 K 5% 1/2W	0008-0190
R1149	1	Resistor	CF 1 M 5% 1/2W	0008-0292

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL.	MANUFACTURER, NOTES	STOCK NO.
R1150	1	Resistor	CF 51 5% 1/4W	0008-0004
R1151	1	Resistor	CF 3.9 K 5% 1/4W	0008-0181
R1152	1	Resistor	CF 51 5% 1/4W	0008-0004
R1153	1	Resistor	CF 2.7 K 5% 1/4W	0008-0213
R1154	1	Resistor	CF 18 K 5% 1/4W	0008-0295
R1155	1	Resistor	CF 470 K 5% 1/4W	0008-0206
R1156	1	Resistor	CF 330 K 5% 1/4W	0008-0403
R1157	1	Resistor	MF 82.5 K 1% 1/4W MF4C RN55C-8252-F	0008-0070
R1158	1	Resistor	MF 90.9 K 1% 1/4W " RN55C-90 92-F	0008-0298
R1159	1	Resistor	MF 13.0 K 1% 1/4W " RN55C-1302-F	0008-0328
R1160	1	Resistor	CF 330 5% 1/4W Amp. CR-25	0008-0242
R1161	1	Resistor	ZERO ohm Jumper Tevis WI-40	0008-0612

1) Select at Test.

ITEM QTY	DESIGNATION	ORDERING INFORMATION		STOCK NO.	
		VALUE, SIZE, TOL	MANUFACTURER, NOTES		
C1101	1 Cap Cer	0.22 uF	50V	Centralab CW30C-224 K	0002-0263
C1102	1 Cap M-Poly	10 uF	10% 200V	M/E 708A1CF106K201X Sprague	0002-0360
C1103	1 Cap Tant	22 uF	10% 15V	196D226X9015 KAL	0032-0007
C1104	1 Cap Tant	22 uF	10% 15V	196D226X9015 KAL	0032-0007
C1105	1				
C1106	1 Cap Tant	100 uF	10% 20V	196D107X9020 TE4 Sprague	0032-0090
C1107	1 Cap Tant	100 uF	10% 20V	196D107X9020 TE4	0032-0090
C1108	1 Cap Cer	33 pF	2% NPO	M/E 2222-63J-10339	0002-0052
C1109	1 Cap M-Poly	10 uF	10% 200V	M/E 708A1CF106K201X Sprague	0002-0360
C1110	1 Cap Tant	100 uF	10% 20V	196D107X9020 TE4	0032-0090
C1111	1 Cap Cer	0.0022 uF	10% 50V	Centralab CM15C 222 K	0002-0273
C1112	1 Cap Tant	6.8 uF	10% 35V	196D334X9035 HAL Sprague	0032-0086
C1113	1 Cap Tant	0.68 uF	10% 35V	196D684X9035 JAL	0032-0107
C1114	1 Cap Cer	15 pF	2% NPO	M/E 2222-63J-10159	0002-0049 (1)
C1115	1 Cap Cer	0.0033 uF	10% 50V	Centralab CM15C 332 K	0002-0272
U1101	1 I.C.	Dual SPDT Analog Sw		Harris HI-1-5043-5	0035-0316
U1102	1 I.C.	Dual FET Op-Amp		Nat. LF 353 N	0035-0303
U1103	1 I.C.	Dual FET Op-Amp		Nat. LF 353 N	0035-0303
U1104	1 I.C.	Bi FET Op-Amp		Nat. LF 355 N	0035-0259
U1105	1 I.C.	Regulator		Nat. LM 317 T	0035-0315

[illegible]

ITEM	QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO.
VRL101	1	Diode	Zener 1N 5230 B		0035-0019
VRL102	1	Diode	Zener 1N 5235 B		0035-0189
VRL103	1	Diode	Zener 1N 5235 B		0035-0189
VRL104	1	Diode	Zener 1N 5236 B		0035-0200
VRL105	1	Diode	Zener 1N 5236 B		0035-0200
Q1101	1	Transistor	2N 2219 Motorola		0010-0003
Q1102	1	Transistor	2N 2905 Motorola		0010-0002
Q1103	1	Transistor	2N 4393 Motorola		0010-0148
Q1104	1	Transistor	BCY 59 X NCS		0010-0184
Q1105	1	Transistor	BCY 59 X NCS		0010-0184
Q1106	1	Transistor	BCY 59 X NCS		0010-0184
T1101	1	Transformer	TNI T 1297		0012-0008
T1102	1	Transformer	TNI T 1262		0012-0010

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
R1201	1 Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1202	1 Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1203	1 Resistor	MF 23.7 K 1% 1/4W	RN55C-2372-F	0008-0059
R1204	1 Resistor	MF 26.7 K 1% 1/4W	RN55C-2672-F	0008-0060
R1205	1 Resistor	MF 35.7 K 1% 1/4W	RN55C-3572-F	0008-0064
R1206	1 Resistor	MF 6.81 K 1% 1/4W	RN55C-6811-F	0008-0321
R1207	1 Resistor	MF 6.81 K 1% 1/4W	RN55C-6811-F	0008-0321
R1208	1 Resistor	MF 3.16 K 1% 1/4W	RN55C-3161-F	0008-0052
R1209	1 Resistor	MF 10.0 K 1% 1/4W	RN55C-1002-F	0008-0311
R1210	1 Resistor	MF 23.7 K 1% 1/4W	RN55C-2372-F	0008-0059
R1211	1 Resistor	MF 23.7 K 1% 1/4W	RN55C-2372-F	0008-0059
R1212	1 Resistor	MF 18.7 K 1% 1/4W	RN55C-1872-F	0008-0667
R1213	1 Resistor	MF 22.6 K 1% 1/4W	RN55C-2262-F	0008-0668
R1214	1 Resistor	MF 23.7 K 1% 1/4W	RN55C-2372-F	0008-0059
R1215	1 Resistor	MF 23.7 K 1% 1/4W	RN55C-2372-F	0008-0059
R1216	1 Resistor	MF 30.9 K 1% 1/4W	RN55C-3092-F	0008-0430
R1217	1 Resistor	MF 30.9 K 1% 1/4W	RN55C-3092-F	0008-0430
R1218	1 Resistor	MF 28.0 K 1% 1/4W	RN55C-2802-F	0008-0306
R1219	1 Resistor	MF 28.0 K 1% 1/4W	RN55C-2802-F	0008-0306
R1220	1 Resistor	MF 8.25 K 1% 1/4W	RN55C-8251-F	0008-0329
R1221	1 Resistor	MF 121 K 1% 1/4W	RN55C-1213-F	0008-0231
R1222	1 Resistor	MF 30.1 K 1% 1/4W	RN55C-3012-F	0008-0061
R1223	1 Resistor	MF 21.0 K 1% 1/4W	RN55C-2102-F	0008-0280
R1224	1 Resistor	MF 21.0 K 1% 1/4W	RN55C-2102-F	0008-0280
R1225	1 Resistor	MF 21.0 K 1% 1/4W	RN55C-2102-F	0008-0280

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
R1226	1 Resistor	MF 14.7 K 1% 1/4W	RN55C-1472-F	0008-0669
R1227	1 Resistor	MF 14.7 K 1% 1/4W	RN55C-1472-F	0008-0669
R1228	1 Resistor	MF 11.0 K 1% 1/4W	RN55C-1102-F	0008-0056
R1229	1 Resistor	CF 390 K 5% 1/4W	Amp. CR-25	0008-0012
R1230	1 Resistor	MF 61.9 K 1% 1/4W	RN55C-6182-F	0008-0069
R1231	1 Resistor	MF 392 1% 1/4W	RN55C-3920-F	0008-0043
R1232	1 Resistor	MF 31.6 K 1% 1/4W	RN55C-3162-F	0008-0062
R1233	1 Resistor	MF 17.8 K 1% 1/4W	RN55C-1782-F	0008-0332
R1234	1 Resistor	MF 1.1 K 1% 1/4W	RN55C-1101-F	0008-0050
R1235	1 Resistor	MF 174 K 1% 1/4W	RN55C-1743-F	0008-0671
R1236	1 Resistor	MF 8.25 K 1% 1/4W	RN55C-8251-F	0008-0329
R1237	1 Resistor	MF 19.1 K 1% 1/4W	RN55C-1912-F	0008-0641
R1238	1 Resistor	MF 4.75 K 1% 1/4W	RN55C-4751-F	0008-0227
R1239	1 Resistor	MF 6.81 K 1% 1/4W	RN55C-6811-F	0008-0321
R1240	1 Resistor	MF 11.0 K 1% 1/4W	RN55C-1102-F	0008-0056
R1241	1 Resistor	MF 15.0 K 1% 1/4W	RN55C-1502-F	0008-0346
R1242	1 Resistor	MF 3.01 K 1% 1/4W	RN55C-3011-F	0008-0299
R1243	1 Resistor	MF 33.2 K 1% 1/4W	RN55C-3322-F	0008-0286
R1244	1 Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1245	1 Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1246	1 Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1247	1 Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1248	1 Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1249	1 Resistor	CF 22 5% 1/4W	Amp. CR-25	0003-0234
R1250	1 Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234

SERIES A	
9202-7612	Page 3
OF	8

ITEM	QTY	DESIGNATION	ORDERING INFORMATION		STOCK NO.
			VALUE, SIZE, TOL	MANUFACTURER, NOTES	
R1251	1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1252	1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1253	1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1254	1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1255	1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1256	1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1257	1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1258	1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1259	1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1260	1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1261	1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
R1262	1	Resistor	MF 10.0 K 1% 1/4W	RN55C-1002-F	0008-0311
R1263	1	Resistor	MF 4.75 K 1% 1/4W	RN55C-4752-F	0008-0227
R1264	1	Resistor	MF 6.81 K 1% 1/4W	RN55C-6811-F	0008-0321
R1265	1	Resistor	MF 6.65 K 1% 1/4W	RN55C-6651-F	0008-0679
R1266	1	Resistor	MF 11.0 K 1% 1/4W	RN55C-1102-F	0008-0056
R1267	1	Resistor	MF 46.4 K 1% 1/4W	RN55C-4642-F	0008-0066
R1268	1	Resistor	MF 2.67 K 1% 1/4W	RN55C-2671-F	0008-0326
R1269	1	Resistor	MF 10 1% 1/4W	RN55D-10R0-F	0008-0598
R1270	1	Resistor	MF 100 K 1% 1/4W	RN55C-1003-F	0008-0340
R1271	1	Resistor	MF 10.0 K 1% 1/4W	RN55C-1002-F	0008-0311
R1272	1	Resistor	MF 1.0 K 1% 1/4W	RN55C-1001-F	0008-0225
R1273	1	Resistor	MF 1.3 K 1% 1/4W	RN55C-1301-F	0008-0262
R1274	1	Resistor	MF 1.18 K 1% 1/4W	RN55C-1181-F	0008-0328
R1275	1	Resistor	MF 825 1% 1/4W	RN55C-8250-F	0008-0355

1) May be changed at test.

SERIES A	
9202-7612	Page 4
OF	8

ITEM	QTY	DESIGNATION	ORDERING INFORMATION		STOCK NO.
			VALUE, SIZE, TOL	MANUFACTURER, NOTES	
C1201	1	Cap Tant	22 uF 10% 15V	Sprague	0032-0007
C1202	1	Cap Tant	22 uF 10% 15V	196D226X9015 KAI	0032-0007
C1203	1	Cap Cer	0.1 uF 10% 50V	CentraLab CW30C 104K	0002-0029
C1204	1	Cap Mica	6800 pF 2% 300V	ARCO DM19DC682G03	0002-0369
C1205	1	Cap Mica	6800 pF 2% 300V	DM19DC662G03	0002-0369
C1206	1	Cap Poly	0.1 uF 10% 100V	Stettner-Trush	0002-0376
C1207	1	Cap Poly	0.1 uF 100V	KP 1830-410/01	0002-0376
C1208	1	Cap Mica	6800 pF 2% 300V	ARCO DM19DC682G03	0002-0369
C1209	1	Cap Mica	560 pF 2% 300V	ARCO DM15DC561G03	0002-0361
C1210	1	Cap Mica	3300 pF 2% 500V	ARCO DM19DD332G03	0002-0366
C1211	1	Cap Mica	1300 pF 2% 500V	ARCO DM19DD132G03	0002-0387
C1212	1	Cap Mica	1800 pF 2% 500V	ARCO DM19DD182G03	0002-0363
C1213	1	Cap Mica	1580 pF 2% 500V	ARCO DM19DD1 2G03	0002-0388
C1214	1	Cap Mica	5600 pF 2% 300V	ARCO DM19DC562G03	0002-0368
C1215	1	Cap Mica	240 pF 2% 100V	ARCO DM10DA241G03	0002-0389
C1216	1	Cap Mica	2000 pF 2% 500V	ARCO DM19DD202G03	0002-0380
C1217	1	Cap Mica	910 pF 2% 300V	ARCO DM15DC911G03	0002-0370
C1218	1	Cap Mica	3900 pF 2% 300V	ARCO DM19DC392G03	0002-0390
C1219	1	Cap Mica	1100 pF 2% 300V	ARCO DM15DC112G03	0002-0391
C1220	1	Cap Mica	300 pF 2% 100V	ARCO DM10DA301G03	0002-0392
C1221	1	Cap Mica	2000 pF 2% 500V	ARCO DM19DD202G03	0002-0380
C1222	1	Cap Mica	3300 pF 2% 300V	ARCO DM19DC332G03	0002-0366
C1223	1	Cap Mica	360 pF 2% 100V	ARCO DM10DA361G03	0002-0372
C1224	1	Cap Poly	0.1 uF 10% 100V	Stettner-Trush	0002-0376
C1225	1	Cap Poly	0.1 uF 10% 100V	KP 1830-410/01	0002-0376

1) May be changed at test.

ITEM NO.	DESIGNATION	VALUE, SIZE, TOL.	MANUFACTURER NOTES	STOCK NO.
R1276	Resistor	MF 392 1% 1/4W	RN55C-3920-F	0008-0043
R1277	Resistor	MF 1.1 K 1% 1/4W	RN55C-1101-F	0008-0050
R1278	Resistor	CF 1.0 M 5% 1/4W	Amp. CR-25	0008-0292
R1279	Resistor			

2) Select at test.

ITEM ID	DESIGNATION	VALUE, SIZE, TC	MANUFACTURER	CON NO
C1226	Cap Poly	0.1 uF 10% 100V	Stettner-Trush KP 1830-410/01	0002-0376
C1227	Cap Poly	0.1 uF 10% 100V	KP 1830-410/01	0002-0376
C1228	Cap Poly	0.1 uF 10% 100V	KP 1830-410/01	0002-0376
C1229	Cap Mica	910 pF 2% 300V	ARCO DM15DC911G03	0002-0370
C1230	Cap Mica	680 pF 2% 300V	ARCO DM15DC681G03	0002-0393
C1231	Cap Mica	820 pF 2% 300V	ARCO DM15DC821G03	0002-0394
C1232	Cap Mica	360 pF 2% 100V	ARCO DM10DA361G03	0002-0372
C1233	Cap Mica	3000 pF 2% 300V	ARCO DM19DC302G03	0002-0395
C1234	Cap Cer	150 pF 2% N150	M/E 2222-631-1034151	0002-0011
C1235	Cap Cer	27 pF 2% NPO	M/E 2222-631-102279	0002-0220
C1236				
C1237	Cap Cer	39 pF 2% NPO	M/E 2222-631-10399	0002-0221
C1238	Cap Cer	180 pF 2% N750	M/E 2222-631-58181	0002-0299
C1239	Cap Cer	82 pF 2% NPO	M/E 2222-631-10829	0002-0055
C1240	Cap Cer	22 pF 2% NPO	M/E 2222-631-10229	0002-0051
C1241	Cap Cer	82 pF 2% NPO	M/E 2222-631-10829	0002-0055
C1242	Cap Cer	15 pF 2% NPO	M/E 2222-631-10159	0002-0049
C1243				2)
C1244	Cap Tant	22 uF 10V 15V	Sprague 196D226X9015 KAL	0032-0007
C1245	Cap Tant	22 uF 10% 15V	196D226X9015 KAL	0032-0007
C1246	Cap Tant	22 uF 10% 15V	196D226X9015 KAL	0032-0007
C1247	Cap Tant	22 uF 10% 15V	196D226X9015 KAL	0032-0007
C1248	Cap Tant	22 uF 10% 15V	196D226X9015 KAL	0032-0007
C1249	Cap Tant	22 uF 10% 15V	196D226X9015 KAL	0032-0007
C1250	Cap Tant	22 uF 10% 15V	196D226X9015 KAL	0032-0007

ITEM QTY		DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
C1251	1	Cap Tant	22 uF 10% 15V	Sprague 196D226X9015 KAI	0032-0007
C1252	1	Cap Tant	22 uF 10% 15V	196D226X9015 KAI	0032-0007
C1253	1	Cap Tant	22 uF 10% 15V	196D226X9015 KAI	0032-0007
C1254	1	Cap Tant	22 uF 10% 15V	196D226X9015 KAI	0032-0007
C1255	1	Cap Tant	22 uF 10% 15V	196D226X9015 KAI	0032-0007
C1256	1	Cap Tant	22 uF 10% 15V	196D226X9015 KAI	0032-0007
C1257	1	Cap Tant	22 uF 10% 15V	196D226X9015 KAI	0032-0007
C1258	1	Cap Tant	22 uF 10% 15V	196D226X9015 KAI	0032-0007
C1259	1	Cap Tant	22 uF 10% 15V	196D226X9015 KAI	0032-0007
C1260	1	Cap Tant	22 uF 10% 15V	196D226X9015 KAI	0032-0007
C1261	1	Cap Tant	22 uF 10% 15V	196D226X9015 KAI	0032-0007
C1262					
C1263	1	Cap Mica	10000 pF 2% 300V	ARCO DM20DC103603	0002-0396
C1264	1	Cap Cer	120 pF 2% NPO	M/E 2222-631-121	0002-0223
C1265	1	Cap Trim	3/15 pF Horiz	ERIE 538-011 D 3-15 20	0002-0397
C1266	1	Cap Mica	820 pF 2% 300V	ARCO DM15DC821G03	0002-0394
C1267	1	Cap Mica	910 pF 2% 300V	ARCO DM15DC911G03	0002-0370
C1268	1	Cap Cer	0.068 uF 10% 50V	Centralab CM20C 683 K	0002-0280
C1269	1	Cap Cer	8.2 pF .25% NPO	M/E 2222-631-09828	0002-0057
C1270	1	Cap Cer	22 pF 2% NPO	M/E 2222-631-10229	0002-0051
C1271	1				2)
C1272	1	Cap Cer	8.2 pF .25% NPO	M/E 2222-631-09828	0002-0057

2) Selectr at test.

ITEM QTY		DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
U1201	1	I.C.	J-FET Op-Amp 14p	National LF 347 N	0035-0314
U1202	1	I.C.	Dual-FET Op-Amp 8p	National LF 353 N	0035-0303
U1203	1	I.C.	Bi-FET Op-Amp 8p	National LF 355 BN	0035-0259
U1204	1	I.C.	Dual-FET Op-Amp 8p	National LF 353 N	0035-0303
U1205	1	I.C.	Bi-FET Op-Amp 8p	National LF 355 BN	0035-0259
U1206	1	I.C.	Dual-FET Op-Amp 8p	National LF 353 N	0035-0303
U1207	1	I.C.	Dual-FET Op-Amp 8p	National LF 353 N	0035-0303
U1208	1	I.C.	Bi-FET Op-Amp 8p	National LF 355 BN	0035-0259
U1209	1	I.C.	Dual-FET Op-Amp 8p	National LF 353 N	0035-0303
FL1201	1	Filter	Notch, 826 Hz	WGI 9202-9550-002	
S1201	1				
S1202	1				
S1203	1	Switch Assembly 55		WGI 9202-8006-007/5	
S1204	1				
S1205	1				
1		P.C. Board	Filter, drilled	WGI 9202-7012-02	
2		Socket Terminal Carrier		Augat 716 AG 2D	0034-0025
6		Receptical		Germ.Amp 380-598-1	0003-0202

3) 32 pins used per P.C. Board.

ITEM	QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO.
R1301	1	Resistor	MF 9.09 K 0.1% 1/4W	MF4C RN55C-9091-B	0008-0624
R1302	1	Resistor	MF 332 1% 1/4W	MF4C RN55C-3320-F	0008-0131
R1303	1	Var. Resist	100 Ttm Cerm Vert 25T	Bourns 3299W-1-101	0038-0079
R1304	1	Resistor	MF 121 1% 1/4W	MF4C RN55C-1210-F	0008-0623
R1305	1	Resistor	MF 9.09 K 0.1% 1/4W	RN55C-9091-B	0008-0624
R1306	1	Resistor	MF 1.01 K 0.1% 1/4W	RN55C-1011-B	0008-0625
R1307	1	Resistor	CF 1.0 M 5% 1/4W	Amp. CR-25	0008-0292
R1308	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1309	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1310	1	Resistor	MF 9.09 K 1% 1/4W	MF4C RN55C-9091-F	0008-0055
R1311	1	Resistor	MF 1.0 K 1% 1/4W	RN55C-1001-F	0008-0225
R1312	1	Resistor	MF 9.09 K 0.1% 1/4W	RN55C-9091-B	0008-0624
R1313	1	Resistor	MF 1.01 K 0.1% 1/4W	RN55C-1011-B	0008-0625
R1314	1	Resistor	CF 1.0 M 5% 1/4W	Amp. CR-25	0008-0292
R1315	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1316	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1317	1	Resistor	MF 9.09 K 1% 1/4W	MF4C RN55C-9091-F	0008-0055
R1318	1	Resistor	MF 1.0 K 1% 1/4W	RN55C-1001-F	0008-0225
R1319	1	Resistor	MF 9.09 K 0.1% 1/4W	RN55C-9091-B	0008-0624
R1320	1	Resistor	MF 1.01 K 0.1% 1/4W	RN55C-1011-B	0008-0625
R1321	1	Resistor	CF 1.0 M 5% 1/4W	Amp. CR-25	0008-0292
R1322	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1323	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1324	1	Resistor	MF 10 K 1% 1/4W	MF4C RN55C-1002-F	0008-0311
R1325	1	Resistor	MF 4.64 K 1% 1/4W	RN55C-4641-F	0008-0324

ITEM	QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO.
R1326	1	Resistor	MF 10.4 K 0.1% 1/4W	MF4C RN55C-1042-B	0008-0626
R1327	1	Resistor	MF 4.81 K 0.1% 1/4W	RN55C-4812-B	0008-0627
R1328	1	Resistor	CF 1.0 M 5% 1/4W	Amp. CR-25	0008-0292
R1329	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1330	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1331	1	Resistor	MF 10 K 1% 1/4W	MF4C RN55C-1002-F	0008-0311
R1332	1	Resistor	MF 5.11 K 1% 1/4W	RN55C-5111-F	0008-0347
R1333	1	Var. Resist	2 K 0.5W Cerm 25T	Bourns 3299X-1-202	0038-0137
R1334	1	Resistor	MF 3.92 K 0.1% 1/4W	MF4C RN55C-3921-B	0008-0628
R1335	1	Resistor	MF 2.46 K 0.1% 1/4W	RN55C-2461-B	0008-0629
R1336	1	Resistor	MF 4.22 K 0.1% 1/4W	RN55C-4221-B	0008-0630
R1337	1	Resistor	CF 1.0 M 5% 1/4W	Amp. CR-25	0008-0292
R1338	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1339	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1340	1	Resistor	MF 1.1 K 1% 1/4W	MF4C RN55C-1101-F	0008-0050
R1341	1	Resistor	MF 976 1% 1/4W	RN55C-9760-F	0008-0529
R1342	1	Resistor	MF 876 0.1% 1/4W	RN55C-8760-B	0008-0631
R1343	1	Resistor	CF 1.0 M 5% 1/4W	Amp. CR-25	0008-0292
R1344	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1345	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1346	1	Resistor	MF 9.09 K 1% 1/4W	MF4C RN55C-9091-F	0008-0055
R1347	1	Resistor	MF 2.21 K 1% 1/4W	MF4C RN55C-2211-F	0008-0356
R1348	1	Resistor	MF 5.62 K 1% 1/4W	RN55C-5621-F	0008-0297
R1349	1	Resistor	MF 17.8 K 1% 1/4W	RN55C-1782-F	0008-0332
R1350	1	Resistor	MF 17.8 K 1% 1/4W	RN55C-1782-F	0008-0332

SERIES A...	9202-7613
PAGE 3	OF 13

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL.	MANUFACTURER, NOTES	STOCK NO.
R1351 1	Resistor	MF 2.37 K 1% ½W	MF4C RN55C-2371-F	0008-0320
R1352 1	Resistor	MF 2.21 K 1% ½W	" RN55C-2211-F	0008-0356
R1353 1	Resistor	MF 2.37 K 1% ½W	" RN55C-2371-F	0008-0320
R1354 1	Resistor	MF 2.21 K 1% ½W	" RN55C-2211-F	0008-0356
R1355 1	Resistor	MF 22.1 K 1% ½W	" RN55C-2212-F	0008-0338
R1356 1	Resistor	MF 75.0 1% ½W	" RN55C-75P0-F	0008-0223
R1357	Resistor			
R1358 1	Resistor	CF 22 K 5% ½W	Amp. CR-25	0008-0187
R1359	Resistor			
R1360 1	Resistor	MF 22.1 K 1% ½W	" RN55C-2212-F	0008-0338
R1361 1	Resistor	MF 22.1 K 1% ½W	" RN55C-2212-F	00080338
R1362	Resistor			
R1363 1	Resistor	MF 11 K 1% ½W	" RN55C-1102-F	0008-0056
R1364	Resistor			
R1365	Resistor			
R1366	Resistor			
R1367 1	Resistor			
R1368				1)
R1369				1)
R1370 1	Resistor	MF 25.5 K 1% ½W	" RN55C-2552-F	0008-0622
R1371 1	Resistor	MF 10 K 1% ½W	" RN55C-1002-F	0008-0311
R1372 1	Resistor	MF 51.1 K 1% ½W	" RN55C-5112-F	0048-0067
R1373 1	Resistor	MF 1 K 1% ½W	" RN55C-1001-F	0008-0225
R1374 1	Resistor	MF 25.5 K 1% ½W	" RN55C-2552-B	0008-0622
R1375 1	Resistor	MF 150 K 0.1% ½W	" RN55C-1503-B	0008-0633

1) To be determined.

SERIES A...	9202-7613
PAGE 4	OF 13

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL.	MANUFACTURER, NOTES	STOCK NO.
R1376 1	Resistor	MF 34.4 K 0.1% ½W	MF4C RN55C-3442-B	0008-0634
R1377 1	Resistor	MF 14.7 K 0.1% ½W	" RN55C-1472-B	0008-0635
R1378 1	Resistor	MF 28.4 K 0.1% ½W	" RN55C-2842-B	0008-0636
R1379 1	Resistor	MF 4.02 K 0.1% ½W	" RN55C-4021-B	0008-0637
R1380 1	Resistor	CF 10 K 5% ½W	Amp. CR-25	0008-0185
R1381 1	Resistor	MF 750 K 0.1% ½W	MF4C RN55C-7503-B	0008-0638
R1382 1	Resistor	CF 10 K 5% ½W	Amp. CR-25	0008-0185
R1383 1	Resistor	MF 100 K 0.1% ½W	MF4C RN55C-1003-B	0008-0639
R1384 1	Resistor	MF 10.5 K 1% ½W	" RN55C-1052-F	0008-0640
R1385 1	Resistor	MF 33.2 K 1% ½W	" RN55C-3322-F	0008-0286
R1386 1	Resistor	MF 19.1 K 1% ½W	" RN55C-1912-F	0008-0641
R1387 1	Resistor	MF 8.25 K 1% ½W	" RN55C-8251-F	0008-0329
R1388 1	Resistor	CF 100 5% ½W	Amp. CR-25	0008-0172
R1389 1	Resistor	CF 100 5% ½W	Amp. CR-25	0008-0172
R1390 1	Var. Resist	500 Trim Cer™ 25T	Bourns 3299W-1-501	0008-0138
R1391 1	Var. Resist	25 K Trim Cer™ 25T	Bourns 3299W-1-253	0038-0115
R1392 1	Resistor	MF 470 K 1% ½W	MF4C RN55C-4703-F	0008-0642
R1393 1	Resistor	MF 255 1% ½W	" RN55C-2550-F	0008-0351
R1394 1	Resistor	MF 4.32 K 1% ½W	" RN55C-4321-F	0008-0327
R1395 1	Var. Resist	5 K Trim Cer™ 25T	Bourns 3299W-1-502	0038-0078
R1396 1	Resistor	MF 7.5 K 1% ½W	MF4C RN55C-7501-F	0008-0054
R1397 1	Resistor	MF 20 K 1% ½W	" RN55C-2002-F	0008-0337
R1398 1	Resistor	MF 4.99 K 1% ½W	" RN55C-4991-F	0008-0365
R1399 1	Resistor	CF 3.3 K 5% ½W	Amp. CR-25	0008-0179
R1400 1	Resistor	CF 100 5% ½W	Amp. CR-25	0008-0172

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
R13101 1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R13102 1	Resistor	CF 3.3 K 5% 1/4W	Amp. CR-25	0008-0179
R13103 1	Resistor	MF 11 K 1% 1/4W	MF4C RN55C-1102-F	0008-0056
R13104 1	Var. Resist	500 Trim Cer. 25T	Bourns 3299W-1-502	0038-0138
R13105 1	Resistor	MF 1.78 K 1% 1/4W	MF4C RN55C-1781-F	0008-0331
R13106 1	Resistor	MF 37.4 K 1% 1/4W	" RN55C-3742-F	0008-0643
R13107 1	Var. Resist	10 K Trim Cer. 25T	Bourns 3299W-1-103	0038-0018
R13108 1	Resistor	MF 100 K 1% 1/4W	MF4C RN55C-1003-F	0008-0340
R13109 1	Resistor	CF 51 K 5% 1/4W	Amp. CR-25	0008-0018
R13110 1	Resistor	CF 47 K 5% 1/4W	Amp. CR-25	0008-0190
R13111 1	Resistor	CF 150 5% 1/4W	Amp. CR-25	0008-0215
R13112 1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R13113 1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R13114 1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R13115				
R13116 1	Resistor	MF 25.5 K 1% 1/4W	MF4C RN55C-2552-B	0008-0652
R13117 1	Resistor	MF 51.1 K 0.1% 1/4W	" RN55C-5112-B	0008-0644
R13118 1	Resistor	MF 7.15 K 0.1% 1/4W	" RN55C-7151-B	0008-0563
R13119 1	Resistor	CF 3.3 K 5% 1/4W	Amp. CR-25	0008-0179
R13120 1	Resistor	CF 1.0 M 5% 1/4W	Amp. CR-25	0008-0292
R13121 1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R13122 1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R13123 1	Resistor	Zero ohm Jumper	Tevis WL-40	0008-0612
R13124 1	Resistor	Zero ohm Jumper	Tevis WL-40	0008-0612
R13125 1	Resistor	Zero ohm Jumper	Tevis WL-40	0008-0612

SERIES A...
PAGE 5
9202-7613
OF 13

11

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
R13126	Resistor			
R13127	Resistor			
R13128	Resistor			
R13129	Resistor			
R13130	Resistor			
R13131	Resistor			
R13132	Resistor			
R13133 1	Resistor	CF 270 5% 1/4W	Amp. CR-25	0008-0173
R13134 1	Resistor	MF 2.67 K 1% 1/4W	MF4C RN55C-2671-F	0008-0336
R13135 1	Resistor	MF 1.78 K 1% 1/4W	" RN55C-1781-F	0008-0331
R13136 1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R13137 1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R13138 1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R13139 1	Resistor	MF 9.09 K 1% 1/4W	MF4C RN55C-9091-F	0008-0055
R13140 1	Resistor	MF 1.0 K 1% 1/4W	" RN55C-1001-F	0008-0225
R13141 1	Resistor	MF 23.7 K 1% 1/4W	" RN55C-2372-F	0008-0059
R13142 1	Resistor	MF 15.8 K 1% 1/4W	" RN55C-1582-F	0008-0058
R13143 1	Resistor	MF 681 1% 1/4W	" RN6810-F	0008-0047
R13144 1	Resistor	CF 5.6 K 5% 1/4W	Amp. CR-25	0008-0375
R13145 1	Resistor	CF 4.7 K 5% 1/4W	Amp. CR-25	0008-0182
R13146 1	Resistor			
R13147 1	Resistor	MF 158 K 1% 1/4W	MF4C RN55C-1583-F	0008-0666
R13148 1	Resistor	MF 22.1 K 1% 1/4W	" RN55C-2212-F	0008-0338
R13149 1	Resistor	CF 180 K 5% 1/4W	Amp. CR-25	0008-0195
R13150 1	Resistor	CF 82 K 5% 1/4W	Amp. CR-25	0008-0193

SERIES A...
PAGE 6
9202-7613
OF 13

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL			MANUFACTURER, NOTES			STOCK NO
R13151 1	Resistor	MF	200	1% $\frac{1}{4}$ W	ME4C RN55C-2000-F			0008-0036
R13152 1	Resistor	MF	32.4 K	1% $\frac{1}{4}$ W	" RN55C-3242-F			0008-0308
R13153 1	Resistor	MF	32.4 K	1% $\frac{1}{4}$ W	" RN55C-3242-F			0008-0308
R13154 1	Resistor	MF	22.1 K	1% $\frac{1}{4}$ W	" RN55C-2212-F			0008-0338
R13155 1	Resistor	MF	2.0 K	1% $\frac{1}{4}$ W	ME4C RN55C-2001-F			0008 0360
R13156 1	Resistor	MF	1.78 K	1% $\frac{1}{4}$ W	" RN55C-1781-F			0008-0331
R13157 1	Resistor	MF	357	1% $\frac{1}{4}$ W	" RN55C-3570-F			0008-0042
R13158 1	Resistor	MF	200 K	1% $\frac{1}{4}$ W	" RN55C-2003-F			0008-0316
R13159 1	Resistor	CF	330	5% $\frac{1}{4}$ W	Amp. CR-25			0008-0242
R13160 1	Resistor		Zero ohm Jumper		Tevis WL-40			0008-0612

SERIES A...	9202-7613	PAGE 7	OF 13
-------------	-----------	--------	-------

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL			MANUFACTURER, NOTES			STOCK NO
C1301 1	Cap Tant	22	uF	10%	15V	Sprague	196D226X9015 KAI	0032-0007
C1302 1	Cap Tant	22	uF	10%	15V	196D2269015 KAI		0032-0007
C1303 1	Cap Cer	27	pF	2%	NPO	M/E 2222-631-10279		0002-0220
C1304 1	Cap Tant	22	uF	10%	15V	Sprague	196D226X9015 KAI	0032-0007
C1305 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1306 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1307 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1308 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1309 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1310 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1311 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1312 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1313 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1314 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1315 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1316 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1317 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1318 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1319 1	Cap Tant	22	uF	10%	15V	196D226X9015 KAI		0032-0007
C1320 1	Cap Cer	39	pF	2%	NPO	M/E 2222-631-10399		0002-0221
C1321 1	Cap Cer	120	pF	2%	NPO	M/E 2222-631-10121		0002-0223
C1322 1	Cap Tant	6.8	uF	10%	35V	Sprague	196D685X9035 KAI	0032-0086
C1323 1	Cap Tant	6.8	uF	10%	35V	196D685X9025 KAI		0032-0086
C1324 1								
C1325 1	Cap Tant	22	uF	10%	15V	Sprague	196D226X9015 KAI	0032-0007

SERIES A...	9202-7613	PAGE 8	OF 13
-------------	-----------	--------	-------

ITEM QTY	DESIGNATION	ORDERING INFORMATION		STOCK NO
		VALUE, SIZE, TOL	MANUFACTURER, NOTES	
C1326				
C1327				
C1328				
C1329				
C1330				
C1331				
C1332	1 Cap Tant	3.3 uF 10%	Sprague 196D335X9035 JAI	0032-0091
C1333	1 Cap Tant	3.3 uF 10%	196D335X9035 JAI	0032-0091
C1334	1 Cap Tant	4.7 uF 10%	196D475X9035 JAI	0032-0109
C1335	1 Cap Cer	0.0022 uF 10%	Centralab CW15C222 K	0002-0273
C1336	1 Cap Mica	560 pF 2%	ARCO DM15DC511G03	0002-0361
C1337	1 Cap Cer	56 pF 2%	M/E 2222-631-10569	0002-0222
C1338	1 Cap Tant	22 uF 10%	Sprague 196D226X9015 KAI	0032-0007
C1339	1 Cap Tant	22 uF 10%	196D226X9015 KAI	0032-0007
C1340	1 Cap Tant	6.8 uF 10%	196D685X9035 KAI	0032-0086
C1341	1 Cap Tant	6.8 uF 10%	196D685X9035 KAI	0032-0086
C1342	1 Cap Cer	0.1 uF 20%	RE 50-104 M	0002-0377
C1343	1 Cap Cer	0.1 uF 20%	RE 50-104 M	0002-0377
C1344	1 Cap Tant	22 uF 10%	Sprague 196D226X9015 KAI	0032-0007
C1345	1 Cap Tant	22 uF 10%	196D226X9015 KAI	0032-0007
C1346	1 Cap Cer	56 pF 2%	NPO	0002-0222
C1347	1 Cap Polycarb	1.0 uF 5%	ERC MKC 1860-510/06	0002-0295
C1348	1 Cap Cer	0.1 uF 10%	Centralab CW30C104 K	0002-0029
C1349	1 Cap Cer	0.22 uF 20%	Centralab CW30C224 K	0002-0378
C1350	1 Cap Cer	0.0015 uF 10%	Centralab CW15C152 K	0002-0285

ITEM QTY	DESIGNATION	ORDERING INFORMATION		STOCK NO
		VALUE, SIZE, TOL	MANUFACTURER, NOTES	
C1351	1 Cap Tant	6.8 uF 10%	Sprague 196D685X9035 KAI	0032-0086
C1352	1 Cap Tant	6.8 uF 10%	196D685X9035 KAI	0032-0086
C1353				
C1354				
C1355	1 Cap Cer	15 pF 2%	M/E 2222-631-10159	0002-0049
C1356	1 Cap Cer	0.22 uF 10%	Centralab CW30C224 K	0002-0263
C1357	1 Cap Cer	0.1 uF 10%	Centralab CW30C104 K	0002-0029
C1358	1 Cap Cer	18 pF 2%	M/E 2222-631-1	0002-0338
C1359	1 Cap Cer	0.1 uF 10%	Centralab CW30C104 K	0002-0029
C1360	1 Cap Tant	22 uF 10%	Sprague 196D226X9015 KAI	0032-0007
C1361	1 Cap Tant	22 uF 10%	196D226X9015 KAI	0032-0007
C1362	1 Cap Tant	22 uF 10%	Sprague 196D226X9015 KAI	0032-0007
C1363	1 Cap Tant	22 uF 10%	196D226X9015 KAI	0032-0007
C1364				
C1365	1 Cap Cer	0.0033 uF 10%	Centralab CW15C332 K	0002-0272
C1366	1 Cap Cer	0.0082 uF 10%	Centralab CW15C822 K	0002-0282
C1367	1 Cap Tant	22 uF 10%	Sprague 196D226X9015 KAI	0032-0007
C1370	1 Cap Tant	22 uF 10%	198D226X9015 KAI	0032-0007
U1301	1 I.C.		Harris HI1-201-5	0035-0258
U1302	1 I.C.		Nat. LF 357 BN	0035-0302
U1303	1 I.C.		Harris HI2-200-5	0035-0230
U1304	1 I.C.		Nat. LF 357 BN	0035-0302
U1305	1 I.C.		Harris HI2-200-5	0035-0230
U1306	1 I.C.		Nat. LF 356 N	0035-0325
U1307	1 I.C.		Harris HI2-200-5	0035-0230

ITEM QTY	DESIGNATION	ORDERING INFORMATION			STOCK NO.
		VALUE, SIZE, TOL.	MANUFACTURER, NOTES		
U1308 1	I.C.	J FET Op-Amp	Nat. LF 356 N	0035-0325	
U1309 1	I.C.	MUX CMOS	Motorola MC 14051 BCP	0035-0228	
U1310 1	I.C.	J FET Op-Amp	Nat. LF 355 BN	0035-0259	
U1311 1	I.C.	MUX CMOS	Motorola MC 14051 BCP	0035-0228	
U1312 1	I.C.	J FET Dual Op-Amp	Nat. LF 353 N	0035-0303	
U1313 1	I.C.	J FET Op-Amp	Nat. LF 356 BN	0035-0325	
U1314 1	I.C.	J FET Op-Amp	Nat. LF 347 N	0035-0314	
U1315 1	I.C.	Quad SPST CMOS	Harria HI 1-201-5	0035-0258	
U1316 1	I.C.	Quad 2-Input NAND CMOS	Motorola MC 14011 BCP	0035-0186	
U1317 1	I.C.	J FET Op-Amp	Nat. LF 355 BN	0035-0259	
U1319 1	I.C.	RMS-DC Converter	AD 536 AJH	0035-0327	
U1319 1	I.C.	Quad Comparator	Nat. LM 339N	0035-0167	
U1320 1	I.C.	J FET Op-Amp	Nat. LF 355 BN	0035-0259	
U1321 1	I.C.	Op-Amp	RCA CA 3130	0035-0268	
U1322 1	I.C.	Dual Mono-Flip CMOS	Motorola MC 14538 BCP	0035-0328	
U1323 1	I.C.	Up/Down Count CMOS	Motorola MC 14510 BCP	0035-0278	
U1324 1	I.C.	Up/Down Count CMOS	Motorola MC 14510 BCP	0035-0278	
U1325 1	I.C.	Quad 2-Input NAND CMOS	Motorola MC 14011 BCP	0035-0186	
U1326 1	I.C.	Hex Inverter CMOS	Motorola MC 14049 BCP	0035-0179	
U1327 1	I.C.	Quad 2-Input NOR CMOS	Motorola MC 14001 BCP	0035-0169	
U1328 1	I.C.	Quad 2-Input NOR CMOS	Motorola MC 14001 BCP	0035-0189	
U1329 1	I.C.	J FET Dual	Nat. LF 353 N	0035-0303	
U1330 1	I.C.	DPDT Dual	Harria HI 1-5043-5	0035-0316	
U1331 1	I.C.	SPST CMOS	Harria HI 2-200-5	0035-0230	
U1332 1	I.C.	J FET Op-Amp	Nat. LF 355 BN	0035-0259	

SERIES A...	9202-7613	OF 13
-------------	-----------	-------

ITEM QTY	DESIGNATION	ORDERING INFORMATION			STOCK NO.
		VALUE, SIZE, TOL.	MANUFACTURER, NOTES		
CR1301 1	Diode	Hot Carrier	HP 5082-2800	0037-0018	
CR1302 1	Diode	Hot Carrier	HP 5082-2800	0037-0018	
CR1303 1	Diode	Switching 1N 4448	Jedec	0037-0001	
CR1304 1	Diode	Switching 1N 4448	Jedec	0037-0001	
CR1305 1	Diode	Switching 1N 4448	Jedec	0037-0001	
CR1306 1	Diode	Switching 1N 4448	Jedec	0037-0001	
CR1307 1	Diode	Switching 1N 4448	Jedec	0037-0001	
CR1308 1	Diode	Switching 1N 4448	Jedec	0037-0001	
CR1309 1	Diode	Switching 1N 4448	Jedec	0037-0001	
CR1310 1	Diode	Hot Carrier	HP 5082-2800	0037-0018	
CR1311 1	Diode	Hot Carrier	HP 5082-2800	0037-0018	
VR1301 1	Zener Diode	Voltage Ref.	National LM 329 BZ	0037-0201	

SERIES A...	9202-7613	PAGE 12
-------------	-----------	---------

ITEM	QTY	DESIGNATION	ORDERING INFORMATION			STOCK NO.
			VALUE, SIZE, TOL	MANUFACTURER, NOTES		
12						
13	1	Shield Assembly	WGI 9202-7003-043/B			
14	4	Screw	M 3x5mm Cyl Crsl	ZLK 1875 A	0005-0200	
15	4	Washer	M 3 Flat		0005-0274	
16						
S1301	1					
S1302	1	Switch Assembly 4 S	WGI 9202-8003-00/B			
S1303	1					
S1304	1					
S1305	1	Switch 1 S	WGI 9202-8004-00/B			
TP 1-TP 3	3	Rivet	Testpoint	WGR 00-3000.19/5	0003-0274	
1	1	P.C. Board	A / D drilled	WGI 9202-7003-02		
2	6	Spacer	Switch,	WGI 9202-0100-07/A		
3	4	Mtg. Pad	10 pin (T0-100)	Milton Ross 10311 DAP	0028-0155	
4	1	Mtg. Pad	8 pin I.C.	Thermalloy 7717-8 DAP	0028-0128	
5	1	Socket Terminal Carrier (E1...E7)	Augat 716 AG 2D		0034-0025	
6	2	Handle	P.C. Board gy	WGR 00-3705.55/4	0028-0112	
7	4	Rivet	f. Handle	WGR 5 W 32/3/0	0005-0021	
8						
9	1	Label	Signal Triangle	WGR 0000-7575.994	0021-0029	
10						
11						

1) 7 Terminals used per P.C. Board.

SERIES A...	9200-7613	PAGE 13	OF 13
-------------	-----------	---------	-------

ITEM QTY	DESIGNATION	ORDERING INFORMATION		STOCK NO
		VALUE, SIZE, TOL	MANUFACTURER, NOTES	
R1401 1	Resistor	CF 3.3 K 5% 1/4W	Amp. CR-25	0008-0179
R1402 1	Resistor	CF 680 K 5% 1/4W	Amp. CR-25	0008-0246
R1403 1	Resistor	CF 150 K 5% 1/4W	Amp. CR-25	0008-0196
R1404 1	Resistor	CF 2.2 K 5% 1/4W	Amp. CR-25	0008-0216
R1405 1	Resistor	CF 2.2 K 5% 1/4W	Amp. CR-25	0008-0216
R1406 1	Resistor	CF 10 K 5% 1/4W	Amp. CR-25	0008-0185
R1407 1	Resistor	CF 39 K 5% 1/4W	Amp. CR-25	0008-0016
R1408 1	Resistor	CF 560 5% 1/4W	Amp. CR-25	0008-0250
R1409 1	Resistor	CF 82 K 5% 1/4W	Amp. CR-25	0008-0193
R1410 1	Resistor	CF 6.8 K 5% 1/4W	Amp. CR-25	0008-0291
R1411 1	Resistor	MF 46.4 K 1% 1/4W	MF4C RN55C-46420F	0008-0066
R1412 1	Resistor	CF 1.0 M 5% 1/4W	Amp. CR-25	0008-0292
R1413 1	Resistor	MF 100 K 1% 1/4W	MF4C RN55C-1003-F	0008-0340
R1414 1	Resistor	CF 4.7 K 5% 1/4W	Amp. CR-25	0008-0182
R1415 1	Resistor	CF 10 K 5% 1/4W	Amp. CR-25	0008-0185
R1416	Resistor			
R1417 1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1416 1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1419 1	Resistor	CF 390 5% 1/4W	Amp. CR-25	0008-0208
R1420 1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1421 1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1422 1	Resistor	MF 11 K 1% 1/4W	MF4C RN55C-1102-F	0008-0056
R1423 1	Resistor	MF 100 K 1% 1/4W	MF4C RN55C-1003-F	0008-0340
R1424 1	Resistor	CF 3.9 M 5% 1/4W	Amp. CR-25	0008-0483
R1425 1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194

SERIES A...	9202-7614
PAGE 1	CF 6

ITEM QTY	DESIGNATION	ORDERING INFORMATION		STOCK NO
		VALUE, SIZE, TOL	MANUFACTURER, NOTES	
R1426 1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1427 1	Resistor	CF 470 K 5% 1/4W	Amp. CR-25	0008-0206
R1428 1	Resistor	CF 12 K 5% 1/4W	Amp. CR-25	0008-0184
R1429 1	Resistor	CF 2.7 K 5% 1/4W	Amp. CR-25	0008-0213
R1430 1	Resistor	CF 330 K 5% 1/4W	Amp. CR-25	0008-0403
C1401 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1402 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1403 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1404				
C1405				
C1406 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1407 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1408 1	Cap Cer	100 pF 2% NPO	M/E 2222-631-10101	0002-0010
C1409 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1410 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1411 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1412 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1413 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1414 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1415 1	Cap Cer	0.01 uF 10% 50V	Centralab CW15C103 K	0002-0270
C1416 1	Cap Tant	1.0 uF 10% 35V	Sprague 16D105X9035 HA1	0002-0092
C1417 1	Cap Cer	0.1 uF 10% 50V	Centralab CW30C104 K	0002-0029

SERIES A...	9202-7614
PAGE 2	OF 6

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO.
C1418	1	Cap Cer	22 PF 2% NPO	M/E 2222-631-10229
C1419	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1420	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1421	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1422	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1423	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1424	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1425	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1426	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1427	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1428	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1429	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1430	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1431	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1432	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1433	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1434	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1435	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1436	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1437	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1438	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1439	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1440	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1441	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1442	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO.
C1443	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1444	1	Cap Cer	0.01 uF 10% 50V	Centralab CM15C103 K
C1445	1	Cap Cer	18 PF 2% NPO	M/E 2222-631-10189
U1401	1	I.C.	Quad Comparator	Nat. LM 339 N
U1402	1	I.C.	Phase Lock Loop	Motorola MC 14046 BCP
U1403	1	I.C.	4-Bit Decade Count	Nat. MM 74C90 N
U1404	1	I.C.	Quad Exclusive OR	Motorola MC 14070 BCP
U1405		I.C.		
U1406	1	I.C.	BCD to 7 Segm. Driv	Motorola MC 14543 BCP
U1407	1	I.C.	BCD to 7 Segm. Driv	Motorola MC 14543 BCP
U1408	1	I.C.	BCD to 7 Segm. Driv	Motorola MC 14543 BCP
U1409	1	I.C.	Voltage Detector	Intersil ILC 8211CPA
U1410	1	I.C.	Quad Ex OR	Motorola MC 14070 BCP
U1411	1	I.C.	Hex Invert Buffer	Motorola MC 14049 BCP
U1412	1	I.C.	Quad 2-Input AND	Motorola MC 14081 BCP
U1413	1	I.C.	NBCD Adder	Motorola MC 14560 BCP
U1414	1	I.C.	NBCD Adder	Motorola MC 14560 BCP
U1415	1	I.C.	NBCD Adder	Motorola MC 14560 BCP
U1416	1	I.C.	Voltage Detector	Intersil ILC 8212 CPA
U1417	1	I.C.	Triple 3-Input NAND	Motorola MC 14023 BCP
U1418	1	I.C.	Hex Invert Buffer	Motorola MC 14049 BCP

ITEM	QTY	DESIGNATION	VALUE, SIZE, TOL.	MANUFACTURER, NOTES	STOCK NO.
U1419	1	I.C.	Dual D F-F	Motorola MC 14013 BCP	0035-0182
U1420	1	I.C.	Quad 2-Inp NOR	Motorola MC 14001 BCP	0035-0189
U1421	1	I.C.	Decade Count Divide	Motorola MC 14017 BCP	0035-0110
U1422	1	I.C.	Hex Invert Buffer	Motorola MC 14049 BCP	0035-0179
U1423	1	I.C.	9's Complementer	Motorola MC 14561 BCP	0035-0319
U1424	1	I.C.	9's Complementer	Motorola MC 14561 BCP	0035-0319
U1425	1	I.C.	9's Complementer	Motorola MC 14561 BCP	0035-0319
U1426	1	I.C.	14 Stage Counter	Motorola MC 14040 BCP	0035-0262
U1427	1	I.C.	Dual 4-Inp NAND	Motorola MC 14012 BCP	0035-0123
U1428	1	I.C.	7 stage Counter	Motorola MC 14024 BCP	0035-0111
U1429	1	I.C.	Quad 2-Inp AND	Motorola MC 14081 BCP	0035-0181
U1430	1	I.C.	Dual J-K F-F	Motorola MC 14027 BCP	0035-0112
U1431	1	I.C.	Dual J-K F-F	Motorola MC 14027 BCP	0035-0112
U1432	1	I.C.	Triple 3-Inp NOR	Motorola MC 14025 BCP	0035-0320
U1433	1	I.C.	NBCD Adder	Motorola MC 14560 BCP	0035-0256
U1434	1	I.C.	NBCD Adder	Motorola MC 14560 BCP	0035-0256
U1435	1	I.C.	Dual Up-Counter	Motorola MC 14518 BCP	0035-0107
U1436	1	I.C.	Dual D F-F	Motorola MC 14013 BCP	0035-0182
U1437	1	I.C.	7 Stage Counter	Motorola MC 14024 BCP	0035-0111
U1438	1	I.C.	Quad 2-Inp NOR	Motorola MC 14001 BCP	0035-0189
U1439	1	I.C.	Triple 3-Inp NOR	Motorola MC 14025 BCP	0035-0320
U1440	1	I.C.	Quad 2-Inp NOR	Motorola MC 14001 BCP	0035-0189
U1441	1	I.C.	Quad Exclusive OR	Motorola MC 14070 BCP	0035-0318
U1442		I.C.			
U1443	1	I.C.	Quad 2 Inp AND	Motorola MC 14081 BCP	0035-0181

ITEM	QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO.
U1444	1	I.C.	3 Imp.	Motorola MC 14075 BCP	0035-0335
U1445	1	I.C.	Hex Type-D F-F	Motorola MC 14174BCP	0035-0309
Q1401	1	Transistor	BYC-59 D NPN	NCS BCY 59 D	0010-0184
VR1401	1	Zener Diode	Reference 10-92	Nat. LM 329 BZ	0037-0201
J1401	1	Socket	40 pin I.C. DIP	Augat 540 AG 37D	0034-0027
D1402	1	Socket	16 pin I.C. DIP	Augat 516 AG-37 F	0034-0023
P1402	1	Jumper Plug	Dual In-Line 16 pin	CA-16 NW	0003-0351
	1	Cover	F. Jumper Plug	CA-16-400-000	0003-0351
I	1	P.C. Board	Arith., drilled	WGI 9202-7004-02	
2	2	Handle	P.C. Board gy	WGR 00-3705.55/4	0028-0112
3	4	Rivet	F. Handle	WGR 5 WN 33/3/0	0005-0021
4	1	Label	Signal Triangle	WGR 0000-7575.994	0021-0029

ITEM	QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
R1501	1	Resistor	CF 56 5% 1/4W	Amp. CR-25	0008-0239
R1502	1	Resistor	CF 3.3 M 5% 1/4W	Amp. CR-25	0008-0575
R1503	1	Resistor	CF 2.2 K 5% 1/4W	Amp. CR-25	0008-0216
R1504	1	Resistor	CF 150 K 5% 1/4W	Amp. CR-25	0008-0196
R1505	1	Resistor	CF 560 K 5% 1/4W	Amp. CR-25	0008-0210
R1506	1	Resistor	CF 220 K 5% 1/4W	Amp. CR-25	0008-0251
R1507	1	Resistor	MF 30.1 K 1% 1/4W	MF4C RN55C-3012-F	0008-0061
R1508	1	Resistor	MF 3.57 K 1% 1/4W	" RN55C-3571-F	0008-0053
R1509	1	Resistor	CF 22 K 5% 1/4W	Amp. CR-25	0008-0187
R1510	1	Resistor	CF 33 K 5% 1/4W	Amp. CR-25	0008-0249
R1511	1	Resistor	CF 33 K 5% 1/4W	Amp. CR-25	0008-0249
R1512	1	Resistor	CF 6.8 K 5% 1/4W	Amp. CR-25	0008-0291
R1513	1	Resistor	CF 33 K 5% 1/4W	Amp. CR-25	0008-0249
R1514	1	Resistor	CF 22 K 5% 1/4W	Amp. CR-25	0008-0187
R1515	1	Resistor	CF 56 5% 1/4W	Amp. CR-25	0008-0239
R1516	1	Resistor	CF 10 K 5% 1/4W	Amp. CR-25	0008-0185
R1517	1	Resistor	CF 10 K 5% 1/4W	Amp. CR-25	0008-0185
R1518	1	Resistor	CF 150 K 5% 1/4W	Amp. CR-25	0008-0196
R1519	1	Resistor	MF 15.8 K 1% 1/4W	MF4C RN55C-1582-F	0008-0058
R1520	1	Resistor	MF 10 K 1% 1/4W	" RN55C-1002-F	0008-0311
R1521	1	Resistor	MF 20 K 1% 1/4W	" RN55C-2002-F	0008-0337
R1522	1	Resistor	MF 15.8 K 1% 1/4W	" RN55C-1582-F	0008-0058
R1523	1	Resistor	MF 10 K 1% 1/4W	" RN55C-1002-F	0008-0311
R1524	1	Resistor	MF 20 K 1% 1/4W	" RN55C-2002-F	0008-0337
R1525	1	Resistor	MF 15.8 K 1% 1/4W	" RN55C-1582-F	0008-0058

SERIES A...	9202-7615	PAGE 2	OF 8
-------------	-----------	--------	------

ITEM	QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
R1526	1	Resistor	MF 10 K 1% 1/4W	MF4C RN55C-1002-F	0008-0311
R1527	1	Resistor	MF 20 K 1% 1/4W	" RN55C-2002-F	0008-0337
R1528	1	Resistor	MF 15.8 K 1% 1/4W	" RN55C-1582-F	0008-0058
R1529	1	Resistor	MF 10 K 1% 1/4W	" RN55C-1002-F	0008-0311
R1530	1	Resistor	MF 20 K 1% 1/4W	" RN55C-2002-F	0008-0337
R1531	1	Resistor	CF 75 K 5% 1/4W	Amp. CR-25	0008-0020
R1532	1	Var. Resist	22 K Cer. Horiz. 1/2W	WV 17 1/2	0038-0089
R1533	1	Resistor	CF 82 K 5% 1/4W	Amp. CR-25	0008-0193
R1534	1	Resistor	CF 1.0 M 5% 1/4W	Amp. CR-25	0008-0292
R1535	1	Resistor	MF 5.62 K 0.1% 1/4W	MF4C RN55C-5621-B	0008-0562
R1536	1	Resistor	CF 10 K 5% 1/4W	Amp. CR-25	0008-0185
R1537	1	Resistor	MF 5.62 K 0.1% 1/4W	MF4C RN55C-5621-B	0008-0562
R1538	1	Resistor	CF 470 5% 1/4W	Amp. CR-25	0008-0174
R1539	1	Resistor	CF 22 K 5% 1/4W	Amp. CR-25	0008-0187
R1540	1	Resistor	CF 3.9 K 5% 1/4W	Amp. CR-25	0008-0181
R1541	1	Resistor	CF 4.7 K 5% 1/4W	Amp. CR-25	0008-0182
R1542	1	Resistor	MF 2.37 K 1% 1/4W	MF4C RN55C-2371-F	0008-0320
R1543	1	Resistor	MF 30.1 K 1% 1/4W	" RN55C-3012-F	0008-0061
R1544	1	Resistor	MF 4.32 K 1% 1/4W	" RN55C-4321-F	0008-0327
R1545	1	Resistor	MF 17.8 K 1% 1/4W	" RN55C-1782-F	0008-0332
R1546	1	Resistor	MF 6.19 K 1% 1/4W	" RN55C-6191-F	0008-0326
R1547	1	Resistor	MF 11.8 K 1% 1/4W	" RN55C-1182-F	0008-0057
R1548	1	Resistor	MF 10.7 K 1% 1/4W	" RN55C-1072-F	0008-0509
R1549	1	Resistor	MF 26.7 K 1% 1/4W	" RN55C-2672-F	0008-0060
R1550	1	Resistor	CF 15 5% 1/4W	Amp. CR-25	0008-0001

SERIES A...	9202-7615	PAGE 2	OF 8
-------------	-----------	--------	------

ITEM	QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO.
R1551	1	Resistor	CF 15 5% 1/4W	Amp. CR-25	0008-0001
R1552	1	Resistor	CF 15 5% 1/4W	Amp. CR-25	0008-0001
R1553	1	Resistor	CF 15 5% 1/4W	Amp. CR-25	0008-0001
R1554	1	Resistor	CF 10 K 5% 1/4W	Amp. CR-25	0008-0185
R1555	1	Resistor	CF 470 K 5% 1/4W	Amp. CR-25	0008-0206
R1556	1	Resistor	CF 3.3 K 5% 1/4W	Amp. CR-25	0008-0179
R1557	1	Resistor	CF 470 K 5% 1/4W	Amp. CR-25	0008-0206
R1558	1	Resistor	CF 3.3 M 5% 1/4W	Amp. CR-25	0008-0575
R1559	1	Var. Resist	22 K Horiz Cerm 0.5W	W 17/2/8	0038-0089
R1560	1	Resistor	CF 1.8 K 5% 1/4W	Amp. CR-25	0008-0244
R1561	1	Resistor	CF 1.8 K 5% 1/4W	Amp. CR-25	0008-0244
R1562	1	Resistor	CF 22 K 5% 1/4W	Amp. CR-25	0008-0187
R1563	1	Resistor	CF 22 K 5% 1/4W	Amp. CR-25	0008-0187
R1564	1	Resistor	CF 10 K 5% 1/4W	Amp. CR-25	0008-0185
R1565	1	Resistor	CF 2.7 K 5% 1/4W	Amp. CR-25	0008-0213
R1566	1	Resistor	CF 33 K 5% 1/4W	Amp. CR-25	0008-0249
R1567	1	Resistor	CF 10 K 5% 1/4W	Amp. CR-25	0008-0185
R1568	1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1569	1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1570	1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1571	1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1572	1	Resistor	CF 100 5% 1/4W	Amp. CR-25	0008-0172
R1573	1	Resistor	Zero ohm Jumper	Tevis WL-40	0008-0612
R1574	1	Resistor	Zero ohm Jumper	Tevis WL-40	0008-0612
R1575	1	Resistor	Zero ohm Jumper	Tevis WL-40	0008-0612

SERIES A...	9202-7615	PAGE 3	OF 8
-------------	-----------	--------	------

ITEM	QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO.
R1576	1	Resistor	Zero ohm Jumper	Tevis WL-40	0008-0612
R1577	1	Resistor	Zero ohm Jumper	Tevis WL-40	0008-0612
R1378	1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1379	1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1380	1	Resistor	CF 100 K 5% 1/4W	Amp. CR-25	0008-0194
R1381	1	Resistor	CF 1.0 K 5% 1/4W	Amp. CR-25	0008-0203
C1501	1	Cap Cer	10 pF 2% NPO	M/E 2222-631-10109	0002-0047
C1502					
C1503	1	Cap Cer	47 pF 2% NPO	M/E 2222-631-10479	0002-0053
C1504	1	Cap Tant	6.8 uF 10% 35V	Sprague 196D685-X9035 KAJ	0002-0086
C1505	1	Cap Cer	47 pF 2% NPO	M/E 2222-631-10479	0002-0053
C1506	1	Cap Tant	22 uF 10% 15V	Sprague 196D226X9015 KAJ	0032-0007
C1507	1	Cap Cer	22 pF 2% NPO	M/E 2222-631-10229	0002-0051
C1508	1	Cap Cer	82 pF 2% NPO	M/E 2222-631-10829	0002-0055
C1509	1	Cap Cer	0.22 uF 10% 50V	Centralab CW30C224 K	0002-0263
C1510	1	Cap Cer	0.22 uF 10% 50V	Centralab CW30C224 K	0002-0263
C1511	1	Cap Cer	0.22 uF 10% 50V	Centralab CW30C224 K	0002-0263
C1512	1	Cap Tant	22 uF 10% 15V	Sprague 196D226X9015 KAJ	0032-0007
C1513	1	Cap Tant	1.0 uF 10% 35V	196D105X9035 HAJ	0032-00092
C1514	1	Cap Mica	1200 pF 2% 300V	ARCO DM15DC122G03	0002-0373
C1515	1	Cap Tant	6.8 uF 10% 35V	Sprague 196D685X9035 KAJ	0032-0086
C1516	1	Cap Cer	10 pF 2% 50V	M/E 2222-631-10109	0002-0047
C1517	1	Cap Cer	0.1 uF 10% 50V	Centralab CW30C104 K	0002-0029
C1518		Cap Mica	1200 pF 2% 300V	ARCO DM15DC122G03	0002-0373
C1519		Cap Cer	47 pF 2% NPO	M/E 2222-631-10479	0002-0053

SERIES A...	202-7615	PAGE 4	OF 8
-------------	----------	--------	------

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
C1520	1	Cap Mica	ARCO DM15DC122G03	0002-0373
C1521	1	Cap Cer	M/E 2222-631-10479	0002-0053
C1522	1	Cap Mica	ARCO DM15DC122G03	0002-0373
C1523	1	Cap Cer	M/E 2222-631-10479	0002-0053
C1524	1	Cap Mica	ARCO DM15DC122G03	0002-0373
C1525	1	Cap Cer	M/E 2222-631-10479	0002-0053
C1526	1	Trimmer	ERIE 538-011	0002-0244
C1527	1	Cap Cer	Centralab CW30C104 K	0002-0029
C1528	1	Cap Tant	Sprague 196D226X9015 KA1	0032-0007
C1529	1	Cap Tant	196D685X9035 KA1	0032-0086
C1530	1	Cap Tant	196D685X9035 KA1	0032-0086
C1531	1	Cap Mica	ARCO DM10DC361G03	0002-0372
C1532	1	Cap Mica	ARCO DM15DC122G03	0002-0373
C1533	1	Cap Mica	ARCO DM10DA391G03	0002-0367
C1534	1	Cap Mica	ARCO DM15DC122G03	0002-0373
C1535	1	Cap Mica	ARCO DM10DA331G03	0002-0374
C1536	1	Cap Mica	ARCO DM15DC122G03	0002-0373
C1537	1	Cap Cer	M/E 2222-631-10479	0002-0053
C1538	1	Cap Mica	ARCO DM19DD182G03	0002-0363
C1539	1	Cap Cer	M/E 2222-631-10101	0002-0010
C1540	1	Cap Cer	Centralab CW15C152 K	0002-0285
C1541	1	Cap Tant	Sprague 196D685X9035 KA1	0032-0086
C1542	1	Cap Tant	196D226X9015 HA1	0032-0007
C1543	1	Cap Tant	196D226X9015 KA1	0032-0007
C1544	1	Cap Cer	Centralab CW20C223 K	0002-0255

9202-7615
SERIES A...
PAGE 5
OF 8

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO
C1545	1	Cap Cer	0.22 uF 10% 50V	Centralab CW30C224 K
C1546	1	Cap Tant	6.8 uF 10% 35V	Sprague 196D685X9035 KA1
C1547	1	Cap Cer	4.7 pF .25 pF NPO	M/E 2222-631-09478
C1548	1	Cap Tant	22 uF 10% 15V	Sprague 196D226X9015 KA1
C1549	1	Cap Tant	22 uF 10% 15V	196D226X9015 KA1
C1550	1	Cap Tant	22 uF 10% 15V	196D226X9015 KA1
C1551	1	Cap Cer	0.0047 uF 10% 50V	Centralab CW15C472 K
C1552	1	Cap Tant	1.0 uF 10% 35V	Sprague 196D103X9035 HA1
C1553	1	Cap Tant	1.0 uF 10% 35V	196D103X9035 HA1
C1554	1	Cap Tant	1.0 uF 10% 35V	196D103X9035 HA1
C1555	1	Cap Tant	100 uF 10% 20V	196D107X9020 TE4
U1501	1	I.C.	Quad EX-OR Gate	Motorola MC 14070 BCP
U1502	1	I.C.	Bi-Quinary Counter	Nat. MM 74C90 N
U1503	1	I.C.	Dual Decade Counter	Motorola MC 14518 B
U1504	1	I.C.	Dual Decade Counter	Motorola MC 14518 B
U1505	1	I.C.	Bi-Quinary Counter	Nat. MM 74C90 N
U1506	1	I.C.	Phase Lock Loop	Motorola MC 14046 CP
U1507	1	I.C.	Mono-Ast. Vibrator	Motorola MC 14047 BE
U1508	1	I.C.	Quad EX-OR Gate	Motorola MC 14070 BCP
U1509	1	I.C.	Dual Bi-FET Op-Amp	Nat. LF 353 N
U1510	1	I.C.	Dual Bi-FET Op-Amp	Nat. LF 353 N
U1511	1	I.C.	Progr. Div. N-Count	Motorola MC 14522 B
U1512	1	I.C.	Progr. Div. N-Count	Motorola MC 14522 B
U1513	1	I.C.	Progr. Div. N-Count	Motorola MC 14522 B

9202-7615
SERIES A...
PAGE 6
OF 8

ITEM QTY	DESIGNATION	ORDERING INFORMATION		STOCK NO.
		VALUE, SIZE, TOL	MANUFACTURER, NOTES	
U1514 1	I.C.	Dual Progr.Div.-N-Count	Motorola MC 14569 B	0035-0323
U1515 1	I.C.	Preset U-D Counter	Motorola MC 14510 BCP	0035-0278
U1516 1	I.C.	Preset U-D Counter	Motorola MC 14510 BCP	0035-0278
U1517 1	I.C.	Preset U-D Counter	Motorola MC 14510 BCP	0035-0278
U1518 1	I.C.	Preset U-D Counter	Motorola MC 14510 BCP	0035-0278
U1519 1	I.C.	Preset U-D Counter	Motorola MC 14510 BCP	0035-0278
U1520 1	I.C.	Dual Bi-FET Op-Amp	Nat. LF 353 N	0035-0303
U1521 1	I.C.	Triple SPDT Anal.Sw	Motorola MC 14053 BCP	0035-0324
U1522 1	I.C.	Triple 3-1np NAND	Motorola MC 14023 BCP	0035-0183
U1523 1	I.C.	Quad 2-1np NOR	Motorola MC 14001 BCP	0035-0189
U1524 1	I.C.	Quad 2-1np NAND	Motorola MC 14011 BCP	0035-0186
U1525 1	I.C.	Dual D F-F	Motorola MC 14013 BCP	0035-0182
U1526 1	I.C.	Bi-FET Op-Amp	Nat. LF 356 N	0035-0325
U1527 1	I.C.	Dual Bi-FET Op-Amp	Nat. LF 353 N	0035-0303
U1528 1	I.C.	Dual Bi-FET Op-Amp	Nat. LF 353 N	0035-0303
U1529 1	I.C.	Dual Decade Counter	Motorola MC 14518 BCP	0035-0107
CR1501 1	Diode	Switching 1N 4448	Jedec	0037-0001
CR1502 1	Diode	Switching 1N 4448	Jedec	0037-0001
CR1503 1	Diode	Switching 1N 4448	Jedec	0037-0001
CR1504 1	Diode	Switching 1N 4448	Jedec	0037-0001
CR1505 1	Diode	Switching 1N 4448	Jedec	0037-0001
VR1501	Zener Diode	1N 5226 B		0037-0152
VR1502	Zener Diode	1N 5226 B		0037-0152

SERIES A...
PAGE 7
OF 8
9202-7615

1) As required per Board.

ITEM QTY	DESIGNATION	ORDERING INFORMATION		STOCK NO.
		VALUE, SIZE, TOL	MANUFACTURER, NOTES	
Q1501 1	Transistor	2N 2222 NPN	Jedec	D010-0010
Q1502 1	Transistor	2N 3251 PNP	Motorola	D010-0006
Q1503 1	Transistor	2N 2222 NPN	Jedec	D010-0010
Y1501 1	Crystal	1 Mhz	WGI 9202-9701	9202-9701
1	P.C. Board	Synthes. drilled	WGI 9202-7005-02	
2	Handle	P.C. Board gy	WGR 0000-3705.55/4	0028-0112
3	Rivet	F. Handle	WGR 5 WN 33/3/0	0005-0021
TP 1-7	Rivet	Testpoint	WGR 3000.19/5	0003-0274
4	Socket Terminal Carrier	Augat 716 AG 2D	0034-0025	1)
5	Terminal	Solder	WGR 0000-2901.02/4	0027-0033
6	Label	Signal Triangle	WGR 0000-7575.994	0021-0029

SERIES A...
PAGE 8
OF 8
9202-7615

9202-7616	SERIES A...
PAGE 1	OF 2

ITEM	QTY	DESIGNATION	VALUE, SIZE, TOL.	MANUFACTURER, NOTES	STOCK NO.
R1601	1	Var. Resist	Dual Pot (Level)	Allen-Bradley LKKC 99328	0038-0139
R1602	1	Var. Resist	Pot w/Switch (Spkr)	CTS Type TW-082-T450	0038-0140
R1603	1	Resistor	CF 5.6 5% 1/4W	Amp. CR-25	0008-0375
R1604	1	Resistor	CF 2.2 K 5% 1/4W	Amp. CR-25	0008-0216
R1605	1	Resistor	CF 8.2 K 5% 1/4W	Amp. CR-25	0008-0014
C1601	1	Cap Cer	33 pF 2% NPO	M/E 2222-631-10339	0002-0052
U1601	1	I.C.	Freq. Counter	Interstat ICM 7224 IPL	0035-0332
DS1601	1	Display	L.C.D. (Level)	Hamlin 3909-366-06-0	0037-0202
DS1604	1	Display	L.C.D. (Freq.)	Hamlin 3909-366-06-0	0037-0202
DS1605	1	L.E.D.	green T-1	HP HLMF-1501	0037-0014
U1601	1	Connector	26 pin Male	3M 3429-2202	0003-0332
U1601	1	Cable Assy w/Connector both Ends	AP 922621-40-04-64	0001-0114	
	1	Switch	Slide 6u Au	WGR 2 WN 13/4/2	0011-0068

9202-7616	SERIES A...
PAGE 2	OF 2

ITEM	QTY	DESIGNATION	VALUE, SIZE, TOL.	MANUFACTURER, NOTES	STOCK NO.
1	1	P.C. Board	Display, drilled	WGI 9202-7006-02	
2					
3	4	Socket Strip	I.C. 20 pin	Augat 325-AG1D-20	0034-0028
4	1	Socket	DIP 40 pin	Augat 540-AG 37D	0034-0027
5					
6					
7					
8	1	Tubing	clear, heatshrink	Alpha FIT 221 3/16"	0031-0015
9					
10					
11					
12					
B1601	1	Motor Assy	premounted	WGR 829-7036.818/4	
14	1	Flywheel	for "	WGR 829-7036.067/5	
15	1	Washer	for Tachometer	WGI 9202-0100-08/A	
16	3	Screw	M 2x5mm Cy1 S1	DIN 84	0005-0239
17	1	Set Screw	M 2.5x3mm	DIN 916	0005-0355
18					
19					
20	2	Ty-Rap	(Optional)		
21	1	Label	Signal Triangle	WGR 0000-7575.994	0021-0029
22		Hook-up Wire	AWG 22, Brn, Wht, Yel, Blk $\approx$ 12 " each		
23	2	Receptacle		Germ Amp 925-574-3	0003-0251
24	2	Sleeve	f. Recept.	WGR 0000-3706.22/4	0028-0028
25					

ITEM QTY	DESIGNATION	ORDERING INFORMATION		STOCK NO.
		VALUE, SIZE, TOL	MANUFACTURER, NOTES	
1	Resistor	68 ohm 1% 10W	Claroestat VC 10 F	0008-0648
1	Resistor	68 ohm 1% 10W	Claroestat VC 10 F	0008-0648
1	Resistor	CF 430 5% 1/4W	Amp. CR-25	0008-0343
1	Resistor	CF 22 5% 1/4W	Amp. CR-25	0008-0234
1	Resistor	CF 10 K 5% 1/4W	Amp. CR-25	0008-0185
1	Resistor	CF 10 5% 1/4W	Amp. CR-25	0008-0201
1	Resistor	CF 910 5% 1/4W	Amp. CR-25	0008-0011
1	Cap Al-Elyt	3300 uF 20% 35V	ELNA 35RPE 3300	0032-0110
1	Cap Al-Elyt	3300 uF 20% 35V	ELNA 35RPE 3300	0032-0110
1	Cap Cer	0.22 uF 10% 50V	Centralab CW30C224 K	0002-0263
1	Cap Cer	0.22 uF 10% 50V	Centralab CW30C224 K	0002-0263
1	Cap Tant	1.0 uF 10% 35V	Sprague 196D105X9035 HA1	0032-0092
1	Cap Tant	1.0 uF 10% 35V	196D105X9035 HA1	0032-0092
1	Cap Tant	1.0 uF 10% 35V	196D105X9035 HA1	0032-0092
1	Cap Cer	0.0082 uF 10% 50V	Centralab CW15C822 K	0002-0282
1	Cap Cer	0.1 uF 10% 50V	Centralab CW30C104 K	0002-0029
1	Cap Tant	22 uF 10% 15V	Sprague 196D226X9015 KA1	0032-0007
1	Cap Cer	0.1 uF 10% 50V	Centralab CW30104 K	0002-0029
1	Cap Tant	100 uF 10% 20V	Sprague 196D107X9020 TE4	0032-0090

SERIES A...	9202-7617
PAGE 1	OF 4

ITEM QTY	DESIGNATION	VALUE, SIZE, TOL	MANUFACTURER, NOTES	STOCK NO.
1	Diode	Rectifier 1N 4002	Jedec	0037-0020
1	Diode	Rectifier 1N 4002	Jedec	0037-0020
1	Diode	Rectifier 1N 4002	Jedec	0037-0020
1	Diode	Rectifier 1N 4002	Jedec	0037-0020
1	Diode	Rectifier 1N 4002	Jedec	0037-0020
1	Diode	Rectifier 1N 4002	Jedec	0037-0020
1	Diode	Rectifier 1N 4002	Jedec	0037-0020
1	Diode	Rectifier 1N 4002	Jedec	0037-0020
1	Diode	Rectifier 1N 4002	Jedec	0037-0020
1	Diode	Hot-Carrier 1N 5818	Motorola	0037-0203
1	Diode	Hot-Carrier 1N 5818	Motorola	0037-0203
1	Diode	16 Volt 1N 5353	Motorola	0037-0204
1	Zener Diode	5.1 V 5% 1N 5231 B	Motorola	0037-0059
1	I.C.	15V Pos. Regulator	Motorola MC 7815 CP	0035-0002
1	I.C.	15V Neg. Regulator	Motorola MC 7915 CP	0035-0003
1	I.C.	Audio Amp	Nat. LM 386 N-1	0035-0326
	Hook-up Wire	AWG 22, Stranded Purple, Yel, Wht/Org, Blk, Wht, Org ~ 12" each		

SERIES A...	9202-7617
PAGE 2	OF 4

ITEM QTY	DESIGNATION	ORDERING INFORMATION		STOCK NO.
		VALUE, SIZE, TOL	MANUFACTURER, NOTES	
J1801	1	Connector	TEKA TPI-221-S04	0003-0337
J1802	1	Connector	TEKA TPI-221-S04	0003-0337
J1803	1	Connector	TEKA TPI-221-S04	0003-0337
J1804	1	Connector	TEKA TPI-221-S04	0003-0337
J1805	1	Connector	TEKA TPI-221-S04	0003-0337
J1806	1	Connector	Panduit HLSS156-6-C	0003-0334
R1801	1	Resistor	CF 4.7 k 5% 1/4W	0008-0182
S1801	1			
S1802	1	Switch Assembly 4 S	WGI 9202-8003-00/B	
S1803	1			
S1804	1			
W1801	1	Cable Assy w/Connector both Ends	AP 922522-36-02-4	0001-0115
1	1	P.C. Board	Mother, drilled	WGI 9202-7008-02
2				
3				
5				
6	10	Screw	M 3x10mm CY1 CR1	ZLK 1875 A
7	10	Clinch Nut	M 3 B	WN 32/3/1
8	10	Washer	Flat M 3	
9	2	Spacer	f. Switch	WGI 9202-0100-07/A
10				

SERIES A...	9202-761B	PAGE 1	OF 1
-------------	-----------	--------	------