

---

# XPower Powerpacks with User Replaceable Batteries: Replacement Instructions

---

Addenda/Errata

976-0136-01-01 Rev A

---

## Introduction

This Addenda/Errata sheet provides information which is intended to replace the battery replacement information in some of the manuals for the XPower Powerpack and Eliminator branded products.

---

**Important:** If your product has more than one battery, the same information applies to replacing multiple batteries as it does to replacing a single battery.

---

## Replacing the Internal Battery

### Battery Life

The high quality battery used in the XPower Powerpack will serve as a reliable power source for years when properly maintained. To maximize battery life, it is important to recharge the XPower Powerpack battery after each use.

---

**Important:** Recharge the XPower Powerpack fully at least every three months if it is placed in storage or in a vehicle trunk. Store in a location that maintains a temperature range between 32 and 86 °F (0 and 30 °C). Failure to maintain the unit will void the product warranty.

---

### Obtaining a Replacement Battery

When the battery reaches the end of its service life, you may purchase a replacement through an industrial battery supplier. The supplier should specialize in deep-cycle batteries. The recommended replacement batteries are standard sizes used for a variety of applications (not just the Powerpack), so you may rest assured that the battery will continue to be widely available many years into the future.

The factory-installed 21 amp-hour battery (batteries) in your Powerpack is (are) not available in North America. The recommended replacement batteries have smaller amp-hour capacities. Using smaller capacity batteries will not affect the Powerpack's output power, but will result in slightly shorter runtimes for AC and DC products.

Refer to the table below for a list of batteries approved for use with the XPower Powerpack:

Battery	Capacity (Ah)
SLA1122 (ibsa.com)	18
SLA-12V18 (batterymart.com)	18
SLA-12170 (gotbatteries.com)	17
UB12180 (batterywholesale.com)	18
Yuasa NP18-12BFR (gotbatteries.com)	18
EP17-12-B1 (powerstream.com)	17
Power-Sonic PSH-12180 (batteryweb.com)	18
Panasonic LC-X1220P (gotbatteries.com)	18

For the latest battery replacement information, visit [www.xantrex.com/support](http://www.xantrex.com/support) and view the Powerpacks FAQ. The Powerpacks FAQ has a battery replacement guide.

### **Trademarks**

Xantrex is a registered trademark of Xantrex International.

Other trademarks, registered trademarks, and product names are the property of their respective owners and are used herein for identification purposes only.

### **Notice of Copyright**

*Addenda/Errata XPower Powerpacks with User Replaceable Batteries: Replacement Instructions* © August 2006 Xantrex International. All rights reserved.

### **Exclusion for Documentation**

Unless specifically agreed to in writing, Xantrex Technology Inc. ("Xantrex")

(A) MAKES NO WARRANTY AS TO THE ACCURACY, SUFFICIENCY OR SUITABILITY OF ANY TECHNICAL OR OTHER INFORMATION PROVIDED IN ITS MANUALS OR OTHER DOCUMENTATION.

(B) ASSUMES NO RESPONSIBILITY OR LIABILITY FOR LOSSES, DAMAGES, COSTS OR EXPENSES, WHETHER SPECIAL, DIRECT, INDIRECT, CONSEQUENTIAL OR INCIDENTAL, WHICH MIGHT ARISE OUT OF THE USE OF SUCH INFORMATION. THE USE OF ANY SUCH INFORMATION WILL BE ENTIRELY AT THE USER'S RISK; AND

(C) REMINDS YOU THAT IF THIS MANUAL IS IN ANY LANGUAGE OTHER THAN ENGLISH, ALTHOUGH STEPS HAVE BEEN TAKEN TO MAINTAIN THE ACCURACY OF THE TRANSLATION, THE ACCURACY CANNOT BE GUARANTEED. APPROVED XANTREX CONTENT IS CONTAINED WITH THE ENGLISH LANGUAGE VERSION WHICH IS POSTED AT [WWW.XANTREX.COM](http://WWW.XANTREX.COM).

### **Date and Revision**

August 2006 Rev A

### **Part Number**

976-0136-01-01

### **Contact Information**

Telephone: 1 360 925 5097 (direct)  
Fax: 1 360 925 5143 (direct)  
Email: [customerservice@xantrex.com](mailto:customerservice@xantrex.com)  
Web: [www.xantrex.com](http://www.xantrex.com)

