



High Performance, Multistage Charging

Truecharge multistage battery chargers are microprocessor controlled for fast and accurate charging of all deep-cycle 'house' batteries. A wide AC input voltage range enables proper delivery of a full three-stage charge, even when charging from less than perfect quality shorepower or generator power. Smart features, such as adjustable temperature compensation and independent settings prevent battery damage due to overcharging and help extend the life of expensive batteries. All Truecharge battery chargers come with a one-year warranty.

Truecharge 10 / 10TB

- ▶ 10-amp DC output
- ▶ Microprocessor-controlled, multistage charging
- ▶ Charges up to two battery banks simultaneously (Truecharge 10TB)
- ▶ Covered terminal block with screw terminals for safe and easy connection (Truecharge 10TB)
- ▶ Easy battery connection with clip leads (Truecharge 10)
- ▶ Three settings for temperature compensation (Truecharge 10)
- ▶ Settings for flooded, gel or lead-acid batteries
- ▶ Wide voltage range operation (90-135 Vac, 50/60 Hz)
- ▶ Automatic 21-day top-up program

Truecharge 20 + / 40 +

- ▶ 20 and 40 amp output
- ▶ Microprocessor-controlled, multistage charging
- ▶ Charges up to three battery banks simultaneously
- ▶ Independent settings for AGM, flooded, gel or lead-acid batteries
- ▶ Wide voltage range operation (90-135 Vac, 50/60 Hz)
- ▶ Automatic 21-day top-up program
- ▶ Durable and corrosion resistant chassis
- ▶ Optional remote LED panel to indicate battery and charge status
- ▶ Optional battery temperature sensor

Protection Features

- ▶ Over-temperature shutdown and overload protection
- ▶ Ignition-protected for installation in gas engine compartments (10TB, 20+ and 40+)
- ▶ Transformer isolated for safety and to protect against electrolysis
- ▶ Reverse-polarity protection
- ▶ Short-circuit and surge protection



NRTL/C

CSA/NRTL Certified to UL and CSA Standards

Xantrex Technology Inc.

Headquarters
8999 Nelson Way
Burnaby, British Columbia
Canada V5A 4B5
800 670 0707 Toll Free
604 420 1591 Fax

5916 195th Street NE
Arlington, Washington
USA 98223
800 446 6180 Toll Free
360 925 5143 Fax

www.xantrex.com

10, 20 and 40 amp Multistage Battery Chargers

Electrical Specifications		
Models	Truecharge 10 / 10TB	Truecharge 20+ / 40+
Output current	10 A @ 14.5 V nominal	20 A @ 14.5 V nominal / 40 A @ 14.5 V nominal
Output voltage (nominal, depending on settings)		
• Charge	13.8 - 14.8 Vdc / 14.2 - 14.4 Vdc	13.8 - 14.8 Vdc
• Float	13.1 - 14.2 Vdc / 13.5 - 13.8 Vdc	13.1 - 14.2 Vdc
• Equalize		15.5 Vdc @ 5 A maximum
DC output connections	Clip leads / Dual	Three
AC input voltage	90-135 Vac, 50/60 Hz	90-135 Vac, 50/60 Hz
Temperature compensation	Three settings / None	Three settings or optional remote sensor
Charger efficiency	85% approx.	85% approx.
Recommended battery type	Gel and flooded	Gel, flooded and AGM
Recommended battery size	25 Ah to 100 Ah	100 Ah to 400 Ah / 400 Ah and up

General Specifications		
Models	Truecharge 10 / 10TB	Truecharge 20+ / 40+
Operating temperature	0°C to 30°C / 0°C to 40°C	0°C to 30°C
Storage temperature	-25°C to 70°C	-25°C to 70°C
Battery connection	Alligator clip leads / Two separate pos. terminal, one common neg. terminal	Three pos. terminals, one neg. terminal
Dimensions (H x W x L)	2.75 x 6.5 x 9.0" (70 x 165 x 230 mm) 2.75 x 6.7 x 15.1" (70 x 172 x 385 mm)	2.75 x 6.5 x 10.65" (70 x 165 x 270 mm) 2.75 x 6.5 x 10.65" (70 x 165 x 270 mm)
Weight	3.0 lb (1.4 kg)	6.9 lb (3.1 kg)
Warranty	One year	One year
Part Number	804-0100 (Truecharge 10) 804-0111 (Truecharge 10TB)	804-0220 (Truecharge 20+) 808-0200 (Truecharge 20+ Remote Panel) 804-0440 (Truecharge 40+) 808-0400 (Truecharge 40+ Remote Panel) 808-0231 (Truecharge 20+ / 40+ Temperature Sensor)

Regulatory Approvals

Truecharge 10	CSA/NRTL approved to CSA 107.2, UL 1236
Truecharge 10TB	CSA/NRTL approved to CSA 107.2, UL 1236 , including the Marine Supplement and ignition protection
Truecharge 20+ / 40+	CSA/NRTL approved to CSA 107.2, UL 1236, UL 458, UL 1564 , including the Marine Supplement and ignition protection

Note: Specifications subject to change without notice.

Three-stage Charging

Multistage charging ensures batteries receive optimum charging, but with minimal wear and tear, regulating the voltage and current delivered to the batteries in three automatic stages:

- ▶ **Bulk:** Replaces 70-80% of the battery's state of charge at the fastest possible rate.
- ▶ **Absorption:** Replenishes the remaining 20-30% of charge, bringing the battery to a full charge at a slow, safe rate.
- ▶ **Float:** Voltage is reduced and held constant in order to prevent damage and keep batteries at a full charge.