

Pocket power for the digital world

The XPower Pocket Inverter 175 utilizes advanced electronics to convert the 12 volt DC battery power from a vehicle or airplane into 115 volt household AC electricity, so if your laptop battery runs down, you can just plug straight into the AC outlet on the inverter and keep working, just like you're at home. In addition to the AC power outlet, this inverter includes a USB charge port which can power or charge iPod™, Blackberry™, iPaq™, Palm™ and a wide range of other electronic devices you can't live without. As one of the smallest inverters on the market today, weighing only 0.7lbs, this inverter easily fits inside even the most overburdened carry-on or laptop bag. With the integrated vehicle and airplane connector you can keep your iPod™ music flowing, your cell phone charged and your laptop running nearly anywhere you go.

Product Features

- Converts 12 VDC power from vehicle battery into 115 VAC power
- ▶ Three-prong AC outlet to handle all chargers and adapters for mobile electronics
- USB power port
- ▶ Blue LED power indicator
- ▶ DC cable with vehicle and airplane connector
- Compact and lightweight
- One year warranty
- Carry case for inverter & cables

Protection Features

- Over-temperature shutdown
- ▶ Low battery voltage shutdown (10.5 VDC and automatic reset)
- Overload shutdown
- External fuse 20 A (user changeable)



Xantrex Technology Inc.

Headquarters 8999 Nelson Way Burnaby, British Columbia Canada V5A 4B5 800 670 0707 Toll Free 604 420 1591 Fax

5916 195th Street NE Arlington, Washington USA 98223 800 446 6180 Toll Free 360 925 5143 Fax

www.xantrex.com

100W DC to AC Inverter for Mobile Office Equipment

| Electrical Specifications | | |
|-------------------------------|---------------------------------------|--|
| Output power (5 min) | 175 W | |
| Output power (continuous) | 140 W | |
| Surge capacity (peak) | 280 W | |
| AC output voltage | 115 +/- 10 volts AC RMS | |
| AC output frequency | 60 +/- 4 Hz | |
| AC output waveform | Modified sine wave | |
| DC input voltage range | 10.5-15 volts DC | |
| Battery drain with no AC load | 0.25 amps DC (at 12 V input) | |
| Dimensions (L x W x H) | 5.5 x 3.0 x 1" (13.75 x 7.5 x 2.5 cm) | |
| Weight | 0.7 lbs (318 g) | |
| Warranty | One year | |
| UPC | 715535113308 | |
| FGA Part Number | 813-0091 | |

Note: Specifications subject to change without notice.



| XPower Pocket Inverter 175 Packaging Specifications | | | | | |
|---|---------------------|----------------------|-----------------------|--|--|
| Packaging | Individual | Inner Carton | Master Carton | | |
| Quantity | 1 | 5 | 20 | | |
| Size (L x W x H) | 6.56 x 10.88 x 3.5" | 6.86 x 11.88 x 17.8" | 27.94 x 12.88 x 36.1" | | |
| Weight | 0.90 lbs | 4.50 lbs | 18 lbs | | |





