

JUXTA W Series

General Specification

Model WX3□-HS (Variable software type)
High Selector

JUXTA

1. GENERAL

This is a variable software type computing unit which accepts two mV inputs signal from a converter and outputs one input signal whichever is the higher as isolated various voltage or current, signal.

2. SPECIFICATION

Model No.	WX3A-HS, WX3V-HS
Input signal	mV signal:two points
Measuring range	-2 to 10mV (There is accuracy limitation for spans of more than 3mV and less than 10mV.) -10 to 50mV (For span of more than 10mV) -50 to 250mV (For span of more than 50mV) -100 to 1250mV (For span of more than 250mV) (*1)
Input resistance	1MΩ (At power failure:More than 3 kΩ)
Output signal	4 to 20mA, 2 to 10mA, 1 to 5mA, 0 to 20mA, 0 to 16mA, 0 to 10mA or 0 to 1mA DC 0 to 10mV, 0 to 100mV, 0 to 1V, 0 to 10V, 0 to 5V, 1 to 5V or -10 to +10 V DC
Basic accuracy	±0.2 of measuring span
Signal insulation	Between input signal and output signal, power supply circuit and grounding
Insulation resistance	Between input signal and output signal, power supply circuit and grounding:100MΩ/500V DC
Dielectric strength	Between input signal and output signal, power supply circuit and grounding, and power supply circuit and output signal and grounding:1500V AC/min Between output signal and grounding:1000V AC/min
Power supply voltage	85 to 264V AC 47 to 63 Hz or 24V DC ±10%
Ambient temperature/humidity	0 to 50°C (32 to 122°F) and 5 to 93% relative humidity (No condensation)
Effect of ambient temperature	±0.2% of span for 10°C (50°F) change
Effect of power supply voltage	±0.2% of span for 85 to 264V AC or 24V DC ±10% regulation
Power consumption	100V AC, 7.0VA (voltage output) and 100V AC, 8.5VA (current output) 24V DC, 60mA (voltage output) and 24V DC, 82mA (current output)
Dimensions	72(2.83") H×48(1.89") W×127(5.00") D mm(inch)
Weight	Approx. 280g
Accessories	Tag number label :1 sheet Mounting blocks:2 pcs.

(*1) Specify measuring range from □ to □mV.

Range accuracy for span of less than 10mV:0.2×10 (mV input span)%

WX3□-HS-□□-□ * B

Ordering Information

MODEL _____
 SOFTWARE TYPE _____
 3: Variable type
 OUTPUT _____
 A: Current
 V: Voltage
 INPUT SIGNAL _____
 1: Voltage Signal
 0: Current Signal (non standard)
 OUTPUT SIGNAL _____
 A : 4~20mA DC 1 : 0~ 10mV DC
 B : 2~10mA DC 2 : 0~100mV DC
 C : 1~ 5mA DC 3 : 0~ 1V DC
 D : 0~20mA DC 4 : 0~10V DC
 E : 0~16mA DC 5 : 0~ 5V DC
 F : 0~10mA DC 6 : 1~ 5V DC
 G : 0~ 1mA DC 7 : -10~+10V DC
 Z : Specify current. 0 : Specify voltage.
 (30mA max.) (-10V~+10V)
 POWER SOURCE _____
 1 : 24V DC ±10%
 2 : 85~264V AC

Input Measuring Range		
Range name	Allowable min. span	Allowable Measuring Range
HH	250mV	-100~1250mV
H	50mV	-50~250mV
L	10mV	-10~50mV
LL	3mV	-2~10mV
However, accuracy of less than 10mV span is $0.2\% \times \frac{10\text{mV}}{\text{input span(mV)}} (\%)$		
Recommended Input Range		
Voltage signal	0~10mV DC	
	0~100mV DC	
	0~1V DC	

● OUTPUT RESISTANCE AND LOAD RESISTANCE ●

Output Signal	Load Resistance	Output Impedance
4 to 20mA DC	0 to 750 Ω	5MΩ or more
2 to 10mA DC	0 to 1500 Ω	
1 to 5mA DC	0 to 3000 Ω	
0 to 20mA DC	0 to 750 Ω	
0 to 16mA DC	0 to 900 Ω	
0 to 10mA DC	0 to 1500 Ω	
0 to 1mA DC	0 to 15k Ω	

Output Signal	Load Resistance	Output Impedance
0 to 10mV DC	100k Ω or more	100 Ω, or less
0 to 100mV DC		
0 to 1V DC	2k Ω or more	1 Ω or less
0 to 5V DC		
1 to 5V DC		
0 to 10V DC	10k Ω or more	
-10 to +10V DC		

Subject to change without notice for grade up quality and performance