

ACORN USER

BBC MICRO • ELECTRON • ATOM

AUGUST 1984 £1

Satellite link:
watch the weather
on your BBC micro

Electron:
learn to use
your keyboard

Listings:
how to find and
correct errors

Music:
a trio of tunes to
type in and play

MICROTOTS
TEACHING
YOUNGSTERS
WITH A MICRO



Competition:
5 torch
communication
systems
to be won.
Each worth
£180

SCHIZOPHRENIC!



AVAILABLE FROM ALL LVL DEALERS. (FOR FURTHER INFORMATION TELEPHONE 0602 394000)

The new SABA colour TV that
doubles up as a colour computer monitor
(or is it the other way around?).



Scientific House,
Bridge Street, Sandiacre
Nottingham, NG10 5BA
Telephone (0602) 394000



Computerama

the source

ROM SOFTWARE	INC VAT
Wordwise	39.95
View	59.00
Printmaster	32.95
Caretaker	32.95
Disc Doctor	32.95
Termi (terminal emulator)	32.95
Graphics Extension	32.95
DFS, The Upgrade	27.95
Acorn Speech System Upgrade	55.00
HCCS Forth	39.95
HCCS Logo Forth	67.85
HCCS Pascal	57.00
HCCS Excal	74.75
ROM Expansion Board (ATPL)	
The Best!	43.70

BOOKS	NO VAT
BBC Micro Disc Companion	7.95
Creative Graphics	7.50
Graphs & Charts	7.50
Lisp Manual	7.50
Forth Manual	7.50
BCPL Manual	15.00

Discovering BBC Micro	INC VAT
Machine Code	6.95
BBC Micro Disk Manual	1.95
Disk Systems For The BBC Micro	6.95

MICRO POWER	INC VAT
Killer Gorilla	7.95
Cybertron Mission	7.95
Cosmic Combat	7.95
Chess B	7.95
Danger LXB	7.95
Escape Moonbase Alpha	7.95
Felix in Factory	7.95
Felix & Fruit Monsters	7.95
Nemesis	7.95
Bumble Bee	7.95
Wizards Challenge	7.95
Jet Power Jack	7.95
Positron	7.95
Demon Decorator	6.85
Alien Swirl	7.95
Alien Destroyers	7.95
Space Jailer	7.95
Ghouls	7.95
Moon Raider	7.95
The Mine	7.95
Hell Driver	7.95
Labyrinths of LaCoché	7.95
Zam	7.95
Blockbuster	7.95
Rubble Trouble	7.95
Frenzy	7.95
Stock Car	7.95

SUPERIOR SOFTWARE	INC VAT
Hunchback	7.95
Overdrive	7.95
Battletank	7.95
Cosmic Kidnap	7.95
Star Battle	7.95
Moon Mission	7.95
Percy Penguin	7.95
Boris In The Underworld	7.95
Rocky	7.95
Spiritfire Command	7.95
Crazy Painter	7.95
Road Racer	7.95

OPUS	INC VAT
Dogfight	8.95

BUG-BYTE	INC VAT
Twin Kingdom Valley	9.95

DYNABYTE	INC VAT
Pool	7.95
Horse race	7.95
Lemming Syndrome	7.95
Corporate Climber	7.95

BBC/ACORN SOFT	INC VAT
Algebraic Manipulation	9.95
Business Games	9.95
Castle of Riddles	9.95
Creative Graphics	9.95
Countdown to Doom	9.95
Forth	16.85
Graphs & Charts	9.95
Hopper	9.95
Lisp	16.85
BCPL (Rom + Disc)	99.95
Missile Base	9.95
Meteors	9.95
Kingdom Of Hamil	9.95
Monsters	9.95
Planetoid	9.95
Rocket Raid	9.95
Snooker	9.95
Sphinx Adventure	9.95
Starship Command	9.95
Tree of Knowledge	9.95
Snapper	9.95
Shirley Conran's Magic Garden	9.95
Personal Money Management	9.95
Draughts and Reversi	9.95
Aviator C/D	14.95/17.25
J C B Digger	7.95
Free Fall Games	9.95
Caroussel	9.95

ACORN SOFT EDUCATIONAL SOFTWARE NOW AVAILABLE	INC VAT
White Knight II	11.50
Vutype	16.10
Tax Calc	17.25
Beyond Basic	11.50
Toolbox	21.00
Canyon	10.00
Record Keeper	15.00
Doctor Who	10.00
ACORN SOFT MIRLE NOW IN STOCK	P.O.A.

IMAGINE	INC VAT
Pedro	5.50
Cosmic Cruiser	5.50

INVASION SOFTWARE	INC VAT
Eagles Wing	7.95
Spooks and Spiders	7.95
3-D Bomb Alley	7.95
Guns smoke	7.95
Vortex	7.95
Attack on Alpha Centauri	7.95

VISIONS	INC VAT
Snooker	7.95
Digger	7.95
Daredevil Dennis	7.95
Nifty Lifty	7.95
Demolater	7.95
Pengi	7.95

PSION	INC VAT
Saloon Sally	6.95
VuCalc	14.95
VuFile	14.95

MELBOURNE HOUSE	INC VAT
The Hobbit	14.95

COMPUTERAMA SOLID STATE JOYSTICK INTERFACE

***with RAPID-FIRE feature**
Now a totally new concept in joystick control for your BBC Micro. Simply plug into the analogue port, and connect ANY Atari type joystick for instant joystick control. FREE keyboard conversion programme allows joystick control of keyboard-only games. No memory-conflicts with this one - due to our unique Relocatable Code feature. **ORDER TODAY.** Only a few available. Demand is bound to be high. **ONLY £14.95** + 50p Carriage.

RING FOR LATEST PRICES, MANY REDUCTIONS EXPECTED

TORCH Z80 DISC PACK WITH OVER £1,100 OF SOFTWARE FREE

ORDER TODAY - Get the Z80 version of BBC BASIC FREE! With £125 worth of BBC Micro programmes up to twice as fast, gives 32K for graphics AND 48K for basic programming. **NOW ONLY £199**

INC. VAT Free carriage UK only. Software includes:
 ● PERFECT WRITER ● PERFECT SPELLER ● PERFECT CALC ● PERFECT FILER ● TORCH NET
 The TORCH Z80 DISC PACK is the most powerful BBC Micro disc upgrade available. It provides 800K of storage plus a Z80 Second Processor running Torch's own CP/M compatible operating system. Clip this ad to your order to receive free 40 80T converter programme.
 ● NEW TORCH ZEPHD PACK. Add Torch Power to any 80 track drive. Complete 2nd Processor AND Free Perfect software worth £1000. **ONLY £343** INC. VAT

QUICKSHOT II BBC MICRO JOYSTICK

Now with rapid fire Option and Solid State Interface. Optional Relocatable code feature - means that it WORKS with more games than any other similar interface. This SELF-CENTERING JOYSTICK works even with keyboard-only programmes. A sensation at the Micro User Show. More fun - reaches the games other joysticks cannot. Limited supplies of this item. **£19.95** + £1.55 p&p

WE ACCEPT INSTITUTIONAL EDUCATIONAL ORDERS

ATPL SIDEWISE ROM EXPANSION BOARD

- Full Sidewise Rom Expansion to 16 Roms
- 16K Battery backed CMOS Ram option
- No soldering required to fit sideways
- Plug-in-and-go construction - Mounts neatly inside the BBC Micro
- Full buffering of address and data buses - prevents data bus loading problems associated with unbuffered boards
- Pin 1 of on-board sockets are connected properly - No spurious crashes due to this known fault on BBC Micro. Existing sockets on BBC Micro are accessible without removing sideways.

ONLY £43.70 + £1.00 carriage

24 HOUR DESPATCH ON STOCK ITEMS

JUKI 6100 DAISYWHEEL PRINTER

SAVE OVER £130
FREE 10 Ribbons
FREE Printer Cable
FREE Paper

These items Alone could cost over £80 Elsewhere. **COMPLETE PACKAGE Worth £535**

COMPUTERAMA PRICE ONLY £399

MAIL ORDER No Stamp Required
Post your order today to **COMPUTERAMA DEPT. AUB FREEPOST STAFFORD ST16 2BR** OR TELEPHONE OUR MAIL ORDER HOT LINE With your ACCESS or VISA number, we will endeavour to despatch immediately - (0785) 41899.

Call in today, Home Computer Centre for the BBC Micro enthusiast. Send large SAE for further details of any product.

CARRIAGE
Micro's, Monitors, Disc Drives, Printers £8.00, Books £1.00 each, Cassette Decks £2.00, Leads and software 50p/item (£1.50 max).

EPSON FX80

A SUPERB PRINTER AT A SUPERB PRICE

This most popular of HIGH PERFORMANCE dot matrix printers has all the features you could ask for:

- 160 cps 11 x 9 matrix
- proportional spacing
- Normal, Elite & Italic Characters
- Factor & Friction Feed 10" Carriage
- Bi-directional Logic Seeking
- Centronics Interface Standard
- Down-loadable Character Set User Defined
- Condensed & Double Width Printing
- Super & Subscripts
- Dot Addressable Graphics

NOW AT THE AMAZING PRICE OF £389 INC. VAT

QUICKSHOT II BBC MICRO JOYSTICK

Now with rapid fire Option and Solid State Interface. Optional Relocatable code feature - means that it WORKS with more games than any other similar interface. This SELF-CENTERING JOYSTICK works even with keyboard-only programmes. A sensation at the Micro User Show. More fun - reaches the games other joysticks cannot. Limited supplies of this item. **£19.95** + £1.55 p&p

ATPL SIDEWISE ROM EXPANSION BOARD

- Full Sidewise Rom Expansion to 16 Roms
- 16K Battery backed CMOS Ram option
- No soldering required to fit sideways
- Plug-in-and-go construction - Mounts neatly inside the BBC Micro
- Full buffering of address and data buses - prevents data bus loading problems associated with unbuffered boards
- Pin 1 of on-board sockets are connected properly - No spurious crashes due to this known fault on BBC Micro. Existing sockets on BBC Micro are accessible without removing sideways.

ONLY £43.70 + £1.00 carriage

24 HOUR DESPATCH ON STOCK ITEMS

HARDWARE CORNER

BBC	INC VAT
ACORN ELECTRON	199.00
BBC Micro Model B	399.00
BBC Micro Model B + Double density DOS	P.O.A.
BBC Micro Disc Upgrade	95.00
BBC Micro Teletext Receiver	225.00
BBC Micro Z80 2nd Processor	T.B.A.
BBC Micro 6502 2nd Processor	T.B.A.
Double Density DOS Upgrade	104.95
Pace DFS	39.95

DISC DRIVES	INC VAT
LVL Dual 100K	340.00
Pace Single 100K	169.95
Pace Single 40/80T D/Sided	282.90
Pace Dual 100K	338.00
Pace Dual 40/80T D/Sided	573.95
Torch Dual 400K Z80 Disc Pack	799.00
Pace 200K 40T D/Sided	243.00
HOBBIT FLOPPY DRIVES	99.95

MONITORS	INC VAT
Microvitec 14" Colour	229.00
Sanyo 14" Colour	269.00
Fidelity 14" Colour Monitor	199.00
Grundig 14" Colour TV/Monitor	309.00
Sanyo 12" Green	89.95

PRINTERS	INC VAT
Epson RX80	269.00
Epson RX80FT	299.00
Epson FX80	389.00
Epson FX100	589.00
Shirwa CP80	229.00
Riteman	286.00
Juki 6100 Daisywheel	399.00

MISCELLANEOUS	INC VAT
Sanyo DR101 Data Recorder	39.95
Sanyo DR202 Data Recorder	44.95
Cassette leads - all types	2.80
Computerama Joystick interface Quickshot Joystick (FOR BBC MICRO)	14.95
Printer Cable (Parallel) 1.2 m	19.95
BBC Micro Deluxe Cover	9.95
Light Pen	5.95
Data Cassettes 5 x C20/C15	28.75
The Plug Power Filter	14.95

ORDER A COMPLETE SYSTEM - GET ALL LEADS FREE

MICROBYTE	INC VAT
3D Space Ranger	7.95
Pinball	7.95

CLARES	INC VAT
B-Base	25.00
Replica II (Disc Only)	12.00
Graph Disc	12.85
The Key (Disc Only)	12.95
Shadow/Inspector	7.95
State 40/80T for Discs	7.95

DR SOFT	INC VAT
747 Flight Simulator	8.95
Gorph	7.95

AMCOM	INC VAT
Fortress (C/D)	7.95/11.95
Space Highway	7.95

GEMINI	INC VAT
Business Combination Packs 1, 2, 3, 4	P.O.A.
Data Base	19.95

SOFTWARE FOR ALL	INC VAT
Stock Control (C/D)	19.95/29.95
Invoicing/Statements	19.95/29.95
Sales/Purchases (C/D)	19.95/29.95

ADVENTURE INTERNATIONAL	INC VAT
The Hulk	9.95
Adventureland	9.95
Voodoo Castle	9.95
Secret Mission	9.95
Pirate Adventure	9.95

SOFTSPOT	INC VAT
Transistors Revenge	6.95
Heist	6.95

H. SOFT (WATFORD)	INC VAT
Penguin	7.95

ALLIGATA	INC VAT
Sphinx	7.95
Neanderthal Man	7.95
Blogger	7.95

HEWSON	INC VAT
Heathrow Air Traffic Control	7.95

CRJ	INC VAT
Test Match	7.95

A&F	INC VAT
Chuckie Egg	7.90
Cylon Attack	7.90
180 1 Darts	7.90

AARDVARK	INC VAT
Zalaga	6.90
Freddie	6.90

ADDICTIVE	INC VAT
Football Manager	6.90
MIRRORSOFT First Steps With The Mr. Men	9.95

MICRO USER	INC VAT
Micro Olympics	6.90

MICRODEAL	INC VAT
Air Traffic Control	9.95
Space Shuttle (C/D)	7.95/9.95

MRM SOFTWARE	INC VAT
Q-Man's Brother	5.70
Diamond Mine	5.70
Guy In The Hat	5.70
3D Munchy	5.70
Castle Assault	5.70
Darts	5.70

SOFTWARE PROJECTS	INC VAT
Legion	6.95

MOSAIC	INC VAT
My Secret File	9.95

OCEAN	INC VAT
Mr. Wimpey	6.90

50 MONEY SAVER!

with every order, five pounds worth of moneysaving vouchers

Computerama

STAFFORD 59 Foregate Street Tel: (0785) 41899
STOKE-ON-TRENT 11 Market Square Arcade, Hanley Tel: (0782) 268620
SHREWSBURY 13 Castle Gates Tel: (0743) 60528



August 1984 No 25
Cover photograph by John Barlow; make-up by Paula Owen; clothes from Benetton and Brown's

Editor **Tony Quinn**
Production editor **Keith Parish**
Technical editors **Alex van Someren,**
Bruce Smith
Editorial assistant **Kitty Milne**
Art editor **Nigel Wingrove**
Art assistant **Frances King**
Publishing director **Michael Potter**
Editorial director **Christopher Ward**

Editorial
Redwood Publishing,
68 Long Acre, London
WC2E 9JH. Tel: 01-836 2441

Advertising
Computer Marketplace Ltd, 20
Orange St, London WC2H 7ED.
Tel: 01-930 1612

Subscriptions
Jan Potter, Subscriptions manager.
Tel: Nutfield Ridge (073782) 2957.
Correspondence: Redwood Pub-
lishing, 68 Long Acre, London
WC2E 9JH.

Annual subscription rates:
UK £15
Europe £18
Middle East £20
The Americas and Africa £22
Rest of the World £24
Prices include p&p for 12 issues

Acorn User welcomes submissions from readers. Articles should be typed, double-spaced text, with diagrams on separate sheets. Please enclose programs on disc or cassette, with a listing if possible. Photos should be 35mm, or larger, transparencies, or 5in by 7in black and white prints. Ensure your name is on everything. Please include a suitable stamped, addressed envelope for return. Articles are acknowledged on receipt.

Typeset and printed in Great Britain by Watmoughs Ltd, Bradford. Print production by Aquarius Print and Design, London. Distributed to the news trade by Comag, Tavistock Rd, West Drayton, Middlesex UB7 7QE. Tel: (0895) 44405.

© Redwood Publishing 1984
All rights reserved. No part of this publication may be reproduced without prior written permission of the publisher. The publisher cannot accept any responsibility for claims or errors in articles, programs or advertisements published. The opinions expressed on the pages of this magazine are those of the authors and do not necessarily represent those of the publisher, Acorn Computers Ltd, or Acornsoft Ltd. Acorn, Acornsoft, and the Acorn symbol are the registered trademarks of Acorn Computers Ltd and Acornsoft Ltd.



New Users

First Byte 33

Confused by the keyboard? Bamboozled by listings? Turned off by envelopes? First Byte aims to solve these problems

First, Tessie Revivis explains how to get your fingers tapping, and produces a program to write programs

Next, Martin Phillips tests you on how well you can find and correct faults on listings – with simple, step-by-step examples

Then, we've got three tunes from Gary Pesticcio and Darran Bristow which shows what can be done with a bit of sound and data

Hints & Tips 50

Queries from readers answered by Martin Phillips include: adding a second disc drive; using Wordwise with Epson printers; changing colours; using the cursor – and avoiding memory problems when running tape programs on disc machines

Letters 59

Second processors and ROMs, GOSUBS versus procedures, bugs in July's *Inspect* program, serial printers and the Atom, Electrons in Australia, 6502 op codes and high scores for games all demand our readers' attention in this month's postbag

Dear Kitty . . . 63

What do people actually do with computers? Are computers a passing fad? Do users know what they're talking about? Kitty answers the questions that aren't as simple as they might sound

Business

Plan for business 89

John Vaux introduces the Plan series of packages with Acorn's Z80 second processor: a spreadsheet for financial calculations; wordprocessor; and a 'card index' database

Education

Teaching toddlers 104

Joe Telford takes his Jottings home to explain how even two-year-olds can use the micro – with the help of parents and overlays

Zoo-time for micros 112

Susan Kingsbury builds a simple activity board to entertain, educate and delight children. She uses it to take children to the zoo, but the applications are endless

Atom

Atom Forum 121

Teletext displays, op codes, disc drives, Wordpack on the Epson, and Barry Pickles is in charge

Avoiding errors 127

Vincent Fojut explains how left justification helps you cope with typing mistakes

Reviews

Books 139

Hardware guide from Wise Owl, BBC in education by Eric Deeson, assembly language by John Ferguson and Tony Shaw, databases in schools by Derrick Daines

Yellow listing pages

An extra 16-page section devoted solely to the major program listings in this issue

Easy listening i
Two musical programs

Beeb Forum ii
Utilities from readers

First Byte iii
Correcting errors in listings


Beeb Forum vii

How it works ix
Random numbers in action

Teaching toddlers xi
Five programs in one

Zoo-time for micros xv
Utility board program

Atom xvi
Avoiding errors



Educational software 143

Slick from BP Educational software, and *The Examiner* from Acornsoft are put to the test by Geoff Nairn

Micronet software 145

Bill Penfold gives his views on a software enhancement for Micronet

Picture makers 147

Three drawing and painting packages from Acornsoft, Beebsoft and Goldstar are compared by Dee Vince

Games 153

Stock Car from Micropower, *Airline* from CES, *Hopper* from Acornsoft, *Frenzy* from Micropower

Versatile interface 157

Paul Beverley finds so many applications for MCP Microdevelopment's Interbeeb that he doesn't know where to begin . . .

Torch Unicomm 161

Modem and software for BBC machines with the Torch Z80 second processor put under the spotlight by Alex van Someren

Regulars

The News 7

Concern over Acorn's role in education, *The Times* set to launch schools database, BBC micros in India, Acorn User exhibition

Beeb Forum 65

Bruce Smith presents your most pertinent ideas – plus 6502 second processor and Tube tips from Robin Newman

How it works 78

Random numbers and how to make them better by Paul Beverley

Competition 87

Solve the message from Mad Alex and you could win a Torch Unicomm worth £180

Top 20 software 137

The ups and downs among the games sellers, plus our Soft Options round-up of new releases

Acorn Abuser's Diary 176

Find out who wants to sue us this month . . . could it be the *Someday Times*?

IN THIS ISSUE...

MICROTOTS


I Teaching toddlers 104

We introduce keyboard overlays to enable young children to use micros with the aid of their parents. If you can't type in the listings, remember you can send off for our program cassette (page 81)



II Zoo time 112

Build a simple activity board which uses a moving figure to trigger messages on your BBC micro



Downloading the weather 27

Michael Furminger links his BBC to satellites and displays weather pictures. Robin Mudge explains how it's done

Readers' pictures 165

Can you rival Malcolm Banthorpe's Coke can? If so, there's a spot for you in Micro Gallery where readers display their art – and win software prizes

PLUS: Three picture-drawing programs reviewed. See page 147



NEXT MONTH...

Muscle in on the airwaves

Tune in to RTTY and the dots, dashes and bleeps of short wave radio


Super plotting

The Parfitt plotter is soon to have a scribe, opto sensor (which digitised the image here), drill and special software added. We take a sneak preview

Unicorn review

Torch offers a 10Mb hard disc, floppy disc and Unix on the 68000 chip in its top-of-the-range Unicorn. We take a critical look

PLUS – May competition results



Electronequip


(Authorised BBC Dealer, and service centre)

*** SPECIAL OFFERS**
Mail order only

*** EPSON**

RX-80FT £225.25 + VAT


FX-80 £320.88 + VAT



Printer price includes cable for BBC and screen dump rom is available for £11.50

SIDEWISE

SIDEWISE FITTED



"SIDEWAYS" rom board for BBC Micro.
No soldering required £38.00 + VAT

VOLTMACE JOYSTICKS

*** 10% off list prices**



	Discounted price
JSVOLT 14 Voltmace Delta 14B Joysticks	13.46
JSVOLTAD Voltmace 14B/1 Adaptor Box	13.36
JSVOLT3B Voltmace Delta 3B Twin Joysticks	18.09

Prices subject to variation without prior notification

TRADE ENQUIRIES WELCOME
Access & Barclaycard Accepted
Large Stocks - 24 Hour Despatch
Carriage 46p

**5 FREE ACORNSOFT
GAMES & CASSETTE
RECORDER WITH EVERY
BBC SOLD**



Electronequip is an authorised Acorn service centre and has been an Acorn dealer since the introduction of the Atom. Our demonstration facilities include 20 station Econet and Torchnet systems.

Ref.	BBC Micros	Ex VAT	Inc VAT
ANB01	BBC Model B Micro Computer	348.26	399.00
ANB02	BBC Model B with Econet Interface	389.14	446.00
ANB03	BBC Model B with Disc Interface	409.14	469.00
ANB04	BBC Model B with Disc & Econet Interface	450.01	516.00

3" Micro Disc £129.95
(inc. VAT)

**Disc Interface &
Drive**
£198.95 (inc. VAT)



Micro Disc Drive for the BBC Micro

The Micro disc drive offers a method of low cost quick access to programs. The drive is essentially a small version of a 5¼" disc drive and offers similar features to the larger drive. The data is stored on a 3" disc, this is enclosed in a protective hard plastic cassette which features a write protect switch. The micro drive requires the standard Acorn disc interface, but a new disc filing system rom. Acorn DFS may be exchanged for the micro DFS for £12.00. The new micro disc filing system can read and write to Acorn DFS discs. Thus if a 5¼ inch and a micro floppy were connected on the same cable files could be transferred between them.
Capacity: 80.64 K bytes **Transfer Rate:** 125k bit/s.

BRANCHES

FAREHAM: 59 WEST STREET (0329) 230670
KINGS LYNN: 17 TENNYSON AVE. (0553) 3782
MAIL ORDER: 36-38 WEST STREET
FAREHAM, HANTS. (0329) 230670



Electronequip

36-38 West Street, Fareham, Hants (0329) 230670



FIRST BYTE ELECTRON JOYSTICK INTERFACE

Printer
Interface
OUT NOW
Uses normal BBC printer commands
No software required!



ELECTRON JOYSTICK INTERFACE

Electron users! This is the add-on everyone wants. It's the new Electron switched joystick interface from First Byte - available now with free conversion tape that vastly extends your game range right away.

The interface operates with all 'Atari-style' 9-pin joysticks, and its many advanced design features put it way out in front for quality and reliability. That's why, to date 15 major software houses are already bringing out games that work directly with the First Byte Electron Joystick Interface - and many more are sure to follow.

FREE conversion tape - play all these top games right now

Every Electron Joystick Interface comes with a free conversion tape, so you can use some of the most popular games around right now:

- | | | |
|------------------------|------------------|--------------------|
| ● Killer Gorilla | ● Kamakazi | ● Lunar Rescue |
| ● Moonraider | ● Chuckie Egg | ● Bugblaster |
| ● Positron | ● Atom Smasher | ● Blagger |
| ● Croaker | ● Alien Break In | ● Bed Bugs |
| ● Swoop | ● Birds of Prey | ● Alien Dropout |
| ● Bandits at 3 o'clock | ● Galaxy Wars | ● Daredevil Dennis |
| ● Escape from | ● City Defence | ● Snooker |
| ● Moonbase Alpha | ● Monsters | ● Diamond Mine |
| ● Cybertron Mission | ● Pool | ● Vortex |
| ● Cylon Attack | ● Pengwyn | |

The conversion tape also allows you to configure most other games for joystick control.

Games specially for the First Byte Interface

All these major software houses are bringing out games that work with the First Byte Electron Interface, with no conversion tape needed.


- | | | | |
|-----------------|------------|------------|---------------------|
| ● Alligata | ● Romik | ● Aardvark | ● Software Invasion |
| ● A & F | ● Bug-Byte | ● Optima | ● MRM |
| ● Program Power | ● Visions | ● Postern | ● Beebug-soft |
| ● Superior | ● Virgin | ● Phoenix | |

The First Byte Electron Joystick Interface - available now from all good dealers and W. H. Smith.

Look at these advanced design features.

Works with all 'Atari-style' 9-pin joysticks and utilises rapid-fire mode on Quickshot 2.

Only 2 chips for ultra-high reliability and low power consumption ensuring safe operation with the Electron.



Custom-built, colour-coordinated case in high-impact plastic. Special fitments ensure that when the joystick is plugged in, the case takes the strain, not the soldered joints.

Gold-plated connectors ensure a perfect contact. Metal polarising key and nylon end caps ensure positive locking.



A GENUINE FIRST BYTE
ADD-ON

First Byte Computers,
10, Castlefields,
Main Centre, Derby.
DE1 2PE
Tel: Derby (0332) 365280

Concern over CES move to Acornsoft HQ

ACORN is to re-organise its educational arm CES—but managing director Chris Curry has set out to reassure the educational establishment about the future of the group.

CES (Computer Education Service) was taken over from ICL by Acorn last October and now the group is to move from Maidenhead to come under Acornsoft's wing.

The five programming staff have been asked to move to Cambridge, some having the option of jobs in Acorn International and staying in Maidenhead. The information officer has, however, been made redundant as her role is to be taken over by staff already in Cambridge.

Closer

Chris Curry explained: 'Educational software will continue to be the responsibility of CES, but the group will come under the aegis of Acornsoft management.

'We are going to increase the scale of CES operations and put more people and money into CES. It must be closer to the body of the company to prevent duplication.'

Reputation

CES has gained a good reputation and established a close liaison with many schools, including providing people to help with courses.

Howard Curtis, chief examiner of 'O' level computer studies for the Joint Metriculation Board, told *Acorn User*: 'CES has my full support and I think it is a pity the changes have been made without consultation—and that they're losing a dedicated information officer.'

'Schools and advisers are crying out for help and CES is one of the bodies they look to. CES gives Acorn a friendlier face than exists within the rest of the company.'

Colin Monson, adviser for more than 400 schools in Berkshire, also expressed concern: 'Our contact with Acorn is through CES, as we have found it difficult to go to Acorn, and the dealers know little more than we do.'

Acorn focuses on video discs

ACORN is to set up a special group to develop its interactive video disc technology and keep the company's lead over Japanese competition.

An interface will be launched before the end of the year to enable the BBC micro to control video discs running on the Pioneer system. And in the spring a special unit will be released combining the BBC's intelligence with the interface and software.

Acorn MD Chris Curry told *Acorn User*: 'The interactive video centre will be run from the HQ of Acorn International in Maidenhead. It will concentrate on further development. There will be a promotional force to sell equipment and generate links with industry for training. Another team will create course material.

'We have a good start in the field, but the Japanese are snapping at our heels.'

At present video discs can



Curry: 'Japanese at our heels'

only have information read from them, although Acorn's recent deal with BSR in Hong Kong aims to develop read-write laser discs. The great advantage of video over floppy and hard Winchester discs is their storage capacity.

Curry sees a big market for the present technology with interactive video, programs and data mixed on one disc.

Acorn first demonstrated a BBC micro controlling video

18 months ago at the BBC's exhibition in January 1983. The system controlled film of birds in flight and then asked questions which were answered on the Beeb's keyboard.

The BBC is already considering doing material for schools to back up TV series. Peter Bratt, producer of the *Science Topics* series said: 'The BBC is very interested in the possibilities of interactive video and the Acorn interface will make our life easier.'

'One of the *Science Topics* programmes is being considered at the moment as a high priority to base an interactive disc around. However it's not something we would rush at.

'If we did go ahead it would be an important step and we want to get it right—not just illustrated CAL. We would want to take full advantage of interactive video.'

News for schools database service

by Geoff Nairn

NEWS International, owner of *The Times*, looks set to launch a 'dial-up' information service for schools.

A variety of educational news and information will be put on a large database which could then be accessed using a telephone and modem.

A trial service has been running using a closed database on Telecom Gold (British Telecom's electronic mail network), to send the information around the country.

If the scheme is given the go-ahead, a much-reduced subscription charge will have to be negotiated with BT to run on Gold, for the standard subscriber has to pay £100 to join and then a minimum of £10 per month—plus phone bills. The other option would be for News

International to set up its own computers to run the database.

The trials has been running in several schools for six months—although no-one will say where. In fact News International has refused to discuss the project at all. A final decision has yet to be taken on the format and extent of the scheme, but it would obviously be of immense benefit to schools and information technology in general.

Micronet stars

STAR NET is a space war game now on Micronet—with up to 1000 players at a time. Each move costs 10p, but there is a prize for the first emperor of the 3000-star universe.

Professionals on-line to DB

SPECIALISED 'dial-up' database services already exist in this country, but they are expensive to use. Eurolex caters for the legal profession, and enables lawyers to study the latest cases and access a library of more than 44,000 reports. In total, 300 million words of legal information reside in the computer data files. It can be accessed using Telecom Gold, or indeed by dialling an ordinary phone number; but at £75 an hour few amateurs would want to use it.

The British Library runs Blaise, which enables provincial libraries to see what books are held at headquarters. The Polis database is a computerised version of Hansard, the House of Commons' journal.

British and American news services have been using computers for some time. Reuters has a very successful database service for financial news and its reporters send in copy from portable computers.

THREE NEW PROGRAMS FROM MICROTEST

DAIRYFILE FOR DAIRY FARMERS

Keep on that economic line between over and under feeding!

Save time recording milk yield and calculating feed amounts!

Quickly decide feeding policy with the 'Monthly Calving Group' Performance Graph!

Print out a recording sheet with cows in numerical order. Print out graphs or tables of individual cows or Monthly Groups showing serving and pregnancy details, illness record, Calving Index, weekly and running total Margin over Concentrate. See at a glance cows due for serving, pregnancy diagnosis and drying off. Keep track of weekly total feed cost and milk sale price.

All this and more with DAIRYFILE.


Predict cow or Monthly Group total lactation yield. Compare with Standard Lactation Curves. All old data preserved - compare Monthly Groups over the years. Which is the most profitable month?

Find out with DAIRYFILE - for up to 200 lactating cows.

£69.00 inc. VAT (disc only) + p&p 50p

2 x 40 Track Drives Required or 1 or more 80 Track Drives. Please state which when ordering.

SATAN'S CHALLENGE or (Nevil Rides Out)



A Black Magic Adventure

Dare you take up the challenge laid down by the most evil and sinister of all beings... the devil himself. If you do you will find yourself alone and at the mercy of the twisted fancies and whims of a cold and calculating mind.

Occult forces are threatening the lives of those near and dear to you. Their only salvation rests in your hands but in accepting the challenge your own existence is put in severe peril.

In taking up the challenge you have to find The TALISMAN and locate a pentagram which then has to be prepared for the final rite. In the meantime dark forces will be opposing you making a difficult task almost impossible.

Do not allow yourself to be lulled into a sense of security for it will be short lived. Many have gone before only to swell the ranks of the damned.

This is the latest adventure from the stables of Microtest and has been written with the acclaimed features of other adventures in mind e.g save facility, quick response, simple but extensive commands, a mixture of logical and friendly problems to solve.

Be warned this is an easy adventure to get into but devilishly difficult to end.

Cassette £7.95 inc. VAT Disc £9.45 inc. VAT + p&p 50p Disc 40 or 80 Track.

MICROTEST FONT ROM.

This exciting new ROM from Microtest will enable you to get all sorts of new characters and fonts from your BBC Computer. Once you have produced your masterpiece on the screen, all you have to do is use the inbuilt screen-dump utility to produce a hard copy on to paper.

Typing *HELP FONTS gives a list of available fonts and the blocks of characters which they replace.

Available fonts are:

- *Accents Accents and miscellaneous.
- *Block Small capitals.
- *Data Like the bottoms of of cheques.
- *Greek It's all Greek to me too!
- *Joined Standard capitals with joined up lower case.
- *Maths A mix of until now unobtainable Mathematical symbols.
- *Miscellaneous A few oddities which often are very necessary.
- *Thick Thick text (for MODEs 0&3) to enhance 80 column mode.
- *Thin Thin text (for MODEs 2&5) which makes modes 2 & 5 much more readable or perhaps "READABLE".
- *Vertical For labelling graphs.

The ROM has a dump facility which will produce a screen dump of any MODE for 0 to 6 on an Epson, Star printer, CTI CP80 or MT80.

The ROM uses absolutely NO user memory and can be used with word processors etc. as well as normal BASIC programs.

£17.50 inc. VAT + p&p 50p

Microtest Starstick ROM & Joystick Package

Now available the Starstick ROM and Joystick. This comes in three forms:



Enables you to use our joysticks even on programs that do not offer joystick capability.

- (A) The Starstick ROM and Quickshot I Joystick
Price 17.95 + VAT = 19.84
- (B) The Starstick ROM and Quickshot II Joystick
Price 19.25 + VAT = 22.14
- (C) The Starstick ROM and patch lead, choose your own Spectrum/Atari style joystick
Price 15.25 + VAT = 17.54


Post and Packing £1.00 inc. VAT per item

This enables you to plug the Rapid action self centring joysticks until now only available for the Spectrum/Atari/CBM machines into the user port of the BBC. Model A users please note NO ANALOGUE INTERFACE REQUIRED.

Disc Users Note - pressing BREAK, SHIFT-BREAK or CONTROL BREAK does not modify or destroy the STARSTICK software so Disc Users please feel free to Boot!

The software patch provided in the ROM is interrupt driven and adds the following commands to your computer.

- * STICK turn on the STARSTICK ROM
- * NSTICK turn off the STARSTICK ROM
- * SETSTICK set up joystick to users spec
- * SAVE "NAME" 140 160 saves your user-key protocols
- * ADVAL emulate standard analogue joysticks
- * PAUSE define key to Freeze game
- * NPAUSE turn off ability to freeze game
- * "NAME" predefined key protocols set up for software houses programs
- * HELP KEYS displays currently selected key protocols
- * REPEAT enables auto-repeat fire
- * NREPEAT disables auto-repeat fire



DEALER ENQUIRIES
and
EXPORT ORDERS
WELCOME

available from

MICROTEST LTD

18 Normandy Way, Bodmin, Cornwall PL31 1EX

Telephone: 0208 3812

OR ANY GOOD DEALER

Large picture shows BBC Computer System and a Quickshot II Joystick. Small inset just a few of the joysticks that will work with the patch lead. Screenshot by kind permission of SUPERIOR SOFTWARE

VISA





Super Champ enters UK ring

THE Super Champ, claimed to be the top-selling joystick in the US for the last two years, is now available in the UK.

Its distributor, Dean Electronics of Ascot, says it has several features so far not available to UK games players: 10 feet of retractable cable; a contoured handle to suit both left and right-hand players; and a swivel base with suction cups for single-handed control.

It is compatible with the Electron and BBC B through an interface and costs £12.95 through high street stores or direct (£1 for p&p) from Dean Electronics, Glendale Park, Fernbank Road, Ascot, Berks.

The end for 'A'

THE BBC model A micro will no longer be sold from September 1984. This is, says Acorn, because it accounts for only a small percentage of BBC microcomputer sales.

Orders for the model A will be honoured up to August 31.

Sales of both models A and B since the launch of the BBC micro in 1982 now exceed 300,000 units worldwide.

Budget monitor

OPUS has launched a high resolution monitor that it claims costs about £100 less than its rivals.

It is a 14in RGB monitor manufactured by JVC and costs £279.39, including VAT, cable, delivery, manual and a year's guarantee.

Resolution is 580 x 470 and display 80 x 25.

Opus also markets a medium resolution monitor (370 x 470) at £221.89. Both are available from Opus dealers.

Indian schools to take Beeb micros in bulk?

INDIA could soon become Acorn's biggest overseas market—the jewel in the computer company's export crown.

Information Technology Minister Kenneth Baker has already held out the prospect to Parliament, predicting that the BBC micro is set to become the standard educational micro in Indian schools.

But what the Minister failed to mention was that the super-salesman whose efforts helped pull off the coup was ... Her Majesty the Queen.

For it was her gift of half-a-dozen Econet systems to the Indian President Zail Singh during the Royal tour last year that helped lay the foundations of this potentially huge export market.

A joint working party has already been set up between the Department of Trade and


Industry and the Indian government to examine the long-term provision of British micros.

The Beeb, though, is already doing very well in the Indian market—based on its success in providing the overwhelming majority of micros in the British government's schools scheme.

The growing overseas prospects are not confined to India however. More than 30 countries have sent educational teams to the United Kingdom to study how Britain has established its computer education programme.

The result, according to Mr Baker, is that Acorn and other companies involved in the schools scheme are now selling abroad 'in substantial quantities.'

The current Micro-computers in Schools scheme



Kenneth Baker: boasts success

is due to end in December.

The Minister told MPs: 'The scheme has undoubtedly been a success and we can rightly boast that we are, in terms of education, the most advanced in the use of computers.'

Now Department of Trade and Industry officials are looking at whether further support schemes are necessary.

This short section of text illustrates some of the facilities available when typesetting with TypeWise and the Anvil System.

Typefaces

The new Wordwise print control codes IT (italic) and B0 (bold-face) are used for *italics* and **bold** respectively; ' and , followed by ~ or V produce ^{superscript} and _{subscript} in the same way as Wordwise does using its OC codes on a full-function printer. The codes T(no.) and H(no.) are used to change text and heading styles, which may be any or all of type-size, type-face, line-advance, linelength, indents and justification.

Typewise example

Your text typeset

WORDWISE users can now have their text professionally typeset. The service, which lets you have direct control of such things as type font, type size and headings, is provided by Somerset company Wordsmiths.

With its *Typewise* system, the user has, in addition to the normal Wordwise embedded commands which set such things as margins and tab stops, extra 'typestyle' commands embedded in the text. These are ignored by Wordwise, but if a text file using these additional commands is sent to Wordsmiths, it will be typeset on their computerised

Anvil system. The cost works out at about 75p per 'k' of text.

A program called *Read* is available at £25 to complement the service. This will display your files on the screen with all the control codes highlighted. This gives you some idea of how the text is going to appear in print.

Wordsmiths has run the Anvil service for Wordstar users for about two years, and several computing books for the Beeb and Electron have been produced using it, including *Beyond Basic*. But this is the first typesetting service for a cheap wordprocessing package on a Beeb.

Switch on to amateur TV


DESPITE the range of broadcast and cable TV services now available, it seems that some people are still not satisfied. Amateur TV, using the Slow Scan TV system, is becoming increasingly popular—especially among the amateur radio brigade.

One such 'ham', John Melvin, has developed an add-on for the Beeb which enables you to receive SSTV transmissions and display the pictures on the monitor screen.

The unit plugs into the Beeb's I/O port and comes complete with software and demonstration TV pictures.

Previously, the reception of SSTV required expensive equipment. At £93—or £17.50 for just the construction details—John Melvin's solution is considerably cheaper.

For further information contact John Melvin at 2 Salters Court, Gosforth, Newcastle, or if you are a ham give him a call—his shortwave call sign is G3LIV.



Powertran robots, from left to right: Genesis P101 at £1700, Micro Grasp at £312, Hebot at £115, and Genesis P102 at £1200

CALLing all educationalists

THE use of computers is one of the most debated subjects in education, with little sign of a consistent policy in schools. CAL 85 is a symposium which hopes to alleviate the confusion.

CAL, computer-aided learning, means learning with, rather than about, computers. The meeting will take place from April 10-13 next year and will include workshops, lectures, exhibitions and demonstrations.

The organisers are keen to attract delegates from all levels of education and emphasise the desire to see participation from primary and secondary schools.

Readers who would like to give papers or have ideas for workshops should contact Richard Phillips at the Shell Centre, University of Nottingham NG7 2RD.

Z80 'gift' in Torch package

GCC is set to follow up its Starbase database software with a set of CP/M financial packages to run on the Torch Z80 second processor.

First is the *Sage* integrated accounts program which comes with the Z80 thrown in at £431. Next is a spreadsheet called *Cracker*, designed to work with 80-track, double-sided disc drives.

GCC has exclusive rights to implement *Sage* on the BBC micro, with customers getting a free Z80 for the price normally charged for the software alone.

Cracker was described by Barry Billingham at GCC as very friendly and more power-

ful than Perfectcalc. It will take DBase II files and should come in at under £200.

At the end of July an update to Starbase on disc will enable it to work with Computer Concepts' Wordwise word processing chip.

Later in the year, a memory board will be released which will hold up to four 8k RAMs and 16 ROMs.

The Z80 second processor supplied with Sage comes in a wedge-shaped box which is smaller than a standard disc drive. Included with it is a sideways ROM and the Torch CP/N operating system on disc. It connects by a single cable to the BBC's Tube interface.

Four ways to make a robot connection

FOUR robots from Powertran Cybernetics can all be connected to the BBC micro, although you'll need to be able to assemble them and write the software yourself.

Top of the range is the Genesis P102, which has a built-in microprocessor, memory and control box. It costs about £1700. A simpler version, the P101, is £500 cheaper. Both come with RS232 connections, but they are capable of being used on their own.

Micro Grasp is an electrically powered arm costing £312, and Hebot is a turtle at about £115. These prices include a special interface board which is configured for a Sinclair, but can be adapted for the BBC. These two plug into the user port.

The turtle includes collision detectors, retractable pen, flashing eyes and a horn! It also features two-wheel drive.

The Powertran robot kits are designed mainly for computer studies courses and as extensions of control studies. Assembly instructions and tips on programming the devices are included in the price.

Details from Powertran Cybernetics, Portway Industrial Estate, Andover, Hants SP10 3AA.

Adventurous line in learning

STORY is an educational program for children which enables them to write their own illustrated stories. As the text develops, certain keywords trigger off pictures displayed on the screen.

There are 64 pre-pro-

grammed pictures in the software, up to seven of which can be used in each composition. Once the story has been completed, it can be saved and printed out.

Story costs £7.50 from H&H Software on cassette. Disc ver-

sions are also available. The program comes with a 16-page booklet.

Readers with Concept keypads can help children develop shape and letter skills with two programs from LTS of Studley, Warwicks at £9.95 each.

Reliable Original Microcomputer Software



Available from all good BBC Computer Dealers.
Available by Mail Order from Computer Concepts, 16 Wayside, Chipperfield, Herts WD4 9SJ.
Or by 'phoning with your credit card number on (09277) 69727.



TORCH UNICORN

Designed with a total expansion capability

The Torch upgrade will give you a sophisticated business/professional system. However it doesn't stop there — it gives you the potential to expand — an expansion that no other current system can offer. Today, (not promises of 'one day'!), we are able to offer Hard Disc capability, networking of up to 254 machines, right up to the extra processing power of a 68000 32bit processor with 256K RAM, and optional UNIX operating system. **The potential is here!** The TORCHNET system, (software is included with all systems!), is a cost-effective method of linking office computing equipment in a simple and expandable fashion. TORCH means communication, whether it is inter-room communication, automatic 'home-to-office' communication, or electronic mail allowing a Torch user to initiate telex transfers, send tele-messages, use Electronic Mail (e.g. Telecom Gold), and talk to large mainframes. — **The potential is here!** Hardware is of no use without a suitable range of software, and the Torch can choose from a massive range of business, financial, application and language software. (Did you know that the Torch system has five times more software available for it than the IBM PC!) Why not contact us for your requirements?



TORCH BBC ADD-ON PRODUCTS

TORCH Z80 DISC PACK

The proven upgrade for the BBC Micro. Comprising 2x400K disc drive, Z80 processor with 64K of memory, and a CP/M compatible operating system. The system is supplied complete with the PERFECT software range including PERFECT WRITER, PERFECT SPELLER, PERFECT CALC, and PERFECT FILE. Full TORCHNET software is also supplied allowing sophisticated networking between other units.

NEW TORCH Z80 PACK PRICE £699.
SOFTWARE PACKAGE INCLUDES Z80 BASIC

The TORCH Z80 SECOND PROCESSOR CARD — for those who already have suitable disc drives. The card is supplied with all the free perfect software and Z80 basic, as detailed above, presenting a very attractive package. **£299.**

VIDEO DIGITISER

Supplied complete with integral power supply, and ROM based software, it interfaces with the computer via the 1Mhz bus. A signal supplied from any standard video camera/recorder will supply a high quality picture, with eight different grey scale levels. The friendly yet sophisticated menu-driven software comes complete with an Epson printer dump. **£250(a)**

MICROTEXT

Developed by the National Physical Laboratory, is a programming system designed to simplify the production of a wide range of man-computer dialogues. Using MICROTEXT, an expert in any field can construct their own complete courses of computer-based instructional material. Applications include interviewing systems, teaching packages, training courses and interactive demonstrations and simulation. Cassette **£43.35(c)** Disc **£52(c)**.

ACORN COMPUTER SYSTEMS

BBC Model B	£348.00a
BBC Model B + Econet	£389.00a
BBC Model B + DFS	£429.00a
BBC Model B + DFS + Econet	£470.00a
6502 2nd Processor	£175.00b
Acorn Z80 2nd Processor	£263.00a
Acorn Electron	£169.00b
BBC Teletext Receiver	£195.00a
BBC Dust Cover	£4.00d
Pair of Joysticks	£11.70c
Acorn Bit Stick	£3.28b

TORCH Z80 SYSTEM

TORCH Z80 Disc pack	£699.00a
TORCH Z80 2nd Processor Card	£299.00a
TORCH ZHD240 20Mb	£1995a

UPGRADE KITS

A to B Upgrade Kit	£75.00d
DFS Kit	£95.00d
Econet Kit	£55.00d
Speech Kit	£47.00d
Installation	£15.00
Installation	£25.00
Installation	£10.00

ECONET ACCESSORIES

Printer Server Rom	£41.00b
File Server level 1	£86.00b
File Server Level 2	£216.00b
Clock + 2 Terminators	£92.00b
Econet User Guide	£10.00d

BBC FIRMWARE

1.2 Operating System	£7.50d
Basic II Rom	£32.00d
View Word Processor Rom	£52.00c
Wordwise W/P Rom	£34.00c
BCPL ROM + Disc	£87.00b
Disc Doctor Utility Rom	£28.00d
Termi Emulator Rom	£28.00d
ULTRACALC Rom (BBC Publications)	£65.00c
Gremlin debug rom	£28.00d
Computer Concepts Graphics Rom	£28.00d
EXMON	£20.00d
TOOL KIT	£20.00d
Printmaster Rom (FX80)	£28.00d
Communicator Rom	£59.00c

BBC ANCILLARY HARDWARE

EPROM Programmer	£89.00b
Smartmouth Speech Synthesiser	£37.00b
RH Light Pen	£39.50b
"Time-Warp" Real-Time	£29.00b
Clock/Calendar	£29.00b
ACORN IEEE Interface ANKOI	£282.00c
Buzzbox Modem	£69.00b

PRINTERS & PLOTTERS

EPSON FX-80	£325.00a
EPSON RX-80 FT	£250.00a
EPSON FX-100	£480.00a
EPSON DX-100	£375.00a
Printer Share + Cable SEI	£88.00c
JUKI 6 100 Daisy wheel	£350.00a
MCP40 Col. Printer/Plotter	£110.00a

Accessories:

Parallel Printer Lead	£10.00d
Serial Printer Lead	£8.00d
Epson Serial Interface 2K 8148	£50.00c
Epson Serial Interface 8143	£35.00c
FX80 Dust Cover	£4.00d
Epson Paper Roll Holder	£17.00c
FX-80 Tractor Attachment	£37.00c
PAPER Fanfold 2000 sheets	£13.50b
Ribbon MX80/RX80/FX80	£6.50c
Ribbon MX/RX/FX100	£12.50c
Gemini Delta 10	£300.00a
Grappad Graphics Tablet	£125.00c
Graphics Plotter/Workstation	£490.00a
Basic Plotter	£270.00a
PSU12	£45.00
PSU24	£79.00
Power Adaptor Cable	£4.50
Software on disc	£3.50
Driller/Router	£79.00
Opto Sensor	£72.00

COLOUR/GREEN MONITORS (leads incld)

Microvitec 1431 14" RGB Std Res	£179.00a
Microvitec 1431 14" RGB/PAL + Sound	£225.00a
Microvitec 1451 14" RGB Med Res	£295.00a
Microvitec 1441 14" RGB Hi Res	£420.00a
Microvitec 2031 14" RGB Std Res	£287.00a
KAGA Vision Ex 12" RGB	£195.00a
KAGA Vision II Hi Res	£260.00a
KAGA Vision III 12" RGB Super Hi Res	£358.00a
KAGA 12" Green Hi Res	£106.00a
SANYO DM8112CX 12" Green Hi Res	£99.00a
KAGA RGB Lead	£6.50d
BNC Green Screen Monitor Lead	£3.00d

BBC COMPATIBLES 5.25" DISC DRIVES:

(All include cables, manual + format disc)	
100K (40 Track Teac	£120.00a
100K (40 Track) with psu Tec	£145.00a
200K (40/80 Track) Teac	£175.00a
200K (80 Track) with psu Tec	£190.00a
400K (80 Track DS) with psu	£185.00a
400K (80TDS) with psu Mitsubishi	£225.00a
2 x 100K (40 Track) with psu Teac	£300.00a
2 x 200K (40/80 Track) with psu Teac	£400.00a
2 x 400 (80 Track DS) with psu	£420.00a
3" Hitachi 100K Drive	£150.00c

ALL PRICES EXCLUDE VAT. Please add carriage 50p

GRAFPAD

A low cost graphic-tablet offering the performance and durability required for the business, industrial and educational user. It is small, accurate & reliable. Working area: 240 x 192mm + Menu area. **£125 plus CAD program £125(b)**.

MONITORS

MICROVITEC — a range of British Made DTI/ACORN Approved Std/Med/Hi-resolution RGB colour monitors that have a consistent, reliable performance. Also available in RGB/PAL/SOUND versions. The KAGA range provides a similar performance in 12" screen format. Our Japanese manufactured Hi-Res green screen **SANYO** is an ideal solution for high clarity 80 column text display. The **KAGA** green screen, with its 'chemically etched' anti-glare screen for the discerning user. All monitors are supplied with suitable leads at no extra charge.



GRAPHICS PLOTTER/WORKSTATION

Equally at home in the artists studio, hobbyists workshop, science laboratory, classroom, and production floor, this system has something to offer everyone. The 3-colour graphics plotter provides both precision and versatility. The carriage can be moved with an accuracy of 0.025 cm. over an A4 area — the plotter being able to accept paper and far thicker materials at sizes of up to A3. The basic colour plotter carries three colour pens each of which is software selectable. Various add-ons greatly increase the versatility of the unit, while still retaining the unit's accuracy. The servo controlled drill/router, and a scriber enables drilling, cutting and scribing in various materials. A unique Opto Sensor (using a Hewlett Packard Device) turns the plotter into a high resolution scanning digitiser to read and store whole diagrams, for example, for use in map work. This unique versatile Workstation is supplied complete at **£490**. Basic Plotter **£270**.

Our in depth stocks allow us to offer immediate deliveries on most items and our aim is to provide the best available products at competitive prices. In addition to the items listed above we carry extensive stocks of: connectors, connector assemblies, components including TTLs, CMOS, RAMS, EPROMS and CPUs. Spares for the BBC computers are normally available from stock. Orders from government departments, public bodies, hospitals, schools, colleges, universities and recognised PLCs welcome. We specialise in world wide exports. No VAT on exports. Our specially negotiated freight charges to many countries ensure the customer considerable savings on charges.

Everything you need for your BBC Computer

Plus friendly service and professional advice

Accessories:

Single Disc Cable	£6.00d
Double Disc Cable	£8.50d
3M DISCS with Lifetime Warranty	
40T SS/DD	Pkt of 10 £16.00c
40 DS/DD	Pkt of 10 £22.00c
80T SS/DD	Pkt of 10 £26.00c
80T DS/DD	Pkt of 10 £30.00c
3" Double Sided Disc	Each £4.50c
FLOPPICLENE Drive Head Cleaning Kit	£14.50c
Disc Library Case	£1.90d
Disc File Case 30/40	£8.00c
Disc Lockable Case 30/40	£15.00c
Disc Lockable Case 60/70	£27.00b

EPROMS:
Please phone for availability

SOFTWARE:

ACORN/MERLE BUSINESS SOFTWARE
Invoicing, Stock Control, Accounts Payable,
Accounts Receivable, Order Processing
Mailing System Each £22.65d

GEMINI Business-Full Range
ACORN SOFT-Full Range
ACORN LANGUAGES including BCL, LISP
S.Pascal Disc £17.30d
BCPL Calculations Disc £17.30d
FORTH with Manuals
BBCSOFT-Full Range
PROGRAM POWER-Full Range
BEEBUGSOFT-Full Range
Wordwise Spellcheck Disc £16.50d
Design £16.50d
Superplot £16.50d
Masterfile (Database) £16.50d
Teletext Pack (Mode 7 Graphics) £16.50d

CASSETTE RECORDERS:

SANYO DR 10 1 Data Recorder	£30.00b
Datex Slim Line	£20.00c
BBC Tape Recorder	£28.50b
Cassette Lead	£3.00d
Computer Grade C-12 cassette	£0.45d
Computer Grade Cassette 10 off	£4.00c
Phillips Mini-data cassette	£3.00d

BOOKS (NO VAT) p&p £1.50/book

Let Your BBC Teach U to Program	£3.50
BBC Micro Revealed	£3.00
100 Programs for the BBC	£6.95
30 Hour Basic	£5.95
35 Educational Progs	£6.95
6502 Applications	£9.75

6502 Assembly Lang Programming	£12.95
6502 M/Code for Beginners	£5.95
6809 Assembly Lang Programming	£13.95
Advanced Prog Tech for BBC	£7.95
Advanced 6502	£10.25
Advanced User Guide	£12.50
Assembly Lang Pro on the BBC	£7.95
Assembly Lang for the BBC	£7.95
Assembly Lang Prog for Electron	£7.95
Assembly Lang Prog for Electron	£7.95
Assembly Lang Programming	£8.95
Basic Prog on the BBC	£5.95
BBC Basic	£5.95
BBC Basic for Beginners	£6.95
BBC Micro for Beginners	£6.95
BBC Micro Compendium	£14.95
BBC Micro Disk Companion	£6.95
BBC Micro Expert Guide	£6.95
BBC Micro Graphics & Sound	£6.95
BBC Micro in Education	£6.50
BBC Micro Revealed	£5.00
BCPL User Manual	£15.00
Beyond Basic	£7.25
Creating Adventure Progs	£6.95
Creative Graphics	£7.50
DIY Robotics & Sensors	£6.95
Discovering BBC M/Code	£6.95
Forth	£7.50
Friendly Computer Book	£6.95
Graphics on the BBC Micro	£6.95
Graphs & Charts	£7.50
Interfacing the 6502	£10.95
Intro BBC Micro	£5.95
LISP	£7.50
Making Music on the BBC Computer	£5.95
Micro Basic Sound Graphics	£7.95
MOS Memory Data Book	£3.95
Prog the BBC Micro	£6.50
Programming the 6502	£9.95
Programming the 6809	£11.35
Programming the 8086/8088	£10.95
Programming the BBC	£6.50
Programming the Z80	£9.95
Start Prog with Electron	£6.95
Structured Programming	£6.50
The Electron Book	£7.95
TORCH Z80 Disc Pack Guide	£10.00
TTL Data Book Vol-1	£9.00
TTL Data Book Vol-2	£8.50
BBC User Guide	£15.00
Using BBC Basic	£10.00
Using Floppy Disks	£6.95
Using the 6502 Assembly Lang	£14.50
Z80 Applications Book	£10.95


MANY MORE BOOKS IN STOCK

ULTRACALC

With advanced features, such as: *Handling of labels as well as numbers, as values, allowing the search of a list by a meaningful name, instead of just a number. *Efficient memory usage allowing large spreadsheets to be constructed. *Variable width columns. Facilities include SUM, Replicate & most mathematical functions. It helps you to create and manipulate *Budgets *Cash-Flow forecasts *Price Lists *Balance Sheets *Time Sheets *Order Entry *Small Databases *Scientific Calculations etc. **£65.**

DISC DRIVES:

A full range of disc drives fitted with quality Japanese slimline mechanisms, (such as TEAC, MITSUBISHI etc.) are supplied ready to connect to your BBC, and come complete with necessary cables, formatting disc, manual etc. TEAC & MITSUBISHI mechanisms can operate in single and double density modes. The switchable disc drives give the user flexibility, by allowing access to both 40 & 80 Track discs. We have a full range of diskettes, variety of disc storage cases, disc-drive cables. The Floppiclene head cleaning kit is the



Switchable single 400K and 800K Drives now in stock

ideal way to ensure optimum performance of your drives. The use of disposable cleaning discs eliminate the risk of recontamination and abrasion, and ensure continuous data capture and transmission.

SCOTCH 3M FLOPPY DISCS

We now stock the high performance yet economical 3M range. Due to advanced production techniques, a higher standard has now been reached, enabling Scotch to guarantee error free performance for life.

3" HITACHI DISC DRIVES

The latest in miniature data-storage technology. Totally hardware & software compatible with 5 1/4" drives (can be used together!). Supplied complete with format disc, manual, cables etc. **£150(b).**

ACORN IEEE INTERFACE

A full implementation of the IEEE-488 standard, providing computer control of compatible scientific & technical equipment, at a lower price than other systems. Typical applications are in experimental work in academic and industrial laboratories. The interface can support a network of up to 14 other compatible devices, and would typically link several items of test equipment allowing them to run with the optimum of efficiency. The IEEE Filing System ROM is supplied. **£282.**

TELETEXT


Converts your BBC into a fully fledged Teletext Terminal. In addition to normal reception of Teletext pages, it is able to 'download' software as well as saving standard pages on any of the four TV channels. **£196.**

Continued on page ...

INSTITUTIONS & EDUCATIONAL ESTABLISHMENTS

Our bulk purchasing power enables us to provide very competitive quotations, as well as being able to supply in quantity, a very wide range of equipment, accessories and spare parts from stock.

unless indicated as follows: (a) £8 (b) £2.50 (c) £1.50 (d) £1.00



PRINTERS

We have a range of printers that will meet most requirements. EPSON—the high quality dot-matrix printers that set the standard in the industry—versatile printers that provide the optimum in performance & reliability. The RX80/FT provides all standard printing & graphic functions, (single

sheets & perforated paper), with the de-luxe FX80 giving in addition proportional printing, italics, programmable characters etc. The FX100 also allows the use of 15" wide paper. Epson DX100—a new daisy wheel has the hallmark of Epson's quality performance and reliability. The JUKI and BROTHER daisywheels provide a quality normally found in printers costing far more. Printer cables, interfaces, ribbons, paper etc. are all normally available from stock.

6502 2nd Processor & Bit Stick now in stock.

BUZZBOX

This is a full specification, direct connect modem, with both Originate & Answer modes, allowing access to the many databases, bulletin boards, as well as inter-computer communications. The modem conforms to the international CCITT V21 300/300 Baud standard. (NOTE: Not suitable for PRESTEL). Having full BT Approval, it connects directly to the telephone line, for optimum performance. Being battery powered, it is totally portable (optional power supply available). **£69.** BBC Lead **£3.50.** External PSU **£8.00**

MAIL ORDER TO: 17 Burnley Road, London NW10 1ED
(Tel: 01-452 1500, 01-450 6597 Telex 922800)

SHOPS AT: NW London: 15 Burnley Road, London NW10 1ED
(Dollis Hill) 2 mins walk, ample car parking space
West London: 305 Edgware Road, London W2. Tel: 01-723 0233
(Near Edgware Road)

TECHNOMATIC LTD.

All prices exclude carriage & VAT. Please add carriage as indicated and add 15% VAT to the total order value. For fast delivery telephone your order quoting VISA or Access card or official order number
Minimum telephone order £5).

EPROMER II

Our current version of the highly popular Eprom programmer is now being enhanced to provide more and better facilities for easy programming by the user. The software will maintain its superiority over all currently available similar programmers. The range of eproms handled has been widened, to include

the eproms with lower programming voltage and eproms which can be programmed using algorithm. Control of all operations has been moved to the keyboard. The screen display has been improved to give more information. The screen editing facilities have also been modified to simplify the data entry.

Preliminary Information

- * The new Eprom Programmer will now program 2516, 2532, 2564, 2716, 2732, 2764, 27128 and 27256 + 5v eproms, and all but the 27256 in a single pass.
- * The programmer will be supplied with integral power supply, and interfaces with the BBC via the 1MHz bus. It is fully buffered and complies with Acorn protocols. There is no power drain from the computer.
- * No knobs or switches to fiddle with — total control from the keyboard
- * Fully software driven with easy to understand instructions displayed on the screen.
- * Eprom type selectable from the keyboard
- * Selectable programming voltage 25/21/12.5V
- * Defaults to normal programming with high speed algorithmic programming selectable, for a device with suitable capability.
- * Continuous screen display of eprom type, option and address range selected.
- * Full screen editor with HEX or ASCII input. Constant display of logical eprom address and the actual ram address.
- * Can read, blank check, program and verify at any address/addresses on the eprom.
- * Full Tape/Disc filing facility.
- * Several basic programs can be entered on a single eprom and called up with individual name.

EPROM ERASERS




UV1T Eraser with built-in timer and mains indicator. Built-in safety interlock to avoid accidental exposure to the harmful UV rays. It can handle up to 5 eproms at a time with an average erasing time of about 20 mins. £59 + £2p&p.
UV1 as above but without the timer. £47 + £2p&p.

SPECIAL OFFER
EPSON FX80
PRINTER
ONLY £325

including BBC printer lead
Twelve Months full warranty.
Offer valid while stocks last.

'TIME-WARP' REAL-TIME-CLOCK/CALENDAR

A low cost unit that opens up the total range of Real-Time applications. With its full battery backup, possibilities include an Electronic Diary, continuous display of 'on-screen' time and date information automatic document dating, precise timing & control in scientific applications, recreational use in games etc — its uses are endless and are simply limited by one's imagination. Simply plugs into the user port — no specialist installation required — No ROMS. Supplied with extensive applications software.
Please phone for details.
£29.00 + £2.50 carriage.



SMARTMOUTH

The original 'infinite speech'.
Still the best.

A ready built totally self contained speech synthesiser unit, attractively packaged with built-in speaker, AUX output socket etc. — no installation problems! It allows the creation of any English word, with both ease and simplicity, while, at the same time being economical in memory usage. You can easily add speech to most existing programs vocabulary, whole applications commercial, recreational etc. no need to plug into due to the SMARTMOUTH is supplied with demo and development programs on cassette, and full software instructions. £37 + £2.50 carriage.



Due to its remarkable infinite spectrum of computer — these include industrial, educational, scientific, No specialist installation — to open your computer, simply the the user port — and simple software, no ROMS are needed.

BEEBUGSOFT

A professional range of Firmware/ Software to suit both the advanced programmer and the user. From the well known 'EXMON' and 'TOOLKIT' to the WORDWISE SPELLCHECK.

STOP PRESS

- * Acorn/Prestel Adaptor now in stock
- * Z80 2nd Processor enquire about availability
- * See our other advertisement on page 14

MAIL ORDERS TO: 17 Burnley Road, London NW10 1ED
(Tel: 01-452 1500, 01-450 6597 Telex 922800)

SHOPS AT: NW London: 15 Burnley Road, London NW10 1ED
(Dollis Hill 2 mins walk, ample car parking space)

West London: 305 Edgware Road, London W2. Tel: 01-723 0233
(Near Edgware Road)

TECHNOMATIC LTD.

All prices exclude carriage & VAT. Please add carriage as indicated and add 15% VAT to the total order value. For fast delivery telephone your order quoting VISA or Access card or official order number.
(Minimum telephone order £5).

Action in Olympia

THIS year's Acorn User Exhibition, to be held at Olympia on August 16-19, looks set to easily top last year's show, with 35,000 people expected to pass through the doors.

About 140 exhibitors have booked stands, so there should be something for everyone. As you might expect, Acorn Computers will be there in force, as will your's truly *Acorn User* with a problem clinic for readers.

The education sector will be well represented with many familiar names—and quite a few new ones. ASK, Golem, Edsoft and Softcentre will represent the educational 'cottage industry', with MUSE and MEP as the Government-backed 'heavyweights'.

In among the usual plethora of peripheral suppliers are to be found several new products. Microware will be showing a new range of Epson 5¼in disc drives; and Silicon Disk, the RAM alternative to disc drives, will be available at a discount from Solidisk.

Two new modems will be putting in an appearance at the show. The first, the Nightingale, runs at 300, 1200 or 1200/75baud and so can access bulletin boards, Prestel and Telecom Gold. It is being marketed by Pace.

Even more interesting is the Loco Systems SCM 100 modem. SCM stands for Software Controlled Modem—in other words, a ROM chip that plugs into your Beeb to control the modem directly. The beauty of this is that there are no controls on the modem itself—the software automatically selects such things as baud rate and protocols depending on the service you've dialled. As they say, 'Approval is being sought' for both these modems.

With the arrival of Acorn's

Geoff Nairn reports on the big stories to emerge—so far—from the Acorn User Exhibition: amazing modems, spritely advances and software that exploits the 6502 second processor.

Plenty of peripherals and the programs to put them into action will be receiving their first public showing.

Arm-in-arm with a robot

R2D2—that lovable whistling dustbin from the film Star Wars—is rumoured to have his heart set on going to the Acorn User show.

Tony Dyson, the robot's maker, runs a company called Droid Factory which, from making promotional robots, has now gone down-market with a £400 robot arm for the Beeb. (Unfortunately R2D2 will not be for sale.)

As well as R2D2, Tony was also responsible for the robot seen showing John Cleese a thing or two in the recent Sony adverts on television.

The robot arm is based on an industrial version and is claimed to consume very little power as it uses servo motors rather than stepper motors. It also has inter-changeable



fingers which, although embarrassing to humans, is a plus point for robots.

R2D2, when asked to comment on Tony's latest protege, could only whistle '!!*??!'.

Ultra the android is the Droid Factory's latest offering at Unit 14, 70 Wooton Rd, Abingdon, Oxfordshire.

6502 second processor for the Beeb, the race was on to see who would be first to produce software which properly exploited it.

Well, Cardiff Micro Software has come up with a disc-based database program called Datafile which uses the second processor to store up to 3000 records on a double-sided, 80-track disc. Unusually, there is

also a version which runs on Econet.

Simonsoft is using the Exhibition to launch its new series of Beeb games. They concern Oz the caveman. Simonsoft also will be demonstrating Sprites Version 2—an animation package which can produce an 18-fold increase in speed over normal Basic.

The Educational Software


Micropower packs 'em onto disc

MICROPOWER is to make disc versions of its best-selling games available for the first time at the Acorn User Exhibition.

The top 11 will be on 5¼in discs at £9.95 each that run on 40 or 80-track drives. For those who have the games on cassette, there will be an exchange service. The company will swap a cassette for a disc for £4.95.

The games are: *Killer Gorilla*, *Rouble Trouble*, *Stock Car*, *Frenzy*, *Block Buster*, *Gouls*, *Jet-Power Jack*, *Felix in the Factory*, *The Mine*, *Cybertron Mission*—and one other to be launched at the show.

These discs and the rest of the range will be available only on mail order after the show (postage 55p extra).



15

AMS lets mouse loose

ADVANCED Memory Systems is set to let loose a pet mouse at the Acorn User Show. But before the Olympia officials call in a pest control officer, we should say that this mouse is of the non-furry variety.

AMS, who were first with the 3in disc drive, have now pulled off a similar coup with the first 'mouse' for a home computer. A mouse is a small hand-held box which, as you move it around the desk top, moves a pointer on the screen. Up to now only business machines such as Apple's Lisa have used mice; now the Beeb gets its own mechanical rodent.

AMS claims any program can be converted for use with the £70 mouse, in much the same way as a joystick. Four main uses are envisaged: word-processing; on-screen editing of programs; games; and graphics.


Company has some new programs for the Robin Lightpen, which talks as well as draws.

The show runs from August 17-19, 10am to 6pm (5pm on last day). On Thursday 16th, times are 10am to 7pm, with the morning reserved for the trade. Tickets cost £2, or £1 for under 16s.

For details of bulk discount tickets and the Exhibition, contact:

Computer Marketplace Exhibitions, 20 Orange St, London WC2H 7ED.

STAR *ATTRACTIONS*



DAISYWHEEL PRINTERS

BROTHER HR 15	13 cps	£349.95 + VAT = £402.44
STAR POWERTYPE	18 cps	£328.95 + VAT = £378.29
EPSON DX 100	18 cps	£369.95 + VAT = £425.44

DOT MATRIX PRINTERS

EPSON RX 80	100 cps	£198.95 + VAT = £228.79
EPSON RX 80 F/T	100 cps	£228.95 + VAT = £263.29
EPSON RX 100	100 cps	£384.95 + VAT = £442.69
EPSON FX 80	160 cps	£340.95 + VAT = £392.09
STAR GEMINI-10X	120 cps	£189.95 + VAT = £218.44
STAR DELTA 10	160 cps	£319.95 + VAT = £367.94
STAR RADIX 10	200 cps	£498.95 + VAT = £573.79

THERMAL MATRIX PRINTERS

STAR STX 80	60 cps	£129.95 + VAT = £149.44
BROTHER HR 5	30 cps	£129.95 + VAT = £149.44
BROTHER EP 44	16 cps	£216.95 + VAT = £249.49

PAPER — RIBBONS — SHEET FEEDERS — TRACTOR FEEDS
INTERFACES — CALL FOR BEST PRICES

GEMINI 10X

£189.95

+ VAT = £218.44



AFTER SALES SERVICE



12 MONTH GUARANTEE



BBC LEAD S £9.95 + VAT



DELIVERY £10 + VAT



DATASTAR SYSTEMS UK

UNICOM HOUSE 182 ROYAL COLLEGE STREET LONDON NW1 9NN
01-482 1711



TELEX 295931 UNICOM G



TAX-FREE EXPORT & DEALER ENQUIRIES WELCOME



ADD 40 COMMANDS TO BBC BASIC WITH ONE ROM

GRAPHICS

SCALE is a powerful and totally flexible statement that allows the user to take control of the scaling of the screen. Integers, real numbers and variables can be used.

ROTATE is used to 'rotate' the axes about a point and by an angle both defined by the ROTATE statement on a scaled screen.

CIRCLE and **ELLIPSE** allow a multitude of shapes to be drawn using a single statement, including: any regular polygon, circles, arcs, solid sectors, triangles, squares, etc.

FILL is used to 'fill' a previously drawn area, with **CFILL** setting the colour/pattern/shade within pre-drawn bounds.

TRANS is used to translate the scaled area across the screen by the use of cartesian co-ordinates, subsequent graphics commands making use of the now displaced scaled area.

Plus: SMOVE, SDRAW, SPLOT and UNSCALE.

4
IN
1

LLIST can be programmed, unlike LIST, and under the User's control, multiple statement lines can be split up into their component parts allowing for greater ease of reading.

LGOTO is similar to the GOTO statement but more powerful in that it enables the user to jump to 'labelled lines' allowing for neater and more readable programmes.

SORT allows the user to sort all or part of a string array into alphabetical order using a single statement. Invaluable for data processing.

SETWIN and **WIN** allow the user to define, using SETWIN, and display, using WIN up to seven complete windows on the screen. The user being able to select and return to previously de-selected windows at will, the cursor maintaining it's last used position within that window.

Plus: OPT, POPFOR, POPGOS, POPREP and ADDCOMM.

GENERAL

Compatible with: Acorn DFS,
Amcom(Pace) DFS, Watford DFS,
Wordwise, Disc Doctor.
Model B, BASIC 1 or 2, OS 1.20

ADDCOMM

Plus: *HELP displays the full syntax of all commands. Price includes a detailed ring-bound User Guide.

LOGO

LMOVE is used to position the LOGO cursor, usually used prior to further LOGO statements.

ANGLE is used to set the intended direction of the LOGO cursor, the angle being described in degrees.

ADVANCE is used to move the cursor in the direction as set by ANGLE by the distance described in the ADVANCE statement.

TURN gives the cursor a new direction by turning it a certain number of degrees anti-clockwise from its previous direction.

PEN defines the kind of trail left by the LOGO turtle using the internal plot codes.

LCIRCLE and **LELLIPSE** are the LOGO equivalents of the similar enhanced graphics commands, the shape centre being the current LOGO cursor position.

LPOS is used to return the position of the LOGO cursor from a SCALED screen.

£28

includes V.A.T. post and packing.

NOW AVAILABLE FOR

ELECTRON
WITH ROM BOARD

CHAR is a simplified 'character' designing facility using an enlarged grid that enables the user to quickly and easily construct or alter graphic and pseudo-alphanumeric characters.

COMPACT is used to reduce the size of all or part of an existing program by intelligently appending lines together.

FIND is used to search all or part of a program to find any desired character or set of characters.

GREP and **SREP** are two related commands that enable the user to replace a character or group of characters with any other character or group of characters, under total control of user.

LVAR is used to list all, or alphabetically selected, variable names currently within memory.

VERIFY is a simple command to confirm that a copy to tape or disc is exactly the same as the original program in memory.

Plus: MEM, GOODFROG, KILLREM and FKEYS.

HOLMI


These commands are unlike those on any other ROM, since they are used in exactly the same way as the standard BASIC commands - i.e. any numeric/string expression, multi-line statements, access to any variable, and, of course no stars!

VINE MICROS, MARSHBOROUGH,
SANDWICH, KENT. CT13 OPG.
(Or send stamp for Brochure.)

THE GREAT SUMMER SALE

100K (ACORN DFS) / 200K (DOUBLE DENSITY) BBC DRIVE
ONLY £110 + VAT = £126.50 Carriage £8 extra

FULL YEAR WARRANTY
 ACCESS WELCOME



* EDUCATIONAL ORDERS WELCOME!

* DEALER AND EXPORT ENQUIRIES INVITED

Slimline, half height, top quality disk drive from CHINON, Japan featuring full microprocessor control (no LSI gimmick!), quietest operation and lowest power requirement in the industry (+5V @ 450 mA and +12V @ 190 mA).

Beautifully boxed in metal case and in matching BBC colour and supplied complete with:

- ★ Disk Drive Cable and Power Lead
- ★ Formatter Disk
- ★ DFS Manual

TELEPHONE FOR INCREDIBLE PRICES ON FULL RANGE OF BBC DRIVES!

micronix computers Ltd
 Suite 2, 26 Charing Cross Road, London WC2. Tel. 01-240 0213/0217. Telex. 295173 VILORD G



ATOMIC MACHINE CODE

A book containing 23 fully explained machine code programmes for the Atom.

DATA SORTS ● MODE 4 CHARACTERS ●
 GAMES ● POOLS PREDICTION ● TOOL KIT ●

Over 50K of programmes in 1 book for £5.75 inc.
 Book and Cassette (source code) £15.50.
 Book and Cassette (ready to run) £15.50.
 Cassette only £11.50.



TOOL KIT

20 useful programmes for the BBC on one cassette.


BAD PROGRAMME LIST ● BAD PROGRAMME FIX ● FIND PROCS ●
 FIND DEFPROCS
 BIGLETTERS ● FIND BYTE ● FIND VARIABLE ● AND MANY OTHERS. ●

£3.95 inc.

ECCE Productions, 3/73 Station Road,
 Sidcup, Kent. DA15 7DR.
 Tel: 01-302 1667. (Mail order only)

EPROM PROGRAMMER FOR THE BBC

A very high quality product direct from the manufacturers, contained in attractive sloping box with low insertion force socket and neon indicator for programming fitted as standard, the software adopts the high efficiency method for programming 2764 and 27128. This allows up to 100% faster programming, software in machine code, supplied on cassette and can be placed in eeprom. Very easy to use, menu driven with easy to use instructions. This unit is completely self contained with its own power supply and plugs into the user port.



THIS PROFESSIONAL UNIT ALLOWS:

1. Will program: 2716, 2732, 2532, 2764 and 27128 eeproms.
2. Copy eeprom into memory and compute checksum.
3. Blank check eeprom.
4. Program eeprom from memory.
5. Verify byte by byte and compute checksum.
6. allow buffer start area to be changed.
7. All operating system calls may be used when in menu mode.
8. Semi-intelligent programming. Typical time to program a 2764 8k device is approx. 50 sec. depending on the data to be programmed.
9. Additional software supplied to enable your own program (basic or machine code) to be put into eeprom with the necessary leader information to allow calling with a *command. Downshift routine to enable basic programs to be run is also supplied.

COST £46.50 please add 15% VAT £1.00 post and package

ALSO AVAILABLE RAM/ROM CARD
 (Details on Request)

ORDERS TO:

**H.C.R. ELECTRONICS, Industrial Unit,
 Parker Road, Chelmsford, Essex CM2 0ES**

Access Orders Phone:

Chelmsford (0245) 350188 24 hours



Beeb in GLC competition

A BBC micro game has taken joint first place in a Greater London Council competition. The idea was to design a video game which would successfully get across the GLC's anti-racist message.

Competitors had a free hand over the type of game – but it had to include an anti-racist quiz consisting of 12 questions – for example, 'How many black people live in London' – before the game itself could be completed.

Ian Lambert's entry for the Beeb featured that familiar sight around London, the red double decker bus.

Ian is pictured receiving his cheque from GLC Leader Ken Livingstone.

Also in the picture are his son Ivan, Paul Boateng, vice-chairman of the Ethnic Minorities Committee, and John Carr, chairman of the Staff committee.



It's official – a Prestel adaptor

A VIEWDATA interface that links the BBC micro to Prestel and the electronic mail services has been launched by Acorn.

The Prestel Adaptor connects the Beeb directly to the telephone network, turning it into a powerful two-way computer terminal. The system can then automatically dial-up and access remote computers, including the Prestel and Telecom Gold facilities (if you've got the software).

It plugs into the RS423 port on the micro and the modern Type 600 BT telephone socket. The unit operates in full duplex mode, baud rate 1200/75.

The adaptor costs £113.85 (inc. VAT), and comes complete with a viewdata telecommunications ROM and user guide. It is available only by mail order from Vector Marketing, London Road, Denington Estate, Wellingborough, North Hants NN8 2RL.

18

Scientific suites

TWO companies have set out to provide software for scientists and engineers on the BBC micro.

Crecy Computer Systems is aiming a suite of programs at energy engineers and managers. The initial package has five parts, concerned with fuel, boilers, steam and steam turbines. A second unit on heat recovery is under way.


The pack is designed for

people who have no experience of using computers and will run on a model B. It costs £45 on disc, including manual, from Crecy at 148 Liverpool Road, Penwortham, Preston.

Finersoft has released *Bstat*, which, as the name suggests, deals with statistical analysis.

Bstat costs £15 from Finersoft at 30 Edna Street, London SW11 3DP.

StarBASE... a new database



StarBASE... for the BBC

StarBASE meets and even exceeds professional standards found on large installations. It is unique in speed, flexibility and ease of use.

Price? Only £69.00 inc VAT (plus £1.50 p & p).

SEE US AT

The 2nd
Official
Acorn User
Exhibition

OLYMPIA
16-19 AUGUST
1984

Z80 second processor for BBC

Microcomputer with SAGE integrated accounts

program

£375 + VAT

STOCK SUBJECT TO PRIOR SALE
Local authority enquiries welcome.
Prices correct at time of going to press.




GCC (Cambridge) Limited
66 High Street, Sawston, Cambridge CB2 4BG
Telephone: Cambridge (0223) 835330/834641
Telex: 81594 SAWCOM



Print from Japan

Disk Drives from Cumana



CUMANA'S DISK DRIVE for the BBC microcomputer

- High quality 5 1/4 inch Japanese disk drives
- Cabinet finished in hard wearing BBC beige
- 12 months warranty
- Fully assembled and tested



Like the beautiful prints from Japan, Cumana disk drives represent the very highest standards in design and production. Also like the prints, Cumana disk drives represent the highest state of the art; and they not only look beautiful, they perform beautifully as well.

Cumana disk drives for the BBC Microcomputer are available in slimline single, dual and dual switchable versions. They have 12 months warranty, are fully assembled and tested before packaging, and are available — at unbeatable value for money prices — from W. H. Smith, The John Lewis Partnership, Greens Leisure, Laskys, Spectrum (UK, area distributors (see below) and Cumana's national dealer network.

Look out for the distinctive Cumana packaging in your high street, today!

Area distributors:
HCCS Associates (Gateshead) 0632-821924, Eltec (Bradford) 0274-722512, Basic Business Systems (Nottingham) 0602-819713, Walters Computer Systems (Stourbridge) 03843-70811, Microage Distribution (North London) 01-205 7688, J. S. Simnett Computers (South London) 01-390 6161, Ferranti & Craig (Basingstoke) 0256-69966, Gwent Computers (Wales) 0633-215008, National Micro Centre (Stockport) 061-456 9548, Microworld (Edinburgh) 031-228 1111, Microtest (Cornwall) 0208-3171, DRG Business Machines (Weston-Super-Mare) 0934-415398, Kingdom Design (Belfast) 0232-643720, Hugh Symonds (Bournemouth) 0202-26535, Audio & Computer Centre (Jersey) 0534-74000.

The Highest State of the Art



Cumana Limited,
Pines Trading Estate, Broad Street,
Guildford, Surrey, GU3 3BH.
Telephone: Guildford (0483) 503121.
Telex: 859380.

For further information
about Cumana disk
drives for the BBC
Micro, please complete
and return this coupon.

Name _____

Address _____

Interests:

Home Use

Education

Dealer

Business

Tel. No. _____

AU8/84

Note: If dealer, please attach this form to your letterheading.

Introducing BEEBUGSOFT

Until recently a very special range of applications and utility packages for the BBC micro has been unavailable to the general public.


This software has been produced by the BBC user group BEEBUG for its members. BEEBUG members tend to be a demanding and discerning group of individuals; and the range of software produced has been kept to a consistently high standard through their constant vigilance.

As a result, BEEBUG software is highly acclaimed amongst BEEBUG's 25,000 members. Independent reviews from the major computing magazines seem to take a similar view of the software, as you can see from their comments.

SPELLCHECK

The disc based spelling checker for text created on Wordwise or View.

"... invaluable ... fast and reliable ... a worthwhile investment"
PCN February 1984




TOOLKIT

27 new commands in eprom to speed up Basic program development and debugging.

"... an indispensable aid"
EDUCATIONAL COMPUTING March 1984

"... worth every penny ... highly recommended"
COMPUTING TODAY June 1984

"... its range of utilities is excellent"
MICRONET May 1984




SPRITE UTILITIES

A game writers utility pack enabling high speed arcade games to be quickly written in Basic.

"... definitely recommended ... excellent"
ELECTRONICS AND COMPUTING May 1984

"... Sprite Utilities wins through"
ACORN USER May 1984






PAINTBOX

Probably the ultimate joystick drawing package on the BBC Micro, great fun and highly educational.


"... amazingly versatile ... easy to use ... (one of the most feature laden picture creating programs around) ... tremendous potential"
EDUCATIONAL COMPUTING Jan 1984

"... a very sophisticated and versatile utility"
ELECTRONICS AND COMPUTING May 1984






TELETEXT PACK
 A powerful screen editor for quickly creating Teletext Mode 7 screens.
 "... provides teletext editing facilities in a well thought out manner"
 ELECTRONICS AND COMPUTING April 1984
 "... a very neat utility"
 MICRONET April 1984




EXMON
 An extremely powerful machine code monitor on cassette or eprom, offering 35 new commands for debugging machine-code.
 "... exceptionally comprehensive ... would be hard to improve upon"
 YOUR COMPUTER August 1983
 "... using EXMON is a delight"
 MICRONET May 1984



DESIGN
 A Computer Aided Design package to allow screens to be quickly created for display, demonstration, handouts etc.
 "... a first rate screen processor ... immense value to schools and colleges"
 EDUCATIONAL COMPUTING April 1984

BEEBUGSOFT products may now be obtained from major dealers including selected



MASTERFILE
 A flexible general purpose database on cassette or disc; the disc version using random access files.
 "... works well and offers an efficient database"
 PCN November 1983


branches of W.H. Smith. 

Alternatively all products are available from us on mail order from our despatch department in High Wycombe.

BEEBUGSOFT dept 13 PO BOX 109 HIGH WYCOMBE BUCKS HP10 8HQ

TEL: ST. ALBANS (0727) 60263

How long have you waited for the right drive?




THE FIRST CHOICE FOR THE B.B.C. MICRO

THE UNIT Precision engineered by Hitachi using tomorrow's technology today. Housed in a High Stability aluminium one piece casing for durability and smooth function. The case is finished in a tough epoxy coating which complements the BBC micro and other quality equipment.






COMPLETE PACKAGE Supplied with data and power cables, utility disc, and instruction manual. Ready to plug in and use. Compatible with all known disc interfaces for the BBC micro. Powered by the BBC micro – no extra power supply required. 12 month parts and labour guarantee.

THE MEDIA The disc is encased in rigid plastic and the disc surfaces are protected by a stainless steel shutter which is automatically opened and closed by the disc drive.



SPECIFICATIONS Track to track access time is 3 ms. Data transfer rate 125 Kbs⁻¹. Dual double sided Disc drives give 1 Megabyte of on-line storage.

TERMINOLOGY GUIDE

-  A single sided drive accesses one side of a disc at a time.
-  Dual single sided drives access two sides at a time.
-  A double sided drive accesses both sides of a disc at a time.
-  Dual double sided drives access all four sides at a time. No need to turn discs over in double sided drives.
-  Unformatted capacity of one disc is 500K (double density), 250K (single density). Storage density is dependant on interface used.

Please send me:

- Single Disc Drive Double Sided Pack @ £219.99.
- Double Disc Drive Double Sided Pack @ £399.99.
- Single Disc Drive Single Sided Pack @ £179.99.
- Double Disc Drive Single Sided Pack @ £339.99.
- Pack of 5 3" Discs – uncased @ £22.50.
- Pack of 10 3" Discs – uncased @ £41.00.
- Pack of 5 3" Discs – CASED @ £24.00.
- Pack of 10 3" Discs – CASED @ £44.50.
- Double Density Disc Interface @ £109.95.


All prices include VAT, post and packing. Generous Dealer Terms Available.

Name _____

Address _____

SPIDER SYSTEMS Web House, 29 Elmfield Road, Stockport SK8 8SE. Telephone: 061-483 7692.

**Word-processing:
a complete range of
packages starting at
£899—including VAT
READY TO USE!**



**Package comprises: BBC Model B
Microcomputer • 100K Disk drive
• 80 column printer and free
delivery in the UK! • Optional disk
drives and printers • Wordwise.**

Computers

BBC 'B'	£399.00
Acorn Electron	£199.00
BBC 'B' + DFS	£469.00

Delivery £10.00

Monitors

Sanyo 14" Green	£86.31
Philips 12" Green	£80.00
Philips 12" Amber	£72.50
GM1211 12" Green	£101.00
Sanyo 14" Colour	£245.00
Nordemende TV/Monitor	£249.00

Delivery £10.00 per item

Books

BBC	
Advanced User Guide (hardback)	£16.95
Advanced User Guide (paperback)	£12.95
30-hour Basic	£6.95
<i>... and many other books on BBC, Electron, Sinclair and Commodore.</i>	

Delivery £1.00

Cassette Recorders

Sanyo	£28.00
Benksom/Team	£19.00
Sanyo DR101	£33.95

Delivery £3.00 per item

Joysticks

Super Champ	£16.95
Mini Champ	£14.00
Quickshot II	£11.95
Kempston Joystick Interface	£15.00

BBC Joysticks

Emax Professional Joystick	£28.00
Micro Aids Joystick (pair)	£15.00
Zip Stick	£15.00

Delivery £2.00 per item

**namal
products**
for 1984

Printers



One of the newest printers on the market, the KAI dot-matrix printer has both parallel (Centronics) and serial (RS-232C) interfaces and is thus compatible with all the major systems, including the IBM PC. An impressive list of features includes a print speed of 100 characters/sec and high through-put with bi-directional logic seeking, 66 LPM.
Excellent value at £210.00

KAI-100EX	£210.00
Epson FX80	£395.00
Epson RX80FT	£315.00
Epson RX80T	£275.00
Seikosha GP100A	£200.00
Juki 6100	£395.00
Mannesman Tally	£225.00
MCP40	£129.95

Delivery £10.00 per item

TEAC Slimline Disk Drives

Single Disk Drives

100K (40TPI)	£120.00
200K (40/80TPI) Switchable	£140.00
400K (40/80TPI) Switchable	£180.00

All drives fully cased with cables and format disk: ready to use.
Disk with power supply extra £30.00

Dual Disk Drives


200K (2 × 100K)	£295.00
400K (2 × 200K)	£325.00
800K (2 × 400K)	£450.00

Dual drives include a power supply
Delivery £6.00 per item

**ALL PRICES
INCLUDE VAT**
Credit terms available
for orders of £500 or over.
Access, Barclaycard, American
Express and Diners Club welcome.



Ordering is easy: Telephone Hotline (0223) 355404.



Type and Talk

Speech Computer RS232 Interface.
Can convert text into speech quickly.
Easily programmed. Only **£171.35**
Delivery £5.00

BBC ROMs

Wordwise	£46.00
Disk Doctor	£33.35
View	£59.80
Graphics Rom	£32.90
Printmaster	£33.35
Gremlin Rom	£33.35

Delivery £1.00

Diskettes

per 10

3M	
744 S/S D/D 48TPI	£20.68
745 D/S D/D 48TPI	£28.00
746 S/S D/D 96TPI	£32.00
747 D/S D/D 96TPI	£37.00

Verbatim	
S/S D/D 48TPI	£20.00
S/S D/D 96TPI	£29.50

Xidex	
S/S D/D 48TPI	£27.50
S/S D/D 96TPI	£39.40

Delivery £1.00 per item

**NOW AVAILABLE:
ACORNSOFT
GAMES/LANGUAGES/
BUSINESS.**

We stock a large range of software:

- Games • Educational
- Business

Call for software list and catalogue

**Cambridge
Microcomputer
Centre**

The Peripheral Centre of East Anglia

153-4 East Road, Cambridge CB1 1DD
Telephone (0223) 355404 Telex 817445

Cambridge Microcomputer Centre is a wholly owned subsidiary of Namal Associates Limited

Amazing how played out some things



become.

Will you think the same of your micro in 6 months' time?

Remember the days when every record player was gifted with a needle instead of a stylus. 45's were "in," 78's were "out."

Before the days of hi-fi and laser discs. When a graphic equaliser was a breakthrough on the football pitch instead of in music technology.

Look at a record player now and it's a museum piece.

It's like that with micros too. The machine you thought would give endless hours of fun and interest often becomes a five minute wonder. Played out within months. Or so you thought.

But imagine communicating with other micro users on a nationwide mainframe system. Updating yourself

daily with the very latest computer news and reviews. Paging a special Bulletin Board. Feasting from Prestel's vast menu. Even downloading a choice of software *absolutely free*.

In fact, imagine 30,000 pages at your fingertips and you've imagined what it's like to be on line with the Micronet 800 system.

For just £13 a quarter (and, for most of you, a local telephone call whenever you want to connect up) you could subscribe to the Micronet system.

The only extra you need to connect up is a modem unit. Which is a small enough outlay for what it buys.

Micronet's features are almost limitless and constantly updating so why not see it in action at John Lewis stores, selected W. H. Smith shops and Spectrum UK dealers.

Or fill in the coupon for our brochure.

You'll find you won't want to play on anything else.



Please send me the full facts about Micronet 800.

Name

Make/Model of Micro

Address

Telephone

MICRONET 800, Durrant House, 8 Herbal Hill, London EC1R 5JF. Telephone 01-278 3143

AUB/84

MICRONET 800, Durrant House, 8 Herbal Hill, London EC1R 5JF. Telephone 01-278 3143

*Prestel and the Prestel symbol are trademarks of British Telecommunications.

Making the most of your micro.

BBC MICRO IN MANCHESTER

PRICES ...

All our prices are constantly moving, so please ring us to check the latest price.

FREE DELIVERY TODAY (Orders over £90)

If you are in Greater Manchester, Cheshire, Lancashire, Merseyside, West Yorkshire or South Yorkshire, if you ring us now we can send one of our highly trained staff to install your computer equipment Today. (Now for Business software too!)

WE WILL INSTALL IT

TEAC 55SRS2



£157.95 inc VAT

The latest 55 series from TEAC is now available from us. These disk drives are the new LSI low power consumption high performance version of the famous 55 series.
100K version (40 tk, 200K with LDOS) at **£157.95 inc VAT - 55A2**
400K version (40/80 tk, 800K with LDOS) at **£227.95 inc VAT - 55F2**
100K Chinon (40 tk, 200K with LDOS) At £135.00 inc VAT
Dual 100K Chinon at **£229**

ACORN ADD-ONS

6502 Processor **£199 inc VAT**
Z80 Processor (includes all software) **£299 inc VAT**
Bitstick System **£385 + VAT**


BUSINESS SOFTWARE

All Acornsoft Business software
£24.95 inc VAT per module

Payroll, Mailmerge, Integrated Accounts, Databases, Word Processing

- WE WILL DELIVER AND INSTALL!

CANON



£299

The CANON is a Centronics, 16 x 16 Dot Matrix head. It prints at 160 cps, is bidirectional and logic seeking. Buffer is 8K. Prints 17 to 5 characters per inch. Prints 136 to 40 columns. Multiple character sets including down-loadable and italics. Epson compatible. But the best thing of all is that the CANON also prints in letter-quality mode - which is near to a daisywheel print face. Incredible value for money!

SPECIAL OFFER

BBC 'B' + LDOS + 200K DISK DRIVE

£599 inc VAT

EX STOCK - WE CAN DELIVER IT NOW!



TECH COMPUTERS

**184 Market Street,
Hyde, Cheshire
SK14 1EX
061-366 7794
061-366 8223**



BBC MICRO HARDWARE (inc VAT)

BBC Model B £399

BBC Model A £299

BBC Model A + 32K £339

ELECTRON (should now be available) £199

Disk Interface £89

Disk Interface with double capacity option £89

Speech Synthesiser £59


FLOPPY DISKS

Double Sided - Double Density

£1.50 inc VAT

Box of Ten **£14.50 inc VAT**

MONITORS



COLOUR
Microvitec **£219 + VAT**
Sanyo Normal **£209 + VAT**
Ferguson TV/Monitor **£214.95 + VAT**
GREEN
Sanyo Normal **£79 + VAT**
Sanyo Hi-Res **£109 + VAT**
Philips Hi-Res **£79 inc VAT**

PERIPHERALS

MODEMS

OEL200 **£73 + VAT**

Prestel Terminal

£17.39 + VAT


Teletext

£195.65 + VAT

Joysticks

£14.95 inc VAT

PRINTERS



DAISYWHEELS
QUME Data **£299 + VAT**
Brother HR15 **£329 + VAT**
Brother Sheet Feeder **£199 + VAT**
DOT MATRIX
Epson FX80 **£399 + VAT**
Epson RX80 **£249 + VAT**
Epson RX80 F/T **£279 + VAT**

AS USUAL LOADS OF SOFTWARE AVAILABLE Tel: 061-366 8223

DOWNLOADING WEATHER

The outlook is bright for Beeb users to receive satellite pictures, says Robin Mudge

27

SWITCH on the TV in the early evening and you are bound to see one of those magnificent satellite pictures the weather men are so fond of. They are taken by satellites continuously orbiting the earth to help meteorologists study the world's climate, and predict our weather. The equipment they use is exorbitant, but now, using the BBC micro and a few peripherals, you can receive and display pictures broadcast by the American NOAA and Russian Meteor satellites.

Their orbits almost pass over the North and South poles and they take about 102 minutes for each revolution, during which time the earth turns about 25.5 degrees so each time the satellite goes round it looks at a different part of the globe. In this way a complete picture of the earth is built up in strips, each one slightly overlapping the last (figures 1 and 2).

The satellite takes two pictures side by side, one with visible light and the other with infra-red, as shown on page 29. The satellite spins rapidly and special equipment on board scans the earth's surface and sends a TV picture at 120 lines a minute, ie one line in half a second. This is a slow scan picture, when you consider that a domestic TV scans 625 lines in 1/25th of a second. Each scanned line is split into two, one part representing the infra-red and the other the visible light pictures and an FM radio signal is transmitted from the satellite on 137.5 MHz or 137.62 MHz.

Receiving the satellite signal is reasonably straightforward using professional receivers, or amateur versions costing far less: a suitable kit can cost as little as £50. Basically the receiver is little more than a modified domestic FM radio. A suitable crossed dipole aerial can also be bought, or




Figure 1. Consecutive orbits

made from an old BBC1 TV aerial.

The picture information is carried by a 2.4kHz audible tone which changes with the brightness of the image: louder for the bright parts. This tone is used to

MICHAEL Furminger uses the BBC micro at Nene College in Northampton to download weather satellite information for his courses. It all started as part of a combined studies degree which covered metrology.

Michael explained: 'I picked the idea up and then along came the BBC micro with its interfaces and graphics. We then built a fast A/D converter, wrote the software and away we went.'

The weather pictures are used to give a day-to-day illustration of current weather patterns, and hence simple short-term forecasting. Over a longer period, the pictures saved build into an information base for further analysis. One of the major advantages is that the infra-red scale gives a very clear indication of weather patterns, as the hot and cold fronts show up very well.

And the idea has caught on: 'It has been taken up by many colleges and universities who have all built working models. I even had a call from Jodrell Bank!'




THIS IS THE BIG ONE!

The 2nd Official Acorn User Exhibition

OLYMPIA AUGUST 1984

Thursday 16th – 10am to 7pm
Friday 17th – 10am to 6pm
Saturday 18th – 10am to 6pm
Sunday 19th – 10am to 5pm

* Please note 10am to 2pm on Thursday 16th
is Trade Morning – By invitation only.



© Certain Advertising Ltd 01-930 1612

BIG VALUE

The success story of Acorn Computers, the BBC Micro and Electron is mirrored by suppliers who have produced more and more hardware, software, supplies and services. And they'll all be at the exhibition – disk drives, plotters, printers, monitors, joysticks, robots, books and magazines, all kinds of software – everything for the Acorn owner.

And of course Acorn will be there in force with all their latest developments and software.

There'll be special offers, competitions, advice centres and special events as well.

And all this for only £3.00 at the door, under sixteens £2.00. (Use the coupon to beat the queues and save £1.00).

BIG VENUE

Olympia 2 is the brand new exhibition centre next to the old Olympia. It's got everything, wide gangways, lots of space to sit down and rest, plenty of catering areas.

Getting there is easy too, its got its own tube station, bus routes 9, 27, 28, 33, 49, 73 and 91 go right pass the door, and there's car parking too!

BIG SUPPORT

Remember this is the *Official Acorn User Show*, it's the most informative prestigious and influential user show in the country. Whether you're a businessman, serious user or games enthusiast there's something for you.

For details of exhibition stands and advance ticket sales contact the organisers.

Computer Marketplace (Exhibitions) Ltd. A Rushworth Dales Group Company, 20 Orange Street, London. WC2H 7ED Tel: 01-930 1612

BEAT THE QUEUES! SAVE MONEY! ORDER YOUR TICKET IN ADVANCE.

Buy your ticket now and save queuing. There will be special entrances for advance ticket holders.

Please send me _____ (qty) tickets at £2.00 and _____ (qty) under sixteen tickets at £1.00. I enclose my cheque/PO to the value of £_____ or debit my Access card. No. _____

NAME _____ SIGNED _____

ADDRESS _____

_____ POSTCODE _____

GROUPS – Order 15 or more tickets and you qualify for a further 20% discount.


To: Computer Marketplace (Exhibitions) Ltd. A Rushworth Dales Company, 20 Orange Street, London WC2H 7ED.

drive a facsimile (facs) recorder. In these machines a piece of light or heat sensitive paper is wrapped around a rotating drum and an image is exposed or burnt onto it by a scanning light or heating diode.

The transmission of facsimile pictures itself isn't new because the BBC used to transmit them in 1934 but the facs kits were expensive even then. Today a facs recorder can cost many thousands of pounds and this is where the BBC micro comes in, as with suitable software it can display a very good picture.

Michael Furminger from Nene College in Northampton has designed an excellent system which uses the BBC micro to display satellite pictures instead of an expensive facs recorder. He supplies the circuit diagrams and software for the project for only £5. His project breaks down into three parts: an accurate clock; a fast analogue to digital converter; and suitable software for the BBC micro.

The first two are construction projects. The clock is needed to synchronise the start of each picture line. Looking at the diagram of the received satellite waveform you will see two large pulses, one at the beginning and the other separating the two pictures (figure 3). These are synchronising pulses. The software has to accurately line all of these pulses one under each other to produce a square picture. If this is not done properly the picture can skew to left or right causing distortion. The clock is crystal controlled and produces accurate 2Hz pulses which the software uses to synchronise the lines. It is much easier to record the satellite signals on a stereo cassette or reel to reel tape recorder with the clock pulses on another track so they can be passed through the BBC micro at a much more leisurely rate after the satellite has passed.



The satellite takes two pictures side by side

Before the computer can display a picture the 2.4kHz analogue signal has to be turned into a digital one. Each line takes just half a second, which is too fast for the BBC's internal A to D converter (ADC). An external ADC with a

very fast conversion time is needed and the signal is passed on to the Beeb's user port along with the 2Hz pulses from the other tape track.

The software produces a picture in either mode 1 or 2. In mode 1 a picture with resolution 320 by 256 pixels and four colours is produced, and in mode 2, 160 by 256 and eight colours. The software presents you with a menu allowing you to select a screen mode that displays a good black and white image, or a colour range designed to show different temperature bands on the infra-red picture. A picture is slowly

built up on the screen as data is converted from the tape recorder. The image-producing routines run in machine code as Basic is not fast enough to process the data from the high speed ADC. Of course the software does a lot more than this as it corrects the geometric distortion found in the raw unprocessed pictures, which look like tall thin strips with all the land features highly squashed. Other programs in the package allow you to store




Figure 2. During the 102-minute orbit the earth turns about 25.5 degrees




Figure 3. Received satellite waveform, showing synchronising pulses



Picture transmitted by the American polar-orbiting weather satellite Tiros-N

pictures and view them at will and there is also a prediction program that helps tell you when the satellite is going to be overhead within receiving range—usually just two or three different times each day. Proper prediction tables can be purchased from the NASA Information Bureau.

The only disadvantage of Michael's package is the fact that the constructional details for the clock and high speed analogue to digital converter are limited to a schematic circuit diagram. You will have to make a hard-wired version or design an appropriate circuit board, but what can you expect for £5?

David Duff also has written software to turn the BBC micro into a weather picture display using the Unilab computer interface which has a built-in, high speed A to D converter.

Whichever system you choose to use you must get a letter of permission to receive weather satellite pictures from the Radio Regulatory Department of the Home Office. If you don't fancy the construction work and haven't got any friends who know which end of a soldering iron is hot, then you can buy a complete system for receiving weather satellites for about £2,100.

Hardware contacts

Receivers

Ambit International,
Parks Lane,
Broxbourne,
Essex.

Supply a kit to make a satellite receiver at about £50.

Microwave Modules,
Brookfield Drive,
Aintree,
Liverpool L9 7AN.

Supply a ready-built satellite receiver for £345 and also make a converter that changes the 137MHz to 30MHz which could be received by a modified CB radio.

Feedback Instruments,
Park Road,
Crowborough,
East Sussex TN6 2QR.

Make an entire receiving system including display for £2,100.

Aerials

Jaybeams,
Kettering Road North,
Northampton NN3 1EZ.

Supply a full range of aerials including one suitable for satellite reception.

Software contacts

Michael Furminger,
Nene College,
St George's Avenue,
Northampton.

Michael supplies a complete set of instructions to build the hardware, and the software necessary to receive satellite pictures for £5.

A copy of David Duff's listing to receive satellite pictures with the Unilab computer interface is available for 50p and a stamped, addressed envelope from *Acorn User*, 68 Long Acre, London WC2E 9JH.

References

'BBC weather satellite display', by M Furminger, *Electronics and Computing*, July 1983

Reception and processing of Tiros-N weather satellite telemetry by J Gilbert and T Terrell

'Meteosat high resolution images', by M Christieson, *Wireless World*, August 1982

NOAA Handbook, available from the US Dept of Commerce, National Earth Satellite Service, Washington DC 20233

What the competition hasn't been waiting for.

Latest version of Forth for the BBC
(Is not rehashed Forth 79 Code)

Unique Stack Display Utility



16k Eprom type 27128

Multi-tasking operating system
for Real-Time use.

Here's the Forth Eprom for the BBC Micro that makes all others out of date.

It's Multi-Forth 83 from David Husband who has built his reputation for Quality Forth products with his ZX81-Forth ROM, Spectrum Forth-I/O Cartridge and now New Multi-Forth 83 for the BBC Micro. This is not rehashed Forth 79 Code, but a completely new version of the Forth 83 Standard. It's unique in that it Multi-tasks, and therefore the user can have a number of Forth programs executing simultaneously and transparently of each other.

Multi-Forth 83 sits in the sideways ROM area of the BBC along with any other ROMs in use. It is compatible with the MOS, and specially vectored to enable a system to be reconfigured. It contains a Standard 6502 Assembler, a Standard Screen Editor, and a Unique Stack Display Utility.

With this Forth, David Husband has provided the BBC Micro with capabilities never before realised. And being 16K rather than 8K is twice the size of other versions. Multi-Forth 83 is supplied with an

extensive Manual (170 pages plus) and at £45+VAT it is superb value.

Order it using the coupon adding £2.30 p&p (£5 for Europe, £10 outside) or if you want more information, tick that box instead. Either way, it will put you one step ahead of the competition.

Please send me Multi-Forth 83 for BBC Micro. £45+VAT. De-luxe System inc. Disc £80+VAT. Cheques to Skywave Software Readers' A/C (or enter Visa No.)

Name _____
Address _____
Post code _____

Please send me more information:
 Multi-Forth 83
 ZX81-Forth ROM
 Spectrum Forth-I/O Cartridge


Skywave SOFTWARE

SUBJECT TO AVAILABILITY FOR I.O.S. ONWARDS.
Send to Skywave Software, 73 Curzon Road, Bournemouth,
BH1 4PW, Dorset, England. Tel: (0202) 302385


MULTI-FORTH 83 FOR THE BBC MICRO

M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R

DISK SOFTWARE FROM MICRO POWER



AVAILABLE FOR THE FOLLOWING TITLES:
**KILLER GORILLA; THE MINE;
 CYBERTRON MISSION; STOCK CAR;
 BLOCKBUSTER; RUBBLE TROUBLE;
 FRENZY; FELIX IN THE FACTORY;
 GHOULS; JET POWER JACK.**



PLEASE ADD 55p TO EACH ORDER TO COVER POSTAGE AND PACKING.

£9.95 EACH

- All 10 games are packaged with full colour artwork in an A5 vinyl sleeve.
- Each disk will work on both 40 and 80 track drives.
- Instructions and screen photograph on the back cover.
- Available NOW from your local dealer or by mail order.

SPECIAL OFFER: Return your Micro Power cassette enclosing £4.95 for the disk version or come along to our stand at the Acorn User Show 16-19 August.
NOTE: The rest of our range of titles for the BBC Micro (except Filer and Draw) will also be available on disk but without the colour packaging. These programs will be available from the beginning of August and by mail order ONLY.

M I C R O P O W E R


MICRO POWER LTD.,
 Sheepsca House,
 Sheepsca Street South,
 Leeds LS7 1AD
 Tel: 0532 436300

SEE US AT
 The 2nd
 Official
 Acorn User
 Exhibition
 OLYMPIA
 16-19 AUGUST
 1984



M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R

KEYBOARD BASICS



A PART from the actual process of learning to program, the keyboard can be one of the biggest obstacles to using your computer. If you've ever used a normal typewriter, you should have few problems, because there are few differences. On the other hand, if you have never used one then you must endeavour to learn your way around the keys. This takes time, and can be frustrating as no doubt you'll be in a hurry to get a program running. However, speed, two, three and even four fingers will come, eventually!

The keyboard on your Electron or BBC is often referred to as a 'QWERTY' keyboard. This isn't a fancy abbreviation, but simply denotes the fact that these are the first six letter keys (see photograph).

The major difference on the Elk's keyboard to a typewriter is that it doesn't have a return lever to take the typing carriage back to its start position on reaching the end of a line. Being more like an electric typewriter, the computer has a special key to do this, called the RETURN key. This is at the far right of the keyboard. Try pressing this a few times and you should see it perform a carriage return which scrolls (moves) the screen and any text on it up by one line, with any text at the top of the screen moving off of it and a new blank line replacing it at the bottom. Try it!

Now type some of the letter keys, try QWERTY for example. This will appear on the screen as the letters Q,W,E,R,T and Y. These are all capitals, or 'upper case'. However, just like a normal typewriter, it is possible to type each letter as a lower-case character. To do this you need to tell the Elk by pressing two keys at the same time. The keys are those marked SHIFT and CAPS LK and you'll find these on the extreme left. If you do this correctly the small yellow light next to the CAPS LK key will be extinguished. Try typing QWERTY again, this time it will appear as q,w,e,r,t and y! To get back to upper-case, press the same two keys together again, now the small yellow light will come on again. In most instances, a computer program must be written in upper-case characters as this is how the Elk recognizes program commands. If you only wish to type in a single lower-case character without leaving the upper-case mode, you can do this simply by holding the SHIFT key

The keyboard can be a great obstacle to learning about your micro. Tessie Revivis' program will set your fingers tapping

33

down and pressing the key you require in lower case.

The number keys all have a black symbol above them. For example, above the 1 key there is an exclamation mark (!). These are the characters that can be printed using the SHIFT-CAPS LK sequence first of all. Try printing a few, then come back to the normal unshifted mode. If at anytime you can't get back to normal capitals, then remem-

ber you can always reset the Elk by pressing the BREAK key.

On the front of most keys you will probably have noticed the red coloured printing. On the letter keys these are in the form of words which relate to Basic commands, the instructions used by the Elk. Not every single command is available on the keys, there are too many and not enough keys, so only the more frequently-used ones are found

```

10 REM *** RANDOM PROGRAM GENERATOR ***
20 REM *** FOR ELK AND BBC MICROS ***
30 MODE 6
40 VDU19,0,4;0;0;
50 PRINTSPC(6);"RANDOM PROGRAM GENERATOR"
60 PRINT' SPC(4);"(c) Acorn User August 1984"
70 PRINT'"Save this program on tape first"'
80 PRINT"Now type NEW <RETURN>"
90 PRINTSPC(8);"and then AUTO<RETURN>"
100 PRINT"Now hit function key f0 and then"
110 PRINT"hit the other function keys, f1 to f9"
120 PRINT"as often as you like!"
130 PRINT"When you get fed up press ESCAPE"
140 PRINT"and then RUN the program"
150 PRINT"to see your master creation!"
160 *KEY0 MODE 5;M
170 *KEY1 SOUND 1,-15,RND(200),RND(20) !M
180 *KEY2 MOVE RND(1000),RND(1000) !M
190 *KEY3 PLOT 85,RND(1000),RND(1000) !M
200 *KEY4 GCOL1,2 !M
210 *KEY5 DRAW RND(1000),RND(1000) !M
220 *KEY6 GCOL2,3 !M
230 *KEY7 COLOUR RND(4):PRINT"HELLO" !M
240 *KEY8 GCOL2,2 !M
250 *KEY9 SOUND1,-15,RND(100),10 !M

```

Listing 1. Just type in and RUN this program to create other programs!

8-DFS

For The BBC Supports:

- ⇒ Most 8" Floppy Drives in Single Density Mode
- ⇒ Both 8" and 5.25" Drives on the Same BBC
- ⇒ Self Contained Utilities
- ⇒ Potentially 2 Megabytes On-Line Storage

(384 files)

8-DFS is the only DFS to support 8" drives on the BBC and is both ACORN approved and compatible with ACORN filing system.

8-DFS ROM Complete **£44.95** +
£1.50 P&P

Installation Manual Only **£3.00**

VOGAN Products
The White House
21 Grove Road, Hazlemere,
Bucks. HP15 7QY

YOU'VE READ THE MAGAZINES YOU'VE PLAYED THE GAMES NOW FIND OUT WHAT YOU CAN REALLY DO!

Join the Micro Programmers

– get the newsletter produced by and for BBC Micro and Electron Programmers.

- * EXCHANGE AND SOLVE PROBLEMS
- * DETAILS OF *FX (OSBYTE) CALLS, OSWORD, INTRINSIC SUBROUTINES
- * ADVANCED TOPICS, ASSEMBLY LANGUAGE
- * ROUTINES TO ADD TO YOUR OWN PROGRAMS
- * HELP, IDEAS, PRACTICAL ADVICE

Six issues only £4.50 inclusive.

Send A4 SAE for FREE sample issue.

Contributions and user-queries always welcome.

UK Subscriptions (no stamp required):

Micro Programmer, **FREEPOST**, Hastings TN34 2BR

Enquiries and foreign orders:

Gavin Haines, 43 Cornwallis Gardens, Hastings,
East Sussex TN34 1LX. Telephone 0424 714102

Micro Programmer

■ Please cut out or copy ■

- I enclose an A4 SAE for my FREE sample issue
- I wish to subscribe. I enclose a cheque/P.O. for £4.50 made payable to 'Micro Programmer'


NAME

ADDRESS

..... POST CODE

Micro Programmer, FREEPOST, Hastings, East Sussex TN34 2BR

Authorised Dealer & Service Centre
IN
MID-SUSSEX



BBC
MICRO COMPUTER



- **HARDWARE**
BBC B's & wide range of Monitors,
Printers, Disc Drives
- **SERVICING/UPGRADING**
On site Engineering
- **SOFTWARE** Variety of Educational/
Games/Business Packages
- **COURSES** Beginners
& upwards on BBC
Micro from £15.00.
Day/Evening.
Children/Adults

PHONE
BURGESS HILL
(04446)

45636

Visit our New Computer Store




michael
Business Systems Ltd

195 LONDON ROAD BURGESS HILL SUSSEX

Gemini
Business Software

NEW!



£99.95
per
module


Integrated Accounting Programs for BBC 32K Micro

....Simultaneously and automatically integrates several accounting functions and provides accurate and up to date management information, including Balance Sheets.....all at the touch of a button.

Full, descriptive leaflet available from most good software shops, or direct from:



Gemini Marketing Limited
18a Littleham Road Exmouth Devon EX8 2QG England
Telephone (0395) 265165/265832 Telex 42956 Attn Gemini



35

The Electron keyboard, though smaller, is more complicated than the BBC micro's, because many keys have more than one role

here. By holding down the key marked FUNC (it 'shares' the CAPS LK key) and pressing the key with the command you want, the entire command will be printed onto the screen, giving you single-key, command entry. You can type in a command word normally, it just takes longer. To illustrate the point we can write a very short program to make the Electron beep!

First, press the BREAK key to 'clear' the computer of any rubbish on the screen. Now type in the numbers 1 and 0, in other words the number 10. This is called the line number and is used by the computer to keep the program lines in order, so that line number 10 will come before line 20 which in turn will come before 30 and so forth. The fact that I've just gone in steps of ten has no relevance except that computer programs normally do: it means you can have extra lines without renumbering. Now hold the FUNC key down and press the V key. The letters VDU should have appeared on the screen. Release the FUNC key and now press key number 7; finally, perform a carriage return by pressing the RETURN key. The final result should look like this:

```
10VDU7
```

To run the program hold FUNC down

and press the RUN key which shares the R key. The result should be a short beep.

If you look at the number keys you will see that the secondary FUNCTION of these is given as *f1*, *f2* etc. These are the function keys which are somewhat unique to the Electron and BBC micros. They are in effect programmable keys, which means you can insert a command or a series of commands into them. Pressing FUNC and the particular key will cause the items programmed into that key to be printed. For example, the command CLS is used frequently within programs but does not appear as a pre-programmed key. We could program the *f1* key to produce PRINT by entering the following line (remembering to press RETURN after):

```
*KEY1CLS
```

This has entered the command CLS into function key 1. To prove this, hold the FUNC key down and press the 1 key; the letters CLS should appear on the screen. Other function keys can be programmed in a similar manner using the *KEY command which should be followed by the key number.

To end this month's section of First Byte, we present a program that will

write other programs! Enter listing 1, which programs the function keys to perform certain tasks. Once you have entered it type RUN (remember to hit the RETURN key at the end) to define the function keys. If you wish, save the program to tape at this point. You will see from the listing that the definitions contain a '!' symbol followed by a capital letter M. This sequence is used to tell the Electron to perform a return after printing the key definition. To obtain the '!' sign you'll need to type SHIFT and the '!' key which can be found to the left of the BREAK key.

Now type AUTO (and then RETURN); this command provides an AUTOMATIC line numbering service, first throwing up line 10 and then line numbers in increments of 10 every time the RETURN key is pressed. As each line number is presented press a function key (ie FUNC and the particular numeric key) to enter a line of text. Press the function keys randomly and when you get fed up, hit the key marked ESCAPE. To run your random creation, press FUNC and R together and admire the results. When you want another program hit the ESCAPE key and repeat the sequence. There's no need to re-enter the key definition program as it will stay in the micro's memory.

Computer Concepts...

Gremlin

Wordwise

Printmaster

Graphics

Communicator

Caretaker

Termi

DiscDoc

...are moving to

Gadden Place, Hemel Hempstead, Herts. HP2 6EX 0442 63933

HOW TO CORRECT PROGRAM LISTINGS

LISTINGS typed in from magazines often won't work: sometimes the program is wrong, but often typing mistakes are the cause and it can be difficult to know where to start looking for faults. It is a tedious task to find all the mistakes, and, as Schmendrick's law explains, no matter how carefully you check a listing and no matter how many mistakes you find, there is always one more!

Correcting listings is a matter of practice and experience that is slowly and painfully acquired, so this month I present a program that is guaranteed *not* to run (how many other magazines offer such service?). The idea is to spot as many faults in the listing as possible. To make the task a little easier, a corrected copy is included. However, those brave or skilled enough can try to find all the mistakes (there are 50) with-

out looking at the corrected version. Some will only be found when the program is typed in and run, and there is quite a collection of different error messages that will appear. If all else fails, a third version has every mistake indicated.

After all that effort, the program has to do something. This particular one can be used to find out about those mysterious hexadecimal (hex) numbers and how they relate to our normal counting system which uses base 10. It shows graphically and numerically the relationship between base 10 numbers (denary) and base 16 (hex) numbers. It will work equally well on the Electron or on the BBC. The program steps through the first 255 hexadecimal numbers showing how they are converted to base 10. Pressing the escape key at any time allows a denary

40 PROCinitialise. This procedure initialises the screen colours, some of the variables and an array.
50 PROCclocks. Draws the two hexadecimal clocks on the screen.
60 This line takes the user into the second part of the program if the escape key is pressed.
70 PROCrun is the first part of the program where each number is converted from hexadecimal into denary in turn.
80-100 The run loop for the second part of the program. This is an infinite loop, and will repeat until escape or break is pressed.
140 Switch off key auto-repeat.
150 Set print field width to 0. This ensures that when numbers are printed out no gap will be left between them.
160 Dimension B and oldB will be used to store the values of the hexadecimal numbers. The array hex\$ contains the hexadecimal symbol for the appropriate hex number.
170 Switch off the cursor.
180 Change the background colour to blue.
190 Change colour yellow to be black.
200 Define graphics window.
210-230 Routine to store the basic hexadecimal symbols 0-9 and A-F in the array hex\$.
240 Clear screen, defined by the graphics window, and colour it red.
260 Define a text window in the bottom part of the screen.

300 Join text and graphics cursors.
310-330 Print title at top of screen in colour 2.
340-500 First print two sets of hexadecimal numbers in two circles, and then draw the circles. To simplify the program, the graphics origin is moved to the centre of each circle as it is drawn.
550-570 Cycle through the first 255 hexadecimal numbers. PROCdisplay will show the numbers numerically and graphically.
600-710 This procedure takes a number, converts it to two hexadecimal digits, B(0) and B(1). Then it undraws the clock hands and redraws them in the new positions. PROCprint handles the numeric printing in the bottom half of the screen. The program then halts until a key is pressed before ending the procedure.
730-960 This is a long, drawn out routine to print the numeric information on the screen. It could have been shortened had it not been necessary to use several colours for clarity of display.
980-1040 This procedure draws (or undraws) the clock hands for either clock. If Z = 5 the procedure will draw a line, if Z = 7 it will undraw the line.
1060-1120 This routine forms part of the second half of the program, and repeats until a number in the range 0 to 255 is input. It then calls up the display routine before returning to the main part of the program.

Martin Phillips offers his advice

number to be entered and the conversion is displayed on the screen. The hexadecimal numbers are shown in black, and the denary numbers in red. Table 1 gives a description of the program and what the various parts do.

37

```

20 REM Uncorrected version
30 MODE 1
40 PROCinitialise
50 PROCclock
60 ON ERROR GOTO 80
70 PROCrun
80 REPEAT
90 PROCINPUT
100 UNTIL0
110 END
120 :
130 DEFPROCinitialise

```

```

20 REM Correct version
30 MODE 1
40 PROCinitialise
50 PROCclocks
60 ON ERROR GOTO 80
70 PROCrun
80 REPEAT
90 PROCinput
100 UNTIL0
110 END
120 :
130 DEFPROCinitialise

```

```

20 REM Uncorrected version
30 MODE 1
40 PROCinitialise
50 PROCclock
        ↑
60 ON ERROR GOTO 80
70 PROCrun
80 REPEAT
90 PROCINPUT
        ↑↑↑↑↑
100 UNTIL0
110 END
120 :
130 DEFPROCinitialise
        ↑↑

```

Samples of Martin Phillips' three programs. They can be found in full on pages iii to vi

Table 1. Demonstrates the relationship between denary and hex numbers



Watford Electronics



Dept. BBC, CARDIFF ROAD, WATFORD, HERTS. ENGLAND.

Tel: Watford (0923) 40588/37774 Telex: 8956095 WAELEC

ACCESS ORDERS Tel: (0923) 50234



BBC MICRO Model B £346

★ ★ ★ ★

SPECIAL OFFER

For every purchase of BBC Micro during July 1984, we will supply a Data Recorder worth £24 absolutely **FREE**. (At Watford we give you a great deal for your money).

ELECTRON MICRO £199

Dust Cover for BBC Micro

Protects your expensive Micro from foreign bodies. **£3.50**

SEIKOSHA GP100A PRINTER


10" Tractor Feed, 80 columns, 50CPS. Normal & Double width Char, Dot res graphics. Parallel Interface standard. SPECIAL OFFER Only: **£144** £7 carr.)

FRICTION FEED

Attachment for GP100A or 250X Printers **£28**

GP-700 Colour Printer **Screen-dump** routine in ROM FOR BBC Micro

£12



EPSON

RX80

100 CPS, 9 x 9 matrix, dot addressable graphics, condensed and double width printing. Normal, Italic and Elite Graphics. Tractor feed, 10" max width, bi-directional, logic seeking. Centronics Interface standard.

ONLY **£229** (£7 carr.)

EPSON RX80 F/T PRINTER

As above but has both Friction and Tractor Feed. **£245.00** (£7 carr. Securicor)

PRINTER INTERFACE BUFFER

Neatly packaged self contained box, supplied complete with all leads, manual and detachable power supply.

Price: 16K Unit **£115**
Price: 48K Unit **£149**

Epson FX80 Printer

160 CPS, 11 x 9 matrix, proportional spacing, superscripts, subscripts, dot addressable graphics. Normal, Italic and Elite characters. Up to 256 user definable characters. Down loadable character set. Condensed and double width printing. Full proportional spacing. Four user defined margin positions. Tractor and Friction feed. 10" maximum width Bi-directional, logic seeking Centronics interface standard.

ONLY **£319** (£7 carr.)

Epson FX100 Printer

Same as FX80 but has a 15" wide Carriage **£495**

Type	Ribbons	Dust Covers
MX80FT	£4.75	£4.50
MX100/FX100	£10.00	£5.25
FX80	£4.75	£4.95
RX80	£4.75	£4.50
GP80	£4.50	-
GP100	£4.95	£3.95
GP250	£5.95	£3.95
GP700	£18.50	-
KAGA KP810	£5.95	-

RX & FX PRINTER INTERFACES

RS232	£35	RS232 + 2K Buffer	£59
IEEE 488	£65	2K Parallel	£58

BROTHER HR-15 DAISY-WHEEL PRINTER

An exceptionally high quality daisy wheel printer at the price of a dot matrix printer. 18CPS; bi-directional, 3K of buffer; has clear buffer facility, carriage skip movement, proportional spacing; underlining; bold print and shadow print. Prints in two colours; super and subscript facility. Impact control facility to vary pressure on paper for making carbon copies. Has Centronics parallel or RS-232 interface. Connects directly to BBC Micro. A ribbon cassette plus a separate red ribbon. Optional extras: single sheet feeder takes up to 150 A4 sheets; a keyboard that transforms HR15 into a sophisticated electronics typewriter. Attractively finished in beige.

ONLY **£349**

Single Sheet Feeder **£199**
Keyboard **£150**
RIBBONS: Carbon **£3**; Fabric **£3**;
Multistrike **£6**

LISTING PAPER (Plain)

1,000 Sheets 9 $\frac{1}{2}$ " Fanfold Paper	£7
2,000 Sheets 9 $\frac{1}{2}$ " Fanfold Paper	£13
1,000 Sheets 15" Fanfold Paper	£9
Teletypewriter Roll (Econo paper)	£4

PRINTER LABELS

(continuous stationery)

1,000 90 x 36mm	£5.50
1,000 90 x 49mm	£7.75
1,000 102 x 36mm	£6.25

Carriage on Printer Paper or Labels **£1.50**

BBC Micro WORD-PROCESSING PACKAGE


A complete word processing package consisting of: BBC Model B, Zenith 12" Green or Amber Monitor, Twin 200K highly reliable (1 year warranty) Teac Disc Drives in matching beige colour, the popular WORDWISE word processor, Watford's own highly sophisticated 62 File DFS interface fitted, world renowned Brother HR 15 Daisy Wheel Printer, Gemini's BEEBCALC Spreadsheet Analysis, MAILING LIST and DATABASE Softwares on Disc. 10 blank 3M Discs (Lifetime warranty). A 4 way mains distribution socket. 10 blank diskettes, 500 sheets of fan-fold paper. Manuals and all the leads. To enable you to carry your Micro around, we shall pack it in our Antique Brown leatherette Attache carrying case.

ONLY **£1,249** (carr. £15)

(P.S. We will alter the package to suit your requirement. Call in for a demonstration).

NEW

KAGA KP810



This new JAPANESE printer has EPSON FX/RX compatible commands. 140 CPS Dot matrix Printer, offers **NEAR LETTER QUALITY** print in a 23 x 18 dot matrix in addition to the standard Epson style type-faces on the 11 x 9 matrix. Friction feed, Adjustable tractor feed, Single sheet feed and built-in Paper Roll Holder. Normal, Italic, Enlarged, Condensed, Super and Subscript, Dot addressable graphics (8, 9 and 16 pin modes). Proportional spacing. (Optional extra: Down loadable character set in 8K ROM or RAM). **NEAR LETTER QUALITY** print, selectable at switch on. 10" maximum width, bi-directional, logic seeking. 3K Buffer. Half speed quiet mode. Convenient Paper-out sensor switch. Centronics Interface standard. All this plus our no quibble 12 months warranty.

Special Introductory Offer: ONLY **£269**
RS232 Interface + 2K Buffer **£89**

KAGA KP910 PRINTER

Similar features as the above KP810 printer but has extra wide carriage. Will accept upto 17" maximum width paper. 156 column normal and 265 column condensed.

ONLY: **£349**

PRINTER LEAD 36"


Ready made printer lead to interface BBC Micro to EPSON, SEIKOSHA, NEC, STAR, JUKI, BROTHER, SHINWA, etc., Printers.

ONLY **£7**

Special Extra long 5 feet Cable

£10

EPROM PROGRAMMER



At last! - the EPROM Programmer for BBC Micro Computer from WATFORD ELECTRONICS

that will suit both your pocket and all your requirements. Programs all popular types of EPROMS from 2K bytes up to 16K bytes - 2716 - 2516 - 2532 - 2564 - 2764 - 27128. Our Programmer has been designed to make sure the EPROMS are neither programmed too fast nor too slow; just at the right speed as recommended by the manufacturers of the EPROMS (any deviation in timings can burn their brains out).

This extremely powerful system is designed for your needs of TODAY & TOMORROW! - BBC Basic programs can be copied into EPROM and subsequently re-loaded faster than from a disc! Suitable for both hobbyist and professional users!

Just look at these features:

- **COMPLETELY SELF CONTAINED** - Housed in its own sturdy case - Uses its own power supply - connects directly to the 1MHz Bus - Simple and Safe!
- **FULL SOFTWARE SUPPORT** - Comes complete with simple to use fully machine code ROM based software and easy to understand manual. Facilities include Verification, Reading, Virgin Testing, Writing, Editing, Saving, Loading and more! NOTE!! - This software does not simply comprise hastily prepared routines to get you going, but is a professional, purpose designed applications package.
- **ACORN BUS COMPATIBLE** - Use of the 1MHz connection complies with all Acorn addressing recommendations - That means you can still add-on such things as the TELETXT, IEEE 488 TUBE and PRESTEL
- Allows more than one program to reside in an EPROM using the ROM Filing System.

ONLY £89 incl. Manual (£3 carr.)


TEX EPROM ERASERS

EPROMs need careful treatment to survive their expected lifetime. Rushing it could burn their brains out. So cop-out of this helter-skelter world; take it easy the TEX way and give your chips a well earned break. Cool, gentle and affordable. EPROMPT does it properly.

Two versions available:


- **EPROMPT EB** - The standard version. Erases up to 16 chips. £28.00
 - **EPROMPT GT** - Erases up to 28 chips. Has an incorporated safety switch which automatically switches off the UV lamp when the Eraser is opened. £30.00
- Spare 'UV' Lamp bulbs. £9

PLASTIC LIBRARY CASES



for Disc Storage 5 1/4" (holds 10) £2

MONITORS



- **MICROVITEC 1431**
14" Colour Monitor, RGB Input. (as used in BBC programmes) FREE Interface Lead. **Special Offer £174**
- **MICROVITEC 1451** Hi-res
14" Monitor incl. lead **£295**
- **MICROVITEC 1441** Super Hi-res
14" Colour Monitor **£389**
- **KAGA RGB 12"** Medium Resolution Colour **£195**
- **KAGA RGB 12"** High Resolution Colour **£259**
- **KAGA 12"** Standard resolution colour
MONITOR/COMPOSITE VIDEO **ONLY £195**
- **BNC** Connecting Lead **£3**
- **RGB** Connecting Lead **£5**
- **ZENITH 12"** High resolution, jitter free picture, Amber or Green **£75**
Carriage on Monitors £7 (Securicor)

5 1/4" DISKETTES

(Lifetime warranty)


Why settle for less, Buy the best.

- 10 Verbatim or 3M Diskettes S/S D/D **£17**
- 10 Verbatim or 3M Diskettes D/S D/D **£28**

DISC ALBUMS

Attractively finished in beige leatherlook vinyl. Stores, protects and displays 20 discs in double-sided clear view pockets. **ONLY £4.95**

LOCKABLE STORAGE UNITS



Attractively finished, strong beige plastic base fitted with dividers. Smoke acrylic top. Supplied with adhesive title strips for ease of filing.

- M-35 Holds upto 35 mini discs **£14**
- M-85 Holds upto 85 mini discs **£18**

FLOPPY HEAD CLEANER KIT

Unless your Office/Home is dust free, you should clean floppy-heads at least once a week to avoid the risk of cross contamination. Very simple to use. **Only £14**

MONITOR CRT SCREEN CLEANING KIT

The anti-static spray controls dangerous static charges on the screen surface and ensures its optical clarity. **£12**

KEYBOARD CLEANING KIT

£16


PRINTED CIRCUIT BOARD CLEANING & LUBRICATION KIT

£14

DISC DRIVES CASED WITH CABLES (less PSU)

(All Drives are NEW SLIM-LINE Type)



NEW LOW PRICES



- **CLS 100** Single, TEC Single sided 40 track 100K, 5 1/4" Disc Drive **£119**
- **CLS400** Single, Mitsubishi Double sided 80 track 400K, 5 1/4" Disc Drive **£179**
- **CLS400S** Single, Mitsubishi Double sided 40/80 track Switchable, 400K, 5 1/4" Disc Drive **£215**
- **CLD200** TEC Single sided 40 track 200K, twin 5 1/4" Drives **£245**
- **CLD800** Mitsubishi Double sided 80 track 800K, 5 1/4" TWIN Drives **£359**
- **CLD800S** Mitsubishi Double sided 40/80 track switchable, 800K, Drives **£399**

(CUMANA) DRIVES CASED

WITH PSU & CABLES



- **CS100** TEC Single sided 40 track 100K 5 1/4" Single Disc Drive **£139**
- **CS200** TEC Single sided 80 track 200K 5 1/4" Single Disc Drive **£205**
- **CS400** Mitsubishi Double sided 80 track 400K 5 1/4" Single Drive **£225**
- **CS400S** Mitsubishi Double sided 40/80 track 400K 5 1/4" Single Drive **£340**
- **CD200** TEC Single sided 40 track 200K 5 1/4" TWIN Disc Drives **£245**
- **CD400** TEC Single sided 40 track 200K 5 1/4" TWIN Disc Drives **£365**
- **CD800** Mitsubishi Double sided 80 track 800K 5 1/4" TWIN Drives **£425**
- **CD800S** Mitsubishi Double sided 40/80 track Switchable 800K TWIN Drives **£465**
- **SPARE DRIVE CABLES, SINGLE £6; DUAL £8**
- **DFS Manual (comprehensive) £7.50 (No VAT)**

P.S.

1. You do not require Formatting Discs when using our DFS as the formatting program is in the ROM, nor do you require expensive 40/80 track switchable drives as with our DFS you can read and write both 40 and 80 track discs in an 80 track drive (software switchable).


2. Our **MITSUBISHI** Slimline Disc Drives are Double Sided, Double Density, 1 Megabyte. Track density 96 TPI, track to track access time 3mSec. They are fast, efficient and highly reliable.

Continued



WONDERFUL WATFORD

TWO DATABASE SOFTWARE for BBC MICRO



DISCDATA

At last for BBC Micro Disc users, Watford Electronics have produced 'DISCDATA' which must be the most versatile general database at the price on the market. The length of your files is restricted only by the space on your disc. You can have upto 20 fields with 'page' length records of upto 254 characters. The program is completely menu driven obviating reference to a manual although written guidance is given with the program. Add and delete records, amend title, field names and records, sort on any field and search for any record or group of records in any field. You do not need to abandon or rewrite your files if you wish to add additional fields or extend the length of any field, the program will rewrite the files for you. Your files can be in any drive. Output can be in 40, 80 or 132 character width with Printer routines. Two forms of output are provided for horizontal for label type output and a tabulated output with title and headings. What is more, the selected fields can be placed in any order on the screen. In the horizontal mode you can scan backwards or forwards with wrap around effect. Output can be started or stopped anywhere in the file. There is automatic totalling on decimal fields and an automatic count of the number of records output. Now with extra 3 features: Allows string search; Calculations can be done on numeric fields; Create Sub-Files from the main File.


On disc at **Only £15**
It has to be the best value.

FILE-PLUS

Now even more powerful with the added facility of a SHELL SORT on any field. This must make DATA-PLUS the most powerful and versatile Database to be found on BBC Micro. A 16K ROM containing the most flexible and easy to use disk based Database system on the market. A database may occupy your total on-line storage capacity. You may design any number of data entry forms using a "paint" on screen technique. Forms may be upto 3 screens in size. A form may be used to Add, Delete, Update, Print and Spool records from your Database. Quick search facility on any text field. A query language provides full maths support (-, +, /, *, +-999999999.9999) and compare facilities (=, >, <, <=, >=, &, !) when used with the keywords - Assign, Compare, Display, End, Goto, If, Ift, Print, Read, Search, Spool and Update. Full printed output control via embedded commands. Supplied with 70 page manual and fitting instructions.

Only £43

BUFFER & BACKUP ROM



A very versatile firmware. An ideal ROM for engineers, programmers, teachers, students, etc.

- ★ Converts your Sideways RAM to a 4K or 16K BUFFER for a parallel printer. (Uses * FX5,3). (You no longer require to purchase expensive (£100+) Printer Buffers.)
- ★ Dumps selection of Disc files to Tape.
- ★ Makes backup copies of tapes onto Tape, Disc and Hobbit.
- ★ Displays contents of a chosen paged ROM on screen.
- ★ Menu display on 'shift-break' using ROM Filing System.
- ★ Comprehensive Manual

Simply a give away at **£18**

GEMINI'S BUSINESS SOFTWARE

Cashbook Accounts	£52
Final Accounts	£52
Invoices & Statements	£17.25
Commercial Accounts	£17.25
Mailing List	£17.25
Database	£17.25
Stock Control	£17.25
Home Accounts	£17.25
Beebcalc Spreadsheet Analysis	£17.25
Beebplot	£17.25
Payroll	£39

N.B. All the above Gemini software is on tape. For Disc Based (40/80 track) please add £3.

VERSATILE LIGHT PEN SOFTWARE

- Enjoy, Explore, Educate!
- Pixil, Line, Character Definition
- Free hand drawing
- All Colours - MANY Special Effects
- Fill, Refill and Stripes
- User defined "Brushed Strokes" plus Character definer
- Grid, Scale, Perspective aids
- 2 TO 200 Points palletable in one Design with Circles and "RUBBER BANDING"
- Move design/character to any screen position
- Save and Load screens, User defined Graphics and line drawings for video titles, Own programmes, etc.
- Many Educational uses
- Instruction booklet included
- Full software support for "CUSTOM USE"
- Works with Watford, RH, Acorn User, DIY, and many other LIGHT PENS
- Available on DISC or TAPE


Price: Tape **£10**; Disc **£11**

DISC EXECUTOR

Disc Executor is a highly sophisticated disc utility which allows you to transfer all tape based software that we know of onto disc. You no longer have to throw away any of your cassette based software on acquiring a disc drive. It handles 'locked' programs and allows you to load full length adventure type programs (i.e. up to 6E blocks) and programs that load below &E00. It is very simple to operate (full instructions supplied). It saves you your valuable time and money too. Our Disc executor is not a Replica, its the 'Real Thing'. Available in both 40 and 80 track discs. Please specify when ordering.

Price: **£10**

ROM MANAGER



This unique piece of firmware has been designed to allow the USER to access the BBC Micro's Sideways Rom Paging facility to the full. The 18 Commands our ROM MANAGER adds to your computer are concerned with 3 aspects of ROM use:

1. **ROM CONTROL** - Ability to activate at random any of the ROMs present in the Micro.
2. **BBC MICRO's STATUS** - e.g. Checksum on any ROM, and the Filing system currently active.
3. **ROM DEVELOPMENT** - Allows main memory to be used like Sideways RAM.

The Commands available are:

- ★ **CHECKSUM** - generates a CRC for the specified ROM.
- ★ **DIRECT** - allows you to pass a particular command to the specified ROM.
- ★ **EXAMINE** - allows examination of the named ROM.
- ★ **EXPLAIN** - gives detailed description of the first 22 FX codes.
- ★ **FILE** - passes the command directly to the currently selected filing system.
- ★ **FUNCTION** - displays the string currently programmed onto the function keys.
- ★ **INCLUDE** - allows he main memory to be used for developing ROM software without need to purchase expensive sideways RAM.
- ★ **MODIFY** - any location in memory is displayed and can be modified with this command.
- ★ **NAMES** - displays the names of any resident ROMs.
- ★ **RAM** - allows the command to be passed directly to the 'RAM based ROM'.
- ★ **REMOVE** - turns off the 'RAM based ROM' option.
- ★ **SPECIFY and *DEFAULT** - specifies the default ROM and passes the named command to the default ROM specified.
- ★ **STOP and *START** - allows the named ROM to be disabled or enabled, preventing clashes between ROMs.
- ★ **STATUS** - provides information about the ROMs inside the BBC micro, including the socket number, the name of the ROM, its length, whether or not it is enabled and supports language or service entry points.
- ★ **VALUES** - outputs information concerning the status of ROM MANAGER e.g. the socket number it occupies, the number of active ROMs with a higher priority than itself, the current filing system.
- ★ **VECTOR** - the same function as *DIRECT, but provided in case *DIRECT clashes with other ROMs.

In our opinion this ROM is one of the most useful utility ROMs available on the market, and is a must for anyone using ROM based software.

Introductory Price: **Only £19**

ADE


The complete program development package on 16K ROM. A must for all the Assembly Language Programmers.

Introductory price: **Only: £52**

ACCESS HOT LINE

Tel: 0923 50234

BEEB MON



Watford's own Machine code Monitor ROM written by Andrew Bray (Cambridge), co-author of the BBC Micro Advance User Guide.

The most powerful and versatile machine code monitor ROM yet written for BBC Micro. It has all the normal memory editing, moving and relocating facilities, plus all editing is with a full screen editor allowing scrolling up and down memory, entering in Hex, ASCII or standard assembler mnemonics.

In use as a debugging tool, you run code under a total emulation system. Everfelt a desperate urge to set a breakpoint in ROM? No problem - you can even have breakpoint on reading or writing locations in memory and on register contents. The system fully supports debugging of sideways ROMs e.g. BASIC can fully and easily be run from within Beebmon and from there DFS and other sideways ROMs can be used in total emulation mode.

Beebmon can even run itself. In so doing you can nest Beebmon up to a level limited only by the memory size. Beebmon uses 256 bytes of workspace, located anywhere in memory, even on the 1MHz Bus. Beebmon effectively uses no zero page workspace, so your program (e.g. BASIC) can use any or all of the base page. How does it achieve this? By providing a 6502 interpreter all programs running under it exist in a virtual BBC, so special memory locations like the ROM latch are not actually accessed by your programs, instead they alter a location in Beebmon's workspace. Emulation also allows immediate return to Beebmon command level by ctrl-escape no matter what code is being executed at the time. All this exceptional power and flexibility is complemented by a clear and detailed manual included in a value for money price of:

£22



Discover the hidden secrets of BASIC and the OPERATING SYSTEM with this easy to use programmers tool.

A ROM based machine code Disassembler for the BBC micro. It enables machine code programs to be listed in BASIC/DUMP format and thus is the perfect complement to the built in assembler. It allows Sideways ROMs, files on disk or tape to be listed, and also has a comprehensive editor, allowing mnemonics to be altered directly, as well as HEX, DECIMAL, ASCII and BINARY memory editing. There is also a full set of labelling facilities available (up to 3,200 labels), with the major locations and routines already labelled.

Thus DIS-ASM enables any monitor program, such as BEEBMON to be used to much greater effect as it is not necessary to disassemble memory each time the display is altered.

ONLY £16

(Price includes a comprehensive manual and fitting instructions.)

COMPUTER CONCEPT'S ROMS

Graphics ROM **£28**

Basic Utility ROM **£28**

DISC DOCTOR

A sophisticated Disc Utility ROM with many useful commands. (For detail description please refer to Computer Concept's advert in this magazine.)

£27

Wordwise

Without doubt a very sophisticated piece of software for the BBC Micro. It has all the features of a professional word processor yet is easy to use.

SPECIAL OFFER THIS MONTH: £32

THE INVESTIGATOR

Now you can make up back-up copies of all your Discs. Put the precious originals away in the safe and use your duplicates.

See what your 8271 can do! With Watford's Investigator you can find out about track formatting, sector length, etc. Investigate your disc and then make up your back-up copy.

Disc based software includes a comprehensive manual.

Price: £15

(Please specify 40 or 80 track when ordering)

CRAWLER

A new challenge for your reflexes, exercise for your fingers. Crawler is the best yet BBC version of the popular arcade game "CENTIPEDE". Blast the voracious caterpillar before it eats you. Avoid the wandering spiders. Shoot the scorpions before they poison the mushrooms. Kill the descending fleas as they cause massive mushroom growth. This game is a delight to play. The controls are responsive and fast yet precise.

Only £5

LIGHT PEN


A Light Pen for BBC Micro including our highly sophisticated Pen-Pal software on tape.

Only: £18

(Please add £2 for software on disc)

WATFORD - Always a step ahead

GRAPH PAD



With this popular British Micro's Graph-pad, you can add new dimension to your computer enjoyment. It helps you to create your own application programs by the simple use of the Graphpad. Ideal for Educational use. Supplied complete with Cables, Manual and a two program cassette.

Price: £125

GAMES SOFTWARE

CHESS	£6.95
CROACKER	£6.95
Escape from MOONBASE ALPHA	£6.95
CHUCKIE EGG	£7.90
FELIX in the FACTORY	£6.95
GALACTIC COMMANDER	£6.95
KILLER GORILLA	£6.95
MUNCHYMAN	£5.95
MOONRAIDER	£6.95
MUSIC SYNTHESISER	£8.25
PENGO (Watford)	£7.75
SWOOP	£6.95
Twin Kingdom Valley	£8.25
747 FLIGHT SIMULATOR	£7.75

LEVEL 9 ADVENTURE GAMES

COLOSSAL ADVENTURE. The classical mainframe game "Adventure" with all the original puzzles plus 70 extra rooms.

£8.65

ADVENTURE QUEST. Through forest, mountains, desert, caves, water, fire, moorland and swamp on an epic quest vs tyranny.

£8.50

DUNGEON ADVENTURE. Over 100 puzzles in the Demon Lord's dungeons.

£8.50

SNOWBALL. Save a 7000 location colony starship in 2302 AD.

£8.50

SURGE PROTECTOR Plug

Safely eliminates dangerous voltage surges. During a thunderstorm, a nearby lightning strike can induce high voltage spikes in the voltage supply or fluctuating loads can also result in transient overvoltages which if unchecked, lead to expensive data corruption/loss. Our surge protection plug will provide the necessary surge protection. Simply replace your standard 13Amp mains plug with the surge protection plug (which is almost the same size). Ideal for computers, Hi-Fi systems, precision instruments, fridge freezers, etc. Max. surge current 2KAmp; Max. Voltage 250 Volts. A must for all serious computer users.

Price: £8.95

WATFORD ELECTRONICS

Continued →

MK 2 13 ROM SOCKET EXPANSION BOARD

Now all lines fully buffered – On board battery back-up facility – will now accept EPROMs 2716, 2732, 2764 & 27128 and ROMs 6116 & 6264.

Simply plugs into one of the four ROM sockets currently available in BBC Micro. There are only 5 solder connections to be made. Full instructions are supplied. This board has been ergonomically designed to enable the user, easy further expansion inside the Micro, e.g. Double Density Board, Torch Board, etc. (At Watford, we think ahead.)

Our Mk2 13 ROM Socket Board enables the User to increase the sideways ROM capacity from the basic 4 sockets upto full 16 capable of being supported by current operating systems. In addition the board is designed with the facility to hold upto 16K RAM, which when switched into operation is automatically selected by any WRITE signal to the Sideways ROM area. This gives the User the ability to write a utility or language and upon pressing break have the utility or language up and running (new ROM software can be developed and tested in situ.)

The Board gives the User, plenty of freedom to explore the possibilities of the new paged ROMs due in the coming months and offers them the chance to develop their own.

All lines are fully buffered and the Board meets or exceeds all timings for operation in the BBC Microcomputer. When fully populated, the ROM Board consumes less than half the recommended maximum current limit.

Supplied ready-built and tested complete with fitting instructions.

ONLY £32.50 (carr. £1)

Versatile **BEEB SPEECH** **SYNTHESISER** Unit



SIMPLY the best! – An unlimited speech synthesis system. Complete with easy-to-follow manual. Controlling software is in ROM so no Cassette Loading problems!

PHONEMES for word synthesis – That means unlimited vocabulary! No extra speech dictionary chips to buy!

BUILT-in Library of approximately 500 words to get you started.

ENGLISH accent – Utilises inflexion techniques to produce highly comprehensible speech.

EASY to use system – Just plug the software ROM into a socket, the Speech unit into the User Port, and away you go! No specialised 'dealer upgrade' required!

COMPACT unit – The whole system is built into a small case – easily tucked behind the computer. Auxillary output socket provided for direct connection to an external amplifier.


HOURS of fun! – Suitable for any application – Games, Educational Programs, Specialised Packages.

We know this all seems to good to be true but **DON'T BE LEFT SPEECHLESS!** Order your Versatile Speech Unit now!

Only £44

THE ULTIMATE DFS FOR BBC MICRO

by



Highly acclaimed at The ACORN and BBC MICRO USER Shows. What do the independent press say?

Good value for money – *Beebug Aug. '83*
A very worthwhile package – *The Micro User*
You'll be buying a very powerful package – *Personal Computer News*
Superior DFS: Excellent disc sector editor – *Computer Answers*

Without a doubt, the most sophisticated DFS Software yet written for BBC Micro Computer. This powerful new DFS is fully compatible with ACORN DFS yet has much increased power due to additions, carefully designed to make life easier in normal use. It consists of over 14K of efficiently written machine code. It is entirely self contained and so does not require a utilities disc to function.

PRICES:
DFS (Disc Filing System) ROM **£29**

Complete Disc Interface Kit including DFS ROM & Fitting instructions £99

Disc Filing System Manual. Comprehensive and clearly written **£7.50** (no VAT)


P.S. We will exchange your existing ACORN DFS or PACE (AMCOM) DFS for Watford's highly sophisticated 16K DFS ROM for **£25**

Watford's DFS is exclusively available from Watford Electronics. We do NOT retail through any dealers. Every ROM carries a label with our LOGO and a serial number.

EPROMs & CMOS RAMs

2764-250nS (8K ROM)	£5.95
27128-250nS (16K ROM)	£24.00
6116-150nS (2K RAM)	£6.00
6264-150nS (8K RAM)	£32.00

SPECIAL DISC DRIVE OFFER NEW SLIMLINE, 5 1/4", CASED WITH CABLES



CLS100 TEC, Single 100K, 40 track, Single Sided	£115
CLS400 Mitsubishi, Single 400K, 80 track, Double Sided	£165
CLD200 TEC, Twin 200K, 40 track, Single Sided	£225
CLD800 Mitsubishi, Twin 800K, 80 track, Double Sided	£325

(Carriage £5 securicor, insured)

BEEBFONT ROM

BEEBFONT is a remarkable new concept in BBC software, exclusively available from Watford. Once fitted, the 16K ROM will enable you to produce attractive text displays in following different styles:

ABCDEFGHIJKLMNPO

abcdefghijklmnop

ABCDEFGHIJKLMNPO

ABCDEFGHIJKLMNPO

abcdefghijklmnop

ABCDEFGHIJKLMNPO

ABCDEFGHIJKLMNPO

abcdefghijklmnop

ABCDEFGHIJKLMNPO

ABCDEFGHIJKLMNPO

abcdefghijklmnop

ABCDEFGHIJKLMNPO

ABCDEFGHIJKLMNPO

- ★ It works in modes 0, 1, 2, 4, using full colour.
- ★ Simply use Ctrl-V to select the font and all further screen output will be in a new style.
- ★ Even the ordinary Beeb character set can be enhanced by doubling height or width and emphasising to give bold print.
- ★ A comprehensive editor is included which enables the user to design his own characters.
- ★ A spooling program is provided, which enables pre-formatted text files to be displayed on an EPSON FX, RX, and NEC Printers, using the full range of character styles. (Please specify printer type when ordering). Can be used with WORDWISE.
- ★ This really must be one of the most original and exciting products of the year.
- ★ A twenty page manual is provided and the demo/editor software comes on disc or cassette (please specify when ordering). **ONLY £39**

WATFORD'S BEEB PRINTER ROM



"Makes Printing Childs Play"

Are you fed up with not being able to unravel your printer manual and use all those features you paid for? Need sensible paging for use in the creation of booklets? Then you certainly need our Beeb Printer ROM.

A machine code printer utility in ROM.

- 'Single' key operations replace control code sequences for underline, font and size selection, paper movement, etc. Up to 30 come pre-defined, without effecting normal fn key usage.
- This rom allows easy control of your printer from 'Within' WORDWISE text. Instead of long escape sequences, you just 'OC' a single number to Select, Underline, Print Styles, etc.
- Automatic fanfold page margins. Puts gaps in listings. PRINTed text etc to skip the folds. The gap size alternates to minimise paper wastage when using binders.
- Form feed and related commands, made available on ALL printers. Can also provide a left margin.
- User defined characters embedded within text are printed as on VDU.
- Commands select option for GP100, STAR, NEC, MX/FX, LP VII/DMP100, DMP200. Operates with Parallel and Serial Printers.
- Fully functional with the popular WORDWISE wordprocessor.

Supplied complete with a comprehensive 50 page manual.

Price: £24

(When ordering, please specify printer type)

DUMP OUT 3

A highly sophisticated machine code ROM providing screen to printer dumps in any mode, plus window setting utilities and two new OSWORD calls that allow you to use the Beeb graphic coordinate system for plotting or testing mode 7 'pixels'.

*GIMAGE Ultra sophisticated dump of any graphic screen, using up to 8 tones. Handles **FULL MODE 7 text**, graphics, double-height and colour and mode 8. 14 optional parameters, using 'prefixing' so that you only need specify the ones that you want. The parameters include:

- V<scale>, H<scale>. These are both 2 byte numbers giving you very fine control over the dump size from minute to enormous. Unlike other dump Roms, scale does not vary with screen mode.
 - R <0-3> Dump rotation 0, 90, 180, 270 degrees.
 - I<indent> Set gap from left edge of paper.
 - X <min> <max>, Y <min> <max>. The area of the screen dumped is that in the graphics window; alternatively these parameters may be given.
 - P Physical colour values used for dumping. (Otherwise use a negative scale, i.e. white prints darkest.)
 - T Two tone dumps for higher resolution.
 - M <mask> 8 bits controlling colour masking.
 - E Contrast expansion. Makes mode 7 text characters and separated graphics stand out more clearly from the background.
 - C All mode 7 graphics printed as reduced size dumps.
 - *GWINDOW Draws graphic window on screen, its size and position can then be altered using the cursor keys.
 - *TIMAGE <indent> Does a fast, text only dump of the text window in any mode.
 - *TWINDOW As GWINDOW but for text.
- DUMP OUT 3 gives you ALL of the GIMAGE facilities listed above and GWINDOW in mode 7 as well, not just hi-res modes.
- Ideal for CP80, GP80, DP100, GP250, STAR, KAGA/TAXAN, NEC, SHINWA, CP80, GEMINI, EPSON MX/RX/FX, LPVII, DMP100/120/200/400 Printers.
- Comprehensive Manual included. **Only: £19**

WATFORD JOINS THE COMMUNICATION REVOLUTION

MODEM 84

APPROVED for use with telecommunication systems run by British Telecommunications in accordance with the conditions in the instructions for use.

With the launch of Watford's MODEM 84 you can now hook into PRESTEL, MICRONET, HOMELINK, TELECOM GOLD, etc., for about the cost of a good tape recorder. Prestel gives you access to an incomparable database covering almost every subject under the Sun. There is Micronet with lots of free programs that you can download and run. Details of Clubs and User groups, a diary of meetings and exhibitions, news and reviews, technical information, etc. There is Homelink with On-line banking. And there is armchair shopping, travel information, Entertainment, World News, Sports News, Business News, Weather information, Electronic mail and lots more. The basic Prestel subscription is only £5 per quarter for domestic user and at off-peak times there is no charge for access time. Can you afford not to be part of this revolution?

Now using the latest techniques and the new generation of Modem chips, Watford have developed a Modem that is newer, better and yet cheaper than any on the market.

Compare the Specifications:

MODEM

- Direct-connect Modem using BT approved isolation components.
- Full Duplex V23 operation for Prestel and TELECOM GOLD operation (1200/75 Baud).
- User-to-User half duplex 1200/1200 Baud operation with AUTOMATIC SEND/RECEIVE switch (BEWARE - most MODEMS switch manually between send and receive, which precludes the use of intelligent user-to-user software).
- Simple single button operation and comprehensive LED status display.
- Attractively finished. Sized to sit on the Disc drive.



NEW SUPER PRESTEL INTERFACE ROM

Fully compatible with Watford's MODEM 84 as well as with PRISM and most other Modems.

- Supports full Prestel Colour Alpha and Graphic Characters including Double Height, Flashing, Conceal/Reveal.
- Called by simple *PRESTEL command. Disc and Tape configurations fully supported.
- Telesoftware downloader included.
- Comprehensive MAILBOX facilities including offline editor.
- Auto Logon sequence, can be burnt into ROM if desired.
- Unique "TAG" facility allows tagging and recall of interesting pages - avoids the common and annoying 'NOW WHERE WAS THAT PAGE' problem.
- Page load and save to tape or disc. Pages are automatically saved under Page Number reference in a 'FRAME' directory.
- Print page options are ASCII only (i.e. with suppression of Graphics) - fast and works with any printer - as well as a full graphics dump for the popular Epson printer.
- 'USER' function call built into interface with specialist add-on routines (your own as well as ours).
- All the above facilities available from Function Keys. An overlay is provided giving simple yet comprehensive guidance to the key functions.
- Comprehensive instruction manual supplied.

PRICES:

SOFTWARE ROM incl. Comprehensive Manual	£20
MODEM 84 (without software)	£62
MODEM 84, SOFTWARE ROM and Operating Manuals	ONLY: £75 (£2 carr.)

(Please allow upto 28 days for delivery)

Please write to Watford Electronics for full details, Order and Application Forms.

NEW FX80 PRINTER DRIVER for VIEW

Do you want to use Italics or Enlarged Characters with View? French or German Characters? These and other FONTS from FX80 character sets can be accessed using our Printer Driver with VIEW. The disc contains an example as well shows how to use. Available on 40 or 80 track Disc. **ONLY: £7.50**

EPSON DUMP ROM

A specially designed Dump ROM for EPSON RX, FX and the new Kaga KP810 Printers. Will accurately DUMP all Screen modes including TELETXT, GRAPHICS and DOUBLE HEIGHT. MULTITONE DUMPS are also supported. Simple single command (*SCDUMP) operation.

Only: £16

TINY PASCAL for BBC Micro £59

VIEW

Wordprocessor (New version) **£52**

FORTH ROM for BBC

This superb (FIG FORTH) compiling language now available in ROM. Simply plugs into one of the ROM Sockets. Manual included. **£33**

**WATFORD
ELECTRONICS**

Continued

BOOKS (No VAT on Books)

30 Programs - BBC Micro	£3.25
30 Hour BASIC (BBC Micro)	£6.95
35 Education Programs for BBC	£6.95
36 Challenging Games for BBC	£5.95
40 Educational Programs for BBC	£5.95
100 Programs for BBC Micro	£6.95
Cassette version of above	£10.00
6502 Application Book	£11.95
6502 Assembly Language Program ..	£13.95
6502 Assembly Language Subroutines	£14.25
6502 Machine Code for Beginners	£5.95
6502 Software Design	£10.50
A young persons guide to BBC Basic ..	£4.50
Advanced Machine Code Technique for BBC	£7.95
Advanced User Guide for BBC Micro	£12.50
Advanced Graphics with BBC	£9.95
Advanced 6502 Interfacing	£10.95
Advanced 6502 Programming	£12.45
Assembly Language Programming on BBC Micro	£7.95
Advanced Programming Techniques for the BBC Micro	£7.95
BBC Basic	£7.95
Assembly Lang. Prog. on BBC	£7.40
BBC BASIC	£5.95
BBC Basic for Beginners	£6.95
BBC DIY Robotics & Sensors	£6.95
BBC Forth	£7.50
BBC Lisp	£7.50
BBC Micro An Expert Guide	£6.95
BBC Micro Book BASIC Sound & Graphics	£7.95
BBC Micro Graphics and Sound	£6.95
BBC Micro Programs in Basic	£5.95
BBC Micro ROM PAGING System Explained	£2.95
BBC Micro Revealed	£6.95
BBC Micro Assembly Lang. Prog.	£7.95
BBC Micro Disc Companion	£7.95
BBC Micro in Education	£6.50
Basic Programming on BBC Micro	£5.95
Best of PCW Software (BBC)	£5.95
CP/M Users Guide	£13.95
Creating Adventure Programs on BBC Micros	£6.95
Creative Graphics Cassette (Acornsoft). Has 36 graphics programs	£8.95
Creative graphics on BBC Micro	£7.50
Complete Programmer for BBC	£5.95
DISC FILING SYSTEM (DFS) Operating Manual for BBC	£7.50
Discover BBC Machine Code	£6.95
Discover FORTH	£13.95
DIY Robotics & Sensors with BBC	£6.95
Further Prog. for BBC Micro	£5.95
FORTH Programming	£14.40
Functional Forth for the BBC Micro	£5.95
Games on your BBC Micro	£2.95
Games BBC Computer Can Play	£6.95
Graphs & Charts on BBC Micro	£7.50
Graphic Art for BBC Computer	£5.95
Graphs and Charts (Cassette)	£7.50
Graphics on BBC Micro	£6.95
Hobbit (Book and Cassette)	£14.95
Introducing the BBC Micro	£5.95
Introduction to FORTH	£9.30
Intro to Micro Beginners Book (3 Ed.)	£9.90
Let your BBC teach u to program	£6.45
LISP	£9.25
Logo Programming	£8.95
Mastering VISICALC	£12.45
Mastering CP/M	£13.65
Micros in the Classroom	£4.90
Programming the 6502	£11.95
Programming & Interfacing 6502	£16.00
Programming the BBC Micro	£6.95
PASCAL	£9.25
Programming for Education on BBC ..	£5.95
Structured Prog. with BBC BASIC	£6.50
The Complete FORTH	£6.95
The BBC Micro Book, BASIC, SOUND & GRAPHICS	£7.40
Using Floppy Discs with BBC Micro ..	£5.95
Using BBC Basic	£6.95
Using 6502 Ass. Language	£14.50
Wordstar & CP/M made easy	£6.95

DOUBLE DENSITY BOARD FOR BBC

We are proud to announce the launch of our Double Density Board for the BBC Micro. The DDFS software that we supply is a version of our highly acclaimed standard 16K DFS for the BBC Micro. It will automatically tell whether a single or double density disc is being accessed, as well as allowing the option of reading 40 track disc on an 80 track drive. Now on your 80 track Double Sided Drive you will have 720K storage instead of the usual 400K and with higher speed than ever before (of course this is a BONUS at NO EXTRA COST). Complete Double Density Upgrade Unit will cost same as single density Kit.

Delivery 8 weeks (approx)

DATA RECORDER & ACCESSORIES

Top quality Slimline, portable Data Recorder for computer use. Mains/Battery, operated with counter **£24.00**

DATA RECORDER CABLE
For our Data Recorder to BBC Micro **£2.50**

DATA CASSETTES Top grade C12 Data
Cassettes in library cases. **36p**

ATTACHE CARRYING CASE for BBC Micro

These Attache Carrying cases are attractively finished in mottled antique brown leatherette. An ideal and very safe way to carry your BBC Microcomputer. Price: **£12 (£2 carr.)**

**This space reserved
for our
'Launch of the Year'
Hardware.**

- to be unveiled at
the Electron & BBC
Micro User Show,
Alexandra Palace -
July 19-22.



VOLTMACE'S DELTA 14 Hand-set

Price: 'Delta 14' Hand set **£12.50**
ADAPTOR MODULE **£12.55**
Tape **£5.10**
TRANSFER PROGRAM **Disc £7.95**

JOYSTICKS for BEEB

Two versions available:
SINGLE: Player type **£7.00 each**
TWO Players type **£12.00 per pair**

Prices subject to change without notice and availability.


MAIL ORDER AND RETAIL SHOP. TRADE AND EXPORT INQUIRIES WELCOME. GOVERNMENT AND EDUCATIONAL ESTABLISHMENTS OFFICIAL ORDERS ACCEPTED. CARRIAGE: Unless stated otherwise, please add 75p to all cash orders.

VAT: UK customers please add 15% VAT to the total cost incl. Carriage.

SHOP HOURS: 9.00am to 6.00pm. Monday to Saturday. (Ample Free Car Parking Spaces) ACCESS ORDERS: Simply phone: Watford (0923) 50234. (24 Hours)

Watford Electronics
Dept. BBC, Cardiff Road, Watford, Herts, England.
Telephone: 0923 40588/37774. Telex: 8956095

PLINTH FOR BBC MICRO



Protect your micro from the weight of the heavy TV/Monitor. This sturdy plinth is attractively finished in BBC colour. Air vent slots have been provided to allow maximum air circulation. It can be used to support a monitor or a printer. The micro slides underneath comfortably. A must for every BBC Micro owner, specially for those who have to move/open their computer frequently.


Single Decker **£11 (carr. £1.50)**
Double Decker **£20 (carr. £2.00)**

PLINTH FOR PRINTERS

Keeps your desk tidy. Place the printer on the plinth and the paper underneath. Finished in BBC colour.

£10 (carr. £1.50)

4 WAY MAINS DISTRIBUTION SOCKET



A highly versatile space saving solution when multi-power outlets are required. Can be wall or floor mounted. Ideal for Micro Computer and peripherals application. Prevents you getting a dangerous tangle of plugs and adapters.

Only: **£9.50**

READY-MADE LEADS

CASSETTE LEADS 7 pin DIN Plug
to 5 pin DIN Plug + 1 Jack Plug **£2.00**
to 3 pin DIN Plug + 1 Jack Plug **£2.00**
to 7 pin DIN Plug **£2.50**
to 3 Jack Plugs **£2.00**
6 pin DIN to 6 pin DIN Plug (RGB) **£2.50**
Monitor Lead, BNC to PHONO **£3.00**
Disc Drive to BBC Micro Power Lead
Single: **£3.00** Dual **£3.75**

MISCELLANEOUS CONNECTORS

	Plugs	Sockets
RGB (6 PIN DIN)	30p	45p
RS423 (5 pin Domino)	40p	50p
Cassette (7 pin DIN)	25p	65p
ECONET (5 pin DIN)	20p	30p
Paddles (15 pin 'D')	110p	215p
BBC Power Plug 6 way	80p	-
Disc Drive Plug 4 way	75p	-

SYSTEMS



ADVANCE 86

IBM compatible, 128K RAM, 2 x 320K Drives. Price includes: Perfect Writer, Perfect Speller, Perfect Filer and Perfect Calc, plus 12 months on site warranty (monitor available at extra cost).

£1437

SANYO 555


80% IBM compatible, 128K RAM, 2 x 160K Drives. Price includes: Wordstar, Mailmerge, Info-Star and Calc-Star. Limited number of SAGE Accounts still available.

(Monitor available at extra cost) £1148



ELECTRON £199

Includes free software tape



BBC-B £399

Includes free tape recorder. Full range of Software and Disk Drives available.

PRINTERS


Brother Printer HR 15 £399

Juki Daisywheel 6100 £389

Daisystep £295

EPSON RX80 FT £299

EPSON FX80 £389



Including lead for BBC.

DISKETTES



Memorex, in packs of 10

SS 40tk.....£18.00

DS 40tk.....£23.00

SS 80tk.....£26.00

DS 80tk.....£29.00


Including VAT, p&p.

Stay tuned to Microware for further discounts

EPSON DISK DRIVES

200K-400K-800K

plus new 3 1/2" range (including manual 8 formatter)




100k single unit £139

100k dual unit £229

200k single unit £195


200k dual unit £325



400k single unit £225

400k dual unit £349

Switchable £375



UDM DDFS £95

MONITORS


Microvitec colour

Normal res. £199

Medium res. £299

High res. £399

Sanyo/BMC 12" C £110




Call for our full price list.

ACCESSORIES

BBC Stands.....£15.00

Dust covers.....£5.60

(for BBC, Drives and Printers)



Disk storage boxes.....£17.00 (takes 35)

Disk storage boxes.....£25.00 (takes 80)

Prices include VAT, p&p.

ORDER FORM

Product	Price	Qty.	Total
_____	_____	_____	£_____
_____	_____	_____	£_____
_____	_____	_____	£_____
_____	_____	_____	£_____
_____	_____	_____	£_____
_____	_____	_____	£_____
_____	_____	_____	£_____
_____	_____	_____	£_____

SEND DETAILS ON _____

TOTAL SUM ENCLOSED (Cheque or credit card no.) £_____

ALL PRODUCTS ARE BRAND NEW, BOXED AND OFFERED WITH FULL MANUFACTURERS WARRANTY. All prices include VAT & delivery

MICROWARE

14 Charles Street Hanley Stoke-on-Trent
(0782) 269 883
67 Westow St. Upper Norwood London SE19
01-771 5123
637 Holloway Road London N19 5SS
01-272 6398

SEE US AT

The 2nd
Official
Acom User
Exhibition
OLYMPIA
16-19 AUGUST
1984

I enclose my order for the above products.

Name _____

Address _____

Signed _____

Increase your fire power!

More than just a joystick - a system

- ▲ Nylon encased - Steel shafted joystick with ball and socket joint.
- ▲ Fast sprung return to centre.
- ▲ Graphite wiper linear potentiometers.
- ▲ 12 Months Guarantee.
- ▲ 7 day Money back Guarantee (on Hardware).

DELTA 14b HANDSET £14.95
DELTA 14b/1 A/D/USER PORT INTERFACE £14.85
DELTA DRIVER CASSETTE £5.95 or DISC £9.95
 Prices include VAT and P&P. SAE for more detailed information.

VOLTMACE LTD
PARK DRIVE
BALDOCK
HERTS
SG7 6EZ
 Tel: (0462) 894410

Numerous stockists
 nationwide or direct
 from us.



Callers welcome at the
 factory - Monday to Friday.



Complete control at your fingertips

A superb joystick and a keypad for the price of either one. Plus the software to integrate it into the computer's system.


One handset will work on it's own in the A/D port as a joystick and two fire buttons. Joystick is immediately compatible with ACORNSOFT and similar software. The interface joins together the analogue and the user ports to use the full keypads giving a total of 24 user definable keys. The interface can also be used as a splitter for the A/D port to take two items at the same time, e.g. joystick and lightpen.

DELTA DRIVER on cassette or disc: Two programs on each cassette or disc. One converts machine code programs from the keyboard to the joystick or keypad, with adjustable sensitivity on the joystick and will run on any O.S. The second program (needs O.S. 1.0 or later and an interface) duplicates any keyboard keys on the keypads, in the operating system, so that it can become a numeric keypad or will take on the function keys.

Voltmacedelta 14b

Robot Plotter

£59.50
 INC. VAT
 CARRIAGE
 £3.00



- ★ FOR BBC MICRO MODEL B CASSETTE OR DISC
- ★ ENABLES PICTURES TO BE DRAWN OR TRACED
- ★ WORKS IN ANY GRAPHICS MODE - COLOUR SELECTABLE
- ★ DESIGNED BY A TEACHER FOR EDUCATIONAL USES BY STAFF AND PUPILS
- ★ TRANSPARENT TABLET ALLOWS DIAGRAMS AND MAPS, ETC. TO BE COPIED
- ★ ROUTINE INCLUDED TO SAVE QUICKLY TO DISC OR CASSETTE
- ★ SCREEN DUMPS FOR EPSON AND SEIKOSHA PRINTERS
- ★ TRIED AND TESTED - DIRECT FROM THE MANUFACTURER

COMMANDS FOR:

- LINES
- CIRCLES
- RECTANGLES
- INFILLING
- COPY AND MOVE
- PRINT AT
- AS WELL AS TRACE MODE

Please send me
 I enclose Cheque/P.O. for
 Name
 Address Code


GOVERNMENT AND EDUCATIONAL ESTABLISHMENT
 OFFICIAL ORDERS WELCOME

Robot COMPUTER DEVELOPMENTS LIMITED

NATIONAL INDUSTRIAL ESTATE
BONTOFT AVENUE, HULL HU5 4HF
TEL: (0482) 448562.

SERIOUS SOFTWARE from BEEBUGSOFT

DESIGN (C.A.D. PACK)



DESIGN is a screen processor which allows information to be displayed in a format suitable for demonstrations, slide projections, handouts or presentations.

Graphs, Pie Charts and Bar Charts are quickly produced on automatically drawn and scaled axes.

Text may be written anywhere on the screen and may be displayed normally, enlarged, underlined or sideways.

Twenty user-defined characters and four large macro characters are supplied, and may be placed anywhere on the screen or redefined as required.

Machine code screen dumps are included for Epson, Seikosha, Shinwa and Star printers and details on how to load dumps for other printers are also included.

Screens may also be saved and reloaded to cassette or disc.

Extensive use of the function keys is made for all the major commands on DESIGN, and a key strip is provided.


DISC
£19.00

CASSETTE
£10.00

"A first rate screen processor... immense value to schools and colleges... ideal tool for preparing display material..."

Educational Computing
April 1984

SPRITE UTILITIES



SPRITE UTILITIES A game writer's utility pack which allows high speed arcade games to be written in Basic.

This is achieved by using the set of supplied machine code sprite routines to move multi-coloured characters (sprites), of your own design, around the screen at high speed.

Control of the sprites' movements is by user written Basic program. Specific commands to the sprites are very simple.

Sprites are generated in mode 2 on a 8 x 16 grid and may include any of the available 16 colours.

Up to seven sprites may be displayed and controlled on the screen at any one time. A special super sprite facility enables clones of each sprite to be created, to provide animation.

"... Definitely recommended"
Electronics & Computing May 1984

"... For my money Sprite Utilities wins through..."
Acorn User May 1984

DISC
£12.00

CASSETTE
£10.00

BEEBUGSOFT, PO BOX 109, HIGH WYCOMBE, BUCKS. HP10 8HQ

BEEBUGSOFT products are available from major dealers including selected branches of W. H. Smiths. You may also order direct from Beebugsoft.

Please send me.....Design Discs @ £19.00.....Design Cassettes @ £10.00

Please send me.....Sprites Discs @ £12.00.....Sprites Cassettes @ £10.00

Name


Address

Send Cheque/Postal Orders to BEEBUGSOFT, PO BOX 109, HIGH WYCOMBE, BUCKS. HP10 8HP
(Distribution agents for Beebug Publications Ltd.)

SEE ALSO BEEBUGSOFT DOUBLE COLOUR ADVERT IN THIS ISSUE

TOOLKIT ROM from BEEBUGSOFT

BASIC Programmer's Aid for the BBC micro



©BEEBUGSOFT 1984

- 27 new commands to make life easier
- Saves hours in program development and debugging
- Supports both cassette and disc systems
- No command name conflict with other Roms
- Ideal for expert and novice alike
- Fitting instructions and a 32 page manual supplied
- You'll wonder how you ever managed without it

SPECIAL FEATURES INCLUDE

SCREEN EDITOR An extremely powerful editor, allowing the use of cursor keys to list a program line-by-line in either direction and move to any part of a program to overwrite or insert new code and corrections.

ERROR DETECTION Powerful facility to trap an error in a Basic program as it runs. It will then automatically enter the Screen Editor, display the line in error and position the cursor close to the statement at fault.

"TOOLKIT is an essential utility for all Basic programmers using the BBC Micro. . . . The range is enormous. . . . an indispensable aid packed full of powerful utilities."

EDUCATIONAL COMPUTING MARCH 1984

"... highly recommended."

PCN MARCH 17 1984

"The Beebugsoft Toolkit costs £27 and in my opinion is worth every penny. Since it has been installed in my BBC it has been used extensively and I can find no fault with it. Highly recommended to lazy programmers!"

COMPUTING TODAY JUNE 1984

COMMANDS

*CHECK	Verify a program or data in memory with disc/cassette.
*CLEAR	Clear all variables including integers.
*EDIT	Enter full screen editor.
*FREE	Display free memory and pseudo variables.
*HELP INFO	Display a screenful of useful system information.
*MEMORY	Display memory contents.
*MERGE	Merge a program in memory with one on disc/cassette.
*MOVE	Move program to run at specified address.
*NEW	As NEW, but can be issued from within a program.
*OFF	Cancel enhanced error handling.
*OLD	As OLD, but can be issued from within a program.
*ON	Auto error handling—enters editor at line in error.
*PACK	Efficient program compactor.
*RECOVER	Intelligently recover bad programs.
*RENUMBER	Allow partial renumbering.
*REPORT	Extended error reporting facility.
*SCREEN	Screen dump to cassette or disc.
*UTIL	Display utilities menu.
*UTIL 1	String search.
*UTIL 2	String search and replace.
*UTIL 3	Move Basic program lines.
*UTIL 4	List procedures and functions.
*UTIL 5	List values of A% to Z%.
*UTIL 6	List numeric variables.
*UTIL 7	List string variables.
*UTIL 8	List names of arrays.
*UTIL 9	Set up range for utilities 1 and 2.

BEEBUGSOFT, PO BOX 109, HIGH WYCOMBE, BUCKS HP10 8HQ

Please send me.....Toolkit(s) at £27.00 each

Name

Address

Send Cheque/Postal Order to BEEBUGSOFT,
DEPT 13 , PO BOX 109, HIGH WYCOMBE, BUCKS HP10 8HQ
(Distribution agents for BEEBUG Publications Ltd.)


Available from your dealer
and selected branches of
W.H. Smiths

£27.00

Including
VAT & P&P



SEE ALSO BEEBUGSOFT DOUBLE COLOUR ADVERT IN THIS ISSUE.



Martin Phillips offers his advice on second disc drives, lists commands for Epson printers and an answer to error messages

50

£5 **Doubling up with a second disc drive**


BUYING a second disc drive was the subject of a letter from Mr N Smith from Stoke-on-Trent which wins him £5. He asked if it was possible to add a second drive to his single 40-track, single-sided drive (5¼in discs). The answer is yes, it is easy to do. The connections are straightforward, and only some links on the disc drive circuit board need changing for both drives to be accessed.

The major problem is one of power, unless both drives have their own supply. If the single drive runs from the BBC's power supply, then a second drive can be run from that too, but be warned, this is getting near the limit of the capabilities of the system. The easy answer is to buy a second drive with its own power supply.

The other alternative is to look at the adverts for suppliers of a single drive with power supply in a case designed to take two drives. Here readers should be aware of sizes. There are two 5¼in drive sizes, full-height and half-height, and you can do this only with the half-height drives. These are about 4-5cm high, not including the case. I, in fact, bought a single drive in a double case, then bought a second drive when funds permitted.

The second drive can be 40 or 80-track, single or double sided and may not even be the same make, although this is advisable.

Once the power supply has been sorted out, the ribbon cable from the BBC's disc port to the drive needs to be altered to take the second drive. A second ribbon cable can be fitted on the first without breaking the connections using a Scotchflex 3365/34 or Amp 1-585717-5 connector. This can be fitted anywhere on the ribbon cable, but work out the best place for yourself *before* you actually do it. The new connector is put over the first cable, the top is put on



IF YOU have a technical hitch or a programming problem let Martin Phillips give his diagnosis. We'll pay £5 if you raise a really interesting point. Please give full details of the system you're using and include a listing where appropriate, making your question as specific as possible. **WRITE TO:** Hints & Tips, Acorn User, Redwood Publishing, 68 Long Acre, London WC2E 9JH.

and the assembly squeezed together in a vice. If you have first disconnected the second cable from its drive plug it back into the edge connector on the disc drive circuit board. The colour marker on the cable should be to the right looking from the front of the drive when fitted, but check which way round the cable is in the original drive. As an alternative, a cable can be purchased with two connectors to suit a double drive.

Next, the links need to be set on the second drive's circuit board. These are sometimes in the form of a row of switches, or else a series of small links similar to those on the BBC circuit board. The common types of drive available are Mitsubishi, Tec, Teac and Canon, although more makes are coming onto the market.

There are two sets of links on the Mitsubishi board. Looking from the front of the unit, they are both situated at the far right-hand side near the edge connector. They are a series of pins with coloured jumper clips across pairs of terminals, and can be removed by lifting the clips off the pins.

The link set nearest the edge connector and at right-angles to it should be connected as follows:

	Bottom drive	Top drive
DS0	link	n/c
DS1	n/c	link
DS2	n/c	n/c
DS3	n/c	n/c
MX	n/c	n/c
HS	link	link
HM	n/c	n/c

DS0-4 are the drive selects. These can be changed, but the two drives must have different numbers. It is usual to only use 0 and 1, as the reverse side of double-sided discs use 2 and 3 without any further selection. HM and HS stand for head-to-motor and head-to-select. Either could be selected, but the normal one is HS. In other words the read/write head will only engage the floppy disc when that head is required to communicate with the computer. This is noisier and slower, but reduces wear on the disc and head. Also, it is not so likely to corrupt a disc if the unit is switched off with the disc still in place. The Tec drive does not have a head load solenoid, and so these links are not present. MX is the multiplexing link and should normally be unconnected. MX should always be left unconnected on the half-height drives but on the full height Teac drives this link is the wrong way round, and needs to be made. The half-height Teac drives have come into line with the other drives and do not require the link to be made.

The other set of links are the resistor terminator set. All floppy disc drives need to have the drive cable terminated by a resistor. If a second drive is being installed these resistors should be removed. On the Mitsubishi, they are a series of eight links in a row, near the other links, but on the Teac these resistors are in an IC-type package in

white labelled BECKMAN. This package should be removed from its socket. On the Tec this resistor is also mounted in an IC-type package and can be removed from its socket. As most of the ICs are soldered directly to the board and not socketed, these resistor networks are quite easy to identify. They are very near to the edge connector.

Translating printer commands

for Epson with Wordwise

AT THE request of *Dear Kitty* I include a list of printer commands for Epson printers being used with Wordwise (table 1). The printer manuals have to be written for a variety of computers, and as such need some translation for the BBC micro. Readers with other printers will no doubt find the codes very similar as there is quite good standardisation here.

If using the older Epson printers it might be necessary to include a 1 before each command (eg OC1,27,1, 69). This will be necessary if using these commands with VDU statements for inclusion in programs (eg VDU1,27, 1,69). The commands listed here are the ones I use most frequently. This list pinned up near the computer saves much time and effort.

OC14	Double width (one line only)
OC20	Cancel double width (one line only)
OC27,87,1	Double width
OC27,87,0	Cancel double width
OC27,52	Italics
OC27,53	Cancel italics
OC27,51,72	Double line spacing
OC27,50	Normal line spacing
OC15	Condensed mode
OC18	Cancel condensed mode
OC27,80	Pica mode
OC27,77	Elite mode
OC27,82,X	Alternate character set (English..X=3, American..X=0)
OC27,69	Emphasised printing
OC27,70	Cancel emphasised printing
OC27,71	Double-strike mode setting
OC27,72	Cancel double-strike mode
OC27,78,n	Skip-over perforation setting
OC27,79	Cancel skip-over
OC27,45,1	Underline mode
OC27,45,0	Cancel underline
OC27,83,0	Superscript on
OC27,84	Superscript off
OC27,83,1	Subscript on
OC27,84	Subscript off
OC27,64	Initialise printer. (reset)

Table 1. Translation commands. A list kept to hand saves time and effort

A brighter way

of changing

background colour

ANDY HOLLIS from Exeter has sent in a simple tip to change the background colour when listing programs. There are several ways this can be done, but the way suggested is particularly neat and quick.

Keep the CTRL key pressed and press the keys:

V6SBA000.

This will get mode 6, and turn the background colour to red. Then the printing on the screen will appear in white with black between each line of print. This makes it easier to debug listings. Other background colours (including the flashing colours) can be obtained by changing the 'A'. For instance, 'D' will give a blue background.

This method of changing the background colour and mode cannot be used in programs, and the programmer will need to use the VDU statements in their more normal form.

Two techniques

for turning

the cursor off

SOME months ago, one of my more learned friends peered over my shoulder at a program I was writing, and exclaimed 'You're not still switching the cursor off like that! Haven't you seen the new command?' I almost gave up programming on the spot. However, I have since found that the 'old' method of switching the cursor off can sometimes be used to advantage over the newer method.

There are two ways of turning the cursor off with the BBC, and although one is not in the Electron manual, both work just as well on the Elk.

Diagnosing listings

Martin Phillips goes through some useful techniques to use when you find a program you've typed in doesn't work.

Turn to First Byte on page 33.

The one given in both user guides is:

Cursor off: VDU23, 1, 0; 0; 0; 0;
Cursor on: VDU23, 1, 1; 0; 0; 0;

The BBC guide also says the cursor can be switched off another way:

Cursor off: VDU23;8202;0;0;0;

This latter method produces an interesting character on the screen. It turns the character to be copied the inverse of itself. However, it does have more uses and is more robust. The for-

mer command can be switched on again using VDU4 as well as the command given above. The only way to switch the VDU23;8202 back on is to change mode.

If you are writing a program that requires the text and graphics cursors to be joined and separated repeatedly (VDU5 and VDU4), then the latter method for switching the cursor off using VDU23;8202 is the better one to use as it needs to be used only once in the program (unless the mode is changed).

How to avoid memory problems

when switching from cassette to disc

WHY should programs that would run on cassette start giving error messages like 'No room' or 'Bad mode' on a disc system? asks Mr Winterton. Some programs seem to 'stick' when they get to the menu page and go no further.

The reason is that when a disc filing system (DFS) chip is fitted to a BBC computer it needs some memory of its own to store information. This workspace is just under 3k long, and it is taken from the memory normally used for programs. When the computer is switched on or break is pressed, the DFS grabs its workspace and moves PAGE, the position at which the user's program is loaded. On a cassette machine, PAGE is set to &E00, but on a disc machine this is moved to &1900. (Econet and teletext similarly grab some of the memory for their workspace if fitted.)

The problem experienced by Mr Winterton usually occurs in programs that use graphics and it is when a mode change occurs that the program now finds that it has not enough memory left, hence the 'Bad mode' error. Sometimes a program has an error routine that sends the program back to the menu or title page if an error occurs.

In this case, the program will appear

to cease functioning and remain at the menu or title page with the only option being to press the break key. If one then removes the error routine, the program will usually respond with the 'Bad mode' or similar error.

What can be done? Provided that there is enough memory space to load the program in from disc, then once loaded the program can be moved down in memory to start at &E00. Once this has been done the computer will think it is a tape machine, and so will be unable to then load a data file from disc. Also, pressing break will give a 'bad program' message, and the program will have to be reloaded from disc.

A short routine is shown in listing 1 which will move the program down in memory and then re-run it. This listing can be *SPOOLED and then added to the program in question by using *EXEC with the program loaded in the machine. Then the program must be re-saved on disc before it is run. Do check that the program does not use lines above 30000 or uses line 0. If it does, renumber it first. The routine uses line 0 to test if the program is loaded above &E00, and only relocates it if it is. Line 0 is used, as it is rare for a program to start here and so it is unlikely to overwrite any original program lines.

```

0 IF PAGE>&E00 GOTO 32000
32000 *TAPE
32010 FOR I%=0 TO TOP-PAGE STEP4
32020 I%!=&E00=I%!PAGE: NEXT
32030 ?&13=?&13-(PAGE-&E00) DIV256
32040 PAGE=&E00: RUN
    
```

Listing 1. Shifts program down in memory

£24.⁹⁵

PRICE BREAKTHROUGH

BBC SPEECH

Speech Synthesizer for the BBC Computer



Price includes V A T.
Postage and Packing
Delivery normally 14 days.
Export orders at no extra cost.
Dealer enquiries welcome.
Send cheque/PO now to -

- Totally unlimited vocabulary is now possible with the revolutionary "SWEET TALKER" Speech Synthesizer for the B.B.C. A or B Microcomputer, any series.
- The CHEETAH "SWEET TALKER" simply plugs into speech socket IC99 within the computer. No soldering, no cutting of tracks, no headaches.
- Based on an allophone system you can easily program any word, sentence or phrase and incorporate speech into your software games.
- Fully tested and guaranteed. Complete with demonstration cassette and full instructions.

Cheetah, products available from branches of

John Menzies *Boots* **WHSMITH** and **Rumbelows**

Cheetah

Marketing



Cheetah Marketing Ltd, Dept. A/U 24 Ray Street,
London EC1R 3DJ. Tel: 01 833 4909.
Telex: 8954958.

The Data Store

6 CHATTERTON ROAD
BROMLEY
KENT

for the BBC MICRO
OFFICIAL ACORN DEALERS

WIDE SELECTION OF SOFTWARE
AND PERIPHERAL EQUIPMENT
INCLUDING

**EPSON, NEC, SEIKOSHA
PRINTERS**

**ZENITH, CABEL
MONITORS**

**CUMANA
DISC-DRIVES**


BOOKS AND CABLES AVAILABLE
plus our personal advice service

MACHINES DELIVERED & SET UP
IN YOUR HOME

PHONE 01 460 8991 (9.30 - 5.30)
ORPINGTON 26698 (Evenings)
(CLOSED WEDNESDAY)

MICROTEK COMPUTER SERVICES

Authorised

acorn  **dealer**

**B.B.C. B & acorn
electron**

CUMANA disk drives
DECCACOLOUR & MICROVITEC monitors
SEIKOSHA, EPSON & DAISYSTEP printers
ACORNSOFT/MERLE business software
ACORNSOFT full range

**NEXUS HOUSE
2 CRAY ROAD
SIDCUP, KENT
01 300 3075/6**

ACCESS/BARCLAYCARD WELCOME

3D COMPUTERS

THE HOME COMPUTER
SPECIALISTS

WITH MORE BRANCHES THAN
ANY OTHER ACORN DEALER
WE OFFER

ONE-STOP SHOPPING

FOR YOUR
**BBC MICRO
AND
ELECTRON**

WE REFUSE TO BE UNDERSOLD
AND WILL MATCH THE LOWEST
ADVERTISED PRICE ON ALL
PRODUCTS.

INSTANT CREDIT UP TO £1000.

SOFTWARE

PROGRAM POWER
BUG-BYTE
SUPERIOR SOFTWARE
A & F
SIMON HESSEL
MOLIMERX
ALLIGATA
ACORNSOFT

PERIPHERALS

DISCS SINGLE/DUAL
TORCH Z80 DISCS
CUMANA DISCS
PRINTERS
JOYSTICKS
MONITORS
B & W/COLOUR
LIGHT PENS
BBC BUGGY

*large range of books,
diskettes, cassettes &
printer paper always
in stock*

*Easy parking at all
branches*

TOLWORTH

230 Tolworth Rise South,
Tolworth, Surbiton,
Surrey KT5 9NB.
Tel: 01-337 4317

SUTTON

30 Station Road,
Belmont, Sutton,
Surrey SM2 6BS.
Tel: 01-642 2534

EALING

114 Gunnersbury Avenue,
Ealing, London W5 4HB.
Tel: 01-992 5855

NEWBURY

26, Stanley Road,
Newbury
Berks RG14 7PB.
Tel: (0635) 30047

RICKMANSWORTH

Grey Stone Works,
The Green, Croxley Green,
Rickmansworth,
Herts W03 3AJ.
Tel: 0923 779250

LUTON

1 Manor Road,
Caddington, Luton,
Beds LU1 4EE
Tel: (0582) 458575



ACORN/BBC AT LION HOUSE

Lion House, in the centre of Tottenham Court Road, is now the Largest Acorn Centre in Europe.

Here you will find the best and most up to date selection of Acorn based disk drives, printers, monitors, second processors, plotters, ROM, cassette, and disk based software, books, stationery and supplies.

You'll get helpful advice from knowledgeable assistants and the lowest possible prices. If you're into Acorn products then call into Lion House.

JUST ARRIVED ACORN Z80 SECOND PROCESSOR

Turns the BBC Computer into a business system. The Z80 will run CP/M, which has become the standard operating system for running business programs.

Z80 2nd Processor comes complete with free software programs: Word processing, filing, financial modelling and three programming languages: BBC, Mallard Basic, CIS Cobol.

MICROS

BBC MODEL A - 16K RAM	£299.00 (a)
BBC MODEL B - 32K RAM	£399.00 (a)
BBC MODEL BD - 32K RAM, ACORN DISK INTERFACE	£469.00 (a)
ACORN ELECTRON	£199.00 (a)

We also stock a large range of Electron software and add-ons

micronet 800

Join the communications revolution with Micronet 800 at Lion House and get your first 8 weeks subscription FREE!*

Micronet links you to thousands of micro users nationwide, via Prestel's mainframe computers and your telephone line. Enter the exciting world of electronic mail, bulletin boards, teleshopping and free programs to "download", plus access to Prestel's huge database of information. Also see Micronet's new STARNET game for 1000 simultaneous players!

JOIN MICRONET AT LION HOUSE!

*offer closes SATURDAY JULY 28th.

Complete Package:

£299.00


+ £3.50 p.p.

Lion Micro Computers is one of the oldest established retail and business outlets for micros in the U.K. We have built up an unrivalled reputation, for service and support.

We are *not* a chemist shop.
We are *not* a newsagent
We do *not* just sell boxes
We do provide a complete service for our customers.

ADD-ONS

A-B UPGRADE KIT	£92.00
SINGLE 100K DRIVE	£265.00 (a)
DOUBLE 800K DRIVE	£803.85 (a)
TELETEXT RECEIVER	£225.00 (b)
CASSETTE RECORDER	£29.50 (b)
ECONET INTERFACE	£70.00 (c)
DFS DISK INTERFACE	£103.50 (d)
SPEECH INTERFACE	£55.00 (c)
GAMES PADDLES	£13.00
6502 2ND PROCESSOR	£199.00 (b)
Z80 2ND PROCESSOR	£295.00 (b)
BIT STICK	£375.00 (b)
IEEE INTERFACE	£325.00 (b)



THE WINDOW FOR THE
COMPUTER INDUSTRY

FREE!

A data recorder and five assorted Acornsoft cassettes or 8 Acornsoft cassettes with every BBC 'B' purchased.

£10 voucher

This voucher is worth £10 when used as part payment for any purchase of £100 or more. Only one voucher may be used per purchase against any Acorn/BBC related products as per this leaflet. Offer closes 31st July 1984.

Lion Micro Computers

Lion House, 227 Tottenham Court Road,
London W1P 0HX. 01.580 7383.



BBC COMPATIBLE 5¹/₄" DISK DRIVES AT LION HOUSE

PACE

PSD1 SS 40T SINGLE 100K	£174.15 (a)
PSD2 DS 40T SINGLE 200K	£428.07 (a)
PSD3 DS 40/80T SINGLE 200/400K	£289.15 (a)
PSD4 DS 80T SINGLE 400K	£257.93 (a)
PDD1 SS 40 DUAL 200K	£345.00 (a)
PDD2 DS 40 DUAL 400K	£483.00 (a)
PDD3 DS 40/80T DUAL 400K	£573.36 (a)
PDD4 DS 80 DUAL 800K	£479.71 (a)
PDD5 SS 40/80T DUAL 200/400K	£501.07 (a)

MICROWARE

ZL241BH 40T DS SINGLE 200K	£241.50 (a)
ZL242BH 40T DS DUAL 400K	£438.64 (a)
ZL281BH 80T DS SINGLE 400K	£279.29 (a)
ZL282BH 80T DS DUAL 800K	£517.50 (a)
ZL281BH 40/80T SINGLE 400K	£299.00 (a)
ZL282BH 40/80T DUAL 800K	£537.00 (a)
ZL282BHXX 40/80T EACH DRIVE DUAL 800K	£556.93 (a)

CUMANA

CS100 SS 40T SINGLE POWER SUPPLY 100K	£199.00 (a)
---------------------------------------	-------------

TORCH

TORCH Z80A DISK PACK	£769.00 (a)
TORCH Z80A CELL PROCESSOR	£375.00 (b)

BBC COMPATIBLE PRINTERS AT LION HOUSE

EPSON

RX80 DOT MATRIX	£309.00 (a)
RX80FT DOT MATRIX	£329.00 (a)
FX80FT DOT MATRIX	£439.00 (a)
SERIAL BOARD	£39.95 (c)
FX80 TRACTOR UNIT	£42.17 (c)

JUKI

JUKI 6100 DAISYWHEEL	£429.00 (a)
JUKI TRACTOR UNIT	£117.00 (b)
JUKI SERIAL INTERFACE	£71.00 (b)

BROTHER

EP44 DOT MATRIX	£245.00 (a)
HR1 DAISYWHEEL	£688.85 (a)
HR5 DOT MATRIX	£182.85 (a)
HR15 DAISYWHEEL	£455.00 (a)
HR25 DAISYWHEEL	£750.00 (a)
HR15 TRACTOR UNIT	£109.25 (a)
HR15 SHEET FEEDER	£253.00 (b)
HR15 KEYBOARD	£172.50 (b)

BBC COMPATIBLE MONITORS AT LION HOUSE

MONITORS

HANTEREX 9" GREEN/AMBER	£110.00 (a)	KAGA VISION II 12" RGB COLOUR (HIGH RES)	£322.00 (a)
HANTEREX 12" GREEN/AMBER	£117.00 (a)	KAGA VISION III 12" RGB COLOUR (SUPER HIGH RES)	£458.85 (a)
HANTEREX 14" RGB COLOUR MONITOR	£199.50 (a)	MICROVITEC 1431 14" RGB Standard RES	£228.85 (a)
(SPECIAL LIMITED OFFER)		MICROVITEC 1451 14" RGB (HIGH RES)	£385.25 (a)
KAGA-TAXAN 12" GREEN	£125.00 (a)		
KAGA-TAXAN I EX 12" RGB COLOUR (MED RES)	£268.00 (a)		

OTHERS

SANPLE DAISY STEP 2000	£343.95 (a)
SHINWA CP-80	£259.95 (a)
BBC CENTRONICS PRINTER CABLE	£16.95 (d)
BBC SERIAL PRINTER CABLE	£12.95 (d)

DISKS AT LION HOUSE

SCOTCH/ CONTROL DATA/ DENNISON (BOX OF 10)

SS DD 40T	£24.95 (d)
DS DD 40T	£34.50 (d)
SS DD 80T	£34.50 (d)
DS DD 80T	£41.86 (d)

DATALIFE

MD525 SS DD 40T	£23.00 (d)
MD550 DS DD 40T	£33.54 (d)
MD577 SS DD 80T	£27.10 (d)
MD557 DS DD 80T (TWIN PACK)	£36.31 (d)
MD525	£ 4.98
MD550	£ 6.94
CLEANING KIT	£ 6.03
10 CLEANING DISKS	£11.54

BBC BUSINESS PACKAGES

A large selection of business packages, available on disk, each package can be linked to provide a full integrated business system. Modules comprise invoicing, order processing, stock control, accounts, purchasing, mailing, word-processing (on ROM), spreadsheets etc. Come in and speak to our experts regarding your needs.

ROM BASED SOFTWARE

CARETAKER - BASIC UTILITY ROM	£33.35	TOOLSTAR - PROGRAMME DEBUGGING ROM	£34.00
COMMUNICATOR - COMMUNICATIONS ROM	£69.00	TERMI - TERMINAL/MODEM UTILITY ROM	£33.35
COMMSTAR - COMMUNICATIONS ROM	£34.00	VIEW - ACORN WORD PROCESSING PACKAGE	£59.80
DISK DOCTOR - DISK UTILITIES ROM	£33.35	VIEWSHEET - ACORN SPREADSHEET PACKAGE	£59.80
GRAPHICS ROM - UTILITY ROM (OVER 28 GRAPHIC COMMANDS)	£33.35	WORDWINE - WORD PROCESSING PACKAGE	£46.00
GREMLIN - MACHINE LANGUAGE MONITOR ROM	£33.35	ULTRACALC - SPREADSHEET PACKAGE	£65.00
PRINTMASTER - EPSON PRINTER UTILITIES ROM	£33.35		

ACORN BUSINESS SOFTWARE


INVOICING	£24.95	ACCOUNTS PAYABLE	£24.95
ORDER PROCESSING	£24.95	STOCK CONTROL	£24.95
ACCOUNTS RECEIVABLE	£24.95	PURCHASING	£24.95
		MAILING	£24.95

WE ALSO STOCK A FULL RANGE OF OTHER BUSINESS AND GAMES PACKAGES.

AND OF COURSE A COMPLETE RANGE OF GAMES

Lion Micro Computers

Lion House, 227 Tottenham Court Road, London W1P 0HX. 01.580 7383.



Overwhelmed

with software

Sir, Having read the review of Acorn's Z80 second processor, I wonder whether Acorn has 'scoured the world' for a 'rag bag' of software that will leave most serious users thinking where do they go next.

Acorn's marketing strategy seems to be to overwhelm potential customers with the sheer weight of software. Indeed one suspects that there is more paper in the package than electronic circuitry - so much for the paperless office!

One cannot help but think from the size of the software bundle, with its 11 separate items and high valuation of £3,000, that there is some desperation on the part of the software houses to sell their products, hence the enormous giveaway. It is interesting to note that not many of the more widely known products are being offered in the package, although some are mentioned as being suitable in your Q/A session.

Your brief description of the software seems to raise more questions than it answers. *Nucleus* looks very flexible, but why the need for *FilePlan* and does the latter then require the purchase of *MailPlan*? *MemoPlan* would seem to be a comprehensive word processor, although there is again the suggestion that a further package will be required to make the best use of it.

However, alongside it, *GraphPlan* looks positively crude, despite its colour graphics. With 50 x 20 cells, the latter is smaller than the cassette-based *Beebcalc* from Gemini. It has no split screen facility and does not appear to cater for linked worksheets such as those provided by *Multi Plan* from Microsoft. Finally, what use is a graphics package that is not actually used by any of the bundled software?

I would have preferred a

fully integrated suite of programs offered, which seems to have been the Torch and Sinclair approach, or, better still, a choice of suites for say small business applications, financial analysts, the serious programmer or scientific and technical applications.

Perhaps when you do a full review of Acorn's Z80 software, you could also do a comparison with the offering from Torch.

One question for Torch - is CP/N really fully compatible with CP/M and, if so, why needlessly confuse the potential customer with different terminology?

Robin A Richmond
Leamington Spa
Warwickshire

Second processor

problems

Sir, Having just purchased the 6502 second processor I find that *none* of my paged ROMs will work with it switched on, eg I am totally unable to use: *Wordwise*, *Graphics*, *Exmon*, *Micronet*, *Commstar*, *Toolkit* unless I have the second processor switched off!

It seems that Acorn has 'conned' me into believing the second processor is the best thing since sliced bread. Maybe it is, but having it is proving to be totally useless when one considers the usefulness of the above ROMs.

I suppose the suppliers of these ROMs may decide to re-write them for the likes of me. I only hope they will take the existing ROMs in exchange, because having spent £200 on the second processor I'm not willing to spend around a further £150 to upgrade all the ROMs.

Also, when operating in Mode 7, why have I not got 71k of memory available? (26k from the existing BBC 'B' plus 45k from the second processor).

Will someone please explain why, with the second processor (operating in Hi-Basic) I have only gained 19k (45k-26k) and *not* a full extra 45k as mentioned in the second User Guide?

If, on switch-on, the original BBC 'B' Basic ROM is copied into the second processor, what's happened to the original 26k that I was able to use? The second Guide, chapter 9, 'Distinguishing between Mem-

ories' is no help in saying 'suppose you run a machine code program . . .'. Suppose you *don't*. How do I recover the original BBC 'B' 26k of memory?

Anyone want to buy a brand new 6502 second processor?

I Crawford
Banbury

Difficult times

Down Under

Sir, As tales of would-be Electron owners lining up on cold December mornings to purchase their very own 'Cambridge Cabbage Patch Dolls' reach us in Australia (yes, the computer magazines are that far behind), I would like to tell the story of my own little Acorn, and maybe cheer up those who thought they were badly done by.

Firstly, no Aussie computer magazine mentioned the arrival of the Electron in this country. Everyone here buys either Commodores or Apple lookalikes. The Beeb has been available for some time, but its price has kept its numbers down. (The current Australian price is equal to just over £1,000.)

I'd read about the Electron in some English journals, and was on the verge of ordering one from England when I noticed that a Sydney Computer shop had them in stock. Expecting a rush, I hurried over.

Not only were there some left, none were yet sold. In fact the dealer said he was having a hard time getting people to look at them, let alone sell any.

So I bought one.

Now I have no gripes about the machine itself. I have no need to sing its praises in your magazine. Even the interfacing (or the lack of it) has posed no problems. But don't talk about support . . .

Despite searching some six Acorn dealers (one of whom didn't know it was even though the distributor gave me its name and address), no Electron software was available. In fact this is still the situation some two months after buying the machine. The dealers told me to contact the distributors who said that they didn't have any and to contact the dealers.

The results was that the Acorn Electron must be the only computer on the Australian market with no software

support, and considering the number of Asian imports we get, that's not a bad effort. The available BBC programs are very limited, and not always compatible.

So I am left with a superb machine, an introductory cassette, and a pile of Pommy magazines with BBC and Electron listings.

I would like my full name and address to be printed so that any enterprising UK companies might like to let me know what they have for the Electron. And when I order software, don't bother with copy protection, because there's nobody else Down Under to even give the stuff to!

Earl White
5 Leopold St
Croydon Park 2133
Sydney, NSW
Australia

Second success

with Ultracalc

Sir, On page 84 of your May issue, Clive Williamson says that our spreadsheet 'Ultracalc' does not work with the second processor. It does! I have had it running on the other side of the Tube where about 5k extra memory is gained on a disc system.

David Atherton
BBC Publications
London W1

Serial printers

and the Atom

Sir, Way back in January '81, I purchased an Acorn Atom. Since then I have expanded it to 96K (at present) of which 42K is ROM; incidentally, I have been using 'sideways' principle since 1982; during this time I have discarded the original case, and changed the keyboard in favour of what was once an old Univac keyboard, so now I don't need to press shift to get punctuation.

Also, the old PCB did not lend itself to much modification so I rebuilt the circuit on plain BHP and used verowire.

I have rewritten the original ROM to give me 15 ports (inc ROM/RAM switching) between #B040 and #B3FF and a text start at #0C00 plus a few other uses.

The whole shebang is housed in a metal cabinet

COURSES FOR THE BBC & ELECTRON

DR
WATSON
series



£9.95

BASIC Adventures In Space (age 7 upwards)

This is for the more junior reader and is written as a three part adventure story which teaches the language BASIC. Part 1 is available for the BBC computer now, and an ELECTRON version will be out shortly.

The first half of the book included in the course is the adventure story, in which heroes are accidentally teleported onto a derelict spaceship. They must learn how to operate the spaceship's computer if they are to escape.

The second half of the book is a special 'easy reference' section. Each BASIC command covered in the story is given a separate, careful explanation, complete with at least one example in each case.

The book is complemented by full software provided on tape. This includes the programs which are on the spaceship's computer, and four 'Computer Aided Learning' programs. These teach the major BASIC commands, and demonstrate a complete program, explaining it as it runs.



£12.50

Assembly Language Courses For The BBC And Electron

These courses use the well proved Dr Watson formula that has been described by critics as "worth its weight in gold". No prior knowledge of assembly language or machine-code is assumed, and the aim is to ensure that every reader really succeeds.

Tested on beginners, these courses will have readers running their first assembly language program within ten minutes of opening the book.

The full 6502 instruction set is covered in detail, and each command is demonstrated with short example programs.

The courses include full software on tape:

Disassembler – this disassembles code anywhere in memory.

Search Utility – searches for a number or string anywhere in memory.

Binary/BCD/Hexadecimal tutor – this 'Computer Aided Learning' tutor teaches the various mathematical notations used in machine-code programming.



£10.50

BASIC Courses

These project based courses guide you step-by-step through BASIC, developing games and utilities using progressively more complex commands and structures. All the software developed is provided on tape so you can get a taste of the programs first and then dissect and understand them whilst working along with the detailed explanations given in the book.

Beginners BASIC For The BBC

Starting from first principles and avoiding technical language, the reader is shown how to develop and write eight major programs. Starting with a simple number guessing game, then a 'hangman' game, a simple video 'squash' game, all the way up to a fully-fledged draughts-like board game, 'diamonds of time'.

Advanced BASIC For The BBC

Programs developed and explained include a general-purpose bar graph plotter; a space-invaders type video game; a 'tune plot' program that allows the user to create tunes without having to know any music; an envelope shaping utility to aid development of complex sounds; and a data filing program which will allow a 100K disc to hold at least 250 records with 20 fields in each record.

(soon to be available for the Electron)

HONEY
FOLD

HONEYFOLD SOFTWARE LTD

Standfast House
Bath Place
High Street, Barnet
London EN5 1ED
Tel: 01-441 4130

**COURSES AVAILABLE FROM:
W.H. Smiths, BOOTS, SPECTRUM
stores and all good computer
shops and many bookshops.**

once used as a compressor housing, together with an automatic battery back-up supply to alleviate mains power cuts.

As a little diversion, may I point out that on page 121 of your June issue Vincent Fojut is totally wrong as to using a serial printer on an Atom; I am currently using an ITT Envoy printer, and have used Creed 7B teletypes, both of which are serial formats.

Anyway my question is one of name. Is my machine an Acorn Atom or not?

N J Tubb
Crawley
Sussex

PS. If you are wondering about the FP using #2800, I've also rewritten that to use #0B00 instead.

Vincent Fojut replies: I actually said that 'a serial printer cannot be used *directly* with the Atom.' That is, unlike the Beeb, you cannot plug a serial printer straight into a standard, unmodified Atom, and expect it to work.

This is not to say that it's impossible to drive a serial printer from the Atom - but you must develop (or purchase) additional software and/or hardware to make things work, as you will undoubtedly know from your own experience.

Other readers, who don't want to do the work themselves, may like to know of the Disatom utility ROM by Procyon. Amongst other things, this enables you to use the Atom's cassette port as an output driver for serial devices. Contact: Focusplan, 57 Westgate, Cleckheaton, W Yorks BD19 5HH.

Misleading

test programs

Sir, I would like to correct a misunderstanding about the relative speed of using GOSUB or PROC on the BBC computer and Electron in Gary Smallridge's article 'Basic increase in speed and space' (*Acorn User* June). In this Mr Smallridge states that using GOSUBs is faster than using procedures, contrary to the statement in the *User Guide* (page 195). He gives a program that proves this.

Unfortunately, this type of test program is misleading because of the different way

the interpreter handles the two types of routine call. For GOSUB the interpreter searches through the program from the start until the destination line number is found. The time taken depends on the position of the routine in the program. For a short program like the test the GOSUB call can be quite fast, but as the program becomes longer the speed deteriorates rapidly. In contrast, after the first reference to a procedure the interpreter 'knows' the location of the procedure definition and can call it directly without having to search. This means that in practice procedures will be much faster.

A more realistic test program that demonstrates this is given in figure 1, with results for varying program lengths. For programs where the subroutines are beyond the fifteenth line procedures are faster and for longer programs the difference becomes substantial. The speed of a procedure call is essentially independent of the size of the program.

Robert Tidey
Middlesex

Undocumented

op codes

Sir, The suggestion that certain undocumented 6502 op codes are 'newly discovered' (Atom Forum, June) is somewhat wide of the mark.

Several articles have appeared on this subject, the earliest I can find being in *Byte* as far back as December 1977!

However, full marks to Barry Pickles for resurrecting the subject and for producing a very useful table.

It should be noted that the 65C02 (plug compatible with the 6502) does use some of these, including all the x7 and xF codes.

Finally, has anyone installed a 65C02 in one of the Acorn machines?

Geoff Smith
Worcester Park
Surrey

When experts

are in error

Sir, I am saddened to see an otherwise excellent magazine

```
10 TIME=0:FOR I%=1 TO 1000:GOSUB 10000:NEXT
15 PRINT TIME/100:STOP
```

```
100
```

```
101
```

```
102
```

```
.....Variable number of lines containing one space
```

```
10000 RETURN
```

```
20000 DEFPROC A:ENDPROC
```

Number of lines	GOSUB	PROCedures
1	0.46	0.69
5	0.52	0.69
10	0.60	0.69
50	1.18	0.69
100	1.92	0.70
500	7.8	0.70
1000	15.16	0.70

```
10 INPUT "NUMBER OF LINES",NL
```

```
20 PAGE=PAGE+&100
```

```
30 FOR N%=100 TO NL+99
```

```
40 !I=&5000000+(N%MOD256)*&10000+(N%DIV256)*&100+13
   !I?4=32:I=I+5
```

```
60 NEXT N%
```

```
70 !I=&FF0D
```

Figure 1. Robert Tidey's program (top) for testing execution of GOSUB calls. To test PROCedures replace GOSUB 1000 with PROC A. The results for different numbers of program lines are shown. The other program was the one used to create the dummy lines in the test program

spoilt by the inclusion of articles which contain statements that are inaccurate and in some cases simply incorrect, particularly when these articles are written by professional programmers to help the 'less adept' amateur. In particular, Gary Smallridge's article in the June issue contains several such errors.

In section 7 he advises users not to 'start variable names or procedure names with the same letter'. While this is excellent advice for variable names, it will have no effect on procedure or user-defined function names. This is because of the way these are stored in memory. The Basic interpreter has 28 linked lists for accessing these names, one for variables starting with each letter of the alphabet, one for procedures and one for user defined functions. It is faster to spread the variables between these lists but as procedures and functions have their own lists no gain is obtained with this technique.

In the section on saving memory he states that 'in BBC Basic a real number will use five bytes of memory whereas integers (eg, 1%, FRED%) will use only four.' In fact there are three types of numeric scalar

variables (ie single numbers, excluding arrays). These are the resident integer variables, normal integer variables and real variables. The resident integer variables, as he points out earlier in the article, require no additional memory as they are already declared in reserved locations. Normal integer variables require the length of the name, including the '%' plus six additional bytes, four to store the value and two to store the pointer to the next variable starting with the same letter.

Although the first letter of the name is not stored but implied from the linked list in which the variable occurs, an additional zero byte is required as the terminator for the variable name. As such the variable FRED% would require a total of 11 bytes of memory. A real variable, as he suggests, does require an additional byte to store the value giving a total of the length of the name plus seven additional bytes. However, as there is no terminator on real variables, this saves one byte, giving the same amount of memory required for variables with the same name. A real variable FRED would still require 11 bytes of storage.


Synergy Software

PROFESSIONAL SOFTWARE FOR THE BBC MICRO

EASIPILOT

EASIPILOT is a sophisticated AND user friendly graph package for the BBC Micro, placed 14th in the top 20 Educational packages by the leading Educational Computing Magazine. EASIPILOT has also come to be regarded as an 'outstanding business package' and 'excellent value for money'.

Note:- EASIPILOT 3 comes complete with the number charting program DATA PLOTTER with graph magnification, colour and moving average facilities. SUPERB VALUE AT £22.95.



EASIPILOT FACILITES

	DISK	CASSETTE
Line, Bar and Pie Charts	YES	YES
Auto & Manual Scaling	YES	YES
Grid & Scatter Options	YES	YES
No of simultaneous graphs	5	3
Overwrite memory	YES	NO
Screensave facility	YES	YES
Screendump facility	YES	YES
Fixed description per graph (char's)	up to 200	100
Full plot and axis editing	YES	YES
Save, Load & *CAT facilities	YES	YES
Single file selection	YES	NO
Operating Manual (pages)	52	52

All our programs will produce hard copy on the following printers:- EPSON (entire range), Shinwa CP80, Star DP 510, Seikosha (GP80A & GP100A). Share Analyser will produce reports on any BBC compatible printer.

PLEASE NOTE:- Our programs CANNOT BE OBTAINED FROM YOUR LOCAL DEALER so send for details NOW.

PROGRAM	PRICE
Data Plotter (cassette) .. Model B & Electron	£7.00
Data Plotter (disk) .. Model B	£8.00
Easiplot 1 (cassette) .. Model B & Electron	£15.95
Easiplot 2 (disk only) .. Model B	£19.95
Easiplot 3 (including Data Plotter-disk only)	£22.95
Share Analyser (cassette) .. Model B & Electron	£14.95
Share Analyser (disk only) .. Model B	£19.95

Disk orders .. please state 40 or 80 track (add £1 for 80 track and £1.50 for overseas orders). We will upgrade Easiplot 1 to Easiplot 2 for £7 (£10 to Easiplot 3).

Write for full details of all our programs or leave your name and address with our Answerphone service (Luton 33858).

All programs are normally despatched within 24 hours.

SHARE ANALYSER

SHARE ANALYSER is a sophisticated portfolio reporting and share analysis package designed for the small investor. The disk version has a capacity of 20,000 SHARE PRICES and up to 320 buy/sell deals covering 20 share names. Share Analyser has facilities for profit flexing and multiple merging of graphs and a variety of selectable indicators. **SHARE ANALYSER IS A MUST FOR THE INVESTOR AT A BARGAIN PRICE.**

PROFIT STATEMENT

NAME BRITISH PETROLEUM		
DEALINGS		
Bought	Av Price	Cost
600	338	2028
Sold	Av Price	Income
300	426	1278
Held	Curr Price	Mkt Valn
300	438	1314
	Gross Profit	564
	Income	257
	Expenses	101
	Net Profit	720
	% Gain	= 36

SHARE ANALYSER FACILITIES

	DISK	CASSETTE
No of prices stored	20,000	Appx 1700
Max no' of Holdings	20	20
Transactions per holding	16	16
Range adjuster	YES	NO
File Manager	YES	NO
Printer Manager	YES	NO

REPORTS PRODUCED:-

Portfolio Valuation	YES	YES
Portfolio Profit Analysis	YES	YES
Share Profit Analysis	YES	YES
Share Movement Analysis	YES	YES
Transaction Record Report	YES	NO
File Status Report	YES	NO

GRAPHICS FACILITIES:-

Magnification option	YES	YES
Grid	YES	YES
Autoscale	YES	YES
Screenwrite	YES	YES
Screendump	YES	YES

SELECTABLE GRAPHICAL INDICATORS:-

Lagged Moving Average	YES	YES
Centred Moving Average	YES	YES
Rise and fall indicator	YES	YES
Weekly/Daily Low indicator	YES	YES
Superimpose Facility	YES	YES

Send cheque/P.O. etc to

Synergy Software, 7 St Andrews Close, Slip End, Luton, LU1 4DE.

There is only a saving in memory made when integer arrays are used instead of real arrays. In this case one byte is saved for every element in the array, less the extra byte required in the name.

Although I understand it is difficult to check the accuracy of the information in every article, I would like to state that this quality of writing tends to reinforce the opinion held by many people that so-called 'computer experts' have little more ability in the field than most people who have just bought a home micro but have not yet learnt the jargon.

Mark Simms
Bristol

Desk design

Sir, As a part of my 'A' level design course I am designing a computer desk/work unit with the home user in mind. At the moment I am investigating what form one of these units should adopt, whether it be an expandable system or a solid single unit.

As I will be designing, making and possibly selling the design of this desk, I would be very grateful for any ideas.

S Plenderleith
Kirkbie Kendal School
Lound Road
Kendal LA97EQ

Inspect bags

Sir, Unfortunately in editing my program, *Inspect*, which appeared in your July issue, a couple of bugs have crept in. Line 310 should read:

```
310 LDX #8
and line 640 should be:
640 LDA #8
```

To save a usable version, enter these changes and type *SAVE INSPECT 8D0 9FF

Mark Coles

Rocket Raid	39,780	Meteors	22,980
Snapper (keyboard)	131,810	Chuckie Egg	1,048,820
Danger UXB	320,750	Pengo	35,790
Overdrive	55,210	Crazy Painter	55,240

Stephen Green

Android Attack	602,590	Arcadians	27,300
Starship Command	2,059	Zalaga	111,930

Robet Hirskyj

Planetoids	346,775
-------------------	---------

ASK a silly question, pass a fair comment, stage an angry protest - we don't mind what you write to us about (or about us!). Keep 'em short, keep 'em sweet, but keep 'em coming! The address is: Letters, Acorn User, Redwood Publishing, 68 Long Acre, London WC2E 9JH.

and you should find that all will be OK.

M Clayden
Merseyside

Tape loader

Sir, The listings for 'Tape Loader' in *Acorn User*, June are not the final versions of the program. They contain at least one error and if the main program is 'pruned' as suggested in the accompanying article it may subsequently crash. The changes given in figure 2 should make the program run correctly and more smoothly.

John Bexon
Kent

```
LISTING 1.
50 LD MEM=TOP+&B0:
   TP%=TOP-1
80 *KEY10 OLD:
   MEND:MRUN:M
320 RZ=FNC(TP%)
630 RESTORE 1002:CT%=-1
   :CLS:PRINT""Programs
   on this tape are:
   -"";LZ=FNC(TP%)
In line 750 instead of
KEY f0 use BREAK

Listing 2.
80 *KEY10 ?&21B=&D0;
   ?&219=&D: ?&20A=&D6:
   ?&20B=&D: OLD: MEND:
   MRUN:M
```

Figure 2

High rollers

Sir, I have an idea to improve your magazine, that is if you can improve on perfection (creep, creep). It came to me (the idea that is), while reading B Nesbit's letter in your June issue. How about keeping a list of the highest scores achieved by readers at various popular games?

Mark Coles
Birmingham

A number of readers have written in to boast of their performance in various games. We list the high scores below to get the ball rolling. Record-breakers please write in.

Kitty answers

the simple questions that confuse many



Q Since we got our BBC micro, my husband never takes his hands off it from the time he gets home. I don't mind this, in fact it's nice to see him take such an interest in something. However, when I ask him what he's doing till the small hours, his answers are incomprehensible - I'm not even sure he knows what he's talking about.

Rosie Reynolds
Cornwall

A When I first got my BBC I also found myself absolutely engrossed - I had to put an alarm clock on top of the TV to remind me of just how much time was passing! The main thing about getting to grips with a micro is the splendid sense of achievement when you set yourself a problem and then manage to solve it in a logical way. Writing your first program which actually works is just like passing a driving test!

Q Most of my friends at work have got computers and seem to talk about nothing else. What use are home micros? When I ask what use they are, all I get are evasive replies - as if none of my friends want to admit that they are of no use at all. Can this be true?

Nicholas Spencer
London

A It all depends on what you mean by useful. As an aid to logical thought, yes, they are useful. However, a Beeb on its own (with no add-ons) is useless for so-called usefulness - it won't run the central heating or manage your household budget. That said, a lone Beeb is useful in that it gives you an interest and stops you watching so much TV; if you get involved in graphics it will brush up your geometry - it's also just plain fun.

If, though, you have some add-ons (printer or discs) then it can become a wordproces-

sor - and you'll never want to touch a typewriter again! It's also very handy for mailing lists and other time-consuming repetitive tasks.

Going one stage further, a Z80 second processor will turn your Beeb into a proper business system - accounts, stock control - virtually everything a small business could need.

Some of the articles in this issue may set you thinking about education, and teaching your children, which is something else a micro can do.

But remember, a computer for most people becomes an end in itself: it just replaces watching TV, or tinkering with cars, or doing crosswords.

Q Having saved up nearly five hundred pounds to buy a BBC micro and the bits to make it work, I was expecting not to have to spend any more. Little did I know that it would continue to be a drain on our holiday money. It seems my family will never stop wanting more software and add-ons! What I want to know is whether the micro is going to be a passing fad like skateboards or roller-skates?

Michael Fernandez
Dorset

A I just wish someone did know the final answer to this question! A home computer is certainly different from other toys; it doesn't have to be used just as a toy and there are plenty of useful things it can do.

Second, a computer is more like Lego or Meccano than a pair of roller-skates. You can build many different things around it and it is only really limited by the imagination of the user.

For the home computer to die out a better toy must come along: it's difficult to imagine a more versatile one.

The company which brought you the first self-build Arcade game and the first Adventure with sound, just had to be the one to give you the very first QUEST for the Beeb!

Swords and Sorcery

a new experience...

QUEST programs originated on the American mainframe computers, and were converted to micros, though requiring so much memory could only be made to work on expanded Apple micros and the like. Now, Kansas have crammed a full feature Quest into 32K, giving every BBC Micro owner the opportunity to play and experience these unique games.

So what is a Quest? Think of an Adventure, then think of very much more. A Quest is operated similar to an Adventure, but no longer are you alone, starting with three helpers. As you progress you will encounter many other characters, but unlike an Adventure program where all characters are passive, these can be either hostile, friendly or indifferent. If hostile you have to fight, and quickly; if friendly they may join your team bringing more strength, magical ability and carrying capability; if indifferent you could perhaps try a bribe (but beware if you offer too little) or you could sell an object and raise yourself more cash as well as lessening your load.

But most of the effort is your own, with treasure, money, magic and strength all having a bearing on your progress. At times it will pay to be vicious and abandon your friends as they become weaker, or even go in fighting before characters show their true colours, the element of surprise using less strength.

As can be expected in Swords and Sorcery there is a story:

Once upon a time in a far away land called Iriuma a magical Princess cast a spell of banishment on the wicked Sorcerer Brogfelt. However, just before the spell took effect, Brogfelt threw his arms into the shape of changing and cast a return spell, changing princess Ilear into a diamond. Taking the diamond with him, Brogfelt took sanctuary in the Dungeons of Terror amongst the various monsters and demi-humans. Here he split the diamond into four parts and changed each part into a different crystal. Brogfelt then hid each crystal in the dungeons never to be found again. When the king heard of this he summoned all his faithful Knights to him and offered half his lands for the four crystals. Sadly they all perished in the Dungeons of Terror attempting it. Now the king has offered anyone his other daughter's hand together with half his lands. Hearing this, you set off to the king's palace to offer your services. The king is astounded but nevertheless offers you a party of three prisoners from his jail, promising them a full pardon if they will go and aid you. As you leave the king stops you and thrusts a scrap of paper into your hand explaining that it contains the location of each part of the crystal from the entrance of the dungeons. It was written very shakily and stained in blood. The king says: "Let me introduce you to the three prisoners that I have volunteered to go along with you..."

The characters you meet include a Troll, Orc, Thief, Dwarf, Goblin, Madman, Witch, Hobgoblin, Mad Monk and of course the wicked wizard himself, all in fact you would expect in a magical Swords and Sorcery...

All the objects have a use, but be careful, for picking the Dragons Tooth could be fatal; though if you find the Staff of Healing try and get it; an Idol of a forgotten God should be left well alone; the Ring may help you; the Magic Axe certainly will; the Old Book will give some clues; rub the Glass Ball; used properly the Magic Carpet will get you out of trouble; the Rolled Scroll too is useful; but not so the Fools Gold; be careful with the Bottle of Liquid; but drink the Magic Potion; treat the Golden Orb with care; but of course the Sword is the greatest help of all. And so it goes on, and on and on...

Unlike an Adventure game, were once you have solved the plot, and it is all finished for good, Swords and Sorcery generates an entirely different scenerio every time, even though totally logical! But if you really intend to see a game right through to the end, the game saving facility allows you to do this, playing the same scenerio, time after time, to its end. It is so different from an Adventure, that it actually has nine—yes nine—levels of play, with the ninth having so many locations and of such complexity, that we would be amazed if anybody ever solved it!

If you are an Adventure addict, this will really spoil you! If you do not care for Adventures the activity in this unique game will suit you as well. It is one of those you just will not be able to leave alone...

Though there are many Adventure games using the word Quest in their title, these are not Quests in this, the true sense of the word, but are just ordinary Adventures.

FEATURES a Map routine showing exactly where you are and where you have explored.

FEATURES colour denoting the different aspects of the game.

FEATURES sound on or sound off facility.

FEATURES entirely different scenerio for every game and all totally logical

FEATURES nine levels of difficulty from fairly easy to impossible.

FEATURES game saving routine to be able to replay the same scenerio.

Only available from Kansas at £10.35 Vat and post paid.

Our normal return first class post service applies, with same day postage if ordered on Access or Barclaycard.

This program carries our famed lifetime guarantee.

Available on cassette only for BBC model B.



Kansas City Systems, Unit 3, Sutton Springs Wood, Chesterfield, S44 5XF.
Tel. 0246 850357



Bruce Smith is in charge as readers chip in on legitimate access, printer toggling, file sizing, plus tips on Wordwise

Access information

£5

without peeking

or poking

THERE are three items, says Ellis Thomas, in January's *Beeb Forum* which, though apparently unconnected, have an underlying factor: the ability to access information legitimately without peeking or poking.

First, the cursor problem in 'Less Peeking'. The *Advanced User Guide* tells us (page 15) the codes placed in the input buffer for the soft keys, so the cursor keys can be driven from running programs by placing the relevant code in the input buffer to be acted upon, using *FX138,0,N (cursor editing must be enabled, of course, see *FX4). The relevant codes are:

```
&8F 143 ↑
&8E 142 ↓
&8D 141 →
&8C 140 ←
&8B 139 COPY
```

So we can not only position the cursor, but also do the copy from the running program, leaving the characters in the input buffer as if we had used cursor and copy keys from the keyboard. The only problem is that the starting point

for cursor movement is that defined at the time of input (INPUT or GET\$), not that at the time the codes are placed in the buffer. The example given can thus be replaced by listing 1. The prompt @? is followed by the copied string, awaiting modification by using delete, or addition of characters prior to input by pressing return.

```
1090REM by Ellis Thomas
1100DEFFPROCCat
1110LOCAL C%: C%=0
1120Name$=""
1130*FX15,1
1140*FX4,0
1150*FX138,0,143
1160REPEAT
1170Name$=Name$ + FNCopy(" ")
1180C%=C%+1
1190UNTIL C%>=10
1200Rest$=""
1210REPEAT
1220Rest$=Rest$ + FNCopy(CHR$(C%-1))
1230C%=C%+1
1240UNTIL C%>=39
1250ENDPROC
1300DEFFNCopy(Omit$)
1310LOCAL C$
1320*FX138,0,139
1330C$=GET$
1340IF C$=Omit$ THEN ""
1350=C$
```

Listing 2.

This brings us to 'Cassette space'. The table of addresses in memory page 3 is given in the *Advanced User Guide* (page 279). Here we see that we can use OSBYTE &A0 to access these values, which presumably makes us Tube compatible, and safe from this

data being moved to another page in a new operating system. However, we are left with the problem of reliance on the layout within the page. An alternative approach is to read the file details from the screen using cursor and copy keys. Changes to the screen layout will at least be obvious to see in a new OS. Listing 2 gives an idea of how to read the file name and so on from the screen immediately following reading the file with *LOAD, using *OPT1,2. A call to PROCCat yields the name in Name\$, and the addresses in Rest\$:

```
Block No - MID$(Rest$,2,2)
Length - MID$(Rest$,5,4)
Load add - MID$(Rest$,13,8)
Exec add - MID$(Rest$,22,8)
```

The FNCopy enables us to omit a nominated character so that the trailing spaces on the filename can be easily avoided; use of GET\$ avoids the copied characters being printed. Using these procedures, a utility to copy a cassette file automatically for back-up has been readily constructed.

Finally, 'Locked for program protection' had a problem placing the token for OLD in the input buffer. The reason for this is that the OLD token is &CB (203). When an attempt is made to place it in the input buffer, this behaves as &8B (139) which is copy, so no character is actually placed in the input buffer, the same as when copy is pressed without having pressed a cursor key. The set of codes appears to be repeated every 16 up to &FB - &FF.

Printer on,

£10

printer off

C Binstead of Andover wins himself £10 for this useful machine code utility. We'll let him explain...

The interrupt routine in listing 3 (yellow page ii) will possibly be of more use to disc users than readers with cassette-based systems, although the latter may find use for it. PTRTGLR was originally written for use with the *DUMP statement to enable printer dumping of selected sections of the output.

page 70▶

```
10 REM Copy from running program
20 REM by Ellis Thomas
30 CLS: PRINTTAB(1,2)"ABCDEFG"
40 FOR X%=5 TO 3 STEP-1
50 REM Up cursor
60 *FX138,0,143
70 NEXT
80 REM Left
90 *FX138,0,140
100 FOR X%=1 TO 7
110 REM Copy
120 *FX138,0,139
130 NEXT
140 INPUTTAB(0,5) "@", A$
150 PRINTTAB(0,10)"Input was """;A$;" """"
160 END
```

Listing 1.

Beeb Forum is a platform for ideas, tips and applications relating to the BBC micro and the Electron, intended for experienced programmers to share their thoughts. For every reader's tip published we pay £5 - or more for something special. Contributions should be typed or printed, with substantial listings on cassette. WRITE TO Beeb Forum, Acorn User, Redwood Publishing, London WC2E 9JH.

SECONDS

50

Robin Newman finds a way around trouble with the Tube

66

HAVING recently acquired a 6502 second processor, I have been finding out the hard way the validity of the warnings given by Acorn concerning the use of direct memory addressing in programs, which can make them unusable in a second processor. The problem occurs in any program which tries to do one of the following:

- Directly 'poke' or 'peek' the screen. This is now in the BBC machine (the input/output (I/O) machine) memory map, whereas the Basic program will be running in the 2P (short for second processor). You will be peeking or poking 2P memory with unpredictable results.

- Directly accessing the user VIA addresses. These are also now in the 'wrong' processor memory map.

- Using unofficial pointers like &F4 which contains the currently selected ROM identity. Note that using Basic pointers like &18 for PAGE and &12, &13 for TOP still appears to be OK (though undesirable?) as Basic maintains its pointers in the 2P memory map.

- Using programs which maintain data areas at &A00 or &C00. As the default value of PAGE is &800 in the 2P, this will cause these safe data areas to appear on top of the program, thus destroying it! Note that user-defined characters are still stored in the I/O memory map, as are function key definitions, so neither can be accessed by direct peeking using the ? operator.

What then can be done about these problems? Most are easily avoidable, albeit at the expense of slightly more involved programming. It is possible to directly peek or poke a memory location if you use the legal method. This uses OSWORD with A%=5 for peeking and A%=6 for poking. Examples are given in the 2P handbook, and these calls are also detailed in the *User Guide* (p460) and the *Advanced User Guide* (p249). To access the user VIA, or other devices in the FRED, JIM, and SHEILA pages of the I/O memory map, OSBYTE calls with A% = 146 to 151 can be used (*UG* p436, *AUG* p170).

Having converted one or two of my own programs to work with the 2P, I turned my attention to the commercial sideways ROMs which I had access to. Sadly many of these would not work. (The Acornsoft ones like *View* and *BCPL* did!). Often the problem appeared to be trivial. Directly poking a help or menu page to the screen, for

example. However, many of the monitor-type ROMs which incorporate a facility to dump or disassemble other sideways ROMs would not perform this task correctly. The reason is not hard to see. Sideways ROMs are selected by writing their slot number to location &FE30 in the I/O memory map, which contains a write-only switch. A record of the state of this switch is maintained in location &F4. The monitor ROM copies a routine into RAM which then switches these locations to the ROM you desire to inspect, and then accesses it usually using indirect-indexed addressing, before switching back to the monitor ROM. However, when such a sideways language ROM is selected with a 2P installed, it is copied across to the 2P automatically, and then executed in the 2P memory space. Thus the switch at &FE30 and the copy at &F4 are not available, as they are in the wrong memory map!

Thus to use this facility from the 2P, it is necessary to access &FE30 and &F4 in the I/O memory map, and to read the required ROM data, again in the I/O map, before sending the resulting information back to the 2P. This requires a certain amount of machine code to be resident in the I/O memory map to carry out the task. There are two problems. First how do you get the code there, and second, how do you execute it? There are two solutions to the first problem. The code can be loaded directly from tape/disc/net into the I/O processor rather than the 2P by using an eight-digit load address with the first four digits set to &FF. Thus if the code should reside at &1500 in the I/O map, then type *LOAD progname FFFF1500. (To load it into the 2P set the first four digits to 0 - *LOAD progname 1500 or *LOAD progname 00001500). The second method is to prepare the code in the 2P and then use OSWORD 6 to copy it across byte by byte.

The second problem, how to execute the code in the I/O processor, is solved as follows. The beginning of page &200 in both processors memory maps hold a series of vectors through which various operating system calls are indirected. The particular one of interest is the USERV vector located at &200 in the I/O memory. This is used by the commands *CODE and *LINE, which have been discussed before in *Acorn User* (November 1983 pp 51-53). Alternatively, OSBYTE 136 can be used to access this vector. The vector contents in the I/O memory map are altered

(using OSWORD 6) to point to the code which has been poked across into the I/O memory. The code can then be executed by calling OSBYTE 136 in the 2P.

The example program (yellow page vii) uses this technique to allow you dump the first 'page' of a sideways ROM onto the screen.

PROCwrite(data,addr) writes the byte 'data' to the I/O memory address 'addr'. FNread(addr) reads the contents of the byte at 'addr' in the I/O memory. PROCstarcode performs a *CODE command, using OSBYTE 136. This calls the machine code routine which has been placed in the I/O memory by PROCover. The code consists of the following instructions:

```
JSR &FFB9
STA &F6
RTS
```

The routine &FFB9 (OSRDRM) is contained in the 1.2 OS ROM. It is documented in the *AUG* on page 106. On entry the Y register contains the ROM number to be accessed, and the routine returns with the byte whose address is contained in &F6 and &F7 in the accumulator. For those who dislike using this unofficial OS routine, it essentially contains the following code given in figure 1 (yellow page vii). If desired, this can be substituted into the data statement at line 510, provided the count in line 460 is changed accordingly. Thus lines 460 and 510 would be changed, as in figure 2 (yellow page vii).

Finally, for those who do not have a 2P, program (yellow listing page vii) will run on a stand-alone BBC machine without modification, provided it has OS 1.2. The code which is accessed by the USERV is located at &2200 onwards, which is clear of the top location used by the program, even if PAGE is &1B00 (for a disc + Econet machine). It is also clear of the highest location used by the 2P. This uses an extra &600 above the default page value, as the character font is automatically fully exploded, (equivalent to a *FX20,6 command) allowing any ASCII character to be redefined. (Note: If you have a sideways ROM board fitted, you can change the range of R% in lines 50 and 60 to 0-15.)

Telephone
Orders
574 5271

The Twillstar Reliability. It's what makes us The Leading Computer Shop!


* TAKE ADVANTAGE OF OUR 24 HOUR TELEPHONE ORDERING SERVICE *

PRINTERS

FREE INTERFACE CABLE & 500 SHEETS OF PAPER WITH ALL PRINTERS

DOT MATRIX £389

EPSON
FX80




EPSON R80 ...£279

EPSON FX100.....£489

FX80 is even faster. An astonishing 160 characters per second, proportional spacing, quick forms tear-off, superscripts, subscripts, dot addressable graphics and down loadable characters set. Standard Centronics parallel compatible interface with optional RS-232C/current loop and IEEE interfaces. The FX80 is pin fed and friction fed and can feed single sheets (optional tractor feed).

MONITORS

ALL MONITORS COME WITH FREE CONNECTING CABLES



£215

NOVEX 14" MONITOR

Low-cost model for personal computers. 14" Screen colour display. R.G.B. and composite inputs.

Switch to allow monitor to be used as green screen monitor. Switch mode auto-regulated power supply. Professionally-styled Metal-Cabinet in BBC Micro-colours.

ACORN SPEECH SYSTEM

The system contains a Speech Processor and a special chip called a Phrase Read Only Memory (PHROM).

The Speech Processor contains a digital filter which is rather like a computer version of the human vocal tract. It relies on being fed to a large number of parameters to produce the necessary sounds for making speech.


£55.00

DAISYWHEELS

£379


JUKI 6100

20 CPS max (13 CPS Shannon text)
10, 12, 16 CPI and proportional spacing up to 220 characters per line, diablo protocol. Bold, shadow printing and underlining.



SHINWA CP 80

80 column, friction and adjustable tractor feed, bi-directional logic seeking HI-RES graphics and block graphics sub and super scripts, condensed and emphasised print, and underlining vertical and horizontal tabs, self test, italic print, etc.



£230

TV/MONITOR £249



14" TV/MONITOR

This TV Monitor is not a modified television as many TV Monitors are, but a 14" TV/Monitor which has been designed to perform both functions. It has RGB and Composites video and sound. An RGB cable for a BBC is supplied as standard. With Remote Control.


MICROVITEC 14" Colour Monitors

Microvitec 1431 14 Std. Res.....	£199.00
Med. Res.....	£345.00
Hi-Res.....	£442.00

DISK DRIVES

TEAC DISK DRIVES

INCLUDES FREE CABLES, FORMATTING DISK & MANUALS



TEAC 55A S/S 40 TRACK

100K Single.....	£140.00
200K Dual.....	£280.00

TEAC 55E S/S 80 TRACK


200K Single.....	£190.00
400 Dual.....	£380.00

TEAC 55F D/S 80 TRACK

400K Single.....	£220.00
800K Dual.....	£440.00
Power Supply Unit (Optional).....	£29.00
40/80 Switch.....	£ 8.00


BROTHER HR15

£395



13 CPS. 10, 12, 15 CIP and proportional spacing up to 165 characters per line, colour printing, shadow printing, super/sub script, auto underlining, text reprinting, 3K Buffer Standard.
Keyboard.....£160
Sheet Feeder.....£228
Tractor Unit.....£109

WORD PROCESSING PACKAGE



£1,260

BBC Model B plus Disc Interface fitted view, VDU Green Monitor, Daisywheel Printer, 200K Dual Disk Drives and manual and formatting disk. Only £1,260 (inc. all cables)

SEE US AT

The 2nd
Official
Acorn User
Exhibition

OLYMPIA
16-19 AUGUST
1984

HOW TO ORDER

You may purchase any of the items listed by cheque made payable to: Twillstar Computers Ltd. Barclaycard or Access. All you have to do is fill in your requirements on a separate sheet of paper, post to us and we will despatch within 24 hours, subject to availability. All prices inclusive of 15% VAT. ADD £2.50 P&P for orders below £150. OVER. ADD £8 P&P. CREDIT CARD HOLDERS MAY ORDER BY TELEPHONE. GIVE CARD NUMBER, NAME, ADDRESS AND ITEMS REQUIRED. PLEASE NOTE VAT IS NOT CHARGED ON EXPORT ORDERS. EXPORT CUSTOMERS PLEASE RING FOR DETAILS OF P&P.

TCL

Twillstar Computers Limited

17 REGINA ROAD · SOUTHALL · MIDDLESEX
TEL: (01) 574 5271 · TELEX NO. 25247 TIL

open 6
days a week
10am - 8pm

NEW CHIP WITH TUBE

What follows will, initially, only be of interest to those who have acquired a DNFS ROM as part of the 6502 second processor package. However, as this chip is being 'rommed' it seems likely that it will supersede the DFS 0.9 and NFS 3.34 chips which have to date been supplied with disc and Econet interfaces, and thus become of wider interest.

The DNFS chip supplied with 6502 second processors can in two senses be described as three in one. First, it contains three separate sections of code. A disk filing system, a network filing system, and code to set up the Tube interface to the second processor. This latter section of code (some &400 bytes long) is automatically copied down to pages &400 to &700 of the input/output processor (the original BBC computer) if the Tube hardware is detected on power-up (or CTRL-BREAK). The first 8k of the 16k DNFS ROM also contains the Net filing system, while the disk filing system software largely resides in the second 8k of the ROM.

Because two filing systems are in the same ROM, provision has to be made to disable each one separately, as the combined ROM may be used in machines which have only one (or even neither) of the two associated hardware interfaces fitted. A software switch has been incorporated in the ROM to do this.

During the power-up sequence the ROM receives two service calls to allocate the memory required by the filing systems it supports. It is these which cause (among other things) the default value of page to be adjusted to &1200 (NFS only supported), &1900 (DFS only), or &1B00—both NFS and DFS supported. (This assumes the second processor is not connected, although such memory allocations still take place in the I/O memory map if it is, although they remain hidden from the user in that case.)

The service entry at &8003 points to &80F7. Inspection of the code from that address onwards finds the service call (code 1) for allocating memory to the NFS at &8105. Initially this tests for the presence of the 68B54 Advanced Data Link Controller chip which is the heart of the Network hardware interface. If the test fails, the most significant bit of the byte allocated to the ROM in the workspace table from &DF0 to &DFF is set. This is tested on subsequent calls to the NFS and if set it causes all such calls to be ignored: ie the NFS does not

DNFS chip reviewed by Robin Newman

appear to be present in the ROM. Thus if the user sets this bit directly, the NFS can be effectively switched off, and will remain so until the machine is switched off again (or the bit is directly reset).

A similar test is made at the start of the code servicing the DFS (from &B494 onwards). In this case the status register of the 8271 (at &FE80) is read. According to the 8271 data sheet, this will always return 0 in bits 0 and 1. However, if the 8271 is not fitted the data lines will be pulled high and these bits will both be a 1. In this case the code ignores calls to the DFS. However, it appears that a software switch is also provided to cause DFS calls to be ignored. Code at &B49C tests bit 6 of the same byte that contains the NFS ignore flag. If bit 6 is set, the DFS call is ignored. I have not yet found where this is used in the ROM, but the user can take advantage of this facility directly to disable the DFS if required.

So much for the background, but of what use is this all, and how in practice is the disabling/re-enabling carried out? The advantage of the disabling is that it is possible with a simple software 'poke' to change the configuration of your machine so that it behaves as: a machine fitted with only a DFS; a machine fitted with only an NFS; or as a machine fitted with no additional filing system, ie a standard tape machine, (with sideways ROM support). In each case, the default value of page (the system OSHWM) will take up the value it would have for the particular system concerned, thus releasing valuable memory space for the user. The only way to do this with the old discrete DFS and NFS is to physically remove some chips, as it is no good using the dodge of putting a 0 in the relevant position in the ROM type table at &2A1-&2B0, as this will be reset

when the break key is pressed, and so you could not push break to reset page and the default filing system. Thus the second claim for this DNFS ROM as being three in one becomes apparent. With its help and a simple software command, your machine can be quickly turned from a simple tape machine to a disc-only or network-only machine, or to a full-blown disc plus net machine (assuming the machine has the relevant hardware interfaces). One example is when using a 'tape'-based program from disc. After loading, the DFS is disabled, and the program relocated to &E00. It can now be RUN in the correct environment, and (unless it is protected) will survive break.

Now for the 'how'. First, a word of warning, particularly to games addicts. The process can happen inadvertently if you use a program which uses page &D00. The disabling flag is contained in a byte between &DF0 and &DFF (dependant upon the position of the DNFS ROM sideways 'slot'). If the game or other software corrupts this byte, you may find when you push break or CTRL-BREAK at the end of the game, that your DFS or NFS has totally disappeared, and that you can only get it back by switching the machine off and on again! (In fact it is possible to retrieve the situation with a memory 'poke'.) The first thing to ascertain is the position of the DNFS ROM in the available sideways ROM slots. Mine is situated next to the Basic ROM in the slot second from the right-hand edge of the circuit board. This is slot 13 or &E, and in this case the relevant byte in the workspace table is &DF0 + &E which gives &DFE. This location will be used in the following description, but change it to your DNFS slot.

To disable NFS. This requires the msb of &DFE to be set. The 'nicest' way to do this is to type:

```
?DFE = ?DFE OR &80 <return>
```

Alternatively, look at the contents of &DFE (using P. ~&DFE <return>), which in my case gives &17, although this may differ depending upon your machine configuration, and then add &80 to this value, giving &97, before

page 70 ►

I WOULD like to acknowledge the help I have received from three sources. First Acorn (yes they do answer the telephone and are helpful with technical enquiries), second, Chris Dawkins of Felsted School, and third, but by no means least, the Advanced User Guide, pp 246 (*FX255 details), 273 (paged ROM type table), 281 (paged ROM workspace table), and 320-321 (service calls types 1 and 2).

RN

TCL-PANASONIC

3" Disk Drive - The Choice ...

Special!

ONLY
£99 + VAT



Twillstar Computers Offer

INGENUITY, DURABILITY, COMPATABILITY ...

This is the Twillstar (TCL) Panasonic 3" Disk Drive which features the ingenious dual-sided cartridge protected disk, 200K (100K per side). Ideal for use in education and other environments where rough use is envisaged.

Compatible with all disk interfaces, comprehensive manual and utilities on either disk or EPROM.

DESIGN, COLOUR, SIZE ...

This 3" Disk Drive is totally housed in a high stability aluminium two piece casing, with a light plastic face, and a unique automatic steel shutter which protects the disk surface. A highly sensitive injection key allows easy insertion and extraction of your diskette. The case is finished in a tough coating of beige to match the colour of your BBC.

The size is a compact 160mm length x 90mm wide x 55mm deep.

FEATURES, CAPACITY, USAGE ...

This 3" Disk Drive uses 3" diskettes which are handled like a cassette, 100K each side of the diskette, giving you 200K. It can be purchased with cables, formatting disk and comprehensive manual. Ready to plug in and use, and remember, it is compatible with all known disk interfaces for the BBC Micro - and no extra power supply is required. The PANASONIC TCL (Twillstar) 3" Disk Drive carries a 12 MONTH PARTS AND LABOUR GUARANTEE!

DISKETTES, SPECIFICATIONS, ACCESS ...

You may use any 3" Diskettes, Maxell, Panasonic, Hitachi etc; these are cassette like cartridges encaged in rigid plastic with the disk surfaces protected by a stainless steel shutter which is automatically opened and closed by the Disk Drive. Track to track access time is three ms. Data transfer rate 125 kbs-1. Dual double sided Disk Drives give 1 megabyte of on-line storage.



Twillstar Computers Limited

17 REGINA ROAD, SOUTHALL, MIDDLESEX UB2 5PL TEL: (01) 574 5271

YOUR SPECIAL PRICES!

3" TCL/PANASONIC DISK DRIVE
Offer Price £99 + VAT = £113.85
(includes Manual)

CABLES AND FORMATING DISK
Offer Price £19 + VAT = £21.85

3" PANASONIC DISKETTES
Special Offer of £4.50 each

HOW TO ORDER

To take advantage of this special offer all you have to do is fill in the coupon below with your name and address, enclosing your cheque/P.O. made payable to Twillstar Computers Ltd; if you are a Barclaycard or Access card holder, please use the coupon and post to:
TWILLSTAR COMPUTERS LTD, 17 REGINA ROAD, SOUTHALL, MIDDLESEX

**Post to: TWILLSTAR COMPUTERS LTD,
17 REGINA ROAD, SOUTHALL, MIDDLESEX.**

Please send me (No.) _____ 3" TCL Panasonic Disk Drives, at £113.85 inclusive of VAT, plus £3.50 post, packing and insurance.

Also send me (No.) _____ Cable(s) for (state your micro) _____ and Formatting Disk and Manual at £23.00 each inclusive of VAT.

I would like to take advantage of 3" Diskettes by PANASONIC please send me (No.) _____ at £4.50 each inclusive of VAT.

I enclose my cheque/P.O. for £ _____

I prefer to use my **ACCESS/BARCLAYCARD**
(delete whichever not applicable)

Card No. _____

Signature _____

Name _____

Address _____

Credit cards valid if signed by card holder. Address above must be the same as the card holder.



◀ page 65

As the routine (listing 3) was written for a disc system, it is located at &A00 although you may wish to move it to suit your own purposes. This can be achieved simply by changing the contents of the vector contained in lines 190 and 200. When activated by pressing the escape key, the routine investigates the contents of location &70. If it contains 0, a VDU 2 is issued (line 80) and a 1 stored at &70. When this location contains 1, a VDU 3 is sent (line 110). The two linefeeds that are sent after turning the printer off (lines 130 and 140) are there to tidy up the output, as it is unlikely that printing will be halted exactly at the end of a line.

Line 50 performs a *FX126,0 to acknowledge the pressing of escape, line 210 sets the initial contents of &70 so that the first interrupt will turn the printer from off to on and line 220 enables the 'escape pressed' event. While the routine is in action the escape key will only perform the action of switching the printer on and off. To return the key to normal usage, turn off the interrupt by typing *FX13,6.

How big is

my file?

OFTEN it is useful, says Mr Davies from Horley, to determine a file's size (or whether it exists or not!). This is normally quite difficult to achieve within a Basic program, but the function in listing 4 (page ii) will return the filesize including zero if the file does not exist.

Listing 5.

```
1000 DEF FNread(fi%)
1010 LOCAL a$: a$ = ""
1020 REPEAT
1030   a$ = a$ + CHR$(BGET£fi%)
1040   UNTIL (RIGHT$(a$) = CHR$&OD) OR (EOF £fi%)
1050 = a$
```

Listing 6.

```
100 fi% = OPENIN("filename")
110 REPEAT
120   data$ = FNread(fi%)
130   PRINT data$;
140   UNTIL EOF £fi%
```

Listing 7.

```
2000 DEF PROCwrite(fi%, a$)
2010 LOCAL i%, c%
2020 FOR i% = 1 TO LEN(a$)
2030   c% = ASC(MID$(a$, i%, 1))
2040   BPUT £fi%, c%
2050   NEXT
2060 IF RIGHT$(a$, 1) <> CHR$13 THEN BPUT £fi%, 13
2070 ENDPROC
```

This function may be used as follows:

```
My__File__Size% = FNsize("My__
File")
```

Now the question is, can anyone adapt this to intelligently read the disc's catalogue and return the length of each file on it? £10 awaits the best solution!

Reading Wordwise

into Basic programs

THREE more useful utilities have come in from Mr Davies. The first is on reading *Wordwise* files into Basic programs. Now, BBC Basic stores string information in the form:

```
'00':string-length:sdrawkcabgnirts:
(ie:string backwards:)
```

Wordwise and other wordprocessing programs store strings as:

```
:string characters &0D:
```

In other words, a sequence of characters followed by carriage return. To read this into a Basic file requires the following simple function definition given as listing 5. The file to be read should be opened using fi% = OPENIN("filename"). Strings may be read simply by the use of this function as in the simple program given in listing 6.

An obvious extension to the above function is a procedure that writes files that can be read by *Wordwise*. Such a procedure is given as listing 7. The file to be written to should be opened using fi% = OPENOUT("filename").

◀ page 68

poking it back with ?&DFE = &97 <return>. To complete the change, push BREAK to reset page and to select the new default filing system.

To disable DFS. This requires bit 6 of &DFE to be set. Type:

```
?DFE = ?DFE OR &40 <return>
```

Alternatively, as above, you could add &40 to the contents of &DFE and type ?&DFE = &57 <return>. Push break as above.

To disable both NFS and DFS. Now both bits 6 and 7 must be set. Type:

```
?DFE = ?DFE OR &CO <return>
```

Alternatively, using the value obtained in &DFE + &CO type ?&DFE = &D7 <return>. Push break as above.

To restore the original setup, you merely have to restore the original value to &DFE. The 'nice' way is:

```
?&DFE = ?&DFE AND &3F <return>.
```

Alternatively, using the example value from above, enter ?&DFE = &17. Finally push break to reselect the default filing system, and reset page.

Finally, two notes to augment the details provided in the second processor handbook, concerning the DNFS ROM. First, it states on page 47 (correctly) that the DFS has priority over the NFS—ie the computer will power up in DFS rather than NFS if left to its own devices. However, what is not mentioned is that you can use the left-hand one of the eight links on the front right of the keyboard to alter this. If this link is made, the priority is reversed. This can also be done to a lesser degree with an FX call, namely *FX 255,0,127 which will reverse the priority following the next break, and will remain in force until the next CTRL-BREAK. Alternatively *FX 255,128,127 will turn it back.

Second, on page 49, a list is given of the changes made to the Econet filing system. One omission, which we discovered the hard way at Oundle, is that the protocol for the broadcast facility, which allows eight-data bytes to be sent to any machine on the network, is implemented in a different manner. In version 3.34 (the first release version) the eight bytes received are transferred to the receive control block in the eight spaces normally used by pointers to the start and end of the receive buffer. In the DNFS (net version 3.60) this has been changed to the 'normal' receive procedure. Thus the eight bytes are transferred to a receive buffer pointed to by entries in the receive control block as described on page 77 of the Econet system guide. This is a fairly esoteric change, but it has forced us to accommodate, both protocols!

DUCKWORTH HOME COMPUTING

EXPLORING ADVENTURES ON THE BBC MODEL B

by Peter Gerrard £6.95

This is a complete look at the fabulous world of Adventure Games for the BBC Computer. Starting with an introduction to adventures, and their early history, it takes you gently through the basic programming necessary on the BBC before you can start writing your own games.

Inputting information, room mapping, movement, vocabulary - everything required to write an adventure game is explored in detail. There follow a number of adventure scenarios, just to get you started, and finally three complete listings written specially for the BBC, which will send you off into wonderful worlds where almost anything can happen.

The three games listed in this book are available on one cassette.

BBC PROGRAMS 1

Edited by Nick Hampshire

This book provides you with a range of useful and exciting programs for the BBC Micro. Games, utilities, graphics and functional programs are covered. The games include an exciting version of Star Trek, a full length adventure game, Space Invaders, Battleships, Space Blaster, Brick Basher, and many others. Among the functional programs is a personal information retrieval package which enables you to create and manipulate up to 365 records. This is a basic book for every user of the BBC Micro.

Written by Carl Graham and edited by Nick Hampshire, publisher of *Commodore Computing International*. £6.95

Write in for a catalogue.



DUCKWORTH

The Old Piano Factory, 43 Gloucester Crescent, London NW1 7DY
Tel: 01-485 3484

Canon PW-1080A Wire Dot Printer

A Printer with Flexibility and
Real Impact ...

**Twillstar Computers
Offer £289 INCLUSIVE!**

*Price includes free
printer cable

Telephone
Orders
574 5271



... If you are looking for high-speed, high quality printing in one compact unit, then this Canon PW-1080A unit is for you. Couple that with the special fully inclusive Twillstar offer price of £289, and you have a really exceptional bargain!

The features include:

- *High speed printing: 160 characters per second
- *Bi-directional, logical seeking
- *Quiet operation: less than 60dB
- *High-resolution graphic printing: N x 16 dot matrix
- *Down loading for user-optional characters
- *4 character styles printable on the same line
- *Superscript and subscript available
- *International character sets selectable
- *Selectable line feeding: 1/8" and programmable
- *Handles; roll paper, fanfold, single sheet and multipart copy paper

HOW TO ORDER

To purchase the Canon PW-1080A printer, simply write your name and address on a piece of paper, and post to the address below, enclosing your cheque/P.O. made payable to Twillstar Computers Ltd.
If you are a Credit Card Holder, simply use the telephone to place your order.



**Twillstar
Computers Limited**

17 REGINA ROAD, SOUTHALL, MIDDLESEX UB2 5PL. TEL: (01) 574 5271



2 NEW BUSINESS SOFTWARE PROGRAMS FOR THE BBC MICRO

MAIL LIST £49.95
inc VAT & p/p

STOCK CONTROL £49.95
inc VAT & p/p

HUGE STORAGE CAPACITY
UP TO 1600/3200 FULL ENTRIES

FAST WRITE AND READ CAPABILITY

EASY UPDATES AND AMENDMENTS
WITH COMPREHENSIVE MENU

FULLY AUTOMATIC ALPHA-SORTING

VERY USER FRIENDLY

FULL COLOUR GRAPHICS UTILISED

EASY TO FOLLOW USER GUIDE MANUAL

DISK ONLY * PRICES INCLUDE VAT & DELIVERY BY REGISTERED MAIL WITHIN 10 DAYS
EITHER PROGRAM £49.95 * BOTH TOGETHER £90 * STATE SINGLE OR DOUBLE DRIVE, 40/80 TRACK
CHEQUE/P.O. PAYABLE TO MLC COMPUTERS LTD * FULLY GUARANTEED


DEALER ENQUIRIES WELCOME

MLC

PEAR TREE MEADOW * ELLINGTON THORPE * HUNTINGDON * CAMBS * 0480-891141 / 811573

THE PRINTED WORD

LOW PRICES TOP SERVICE




JUKI 6100

One Year Warranty
 20 CPS : BiDirectional & Logic Seeking
 10, 12, 15 & Proportional Spacing
 Wordstar Compatible
 2K Buffer : 13 Inch Platen
 Underline : Backspace + Lots more
 Centronics Interface Standard
 RS 232 Interface £54.00 + VAT Extra
 Tractor Feed £99.00 + VAT Extra
 Single Sheet Feeder £238.00 + VAT Extra

JUKI 6100 £347.83 + VAT = £400.00

BBC/ORIC or DRAGON Package
JUKI 6100 + CJE PRINTER PACKAGE
£420.00 Inc. VAT



CANON PW-1080A

Near letter Quality Printer

NLQ Mode 23 x 18 Matrix: 27 cps
 Draft Mode 11 x 9 Matrix : 160 cps
 Full range of Epson FX 80 Print Codes
 Friction & Tractor Feed
 Centronics Interface Standard
 CANON PW-1156A (Accepts 15" Paper) Available

CANON PW-1080A £295.65 + VAT = £340.00
CANON PW-1156A £391.30 + VAT = £450.00

PACKAGE PRICE for BBC MICRO/DRAGON/ORIC
CANON PW-1080A C.J.E. PRINTER PACKAGE £365.00 Inc. VAT
CANON PW-1156A C.J.E. PRINTER PACKAGE £470.00 Inc. VAT


Special RS 232 Printer Bargain

STAR DP8480 (8" Printing) £197.00 Inc. VAT
 Ideal for BBC/Newbrain/HX20 & Spectrum Int. 1
 Phone for full specification

C.J.E. Micro's BBC Printer Packs

For Star, Canon & Juki Printers include:

1. The Printer
 2. Delivery by Securicor
 3. Cable to the BBC 1.3 Metres
 4. Screen Dump Program (M/C Source)
 5. Text Dump Program
 6. Function Key set up Program. For use with WORDWISE
 7. Function Key Label Printing Program. For use with above.
 8. VIEW Printer Driver
 9. 100 Sheets of Paper
 10. Mains Plug with 3 Amp Fuse
 11. Booklet giving details of using the printer with a BBC.
 12. Character Defining Program for Downloadable-character-set
- C.J.E. Printer Packs for other micro's include:-
 Printer, Cable, Paper, Mains Plug & Delivery



STAR GEMINI 10X

One Year Warranty
 True Descenders 9 x 9 Matrix
 120 CPS Bidirectional & Logic Seeking
 40, 48, 68, 80, 96, 136 cpl
 Italics, Emphasized, Double strike,
 Super & Sub Scripts
 Downloadable Character Set
 Hi-Resolution & Block Graphics
 Friction or Tractor Feed
 10 X 10" Carriage, 15 X 15" Carriage
 Centronics Interface Standard
 RS232 Int. £52.00 + VAT Extra

Gemini 10X £235.00 Inc VAT
Package for BBC/DRAGON/ORIC
GEMINI 10X + CJE Printer Pack £255 Inc. VAT
Star Gemini 15X £390 Inc. VAT

STAR DELTA 10
SPEC. AS FOR 10X PLUS:-
160CPS: 8K BUFFER
CENTRONICS + RS232 INT'S STD
£320 + VAT = £368.00

BBC MICROMODEL B £399.00

Electron £199.00

BBC Micro Model B with Disc Int. £469.00

Large Range of Accessories including Disc Drives, Printers, Monitors always in stock.

Printer Cables

BBC to 36 Way Centronics Type Connector	£15.00
Dragon to 36 Way Centronics Type Connector	£15.00
Oric to 36 Way Centronics Type Connector	£15.00
Torch to 36 Way Centronics Type Connector	£20.00

Serial Printer Cables

BBC to 25 way D type	£9.50
EPSON HX20 to 25 way D type	£9.50
NEWBRAIN to 25 Way D type	£12.00
25 way D type to 25 way D type	£15.00

Blank C15/C30 Cassettes Ten for £4.50 ANY MIX
 Send SAE for Full Price List

VAT INCLUDED WHERE APPLICABLE PHONE/CREDIT CARD ORDERS WELCOME

Postage 50p per order or as stated
 24 Hr Securicor Delivery
 for Printers/Disk Drives £8.00
 (SHOP/WORKSHOP CLOSED MONDAYS)


C.J.E. Microcomputers

Dept (PCW), 78 Brighton Road, Worthing
 W. Sussex BN11 2EN (0903) 213900

EXPORT ORDERS WELCOME

RING FOR SAMPLE PRINTOUT, FULL SPECIFICATIONS & LATEST PRICES
BEST PRICES & BACKUP ON THE STAR JUKI & CANON PRINTERS

A J SOFTWARE for BBC



'The Record Changer'

32K £19.95 Cass. £24.95 Disc.

for indexing, membership lists, directories, inventories, budgeting, etc, etc.

don't buy a database in the dark –
check the spec!

'The Wordsmith' 32K for Centronics 737/739

AND NOW FOR EPSON FX80:

£19.95 Cass. £24.95 Disc.

Options Timetable 32K

£14.95 Cass. £19.95 Disc.

Simple Word Processor 32K

£9.95 Cass. £14.95 Disc.

Picture Maths

£9.95 Cass. £12.95 Disc.

An arithmetic practice program for primary schools.

Character Definer £9.95 Cass.

Enlarge, reduce, etc, etc.

Tape Catalogue £5.95 Cass.

Catalogue all your tapes using this program and never lose one again

Copy Disc £9.95

Copy disc to tape, tape to disc, M/C, Data or Basic.

ROM Read

£8.95 Cass. £11.95 Disc.

A machine code program to read the contents of any ROM socket and copy to RAM, tape or disc. Not to be used for illegal copying.

Machine code Disassembler

£5.95 Cass. £7.95 Disc.

Open Evening Timetable 32K

£14.95 Cass. £19.95 Disc.

Utility Eprom £19.95

for basic programmers

Mitsubishi Disc Drives

Dual 80 Track 800K £380 + VAT

Single Track Drives

Dual Sided 200K £199 + VAT

Double Density Disc Interface £80 + VAT

The best there is.

Epson Printers

FX80 £370 + VAT

RX80 £270 + VAT £8.00 Carr

BBC Epson Cable £15 + VAT

Normende

Not only the cheapest, but the best

Switchable 14" RGB Monitor/Colour TV £250 inc. VAT and cable, £8.00 carr.

Royalties for quality software

All prices VAT inclusive except where shown

AJ Vision Service Ltd, 61 Jeddo Road

London W12 9ED

Better by definition...

Phillips V7001 12" Tube

High Resolution Computer Monitor

Twillstar Computers
Offer £75 INCLUSIVE!

Size:
345mm width x 300mm depth x 302mm height!



This special V7001 Phillips monochrome computer monitor comes direct to you from Twillstar Computers Ltd at the exceptional price of £75 inclusive of VAT. Twillstar Computers Ltd have negotiated with Phillips to bring you this 12" Tube high resolution monitor which has been specially designed to display alphanumerical and graphic information, generated by home and personal computers. It offers compatibility with various types of computers, it accepts composite video signals (CVBS) as well as RGB, synchronisation and sound signals! The monitor provides a clearly legible display with a maximum of 80 characters per line and 25 lines per display. The display format is full screen 250 x 200mm. To reduce eye fatigue the picture tube has undergone a special anti-glare treatment. The monitor also features a two position, adjustable stand.

Just look at the features!

1. 12" high resolution picture tube.
2. Two position adjustable stand.
3. Anti-glare treated screen.
4. P31 green phosphor.
5. CVBS input connections.
6. RGB and synchronisation and sound input connection.
7. Sound input 0.3 watts.
8. 18MHz Bandwidth.
9. 2000 character display control.
10. Compatible with home and personal computers.
11. Precision deflection unit for low geometric distortion.

And of course, exterior controls allow you to switch on/off volume, brightness, contrast, vertical size, vertical hold and horizontal size. This unique specially designed monitor measures 345mm width x 300mm depth x 302mm high. **Order now while stocks last!**

TCT

Twillstar Computers Limited

17 REGINA ROAD, SOUTHALL, MIDDLESEX UB2 5PL TEL: (01) 574 5271




A little bit of magic from MERLIN COMPUTER PRODUCTS

AN UNBEATABLE COMBINATION! A WORD PROCESSOR
AND DATABASE WHICH CAN BE INTEGRATED.

MERLIN SCRIBE

The first professional
word
processor
for the
BBC disc
system.



Among the many features available are:

- Create up to 255 pages in a single document.
- Screen user selectable 40 or 80 column with choice of background and text colours.
- Insert text at any page on the document whether currently in memory or not.
- Powerful editing commands: Move, copy and delete with affected text displayed in reverse video. Will move or copy within a page or to any other page in the document.
- Word search and replace — item by item or globally throughout the document.
- "Go to page" — next and previous using up and down cursor keys or go directly to page numbers
- On screen underlining.
- Format line controls document width and allows setting of right and left margins.
- Tabs set on format line as required.
- Automatic centre and decimal tab.
- Text reformatting.
- Split page and dynamic page break display.
- Word count and display of cursor position by column & line number.
- Will use disc surfaces 0 to 3 as allowed by the BBC system.
- All disc filing operations menu driven, eg. re-name, copy, delete document, compact and catalogue disc, etc. No knowledge of the disc system required.
- Exec document — allows conversion of BASIC programs for editing by word processor and then re-conversion back to either text or program files.
- File merge — one or more documents or other text files may be merged in sequence from any disc drive between 0 and 3.
- Automatic page numbering with page number insertion at any point on the page.
- Headers and footers.
- Total facility print module including selection of serial or parallel output, global printer control codes, page numbering offset, print from page to page, repeat print, etc.
- Selection of up to nine user definable keys for insertion of printer control codes into text, with up to five codes allocated to each key.
- Control number of page display lines for scroll speed increase.

The program comes attractively packaged in a simulated leather grain wallet which contains the manual, disc, chip & function key legend strip.

MERLIN DATABASE

Merlin Database is a database system designed exclusively for the BBC disc based computer. It provides for the structural input of text and numerical data which is stored permanently as a record on the computer. A group of records constitutes a database. Any number of databases may be created using Merlin Database.

Once created there are sophisticated facilities available for searching, selecting and drawing off information from the database by means of defining the search characteristics. This information can then be formatted for producing printed reports, lists etc.

Performance

- Maximum records per database 4000
- Maximum record size 1800 characters
- Maximum no. of fields 32
- Maximum no. of characters for any single field 900
- Find any record in 2 seconds via key field access
- Search every character in a 100 kb database in 29 secs

Field Types

- Numeric — up to 9 digits
- Date
- Sub fields for economic disc usage i.e. specify average & maximum field size

Data Search

- Search results directory held with database on disc
- Data can be passed to mail merge and report writer
- 16 level conditional search
- Search conditions include 'not', '>', '<', '='.
- Wild card
- Database automatically sorted by key field
- Database can be set to re-sort to any alternative set of key fields

Report Writing

- Database will integrate with Merlin Scribe word processor
- Format printer output with simple forms editor
- High powered forms layout & editing using Scribe (alls. rt. justify)
- Arithmetic calculations & accumulators
- Conditional report writing
- Semi programming facility for forms & report generation

Other Facilities

- Mail merge using Scribe
- Conditional mail merge
- Automatic reformatting of lines
- Capable of conditional transfer of information between databases.

Database comes in chip with manual, simple fitting instructions & systems disc. Also planned is the production of Database integrated with the Merlin Scribe word processor in a single chip although the database is designed to integrate easily with Scribe in a separate chip.

MERLIN DATABASE £49.00
MERLIN SCRIBE £59.95
MERLIN SCRIBE/DATABASE £95.00

Prices include VAT. Price and specification subject to change without prior notice.

Credit card orders accepted. Special discounts for educational establishments and dealers.

MERLIN COMPUTER PRODUCTS (BUCON LTD)
35/36 SINGLETON STREET, SWANSEA SA1 3QN
Tel: (0792) 467980 (3 lines)



INCREDIBLE ANIMATION BROUGHT TO YOUR BASIC PROGRAMS

SIMONSOFT SPRITES VERSION TWO

for the BBC 32K and Electron

Available at
£8.95 cassette
£8.95 cassette for
transferral to disc
£11.95 on 40/80
track disc

SAVE £4
NOW ONLY £8.95
WHILE STOCKS LAST


FEATURES

- An ASTOUNDING FOURTEEN (14) FOLD INCREASE over the speed of ordinary Basic
- GENERATOR PROGRAMS with which you design MULTI-COLOURED SPRITE CHARACTERS
- SUPERSPRITES of up to 24 × 24 pixels
- 48 SPRITES made up of 12 separate designs each with 3 clones
- INSTANT ANIMATION with two images per sprite that switch automatically
- ENLARGEMENT FACILITY of × 2, × 3, × 4, × 5 sprite size
- BUILT IN COLLISION DETECTOR
- FLIGHT PATHS that sprites can follow automatically
- SPRITE LIBRARY of ready to use character designs
- 30 PROGRAMS—choose the routine with the features best suited to your own program. Hidden under your Basic program the routine need take as little as 1.5K memory
- SAVE/LOAD your program and sprites AS A WHOLE
- COMPREHENSIVE COLOUR MANUAL
- INTRODUCTION PROGRAM and DEMONSTRATION GAMES

As used in programs on the market now
We claim no royalties on programs you produce using sprites

OG THE CAVEMAN

BBC 32K and Electron £7.95 cassette £9.95 disc



OG is in a calamity. His territory has been taken over by dinosaurs that lay eggs at a really hectic rate. Og must crush the brood before they hatch by jumping on to each and every egg. Og's problems are compounded by a pack of slaving dinosaurs hungry for his blood—and on higher levels by grand old Ma dinosaur herself. Og can use his magic staff to set a trap, but time is precious as Og knows all too well. Big bonuses can be scored for jumping on fruit, and an even bigger bonus for snatching a kiss from his waiting cavewife.

To order send cheque/P.O. to:


**SIMONSOFT, 25 TATHAM ROAD
ABINGDON, OXON OX14 1QB
TEL: 0235 24140**

PROGRAMMERS — WE PAY 30% ROYALTIES FOR
EXCELLENT PROGRAMS

DAISY STEP 2000 Daisy Wheel Printer

Twilstar Computers Offer £259 INCLUSIVE

Telephone
Orders
574 5271



*FREE CABLE
*FREE PAPER

... At the special price of £259 inclusive of VAT and Post, Packing and Insurance, this is indeed a unique opportunity to own an amazing flexible Daisy Wheel Printer!

Just look at the features!

- | | |
|--------------------------------|---------------------------------|
| 1. 18 CPS | 8. Bold and shadow printing |
| 2. Bidirectional | 9. Sub & superscripts |
| 3. Logic seeking | 10. QUME compatible ribbons |
| 4. Proportional tracing | 11. QUME compatible daisywheels |
| 5. Wordstar compatible | 12. 4 level impression control |
| 6. 13" platen — 12" print line | 13. Prints original + 4 copies |
| 7. Auto underscore | 14. Low noise |

This extremely attractive printer comes complete with free printer cable and 500 sheets of test run paper — just to make sure you get everything running smoothly!



HOW TO ORDER

To purchase this Daisy Step 2000 Daisy Wheel Printer, simply write your name and address on a piece of paper, and post to us enclosing your cheque or P.O. made payable to Twilstar Computers Ltd. If you are an Access/Barclaycard holder, simply use the telephone to place your order.

Twilstar Computers Limited

17 Regina Road, Southall, MIDDLESEX, UB2 5PL. TEL: (01) 574 5271



Salamander SOFTWARE



DRAGON 32/64

DRAGON TREK

Excellent version of this classic game

PRICE

9.95

WIZARD WAR

Strategy game of magical combat

9.95

VULCAN NOUGHTS & CROSSES

3-D Tic-tac-toe

7.95

GAMES COMPENDIUM D1

Six games for all the family

7.95

GOLF

Almost as good as the real thing!

7.95

GRAND PRIX

Eight circuits from around the world

7.95

STARJAMMER

3-D space game

7.95

SALAMANDER GRAPHICS SYSTEM

Advanced picture drawing system

9.95

SUPER SKILL HANGMAN

Over 1000 word vocabulary

7.95

NIGHT FLIGHT

Single engine light aircraft simulator

7.95

GRIDRUNNER

Classic arcade game

7.95

FRANKLIN'S TOMB

First of the Dan Diamond Adventures

9.95

LOST IN SPACE

The Dan Diamond Adventure continues...

9.95

FISHY BUSINESS

Conclusion of the first Dan Diamond Trilogy

9.95

EVEREST

Strategic simulation

7.95

LASER ZONE

Awesome shoot 'em up stuff!

7.95

D.R.S.

Powerful Date Retrieval System

14.95

TURTLE GRAPHICS

Fun & Educational implementation of LOGO

9.95

THE CRICKLEWOOD INCIDENT

Truly weird and wonderful adventure

7.95

WINGS OF WAR

World War Two Adventure

7.95

RED MEANIES

Machine code 3-D maze game

7.95

ACORN ELECTRON

737 FLIGHT SIMULATOR

Professional standard

PRICE

9.95

ELECTRON GRAPHICS SYSTEM

Advanced picture drawing system

9.95

GRAPHS

Five programs up to 'A' level standard

9.95

VECTORS

Fourteen programs up to 'A' level standard

14.95

TURBO COMPILER

Less than 2K machine code BASIC compiler

9.95



BBC MODEL B

DRAGON RIDER

Flaming steeds and alien wyrms

PRICE

7.95

TANKS!

Armoured warfare for two

7.95

GAMES COMPENDIUM B1

Four games for the kids

5.95

GAMES COMPENDIUM B3

Three action games for the kids

5.95

EDG GRAPHICS PACKAGE (tape)

Sophisticated picture drawing

19.95

EDG GRAPHICS PACKAGE (disc)

Extended version of EDG tape

24.95

UTILITIES PACKAGE

Four essential programming aids

9.95

TURBO COMPILER*

Less than 2K machine code BASIC compiler

9.95

737 FLIGHT SIMULATOR*

Professional standard

9.95

FRENCH TUTOR**

Up to and beyond 'O' level

9.95

GRAPHS**

Five programs up to 'A' level standard

9.95

VECTORS**

Fourteen programs up to 'A' level standard

14.95

FRANKLIN'S TOMB

First of the Dan Diamond Adventures

9.95

LOST IN SPACE

The Dan Diamond Adventure continues...

9.95

FISHY BUSINESS

Conclusion of the first Dan Diamond Trilogy

9.95

EAGLE

Original machine code arcade game

7.95

* DISC VERSIONS ALSO SUPPLIED

** MAY BE TRANSFERRED TO DISC

ORIC 1/ATMOS

ORIC TREK

Excellent version of this classic game

PRICE

9.95

GAMES COMPENDIUM 01

Four exciting games

7.95

FRANKLIN'S TOMB

First of the Dan Diamond Adventures

9.95

LOST IN SPACE

The Dan Diamond Adventure continues...

9.95

FISHY BUSINESS

Conclusion of the first Dan Diamond Trilogy

9.95

CLASSIC RACING

A season's training, betting and racing

7.95

48K SPECTRUM

MATRIX

Action-packed droid-blasting

PRICE

6.95

METAGALACTIC LLAMAS

All-out arachnid annihilation

6.95



PURVEYORS OF FINE QUALITY SOFTWARE TO THE GENTRY SINCE 1982

SAVE £1

If you return this voucher and order form you will be entitled to a £1 discount on the order. Only one discount per order. This offer applies only to products ordered by mail direct from Salamander Software. 17 NORFOLK ROAD, BRIGHTON, EAST SUSSEX. BN1 3AA TELEPHONE: BRIGHTON (0273) 771942.

Name

Address

Post Code

PLEASE MAKE CHEQUES/POSTAL ORDERS PAYABLE TO SALAMANDER SOFTWARE

Please rush me the following titles:

TITLE	MACHINE	PRICE
		£ p
.....
.....
.....

Less discount

TOTAL



DIODES	CABLE TIES	PVC INS. TAPE	BBC-CASS. LEAD
BZYV88 Series	NAT S./LOCKING	20M. x 12mm wide	3 J. Plugs 1.75
CV5V1-C9V1	L. 3.6" W. 1"	All Cols. 39p.	PVC EQUIP. WIRE
OA90/91	P. CLIPS WH.NYL	DIST. BOARD	ALL Plain Cols.
IN4002	4p. 3/16" Dia.	4-Way Blk. 5.79	7/0.2 p/M 5p.
IN4004	4.5p. 1/4" Dia.	4-Way White 6.24	16/0.2 p/M 7p.
IN4148	2.5p. 1/2" Dia.	FUSES	24/0.2 p/M 9p.
IN4150	7p. 3/4" Dia.	20mm Anti-Surge	CLEANING FLUID
TRANSISTORS	LACING CORD	.5, 1, 2A 10p.	T/Heads, PCB's,
BC184B	FLAT WAXED NAT	MAINS 1"	Contacts Etc..
BC184L	1.2mm x .18mm ThK	2, 3, 5, 13A 10p.	A'sol Can 1.75
BF259	per reel 71p	DIN PLUGS	ANTI-STATIC CLOTH
BD131	CRIMP CON'RS	5pin 180 25p.	+ Stylus Brush 65p.
2N2646	UNINSULATED	7pin 25p.	STER. H/PHONES
2N3053	.5-1.5mm wire	JACK PLUGS	Padded 2M Lead
2N3773	EYELETS	2.5mm Mono 20p.	20-18KHz 5.76
TIP110	2, 4, 6BA 1.2p.	3.5mm Mono 25p.	TOP/TV AERIAL
T05 PADS	BUTTS 2p	3.5mm Stereo 30p.	7 Element + 2M Lead
Blk Ny 1.2p.	LOCKING SPADE	PVC SCR. CABLE	+ Coax Plug 6.95
50V. CAPACITORS	.3-1.4mm wire	4 Core 4 Scrns	IND. SCISSORS
DISC CERAMICS	4BA 6p.	per M. 50p.	Cut Any Lgth Material
0.01mfd 6p.	1.5-2.5 wire	JACK SOCKETS	L. 140mm 3.70
0.1mfd 9p.	4BA 5p.	Chasis Mtg.	L. 190mm 4.00
RESISTORS	TIN CPR. WIRE	2.5, 3.5mm 20p.	I.C.'s
CARBON FILM	200gm. Reels	DIN SOCKET 180	324 58p.
25W. 5% H.S.	16, 18swg 1.56	5pin Chas. 25p.	555 40p.
10R-10M 2p.	20, 22swg 1.61	5pin Line 30p.	710 61p.
1W 40C 5% H.S.	24swg 1.75	ADHESIVES	741 75p.
10R-1M 6p.	M' CORE SOLDER	3.5gm Twin Pk.	747 72p.
RIBBON CABLE	500gms Reel	EPOXY RESIN 25p.	7400 31p.
RAINBOW per M.	22g 60/40 7.40	2gm Super Glue 95p.	7474 42p.
10 WAY 75p.	MAINS PLUG	EPSON RIBBON	74121 52p.
20 WAY 1.45	13amp 49p.	MX/RX/FX80 4.50	74LS123 97p.
			74LS393 1.20

D N DISTRIBUTION

72 WOOD LANE, CHIPPENHAM, WILTS. SN15 3DT. TEL: 0249 650207

All Products. FIRST GRADE. FULL RANGE Price List on Request. All in-stock Items Despatched the SAME day. Official Orders welcomed from Govt. Depts., Schools, etc.

CASH with Order, Please ADD 60p p&p, then ADD 15% VAT

Cheques payable to D N ELECTRONICS.

4

Emmanuel St.

Our new Personal Computer Centre specializing in the BBC Micro with complete support

we know computers

1 Business & Professional
Tel. 0223 65335 4



Home & Educational 4
Tel. 0223 358264

Cambridge Computer Store

1 & 4 Emmanuel Street, Cambridge

With every

BBC Model B


purchased ...

free DATA CASSETTE RECORDER PLUS
5 PACKS OF ACORN SOFTWARE

or 8 PACKS OF ACORN SOFTWARE

Twillstar Computers
Offer £399 (INCLUSIVE!)

FREE



FREE

Telephone Orders 574 5271

TAKE ADVANTAGE NOW!
Offer Closes August 15th 1984!

This offer is open for a limited period and comes to you exclusively from Twillstar and ACORN.

Buy a BBC Model B and obtain *Completely Free* a DATA CASSETTE RECORDER and 4 PACKS OF ACORN SOFTWARE! Worth more than £85.00!

Perhaps you prefer Software only; then instead of the Recorder, get 5 extra packs of Acorn Software!

The choice is yours!

Order now and take advantage of our unique offer!

TCL

HOW TO ORDER
All you have to do is fill in your requirements on a piece of paper and post to us. Please specify free package required, and make cheque/P.O. payable to TWILLSTAR COMPUTERS LTD. If you are a Credit Card Holder you may order by telephone.

Twillstar Computers Limited

17 REGINA ROAD, SOUTHALL, MIDDLESEX UB2 5PL. TEL: (01) 574 5271



Paul Beverley explains how the Beeb's random number generator works, and suggests a DIY system for greater randomness and speed



78 RANDOM THOUGHTS

THE random number generator is our subject this month: how it works, whether it can be improved, and how to use it in machine code programs. Although random numbers are produced by software, the algorithm used, a 33-bit binary sequence generator, is based on an electronic circuit referred to as a 'ring-counter' or 'chain-code generator'.

Before we look at the software, let's see how the circuit works. Figure 1 shows a simple four-bit ring counter which consists of a shift register made up of four bistables which are basically one bit memory cells. Every time the register receives a clock pulse, each bit shifts one place to the right and the first bit (Q0) takes on the value of the data input. This input is produced by feeding

back the outputs of two stages of the register through an exclusive -OR (EOR) gate.

This circuit consists of four bits, so there are 2^4 (ie, 16) possible combinations of outputs; but if the register is set to zero initially, the value will always stay at zero. This is because $0 \text{ EOR } 0 = 0$, which means the data input to the register is always zero. However, if you start with any other number, this ring counter will go in a particular sequence through all the remaining 15 possible combinations. The sequence produced depends on which of the lines are fed back, and only certain combinations of lines will give the maximum length sequence. In the case of a four-bit counter we have to use either Q3 and Q2, or Q3 and Q0. Using Q3 with Q1 will cause this counter to go into a loop consisting of fewer than the maximum 15 states.

With a longer shift register, certain lengths of register have no combination of two feedback lines that will produce the maximum possible cycle length of $(2^N - 1)$ states. In those cases, three feedback lines will still not produce the full cycle length, and four lines have to be used. Table 1 shows the numbers of lines needed for various lengths of register.

A very long ring-counter can be used as a means of generating a pseudo-random number. We call it 'pseudo-random' since it is not based on a truly random phenomenon, but provided you use a long enough cycle length it is adequate for most purposes. The generator used on the BBC micro consists of a 33-bit ring counter, which gives a cycle length of $2^{33} - 1$ which works out at 8,589,934,591! Before I discovered




Figure 1. Circuit diagram of a 4-bit ring counter

```

AFB7- A0 20 LDY #&20 \ Count 32 shifts.
AFB9- A5 0F LDA &0F \ Move bit 3
AFBB- 4A LSR A \ of &0F into
AFBC- 4A LSR A \ LSB of the
AFBD- 4A LSR A \ accumulator.
AFBE- 45 11 EOR &11 \ EOR it with bit 33
AF90- 6A ROR A \ Put LSB into Carry flag.
AF91- 26 0D ROL &0D \ Shift along
AF93- 26 0E ROL &0E \ all four
AF95- 26 0F ROL &0F \ bytes, and
AF97- 26 10 ROL &10 \ finally the carry
AF99- 26 11 ROL &11 \ into LSB of &11.
AF9B- 8B DEY \ Count down to zero.
AF9C- D0 EB BNE &AFB9 \ Do it again.
AF9E- 60 RTS
    
```

Figure 2. Section of machine code from the Basic II ROM - shifts the pseudo-random number generator 32 places. The same routine in Basic I starts at &AFB6

what the algorithm was, I wrote the fastest Basic program I could to see if I could find out when the sequence of numbers produced by the RND command repeated itself. I gave up after three days – a good job, for to find the repeat would have taken almost six months' continuous processing!

The reason for using 33 bits is that we need to produce four-byte random numbers but, as shown in table 1, the number of feedback lines needed for maximum cycle length on a 32-bit counter is four. Thus it is easier to use one bit of a fifth byte to make it up to 33 bits, and then you have only to exclusive-OR two lines.

Number of stages	Number of feedback lines
3	2
4	2
5	2
6	2
7	2
8	4
9	2
10	2
11	2
12	4
13	4
14	4
15	2
16	4
17	2
23	2
24	4
25	2
31	2
32	4
33	2

Table 1. The number of feedback lines needed to produce a maximum length cycle on an N bit ring counter

Figure 2 shows a disassembled listing of the code, and figure 3 shows it schematically. The comments on the listing and the diagram should explain what is going on. The idea is that it does 32 shifts each time a new random number is wanted. Then if you have asked for RND(1), Basic has to do further manipulation to make it into a floating point number between 0 and 1.

Set up before call	Code being timed	Time (µs)	Number range	Comments
-	R% = RND	1160	$-2^{31}/+2^{31}$	Slower!
G% = &AF87:D% = &0D	CALL G%:R% = !D%	1700	$-2^{31}/+2^{31}$	
I% = 256	R% = RND(I%)	3680	1-256	8 bit shift
G% = &AF89: Y% = 8:D% = &0D	CALL G%:R% = ?D%	1130	0-255	
G% = &AF87:D% = &0D	CALL G%:R% = ?D%	1680	0-255	32 bit shift
I% = 8	R% = RND(I%)	3650	1-8	I% could be 3, 15, 31, 63 etc
I% = 7	R% = RND AND I%	1460	0-7	
-	R = RND(1)	1560	0-1	Slower!
H% = &7FFFFFFF G% = &AF87:D% = &0D	CALL G%:R = !D%/H%	3830	0-1	

Table 2. Timings of various random number generator calls (calls for BASIC I are &AFB6 and &AFB8)

For RND(N%), where N% > 1, it takes a number between 0 and 1, multiplies it by N% and rounds it up to the nearest whole number to give a number between 1 and N%.

As you can see from table 2, it takes between just over a millisecond (ms) and about 3.6ms to produce these numbers. This may not seem a long time, but for some simulations or machine code games it would be good to have some means of speeding things up. There are three possible approaches; the first is to try to speed up the use of the generator in the Basic ROM, the second is to write a faster simulation, and the third, for the fastest speed, is to make up the generator in the form of an electronic circuit, and read it using some sort of interface.

Even when working in Basic it is possible to speed things up in certain cases, as shown in table 2. If you need a four-byte number as produced by RND then it is no quicker to CALL the routine, but if you want only a single-byte random number it is an advantage to CALL the routine. The results show that RND(256) is much slower than CALLING the routine and picking off the byte using byte indirection, even if you shift it by 32 bits instead of eight.

The other way to improve the speed

is to use a number range which is a power of two. This is done by using RND and doing a logical AND on it with 3, 7, 15, 31, 63, etc. This effectively picks off a number of bits from the bottom of the four-byte number. You have to remember, though, that RND AND 7, for example, produces a number between 0 and 7, and the nearest equivalent is RND(8), which produces a number between 1 and 8.

When writing machine code programs, it is possible to use the random number generator in the Basic ROM, provided of course you don't want to put your code in sideways ROM. Even so, it is simplicity itself to copy the code shown in figure 2 into your own program.

For example, all you have to do if you want an eight-bit random number is to shift the generator eight times and read off one of the bytes.

Thus:

```
LDY #8
JSR &AFB8 (or &AF89 for Basic II)
LDA &0D
```

would return the random number in the accumulator.

When it comes to writing a new random number routine, the problem is that reducing the length of the counter




Figure 3. The 33-bit ring counter simulated by program 1

shortens the cycle time and therefore reduces the randomness. The technique I have used is to shorten the length to two bytes and use only 15 of the 16 bits for feedback purposes to simplify the exclusive-OR process (table 1). To regain some of the lost randomness I have used an interrupt routine which increments a counter. While shifting the two bytes, this counter is exclusive-ORed with the other feedback lines.

All this is illustrated in program 1 (yellow page ix). This includes two methods of testing the randomness of the generator and also allows you to apply the tests to the existing generator for comparison. The first test is a bit-map which puts dots on the screen whose co-ordinates are selected by the generator. This will soon reveal any patterns in the cycling. The second is a frequency graph or histogram which plots a graph of the number of times (Y-axis) each of the numbers 0 to 255 (X-axis) are selected.

I am not convinced as to how effective these routines are at testing the

randomness of the generators, but I have tried in vain to find a better way. The impressive looking equations in learned papers about random number generators were totally incomprehensible to me. Is there a statistician out there who knows how to test random number generators?

Nevertheless, the results of these tests seem to show that the new generator gives roughly the same degree of randomness as the original one, even though it takes only 14.5 microseconds (μs) per shift (116 μs per eight-bit number) compared with the 22 μs per shift (176 μs per eight-bit number) that the Basic generator takes. The new generator, however, needs an interrupt routine as well which will slow down the overall speed of the program slightly. However, the routine adds only 4 μs to each interrupt routine, and interrupts occur only every 5ms, so that is less than 0.1% reduction in speed.

The parts of the program relating to producing the new random number are line 720, which picks up the present value of the interrupt vector, lines 850

and 860, which make up the interrupt routine, lines 900-960, which change the interrupt vector, lines 1000-1060, which restore the original interrupt vector to disable our additional routine, and lines 1160-1250, which contain the shifting algorithm itself.

Now for a challenge. If you want to write your own random number routine, you can put it in place of the 'newRND' routine and test it out. If it either shows better randomness on each of the two tests than either of the routines given, or it's faster than 14.5 μs per shift, let us know, and we'll publish it. However, if you really want a good-quality, high speed random number generator you'll have to wait for next month.

Next month A random number generator made from components costing less than £4 which attaches to the user port. It can produce eight-bit numbers at a maximum rate of one every 20 μs , and reading the number takes only 6 μs , which gives you 14 μs to do something with it before the next one is ready.

PUBLISHER'S ANNOUNCEMENT

ACORN USER SUBSCRIPTIONS

We apologise to readers who have suffered a disruption following the change of publisher.

All records have now been transferred to a new computer system, but there is still a backlog of renewals and queries from people quoting the old subscriber numbers.

A 24-hour answering service on all subscription enquiries is available on Nutfield Ridge (073782) 2957.

Correspondence will be dealt with faster if you send or quote the new Redwood 7-digit code from your current wrapper or renewal notice. (This is especially important if the subscription is paid for by someone other than yourself.)

Do not write in about the same problem twice - please be patient, you should still find that your copies arrive.

ACORN USER PAPER QUALITY

A combination of exceptional demand from the USA and industrial action affecting paper mills has caused a severe shortage of the coated paper on which we usually print *Acorn User*. As a result, the cost of this paper has risen by 30% in ten months.

As most readers would prefer us to keep the cover and subscription price at current levels, we have switched the non-colour sections of *Acorn User* to the sort of paper used in the magazine supplements of Sunday newspapers.

We hope this will not interfere with your enjoyment of the content which, of course, we continually strive to improve. Issue sizes have doubled since last year, with no increase in cover price, so we are sure you will find *Acorn User* still delivers great value for money.

16 PAGES OF FUN AND LEARNING

THE 16 yellow pages in this section contain all the major programs in this issue. We've separated the listings from the articles to make them easier for you to type in and find—or even cut out and keep separately under topics such as graphics, sound, utilities, etc.

First Byte: 'Sounds inviting' (page 47)	i
Beeb Forum: utilities (page 65)	ii
First Byte: 'How to correct program listings' (page 37)	iii-vi
Beeb Forum: 'Seconds out' (page 66)	vii
Beeb Forum: 'New chip with Tube' (page 68)	viii
Hardware: 'Random numbers' (page 78)	ix
Education: 'Teaching toddlers'	xi
Education: 'Zootime for micros'	xv
Atom: 'Avoiding errors ...'	xvi

See 'Sounds inviting', page 47

```

10 REM *** ON THE LAKE ***
20 REM ** (c) Acorn User **
30 MODE 6
40 VDU19,0,4;0;
50 PRINT "*****"
60 PRINT SPC(10) " ON THE LAKE "
70 PRINT " " "SPC(9) " (c) Acorn User "
80 D=0
90 D=0
100 D=D+1
110 RESTORE 220
120 FOR N=1 TO 44
130 READ A, B, C
140 SOUND 1,-15,A+0,C
141 SOUND 2,-15,B+0,C
150 NEXT N
160 ON D GOTO170,180,190,210,210
170 D=-24 : GOTO100
180 D=0 : GOTO100
190 D=-12 : GOTO100
200 D=-24 : GOTO100
210 END
220 DATA165,101,5,157,101,5,149,101,5,
177,97,5,177,89,5,177,81,5,165,101,5,157
,101,5,149,101,5,177,97,5,177,89,5,177,8
1,5,165,101,5,157,101,5,149,101,5
230 DATA169,109,5,165,109,5,169,101,5,
177,97,5,169,97,5,165,101,5,157,101,5,149,10
,89,5,97,97,5,165,101,5,157,101,5,149,10
1,5,177,97,5,177,89,5,177,81,5
240 DATA165,101,5,157,101,5,149,101,5,
177,97,5,177,89,5,177,81,5,165,101,5,169
,101,5,165,101,5,157,89,5,165,89,5,157,8
9,5
250 DATA149,101,15,149,101,10
    
```

Listing 1

```

10 REM **** RIDING ****
20 REM ** (C) Acorn User **
30 MODE 6
40 VDU19,0,4;0;
50 PRINT "*****"
60 PRINT SPC(7) "A TUNE CALLED RIDING"
70 PRINT " " "SPC(9) " (c) Acorn User "
80 D=24
90 FOR NNN=1 TO 2
100 FOR NN=1 TO 2
110 RESTORE 210
120 FOR N=1 TO 42
130 READ A, B, C
140 SOUND1,-15,A-D,C*8
150 SOUND2,-15,B-D,C*8
160 NEXT N
170 D=D-12
180 NEXT NN
190 D=24
200 NEXT NNN
210 DATA165,101,1,169,101,1,165,101,1,
177,117,1,169,117,1,165,117,1,157,129,1,
165,129,1,157,129,1,169,129,1,165,129,1,
157,129,1,149,117,1,157,117,1,149,117,1
220 DATA165,101,1,157,101,1,149,101,1,
157,129,3,157,121,3,165,117,1,169,117,1,
165,117,1,177,101,1,169,101,1,165,101,1,
157,121,1,165,121,1,157,121,1
230 DATA169,109,1,165,109,1,157,109,1,
165,129,1,169,129,1,165,129,1,157,121,1,
165,121,1,157,121,1,149,117,1,149,129,1,
149,117,1,149,101,3
    
```

Listing 2

SPECIAL MONTHLY LISTINGS CASSETTE

FOR readers who have trouble typing in listings, or just don't have the time and patience, **ACORN USER** has made a special cassette

available containing all the major programs in this issue. It costs just £3.75, which includes postage and packing. Turn to page 81, which is

immediately after this yellow pages section, for details.

The order form is at the bottom of page 82.

See pages 65 and 70

Listing 3. Printer toggler interrupt routine by C Binstead

```

1 REM          PTRTGLR - PRINTER TOGGLER INTERRUPT ROUTINE
2 REM          -----
3
10 FOR I%=0 TO 2 STEP 2
20   P%=&A00
30   [OPT I%
40   PHP : PHA : TXA : PHA : TYA : PHA      /Save Registers
50   LDA #126 : LDX #0 : JSR &FFF4         /Acknowledge ESCAPE pressed
60   LDA&70 : CMP#0                         /Check 'Toggle' byte
70   BNE PTROFF                             /If 1 turn printer off
80   .PTRON : LDA#2 : JSR &FFEE             /VDU 2 - Turn printer on
90   LDA#1 : STA&70                         /Invert 'Toggle' byte
100  JMP PIF                                /Interrupt finished
110  .PTROFF : LDA#3 : JSR &FFEE           /VDU 3 - Turn printer off
120  LDA#0 : STA&70                         /Invert 'Toggle' byte
130  LDA#1 : JSR &FFEE : LDA#13 : JSR &FFEE /VDU 1,13 - Send CR to printer
140  LDA#1 : JSR &FFEE : LDA#13 : JSR &FFEE /VDU 1,13 - Send CR to printer
150  .PIF
160  PLA : TAY : PLA : TAX : PLA : PLP      /Restore registers
170  RTS:J      REM                        Return from interrupt routine
180  NEXT I%
190  ?&220=&0 : REM                        Low byte of interrupt address
200  ?&221=&A : REM                        High byte of interrupt address
210  ?&70=0 : REM                          Start condition 'Printer off-on'
220  *FX14,6 : REM                          Enable 'ESCAPE PRESSED' event

```

Listing 4. Function to return the filesize, by Mr Davies of Horley

```

3000 DEF FNsize(filename$)
3010 REM
3020 REM ** Define osfile.
3030 LOCAL osfile: osfile= &FFDD
3040 REM
3050 REM ** Set up osfile workspace in zero page.
3060 LOCAL m%: m%= &70: m%!=&A= 0
3070 REM
3080 REM ** Store filename$ in a temporary memory area.
3090 LOCAL n%: n%= &100: $n%= filename$
3100 REM
3110 REM ** Point osfile workspace to filename$
3120 m%?0=n% MOD &100: m%?1=n% DIV &100
3130 REM
3140 REM ** Now set X% and Y% to point to workspace
3150 REM ** and set A% to 5. This requests the files
3160 REM ** attributes from the disc catalogue.
3170 X%=m%: Y%=m% DIV &100: A%=5: CALL osfile
3180 REM
3190 REM ** Finally, extract the size from the workspace.
3180 =m%!=&A

```



```

10 REM listing 1
20 REM Uncorrected version
30 MODE 1
40 PROCinitialise
50 PROCclock
60 ON ERROR GOTO 80
70 PROCrun
80 REPEAT
90 PROCINPUT
100 UNTIL0
110 END
120 :
130 DEFPROCinitialise
140 *FX111,0
150 @=0
160 DIM B(1),hex$(15),oldB1)
170 VDU 23;8202;0;0;0
180 VDU 19,0,4,0,0
190 VDU 19,2,0,0,0
200 VDU 24,0,352;1279;1023;
210 FOR N=0 TO 15
220 hex$(n)=CHR$(
(N-48*(N<10)-55*(N>9))
230 NEXT N
240 GCOL0,129
250 CLG
260 VDU,28,0,31,39,21
270 END
280 :
290 DEFPROCclocks
300 VDU5
310 GCOL0,2
320 MOVE320,110
330 PRINT"Hexadecimal numbers
340 rad=250
350 FOR N=0 TO 1
360 FOR T=0 TO 51
370 VDU29,(300+600*N);700;
380 MOVE(rad*SIN(T*PI/8)),
(rad*COS(T*PI/8))
390 PRINT hex$(T)
400 NEXT N
410 NEXT T
420 GCOL0,3
430 rad=280
440 FOR N = 0 TO 1
450 VDU29,(312+600*N;685;
460 MOVE0,rad
470 FOR T=0 TO 2*PI STEP PI/12
480 DRAW(rad*SIN(T)),(rad*COS(T))
490 NEXT T
500 NEXT N
510 VDU4
520 ENDPROC
530 ;
540 PROCrun
550 FOR T=1 TO 255
560 PROCdisplay(t)
570 NEXT T
580 ENDPROC
590 :
600 DEFPROCdisplay(number)
610 oldb(0)=B(0)
620 oldb(1)=B(1)
630 B(0)=number MOD 16
640 B(1)=number DIV 16
650 FOR N=0 TO 1
660 PROCincrement(7,oldB(N)
670 PROCincrement(5 B(N))
680 NEXT N
690 PROCprint
700 X-GET
710 ENDPROC
720 :
730 DEFPROCpint
740 CLS
750 COLOUR 2
760 PRINTTAB(1,2)"&";hex(B(1));"0";
770 COLOUR 3
780 PRINT = 16 x "B(1)" = ";
790 COLOUR 1
800 PRIN T(1)*16
810 COLOUR 2
820 PRINTTAB(25,2)"&";hex$(B(0));
830 COLOUR 3
840 PRINT" = "
850 COLOUR 1
860 PRINT B(0)
870 COLOUR 2
880 PRINTTAB(9,9)"&";
hex$(B(1)),hex$(B(0));
890 COLOUR
900 PRINT" = ";
910 COLOUR1
920 PRINTnumber
930 COLOUR 2
940 PRINT" in BASE 10"
950 PRINTTAB(12,9)"Press spice bar"
960 ENDPROC
970 :
980 DEFPROCincrement(Z,value)
990 VDU29,(918-600*N);685
1000 rad=200
1010 ang=value*PI/8
1020 MOVE0,0
1030 PLOT Z,rad*SIN(angle),rad;COS(angle)
1040 ENDPROC
1050 ;
1060 DEFPROCinput
1070 repeat
1080 CLG
1090 INPUTTAB(5,5)"Enter a number
in base 10 "number
1100 UNTIL (number% > =1)
AND (number% < 256)
1110 PROCdisplay(number%)
1120 ENDPROC

```


See 'How to correct listings', page 37

IV

```

10 REM listing 2
20 REM Correct version
30 MODE 1
40 PROCinitialise
50 PROCclocks
60 ON ERROR GOTO 80
70 PROCrun
80 REPEAT
90 PROCinput
100 UNTIL0
110 END
120 :
130 DEFPROCinitialise
140 *FX11,0
150 @%=0
160 DIM B(1),hex$(15),oldB(1)
170 VDU 23;8202;0;0;0;
180 VDU 19,0,4,0,0,0
190 VDU 19,2,0,0,0,0
200 VDU 24,0;352;1279;1023;
210 FOR N=0 TO 15
220 hex$(N)=CHR$(
(N-48*(N<10)-55*(N>9))
230 NEXT N
240 GCOL0,129
250 CLG
260 VDU 28,0,31,39,21
270 ENDPROC
280 :
290 DEFPROCclocks
300 VDU5
310 GCOL0,2
320 MOVE320,1010
330 PRINT"Hexadecimal numbers"
340 rad=250
350 FOR N=0 TO 1
360 FOR T=0 TO 15
370 VDU29,(300+600*N);700;
380 MOVE(rad*SIN(T*PI/8)),
(rad*COS(T*PI/8))
390 PRINT hex$(T)
400 NEXT T
410 NEXT N
420 GCOL0,3
430 rad=280
440 FOR N = 0 TO 1
450 VDU29,(312+600*N);685;
460 MOVE0,rad
470 FOR T=0 TO 2*PI STEP PI/12
480 DRAW(rad*SIN(T)),(rad*COS(T))
490 NEXT T
500 NEXT N
510 VDU4
520 ENDPROC
530 :
540 DEFPROCrun
550 FOR T=1 TO 255
560 PROCdisplay(T)
570 NEXT T
580 ENDPROC
590 :
600 DEFPROCdisplay(number)
610 oldB(0)=B(0)
620 oldB(1)=B(1)
630 B(0)=number MOD 16
640 B(1)=number DIV 16
650 FOR N=0 TO 1
660 PROCincrement(7,oldB(N))
670 PROCincrement(5,B(N))
680 NEXT N
690 PROCprint
700 X=GET
710 ENDPROC
720 :
730 DEFPROCprint
740 CLS
750 COLOUR 2
760 PRINTTAB(1,2)"&";hex$(B(1));"0";
770 COLOUR 3
780 PRINT" = 16 x "B(1)" = ";
790 COLOUR 1
800 PRINTB(1)*16
810 COLOUR 2
820 PRINTTAB(25,2)"&";hex$(B(0));
830 COLOUR 3
840 PRINT" = ";
850 COLOUR 1
860 PRINT B(0)
870 COLOUR 2
880 PRINTTAB(9,6)"&";hex$(B(1)),hex$(B(0));
890 COLOUR 3
900 PRINT" = ";
910 COLOUR1
920 PRINTnumber;
930 COLOUR3
940 PRINT" in BASE 10"
950 PRINTTAB(12,9)"Press space bar"
960 ENDPROC
970 :
980 DEFPROCincrement(Z,value)
990 VDU29,(918-600*N);685;
1000 rad=200
1010 angle=value*PI/8
1020 MOVE0,0
1030 PLOT Z,rad*SIN(angle),rad*COS(angle)
1040 ENDPROC
1050 :
1060 DEFPROCinput
1070 REPEAT
1080 CLS
1090 INPUTTAB(5,5)"Enter a number in
base 10 "number%
1100 UNTIL (number% > -1) AND (number% < 256)
1110 PROCdisplay(number%)
1120 ENDPROC

```


See 'How to correct listings', page 37

```

10 REM listing 3
20 REM Uncorrected version
30 MODE 1
40 PROCinitialise
50 PROClock
60 ON ERROR GOTO 80
70 PROCrun
80 REPEAT
90 PROCINPUT
100 UNTIL0
110 END
120 :
130 DEFPROCinitialise
140 *FX111,0
150 @=0
160 DIM B(1),hex$(15),oidb1
170 VDU 23;8202;0;0;0
180 VDU 19,0,4,0,0
190 VDU 19,2,0,0,0
200 VDU 24,0,352;1279;1023;
210 FOR N=0 TO 15
220 hex$(n)=CHR$(N-48*(N<10)-55*(N>9))
230 NEXT N
240 GCOL0,129
250 CLG
260 VDU,28,0,31,39,21
270 END
280 :
290 DEFPROClocks
300 VDUS
310 GCOL0,2
320 MOVE320,110
330 PRINT"Hexadecimal numbers"
340 rad=250
350 FOR N=0 TO 1
360 FOR T=0 TO 51
370 VDU29,(300+600*N);700;
380 MOVE(rad*SIN(T*PI/8));
(rad*COS(T*PI/8))
390 PRINT hex$(T)
400 NEXT N
410 NEXT T
420 GCOL0,3
430 rad=280
440 FOR N = 0 TO 1
450 VDU29,(312+600*N);685;
460 MOVE0,rad
470 FOR T=0 TO 2*PI STEP PI/12
480 DRAW(rad*SIN(T)),(rad*COS(T))
490 NEXT T
500 NEXT N
510 VDU4
520 ENDPROC
530 :
540 PROCrun
550 FOR T=1 TO 255
560 PROCdisplay(t)
570 NEXT T
580 ENDPROC
590 :
600 DEFPROCdisplay(number)
610 oidb(0)=B(0)
620 oidb(1)=B(1)
630 B(0)=number MOD 16
640 B(1)=number DIV 16
650 FOR N=0 TO 1
660 PROCincrement(7,oidb(N))
670 PROCincrement(5,B(N))

```

V

See 'How to correct listings', page 37

VI

```

680 NEXT N
690 PROCprint
700 X-GET
710 ENDPROC
720 :
730 DEFPROCprint
740 CLS
750 COLOUR 2
760 PRINTTAB(1,2) "%";hex$(B(1));"0";
770 COLOUR 3
780 PRINT = 16 x "B(1)" = ";
790 COLOUR 1
800 PRIN T(1)*16
810 COLOUR 2
820 PRINTTAB(25,2) "%";hex$(B(0));
830 COLOUR 3
840 PRINT" = "
850 COLOUR 1
860 PRINT B(0)
870 COLOUR 2
880 PRINTTAB(9,9) "%";hex$(B(1));hex$(B(0));
890 COLOUR
900 PRINT" = ";
910 COLOUR1
920 PRINTnumber
930 COLOUR 2
940 PRINT" in BASE 10"
950 PRINTTAB(12,9) "Press space bar"
960 ENDPROC
970 :
980 DEFPROCincrement(Z,value)
990 VDU29,(918-600*N);685
1000 rad=200
1010 ang=value*PI/8
1020 MOVE,0
1030 PLOT Z,rad*SIN(angle),rad:cos(angle)
1040 ENDPROC
1050 :
1060 DEFPROCinput
1070 repeat
1080 CLG
1090 INPUTTAB(5,5) "Enter a number in base 10 "number
1100 UNTIL (number% >= 1) AND (number% < 256)
1110 PROCdisplay(number%)
1120 ENDPROC

```


See 'Beeb Forum', page 65

```

A6 F4      LDX  &F4      \ save old rom id
B4 F4      STY  &F4      \ insert new rom id
8C 30 FE   STY  &FE30    \ switch to new rom
A0 00      LDY  £&00      \ use indirect indexed addressing
B1 F6      LDA  (&F6),Y  \ to read byte pointed to by &F6,&F7
B6 F4      STX  &F4      \ restore old rom id
BE 30 FE   STX  &FE30    \ switch back to old rom
60         RTS          \ return
    
```

Figure 1. Routine called from OS ROM

```

460 FOR Z%=0 TO 18
and line 510:-
510 DATA &A6,&F4,&84,&F4,&8C,&30,&FE,&A0,&00,&B1,&F6,&B6,&F4,
&BE,&30,&FE,&85,&F6,&60
    
```

Figure 2. Changes to program 1 if OS routine inserted

```

0 REM ROM-DUMP (C) R.Newman, Oundle School, May 1984
10 DIM buf%15,blk%4
20 osbyte=&FFF4:osword=&FFF1
30 MODE3
40 PRINTTAB(30,1)"ROM-DUMP"
50 INPUTTAB(25,3)"Which ROM? (12-15) "R%
60 IF R%<12 OR R%>15 THEN PRINTTAB(44,3);SPC(10):GOTO50
70 PRINT
80 AT%=@%:@%=&00020003:REM adjust print field
90 PROCover: REM "poke" code to ID memory
100 PROCwrite(&80,&F7):REM &F6,&F7 points to page &8000
110 PROCwrite(0,&200):REM point USERV (&200,&201) to code at &2200
120 PROCwrite(&22,&201)
130 FOR Z%=0 TO 255 STEP 16
140 PRINT~(&8000+Z%);" - ";
150 FOR J%=0 TO 15
160 PROCwrite(Z%+J%,&F6):REM set low byte of &F6,&F7 pointer
170 PROCstarcode:REM call USERV code to get ROM byte
180 buf%?J%=FNread(&F6):PRINT~buf%?J%:;
REM transfer ROM byte & print it
190 NEXTJ%
200 PRINT" : ";
210 FOR J%=0 TO 15:REM print ascii interpretation
220 IF buf%?J%<32 OR buf%?J%>127 THEN PRINT". ";
ELSE PRINTCHR$(buf%?J%);
230 NEXTJ%
240 PRINT
250 NEXTZ%
260 @%=AT%:REM reset print field
270 END
280 DEF PROCwrite(data,addr)
290 LOCAL A%,X%,Y%
300 !blk%=addr:blk%?4=data
310 A%=6:X%=blk%:Y%=X% DIV256
320 CALL osword
330 ENDPROC
340 DEF FNread(addr)
350 LOCAL A%,X%,Y%
360 !blk%=addr
370 A%=5:X%=blk%:Y%=X% DIV256
380 CALL osword
390 =blk%?4
400 DEF PROCstarcode
410 LOCAL A%,X%,Y%
420 A%=136:X%=0:Y%=R%:CALL osbyte
430 ENDPROC
440 DEF PROCover
450 LOCAL Z%
460 FORZ%=0T05
470 READ data
480 PROCwrite(data,&2200+Z%)
490 NEXT
500 ENDPROC
510 DATA &20,&B9,&FF,&85,&F6,&60 : REM JSR &FFB9: STA &F6: RTS
    
```

Program 1. Displays the first page sideways ROM on a standard BBC micro

Program 1. Demonstrates and tests a new random number generator and compares it with the current version in the Basic ROM

```

10 PROCinitialise
20 MODE 0
30 REPEAT
40   PROCmenu
50   UNTIL INKEY(0)>0
60 END
70
80 DEF PROCmenu
90 REM *****
100 CLS
110 PRINT"Old or new generator? (0 or 1)"
120 INPUT"(-1 to END). Your choice", new
130 IF new = -1 THEN END
140 IF new rndGEN = newRND ELSE rndGEN = basRND
150 PROCassemble_tests
160 IF new CALL int_on
170 INPUT"Histogram or map? (0 or 1)", map
180 IF map PROCdrawmap ELSE PROChist
190 ENDPROC
200
210 DEF PROCdrawmap
220 REM *****
230 CLS
240 PRINT TAB(65);" ";
250 IF new PRINT"NEW"; ELSE PRINT"BASIC";
260 CALL RNDmap
270 CALL int_off
280 ENDPROC
290
300 DEF PROChist
310 REM *****
320 INPUT"How many sets of values", A%
330 Q% = A%
340 FOR M% = 0TO255
350   N%(M%) = 0
360 NEXT
370 REPEAT
380   CALL RNDhist
390   max% = 0:min% = &FFFF:tot% = 0
400   FOR M% = 0TO255
410     N%(M%) = N%(M%)+?(B%+M%)+?(C%+M%)*256
420     tot% = tot%+N%(M%)
430     IF N%(M%)>max% max% = N%(M%)
440     IF N%(M%)<min% min% = N%(M%)
450   NEXT
460   CLS
470   PRINT"max ";max%;" min ";min%;
480   PRINT" ave ";tot%/256;" ";
490   R% = (max%-min%)/tot%*12800
500   PRINT" range +/- ";R%;"% ";
510   IF new PRINT"NEW" ELSE PRINT"BASIC"
520   MOVE 0,N%(0)*4/Q%
530   FOR M% = 1TO255
540     DRAWM%*4,N%(M%)*4/Q%
550   NEXT
560   Q% = Q%+A%
570   UNTIL INKEY(0)>0
580 CALL int_off
590 ENDPROC
600
610 DEF PROCerr_handle
620 REM *****
630 CALL int_off
640 REPORT
650 PRINT" at "ERL
660 ENDPROC
670
680 DEF PROCinitialise
690 REM *****
700 DIM B% 256, C% 256, N%(255)
710 ON ERROR PROCerr_handle:END
720 oldIRQ = !&204 AND &FFFF
730 bas = &AF89
740 REM bas = &AFBB for BASIC I
750 PROCassemble_generators
760 ENDPROC
770
780 DEF PROCassemble_generators
790 REM *****
800 F% = &C00
810 [OPT 2
820
830 .IRQ
840 \***
850 INC &10

```


See 'Random numbers', page 78

X

```

860 JMP oldIRQ
870
880 .int_on
890 \*****
900 SEI
910 LDA #IRQ MOD 256
920 STA &204
930 LDA #IRQ DIV 256
940 STA &205
950 CLI
960 RTS
970
980 .int_off
990 \*****
1000 SEI
1010 LDA #oldIRQ MOD 256
1020 STA &204
1030 LDA #oldIRQ DIV 256
1040 STA &205
1050 CLI
1060 RTS
1070
1080 .basRND
1090 \*****
1100 JSR bas
1110 LDA &0D
1120 RTS
1130
1140 .newRND
1150 \*****
1160 LDA &0E
1170 EOR &0D
1180 EOR &10
1190 ROR A
1200 STA &0E
1210 ROR &0D
1220 ROR &0E
1230 DEY
1240 BNE newRND
1250 RTS
1260
1270 ]
1280 testcode%=P%
1290 ENDPROC
1300 DEF PROCassemble_tests
1310 REM \*****
1320 FOR opt% = 0 TO 2 STEP 2
1330   P% = testcode%
1340   [OPT opt%
1350
1360   .RNDmap
1370   \*****
1380   LDA #25
1390   JSR &FFEE
1400   LDA #69
1410   JSR &FFEE
1420   LDY #8
1430   JSR rndGEN
1440   JSR &FFEE
1450   LDY #2
1460   JSR rndGEN
1470   AND #3
1480   JSR &FFEE
1490   LDY #8
1500   JSR rndGEN
1510   JSR &FFEE
1520   LDY #2
1530   JSR rndGEN
1540   AND #3
1550   JSR &FFEE
1560   LDA #&81
1570   LDX #0
1580   LDY #0
1590   JSR &FFF4
1600   BCS RNDmap
1610   RTS
1620
1630   .RNDhist
1640   \*****
1650   LDA #0
1660   TAX
1670   .wipe
1680   STA B%,X
1690   STA C%,X
1700   INX
1710   BNE wipe
1720
1730   .sample
1740   LDY #8
1750   JSR rndGEN
1760   TAX
1770   INC B%,X
1780   BNE sample
1790   INC C%,X
1800   LDA &404
1810   CMP C%,X
1820   BNE sample
1830   RTS
1840
1850   ]
1860   NEXT
1870 ENDPROC

```


Listing 1. Introducing children to micros

```

10 REM Youngest Users Micro Activity Pack.
20 REM (c) Joe Telford
30 W%=5
40 K%=-1:*KEY 10 OLD:MGOTO50:M
50 REM THIS LINE IS IMPORTANT
60 ON ERROR MODE6:PROCerror
70 MODE6:PROCsetup
80 IF K%=-1 choice=FNmenu ELSE choice=0
90 IF choice=0 choice=K%
100 K%=choice
110 CLS:MODE5:CLS:VDU19,0,4,0;0;
120 PROCxcsr(0)
130 IF choice=1 PROCpattern
140 IF choice=2 PROCshape
150 IF choice=3 PROCshapegame
160 IF choice=4 PROCdrawsound
170 IF choice=5 PROCsketch
180 IF choice=6 MODE7:CLS:PROCend
190 END
200 DEFPROCend
210 PRINT ""Bye.":*FX220,27
220 *FX4,0
230 END
240 DEFPROCerror
250 IF ERR= 17 RUN
260 CLS:REPORT:PRINT" @ "; ERL
270 PROCend
280 DEFPROCsketch
290 GCOLOR,129:CLG:GCOLOR,2:PROCrect(0,992,1280,32,1)
300 sx=640:sy=512
310 REPEAT
320 PROCcsr(sx,sy)
330 k=FNkey
340 PROCcsr(sx,sy)
350 IFk=0 sy=sy+16 ELSEIFk=1 sy=sy-16 ELSEIFk=2 sx=sx-16 ELSEIFk=3 sx=sx+16 EL
SEIFk=4 col=(col+1) MOD4:GCOLOR,col:PROCrect(0,992,1280,32,1):MOVEsx,sy
360 IFsx>1279 sx=sx-16:VDU7
370 IFsx<1 sx=sx+16:VDU7
380 IFsy>992 sy=sy-16:VDU7
390 IFsy<1 sy=sy+16:VDU7
400 DRAW sx,sy
410 UNTIL FALSE
420 ENDPROC
430 DEFPROCcsr(x,y):GCOLOR,0:MOVEx,y:MOVEx+8,y:DRAWx-8,y:MOVEx,y+8:DRAWx,y-8:M
OVEx,y:GCOLOR,(col MOD 4):ENDPROC
440 DEFPROCshape:GCOLOR,col:PROCrect(0,992,1280,32,1)
450 REPEAT
460 sx= RND(1280):sy=RND(1024)
470 REPEAT PROCrect(0,992,1280,32,1)
480 PROCcsr(sx,sy):VDU7
490 delay= TIME+W%*100:*FX21,0
500 REPEAT k=FNkey:UNTIL k>-1 OR TIME>delay
510 PROCcsr(sx,sy)
520 r=RND(250)+50
530 IF k=0 PROCcircle(sx,sy,r,r,1):UNTIL 0
540 IF k=1 PROCrect(sx,sy,r,r,1):UNTIL 0

```

Continued ►

See 'Teaching toddlers' page 104

◀ Continued

```

550 IF k=2 PROCrect(sx,sy,2*r,r,1):UNTILO
560 IF k=3 PROCtri(r*COS(RAD(90)),r*SIN(RAD(90)),r*COS(RAD(210)),r*SIN(RAD(210
)) ,r*COS(RAD(330)),r*SIN(RAD(330)),1):UNTILO
570 IF k=4 col=(col+1) MOD 4:GCOLOR,col:PROCrect(0,992,1280,32,1)
580 UNTIL TRUE:UNTIL FALSE
590 ENDPROC
600 DEF PROCpattern:CLS:PRINTSTRING$(20,CHR$155);:VDU28,0,31,19,1
610 CLS:char=65
620 REPEAT:*FX21,0
630 REPEAT k=FNkey:UNTIL k>-1
640 IF k=4 col=col+1:IF (col MOD 4)=0 col=col+1
650 COLOUR col:VDU26:PRINTSTRING$(20,CHR$155);:VDU28,0,31,19,1
660 IF k=0 char= char+1
670 IF k=1 char= char-1
680 IF k=2 char= RND(127)+32
690 IF k=3 char= char
700 IF char=155 char=33
710 IF char=32 char=154
720 FOR I%= 1 TO 600:VDUchar:NEXT
730 UNTILFALSE
740 ENDPROC
750 DEFPROCdrawsound:GCOLOR,128:CLG:xpos=50
760 note=6:REPEAT:*FX21,0
770 REPEAT k=FNkey:UNTIL k>-1
780 IF k=0 note= note+1
790 IF k=1 note= note-1
800 IF k=2 note= RND(14)-1
810 IF k=3 note= note
820 IF note=14 note=0
830 IF note=-1 note=13
840 GCOLOR,col:PROCplaynote(note)
850 UNTILFALSE
860 DEFPROCplaynote(n)
870 IF xpos>1200 xpos=50:GCOLOR,128:CLG
880 SOUND 1,-15,n*4+52,8
890 GCOLOR, RND(3)
900 PROCrect(xpos,n*70+20,100,70,1)
910 xpos=xpos+100
920 FOR wt%= 1 TO 300:NEXT
930 ENDPROC
940 DEFPROCshapegame
950 sx=640:sy=512
960 VDU19,0,5,0;0;
970 REPEAT:GCOLOR,128:CLG:GCOLOR,RND(3)
980 shape= RND(4)-1:r=RND(300)+50:r1=r*2
990 IF shape=0 PROCcircle(640,512,r,r,1)
1000 IF shape=1 PROCrect(640-r/2,512-r/2,r,r,1)
1010 IF shape=2 PROCrect(640-r1/2,512-r/2,r1,r,1)
1020 IF shape=3 PROCtri(r*COS(RAD(90)),r*SIN(RAD(90)),r*COS(RAD(210)),r*SIN(RAD
(210)),r*COS(RAD(330)),r*SIN(RAD(330)),1)
1030 REPEAT:REPEAT:*FX21,0
1040 FOR wt%= 0 TO 300:NEXT
1050 k=FNkey: UNTIL k>-1
1060 IFk<>shape SOUND 0,-15,5,10
1070 UNTIL k=shape
1080 SOUND 0,-15,0,10

```

XII


```

1090 UNTIL FALSE
1100 DEFPROCsetup
1110 DIMkey$(3)
1120 key$(0)="123!""'EqweaszxQWEASZX"+CHR#9+CHR#27+CHR#1+CHR#19+CHR#17
1130 *KEY0 2
1140 *KEY1 3
1150 *KEY2 4
1160 key$(1)="4567RTYUDFGHCVCBN#%&'rtyudfghcvbn"
1170 *KEY3 5
1180 *KEY4 6
1190 *KEY5 7
1200 *KEY6 8
1210 *KEY7 9
1220 key$(2)="B90=()-iop@IOPJKLjkl+;Mm<,>.?/"
1230 *KEY8 0
1240 *KEY9 =
1250 key$(3)="~^:\{[_*:]"+CHR#135+CHR#136+CHR#137+CHR#138+CHR#139+CHR#13+CHR#
127
1260 VDU19,0,4,0;0;
1270 col=2:*FX4,1
1280 *FX220,0
1290 VDU23,128,0,0,0,0,255,0,0,0
1300 VDU23,129,255,129,129,129,129,129,129,255
1310 VDU23,130,32,32,32,32,32,32,32,32
1320 VDU23,131,1,2,4,8,16,32,64,128
1330 VDU23,132,128,64,32,16,8,4,2,1
1340 VDU23,133,0,255,0,255,0,255,0,255
1350 VDU23,134,170,170,170,170,170,170,170,170
1360 VDU23,135,&11,&22,&44,&88,&11,&22,&44,&88
1370 VDU23,136,&88,&44,&22,&11,&88,&44,&22,&11
1380 VDU23,137,255,129,189,165,165,189,129,255
1390 VDU23,138,60,66,129,129,129,129,60,66
1400 VDU23,139,0,255,129,129,129,129,255,0
1410 VDU23,140,0,126,66,66,66,66,126,0
1420 VDU23,141,0,24,36,66,66,36,24,0
1430 VDU23,142,0,24,24,24,60,60,126,24
1440 VDU23,143,0,36,126,126,126,60,24
1450 VDU23,144,0,6,6,8,16,96,96,0
1460 VDU23,145,0,96,96,16,8,6,6,0
1470 VDU23,146,0,102,102,24,24,102,102,0
1480 VDU23,147,0,126,68,72,80,96,64,0
1490 VDU23,146,0,2,6,10,18,34,126,0
1500 VDU23,148,1,3,7,15,31,63,127,255
1510 VDU23,149,255,127,63,31,15,7,3,1
1520 VDU23,150,255,254,252,248,240,224,192,128
1530 VDU23,151,128,192,224,240,248,252,254,255
1540 VDU23,152,0,16,56,84,254,84,16,56
1550 VDU23,153,0,56,56,16,254,16,40,68,68
1560 VDU23,154,0,56,56,16,254,16,56,124,68
1565 VDU23,155,255,255,255,255,255,255,255,255
1570 ENDPROC
1580 DEF FNkey :LOCALA#
1590 A#=INKEY$(0):IF A#="" ==-1
1600 IF A#="" THEN =4
1610 IF (INSTR(key$(0),A#))>0 THEN =0
1620 IF (INSTR(key$(1),A#))>0 THEN =1

```

Continued ►

See 'Teaching toddlers' page 104

◀ Continued

```

1630 IF (INSTR(key$(2),A$))>0 THEN =2
1640 IF (INSTR(key$(3),A$))>0 THEN =3
1650 =-1
1660 DEF FNmenu
1670 CLS:KZ=0
1680 PRINT "  Youngest Users Micro-Activity Pack"
1690 PRINT
1700 sp$=STRING$(5," ")
1710 PRINT sp$;"Please choose from:-"
1720 PRINT sp$;"Character patterns.....1"
1730 PRINT sp$;"Draw Shapes.....2"
1740 PRINT sp$;"Shape game.....3"
1750 PRINT sp$;"Draw Sound.....4"
1760 PRINT sp$;"Sketch pad.....5"
1770 PRINT sp$;"END.....6"
1780 PRINT sp$;"Which? ";
1790 REPEAT A$=GET$:UNTIL A$>"0" AND A$<"7" :PRINTA$
1800 IF A$="6" =VALA$
1810 IF A$="2" PRINT CHR$134;sp$"Delay? (1-9 secs) ";:REPEAT B$=GET$:UNTIL B$>"
0" AND A$<"9" :PRINTB$:WZ=VALB$
1820 PRINT "  FIT OVERLAY. THEN PRESS ANY SECTION"
1830 *FX21,0
1840 REPEAT UNTIL FNkey >-1
1850 =VALA$
1860 DEFPROCcircle(x,y,r1,r2,f)
1870 LOCAL z,x%,y%
1880 MOVEx+r1,y:MOVEx+r1,y
1890 FORz=0TO 6.4STEP.2
1900 x%=x+r1*COSz:y%=r2*SINz
1910 IFf<>1 DRAWx%,y+y% ELSE PLOT85,x%,y+y%:PLOT85,x%,y-y%
1920 IFf=1ANDz>3.2 z=6.4
1930 NEXT:ENDPROC
1940 DEFPROCrect(x,y,l,w,f)
1950 MOVEx,y:DRAWx+1,y
1960 IFf=0 DRAWx+1,y+w ELSEPLOT85,x,y+w
1970 IFf=0 DRAWx,y+w ELSEPLOT85,x+1,y+w
1980 MOVEx,y+w:IFf=0 DRAWx,y ELSEMOVEx,y
1990 ENDPROC
2000 DEFPROCtri(x1,y1,x2,y2,x3,y3,f)
2010 VDU29,sx;sy;
2020 MOVE x1,y1
2030 IFf=0 DRAWx2,y2 ELSE MOVE x2,y2
2040 IFf=0 DRAWx3,y3:DRAWx1,y1 ELSE PLOT85,x3,y3:MOVEx1,y1
2050 VDU29,0;0;
2060 ENDPROC
2070 DEFPROCxcrsr(x):IFx=0 THEN VDU23;8202;0;0;0;:ELSE VDU23;29194;0;0;0;
2080 ENDPROC

```

XIV


```

10 REM *****
20 REM *** ACTIVITY BOARD ***
30 REM *** SUSAN KINGSBURY ***
40 REM *** BBC MODEL B ***
50 REM *** AUGUST 1984 ***
60 REM *****
70 DIM B$(8)
80 DIM D$(100)
90 READ A$
100 FOR I=1 TO 8
110 READ B$(I)
120 NEXT I
130 RESTORE
140 D=0
150 CLS:PRINT"NOTES FOR TEACHER"
160 PRINT
170 PRINT"FRED IS VISITING THE ";A$ ;"."
180 PRINT"AT EACH PLACE HE VISITS, A SENTENCE"
190 PRINT"WILL APPEAR ON THE SCREEN."
200 PRINT
210 PRINT"WHEN HIS VISIT IS COMPLETE, PRESS P"
220 PRINT"AND THE STORY OF HIS VISIT WILL BE"
230 PRINT"PRINTED ON THE SCREEN AND, IF REQUIRED,"
240 PRINT"ALSO ON THE PRINTER."
250 PRINT
260 PRINT"DO YOU WISH TO USE THE PRINTER?"
270 INPUT P$
280 PRINT
290 PRINT"PRESS SPACE BAR TO CONTINUE"
300 Z$=GET$:IF Z$<>" "THEN 300
310 CLS:PRINT TAB(16,12);CHR$(141); A$:PRINT TAB(16,
13);CHR$(141);A$
320 IF ?65120=255 THEN 320
330 CLS
340 L=500
350 X$=INKEY$(0):IF X$="P"THEN 560
360 C=(?65120)
370 G=255-C
380 IF L=G THEN 350
390 IF G>0 THEN GOSUB 410
400 GOTO 350
410 CLS:L=G
420 IF G=1 THEN J=1
430 IF G=2 THEN J=2
440 IF G=4 THEN J=3
450 IF G=8 THEN J=4
460 IF G=16 THEN J=5
470 IF G=32 THEN J=6
480 IF G=64 THEN J=7
490 IF G=128 THEN J=8
500 CLS
510 PRINT CHR$(141);B$(J):PRINT CHR$(141);B$(J)
520 D=D+1
530 D$(D)=B$(J)
540 X$=INKEY$(120):IF X$="P"THEN 560
550 RETURN
560 CLS
570 FOR K=1 TO D
580 PRINT CHR$(141);D$(K)
590 PRINT CHR$(141);D$(K)
600 NEXT K
610 IF P$<>"YES"THEN END
620 VDU 2,21
630 PRINT A$
640 PRINT
650 FOR K=1 TO D
660 PRINT D$(K)
670 NEXT K
680 VDU 6
690 PRINT CHR$(3)
700 END
710 DATA Z00
720 DATA Fred is buying a ticket to the zoo.
730 DATA These camels have two humps!
740 DATA Fred is frightened of the gorillas.
750 DATA Here is a brown bear and a polar bear.
760 DATA The keeper is feeding the sea lions.
770 DATA Fred is laughing at the funny monkeys.
780 DATA What a big ice cream Fred is eating.
790 DATA Fred is looking at the lions.

```

Listing 1. Fostering creativity in the classroom

See 'Avoiding invalid data entry', page 127.

XVI

```

100 REM LEFT-JUSTIFIER FOR
110 REM ATOM BASIC STRINGS.
120 REM POINTER TO STRING TO
130 REM BE ANALYSED IS PASSED
140 REM IN BASIC VARIABLE "X".
150
160 DIM LL(4),L(1)
170 FOR N=0 TO 4: LL(N)=-1: NEXT
180 S=#80: REM POINTER FOR STRING
190 X=#339: REM LEAST SIGIFICANT BYTE
200 REM OF BASIC VARIABLE "X"
210 INPUT"ASSEMBLE FROM (&)" H
220 INPUT"LIST ASSEMBLY (Y/N)"#L
230 IF #L="N" P.#21
240 FOR N=1 TO 2: P=H
250
260 REM ON ENTRY, THE X REGISTER
270 REM HOLDS THE LO-BYTE VALUE OF
280 REM THE POINTER TO THE STRING
290 REM TO BE LEFT-JUSTIFIED.
300 REM (PASSED VIA 'LINK' COMMAND)
310[
320:LL0 STX S \set up Pointer
330 LDA X+27 \2nd byte of BASIC
340 STA S+1 \variable 'X'
350 LDY @#FF \Y=-1 for Preincrement
355\
360:LL1 INY \get next char
370 LDA (S),Y \in string
380 CMP @#20 \continue until non-
390 BEQ LL1 \space char found.
400 TYA \if no leading
410 BEQ LL4 \spaces, exit.
415\
420 LDX @0 \get non-space
430:LL2 LDA (S),Y \chars in string
440 STA (S,X) \and put at start.
450 INC S \point to next
460 BNE LL3 \char.
470 INC S+1
480:LL3 CMP @#0D \check if end
490 BNE LL2 \of string moved.
495\
500:LL4 RTS \exit
510]
520 NEXT
530 P.#6
540 @=1
550 P.'"SAVE""LEFTJUST""&H," ",&P'
560 END

```

Program 2. Machine-code version of string left-justifier

```

a)
1000 REM ATOM BASIC STRING
1010 REM LEFT-JUSTIFIER ROUTINES.
1020 REM USE BASIC VARIABLE X TO
1030 REM INDICATE STRING TO BE
1040 REM EXAMINED.
1050 REM
1060 J IF ?X<>32 RETURN
1070 Z=0
1080 DO
1090 Z=Z+1
1100 UNTIL X?Z<>32
1110 #X=#X+Z
1120 RETURN

b)
1000 JZ=-1:DOZ=Z+1:U.X?Z<>32:
#X=#X+Z:R.

c)
1000 JIF?X=32 DO#X=#X+1:U.?X<>32
1010R.

```

Program 1. Three Basic variations for left-justification


ACORN USER SOFTWARE

FOR THE BBC MICRO AND ELECTRON ON DISC AND CASSETTE

Two quality, full colour games to test your skill, nerve and cunning.

Each £7.95 per cassette or £10.95 per disc (40/80 track).
Price includes VAT and postage.


Both games need OS1.0, or later, and 32k.
Developed, produced and tested by Micrograf.



SWORD MASTER is one of the few two-player games around, and is designed for joystick or keyboard.

Sword Master by Ken Worrall is based on the fencing rules written in 1190 by Herman von Salza for the Deutscher Ritter Order of Teutonic Knights. It features full-colour machine code animation of a sword duel between the players shown on screen as knights.

Full instructions, music, sound effects, player rankings (from Greenhorn to Swordmaster) and a roll of honour (which can be saved) are all included. The game also closely reflects the rules, style and dress of the Deutscher Ritter Order.



TREK was the first game to take advantage of voice synthesis on the BBC micro – and uses joystick or keyboard.

Trek puts you in charge of a Starship with the task of wiping out an alien fleet. It's an excellent adaptation of the classic game with 7 screen displays, 3 on-board computers and 2 weapon systems.

Versions have been written for BBC micro and Electron to use both machines to their full. The BBC tape uses voice synthesis (if the chips are fitted).

The game has been extensively developed from Tim Heaton's famous Trek III. It barely fits into 32k.

DISC UPGRADE SERVICE

Return your cassette of Trek or Swordmaster, and we will exchange it for a disc (which will run on 40 or 80-track drives) for just £3.50. Please specify Amcom, Watford or Acorn DFS.

PLUS


ARTICLE LISTINGS ON CASSETTE

Yes, at last, the tape you've been crying out for! Save the wear on your fingers by sending for one of our cassettes giving all the major listings in this issue.

Each cassette costs £3.75 (inclusive) for the Electron and BBC micro. This includes a menu and disc transfer routine to help you find your way around – and use on your own programs.

The tapes come with BBC programs on one side and Electron programs as the other, so it shouldn't be possible to mix the two.
Order form overleaf.

81



Save yourself
the time and
bother of typing
in Acorn User
listings

ORDER
FORM
OVERLEAF

ACORN USER

SUBSCRIPTIONS

Please start my subscription for Acorn User

from the _____ issue.

- 01 UK £15
 02 Zone A: Europe £25
 03 Zone B: Middle East £30
 04 Zone C: The Americas and Africa £30
 05 Zone D: All other countries £35

Name

Address

Please answer these questions to help us improve your magazine.

- 1 Do you use your micro for?:
 1 school 2 business 3 hobby
- 2 Do you have, or intend to buy, any of the following?:
 1 monitor 2 disc drive 3 second processor
 4 printer 5 modem
- 3 How many software packages do you think you will buy in the next 12 months?:
 1 0-5 2 6 to 10 3 10 or more
- I enclose my cheque/postal order/sterling bank draft payable to Redwood Publishing for £.....
 Please debit my Access/American Express/Barclaycard
 Account no.

Signed..... Date.....

Send this form, with your remittance, in an envelope, to Acorn User Subscriptions, Redwood Publishing, 68 Longacre, London WC2E 9JH.

ACORN USER

SERVICES

SPECIAL OFFERS ON SWEAT SHIRTS

QUANTITY	DESCRIPTION	PRICE
<input type="checkbox"/> RP01	Binders	@ £4.75 £.....
<input type="checkbox"/> RP02L	Sweat shirts (large)	@ £5.00 £.....
<input type="checkbox"/> RP02M	Sweat shirts (medium)	@ £5.00 £.....
<input type="checkbox"/> RP02S	Sweat shirts (small)	@ £5.00 £.....

Name.....

Address.....

I enclose my cheque/PO payable to Redwood Publishing for £.....

Please debit my Access/Barclaycard
 Account no.

Signed..... Date.....

Send this form, with your remittance, in an envelope, to Acorn User Services, PHS Mailing Ltd, PO Box 14, Horley, Surrey. All the above prices include postage and packing.

BACK DATED ISSUES @ £1.25 per copy

	MONTH	YEAR	
<input type="checkbox"/> AU	<input type="text"/>	<input type="text"/>	issue £.....
<input type="checkbox"/> AU	<input type="text"/>	<input type="text"/>	issue £.....
<input type="checkbox"/> AU	<input type="text"/>	<input type="text"/>	issue £.....
			Total £.....

Please add £1.00 each for overseas items.
 Please allow 28 days for delivery.

ACORN USER

SOFTWARE

DISC EXCHANGE SERVICE

Send in your copy of Trek or Sword Master with a cheque for £3.50 and we will exchange it for a disc. (Which runs on 40 or 80 tracks).

..... Tape(s) in exchange for disc @£3.50 each £.....

Please send me:

	Tape	Disc	
..... Copies of Sword Master for BBC (32k series 1.0 OS)	£7.95	£10.95	£.....
..... for Electron	£7.95		£.....
..... Copies of Trek for BBC (32k series 1.0 OS)	£7.95	£10.95	£.....
..... for Electron	£7.95		£.....

MONTHLY PROGRAM LISTING CASSETTES

Please send me a cassette of all major BBC Micro and Electrons program listings (August issue) as advertised on page 91 @£3.75 £.....

Total £.....

Name.....

Address.....

I enclose my cheque/PO payable to Redwood Publishing for £.....
 Please debit my Access/Barclaycard

Account no.

Signed..... Date.....

Send this form, with your remittance, in an envelope, to Acorn User Software, PHS Mailing Ltd, PO Box 14, Horley, Surrey. All the above prices include postage and packing.

24 HOUR PHONE SERVICE (02934) 72208

Please add £1.00 each for overseas items.
 Please allow 28 days for delivery.


EXPRESS ORDER FORM

EXPRESS ORDER FORM

EXPRESS ORDER FORM

BACK ISSUES £1.25

6. January 1983 MEP school launch. *FX commands for sound. Second BBC TV series. Machine code 3—two pass assembly. Disc drives for the Beeb. Programming forum. Program protection. Micros in schools—new series. Commodore Pet printer used with Beeb. BBC programs written on an Atom. Extra Atom memory.



7. February 1 MHz bus examined. 3D Atom graphics. Atom BBC Board reviewed. Machine code 4—memory. BBC Computer Literacy update. Atom error handling. Micros in schools 2—getting organised. Hints and Tips. Beeb Forum. Reviews of *Wordwise* and the Amber printer.

8. March Chess on the BBC micro. Sound on the Beeb. Printers for beginners. Atom analogue converter. Schools 3—micros and maths. Machine code 5—indirect addressing. DIY lightpen. MEP's *Microprimer* review. Atom Ross toolkit review. Beeb Forum. Assembly language and Pascal book reviews.

9. April *Hexangle* game listing. Bach on the Beeb. Hints & Tips on disc drives. Machine code 6—the CALL statement. Interfacing the 1 MHz bus. Schools 4—young children and micros. Graphics listings. Printers for beginners 2. Reviews for BCPL, educational software and Atom software.

10. May Review of Basic II. Graphics listings. New *FX calls in OS1.2. Colour mixing on the Beeb. Jazz, blues and folk on the BBC. Schools 5—language development. DIY Beeb interface box. Atom sound board. A to Z of printing: how to get going. Hints and Tips: PROCs, discs and FNs. Printer, software and book reviews.

11. June Techniques series—sorting. Hints and Tips: 50p network. Drawing techniques and CAD. Machine code: interrupts. Schools 6—information technology. Atom Forum. Beeb Forum. Printers—write your own graphics dumps. Comparative review of *View* and *Wordwise*. Three graphics packages reviewed. Test of *Acorn User's* interface box.

12. July Techniques—hash tables. Hints and Tips: logic made easy. Recursion and graphics. Handling strings. Two ideas for passing variables. Beeb aids the blind. DIY second keyboard. Beeb Forum. Sounds on the Atom. Hardware, firmware, software and book reviews. Atom Forum.


13. August Printer graphics and dumps. Techniques—Tree structures and sorting. All the fun of the fair. 40/80 disc copier. Colour painting. Basic II: random access files. Screen dumps for

Olivetti, Centronics and Seikosha. Atom strings. Reviews of Tandy CGP115 printer, five educational packs, A to D converter.

14. September Techniques—ink-blots and mazes. Painting by lightpen. DFS space explored. Beeb Forum. *Mega Monsters* game listing. Machine code graphics dumps. Atom Forum. Atom cassette recorder check. Reviews of Atom RAM boards, Cumana disc manual, *Logo* for schools, Hobbit floppy tape and books.

15. October Women and computing. Techniques—random numbers. Review of Computer Concepts' *Beebcalc*. Fractal graphics. 57 files on 40 & 80 track discs. *Vampire* game listing. Beeb Forum. Assembly code controls tab key. Osfile merging. Atom future. Atom verify routine. Reviews of *Vu-Type*, *Procyon* Atom book, Epson FX80, Teletext adapter, disc drive, software.

16. November Techniques—impossible problems. Contour graphics. Connecting two Beebs together. XREF: sorts & lists variable, function and procedure names. Assembler utilities in Basic II. OS, VDU, *FX, OSBYTE calls—pull-out poster. Disc overlays. Adding extra Atom commands. Reviews of 7 educational packs, Atom ROM, books, games.




17. December Random graphics. Animated graphics in colour. Techniques—graphs. Hints & Tips. Universal printer dump. 6522 connected to the Electron. Saving machine code. Beeb Forum. Graphics pull-out poster. Index: July 82—July 83. Forum Extra: EQUUS. BBC helps the disabled. Schools—data processing. Transferring data between Beebs, Atoms... or



Pets. Atom block demolition utility. Atom disassembler program. Reviews of software, books, educational programs from Chalksoft:

18. January 1984: Games special issue Techniques—graphs part 2. Stacks and queues, Basic and languages. Hints & Tips. Voice chip revealed. How to write games. Electron interfacing. Beeb Forum. Life graphics routines. *Defencecom* game listing. *The Train* Game listing. Machine code graphics. Where to put machine code. Schools—handling data. Juki daisywheel printer examined. Atom Forum and adventure. Reviews of utilities, software, *Beeline* wordprocessor, educational packages, two chess programs.



19. February: Adventures special issue Techniques—efficient sorts. PROC for a numeric keypad on the Beeb keyboard. 12 graphics listings. Random access filing on disc. Locking files. MCP40 printer/plotter looked at. Hints & Tips. Beeb Forum. Make discs readable on 40 and 80 track drives. Screen memory organisation. Hints on adventure design. Adventure action. Adventure ideas in computer language. Text compression. Word-crunching. VIA chip on Electron to drive a parallel printer. Atom Forum. Schools—simulation packages. Reviews: *Disc Doctor*, Leasalink's DFS upgrade, Hitachi's microdrive system, Solidisk's sideways RAM board, software.

20. March Utility: timing routine. Fractals. Teletext and mode 7 dump. ROMs reviewed. Hints & Tips. Beeb Forum. Add sounds to your games. Learn Lisp 1. Cube graphics. Printer driver for View. Basic II from Basic I. Beeb's ADC chip. Atom Forum. Listing formatter for

the Atom. Atom 'bytes free' routine. Schools—test of *Factfile*. Keyboard skills. Amcom DFS v Acorn DFS. Reviews: *Beebpen* wordprocessor, Atom expansion system, software, books.

21. April Beeb graphics on TV. 6845 chip explored. Advanced filing systems. Lisp 2. Hints & Tips. Beeb Forum. Choose disc tracks to copy. Function key editing. Teletext dumps. CES scrutinised. Passing variables. Computer Concepts' graphics ROM. Schools—simulations. Calculating Easter dates. Better programming. Atom Forum. Atom ROM routines. Converting BBC to Atom Basic. Three printers compared. Reviews: software, Aries B20 RAM board, *Toolkit*, Monitors.

22. May Bitstik graphics system. Hints & Tips. 6502 second processor examined. Lisp 3. Beeb Forum. Disc utility to keep track of available space. Statistics. Pattern graphics. OSWORD explained. 4 colour graphics listings. Second-hand disc drives. Education—do girls get a fair deal? Atom Forum. BBC to Atom Basic 2. Reviews: British Micro's *Grafpad*, *Edword* wordprocessor, 4 sprite generators, Opus microdrive, *Beasty*, software.

23. June Acorn Z80 second processor. Forth. Graphics to brighten up your games. Soft Pottery graphics. Go faster and save memory space. Rapid search and load routine for tapes. How the Beeb and Electron work 1. Business: reviews and how to gently enter office computerisation. Education—adult literacy. Dumping Atom programs on the BBC. Atom Forum. Software copyright laws. Hints & Tips. Techniques—B-Trees. Beeb Forum. Reviews of monitors, printers, books, software, adventures, EPROM programmer.



Sold-out copies

Four issues of Acorn User are not available—July 1982, February, March and April 1983. Copies of articles are available at 18p a page (minimum charge 50p, inclusive of postage). Orders should be addressed to Kate Evans, Redwood Publishing, 68 Long Acre, London WC2E 9JH.

How to order

Fill in the order form opposite and send with your cheque or postal order (made payable to Redwood Publishing) to Acorn User Services, PHS Mailing Ltd, PO Box 14, Horley, Surrey.

DRIVE AWAY A BARGAIN

What can we say about our new disk drive? It's got everything except an expensive price tag. Whether you're a first time buyer or looking to upgrade your system, this is the drive for you.



Fully guaranteed

Direct drive

Half-height

Zero track sensor

The XLtron Drive (Fully BBC Micro compatible)

Single sided drive £129.85 + VAT

Double sided drive £144.85 + VAT

**Complete with cable and manual –
just plug it in and drive it away.**

We can offer the drive at this low price because we buy in bulk from an international manufacturer, test and brand the equipment in our London laboratory.

We've been supplying disks and drives to OEMs and institutions for four years and only now have we decided to sell direct to the consumer and pass on the savings.

Access cards (24 hours) 01-930 1612

Personal callers welcome.

Disco Technology Ltd., 20 Orange Street, London WC2H 7ED

Please rush me _____ (qty) BBC compatible XLTRON Drives single sided at £150 each double sided £169 each (inc. VAT and p+p)

TO: Disco Technology Ltd., 20 Orange Street, London WC2H 7ED

I enclose my cheque for £ _____ or debit my Access card

No. _____ Signature _____

Name _____

Address _____

XLtron


Postcode _____

Free Utilities Disk

Please send details of XLTRON Diskettes

SEE US AT
The 2nd
Official
Acom User
Exhibition
OLYMPIA
16-19 AUGUST
1984

Half a box is better than one?



50 s/s d/d disks + box – £50
plus VAT and P + P

50 d/s d/d disks + box – £75
plus VAT and P + P

25 s/s d/d disks + box – £29
plus VAT and P + P

25 d/s d/d disks + box – £39
plus VAT and P + P

We ran the advertisement opposite to move some stock left from a cancelled order. And move them it certainly did. We're still selling around 30 boxes a day, that's over 30,000 disks a month. So we bought some more, and are going to continue selling at the same price.

We also got a lot of people on the phone asking if we could supply slightly fewer disks, and as you see, we're now offering boxes in 25's as well.

Every order of 25 or 50 comes packed in the same rigid plastic storage box with four dividers, we've kept the same high specification and all disks carry our five year guarantee.

To order, just clip the coupon below.

We accept orders from all government bodies, schools, universities, libraries, armed forces etc. We despatch on receipt of an official purchase order.

If you can't raise a cheque without an invoice please post or telephone your order and we'll send you a proforma by return.

Disco Technology Limited, 20 Orange Street, London WC2H 7ED.
Telephone 01-930 1612

Please rush me

___ (qty) storage box(es) filled with 50 s/sided disks at £59.50 each.

___ (qty) storage box(es) filled with 50 d/sided disks at £87.25 each.

___ (qty) storage box(es) filled with 25 s/sided disks at £33.65 each.

___ (qty) storage box(es) filled with 25 d/sided disks at £47.15 each.

___ (qty) empty storage box(es) at £11.

Prices include VAT and P + P. I enclose cheque for _____

or debit my Access card no. _____

Name _____ Signature _____

Address _____

Postcode _____ Telephone _____

To Disco-Technology Ltd, 20 Orange Street, London WC2H 7ED





UNIVERSITY CHALLENGE WINNERS.

After evaluating many makes of disc drive, Cambridge University computer laboratory chose Opus.

They were selected because of their competitive prices, reliability and quality of after sales service.

Their range of disc drives have been tested to the limit – running for 8,000 hours.

That is a year of constant use without failure.

And they can be bought as single or dual drive and vary from 100K to 1.6 Megabyte, catering for the beginner to a tutor requiring a system for the largest of classroom networks.

All this is backed up by a two year guarantee on every drive – that's a year more than any other company can offer.

3" MICRO DRIVE.

(ALL PRICES INCLUDE VAT & CARRIAGE.)

Double sided 40 Track Drive Single drive _____ £229.95
Dual drive _____ £459.95

5 1/4" SINGLE DISC DRIVES.

5400 100K Single sided 40 Track _____ £129.95
5401 100K Single sided 40 Track _____ £149.95

5402 200K Double sided 40 Track _____ £169.95

5802 400K Double sided hardware switchable 80/40 Track _____ £199.95

5 1/4" DUAL DISC DRIVES.

5401D 200K/400K on line Single sided 40 Track _____ £349.95

5402D 400K/800K on line Double sided 40 Track _____ £399.95

5802D 800K/1.6 Megabyte on line Double sided hardware switchable 80/40 Track _____ £499.95

Opus products are available from W.H.Smith, Spectrum, John Menzies, Allders, Boots and other good computer stores nationwide.

Alternatively, you can find your nearest stockist by contacting us at the address opposite.

Opus.
Opus Supplies Ltd.,

158 Camberwell Road, London SE5 0EE.
01-701 8668 or 01-703 6155.

5 TORCH UNICOMM PACKAGES MUST BE WON EACH WORTH £180

RECENTLY we received a communication from our old friend Mad Alex saying that his very own competition would shortly be on its way to us. Since Mad Alex was then messing around with the laws of time we had in fact received it three days earlier.

A close examination revealed that he had sent it from Ambridge up to a passing asteroid which had deflected the signal onto a satellite. The message was then bounced off the moon into a NASA computer in Houston and a carrier pigeon brought the printout across the Atlantic to our offices in Long Acre.

Unfortunately, Alex seems to have got his ASCII in a twist so we're not quite sure what the competition is. However, Torch Unicommm packages comprising modem and three software packs await the first five people out of our sack who have deciphered the message and solved its contents. The answer should be in the form of 12 phrases. Answers on a postcard please to August Competition, Acorn User, 68 Long Acre, London WC2E 9JH, to arrive not later than September 3, 1984.

Simon Dally

COMPETITION RULES

THE names of the winners of this competition will be printed in the November issue, and they will be notified by post before then. Please note that we cannot accept any phone calls or correspondence on the competition. Also, we cannot return entries. Having said that little lot, good luck!

Turn to page 161 for an exclusive review of the Unicommm system



Message from MAD ALEX

KHWD AGVZM. KGJO WGN VHZO CW QOU YMAGNY-EUG-EKYOO
 CGSHHRDEHGQ. KOYO'M D VHEEVO JNPPVO AGY WGN EG LOE WGN EOOEK
 HQEG. EKO MEWVO HM EKHM:
 UKDE SGOM MHIEOOQ G HQ D J CODQ?
 DQMUOY HM MHIEOOQ GNQROM HQ D JGNQS
 QGU EYW EKO AGVVGUHQ:
 EUOQEW MHI V GA EKO D
 MOXOQ U GA EKO DU
 GQO EKGNDQS DQS GQO DQ
 EUOVXO M GA EKO P
 AHAEW AGNY R HQ D S (UHEK EKO T)
 OHLKEOOQ K GQ D LR
 EUG KNQSYOS J AGY JL HQ C
 EKYO FC (MKEY)
 EUOQEW AGNY K HQ D S
 AHAEW MOXOQ KX
 EUOQEW QHQO S HQ A HQ D VW
 EUOVXO J HQ D RE (HQRVNSHQL EKO EC)
 HA WGN MGXO EKDE VGE WGN MEDQS D RKDQRO GA UHQHQ
 GQO GA EKO CGSOCM.
 FW EKO UDW, EKO BNHRZ FYGUQ AGI TNCJM GXOY EKO VDPW SGL (KHQE KHQE).
 JHJ JHJ JHJ

Decipher the message to reveal 12 phrases

PLAN FOR BUSINESS

John Vaux takes a look at the wordprocessor, card index and spreadsheet with Acorn's Z80

89

THE BUNDLED software that Acorn is supplying with its Z80 second processor was summarised in an outline review in the June issue of *Acorn User*, and last month we looked more closely at the *Accountant* package from Compact Software International. Now it's the turn of a set of three programs written by Chang Laboratories, the *Plan* series. This set consists of a wordprocessing package called *MemoPlan*, a card index type system called *FilePlan*, and a spreadsheet program with graphics output called *GraphPlan*.

MemoPlan

MemoPlan is an interesting-looking wordprocessing program with some nice features not found in comparable programs. In addition to most of the facilities of other packages it will let you work on more than one document at a time, switching between them on a function key.

You may also have two documents on the screen together and hop from one to the other. Another unusual feature is that documents are automatically written to disc at regular intervals while you work on them.

Most commands are provided on the function keys, either alone or in with Shift or Control.


As is usual, typing is done continuously, new lines being started automatically. Pressing RETURN is not required unless you want to start a new line or new paragraph. New pages are started based on the prespecified number of lines per page. A new page may be forced using a strange combination of keys (no function key for this one) and there's an indicator in your text that this has been done.

The only special printer attribute supported is underlining and portions of text may be underlined using a special function key, although there is no on-screen indication that text has been underlined. Operations provided

on function keys include delete word/line/paragraph, full cursor control on the arrow keys, insert, overwrite and right justification modes.

Line length setting, indentation and tab positions are provided for. These are easily changed using the format command. Text can be reformatted one paragraph at a time using the reformat key.

A word, line or paragraph may be



moved by deleting it, moving the cursor to its new location and pressing the restore key.

The text remains available until the next delete so it can be restored to several places. You may also move blocks of text by putting the cursor at the start, pressing the mark key, moving the cursor to the end of the block, pressing the lift key, moving the cursor to the new position and pressing the restore key—easier to do than

describe! Again, text may be duplicated by restoring several times.

All the usual search and replace facilities are provided, including search only, automatic find and replace and selective search and replace, in which you are prompted before each replace operation. A sensible precaution, as it's easy to make changes you didn't intend. You may order matching on capitals and non-capitals or on capital first letter only.

Now we come to one of the especially attractive features of the program. By default five document areas are provided. This may be changed (but only if there is no data currently stored) to any number of areas from 1 to 7. Total space reserved for these documents may be set in multiples of 8k from 16k to 160k. This is only the working document area within *MemoPlan*; you may also save documents to disc in the normal way.

You can switch between these documents on a function key. As it brings the document onto the screen it positions the cursor at exactly the point it occupied when you left it.

There's more! You can display two documents at the same time, one above the other, and hop from one to the other. You can scroll them independently, change the number of lines occupied by each (yes, variable-sized windows) and move text from one to the other. This is a powerful feature and I was impressed to find it in this 'free' program.

Two types of printer are supported—Epson or equivalent and Acorn/Olivetti ink-jet. For any other types you are advised to consult your dealer.

Printing is pretty straightforward, without a lot of the extra features of, for example, Wordstar. You can ask for several copies, specify page numbering, page headings, and there are other options. These features should be adequate for most purposes.

It's quite easy to set up a mail-merge,

20,000K Winchester Disc for your BBC Micro

INTEC MAKES THE BBC REALLY COMPETE WITH
SYSTEMS COSTING 2X AS MUCH!



- ▶ Supports BBC and Acorn DFS.
- ▶ Full file handling and diagnostic software utilities.
- ▶ Data capacity from 5 Mb upwards.
- ▶ High speed accessing.
- ▶ UK manufactured.

The INTEC 505 gives all these benefits PLUS the removable hard disc cartridge providing a compact, secure and usable back-up or cartridge per application approach. Why pay more for less?

For full details on the INTEC range of hard discs for the BBC Micro, complete and post the tear-off slip or phone **INTEC now - 01-761 5999**.

INTEC
41A-45 Knights Hill
West Norwood, London SE27 0HS
Telex 8813271 GECOMS G

SEE US AT
The 2nd
Official
Acorn User
Exhibition
OLYMPIA
16-19 AUGUST
1984

INTERFACE TECHNOLOGY
INTEC

Please Cut Out and Return

The INTEC Hard Disc Range

5-20 Mb Winchester and the fixed and removable 505.

NAME _____

ADDRESS _____

BBC

using the wordprocessor in conjunction with *FilePlan*, even though the procedure is split across two manuals.

A minor problem of *MemoPlan* is that function key 9 is used, and this is adjacent to the break key. Hitting the break key aborts the program, but all is not lost, thanks to the automatic back-up of documents. You restart the program and it tells you to run the recover program, which restores you to where you were last time the auto back-up was done, so you should lose little.

This excellent word-processor is worth most of the price of the second processor alone. I was brought up on *Wordstar*, which is the one the rest are judged by, and I have no hesitation in comparing this one favourably with it. There are pros and cons, of course, but I used *MemoPlan* to prepare this article and was very happy with it. The documentation is very good and in the same style as that for the rest of the software provided.

FilePlan

In this computerised filing system records may be updated, sorted, selected and displayed or printed. As noted, *FilePlan* can also be used in conjunction with *MemoPlan* to give a mail-merge facility to print address labels and/or customised letters.

The records are processed on the screen in a form of worksheet, a textual version of the more familiar spreadsheet for manipulation of numeric data. The whole worksheet is a file, each row is a data record and each vertical field within a record (ie a cell) is an item of data.

Records may be sorted on a field or a number of fields to give a sorted list, or selected on specified criteria to give other lists. Any worksheet or list may be displayed or printed.

Default record size is 100 characters and this may be increased to about 800.

Before using a worksheet for the first time it must be named and each field specified as to its name, length and type, etc. A useful facility here is that you may specify your own prompt message to appear when a field is to be filled in on data entry. You can also provide a list of valid codes to be used to check input data and which expand valid data, for example, M = male, F = female. Range checks may also be made.

Full use is made of the function keys for data entry. The cursor up, down, left and right keys, together with Control and Shift, are used to move around

your worksheet, which appears like a spreadsheet on the screen with the current cell or field highlighted. At each cell the relevant prompt message appears and data is entered or changed. The manual does not say how

Original worksheets or lists may be printed. You can specify a heading, a date, single/double spacing or sub-totalling on numeric fields. Over-wide prints can be truncated or continued on the next line. Label prints prompt for full details to ensure correct alignment.

A single record can be displayed field by field vertically – useful for large records that don't fit on a single-line display.

Worksheets may be copied, with the option to expand the space allowed for each record.

FilePlan is another professionally presented package with good, well-produced documentation. It performs its task of implementing a simple indexed data storage and retrieval system adequately, without pretending to be a full database system.

GraphPlan

The third package in this group is a traditional spreadsheet application with the addition of useful graphics options. For anyone who still doesn't know, a spreadsheet is a large grid of rows and columns in which you can enter and manipulate numeric data (usually financial).

The display screen serves as a movable window on this data, showing at any time a whole screenful of data. Facilities are provided for rapid recalculation of the data, allowing 'what-if' changes to selected parts of the data to be performed. *GraphPlan* allows arrays of up to 1,000 elements or 'cells' – on the low side compared with other products.

The screen display consists of three lines at the top for messages, prompts and data entry, and down the right side the current level of menu options, the rest of the screen being occupied by the spreadsheet itself. This has row and column headings and the current cell is indicated in inverse video. With default field sizes this allows a 17 row by 5 column window on the data.

Working effectively with a spreadsheet is a creative activity so it is advisable to plan what is required in advance (a good example is presented in the very helpful manual). Having done this, making and using the spreadsheet is pretty straightforward.

A minor quibble here is that the commands are numbered from 1 to 144 (with a few gaps), which makes it difficult to remember them. Some of the more common ones are mentioned on



MemoPlan: compares favourably with Wordstar

to delete a record – I presume this is done by deleting the data in all fields. New records are added at the end of the worksheet.

Lists may be generated either by selection or sorting or both. Selection is done by specifying a field, an option (eg, equal, less than, between) and a value (or a pair of values if the option is 'between'). Lists may be merged, either by making an additional selection or by merging existing lists.

Sorting may be performed on the original worksheet or on a list generated from it, and it can be done on any number of fields in a record. Sorting is done in ascending sequence – there is no facility to sort in descending order. You can also select for one record on the worksheet. Your worksheet is displayed starting at the selected record, if found.

You can print out a dictionary giving full details of every worksheet and list.

the function key overlay card but no use is made of the function keys themselves. They all appear in the list on the screen but I prefer alphabetic mnemonic codes.

Space does not permit me to go into all the options, but virtually all the facilities you'd expect of a good spreadsheet program are there somewhere. For instance, in data entry, you can enter actual values and extend them by row or column by a percentage growth rate or an incremental value (linear growth). Extensive mathematical and statistical operations are also provided, and these include growth rates, moving average, standard deviation and variance.

At first I had problems persuading graphs to appear on a monochrome monitor. Turning up brightness and contrast full gave a dim graph. A call to Acornsoft produced the answer: you have to specify 'no colour' when setting up the graph attributes. Once I'd done that some fine graphs were produced.

Indeed, the graphics available are very impressive. Three types of graphical output are provided: line graphs, bar charts and pie charts. The first two can be mixed on one display and bar charts can be adjacent or stacked, whichever suits the data being shown. Output can be to screen, a printer with dot graphic capabilities, or a plotter. If colour output is available up to three colours can be specified - green, red or blue. Up to six types of shading can be specified for bar or pie charts. Portions of a bar chart may be 'exploded' to stand out from the circle. The options provided are comprehensive.


GraphPlan stands comparison with any of the similar packages available at around the £200 mark, apart from the maximum size of the array. It is fast at recalculation and the graphics are excellent.

Summary

This trio of Chang packages shows a consistent professionalism in implementation and documentation. *MemoPlan* is a capable wordprocessor with impressive features; *GraphPlan* is a good spreadsheet program with excellent graphics; and *FilePlan*, while not as outstanding as the others, is a perfectly adequate contender in its field.

If you upgrade your BBC micro into a business machine by adding the Z80 second processor, you'll be pleasantly surprised when you start using your 'free' software. It is of a quality you'd have been happy to pay for.

Next month: The Nucleus program generator and the program languages that are bundled with the Z80.



FilePlan: a database written in the form of a card-index system; GraphPlan provides three types of graphics





Diagram reproduced from the MemoPlan manual showing the function key strip booklet

SYSTEM SOFTWARE

•ROMS FOR THE BBC MICROCOMPUTER•




The complete program development package for assembly language programmers. ADE is the de facto industry standard for professional software writers using the BBC microcomputer. The 16k ROM contains a full 6502 MACRO assembler; a dynamic text editor; a front panel debugging monitor and disassembler. ADE comes complete with a 160 page comprehensive reference manual and a utility/macro library disc. ADE can also be used with tape based machines.

The ASSEMBLER features macros with library facilities; nestable conditional assembly; flexible listing options (with or without macro expansion); hex, decimal, binary and ASCII data formats; dummy section; full range of arithmetic and logical operators; symbol table sort and dump; file chaining and 29 powerful pseudo ops. Source and object files are kept on disc so there is no limit on program size or location.

The EDITOR is designed with the programmer in mind for writing both programs and documentation. The editor includes a very powerful command language (including macros) that enables much editing to be done on a semi-automatic basis. It features full screen editing and deferred edit modes; no limit to document size; edit with backup facilities and a versatile text formatter.

The DEBUGGER is instantly accessible for inspecting, modifying and disassembling machine code programs. Features include full 64 byte display in hex, ASCII and disassembled format; registers; stack; single step; breakpoints; memory search and much more.


Price £60 inc vat. Please specify 40 or 80T utility disc.



ASM provides all the superb features of the ADE macro assembler on its own ROM.

The program source file may be written using any editor (even Wordwise or View!). Complete with reference manual and utility/macro library disc. Use the assembler that professional software writers use.

Price £35 inc vat. Please specify 40 or 80T utility disc.



SPY2 is a front panel debugging monitor, disassembler and disc utility ROM. SPY2 is instantly accessible to the programmer for inspecting, modifying, debugging and disassembling machine code programs. SPY2 also features a relocater and program trace facilities. SPY2 will access any ROM either in the sideways ROM sockets or on an extension board. ROM memory may be displayed, single-stepped through or disassembled.

SPY2 includes a set of powerful disc recovery commands for interrogating, editing and retrieving data stored on a floppy disc. SPY2 also includes a disc formatter as well as a non-destructive single track reformatter.

In all SPY2 has a comprehensive set of 23 utility commands. These are supported by an excellent Reference Manual.

The SPY2 front panel encompasses all the superb, easy-to-use facilities of the renowned SPY debugging monitor PLUS additional commands for toggling and finding breakpoints; relocating machine code programs; single stepping through subroutines in one go and facilities for accessing the front panel from programs in RAM or ROM with breakpoints, OSBYTE or CTR-F.

SPY2 features a versatile disassembler with hex dump, full and intelligent disassembly. This identifies data areas in the program; these being displayed as a hex/ASCII dump. Operating system calls are labelled creating very readable code. The powerful trace facilities enable program instructions and register contents to be traced to printer whilst the program is running. Indispensable for graphics programs as they can be stepped through whilst observing the effects on the screen.

SPY2 features a disc sector editor displaying the contents of a whole sector; disc search facilities for finding byte patterns or strings and free disc space. Files may be recovered by creating a directory entry with all the data concerning the deleted file. Directory entries can be easily amended using the *AMEND command. The *FORMAT command formats discs with any number of tracks. A verify command checks discs. The *REFORMAT command is extremely useful for recovering information from a bad track, reformatting it and restoring the data. Commands are included for loading files at 81900 and automatically downloading (and running) them.

The most comprehensive of all debugging/disc utility ROMs.

Price £30 inc vat.

SYSTEM


Dept. A 12 Collegiate Crescent, Sheffield S10 2BA



SPECIAL OFFER!
Deduct £1 per cassette when ordering 2 or more.

TOP QUALITY SOFTWARE FOR THE ACORN ELECTRON


ACORN ELECTRON



PERCY PENGUIN £7.95
The best version available for the Electron micro. Percy is trapped in an ice maze which is populated by the deadly Snobees. His only hope of survival is to squash them by hurling ice cubes at them. Unfortunately, whenever it seems that he has won, a deadlier breed appears. Hi-score, rankings, excellent graphics and sound.
NEW RELEASE



MR. WIZ £7.95
From the author of Percy Penguin, Mr. Wiz is a fast-action multi-scene game. Guide Mr. Wiz around the garden to eat the cherries whilst avoiding the evil gremlins. The gremlins can be killed by dropping apples on them or by throwing the crystal ball. Extra points can be gained by eating the magic mushroom, but beware... this is the home of the gremlins and makes them permanently furious! Sound effects and tunes, hi-score, rankings. Superb arcade-style action.
NEW RELEASE



CHES £7.95
A highly versatile implementation of Chess. Play black or white against the computer or a human opponent. The skill level of the computer's play can be varied widely, and moves are entered either by co-ordinates, cursor control, or joystick control. Moves can be taken back if an error has been made, and the board can be modified at any time. Games can be 'saved' or 'loaded', and the last game can be replayed. The computer will, if requested, suggest your moves.
NEW RELEASE



CENTIBUG £7.95
The centibug descends from the top of the screen weaving intimidatingly between the mushrooms. Your objective is to shoot all the segments of the centibug before it reaches the bottom of the screen. Features include: spiders, snails, flies, 6 skill levels, hi-score, rankings, and increasing difficulty.



ALIEN DROPOUT £7.95
A novel and unusual program. Arcade-action with this exciting multi-stage shooting game. The objective of the game is to shoot the aliens out of their 'boxes' before the 'boxes' fill up. Once full, the aliens fly down relentlessly, exploding as they hit the ground. The game features include: 6 skill levels, rankings, hi-score, increasing difficulty.



STRANDED £7.95
An adventure game using hi-resolution full-colour graphics. You are stranded on a strange planet, and your mission is to return to civilisation and home. Many of the locations are shown graphically, including the spaceship, the cliffs, the mountains, and (if you succeed) your home. You must carefully explore your environment searching for hidden clues to help you in your quest.
NEW RELEASE



WORLD GEOGRAPHY £7.95
This program covers 166 countries which are divided into 8 categories of difficulty. Each country is pinpointed on an accurate hi-resolution screen map of the world, and the user is asked the capital and/or population. At the end of the test, the percentage of correct answers is given, so that the student can monitor his geographical knowledge.

ALSO AVAILABLE:

INVADERS	£7.95	DISASSEMBLER	£7.95
FRUIT MACHINE	£7.95	DRAUGHTS	£6.95
CONSTELLATION	£7.95	REVERSI	£6.95

DEALERS - Our software is now available at all good dealers including: selected branches of W. H. Smith and Boots; all major computer dealers - Microstyle, Electronequip, 3D Computers, Computarama, GTM Computers, etc.; and our software is also available through all the major distributors, and directly from us.

WE PAY UP TO 20% ROYALTIES FOR HIGH QUALITY BBC MICRO AND ELECTRON PROGRAMS.



SUPERIOR SOFTWARE LTD.
Dept. AU8, Regent House,
Skinner Lane, Leeds 7
Tel: 0532 459453

OUR GUARANTEE

- (1) All our software is available before we advertise.
- (2) All our software is despatched within 48 hours by first-class post.
- (3) In the unlikely event that any of our software fails to load, return your cassette to us and we will immediately send a replacement.

LVL COMPUTERTOWN

Whether its your first computer or whether you're already an enthusiast, LVL COMPUTERTOWN offers you the quality of service you expect from experts. If you invest money, you go to a bank or a broker - a specialist who can guide and advise you on the best return for your capital. At LVL COMPUTERTOWN we're specialists too. We're there to help guide you through the micro maze, keep you up to date on innovations, help you get the best value for money, whether your computer is for you, your children or your business. Your computer can change your life - make sure you change it for the better: Come and talk to the experts and move into micros with LVL COMPUTERTOWN

JOYSTICKS



- 12 months guarantee
- Fully compatible with the BBC model 'B' or 'A' fitted with an A/D interface and an analogue port.
- Nylon encased-steel shafted joysticks with ball and socket joint
- Fast spring return to centre
- Graphite wiper linear potentiometers

British made and fully guaranteed, the LVL twin joysticks are professional units with which your aim should be nothing less than total control. They will operate any programmes that have a joystick option and are written in a way that is compatible with **ACORNSOFT**

£21.95

COMPUTERS

BBC MICROCOMPUTER




Model B	£399
Model B with ECONET	£446
Model B with DOS	£469
Model B with DOS & ECONET	£516



£199.00


The new personal computer from Acorn Computers. An ideal machine for learning computing — and for having a lot of fun at the same time. But it's much more than just a toy. It's graphic facilities are the most sophisticated available in it's price range.

PRINTERS



Epson RX80	£288.77
Seikosha GP100A	£238.05
Silver Reed EX500	
Parallel	£343.85

DISK DRIVES



An example of superior technology, total reliability and outstanding performance, combine to produce the LVL Disk Drive Family.

Truly professional units designed to work with the BBC Microcomputer.

CHECK OUT
NEW
PRICES WITH
YOUR NEAREST
DEALER.

DATA RECORDERS



A
REFLECTION
OF
SUPERIORITY


The Bell & Howell/LVL
Computer Compatible Data
Recorder

£39.95

- Automatic Level Control
- Automatic Tape Stop
- Tape Counter
- Remote Motor Control

SOFTWARE

At your local COMPUTERTOWN Dealer you'll find thousands of Titles for most popular home computers, offered at prices and skill levels to suit all your desires. To avoid disappointment please telephone your local stockist for a full availability and price list.



ALL PRICES
INCLUDE
VAT.

The items featured represent a very small selection from our vast product range, and at the time of going to press were all available from stock.

However, not all dealers carry every advertised item, please telephone before making your journey.

For further details, and full product literature pack call or telephone your nearest LVL Computertown Dealer.

CHESHIRE

C-TECH SOFTWARE
184, Market St.
HYDE
Cheshire
061 366 8223

CUMBRIA

• THE COMPUTER SHOP
56/58 Lowther St.
CARLISLE
Cumbria
0228 27710

ESSEX

A.C.L.
1, Northmall
GRAYS, ESSEX
0375 79834
BROADWAY MUSIC
AND VISION
Woodford Green
ESSEX
01 504 7500

GREATER MANCHESTER

• LOMAX
8, Exchange St.
St. Annes Square
MANCHESTER
061 832 6167

WORCS

SPURTREE COMPUTING
LTD.
Council Buildings,
Teme Street,
TENBURY WELLS,
Worcestershire
0584 811353/811304

MERSEYSIDE

• THORNGUARD
46, Penaby Rd.
HESWALL
The Wirral,
Merseyside
051 342 7516

NOTTS'

S P ELECTRONICS
48, Linby Rd.
HUCKNALL
Notts.
0602 640377

COMPUTERTOWN (UK) LTD.
230, Derby Rd,
STAPLEFORD
Notts.
0602 398484

OXFORD

ABSOLUTE SOUND
AND VIDEO (Oxford) Ltd
19, Old High St. Headington
OXFORD
0865 65961

AVON

K & K COMPUTERS
32, Alfred Street.
**WESTON
SUPERMARE**
Avon
0934 419324
COLSTON COMPUTER
CENTRE LTD.
The Colston Centre,
11, Colston Ave.
BRISTOL
0272 276619

YORKSHIRE

HOME & BUSINESS COMPUTERS
59, Daisy Hill
DEWSBURY
Yorks
0824 485300

BUCKS'

HI-VU ELECTRONICS
38, Church St. Wolverton
MILTON KEYNES
Bedford
0908 312808

SUSSEX

CJE MICROS
78, Brighton Rd
WORTHING
West Sussex
0903 213900

WEST MIDLANDS

JBC MICRO SERVICES
200 Earlsdon Ave.
Nth. Earlsdon
COVENTRY
0203 73813

WILTSHIRE

WILTSHIRE MICRO
CENTRE
Unit 6,
Central Trading Estate,
Signal Way,
Old Town,
SWINDON
0793 612299

ISLE OF WIGHT

EXCELL
4, Foreland Rd
BEMBRIDGE
Isle of Wight
098 387 2578

YOUR
LOCAL



DEALER

HEREFORD

KEMPSONS
26, St. Owen St.,
HEREFORD
0432 273480

KENT

KENT MICRO
57, Union St
MAIDSTONE
Kent
0622 52784

GRAVENSND
COMPUTERS
39, The Terrace,
GRAVESEND
0474 50677

LEICESTER

PERCY LORD & SON
63, Blaby Rd
WIGSTON
Leicester
0533 785033

LONDON

CANNONBURY RADIO
185 Upper St
ISLINGTON N1
London
01 226 9392

PAUL ELECTRICAL
250/2, Grand Drive,
Raynes Park,
LONDON SW20
01 542 6546

WOODS RADIO
257, Lavender Hill,
Battersea,
LONDON
01 228 1768

SALOP

MEDLICOTT BROS
53, Mardol
SHREWSBURY
Shropshire
0743 3060

NORTH LAND

NEWTONS
Main St,
SEAHOUSES
0665 720307

STAFFS

I W BAGNALL
18, Salter St
STAFFORD
0785 3420

SUFFOLK

S J EMERY & CO
10, Market Place,
BUNGAY,
Suffolk
0986 2141

SURREY

• HASLEMERE COMPS
25, Junction Place,
HASLEMERE
Surrey
0428 53850

P & H ELECTRONICS
5, The Parade,
Reading Road,
YATELEY
Surrey.
0252 - 877 222

LANCASHIRE

• P V MICROS
38A Water St
ACCRINGTON
Lancs
0254 36521

Home & Business
Computers Ltd.
54, Yorkshire Street,
OLDHAM
061 633 1608

Home & Business
Computers (RCH) Ltd.
73, Yorkshire Street,
ROCHDALE
0706 344654

WALES

S I R
91, Whitechurch Rd
Cyncoed
CARDIFF
Wales
0222 621813

THE COMPUTER SHOP
41, The Hayes,
CARDIFF,
Wales.
0222 26666

SCOTLAND

COMMSCOT
30 Gordon St.
GLASGOW
041 226 4878

SERIOUS DECISIONS NEED THE SUPPORT OF OUR 80 COLUMNS



Most serious users of micro computers require the facility to display in 80 columns, especially for word processing. Try this on most monitors and the result will be a frustratingly fuzzy image.

The Microvitec CUB 653 gives the user not only glowing colour, but also pin-sharp-images, thanks to a medium resolution screen 653 pixels wide by 585 high, plus a selective transmission

panel giving super-high contrast. These features make this model from the CUB range of monitors the perfect partner for the high resolutions generated by BBC B, SINCLAIR Q.L., I.B.M.,

MICROVITEC
cub
COLOUR DISPLAYS

ELECTRON, ORIC, APPLE II and Iie, and many others.

So if you wish to sharpen your image, whether in the office or at home, decide Microvitec:

Remember – the highest quality doesn't have to mean the highest cost.

Call at your local dealer or contact us direct and we'll send you full details with a pleasant surprise – our price list.



Microvitec PLC., Futures Way, Bolling Road, Bradford, West Yorkshire, BD4 7TU, England. Tel: (0274) 390011 Telex: 517717

Microvitec Monitors are available from your specialist local computer dealer, selected branches of W. H. Smith, John Lewis Partnership, Lasky's, John Menzies, Greens at Debenhams and other leading retailers.

CHASE DATA

PRICES SENSATION

Canon 110: Case/Cables all INCL £99

Canon 220: 400K (40/80 switching)

Case/Cables all INCL £169

N.B. These are state of the Art Disc Drives; Direct Drive
40 track 6mms Access/80 track 3ms Access.

DFS Kits available
ex stock
all inclusive price £109

SLIM CANON DISC DRIVES:

MODEL:	SPECIFICATION OF EACH DRIVE
110	S/SIDED 40 TRACK 100K
210	D/SIDED 40 TRACK 200K
220	D/SIDED 80 TRACK 400K (40/80 TRACK SWITCHING)

■ All **CANON** 40/80 switchable disc drives feature an on-board dual-colour LED on the front panel to show track mode selected. This is coupled with our own unique two-stage illumination, to give a clear operating status, as follows:

40 TRACK MODE: _____ LED GREEN

80 TRACK MODE: _____ LED RED

POWER ON: _____ HALF-ILLUMINATION (GREEN OR RED)

DRIVE SELECTED _____ FULL-ILLUMINATION (GREEN OR RED)

■ Super-slim **CANON** drives, models 211 and 221 and the **SANYO** model 548S, are available with their own **custom-built secondary switching power supply**. This is safe, low in heat generation and excellent value for money.

■ The **SANYO** disc drive is our latest acquisition in quality Japanese products. This is a "half-height" unit of standard dimensions.

LTD DISC DRIVES

**FOR THE
BBC
MICRO**

SLIM SANYO DISC DRIVES:

MODEL: SPECIFICATION OF EACH DRIVE
548S S/SIDED 40 TRACK 100K

SUPER-SLIM CANON DISC DRIVES:

MODEL: SPECIFICATION OF EACH DRIVE
211 D/SIDED 40 TRACK 200K
221 D/SIDED 80 TRACK 400K
(40/80 TRACK SWITCHING)

All inclusive price list:

This means: disc drive + case + all power & data cables + U.K. carriage + utilities disc & manual + V.A.T.

MODEL:	CANON					SANYO
	110	210	220	211	221	548S
Formatted Capacity per drive on BBC Micro:	100k	200k	400k	200k	400k	100k
Single Drive & Case:	£99	£139	£169	£179	£236	£154
Single Drive & Case/P. Supply:	£124	£164	£194	£209	£266	£184
Dual Drive & Case:	£204	£274	£314	£329	£437	£284
Dual Drive & Case/P. Supply:	£229	£299	£339	£359	£467	£314

Support:

Warranty: All disc drives sold by Chase Data Ltd. come with a full one-year warranty on parts & labour.

Non-warranty service: As THE experts in our field we can offer service on most makes of floppy disc drive.

Recalibration & Alignment ... £25 per unit inc. VAT. (parts extra). Phone for details: (Tel: 0784 38487)

Payment



By Post: Send your remittance (cheques only please) with your order to:

CHASE DATA LTD


P.O. Box 6, Woking, Surrey, GU21 4PB.

By Phone:  (Tel: 0784 38487).

Draw with the BBC micro and show the true potential of your machine

Fill shapes in one of 23 colours (Mode I)
 Draw points, lines, rectangles ellipses and circles
 Smooth curves
 Wire frame diagrams
 Hidden line removal
 Draw in perspective
 Measure scaled distances
 Ekta sketch lines, Half tone facility
 Mirror images
 Repeat images, SS, enlarged, reduced, stretched
 Actual colour displayed
 Store up to 10 ellipses or circles in memory
 Redraw any one of these at cursor position
 Change any actual colour for one of 8 others
 Clear screen, load screen, save screen
 Print characters or numbers at any pixel point
 Error messages for incorrect input
 Fully comprehensive manual

35¢ 496 • □ ••• 3



This programme has been purpose designed by professional Graphic Designers for simplicity and ease of use, and is undoubtedly the most versatile drawing programme on the market at this time. There is no need to input any numerical data, as all judgements are made visually. The BBC Micro is the finest drawing machine in its price range. Find out what it can do.

The A. B. Designs drawing programme costs only £36 for over 70 functions (model B). New AB2 Program, available on disc (price £61) and cassette (price £51). When ordering send Cheque/PO and VAT at 15%. Please include phone no. with all correspondence. For further information send SAE and phone no. to A. B. Designs, 81 Sutton Common Road, Sutton, Surrey. 01.644 6643 (closed all day Thursday).

HARRIS McCUTCHEON SYSTEMS

are pleased to release

HMS HOME ACCOUNTS.....	£28.75
HMS VAT TRADER'S LEDGER.....	£21.50
HMS BASIC ENVIRONMENT.....	£14.50

to BBC Microcomputer users with a minimum configuration of 1 x 40 track single sided disc and an 8" 132 column (condensed mode) printer, to a maximum configuration of 2 x 80 track double sided disc and a 15" printer. The programs allow user allocation of each file between *DRIVE0, 1, 2 or 3, thus making full use of the disc space available. HMS HOME ACCOUNTS allows all financial transactions within a defined environment to be recorded, printed and analysed. Accounts may be reconciled with statements or passbooks, uncleared entries being highlighted. Depending on the analysis structure you choose, the system can keep track of anything from answering "how much is in the piggybank?" to independent tracking of multiple bank accounts, credit cards, building society accounts and cash in hand. The only reason for keeping home accounts in any form is to have your current financial state apparent on demand and reconcile statements received in order to find out where the money goes. This program is designed expressly for these requirements. You wouldn't keep them if these areas were of no concern, and being of concern you want to keep them thoroughly and effectively. HMS HOME ACCOUNTS allows this.

HMS VAT TRADER'S LEDGER, on the other hand, fulfills a different requirement. Instead of emphasizing analysis, the VAT trader wants to record all his invoices and bills in the least time possible consistent with making out the quarterly VAT return and getting a well-presented ledger listing on demand. Varying and multiple VAT rates are of course catered for. Add the facility to maintain period totals on user-defined bases other than VAT quarters (such as weekly, monthly and to the end of each trading account), and HMS VAT TRADER'S LEDGER should be a boon to you as a sole trader through to the low transaction company.

Both systems allow for 1000 to 10000 records per file depending on configuration and use, and initialise on shift-BREAK without user OS intervention. Fully documented source listings and optional user-modifiable VIEW text operating documentation are included on the master disc, and hard copy manuals are provided.

HMS BASIC ENVIRONMENT is specifically an aid to BASIC program development designed to encourage the creation of well-structured readable code in circumstances where memory becomes a constraint. Procedures to handlescreen I/O, cursor switching, CLI invocation, and keyboard validation are provided, with a linking BASIC source file compressor which includes variable name compression to two bytes. The ability to link as many BASIC source modules as desired into a single condensed running version resolves the coder's conflict between space and intelligibility; 60% compression is effected on our sources for the above accounts packages.

The disc, manual and information contained are sold under license subject to the condition that they are for single user single site application by or on behalf of the purchaser, are not for resale in whole or in part either as originals or copies, and may not be supplied to a third party as part of a package or used as part of a package supplied by a third party to the purchaser, without the written consent of the copyright holders. Damages will be claimed where this occurs, with revocation of license. Purchase indicates acceptance of license terms.

I enclose £.....for the following products (tick and delete where appropriate)

HMS HOME ACCOUNTS (£28.75).....
 HMS VAT TRADER'S LEDGER (£21.50).....
 HMS BASIC ENVIRONMENT (£14.50).....

VAT, disc, manual, post and packing inclusive.

The credit card companies 4% take precludes our offering their service.

Please supply on 40/80 track disc. I have VIEW/WORDWISE; OS 1.0/1.2; BASIC I/II

Name.....

Address.....

Postcode.....

Telephone..... Date.....

Please send with cheque or postal order to: Harris McCutcheon Systems, 40 Huntingdon Street, London N1 1HM (01 609 3207)

A STAR IS BORN



COMMSTAR

TOOLSTAR

PRESTEL, MICRONET, BBC to BBC file transfer, Terminal Emulation.

Commstar is unique and complete, a total solution. Imagine, a single Eprom-based package of sophisticated communications software that caters for all your requirements.

Imagine Commstar

Take for example British Telecom's Prestel service offering access to a multitude of up-to-the-minute information pages, world news or weather and much more. Instant access to Micronet 800 with many free programs that can be downloaded in seconds, free advice and news. Expand your horizons and find out just how versatile our computer can really be!

How many times have you wanted to get a copy of a program to a friend or a business colleague, quickly? With Commstar you can transfer a file of ANY type, between two BBC's (which may be thousands of miles apart), in the space of a phone call.

It really is that simple!

Commstar is 'intelligent'. It offers many advanced features to ensure simple and effective communication with the remote system.

Consider the following features:

Prestel Mode

Prestel mode features full colour Prestel graphics including double height and flashing characters. Full Telesoftware capability is offered allowing the many free programs offered by Micronet 800 to be downloaded into your computer. Pages of particular interest may be 'marked' for later retrieval and display. Page images may be copied and saved to a file on the current filing system.

Terminal Mode

In terminal mode all input may be copied into a buffer in memory or spooled directly on to disc. Full control over buffered data is provided allowing it to be listed to screen or printer, sent to the RS423, saved to or loaded from the current filing system (including TAPE).

Commstar allows full configuration and easy control over the protocols used. Send and receive baud rates, word length, parity and number of stop bits are selected from a simple table of options.

When in chat mode (80 or 40 column), characters transmitted by the host will be displayed on the BBC screen and characters typed on the BBC will be sent to the host.

Commstar allows ANY type of file (not just ASCII) to be transferred 'safely' using XMODEM protocols. In fact, four individual methods of transmission are provided for within Commstar giving great flexibility.

Using a disk based 'emulation file' Commstar can be configured to emulate virtually any terminal type including VT100, within the capabilities of the BBC.

In addition to the above, most MOS commands can be executed from within Commstar, errors are trapped by Commstar's own error handling routines and an optional elapsed time clock may be displayed. Data filter, Local Echo, Auto-line-feed, printer on/off and XON/XOFF protocols may be toggled in or out by a single key press, extensive use being made of the function keys.

Finally, Commstar may be fitted into any of the sideways ROM sockets and is provided with a comprehensive manual.

£34 inc. VAT & Carriage.

A revolutionary new approach to program development aids.

Toolstar is a powerful new utility Rom that will open up a whole new world for BBC micro users. Toolstar adopts a revolutionary new approach to program development aids. It has been designed specifically to assist both Basic and Machine code programmers by providing an integrated set of powerful building blocks which rapidly become an indispensable complement to the built in facilities of your BBC micro.

This package contains the Toolstar firmware in Eprom and a very comprehensive manual (over 150 pages), containing many examples and illustrations to help you make the best use of Toolstar's exciting capabilities.

Toolstar sheds new light on your BBC micro

Toolstar, being Eprom-based will be permanently resident in your computer allowing all of its commands to be immediately available. It is 'transparent' to both the user and the operating system; once a command has been executed, control is returned to Basic, or whichever ROM had control prior to the command.

Full error handling has been incorporated and for new users there are full help menus describing each command and its syntax.

Powerful building blocks for Basic programmers?

Within Toolstar there are 22 commands, 8 of which operate between PAGE and TOP i.e. on the current Basic program or Basic programming environment. These commands obey standard Basic command syntax rules.

Reveal the deepest secrets of your discs

Toolstar allows the operations of Formatting, Verifying, reading or writing a disc sector to be carried out very simply from Basic i.e. all the necessary building blocks required to develop a comprehensive set of disc utilities, simply and effectively.

Lost your memory? - No more amnesia with Toolstar!

In addition to the commands described above there are 9 commands which operate on the whole of the BBC's memory and are designed to complement the BBC's built-in assembler. These include a full feature disassembler and memory dump, each with forward and reverse scrolling.

If this is not enough Toolstar can be Extended!

There are three help menus on Toolstar which may be obtained by typing HELP TOOLS, 'HELP MCODE or 'HELP EXTEND. The third option menu will initially display the following:

'HELP EXTEND
EXTEND - RAM address >>
i.e. typing 'EXTEND <address> will allow the user to extend the facilities of Toolstar with routines which are supplied by himself. The manual describes fully how this operation is carried out and illustrates it with several examples.

In the future such utilities will be made available on disc and cassette from Pace, thus allowing a comprehensive library of utility programs to be built-up.

£34.00 inc. VAT & Carriage.

**Access and Barclaycard
Dealer Enquiries welcome**

Send for more information to:



**92, New Cross Street,
Bradford BD5 8BS.
Telephone: 0274 729306
Telex: 51564**

TEACHING TODDLERS



104 Fun and learning for children as young as two with programs and micro overlays from Joe Telford

THE ideas and programs in this month's Jottings form an activity pack aimed at the youngest users. Toddlers, children in nursery or early primary classes should all be entranced, and six-year-olds too might find it interesting though many will already have keyboard skills in excess of this pack. The programs aim to get young infants playing with the computer, and give parents or teachers the chance to introduce and talk about the computer and related activities. Children will be introduced to basic concepts in shape, sound, pattern and colour, which, combined with discussion and guidance from adults, help develop reasoning skills.

The ideal way to use the pack is to allow children to work in small groups and explore each application—far better than a silent single child sitting in front of a computer. If a one-to-one situation does occur, the parent or teacher should spend time with the child, talking with and listening to that child's ideas and thoughts. This is where the value of this activity pack lies.

The programs are based around a number of activities, forming a larger program called *Yumap* (youngest user's micro activity pack). Although each section can be used by children, selection is best done by an adult, as an amount of reading is required. On chaining *Yumap* a menu page is shown which offers the choices:

1. Character patterns
2. Drawing shapes
3. Shape game
4. Drawing sound
5. Sketchpad
6. End program


Each section is described on pages 107 and 108, while the overlays for each are printed opposite and overleaf. The listings are on yellow pages xi-xiv, and on our listings cassette (see page 82).

Keys and colour

Whenever the break key is pressed the program ends, restarts, finds the correct section and returns to it. All that appears to have happened is that the screen has cleared. You might like to use this 'clear screen' facility by marking where the break key is found on each overlay.

The escape key has been reconfigured to act only when CTRL and @ are pressed together. This returns the program to the selection menu, and is sufficiently well hidden to prevent children from accidentally causing such an event.

In the three sections with coloured



crayon symbols, the current colour is indicated by a band at the top of the screen. If this band is not visible (in choices 2 and 5), the colour used is the background colour and rubbing out will take place.

Fitting the overlays

Each overlay can be coloured and

laminated or covered with transparent adhesive plastic to make it last. Before fitting an overlay, make a firm crease along the dotted line so that a strip of about one inch of overlay is folded downwards. Next fit the top strip of the overlay (containing its title) under the clear plastic function key holding band and adjust it to cover most of the keyboard. The part of the overlay already folded will now fall close to the front casing of the micro. Fit a large elastic band around the micro and trap this flap under it. The overlay should now be secure and ready for use.


Although any area of any panel can be used, it is best to actually press a figure as these are generally most central. An adult may need only one finger but small hands can also do the job.

Inside the program

Figure 1 shows the main sections of the program, and the table of frequently used pro-cedures shows these are split into two. The first group consists of graphics pro-cedures for drawing triangles, rectangles and circles (see past Jottings). The second group includes two utilities, one for drawing a cross in the inverse screen colour and the second to make the areas of the keyboard match the areas of the overlays.

In the PROCsetup pro-cedure one task is to allocate characters to a string array. Whenever the keyboard is pressed a character will be generated and placed into A\$ at line 1590. A\$ is then compared using INSTR\$(A\$, 'Key\$(' and, depending on where it is found, a number is returned to the calling routine. This number is 0 if a key below the leftmost panel is pressed, 1 is generated by the next panel, 2 by the next, 3 by the rightmost panel and 4 by the space bar (colour panel). *page 108*►



DRAW SOUND - NOTE PLAYER



Cut out this full-size keyboard overlay and use as guide for other shown reduced overlay!

CHARACTER PATTERNS

106



- Stick to front of micro
- Covers space bar
- Fold over front edge of micro
- Main area fits over keys
- Slip under BBC's plastic strip or stick to Electron

Overleaf is a full-size overlay to use as a guide to making up the other four on this page: a great chance to get the felt pens out! Your child might like to use pictures of herself/himself on the overlays

SKETCH

DRAWING SHAPES

SHAPE GAME

1 Character patterns

On typing the number 1, a message appears which instructs the adult to attach a keyboard overlay to the computer (see instructions at the end of this article). In this case, the overlay to use is the one marked *Character patterns*, which contains pictures of four children in panels, plus drawings of three coloured pencils. Once fitted, a panel of the overlay can be pressed to start the character pattern section.

The screen now obeys the instructions given by pressing any of the panels. When the panel of the child walking upstairs is pressed, the pattern on the screen will move forward through a pattern sequence. This

sequence used consists of 123 items, including upper and lower case alphabets, numbers and graphic characters. After the last character the sequence will restart.

If the 'child walking downstairs' is pressed the characters will be displayed in reverse sequence. If the 'jumping child' is pressed, characters are displayed in random order, while the 'standing child' maintains the currently displayed character. At the beginning, the first character displayed (by pressing 'child standing') will be 'A'.

The colour of the characters is yellow at first, but pressing the fifth

panel showing the coloured pencils steps through yellow, white and red, then back to yellow.

The children can use this section to explore the relations between patterns, and parts of patterns, and to stimulate discussion about their findings. They will see discrete shapes, patterns formed by repetition of these shapes, and patterns which seem to merge together. Talk to them about heart or rocket shapes, stripey patterns and rows, lines or boxes. Children can then move on to practical pattern activities such as drawing, colouring, painting, sticking, mosaic-work or even potato printing.

2 Drawing shapes

On typing the number 2 at the menu, a message appears which asks the user to enter a delay time (between one and nine seconds) for the children using the program. To start, set it to nine seconds, then reduce it as the children get quicker. Next, a message instructs the adult to attach the overlay marked *Drawing shapes* which has four shapes in panels, plus four coloured pencils.

The start screen is blue and then a small cross appears, to the sound of a beep. This will move every nine seconds (or as per your setting), beeping as it does so. Children will

need to follow the cross, because that's where all the action occurs. Pressing any panel produces a shape of random size in the current crayon colour, and its position will be indicated by the cross on the screen. The four shapes are circle, square, oblong and triangle. The initial shape colour is yellow, but pressing the crayon panel steps the colours through yellow, white, blue (which rubs out) and red, then back to yellow. Shapes may be drawn on top of each other in any colour, though the cross and shape size move at random.

The shapes panel lets children

investigate and explore positioning and overlaying shapes, as well as the shapes themselves. Language is developed as the children describe what they have done and what they are about to do. Problems can be set, ranging from a simple 'Can you show me a circle?' to a more complex 'Can you put a red triangle between those two circles?' Matching exercises can also be performed, such as 'I have put three red circles on the screen. Can you show me the same number of yellow circles?' Children can develop other shape ideas, with or without the micro, using cut-outs and cards.

3 Shape game

Typing the number 3 at the menu results in a message to attach the keyboard overlay marked *Shape game*. Pressing any of the four shapes in panels starts the game. The screen clears to a purple background with a shape in the centre. This shape will have a random size, and the aim of the game is to make it vanish. This can only be done by the child recognising the shape and pressing the matching shape on the keyboard

overlay. If the wrong one is pressed, a hissing noise is heard, while a correct match gives a buzzing sound and the shape vanishes. Another shape takes its place and the game continues.

In this section variation in size adds to the interest, because the children have to realise (for example) that a square is a square no matter what size it takes. The random colour of any shape emphasises the fact that colour is not an attribute of any one

shape. Children might learn to recognise the simple shapes using this section, but without discussion and further practical work they will be learning without understanding. Follow-on work is closely related to that from the last section, though it would be particularly useful to allow the children to experiment: 'Can you make that oblong stand on end? It didn't when we used the computer. Is it still an oblong?'

4 Draw sound

Menu option 4 asks for the overlay marked *Draw sound-note player*. This has four human figures in panels, pressing any one starts the section and the screen turns blue and rectangles can be painted on the screen, each given a random colour. The height position of each rectangle on the screen indicates its pitch in a range of just over one octave. Adjacent rectangles are a semitone apart. Control over the sounds generated is by pressing a panel. The first panel shows a man walking upstairs and pressing this makes the note played go one semitone higher. After the

highest note the sequence will restart from the lowest note. The 'Man walking downstairs' plays the note one semitone lower. After the lowest note the sequence will restart from the highest note. If you press the jumping man, notes will play at random, and the man standing repeats the note played at the same pitch.

Whenever the screen is filled, it will automatically clear and the next note played will be displayed at the left of the screen, at the selected pitch.

The children can use this section to investigate informally the relationships between musical sounds. Much

adult input is needed because words like Up and Down, High and Low, Same or Different may all be introduced. Children can be set musical tasks, or be asked to set each other simple problems. For example 'Can you make the man walk upstairs?' or 'Can you make the sound go up three stairs then down 4?' or 'Can you make the sound of a police car?' Conventional musical instruments such as xylophones can take the explorations further, eg. 'Can you find that note on the xylophone?' Parents will soon find that many young infants do not find such tasks easy.

5 Sketch

On typing the number 5, a message appears which instructs the adult to attach the overlay marked *Sketch* which shows four pencils in different orientations, each in a single panel, and four crayons together in one panel. Press any panel to start and the screen clears to red with a cross in the

centre. This cross can be moved up, down, left and right by pressing the appropriate pencil. As the cross moves it leaves a line behind it in the current crayon colour. Pressing the colour panel changes the initial yellow through white, blue, red (for rubbing out) and back to yellow. This

section has an auto-repeat that allows the pencil to draw as long as a panel is held down.

The sketch routine gives children the chance to draw perfectly straight lines, and to build up shapes. Children can be asked to make bricks, boxes, nets, mazes and many other objects.

◀page 104

If none of these panels is pressed - 1 is returned.

The aim of PROCerror is to display any error in program execution. If the relocated escape key is pressed this procedure forces a reRUN.

PROCsetup does several house-keeping tasks. It sets up the function keys, the sections of the keyboard, the cursor keys, the initial 'crayon' colour, the relocation of the escape key, and a number of defined graphics used in PROCpattern.

The function FNmenu handles selection of any one of the five different sections available. It prints a menu, asks for input, then returns to the main body of the program with the number of the routine to call. PROCcsr turns the text cursor on and off. PROCend resets the cursor keys, and ends. After using this option to exit, function keys, etc, can be cleared by pressing the CTRL and BREAK keys together (CTRL-BREAK).

PROCpattern exists between lines 600 and 740. Input from the keyboard increments, decrements or randomises a pointer which indicates the ASCII value of current character to be displayed. The pattern is displayed by line 720. Once entered the procedure repeats until ESCAPE or CTRL-BREAK is hit.

PROCshape is found between lines 440 and 590. It draws a cross on the screen by referencing PROCcsr, then examines the keyboard for characters pressed. If none is pressed in the time limit set at line 490, the cross is moved at random and the process repeats. If, however, a panel is pressed, action is taken by calling one of the graphics procedures, or by incrementing the drawing colour.

In line 980 of PROCshapegame, a shape is chosen at random and the choice routine from line 990 to 1020 draws the shape which mates the random number chosen. The procedure then loops until a keyboard panel is pressed at line 1050 and either hisses if the shape is incorrect (line 1060) or exits the loop (line 1070), buzzes and restarts the procedure (lines 1080, 1090).

PROCdrawsound is similar to PROCpattern in that an index (the variable 'note') to a particular note is incre-

mented, decremented or randomised, then that note is played using the index as the basis of a simple formula (line 880). In line 900 another formula uses this index to position a rectangle on the screen to match the pitch of the note.

PROCsketch is found between lines 280 and 410. PROCcsr is continually called upon to draw a cross on the screen. If any of the overlay panels are pressed, this is detected by FNkey and the IF... THEN statements between lines 350 and 390 take appropriate action. This procedure is in effect an infinite loop, from which return is only via the CTRL-@ relocated escape key.


Difficulties brought about by tiny fingers locating the break key can cause concern at first, but provided (as in this application) the stage of the section in use is not important, the problem is reduced to simply working out which section to restart. The approach taken here would not be able to maintain variables, or other data, and hence is only one step better than the well-known *KEY10 OLD!MRUN!M technique. Line 40 contains the key to the solution. If the

program is run, as it will be at first, K% is set at - 1 and the break is set as:

```
*KEY 10 OLD!MGOTO50!M
```

with apologies to purists for the GOTO (I haven't had a good GOTO in ages).

This means that when BREAK is pressed the program restarts from line 50, hence W% and K% are not initialised. W% is simply the delay in seconds used in the drawshapes procedure, K%, however, is a pointer to the section of the program currently in use. If it is set to - 1 the menu is accessed (line 80), otherwise the contents of K% are used to set the variable 'choice' which then selects the section to be executed. When a menu is called, the fact that 'choice' contains something other than 0 indicates that K% must be set to this value, and this is done at line 100. The result is simply that on running or using escape (CTRL-@) to rerun, the menu is invoked. Pressing the break key causes the program to skip the menu and use the section indicated by K%. The effect, to the user, is simply of the screen clearing.



M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R



GET ON THE RIGHT TRACK WITH MICRO POWER



Micro Power are an official service and information centre, and we are major suppliers to Government and educational establishments. We stock the complete range of Acornsoft and Micro Power software as well as a wide range of B.B.C. Micro and general computing books. Our expert staff are always on hand to provide advice and assistance in the relaxed atmosphere of our showroom.

COMPUTERS

MIDSUMMER SPECIAL

- B.B.C. Micro + Cassette Recorder AND Five Micro Power or selected Acornsoft Tapes 399.00
- B.B.C. Model B plus DFS + 4 tapes 469.00
- B.B.C. Model B plus Econet + 4 tapes ... 446.00
- B.B.C. Model B plus DFS and Econet 516.00
- Acorn Electron + Cassette Recorder OR Five Micro Power Tapes 199.00

MONITORS

- Kaga 12" Green Screen 123.05
- Ferguson TX Monitor/TV 335.95
- Sanyo DM2112 12" Green Screen 74.95
- Microvitec 14" RGB/PAL and audio output 258.75
- Microvitec monitor (plastic) 286.85
- Microvitec monitor (metal) 228.85
- Plinth for above 5.75

DISK DRIVES

- Pace 40 track 100K 156.40
- Pace 40 track double sided 200K 220.80
- Pace 40/80 track double sided 200/400K 241.50
- Pace 40 track double drive 200K 310.05
- Pace 40 track double sided double drive 400K 434.70
- Mitsubishi 40/80 track double sided double drive 400/800K 567.85
- orch Z80 Disk Pack 80 track double sided double drive (including Perfect software) 803.85
- .MS HFD 3055 3" 100K 199.00

PRINTERS


- Epson FX80 425.95
- Epson RX80 F/T 293.95
- Brother HR15 Daisywheel 436.70
- Smith Corona TP-I daisywheel 270.20
- MCP 40 4-colour printer/plotter 129.95

ACCESSORIES

- Elftone Digicorder (including leads) 25.95
- Acorn BBC cassette recorders (inc. leads) 35.00
- Scotch D/S D/D Disks (Box of 10) 32.50
- Disk storage cases 19.95
- Vinyl dust covers for computers, disk drives, monitors and printers 4.50
- Sureshot self centering arcade joystick 18.22
- Sureshot self centering double joysticks ... 34.44
- Acorn joysticks 19.00
- System Sac 19.95
- Printer cables (parallel or serial) 15.50
- Stack light pen 28.75
- Speech synthesiser plus cartridge socket (Free 1.2 if required) 55.00
- Acorn Disk interface (Free 1.2 ROM if req.) 97.00
- Pace disk interface kit 95.00
- 1.2 ROM upgrade 11.50
- Econet (Free 1.2 ROM if req.) 70.00
- Teletext adaptor (Free 1.2 ROM if req.) 225.00
- Wordwise wordprocessor 45.42
- Auto Prommers Eprom Programmer 138.00
- Tutor Mate shelves 10.50
- 3M unlabelled Disks (Ten) 15.00
- Maxell 3" disk 4.95
- First Byte Electron joystick interface (inc. cassette) 24.95
- Micro Power potentiometer joystick 12.95
- Micro Power double joysticks 18.95

ALL PRICES INCLUSIVE OF V.A.T.
We provide free fitting for all firmware.

ALL ROADS LEAD TO MICRO POWER!



*HP facilities available. Please contact us for further details.

*Free parking. All prices correct at time of going to press.



Showroom: MICRO POWER LTD., Northwood House, North Street, Leeds LS7 2AA; Tel: (0532) 458800

Mail Order: MICRO POWER LTD., Sheepscair House, 15, Sheepscair Street South, Leeds LS7 1AD; Tel: (0532) 436300

Send an SAE for our complete listing of hardware, software and books.

SPECIALISTS IN ECONET

CARRIAGE FREE for ALL hardware
Books and software only 55p per order
U.K. Mainland Only

M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R

B-BASE: £25—8 Great Features

WHAT IS A DATABASE?

It is a FILE which contains RECORDS. Records consist of a number of FIELDS containing the information—an analogy can be drawn with a card index in which a box of cards is the file. Each card is a record and each line on the card is a field.

SPECIFICATION

- 1) Random Access—disc based, single or dual drives
- 2) File Size—99K (40 track), 199K (80 track)—65,000 + records
- 3) Record Size—up to 2048 characters and 200 fields
- 4) Field Size—up to 254 characters with complete line scanning
- 5) Access any record using Primary Key in 2 seconds
- 6) Holds—1200 NAMES AND ADDRESS records on 100K disk
- 7) Search—500 records on 5 fields in 60 seconds
- 8) Sort—500 records on 3 fields in 60 seconds

SYSTEM FEATURES

SEARCH PARAMETERS = , < , > , > = , < = , < > , INSTR

CALCULATE—Global or local totals and functions using any valid BBC expression

POWERFUL PRINTOUT OPTION—Eliminates need for separate mailing program, Parallel/Serial Printout allows setting of printer control codes, line spacing, tabulation, Headings etc, plus label printing with horizontal and vertical tab control.

REDEFINE—Titles, field widths, number of fields etc.

TRANSFER—Records from one file to another

SEARCH LISTS—Allow creation of sub-Databases within main Database but without having to save data again.

DATE FORMATS—6 formats for printout

All timings and sizes are relative to ACORN DFS. Compatible with ACORN DFS, WATFORD 1.3 and latest AMCOM DFS.

All Disc Software now available on 3" disc—add £3 to printed prices

Send S.A.E. for detailed data sheet

REPLICA II: £12.00.

The original REPLICA set a very high standard so the specification we set our chief programmer included some impossible features. In fact ACORN state that some of the things that we have done are impossible, it just took us longer that's all. REPLICA II transfers most cassette based programs to disk, even more than REPLICA. When you buy disk drives you do not have to throw away expensive cassette based programs.

REPLICA II transfers 'LOCKED' programs, programs loading as files, programs that load below &E00, those with up to 6 sections and those up to &6E in length eg adventure programs. No waiting for 6 minutes whilst adventure programs load.

REPLICA II is very easy to use. The user enters a name, how many sections and whether CHAIN*, RUN or* LOAD to load the first section. Press play and let the program do the rest, even a menu. Think how much it will cost you to buy just 1 disk version of your favourite program—REPLICA II which will hold up to 16 programs, limited only by the disc capacity.

CLARES NO1 IN UTILITY SOFTWARE!

BEEBSYNTH: disk £11.00 cassette £8.00

A very powerful, easy to use sound generating program for expert and novice. Up to 16 envelopes can be defined and saved. The envelope definer is easy to use, control is through the cursor keys and the effects of changes can be heard immediately. When you have defined your envelopes press 'K' for Keyboard and the keyboard is transformed into a musical instrument, but you control which instrument. Plays chords, not just single notes, change pitch and duration etc. A superb program that you can use immediately. Unlimited sounds at your disposal. Recommended by MICRO USER, PCN, HCW etc.

GRAFKEY/GRAFDISK: disk £12.95 cassette £9.00

The 'GRAF' series of programs are, to our knowledge, the cheapest entry to the CAD (Computer Aided Design) field on the BBC micro. Input is either joystick or keyboard. All graphics modes can be used and altered whilst running, the functions provided are: Line, rectangle, triangle, circle, text (upper and lower case), paint and colour pallet (8 colours and flashing). Drawing aids include:

Alignment grid, circle copy, delete, free memory, purge memory, variable cursor speed, clear screen and redraw. Save drawings to tape in about 20 seconds or to disk in about 2 seconds.

Rubber Band is a very flexible line drawing facility. Pictures can be saved and included in your own programs, very easily. GRAFDISK also provides a screen save facility. Recommended by BBC MICRO USER, PCN, ELECTRONICS & COMPUTING, LASERBUG etc, used by universities, colleges and business, as well as the enthusiast.

SINGLE KEY: (requires 1.2 0.S) £5.00

SINGLE KEY ENTRY provides the user with single key entry of all 66 keywords on the BBC micro. Speeds up your program input, it's just like having 66 function keys and it only occupies 256 bytes. Compatible with BASIC 1 & Basic 2.

VIEWpoint: £12.00

VIEW PRINTER DRIVER FOR EPSON FX80 Multi-page drive with print menu allowing the setting of global (document wide) printer functions at printer initialisation.

1) Multiple choice of highlight options including underline, italics, bold, enlarged,

proportional, condensed, superscript, subscript.

2) Choice of any one of the nine language character sets held in the printer ROM.

3) Choice of PICA or ELITE type face.

4) Print intensity: normal or dark.

5) Single sheet or continuous printing.

6) Slow (accurate line feed) or fast print speed.

7) Choice of "PAD character. Selection of " " as the PAD character switches off the backslash trap to allow full implementation of the foreign language character sets.

User Defined Character Definition

The print menu program also contains a sophisticated character generator which allows the construction of 95 user defined characters which are then accessible from VIEW via a highlight option. The characters are displayed in an 8x11 grid and can be printed (singly or as a set), stored, examined or changed at will.

Supplied on disc with comprehensive user manual.

THE NO1

All prices inclusive of VAT & Carriage—NO EXTRAS!

We're not short of Utility Software.

Clares
MICRO SUPPLIES

Dept AU8
98 Middlewich Rd.,
Northwich, Cheshire CW9 7DA
Tel: 0606 48511
Open 9—5pm Monday—Friday



Clares
UTILITY SOFTWARE



TIME FOR MICROS

Susan Kingsbury's activity board project brings day-trip fun to using the computer in class

PARENTS and teachers who have recently gained access to a BBC micro will no doubt be looking for imaginative ideas for its use. *Acorn User's* DIY activity board is a simple but effective device which, in conjunction with the computer, can be used in a variety of ways to foster both creativity and learning. Ideas for its use can come as readily from the children as from the teacher.

This article presents a program (listing 1, page XV) to operate with the board that, after typing into the computer and saving on tape, can be adapted by changing the data lines at the end.

The activity board can be built for a mere £12 or so. It is a simple structure consisting of a sheet of perspex (or, cheaper, hardboard or plywood) supported on four cottonreels. Underneath are switches wired to the BBC micro and these are activated individually by moving a magnetised object across the board. This simple arrangement is the




Figure 1. Dry-reed relay switch

stage on which a variety of scenes can be enacted, with questions and prompts being channelled through the micro and displayed on its screen.

Imagine, for example, that on top of the board is placed a sheet of paper showing a groundplan of a zoo (see page 114). Mapped out are eight attractions such as a bear pit, a lion's cage

and so on for which toy animals are used. A small wooden toy, which we'll call Fred, with a magnet set into his underside, is moved around the zoo, stopping at places that take his interest. Each time he stops, an appropriate sentence, in double-height letters, appears on the screen. When Fred has seen all he wants to see, the pupil types P on the computer and the whole story of Fred's day at the zoo is displayed on the screen. If you have a printer, the story may be printed out at this stage too.

Fred is taken on his tour by a child, who is encouraged to read each new sentence as it appears. By the end the pupil will have written a story just by moving Fred around. In this way, the board could help to teach reading or provide incentive for slow readers.

Once everyone in the class is familiar with the idea, the pupils could devise their own scenario, such as a moon-landing or a race-track, draw the groundplan, make models for the stopping places and change the data lines at the end of the program to give appropriate sentences. Thus they could all be involved over a period of time.

In more detail, this is how the board functions. On the underside there's a reed switch (figure 1) at each stopping place. The reed becomes magnetised when Fred's magnet is positioned above it, the two halves of the reed attracting each other and the switch closing. When Fred moves away, the springiness of the reed opens the switch (figure 2).

Soldered to the ends of the reed switches are wires which make up a cable connected to the BBC machine's user port. When a switch closes, a signal is sent along the cable to the computer and, under the control of the program, the appropriate sentence appears on its screen.

Making the board

You'll need eight dry-reed relay switches (see panel). Look at one of them from the side so that you can see the gap between the halves of the reed. Bring a magnet near to the switch and watch it close. You will hear a click as it does so, and another as it opens when the magnet is moved away.

Taking care not to break the glass at the ends of the switch, bend the wire at its ends to form legs at right angles to the switch (figure 3). Repeat this for all switches, then space them out on the underside of the board and tape them in position with the legs sticking out. You can glue them later.




Figure 2. The magnet closes the switch as it passes overhead

The board is linked to the micro via a user port connector and a yard of ribbon cable (see panel). Bring the free end of the cable onto the underside of the board at one of the long edges (the board should measure 30 x 40 cm, the

size of an A3 sheet). Take enough cable to reach the furthest reed switch and separate the wires back to this point (we are not going to use all the wires and the first four, counting the red edge wire as number 1, can be kept together and taped out of the way). Secure the cable to the underside of the board near the long edge using Sellotape or insulating tape (see page 114).

Take wires 5 and 6 and trim them to a length that easily reaches your first switch. Strip about 2 cm of plastic from the ends of the wires. Wind the end of wire 5 around one leg of the switch and wire 6 round the other leg. Solder firmly in place. Label this switch 1.

Taking the rest of the wires in pairs – 7 and 8, 9 and 10 and so on – solder them to each of the reed switches, numbering the switches as you go, up to switch 8. The position of the switches is not important – the numbering merely enables you to relate each switch to its appropriate sentence. Tape any loose wires firmly to the board and make sure the cable is secured near the edge.

You'll find it helpful to stick a small label on the upper side of the board above each switch to mark its position, which you can check by moving Fred around and listening for the click of the switches closing. Stick four cotton reels on the corners to support the board, turn it the right way up – and away we go!

To check that all is working, plug the connector into the user port on the underside of the BBC machine, type in this little program:

```
10 PRINT 255-(?65120)
20 GOTO 10
```

and run it. At first you'll see a column of

zeros on the screen. Move Fred over switch 1 and the zeros should change to ones. Test all switches 1 to 8 and you should see the numbers 1, 2, 4, 8, 16, 32, 64 and 128. If necessary, adjust the positions of the switches to make sure they close when Fred is above them, and check your soldering.

Draw your zoo plan with the stopping places corresponding exactly to your switch positions. Add your toy animals, type in the *Zoo* program and Fred is ready to make his visit.

The program

The program begins with a note for the teacher and asks whether you wish to use the printer. Type Yes or No and press the space bar to continue. As Fred is moved around the zoo the sentence on the screen should correspond with the place he is visiting. Type P to




Figure 3. Reed switch with wire bent at angles

see your story on the screen and, if required, to have it printed out.

Listing 2 shows the notes for the teacher as they appear on the screen at the beginning of the program and listing 3 is the printout of Fred's visit to the zoo. He can, of course, pass the stopping places in any order.

To change the sentences to fit a new situation, change the data lines 690 to 770. Type your new title on line 690, followed by your eight new sentences. One important point – because of the double-height letters, the sentence must not be longer than one line. If you want single-height letters type line 500 as follows:

```
500 PRINT B$(J)
```


and line 560 as follows:

```
560 PRINT D$(K)
```

and leave out line 570.

PROGRAM ANALYSIS

70,80	Dimension arrays – B\$(number of sentences in data); D\$(possible number of sentences in whole story)
90	Reads title from data
100-120	Reads sentences from data
130	Sets number of places visited to zero
140-280	Prints notes for adult on screen, and registers whether printer is required
290	Waits for space bar to be pressed before continuing
300	Clears screen and prints title in double-height letters
310	Checks whether Fred has set off
320	Clears screen
330-500	Scans user port to see whether Fred has arrived at a new place. If so, prints appropriate sentence on screen. L checks that he has left his previous stopping place and is not just moving about near it
340	Checks whether P has been typed on completion of visit. If so, program jumps to line 540 to display story
510	Adds 1 to number of places visited
520	Stores sentences in array for final display of whole story
530	Returns from sentence subroutine begun at line 400 to check for next place visited
540-580	Prints whole story on screen
590	If print-out not required program ends
600-680	Writes story to printer then program ends
690-770	Data



Odds and ends

- 4 cotton reels
- Toy animals or models made by pupils
- Coloured sticky paper
- Sheets of A3 paper
- Clips for corners
- Insulating tape or Sellotape

Tools

- Soldering iron and solder
- Wire-cutters and strippers


Addresses

Radio Spares Components Ltd
PO Box 427
13-17 Epworth Street
London EC2P 2HA

Midwich Computer Company Ltd
Rickingham House
Hinderclay Road
Rickingham
Suffolk IP22 1HH


Parts list for Acorn User activity board

1 piece of perspex 30 × 40cm from local signwriter (or use plywood or hardboard)	£4.50
8 dry-reed relay switches @40p each from Radio Spares Components Ltd Form A, type 7-RSR-A, stock no 338-147	£3.20
1 User Port connector and 36in cable from Midwich Computer Company Ltd BBC22	£2.46
1 wooden animal with magnet attached from local toyshop	£0.35
Grand total	£10.51




BUILDING THE BOARD

ABOVE: The utility board set up as a zoo with a magnetised figure 'Fred' at the entrance. The order and position of the animals can be changed by varying the order of DATA statements in the listing. Obviously the overlays can be as simple or complicated as you want. All sorts of activities could be developed - theatres, museums, mazes, adventures etc, and the DATA can even include pictures.



LEFT: Constructing the board. The reed switches are taped to the perspex, as are the wires. Note the cotton reels used as legs! In this picture one of the wires to the user port is being soldered onto a reed switch. Wires 1 to 4 have been trimmed back and are covered by the tape.



BELOW: The underside of the completed board. Note the position of the user port cable.



For little Acorns Mighty SHARDS Grow

SHARDS

Software



If you want well written and presented software for your Acorn computer then take a look at Shards. Shards can offer you entertainment and educational software that really is a cut above the rest.

Take a look at Shards.

Adventure and Strategy Games

Pettigrews Diary £7.95

A massive 90K graphic/text adventure with a difference. Can you solve it?

Empire £6.95

A superb graphic strategy game against the computer. 8 levels of difficulty. Played on a world map. Win at level 7 or 8 and you deserve a pat on the back!

Mystery of the Java Star £7.95

A graphic adventure for all the family. Utilises 100K of memory. Gripping stuff!

Educational

Fun to Learn, the definitive educational series - written by teachers and used in schools nationwide. All programs are menu based and make superb use of graphics. 100% user friendly and error trapped.

"This is how educational software should be written..."

Fun to Learn £6.95

A comprehensive program for 6-12 year olds.

Monster Maths £6.95

Helps develop basic maths and logical skills for 6-14 year olds.

Laser Letters £6.95

Educational word games for 6 year olds to teenagers. Three separate 500 word vocabularies.

Frac Attack £6.95

Fun with fractions for 8-14 year olds.

Science 1 £6.95

Science education for 11-16 year olds. Covers the use of lenses, meters, thermometers and balances. Super graphics.

Selected titles available at larger branches of Boots and W. H. Smith and all good stockists or by sending a cheque/P.O.

direct to us at:- Suite G, Roycraft House, Linton Road, Barking, Essex. Tel:- 01-591 7666 (4 lines)

(BBC & Electron)

(BBC & Electron)

(BBC & Electron)

Home Computing Weekly

(BBC)

(BBC)

(BBC)

(BBC)

(BBC & Electron)

Please send me a copy of:- (please tick)

Pettigrews Diary Fun to Learn

Empire Monster Maths

Mystery of Java Star Laser Letters

Science 1 Frac Attack

Please indicate which version required:-

BBC B Acorn Electron

To (Name)

(Address)

Please debit my Access/Visa account.

A/C No.


I enclose a cheque/P.O. remittance for £

(Signed)

All cheques/P.O. to be made payable to
Shards Software

* All orders despatched within 24 hours of receipt.

CLEARLY HE HAD ONLY ONE KEYBOARD IN MIND WHEN HE DESIGNED THE HUMAN HAND



IMAGINE A KEYBOARD

... so simple to use that in under an hour you're touch typing the entire alphabet, numbers and punctuation.

... so effortless it needs only one hand, your eyes never leaving the screen or the document you're copying.

A keyboard you can hold in your palm, and yet, so powerful, it can replace every input, command and function key of your BBC computer...

Just think how effortless it would be if you could touch type your programs, data and text.

How you could lean back and relax; be faster and more accurate; your mind free to think, and your eyes to read.


IT'S CALLED **QUINKEY**

And for **£49.95** you'll get everything you need — hardware and software — to use Quinkey with your BBC computer.

HOW CAN 6 KEYS DO THE WORK OF 72?


You simply press the keys in different combinations. Each combination represents a character.

Quinkey has 5 keys plus a Control key, each finger belonging to its own key — so there's no need to hunt and peck ... BUT ...



... HERE'S THE MAGIC!

Look at these diagrams:



See how the lines joining the key combinations form the characters? For each letter there's an instantly recognised and easily memorised visual clue.

That's the trick — and it works!

QUINKEY IN THE CLASSROOM.

Quinkey keyboards allow up to four children to use one BBC computer at the same time. "QUAD" software supplied with the Educational Pack enables children to write simultaneously on a split screen and print out their work separately.

(Send the coupon if you would like more information about the remarkable results that children of all ages and abilities are having with Quinkey.)



YOU CAN TRY IT NOW!

Rest the fingers of your right hand on a table top. Imagine the keys.

To write an "I" you press your Thumb and Index finger down at the same time.

For an "L" you press your Thumb, Index and Little fingers.

To write "Y" you use your Thumb, Middle and Ring fingers... and so on.

That's all there is to it.

Here's what users are saying about the keyboard:

- PETER RODWELL (as Editor of 'Personal Computer World') "took me half an hour to learn the alphabet... far easier than learning to type. It's an addictive device, and I'm starting to wonder how I ever managed without one."

- PETER WHEELER (in the 'Times Educational Supplement') "a new user can start to touch type after one hour's usage."

- FRANK DALE (BBC Producer - writing in 'Electronic Times') "no other machine is so easy to use, so easy to learn, so generally useful..."

NO RISK, MONEY BACK GUARANTEE.

If you're unhappy with your Quinkey just return it within two weeks for a full and courteous refund.

ONLY £49.95 (including VAT and postage & packing). **HERE'S WHAT YOU GET.**

- ★ One Quinkey keyboard.
- ★ Breakthrough multi-channel interface for up to four keyboards (plug into analogue port).
- ★ Two new powerful software packages, PROG & WP (described below).
- ★ Comprehensive Quinkey manual.

"PROG" and "WP" (free with the Quinkey package) are utility programs written specially for the BBC.

"PROG" enables your BBC to recognise and interpret the signals from the Quinkey keyboard. It combines easily with your application programs enabling you to use Quinkey as a comprehensive alternative keyboard.

"WP" optimises Quinkey to work with word-processing packages "Wordwise," "View" and "Edword" - a perfect text-writing combination.

KEYBOARD RANGE.

All BBC "B" keyboard inputs generate from the Quinkey, except the hard-wire key, "Break."

TECHNICAL DATA:

Loading length: &605. Running length: &300.
No zero-page locations, all ADC channels.
Interrupt service vector IRQ2V, correctly chained.

TESTED COMPATIBILITY

BBC Model "B"
OS 1.2
BASIC I or BASIC II (unless using INKEY with negative argument)
DFS 0.90
View A1.4
Wordwise 1.17
Edword

Acorn

Acorn
Acorn
Acornsoft
Computer Concepts
Clwyd Technics

Order from your nearest BBC Acorn dealer or by sending in the coupon below, now.

microwriter

An associate company of the Hambro Life Group of Companies

31 Southampton Row, London WC1B 5HJ

To: Vector Marketing Ltd., Denington Estate, Wellingborough, Northants. NN8 2RL.		
PLEASE SEND:		
001 _____	Quinkey pack(s) @ £49.95	£ _____
002 _____	Extra keyboard(s) @ £29.95	£ _____
003 _____	Educational Pack(s) @ £148.80 (Quinkey pack plus 3 extra keyboards and additional "QUAD" software)	£ _____
	postage and packing	£ 2.50

I realise that I can return the pack(s) undamaged within two weeks of receipt of order, if I am not fully satisfied, for a complete refund.

Send more information about Quinkey in the classroom.

I enclose a cheque made payable to:

Vector Marketing "Microwriter Ltd" for £ _____

Or debit my Visa/Access credit card No. _____

SIGNED: _____

NAME: _____

ADDRESS: _____

MU 7/84

Please allow up to 28 days for delivery.

Reg. no. 1374069

microwriter
QUINKEY

THE BEST IDEA SINCE THE HUMAN HAND

MEMOTECH BBC CBM64 SPECTRUM ORIC1 LYNX NASCOM ATARI

**Trapped in a fiendish Level 9 Adventure?
Your lamp burning low? Every exit guarded?**

You need escape plans! Send for one of Level 9's great new clue sheets for help. The clue sheets are free and each answers hundreds of questions: follow the instructions supplied with your adventure to get one. (Don't forget to send a stamped self-addressed envelope and tell us which game you have.)

NEW REVIEWS: "Level 9 are fast establishing a name for themselves among computer adventurers as the Number 1 producers of quality adventure software. All their adventures are text only, but because of a special coding they have developed, the amount of description and the number of locations packed in 32K is truly amazing."

— Midweek, 10 May 84

"Quicksilva call themselves the 'Game Lords'. That might be open to argument. But there can be no doubt that Pete Austin and the team at Level 9 are the 'Lords of Adventure'.

— Central Press Features, April 84

"Play Lords of Time and get nine times the pleasure!"
— Your Computer, May 84

AVAILABLE FROM: WH Smith and good computer shops nationwide.

If your local dealer doesn't stock Level 9 adventures yet, ask him to contact us or: Centresoft, Drake Distribution, Ferranti & Craig, Hi-Tech, Lime Tree, Microdeal, R&R or Wonderbridge.

Level 9 Computing

- Colossal Adventure:** the original mainframe adventure with 70 extra locations
- Adventure Quest:** an epic journey across the weird landscape of Middle Earth
- Dungeon Adventure:** a truly massive game which completes the Middle Earth Trilogy
- Snowball:** could this be the biggest SF adventure in the world?
- Lords of Time:** an imaginative romp through World History



I ENCLOSE A CHEQUE/PO FOR £9.90 EACH

My name:

My address:

My micro is a:
(one of those listed on the arch above, with at least 32K of memory).

Contact:
LEVEL 9 COMPUTING
Dept. A, 229, Hughenden Road
High Wycombe, Bucks. HP13 5PG
Telephone: (0494) 26871



BBC/ELECTRON PROFESSIONAL SOFTWARE

Our educational software is used in thousands of schools and homes throughout Great Britain.

KON-TIKI by J Amos *BBC* Tape £12.95 Disc £14.95
Simulation program based on Thor Heyerdahl's KON-TIKI expedition. Enjoy a journey on the Kon-Tiki recording on a map the raft's position and entering notes in the logbook on creatures found, unusual events etc. Inclusive of booklet, background information, maps and fully supportive illustrated data sheets.

EDUCATIONAL 1 *BBC/ELECTRON* Tape £8.00 Disc £10.00
Hours of fun and learning for children aged five to nine years. Animated graphics will encourage children to enjoy counting, maths, spelling, and telling the time. The tape includes six programs: MATH1, MATH2, CUBECOUNT, SHAPES, SPELL and CLOCK.
... 'An excellent mixture of games' ... *Personal Software - Autumn 1983.*

EDUCATIONAL 2 *BBC/ELECTRON* Tape £8.00 Disc £10.00
Although similar to Educational 1 this tape is more advanced and aimed at seven to 12 year olds. The tape includes MATH1, MATH2, AREA, MEMORY, CUBECOUNT and SPELL.

FUN WITH NUMBERS *BBC/ELECTRON* Tape £8.00 Disc £10.00
These programs will teach and test basic counting, addition and subtraction to four to seven year olds. The tape includes COUNTING, ADDING and an arcade type game to exercise addition and subtraction. With sound and visual effects.

FUN WITH WORDS *BBC/ELECTRON* Tape £8.00 Disc £10.00
Start your fun with alphabet puzzle, continue your play with VOWELS, learn the difference between THERE and THEIR, have games with SUFFIXES and reward yourself with a game of HANGMAN.
... 'Very good indeed' ... *A&B Computing - Jan/Feb 1984.*

JIGSAW AND SLIDING PUZZLES *BBC/ELECTRON* Tape £7.95 Disc £9.95
There are two jigsaw and four sliding puzzles on a 3 x 3 and 4 x 4 grid. Each program starts off at an easy level to ensure initial success but gradually becomes harder. It helps children to develop spatial imagination and in solving problems. The tape includes: OBLONG, JIGSAW, HOUSE, NUMBERS, CLOWN and LETTERS!

GAMES & UTILITIES

GAMES OF LOGIC *BBC* Tape £4.95 Disc £6.95
For children and adults alike. The tape includes AUCTION, FLIP, REVERSE, TELEPATHY and HEXA 15.
... 'This package is good value' ... *Acorn User - Nov 1983.*

SUPERLIFE *BBC/ELECTRON* Tape £4.95 Disc £6.95
Fast (machine code) version of a popular 'GAME OF LIFE' in a large universe.

KATAKOMBS *BBC* Tape £5.95 Disc £7.95
The ultimate adventure game.

UTILITIES *BBC/ELECTRON* Tape £5.95 Disc £7.95
An assortment of useful procedures and functions which can save you hours/days of programming effort: date conversion, input and validation routine, graphic routines, sort, search and many more.

★ **SPECIAL OFFER** ★
Buy three titles and deduct £4.00
Add 50p p&p per order. Please state BBC or Electron. Cheque/PO.

Golem Ltd, Dept A, 77 Qualitas, Bracknell, Berks RG12 4QG. Tel: 0344 50720.

EXPANDABLE CONSOLE FOR BBC MICRO



As supplied to Universities, Colleges, Schools, business & home users

A professional console to house disc drives/2nd processor/Torch dual drives/teletext, etc. All untidy wiring out of sight in the strong aluminium console in a matching textured colour. AVAILABLE NOW a bolt on extra module for extra expansions.

Also available a matching printer stand, yes stack your paper under the printer.

ALSO VDU STANDS AVAILABLE

Torch version available



ELECTRON CONSOLES

The console houses the electron and will safely support the expansion interfaces which plug into the rear of the micro, supports the VDU and tidies up all wiring, allows expansion to disc at a later date.

PRICES

Special Torch Version £46.99 + £4 p/p
BBC Console £44.99 + £4 p/p
Bolt on expansion £14.99 + £2 p/p
VDU/Printer Stand £14.99 + £2 p/p
Electron Console £34.99 + £4 p/p

Please add VAT @ 15% to all prices

For further information enclose sae or send cheque to,

Mail Order Only


Silent 01-801 3014
COMPUTERS

27 Wycombe Rd
London N17

Viewing by arrangement

24 hour
ansaphone

Please allow 28 days for delivery



TOP SAVINGS

PRINTERS	EX VAT	INC VAT
BROTHER HR 15	329.00	379.65
TRACTOR	62.00	71.30
SHEETFEEDER	185.00	212.75
KEYBOARD	135.00	155.25
EPSON RX80T	195.00	224.25
EPSON RX80F/T	220.00	253.00
EPSON FX80P/T	324.00	372.60
EPSON RX100F/T	350.00	402.50
EPSON FX100F/T	430.00	494.50
FX80 TRACTOR	30.00	34.50
JUKI 6100	325.00	373.75
MANNESMANN TALLY MT 80	199.00	228.85
NEC 2050 (IBM PC)	725.00	833.75
OKI MICROLINE 82A	255.00	293.25
OKI MICROLINE 83A	395.00	454.25
OKI MICROLINE 92P	379.00	435.85
SEIKOSHA GP 100A	165.00	189.75
SHINWA CP80	175.00	201.25
STAR GEMINI 10X	199.00	228.85
STAR DELTA 10	329.00	378.35
COMPUTERS		
COMMODORE 64	152.17	174.99
COMMODORE 1541 DISK	165.21	189.99
COMMODORE C2N CASSETTE	32.00	36.80
INTFACE 64-PAREL	59.50	68.43
APRICOT 2 x DISK + MONITOR	1425.00	1638.75
APRICOT 10 MB + MONITOR	2295.00	2639.00
SANYO MBC555	795.00	914.25
EPSON QX10	1600.00	1840.00

MAYFAIR MICROS

BLENHEIM HOUSE, PODMORE ROAD, LONDON SW18 1AJ
01-870 3255

UK's LOWEST PRINTER PRICES!

PRINTERLAND



ORDERED TODAY - DELIVERED TOMORROW
DOT-MATRIX

EPSON RX 80	£189.95
EPSON RX 80 F/T	£214.00
EPSON RX100	£329.00
EPSON FX 80	£317.00
EPSON FX100	£425.00

DOT MATRIX PLUS NEAR-LETTER QUALITY

CANON PW1080A	£275.00
---------------	---------

DAISY-WHEEL

JUKI 6100	£345.00
EPSON DX100	£356.00

ACCESSORIES

WORDWISE	£32.00
PAPER (2000 Sheets)	£12.00
BBC/PRINTER CABLE	£10.95

COPYALL DISK

● Copies ALL protected disks inc. tape to disk utilities.	
● Best on the market	
● Copies from original to your blank disk	£10.25

Educational, G'ment plus O'seas Orders Welcome

Please add 15% VAT. Delivery Printers £10.00. Paper £3.00. Other 50p
Printerland, Unit 27, Estate Buildings, Railway St., Huddersfield HD1 1JP

TEL HUDDERSFIELD (0484) 514105

DOT MATRIX PRINTERS



ALL PRINTERS HAVE CENTRONIC PARALLEL INTERFACE UNLESS OTHERWISE STATED. ALL PRINTERS HAVE HI-RES. DOT ADDRESSABLE GRAPHIC MODE. PLEASE SEND SAE FOR FULL DETAILS.

EPSON FX 80 160 CPS, 10" wide fric. & pin feed FX 100 180 CPS, 15" wide fric. & tract feed RX80 F/T 100 CPS, 10" wide fric. & tract feed RX801 100 CPS, 10" wide tractor feed LQ1500 200 CPS Letter quality printer 8143 RS 23 Interface for FX and RX printers 8148 RS232 Interface with 2K buffer, xon/xoff Ribbon Cartridge for FX80 FX80 & MX80 Ribbon Cartridge for FX100 & MX100	£344 + VAT = £395 £431 + VAT = £495 £261 + VAT = £299 £234 + VAT = £269 £29 + VAT = £33 £60 + VAT = £59 £7 + VAT = £7 £12 + VAT = £13
STAR Gemini 10X 120 CPS, 10" wide fric. & tract feed Gemini 15X 120 CPS, 15" wide fric. & tract feed Delta 10 160 CPS, 10" wide fric. & tract feed Delta 15 160 CPS, 15" wide fric. & tract feed Radix-10 200 CPS, N.L.Q. 16K Buffer Par & serial interface, downloadable characters, incredible value at Radix-15 15" wide version of Radix-10	£200 + VAT = £229 £295 + VAT = £339 £327 + VAT = £375 £414 + VAT = £475 £431 + VAT = £495 £518 + VAT = £595
SEIKOSHA GP100A 50 CPS, 10" wide tractor feed GP250X 50 CPS, 10" wide tractor feed ser. & par. GP100VC 300 CPS, 10" wide, VIC 20 & 64 interf. GP500A 50 CPS, 10" wide tractor feed GP550A 50 CPS, 10" wide friction & tract. correspondence quality GP100AS. Serial interface, ideal for Spectrum with microdrive	£156 + VAT = £179 £196 + VAT = £225 £174 + VAT = £199 £187 + VAT = £215 £234 + VAT = £269 £174 + VAT = £199
SHINWA CP80 80 CPS, 10" wide friction & tract. feed Spare ribbon cartridge for CP80	£187 + VAT = £215 £6 + VAT = £6
RITEMAN Compact 120 CPS, 80 col. fric. & tract. feed	£200 + VAT = £229
CANON PW100DA 160 CPS, 10" wide, 27 CPS N.L.Q. 24 x 16 matrix PW156A 160 CPS, 15" wide, 27 CPS N.L.Q. 24 x 16 matrix	£283 + VAT = £325 £347 + VAT = £399
COLOUR PRINTERS Sekosha GP700A, 7 colour, 50 CPS printer Canon FJ1000A, 7 colour, 40 CPS ink jet printer CPP40 40 column 4 colour battery operated	£47 + VAT = £59 £391 + VAT = £449 £118 + VAT = £135

ALL OUR PRINTERS HAVE 1 YEAR WARRANTY

DAISYWHEEL PRINTERS



JUKI 6100 20 CPS Bi-Directional Logic seeking 10.12.15 CP1 + PS Spacing 2K buffer, bes. selling Daisywheel Singer sheet feeder unit Tractor Unit RS 232 Interface Spare Daisywheel	£349 + VAT = £395 £217 + VAT = £249 £95 + VAT = £109 £52 + VAT = £59 £17 + VAT = £19
BROTHER HR-15 13 CPS, Bi-directional, 10.12.15 CP1 + PS Keyboard Unit Single Sheet Feeder Unit Tractor Unit	£344 + VAT = £395 £139 + VAT = £159 £217 + VAT = £249 £95 + VAT = £109
DAISY STEP 2000 20 CPS Unidirectional, 10.12.15 CP1	£260 + VAT = £299
SMITH CORONA TP1 12 CPS, 10.12, CP1 unidirectional	£208 + VAT = £239

PROFESSIONAL MONITORS

*SANYO
*MICROVITEC
*FIDELITY
*PHOENIX



SANYO DM6112 12" Green screen 18 MHz Hi-Res DM2112 12" Green screen 15 MHz Monitor CD3125 14" RGB Normal Res. Colour Monitor CD3117 14" RGB Medium Res. Colour Monitor CD3115 14" RGB High Res. Colour Monitor	£86 + VAT = £99 £66 + VAT = £75 £172 + VAT = £199 £286 + VAT = £329 £391 + VAT = £449
MICROVITEC CUB 1431 MS 14" RGB Normal Res. Colour Monitor 1441 MS 14" RGB Medium Res. Colour Monitor 1451 MS 14" RGB High Res. Colour Monitor	£173 + VAT = £199 £321 + VAT = £369 £417 + VAT = £479
FIDELITY Colour Monitor CM14 14" RGB, RGBY Composite sound, col.	£187 + VAT = £215
PHOENIX Phoenix High Res. 12" Green Monitor Phoenix High Res. 12" Amber Monitor	£66 + VAT = £75 £69 + VAT = £79

BBC MICROCOMPUTER SYSTEM

WE ARE AN OFFICIAL BBC COMPUTER DISTRIBUTOR
DEALER ENQUIRIES ARE WELCOMED

Acorn Electron £199 INC VAT

WE SUPPLY FREE 30 HOUR BASIC BOOK AND A DUST COVER WITH EACH BBC COMPUTER

BBC is the best microcomputer currently on the market. 32K RAM, 32K ROM, 8 modes of operation, full colour, full-size keyboard, internal expansions such as disc interface, speech synthesizer, Econet interface - in short it is a personal computer capable of expanding into a small business system.

BBC Microcomputer Model B BBC Mod B - disk interface BBC Mod B - Econet interface BBC Mod B - disk and Econet interfaces BBC 100K disk drive BBC dual 800K disk drive Torch Z80 disk pack including Z80 2nd processor, 64K RAM and CPN operating system - Free Perfect Software BBC Teletext receiver (Aug) BBC cassette recorder and lead Disk interface kit (free fitting) Mod A to Mod B upgrade kit Fitting charge for A to B upgrade kit 16K memory upgrade kit Games paddies 12" monochrome monitor incl. cable 14" Colour monitor incl. cable User guide Econet interface (free fitting) Speech interface (free fitting) BBC disk manual - formatting disk Parallel printer cable BBC word processor (i/w) BBC Fourth language cassette BBC Lisp language cassette	£348 + VAT = £399 £409 + VAT = £469 £389 + VAT = £447 £450 + VAT = £517 £230 + VAT = £266 £699 + VAT = £803 £696 + VAT = £799 £196 + VAT = £225 £26 + VAT = £29 £84 + VAT = £96 £70 + VAT = £80 £20 + VAT = £23 £84 + VAT = £96 £10 + VAT = £12 £99 + VAT = £102 £199 + VAT = £222 £10 + VAT = £10 £60 + VAT = £69 £47 + VAT = £54 £30 + VAT = £34 £10 + VAT = £11 £52 + VAT = £59 £15 + VAT = £17
--	--

APPROVED ECONET SERVICE CENTRE
WE STOCK A LARGE RANGE OF SOFTWARE FOR BBC MICRO INCLUDING ACORN/MSFT BBC SOFTWARE LONGMANS SOFTWARE PLEASE SEND LARGE STAMPED ADDRESSED ENVELOPE FOR FULL DETAILS

TORCH Z80 2nd PROCESSOR For only £347 + VAT

Torch 2nd Processor Z80 is supplied with perfect writer (a powerful Word Processor), perfect spellier (spelling checking program - I should have used one for making this advert!), Perfect Filter (A Database Program), Perfect Calc (Spread Sheet). It includes 64K memory (Almost 60K available to user). Fits inside BBC Computer.

Z80 2nd Process + Perfect Software Z80 Processor + Perfect Software + Dual 800K Disk Drives	£347 + VAT = £399 £695 + VAT = £799
--	--

GUARANTEED LOWEST PRICES

100% BBC COMPATIBLE MITSUBISHI AND TEAC SLIMLINE DISK DRIVES



NEW LOWER PRICES!

These drives are supplied ready cased with all the necessary cables, formatting program and User Guide. There are some very useful utilities included on formatting disc e.g. A DISASSEMBLER: This is 6502 machine code disassembler. * DUP: To copy and rename a file on disc. * FORMAT: Formatting program for 40 & 80 tracks. * FREE: This utility provides a disk usage analysis. * MDUMP: Enables you to display and modify any part of BBC memory. * MERGE: Merge a number of text files into one file. * RELOCATE: Downloads a basic program to AEOU. * SDUMP: Screen dump for EPSON in all graphic modes. * VERIFY: Verifies every sector on a disk. * MENU: A flexible menu program.

Single drive 100K 40 trks. single Sided Single drive 200K 40 trks. single sided Single drive 200K 40 trks. double sided Dual drive 400K 40 trks. double sided Single drive 400K 80 trks. double sided Single drive 400K 40/80 trks. switchable, DS Dual drive 800K 80 trks. double sided Dual drive 800K 40/80 trks. switchable, DS	£147 + VAT = £169 £286 + VAT = £329 £173 + VAT = £199 £330 + VAT = £379 £217 + VAT = £249 £382 + VAT = £439 £408 + VAT = £469
--	---

All above drives are low power slimline. (0.3 A typ at 12v and 0.4 A at 5v per drive). Normally extra power supply is not required. The BBC Computer power supply is designed to drive two low power drives (IT IS NOT DESIGNED TO DRIVE INTERNAL ROM BOARD).
40 Track SS/DD diskettes (10 Box) £18 + VAT = £20
40 Track DS/DD diskettes (10 Box) £23 + VAT = £26
80 Track SS/DD diskettes (10 Box) £28 + VAT = £32
80 Track DS/DD diskettes (10 Box) £30 + VAT = £34
ALL ABOVE DISKETTS ARE CERTIFIED EITHER MEMOREX OR DETALIFE

YOUR CONTACTS AT AKHTER ARE

DEALER/BULK ENQUIRIES TELEPHONE ORDERS DEALER ORDERS BUSINESS SYSTEMS ENQUIRIES EXPORT ENQUIRIES ECONET SYSTEM TECHNICAL ENQUIRIES ACCOUNTS DESPATCH REPAIRS	HAMAYUN MUGHAL PAULA HAYES TONY GLOVER DENNIS SUTCH MAHAMAD EDIB ALAN LAFFOLEY CARON ANDREWS PAUL SWIFT JOHN MAULLE
--	---

Prices Correct at the time of this advertisement going to press.

BUSINESS SYSTEMS



APRICOT - SIRIUS - SANYO IBM - TEXAS - TORCH

APRICOT "Portable Executive Computer" 16 Bit Micro, 256K RAM up to 1.44 megabytes floppy disk storage, 3 1/2" Sony disks. Portable brief case styling. Modem with auto dialler (optional) hard disk optional. Vast software library (compatible with Sirius 1)
Apricot with Single Drive and Monitor £1690 + VAT
Apricot with Double Drive and Monitor and Free Printer or 2nd Monitor £1890 + VAT

SANYO PROFESSIONAL COMPUTER
16 Bit Micro 128K RAM expandable to 256K. Single or Double Disk Drive built in full colour graphics (640 x 200 pixels in 8 colours) IBM compatible. Free software, Sanyo MBC 550 128K RAM single drive and free software including Wordstar and Calcstar
Sanyo MBC 555 128K double drive and free software including Wordstar, Calcstar, Inforstar Databstar etc. £1999 + VAT


SIRIUS 1 Sirius 1 Computer with 128K RAM and 1.2 megabyte floppy disc storage including CP/M 86, MS DOS and Microsoft Basic £2195 + VAT
Sirius 1 Computer with 256K RAM and 2.4 megabyte floppy disc storage including C/M 86 MS DOS & Microsoft Basic £2895 + VAT

TORCH
CF500 COMPUTER with colour monitor includes Twin 400K disks. Torchnet Operating System free perfect software (perfect writer, perfect spellier, perfect calc perfect filter), Torchmail Plus (Electronic Mail), Torch Mars (Financial modelling with graphics), Torchtel (Viewdata Access System) Executive Aid (Menu System)
Data! 600 (Link to outside mainframe services i.e. Telecom Gold) £2950 + VAT

TEXAS INSTRUMENTS PROFESSIONAL COMPUTER
T1 502 Dual 320K Drives 256K RAM. Up to 10 megabyte on board storage possible. T1 speech command hardware option brings a new level of user friendliness to computing. Allows voice operated keyboard control (Optional) Price £2650 + VAT

MAINTENANCE CONTRACTS ARE AVAILABLE.

COMPLETE WORDPROCESSING SYSTEMS INCLUDING DAISYWHEEL PRINTER From £695 + VAT



SYSTEM 1 BBC Micro model B + Disk Interface, Phoenix monitor, Smith Corona TP1 Daisywheel Printer, Casselt Recorder + all the necessary cables and documentation £695 + VAT = £799.25

SYSTEM 2 BBC Micro model B + Disk Interface, Phoenix Monitor, 100K Single Disk Drive, Wordwise, Smith Corona Daisywheel Printer + all the necessary cables and documentation Price only £895 + VAT = £1029.25

SYSTEM 3 BBC Micro model B + Disk Interface, Phoenix Monitor, Dual Disk Drives 200K, Wordwise, Smith Corona Daisywheel Printer + all the necessary cables and documentation. Price £999 + VAT = £1148.85

SYSTEM 4 BBC Micro model B + Disk Interface, Sanyo High-Res Green Monitor, Wordwise (or view), Juki 6100 Daisywheel Printer, Single 400K Disk Drive + all the necessary cables and documentation. £1049 + VAT = £1206.35

SYSTEM 5 BBC Mod B Micro + Disk Interface, Sanyo High Res Green Monitor, Wordwise (or view), Juki 6100 Daisywheel Printer, Dual Disk Drive 800K + all the necessary cables and documentation. Price £1195 + VAT = £1374.25

SYSTEM 6 Sanyo 16 Bit IBM pc Compatible Micro, 128K RAM, Single Disk Drive 160K, Wordstar, Calc Star, Sanyo High Res. Green Monitor, Juki 6100 Daisywheel Printer + all cable and documentation. Price Only £1145 + VAT = £1316.75

SYSTEM 7 Sanyo 16 Bit IBM pc Compatible Micro 128K RAM, Dual Disk Drives 360K, Wordstar, Calc Star, Mailmerge, Inforstar, Spellstar Databstar, Sanyo High Res Green Monitor, Juki 6100 Daisywheel Printer + and all necessary cables and documentation. Price £1395 + VAT = £1604.25

SYSTEM 8 All the components of System 6 but with Sanyo High Res Colour Monitor and Wordstar with Colour Facilities. Price £1445 + VAT = £1661.75

SYSTEM 9 All the components of System 7 but with Sanyo High Res Colour Monitor and Wordstar with Colour Facilities. Price £1695 + VAT = £1949.25

WE CAN ALSO SUPPLY PACKAGES WITH COMPONENTS OF YOUR OWN CHOICE. PLEASE PHONE (0279) 412639 AND ASK FOR HAMAYUN MUGHAL FOR A PRICE.



AKHTER INSTRUMENTS LTD T/A

COMPUTER GROUP

28/29 BURNT MILL
HARLOW, ESSEX. CM20 2HU U.K.
Tel. HARLOW (0279) 443521 Telex: 818894 AKHTER G

ORDERING INFORMATION:


We accept official orders from UK Government and Education establishments. Carriage is Free (UK only) for normal delivery. If express delivery is required please add £8.00 + VAT per parcel. We accept telephone orders on Barclay and Access Card please ring (0279) 443521 (10 lines). All cheques made payable to "AKHTER INSTRUMENTS".

N.B. ALL VAT INCLUDED PRICES ARE THE CORRECT PRICES. EXCL. VAT PRICES HAVE BEEN ROUNDED UP TO NEAREST POUND.



SEE US AT
The 2nd Official
Acorn User
Exhibition
OLYMPIA
16-19 AUGUST
1984

OPENING HOURS: MON-FRI 9am-6.30pm, SAT 10am-5pm
We welcome callers, no parking problems.



This month Barry Pickles turns his attention to teletext-style displays, extra codes for Epson printers and two screen dumps

A modular

program for

teletext display

LISTING 1 lets you create teletext-style displays on the Atom. The functions are set out in a menu and the program has been written in a modular style, so you can add to it. On selecting the CREATE option, you are presented with a blank screen – the screen number appears in the top left. You may move anywhere on the screen, using the cursor controls and return, and type your text wherever. The delete key functions as normal.

Once you are satisfied with the screen, press ESC, followed by any other key, to store the screen. Before storing, the cursor and the first two cells on the screen (where the screen number is) are deleted and they will not appear on the final display. Screens are stored sequentially from #8200 onwards, up to a maximum of ten. CREATE keeps track of the current screen number and attempting to create an eleventh screen will automatically route to the SAVE routine. In EDIT mode, the appropriate screen is displayed and you write/edit it just as you did in creating a screen, pressing ESC and another key to store it back in the correct place in memory. One difference is that the cursor will leave a mark at its initial position – this must be deleted by overwriting it with a space.

The DISPLAY option automatically rotates the selected number of screens and will continue until you press the CTRL key, to return you to the menu. The delay between screens can be altered and is on line 570.

You may save the screens created so far at any time, returning to the menu afterwards, but selecting the QUIT option automatically saves the screens (for safety) before ending.

The machine-code does the work of creating the screen, testing first for ESC (line 40), RETURN (line 50) and, if neither of these are found, jumping to

```

5REM:         teletext
6REM: by Barry Pickles
7REM: (c)ACORN USER 1984
10DIMLL2;P=#2800;S=1
15F=0;@=2;P.$21;Z=#B001;[
20:LL1 JSR#FFE3;RTS
30:LL2 JSR#FFF4
40:LL0 JSR#FFE3;CMP@27
50   BEQ LL1;CMP@13
60   BNE LL2;JSR#FFED
70   JMP LL0;];P.$6
80aGOS.d;R=100*C;G.R
100 REM:LOAD TEXT
110 *LOAD"SCREENS"
120 G.a
200eREM:SAVE TEXT
210 E=#8200+(512*S)
220 *SAVE"SCREENS" 8200 E
230 IFF;@=8;END
240 G.a
300 REM: CREATE SCREEN
310 P.$12,S
320 LI.LL0;GOS.b
330 S=S+1;IFS>10;F=1;G.e
340 G.a
400 REM: EDIT SCREEN
410 IN."SCREEN NO."Q
420 E=#8000+(512*Q)
430 F.N=#8000 TO #8200 S.4
440 !N=!E;E=E+4;N.;LI.LL0
450 C=?#DF*256+?#DE+?#EO
460 ?C=32;E=#8000+(512*Q)
470 F.N=#8000 TO #8200 S.4
480 !E=!N;E=E+4;N.
490 G.a
500 REM: ROTATING DISPLAY
510 P.$12;IN."SCREENS 1 TO"Q
520cM=M+1;IFM=100;G.a
530 IFM>Q;M=1
540 E=#8000+(512*M)
550 F.N=#8000 TO #8200 S.4
560 !N=!E;E=E+4;N.N
570 F.D=1 TO 1000;WAIT
580 IF ?Z&#40=0;D=1201;M=99
590 N.D;G.c
600 REM: END
610 F=1;G.e
700dREM:MENU
710 P.$12"           menu""
720 P." 1 - LOAD TAPE FILE""
730 P." 2 - SAVE TAPE FILE""
740 P." 3 - CREATE SCREEN ""
750 P." 4 - EDIT SCREEN""
760 P." 5 - DISPLAY""
770 P." 6 - QUIT""
780 IN."SELECT OPTION"C
790 IFC<1 ORC>6;G.d
795 M=0;R.
800bREM: STORE SCREEN
810 C=?#DF*256+?#DE+?#EO
820 ?C=32;E=#8000+(512*S)
830 ?#8001=32;?#8002=32
840 F.N=#8000 TO #8200 S.4
850 !E=!N;E=E+4;N.
860 R.

```

Listing 1. Requires 1.5k text memory and at least 1k screen RAM

LL2 which echoes the keypress to the screen. The action of removing the cursor and screen number is in lines 810-830.

Code comments

FOLLOWING the list of undocumented 6502 op-codes in the June issue, several useful comments have been received. The first, from M Niman of Manchester points out that the code #9C performs the action: STZ absolute, X and not as stated in the article. Quite right, Mr Niman, I stand corrected! Mr Niman also asks me to point out that there are several versions of the 6502 and the undocumented codes are not necessarily compatible between each version. This may indeed be so and the same warning applies to all undocumented code. However, the codes were tested on the Rockwell and Synertek versions and found compatible.

It should be noted that the codes are

not compatible with the extended instruction set of the new CMOS 65C02 (the full instruction set details of this chip can be found in the October 1983 issue of *Elektron*). Finally, Mr Niman mentions the new chip from Western Digital, the 65SC816. This is the 8/16 bit version of the 6502 and is said to be fully pin-compatible.

Geoff Smith of Worcester Park suggests that op-code #AB loads the same immediate operand into A and X, setting bit 4 to 0. I've tested this a number of times, and the arithmetic results are not consistent. However, bit 4 is always set to 0, so perhaps someone will have a use for this code.

Invented a routine or discovered a hardware modification for the Atom? Here's a chance to show your originality and win some cash. Send your idea to: Atom Forum, Acorn User, Redwood Publishing, 68 Long Acre, London WC2 9JH.

NOW AVAILABLE
FROM JOHN MENZIES
AND W.H. SMITH

A DOUBLE-SIDED 3" DISC DRIVE AT A SINGULAR PRICE.



THE OPUS
SUPER 3 MICRODRIVE.

£229.95 (INC. VAT)

FOR USE WITH YOUR BBC MICRO.

For only £229.95 (and that includes VAT, and all the necessary leads) you can have an OPUS 500k double-sided disc drive. And remember 3" disc drives are fast becoming the standard for home and business use.

This is an even bigger bargain than it sounds. For you're getting a double sided drive at the price that other company's sell single sided drives for. It reads and writes to the disc cartridge from both sides, giving you twice the on-line capability of other 3" drives. And there's no need to flip the disc over!

STATE OF THE ART TECHNOLOGY FEATURING:

- Easy to connect to the BBC Micro
- Compatible with most other makes
- Comprehensive manual
- Free disc cartridge
- Format, verify and other utilities provided
- Direct Drive
- Double sided
- One touch cartridge load
- 3 ms access time
- Portable, compact and reliable
- Two years' full guarantee
- Totally compatible with 5¼" drives

TECHNICAL PERFORMANCE.

	Single Density	Double Density
Capacity	250K Bytes	500K Bytes
Recording density	4,915 BP1	9,830 BP1
Track density	100 TP1	100 TP1
Total number of tracks	40 (each side)	40 (each side)
Recording method	FM	MFM
Rotational speed	300 RPM	300 RPM
Transfer rate	125K Bits/Sec	250K Bits/Sec
Access time track to track	3 ms	3 ms
Access time settling	20 ms	20 ms
Motor start time	0.5 sec	0.5 sec

The Opus Super 3 Microdrive is now available from W.H. Smith, John Menzies and leading specialist shops. Dual disc drives are also available for £460.

OPUS SUPPLIES LTD.

158 Camberwell Road, London SE5 0EE.

Opening hours: 9.00-6.00 Monday-Friday, 9.00-1.30p.m. Saturday.

☎ 01-701 8668
01-703 6155

To: Opus Supplies Ltd., 158 Camberwell Road, London SE5 0EE. Please rush me the following: **(ALL PRICES INCLUDE VAT & CARRIAGE.)**

Quantity	Description	Price
	Single drive(s) at £229.95 ea.	✓
	Dual drive(s) at £459.95 ea.	
	TOTAL	

I enclose a cheque for £ _____
Or please debit my credit card account with
the amount of £ _____
My Access/Barclaycard (please tick) No. is _____

Name _____

Address _____ AC22

Telephone _____

Opus.
Opus Supplies Ltd.

Searching for

compatible drive

MR A SULEIMAN of Wolverhampton asks which drives are compatible with the Atom. Well, the standard Atom DOS is configured for the Olivetti/Shugart-type drive, but it can, on request, be customised for the Tandon drives. I'm not sure about the new 3in drives, but I suspect they are also compatible, since they work on the Beeb.

You will need the Atom DOS and some extra memory, and the complete interface (needing only a drive unit) is available from Control Universal in Cambridge. However, I hear on the grapevine that CU is scrapping the original interface in favour of a double-density version, so have a word with them before buying a drive.

Finding the

interpreter

RICHARD GATES of East Dereham wrote to tell me of a strange result obtained when he accidentally typed in P.CHR\$(0) in direct mode. What he got was 94, which was the number of last error he produced.

After some experimenting, he found that P.CHA was equivalent to P.?A. However, he admitted defeat when trying P.CHA\$(0)?!

What Mr Gates discovered is the way that the interpreter works. The manual, you remember, tells you that, for most cases, spaces and brackets are not significant.

The interpreter works along a line from the left, until it encounters either an error or something it can interpret. As soon as it finds something meaningful, it stops, stores its position, and interprets the command/function, then carries on from where it left off. Now, you recall that a letter can be a variable or a pointer to an address, so, in the case of P.CHR\$(0), the interpreter correctly interprets P., then moves on. The next thing it finds is CHR, which is a valid function, meaning the first character of \$R. Now it comes to \$(0). There was no comma separating the two, but the interpreter doesn't need one and \$(0) is again a valid function. Since location 0 holds the last error number, that is what is printed out. In the latter case, the interpreter reads the function as: P.CHA;P.\$(0)?!

So there you are, Mr Gates. No bugs, just the interpreter not giving up unless it has to.

```

10 REM PRINTER CODES
20 ?40900=0
30 IN."STORE CODE AT "Q
40 DIM LL6;F.Z=0 TO 6;LLZ=£2000;N.Z;F.Z=0T01;P=Q
50 P.$21
60C
70 LDA@ LLO%256;STAE208;LDA@(LLO/256);STAE209
80 LDX@£60;STX£E7;JSR£AC4B
90 LDA@£20;STAE21C;LDA@£7F
100 STAE21D;LDA@£AC;STAE21E;LDA@£A2;STAE21F;LDA@£4;STAE220
110 LDA@£20;STAE221;LDA@£B3
120 STAE222;LDA@£FB;STAE223;LDA@£60;STAE224
130 JMP£A03C
140:LLO CMP@£2;BEQP+5;JMP£ACCE
150 LDA@LL1%256;STAE208;LDA@LLO/256;STAE209;LDA@2;JMP£ACCE
160:LL1 CMP@£3;BNEP+£11
170 LDA@LLO%256;STAE208;LDA@LLO/256;STAE209;LDA@3;JMP£ACCE
180 CMP@£7E
190 BEQP+5;JMP£ACCE
200 LDA@(LL2%256);STAE208;LDA@(LL2/256);STAE209;RTS
210:LL2 STXLL3+86;LDX@£FF
220 INX;CMLL3,X;BNEP-4
230 LDALL3+16,X;TAX;DEX
240 INX;LDALL3+32,X;BMIP+8
250 JSR£FEFB
260 JMP£-£9
270 LDA@(LL1%256);STAE208;LDA@(LL1/256);STAE209
280 LDXLL3+86;RTS;:LL3;J
290 N.Z
300 A=LL3; !A=£64636261;A=A+4; !A=£68676665;A=A+4; !A=£6C6B6A69
310 A=A+4; !A=£706F6E6D
320A=LL3+16; !A=£0C080400;A=A+4; !A=£19161310;A=A+4
330 !A=£25221F1C;A=A+4; !A=£322F2B28
340A=LL3+32; !A=£80012D1B;A=A+4; !A=£80002D1B
350 A=A+4; !A=£8001531B;A=A+4; !A=£8000531B;A=A+4
360 !A=£1B80541B;A=A+4; !A=£461B8045;A=A+4
370 !A=£80471B80;A=A+4; !A=£1B80481B;A=A+4; !A=£141B800E
380 A=A+4; !A=£800F1B80;A=A+4; !A=£1B80121B;A=A+4
390 !A=£1B801241;A=A+4; !A=£401B8032;A=A+4; ?A=£80
400 P.$6
410 ?£20A=£1C; ?£20B=£02
415 LINK Q
420 E.
    
```

Listing 2. P McArdle's Wordpack patch

Wordpack patching to provide

extra codes for Epson printers

LISTING 2 comes from P McArdle of Galway and is a patch for *Wordpack* users, giving extra codes for Epson printer functions. Unlike other *Wordpack* codes, these may be used anywhere in a line, but they will be counted as characters for justification purposes. The codes are held in a look-up table, beginning on line 300 and they may be altered to suit other printers. Used with *Wordpack*, you will need extra RAM to store the assembled code. The listing assumes RAM from #2000 and the vector set at the end of line 100 and the start of line 110 should point to Q+4. Those who use the new Bearsoft *Editor* may assemble the code at #2800 and must also alter the JMP on line 130 to #A01B.

The codes are each output using two characters. The only special character which may not be used for any other purpose in the text is ~ [shift `]. This character is followed by a code letter:

~a underline
~b cancel underline

~c subscript
~d superscript
~e cancel super/sub-script
~f emphasised print
~g cancel emphasised print
~h double print
~i cancel double print
~j big print return cancels
~k cancel big print
~l small print
~m cancel small print
~n double line spacing
~o normal line spacing
~p initialise printer

The program has the following properties. The code it compiles occupies less than 256 bytes. This is placed at the address requested at the start of the program. If RAM is available below #2800 then use it; if not, be careful not to overwrite it. Line 20 is a ROM switch command: if you need one put it here. The program debounces the Atom's keyboard. If you do not want this, delete lines 90 to 120 and line 410.

TECHNICAL EDITOR

£8000 to £14000

BEEBUG Publications Ltd. require a **Technical Editor** to take an important and responsible role in a team producing two computer magazines, for the Acorn Electron and BBC microcomputers. Previous experience with either of these machines is highly desirable together with the ability to write in a clear and interesting style.


The successful candidate will probably have a number of years experience either in microcomputing or in journalism. If you think that you have the right skills and experience to undertake this demanding and interesting job then write to:

BEEBUG Publications Ltd., Personnel Department, P.O. BOX 50, St. Albans, Herts.
enclosing a curriculum vitae, and samples of your own work.

Datapen

BBC Lightpen Programs


Datapen



BEEB PEN DRAWING PROGRAM


A comprehensive Mode 2 colour drawing program allowing plot commands, painting, circles, text, character defining, saving and loading to tape or disc, all to be selected and used with the lightpen.

PRICE £11.95 Introductory Offer £9.95



TELETEXT DISPLAY CREATOR/EDITOR

Allows the busy programmer to quickly create Mode 7 colour graphics and test screens for combination into his or her own programs. Movable on screen menu allows use of complete screen for graphics. Full instructions and a discussion on teletext features are provided. **PRICE £9.95 Introductory Offer £7.95**



BRITAIN

The first in a series of educational Geography and Geology programs. Britain comes complete with three sets of tests, and these may be very easily changed by adding DATA statements in the Basic program. Full instructions and grid map supplied.

PRICE £6.95 Introductory Offer £5.95

SUPERIOR PERFORMANCE

- Insensitive to ambient lighting
- Responds to different colours
- Program accessible LED lamp readout
- Switch for program control



SUPERIOR PROGRAMS

- Tape storage of your work
- Good documentation
- User routines provided on tape and on printout

The Datapen Lightpen itself comes complete with handbook, software on tape including two drawing programs and a printed listing showing useful routines.

PRICE £25.00

Two drawing programs, SKETCH and SHAPE-CREATE are included with the lightpen and the programs shown above may be ordered additionally, or separately as required.

All prices above include VAT, postage and packing.

Please send your cheque/P.O. to:-

Dept. AU2, Datapen Microtechnology Ltd.,
Kingsclere Road, Overton,
Hants. RG25 3JB



Star modifications for screen dump

A SCREEN dump for the Epson MX80 by Chris Shepherd of London is given in listing 3. It is enabled by LINK #xxxx, where xxxx is the start of the machine-code. It can be modified for the Star

range of printers by deleting line 570, then rewriting the following lines:

```
310 LDA@76;JSR#FEFB
610 LDA@140;JSR#FEFB
```

```
100 REM GRAPHICS DUMP
110 REM C.A.SHEPHERD
120 REM
130 P.$12;DIMLL10
140 P.'"ASSEMBLE TO"';
IN."(E.G.#3B00)"Q
150 P.'"LIST"';IN."
(1=YES,0=NO)"L
160F.I=0TO10;LLI=Q;N.
170P.$21
180F.I=0TO1
190P=Q
200I
210:LL0 LDA @2
220JSR#FEFB
230LDA@#FF;STA #8A
240LDA@#7F;STA #81
250LDA@#E0;STA #80
260LDA@0;STA #8D
270LDX@#3F;STX #8B
280:LL1 LDY@0
290STY#89
300LDA@27;JSR #FEFB
310LDA@75;JSR #FEFB
320LDA@00;JSR #FEFB
330LDA@#01;JSR #FEFB
340:LL2 LDX @7
350 CLC
360:LL3 LDA (#80),Y
370STA #81,X
380TYA
390ADC@#20
400TAY
410DEX
420BNE LL3
430LDY@8
440:LL4 LDX@7
450:LL5 ASL #81,X
460ROL A
470DEX;BNE LL5
480AND #8B
490AND #8A
500JSR #FF10
510 DEY
520BNE LL4
530INC#89
540LDY#89
550CPY@32
560BNE LL2
570LDA@#FF;STA #8B
580LDA@27;JSR#FEFB
590LDA@74;JSR#FEFB
600LDA@20;JSR#FEFB
610LDA@224
620CLC
630ADC #80;STA#80;LDA@0
640ADC #81;STA #81
650INC#8D
660LDA#8D
670CMP@27
680BMI LL6
690BNE LL7
700LDA@#70
710STA#8A
720:LL6 JMP LL1
730:LL7 LDA @3;JSR #FEFB
740RTS
750J
760IFL P.$6
770N.
780@=4
790P.$6'"OCCUPIES #"&Q" TO #"&P'
800 E.
810 REM
820 REM A GRAPHICS DUMP IS
830 REM OBTAINED BY INSERTING
840 REM THE COMMAND, LINK#XXXX
850 REM WHERE XXXX IS THE
860 REM ASSEMBLED CODE START
870 REM ADDRESS IN HEX.
```

Listing 3. Chris Shepherd's program for Epson printers

```
90REM PROGRAM TO PRINT THE £ SIGN ON THE AP100A.
100DIMLL1:F.I=1TO2:P=#3D0
110C;PHA;LDA@#FF;STA#8802;LDA#880B;ORA@2;STA#880B
120PLA;PHA;CMP@#5C;BNE LL0;PLA;LDA@#B9;PHA
130:LL0 AND@#80;BEQ LL1;LDA@1
140:LL1 STA#8800;PLA;JMP#FE52;J
150N.I:END
```

Listing 4. Curing an almost universal problem

```
995REM:Subroutine for
996REM:Daisystep 2000
997REM:screen dump on
998REM:the Acorn Atom
999REM:@B.Pickles - 1984
1000dP.$21$2;REM:screen off
1009REM: horizontal spacing
1010P.$27$31;A=4;LI.#FF10
1019REM: vertical spacing
1020P.$27$30;A=2;LI.#FF10
1030P.$27$78;V=#2800
1039REM: bit mask
1040!V=#10204080;V!4=#1020408
1050F.Y=191TO0S.-1
1060F.X=0TO255
1069REM: convert x/y to address
1070P=X/8+(191-Y)*32+#8000
1079REM: test point at x/y
1080Q=(?P&(V?(X&7))<>0)
1090IFQ;P.".";G.b;REM: set
1100P." ";REM: not set
1110bN.;P.';N.
1119REM: back to normal
1120P.$27$26$73$3$6;R.
```

Listing 5. Daisystep 2000 screen dump

Programming

for printing



the pound

NEXT is a short routine (listing 4) from Abe Ellis of Chelmsford. This solves the almost universal complaint that printers insist on printing a # sign, instead of the £ sign. The program is quite simple and the listing to assemble the code into spare space at #3D0 is shown. Before use it is necessary to change the vector as follows:

```
?#209 = 3;?#208 = #D0
```

The keyboard 'backslash' (#5C) is used for the £ sign, but this can be any keyboard character.

So the printer can accept an eight-bit word, bit 7 must be connected to the Atom printer plug, pin 9. This is done using port B, bit 0 of the 6522. Accordingly, pin 10 of IC1 is wired to PL5 pin 9.

Line 110 of the program initialises port B of the 6522. Line 120 looks for the #5C code and changes it to #B9, which is the code used by the AP100A for '£'. Line 130 checks if the msb of the character is a '1' which includes all other special characters in the AP100A. Line 140 sets port B, bit 0 to a '0' or a '1' as required.

The Basic print statement can now be used normally. The symbol which appears on the screen is a graphics symbol but this need not concern us. It must be remembered that if break is pressed the #208/#209 vector must be re-entered as #3D0.

Unfortunately, when the Acornsoft Wordprocessor ROM is entered, the printer vector is re-initialised and there is no way of breaking into the program to correct this. However, I have overcome this as follows.

Assemble the program normally, then enter the wordprocessor and complete all editing. To print out the text it is necessary to enter Basic using 'Q'. Now the vector can be corrected to #3D0 as before, followed by LINK#ACF7 when the printer will print the text.

Problems with

the Daisystep

LISTING 5 provides screen dump programs for the Daisystep 2000 printer.

Next month's Atom Forum will contain screen dumps for the Seikosha and the Centronics 737/739. This should now cover all the popular makes.



ROM SOFTWARE


for the BBC Micro

Caretaker BASIC Utility ROM

*Easy to fit..
Easy to use..*

Facilities include : quick entry of keywords, merging programs from file into the program in memory - sorting the line numbers into order, save and load function key settings, list current variables with values, move a program to a new position in memory, compact a program by removing spaces, REMs and fitting short lines onto long multiple-statement lines - taking account of line numbers etc., plus much more ...

£33.35 incl.



*HELP CARETAKER

```
CARETAKER 1.00
CURSOR (ON/OFF)
EXCHANGE <old> <new> G/S <<length>>
EXPAND <<start>> <<end>>
INSERT <<fsp>> <<lineno>>
KEYLOAD <<fsp>>
KEYSAVE <<fsp>>
LVAR <F><I><S><A><P>
MOVE <address>
MERGE <fsp> <<fsp>>...
NORMALKEY
NOTAB
PARTSAVE <fsp> <<start>> <<end>>
RENUMBER <<1st>> <inc> <start> <end>
RETRIEVE <<bytes>>
SINGLEKEY
SQUASH <S><R><M>
STATUS
TABSTOPS <<columns...>>
```

OS 1.20

>



Write or phone for a full specification.



Computer Concepts, 16 Wayside, Chipperfield, HERTS WD4 9JJ (09277) 69727

As from August 1984, our Address will be:

Gaddesden Place, Hemel Hempstead, HERTS HP2 6EX (0442) 63933





Features include :

Definition and fast movement of sprites, LOGO type turtle graphics using *FORWARD, *BACWARD, *LEFT and *RIGHT commands etc., rotation and scaling of plotting commands, fast CIRCLE and ARC drawing, multi-sized character printing, and much more

All commands may be included within BASIC programs and resident integer variables may be used in the commands.

10,000 Graphics Extension ROMs sold - so far ...

£33.35 incl.



AVOIDING INVALID DATA ENTRY. 1



Most coders have their own system for error-trapping. Vincent Fojut examines a common INPUT problem which can sometimes trap the unwary user

WHEN writing programs, especially for use by others, it is important to cater for invalid data entry, whether deliberate or accidental. The practice is often referred to, somewhat unkindly, as 'idiot-proofing' or 'mug-trapping'. Most coders will have a few routines to detect the more obvious errors, but it is often difficult to foresee all possible causes of 'misinterpretation'. A perfect example is that the operation of AtomBasic's INPUT command can itself trap the unwary.

On the Atom, 'INPUT' works like 'INPUT LINE ...' on the BBC/Electron. That is, anything entered in response to INPUT's prompt, including leading spaces, is passed to Basic for evaluation. With numeric data entry this is not a problem, since Atom's expression evaluator will skip leading spaces until a suitable number, variable or expression is encountered. However, when inputting strings, confusion can arise.

Try running the following simple program on your Atom:

```
10 R=#3000
20 INPUT "AGAIN (YES/NO)" $R
30 IF $R="YES" THEN RUN
40 END
```

Enter 'YES' immediately after the prompt and the program will run again. The second time, enter a couple of spaces before typing in 'YES', and see what happens. On a Beeb or Electron, the program would continue to run. However, on the Atom it stops.

In other words, INPUT on the BBC (without the LINE option) automatically left-justifies any string entered - that is, it removes leading spaces. Atom's INPUT does not do this, which can be disconcerting for the inexperienced user, who may be hard-pressed to see any fault in the apparently correct data entered. Fortunately, it is a simple

matter to implement the required left-justification facility. Both Basic and machine-code solutions are provided herewith.

Program 1 shows a few simple Basic subroutine variations to eliminate leading spaces. In all cases, variable X points to the string to be left-justified, and should be set up before the subroutine call.

Version (a), written 'in full' for clarity, works in the following way:

If the first character in the string is not a space, then the string must already be left-justified, in which case the routine exits immediately. Otherwise, each character of the string is examined in turn, until a non-space char. is found. Once detected, the string starting from the first non-space char. is moved down to the string's original starting address. In this way, unwanted spaces are eradicated.

Version (b) and (c) employ subtly different coding from the original, in an attempt to make the routine as compact as possible. Since version (b) does not use an IF statement, the whole code can be fitted on one line. The only processing overhead is that even if the string is already left-justified, the 'string-move' code is still executed, ie, it 'moves' to where it already is!

In (c), the code drops through to the second line (a RETURN statement) if the first character in the string is not a space. If it is, the whole string (starting at the original address + 1) is repeatedly shunted one byte downwards, until the first char. is not a space. This is obviously slower if there are many leading spaces. For example, 10 spaces means that the entire string is moved 10 times. On the plus side, this variant is the shortest of the three, and uses only one Basic variable, not two.

To see the routines in practice, modify the earlier program thus:

```
10 R=#3000
20 INPUT "AGAIN (YES/NO)" $R
30 X=R; REM X POINTS TO STRING "R"
40 GOSUB J; REM CALL LEFT-JUSTIFIER
50 IF $R="YES" THEN RUN
60 END
```

You should now be able to reply to the prompt either with or without leading spaces.

Providing the correct response is entered (ie, 'YES') the program will always re-run.

Program 2 is a functionally similar program written in machine-code. As before, the Basic variable X is made to point to the string to be analysed, before calling the routine with the LINK command. To try it out, assemble the machine-code at, say #2800 and change line 40 in the previous program example so that 'GOSUB j' becomes 'LINK #2800'.


The program uses two zero-page locations as a string pointer, and once these are set up, the processing is as per version (a) of the Basic routines.

It should be noted that these programs are not limited to use with Atom's INPUT routine. They can be employed in any situation where strings need left-justifying - for example, formatting data in tabular form.

Of course, there's a good deal more to error-trapping than one could cover adequately in an article. But the routines outlined here go one more step towards eliminating the unexpected, and make robust, reliable code a little more easily attainable. If your strings no longer match on input, you can rest assured that it isn't due to spurious spaces.

For complete listings see yellow pages, page xvi.

**The
only
ROM**




**Cartridge System
that does not
overload your pocket
or your BBC Micro**

Why risk damage to your BBC micro every time you want to change ROM's? Instead, store your growing collection of ROM's in professionally-made protective cartridges!

- Insert and remove Wordwise, View, Disc Doctor etc. at will from your micro in absolute safety – no wear or damage to pins to your ROM's.
- Low, low power consumption unlike other systems.
- Saves on memory.
- Price for complete kit including one cartridge only **£19.95 inc. VAT.**
- Extra ROM cartridges £27.75 for five, £49.50 for ten cartridges and single cartridges £6.95 each.

Dealer enquiries welcome.



Viglen
COMPUTER SUPPLIES

Unit 7 Trumplers Way
Hanwell W7 2QA
Tel: (01) 843 9903

Post to: VIGLEN COMPUTER SUPPLIES UNIT 7, TRUMPERS WAY, HANWELL W7 2QA
 Telephone: 01-843-9903. Personal Callers Welcome. Please add £2.00 for postage and packing. (50p only for single cartridge) Kits Cartridges
 I enclose Cheque/P.O. for £
 I prefer to pay ACCESS/BARCLAYCARD (Delete whichever is not applicable)
 Card No. _____
 Signature _____
 Name _____
 Address _____
 Cheques payable to Viglen Computer Supplies

●TEC●Viglen●TEC●Viglen●TEC●Viglen

TEC DRIVES

(As used by Cumana)

	Inc VAT	Excl VAT
Single sided 40 TRACK 100K 5 1/4"	£129.00	£112.17
Single sided 40/80 TRACK 200K switchable 5 1/4"	£169.00	£146.95
Double sided 40/80 TRACK 400K switchable 5 1/4"	£199.00	£173.04
For Dual TEC drives the price is double the single drive prices		
Integral Power Supply		
For single drive	£20.00	£17.39
For dual drive including dual case	£40.00	£34.78


Please add £8 for carriage

All disc drives complete with Professional Case – Ribbon Cable to connect to BBC Micro – Power cable to connect to BBC Micro – Comprehensive Manual – Formatting and utilities disc.

Viglen

COMPUTER SUPPLIES

Unit 7 Trumplers Way
Hanwell W7 2QA
Tel: (01) 843 9903



Post to: VIGLEN COMPUTER SUPPLIES, UNIT 7, TRUMPERS WAY, HANWELL, W7 2QA
Telephone 01-843 9903
Please send me _____
I enclose Cheque/P.O. for £ _____
I prefer to pay ACCESS/BARCLAYCARD No. _____
Card No. _____
Signature _____
Name _____
Address _____
AU8/2

PHILIPS 14" COLOUR TV/MONITOR

£235 inc VAT

TV/Monitor (resolution better than 585 x 450 pixels. Dot-to-dot distance .65mm)

(TV only: £185 inc VAT)

As a company we chose the Philips because we believe it to have the clearest picture as well as being the best value.

Take our word for it, or come and see for yourself.

EASY ON-THE-SPOT PARKING. AND IT'S FREE!


Viglen

Plus £8 carriage and packing

COMPUTER SUPPLIES

Personal Service & Quality coupled with Wholesale Prices, Unit 7 Trumplers Way, Hanwell, London W7 2QA. Telephone: 01-843 9903.

For special attention to your orders or enquiries concerning MONITORS, PRINTERS, COMPUTERS, DISC DRIVES, ring 01-843 9903 NOW or fill in the coupon below.





- Easy to carry • Lightweight • Sparkling picture in seconds • Reliability and performance excellent • Headphone Socket can also be connected to tape recorder • Loudspeaker mute switch • Retractable carrying handle
- Monitor/TV selected by switch • Includes RGB lead connecting direct to your BBC Micro. • Philips Model No. 14CT 2006/05T

Post to: VIGLEN COMPUTER SUPPLIES, UNIT 7, TRUMPERS WAY, HANWELL, LONDON W7 2QA.

Please send me _____ (qty) Philips TV/Monitor at £243 each. I enclose Cheque/P.O. for £ _____ made out to

VIGLEN COMPUTER SUPPLIES or debit my ACCESS/BARCLAYCARD No. _____

Name _____   Signature _____

Address _____

AU 8/3

**THE BBC MICRO SOUND SYSTEM
MICROVOC**

As supplied to Schools & Colleges

SYSTEM INCLUDES:

Speakers, Volume control, jack sockets and all connections (assembled) plus Buzzgo to eliminate the infernal B.B.C. buzz.

Easily fitted with no drilling, soldering or cabinet modifications £23.00 inc VAT and p & p

**MICROVOC WITHOUT SPEAKERS
£15 inclusive**

Now in stock — The Synth. This program allows the mixing and saving of all four channels, including Channel O for cymbals and drums. Complex melodies can now be entered in minutes by even a complete novice.

MICROVOC IS IDEAL FOR SPEECH SYNTHESIS OR COMPUTER PRODUCED MUSIC

MICRO-ADVENT

Ashlyn House, 113 Writtle Road, Chelmsford, Essex.
Tel: 0245 59708

**BBC MICRO REPAIRS
by MICROFIX**

ACORN AUTHORISED SERVICE CENTRE

**"Cumana Disc Drive and Acorn DFS
supplied and fitted at low prices"**

We will repair your faulty BBC micro, disc drive or monitor quickly and at a reasonable charge. Most repairs cost between £10 and £20.

We can also offer extended warranties on all your equipment.
Send S.A.E. for full price list.


Phone 01-968 9214
or call in at

191 Freston Road,
(Latimer Road Tube)
London W10

and ask for
Mark Duffill or Derek Mullings.

**MAKE THE MOST
OF YOUR
COMPUTER.**

**INTERFACE
PUBLICATIONS**



**Acclaimed books from the
experts . . .**

- Dynamic Games for your Electron
Neal Cavalier-Smith. £4.95
- 36 Challenging Games for the BBC Micro
Chris Callender and Tim Rogers. £5.95
- Let Your BBC Micro Teach You to Program
Tim Hartnell. £6.45
- Putting Your BBC Micro to Work (includes a full
word-processing program, plus 14 others)
Chris Callender. £4.95
- Creating Adventure Programs on your Computer
Andrew Nelson. £4.95
- The Easy Way to Program Your New Computer
Tim Hartnell. £3.95
- Practical Applications for the Microcomputer
in the Home.
David Hole. £4.95
- The Art of Structured Programming
Peter Juliff. £5.95

These books are available from most book and computer stores. In case of difficulty, order directly from us.

**Interface Publications, Dept. QAU,
9-11 Kensington High Street, London W8 5NP.**

Please send me the indicated books. I enclose £ _____

Name _____

Address _____



We're the Experts.

(TRADE ONLY: Interface Publications are distributed exclusively in the UK and
Ireland by W H S Distributors. Export trade handled by Interface Publications.)

THE TEAC 3" DISC DRIVE

Single 200K £159 inc VAT + £8 carriage

Cased, and price includes cables, utilities disc and manual.



Supplied with 13 utilities including
 * formatting
 * verifying
 * screen dump
 * disassembler
 * generating 62 files etc.

You can also dual to any 5 1/4" disc drive with or without an integral power supply.





53 Page Manual includes information on How to Transfer successfully from tape to disc. Packed with facts on hardware and software.

Post to: VIGLEN COMPUTER SUPPLIES, UNIT 7, TRUMPERS WAY, HANWELL, LONDON W7 2QA. 01-843 9903

Please send me _____ (qty) TEAC 3" Disc Drive at £159 each + £8 carriage. I enclose Cheque/P.O. for £ _____

made out to VIGLEN COMPUTER SUPPLIES or debit my ACCESS/BARCLAYCARD No. _____

Name _____   Signature _____

Address _____

AU 8/5

UNBEATABLE VALUE!


£115
 inc VAT
 + £8 carriage

CANON
 Model No. MDD110

40 track 100K

★ low power consumption
 (unlike full height drives)

All disc drives come complete with Professional Case – Ribbon cable to connect to BBC Micro – Power cable to connect to BBC Micro – Comprehensive Manual – Formatting and utilities disc.





Viglen
 COMPUTER SUPPLIES

VIGLEN COMPUTER SUPPLIES, UNIT 7 TRUMPERS WAY, HANWELL, LONDON W7 28A. Telephone 01-843 9903. Personal Callers Welcome.

Post to: VIGLEN COMPUTER SUPPLIES, UNIT 7, TRUMPERS WAY, HANWELL, LONDON W7 2QA.

Please send me ____ (qty.) CANON MDD110 DRIVES at £115 each + £8 carriage. I enclose Cheque/P.O. for £ _____ made out to

VIGLEN COMPUTER SUPPLIES or debit my ACCESS/BARCLAYCARD No. _____

Name _____   Signature _____

Address _____

AU8/4

COM-TEC COMPUTER CENTRE LTD



DEALER
AND
SERVICE
CENTRE




DEALER

23 Sheffield Rd
Barnsley
South Yorkshire
Tel: 0226 46972


Educational Orders Welcome

Discounts Available on Bulk

Orders



BBC Model B 399.00
BBC Model B + Disk 469.00
Electron (now in stock) 199.00
Disk Interface Kit 101.00



BNC Green Screen 113.85
Mitrovitec 14" Cub 245.00
Phoenix Green Screen 130.00
BBC Monitor 99.00
Amber Screen 135.00

DISCS

(Scotch 3m)
744 SS40 19.32
745 DS40 27.95
746 SS96 34.50
747 DS96 46.25
7440 Clean kit 19.50

ROMS

Wordwise 45.00
Disc Doctor 33.00
Graphics Ext 33.00
Print Master 33.00
Caretaker 33.00
ADE 60.00
Spy 2 30.00


SOFTWARE

Felix in Factory 7.95	Swoop 7.95
Martian Attack 7.95	Carm 7.95
Cybertron Miss 7.95	Chess 7.95
Hell Driver 7.95	Physics 6.95
Moon Raider 7.95	Where 6.95
Alien Swirl 7.95	World Geog 6.95
Laser Cmnd 6.95	Adventure 7.95
Danger UXB 7.95	Caveman Ad 6.95
Escape Mnbs 7.95	Fairground 7.95
Galactic Cmnd 7.95	Crazy Painter 7.95
Labryn Lacush 7.95	Lost City 7.95
Dambusters 7.95	Monaco 7.95
Lunar Rescue 7.95	Flexibase 9.95
Gideons 7.95	Alligatacalc 9.95
Gamble 7.95	

Order 1: deduct £1.00
Order 2: deduct £3.00
Order 3: deduct £6.00
Order more than 3, deduct £2.00 per game.

PRINTERS

Seikosha GP50A 138.00
Seikosha GP50S 138.00
Seikosha GP500A 228.85
Seikosha GP550A 299.00
Seikosha GP700A 458.00
Seikosha GP250X 264.00
Friction Feed GP100/250 28.00
Epson RX80 310.00
Epson RX80FT 356.00
Epson FX80FT 431.00
Star Gemini 10 x 280.00
Star Gemini 15 x 400.00



SD Single Drive DD Dual Drive
SS Single Sided DS Double Sided

SD SS 40tk 100k 194.00
SD SS 30tk 200k 253.00
SD DS 40tk 200k 228.00
SD SS 80tk 200k 221.00
DD DS 40tk 400k 431.00
DD DS 80tk 800k 511.00
SD DS 40/80 310.00
DD DS 40/80 534.00

All drives include leads, manual and utility disk

4 Colour Plotter + BBC lead 129.95

RIBBONS

Seikosha 4.99 Epson £5.74

Torch Disk Pack 839.00

CARRIAGE FREE ON ALL ITEMS

Access and Barclaycards accepted
Tel: 0229 46972



NEW

NOW AVAILABLE
FOR THE
electron

ONLY
£44.95

SEE US AT

The 2nd
Official
Acorn User
Exhibition
OLYMPIA
16-19 AUGUST
1984

STAND 104

THE SIR COMPUTERS
PRINTER/SWITCHED
JOYSTICK INTERFACE



Also Available for the ELECTRON
the SIR ADC/PRINTER INTERFACE

NOT JUST ANOTHER JOYSTICK PORT - FULL ANALOGUE-TO-DIGITAL CONVERTER provides fully proportional control, essential for use with graphics packages, digitizers, etc; ideal for scientific & educational applications; usable with a wide variety of BBC Micro-compatible analogue and switched Joysticks/Paddles.

CENTRONICS PRINTER INTERFACE - allows use of a wide variety of parallel printers including entire Epson range; complete firmware support included.

HIGH-QUALITY MOULDED CASE - attractively styled plastic unit bolts securely to the back of the computer. EASY TO FIT - no soldering, simply plugs straight into computer's rear edge-connector and is held in place by twin bolts; edge-connector on back of unit provides for further modular expansion if necessary.

THE SIR ELECTRON PRINTER/ADC INTERFACE £65.95
the SIR ROM/RAM EXPANSION BOARD

Provides 12 extra sockets which support a variety of ROM and RAM configurations up to a max of 192K for ROM and 16K for RAM.

ROM and RAM is normally paged in 16K blocks but is easily switchable to 2K, 4K or 8K blocks.

Price: £59.95

NOW COMBINED: BOTH THE ABOVE UNITS (ROM/RAM Expansion Board & Printer/ADC Interface) IN ONE CASE! A complete and comprehensive Electron expansion - ideal for wordprocessing applications amongst many other uses... ONLY £99.00!!

Easy to install - just plugs in.

Professional styled casing bolts to rear of computer.

Fully buffered design.

Permits use of most BBC ROM-based software including utility ROMs, word-processors & languages.

COMPLETE JOYSTICK & PRINTER FEATURES INCLUDE:

JOYSTICK FACILITIES:

- ★ Provides connections for two standard Atari-type joysticks, allowing the use of two-player games.
- ★ Immediately compatible with all games offering a joystick option.
- ★ Extra commands allow joysticks to be defined as any combination of keys, allowing all keyboard-operated games to be used with joysticks.
- ★ Joysticks may be read directly from BASIC using the ADVAL(n) function.

PRINTER FACILITIES:

- ★ Provides connections for a standard Centronics-type printer.
- ★ Allows use of all BBC Microcomputer printer control commands.
- ★ Special command enables a graphics screen to be copied to any Epson dot-matrix printer.

ADDITIONAL SPECIFICATIONS:

- ★ Only Acorn-approved memory locations are used, ensuring complete compatibility with any future devices (sideways ROM/RAM, sound expansion, speech synthesizer, disc system etc.).
- ★ All operating software is held within a paged ROM and is available for use from the moment the computer is switched on. THERE IS NO NEED TO LOAD ANY ADDITIONAL SOFTWARE FROM CASSETTE.
- ★ Housed in a sturdy plastic case.
- ★ Full twelve month guarantee.
- ★ Available direct from SIR COMPUTERS for only £44.95 (inc. VAT).
Please include £1 postage and packaging (U.K. only). Please allow 28 days for delivery.

SIR COMPUTERS - 1st for electron support

All our prices are inclusive of VAT.

Please include £1 postage and packaging for every item ordered on this page.

We also stock a complete range of printers, monitors, disc drives and software - with many hard-to-beat prices. Please telephone us for details.

Access/Barclaycard Telephone orders welcome.

SIR COMPUTERS Ltd

91 WHITCHURCH ROAD, CARDIFF CF4 3JP Telephone: CARDIFF (0222) 621813

Put an end to inefficient, slow cassette tape storage




Speed your data access with a TEAC disk drive from Viglen

Comprehensive, fact-filled, 53 page manual including techniques of loading from cassette to disc. Not available elsewhere



Replacing your cassette with a disk drive means Data Access in less than 5 seconds! If you are looking for a guaranteed disk drive that's fully compatible, at a price that includes VAT, Formatting Disk, User Manual, Case and Leads, then just look at our all-inclusive prices!

When ordering Dual Drives, please state which layout you prefer. A or B.



TEAC 55 Slimline Drives

SINGLE DRIVES CASED	Incl. VAT	Excl. VAT	DUAL DRIVES CASED	Incl. VAT	Excl. VAT
40 TRACK 100K	£143.75	£125.00	40 TRACK 200K	£287.50	£249.57
40 TRACK 200K	£195.00	£169.56	40/80 TRACK SWITCHABLE 400K	£358.00	£311.30
40/80 TRACK SWITCHABLE 200K	£179.00	£155.65	40/80 TRACK SWITCHABLE 800K	£450.00	£391.30
40/80 TRACK SWITCHABLE 400K	£225.00	£195.65	DFS KIT	POA	POA
			Disc Filing System 100% Acorn Compatible		
			Integral Power Supply	£30.00	£26.09

All prices correct at time of going to press and all offers subject to availability.

● Utilities disk includes 13 useful utilities including: ● formatting ● verifying ● screen dump ● disassembler ● generating 62 files, etc.

● Orders welcomed from Educational Establishments and Government Departments.



Full Twelve Months Guarantee

How to order

By post: To purchase any of the items simply fill in the coupon with your requirements. Enclose your Cheque/P.O. or use your Access/Barclaycard. Please make cheques payable to: VIGLEN COMPUTER SUPPLIES and post to above address. Allow seven days for delivery and add £8.00 carriage, package and insurance on all items.

By telephone: Ring (01) 843 9903. Credit Card holders (Access/Barclaycard only) can purchase by telephone. Please give Card No., Name, Address and the items required.

Viglen

COMPUTER SUPPLIES

Unit 7 Trumplers Way
Hanwell W7 2QA
Tel: (01) 843 9903

EASY ON-THE-SPOT PARKING. AND IT'S FREE!

Post to: VIGLEN COMPUTER SUPPLIES UNIT 7, TRUMPERS WAY, HANWELL, W7 2QA

Please send me the following items:

I enclose Cheque/P.O. for £ _____

I prefer to pay by ACCESS/BARCLAYCARD* . Card No: _____

Signature _____

Name _____

Address _____

Layout A or B* _____

*Delete as necessary


AU 8/7

SLOGGER SOFTWARE

MACHINE CODE GAMES FOR **BBC 'B'**, **ELECTRON**, **SPECTRUM 16/48K**

A MAZE IN SPACE

Use Joysticks or Keyboards to navigate your Starship to the planet surface and then into the maze below. Having been told in which section of the maze your target is hidden, your objective is to seek out and destroy it to complete a mission. Beware of the numerous alien defence systems. Two levels of difficulty! Horizontal and diagonal scrolling! How many missions can you complete?




Available now	Cassette	Disc
BBC 'B'	£9.95	£11.95
Special Offer		
Dogfight and A Maze In Space together		
Cassette - £14.95	Disc - £16.95	

Please state 40 or 80 Track if disc

DOG FIGHT

Still undoubtedly the most exciting 2-player game available. The objective is to fire sufficient shots into your enemy aircraft to force it to explode. Eight levels of difficulty. Sun, moving cloud, lightning, ground all provide real combat environment. Can you beat your friends?



Available now	Cassette	Disc
BBC 'B'	£9.95	£11.95
Electron	£7.95	n/a
Spectrum	£5.50	n/a

SLOGGER SOFTWARE

215 BEACON ROAD
CHATHAM, KENT
Tel: (0634) 811634


All prices include VAT and postage

NEW!

from

Viglen

COMPUTER SUPPLIES




Printer Stand

£12.95 INC. VAT

Carriage & Packing £3.00

A PRINTER STAND



- For dot matrix printers
- Raises printer high enough to put continuous stationery underneath
- Beautifully finished in clear perspex • Viglen quality every time
- Will accept paper up to 12½" wide • Non slip rubber pads

Dimensions: 15" (380mm) wide 12½" (320mm) deep 4" (90mm) high

COME TO VIGLEN FOR A FAST, FRIENDLY, PERSONAL SERVICE

DEALER ENQUIRIES WELCOME

Post to: VIGLEN COMPUTER SUPPLIES, UNIT 7, TRUMPERS WAY, HANWELL, LONDON W7 2QA.

Please send me _____ (qty) PRINTER STANDS at £15.95 each. I enclose Cheque/P.O. for £_____ made out to

VIGLEN COMPUTER SUPPLIES or debit my ACCESS/BARCLAYCARD No. _____

Name _____ Signature _____


Address _____

AU 8/6


VIGLEN

branches out

to offer the best value in monitors & printers



**NEW
SPECIAL
OFFERS**



Dot Matrix Printers

Epson RX80/FT **£275.00**
Epson FX80 **£379.00**
Canon PW 1080 A **£289.00**
160 cps with near letter quality printing
including friction and tractor feed.
Shinwa CP80 **£209.00**

Colour Monitors

Microvitec standard 1431 **£199.95**
Microvitec medium 1451 **£315.00**
Microvitec high 1441 **£442.00**
Philips 14" TV/monitor **£235.00**
(RGB Input)

Daisywheel Printers

Juki 6100 **£375.00**
Epson DX100 **£450.00***
SAN PLE 2000 **£299.00**
*Previously £499.00 Limited Stock

Monochrome Monitors

Philips 12" Green V2001 **£75.00**

ALL prices include VAT and leads for the BBC model B micro.
Please add £8 for carriage.
We also stock other computer peripherals, accessories and
complete work processor systems at unbelievable prices.
Please call for our latest offers.
You may also purchase these items direct by calling at
our factory/showroom in Hanwell, London.
Prices correct at time of going to press and offers
subject to availability.

Post to: **VIGLEN COMPUTER SUPPLIES UNIT 7, TRUMPERS WAY, HANWELL, W7 2QA**
Telephone: 01-845 9903. Personal Callers Welcome.
Please send me (state number required)
I enclose Cheque/PO for £ _____
I prefer to pay ACCESS/BARCLAYCARD (Delete whichever is not applicable)
Card No. _____
Signature _____
Name _____
Address _____
AUG/84

Credit cards available to Vigen Computer Supplies
card holder. Address below must
be the same as card holder.

BBC MICRO

- USER SUPPORT -

LOOK WHAT YOU
MISSED IN BEEBUG
VOLUME TWO

- 10 ISSUES OF BEEBUG MAGAZINE
MAILED FREE TO MEMBERS
- 30 EXCITING GAMES AND VISUAL PROGRAMS
- 43 SOFTWARE REVIEWS
- 33 HARDWARE REVIEWS
- 16 BOOK REVIEWS
- 150 HINTS AND TIPS
- 25 APPLICATION PROGRAMS
- SERIES OF ARTICLES FOR BEGINNERS
- MANY ADVANCED TECHNICAL ARTICLES
- NEWS AND PRODUCT INFORMATION
- PLUS SPECIAL OFFERS
- BIG DISCOUNTS ON A WIDE RANGE OF PRODUCTS
- EVENTS
- BRAIN TEASERS
- LOCAL CLUBS
- FULL MAGAZINE INDEX

A YEARS SUBSCRIPTION WOULD HAVE BOUGHT YOU ALL THIS

Figures based on the 10 issues of BEEBUG Volume 2.

BUT IT'S NOT TOO LATE TO JOIN FOR VOLUME THREE

BEEBUG PUBLICATIONS LTD. PO BOX 109, HIGH WYCOMBE, BUCKS

PLEASE ENROL ME FOR VOLUME 3
OF BEEBUG AT £9.90 (10 ISSUES)

NAME

ADDRESS

.....
AMOUNT ENCLOSED

PLEASE MAKE CHEQUES PAYABLE TO
BEEBUG PUBLICATIONS LTD.
AND SEND TO:- DEPT 13, PO BOX 109
HIGH WYCOMBE, BUCKS.
(DISTRIBUTION AGENTS FOR BEEBUG)

BEEBUG HAS BEEN
ESTABLISHED FOR TWO
YEARS AND NOW HAS
OVER 25,000 MEMBERS. IT
OFFERS TOTAL USER
SUPPORT TO ALL BBC
MICRO USERS.

SOFTWARE CHART

TITLE	PUBLISHER	PRICE	MICRO
1 (9) Fortress	Amcom	£8.95	B
2 (1) Snooker	Visions	£8.95	B/E
3 (10) 737 Flight Simulator	Salamander	£9.95	B/E
4 (3) White Knight II	BBCSoft	£10.00	B
5 (2) Twin-Kingdom Valley	Bug-Byte	£9.50	B
6 (16) Daredevil Denis	Visions	£8.95	B
7 (7) Chukkie Egg	A&F	£7.90	B/E
8 (17) Lords of Time	Level 9	£9.90	B
9 (18) Cylon Attack	A&F	£7.90	B/E
10 (6) The Hobbit	Melbourne	£14.95	B
11 (5) Hopper	Acornsoft	£9.95	B/E
12 (—) Battletank	Superior	£7.95	B
13 (8) Hunchback	Superior	£7.95 (£11.95)	B
14 (—) Mr Wimpey	Ocean	£6.90	B
15 (14) Gorph	Dr Soft	£8.95	B
16 (—) Eagle's Wing	Software Invasion	£7.95	B
17 (—) Pengwyn	Postern	£6.95	B/E
18 (20) Transistor's Revenge	Softspot	£7.95	B
19 (19) Dodgy Dealer	OI Consultants	£6.50	B
20 (15) Snapper	Acornsoft	£9.95	B/E

B= BBC E=Electron Prices in brackets are for disc version

BUBBLING UNDER

Confrontation (Lothlorien)
Aviator (Acornsoft)
JCB Digger (Acornsoft)
Cosmic Kidnap (Superior)

Compiled by RAM/Computer

Jet-Power Jack (Program Power)
Chemical Analysis (Acornsoft)
Hulk (Adventure International)
Fruity Fred (Softspot)

THE pace for this month's chart is being set by Amcom's *Fortress* which has cannoned *Snooker* from Visions into second spot. No new Top Ten entries again this month though Superior's *Battle Tank* has blasted its way into number 12. Another new entry is *Mr Wimpey* from Ocean, while *Pengwyn* and *Eagle's Wing* have flown into the number 17 and 16 spots respectively.

Snapper after two years of chart fame is tottering

on the edge of the chart at number 20. Will it stay or be gobbled up by a new entry?

The highest chart climber this month is Evil Knievel's protégé *Daredevil Denis* who rides up ten places to number 6.

Bubbling under from the last issue still are *Aviator*, *Hulk* (we still haven't seen a copy), *Jet Power Jack* and Acornsoft's new earthmover *JCB Digger*, reviewed in July and June respectively.

SOFT ●● OPTIONS

RE-SITTING English literature O Level again this Christmas? Then you might be interested in three new pieces of study software for the Beeb and Elk: Shakespeare's *Macbeth*, *Romeo and Juliet* and *The Merchant of Venice*. Each allows you to follow your own line of questioning, delving into the lover's secrets (is this *Dallas* in disguise?) or who killed who (yes it is!). The programs prompt you in the correct line of questioning and full act and scene references are provided.

Gsoft is providing *Multi-base*, a text editor and a key definer/character generator from its 18 Melbourne Road, London, E17 address. *Multi-base* allows you to use the one main program to create and manipulate a variety of multi files to be used for phone numbers, indexing etc, which can be dumped to a printer or saved on tape or disc. *Text Editor* enables you to write text to the screen which can be edited and printed as required. *Key Definer* sets up each of the function keys with a number of useful utilities to complement your programming techniques, while *Character Definer* is another in the increasingly large range of VDU23 editors.

For those who can't spell, *Spellwise* is the third checking programs for use with Computer Concept's *Wordwise*. With 6000 words in its vocabulary it should cover most of your needs! Contact Dataware, Freepost, Swindon SN3 4BR for more details (write carefully!).

If you've read all the assembly language books around, the *Complete Machine Code Tutor* from New Generation Software is a cassette-based machine code tuition package. The two cassettes contain 27 lessons aimed at trial and error learning. New Generation is at The Bookands, 15 Sunnysbank, Lyncombe Vale, Bath, BA2 4NA.

Apart from all that, things are fairly quiet on the new software front, with many software houses saving up their fares for the Acorn User Exhibition.

SUPPLIED ON CASSETTE
RUNS ON DISC OR TAPE

HOME ACCOUNTS BBC 32K £13.95 (INC)

Complete home finance system packed with sensible facilities to help you maintain up to date records of your BANK, CREDIT CARD, LOAN and SAVINGS ACCOUNTS. Keep track of CHEQUES, RECEIPTS, AUTOMATIC BANKERS ORDERS, BILLS WAITING PAYMENT and much more.
An essential asset for home or club.

BUSINESS ACCOUNTS BBC 32K £17.95 (INC)

Easy to use with small businesses in mind. Facilities include - PURCHASES, SALES, CASH, LEDGER and DAY BOOK LISTINGS, VAT ANALYSIS, CONTROL TOTALS and BANK RECONCILIATION. A simple but effective aid to efficiency.

FLEXIFILE BBC 32K £13.95 (INC)

A powerful, general purpose, file handling system. Quickly create, maintain, sort, select, save and print your own data. Develop complex systems with ease. Invaluable for Home, Club, Schools or Business Records. Offers the use of advanced software techniques to beginner and expert alike.

Cheques or P.O. to Diamondsoft Ltd., FREEPOST, Cheadle Hulme, Cheshire, SK8 5YB. Tel: 061-485 8705

THE DATABASE SOFTWARE FOR THE BBC
THAT GROWS WITH YOUR NEEDS

Filebase II **£19.95 inc.**


- Operates on any format DISC or CASSETTE
- Unique TURBOFILE and MAXIFILE options
- HIGH CAPACITY files (up to a full disc with the MAXIFILE option)
- Files created to USER DEFINED format
 - up to 20 items per record
 - each record up to 255 characters
- VIEW file by easy use of cursor keys
- PRINT files (optional report layouts)
- Print LABELS
- Powerful SEARCH features
- SELECT records to view, print, count, total, change or write a file
- SORT file on any item
- Convert TURBOFILE to MAXIFILE (on disc)

Requires BBC 32K (OS 1.0 or later). Optional disc/printer. Supplied on cassette - loads to any format disc.
Can be supplied on 40 track disc (please add £3)
Overseas orders please add £2.50 to cover postage.

Cheques or P.O. to Diamondsoft Ltd., FREEPOST, Cheadle Hulme, Cheshire SK8 5YB. Tel: 061-485 8705 (24 hrs).



**SIR ROM
EXPANSION BOARD
MODEL TWO**



£49.95

**THE ULTIMATE ROM/RAM
EXPANSION SYSTEM FOR THE
BBC MICRO**

- *12 extra ROM sockets complement those already provided by the micro to allow up to 256K ROM space.
- *Four of these sockets can support either ROM or Static RAM (up to 16K maximum RAM).
- *The Model 2 board allows switching between multiples of 2K, 4K, 8K or 16K ROM/RAM.
- *Fully compatible with all ROMs, including LDOS, Aries B20, and TORCH Z80 2nd processor card.
- *NO soldering, plug-in design.
- *Fits easily inside BBC case.
- *Plugs into CPU socket via short flexible connector.
- *Improved plug design allows the Model 2 board to connect securely to any type of BBC CPU socket with no harm to micro or board.

SEE US AT
The 2nd
Official
Acorn User
Exhibition
OLYMPIA
16-19 AUGUST
1984
STAND 104

*Board is held in place by sturdy supports.
*Full instructions provided.
*Additional features include the ability to transfer paged firmware to disc, and then load back into sideways RAM for future use - giving you no limit to the number of effective ROMs accessible!
SIR BBC MICRO ROM/RAM EXPANSION BOARD (Model 2):
PRICE £49.95
All our prices are inclusive of VAT unless specified otherwise.
Postage & Packaging:
Please add £1 for small items (ROM/RAM boards, software, etc), £2.50 for medium items (disc drives, BBC computers), £10 for heavy items (printers, monitors, etc).
(Postal rates apply within UK only. Please telephone for export rates).
Access/Barclaycard Telephone orders welcome.
SIR COMPUTERS Ltd., 91 WHITCHURCH ROAD, CARDIFF CF4 3JP
Telephone: CARDIFF (0222) 621813

SIR BUSINESS & COMMUNICATIONS

We announce our appointment as TORCH UNICORN Dealers, at a time when Acorn & TORCH are joining forces . . .

THE TORCH UNICORN RANGE:

CP/M compatible extensions to the BBC Microcomputer System:
ZEP 100: Z80 2nd processor card; 64K RAM; FREE SOFTWARE (see below) **£299 + VAT.**

ZDP 240: Z80 Disc Pack comprising ZEP 100; 2 x 400K floppy disc drive; FREE SOFTWARE (see below) **£799 including VAT.**

HDP 240: As ZDP 240 but with one 400K drive replaced by a 20MB Winchester Hard Disc unit . . . **around £1,995 + VAT.**

HDP 68K: As HDP 240 but with twin (Z80B and 68000) "second" processors; provides an extra 256K RAM! . . . **around £2,495 + VAT.**

THE UNICORN: Top of the range. The **TORCH UNICORN** comprises HDP 68K plus **FULL UNIX III** operating system . . . **around £2,895 + VAT.**

TORCH C500: Complete self-contained unit comprising BBC Micro system, ZDP, hi-res colour monitor & British Telecom-approved communication card. **Price available on application.**

FREE SOFTWARE: BBC BASIC (Z80) [allowing almost 48K User Memory!]; 'Perfect' Writer (word processor); 'Perfect' Calc (spreadsheet); 'Perfect' Filer (database filing system); Complete software package normally worth about £1,000!!

BBC MICROCOMPUTER

BBC Model A	£299.00
BBC Model B	£399.00
BBC Model BD	£469.00

MONITORS

Sanyo B/G	£85.00
Microvitec RGB	£219.00

DISC DRIVES

Single 100K	NOW £149.00
Dual 100K	NOW £279.00
Dual 400K	NOW £399.00
Single 40/80 Track	
Double-sided Switchable	£259.00

PRINTERS

Dot Matrix:	
Shinwa CP-80	£219.00
Epson RX-80 F/T	£275.00
Epson FX-80	£389.00
Daisywheel:	
Daisystep 2000	£299.00
Juki 6100	£389.00

SOFTWARE

We have a range of BBC and Electron titles currently in stock including ROM based programs such as **VIEW (£59.80)**, **Computer Concepts' GRAPHICS ROM (£32.20)**, **WORDWISE (£39.95)** and **DISC DOCTOR (£29.95)**.

Please telephone for full details of software range and current stock.

ACORN BBC SECOND PROCESSORS

6502 2nd Processor	£199
Z80 2nd Processor	£299

BBC HARDWARE FACTS

UNDER ONE COVER

'A Hardware Guide for the BBC Microcomputer', Wise-Owl Publications, Hull Innovation Centre, Guildhall Road, Hull, HU1 1HJ, £11.95 (inc VAT) plus £1.50 p&p

This book has 253 A4 size pages, which sounds a lot, but you should be aware that 136 pages are simply re-prints of manufacturers' IC data sheets. The remaining 117 pages are reproduced from a computer printout done on a daisywheel printer, but using a fairly large text format. This means that there are about 400-500 words per page. The following summary gives an idea of the contents of each chapter, plus some indication of its length.

Chapter 1 (five pages) is a general introduction giving an overview of the BBC microcomputer system as a whole. The aim of the book, it says, is to give 'a detailed understanding of the internal workings of the BBC micro'.

Chapter 2 (six pages) is entitled 'Attitudes to work and disciplines required'. It conveys some general ideas of the technical skills needed if you want to start playing with the hardware: how to handle ICs that might be damaged by static, and information on how to solder, de-solder and de-flux PCBs.

Chapter 3 (23 pages), which contains a 'complete description of the circuitry', is where the real meat of the book begins. This number of pages may seem ample space to describe the circuit, but it is an extremely complex machine, and in places the description is a little superficial. Also, the last six pages of the chapter deal with the use and applications of the 1MHz bus.

Chapter 4 (21 pages) is a very full survey of the link selections. The first four pages explain how to remove the main PCB and re-assemble it and give a warning about breaking warranty by doing soldering on the board. I was interested to see that the authors have been unable to find out what link S7 really does. While writing the new service manual I spent some time asking engineers at Acorn what it was for, and no-one there knew either. (Anyone got any ideas?)

There is one notable omission, presumably accidental. When talking about link S23 the reader is referred to the data sheet for the 88LS120 (RS423 driver IC), which it says is included in the book - unfortunately it's not there.


Chapter 5 contains 34 pages of detailed information about how to upgrade the machine from A to B, how to add the disc, Econet and speech inter-

faces, and some indication about adding second processors.

An interlude between chapters 5 and 6 consists of four full-page photographs of the computer indicating the positions of various ICs, fixing screws and so on.

Chapter 6, 'Hints, tips and modifications' (13 pages) contains many ideas which, on the authors' own admission, have been published elsewhere. Nevertheless, it makes a useful compilation. The chapter contains a section about the analogue port which has a number of mistakes. The pin numbering of the plug is incorrect in two of the diagrams, and it gives a method of supposed over-voltage protection which, in certain circumstances, would not only fail to protect the chip but would blow the protecting devices - LEDs. This is because they have forgotten to

A Hardware Guide For The BBC Microcomputer.




Wise Owl Publications

put current limiting resistors in series with each input - 1000 ohms would do.

There are one or two other omissions, apart from the lack of the 88LS120 data sheet. The first is that, except for the cassette interface, no circuit diagram is provided. This reduces the value of the circuit description. Acorn would not give permission for Wise-Owl Publications to reproduce the diagram (despite the fact that it had already been released to the general public in the *Advanced User Guide*). The other omission is that although the preface refers to 'system fault-finding', there seems to be no more than a passing reference to this in the text.

There's quite a lot of useful information in this book, and generally speaking it is of a good technical standard. It is also helpful to have all the datasheets in the one document, but the real question is whether or not it is worth the money (£13.45 inc p&p). Owners of the *Advanced User Guide*



may feel it is not since they already have a link selection survey and a limited description of the hardware. In general though this is a useful text, if a little over-priced.

Paul Beverley

●Wise-Owl has accepted the criticisms in this review and agreed to correct the various errors which were pointed out to them.

PB

LITTLE DEPTH

FOR TEACHERS

'BBC Micro in Education', Eric Deeson, Shiva Publishing, £6.50

AS THE BBC is the most important computer in schools, there is a need for a book written specifically for teachers detailing some of the possible classroom applications. Mr Deeson's book is not it.

The first chapter asks the inevitable question 'What is a computer?' and in a couple of pages swiftly disposes of bytes, CPUs, ROMs, and RAMs - all never to be mentioned again, so why bother in the first place? It also features a feeble drawing of a BBC, monitor and tape recorder sitting on a desk-top - in case you didn't know what such things looked like.

Next we get a Basic programming tutorial from first principles and I mean first principles - for example, 'Press RETURN after each line'. Very laudable, but a bit out of place in this book. Then comes a section on applications - Prestel, wordprocessing and the like, which again is disposed of very quickly.

And so the book continues, jumping from one subject to another and not really covering anything in sufficient depth. The best chapter is the one on graphics, nicely combining program listings with typical applications of computer graphics - CAD, plotters, etc. The worst is on flowcharts and 'top-down programming'.

Throughout the book, Mr Deeson adopts a rather juvenile style: do

HIGH QUALITY COMPUTER DESKS AT HIGHLY COMPETITIVE PRICES.

THE ORGANISER DESK.

- Top shelf for monitor/printer.
- Large desk top area.
- Lower shelf for paper/book storage.
- Teak finish • On castors.
- Self assembly.
- Ample room in front of the shelf for you to sit comfortably.
- Assembled Dimensions: H.31" W.40¼" D.26"



Only **£59.95.**



THE APOLLO RANGE OF BUSINESS DESKS.

- 10 models available to suit leading computer systems. • Immediate delivery.
- Sturdy steel underframes.
- Scratch resistant surfaces.
- Lockable castors. • Prices from **£100.**

All are on display in our showroom and are available from us or dealers throughout the U.K. All prices include VAT and delivery.

For further details contact us at:

158 Camberwell Road, London SE5 0EE. Telephone: 01-701 8668.

Opus.
Opus Supplies Ltd.

See our programs on MICRONET 800

PERSONAL
COMPUTER
SOFTWARE

proxima

Beeb-Text features:
width
Height
Italic

CHARACTER FONTS
ONE SIZE
SIX
SEVEN
THREE EIGHT
FOUR

Spacing
Spacing
Spacing
Thickness

BEEB-TEXT
A sophisticated and unique machine-code program which allows virtually unlimited variation in the BBC's text display. The user has the option of varying character thickness, italic, styles, height, width, colour combinations, etc. Up to 8 different fonts can be displayed in one page including shadowed and outlined types. Beeb-Text displays text in proportional spacing too however the user can also control character and line spacing independently.
Disc £15.00

▲ Prices are fully inclusive, no extra to pay.
▲ P&P on all orders is FREE!
▲ Please make cheques/P.O.'s payable to PROXIMA SOFTWARE.

BIG Print
(c) Proxima Software
Very tall text

CHARACTER BLOCK
76543210 0123456789
Program CHR 792
64 0 O A C T E U
72 H I J K L M N
88 P Q R S T J
96 X Y V
Key L to list menu

GRID CHARACTER BLOCK
DRAWING (0-10) 2
Duplicate grid No?
Key L to list menu

THINK BIG *
A highly effective machine-code program for displaying any dimension text. Can be incorporated into other programs.

Cassette £5.95
Disc £8.95

PIXEL PACKAGE *
Two programs are supplied for designing single colour and multi-colour characters and designs can be mirrored, inverted, rotated and duplicated. The programs even store the resulting data in program lines ready to be used.

Cassette £7.95
Disc £10.95

DISC TOOLS The complete utility disc for twin 80 track drive users and includes a 40/80 or 40/40 or 80/40 backing up facility.
Disc £10.95

TWO PLAYER GAMES *
Two 2-player games including 4Line and Frustration, joystick compatible.
Cassette £6.95
Disc £9.95

"Star" denotes Electron compatible


ROBOBRAIN Arcade fun. Disable the robot's positronic brain but watch out for its self defence.
Cassette £7.95
Disc £10.95

PROXIMA PERSONAL COMPUTER SOFTWARE, 1G10 1BT.
Please specify 40 or 80 track or 3" types when ordering discs.
Our FREE program special offer continues. Contact us for details!

SEE US AT
The 2nd Official Acorn User Exhibition
OLYMPIA
16-19 AUGUST
1984

people actually call the BBC a 'Beebox', and do we really need cartoon drawings of 'bugs' in a book aimed at teachers? In his previous book, *Easy Programming for the BBC Micro*, this device worked well, but here it gets a bit tiresome. In fact, that was a much better book for the newcomer to the BBC, and indeed several chunks from it have found their way into this new book.

The book aims to do too much: teach



the novice Basic programming, cover the many applications of computers, and act as a resource book for teachers. In 170 pages it cannot hope to succeed. Where it would be useful is as a guide to writing educational programs – a very specialised field.

The book contains some useful programs and routines for error-trapping, 'user-friendliness' and easy-to-read instructions, and as such would be invaluable to a teacher who already knows BBC Basic and wants to write his or her own educational software.

Memo to Shiva Publishing: why not call the book *Educational Programming for the BBC Micro* and lose a few of the cartoons?
Geoff Nairn

BASIC ASSEMBLER

'Assembly Language Programming on the Electron' by John Ferguson & Tony Shaw, Addison-Wesley Publishing, 197 pages, £7.95

JOHN FERGUSON and Tony Shaw need no introduction to *Acorn User* readers and this latest book is written in their usual thorough but easy-going style. Basically a rewrite of their book for the Beeb, it is aimed squarely at the newcomer to machine-code.

The first two chapters explain how the computer works at machine-level, and the next three introduce the assembler at its simplest level, followed by a summary. Chapters 6-10 go on to more complex functions, again followed by a summary. Chapter 11 brings the whole thing together, chapter 12 deals with interrupt handling, and chapter 13 rounds off by showing the stages in developing a complete program – a text editor, in this case. The book ends with set of useful appendices and an index. Throughout there are example programs, diagrams and cartoons.

The book contains one or two small mistakes, but nothing worth worrying about. Two things I would like to have seen are a note about 'modulus' effects, when indexing with the X and Y registers, and a note about the 'bug' common to all 6502 processors, which can cause indirect jumps to be incorrectly handled. These are, however, minor criticisms and I commend this book to anyone (not just Electron users) who wants an easy introduction to machine code.
Barry Pickles

DATABASE GEM

'Databases in the Classroom', Derrick Daines, Castle House Publications, £6.95

A WHOLE book for databases in the classroom? That might be the first reaction of most teachers to this book's title, if not indeed 'What's a database?' So some words of explanation are called for: Logo, simulation programs and other educational software are all very well in the classroom, but it is not how children will use computers when they grow up. Boring it may be, but most computers process data – vast quantities of it – held in things called databases. So it's important that tomorrow's generation should know something about how databases work.


The scene is set in the first chapter for today's information society and how it has arisen. As illustration, the story is told of how IBM, the world's largest computer company, grew out of a competition held by the US Government when it could no longer cope with the sheer quantity of census data. This deluge of data doesn't trouble just governments; anyone who has got lost inside the Prestel database will recognise the problem. Today it is no longer a question of what you know but rather knowing how to find out. This skill is something we should all acquire and the process should begin at school. This is Derrick Daines' argument and the basis for his book.

Subsequent chapters cover the tech-

nology of databases and data management: storage media, serial and random access, bubble sorts and the like. To the novice the jargon can be daunting, but here the author introduces buzzwords only when needed.

Being aimed at teachers, the book contains several practical exercises to work through with schoolchildren, using both manual and computer methods. A simple manual system is described which uses punched cards and knitting needles to store and retrieve information on pupils – height, age, number of sisters and brothers, etc. As an example of a computerised system, the database programs in the Microprimer software pack and their possible applications are described. As this software is available free to primary schools, it makes sense to base the examples on this rather than on an expensive machine-specific commercial program.


As if writing a book wasn't enough,



Mr Daines has also written his own database program for the BBC micro and a listing of this appears on the back pages. Written in Basic, it is nevertheless quite sophisticated, allowing up to 1000 records and using both serial and random access methods. Typing in long, dense listings is not everyone's idea of fun, so the program is broken down into separate sections, with accompanying text explaining exactly how each section works. This means it can easily be altered to suit your own needs. At £6.95 the book is worth buying for the database program alone!


Overall, an excellent book which covers a subject not normally dealt with in most schools. If you are a teacher using a BBC micro and you want to give your kids a taste of how computers are used in the real world, this is the book for you.
Geoff Nairn

keyzone



SOLID STATE DESK TOP SWITCHING DEVICES

THE PRINTERSHARERS



PARALLEL

EX. VAT

26 PIN (AS BBC) 3 MICROS TO 1 PRINTER	£65-
26 PIN (AS BBC) 6 MICROS TO 1 PRINTER	£129-
36 PIN (AMPHENOL) 2 MICROS TO 1 PRINTER	£85-
36 PIN (AMPHENOL) 3 MICROS TO 1 PRINTER	£105-


SOLID STATE SWITCHING

- * Solid State Switching
- * Extra cable lengths
- * No plugging/unplugging
- * Easy to operate
- * Simple installation

SAVES TIME & MONEY

- * Saves time
- * Saves money
- * Connect in multiples
- * No limit to sharers
- * 12 months warranty

THE PRINTERCHANGERS



PARALLEL

EX VAT

26 PIN (AS BBC) 1 MICRO TO 3 PRINTERS	£75-
36 PIN (AMPHENOL) 1 MICRO TO 2 PRINTERS	£95-
36 PIN (AMPHENOL) 1 MICRO TO 3 PRINTERS	£115-

KEYZONE SOLID STATE "PRINTERSHARERS" AND "PRINTERCHANGERS" ARE THE ONLY SWITCHING DEVICES TO INCORPORATE THE 26 PIN BBC PRINTER PORT CONNECTIONS.

OPTIONAL

MP1 - DC mains power pack for sharer/changer £6.50

LEADS - PARALLEL

26-26 PIN 2 MTS	£9-	Each pack of 3	£25-
26-36 PIN 1 MT	£10-	Each	
26-36 PIN 1.5 MT	£12.50		
26-36 PIN 2 MT	£15-		

Any cable can be made to order

SERIAL - RS232

3 way 25 pin Printershare/Changer

EX VAT

£75-

LEADS - SERIAL

	EACH	PACK OF 3
25 pin D type plug on each end - 2MT	£12-	£34-
25 pin D type plug on each end - 5MT	£14-	£39.50

KEYZONE LTD

U 14, Regeneration House, School Road, Park Royal, London NW10 6TD. Telephone: 01-965 1684/1804 Telex: 8813271

All products carry a full 12 months guarantee
 All prices are exclusive of postage & VAT
 P&P Switches £1.50 each. MP1 & Leads £0.50
 All Keyzone products are designed and manufactured in the UK and are supplied fully tested to the highest standards.

Copyrite

A program designed for serious users to enable them to maintain backup copies of most of their disc based software. Specify 40 or 80 track versions. Cheques or LEA order to Ephagy Software Products

BBC Disc version

ONLY £10.95 inc p & p

IMPORTANT — For all software producers. Are you concerned about software privacy? If so, why not make use of our Disc-Minder Software protection service.

Ephagy

For further details contact:-

Ephagy Software Products
 Rear of 125, Corporation Road,
 Grimsby
 South Humberside
 DN31 1UR

MIDI



ADVICE & DEMONSTRATION CENTRES



DISCOVER THE REAL MUSICAL CAPABILITIES OF YOUR BEEB WITH THE MIDI INTERFACE


The exciting new Electro-music BBC B Midi Interface is now available direct from City Music at just £159. Simply connects to the User Port and 1 MHz BUS and then via a 5 pin DIN lead to any MIDI equipped keyboard. Complete with "SOFTMUSIC" program on Cassette or Disc for step time composition of around 7000 notes on up to six tracks enabling control of six MIDI instruments, drum machines and sequencers. Phone 01-863 1841 for full details.

The adoption by several of the world's leading manufacturers of electronic musical instruments of MIDI (Musical Instrument Digital Interface) enables Keyboards, Drum Machines, Sequencers etc. to communicate with each other and now, via the MIDI interface with the BBC B micro.

For 25 years, we have specialised in electronic keyboard instruments and are leading main agents for YAMAHA, ROLAND, SCI, KORG etc. The MIDI facility enables musicians to easily compose complex and exciting music using the micro's memory and programming facilities to simultaneously control a whole range of instruments. Our MIDI Advice and Demonstration Centres have a complete range of MIDI instruments on display and demonstration and will welcome you and assist you to explore this exciting field.


SEE US AT

The 2nd Official Acorn User Exhibition
 OLYMPIA
 16-19 AUGUST
 1984



City Music

NORTH HARROW: Pinner Rd 01-863 1841
 TORQUAY: 65 Market St 0803 25488
 TRURO: 16 Pydar St 0872 71359



OILY CHOICE

'Slick!', BP Educational Service (01-920 8985), BBC A or B, tape £18 (education price £11.95).

WHEN it comes to their public image, no-one is more sensitive, or tries harder, than the multi-national oil companies. Tigers, free tumblers and sponsored art exhibitions have all been used to clean up the image of what is inherently a dirty product. BP bring the idea bang up to date with *Slick!*, a 'conservation game' for the BBC micro, in which the object is to minimise the effects of an oil slick at sea.

You are Mr McTaggart, the local pollution officer for a small Scottish fishing village, with £5,000 to spend on anti-pollution methods. On the screen is a map of the harbour and the surrounding area, with the oil slick shown as an ominous black blob moving inexorably



towards the shore. Also shown are the shellfish beds, fisheries and beaches – which, above all, oil should not reach.

The game has two parts: first you decide which anti-pollution method to spend your money on – absorption, sinking, dispersant or shore-cleaning; then the action proper starts. After the oil spill has been announced, the current position of the slick is shown as a map reference, eg, (590,370). You then have to calculate its next position from the speed and direction of the prevailing wind. For example, a 'fresh breeze from the east' will blow the slick three squares to the west. If you guess right, and within the time limit, you can load up a tug with your chosen anti-pollution material and head off for the slick,

moving the tug with the arrow keys.

The above process has to be done in several stages, but once you've reached the slick, you can start unloading the material and so reduce the size of the slick. In addition, you can position static booms across sensitive spots such as the harbour; unfortunately you can't see them on the screen – they appear just as map co-ordinates.

And so the game continues until, inevitably, oil reaches the shore. You are then scored on how successfully you dealt with the slick: from a base score of 50, points are added for correctly predicting the slick's path and protecting the harbour, but are deducted according to how much reaches the shore.

Here one must question BP's objectivity: for example, letting the oil come ashore loses points because, as the guide lets slip, oiled beaches get reported in the press. Similarly, shellfish contaminated with dispersant chemicals don't improve BP's image.

The final section in the user guide, entitled 'Point of Exercise', is perhaps the most telling: 'Nobody wants oil pollution. But we all need oil ... Accidents will happen'. Oh yes?

Incidentally, with all the current talk of software pirates bankrupting the industry and the devious devices adopted to prevent it, the attitude of BP in this respect must seem puzzling, if not embarrassing. Not only are you encouraged to make back-up copies, but there is even an option in the main menu of *Slick!* that automatically transfers the program to disc for you!

As a piece of educational software *Slick!* teaches a variety of skills, from decision-making to map-reading and grid references. The danger is in thinking that a poor score means that you 'lost' – it just means that you didn't choose the method that BP wanted you to choose. Perhaps the Friends of the Earth should bring out an alternative version of *Slick!*

Geoff Nairn

SCHOOL TESTER

'The Examiner', Acornsoft, Model B, tape £9.95

ACORN SOFTWARE is not the most imaginative of software houses, and this especially shows in their range of educational software: elementary maths programs, simple science experiments, and now multiple-choice tests. *The Examiner* lets a teacher design a multiple-choice examination 'paper', in which the computer displays the questions, stores each pupil's answers and produces a table of scores for the whole class.

On first running the program you enter the date and are then presented

with a menu of commands. Only the teacher should see this, for one option displays the answers along with the questions. Others let you load or save a set of questions on tape, enter new questions or run the examination.


If it's a new examination you select the 'enter questions' option and supply a title for your question paper. Up to 40 questions can be set, each with up to four possible answers, only one of which can be correct.

Assuming you have some questions in memory – a sample data file of general knowledge questions comes on the tape – the examination can be run. Just before this the teacher chooses how many questions to use, whether to have time-limits and whether to use sound effects. The only purpose the latter serve, being reminiscent of a motorboat engine, is to get the hapless candidate flustered.

The computer is now turned over to the children and from this point it does a passable imitation of Fort Knox: no amount of mischievous key-pressing will retrieve the menu and the all-important answers. Pressing BREAK or

The Examiner

for the BBC Microcomputer



ESC has no disastrous effect – it's just interpreted as a wrong answer, though CTRL-BREAK will inevitably lose the data.

As each pupil finishes the paper his or her score is stored in memory and when the whole class has finished the teacher can, by the use of a password, see the scores for the whole class. Up to 40 pupils can be examined this way; if the class is larger the paper can still be set, but the scores have to be written down as each pupil finishes.


Overall, the program works well; a lot of thought has gone into making it easy to use, while at the same time making it tamper-proof. The question must be asked, however, as to whether using a computer to set multiple-choice tests is a suitable use of a scarce resource.

Geoff Nairn

SAY GOODBYE TO GOTO!

Step by Step BASIC

BBC Micro/Electron edition ■ Richard Freeman



And to the bugs and the spaghetti! With Step by Step BASIC you learn to write well-structured programs from day 1. Programs that work and that you can see will work. Colour, sound, graphics, files, sorting all included.

BBC/Electron edition (203 pp)	£5.95
BBC/Electron program tape	£5.50
ZX Spectrum edition (177 pp)	£5.95
ZX Spectrum program tape	£5.50

LIFELONG LEARNING LTD
Dept AU, 55 MILTON ROAD
CAMBRIDGE CB4 1XA

INTERFACE SYSTEMS

CLONE

BBC 32K £3.00

You can't afford to be without CLONE. Sooner or later your favourite cassette program will refuse to load due to tape corruption. Act now and create security backup copies with CLONE. CLONE runs on all current BBC cassette systems (os 0.1, 1.0, 1.2) and works with most-all programs, including those with 300 baud sections. CLONE will even backup programs recorded as binary data.

CLONE is probably the most powerful tape-tape backup program available for the BBC-B and is sold STRICTLY ON CONDITION THAT IT IS NOT USED FOR TAPE PIRACY!

Cheques or P.O. to Interface Systems Ltd.
554 - 556 Prescot Road, Old Swan
Liverpool L13
Price:- £3.00 + 50p p&p.

COMPUTER SYSTEMS

HACKERS!

SEE US AT

The 2nd
Official
Acorn User
Exhibition


OLYMPIA
16-19 AUGUST
1984

HERE, NOW, AN ADVANCED MODEM
ESPECIALLY DESIGNED FOR YOU AND
THE BBC MICROCOMPUTER.
ONLY THE LOCO SYSTEMS SCM-100
OFFERS ALL THESE ADVANCED
FEATURES:

- MULTI STANDARD - V21, V23; BELL 103,202 - gives access to Bulletin boards home and abroad and Prestel
- FULL SOFTWARE CONTROL of all modes plus: orig/ans; line seize; carrier detect etc., using BBC micro user port
- AUTO ANSWER - software monitoring facilities give automatic mode selection on answer
- OPERATING SOFTWARE in ROM gives 12 new O.S. commands for easy control
- COMPATIBLE WITH standard comms software including TERMI etc.
- EXPANSION PORT in modem allows for future developments. These include telephone answering capability using BBC speech synthesiser and tone/pulse dialler
- POWERED FROM BBC MICRO - splitter available for use with discs if required
- B.T. APPROVED ISOLATION COMPONENTS - BABT approval applied for
- INCLUDES ALL CONNECTING LEADS

THERE IS ONLY ONE CHOICE

LOCO SYSTEMS



LOCO SYSTEMS, PO BOX 9, TWICKENHAM, MIDDX.

Please send me _____ SCM-100 software controlled modems @ £149.95 each. _____ Disc power adaptor @ £5.95 each

I enclose a cheque/PO order for £ _____ made payable to Loco Systems
Please send me further details (enclose S.A.E) _____

Name _____

Address _____

please allow 28 days for delivery

MAILBOX MODIFICATIONS COME IN

ANSWER TO A JOURNALIST'S PRAYER

IF I WAS still saying my prayers at the foot of my bed it would be only fair to put in the occasional good word for a programmer down in Sussex called Alan Wilmshurst . . . after all, he came up with the answer to my prayers.

You may recall that last August I was describing how Prestel's mailbox might be the answer for those publications needing some system for receiving copy from its journalists but for whom the expense of a mainframe computer couldn't be justified. I was already filing copy on my Beeb to the medical magazine *Doctor* which puts out its own Prestel magazine. The only problem was that I was having to compose each mailbox frame on-line. Those familiar with mailbox will know that this is both time-consuming, ties up the telephone (and so is expensive), and trying to edit mistakes on-line is far from easy.

Since then I have seen a number of methods for composing mailbox frames off-line. The way many BBC



users on Micronet are familiar with is the Micronet ROM which both does away with the need to load the terminal software and enables frames to be prepared. However I am far from impressed, either by the ROM or its mailbox editing facilities. The answer for my money is a combination of programs devised by Alan Wilmshurst. Both of his programs enable up to 20 mailbox frames to be prepared off-line and held in the computer's memory or saved on tape or disc. Pages can be just normal white type on black backgrounds or coloured type with graphics.

The software, called *Auto-Message*, is adapted from Micronet's version 4.0, to enable frames to be downloaded one at a time, plus one or two other neat refinements which make me prefer loading his enhanced software to the instant ROM. But more of the terminal software shortly. First, let's look at the message composer and its features.

When first loaded the program begins by asking whether you will be working with old pages (frames stored either on disc or tape or already in the computer's memory). Pressing 'N' immediately clears the computer's

Bill Penfold revels in a unique combination of programs for serious mailbox users

'Auto-Message' Micronet enhancement by Alan Wilmshurst, Summerhill, Coopers Lane, Crowborough, E Sussex (tel: 0892 662956), tape £6.99

memory. Next, you are asked how many indents you want at the beginning of the first line of the frame. Normally I put in two and for those using the mailbox response frame on Prestel page 77 that is probably the most useful. After that you are presented with a menu of five choices. The first is to prepare a frame (I'll describe how that works in a moment).

The second choice is to load previously-saved frames. If you type 'Y' for yes at the initial screen you are given an option to search for a file name. Once you have completed the frames to send, the third option allows you to 'save' the program. It starts by asking you how many frames you will be saving, and after that the file name.

The fourth option is a useful copy facility. For example, suppose you want to send out the same message to a dozen friends with only a slight difference to each, such as their names, . . . 'Dear Tony . . .' 'Dear Diana . . .' etc. You simply prepare your master frame, say for instance on page 20, then copy it onto pages 1, 2, 3 etc, just adding the alterations to each.

The fifth option simply allows you to leave the program, after which you would probably 'load' the enhanced Micronet software.

But let's go back to the first option. You press one and return and on the screen appears the page on which you will compose your Mailbox message. But first you have to input which frame page you want. The obvious response is to start at frame one and work your way through. However, this enables you to return to a previously completed frame to check or change it.

Next comes another useful feature of the program. The cursor first shoots to the bottom of the page to allow you to put in the mailbox number. You don't have to use this but it can be handy. For instance, if you are sending a long message to the same person, say six or seven frames, you need only type in the mailbox number on the first frame and then before typing in your message use the copy facility on option four, to insert



Flashback to the August '83 issue

the number to the next half-dozen frames. Alternatively you can temporarily leave the program through option five and set the function keys with the mailbox number to insert in each response frame in the composition.

Now you are ready to start typing in your message, and this is where anyone who has tried typing a message while on-line to a mailbox response frame will find the editing facilities a joy. You can delete letters, insert spaces, delete lines above the cursor, insert blank lines and generally use a simple word processor. The delete key works as normal, but the copy key deletes the line above the cursor, and does not close up the text.

I first began using this version of Alan Wilmshurst's program about the beginning of the year and I thought he had gone about as far as he could go: but no, a mailbox message arrived with colour and graphics. The only disadvantage to this is that the response frame is limited to just 12 lines. This can be changed, but only to 13 lines, and you then lose the colour and graphics.

Once you have composed your mailbox messages you don't necessarily



have to save the frames if you are straightaway going to load the Micronet terminal software. However, I invariably do . . . just in case.

Now for the terminal software. To enhance the program to send the prepared messages Alan Wilmshurst provides three separate sub-programs which alter Micronet's 4.0 version. This


page 153 ►

Now available for BBC users

KEVIN TOMS

No.1 Football Game'

FOOTBALL MANAGER





Football Manager

Designed by Kevin Toms

This outstanding game of skill and strategy is now widely available and you can join the many thousands of satisfied customers who have purchased the game. This is no five minute wonder - you will be playing this game for hours over many weeks (we know - our customers tell us!).

Some of the features of the game: -

- Matches in 3D graphics • Transfer market
- Promotion and relegation • F.A. Cup matches
- Injury problems • Full league tables • Four Divisions
- Pick your own team for each match
- As many seasons as you like • Managerial rating • 7 skill levels • Save game facility



Action from the Spectrum version

Prices: BBC Model B	£7.95
Commodore 64	£7.95
Spectrum 48K	£6.95
ZX81 16K	£5.95

(N.B. 3D GRAPHICS ARE NOT INCLUDED IN THE ZX81 VERSION)
Overseas orders add £1.50

Comments about the game from press and our customers.

"FOOTBALL MANAGER is the best game I have yet seen on the Spectrum and my personal favourite of all the games on any micro... To the ordinary person it is an excellent view of what can be done in the field of computer games... The crowning glory of this game is the short set pieces of match highlights which show little stick men running around a pitch, shooting, defending and scoring... It is a compulsive game but people who cannot take game sessions of 9 hours or so, which happened on one happy Sunday, will be grateful to know that there is a 'save to tape' option. FOOTBALL MANAGER has everything it could... The originator, Addictive Games, certainly deserve the name." Rating 19/20 (*Practical Computing* - August 1983)

To order by mail (p&p free) send cheques or postal orders to

Addictive
Addictive Games
7A RICHMOND HILL,
BOURNEMOUTH BH2 6HE
Dealers! For urgent stocks send your headed notepaper direct to our address.

Available from computer software stockists nationwide, including &

BBC NEWS FROM DPI

- Case to hold one drive
- Ribbon cable to connect one drive to BBC Micro
- Power cable to power one drive from BBC Micro
- Switch on rear of case to select 40 or 80 TPI operation when using FD55E or FD55F.

TEAC FD55 SERIES 5.25" 1/2 HEIGHT SLIM-LINE DISC DRIVES.


	Capacity	40TPI	80TPI	
FD55A	40 Track, Single Sided.	100K	N/A	£130
FD55B	40 Track, Double Sided.	200K	N/A	£180
FD55E	40 or 80 Track, Single Sided.	100K	200K	£155
FD55F	40 to 80 Track, Double Sided.	200K	400K	£218

HANDBOOK AND FORMATTING DISC

£15

DELIVERY: Up to 28 days.
WARRANTY: 90 days.
TERMS: Strictly cheque with order.
Send to P.O. Box 11, Stroud, Glos. UK GL5 1JN,
or phone through your
Access or Barclay Card number.

TO ORDER: ADD CARRIAGE/PACKING/INSURANCE AT £10 (COVERS NEXT DAY SECURICOR DELIVERY). THEN V.A.T. AT 15% TO TOTAL. THE ABOVE PRICES ARE VALID UNTIL END OF APRIL 1984.



Only £95

PRINTER AND PLOTTER —MCP 40

- 4 colours
- Selectable 40 or 80 characters per line
- Easy to use—simple software commands
- Standard Centronics interface—cables available for most micros
- Uses 4 1/2" plain paper
- High resolution—over 100 steps/inch

BBC COMPATIBLE FLOPPY DISC SYSTEMS AND DRIVES



- CASE to hold two drives (complete with blanking panel for use should only one drive be installed).
- Ribbon cable to connect **two** drives to B.B.C. Micro.
- Integral power supply for **two** drives.
- Switch on rear of case to select 40 or 80 TPI operation when using FD55E or FD55F.


THIS CASE CONTAINS ALL HARDWARE NECESSARY FOR TWO DRIVES. JUST SELECT ONE OR TWO DRIVES FROM THOSE SHOWN BELOW. IF YOU SELECT JUST ONE NOW, THE SECOND CAN JUST PLUG IN LATER. CASES ONLY SOLD WITH DRIVES.

DIGITAL PERIPHERALS LTD.

Rodney House, Church Street, Stroud, Glos. U.K. GL5 1JN
Tel: (04536) 71387. Telex 43551.

Cristie Company

PICTURES ON A PAGE



Dee Vince reviews three packages claiming to turn micros into electronic canvas and digital oils

Sketch Pad, Goldstar, Electron and BBC, £9.95. Paintbox, Beebugsoft, BBC (joystick only), £10 (disc £12, 3in disc £15). Picture Maker, Acornsoft, BBC, £9.95 (disc £11.50)

IT IS especially interesting to carry out a comparative review when the packages concerned all claim to do exactly the same job, in this case drawing pictures. Judging such software is difficult as there are many different criteria, so I shall try to cover all the various aspects of these programs. Let's start with the loading procedures. *Sketch Pad* has to win here for its novel title page. Part of the screen is drawn with a 'laser' light similar to the opening titles of ITV's *World of Sport*. It's a simple idea, but effective. Now, onto the programs.

All these packages present a blank drawing screen with a horizontal option menu. In the case of *Paintbox* and *Picture Maker* this is at the top, with *Sketch Pad* at the bottom. *Sketch Pad*'s menu displays eight colours and an assortment of drawing options, all on the one menu. *Paintbox* also has a palette of eight colours, but with a secondary menu to cover its range of drawing options. *Picture Maker* gives the ability of using 15 colours, though when drawing only the colours of modes 4 and 5 are available. That might sound contradictory, but I'll explain it later. Let's look at *Picture Maker* first as it is the most difficult of the packages, though the most comprehensive.

Picture Maker works on two levels: a 'catalogue level' and 'picture level'. When first entering the drawing program the user is taken into catalogue level. This is a blank screen showing the number of bytes left in memory and the names of any units (picture files)

which are currently in memory. From this level operating system commands can be used (as well as all disc system commands), and the commands which manage the program's system for naming units, saving and loading, changing screen modes and displaying the current picture.


The picture level is where the drawing takes place, starting off with a blank screen and a menu at the top which says which drawing option is being used: line, text, triangle, etc. In common with the other packages the colours are displayed in a strip, but here *Picture Maker* does differ. As mentioned earlier, 15 colours are available, but not when drawing. What happens is that the extra seven are repeated in the colours of the present screen mode along the strip of palette colours. Confusing? Well, it is! However, it does actually work as the drawing recorded on file contains the colours the user specifies, not those available when drawing; so when the picture is redrawn

the full range of colours is shown.

This is somewhat unfriendly and perhaps another method, such as naming or specifying the number of a colour, would have led to less confusion. But to be fair, *Picture Maker* is a superb package and is easily the best of the three reviewed. It is also the most difficult, but worth the extra effort. *Picture Maker* allows the user to merge different pictures together, each picture being a unit, thus the reason for the catalogue level displaying the different units in memory. Another extensive feature is the text mode. Besides normal size text, a number of special effects are possible. The text size can be changed by a 'transform' option that allows the text to be expanded and rotated. The shape of the text can be changed by altering the scale of the letters in two directions and text can be spaced in any direction. All these transformations allow a variety of effects to be created including special effects such as mirror images and italic typefaces.

The transformations mentioned can also be used while drawing and allow powerful manipulation of a picture unit.

Example
from
Picture
Maker



Little Brothers should be seen but not heard.



**NOW ONLY
£159.95
inc.VAT.**

A maxim which eloquently describes the Brother HR-5.

Less than a foot across, it's nonetheless loaded with features.

The little printer that's low on decibels.

There's one thing the HR-5 won't give you. Earache.

For the annoying 'clickety clack' many printers produce is mercifully absent from the HR-5.

Quietly efficient, it delivers high definition dot matrix text over 80 columns at 30 characters per second (maximum).

Text or graphics with ease.

The HR-5 also has something of an artistic bent. Being capable of producing uni-directional graphics and chart images together with bi-directional text. What's more it will hone down characters into a condensed face, or extend them for added emphasis.

At home with home computers.

Incorporating either a Centronics parallel or

RS-232C interface, the HR-5 is compatible with BBC, Spectrum, Oric, Dragon, Atari and most other home computers and popular software.

Perfectly portable, the battery or mains operated HR-5 weighs less than 4 lbs, and has a starting price of only £159.95 (inc. VAT).

Which is really something to shout about.

PLEASE SEND ME MORE DETAILS OF THE REMARKABLE BROTHER HR-5 PRINTER.

NAME _____ AU 8/84

ADDRESS _____

_____ TEL NO. _____

AVAILABLE FROM: BOOTS, RYMANS, WILDINGS, SELFRIDGES AND ALL GOOD COMPUTER EQUIPMENT STOCKISTS.



DEPT P, BROTHER OFFICE EQUIPMENT DIVISION, JONES + BROTHER, SHEPLEY STREET, GUIDE BRIDGE, AUDENSHAW, MANCHESTER M34 5JD
TEL: 061 330 6531 (10 LINES) 061 330 0111 (6 LINES) 061 330 3036 (4 LINES), TELEX: 669092. BROTHER INDUSTRIES LTD., NAGOYA, JAPAN.

Another feature allows a shape from a previously drawn unit to be taken out and merged into the current picture.

Producing standard shapes is straightforward and requires only choosing the appropriate drawing mode. All three packages have circles, triangles and lines and involve a few easy steps. There is much to cover in *Picture Maker* and I have only pointed out a few of its features. The normal drawing commands are all present and I'll return to the rest of the package shortly. But now to *Paintbox*.

Paintbox can only be used with joysticks, unlike the other two packages. Options are chosen from one of two menus by just touching the appropriate menu option with a cursor and pressing the fire button. It is certainly easy and fixing standard shapes is no problem. Eight colours are used, though by using the 'in-fill' option a ninth colour, which is a mixture of two others in a striped effect, can be created. *Paintbox* also has a feature I like that is lacking from the other packages, namely co-ordi-



Picture Maker

nates of the cursor on the screen. It does, however, only work in one of the 'brush' sizes. That point neatly raises the use of different brush sizes, eight in total, with the option of a ninth variable size chosen by the user. This is done by setting the brush size equal to the length of a drawn line.

The erase option is merely a clear screen facility and changes the background screen to the currently-defined brush colour. This makes erasing part of the picture difficult and means trying to erase your mistake by redrawing in the background colour (though this is not covered in the manual). *Paintbox*, in common with *Picture Maker*, makes use of the GCOL command. This gives a number of effects to choose from and controls the way in which a colour is placed on the screen. This means the plotting of colours can be as specified, OR-ed, AND-ed, EOR-ed or have the colour already there inverted.

The secondary menu allows the choosing of the eight brush sizes and the size of text relates directly to the

size of the brush. *Paintbox* doesn't have the range of commands of *Picture Maker* but is easier than the other packages initially, although it does require a joystick.

Finally, *Sketch Pad* from Goldstar. It was the cheapest of the packages – and the most attractive on first sight. Boxed in a video case, it is well-presented and is provided with a separate list of commands card and a colourful 21 page manual. Options are chosen by pressing the keys usually in conjunction with the control button. Out of the three




Paint box

scope for the added effects of the other two packages. Text can only be entered in one size and as with *Paintbox* there are eight colours with an extra colour available, which is a mix of two colours in one of three effects – chequerboard, striped, or horizontal stripes.

Sketch Pad provides a potentially good command not implemented in either of the other two packages, a magnification function. This allows the



Paint box



Sketch pad

menus I liked this one the most. The pen up/down indicator for instance is a picture of a pen nib either in the air or on the paper. The range of commands is limited to the standard commands (line, triangle, circle, etc) with little

user to enlarge an area four times its normal size for easier correction. Although the area is limited, this is a worthwhile addition.

Having briefly covered the main aspects I'm now going to turn to the

page 153 ▶

Package	Prices	Entry method	Machines	Summary
Picture Maker by Acornsoft	£9.95 cassette £11.50 disc	Keyboard Joystick	BBC B	Easily the most sophisticated, but can also be complicated
Sketch Pad by Goldstar	£9.95 cassette	Keyboard	BBC B Electron	Excellent packaging and presentation; very attractive to children
Paintbox by Beebugsoft	£10 cassette £12 disc £15.3in disc	Joystick	BBC B	Easiest to use, but if you haven't got joysticks...

BBC DUAL DISC PAYROLL PROGRAM

For 150 employees with 100K disc using random access operation.

Calculates most tax codes and national insurance rates. Calculates up to 24 fixed deductions per employee including employer's and employee's pension contribution and S.S.P.

Prints payslips, cheques and cheque list.

Has coin and note analysis.

Has a complete end of year routine for tax returns.

BBC B DISC MAIL MERGE PROGRAM

Produces personalised versions of a standard letter by merging names and addresses held on a data disc with a standard letter produced on Wordwise or Merlinscribe word processors.

Prints letters, envelopes, two abreast labels and the complete file including telephone numbers.

Comprehensive facility for selecting and printing using any user definable criteria.

BBC B DISC MAILING LIST PROGRAM

Stores up to 350 names and addresses per 40 track disc or 700 per 80 track disc.

Incorporates comprehensive search facilities for selective printing of labels, envelopes and letter headings.



MICROS

BBC B £395 + DFS £469
Electron £199
Spectrum £125

MONITOR

Colour/Green Novex 1414 £228
Green Sanyo DM2112 £80

PRINTERS

RX-80 £290
RX-80 F/T £325
Gemini 10X £255

DISC DRIVE

Single 40 track 100K £170
Single 40/80 track 100K £299
Dual 40 track £350
Dual 40/80 track DS £575

SOFTWARE

Payroll :- 40 or 80 track £49.95; Torch Z80 £74.95
Mail merge :- 40 or 80 track £39.95; Torch Z80 £69.95
Mailing list :- 40 or 80 track £19.95; Torch Z80 £29.95
Carriage 50p.

Discs from £19.95, cassettes from £0.55 and joysticks from £17.50, leads from £2.50.

Just arrived hard covers for all micros.

Business systems customised to individual needs such as word processing, payroll, employment agencies and chemist.

All prices inc VAT. Postage extra.

SEND ORDERS TO

CYB COMPUTERS

9 Crown Parade, Crown Lane, Morden,
Surrey SM4 5DA. 01 542 7662.

WE ARE A FEW YARDS FROM MORDEN UNDERGROUND STATION

DATA MINDER

THE DATABASE MANAGER FOR YOU

Dealer inquiries welcomed.

DATAMINDER is a powerful and flexible truly disk based database management system. It is designed to minimise the thought and effort required to set-up, maintain, organise and use large collections of data.

Three screen editors are included. The first provides for easy definition of new files or restructuring of existing files. The second functions like a worksheet for the writing and recall of records. A wide variety of record display formats are available some allowing immediate editing of disk contents. A third screen editor opens-up a wide variety of possibilities for producing customised reports containing information selectively drawn from a file and mail merged letters or circulars. Reports can be structured in standard essay format with the bulk of the text sandwiched between an introduction and conclusion.

For rapid access any or all of the fields can be indexed with a balanced B-Tree structure ensuring optimal record searching and retrieval times. These are typically 3-4 seconds to locate one record from a 1000. Search requests can be specific and include as many fields as you wish. Selection can even be made on the results of commands temporarily manipulating field data.

ADDITIONAL FEATURES INCLUDE

☆ Up to 26600 records in each file, disk capacity and record size allowing. ☆ Maximum of 150 fields per record, containing in total a maximum of 1200 bytes of text. ☆ Sup-

port for string, numeric, integer and date fields. ☆ 5 date formats and strings of up to 150 characters long allowed. ☆ Automatic allocation of disk space for files and extension of this as and when necessary. ☆ Rapid switching between use of separate files. ☆ Batch updating and deleting of records. ☆ Optional program monitor enabling, among other things automatic checking to warn you beforehand of duplicated record entry. ☆ Fields can be inserted, deleted, moved or renamed, indexed or de-indexed. ☆ Field types and entry lengths are also alterable. ☆ Up to 10 files each with any or all of the fields redefined in any of the above variety of ways can be processed in a single batch operation.

The package includes a comprehensive manual introducing you to the system and furnishing dedicated users with all detailed information they could wish for.

ONLY £ 29.50 + £ 2 p&p ex.VAT

Send now for our information leaflet. or order direct by writing to:

Access welcome.

COMPUTERWISE
DAMBRUGGESTRAAT 60
2008 ANTWERPEN BELGIUM
or phone (except sundays)
(010-323) 234 31.54



GSL

A **GSL** COMPUTING PUBLICATION

COMPUTING NEWS


See Us on Stand 14

The 2nd
Official
Acorn User
Exhibition

OLYMPIA
16-19 AUGUST
1984



GSL Winchester Hard Disk System for the BBC Micro NOW INCLUDING REMOVABLE CARTRIDGE DRIVES



GSL staff are working overtime to meet the still increasing demand for their Winchester Systems.

As leading suppliers of Winchester hard disk systems for the BBC micro, GSL has consistently improved both the scope and quality of its products. Since the introduction of the first 20 MByte, 8" Winchester unit at the start of 1983, the range has expanded to include 5.25" drives from 5 to 116 MByte, tape streamers, a comprehensive Winchester Filing System (WFS) and a flexible networking system.

A new addition to this product list is a removable cartridge drive. This is half-height mini-floppy size. The cartridges themselves are less than 4.5" square, and contain 5 MBytes of information. The units are front loading, cartridge replacement being performed in a matter of seconds. Cartridge drives may be used in their own right for stand alone systems, or can be integrated into a system with a large, fixed hard disk for back-up purposes, providing an economical alternative to a tape streamer.

All Winchester systems are fully cased, and self contained, the only connection required, apart from mains, is to the 1MHz bus connector of the BBC micro. The WFS or network (E-Net) firmware is supplied on



The New Streamlined Winchester System.



Winchester Disc Drives are put through a 24 hour intensive test programme prior to despatch to customers around the world.

Eprom. Fully rack mounted systems may also be provided, and other facilities available include a real time clock, and a link board for connecting two micros to one Winchester system.

	Price £
5 MB Winchester System	- 1650.00
10 MB Winchester System	- 1950.00
20 MB Winchester System	- 2400.00
30 MB Winchester System	- 2900.00
40 MB Winchester System	- 3400.00
65 MB Winchester System	- 4700.00
105 MB Winchester System	- 5130.00
140 MB Winchester System	- 7000.00
280 MB Winchester System	- 9500.00

New Winchester Backup Facilities

Backup of the E-Net fileserver Winchester has up to now been limited to selective transfer of user areas to floppy disk. In order to augment this, the following facilities are now (or shortly will be) available.

- (a) Backup of user attributes to floppy disk. (Available on application)
- (b) Full backup of the fileserver drive to a second (similar) Winchester unit. (This should be available within few weeks)
- (c) Full backup to removable cartridge drives. At present only 5 MByte units have been evaluated, necessitating the use of two cartridges for backup of a 10 MByte Winchester. (Expected availability is 1 to 2 months)
- (d) Full backup to tape streamer (20 or 45 MBytes). (Expected availability is 2 months).

Existing single Winchester systems can be upgraded to contain backup units for any of options (b), (c) and (d), additional hardware being accommodated within the current casing. At present the most cost effective solution for pure backup purposes is likely to be option (b), with (d) the most costly, though in the latter case some improvement is hoped for before the end of the year. Prices are available on application.

We are an official Acorn Dealer and Service Centre
Dealer Enquiries Welcome

Return to **GSL COMPUTING**, West Portway Industrial Estate,

Andover, Hampshire
SP10 3SG

I am interested in the following:

(please tick)

The GSL Winchester System

5 MB

10 MB

20 up to 200 MB

The GSL Slim Line Disc Drives

Your full range of Micro Computers and computer peripherals

GSL Analogue Signal Display and Analysis System

GSL Printer Buffer

Name: _____

Position: _____

Company: _____

Address: _____

Phone: _____


Send me by return full technical information

Or phone Jackie Featherstone on Andover (0264) 59633

GEOPHYSICAL SYSTEMS COMPUTING LTD, West Portway Ind.
Est. Andover, Hants SP10 3SG Tel: (0264) 59633 Telex: 47166

ROBOTICS

ROBOT ARM




The Beasty arm mechanism is driven by the Beasty and three servos, the result being a three axis robot arm. The arm uses a hook to manipulate objects although a gripper can be made by using a further servo. This versatile arm has been designed with enthusiasts and schools in mind although where it will end is anyone's guess!

£ 39.95

SEE US AT

The 2nd
Official
Acorn User
Exhibition

THE BEASTY



The popular Beasty interface connects directly to the BBC Microcomputer which enables the computer to accurately control up to four servo motors. The Beasty comes complete with all connection cables, a demonstration program and comprehensive instructions.

£ 29.95


VISION



The EV1 is an electronic camera that links to your computer. Using it's own optical sensor, the camera quickly captures high quality images for visual display, printing and analysis. The EV1 is supplied with a high quality lens, a detailed handbook together with comprehensive software.

£129.95

MAINS CONTROL



The SJR2 Mains Controller gives you safe, low-cost control of two 13amp mains outlets. Each outlet can be independently switched from Basic. There are lots of applications from security to home appliances, so put your Micro in control...

£ 34.50

CONTROL ROM



The Control ROM provides an extension to the BBC Machine for control applications. It's an essential tool for anyone teaching computer control technics, or who wants to use the computer in practical control applications. The process of sending signals to control devices is very crudely handled by most micros and the Control ROM changes this.

£44.85

Phone for further
details All prices
include VAT

COMMOTION

241 Green Street
Enfield EN3 7SJ
Tel: 01-804-1378

★ ASTRONOMY ★

'SKY-BABY' is a highly sophisticated scientific program running on BBC-B (cassette loading). It caters for astronomers ranging from complete beginners to advanced amateurs and aspiring professionals, and for educational institutes.

'SKY-BABY' 's many features include:

- ★ Colour and brightness coded display of stars, planets, sun and moon in selected area of sky
- ★ View from any position on earth, any date and time specified by user
- ★ A library of all stars down to magnitude 4.0 (i.e., 469 stars) including coordinates, magnitudes and names
- ★ Orbital parameters of planets: sun and moon positional formulae
- ★ Star sizes plotted to indicate brightness; sun, moon and planets colour coded
- ★ Moveable 'space probe' to identify name and details of any object displayed on screen
- ★ Details of current position, rising and setting times of any selected object: provision for an additional user-specified object, e.g., known comet, galaxy, radio source, etc.
- ★ Detailed User Guide: sections on program use, astronomical nomenclature and positional astronomy, formulae used, fully annotated expanded program listing, etc., etc.
- ★ Auxiliary program to analyse and list contents of stellar library
- ★ Unhindered access to Author by phone most times: callers welcome

'SKY-BABY' package, consisting of C10 Cassette containing three files (program itself, stellar library, auxiliary program), and 35-page User Guide £12.50 inclusive

NEW: Instructions for disc running, and running on Electron available on request.

payable to:

STELLAR ENTERPRISE, 84 Dudsbury Road, Ferndown, Wimborne, Dorset, BH22 8RG
Phone Bournemouth (0202) 575234

STOCK CARS

ON THE GRID

'Stock Car', Micro Power, BBC B, £7-95

THE object of this game is to drive a stock car round a circuit chosen from six different circuits.

The computer controls three other cars to get in your way or, on an optional two player game, it controls two cars, making a total of four cars on the screen at any one time.

On starting, the computer plays a short tune, the engines start, and you're off! You must change into first gear from neutral going gradually through the gears, dodging the computer's cars, and carefully negotiating the corners.

The graphics are quite good. The game draws six circuits, oil slicks, and the cars, in which your car is detailed,

but the computer's cars are plain. I feel the cars are a little small. I also found that if you get stopped on an oil patch it is hard to see your car, and in which direction it is pointing. On the whole though, the graphics are good—smooth, and without flicker.

The sound also is high standard. The computer plays a short tune before and after the game, you can hear the engines starting, cars bumping and the noise of cars crashing into walls. There are even two separate noises for changing up and down the gears.

This game's flexibility is excellent: You are offered one or two players, up to 40 laps to complete, optional oil slicks, variable skidding, sound on or off, six different circuits, optional joysticks, and joystick sensitivity select.

On the control side, *Stock Car* is a little hard to get the hang of at first, but it seems simple after playing for a while. Driving resembles driving a real car. The keys are very sensitive,



Stock Car: Good graphics and sound

though a little cramped (to allow two people to play at once), and it is sometimes hard to get going once crashed.

Overall, *Stock Car* is an exciting, original, addictive game, with good sound, good, smooth graphics, and comes with clear instructions.

Ian Brettell

153

◀ page 145

includes an altered 'PTERM' which enables you to add a number of useful features. For a start you can insert your private Prestel ID number which is sent by pressing the TAB key. It is also possible to store three other numbers which are sent by pressing CTRL and function keys 6, 7 and 8. It is possible to use these to automatically call up particular Prestel pages, or frequently used mailbox numbers. A third option, although this would be frowned on by Prestel, would be to enter your four-character ID response as well.

As soon as you log on to Prestel you will notice something different on your screen—a stop-watch ticking away the minutes you are on line, and the hours if you are on long enough. If you want to see the seconds as well, just press



CTRL f2. After being on line for seven minutes a short buzzer sounds to warn you there is just a minute to go before being charged for the next eight minutes. The buzzer sounds again after every eight minutes. For the clock alone I reckon this enhanced software beats the pants off the Micronet ROM.

The method of downloading is also fairly straightforward. You go to your mailbox response frame, say Prestel page 77 if it's just an ordinary message or page 88 if you want to send colour

and graphics. The cursor waits for you to input the mailbox number. If you've already put the number into your pre-prepared page you simply press f6 and it appears. Then press f7 and the first frame begins forming, line by line on the screen. For a full 13-line message it takes about 80 seconds.

If it is all right, you send the message in the normal way, then, instead of the return key to clear the page for the next message frame, you press SHIFT f2. Now you can either send the same frame again, possibly with a different mailbox number, or you can move on to the next pre-prepared page by pressing SHIFT f7.


One day of course this form of electronic mail will seem crude and cumbersome. But it is cheap, relatively easy and available.

◀ page 149

remaining parts of the packages. Redrawing a picture is often given less consideration than it should but not in the case of *Picture Maker*. Unlike the other two packages which allow the saved picture to be redrawn (*Paintbox* also giving details of the *LOAD address), *Picture Maker* includes a variety of ways to reshow a picture and provides much needed information to the more experienced computer user.

Picture Maker does not come with one program but five. There is the main drawing program Drawpic, and Showpic for displaying the pictures in any of five screen modes. Picdata converts pictures into Basic data statements for inclusion in a user's own program in a *EXEC file format, and Datapic converts

PICTURES ON A PAGE



this data back into a picture. There is a section on the picture memory data structure in the manual though this is not recommended for beginners! Finally, there is a screen dump facility. This, as it is covered only by an insert in the package, appears to have been an afterthought, but an excellent one it is. From either Drawpic or Showpic a picture can be dumped to disc or tape and then recreated on screen immediately. Reloading a screen dump can either be implemented by the *LOAD command

or by using the Restpic program provided.

The manuals with the packages are good overall. The *Paintbox* manual covers everything, while the *Sketch Pad* version is bright, colourful and extremely friendly. Contrasting with this is the *Picture Maker* manual which runs to 43 pages and is very comprehensive. The overall impression I gained from these packages was that the quality was of a high standard.

However, *Picture Maker* is without a doubt the most advanced out of the three. Its capabilities far outstretch the others, but it is also the most complicated and this must be taken into consideration. For completeness, though, my vote goes to *Picture Maker*.

Dee Vince

Micro Resources Limited

Southfield House, 11 Liverpool Gardens, Worthing, Sussex BN11 1RY
Telephone: Worthing (0903) 213174

BBC Model B	£399.00
BBC Model B Disc Interface	£469.00
BBC Model B Econet	£446.00
BBC Model B Econet & Disc	£516.00
Acorn Electron	£199.00

Acorn 6502 2nd Processor **£199.00**

This allows the BBC Model B to run faster with greatly increased memory especially in high resolution graphics modes, the package includes Tube software, the latest version of the DFS & NFS called DNFS, a Rom containing Hi-Basic and a comprehensive User Guide.

Acorn Z80 2nd Processor **£299.00**

If you have wondered how to make the best use of your BBC for Business, then the Z80 2nd Processor and CP/M must be the answer. This package comes with a suite of business programs, including Memoplan, Fileplan, Graphplan, Accountant, BBC Basic (Z80 Version), Cobal, Neculeus (Programming Aid), Professional Basic. This software alone is worth hundreds of pounds and with CP/M you can buy any of the programs written for this operating system.

Acorn Prestel Adaptor **£99.00**

Makes the BBC Micro into a Prestel Terminal revealing all the pages of information and allows you to use British Telecom Gold for electronic Mail etc.

Acorn Teletext Adaptor **£225.00**

Allows the downloading, storing and running of programs via Ceefax, transmitted free of charge, pages can also be saved and printed from all 4 channels.

Acorn Bitsik **£375.00**

This superb menu driven graphics package allows high quality CAD at a modest price. Needs 6502 2nd Processor and dual 80 track discs drives, a must for all design teams.

Acorn IEEE 488 Interface **£325.00**

Provides computer control of compatible scientific and technical equipment. Useful in experimental work in industry and education.

Acorn Word Processor View **£59.00**

This Rom based word processor has many advanced features including macros, still one of the best available on the market.

Acorn Spreadsheet Viewsheet **£59.00**

A new spreadsheet from Acornsoft comes in a 16K Rom with a comprehensive manual, it is compatible with view and the 6502 2nd processor.

Mass Marco Assembler **£35.00**

A superb machine code assembler in Rom, includes comprehensive manual where the user is introduced to Mass and given step-by-step guide to writing source code and assembling it using Mass. Also includes a utility disc with many useful routines.

All prices include VAT and delivery

BOOKS FOR PERSONAL COMPUTER OWNERS

Games Programming

ERIC SOLOMON

A lively book that will liberate you from the restrictions of interpreted languages such as BASIC and carry you forward to real programming. **Paperback £7.95 net**

Fun Mathematics on Your Microcomputer

CZES KOSNIOWSKI

A whole range of intriguing games all written in BASIC that will painlessly develop your mathematical and computing skills. **Spiral bound £4.95 net**

A Child's Guide to the BBC Micro

JOHN DEWHIRST

A much-praised, highly-illustrated introduction to the BBC Micro's keyboard, memory, and ability to act as both calculator and typewriter. **Paperback £3.95 net**

A Child's Guide to the ZX Spectrum

JOHN DEWHIRST and ROSEMARY TENNISON

A lively guide containing plenty of project ideas and suggestions for children to develop—draw pictures, tell jokes, play tunes, even try your hand at running a game park! **Paperback £3.95 net**

A Child's Guide to the Electron Micro

JOHN DEWHIRST

Designed for children from seven upwards, the simplicity and straightforwardness of this book make it indispensable as an introduction to programming. **Paperback about £3.95 net**

Forthcoming

The ZX Programmer's Companion

JOHN and CATHERINE GRANT

For anyone wondering whether to buy a personal computer, or for those who wish to realise the full potential of the machine they already own, this book will be an ideal companion. **Paperback £6.95 net**

CAMBRIDGE UNIVERSITY PRESS

AIRLINE: OUT-LAKER


THE OPPOSITION

'Airline', Cases Computer Simulations, Model A or B, tape £6.95

FROM the cover picture of a Concorde nose-diving out of the sky, you might be forgiven for thinking that *Airline* is the latest marketing twist – a disaster movie computer program! Not so. *Airline* is a business game in which, as the blurb says, the object is to be more successful than Sir Freddie Laker.

You are chairman of L-AIR, a small struggling airline with initial capital of £3 million. Within seven years – not real time! – you have to try and increase your net assets to £30 million.

At the beginning of each financial year you are presented with a graph of the forecast passenger payloads, from



which you choose the best number of aircraft to operate. For the first year of trading you don't have enough money to buy an airplane outright – they cost £10m each – and so you have to charter the required number, referring to a graph of charter rates. In more profitable years you have to decide whether it is cheaper to hire or buy aircraft, and in this case a graph of loan interest rates can be studied.

In a similar fashion the manning, maintenance and insurance levels have to be chosen: too low means some flights might need to be cancelled, too high and the cost might be crippling.

At the end of the year the accounts are closed and a balance sheet gives L-AIR's overall performance before you start a new financial year. If you lose £10m in one year, as I did, however, the receivers are called in and the company is liquidated!

A nice touch in the program is a 'ticker tape' which occasionally crosses the screen with telex messages – OPEC increase oil prices, for example. Two versions of the program are on the tape: the basic version for

model A, and one for the B with graphs of interest charges and 'chairman's statements' at the end of each year.

Airline features excellent use of graphics, simple instructions and a fair degree of financial realism. It is quite compulsive!

Geoff Nairn

FROG ON THE RUN

'Hopper', Acornsoft, BBC B and Electron, £9.95 (disc £11.50, ROM cartridge £20)

HOPPER is one of my all time favourites having been around in both BBC and Electron versions since the dawn of both machines. Perhaps its popularity has been partly due to the fact that it was also one of the original arcade games that everyone used to play in pubs, clubs and amusement arcades in those pre-home computer days.

The object of the game is to hop your frog, coloured green of course, across a busy motorway onto the riverbank avoiding the crushing wheels of four lanes of congested and fast-moving traffic. Fast-moving logs and turtles' backs provide the only refuge as you leap from one to the other in an effort to jump carefully into one of the five froggy lairs. Fail at any point and you're a gonner! Of course you do have the three obligatory lives and once you have successfully transferred five frogs into their lairs they disappear at two hundred points a go.

The game restarts at this point but is of course much more difficult! This time you must avoid the snake that crawls along the riverbank, beware of submerging turtles as you leap onto their backs and look out for a hungry crocodile that moves invisibly from lair to lair!


Too simple? I forgot to tell you there is a time limit to all this, a clock which counts rapidly down from 400 in about 15 seconds, if you're not safely home by then, well bye bye froggy!

Another nice aspect of *Hopper* is the musical accompaniment which sounds good even on the Elk.

A joystick is best but otherwise four keys are enough to move froggy left, right, forwards and backwards, so there are no problems with knotted fingers.

As a simple relaxing family game I reckon you can't go far wrong with this one.

Bruce Smith



FRENZY IN


THE LABORATORY

'Frenzy', Micropower, BBC B, £7.95

IN THIS game, deadly sub-atomic particles are loose in a scientific research centre. These particles are called Leptons. You must manoeuvre a robot-controlled craft around the laboratory, and trap the Leptons. The craft leaves an ion trail behind it and the area enclosed by the trail is filled in. If a Lepton is enclosed in this area, it is destroyed. You may also capture a Lepton by filling in 95 per cent of the screen. You are pursued by Chasers who follow your trail, and will kill you if you meet them.

The graphics are poor. Your craft is a square, a Lepton is a bouncing line, and a Chaser is a block. However, the movement is smooth, and without flicker.

The game's flexibility is also poor. The only option you're given is a sound on or off option. It would have been nice



to have had a joystick option, and possibly even a difficulty level.

The sound, though, is the best aspect of *Frenzy*. There are effects for starting, moving around, filling in areas, bonuses, and being killed.

The control of the program is very easy. There are five keys to operate, four for movement, and one to leave a trail. The keys are well spaced, and very responsive.


Overall, the graphics aren't up to the standard I would expect from a BBC game, with the BBC's graphics potential. Neither is the flexibility of *Frenzy*, though the sound is quite impressive, the controls are easy, and it is supplied with clear instructions. *Frenzy* isn't really original, in that it reminds me of *Demon Decorator* by the same company. Even though I am not thrilled with *Frenzy*, it has something, though I don't know what, which makes it quite an addictive game. In my opinion, *Frenzy* rates 65 per cent. Ian Brettell

SPECIAL OFFER!

Order both directly from us and deduct £1 from each.

TWO SENSATIONAL NEW RELEASES FROM SUPERIOR SOFTWARE

**BBC
MICRO**






OVERDRIVE (32K)

£7.95

A highly-addictive multi-stage 3D race game. You steer your car left and right, accelerate and decelerate as the opposing cars weave about the road. There are five different stages including night, snow, desert, and riverside scenes. To qualify for the next stage, you must finish in the top twelve. Incredible graphics give the impression that you really are taking part in the race. Highly recommended, and destined to become another top-seller for Superior Software.

●●●NEW RELEASE●●●

OUR PROGRAMS ARE NOW AVAILABLE FROM OVER 1000 OUTLETS THROUGHOUT THE UK AND OVERSEAS. SEE YOUR LOCAL DEALER!



BATTLE TANK (32K)

£7.95

An excellent game, made possible on the BBC computer only by the unique use of a dual-screen display and specially written plotting routines. You are a tank gunner looking out onto a mountain plateau. You see the distant mountains and the pyramid obstacles – and also the enemy tank. Your task is to shoot it before it shoots you. A scanner is displayed in the bottom right-hand corner of the screen. This displays the position of the enemy tank relative to you. You can then turn to get the tank in view. The next stage is to position the tank in the rectangular viewfinder by fine adjustments of your controls.

(KEYBOARD or JOYSTICKS)

●●●NEW RELEASE●●●

WE PAY UP TO 20% ROYALTIES FOR HIGH QUALITY BBC MICRO AND ELECTRON PROGRAMS



SUPERIOR SOFTWARE LTD.

Dept. AU5, Regent House,
Skinner Lane, Leeds 7
Tel: 0532 459453

OUR GUARANTEE

- (1) All our software is available before we advertise.
- (2) All our software is despatched within 48 hours by first-class post.
- (3) In the unlikely event that any of our software fails to load, return your cassette to us and we will immediately send a replacement.

SPECTRUM OF USES FOR BLACK BOX

Interbeeb versatile interface, MCP Microdevelopments, BBC B, £69.95 (basic unit)


DCP Microdevelopments has produced an interface pack for the BBC micro which has such a range of applications that it is difficult to know where to start. Perhaps the best place is with the little black box containing all the hardware.

The black box, which measures 120mm × 80mm × 40mm, contains four switch inputs, four relay outputs, an eight-bit input port, an eight-bit output port and a medium speed, eight-channel analogue to digital converter (ADC). It also has an expansion bus which allows the use of add-on units such as digital to analogue converters and very fast ADCs.

The Interbeeb is connected to the BBC micro's 1MHz bus and is supplied with cable and a separate nine-volt power supply. The addresses used for the interface are those recommended by Acorn, the eight-bit input and output port having the same address (&FCC2)! No confusion occurs though, because if you write to the address, it outputs the data to the output port, and if you read it, you are reading the data on the input port. The voltage levels for the data are 0V and 5V, ie TTL levels. The output port will supply (source) a maximum current of 2.6mA when the output is at logic 1, but will sink 24mA when the output is low, ie logic 0.

The switch inputs are all held at a low voltage level, logic 0, by internal resistors so the user has to connect these through switches to the +5V line. The internal 5V line is terminated close to the switch inputs for easy access.

The four relay outputs are all on-board with their contacts brought out to the edge of the board on 2mm sockets. One line is common to all the relays which are each capable of switching



Interbeeb with power pack, AD and DAC packs

voltages up to 12 volts (ac or dc) and currents up to 1A. The address for the switch inputs and for the relay outputs is &FCC1 with an arrangement similar to the input and output ports, ie writing to the address sets the required relay(s) and reading from the address reads the switch settings. Differentiating between individual relays or switches is achieved by the 'value' assigned to each. For example, the relays have the values 1, 2, 4 and 8 respectively, so to turn them all on, you use ?&FCC1 = 15; similarly to read the switch inputs use switch% = ?&FCC1 to store the value in the variable switch% or PRINT ?&FCC1 to display the value on the screen. If, for example, switch% = 6 then switch inputs 2 and 3 are high (+5V).

The eight-channel ADC has an eight-bit resolution and uses address &FCC0. Conversion is started by writing to this address with a ?&FCC0 = n instruction, where n is the channel number required. The data is then read by an expression such as ADC% = ?&FCC0

(or PRINT ?&FCC0), ADC% returning with the conversion value. The manual quotes the conversion time as being less than 100µs, and on the unit we had for review it was faster – 64µs.

Expansion is via the 'DCP bus' and extra units are simply plugged in. Units available include a very fast analogue to digital converter (AD-Pack) with a conversion time of 10µs which makes real-time processing of audio signals a possibility, and a digital to analogue converter (conversion time 1µs!). Also available are a connector pack for ease of connection to the DCP bus, input and output ports, and an LED indicator pack.

DCP Microdevelopments also makes an Interspec interface unit which is similar to the Interbeeb but for the Spectrum. The facilities on the Interspec are identical, and all the expansion units are cross compatible. Thus it would be possible to develop a project on the BBC machine using Interbeeb and, with the necessary modifications to the Basic program, run it on a Spectrum fitted with an Interspec pack, so you are not tying up an expensive computer for a dedicated task.

The interface is extremely versatile and sufficiently robust to stand up to the sort of wear and tear it might receive in a school laboratory. All in all, a good investment, and although it may seem a little expensive, remember that all peripherals have been affected by the recent rapid rises in the prices of integrated circuits.

Paul Beverley

Prices including VAT (post and packing £1.95)

Interbeeb with 9V mains power supply	£69.95
Interspec	£49.95
Fast A to D pack	£19.95
D to A pack	£19.95
Connector pack	£2.95
LED pack	£0.99

For information contact: DCP Microdevelopments Ltd, 2 Station Close, Lingwood, Norwich NR13 4AX. Technical enquiries should be made on Cambridge (0223) 833902 or Hemel Hempstead (0442) 64225. Educational enquiries to Griffin & George, who also supply the Interbeeb, Interspec and the expansion units.

A World Of Information

Available to you with Nightingale, the new multi-function modem from Pace.

Nightingale is by far the most versatile modem available, at the price, for either home or business use. It offers Prestel/Viewdata baud rates (1200/75 & 75/1200) alongside 300/300 baud full duplex for communication between the BBC and other computers, including bulletin boards.

Nightingale will operate at both European and Bell frequencies for compatibility with CCITT and American systems.

The state-of-the-art modem chip technology employed in Nightingale requires minimal support circuitry resulting in low power consumption, low cost, high quality and extreme reliability.

Nightingale being 'hard wired' is not subject to the noise interference errors common to outdated acoustically coupled devices. In addition Nightingale features a simple self test facility for easy installation.

Nightingale utilises a fully buffered RS 423/232 serial interface and is supplied complete with a lead suitable for connection to the BBC micro, other leads are available on request.

However, in order to use such a versatile modem to its fullest potential, you will require equally sophisticated software. This is where Pace can offer you a total solution — Commstar, unquestionably the most comprehensive communications software available for the BBC.

Supplied on Eprom, Commstar is instantly accessible, simple to use and extremely flexible. Just look at the possibilities: access Prestel, Micronet, Viewfax, Homelink and Telecom Gold, rummage through bulletin boards and chat to literally thousands of other computer users, but there's more. Commstar can be used to emulate specific terminal types such as VT 100 by means of a configuration disc, thus providing the opportunity to use the BBC as an inexpensive workstation for a main frame or mini-computer.

The complete Nightingale/Commstar package for the BBC micro including the modem, cabling and the Commstar Eprom and manual is just £139 plus V.A.T. Nightingale is available separately for the BBC and other computers at £119 plus V.A.T. and Commstar is £29.57 plus V.A.T. Further details are available, please telephone or write for comprehensive fact sheets.



PACE

PACE SOFTWARE LTD.
92 NEW CROSS STREET,
BRADFORD BD5 8BS.
Tel. (0274) 729306 Telex 51564

This modem incorporates the very latest in communication technology and is therefore not yet B.A.B.T. approved.



ELBUG FOR THE ACORN ELECTRON

JOIN NOW FOR A FREE CASSETTE

Join the Electron User Group

Members receive 10 copies of the magazine **ELBUG** each year. **ELBUG** is devoted **EXCLUSIVELY** to the **ELECTRON MICRO**. It is packed with News, Reviews, Hints, Tips, Programming ideas, Major articles, plus Regular program features including games and useful utilities.

ELBUG is produced by **BEEBUG** Publications Ltd., publishers of **BEEBUG**, the magazine of the National User Group for the BBC Micro. **BEEBUG** now has some 20,000 members and has achieved a high reputation both in this country and abroad.

The formula which makes **BEEBUG** an invaluable companion for users of the BBC micro, has been applied to **ELBUG**.

By subscribing to **ELBUG** you gain all the advantages of a single-micro magazine, with

no space wasted on programs and articles for other computers.

BENEFITS OF MEMBERSHIP

ELBUG MAGAZINE

Ten copies a year mailed free of charge.

DISCOUNT SCHEME

Extensive discount scheme with major retailers.

SOFTWARE LIBRARY

A growing range of software titles at budget prices for members.

SOFTWARE CLUB

Substantial discounts on software from major software houses.

LOCAL USER GROUPS

Lists of local affiliated user groups.


SPECIAL OFFER 8 FREE PROGRAMS

Subscribe now, and get a free introductory cassette containing 8 tested programs for the Electron.


1. **SPACE CITY**. Defeat the invading Aliens with your laser, and save the city
2. **3D NOUGHTS AND CROSSES**. Pit your wits against the **ELECTRON** on a 4x4x4 board
3. **RACER**. Guide your racing car to victory, avoiding other cars and obstacles on the track
4. **3D MAZE**. In this challenging game, you must escape from the maze - The screen displays a 3D view from inside the maze
5. **PATCHWORK**. A multicoloured display of continuously changing patterns
6. **KEY SET ROUTINE**. A program to set up the user function keys
7. **MEMORY DISPLAY**. An efficiently written utility to display the contents of memory (ROM and RAM)
8. **CHARACTER DEFINER**. Define individual graphics characters with this useful utility for use in your own programs.



SPACE CITY



RACER



3D MAZE

HOW TO JOIN

To subscribe for one year, and get your FREE CASSETTE send £9.90 (payable to Orbit) plus a strong stamped addressed envelope (for the cassette)

SUBSCRIPTIONS TO: ELBUG, DEPT 13, PO BOX 109, HIGH WYCOMBE, BUCKS

Six months trial subscription (5 issues) UK only £5.90 - FREE CASSETTE OFFER STILL STANDS.
Membership outside UK (one year only): Eire and Europe £16.00. Middle East £19.00. Americas and Africa £21.00. other countries £23.00.
Editorial Address: ORBIT, PO BOX 50, St Albans, Herts.


SUMMER MADNESS SALE FROM SCI(UK)

We challenge you to find a better deal!

EPSON PRICE SPECIALS

EPSON RX80 (DOT MATRIX).....	£249.00	£199 + VAT = £228.85
EPSON RX80FT (DOT MATRIX).....	£285.00	£229 + VAT = £263.35
EPSON FX80 (DOT MATRIX).....	£438.00	£324 + VAT = £372.60
EPSON MX100 (DOT MATRIX).....	£475.00	£355 + VAT = £408.25
EPSON RX100 (DOT MATRIX).....	£450.00	£385 + VAT = £442.75
EPSON FX100 (DOT MATRIX).....	£569.00	£499 + VAT = £573.85

DAISYWHEELS...at an incredible new LOW PRICE!



JUKI 6100.....just £329 + VAT = £378.35

20CPS:BiDirectional & Logic Seeking
10, 12, 15 & Proportional Spacing
Wordstar Compatible
2K Buffer: 13 inch Platen
Underline: Backspace + Lots more
Centronics Interface Standard

**THE DAISYWHEEL THAT
HAS NO COMPETITION**

OPTIONAL RS 232 TRACTOR AND SHEET FEEDER

We will match any Genuine Price Advertised—
SCI(UK) IS NEVER BEATEN ON PRICE

MANY MORE PRINTERS AVAILABLE - 1000s of SCI(UK) BARGAINS




send now for the FAMOUS SCI(UK) Catalogue

for the cheapest prices telephone 0730 63741 or 0730 61745



MORE SCI(UK) BARGAINS


SHINWA CP80....£179.00 + VAT = £205.58



Friction and tractor feed as standard
80cps
Bi-directional logic seeking
13 x 9 dot matrix giving true descenders
Sub and superscripts.
Italic printing and auto underlining
Condensed, emphasised, expanded and
double strike printing (can be mixed in a line)
Parallel interface fitted as standard

FIDELITY 14"

**COLOUR
MONITOR
& COMPOSITE
VIDEO**



£189.00 + VAT = £217.35

New from the world famous CANNON Company

CANNON 1080a NLQ DM best value ever at.....£289.00 + VAT = £322.35

**We have interfaces for all types of computers,
including CBM 64, VIC 20, APPLE, TRS 80,
IBM, BBC, SPECTRUM, QL, etc.**



**24 HOUR SECURICOR DELIVERY £9.50 plus VAT • BANKERS ORDERS, BUILDING SOCIETY CHEQUES, POSTAL
ORDERS — SAME DAY DESPATCH • ALL ORDERS COVERED BY THE MAIL ORDER PROTECTION SCHEME
NATIONWIDE MAINTENANCE CONTRACTS ARRANGED • EDUCATIONAL DISCOUNTS VERY WELCOME
It's SUNDAY - Do you realise you can order NOW - We are open 7 Days a Week.**

RANGEKEY LTD. Trading as SCI(UK)

DEALER ENQUIRIES
WELCOME
WRITE FOR DETAILS

SCI(UK)

SCI (UK) FREEPOST (No stamp needed)
PETERSFIELD HANTS GU 32 2BR

0703 61745

0730 63741

EXPORT ENQUIRIES
NO TAX
DELIVERY AT COST

Personal callers welcomed. 12 High Street, PETERSFIELD, Hants. Telex 86626 MYNEWS G

TALK WITH TORCH

FOR several years now Torch Computers has been shipping products based on the BBC micro. The company's original machine, known as the 'C' series, is a ruggedised BBC computer with expanded keyboard, Torch Z80 second processor and a sophisticated modem. Fairly soon after the C series, Torch released the Z80 second processor card in its own right, and has since shipped more than 10,000 of them to BBC micro owners.

Both the modem and the Z80 card were major selling points of the C machine, though its price of over £2,000 prevented it from selling in huge quantities. Only in the last few months has Acorn managed to get its Z80 card out, and during this time Torch has been the only consistent source of CP/M addons for the BBC micro. More importantly in this context, the modem was a tremendous boon to the machine. It is a Prestel-standard 1200/75 baud device with the all-important auto-dial and auto-answer capabilities.

When the C Series was launched Torch made great noises about the communications capabilities of the machine, and produced a piece of software called Torch Mail to prove it. Torch was in fact absolutely right: the machine is well suited to communications, and the Torch Mail package has been reasonably successful despite a lack of publicity. It is primarily the cost of the machine which I believe has prevented it from getting a lot of public attention, but that situation is soon to change. Torch owners can now use a major upgrade to the Torch Mail software known as, wait for it, Torch Mail Plus! And exciting stuff it is too.

'Hmmm . . . !' I hear readers saying: 'This is *Acorn User*, not *Torch User*'. True enough, and the important thing is that Torch has had the brains to offer a complete package to allow Torch Mail Plus to run on the BBC micro. What is more, it gets a new name, and properly re-written documentation. The Unicomms package, for that is it, will

The Unicomms package

Communications software (with OEL Telemod 2 modem) for a BBC micro fitted with the Torch Z80 pack:

Uniview: viewdata terminal program
Uniterm: electronic mail terminal program
Unimail: computer to computer program

EXCLUSIVE: Alex van Someren

reports on a communications pack

for the BBC micro developed by Torch



Torch C series computer: first with built-in modem

run on a BBC micro with dual drives and a Torch Z80 second processor (no Acorn ones I'm afraid). So the Editor sent me up to darkest Shelford to have a look at it.

Unicomms

The Unicomms package consists of an OEL Telemod 2 modem (no auto-dial or auto-answer, but more on that later), a lead to connect it to your BBC machine and three pieces of software with associated manuals. As I said above the manuals are genuine re-writes, rather than daisy-wheeled versions with every occurrence of 'Torch' replaced with 'BBC micro', which makes a pleasant change. The software is nothing short of gorgeous: just what the doctor ordered with menu-driven controls, pop-up 'Help' windows and screens that change colour to tell you what's going on.

Uniview

Uniview is a viewdata terminal program (ie Prestel, Micronet, etc) which does everything possible for you. It opens up with an 8-column menu of host computers (by name) and switches to mode 7 when you go on-

line. While it can remember telephone numbers for you, it cannot dial them, so after prompting you with the number of the selected host it waits for a carrier tone on the line. After that Uniview will log you on automatically from a stored sequence that was entered previously and which it has saved to disc.


There isn't much you can say about a Prestel terminal in terms of how it looks: pretty standard stuff. Interestingly though, Torch has solved the flicker problem in mode 7 (Acorn doesn't seem to know how) and provide a control-key toggle to turn it on or off.

There are facilities for page saving to disc, happily more than one page per file, and subsequent reviewing is also implemented. Files which have been prepared off-line can be sent up to the host (useful for rude messages to Micronet) and standard format telesoftware can be downloaded to disc for future use. The text part of the screen can be dumped to a printer, but because of the variety of printers in use there is no graphics dump.

Both a Quit facility (which just 'hangs up' the call) and a Logoff command (which can be programmed to send a sequence of characters such as *90£ or whatever) are there. The Reveal function is also provided in software.

microFAST LATEST BARGAIN PRICES


MONITORS



£75
inc VAT

Monochrome	
Sanyo DM2112	£75
Sanyo DM8112CX	£103
Teco with Zoom	£105
Colour	
Microvitec 1431/1431QL	£197
1431 (RGB/PAL/AUDIO)	£225
Microvitec 1451/1453QL	£309
Fidelity CM14	£209

DISK DRIVES




£145
inc VAT

Single	
100K Chinon 40T	£145
200K Sankyo 3" 40T	£190
400K Cumana 80T	£215
400K Mitsubishi 40/80T	£229
Double	
400K Sankyo 3" 40T	£374
800K Cumana 80T	£409
800K Mitsubishi 40/80T	£439

Floppy Disks	
3"	£4.50
5 1/4" S/S 40T	£1.80
5 1/4" D/S 40T	£2.10
5 1/4" D/S 80T	£2.90

TV/MONITORS



£280
inc VAT


ITT RL2301 **£280**

VARIOUS

Torch Ext. Processor + Software	£299
Torch Ext. Processor + software + twin drives	£749
Computer Concepts ROMs	from £32
Acorn Business Software	£24
Acorn Data Recorder	£32

Also various computer desks
and stacking units available


DOT MATRIX



£219
inc VAT

Star Gemini 10	£249
Star Delta 10	£365
KDC FT-5001	£234
Epson RX80	£219
Epson RX80 F/T	£249
Epson FX80	£379
Mannesman MT80	£225

DAISYWHEEL




£249
inc VAT

JUKI 6100	£375
Silver Reed EXP500	£315
Daisy Step 2000	£249


Plus	
JUKI Sheet Feeder	£239
JUKI Tractor Feed	£109

Serial Interface Conversions	
8143—Epson	£30
8148—Epson (2k buffer XON/XOFF protocol)	£65
JUKI	£55
Plus cables from	£12

PROCESSORS



BBC Model B	£399
BBC 'B' with DFS	£469
Acorn Z80 Ext. Processor	£299
Acorn Electron	£199
Torch Unicorn Package	P.O.A.




ALL PRICES INCLUDE VAT

Prices shown are for cash & carry sales and are correct at
time of printing.

Export price list available
Mail order and credit cards accepted
OPEN 9-6 Monday to Saturday

57 Hoxton Square
London N1
Tel: 01-729 1778

DISK INTERFACES



Kenda Mighty Oak	£90
Kenda Professional (double density)	£130
Acorn DFS Kit	£97

BUSINESS SYSTEMS

A.C.T. Apricot
Processors and
Business Systems
assembled to your
specification. Price
dependent on
equipment supplied.
Call us to discuss your
requirement.

microFAST

THE EXPERTS

Uniterm

Uniterm is a terminal emulator for purely text-oriented systems and works within the same basic framework of menus and windows as Uniview. Several extra features such as baud rate settings are provided (not to be tried with the OEL modem though), and a Conceal key to prevent friends/family reading your password as you type it in.

Another key allows text from the host to be spooled to disc, and it appears highlighted on the screen for as long as this is happening. Alternatively, the session can be printed to a parallel printer (the RS232 serial port is already in use, remember). Files may be sent up to the host after off-line preparation, and Telecom Gold users will probably understand what a boon this is.

Again, both Quit and Logoff functions exist, saving time and trouble if your route to the host is made through more than one system.

Unimail

Unimail is the real *pièce de résistance* of this system. It is a highly sophisticated electronic mail package and contains far more functions than we have time for here.

Torch Mail Plus, on which Unimail is based, is the result of about three years of continuous use by Torch and customers alike. As a result it is both versatile and easy to use. Messages and files can be exchanged between Unimail/Torch Mail/Torch Mail Plus systems by dialling them up and then getting the machines to converse in 1200baud blocks of data. The remote system can allow a variety of kinds of access to its files by means of a number of different passwords, everything from total prohibition of use, to the ability to copy files in both directions.

While there is a mind-boggling array of software switches and options, most of them have sensible default values. It is usually possible to hit the return key to set a parameter that you don't want to worry about and this makes life that much more pleasant.

Conclusion

While Uniview and Uniterm provide fairly standard features, they have been executed extremely well. Unimail on the other hand is both absolutely extraordinary and particularly well thought out. I was surprised that more noise has not been made about this package. It will cost about £180, and that can only be a bargain when you consider that the modem costs £85 alone. This product surely deserves to be a winner, and I have every confidence that it will be.

MODEM LOWDOWN




LEFT: The OEL modem is fairly typical of the latest products. The three lights on the left are: POWER – indicates the modem is switched on; CARRIER – lights up when a signal is being sent or received; LINE – when the switch is thrown, the modem is ready to receive or send.

The MODE switch chooses between: PRESTEL – 1200/75baud 'full duplex' standard for Micronet, etc; Tx/Rx – for personal micro to micro communications at half duplex. The only baud rate the modem allows is 1200/1200 for this; Rx – Receive only. Also allows the user to echo messages on the monitor.

163

BELOW: behind the modem. The connector from the phone plugs into the back of the modem. The lead on the right goes from the modem to the new-style BT wall socket (right). The DATA socket in the middle is the RS232 connection which goes into the BBC micro. To the left of this is the fuse and on the very left the power plug.

The RS232 connector has to be purchased separately for the BBC. OEL packages this in with terminal software for £14.95 (cassette), £18.40 (disc) or £19.95 (ROM).



Look out for this sticker (right) on any modem that you buy – it's the official B.A.B.T.-approved sticker, and any modem without it cannot legally be used on the telephone system.

APPROVED for use with telecommunication systems run by British Telecommunications in accordance with the conditions in the instructions for use.

B.T. Approval No. S/1399/3/D/021907



More drive from Broadway.

DISC DRIVES FOR THE BBC MICROCOMPUTER



The Broadway Drive, already in use all over the world by many leading Colleges and Universities, is now available at more competitive prices than ever.

All drives include the Broadway publication "Making the most of your BBC Disc System" and accompanying utilities disc (available separately at £30. per set), and offer the back-up that has made Broadway one of the principal Acorn and BBC dealers.

All 80 track drives are 40/80 compatible, and the unique Broadway 500 will write 80 to 40 tracks. Already in use by many leading software houses.

CHOICE OF 5 MODELS

- * 100 K SINGLE 40 TRACK
- * 200K DOUBLE 40 TRACK
- * 400K SINGLE 40/80 TRACK SWITCHABLE
- * 800K DOUBLE 40/80 TRACK SWITCHABLE
- * NEW 100 K 40 TRACK PLUS 400K 40/80 TRACK SWITCHABLE

Ready to use, includes: Manual, Format Disc & Leads



Broadway

ELECTRONICS Aston Road, Bedford, Beds MK42 0LJ. Telephone: (0234) 58303. Part of the Mushroom Computer group of Companies.



'Almost the real thing' by Malcolm Banthorpe. Because Malcolm is now a regular author – and has won a prize in Micro Gallery before, we've had to exclude his entry. However, we've printed it because it shows what's possible if you try.



Malcolm started with a wire-frame cylinder drawn at a suitable orientation on his own software. This wire-frame structure was used as a three-dimensional grid for superimposing the lettering and other surface detail with a Graphpad graphics tablet.

An ellipse-drawing routine was used to achieve the curves of the lettering. Highlights and shading were added by the Graphpad with Gaelsett's ECFG program.

165

READERS' PICTURES

MICRO GALLERY is an occasional feature showing screenshots of graphics produced by readers. All entries printed receive software as prizes. There are few rules, but entries should be provided on cassette or disc with a short note on how the picture was developed. It also helps us if you can provide a transparency. Send your entry to: Micro Gallery, Acorn User, Redwood Publishing, 68 Long Acre, London WC2E 9JH. Please enclose a stamped addressed envelope if you want your entry returned.




1ST. Lion, Train and Cat by Ron Owen from Middlesex. Congratulations to Ron on a series of pictures – three of which are shown here. They were all plotted in mode 2 using a combination of freehand drawing, pixel plotting, colour fills and user designed graphics. Ron wrote the software to use with Joe Telford's lightpen from AU March '83.

2ND. 3D membrane by Alain Noullez from Belgium. Pride of place goes to another sequence, this time showing the results of stretching a membrane by 3D objects. Alain wrote the software himself in Basic. The type and number of objects used and the membrane can all be altered.

3RD. Goblets by Ranjan Bhattacharya. This is a shot from an animated program which draws the goblets one by one and rotates them about their stems. Ranjan used a similar technique in his entry showing a rotating planet.

SOLIDISK SIDEWAYS RAM: 8,000 UNITS SOLD



"Exciting" (ACORN USER JAN 84), "Power to your Beeb" (PCN 61, MAY 84)

HOW ABOUT COMPATIBILITY?

The Sideways RAM is completely compatible with all issues of BBC computers, disks, all sideways ROMs, second processor, Torch disk pack, Teletext, Econet etc. but NOT with ROM extension boards, since it can replace them.

Its power consumption is so low that you can use it in conjunction with twin disks.

HOW DOES IT WORK?

Occupying the same place as sideways ROMs (such as BASIC, DFS, CPN etc), it is treated like other Sideways ROMs and therefore can replace them.

The Machine Operating System uses Sideways RAMs as naturally as Basic, without procedures or programming rules.

Sideways RAM can run any language, any filing system including Hi-Basic and second processor DFS.

SIDEWAYS RAM POWER IS IN THE SOFTWARE:

Different from Sideways ROMs, Sideways RAM can be written into. This property gives birth to a NEW GENERATION of software for the BBC computer: SERVICE RAMs and VIRTUAL MEMORY PROCESSOR.

Each SERVICE RAM has its own commands and code as its counterpart Sideways ROM but has its own private workspace and storage area thus leaving you with the lowest possible PAGE value (PAGE=&E00). On the other hand, the Virtual Memory Processor can run huge MACRO BASIC programs (Megabytes are not the limit), keep them on disk and uses the basic 32k of RAM as transient program area. All software for the Sideways RAM system is free.

FREE SOFTWARE?

Solidisk Sideways RAMs is bundled with lots and lots of software, FREE and we mean FREE, now and later. It is quite simple: for every Sideways RAM sold, £1 is spent on MORE software. Sideways RAM users are invited to spot new applications and contributions are rewarded at the usual rate of £1 for every 4 bytes of machine code.

The result is printed on the opposite page.

HOW ABOUT THE FUTURE?

Solidisk Sideways RAM is also widely used in schools for ECONET stations, by professional programmers for writing programs, research laboratories for RAM disk data base, at home for wordprocessing and now even games.

New areas are being developed: Telesoft and Teletext logging, Speech Processor assembler and Relational Data base to cite a few.

As the price of 16k EPROMs are as high as £20 at the present time, more Sideways ROM software publishers will be willing to sell their software on disk. Solidisk will mail FREE OF ANY COST their advertisement to ALL Sideways RAM users providing the price of the Disk version reflects savings in the cost of the ROMs. Solidisk believes that the majority of BBC users will have their Sideways RAM fitted before the end of next year.

Also unlike other makes (SIR, APTL, WE Sideways ROM/RAM extension boards and the Aries B20), Solidisk Sideways RAM is expandable from 16k right to 128k and now to 208K. As a result of VLSI technology and volume of sales, Solidisk products also have a lower shop price than any other products.

OTHER PRODUCTS FROM SOLIDISK:

UVIPAC EPROM ERASER:

Uvipac is powered by the mains, simple to operate and can erase 3 Eproms of any type in just 15 minutes. Uvipac is ideal for home use.

DETACHABLE KEYBOARD CASE:

Remove the keyboard from the BBC computer and instal it in the new case. Replace the old 3" keyboard tail by the new 24" cable and you can work really in comfort even for very long hours. The keyboard case is more a productivity tool than just ergonomics.

CPU CASE:

Replace the top of the BBC computer case by this metal CPU case. Sit your monitor on top (it is tough enough to take even your weight!). The CPU case has 2 compartments for half height 5.25" disk drives with fixing screws, air vents and provision for a bolt-on fan. At first sight, there is no trailing wire. Looking inside, there is enough room to accomodate Teletext Adapter, Second Processor, Solidisk and a fan!

DOUBLE DENSITY DISK INTERFACE:

2 versions of this double density interface will be available: as direct replacement for the Acorn Disk Interface (Version A) and as a Second Disk Interface (Version B) adding to your existing interface. They all use the same Western Digital controller chip (WD1770).

Price £39.95 inclusive


DISK DRIVES:

3 models are being offered:


STL55A: 40 tracks single sided, SLT55F: 2 x 80 tracks, double sided and the best of mini floppy technology STL320: 2 x 160 tracks, double sided.

All disk drives are supplied with cables, formatter disk, head cleaning kit and 2 year warranty.

"Break the Ram Barrier" (A&B)



UVIPAC EPROM ERASER



TEAC DISC DRIVES FD55 Series



WHICH SIDEWAYS RAM DO YOU NEED?

Solidisk Sideways RAM is available in 16 (SWR16), equivalent to 1 sideways ROM, 32k (SWR32), equivalent to 2 sideways ROMs, 128k (Solidisk), equivalent to 8 sideways ROMs and the 208k Solidisk equivalent to 12 Sideways ROMs. You can buy a small Sideways RAM now and upgrade it later. From the SWR16 to the SWR32 is by straight exchange, from the SWR32 to the Solidisk is by adding the 96k Solidisk Extension, from 128k to 208k is by exchange of the RAM card.

FREE SOLIDISK SOFTWARE:

WORD64:

WORD 64 is a Service RAM, it uses Solidisk as storage for WORDWISE, up to 64K free characters for any text.

SILEXICON:

SILEXICON is a Spelling Checker for Solidisk. SILEX scans texts at more than a 1,000 words a minute and compares each word against the dictionary, Silexicon marks the mis-spelt words for either addition to the dictionary or eventual correction.

PRINTER BUFFER:

PRINTER BUFFER is a Service RAM, it increases 500 times the normal 32 bytes printer queue to 15K bytes, completely transparent to the user. PRINTER BUFFER is as useful for printing a long document as for a short program listing.

STLEO:

STLEO is a Service RAM, it is Disk Filing System that leaves PAGE at &E00, has built-in disk formatter/verifier and automatic track stepping for 40/80 track disk drives.

STL150:

STL150 is a Service RAM to enhance Acorn's .90 DFS to offer up to 150 directory entries per side.

STL-RFS:

STL-RFS (RAM/ROM filing system) is a Service RAM and an innovation in portable applications. STL RFS saves any program in a Sideways ROM format, it can then be copied onto EPROM to give instant recall of your programs. Plug this EPROM into any sideways socket, type *RFS and it runs itself. Compatible with the ELECTRON and BBC, tape and disks, SWR16, SWR32 and Solidisk.

INDEX:

INDEX is a Service RAM, it stores all the entry points of one or several sequential data files such as mailing list, stock list, accounts etc, merges, sorts them in alphabetical order and gives instant access to any record. INDEX can handle 1,100 records of any size, any type, any number of fields.

MACRO-BASIC:

MACRO-BASIC is a program generator. You use a wordprocessor to create a command file which is then scanned by MACRO. MACRO uses other programs, subroutine libraries, text files (actually any or all files on your disks) as source to generate a bug free BASIC program which can be very large (Megabytes are not the limit).

VIRTUAL MEMORY PROCESSOR:

VIRTUAL MEMORY PROCESSOR (VMP) uses extensively overlay technique and Solidisk as back store for very large programs that cannot be run otherwise. VMP uses the 32k basic RAM as transient area: it operates on a Main Program as generated by MACRO-BASIC, taking different segments from the Solidisk Store, POOL, HOLD, FREE or CLEAR segments from the transient area. For example: VMP will accept 20 segments of 10k of Basic assembler and assembles it into 16k of machine code.

MENU:

MENU puts all computer's resources at your fingertips. MENU displays your Sideways Firmware, Disk Directories, Sideways RAM system, Solidisk System etc.

MORE FREE SIDEWAYS RAM SOFTWARE TO COME:

While others are making promises for software to be written, Solidisk Systems RAM comes with a complete, novel and powerful software package including compatibility with existing sideways software.

Each Sideways RAM is accompanied by the Sideways RAM User Manual, full 1 year warranty, 1 utility disc* and free mailing on all new publications from the Software Support Service.

*It should be understood that we cannot put as much free software on a 40 track single sided as on 80 tracks. The present software package require 160 tracks of storage and can be accommodated on ONE 2 X 80 track double sided diskette, only the most useful programs are supplied on other formats (ie 40 track single sided, 2 X 40 track double sided, 80 track single sided). Should you require the whole collection of free software, please place an order for extra disks.

For the technical minded: the Source Code and Technical Manual (3 floppies and a 300+ page book) price = £10, the SILEXICON EXTENSION PACKAGE (3 floppies and a 40 page manual, 30,000 word dictionary: English and French now, German and Spanish planned) price = £9.00. '4S' also publishes regular updated SWR utility discs at £3.00. Every user can do contract work for the SUPPORT SERVICE and make a lot of money for him/herself!

HOW TO ORDER?

You can order any item using the coupon. Post and packing is only charged once. Access and Barclay card holders can place their order by phone. Educational authorities, Acorn dealers and OEMs can obtain quantity discounts.

Name:

Address:

Credit Card Account:

Callers are requested to ring first for appointment.


Total: £

If ordering more than one item, deduct £1 per item as post and packing cost is only charged once.


SOLIDISK TECHNOLOGY LIMITED
17 SWEYNE AVE
SOUTHEND-ON-SEA
ESSEX SS2 6JQ

SOLIDISK'S NEW TELEPHONE NUMBER:
SOUTHEND-ON-SEA (0702) 354674
(10 lines with automatic exchange)

HOW EASY TO INSTALL:



Push in the base unit



Connect the control wires

SEE US AT

The 2nd
Official
Acorn User
Exhibition

OLYMPIA
16-19 AUGUST
1984

PRICE LIST (including VAT and post & packing)

SIDEWAYS RAM:	
SWR 16K	£43.65
SWR 32K	£59.95
128K SOLIDISK	£150.95
208K SOLIDISK	£243.00

The following are upgrade prices for existing Sideways Ram owners:

16 - 32 (please return complete item)	£18.00
16 - SOLIDISK (please return complete item)	£109.00
32 - SOLIDISK (no return necessary)	£93.00
128K - 208K SOLIDISK	£93.00

DISK DRIVES:

STL55A (40 track, single sided, cased with cables, diskette, manual and 2 years warranty)	£142.95
STL55F (2 X 80 track, double sided, as above)	£232.95
STL320 (2 X 160 tracks, double sided, as above)	£499.00

FLOPPY DISKS (DATALIFE Verbatim):

MD525 (SS/DD 40 or 80 track) box of 10	£16.00
MD550 (DS/DD 40 or 80 track) box of 10	£22.00
MD557 (DS/DD 98 TPI) box of 10	£27.00

CPU CASE

DETACHABLE KEYBOARD CASE £27.99

EPROM PROGRAMMER (used with Sideways Ram)


UVIPAC EPROM ERASER (free standing unit) £20.95

2764 PACK OF 5 £36.00

SOURCE CODE + TECHNICAL MANUAL £10.00

SILEXICON EXTENSION PACKAGE £9.00

WE STOCK A LARGE RANGE OF PRINTERS AND MONITORS. CALL OUR SALES OFFICE FOR IMMEDIATE QUOTATION.





HIGH RESOLUTION THAT COMES HIGHLY RECOMMENDED.

"There is no doubt that the JVC range of ECM colour monitors is excellent value for money . . . there is no loss in quality of picture after long periods . . . and remember, as more and more resolution is available with new micros, the need for a better display will be that much greater."

High recommendation indeed from Personal Computer News. Meanwhile Acorn User said:

"It seems that all 'normal' and 'medium' resolution monitors, including the Sanyo, are simply inadequate to deal with the Beeb's graphics and text output . . . The JVC was excellent, giving clear, legible results . . . Was the JVC better than the Microvitec?* Would I buy one? Yes to both questions."

Our RGB high resolution colour monitor (580 x 470 pixels) sells for £229.95 (excluding VAT) – that's a saving of over £100 compared with other leading monitors of similar specifications.

The unit has a 14" screen and is suitable for the BBC Micro, Electron, Sinclair QL, Lynx, Oric, Apple, IBM and most other leading micros.

MODEL REFERENCE	1302-2 High Resolution
RESOLUTION	580x470 Pixels
C.R.T	14"
SUPPLY	220/240v. 50/60Hz.
E.H.T.	Minimum 19.5kv Maximum 22.5kv
VIDEO BAND WIDTH	10MHz.
DISPLAY	80 characters by 25 lines
SLOT PITCH	0.41mm
INPUT: VIDEO	R.G.B. Analogue/TTL Input
SYNC	Separate Sync on R.G.B. Positive or Negative
EXTERNAL CONTROLS	On/off switch and brightness control

And naturally there's a year's full guarantee.

If you order your monitor by post, you'll receive it within ten days by courier service.

Simply post the coupon below to: Opus Supplies Ltd., 158 Camberwell Road, London SE5 0EE. Or telephone 01-701 8668 quoting your credit card number. Or, of course, you can buy at our showroom between 9.00–6.00pm, Monday–Friday. 9.00–1.30pm, Saturday.

*Microvitec Cub 14" monitor.

To: Opus Supplies Ltd., 158 Camberwell Road, London SE5 0EE.
Please send me:

- _____ High Resolution Colour Monitor(s) at £229.95 each (ex. VAT).
 _____ Medium Resolution Colour Monitor(s) at £179.95 each (ex. VAT).
 _____ Connection lead(s) at £6.00 each.

I understand carriage per monitor will cost an extra £7.00. (N.B. A High Resolution Monitor including VAT, lead, and carriage costs £279.39. A Medium Resolution Monitor including VAT, lead and carriage costs £221.89).

I enclose a cheque for £_____ Or please debit my credit card account with the amount of £_____. My Access/Barclaycard (please tick) no. is _____

Please state the make of your computer _____

Name _____ AC23

Address _____

Telephone _____

Opus.
Opus Supplies Ltd.

We've been absolutely inundated with Free ads — something like four times as many as we can carry. This has led to long delays in publication and disappointment for readers. The free ads are carried in the magazine as space permits, so please allow up to four months for yours to appear.

Acorn User has been alerted to the abuse of the free ad service and, regrettably, can no longer accept entries selling or swapping software.

ACORN User magazines from issue No. 1 (July 1982) to April 1984. A total of 21 magazines in excellent condition. Telephone Gary with your sensible offer. Cophthorne 714678.

HOBBIT floppy tape system for BBC. Leads, manual, ROM plus six extra tapes. Cost around £170, will sell for £90 due to disc upgrade. Tel: 01-423 0745 (Harrow, Middlesex).

A BBC model B for sale. Plus over £400 worth of software, not used for more than 2 hours. Tell me your offer price. Write to B. Manavi, The Hall, Repton, Derby.

BBC B, disc interface, Hitachi 3 in drive, hi-res monitor as used on Apricot, Star Gemini 10X printer, Sanyo DR101 cassette recorder, Wordwise, Beebcalc, Discdoctor, Graphics, Gdumpp ROMs: cost £1,200, selling for £850. Tel: Nigel 061-485 3506.

THE ATOM magazine, No. 6 wanted. Will pay £2. Ring Andrew (0474) 812704.

BBC model B. Six months old. Many games and Wordwise, Basic two, 1.2OS manual, good condition, £390. Tel: Southend (0702) 64715, evenings.

TRS-80 model I/III and Genie Pascal compiler V5.3, £50 ono. Texas TMS 2564 EPROMs, £4. Video Genie and expansion, £330 ono. Write for details: Mike Tubby, 75 Oaklands Avenue, Droitwich, Worcs WR9 7BT.

ATPL sideways ROM expansion board. Unused, in original packaging. Plus Beebcalc ROM £49. Phone (0742) 342870 or write to Mike Robinson, 8 Cyprus Terrace, Sheffield S6 3QH.

BBC model A, with 32k, VIA, analogue I/O + 1.2 OS plus desk/console, software and magazines. Excellent condition, £265. Phone Wolverhampton (0902) 896335.

ACORN Atom, 12k/12k via, PSU, FP ROM, Utility ROM, latest keyboard. Boxed incl. manual, books and programs (Invaders, Cylon Attack, Snapper, etc), £80 ono. Tel: (0324) 711867 (Polmont, nr Grangemouth).

VIEW ROM with manuals in original box £40. Telephone Wantage (02357) 2774 evenings/weekends.

TRS-80 model III micro and recorder, manuals, cables, books and software, only £400. Will separate if necessary. Tel: 570 6393. 81 Broad Walk, Heston, Middlesex TW5 9AA.

BBC model B, Zenith green screen monitor, cassette, £60 software (Lisp, White Knight, games), Advanced User Manual, £425 ono or will split. 0703 617214.

BBC B, 100k disk drive (+ interface) and sideways RAM. Supplied with virtually all the ROMs, business, educational and games software on the market. Valued at well over £3,000, sell for £1,000. Phone (05827) 69152.

8271 disc controller chips for sale. Any offers over £40 considered. Ring Tone 0223 277520 after 6pm.

WANTED! Pets—two needed for school use. Must be fully working, large keyboard, any capacity. Can collect if price reasonable. Please contact Simon Thomas, Sawtry Village College, Sawtry, Huntingdon, Cambs. PE17 5TQ.

WATFORD 13-ROM board—perfect condition, with instructions, £25. Send cheque to P. S. Horner, 10 Carrington Avenue, York YO2 4SH. Tel: (0904) 797721.

VOLTFACE joystick and Voltmace interface, two weeks old, £25 or exchange for Wordwise ROM and manual. Tel: 041-946 9110 or write to Gordon Keenan, 61 Glenfinnan Road, Glasgow G20 8JG.

VECTREX. The complete portable games system, with built-in VDU, sound and joysticks. System complete with Minestorm, Hyperchase and Cosmic Chasm. A super bargain at £85, normally £165. Tel: Stonehenge 43343.

DISC drive 100k Olivetti (as for Acorn), £125. Includes all leads, formatting disc, manual plus £50-worth of software. Ready to plug in and go. Tel: 01-455 1069, evenings.

SHARP MZ80A for sale. Integral monitor and cassette deck. Original guarantee, virtually unused + manual and books, £300 ono. Tel: (0246) 450735, evenings only.

VIDEO Genie EG3008 (Z80A and 3.5 MH3), expansion interface EG3014, monitor, manuals, leads, circuit diagrams, tons of software, including LDOS 5.12, etc, £330 ono. Mike Tubby, 75 Oaklands Avenue, Droitwich, Worcs WR9 7BT.

FOR SALE. BBC B (OS1.2), boxed with lead, manuals, lots of software, magazines and books and dust cover, £395 the lot. Tel: Jason (0803) 28760, after 5pm.

ATOM software required. Mine destroyed. Nick Humphries, 51 Edgemoor Moors Road, Scunthorpe, South Humberside DN15 8ES.

BBC model B with DFS and Wordwise. Opus disc drive, with ten floppy discs. Four months old, hardly used. Worth £800, sell £600. Tel: 01-460 2104. Jim Scolly.

WANTED. Acorn Electron and manual in good condition, will pay £100. Write to A. Elliott, 59 The Mayfields, W-ton WV1 2JH or come round after 6pm.

WANTED. BBC disk drive or Teletext adaptor in exchange for Atari VS plus II cartridges, two joystick paddles (everything in good condition). Tel: 01-889 9887 after 5pm.

ZX81 (16k) RAM and programs, loading aids and manual, PSU, leads etc. Offers. Oric 1 48k RAM, programs, leads, manual. Offers. Big-ears and Chatter Box, with documentation, leads, etc. Offers over £80. Tel: (0689) 35353, evenings only.

ELECTRON. Boxed as new. Six months guarantee, plus software, plus back issues of Acorn User and Elbug Users magazine. Genuine reason for sale. Will deliver to London or Medway. £185 ono. Tel: (0634) 814540.

ATOM word processor ROM with manual, £10. Seikosha GP100 friction feed attachment, unused, cost £28—£10. Tel: (0274) 875976, after 6 pm.

BEST offer over £235 within five days of this advert secures my Electron, plus W. H. Smith cassette recorder, including leads, Money Management, Chess, software and Elbug magazines. Tel: (0794) 22755.

BBC B 1.2OS, Decca colour monitor, BBC cassette recorder. All 7 months old. Leads, plugs, programs, books, magazines, hardly used. No time. £500. Hughes, 1 Beechwood House, Bartley, Near Southampton. Tel: 812107.

ELECTRON books. Assembly Language Programming on the Electron, Ferguson & Shaw, £6. The Electron Book, McGregor & Watt, £6. Programming the 6502, Zaks, £8. Also Acornsoft's Snapper for the Electron, £6. Tel: (0792) 202187 (Swansea).

FREE PERSONAL AD SERVICE

Sell your old hardware or pass on information. Fill in the form below to a maximum of 32 words (one in each box) and send it to Acorn User Free Ads, 68 Long Acre, London WC2E 9JH. Use capital letters, and remember your name, address or telephone number. This is a service to readers—no companies please. One entry per form only, and we cannot guarantee any issue.



SENIOR SCHOOL EDUCATIONAL PROGRAMS

Developed in schools and now available to interested home micro users. Research has identified the compulsory exam topics, and professional programmers have coded these into exciting educational games which have been proven to effectively teach and entertain.

Now available for BBC B and ELECTRON. Each pack contains main program, extra self test program and Core Facts book for only £11.95 or any two for £19.95.

MATHS 1: TRY-ANGLES	Draughts style teaches angles ratios, tan, sin, cos. 25 levels
MATHS 2: COORDINATES	Battleship style teaches x and y in four sectors, directed numbers
PHYSICS 1: OHM RUN	Baseball style teaches D.C. Circuits, resistors, cells, V = IR, Series & Parallel.
PHYSICS 2: ISAAC	Gunnery style teaches mass, weight Newtons Laws and projectiles
GEOGRAPHY 1: MAYDAY	Orienteering style teaches O.S. symbols, grid references, bearings
GEOGRAPHY 2: WEATHER	Forecasting style teaches symbols, pressure systems, synoptic charts

Send your name, address, and cheque/P.O. to DEPT. A.
TUTORIAL SOFTWARE LTD., FREEPOST, WIRRAL, MERSEYSIDE L61 1AB.
Please state BBC B or ELECTRON

GUARDIAN SOFTWARE

presents

for DISK OWNERS SOURCE LIBRARY MANAGER (SLM)

A new concept in ROM based software for the BBC MICRO

Features include:

- ★ Stores and retrieves any amount of BASIC and/or ASSEMBLER source code, upto the full capacity of a disk (100/200k).
- ★ Creates a LIBRARY of upto 399 "members" per 80 track disk or upto 199 "members" per 40 track disk.
- ★ Allows upto 99 versions of a single program or routine.
- ★ Will simply and easily "construct" programs developed in a modular fashion.
- ★ Stores fully documented code which can be "stripped" when required for execution.
- ★ Uses 8 char names and a 20 char description for each "member".
- ★ Is fully menu-driven (i.e. no messy commands).
- ★ Includes 15 page Manual (A4 size) and fitting instructions.
- ★ Many other features too numerous to list here.

FULLY COMPATIBLE WITH 6502 SECOND PROCESSOR

IDEAL FOR BEGINNERS AND
EXPERIENCED PROGRAMMERS ALIKE

PRICE £36 (incl. p&p) or large SAE for Fact Sheet to:

GUARDIAN SOFTWARE
21 Harvey Road, Walton-on-Thames
Surrey KT12 2PZ

InterSoft

Utility Toolkit in ROM for the BBC Micro

A BRIEF SPECIFICATION

- * FIND — find any string or keyword in a Basic program
- * REPLACE — a string or expression with one of ANY length
- * LVAR — decimal or hexadecimal variable list
- * CRUNCH — compacts program into multi-statement lines
- * DEREM — one of three less drastic compacters
- * EXPAND — open up a gap in the line numbering
- * LSTERR — automatic error line listing ready for editing
- * MERGE — one programme to another, with auto renumbering
- * REPAIR — a 'Bad Program' and list suspect lines in it
- * SHIFT — a Basic program up or down to any page
- * KEYS — display defined key contents in editable form
- * MEMLOCS — print all pseudo-variables and memory free
- * LOCK — make a software protected cassette tape
- * PDUMP — a large scale Epson printer dumper with border
- * REMOVE — as Basics' delete but done instantly

Plus ten more useful utilities for program development and debugging. Compare these facilities and our price, then decide on the InterSoft U-TOOLS system.

Needs OS 1.20 (and a spare ROM socket)

£26.95 (Inclusive of VAT and P&P)

Send cheque or P.O. to INTERSOFT

26, Netherfield Road, Sandiacre, Nottingham. NG10 5LN

Trade enquiries welcome

VASM

The VASM System Vida Rebus 6502 Ass v2.0C Page: 0001

001 *H The VASM System
002 ;
; VASM is a complete DISC-BASED Assembler
; and INTEL file Locator System in ROM,
; especially designed for use with standard
; text editors such as View and Wordwise.
; With VASM it becomes possible to develop
; professional machine code programs in a
; professional way.

009
010
001 = 0011 romv QRY Rom Version
0012
0013 cond not romv
1900 0014 org \$1900
0015 else
0016 org \$8000
0017 endc
0018 ;
1900 A200 0019 .start: ldx #0 ;String print routine
1902 B0DE19 0020 1%: lda msg,x ;Get the character
1905 F006 0021 beq 2% ;Finished?
1907 20E3FF 0022 jsr osasci ;No- print it
190A E8 0023 inx
190B 00F5 0024 bne 1% ;and continue.
190D 60 0025 2%: rts
0026 ;

ONLY
£35
plus VAT

DISC-BASED
ASSEMBLER
in ROM
for the
BBC Micro

ex-
stock!

- ▶ Professional 6502 Assembler for Disc Systems
- ▶ Industry Standard Intel Files
- ▶ Compatible with Standard Editors (expands tabs)
- ▶ Full Documentation

ORDER
YOURS
TODAY !!

Now your BBC Computer can be used to develop any size machine code program - in one go! Facilities include Cond.Assembly, Pseudo-Ops., Ext.Libraries, Paged 0/p, Local Labels etc. For quality development - use VASM!

see PRESTEL 288 050 49

VAT REG. NO. 403 9099 54

Symbols:

1928 BUF 0015 BUFLFN 1922 DATA 190E MESS FFE3 OSASCI
0000 ROMV 1900 START

0000 error(s) detected
628F bytes free

VIDA REBUS

PO Box 256 Watford, HERTS. WD1 8HY Tel: (0923) 53514

BBC model B, 1.2OS, DFS, fitted with Wordwise ROM, Sony cassette recorder, manual, cover, etc. £420 ono. Tel: Leeds (0532) 585853.

GRAPHICS digitiser by Minor Miracles, mint condition, never used (unwanted Christmas present), new £20, will sell for £14 or swap for Computer Concepts' Graphics ROM. Contact Roger, (09363) 3872, after 5 pm.

PHOENIX Amber high resolution monitor with anti-glare screen, with cable for BBC micro. Cost £123, sell £60. Phone Swansea (0792) 208361.

ATOM wanted. Floating point ROM, Toolkit ROMs, BBC Basic board, Arcade games. Send details to Joel Connault, Le Plan, F38490 La Batie Divisin, France. Tel: 76 3222 17.

MICROLINE 80 printer, very good condition. Character ROM altered to suit BBC character set, £120 ono. Tel: Richard Harris, Sheffield (0742) 383532.

WORDWISE, Beebcalc, both boxed as new, £20 each. Kenda double density DFS complete, £80. Prism modem plus Micronet software, £50. Tel: 01-380 5377 or 0621-892732 (ansaphone), Bob Fuller.

DO YOU wish to sell your BBC model B for up to £250 cash, any condition considered? Ring Michael, Stithians 860580, evenings, or write to: M. Griffiths, Little Menherion, Carnmenews, Redruth, Cornwall.

BBC official 800k drives, £500. Acornsoft BCPL, £70. Microtext, £30. View word processor, £40. Computer Concepts' Discdoctor, £22. Beebcalc, £22. All items under 7 months old and in excellent condition. Tel: (0327) 703792.

MAGAZINES. Back issues of Popular Computing Weekly, Volume 1, all but No. 35. Volume 2, Nos. 1-17. Offers. Tel: Mansfield (0623) 810619.

BBC B 1.2OS, 6 months old, hardly used. Joysticks, books, magazines and radio cassette recorder, only £350. Tel: (0783) 362862 (near Newcastle upon Tyne).

MICRONET/PRESTEL: Prism acoustic modem for BBC B with all cables, software, boxed. Only £40 ono. G. Lock, 34 Quaker Rd, Ware, Herts. Tel: Ware 66972 after 6pm or weekends.

SHARPSOFT for sale. 5 original M/C Sharp MZ-80K games including Asteroids, Defender, £2.50 each, plus book of games and MZ80K Basic book. Books £3.50 each or everything £17 ono. Tel: W-S-M 419765, after 6 pm.

MATTEL Intellivision for sale, with four boxed cartridges including Space Battle and Astrosmash. Only £80 ono. Phone Thatcham (0635) 67257 after 6pm.

ROM expansion boards, unused. Watford, £28; SIR, £28. Tel: Mersham, Surrey (07374) 2413.

MICROTAN 65, with Tanex, Tanram, hi-res, keyboard, cassette, tapes and manuals, £225. May split. Tel: Weston-Super-Mare 413081.

ROM expander board, X13. Switch ROMs off in pairs if worried about power. Upgrading to double density, can't fit both, £30. Two minute operation to plug in. Excellent design. Tel: (0476) 66923.

ATOM 64k RAM 16k ROM including Ross software utility EPROM plus FP and PSU and intro cassette package and other programs and Atomic Theory and Getting Acquainted books and leads. £130 ono (quick sale). Tel: 01-937 0157, after 6 pm.

WATFORD ROM board, hardly used. Offers around £25. Also over 300 programs to swap on disc. Contact Tufail on 01-843 9172 or write to 29 Lancaster Road, Southall, Middlesex UB1 1NP.

PRINTER, Teletype 33 with RS232 interface, manuals, many spare parts. 110 baud, will suit many computers including Spectrum and BBC. £50 ono. Will deliver within 50 mile radius, else buyer collects. Tel: Scunthorpe (0724) 858569.

WANTED: Atom Disc Interface (Computer Concepts' preferred). Paul Compton, 43 Tuffnells Way, Harpenden, Herts AL5 3HA. Tel: (05827) 60986.

BBC model B. Many programs, joysticks and speech synth (not Acorn). OS1.2 and OS0.1 supplied. £350 ono. M. Malkin, 19 Rhys Avenue, Kimmel Bay, Rhyl, Clwyd LL18 5NS. All replies answered.

BBC B 1.2OS plus disc interface, tape recorder, teletext receiver, Prestel acoustic modem, software, leads, books, magazines - all for £550 ono. Telephone (Hitchin) 0462 59335. (Daytime 0462 51114).

HOBBIT Floppy tape system for BBC with tape operating system, manual and leads. Practically new, for only £100. Tel: 01-341 1195, after 5 pm.

BBC B 32k, 1.2OS, Basic II, Hobbit floppy tape system. Also cassette player, some software books, etc. All as new. £395, no offers. Telephone Farnham (Surrey), 724754, anytime.

ATOM 12k + 16k FP, A + F Utilikit ROM, Getting Acquainted, magic books, manuals, software, 5 volt 3 amp, psu £125. Tel: (0294) 67828.

TRS-80 model 1 level 2 16k. Excellent condition with monitor, cassette recorder, sound amplifier, all manuals and leads, including £300 software and magazines, £299. Contact S. McMath, 20 Lowergate Road, Huncoat, Accrington, Lancashire. Tel: (0254) 392316.

ELECTRON (issue two) with reliable cassette recorder, both under guarantee and in good condition, plus many games, utilities. Only want £220 ono for quick sale. Phone 01-907 3119 after 6pm.

BYTE, Kilobaud, 80 Micro, 73, etc available in exchange for your unwanted American (only) computer magazines. Send list. Smith, 84 Edenfield Gardens, Worcester Park, Surrey, KT4 7DY.

WATFORD Electronics 13 ROM expansion board for BBC, £20 ono. Tel: St Albans (0727) 53946, after 5.30 pm.

RH Electronics lightpen, £25. Acornsoft Forth on disc plus book, £15. Both excellent condition. Tel: (0367) 21631, after 6 pm.

WANTED: Atom owners in and around the Swindon area. Don't feel neglected by our BBC brethren. Contact Andy, Swindon (0793) 39736.

PRINTER MX80T-III only 12 months old, hardly used, immaculate condition with BBC (Centronics) lead, 2,000 sheets of paper and tape of screen dumps, only £270 or offers. Tel: (0509) 506701, after 6 pm.

BBC model B fitted with Watford DFS 1.30, Wordwise and complete with W. H. Smith computer cassette recorder. All in excellent condition, £495. Prism acoustic modem with BBC software, £40 ono. Acorn DFS, £80. Tel: Canterbury 750600.

ATOM 12k + 12k, FP ROM, Programmers toolbox, PSU, manuals, magic book, software etc, £80 ono. Tel: Hughes (0707) 42879.

FOR SALE. Quickshot joystick plus driver program £17. Also 'Games BBC Computers Play' (book) £1.50. Phone Mexborough 582982.

WANTED. BBC micro. Damaged or faulty considered. London/Home Counties area. Ring 01 646 0568, ask for Tim Jones, anytime.

BBC micro GCE German revision programs. 160 nouns, £3. 160 adverbs and adjectives, £3. State which or both, £5 on cassette. Contact E. Muir, 189 Lawrie Park Gardens, London SE26 6XJ.

ATOM 12k + 12k, PSU, FP, toolbox, VIA + lots of books and progs. £60. 808-3228 after 4pm (London).

BBC B 1.2OS, Acorn DFS, Wordwise, software worth £700, 400k double sided switchable disk drive, 34 floppies, green screen monitor. Worth £1,600 - the lot £1,055 ono. Tel: 047 283 378 after 7pm, Kevin Bramhill.

ACORN Atom, 12k RAM, 12k ROM. FP ROM, toolbox, PSU, all leads, £100 of software, all original. Books, manual. Offers around £100. Selling for financial reasons. Phone Geoff on Locks Heath 3889.

ATARI 400, worth £600, includes joystick, recorder and lots of games and basic language and free VCS and 2 cartridges, all going for £240. A bargain! Tel: 021-556 1566 or 021-502 5917.

CUMANA double disc, single side, little used, £325 includes postage. Churcher, 10 Park Avenue, Eastbourne, East Sussex BN22 9RN. Tel: 53822.

TELETEXT adaptor + TFS + manual £160. Hardly used. Write to 1 Japan Street, Cheetham, Manchester M8 7HF.

ACORNSOFT Meteors, £6, VU-type, £12 or swap. Ring Jason (0632) 739558.

HOBBIT Floppy tape system. Zero memory option. Fourteen tapes, £100 ono. Tel: Thame 084-421 3956.

EARLY copies of computer magazines for sale in perfect condition. Some bound. Sae for list. Burton, 37 Green Road, Southsea, Hants. Tel: (0705) 811760.

SALE. HCCS Forth ROM plus manual, £20, also 'Spy' M/C monitor, £10. Willing to sell both for £28. Tel: T. Cain, Thanet (0843) 582852, after 6 pm.

WANTED: Atom technical manual, also software and hardware. Anything interesting considered. Tel: Sandy on Cardiff 619092, after 6 pm on weekdays.

BBC B Acorn DFS. 100k disc drive. Epson MX100 132 column printer. EPROM programmer and eraser. Wordwise. Discs, manuals, books and software. Worth £1,400+, sell £850 ono or split. Tel: Tyneside 284 3677, evenings.

DUAL disc drive for BBC, 40 track, hardly used, £270. Also Gemini Accounts package including Cash Book, Final Accounts, Mail List and Easiledger, £70. Tel: Pulborough (W Sussex) 2596.

WANTED. Any of these ROMs - View WP, Ultracalc, Printmaster, Watford DFS. Tel: 0254 47272.

BBC B Cumana 100k drive, BBC mono monitor, ROM board, lightpen, joysticks + various books + software. Offers over £850, will not split. Also Rega Planar 3 turntable, superb, with Goldring G920/GC cartridge. £150, no offers. Phone Mike, Liverpool 051-933 8387 after 5pm.

FOR SALE. P8271 disc controller chip and DFS ROM. Offers on Preston (Lancs) (0772) 323543.

WANTED. Acorn Electron and manual in good condition. Will pay £100. Write to A. Elliott, 59 The Mayfields, W-ton, WV1 2JH.

MEMO pad program. Includes diary, address book and telephone numbers. Save your own files with this. Works only on cassettes not discs - only £3.50. Write to A. Dence, 8 Beare Close, Hooe, Plymouth PL9 9RT.

EPROMs 27128/16k unused, only £15 each. S. N. Baker, 3 Smallwood Road, Baglan, Port Talbot, South Wales SA12 8AP.

BBC B 1.2OS plus disc interface, tape recorder, Teletext receiver, Prestel acoustic modem, software, leads, books, magazines: all for £550 ono. Tel: 0462-59335 (daytime 0462-51114), Hitchin, Herts.

Now, the BBC

The BBC Micro has now taken a giant step into the world of business computing.

With the addition of its new Z80 second processor, it is the first computer at anywhere near its price to become fully compatible with CP/M software.

As most business computer users can verify, CP/M is the most widely used form of software in business today.

For £299, you're well and truly in business.

At £299, the Z80 adds 64K of usable RAM to the BBC Micro. And it allows you to use the CP/M 2.2 computer operating system.

It's extremely fast.

And besides giving you access to a vast new area of software, it enables you to use GSX graphics-based programs, the perfect complement to the BBC Micro's own superb graphics.

Free software and languages.

The Z80 second processor comes complete with five CP/M business programs.

To handle your word processing, there's MemoPlan. It's a program with some highly sophisticated features, such as a safeguard against data loss through power cuts and the ability to show two documents simultaneously on the screen.


To form your CP/M personal database, there's FilePlan. It stores names, addresses, telephone numbers, stock listings and more. And if you use it with MemoPlan, you can generate personalised letters, labels and mail shots.

To produce forecasts and analyse groups of figures diagrammatically, simply use the GraphPlan program. This is incredibly helpful in working out vital business calculations, converting them into graphs and charts.

Meanwhile, in the book-keeping department, there's the Accountant program.

Use it to enter day-to-day transactions into the computer. Then, at any time, you can ask the computer to produce lists, summaries, reports, audit trails and trial balances. You can readily expand this package to a fully ledger based system, complete with payroll and more.

Finally, to help you to develop your own programs without having specialised experience, the Z80 comes with another software package called Nucleus. It's a system generator which asks you



questions and uses your answers to enable the system to write the program.

You can use Nucleus directly with the Accountant program, or for specialised personal or business activities. Additionally, the Z80 package enables you to use three programming languages.

Your BBC Micro instantly becomes multi-lingual.

To simplify writing your own software with the Z80, there's BBC BASIC.

For running professionally written business programs, there's Professional BASIC.

And then there's CIS COBOL, the leading microcomputer version of COBOL, the language used in mainframe computer applications throughout commerce and industry.

With CIS COBOL, the Z80 also gives you two sophisticated programming aids.

Macro.

One is Animator, an award winning debugging tool which enables you to identify programming errors quickly and easily.

The other is FORMS 2, which helps you to write your own interactive programs in COBOL.

With all these sophisticated features, the Z80 package is exceptional value for money. Indeed, bought separately the programs and languages could cost as much as £3,000.

See the Z80 at work.

The Z80 second processor is designed to be used with the BBC Micro Model B incorporating a Series 1.2 Machine Operating System and linked to a dual 80-track disc drive, a printer and monitor.

Ask your BBC Micro dealer to show you just how far it can go in the world of serious business computing.

For your nearest dealer, ring 01-200 0200.

Technical specification.

The Z80 has a 64K Random Access Memory, running CP/M 2.2 which provides approximately 55K bytes of RAM for user programs.

It operates at a clock rate of 6MHz.

Power supply is integral. Height, 70mm. Width, 210mm.

Depth, 350mm.



The BBC Microcomputer System.

Designed, produced and distributed by Acorn Computers Limited.

THE MICRO PULSE 5.25" DISC DRIVES

ANNOUNCEMENT

* Northern Computers announce 6 new models of Micropulse 5.25" disc drive, manufactured and assembled in the North West, for the BBC computer. These drives are exactly compatible with the two Acorn/BBC disc formats. They are based on the highest quality Teac mechanisms with built-in power supply, as previously supplied by Cumana Ltd.

* Prices from **£119.95** + V.A.T.

* Also: High Quality 3" Compact Disc Drives

* Prices from **£129.95** + V.A.T.

* Each Micropulse disc drive is supplied with a BBC cable, formatter utility disc and comprehensive 55page disc filing system manual for the BBC computer.


* For further details send large S.A.E. to :



Northern Computers,
Churchfield Road,
FRODSHAM
Cheshire WA6 6RD
Tel: 0928 35110

THE MICRO PULSE EXTERNAL ROM BOARDS

For the BBC Computer and the Acorn Electron



- ✦ BRITISH MANUFACTURE ✦
- ✦ ALLOWS 8 ROMS ON LINE ✦
- ✦ HARDWARE-BASED ROM SELECTION AVOIDS SOFTWARE INTERACTION BETWEEN UTILITY ROMS ✦
- ✦ SWITCH TO REQUIRED ROM USING MANUAL SWITCH OUTSIDE THE UNIT ✦
- ✦ RED LIGHTS INDICATE THE SELECTED ROM ✦
- ✦ HIT "BREAK" TO ACCESS ROM, NO NEED TO USE SOFTWARE COMMAND ✦
- ✦ INCLUDES ZIF SOCKET, FOR INSTANT CHANGING OF A SELECTED ROM ✦
- ✦ INCLUDES BBC CABLE AND ROM SOCKET CONNECTOR ✦
- ✦ INCLUDES SIMPLE FITTING INSTRUCTIONS, JUST PLUG IN AND GO!

please contact: Gareth Littler
Mark Howard or
Judith Allen at
Micro Pulse
Division



Churchfield Road,
FRODSHAM
Cheshire WA6 6RD
Tel: 0928 35110

ACORN USER ADVERTISEMENT PAGES – AUGUST ISSUE

AB Designs	102	ECCE	17	Micronix	17
Acorn	172/173	Elbug	159	Micropower	32/109/OBC
Acorn User Show	28	Electronequip	4/5	Microwriter	116/117
Addictive Games	146	Ephagy Software	142	MCL	71
Advent	130	First Byte	6	Northern Computers	174
AJ Vision	73	GCC (Cambridge)	18	Opus	52/86/122/140/168
Akhter	120	Gemini	34	Pace	103/158
Beebug	20/21/124/136	Golem	119	Printerland	119
Beebugsoft	48/49	GSL	151	Proxima	140
Bel Tech	88	Guardian Software	170	Robot	46
Broadway	164	Harris McCutcheon	102	Salamander	76
Brother Industries	148	HCR Electronics	17	SCI (UK)	160
C-Tech	26	Honeyfold Software	60	Screens	92
Cambridge Computer Store	77	Inmac	30	Shards	115
Cambridge Microcomputer Centre	23	Intech	90	Silent Computers	119
Cambridge University Press	154	Interface	130	Simonsoft	75
Cardiff	92	Interface Systems	142	SIR	132/138
Chase Data	100/101	Intersoft	170	Skywave	31
Cheetah Marketing	54	Kansas	64	Slogger Software	134
City Music	142	Keyzone	144	Software Supermarket	99
CJE Micros	72	Level 9	118	Solidisk	166/167
Clares	110/111	Lifelong Learning	142	Spider Systems	22
Commotion	152	Lion House Micros	56/57/58	Stella-Enterprise	152
Computer Concepts	11/36/126	Loco Systems	144	Superior Software	95/156/IBC
Computer Town	96/97	LVL	IFC	Synergy	62
Computerama	1	Mayfair	119	Systems	94
Compwise	150	Merlin	74	Technomatic	12/13/14
Comtec	132	Micheals Business Systems	34	Three D Computers	55
Cumana	19	Micro-Fast	162	Tutorial Software	170
CYB Design	150	Micro-Programmer	34	Twillstar	67/69/71/73/75/77
DB Enterprises	16	Micro-Resources	154	Victor-Morris	92
DN Electronics	77	Micro-Tek Computer Services	55	Vida Rebus	170
Datapen	124	Micro-Test	8	Viglen	128/129/131/133/135
Datastore	55	Micro-Vitec	98	Vine Micros	16
Diamondsoft	138	Microfix	130	Vogan Products	34
Discotek	84/85	Micronet	24/25	Voltmace	46
DPL	146			Watford	38/39/40/41/42/43/44
Duckworth	71			Sorting Program Courtesy of Gemini	

■ **BBC B.** Store your current account records with this file. Handling program disk 40/80 £7 or cassette £5. (0273) 34167. 37 Ravenswood Drive, Woodingdean, Brighton, Sussex.

■ **Original BBC** software for sale: Acornsoft, Program Power, Superior Software etc. May consider swapping. Telephone Lodge Hill 49249. Ask for Victor (after 7pm).

■ **Small boat skippers.** Learn to recognise navigation lights, buoys and flags with Navrec. Eight programs totalling 42k on a 40 track disc. £10 from R. Morris, 8 Normanby Drive, Conahs Quay, Clwyd.

■ **Extra words** for Acorn's speech synthesiser via keyboard socket "Ashtray" cartridge. Only £10.95. Promit, 456 Clayhall Avenue, Barkingside, Ilford, Essex. Hurry—only 20 left.

■ **Print out listings.** Send £1 per program with your cassette/s or 40 track disc for same day service. Also wordprocessing. Send sae for details. Post to: A. J. Services, 104 Craythorne Avenue, Birmingham B20 1LN.

■ **Programs** wanted for new software company. Good rates paid for your own original material. Cottage Software, 3 Conrad Drive, Worcester Park, Surrey. 01-330-1554.

■ **Atom owners!** Build a speech synthesis or colour module. Full technical details including demonstration programs, £3 each. Also available as kits or assembled. K. White, 86 Neal Road, West Kingsdown, Sevenoaks, Kent TN15 6DQ.

■ **Basicode** users. Timer. Records Chipshop programs while asleep. Radio cassette recorder, motor control and BBC A/B necessary. Send £3. A. Shirley, P.O. Box 108, High Wycombe, Bucks HP11 1LA.

■ **Tortoissoft** presents: Magic & Mayhem, an adventure game for the impatient! Pentoms: Graphic puzzle, 2339 solutions. Both programs cassette £7.95. 40 Track disc £9.95. 14a Windsor Road, London W5. Tel: 840 2120.

■ **NEC** PC-8023 dot matrix printer for BBC, in mint condition with user manual, cable and comprehensive screen-dump ROM. Only £240. Also fully expanded Acorn Atom: any offers? Tel: Marc (01) 954 6367.

■ **Three BBC B** programs—our much acclaimed Cricket Simulation, Jewels of Nabooti (an educational adventure); and French Tutor. £6.50 tape, £7.95 40-track disc from S. Grist, 127 Waxwell Lane, Pinner, HA5 3EP.

■ **50** high quality, low cost games including Zaxxon, Dr. Who, Tron, Tempest, Knight Rider & more: all on tape @ £6.95 (tape to disc instructions included). Ranjan, Dept (AU), 3 Wensley Close, Harpenden, Herts, AL5 1RZ. (48 hr despatch service).

■ **Music.** Direct type-a-tune program for Electron plus "tunes for typing". £1. Qwertonic Press, 71 Elmfield Avenue, Teddington TW11 8BX.

■ **Wollensak** stereo cassette copier £900. Hardly used. Copies over 200 C12s an hour. Ideal for program producers. Phone Peter Okell on 061-736 2733 (Manchester).

■ **BBC B/Electron.** New game, "The Blob". Large colour graphics and sound effects. Cheque/PO for £3.95 to Andrew Goble, 18 Buckland Road, London E10 6QS.

■ **Floppy** disks 5¼". Lowest prices cost/disk including VAT and p&p. SSDD: £1.50 (1-4), £1.40 (5 or more). DSDD: add 40p/disk. Cheque/PO to: Babel Ltd, 166A King Charles Road, Surbiton, Surrey KT5 9BQ. Tel: 390-2131.

■ **Spectrum** Analysis. BBC B program calculates frequency spectrum of time waveform input via keyboard or analogue port. Graphical displays. £5 cassette. D. Bonfield, 4 Marsden Way, Orpington BR6 9TX.

■ **20** educational programs in maths, physics, chemistry & geography only £8.95 (tape), £11.95 (disc). Business pack includes word processor, database, Beebcalc, VAT & accounts only £11.95 (tape), £14.95 (disc). Ranjan, Dept (AU), 3 Wensley Close, Harpenden, Herts AL5 1RZ. (48 hr despatch).

■ **Rompull** + Tapedump: £5. Super Diskmenu + EPROM version (on tape): £5. Tape2tape + Tape2disk + Disk2tape + Disk 2disc + tapedup: £5. R-Soft, 22 Marriotts Close, Felmersham, Beds MK43 7HD. Tel: 0234-781730.

■ **Egg** the upgrade—enhances Chuckie Egg—8 new boards—joystick routines—start at any board—up to 255 lives! £3.50 (inc p&p). Sae details to Crystalsoft, Dower Cottage, Gold Hill East, Chalfont St. Peter, Bucks SL9 9DL.

■ **Softspeech** BBC/A/B with your own voice, any vocabulary, 2secs/K, hardware included. Speech module, demos, assembly listings; link to your Basic programs. Tape £10. Opensoft, 12 Blyth Place, Russell Street, Luton, Beds.

■ **Personalise** your BBC micro. Personal message on power-up. Password (optional). On sideways EPROM. Send £15 (or £5 + 2764 EPROM), message, password (8 characters), if required. I. Whetton, 13 Woodleigh, Walton, Brampton, Cumbria.

■ **Sale:** function key definitions, 10 overlays, spiral bound. £1 each or 3 for £2. Funkey Accessories, 71 Rhydhelig Avenue, Cardiff CF4 4DB.

■ **Atom** 12k RAM fp ROM with documentation and two power supplies. Never really used. £50. Also Sony B/W for sale. Tel: 01-870-6664 (Evenings).

■ **FX80** owners. Want near-letter-quality print! Send sae for sample printout or £4 (inc.) to S. Linter, 1A Bull Lane, Boughton, Faversham, Kent, ME13 9AH.

■ **ROM** Filing System: generate your own 8-16k RFS files to run from EPROM/sideway RAM: £5. R-Soft, 22 Marriotts Close, Felmersham, Beds MK43 7HD. Tel: 0234-781730.

■ **BBC "Image"**—ultimate tape back-up copier. Copies virtually everything. Send sae for details of its incredible features. Also locks and unlocks programs. 100% M/C. £3.80. P. Donn, 33 Little Gaynes Lane, Upminster, Essex RM14 2JR.

■ **Professional** programmer offers Basic and Machine Code programming service and private tuition in programming and computer literacy. Tel: 01-693-8434. Micronet 01397653.

■ **Ardsoft** Educational Software announce the release of their new, quality educational software. Free catalogue and demo cassette available on request. Send 50p (p&p) to Ardsoft Educational Software, 20 Castle View, Leeds LS17 5BY.

■ **Joysticks**—top quality at amazing low price. Only £9.95 a pair. Easier to handle and faster than others costing twice as much. Cheque/PO to Peritron, 21 Woodhouse Road, London N12 9EN.

■ **Machine** generated tape copies of your own programs from 28p including tape. Discount for quantity. Hard copies (75p) for debugging or backup. Quotes, ring 0724-734098.

■ **Infant/Junior** schools. 22 tried and tested programs at £2.50 each. (Tape or disc). Large sae for list. 18 Nant Eos, Holywell, Clwyd CH8 7DA.

£10 SMALL AD SERVICE

Please include your cheque for £10 made payable to Redwood Publishing. This is the standard fee. Don't forget your name, address or phone number. Send cheque plus form to Acorn User Small Ads, 68 Long Acre, London WC2E 9JH.

Hermann Hosewheel talks to our man on the Cam Orson Fact

A LIFE IN THE DAY OF A HERMANN

176

“ I awaken at 4.30 each morning and arise immediately. Before breakfast every day I take exercise, it prepares me for the day ahead. Some days I run only a half-marathon, but usually I run the full distance. I wave to Clive as I lap him at Grantchester.

I often fly to San Francisco for discussions at our research centre in Palo Alto. I buy California before returning for lunch with Chris.

We eat at Kings College where I did much of my research. I believe it is very important to keep up the old college ties, in fact we are thinking of buying Kings to house our growing R&D division.

Over lunch Chris and I discuss the next stage of the master plan. This is to asset-strip IBM. The two assets of value to us are their massive customer base and their worldwide chain of office blocks. We intend to strip out every installed IBM mainframe and replace it with a Beeb with Hyper-Tube interface to the Ultimate Machine (UM) that R&D are building.

■ THE MEP has drawn a blank with Sinclair in trying to draw up database guidelines.

Sinclair's boys are the only ones to express a wish *not* to participate, as virtue is apparently seen in incompatibility.

■ MARKETING man Tom Handbay has described reports of his replacement by a graduate as 'premature'. He claims that no-one in Cambridge has yet seen a working



Millionaire entrepreneur Hermann, 34, was born into the aristocratic Hosewheel family. Although the family motto is 'Ich bin nicht ein German' the Hosewheels originated in the Bavarian village of Beebongberg before moving to Austria and wine-making. He followed a distinguished career in particle physics, discovering the atom, proton and electron. He is married to Pamela Rasp, the New Zealand bio-chemist. As yet they have no children but a very large Econet at their home in Cambridge.

All the parasite terminals will be replaced with Acorn terminal emulators connected by our new Psychonet telepathic interface.

The IBM office blocks will give us the chance to diversify our operation into luxury hotels. By simply replacing the office furniture with bedroom furniture and the M in IBM with an acorn we will create in one operation the largest chain of hotels in the world. Hotel managers will come from the Product Services division.

After lunch I go to our R&D labs where I like to spend my afternoons solving the remaining problems on the AUT (Acorn Universal Tube). This is simply a high-frequency radio IO port which will interface with anything attached to a UTI (Universal Tube Interface). So on our future machines we supply just the AUT instead of the many interfaces of the BBC micro and to use, for example, a par-

allel printer only a Centronix UTI would be necessary.

After finishing the AUT we hold a board meeting and decide to buy some property in the City for a new London headquarters. Because we see further than the rest we agree to buy either the Post Office tower or the Natwest building.

In the evening, Pamela and I like to have a quiet night in, watching video repeats of Clive on *Spitting Images*. We are often invited to speak at official dinners, and I spoke recently on 'Acorns in an expanding universe' to the Ecological Astronomers Association. Being a bio-chemist Pamela is a wonderful cook and loves to make the traditional Austro-Maori dish Watanabe-schnitzel. Eddie the Android clears up and after playing with the Econet we retire to bed to finish the day as it started. ”

Next week: Christopher Wand

Graduate and that his recent plastic surgery in Silicon Valley worked wonders.

'I passed my ART (Android's Reliability and Training) examinations first time.'

■ THE Oric Muser has just announced a policy of not commenting on a new product until they know something about it. Trouble is, they need to fill their news pages.

■ ACE investigative reporter Orson Fact has compiled the latest 6502 second processor league table:

China	2
India	6
Wellingborough	17*
Cherry Hinton	293
Soviet Union	1,347,513**

* Still in parts awaiting shipment.

** Courtesy US Department of Defense.

ACORN ABUSER'S

DIARY

OVERHEARD in a Cambridge tavern: 'I hear Acorn's dropped the 16032 second processor.'

'Really? What are they doing instead?'

'Something called the 32016. Apparently the same architecture as the 16032 but twice as late.'

■ A RECENT collaborative venture with Acorn has enabled Commodore to release the Plus 4 computer. It will work as a stand-alone machine but it was really designed as a second processor for the Electron.

We asked Acorn's Jean Vincent when we could expect Acorn to release the Plus 2 and Plus 3 to interface with the Plus 4: 'We are working very hard on them.'

'Currently, with all the add-on boxes, the machine is so deep it falls off the back of the desk.'

■ THIS month's Barry Woodentop Monumental Cockup award goes to Inferior Software for their Spectrum emulator on the Z80 2P.

MD Kai Gooney commented 'We're very excited to have won this award, proving our lead in the race to turn the Beeb into a really serious machine. Our ZX81 emulator is far advanced and after that we'll announce the Oric Atmost 4.8k.'

IN NEXT month's *Acorn User* we ask:

■ 'Does the Z80 second processor work with Disc Doctor in the IO processor?'

■ 'Is Chris Curry related to Gandhi?'


■ 'Is Hermann really a German?'

In the meantime see if you can guess the answers from the following anagram: ON

SPECIAL OFFER!
Order both directly from us and deduct £1 from each.

TWO SENSATIONAL NEW RELEASES FROM SUPERIOR SOFTWARE

**BBC
MICRO**




STAR STRIKER (32K)

£7.95

A multi-stage arcade-style game in which you take control of a 3-stage rocket equipped with 4 side lasers and a central laser cannon. Not only must you defend the rocket against the 6 types of circling alien, and avoid the asteroids and fireballs, but you must also attempt to dock the separate stages of the rocket together. Stunning graphics, sound effects, introductory tunes, hi-score and rankings. Another excellent program from Superior Software. (KEYBOARD or JOYSTICKS)

OUR PROGRAMS ARE NOW AVAILABLE FROM OVER 1000 OUTLETS THROUGHOUT THE UK AND OVERSEAS. SEE YOUR LOCAL DEALER!



MR. WIZ (32K)

£7.95

From the author of Percy Penguin, Mr. Wiz is a fast-action multi-scene game. Guide Mr. Wiz around the garden to eat the cherries whilst avoiding the evil gremlins. The gremlins can be killed by dropping apples on them or by throwing the crystal ball. Extra points can be gained by eating the magic mushroom, but beware... this is the home of the gremlins and makes them permanently furious! Sound effects and tunes, hi-score, rankings. Superb arcade-style action. (KEYBOARDS or JOYSTICKS).

WE PAY UP TO 20% ROYALTIES FOR HIGH QUALITY BBC MICRO AND ELECTRON PROGRAMS



SUPERIOR SOFTWARE LTD.

Dept. AU7, Regent House,
Skinner Lane, Leeds 7
Tel: 0532 459453

OUR GUARANTEE

- (1) All our software is available before we advertise.
- (2) All our software is despatched within 48 hours by first-class post.
- (3) In the unlikely event that any of our software fails to load, return your cassette to us and we will immediately send a replacement.

M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R M

GHOULS

commodore 64
(SUPER-FAST LOADING TIME)
electron
B.B.C. MICRO

Run through the creepy mansion to rescue the power jewels. Dodge ghostly ghouls and bouncing spiders, leap over poison-smeared spikes, scamper along moving platforms and contracting floorboards, and use powerful springs to propel you onto overhanging ledges. Superb animation and spine-tingling sound effects.

£6.95.
(ELECTRON and BBC MICRO versions £7.95)



COMMODORE 64 VERSION

M I C R O
P O W E R

TAKE MY
ADVICE! BOOST YOUR
COLLECTION WITH SWOOP,
FELIX IN THE FACTORY
AND CYBERTRON
MISSION!

MICRO POWER LTD.,
NORTHWOOD HOUSE, NORTH STREET,
LEEDS LS7 2AA TEL: (0532) 458800
SELECTIVE BRANCHES OF BOOTS, CO-OP,
MENZIES, W. H. SMITH, WOOLWORTHS AND ALL
GOOD DEALERS.
AUTHORS! WE PAY 20% ROYALTIES!



M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R M I C R O P O W E R M