

# Computer Use in Continued Fraction Expansions\*

By Evelyn Frank

**Abstract.** In this study, the use of computers is demonstrated for the rapid expansion of a general regular continued fraction with rational elements for  $\sqrt{C + L}$ , where  $C$  and  $L$  are rational numbers,  $C$  positive. Formulas for the expansion are derived. Conditions for the periodicity are considered. A Fortran program for the algorithms is given, as well as sample continued fraction expansions. Up to the present, practically all studies have been concerned with continued fractions with partial numerators  $\pm 1$  and partial denominators positive integers, due to difficulties in calculation. But now the use of computers makes possible the study of a much greater variety of continued fraction expansions. ■

**1. Introduction.** A general regular continued fraction has been defined [3] as a finite or infinite continued fraction

$$(1.1) \quad b_0 + \frac{a_1}{b_1} + \frac{a_2}{b_2} + \dots, \quad a_{n+1}, b_n \neq 0, n = 0, 1, \dots,$$

with *real* numerical elements such that

$$(1.2) \quad b_n \geq 1 + |a_{n+1}|, \quad |a_{n+1}| \geq 1, n = 0, 1, \dots,$$

or with *integral* elements such that

$$(1.3) \quad |a_n| = 1, \quad b_n \geq 1, \quad b_n + a_{n+1} \geq 1, \quad n = 1, 2, \dots.$$

It has been shown in [3] that a continued fraction satisfying the latter conditions can always be transformed into one satisfying (1.2). A general regular continued fraction converges. The continued fraction expansion (1.1) for a real number  $F_0$  is accomplished by a sequence of linear transformations

$$(1.4) \quad F_n = b_n + \frac{a_{n+1}}{F_{n+1}}, \quad F_n \geq 1, \quad n = 0, 1, \dots.$$

In [3] it was shown that, if

$$(1.5) \quad |F_n - b_n| < 1, \quad \text{that is, } F_{n+1} > |a_{n+1}|, \quad n = 0, 1, \dots,$$

a general regular continued fraction expansion satisfying (1.2) converges to the generating number  $F_0$ . An expansion that satisfies (1.3) is semiregular (or regular if  $a_{n+1} = 1$ ) and always converges to the generating number (cf. [6]).

In [4] the author studied general regular continued fraction expansions with real rational numerical elements for  $\sqrt{C + L}$  with  $C$  and  $L$  rational numbers,  $C$  positive. Conditions were also found for general regular expansions (1.1) for  $\sqrt{C + L}$  to be periodic. Simultaneously, the approximations  $x_n$  to  $\sqrt{C + L}$  given by an extension of Newton's formula,

---

Received July 2, 1968, revised September 25, 1968.

\* Presented to the American Mathematical Society. This research was sponsored in part by the National Science Foundation.

$$(1.6) \quad x_n = \frac{x_i \cdot x_j + C - L^2}{x_i + x_j - 2L},$$

where  $x_i$  and  $x_j$  are certain previous approximations to the value  $\sqrt{C + L}$ , were studied. Let  $x_i = X_i/Y_i$  denote the  $i$ th approximant of (1.1). In [4] a complete classification was given concerning which ones of the approximants  $X_i/Y_i$  are also approximations to  $\sqrt{C + L}$  given by formula (1.6).

In this study, the use of computers is demonstrated for the rapid expansion of a general regular continued fraction with rational elements for  $\sqrt{C + L}$ . The use of computers is especially convenient here since the same operations are repeated many times, and computation without computers is extremely arduous.

Furthermore, practically all studies up to this time have been concerned with the elements  $a_i = \pm 1$ ,  $b_i$  positive integers. But now the use of computers makes a study of continued fractions with rational elements no more difficult, since it takes almost no time to work out many examples.

In Section 2, formulas for the expansion of  $\sqrt{C + L}$  into a general regular continued fraction (1.1) with rational elements are derived. These are then modified for application to a computer program. In Section 3, conditions for the periodicity of these expansions are discussed. In Section 4 a summary of the calculation procedure is given, and sample problems computed for a particular class of general regular continued fraction expansions for  $\sqrt{C + L}$  (Table 1). These are given in order to show how easily general regular continued fraction expansions can be generated for a given binomial quadratic surd.

A Fortran program for the expansion of  $\sqrt{C + L}$  into a general regular continued fraction appears in the microfiche section of this issue of the journal.

## 2. Mathematical Description.

I. The first problem is the derivation of formulas for the computation of the expansion (1.1) for  $\sqrt{C + L}$ . For a given binomial quadratic surd  $\sqrt{C + L}$ , one writes

$$(2.1) \quad \sqrt{C + L} = \frac{\sqrt{D + P_0}}{Q_0}.$$

The continued fraction (1.1) is generated by a sequence of linear transformations

$$(2.2) \quad F_n = b_n + \frac{a_{n+1}}{F_{n+1}} = \frac{\sqrt{D + P_n}}{Q_n}, \quad n = 0, 1, \dots.$$

The elements must satisfy (1.2) or (1.3), and (1.5). The transformation (2.2) can be written

$$(2.3) \quad \frac{\sqrt{D + P_n}}{Q_n} = b_n + \frac{a_{n+1}Q_{n+1}}{\sqrt{D + P_{n+1}}}, \quad n = 0, 1, \dots.$$

From this formula, the recurrence relations

$$(2.4) \quad D - P_{n+1}^2 = a_{n+1}Q_nQ_{n+1},$$

and

$$\begin{aligned}
 P_{n+1} &= b_n Q_n - P_n, \\
 (2.5) \quad Q_{n+1} &= \frac{b_n(P_n - P_{n+1}) + a_n Q_{n-1}}{a_{n+1}} = \frac{D - P_{n+1}^2}{a_{n+1} Q_n}, \quad n = 0, 1, \dots, \\
 Q_{-1} &= \frac{D - P_0^2}{Q_0} \quad (a_0 = 1),
 \end{aligned}$$

were derived in [4].

In the continued fractions considered, the  $a_{n+1}$ ,  $b_n$ ,  $Q_{n-1}$ , and  $P_n$ ,  $n = 0, 1, \dots$ , are rational numbers. Consequently, it is more convenient in the computation with computers for one to consider the continued fraction

$$(2.6) \quad \frac{B_0}{D_0} + \frac{A_1/C_1}{B_1/D_1} + \frac{A_2/C_2}{B_2/D_2} + \dots$$

for  $\sqrt{C + L} = (\sqrt{D + P_0/R_0})/(Q_0/S_0)$ . This is generated by the sequence of linear transformations

$$(2.7) \quad \frac{\sqrt{D + P_n/R_n}}{Q_n/S_n} = \frac{B_n}{D_n} + \frac{(A_{n+1}/C_{n+1}) \cdot (Q_{n+1}/S_{n+1})}{\sqrt{D + P_{n+1}/R_{n+1}}}, \quad n = 0, 1, \dots.$$

Thus, for the continued fraction (2.6), the recurrence relations (2.4) and (2.5) become

$$\begin{aligned}
 (2.8) \quad \frac{P_{n+1}}{R_{n+1}} &= \frac{B_n Q_n R_n - D_n P_n S_n}{D_n R_n S_n}, \\
 \frac{Q_{n+1}}{S_{n+1}} &= \frac{[B_n C_n S_{n-1} (P_n R_{n+1} - P_{n+1} R_n) + A_n D_n Q_{n-1} R_n R_{n+1}] C_{n+1}}{A_{n+1} C_n D_n R_n R_{n+1} S_{n-1}} \\
 &= \frac{C_{n+1} S_n (D R_{n+1}^2 - P_{n+1}^2)}{A_{n+1} Q_n R_{n+1}^2}, \quad n = 0, 1, \dots, \\
 \frac{Q_{-1}}{S_{-1}} &= \frac{(D R_0^2 - P_0^2) S_0}{Q_0 R_0^2}.
 \end{aligned}$$

Semiregular continued fractions (continued fractions that satisfy (1.3)) are not considered here, since semiregular expansions for  $\sqrt{C + L}$  have been treated by Perron [6], Goncalves [5], and many others. In fact, the author in [2] gave an Algol program for the expansion of  $\sqrt{C + L}$  into a regular continued fraction. With slight modifications, the expansion into a semiregular continued fraction could be similarly programmed. Consequently, only general regular continued fractions (2.6) that satisfy the conditions

$$\begin{aligned}
 (2.9) \quad \frac{B_n}{D_n} &\geq 1 + \left| \frac{A_{n+1}}{C_{n+1}} \right|, \quad \left| \frac{A_{n+1}}{C_{n+1}} \right| \geq 1, \quad C_{n+1} > 0, \quad D_n > 0, \\
 \left| F_n - \frac{B_n}{D_n} \right| &< 1, \quad \text{i.e. } F_{n+1} > \left| \frac{A_{n+1}}{C_{n+1}} \right|, \quad n = 0, 1, \dots,
 \end{aligned}$$

are treated here. As in the case of semiregular continued fractions, given are the positive integers  $C_{n+1}$  and the positive or negative integers  $A_{n+1}$ ,  $n = 0, 1, \dots$ . Also given are the integers  $P_0$ ,  $Q_0$ , and  $D$  ( $R_0 = S_0 = 1$ ,  $A_0 = C_0 = 1$ ), and the generating

number  $F_0 > 1$ . The positive integers  $B_n$  and  $D_n$  are computed from (2.9) with *certain specific rules concerning their unique values*. As discussed in [3], [4], the continued fraction (2.6) can always be transformed into one for which  $|A_{n+1}/C_{n+1}| > 1$ ,  $B_n/D_n > 1$ , so it is henceforth assumed that these conditions hold.

If  $(\sqrt{D} + P_0)/Q_0$  is negative, one computes (2.6) for  $-(\sqrt{D} + P_0)/Q_0$ , and then multiplies (2.6) by  $-1$ . Furthermore,  $\sqrt{D}$  is taken as the positive root, since, if one is given  $(-\sqrt{D} + P_0)/Q_0$ , one uses the equal value  $(\sqrt{D} - P_0)/(-Q_0)$ .

If the expansion is periodic, one notes that one has obtained a complete period  $p$  when the values of  $P_i/R_i$ ,  $Q_i/S_i$  are repeated. One must of course start with a periodic sequence (of period  $r$ ) of the  $A_{n+1}/C_{n+1}$ . Then  $p = r \cdot k$ , where  $k$  is a positive integer. (This is analogous to the case of semiregular continued fractions when one is given the  $C_{n+1} = 1$ , and the  $A_{n+1}$  are a given periodic sequence such that  $|A_{n+1}| = 1$ .)

However, it may very well happen that there is a fore-period of  $t$  terms, as in the expansion

$$(2.10) \quad \frac{G_0}{H_0} + \frac{M_1/N_1}{G_1/H_1} + \cdots + \frac{M_t/N_t}{G_t/H_t} + K = \frac{X_t + K \cdot X_{t-1}}{Y_t + K \cdot Y_{t-1}},$$

$$K = \left( \frac{A_1/C_1}{B_1/D_1} + \cdots + \frac{A_p/C_p}{B_p/D_p} \right) + \left( \frac{A_1/C_1}{B_1/D_1} + \cdots + \frac{A_p/C_p}{B_p/D_p} \right) + \cdots,$$

where the periodic part does not begin until the  $(t + 1)$ th term, and  $X_t$ ,  $Y_t$  denote the numerator and denominator, respectively, of the  $t$ th approximant. This expansion is called *mixed-periodic*.

II. This portion of the mathematical description of the problem is concerned with additional formulas that one can use for further information about general regular expansions for  $\sqrt{C} + L$ . These are analogous to the computations of the author in [2] on regular continued fraction expansions.

The recurrence relations for the  $X_n$  and  $Y_n$ , the numerator and denominator, respectively, of the  $n$ th approximant of (2.6), are given by

$$(2.11) \quad X_n = B_n X_{n-1}/D_n + A_n X_{n-2}/C_n, \quad Y_n = B_n Y_{n-1}/D_n + A_n Y_{n-2}/C_n,$$

$$n = 1, 2, \dots, X_{-1} = 1, X_0 = B_0/D_0, Y_{-1} = 0, Y_0 = 1.$$

Also of interest is the application of formula (1.6) for the approximants of the expansions considered here. For that purpose it takes the form

$$(2.12) \quad x_{kp-s} = \frac{Q_0^2 X_{kp-s}}{Q_0^2 Y_{kp-s}}$$

$$= \frac{Q_0^2 X_{(k-r)p-s} X_{rp-1} + (D - P_0^2) Y_{(k-r)p-s} Y_{rp-1}}{Q_0^2 (X_{(k-r)p-s} Y_{rp-1} + X_{rp-1} Y_{(k-r)p-s}) - 2P_0 Q_0 Y_{(k-r)p-s} Y_{rp-1}},$$

$$k = 2, 3, \dots, r = 1, 2, \dots, k - r \geq 1, p = 1, 2, \dots, s \leq p.$$

There are numerous other formulas of this type that could also be applied to the approximants of general regular continued fractions on a computer (cf. [1], [4]).

Finally, it is of great importance for one to know how good an approximation to the value of  $\sqrt{C} + L$  is an approximant  $X_n/Y_n$ . For that purpose, one can use the error formula (cf. [3])

$$(2.13) \quad \frac{\left| \frac{A_1 A_2 \cdots A_n}{C_1 C_2 \cdots C_n} \right|}{Y_{n-1}(Y_n + Y_{n-1})} \leq \left| F_0 - \frac{X_{n-1}^*}{Y_{n-1}^*} \right| \leq \frac{\left| \frac{A_1 A_2 \cdots A_n}{C_1 C_2 \cdots C_n} \right|}{Y_{n-1}(Y_n - Y_{n-1})}.$$

Here  $X_{n-1}^*/Y_{n-1}^*$  refers to the approximant  $X_{n-1}/Y_{n-1}$  with all common factors removed from the numerator and denominator.

These three formulas have not been carried through in the Fortran program, since it has been the purpose of this paper to illustrate the usefulness of computers for expansions in general regular continued fractions, but the latter three formulas can likewise easily be applied to computers.

**3. Conditions for the Periodicity of Expansion (2.6) for  $\sqrt{C + L}$ .** It is well known (cf. [5] or [6]) that an infinite semiregular continued fraction (1.3), into which a binomial quadratic surd can be expanded, is always periodic provided the partial numerators  $a_{n+1}$ ,  $n = 0, 1, \dots$ , are a given periodic sequence. Consequently, semi-regular continued fractions are not considered here, and the discussion is concerned only with those general regular continued fractions satisfying conditions (1.2).

In [4] it was shown that a convergent infinite continued fraction that is periodic of period  $p$  always represents a root of a quadratic equation provided the denominator of the  $(p - 1)$ th approximant of (2.6) is not zero. Furthermore, it was shown that a general regular continued fraction (2.6) into which a binomial quadratic surd can be expanded, with the  $A_{n+1}$  and  $C_{n+1}$  a given periodic sequence, and with definite rules for the unique values of the  $B_n/D_n$ , is always periodic provided the  $P_n/R_n$  in formulas (2.8) are integral.

That this is in general not the case can easily be seen if one writes down the successive values of  $R_n$  and  $S_n$  from formulas (2.8). It is seen that these values increase indefinitely, and it is only a fortunate cancellation of factors in the fractions  $P_n/R_n$  and  $Q_n/S_n$  that keeps the values of the numerators and denominators of these fractions bounded, with a consequent possibility for periodicity.

**4. Fortran Program and Sample Problems for a Particular Class of General Regular Continued Fractions.** In the microfiche section of this issue is given a Fortran program for a particular class of general regular continued fraction expansions for  $\sqrt{C + L}$ . In this class, the periodic sequence  $A_{n+1} = -1$ ,  $C_{n+1} = 1$  is chosen. Then the  $B_n/D_n$  are calculated so that in the first formula in (2.8) the  $P_{n+1}/R_{n+1}$  are integral, i.e.  $R_{n+1} = 1$ . This is done in the following way: The denominators  $D_n$  must be factors of  $Q_n$ . The factors 2, 3,  $\dots$ ,  $Q_n$  are tried in that order as factors, and  $D_n$  is set equal to the smallest one that is a factor. If none is a factor, then  $D_n$  is set equal to 1. The numerators  $B_n$  are then chosen as multiples of  $S_n$ , and so chosen that  $|F_n - B_n/D_n| < 1$ , and such that this difference is smallest, if there is a choice. Of course, since  $A_{n+1} = -1$ ,  $B_n/D_n > F_n$ . Thus conditions (2.9) are satisfied.

It is clear that it is *not* always possible to find a  $B_n/D_n$  that satisfies all these conditions. Below, in Table 1, is an illustration of a binomial quadratic surd that cannot be expanded into such a continued fraction. Of course, it would always be possible for one to alter, for example, the choice of  $A_{n+1}/C_{n+1}$ , so that a general regular continued fraction expansion is possible for a given binomial quadratic surd.

TABLE 1. *Examples*

<i>Example 1</i>									
$P = 40$			$Q = 39$			$D = 46$			
$N$	$A$	$C$	$B$	$D$	$P$	$R$	$Q$	$S$	$FN$
0	1	1	4	3	40	1	39	1	1.19955
1	-1	1	117	14	12	1	98	39	7.47460
2	-1	1	28	15	9	1	195	14	1.13309
3	-1	1	65	42	17	1	1134	65	1.36318
4	-1	1	357	65	10	1	65	21	5.42198
5	-1	1	130	9	7	1	63	65	14.21986
6	-1	1	63	13	7	1	65	21	4.45275
7	-1	1	65	21	8	1	378	65	2.54193
8	-1	1	14	5	10	1	65	7	1.80733
9	-1	1	13	7	16	1	294	13	1.00738
10	-1	1	7	5	26	1	195	7	1.17680
11	-1	1	195	41	13	1	287	65	4.48031
12	-1	1	287	65	8	1	1170	287	3.62609
13	-1	1	65	41	10	1	861	65	1.26696
14	-1	1	1148	325	11	1	1625	287	3.14063
15	-1	1	975	287	9	1	2009	325	2.55314
16	-1	1	41	25	12	1	650	41	1.18473
17	-1	1	91	41	14	1	123	13	2.19650
18	-1	1	574	13	7	1	13	41	43.46733
19	-1	1	65	41	7	1	123	13	1.45667
20	-1	1	205	26	8	1	78	41	7.77020
21	-1	1	364	41	7	1	41	26	8.74001
22	-1	1	205	26	7	1	78	41	7.24456
23	-1	1	65	41	8	1	123	13	1.56236
24	-1	1	574	13	7	1	13	41	43.46733
25	-1	1	65	41	7	1	123	13	1.45667
26	-1	1	205	26	8	1	78	41	7.77020
27	-1	1	364	41	7	1	41	26	8.74001
28	-1	1	205	26	7	1	78	41	7.24456
29	-1	1	65	41	8	1	123	13	1.56236
$Fore\text{-}period = 18$				$Period = 6$					
<i>Example 2</i>									
$P = 9$			$Q = 5$			$D = 13$			
$N$	$A$	$C$	$B$	$D$	$P$	$R$	$Q$	$S$	$FN$
0	1	1	13	5	9	1	5	1	2.52111
1	-1	1	40	3	4	1	3	5	12.67591
2	-1	1	8	5	4	1	5	1	1.52111
3	-1	1	40	3	4	1	3	5	12.67591
4	-1	1	8	5	4	1	5	1	1.52111
$Period = 2$									
<i>Example 3</i>									
$P = 51$			$Q = 23$			$D = 73$			
$N$	$A$	$C$	$B$	$D$	$P$	$R$	$Q$	$S$	$FN$
0	1	1	60	23	51	1	23	1	2.58887
***NO CHOICE FOR B***									

Furthermore, one could set down many different rules for the choice of the  $A_{n+1}/C_{n+1}$  and of the consequent computation of the  $B_n/D_n$ . The type of expansion

given here is described in detail in order to illustrate how a general regular expansion is generated. But it must be borne in mind that many other types of such expansions are possible.

The Fortran program was written for the IBM 360 which was the machine available for these computations. Floating-point arithmetic was used in order to obtain the maximum number of digits. Special care was also used in order to avoid round-off error.

A lowest terms subroutine (LTU) was used to reduce to lowest terms all  $B_n/D_n$  and  $Q_n/S_n$ .

Department of Mathematics  
University of Illinois at Chicago Circle  
Chicago, Illinois 60680

1. E. FRANK, "On continued fraction expansions for binomial quadratic surds," *Numer. Math.*, v. 4, 1962, pp. 85-95. MR 25 #3603.
2. E. FRANK, "On continued fraction expansions for binomial quadratic surds. III," *Numer. Math.*, v. 5, 1963, pp. 113-117. MR 27 #5355.
3. E. FRANK, "Continued fraction expansions with real numerical elements," *Univ. Lisboa Revista Fac. Ci. A*, (2), v. 12, 1968, pp. 25-40.
4. E. FRANK, "Continued fraction expansions with rational elements for binomial quadratic surds," *Univ. Lisboa Revista Fac. Ci. A*, (2), 1969.
5. J. VICENTE GONÇALVES, "Sur le développement des irrationnalités quadratiques en fraction continue," *Univ. Lisboa Revista Fac. Ci. A*, (2), v. 4, 1955, pp. 273-282. MR 17, 18.
6. O. PERRON, *Die Lehre von den Kettenbrüchen*, Band I: *Elementare Kettenbrüche*, Teubner, Verlagsgesellschaft, Stuttgart, 1954. MR 16, 239.

```

0045      NJ=Q(K)
C         D IS A DIVISOR OF Q(K)
0046      IF(NQ-1)40,32,28
0047      28 I=2
C         I IS A CANDIDATE FOR D
0048      30 IF((NQ/I)*I-NQ)29,31,29
C         I IS NOT A DIVISOR OF Q, INCREASE I AND TRY AGAIN
0049      29 I=I+1
0050      IF(I,LE,NQ) GO TO 30
0051      32 I=1
C         FINAL CHOICE FOR I IS 1
C         SET INDICATOR FOR LAST TRY
0052      NQ=0
0053      31 DB=I
0054      BB=0.
0055      33 BB=BB+8INC
C         BB IS A CHOICE FOR B
0056      42 IF((BB/DB)-FN(K))33,44,34
0057      34 IF(A(IP).GT.0.) BR=BB-8INC
C         CHECK IF (B/D-FN) LT 1
0058      44 IF(ABS(FN(K)-(BB/DB))-1.)35,36,36
C         9 DOES NOT MEET CRITERION
C         CHECK IF ANOTHER D IS AVAILABLE
0059      36 IF(NQ.GT.0.) GO TO 29
0060      40 WRITE(6,6010)
0061      6010 FORMAT(20X'*** NO CHOICE FOR B/D***')
0062      IF(K-2)98,98,112
0063      112 I=K-1
0064      GO TO 110
C         FOUND B AND D
0065      35 B(K)=BB
0066      D(K)=DB
C         ADJUST THE A/C INDEX
0067      IC=IC+1
0068      IF(IPER-IC)45,46,47
0069      46 IP=2
0070      GO TO 12
0071      45 IC=2
0072      47 IP=IC+1
0073      GO TO 12
0074      120 LUP=K
0075      LUQ=K-1
0076      DO 100 J=2,LUQ
0077      M=J+1
0078      DO 100 I=M,LUP
0079      IF(P(J)-P(I))100,81,100
0080      81 IF(Q(J)-Q(I))100,82,100
0081      82 IF(S(J)-S(I))100,83,100
0082      83 IPRD=I-J
0083      IPRF=J-I
0084      GO TO 110
0085      100 CONTINUE
0086      IPRD=0
0087      110 DO 111 K=1,I

```



```

0088      N=K-1
0089      111 WRITE(6,6003)N,A(K),C(K),B(K),D(K),P(K),R(K),O(K),S(K),FN(K)
0090 6003  FORMAT(23X,12,F6.1,F6.1,2X,6(F8.1,1X),F9.5)
0091      IF(IPRD.EQ.0) GO TO 98
0092      WRITE(6,6015)IPRD,IPFR
0093 6015  FORMAT(21X'PERIOD='I3,5X'FORE-PERIOD ='I3,///)
0094      GO TO 98
0095      99 CALL EXIT
C      THE AUTHOR WISHES TO THANK MR.MARIUS PRAPUOLIS OF THE UNIVERSITY
C      OF ILLINDIS, CHICAGO, FOR HELP IN SETTING UP THE PROGRAM IN THIS
C      PAPER.
0096      ENO

```

```

0001          SUBROUTINE LTU(ARG1,ARG2)
C          THIS SUBROUTINE REDUCES TWO NBRS TO THEIR LOWEST TERMS
0002          NR1= ABS(ARG1)
0003          NR2= ABS(ARG2)
0004          LR2=1
0005          IF(ARG1*ARG2)37,38,38
0006          37 IGN=-1.
0007          GO TO 39
0008          38 IGN=1.
0009          39 IF(NR1-NR2)10,11,12
0010          10 NA=NR1
0011          NB=NR2
0012          GO TO 13
0013          11 NCO=NR1
0014          GO TO 35
0015          12 NA=NR2
0016          NB=NR1
0017          13 N=1
0018          14 NO=NA*N
0019          IF(NB-NO)15,16,17
0020          17 N=N*10
0021          GO TO 14
0022          16 NCD=NA
0023          GO TO 35
0024          15 IF(N-10)18,18,20
0025          18 NU=10
0026          NL=1
0027          NI=1
0028          GO TO 21
0029          20 NU=N
0030          NL=N/10
0031          NI=NL/10
0032          21 DO 27 J=NL,NU,NI
0033          NO=NA*J
0034          LRI=NB-NO
0035          IF(LR1)23,24,25
0036          25 LR2=LRI
0037          27 CONTINUE
0038          WRITE(6,1000)
0039          1000 FORMAT(10X'ERROR ERROR IN LTU*1
0040          RETURN
0041          24 NCD=NA
0042          GO TO 35
0043          23 IF(NI-1)26,26,28
0044          28 NU=J
0045          NL=J-NI
0046          NI=NI/10
0047          GO TO 21
0048          26 IF(LR2-1)30,30,31
0049          30 NCD=1
0050          GO TO 35
0051          31 NB=NA
0052          NA=LR2
0053          GO TO 13

```

0054  
0055  
0056  
0057

35 ARG1=NR1/NCD\*IGN  
ARG2=NR2/NCD  
RETURN  
END

GAUSSIAN QUADRATURES FOR

$$\int_0^{\infty} \exp(-x) f(x) dx / x^m$$

ARNE P. OLSON

TABLE I

The Moments  $\alpha_{n,l} = \int_1^{\infty} \exp(-t) u^l / t^{n-l}$

n-l	$\alpha_{n,l}$	n-l	$\alpha_{n,l}$
10	3.63939940314164016341645E-02	-5	1.19929697821890196840141E 02
9	4.03334943896947068880430E-02	-6	7.19340066372512623363440E 02
8	4.52114820618846664911801E-02	-7	5.03994834404875930585868E 03
7	5.13990667382496561572632E-02	-8	4.03199546318312498891910E 04
6	5.94850407419443846519443E-02	-9	3.62879959565922420445041E 05
5	7.04542374617203983358024E-02	-10	3.6287959635386537589273E 06
4	8.60624913245607282523142E-02	-11	3.99167993668047603062623E 07
3	1.09691967197760136838582E-01	-12	4.7900159996953656486590E 08
2	1.48495506775922047918360E-01	-13	6.22702079997185478417712E 09
1	2.19383934395520273677164E-01	-14	8.71782911999738464196511E 10
0	3.67879441171442321595524E-01	-15	1.30767436799997557373594E 12
-1	7.35758882342884643191047E-01	-16	2.0422789887999770912162E 13
-2	1.83939720585721150797762E 00	-17	3.55687428095999978430116E 14
-3	5.88607105874307714552838E 00	-18	6.40237370572799997962153E 15
-4	2.39121636761437509037090E 01	-19	1.21645100408831999980688E 17