

PRACTICAL

Wireless

THE UK'S BEST SELLING AMATEUR RADIO MAGAZINE

December 1997 £2.20



9 770141 085037

KEYLINES

LETTERS

NEWS

DIARY

CLUBS

COMPUTING

VINTAGE

FOCAL POINT

VHF

ANTENNAS

WHAT IS A ?

HF

BROADCAST

BARGAINS

PROFILES

BOOKS

DEALERS



G3XFD & G1TEX REVIEW

THE AKD MODEL HF3E

"ON TARGET THE SECOND TIME"

FEATURES

QRP CONTEST RESULTS
AMATEUR RADIO IN GERMANY

REVIEWS

THE PALSTAR KH-6 50MHz TRANSCEIVER
THE AKD HF3E TARGET RECEIVER

0.000MHz
START

30.000MHz
END

3 MHz/DIV

30.000MHz
END



Part Exchange Welcome

Waters & Stanton PLC

22, Main Road, Hockley, Essex. SS5 4QS
Open Mon-Sat 9.00AM - 5.30PM

FREE-PHONE ORDER LINE

0500 73-73-88

Buy Now - Pay Later

Pay Nothing for Three Months - INTEREST FREE

On most stock items in our catalogue over £100, pay 10% deposit and nothing more for three months. Then pay the balance or take our credit payment scheme over 1, 2 or 3 years at 26.8% APR - the choice is yours. OFFER ENDS 31/10/97 Subject to credit status.

Orders: 0500 73 73 88
01702 206835
Enquiries 01702 206835
01702 204965
FAX 01702 205843

Only W&S offer all this:

* 10 day Mail Order Approval on all items

If for any reason an item proves unsatisfactory, we will refund the purchase price provided the goods are returned in satisfactory condition within 10 days or purchase.

* Extended Warranty at an Unbeatable Price

We can offer lower cost extended warranties than any other dealer - available up to 5 Years.

* Unbeatable Prices and Deals

We can match or beat our competitors' prices and still offer you the satisfaction of dealing with the UK's best Ham Dealer

* No Surcharge for Credit cards

Some dealers charge extra for credit cards - a charge you won't have to pay at W & S.

* Class A and B Licensees on our Staff

Some dealers have no class A operators - would you buy a car from a salesman who couldn't drive what he was selling?

* ISO 9002 Registered

It says a lot about our commitment to quality and customer service - can you afford to deal elsewhere?

* The Backing of Four Full-Time Service Engineers

We have four full-time service engineers. Try asking some of our competitors if you can visit their service department! We don't send your gear away and make you wait months!

1998 Catalogue




- * Largest in Europe
- * 176 Colour Pages
- * 1000 Photographs
- * 1400 Products
- * Technical Specifications
- * News Snippets

Now established as the foremost equipment guide this edition is completely new with every page in full colour and almost every item illustrated. For the cost of a magazine you can get the best guide ever.

£2.95 plus £1 postage

NEW SG-2020 QRP Rig



1.8 - 30MHz


£499

Production of Index Laboratory's QRP transceiver has now been taken over by SGC who have completely redesigned it and managed to reduce the price as well! Deliveries should have begun by the time you read this. This transceiver promises to become the QRPers dream machine at a price that is affordable. The basic specification is: USB, LSB and CW 0 - 20 Watts; vastly improved receiver front end; Low battery drain; Improved circuit board layout; Receiver bandpass tuning; Built-in keyer; Full QSK; Size 63 x 152 x 178mm.

VHF & UHF Band Pass Filters

2m & 70cm

Digital Communications



NO MORE PAGER PROBLEMS

We guarantee this will kill all QRM caused by strong out of band signals - - - or your money back!

DCI-145 £89.95

Passband: 144 - 146MHz

Loss: Less than 1 dB

Selectivity: -68dB at 136MHz

-55dB at 155MHz

Power: 200 Watts

DCI-435 £119.95

Passband: 430 - 440MHz

Loss: Less than 1 dB

Selectivity: -47dB at 415MHz

-50dB at 455MHz

Power: 200 Watts

DC Mobile Lead

£6.95

Standard 12v DC lead for all modern mobiles. 1.9m long fitted 2 x 15A fuses and using standard "T" connector.



TOP 2m/70cm Mobile

Yaesu FT-8100R



£449 Price Match


or £467 inc 3yr Wtty.

Yaesu's new dual band mobile makes the competition look old and out-dated. You get a detachable head, 300 memories, true dual same band rx, CTCSS encode and the best display in the business. This is proving to be one of the best sellers ever - particularly at Our Price!

TOP 2m/70cm Handy

Adi AT-600

or £314 inc 3yr Wtty.



W&S £279

Reviewed PW August

PW says: "an incredibly well priced radio - amazingly sensitive - audio - worked very well with 12.5kHz channel spacing - An Absolute Cracker"

- * CTCSS encode/decode
- * Full DTMF + 1750Hz tone
- * Alphanumeric memories
- * Full duplex
- * CTCSS tone reader
- * 29 programmable features
- * AM airband receiver
- * Rx up to 990MHz
- * Nicads and charger



2 Years Warranty

W&S £249



- * 3 Power levels - Wideband receive
- * 40 Memories plus call channel
- * 7 Programmable steps
- * Channel or frequency display
- * The best sensitivity in the business
- * Keypad mic and mounting kit
- * CTCSS Encode and Decode!

AR-446 70cm 35W

FULL CTCSS



W&S £269

3W Novice version available

Adi AT-201 2m FM Handy



NEW W&S £149

- * 40 Channels
- * CTCSS Encode
- * CTCSS Decode
- * DTMF
- * Channel Reasout or
- * Frequency Readout
- * Set to Set Cloning

JUST ARRIVED
Look at the Features
Compare the Price

Adi AT-400 70cm FM Handy



Value W&S £169

- * 70cm FM Handy
- * 2W output
- * 5W on 13.8v
- * 1750Hz tone
- * Illuminated keypad
- * Ultra sensitive
- * Wideband Rx
- * 20 memories
- * Keypad entry
- * DTMF
- * Uses AA cells

The Novice Rig

Now the standard radio for Novice hams. It's sensitive, cost effective and was featured on Anglia TV

UK's Top Dealer for YAESU, KENWOOD & ICOM

W&S

NEW Ham Radio Electronic Magazine

<http://www.monitor.co.uk>

Monitor Internet

Provides the latest news of our products, prices and topical features. Log on now and read about ham radio plus much more!

TOP HF Base Station

NEW Yaesu FT-920

Plus £100
Accessory
Voucher

**£1499
Deal
Match**

5 Year Warranty £115

Yaesu FT-1000MPDC

Plus £100
Accessory
Voucher

**£1999
Deal
Match**

5 Year Warranty on FT-1000MPs £115

FT-1000MP £2849 £2199
FT-1000MPDC £2599 £1999

ICOM IC-756 HF Rig

Plus £50
Accessory
Voucher

**£1895
Deal
Match**

- * 100W of pure Magic
- * 160 - 6M
- * SSB - CW - AM - FM
- * Spectrum display
- * Auto ATU
- * Superb DSP built-in
- * CW Memory keyer
- * 100% duty cycle
- * Keypad entry option
- * DXers choice in the USA

KENWOOD HF RIGS

NEW TS-570

Plus £50
Accessory
Voucher

**W&S
£1199**

Kenwoods new transceiver is earning a reputation for offering one of the best receivers in the business. If you are looking for a hot little number that is not too expensive (Radio we mean!), send for brochure.

Yaesu FT-840 HF Rig

Plus £50
Accessory
Voucher

**£749
Deal
Match**

NEW

Garmin GPS-III

With complete
moving map of
the UK
& Europe

£349.95

The new GPS-III is loaded with a moving map covering millions of miles of motorways, ordinary roads, railways, rivers and shorelines. 12 channel receiver means fast positioning from switch-on, and the display width can be zoomed to cover from 500ft to 5,000 miles. Accurate to approx 45ft the display can be electronically rotated to suit car or hiker use. Just sit the GPS-III on the dashboard and watch your progress as you travel. Powered by 4 x AA cells - truly amazing! Get the best possible deal on this from Waters & Stanton. We have the latest UK version - phone today.

NEW IC-746

We will beat any
advertised deal!



160m - 6m 100W
2m 50W
Auto ATU
Spectrum Display
DSP Noise Unit
Electronic Keyer

TOP VHF Base Station

ICOM IC-821H 2m/70cm

Plus £50
Accessory
Voucher

**£1395
Deal
Match**

- * 2m/70cm All Mode
- * 45/40W adjustable
- * Full duplex
- * Satellite features
- * 160 Memories
- * 9600bps capability
- * Electronic keyer
- * IF shift, noise blanker

Yaesu FT-736R 2m/70cm



Special

**£1429
Or Better!
PHONE**

Offers even better value.
The classic 2m/70cm base station that just goes on and on - plus the options of additional band modules.

ICOM IC-207H 2m/70cm Mobile

Price Down

**£329
Deal
Match**

- * 2m & 70cm
- * 50W / 30W
- * Detachable head
- * Packet 9600 bps ready
- * 180 Memory channels
- * CTCSS & 1750Hz tone

New Batteries



- * Rechargeable Alkaline
- * 1.5V cells
- * No memory effects
- * Charging mid cycle is OK
- * 5 year charge shelf life
- * 3 times capacity of ni-cads
- * Very low cost

This is a brand new technology which has major advantages over ni-cads. Now you get a 1.5v cell that will hold its charge for up to 5 years and has 3 times the current capacity of normal ni-cads. We are offering these at a very special price direct from Canada. In stock now!

Starter Kit: Comprise 4 x AA cells and dedicated AC wall charger **£17.99 + £2 p&p**
4 x AA cell Packs: Ready charged. **£4.99 + £1 p&p**

W-MM1 Multimode Modem



**W&S
£69.95**

NEW

- * Packet, AMTOR, CW
- * SSTV, Fax, RTTY
- * NAVTEX, SYNOP
- * Transmit and receive
- * Needs PC 286 or better
- * Includes software
- * No external power required
- * Connects to RS-232

Price Down

ICOM IC-706 MK II

Plus £50
Accessory
Voucher

**£995
Deal
Match**



or £1059 inc 5yr Wtty

160-6m 100W 2m 25W ++

We are pleased to endorse the performance and design of the IC-706 Mk II transceiver as the best compact hf mobile bar none. It out performs and out specifies any other model. The only choice left is which dealer you buy it from! We offer you an unbeatable price and an unbeatable back-up service plus optional extended 5 year warranty for an extra £98!

Send for Brochure



Kachina 505DSP HF Transceiver

The 506DSP transceiver is remotely controlled (up to 23m away - so no noise problem!) from your computer. Includes 100W transceiver module, operator control head and software. This has taken the USA by storm


- * 100W all modes
- * Runs under Windows 3.1 or 95
- * Gen. cov. receiver
- * Variable bandpass filters
- * 1Hz tuning steps
- * Antenna impedance chart
- * RF speech processor
- * SWR alarm
- * Full DSP
- * Full CW break-in
- * Electronic keyer
- * 100 memories
- * Auto notch filter
- * control head mounts in PC or on desk.

Transceiver £1999.00 (Available November)
Auto ATU £249.95

NEW

Kenwood THG71E

- * Dual Band 2m/70cm
- * 200 memories
- * Alphanumeric Display
- * Full CTCSS
- * DTMF
- * Up to 6W out
- * Wideband Receive
- * Illuminated Keypad
- * PC Compatible
- * Windows Programming



Send For Brochure

£239.95

Special Purchase

£349

£229

IC-T7E
Dual Bander

- * 2m & 70cm Handy
- * 70 Memories
- * Full CTCSS
- * Tone scan function
- * Up to 4W out
- * 8 tuning steps
- * DTMF
- * Auto power saver
- * 600mAh 7.2v ni-cad
- * AC charger and helical

Your chance to purchase this fine handheld at a very special price - whilst stocks last

MFJ

Ham Radio Accessories

ORDERS
ONLY ON:
FREEPHONE
0500 73 73 88

MFJ-784B Filter

£239

Price Down!



- Works with any rx. or tcvr.
- DSP filter, fully programmable
- 16 Factory pre-sets
- Plugs directly into audio out
- Drives speaker or headset
- Requires 12v at approx 500mA

MFJ-1278DSPX Data Unit

£399



- Multi-mode
- Packet
- Amtor
- Pactor
- Colour SSTV
- 10 Modes total
- DSP filtering
- Tuning scope
- Simple to use
- Software

MFJ-948 HF ATU

£129

Price Down!



- 300 Watts PEP 150W CW
- 1.8 - 30MHz - with ease!
- Wire, coax or balanced line
- Balun included for best match
- 30 / 300W power meter - PEP / RMS
- Antenna selector, by-pass etc.

MFJ-781 DSP Filter

£139



Just arrived, this new DSP filter that is specially designed for CW and data modes.

- Digital Audio Filter
- CW 50, 100, 200, 500Hz
- Amtor, fax, GTOR, PACTOR
- RTTY, SSTV, We-FAX

MFJ-949 HF ATU

£149

Price Down!



- 160 to 10m 300W PEP 150W CW
- Wire, coax or balanced feed
- Built-in Dummy Load
- 30 / 300W power meter - PEP / RMS
- Antenna selector, by-pass etc.

MFJ-914 Auto Match

£59.95



Your Auto ATU will now match any aerial when used with this.

Auto-Tuner Extender

Connect between auto tuner and transceiver - no more problems with G5RVs and all those difficult antennas - 160 to 10 metres

MFJ-812B 2m VSWR

£36.95

Price Down!



- 144 - 148MHz 30 / 300W
- Forward & Reflected Power
- Reads field strength
- Easy to use - convenient size
- Low cost - efficient accessory

MFJ-921 2m ATU

£69.95



144MHz 200W antenna tuner that helps you get a perfect VSWR every time. Includes VSWR and power meter and fitted SO-239 sockets.

MFJ-864 160M to 70cm

£79.95



- All bands from 1.8MHz to 440MHz
- Cross needle meter - 30 / 300W
- Comprehensive user calibratable
- Separate HF and VHF/UHF sensors
- Illuminated meter (ext. 12V)
- Everything you need in one box
- 185 x 65 x 75mm

MFJ-259 HF Analyser

£229

Price Down!



- 1.8MHz - 170MHz
- Digital Readout
- Resonance
- VSWR
- Impedance
- AA batteries or 12v external

Connect to aerial or coax and adjust it in seconds. Turns hours into minutes and ideas into antennas!

Ameritron 811 1kW

Price Down!



The only currently available HF linear to have passed a full lab. CE test

- 1 kW linear 9dB Gain
- Like a 5 element Monobander!
- Uses low cost 811A tubes
- Built-in rugged AC Supply
- Instant by-pass switch
- PA V/A meter + Grid meter
- Over rated variable capacitors
- Fan cooled for long life
- Very efficient - 600W output
- Easy to tune and connect
- Size 16" x 13.75" x 8"

160 to 10M of DX-Getting Power
Perfectly matches all 100W rigs

£799

MFJ-901B HF Atu

£69.95

Price Down!



MFJ-941E Atu

£109

Price Down!



- 160m to 10m ATU - 300W
- Wires, Coax and Balanced Feed
- Cross Needle VSWR & Power
- 3-Way antenna selector
- By-pass position - Dummy load socket
- Internal Balun - 30 or 300W position
- 260 x 180 x 70mm

MFJ-16010 Wire Tuner

£44.95



Covers 1.8MHz to 30MHz and matches any random wire to your hf transceiver. Handles 300 Watts and fitted SO-239. Ideal for portable work.

MFJ-713 Intermod Filter

£64.95

NEW



A three section high-Q bandpass filter for 145MHz handhelds. Includes rf sensing.

- 144 - 148MHz
- Up 20 50dB rejection
- Defaults to "thru" when off
- Minimum rf T/R required: 50mW
- BNC termination
- Power: PP3 (not supplied)
- Size 70 x 50 x 45mm

MFJ-250X 1kW load

£34.95

Price Down!



- 1kW Dummy Load
- Oil cooled design
- SO-239 socket
- Ideal for linears
- 1MHz to 400MHz

* Oil is not supplied

MFJ-260C 300W

£34.95

- Dummy Load
- 50 Ohm
- 300W
- OK to 450MHz
- Air cooled
- SO-239
- Totally enclosed
- Essential item



MFJ-704 LPF Filter

£39.95

- Low pass filter
- 1.8 - 30MHz
- Cleans up output
- Reduces TVI
- 1kW rating
- SO-239 sockets
- Fully shielded



MFJ-418 CW Tutor

£79.95



This tutor has taken the USA market by storm. There has never been a better way or more convenient way to learn the code. Unlike other tutors this one not only sends random characters and groups, it also sends complete QSOs, just like the real test. And no QSO is ever the same!

- Displays words, letters and numbers
- 3 to 35WPM with natural CW note
- Various modes including Farnsworth
- Enormous vocabulary of words
- Actually sends complete QSO
- Characters or groups
- Headphone socket; Powered from PP3
- Sends text just like an actual test
- A tutor that displays what it sends.

MFJ-9406 6M Trancvr.

£249

Price Down!



- 50 - 50.3MHz 10W SSB
- RF speech processing
- 10MHz xtal filter
- Super performance
- Ideal way to 6M DXing

Waters & Stanton PLC

Enquiries: Tel. 01702 206835 / 204965
Fax. 01702 205843

22, Main Road, Hockley, Essex SS5 4QS

PRACTICAL Wireless

DECEMBER 1997
(ON SALE NOVEMBER 13)
VOL. 73 NO 12 ISSUE 1089
NEXT ISSUE (JANUARY)
ON SALE DECEMBER 11

EDITORIAL & ADVERTISEMENT OFFICES

Practical Wireless
Arrowsmith Court
Station Approach
Broadstone
Dorset BH18 8PW
☎ (01202) 659910
(Out-of-hours service by answering machine)
FAX (01202) 659950

PW's Internet address is:

@pwpub.demon.co.uk You can send
mail to anyone at PW, just insert their
name at the beginning of the address,
e.g. **rob@pwpub.demon.co.uk**

Editor

Rob Mannion G3XFD
Technical Projects Sub-Editor
NG ("Tex") Swann G1TEX
News & Production Editor
Donna Vincent G7TZB
Editorial Assistant
Zoë Crabb
Art Editor Steve Hunt
Page Layouts Paul Blachford & Get Set
Graphics

Advertisement Manager

Roger Hall G4TNT
PO Box 948, London SW6 2DS
☎ 0171-731 6222 FAX 0171-384 1031
Mobile (0585) 851385

Advert Sales and Production (Broadstone Office)

Chris Steadman MBIM (Sales)
Carol Trevarton (Production)
Peter Eldrett (Typesetting)
☎ (01202) 659920 - 9.30am - 5.30pm
FAX (01202) 659950

Books & Subscriptions

Michael Hurst:
CREDIT CARD ORDERS

☎ (01202) 659930
(Out-of-hours service by answering machine)
FAX (01202) 659950

Copyright © PW PUBLISHING LTD. 1997. Copyright in all drawings, photographs
and articles published in Practical Wireless is fully protected and reproduction in
whole or part is expressly forbidden. All reasonable precautions are taken by
Practical Wireless to ensure that the advice and data given to our readers are
reliable. We cannot however guarantee it and we cannot accept legal
responsibility for it. Prices are those current as we go to press.

Published on the second Thursday of each month by PW Publishing Ltd.
Arrowsmith Court, Station Approach, Broadstone, Dorset BH18 8PW. Tel: (01202)
659910. Printed in England by Southernprint (Web Offset) Ltd. Distributed by
Seymour, Windsor House, 1270 London Road, Norbury, London SW16 4DH. Tel:
0181-679 1899, Fax: 0181-679 8907, Telex: 8812945. Sole Agents for Australia and
New Zealand - Gordon and Gotch (Asia) Ltd., South Africa - Central News
Agency. Subscriptions INLAND £25, EUROPE £30, REST OF WORLD £32
(Airmail). REST OF WORLD £32 (Airmail), payable to PRACTICAL WIRELESS,
Subscription Department, PW Publishing Ltd., Arrowsmith Court, Station
Approach, Broadstone, Dorset BH18 8PW. Tel: (01202) 659930. PRACTICAL
WIRELESS is sold subject to the following conditions, namely that it shall not,
without written consent of the publishers first having been given, be lent, re-sold,
hired out or otherwise disposed of by way of trade at more than the
recommended selling price shown on the cover, and that it shall not be lent,
re-sold, hired out or otherwise disposed of in a mutilated condition or in any
unauthorised cover by way of Trade, or affixed to or as part of any publication or
advertising, literary or pictorial matter whatsoever. Practical
Wireless is published monthly for \$45 per year by PW
Publishing Ltd., Arrowsmith Court, Station Approach,
Broadstone, Dorset BH18 8PW. Royal Mail International, c/o
Yellowstone International, 97 Bowles Court, Hackensack, NJ
07601. UK Second Class Postage paid at South Hackensack.
Send USA address changes to Royal Mail International,
c/o Yellowstone International, 2375 Pratt Boulevard, Elk Grove
Village, IL 60007-5937. The USPS (United States Postal Service)
number for Practical Wireless is: 007075.



9 EDITOR'S KEYLINES

10 NEWS 1997

A round-up of what's new from the world of
Amateur Radio

12 RECEIVING YOU

Readers' Letters

14 CLUB SPOTLIGHT

Is your club under the PW spotlight this
month?

16 WHAT IS A ?

Ian Poole G3YWX looks at the varactor diode.

17 RADIO DIARY

Plan your radio rally visits with our
comprehensive list of dates.

19 PRACTICAL WIRELESS 1997 144MHz QRP CONTEST RESULTS

Neill Taylor G4HLX rounds-up the results of
1997 PW 'fun' contest

22 TOPPING'S TIMED OUT

Collin Topping shares his design for a
transmitter 'time-out' unit.

26 REVIEW- PALSTAR KH-6 50MHz HAND-HELD

Richard Newton G0RSN discovers the new
50MHz hand-held from Palstar.

31 ERRORS & UPDATES

32 IT'S A CLASSIC COMBINATION

Ben Nock G4BXD looks at the Trio JR-599
receiver and T-599 transmitter which are now
readily available on the second-hand market.

37 DOUG DeMAW W1FB OBITUARY

The Rev. George Dobbs G3RJY pays a personal
tribute to a man whose life and work signified
an important era in Amateur Radio.

38 AKD HF3E TARGET RECEIVER

Rob Mannion G3XFD and Tex Swann G1TEX put
the new 'up market' version of the HF3
receiver to the test and find that it's right on
'target'.

44 ANTENNA WORKSHOP

Gerald Stancey G3MCK says there's only one
antenna for the 'Typical' amateur- the dipole.

46 BOOK PROFILES

48 AMATEUR RADIO IN GERMANY

Angelika Voss G0CCI
provides an insight into
how Amateur Radio is
structured in her home
country of Germany.



50 CHRISTMAS SUBSCRIPTIONS

Order a gift subscription to PW now and
receive either a diary or two extra issues
absolutely free!

53 CARRYING ON THE PRACTICAL WAY

The Rev. George Dobbs G3RJY provides 'tips
and twinkles' for the festive season.

58 VALVE & VINTAGE

Phil Cadman G4JCP takes his turn in manning
the vintage wireless 'shop'.

63 HF FAR & WIDE

64 VHF REPORT

David Butler G4ASR has all the latest news
from 50 MHz and above

67 BITS & BYTES

70 BROADCAST ROUND-UP

71 FOCAL POINT

Graham Hankins G8EMX looks at the latest
the ATV scene.

72 BARGAIN BASEMENT

Looking for a Christmas bargain? - Look no
further.

76 PRACTICAL WIRELESS 1997 INDEX

80 BOOKSTORE

83 COMING NEXT MONTH



AKD HF3E TARGET RECEIVER REVIEW




Note: Due to technical problems with the printed circuit boards we have been unable to publish Part 2 of The
GDP-430 Hand-Held project this month. Please accept our apologies for any inconvenience caused.

84 ADVERTISERS' INDEX

NEVADA®

**NEW 32 page
AUTUMN catalogue
now available**

SEND A4 S.A.E. FOR YOUR FREE COPY!



ALINCO HOT PRODUCTS

DX-70TH

HF Transceiver with 6 mtrs

£775
£8 P&P

- All HF Bands 100W output
- 50MHz 100W output
- General coverage RX
- Removable front panel
- Receiver pre-amp
- Filters fitted as standard
- Superb TX audio and RX
- Good RX sensitivity
- Full break in on CW
- Speech compressor
- 100 memory channels
- All modes: USB, LSB, CW, AM, FM
- All mode squelch
- CTCSS encoder
- Noise blanker
- Scan facilities
- Quick offset for DX pile-ups
- IF shift control
- Antenna sockets for HF and 6M

DX-70T

100W HF + 10W 6mtr TX

£695
£8 P&P

Alinco's 10W on 6mtrs version of the DX-70 TH above. Narrow receive filters and CTCSS fitted as standard.

DR-M06TH

6mtr FM Mobile
50-54MHz

NEW HI-POWER VERSION

£249.95
£8 P&P

With the new 6 metre repeaters now up and running, this is the ideal radio for the Band. With an optimised receive front end, CTCSS and easy to use controls you will be amazed at the range achievable.

- Repeater shifts
- 100 memories
- CTCSS encoder
- Time-out timer
- Output 20W

DR-605E Dual Band Mobile

£399.95
£8 P&P

Easy to use twin band mobile TX that delivers both high power and performance with user friendly features.

- 50W (2m)-35W (70cms)
- 100 memories
- Full Duplex
- CTCSS encoder fitted

DR-610E Twin Band Mobile

£499.95
£8 P&P

- 136-174/420-470MHz FM
- Channel Scope
- Full duplex
- CTCSS encoder
- AM Airband RX
- 120 memories
- VHF 50W/UHF 35W max

DJ-G5EY Dual Band Handheld

A brilliant twin band handheld that does everything including spectrum display of adjacent channels. The RX has a superb front end that does not suffer with breakthrough like other handhelds & has CTCSS/DTMF built in as standard.

- Spectrum channel display
- Optional extended receive including Airband 108-173.995MHz 400-511.995MHz 800-999.990MHz
- Full VHF/UHF Duplex
- Over air cloning
- Cross band repeat
- Up to 5W RF output
- 100 memories

£299.95
£8 P&P

DJ-191E 2 Metre Handheld

A new slim line 2 metre handheld that's easy to use and has an enormous clear display.

- Up to 5W output (with 9.6V NiCad pack)
- 40 memories channels
- Cloning capable
- CTCSS encoder
- DTMF fitted
- Battery save facility
- Scan functions
- Time out timer

£169.95
£8 P&P

DJ-X10E Scanning Receiver

- 100kHz - 2000MHz
- AM/WFM/NFM/CW/SSB
- 1200 memories
- Channel scope spectrum analyser
- Channel scope peak search
- Keypad lock control
- User friendly features
- Large clear display
- Timer functions
- Battery save facility
- Squelch control
- Dual VFUs
- A super sensitive RX
- Built in 24 built in clock
- Facilities for cloning another set
- Advanced scanning features
- Stylish cabinet with large speaker
- Display - Contrast - Control
- Low battery alarm
- Switchable attenuator
- Selectable control beep tone

£349
£8 P&P

SG 500 Smart Power Cube

500W Mobile HF linear amplifier

- 500W RF output
- 12V operation
- 1.6 - 30MHz
- Microprocessor controlled
- Ideal for fixed - Mobile & Marine

£1150

Monitors your power needs and antenna condition and automatically in less than 15 milliseconds - selects the right bandwidth filter.

NEVADA was recently appointed UK Distributor for SGC

SEND SAE FOR COLOUR LEAFLITS ON FULL ALINCO RANGE

SGC NEW products for the Amateur, Marine or Commercial user

HF-VHF SMARTTUNER®

Model SG231

£499

Now a new low profile metal cased and ruggedised wideband auto ATU that covers HF plus 6 mtrs! Designed for use at the masthead as the centre of a multiband wire antenna - or in mobile, marine or base station operations.

- 1 - 60MHz
- 100W PEP
- Waterproof
- Covers 6 mtr Band
- Multiband with a single mobile whip
- Multiband any length of wire end or centre fed (min 8ft for 160mtrs)

SMARTTUNER®

Weatherproof Automatic Tuners

Now three models of fully automatic weather-proof tuners that use a computer system to continuously monitor all the antenna parameters and instantly select the correct match.

- A non-volatile memory remembers the correct match for the last 500 operating frequencies.
- 1.6MHz 30MHz
- Tunes random wires from 8ft to 300ft
- Multiband with a single wire
- Keeps the RF away from the shack
- Ideal for HF Mobile or Marine multiband operation with a single 7ft whip

SEND AN SAE FOR FULL DETAILS OF THE SGC MODELS

SG 500 Smart Power Cube

500W Mobile HF linear amplifier

- 500W RF output
- 12V operation
- 1.6 - 30MHz
- Microprocessor controlled
- Ideal for fixed - Mobile & Marine

£1150

Monitors your power needs and antenna condition and automatically in less than 15 milliseconds - selects the right bandwidth filter.

NEVADA was recently appointed UK Distributor for SGC

Looking for a NEW HF Radio?then call us for expert advice!

ICOM 756



PRICE £2195 **£1895** £8 p&p

YAESU FT1000MP AC



PRICE £2499 **£2199** £8 p&p

YAESU FT-920



PRICE ... £1699 **£1499** £8 p&p

FT-920 ACCESSORIES

- FM-1 FM Unit £44.00
- YF-116A AM Filter £49.00
- YF-116C CW Filter £49.00

YAESU FT-840



PRICE £849 **£749** £8 p&p

Optional FM fitted.....£39.95

ICOM 706 Mk II



PRICE £1195 **£1049** £8 p&p

IC-706 ACCESSORIES

- FL - 101 9MHz CW Filter 250Hz £69.00
- OPC - 581 Separation cable £29.00
- MB - 63 Bracket for F/panel £6.50
- OPC - 589 Mic adaptor lead £16.50
- AT - 180 Auto ATU (inc 50MHz) £345

DRAKE SW2



PRICE **£499** £8 p&p

OPTIONAL EXTRAS

- Infrared remote control £49.95
- Carrying/tilt handle £7.95
- Mobile mounting kit £14.95



**ON THE
INTERNET?**

VISIT OUR WEBSITE

<http://www.nevada.co.uk>
includes all the very latest secondhand listing

E MAIL US AT:

info@nevada.co.uk

- ✓ **LOW, LOW PRICES**
- ✓ **HUGE STOCKS**
- ✓ **FRIENDLY ADVICE**

... AND PAY BY 3 POST-DATED CHEQUES

ON ANY ITEM OVER £100 IN VALUE
Simply divide the price into 3 equal payments. Write 3 cheques dated in consecutive months starting with today's date. Write your telephone N°, cheque card N° & expiry date on the back of each cheque. Post them to us, enclosing your name & address & we will (subject to status), send your goods immediately.



Palstar™

the NEW name in Amateur Radio!

NEW KH-6 6 metre Handy Transceiver

- 50 - 54MHz
- 4 Watts RF out (12V)
- 2 Watts RF out (9V)
- UK Repeater offsets
- Intelligent Power Save circuit
- CTCSS Encode/Decode
- Scan functions
- Memory recall
- Supplied with 8 cell AA battery case (batteries not included)



Optional Extras P&P £2.75 on each item

KH6/NP-126 NiCad pack (12V)	£29.95
KH6/HF-50L Flexi Higher Gain Whip	£12.95
KH6/CC-27 Soft Case	£9.95
Nic/060 NiCad Mains Charger	£9.95
KH6/DA-27 Slide on DC/Charger adaptor	£7.95
KH6/CP01 Cigar lighter lead	£8.95

only **£149** P&P £6.00

Antenna Tuners

AT300

150W compact tuner

A new compact high quality antenna tuner that provides adjustable impedance matching for all types of antennas. The AT300 also measures power and SWR using an illuminated frequency compensated SWR/Power meter. Using a 48 position switched toroidal inductor with silver plated double contacts it is possible to easily adjust for the lowest SWR Ratio on the selected transmit or receive frequency. A built in dummy load allows for off air tuning and testing.

- Matches dipoles, centre fed doublets, G5RV's, Balanced feeders, Verticals, Single wires, Delta loops, Beams, Windoms and Inverted V's.
- Built in 4:1 Balun for open wire feeders or balanced line fed antennas.
- Bypass position for quick straight through antenna connection but still with SWR/Power monitoring.
- 8 position antenna selector switching.
- 4 way antenna switching including:-
Direct coax 1, coax 2, bypass & dummy load.
Tuned coax 1, coax 2, wire and dummy load.
- Average power reading to 200Watts.
- Standing Wave Ratio measurements with easy set function.

SPECIFICATIONS

Frequency
1.8-30MHz
Power Maximum
150W continuous
150W for 15 sec (dummy load)
Dimensions
8.7cm H x 18.2cm W x 23cm D (approx)
Weight
1.364kg

£129.95

AT1500

1500W high power tuner

The AT1500 is a solidly constructed high power antenna tuner using heavy gauge materials for the case and a "Beefed up" roller inductor constructed from 10 gauge wire on a Delrin low absorption former. Designed by Paul Hrivnak (founder and former owner of Vectronics in Canada) this unit is built to last!

- Matches dipoles, centre fed doublets, G5RV's, Balanced feeders, Verticals, Single wires, Delta loops, Beams, Windoms and Inverted V's.
- Built in 4:1 Balun for open wire feeders or balanced line fed antennas.
- Bypass position for quick straight through antenna connection but still with SWR/Power monitoring.
- 6 position antenna selector switching.
Direct coax 1, coax 2, bypass.
Tuned coax 1, coax 2, wire.
- For balanced feeders select wire and link on back panel.
- Average power reading to 3000Watts.
- Standing Wave Ratio measurements with easy set function.

SPECIFICATIONS

Frequency
1.8-30MHz
Power Maximum
1000W single tone,
1500W PEP
Dimensions
12.9cm H x 32.2cm W x 34cm D incl. terminals (approx)
Weight
4.82kg

£365.95

TIMEWAVE TECHNOLOGY INC

DSP 599ZX

All-Mode Digital Signal Processor




- Enables you to hear weak voice, data, CW
- Hyperspeed DSP (36.8 million instructions per sec)
- Auto notch - kills heterodynes
- Reduces noise automatically
- Built-in test facilities, digital voltmeter + audio signal generator

£349.00 £8 p&p

AEA PK12

Low cost Packet TNC



- 1200 BPS VHF/UHF
- Host mode
- Advanced command set
- GPS firmware
- Net ROM

NEW LOW PRICE

£99.95 £8 p&p

NEW COMET

Triple Band Base 5/8 wave antenna

- 50/144/430MHz
- 300 Watts
- 3.6/8.6dBi gain
- 2.42 metres long

£89.95 £6 p&p

cushcraft CORPORATION

antennas now in stock!

HF Verticals

R7000 10, 12, 15, 17, 20, 30, 40mtr half wave vertical£369.95 £10 p&p
AP8A 10, 12, 15, 17, 20, 30, 40, 80mtr quarter wave vertical£229.95 £8 p&p

VHF Verticals

AR2 2mtr RINGO 1.2m long 3.75 db£39.95 £8 p&p
ARX2 2mtr RINGO RANGER 2.8m 5.5 db£49.95 £8 p&p
ARX2B 2mtr RINGO RANGER 11.43m 7 db£59.95 £8 p&p
AR6 6mtr RINGO 3.1m 3.75 db£59.95 £8 p&p
ARX6 6mtr RINGO RANGER 7.3m 5.5 db£199.95 £8 p&p

Beams

A35 10, 15, 20mtr 3 el Yagi£389.95
A45 10, 15, 20mtr 4 el Yagi£469.95
A3WS 12, 17mtr 3 el Yagi£299.95
A743 30, 40mtr kit for A35£129.95
A744 30, 40mtr kit for A45£129.95
A103 30mtr kit for A3WS£119.95
TEN-3 10mtr 3 el beam£139.95
104CD 10mtr 4 el beam£269.95
154CD 15mtr 4 el beam£289.95
203CD 20mtr 3 el beam£359.95

Visit the **PALSTAR Web Site!** <http://www.palstar.com>

ORDER HOTLINES TEL: (01705) 662145 FAX: (01705) 690626

• 189 London Road • North End • Portsmouth • Hampshire • PO2 9AE

NUTS AND BOLTS

OK, so you've just bought the radio you've been waiting for! But have you got what it takes to make that first QSO?

- Filters
- Power supplies
- Coaxial Cables
- Connectors
- Data Equipment
- Rotators
- Antennas & Accessories

(We have probably the UK's Largest Selection)

- Log Books
- SWR/PWR Meters
- Morse Keys
- Antenna Analysers
- Amplifiers

We can supply all this and lots more.

Call us on 01703 251549 for advice and prices.

NEW AXMINSTER SHOP

By the time you read this Rodney, Bill and Mandy from our Axminster branch should be just moving in to brand new premises just down the road from their current shop.

They will have purpose built displays for Icom, Kenwood and Yaesu radio equipment, customer shacks similar to those in HQ, a coffee area and a whole new range of Kenwood and Sony home entertainment systems.

They will also be updating the range of antennas and radio accessories that they currently stock so they will truly be a "one stop radio shop!"

Watch this space for the opening date when they are planning an opening party with dealer support, raffles and refreshments.

New For Data Enthusiasts

Ever wondered how to receive and transmit SSTV, FAX, RTTY, AMTOR, HF Packet, VHF Packet and CW in one convenient package for under £100.00?

The answer is the New SMC Multimodo Data Communications PC Interface.

Features include:

- * Full technical support
- * User friendly manual
- * Supplied complete with cables and software
- * High quality construction
- * LED tuning display
- * CE Approved

We firmly believe that the SMC Multimodo will open up a whole new world of Data Comms for the Short Wave Listener and Radio Ham alike.

Just £89.00 FREE Postage.

We hold the UK's Largest

Selection of ready made packet radio and multimode leads for most popular radios and scanners. Including those hard to find US style phone sockets and mini din connectors used on most Yaesu and Kenwood radios. Prices start from just £14.95 plus P & P.

SPECIAL OFFER

AR303 Light Duty Rotators



Ideal for VHF, UHF, DXTV and FM Broadcast etc.

Supports up to 50 kilos.

Complete with controller.

ONLY £39.00 P & P £4.00

IT'S GOOD

MAXON EASIWAVE

Many businesses have an ongoing need for reliable professional quality two-way radio at affordable prices, i.e. farmers, business with several offices in a nearby town etc. where conventional telephone lines would be inaccessible and cellular telephones would be too expensive.



The UK Government have recently introduced the Short Range Business Scheme which permits the use of certain UHF radio transceivers in such situations.

We are pleased to offer the new SMC Type Approved Easiwave range of transceivers starting at just £199 plus VAT. The licensing couldn't be easier, just fill in a simple form and mail a cheque off to the DTI! Available now. Please call us now for a free colour brochure.

Is your boss looking for an inexpensive solution to business communications using two-way Radio?....

Many small businesses are discouraged from using two-way radio because of the UK licensing regulations and equipment costs. We can help in many areas including, Low cost short term hire - ideal for public events such as Shows, Expeditions and functions.

Call our direct Hire Sales on (01703) 900 194


HILOMAST Pneumatic Telescopic Masts

We design and build on site a high quality comprehensive range of pneumatic masts.

The masts extend from between five and thirty feet.

They are robustly constructed from heat treated aluminium alloy, with Alloy pistons, Teflon slide rings and neoprene seals.

The masts can be used for supporting directional antennas and cameras etc. whether the sections are partly or fully extended they can be rotated to the required direction and then clamped.



They are extended by using low pressure air. The air is supplied either from a compressor or, for smaller masts, from a foot pump. Locking collars fitted to the top of each section are easily operated by means of a thumb screw. This allows the mast to remain permanently extended without maintaining air pressure. The thumb screws can be replaced by socket sets operated with a T key - both systems are supplied with the mast.

Many comms systems require an easily erected and retracted supporting mast and Hilomasts are designed to meet such needs and demands placed upon them under field conditions.

Prices start from around £900.

For queries or a colour brochure contact Tony Searl on (01703) 255111.



South Midlands Communications Ltd

S M House, School Close, Chandlers Ford Industrial Estate, Eastleigh, Hampshire SO53 4BY
Amateur/Short Wave/Data (01703) 251549. E-mail amateur@smc-comms.com website: <http://www.smc-comms.com>

NEW KENWOOD

The TH-G17E is Kenwood's addition to the thriving dual band handheld market.



Details are limited at the moment but its features will include:

- * 200 Memory channels
- * 6W RF Output (maximum)
- * Built-in CTCSS encode/decode
- * DTMF Remote Control
- * Wide Band RX Coverage

With a projected retail price of around £269 we expect this to be at the top of everyone's Christmas list
So reserve yours now.

YAESU VX1R

The VX-1R is an ultra-compact Dual Band Transceiver with wide-band receive coverage. Though only 81mm high by 47mm wide and 25mm deep the VX-1R is a full-function, scanning transceiver.

The VX-1R provides frequency coverage in the range 76MHz - 999MHz, with facilities for AM, FM Broadcast, Air Band, VHF / UHF TV. Transmit and receive is available in the 144 / 440MHz amateur bands with both encode and decode



facilities for CTCSS and DCS. Additionally, the VX-1R features Windows PC programming capability using ADMS-1D software, back-lit Keyboard and LCD Display. The VX-1R comes supplied with a rechargeable Lithium Ion Battery, AC Adapter/Rapid Charger, Flexible Antenna, Belt Clip and Hand strap.

FEATURES INCLUDE:

- * 290 Memory Channels
 - * CTCSS Encode/Decode
 - * DCS Encode/Decode
 - * 500mW Power Output (1W with sup. AC Adptr.)
 - * AM Air-Band Receive
 - * Size H81 x W47 x D25 mm
 - * Weight 125g with Antenna & Lithium Ion Battery
- ONLY £269.00
Wideband (Export) £279.00

CUSHCRAFT

High Quality Range of Antennas
A14410SN 2m, 10 ele yagi, 13.2dbd£65.00
A14820T 2m, 10 ele, crossed yagi, 12.2dbd£99.00
AR270 2m/70cms dualband vert. 1.13m long£65.00
AR270B 2m/70cms dualband vert. 2.3m long£89.00
22XB 2m Oscar, 22 ele, c/w polarisation switch.£229.00
A50-3S 6m, 3 element yagi 10.5dbd£75.95
A50-6S 6m, 6 element yagi 11.6dbd£229.95
719B 70cms, 19 element yagi ... 15.dbd£109.00
AP8A 3.5 - 28MHz 8 band vertical£199.00
40-2CD 40m, 2 element yagi, 5.5dbd£469.00
Free carriage on Cushcraft aerials.



TO TALK!

AOR AR8000

The AR8000 is leading the way in the scanner field at present by offering the benefits of short wave & professional wide band VHF/UHF receiver.

The numerous features include:
500kHz - 1900MHz
AM/NFM/WFM/USB/LSB/CW
1,000 nameable memories
Internal Nicads, 12V DC and 240AC mains (PSU included)
Optional PC interface.
Available exclusively from SMC the AR8000 MCO Enhanced is ready to use with the Optoelectronics Scout frequency counter and the Siskin Multicat CAT interface.
Phone for a glossy brochure, or better still call in to one of our branches and try one out.
AR8000MCO Enhanced ONLY £324.95

KENWOOD TS-570D

Top of the range DSP HF Transceiver.
Superior performance at a price that won't break the bank.



Transmit 160 - 10m
Receive 500kHz - 30MHz
Mode CW, SSB, AM, FM & FSK. RF Output Power 100W
AM-25W. TX Audio Shaping, CW Autotune, 100 Memories, PC Control Option.
With a FREE TH42E 70cms Handheld and a FREE HF3VNB Antenna
Only While Stocks Last.
PRICE £1199.00

YAESU FT-920

The Latest HF plus 6m All Mode Transceiver.
With DSP, Noise Reduction System, Wideband RX, 100W and much more.

Can You Afford To Be Without One?
With a FREE FM Board and FREE HF3VNB Antenna. Stocks are very limited so call us and place a deposit.
CALL US FOR OUR BEST PRICE
01703 251549

YAESU FT-1000MP

"The very best in the HF Transceiver Field".
We have a few left in stock with FREE MD100A8x Desk Microphones and a FREE HF3VNB Antenna
CALL US FOR OUR BEST PRICE
01703 251549

The Ultimate Mobile Rig.

The IC-706MKII comes 12.5 kHz ready with HF 2m and 6m



with FREE OPC 589 Extension Kit.
CALL US FOR OUR BEST PRICE
01703 251549

NEXT DAY DELIVERY AT NO EXTRA COST!

As of November the 1st we are pleased to announce FREE Next Day delivery on all retail orders over £150.00

UK MAINLAND ONLY

ANDY SMC LONDON

6 Royal Parade, Hanger Lane
London W5A 1ET
0181 997 4476

RODNEY OR BILL SMC AXMINSTER

1 Western Parade, West Street,
Axminster, Devon EX13 5NY
01297 34918

Mail Order/Customer Service
AILSA OR PHIL 01703 251549
Antenna/Rotator Technical Enquiries
NORMAN 0467 462774 (mobile)

UK's Premier Service Centre

Castle Electronics was formed in 1990 by Geoff Wainhouse and John Taylor, when they realised that there was a need for an independent service facility for the Amateur Radio enthusiast. Both are qualified Engineers in Radio Communications and Microprocessor Technology. They are proud to have had Castle Electronics appointed as the authorised service agents and dealers of Kenwood, ICOM and Yaesu equipment. Castle Electronics is the primary sub-contractor for Kenwood service requirements.

**WE WILL DO OUR VERY BEST
TO BEAT ANY OTHER GENUINE ADVERTISED PRICE!**

**Castle
Electronics**

HAS MOVED

Watch this space for exciting
news on new products

KENWOOD

TS-870S



TS-570

TM-V7E



YAESU



FT-736

Dual Band Base
very popular



FT-920



FT-1000MP



FT-50R

ICOM



IC-706 MKII




IC-756



T-7E

GEOFF G4AQU - JOHN G6VJC



Castle Electronics

Unit 20, Halfpenny Green Airport, Bobbington,
Nr. Stourbridge, West Midlands DY7 5DY.

Telephone 01384 221036. Fax 01384 221037



PHONE 01384 221036 OR VISIT US TODAY



EDITOR'S

Keylines

Rob Mannion's viewpoint on the World of Amateur Radio

In the past few years I've seen many of my old friends pass on, and I'm grateful to have fond memories of them. However, on occasions we lose someone who is rather 'special' and the late **Bert Newman G2FIX** was most certainly in this category. And I have no doubt that if you read my obituary to Bert (published in the October issue) you will also understand why he was rather special!

Personally speaking I think that there's a reason for everything - and without realising it we're mostly following a preset path (a program if you like!) and it seems ironic that G2FIX became a 'Silent Key' just as it became necessary to introduce a new category into the *PW* and Kenwood Club Spotlight Magazine competition.

The 'Club Spotlight' club magazine competition has been a resounding success. Starting with 11 excellent entries last year we received 26 for the 1997 competition - and these included clubs who serve their members 'nationally'.

Of course, the 'national' type clubs (WAB, BARTG, BATC, etc.) have very high standards indeed for their magazines. So, the panel of judges all agreed that it was best to introduce the new category. And it so happened that the **British Amateur Radio Teledata Group** ('Bartag' to their many friends) scored the highest number of points in the 'national' category.

Bert's Bell

Having the need to introduce a new award for a rather special group of clubs got me thinking. Then I hit on the idea of commemorating G2FIX in a most appropriate way - by a mounted inscribed bell! Bert was a keen bell-ringer, Radio Amateur 'extraordinaire' and a great communicator (he was a delight to listen to when acting as the Controller of the Royal Air Force Amateur Radio Society Net on the 3.5MHz band).

Then I started the search for a suitable bell. And although the kind members of the RAFARS Net assisted, I was still looking when I was contacted by Bert's family.

They wanted to buy the bell and get it mounted and inscribed!

Having suggested the trophy myself I had been fully prepared to 'put my money where my mouth was'. It didn't seem right to suggest the idea and get someone else to pay for it! However, I was delighted that Bert's family wanted to handle that side of things. A most satisfactory conclusion!

I'm hoping that the first award of 'Bert's Bell' will take place at a ceremony in Salisbury very soon in the presence of G2FIX's family and friends. In future years the Salisbury Club have agreed to supply one extra judge for the 'national' category only and wouldn't it be marvellous if Bert's own specialist society - RAFARS were to take part. It would certainly be appropriate!

So, here's to the future of the competition and everyone who has supported it. And I'm hoping that the 'bell will be ringing' to communicate to others and at the same time commemorate G2FIX's dedication to Amateur Radio, bell-ringing and making friends wherever he went, for many years to come. Good luck everyone!

A FAX From The ARRL

As I was preparing to write this issue of 'Keylines' I received a FAX from the American Radio Relay League Headquarters in the USA. And it appears that I have got it **VERY WRONG** regarding the ARRL's plans for the future of the Handbook (*PW* November) 'Keylines'.

In his FAX demanding that I publish a retraction and 'to take what other steps are necessary' to inform readers that the ARRL **have no plans** to stop producing *The ARRL Handbook For Radio Amateurs* in book form. **Mark Wilson K1RO**, the ARRL Publications Manager/*QST* Editor, has made their position very clear indeed. In fact the ARRL tell me that they consider (as I do) that the Handbook is of **prime importance as a book and in effect it's their 'flagship' publication.**

So, although I am very sorry for the confusion caused - I am very pleased indeed that the news is that the all-important ARRL

Handbook is continuing as a book.

And I'm afraid to say that although there are many reasons why the confusion was caused (many of them my own making) I feel sure that if the letters and FAXes I sent to the ARRL **President Rodney Stafford KB6ZV** - registering my mistaken dismay - in July had been answered - the whole catalogue of errors could have been avoided. They could have corrected me there and then! It's frustrating to be so embarrassingly wrong on this occasion but at least there's good news to impart to you all!

Electronics In Action

As from the February 1998 issue of *PW* we are introducing a new bi-monthly series looking at electronics, applications, projects, techniques and ideas. The new series 'Electronics In Action' is to be compiled by **Tex Swann G1TEX** and will compliment the very successful 'Antennas In Action' which he also compiles, which will continue to appear in the 'opposite' alternative months to the new 'Electronics In Action'.

The new series will enable us to introduce more electronic ideas and projects and 'associated interests' for **your interest**. It will also make it far easier for the Editorial team to use some of the ideas which come in from you the reader. So, if you've got anything you'd like to discuss...why not write, E-mail or speak to Tex G1TEX about it very soon. **He's waiting to hear from you!**

Open Forum At Convention

During late September I attended the 'Young Amateur of The Year' (YAOTY) presentation and luncheon as the guest of the RSGB at the HF Convention at Old Windsor in Berkshire. It's a splendid occasion and I came away feeling very proud of the young people (see report in the news pages) and their achievements, and pleased at the hard work by the RSGB, everyone involved and the active support of the Radiocommunications Agency the YAOTY award.

Despite the support given by the RA to the YAOTY I had been rather surprised and concerned at some comments expressed by a spokesman from the RA at an 'Open Forum' held during the mid-morning.

During the 'Open Forum' one of the RA's spokesmen clearly stated that the Agency really wish us to negotiate with a united hobby. In other words - with one voice. And although that was only one topic it was surely message 'Number 1'.

One of the next 'topics' however (and perhaps message No. 2?) came as rather a surprise to me and many of the audience! The RA spokesman (talking about the trends of modern private mobile radio communications) told the whereas the trend is for modern communications systems to be using really low powers, **"Radio Amateurs like to use Kilowatts!"**

Standing at the back of the audience I could see and almost feel the reaction. And of course - my own reaction was immediate! Along with others I pointed out that the vast majority of transmitting Amateurs **cannot use** (and often don't wish to) high power communications because of EMC problems. Indeed - the sizeable QRP contingent in the audience also expressed their surprise at the remark.

After the 'Open Forum' finished I was left wondering. **Are attitudes and staff changing in the RA?** For many years we have dealt with Civil Servants who have been Radio Amateurs themselves and even those who have no direct interest in our hobby have shown a clear understanding of our aims and objectives. It would be a very great shame indeed if new attitudes and lack of understanding from anyone person in this most important Governmental body worked against us.


Indeed, as one 'within the very senior in the ranks' RSGB friend told me: "We're going to have to fight our corner Rob". I agree fully with what he said...and let's hope Radio Amateurs in general will agree to fight together!

*Rob Mannion
G3XFD*

NEWS 1997

Compiled by Donna Vincent G7TZB

Lowe Catalogue



Lowe Electronics, who have been in business for the past 30 years, have recently published their first catalogue. The 78-page, colour A4 sized, *Lowe Electronics Catalogue* contains products for use in the Communications, Amateur Radio, GPS Navigation and Scanning fields.

Also included are accessory items, together with antennas, components, connectors and other selected products from Lowe's varied range. To get your copy of this comprehensive catalogue just send **four first class stamps** direct to **Lowe Electronics Ltd., Chesterfield Road, Matlock, Derbyshire DE4 5LE**.

Fibre Optic Linking

National Transcommunications Limited (NTL) has recently announced its intention to invest £30 million in the building of a new fibre optic link between Belfast and its core network on the mainland to bring them into the international telecoms marketplace. It's intended that this new service will provide an alternative to using British Telecom for carrying 'traffic' between Eire, Northern Ireland and the rest of the UK. This move also marks NTL's desire to be seen as a real alternative to the national PTTs in mainland UK and Ireland.

The NTL network currently stretches from Winchester (south

of England) to Glasgow and Edinburgh in Scotland, reaching out as far as Cardiff, Bristol and Leicester. The network delivers a fast super highway for advanced communications to support the demand for voice, data, video and fast Internet applications throughout the UK.


In order to develop the latest phase of NTL's network, cables will link in a ring Glasgow, Belfast, Dublin and Lytham St. Annes in Lancashire before re-joining the company's existing network in Manchester. Both of the new undersea routes will consist of 48 fibres and the links will provide the first restorable Synchronous Digital Hierarchy (SDH) connections between Northern and Southern Ireland and the mainland. This new service is due to be completed and in operation by May 1998.

New Alinco From Nevada

Portsmouth-based **Nevada Communications** have announced that a new h.f. transceiver has recently joined the Alinco range. Complimenting the Alinco DX-70, the newly-introduced DX-77 covers all the Amateur Bands between 1.8 and 30MHz providing c.w., am., s.s.b. and f.m. It's capable of a maximum output of 100W (high) and approximately 10W (low).

Featuring a general coverage receiver the DX-77 will be available in two versions. The basic model will be priced at **£675** and the DCX-77T at **£775**. The DX-77T includes the EJ-33U Electronic Keyer unit, the EJ-34U CTCSS unit and the EJ-35U narrow c.w. filter. Further details are available direct from **Nevada Communications at 189 London Road, North End, Portsmouth, Hampshire PO2 9AE. Tel: (01705) 662145, FAX: (01705) 690626.**

Editorial note: We hope to review this new model in PW as soon as it's available.



It's 73s From Martin Lynch!

Martin Lynch & Son have recently joined the ever growing number of companies wishing to make their telephone numbers easier to remember. So, with effect from October 1st telephone callers to the Lynch Emporium have been able to dial **0700 73 73 73** for sales enquiries.

Martin says he chose 73 73 73 as his new number because he felt it was an obvious choice for his business and that even newcomers to Amateur Radio would be familiar with the meaning of 73, therefore making it easy to remember for everyone. The old **0181-566 1120** telephone number is still in use and for the time being Martin's Customer Services number will remain as **0181-566 0566**.

So, now you've got no excuse for not remembering to call Martin Lynch!

Need A Postcard QSL? - Catch A Salmon!

Have you ever wished to have something really different on your QSL card? Ever fancied a magnificent steam locomotive, traction engine or aeroplane? If you have ever longed for any of

these - or wanted a high quality colour postcard view of your town, area of the countryside depicted on your QSL card - there's someone who could help you.

Rob Mannion G3XFD has been searching a long time for a



reasonably priced way of having one of his favourite steam locomotives on a colour postcard as a QSL to reflect his interest in railways and radio. That's how he discovered the large range of postcards produced by **J. Salmon Ltd.**

Based in Sevenoaks in Kent, J. Salmon produce an extremely wide range of colour postcards and Rob saw a selection -

Classic Television

Classic Television is a new publication which has just been launched by **Eagle Eye Publications**. The magazine contains feature articles on all aspects of radio and television from media technology through to trivial snippets of information.

The pilot issue (dated September) contains features on *Dad's Army*, *Robin of Sherwood*, *Carry On* films and much more. Future issues will give an 'airing' to many forgotten programmes as well as looking at shows that are destined to become future 'classics'.

Classic Television costs **£1.95** and is gradually being introduced into many independent newsagents so you should be able to find a copy on their shelves. If not, you can order it direct from **Eagle Eye Publications, PO Box 13325, London W5 4GE. Tel/FAX: 0181-568 9881, E-mail Eepublictn@aol.com** enclosing a cheque or postal order for **£2.20**.



including one of his favourite locomotives - in his local shop. He then wrote to the company and found that they are prepared

to overprint existing postcard views to suit Amateur Radio purposes (perhaps the best approach cost-wise) or they can

Emma's The Young Amateur Of The Year!



Emma Constantine 2E1BVJ receiving one of her many prizes from the RSGB 1997 President Ian Kyle G8AYZ/M10AYZ.

(Photo courtesy of RSGB)



(front) The 1997 YAOTY Runner-Up Mark Haynes 2E0APH standing alongside Emma 2E1BVJ, this year's winner. (Rear, left to right) Dennis Goodwin G4SOT of Icom (UK) Ltd., Hilary Clayton-Smith G4JKS, RSGB President Ian Kyle G8AYZ/M10AYZ, Roger Louth (RA), Vaughan Asque (RA). (Photo by G3XFD)

Emma Constantine 2E1BVJ from West Yorkshire has been awarded the title of Young Amateur of The Year (YAOTY) for 1997. Proud and very confident 15-year old Emma, accompanied by her parents, was formally 'crowned' with her title at a presentation luncheon organised by the RSGB at the HF Convention at Old Windsor on Sunday September 28.

Emma, the first lady winner of the YAOTY, is a founder member of the Rishworth School Radio Club G0SQA and has been Secretary since the age of 12. She helps to run Novice courses and has recently started lunchtime Morse code sessions. Her Head of Science Tony Vinters G0WFG describes Emma as "an excellent ambassador" for Amateur Radio. She further proved this statement by creating a precedent by delivering a short and very confident speech to the assembled officials and guests.

Runner-up this year was 14-year old Mark Haynes 2E0APH from Essex who

was also present at the ceremony with his parents. Mark also set up a school radio club and has also taught Morse to two school friends. He's broadcast on BBC Radio Essex about his hobby, is a keen member of the Air Training Corps and is also active on the h.f. bands on QRP - particularly 28MHz. Mark, who received special prizes from the RA, the RSGB, and Icom UK's now traditional 'goody bag' of gifts and Lowe Electronics who presented a Hi-Mound Morse key. Mark also broke with tradition when he addressed the assembly to express his thanks.

Speaking on behalf of the judging panel who comprise of members from the RSGB and the Radiocommunications Agency, Hilary Clayton-Smith G4JKS specifically remarked on the very high quality of the entries for the 1997 award and the significant increase of nominations in 1997.

After congratulations were offered on behalf of the RA, Roger Louth Head of Mobile Service at the Agency and the RSGB 1997 President, Ian Kyle G8AYZ/M10AYZ presented Emma - who hopes to begin training as a Veterinary Surgeon at University soon - with a cheque for £300, and a certificate signed by the President of the Board of Trade and Secretary of State & Industry Margaret Beckett MP. Emma also received prizes of a guided tour of the RA's Baldock Monitoring Station in Hertfordshire, a Palstar KH-6 50MHz hand-held transceiver and a year's free membership of the RSGB, plus a Tandy DX-394 receiver on behalf of the Tandy Organisation. Other prizes included a one week course at the BT Portishead Radio station where she'll learn about international maritime and aeronautical communications and Siskin Electronics donated a Packet Radio Modem.

Everyone on the Practical Wireless team sends congratulations to everyone involved in the Young Amateur of The Year Award and we will follow their continuing careers with interest as our hobby approaches the new century.

Editor


create cards from your own photographs.

Full details of prices, designs (with samples) and minimum order numbers can be obtained direct from J. Salmon Ltd., Art Printers & Publishers, 100 London Road, Sevenoaks, Kent TN13 1BN. Tel: (01732) 452381, FAX: (01732) 450951.

Pure Energy!

A new range of rechargeable alkaline batteries and compatible charger are now available from Waters & Stanton Electronics.

Common NiCad cells need to be periodically discharged to



avoid a low memory charge developing and often don't hold their charge due to their 1.2V rating. However, the new Pure Energy batteries offer a distinct advantage in that they can be charged up to 250 times, require no initial charge, can be 'topped up' at any time, offer a full 1.5V and are said to have a longer shelf life.

The Pure Energy batteries cost £4.99 for a pack of four and the EnviroCharger, which must be used to charge the batteries, costs £17.99 complete with four AA cells. To place your order or to find out more contact Waters & Stanton on (01702) 206835/204965.

Seeing By Wireless

Available now from the PW Book Store is *Seeing By Wireless* Second Edition by Ray Herbert. This book (now published by PW Publishing Ltd.) is 'hot off the press' and has been fully revised by the author.

Seeing by Wireless is the story of John Logie Baird and Baird Television. It's hard to imagine that television is in fact conceptually older than radio even though it was 1926 before J. L. Baird, often referred to as the 'Father of Television', demonstrated the first true television pictures. This and many other interesting facts are detailed within the pages of Ray's book.

The publication traces the Baird story from the early



demonstrations, which became historical events to International Operations through to Stereoscopic Television. *Seeing by Wireless* gives a fascinating insight, complete with quality photographs, into something that has become an accepted part of everyday life - television.

Seeing by Wireless costs just £4.95 plus £1 P&P UK, £2 P&P overseas. To order your copy either use the form on page 82 of this issue or telephone the Credit Card Hotline on (01202) 659930. Order now to avoid disappointment!

Student Radio Awards

By the time you read this the 1997 Radio 1 Student Radio Awards will have taken place at the Brookes University in Oxford. The event, now in its second year, aims to celebrate the success of Student Radio and to highlight the talents of potential professional broadcasters which has dominated the airwaves in university towns across the UK during the last 12 months.

Student radio, which is part of the NUS and the Student Radio Association, has been developing of the past few years, so much so, that Radio 1 has recognised the need to support this area of broadcasting.

The winners from all the award categories will receive training and work experience packages from Radio 1, including an hour of dedicated air time for the winners of the Best Student Radio Station Award. So, if you're studying at university why not get involved with your student radio station or get one started and who knows next year your station could be one of the entries in the Radio 1 Student Radio Awards.

For more information contact Radio One Awards, c/o NUS Press Office, 461 Holloway Road, London N7 6LJ.

The Star Letter will receive a voucher worth £10 to spend on items from our Book or other services offered by *Practical Wireless*. All other letters will receive a £5 voucher.

RECEIVING You

PW's Postbag. If your letter is published you'll win a prize.

Letters Received Via The 'Internet'

Many letters intended for 'Receiving You' now arrive via the 'Internet'. And although there's no problem in general with E-Mail, many correspondents are forgetting to provide their postal address. I have to remind readers that although we will not publish a full postal address (unless we are asked to do so), we require it if the letter is to be considered. So, please don't forget to include your full postal address and call sign along with your E-Mail hieroglyphics! **Editor**

This Month's Star Letter

Loewe Multiple Valves

Dear Sir

I would like to add extra detail to Charles Miller's excellent review of the famous Loewe multiple valve sets in 'Valve & Vintage' (*PW* October, page 50). I have a set in my collection which came from a retired Customs and Excise Inspector in Tottenham some 20 years ago. He told me that it was made there and that he had acquired it during his visits to the factory.

The set dates from about 1928 and has a Bakelite base and is fitted with metallised valve type 3NFB. He told me Loewe made valves as well as sets there, importing the sealed resistors and capacitors from Germany, hence the Customs interest.

About the same time, Marconi tried to get Loewe to pay the Valve Royalty of 12s 6d on each valve assembly in the unit. The case finished up in the Patents Court, with a technical victory for Loewe, who argued that their valves were sufficiently unique to be covered by German Patents, so no Royalty was due.

The Court agreed that this was true, but that there was infringement of Marconi circuit patents, so a reduced Royalty of 7s 6d per complete 3-valve device and 5s for the 2-valve was payable and that Marconi should pay all the costs! Total production of Loewe valves at that time was in the hundreds of thousands per annum - hence the Marconi interest.

Anthony Hopwood
Worcestershire


Editor's comment: What a fascinating story Anthony! Additionally, an Irish reader from Galway, sending me an s.w.l.'s report, also wrote to me saying that several years ago he attended a sale in Galway city itself. Looking through the catalogue he saw that there were several 'Old Fashioned' valves included. He bought them all for £1 and it wasn't until he saw Charles Miller's article did he find out that the strangest looking valve he'd bought at the sale was a Loewe multiple valve. But...perhaps that's "The luck of the Irish" as the saying goes!



One Valve Challenge

Dear Sir

Reference the piece entitled 'One Valve Challenge' in the *Practical Wireless* for October 1997, I thought that I would send the enclosed circuit* (see note below) and photographs in case of interest. You have said that you have no objection to twin-triodes, etc., in the 'one valve' challenge and this has



from 3.5 to 26MHz in three bands. The small coils are 7/8in plastic formers and reaction is by the Colpitts mode. There is a world of difference between a single triode and a twin triode circuit and this model is very good.

C. M. Lindars
Somerset

Editor's comment: We are unable to reproduce the circuit mentioned by C. M. Lindars because of possible copyright problems. However, the photographs provide some indication of this interesting project. Readers will also be interested to know that C. M. Lindars was the Chief Engineer for the very well known HAC 'one valved receiver' (Heard All Continents) Company who advertised for many years in the Amateur Radio press.

First Use Of Practical Wireless?

Dear Sir

I see in the October *PW*, page 11, the reference to the first issue of the magazine on 24th September 1932. It may be of interest to note that this was **not the first** Newnes weekly to include the words 'Practical Wireless' on the cover, albeit as a subtitle, as you will see from the enclosed photocopy of the cover of *Hobbies and Practical Wireless* for August 20th 1932.

(Editor's note: unfortunately we could not use the photocopy in the magazine).

Although F. J. Camm is not credited with the

enabled me to offer mine, which is based on a twin triode.

In the circuit used there are two stages of r.f. amplification followed by a diode detector, then two stages of a.f. amplification. This is a 'double reflex' circuit.

The circuit is based on a design by **Sir Douglas Hall**, published in the January 1968 issue of *Radio Constructor*. The original circuit uses transistors, MAT 101s, but later revised designs used npn transistors which were silicon.

The receiver covers

knowledge) the very first Mobile Home site in the United Kingdom. It is also the only site that is actually recognised as a 'Village' in its own right by Ordnance Survey map makers. It's history is interesting, but too long for this note.

A lot of Park Home sites have a 'no aerials' rule, TV and stereo radio are received from a common site aerial system for which one pays a 'connection fee'. There is one in Exeter that I know. When buying a Home on a site, you have to sign an agreement to abide by the site rules, so it's wise to read carefully any

agreement first to check out the restrictions. I have checked and these agreements are **enforceable in law**.

Many sites have overhead power lines for domestic electricity, random wire and vertical aerials are definitely out as I know from experience! I operate on all h.f. bands with a full size G5RV (ends dropped slightly) I also operate on 144 and 430MHz, all quite successfully. Poles and towers are a 'no go' on almost every site. I hope that these points will be of interest to prospective buyers.

Ron Wilson G3DSV
Devon

Mobile Home 'Ham'

Dear Sir

As one who has lived in a 'Mobile Home for the last 17 years, I was very interested to read the article 'Mobile Home Ham' by **Dennis Hartwell G0VOV**, page 42 in the October *PW*. However, I would like to make a couple of points on the subject.

Nowadays, they are more properly called 'Park Homes' as none of them are mobile in the sense that was meant originally. The Pathfinder Village site here (near Exeter), was (to the best of anyone's

Editorship of this magazine, the 16 page Wireless Supplement has two articles under his name and the whole magazine bears the typical hallmarks of the great man!

The next copy which I have, dated December 17th 1932 and subsequent issues are entitled *Hobbies and Wireless Supplement*, but still contain Wireless articles by Camm, Barton Chapple, etc., an indication of the prolific output of these writers and the wide interest in wireless in this period.

I myself, at this time, was still hooked on *The Magnet* and *The Gem* and didn't start reading *PW* until about 1940. So it may not surprise you to know that these days the first articles I read each month is 'Valve & Vintage'!

Best wishes for the continued and successful publication of *PW*.
John Goldberg G3ETH
Chester

Editor's comment:
Absolutely fascinating John! As a 'semi vintage' reader of Eagle myself I'm a generation behind Gem & Magnet readers so it's very interesting to read of your memories of the earlier era. So, please readers...as we approach the centenary of 'Amateur Radio' year in 1998...keep those memories flowing.

The Oldest Reader?

Dear Sir

When my friends read the Editor's 'Keylines' editorial in the September issue, they commented that **I must surely be the oldest reader** - however I think I'm certainly not! There must be somebody else 'way out yonder' who has reached their 'personal century' mark!

My friends (there's still a few left) also pull my leg about my never ever throwing anything away so I may well be the only reader who has not only taken *PW* magazine since issue number one, but who still has them on

his library shelves!

As a young schoolboy before the Second World War, I was a keen home constructor and s.w.l. saving my sixpence (old money) per week pocket money to buy tools from Woolworths (the hand drill came in three parts - 6d each), but the pliers were only a tanner, and, of course, I still have both on my workbench! Also, the electric soldering iron, a green 'Solon' type with wider bit, which I seem to remember cost all of 7/6d.

The first test meter was home constructed around a moving iron meter, price 6/6d from Lisle Street, where else? Later the sixpences were saved up to buy an AVO meter...the height of luxury. Yes, I still have both meters as well as the iron, but sadly its element is burnt out.

Unfortunately, I am short of three copies of *PW*, having lent them to a college and they were never returned. They are those for November and December 1950 and July 1980. Can any kind reader help please?
Douglas Byrne G3KPO
Isle of Wight

Republish Transmitter Design

Dear Sir

I'm writing in response to the mention you made ('Editor's comment' following the letter entitled 'A Hobby For Life' in 'Receiving You' October *PW*), about the 4-valve transmitter originally designed and built by **Steve Appleyard G3PND**. I for one would like to see it reprinted!

In the early 1950s I built something similar from *PW*. Since then I have since bought some *PWs* from that period in the hope of finding the circuit and information again.

The one I made was a 3 valve transmitter. It was crystal controlled, working on 3.5MHz and with valve number 2 being a buffer, it went on 14MHz very well, (about 20W out to a G5RV).

Enjoying The Hobby

Dear Sir

I am very new to the field of Amateur Radio, having decided that I would like to have another bash at it listening to Radio Amateurs, and eventually, perhaps, even have a go at transmitting myself.

As a youngster I built a simple radio, on tag-board as I recall. It was not very effective, but it gave me a tremendous feeling of achievement and many hours of pleasure.

Now, I worry. I see reviews in your magazine for expensive radio equipment, which has been professionally designed, uses high quality components, thoroughly tested and extremely well marketed. You then proceed on review of the equipment to tell us all that it actually does the job it was designed for. Well, so it should!

There is no excuse for expensive modern day equipment not to fulfil its design specification. With the modern CAD packages for electronic systems and manufacturing methods with good quality control, there is every reason to expect the equipment to perform reliably.

Gripe almost over! **I have no objections** to anyone spending whatever amount of money **they want** on their hobby. The 'name of the game' after all is enjoyment. But please, let us all get away from pseudo-mystic. Expensive 'Kit' is not necessary for the continued enjoyment of one's hobby.

The articles by the **Rev. George Dobbs G3RJV** are superb in this respect. I realise that

many people may not have the time of the inclination to build 'Kit' for themselves. But for the people who do, these articles are entertaining, informative and at times, a challenge.

My skills as an amateur electronics constructor may well leave a lot to be desired. There are vast gaps in my knowledge of radio theory and amateur radio. But still I press on, recycling as many parts as possible, buying second-hand helps to keep the cost down for me, as does buying components in bulk as and when I can afford them. Hunting for 'bits' is part of the fun.

The argument that specialist parts are needed to enjoy Amateur Radio albeit on a simple level is a myth. I accept that there will be limits on performance of 'home-brewed' equipment, which professionally designed and built equipment will not have, but so what? I can live with that and I suspect so can many other people.

Well, perhaps having somewhat out of the mainstream views, my message really is simple. There is only one thing important in this hobby - apart from necessary good conduct and operational rules - and that is enjoy yourself. Thanks for a really good magazine.

Steve Capriati
Lancashire

Editor's comment: Good luck in the hobby Steve and I've no doubt we'll meet at one of the specialist 'QRP' rallies and eventually on the air - perhaps using 'one valved' receivers with home-brewed transmitters?

The transmitter worked well on a.m. via cathode modulation, using a carbon microphone that needed a good shake every now and then as the granules used to pack together! My receiver was the HRO Senior.

I hope you have enough requests for a reprint. Best wishes and YECHID DA from West Wales!

Sam Rees GW0NLB
Dyfed

Editor's reply: I have asked **Phil Cadman G4JCP** to take another look at this circuit in his 'Valve & Vintage' column during 1998. **Phil's own 'speciality' interest is older projects from PW and readers interested in this aspect are asked to write directly to him.**

New Style PW Cover

Dear Sir

It's me again...your keenest reader and I'm writing to say I like the new style magazine cover very much. And I've had

a thought (please! no jokes about rare events!): What about throwing out a challenge to the readers to come up with a circuit idea/modification that makes use of the 'unused' pin on the microphone socket on a lot of the older generation 144MHz transceivers?

Most of the older sets, e.g. FT-227R, IC-240, etc. are fitted with 4-pin microphone sockets, but only use three of them for connecting the microphone, two for the microphone audio and the third for p.t.t. control, this leaves one lonely neglected little pin, with nothing to do...sad!

As I mentioned before, I use this pin, together with an outboard CTCSS circuit connected in the microphone lead to add this function to an old IC-240 - the audio from the circuit entering through third pin and being fed in beyond the audio tailoring stages of the microphone audio, which would otherwise filter the sub-carrier tone out.

I'm sure that there must be quite a few out

there who have come up with far more ingenious uses for this otherwise 'spare' pin and whilst many may think twice before getting the knives and forks into a new 'all singing and dancing' rig, costing megabucks and requiring a microscope to see what you are doing! These older sets are less intimidating when it comes to taking the lid off. Anyway, like I said, it was just a thought.

Gareth Jones GW4KJW
Gwent

Editor's comment:
Good idea Gareth! Please send any ideas and circuits to Tex Swann G1TEX here in the Broadstone offices for use in a new series. For further information on this matter please see 'Keylines' in this issue.

Send your letters to the PW Offices, marking it clearly for 'Receiving You'



Zoë says:
"keep the News and
those Club magazines
coming!"

CLUB Spotlight

Compiled by Zoë Crabb

Special Event Station

Recently the **Droitwich Spa Amateur Radio Club** operated a Special Event Station with the callsign **GB2SER** at the Hanbury Steam Rally in North Worcestershire. Hanbury is just south of Bromsgrove, in sight of the BBC Droitwich transmitting masts, and is supposed to be the village which the BBC called 'Ambridge' in The Archers radio series. The rally was in aid of Hanbury Parish Church, which needs some restoration.

The Rally attracted hundreds of visitors from all over the country with its display of coal and oil fired Traction engines, as well as stationary engines. There were also displays of ex army scout cars, trucks and jeeps as well as a display of classic cars including an immaculate Model T Ford.

In other arenas were displays of country crafts and the usual stalls and beer tents! It was a really hot, fine day and a marvellous occasion.


The Droitwich Spa ARC operated

over the Saturday and Sunday, on h.f. with an Icom rig running 100W into a G5RV suspended from two ex-Army 25ft masts. The club also operated on v.h.f. with a Yaesu FT-290R MkI with a 100W linear into a 6-element quad loop antenna, as well as on 70cm (430MHz).


A number of club members helped out with operating the rigs and setting-up the station, the stalwart however, being the club Chairman **Eddie Cotton G4PQZ** who operated for hours on end! Other



A general view of some of the engines.



Richard Bourne (and family) in front of the club tent.



Chris Margetts G7VJM operating one of the rigs.

operators in the Sunday were **Chris Margetts G7VJM** and **Derek Thorpe G4RCB**.

Also, the club would like to make a special mention of club member **Richard Bourne**, who although not licensed yet, provided a lot of the man power in setting-up the station and a good deal of equipment. Richard hopes to pass the RAE in the near future and is already studying for the

Morse exam.

Rewarding Year For Bangor

The **Bangor & District Amateur Radio Society** (G13XRQ) have had their most rewarding year ever - on at least four accounts. Firstly, they have just celebrated their 30th anniversary with a major rally that attracted traders from England and Scotland and right across GI.

Secondly, the Society has just moved into a new home, the 'State Room' at the Clandeboy Lodge Hotel, on the outskirts of the town. Thirdly, it's been their most financially successful year in their history, and last but not least, with 64 fully paid-up members, it's the largest radio club in Northern Ireland (and perhaps EI as well!).

At the Society's AGM, the Chairman **Stewart Mackay G14OCK**, Secretary **Harry Squance G14JTF** and Treasurer **Terry Barnes G13USS** were all re-elected. **Keith Burnside G14IYO**, a well-known Ulster Television Presenter, was elected as Vice-Chairman and Editor of the Society's magazine *Contact*.

Other officers were **Roy Finlay G10WVN**, PRO, and **Tony Harvey G17VIW** as Equipment Officer. The committee is as follows: **Norman Newell G13YMY**, **Merrill McNinch G16JGB**, **Bertie Drain G14POC**, **Myles Boyle G10VTS**, **Keith Stevenson G10SSA** and **Jeff Smith M10AEX**.

The Society meet on the first Wednesday of each month and a full programme of speakers and events has been organised for the coming months. Anyone wanting further information should contact **Stewart G14OCK**, QTHR or telephone on (01247) 454049.

New Meeting Dates

The **Ynys Mon Radio Users Group** will, as from October, hold their meetings every 2nd and 4th Wednesdays of the month at the Scout Hall, Llangefni, opposite the Kwik Save shop, at 7.30pm. More events are scheduled to run throughout the year with the club's callsign **MW0AER**. Further information from **Tony Anziani GW4ZWN**, Secretary, on (01407) 832197 anytime.

Junk Sale

The **Lincoln & District Amateur Radio Society** (LADARS) will be holding a Junk Sale on Thursday 27 November at 8pm in the Concert Room at the Lincoln Post Office Club (the LADARS usual meeting place), this is located on Dunkirk Road, off Burton Road, in the uphill parts of Lincoln. The price of tables for selling 'junk' costs £1 each and admission is 50p for people not wanting a table.

Last year, it was the Society's first attempt at running such an event, and overall they were pleased with the evening's attendance and it went very well. The Society hope that this year the success will continue!

As well as the usual radio and electronics 'junk', CYMA Computer Systems will also be present. This is a new, local company which can supply PC spares for upgrades, etc. They also sell new and second user systems at reasonable prices. There will also be a raffle and tickets will be on sale throughout the evening.

Anyone interested in radio or computing will be most welcome to attend the night, also any new members who wish may join LADARS. Further information from **Paul Ward G4RVM**, Secretary, on (01522) 537751.


Duxford Radio Society

Rob Mannion G3XFD recently had an interesting QSO with Max Westley G4WEZ, of The Duxford Radio Society, who has kindly sent in some information about the Society and its history.

The Society originated when members of the Special Forces Signals Section and friends operated a Special Event Station at Duxford Airfield. This was to celebrate the 40th Anniversary of D-Day and VE Day back in 1984/85 respectively, and at the same time putting on exhibitions of war-time radio sets.

Formed as the Duxford Airfield Radio Society in 1986, the name was reduced to Duxford Radio Society in July 1989. From 1986, when GB2IWM was issued as the permanent callsign, co-operation with the Imperial War Museum (IWM) Department of Exhibits and Firearms produced displays appropriate to the special events for which Duxford is well known.

The Society aims to serve the Museum and the interests of its members by active work in documentation, collation, restoration, putting on exhibitions of IWM and members' artefacts, publishing a Newsletter of activities, articles on specific equipment or techniques, as well as increasing the usage of GB2IWM (by a larger roster of operators).



So far, GB2IWM has operated from the Operations Block, behind Hangar 5, used for fighter aircraft control in the Second World War and then during 1990-91 the school room, with more space for exhibits and for the public to move around. The Society now have their own two buildings (permanent) by the Gibraltar Gun, one which has the inner Radio Station room and an outer room which houses the radio equipment display, hopefully, this will eventually be open to the public.

The other building is the restoration workshop and also houses an active display of working restored radios. These rooms are currently only open when members are in attendance.

During the big display days, when Flying aircraft and Military vehicles draw large numbers of spectators, GB2IWM uses mainly s.s.b. with modern rigs, but on other days old c.w. only 'rock-bound' sets have been used.

While the first priorities are the IWM's collection of mainly army and RAF gear, including American items used by British and Allied Forces, items from other countries are desirable for comparison. There is Naval equipment but it does tend to be rather large and mainly kept on HMS Belfast!

The Society is now on a recruiting drive, seeking kindred spirits, not only Amateur radio operators but men and women who can contribute to the project, either from their own past experience or by cataloguing, research and literature or technical manuals, by translation from the several languages used by the allied forces, even from Japanese, since the IWM has some captured radios.

To fit in with the museum's policy, with respect to having only one outside organisation to deal with and insurance requirements, the regularly attending members of the DRS have joined the


Duxford Aviation Society (DAS) forming its Radio Section. In fact, it can be said that the DRS has itself become part of the DAS and abides by the rules of the parent body.

However, it is only necessary for DRS members to join DAS if they are going to attend regularly as access is then easier and free, but 12 working visits are required per year.

The Radio Section of the Duxford Aviation Society have three main aims. 1) To support an interest in the History of Radio in Military employment, including radio in all Armed Forces, Para-Military and Clandestine (Resistance) Groups and extending to radio equipment of other countries for comparison.

2) To support an interest in and assist in the provision of an exhibition of radio equipment in accommodation provided by the Imperial War Museum, Duxford. To restore radio equipment in preparation for use or display and 3) The operation of an amateur radio station with the callsign GB2IWM (or other callsigns that may be provided during special events), using both modern and historic equipment in accordance with the provisions of the amateur licence.

Further information about the Society can be obtained by writing to: **Duxford Radio Society, c/o Imperial War Museum, Duxford Airfield, Cambridge CB2 4QR.**



Spotlight Trophy North Of The Border!

The 1997 winner of the *Practical Wireless* & Kenwood 'Club Spotlight' Club Magazine Trophy is **The Cockenzie & Port Seton Club**, based in the Lothians near Edinburgh in Scotland. However, due to the much increased entries - we had 26 clubs entering this year compared to the 11 in 1996 - the judging was delayed as the panel of adjudicators worked 'overtime' and as they are scattered all over the country - it took some organising!

And although the full results and photographs of the presentations will not appear until the next issue of *PW* - the 'Club Spotlight' trophy, sponsored by Kenwood UK, will be presented to the Cockenzie & Port Seton Club at a ceremony at the Leicester Show at Granby Halls on Friday 17th October.

New Category

The much greater interest shown by Amateur Radio Clubs all over Britain and abroad has meant that a new category - to be formally introduced in 1998 - will be introduced to cater for the 'national' type clubs who entered their very professionally produced magazines and newsletters.

All the judges on the panel, **Dave Wilkins G5HY** of Kenwood, **David Barlow G3PLE**, **Jim Bacon G3YLA**, **Rob Mannion G3XFD** and myself, thought it only fair to introduce the new category and an appropriate award. And as fate would have it, we were given the opportunity to honour the memory of the late **Bert Newman G2FIX** who died in July.

The new award will be presented to the winners in the new category, **The British Amateur Radio Teledata Group (BARTG)**. For further information on BARTG's success and the new trophy - please see 'Keylines' in this issue.

Lighthouse Activity

The **Sutherland & District Amateur Radio Club** took part in the lighthouse weekend back on the 23/24 August 1997 from Tarbat Ness Lighthouse IO87CU, which is located on a Northern peninsula of land where the Dornoch and Moray firths meet.

Tarbat Ness is the second highest lighthouse in Scotland at 146ft 7/4in. It was built in 1837 at a cost of £7300 and was designed by Christopher Stephenson, the cousin of Robert Louis Stephenson, who was the well



(L to R) John Miller GM4JAE, Len 'POPS' Boothroyd (s.w.l.), Derek Gill GMOHLV, Charlie Baird GM7ASN, Frank Baird MM1AUD, Ian Cowan GMOHJ, Kevin Boothroyd GM1FYS.

known builder and inventor of 'The Stephenson's Rocket', the world's first locomotive.

It's a fitting tribute to Stephenson that the Light is now powered by Locomotive Headlamps, 20 of them, all producing four flashes per minute, some 180,000 candle power (that's a lot of candles!) and it's visible for over 20 miles. The Lighthouse has just been repainted from top to bottom, at a cost of over 12 times what it cost to build in 1837!

Everybody enjoyed the weekend and over 550 contacts were made from as far as Indonesia, USA, Canada, South Africa, Honolulu, Israel and most of Europe.

The antenna was a G5RV, sloped from the top of the lighthouse to just over three metres above ground. It worked extremely well, the rig, a Yaesu FT-767GX, running just 10W!

The tent was provided by The Tain Scout Group, who paid the club a visit on the Saturday evening, so thanks go to them and Tom Lane, the Lighthouse Keeper, for the help they gave the club to make it such a wonderful week. Here's to the next lighthouse event!



(L to R) Peter Anderson (Tain Scout Patrol Leader) and seven of the Tain Scouts: Kevin Boothroyd GM1FYS is on the microphone, logging is Charlie Baird GM7ASN and giving a talk on amateur radio is Derek Gill GMOHLV.



Varactor Diode?

Ian Poole G3YWX sets out to answer the question What is A ...
Varactor Diode.

A part from being used purely for rectification, semiconductor diodes have a number of other properties which can be put to good use in a variety of applications. One such property is that they exhibit a change in capacitance when a reverse bias is varied. As a result of this phenomenon diodes designed and used for this application are called varactor (variable reactance) or varicap (variable capacitance) diodes.

The capacitance change can be used in a variety of ways. One of the most obvious is for applying frequency modulation to a signal from a varying audio voltage in an oscillator or in a phase reactance modulator.

Frequency synthesisers make widespread use of varactors. They need to use the control voltage in the phase locked loop (p.l.l.) to control the frequency of the oscillator.

Varactor diodes are also used in voltage controlled filters. Often these filters are controlled by microprocessors where the tuning data is sent to a digital to analogue converter, where the data is converted into an analogue voltage to control the varactor diodes used in the filter.

How They Work

Previously we have already seen that the key area for semiconductor diodes occurs in the junction between the *N* type and *P* type semiconductors. The same is true for varactor diodes. Here the area called the depletion layer does not allow current to flow and acts as if it's a plate capacitor as shown in Fig. 1.

When a reverse bias is applied the depletion layer widens effectively

increasing the gap between the plates and the capacitance becomes less as shown in Fig. 2. In this way, a varactor becomes a voltage controlled capacitor.

Varactor diodes are always run with a reverse bias. A forward bias is avoided because the diode starts to conduct and this has the effect of reducing the '*Q*' of the tuned circuit.

The actual capacitance range which is obtained depends upon a number of factors. One is the area of the junction.

Another factor is the width of the depletion region for a given voltage. This is governed by the doping concentration and it is normally adjusted to give a relatively abrupt junction which results in a greater capacitance change.

Diodes typically operate with reverse bias ranging from around a couple of volts up to 20V and higher. Some may even operate up to as much as 60V, although at the top end of the range comparatively little change in capacitance is seen.

Tuning Range

Obviously the most important characteristic of a diode are its tuning range. Normally two voltage points are specified, one at the top of the range and the other near the bottom at the minimum useable voltage.

It's obviously important to select a diode which combines the correct capacitance range for the available tuning voltage range. The higher voltage specified is normally the maximum reverse bias and this should not be exceeded otherwise breakdown may occur.

An important characteristic of any varactor diode is its *Q*. This is particularly important in a number of applications.

For oscillators used in frequency

synthesisers it affects the noise performance. High *Q* diodes enable a higher *Q* tuned circuit to be achieved, and in turn this reduces the phase noise produced by the circuit.

For filters the *Q* is again very important. A high *Q* diode will enable the filter to give a sharper response, whereas a low *Q* diode will increase the losses. The *Q* of a diode is simply the ratio of the capacitive reactance and the bulk resistance, ie $Q = X_c/R_s$ at a specified frequency.

Reference may also be made to abrupt and hyper-abrupt diodes. These diodes have a very sharp junction and small changes in voltage give relatively large percentage changes in capacitance. These diodes are particularly useful when oscillators or filters need to be 'swept' over large frequency ranges.

Back-To-Back

Varactor diodes can be used in a variety of ways. However, one of the most common is in a back-to-back arrangement like that shown in Fig. 3.

The use of the diodes in the configuration shown in Fig. 3 prevents the alternating r.f. voltage in the circuit from driving the diodes into forward conduction. However, it does mean that the total capacitance of the diode combination is only half that of each diode, assuming they have the same capacitance.

The control voltage is applied through a resistor in the control voltage line and a capacitor to ground to act as a filter. High value resistors, around 10kΩ are generally used as the feed impedance to the diodes is high.

PW

Fig. 1: A Varactor diode.




Fig. 2: Relationship between voltage and capacitance for a Varactor diode.





Fig. 3: A tuned circuit using varactor diodes.



Next Time
I'll be taking a look at the Pin diode




PW Publishing

presents . . .

FERRELL'S CONFIDENTIAL FREQUENCY LIST

10th Edition



only
£19.95
Free P&P!

PW PUBLISHING LTD., FREEPOST, ARROWSMITH COURT,
STATION APPROACH, BROADSTONE, DORSET BH18 8PW.
TEL: (01202) 659930 FAX: (01202) 659950

RADIO Diary

Compiled by Zoë Crabb

1997

November 15: The London Amateur Radio & Computer Christmas Rally is to be held at the Lee Valley Leisure Centre, Picketts Lock Lane, Edmonton, London. Doors open at 10am to 5pm each day. Admission is £2.50 for adults, £1.50 for pensioners and £1.50 for under 14s. With around 100 exhibitors, special interest groups a huge Bring & Buy stand, disabled facilities, bars and restaurants, it's the event with something to interest every radio and computer enthusiast. **RadioSport Ltd., 126 Mount Pleasant Lane, Bricket Wood, Herts AL2 3XD** or telephone on **(01923) 893929**.

November 23: The Bishop Auckland Radio Amateurs Club (BARAC) Rally will take place at Spennymoor Leisure Centre, County Durham, a new venue. There will be the usual stalls, Bring & Buy, catering and bar facilities. The venue also boasts good parking with easy access to a large ground floor hall for disabled visitors and traders. There is lots to do for the family within the confines of the Leisure Centre for those of the family not quite so interested in radio. Doors open at 1100 (1030 for disabled visitors). Admission is £1 (under 14s free of charge with adult). Talk-in on S22. **Mike G0PRQ** on **(01388) 766264**.

November 30: The Portland Amateur Radio Club are holding their 3rd Annual Rally at the Burton Cliff Hotel, Burton Bradstock, Near Bridport, Dorset. Doors open at 11am. Attractions include well known amateur radio traders and dealers, crafts and hobby stalls, computer suppliers, local radio clubs, RAYNET display, raffle, Bring & Buy and an excellent choice of food with a bar open all day. Talk-in on S22 and SU22. Further

information from: **The Rally Organisation, 29 Court Barton, Weston, Portland, Dorset DT5 2HJ** or telephone on **(01305) 823373**.

December 7: The SDX Cluster Support Group & Scottish DX Convention are holding their 3rd SDX Glasgow Rally at the Maryhill Community Halls, Maryhill Road, Glasgow. There will be a variety of special interest groups with stands and displays and Morse test sessions will be available throughout the day. Once again, the famous Jackie & Sandra Cafe will be open for business throughout the day, serving hot and cold snacks, tea, coffee and soft drinks. Doors open at 10.30 for Bring & Buy registration and the cafe is also open from this time. Adults - £3, Senior Citizens - £2 and children under 14 - free of charge with an adult. **John Dundas G4MOOPS** on **0141-638 7670** or Packet @ **GB7SAN/GB7SDX** or E-mail: **j.m.dundas@btinternet.com**

December 7: The 40th Northern Mobile Rally (Harrogate) is to be held at the Flower Hall, Great Yorkshire Showground, Harrogate, North Yorkshire. **Gerald Brady G0UFI**, Rally Manager on **(01765) 640229**.

December 14: The Leeds & District Xmas Radio & Computer Rally is to be held at the Pudsey Civic Centre (Dawsons Corner). All the usual traders will be there, there will also be a talk-in, a licensed bar and disabled facilities, etc. Further information from **John Mortimer** on **(01943) 874650** (Bookings Manager), **Gordon Ryder** on **0113-255 0626** (Rally Manager) or from **Malcolm Robertson** on **0113-225 3379** (Club Secretary).

***December 14:** The Verulam Amateur Radio Club will hold its annual

If you wish to have your Rally featured in Radio Diary, all you have to do is to put together as much information about the Rally as possible, ie. date, location, time, who to contact, etc., and send it to Zoë Crabb at the PW Editorial Office.

rally at the Watford Leisure Centre, Horseshoe Lane, Garston, Watford, Hertfordshire, from 1000 to 1600. The Leisure Centre is located off the A405 near junction 6 of the M1 and junction 21A of the M25. Attractions will include trade stands, Bring & Buy, grand raffle, cafe, licensed bar and free car parking. Morse tests will be available. For further details call **(01923) 262180** or for trade information call **(01923) 265572**.

1998


January 18: The Oldham ARC Mobile Rally is to be held at the Queen Elizabeth Hall, Civic Centre, West Street, Oldham, Lancashire. Doors open at 1100 (1030 for disabled visitors). The event features all the usual traders plus a Bring & Buy stall. Morse tests are available on demand and there is a talk-in on S22 via GB4ORC, commencing at 0730. Mobile Contact prize up to 1400. There will be refreshments and free parking available. **(01706) 846143** or **0161-652 4164**.

February 1: The 13th South Essex Amateur Radio Society Radio Rally will take place at the Paddocks, Long Road, Canvey Island, Essex. This is one of the biggest and best rallies in Essex, (the Paddocks is situated at the end of the A130). Doors open at 1030. Features include amateur radio, computer and electronic component exhibitors, a Bring & Buy, RSGB Morse testing on demand (two passport photos required), home-made refreshments, free car parking with space outside main doors for any disabled visitors. Admission is £1. **David G4UVJ** on **(01268) 697978**.


**Practical Wireless & SWM in attendance*

If you're travelling a long distance to a rally, it could be worth phoning the contact number to check all is well, before setting off.

The Editorial staff of PW cannot be held responsible for information on Rallies, as this is supplied by the organisers and is published in good faith as a service to readers. If you have any queries about a particular event, please contact the organisers direct. Editor



Lowe Electronics Ltd



JRC JST245

All-mode 150W HF plus Six metre transceiver including built-in mains PSU and Auto Tuner



HF Band Plus 50MHz Band. The JST-245 covers the 1.9MHz band plus the 50MHz band, and operates in all the modes including SSB, CW, AM (A3H), AFSK and FM

Some of the outstanding features


- Large Colour LCD Display
- Built-in power supply
- Multiple Antenna Selection
- Stable Frequency Control
- Band Memory
- 200 Channel Memory

Other Standard functions are provided including VFO with equaliser, full break-in, electronics keyer, all-mode squelch, VOX and RF speech compressor.

Lowe Price £2,295.00

OUT NOW...OUT NOW...

Lowe Electronics Catalogue



FREE!
FREE!
FREE!
FREE!

80 pages of exciting products covering- Communications, Amateur Radio, GPS Navigation, Short Wave Listening, Airband & Scanning, Security, Weather Monitoring

Don't miss out - just send four first class stamps to receive your own catalogue!

GPSIII from Garmin



A Global Positioning System receiver with electronic map. It not only shows you the lay of the land, but where you stand, too.

Millions of miles of motorways, roads, railways, rivers and shorelines are programmed into the GPSIII. Yet this versatile personal navigator weighs only 255g and fits comfortably into your hand, on your bicycle or on the dashboard of your car.

Where you are

The GPSIII's 12 parallel channel receiver will find your position fast and keep your position even in dense foliage. Position averaging reduces the effects of Selective Availability (SA) for the best accuracy possible.

Where you've been

The GPSIII tracks your route and stores favourite spots with names, icons and a brief description. With one keystroke, trip odometer and speed calculations are in clear view. It will even display sunrise and sunset times so you're not left in the dark.

Where you're going

Most remarkable about the GPSIII is its basemap. It shows primary landmarks for Europe, Africa, Asia, Australia and Oceania. After telling you how far you are from a given point, it will work out the time of arrival.

Lowe price £429.00

Lowe Electronics Ltd

Chesterfield Road, Matlock
Derbyshire, DE4 5LE

Telephone (General Enquiries) 01629 580800,
Fax 01629 580020

Orders FREEPHONE 0800 174749

Email: info@lowe.co.uk

URL: <http://www.lowe.co.uk>

Branches

Bristol & Wales

79 Gloucester Road, Patchway, Bristol BS12 5QJ
Tel 0117 931 5263 Fax 0117 931 5270

North East, Unit

18B, Airport Industrial Estate, Newcastle, NE3 2EF
Tel 0191 214 5424, Fax 0191 214 0761

Showroom opening hours are 9.30am to 5pm Mon-Fri and 10am to 4pm on Sat, but check with our local branches as times may vary

Practical Wireless 1997 144MHz QRP Contest Results

Despite the fact that Neill Taylor G4HLX has been working in America for most of 1997 once again he's found time to organise PW's 'fun' contest and now it's time to see just how well your entry did this year!

For the 15th *Practical Wireless* 144MHz QRP Contest, held on the 15th of June 1997, we seem to have had a mixture of familiar and unusual happenings! The one complete break with tradition was the weather, which left many portable groups cold and wet.

Amongst the top positions in the results table, however, I see that the stalwarts have managed to pull off a good performance. And this was despite the combination of appalling weather and poor propagation.

Wafflers Win

The accompanying tables tell the full story of how the entrants fared this year. The overall winners are the 'North Wales Wafflers' GW0NWR/P, a group comprising of Dave Bevan GW4DMR, Ted Shipton GW0DSJ, Rick Price GW0VMW, Albert Hall GW0RCZ, Barrie Mee GW7EXH and Tony Cartwright 2W1FPK.

After being runners up last year, and in 1994, the 'North Wales Wafflers' have finally achieved a very convincing win, to gain the coveted PW QRP Contest Winners' Cup. They also win the special prize of an Alinco DJ-190 hand-held transceiver, kindly donated by Mike Devereux G3SED of Nevada Communications.

In second place are the Oldham Radio Club G1ORC/P, equalling their highest position achieved in 1993. Their special prize is a Solar

Panel kindly donated by Bob Keyes GW4IED of Key Solar Products.

The Oldham Radio Club have been taking part in the PW contest almost every year since its inception. And whereas other groups have come and gone, they have been consistent in their good performance.

An analysis of the relative scores of all groups in all 15 annual contests since 1983 shows G1ORC/P in second position overall (the outright leaders are still the 'Bug Bashers' group who dominated the results table in the early years of the contest).

Leading Scottish Station

The leading Scottish station this year was once again the Cockenzie and Port Seton Amateur Radio Club GM0CLN/P,

although this time by a narrower margin over their nearest rivals.


They have again been awarded the **Tennamast Trophy in Memoriam to Frank Hall GM8BZX**, kindly donated and supported by Norrie Brown GM4VHZ of Tennamast.

New Trophy

A new trophy this year, kindly donated by your generous editor, **Rob Mannion G3XFD**, is the **PW EI/GI Trophy Clock**. This will be awarded to **Peter Lowrie G17JYK/P**, who not only beat the friendly competition from Eire, but was also placed 8th overall, and fourth placed single operator.

This year's leading single operator was **PW** contest veteran **Dave Hewitt GW8ZRE/P**, for the second successive year.

As usual PW Contest certificates will be awarded to the leading



It's good to see Novice Licence holders operating in the contest. Here Graham 2E1BUG is operating G6MXL/P as part of the Poole team's efforts.

Practical Wireless 144MHz QRP Contest 1997

Pos.	Callsign	Points	Pos.	Callsign	Points
1	GW0NWR/P	12120	41	G6MXL/P	795
2	G1ORC/P	6136	42	GW4SZV	782
3	GW8ZRE/P	5886	43	GM4YEQ/P	736
4	G4SRS/P	4645	44	G0CKD	636
5	G1POS/P	2793	45	M0BAQ/P	600
6	GW7LQD/P	2717	46	G0TYM/P	572
7	G3RIK/P	2688	47	G4DFV/P	546
8	G17JYK/P	2576	48	G0RXC	528
9	GM0CLN/P	2575	49	M0AYB/P	495
10	G3BP/K	2310	50	G2HR/P	468
11	G8AWO/P	2242	51	G7NRO/P	462
12	G0WNL/P	2190	52	GM1YGV/P	450
13	G8DDY/P	2142	53	G7HAH	420
14	GM4HEL/P	2090	54	G8WVR	410
15	G0PJY/P	2052	55	G3MAE/P	407
16	E16ARB/P	1995	56	G0ADH	396
17	GW4IDE/P	1843	57	G1JGE/P	385
18	G0TOU/P	1792	58	G3NPB	376
19	G0OVJ/P	1776	59	G0RRC	351
20	G0XBM/P	1760	60	G0LDJ/P	310
21	G7OCI/P	1710	61	G6EDB	288
22	GM4ZUK/P	1672	62	G7TUA	225
23	G4HRS/P	1647	63	G7KNQ	204
24	G0VHF/P	1587	64	GM3RTJ/P	180
25	G0BPS	1500	64	M1BGR/P	180
26	G0CRW/P	1395	66	G0HVU/P	168
27	M0APO/P	1330	67	G0PZR/P	152
28	E12SDR/P	1281	68	E12B/P	144
29	G0LPX/P	1119	69	PE1EWR	140
30	G0SRC/P	1110	70	G7XYZ	114
31	G6WIR/P	1035	71	G4NHT	90
32	G0DLR	980	72	G0DEH/P	88
33	G1WOR/P	936	73	G0LGX	84
34	G5ZG/P	915	74	M1AWQ	76
35	G5MS/P	882	75	E1G0TJS/P	66
36	G3LRS/P	876	76	G7HIO	21
37	GW0TPH/P	871	76	F1TVV/P	21
38	GM7SX/P	848	78	M1FSTUN	5
39	GW3LNR/P	840	79	G8EXT/P	1
40	G1WKS/P	825			

Table 1

stations in the various categories, and also to the leading station in each locator square (see table), to keep alive the local competition that many operators seem to enjoy.

Adjudicator Absent

Adjudication of the contest has been somewhat hampered this year by your adjudicator being

Leading multi-operator stations

Pos	Name	Call	Score	QSO	Squ	Loc	Ant	a.s.l.(m)	TX/RX
1	North Wales Wafflers	GW0NWR/P	12120	303	40	IO82	2x17Y	560	FT736
2	Oldham Radio Club	G1ORC/P	6136	236	26	IO93	2x9Y	660	FT290R
4	Stroud Radio Society	G4SRS/P	4645	163	30	IO81	2x11Y	200	FT221R
7	Rochdale & District ARS	G3RIK/P	2688	128	21	IO83	8Y	410	FT290R
9	Cockenzie & Port Seton ARC	GM0CLN/P	2575	103	25	IO85	3x14Y	415	IC275E
10	Wigan - Douglas Valley ARS	G3BP/K	2310	110	21	IO83	11Y	140	IC751E
11	Mark Gray & Ron Gray	G8AWO/P	2242	118	19	IO91	12Z	125	FT236
12	White Noise Listening Soc	G0WNL/P	2190	146	15	IO81	2x15Y	320	FT290R
14	Clyde Coast Contest Group	GM4HEL/P	2090	95	22	IO74	9Y	710	FT290R2
15	Peter, Dave & Graham	G0PJY/P	2052	108	20	IO83	2x2Q	?	IC290

Table 2

Leading single operator stations

Pos	Name	Call	Score	QSO	Squ	Loc	Ant	a.s.l.(m)	TX/RX
3	Dave Hewitt	GW8ZRE/P	5886	218	27	IO83	7Z	275	TR751E
5	Jon Page	G1POS/P	2793	133	21	IO92	10Y	300	FT480R
6	Mike Baguley	GW7LQD/P	2717	143	19	IO82	2x9Y	360	FT290R2
8	Peter Lowrie	G17JYK/P	2576	112	23	IO74	13Y	150	FT290R
13	Peter Thompson	G8DDY/P	2142	119	18	IO90	2x11Y	780	FT221
16	John O'Sullivan	E16ARB/P	1995	84	25	IO63	9Y	440	FT290R
22	Allan Duncan	GM4ZUK/P	1672	88	19	IO86	2x13Y	70	TVVF144a
27	Barry Williams	M0APO/P	1330	95	14	IO93	12Z	335	IC901E
37	Alan Horne	GW0TPH/P	871	67	13	IO83	4Y	600	FT290R2
38	Andy Williams	GM7SX/P	848	53	16	IO85	9Y	730	FT290R2

Table 3

Leading Stations

Overall Winners	North Wales Wafflers	GW0NWR/P
Runners Up	Oldham Radio Club	G1ORC/P
Leading Single Operator	Dave Hewitt	GW8ZRE/P
Runner-up Single Op.	Jon Page	G1POS/P
Leading Fixed Station	Dragonslayers QRP Group	G0BPS
Leading English Station	Oldham Radio Club	G1ORC/P
Leading Welsh Station	North Wales Wafflers	GW1VDF/P
Leading Scottish Station	Cockenzie & Port Seton ARC	GM0CLN/P
Leading N. Ireland Station	Peter Lowrie	GI7JYK/P
Leading Eire Station	John O'Sullivan	EI6ARB/P

Table 4

Leading stations using a single antenna

Pos	Name	Callsign	Antenna
3	Dave Hewitt	GW8ZRE/P	7-element ZL-special
5	Jon Page	G1POS/P	MET 10-element yagi
7	Rochdale & District ARS	G3RIK/P	8-element yagi
8	Peter Lowrie	GI7JYK/P	Cushcraft 13B2 Boomer
10	Wigan - Douglas Valley ARS	G3BPK/P	11-element yagi
11	Mark Gray & Ron Gray	G8AWO/P	12-element ZL-special
14	Clyde Coast Contest Group	GM4HEL/P	Tonna 9-element yagi
16	John O'Sullivan	EI6ARB/P	Maspro 9-element yagi
17	Dave Habro & Dan Esdale	GW4IDF/P	Tonna 17-element yagi
18	Castle Contest Group	G0TOU/P	7-element ZL-special

Table 5

absent from the country for most of the year! My work has taken me to California for a prolonged stay, so that was why, as some of you noticed, G4HLX was not on the air on 15th of June.

As it happened, I found that ARRL were running a 'VHF QSO party' on that same day. It was an event with a rather similar flavour to our own QRP contest, even down to an identical scoring system on 144MHz.

However, I confess that W6/G4HLX was not active in that American event either. This was

because I hadn't got round to assembling a station yet (too many other delights of Southern California to enjoy!).

So, shortly after the closing date for entries, my son **Ben G8EQX** (yes, he's got my old callsign) packaged up all the logs in his suitcase and brought them with him to San Diego. This was when with the rest of the family, he came to stay with me for the summer.

Those few entries which were submitted late were a nuisance, so their score has been penalised by 5%. The two which arrived very late were lucky to be included at all, as special arrangements had to be made for me to obtain the logs!

My 'temporary export' to the USA led to the results being published a month later than usual. This was as anticipated and announced with the rules in June *PW*.

The full detailed results list will, as usual, be sent to all those who provide an s.a.e. with their entries, or if you send one now to the *PW* offices at Broadstone. And of course, they will be available, soon after publication of this

"Hurry up with that QSO...my arm's getting tired"! Members of the Poole Radio Society operating G6MXL/P on the Dorset hills.

issue, on our Internet Web pages at <http://www.rmplc.co.uk/eduweb/sites/ntaylor/pwqrp.html>. This Web site also has an archive of results of previous year's contests, back to 1991, and other contest information. This year however, **I will not be distributing the tables via the Packet radio network.**

Comments & Reports

The comments and reports I've received this year make interesting reading, and for example the Oldham group, G1ORC/P were amongst those for whom the weather at their elevated site, on Kinder Scout: "made working conditions somewhat uncomfortable. We were in cloud all day with visibility about 50 yards, it almost bamboozled the Peak District Wardens who eventually came across us and reported that they had only located us through sound, and homed in on the radio!"

Mike Baguley GW7LQD/P on the other hand notes that: "last year's superb weather was replaced by grey skies, intermittent rain and wind".

At the winner's site, the North Wales Wafflers GW0NWR/P, who set up their station on the Saturday report that: "despite putting

Great weather and a great 'Take off' for the British mainland over the Irish Sea" said Peter Lowrie GI7JYK/P. It must have been a good site because Peter won the newly-introduced EI/GI Trophy for the highest scoring Irish entry!



Leading stations in each locator square

Square	Name	Callsign	No. entrants in square
IO82	Michael Kiely & Patrick Keogh	EI2IB/P	1
IO83	John O'Sullivan	EI6ARB/P	3
IO70	David Blackford	G3NPB	2
IO72	Aberporth Amateur Radio Club	GW4SZV	1
IO74	Peter Lowrie	GI7JYK/P	2
IO76	R. Johnstone	GM1YGV/P	2
IO80	Poole Radio Society	G6MXL/P	2
IO81	Stroud Radio Society	G4SR5/P	4
IO82	North Wales Wafflers	GW0NWR/P	7
IO83	Dave Hewitt	GW8ZRE/P	7
IO84	Castle Contest Group	G0TOU/P	2
IO85	Cockenzie & Port Seton ARC	GM0CLN/P	3
IO86	Allan Duncan	GM4ZUK/P	1
IO90	Peter Thompson	G8DDY/P	4
IO91	Mark Gray & Ron Gray	G8AWO/P	4
IO92	Jon Page	G1POS/P	7
IO93	Oldham Radio Club	G1ORC/P	7
IO94	Drunken Skunk Contest Group	G0LPX/P	5
JO00	Southdown ARS Ladies	G0VU/P	1
JO01	Windbreakers Contest Group	G0VHF/P	11
JO02	Roy Smith	G0RR	1
JO10	Pascal Delmotte	F1TVV	1
JO11	Frank Laanen	PE1EWR	1

Table 6

waterproof gear on we all ended up soaking that night!"

For **Jon Page G1POS/P**, the runner-up single operator, it was: "the first time that I have had to do the contest in the rain". Arriving at his site on the Saturday, he realised that he had "forgotten the box with all the nuts and bolts in". But with no transport, having been given a lift to the site by his wife, he had to improvise. "I used bits of fence wire to hold the mast together and managed to make ten elements of the 14-element. All of this in the pouring rain".

However, while operators in Wales and the Midlands of England were struggling to keep dry, others were more fortunate. **The Mid-Argyll Amateur Radio**

Society GM3RTJ/P report that: "the weather once again was superb with all of us getting quite sunburned".

Weather & Propagation

Accompanying the poor weather in many parts was rather poor radio propagation conditions in all parts. Most stations did not enjoy any exceptional DX, although as usual those stations in good sites and with good antennas managed to work some very good distances.

But also (as usual), many stations were delighted with what they did manage to work. Peter Lowrie GI7JYK/P, for example, says: "I was delighted to work GI/EI7NET/P in IO65 on Rathlin Island for a new square for me



and for my first contact on 144MHz s.s.b. with the island".

Dave Hewitt

GW8ZRE/P was also pleased to contact GI/EI7NET: saying that it was "nice to work IO65 for the first time". Dave also noted a welcome high level of activity in some areas: "Lots of activity from GM/GI/EI. I turned the aerial north and was amazed that I worked so many stations".

The Scottish winners, The Cockerzie and Port Seton Club, GM0CLN/P, also remarked on "a noticeable increase in 'quality' Scottish entries. Another improvement was the level of EI/GI activity". Sadly though, the activity reported was barely reflected in the number of EI and GI logs received and we somehow need to encourage those who participate on the day to send in their entries. The new PW EI/GI Trophy Clock should be an inducement, we hope!

From Cornwall, **David Blackford G3NPB**, reported a lot of local activity: "this year, of my 47 contacts, 38 were Cornish stations". However he doubts that stations in other areas spend much time with their antennas directed to the south-west and asks that "perhaps you could remind stations that there is activity in IO70 and it's another multiplier". (I can

sympathise here, for some operators it can be frustrating failing to get a contact into a square where there really ought to be some activity).

Andy Williams

GM7SXI, heard one contest station calling CQ with these words: "Gentlemen, we are pleading on bended knee for someone in JO03".

Newcomers to the delights of v.h.f. contests discovered some of the unexpected difficulties. For example, **Phil Davies M0AYB/P**, had a task to contend with that will sound familiar to many portable operators: "I was kept busy turning the antenna and 'shooing off' the cows. I don't really mind them licking the car, but I object to them nibbling the windscreen wipers".

The Clyde Coast Contest Group

GM4HEL/P, after the steep climb to their 710m a.s.l. site to set up station on the Saturday, found it hard to get any sleep, as in mid-June at that location that "it was still very light at 2330"! The "impromptu karaoke from GM7GDE and his YL's tent did nothing for the other operators trying to get some sleep"! Their final weary comments was "The sun returned at 0500 just to make sure tired operators were at their best for an early start".

More seriously, on the climb to the site of the Oldham club, G1ORC/P reports that "one of the club members, **Ian Firby**, who came along to assist in carrying the equipment up the hill slipped and fractured his ankle on the way down". (Bad luck Ian. I hope everything's okay now!).

My Job

A few words now about my job as adjudicator! And I'm pleased to say this is made very much easier by the care which many entrants take in presenting their logs and covering information clearly and as required by the rules.


However, there are a substantial number of entrants who still provide incomplete information. The problems include missing list of squares worked, laid out wrongly (e.g. log columns in the wrong order) or logs which are generally hard to read.

The way some entrants provide the covering information I sometimes wonder if they have, in fact, ever read the rules! Serious transgressors will find that their score has been penalised, **but I wonder if I'm not too lenient on some others!** So, let this be a warning: 1998 might be the 'get tough' year, and more entrants will lose points if they haven't provided the information required.

More than one quarter of the entries received were written on the Cover Sheet and Log Sheet stationery downloaded from the Web site. This really does help as I know instantly where to look for the information I need, and can do the log cross-checks much quicker when there is a standard format.

Third Sunday

The PW 144MHz QRP contest has always been held on the third Sunday in June (actually there was one exception, around 1985). Although this has led to some inevitable clashes with other events, for example a few local radio rallies, it has been



A most appropriate callsign - G0VHF/P (Go-VHF-Portable?), a beautiful day and a magnificent looking antenna system for the 'Windbreakers Contest Group' at Walton-On-The-Naze.

generally very popular timing and we shall certainly not change it.

In recent years, the date has also allowed co-ordination with a leg of the RSGB Backpackers' event. Very often, though, the date of the contest has also been 'Father's Day'. Responses to this fall into two categories: The Silverthorn Radio Club G2HR/P tell me that 'we certainly lost some of our team members this year because it clashed with Father's Day - that was their excuse, anyway'!

On the other hand the more common remark is like this one from John Rudd G7OCI/P: "my other operator G7OKV is able to 'escape' as the contest falls on 'Father's Day', so he is able to


have his treat!

Next year, the third Sunday is later in the month, since June starts on a Monday, putting the contest right on the summer solstice, **21st of June 1998**, with the same duration as this year, **0900 - 1600UTC**. So, mark this in your new diaries, and start planning now!

Thank-you to all who took part in this year's QRP contest, and for the enthusiasm which maintains it as the lively, friendly, fun event that we have. Perhaps **David G3NPB**, echoes the thoughts of many when he writes this comment year after year: "as always, it's the highlight of my Amateur Radio year"!

So, here's looking forward to 1998!

Neill Taylor G4HLX



Intrepid (and experienced!) single-operator entrant Dave Hewitt G8ZRE operating as GW8ZRE/P in the 1997 contest.

Practical Wireless, December 1997

Once again on behalf of the Editorial team and all those who take part in the PW 144MHz QRP Contest I have to thank the Neill for the tremendous hard work organising and adjudicating the event requires on his part. Additionally this year, Dr Taylor has had the extra problem of having to do the job whilst being on the West Coast of the USA for most of the time! It meant that the entire Taylor family were involved - and the contest entries being flown to the USA. So, again Neill I thank you on behalf of everybody - we all appreciate your commitment and dedication and hope this wonderfully friendly and important event will continue for many years to come.

Rob Mannion G3XFD, Editor *Practical Wireless*

Topping's Timed Out

By Colin Topping GM6HGW

**Colin Topping
GM6HGW has
come up with
a simple
transmitter
'time-out' unit**

This unit was designed to fit two criteria. One that it should limit the transmissions to a known maximum (but be capable of being terminated at any time within the period) and that it should be both cheap and simple to build. I think I've managed to achieve all those needs!

The circuit of the unit is shown in Fig. 1, and as you can see it is very simple, a single 555 timer chip and a few other components. In its simplicity the workings are easy to understand. The integrated circuit IC1 is connected as a 'single shot' mode. As shown, the output (pin 3) of IC1 is low and will remain there until triggered by taking pin 2 low using S2, the 'Start' switch.

Immediately after S2 shorts to 0V the timing capacitor C1 starts to charge through R1 and the voltage across it rises with a time controlled by R1 and the capacity of C1 itself. At the same time the voltage on pin 3 shoots up to a maximum value, which switches on relay RL1 connecting the common to the normally open contact.

When the voltage across C1 reaches a predetermined value (a known percentage of the supply voltage) the timer takes the voltage on pin three low. This allows the relay RL1 to switch off, returning RL1 to its normal state.

At any time during the time period pressing S1 will (almost) instantly take the voltage on C1 above the threshold point and effectively terminate the timing period. The purpose of diodes D1 and D2 is to protect the integrated timer from the voltage 'kick' (back e.m.f.) caused by rapid changes of current (at switch over) in the coil of relay RL1.

You could have two separate resistors serving the part of R1, each selected by a single pole two-way switch. This is the system I've implemented on my version of the timer - with settings of one and four minutes.

I've not included a shopping list as the unit is so simple - you could use whatever size components that are to hand. Relay RL1 should

have a 12V coil, and may have more contacts than those shown. For easiest time setting I've found that, for R1, the small screwdriver slotted multi-turn 'Cermet' units are best suited.

Simple Construction

I've shown a simple construction diagram, Fig. 2, of one small

layout made on the ubiquitous Veroboard. Using a piece seven tracks wide by 16 holes long, there are only four track breaks needed at C7, D7, E7 and F7. But you don't have to follow this particular layout, but it is small.

So don't sit there get your soldering irons out. No time out for laggards!

PW




Fig. 1: This is the simple circuit of Colin's timer (the unmarked pin on IC1 is pin 2). See the text for a description of how it works.




Fig. 2: Following this Veroboard layout allows a small unit size to be achieved.



MAIL ORDER

0181-951 5781/2

132 High St. Edgware, Middx HA8 7EL

GET THE ACCESSORY CATALOGUE

Send £1 in stamps to receive your copy.



SERENE BASE ANTENNAS

- ***** **STAR BUY TSB-3608** *****
- * Tri band base antenna
 - * 6m, 2, 70cm
 - * 2.15, 6.2, 8.4dBi gain
 - * Glass fibre
 - * construction
 - * Length: 2.42m
 - * PL-259 fitting

NEW LOW
PRICE
£79.95

TSB-3301 GF	144/70, 6.5/9dB (3m)	£69.95
TSB-3302 GF	144/70, 4.5/7.2dB (1.7m)	£54.95
TSB-3303 GF	144/70, 3/6dB (1.1m)	£39.95
TSB-3315 GF	144/70, 8.5/11dB (5.4m)	£149.95
TSB-3608 GF	50/144/70, 2.15/6.2/8.4dBi gain	£79.95

Delivery on above, £10

MOBILE ANTENNAS £6.50 delivery

DB-7900	144/70 cms, (5/7.6dB) 1.5m	£29.99
DB-770M	144/70 cms, (3/5.5dB) 1m	£24.95
DB-1304	144/70 cms, (2.15/3.8dB) .41cms	£19.95
DB-EL2E	144MHz, 1/4ths, 4.5dB (1.8m)	£29.95
DB-285	144MHz, 1/4ths, 3.4dB (1.3m)	£15.95
PL-6M	50MHz 1/4 wave (1m)	£16.95

ACCESSORIES P&P £2.50 on the following

MT-1301	H/Duty Mag Mnt + Coax.....Top Quality	£24.95
MT-3302	H/Duty Hatch/Trunk Mnt.....Top Quality	£24.95
CF-BPF2	2m band pass filter.....	£49.95

Q-TEK ANTENNAS (Del £8)

Q-TEK ZL SPECIALS

2m	5ele (boom 45"/9dBd)	£36.00
2m	7ele (boom 60"/11dBd)	£45.00
2m	12ele (boom 126"/13.8dBd)	£69.00
70cm	7ele (boom 28"/11dBd)	£24.00
70cm	12ele (boom 48"/13.8dBd)	£44.00

Q-TEK YAGIS FOR 2/4/6m + 70cm

2m	5ele (boom 63"/9dBd)	£36.00
2m	8ele (boom 125"/11dBd)	£46.00
2m	11ele (boom 186"/12.7dBd)	£65.00
2m	5ele crossed (boom 64"/9dBd)	£69.00
2m	8ele crossed (boom 126"/11dBd)	£85.00
4m	3ele (boom 45"/7dBd)	£39.00
4m	5ele (boom 128"/9dBd)	£59.00
6m	3ele (boom 72"/7dBd)	£49.00
6m	5ele (boom 142"/9dBd)	£69.00
70cm	13ele (boom 76"/12dBd)	£36.00
70cm	13ele crossed (boom 83"/12dBd)	£55.00

Q-TEK HB9-CV

70cm	HB9CV (boom 12")	£16.95
2mtr	HB9CV (boom 20")	£19.95
4mtr	HB9CV (boom 22.5")	£29.00
6mtr	HB9CV (boom 32.5")	£36.00
10mtr	HB9CV (boom 52")	£65.00

NEW HF MOBILE WHIPS (PL-259)

Easy to mount HF mobile whips ready to go with PL-259 fitting.	
PL-80.....80m whip (approx 1.5m long)	£21.95
PL-40.....40m whip (approx 1.5m long)	£19.95
PL-20.....20m whip (approx 1.5m long)	£19.95
PL-6m.....6m whip (approx 1.2m long)	£16.95

U-120 headset

A high quality headset that will fit hand portable + most HF & VHF/UHF txvrs via optional interface.

£24.95 P&P £3.50

Supplied with two pin molded plug-will fit Alinco/Yaesu/Standard/ADI/Icom hand holds)

F-3035	8 pin "Standard" round	£16.95
F-303Y	8 pin "Yaesu" round	£16.95
F-303K	8 pin "Kenwood" round	£16.95
F-303I	8 pin "Icom" round	£16.95
F-303YP	Modular "Yaesu" phone	£16.95
F-303KP	Modular "Kenwood" phone	£16.95
F-303IP	Modular "Icom" phone	£16.95

D-308B BLACK DELUXE DESK MIC

(with up/down). Super quality. (Supplied with 8 pin pre-wired Yaesu lead)

£49.95 P&P £5

A-08	8 pin "Alinco" round	£9.95
K-08	8 pin "Kenwood" round	£9.95
I-08	8 pin "Icom" round	£9.95
AM-08	Modular phone "Alinco"	£9.95
YM-08	Modular phone "Yaesu"	£9.95



NISSEI METERS

RS-102	1.8-150MHz (200W)	£59.95 p&p £5
RS-402	125-525MHz (200W)	£59.95 p&p £5
RS-101	1.8-60MHz (3kW)	£79.95 p&p £5
RS-502	1.8-525MHz (200W)	£99.95 p&p £5
TSA6601	144/430MHz Pocket PWR/SWR Meter (60W)	£34.95 p&p £1

COAX SWITCHES (P&P £2.50)

CX-401	4 way (SO-239)	£44.95
CX-401 'N'	4 way (N TYPE)	£49.95
CX-201	2 way (SO-239)	£18.95
CX-201 'N'	2 way (N-type)	£24.95

DELUXE G5RVS

Multi-stranded plastic coated heavy duty antenna wire. All parts reusable. Stainless steel and galvanised fittings. Full size - 102ft.



Only **£39.95**

Half size 51ft. Only **£29.95** Carriage £6.00.

NEW Q-TEK INDUCTORS

80mtr inductors. Add them to your 1/2 size G5RV and convert it to a full size. (New length only 69 feet total).

£22.95 P&P £2

DL-60	★ Dummy load ★ DC-500MHz ★ 60W max
★ PL-259 fitting	£16.99 P&P £1

COPPER WIRE (ALL 50MTR ROLLS)

Enamelled	£9.95 P&P £5
Hard drawn	£12.00 P&P £5
Multi-Stranded (Grey PVC)	£8.00 P&P £5
Extra H/duty (Clear coated)	£20.00 P&P £5
Flexweave (H/duty)	£30.00 P&P £5
Flexweave H/duty (20 mtrs)	£12.00 P&P £5
Flexweave (PVC coated 20 mtrs)	£16.00 P&P £5

NEW Q-TEK WINCHES



A range of fully galvanized all steel construction winches with safety ratchet. (SEND SAE FOR SPEC SHEET)

STANDARD WINCHES (DIRECT PULL) P&P £8

QW-400	400LB	£21
QW-800	800LB	£27
QW-1000	1000LB	£31
QW-1200	1200LB	£36
QW-1400	1400LB	£45

BRAKE WINCHES P&P £8

QWB-350	350kgf	£110
QWB-500	500kgf	£151
QWB-650	650kgf	£199
QWB-900	900kgf	£221

TELESCOPIC MASTS

5 section telescopic masts. Starting at 2 1/2" in diameter and finishing with a top section of 1 1/4" diameter we offer a 8 metre and a 12 metre version. Each mast is supplied with guy rings and stainless steel pins for locking the sections when erected. The closed height of the 8 metre mast is just 5 feet and the 12 metre version at 10 feet. All sections are extruded aluminium tube with a 16 gauge wall thickness.

8 mtrs **£69.95** 12 mtrs **£99.95**

Carriage £10.00.

Guy wire kits	P&P £5
Standard kits	£20.95
Heavy duty kits	£25.95

***** NEW PRODUCTS *****

- * Heavy duty free standing tri-pod.
- * Constructed to mil spec. Available for our 8m or 12m telescopic masts (specify which).

ONLY
£84.95
P&P £10

SECTIONAL MASTS Carriage £8.50

4 x 5 foot aluminium sections each swaged at one end.

1 1/4" dia	£19.95
1 1/2" dia	£29.95
1 3/4" dia	£36.95
2" dia	£45.95

WALL BRACKETS

6"	Stand off	£6.95 P&P £5
9"	Stand off	£8.95 P&P £5
12"	T&K Brackets	£12.00 P&P £8
18"	T&K Brackets	£18.00 P&P £8
24"	T&K Brackets	£20.00 P&P £8



MFJ-259

HF digital SWR analyser + 1.8-170MHz counter/resistance meter.

RRP **£225.00** P&P £5



MAIL ORDER TEL: 0181-951 5781/2

Address:- 132 High St. Edgware, Middx HA8 7EL. FAX:- 0181-951 5782

Open Mon-Fri 9.30-5.30pm Sat 9.30-2.00pm. Close to Edgware underground station (Northern line) close to M1, M25, A406.

We now accept Lombard Tricity charge cards NEXT DAY DELIVERY (UK MAINLAND) £10

WEST MIDLANDS BRANCH:- Tel: 01384 481681

Unit 1, Canal View Industrial Estate, Brettel Lane, Brierley Hill, W Mids DY5 3LO



HF TRANSCEIVERS



UK's best selling HF transceiver with 6m + 2m.

SPECIAL OFFER **£995.00**

FREE P-2512 PSU WORTH £90

IC-706 MkI.....OUR PRICE **£799**

IC-756.....OUR PRICE **£PHONE**

IC-706 headsets now available

ALINCO DX-70T

100W HF + 10W 6m transceiver

RRP **£695.00**

Interest free credit available.

£95 deposit & 10 x £60 APR 0%

DX-70 TH High power version.....**£775**

Interest free credit available. £100 deposit 10 x £67.50. APR 0%

DX-70 headsets now available



EX-DISPLAY MODEL

£1049.95



INTEREST FREE CREDIT AVAILABLE

OUR PRICE **£2199.00**

£599 deposit & 10 x £160 APR 0%

ALSO STOCKED

FT-1000MP (DC).....OUR PRICE **£PHONE**

FT-920.....OUR PRICE **£PHONE**

FT-840.....OUR PRICE **£PHONE**

HF ACCESSORIES



P-2512 'M'

25-30 amp power supply with variable volts (3-15). Dual meters (Volts + amps). The UK's best selling power supply. Most of our competitors are

selling the 20A versions for the same price.

RRP **£99.95** OUR PRICE **£89.95**

CE Approved



VECTRONICS VC-300DIP

UK's most popular 300W ATU with built-in dummy load.

SPECIAL OFFER **£139.95**

MFJ-949 Special offer.....**£139.95**

VHF/UHF HANDHELDS

NOW IN STOCK!

KENWOOD TH-G71E

- Dualband 2m/70cm ● Up to 6w output
- 200 memories ● Alphanumeric display
- Full CTCSS ● Wideband receive
- PC compatible



INTRO OFFER **£249.95**

Kenwood TH-235 2m handheld with key pad.....**£149.95**



YAESU VX-1R

The worlds smallest dualband handheld with wideband receive.

OUR PRICE **£269.00**

Yaesu FT-50R dualband handy.....Special offer **£PHONE**



ALINCO DJ-G5

Dualband handheld transceiver. Includes:- twin band Rx (wideband Rx) - full duplex + band scope and much more.

RRP **£299.95**

Rx available 108-999MHz with gaps

DJ-190 2m handheld.....**£149.00**



ICOM IC-T7E

Dualband handheld.

TO CLEAR **£219.95**

AT-400 70cm handheld.....**£149.00**

Palstar KH-6 6M handle.....**£149.00**

HANDHELD ACCESSORIES



NB-30W

2M FM handheld amplifier 2-5W input. 30W output (for 5W ip). Turn your handheld into a mobile for under £50

RRP **£49.95** P&P £2



Nissei EP-300T

Over the ear earpiece with lapel mic & PTT. Fits Kenwood, Alinco, Yaesu or Icom

£22.95 P & P £1 (Please specify brand of radio when ordering)

This Ear/Mic comes with an "over the ear" earpiece as EP-300

MS-107 FIST MICROPHONE.....**£16.95**

T-2602

2m/70cm/23cm (2/3/5.5dB) flexible antenna with wideband receive (14" long BNC).

OUR PRICE **£22.95**

P&P £1

DB-770H

High gain 2m + 70cm telescopic antenna with wideband receive.

OUR PRICE **£24.95**

P&P £1

ALL MODE TRANSCEIVERS



YAESU FT-736R

UK's most popular dualband base station with power supply. Buy one this month and claim a free 6m module worth £300.

SPECIAL OFFER **£1429.00**



YAESU FT-290RII

2m multimode includes FREE FL-2025 25W matching linear. RRP **£759**

OUR PRICE **£449.95**

SAVE **£230.00** (3 PIECES ONLY)



ICOM IC-821H

£1395.00

VHF/UHF MOBILES



YAESU FT-8100R

2m + 70cm FM mobile transceiver with detachable head. Wideband Rx: 110-550/750-1300MHz. True dual receive. 50W on VHF, 35W on UHF. 9600 packet capability via dedicated rear jack panel. RRP **£499**

SALE PRICE **£449.00**

DC.1 DC lead to fit all mobiles (VHF/UHF).....**£9.99**



KENWOOD TM-V7E

Best dual bander on the market.

NEW LOW PRICE

£499.95

ALINCO DR-M06T

Get on the new 6m repeaters with this 20W FM mobile.

Only **£249.95** All Alinco mobiles in stock
DR-140E 2m 50W mobile.....**£249.95**
DR-430 70cm 35W mobile.....**£259.95**
DR-605 Dualband mobile.....**£399.95**

ALINCO's largest UK dealer. Phone today for lowest price or best part-ex deal! We won't be beaten.



ICOM IC-207H

Dualband mobile transceiver with detachable head.

NEW LOW PRICE **£329.00**

1	2 ABC	3 DEF
4 GHI	5 JKL	6 MNO
7 PQRS	8 TUV	9 WXYZ
0		

**YOU'LL NEVER FORGET OUR NEW NUMBER
JUST REMEMBER THE NAME AND
DIAL: 07000 - H-A-Y-D-O-N
07000 - 4-2-9-3-6-6**

OPTOELECTRONICS



TECHTOYZ MICRO COUNTER

Optoelectronics are ready to pioneer the market by proudly introducing the latest in technology for frequency counter, the Techtoy Micro counter. It is the smallest frequency counter in the world with a frequency coverage of 10MHz-1.2GHz. The AA alkaline battery which powers the counter acts as the antenna, so no external antenna is needed.

INTRO PRICE **£89.95**



OPTO SCOUT 3.1-Mk2

Latest mini frequency finder from Optoelectronics. It will capture and memorise up to 400 frequencies that can be recalled directly into the AR-8000. Supplied with ant, nicads and fast charger. RRP ~~£399~~.

SALE PRICE **£349.95**

Opto Cub Our price **£99.95**
Opto Xplorer Our price **£795.95**
Opto Lynx Our price **£129.95**
Micro DTMF decoder Our price **£89.95**
R-11 Interceptor Our price **£349.95**

S.W. RECEIVERS



AOR AR-7030

Brilliant new all mode short wave receiver with synchronous AM + remote control. RRP ~~£799~~.

SALE PRICE **£695.00**

AR-7030 plus OUR PRICE **£879.00**



YAESU FRG-100

UK's best selling SW receiver. It outperforms any other receiver below ~~£600~~.

OUR PRICE **£449.00**



TARGET HF-3

Communication receiver covers 30kHz-30MHz. Complete with power supply and long wire aerial.

RRP **£159.95**

ORDER YOURS TODAY AND CLAIM FREE P&P.

HF-3M OUR PRICE **£189.95**



ROBERTS R-861

Portable SW receiver with SSB and RDS. RRP ~~£199.95~~.

OUR PRICE **£169.95**

COMMUNICATION RECEIVERS



ICOM-IC8500

Wideband receiver covers 100kHz-2GHz. (All mode).

OUR PRICE **£PHONE**



AOR AR-5000

Award winning wide band communication receiver. Covers 10kHz-2600MHz (all mode)

SALE PRICE **£1399.95**



AOR AR-3000A

This highly acclaimed receiver has set its own place in today's demanding market. Your listening

horizons are truly extended by its Rx range of 100kHz to over 2GHz, and high level performance is achieved by its electronically switched 15 band pass filter system.

RRP ~~£950~~ SALE PRICE **£695.00**



BEARCAT BC-9000XLT

An amazing receiver with coverage from 25-1300MHz. 500 memories give ample storage along with auto store, selectable mode, turbo scan (100 channels per sec) alpha numeric facility and much more. RRP ~~£329~~.

SALE PRICE **£259.00**

DIGITAL AUDIO FILTERS



MFJ-784B

Fully featured DSP filter that will work with any transceiver

or receiver.

OUR PRICE **£225.00**

DSP-599ZX RRP ~~£369~~ OUR PRICE **£325.00**

A SMALL SELECTION OF OUR WIDE RANGE OF SECONDHAND

IC-736	As new	£999.95
IC-740	VGC	£469.95
TS-450SAT	VGC	£725.00
IC-471	70cm base	£499.95
FT-840	Ex-demo	£599.95
TS-440S	VGC	£599.95
VX-70T	As new	£599.95
FT-690RII	VGC	£299.95
FT-790R	70cm all mode	£249.95
FT-290R	2m all mode	£179.95
P-2512M	PSU	£59.95
VJ-G5	Dualband h/held as new	£259.95

SCANNERS



ICOM IC-R10

● Handheld scanner ● 500kHz-1300MHz
● All mode ● 1000 channels with alpha tag.

NEW LOW PRICE

£259.00



AR-8000

Wideband handheld scanner covers 500kHz-1900MHz (all mode).

SPECIAL OFFER

£295.00



YUPITERU MVT-7100EX (UK)

100kHz-1650MHz. Wideband scanner with SSB. RRP ~~£349.95~~

OUR PRICE **£225.00**

Soft case for MVT-7100EX OUR PRICE **£19.99**
MVT-9000 SPECIAL OFFER **£345.00**



AX-400 MkII

The smallest handheld scanner in the world. Covers 500kHz - 1300MHz. AM, FM and WFM.

OUR PRICE **£229.95**

FREE DELIVERY

HANDHELD ACCESSORIES



QS-200

Mounts on the air vent grille on a car dashboard to allow easy and safe operation of most handhelds.

£9.95 P&P **£2**



EP-300

Deluxe over the ear earpiece.

£9.95 + P&P **£1**



SCANMASTER SP-55

Boost reception of your scanner with this pre-amp. 25-1500MHz, variable gain, band pass filters.

RRP **£69.95** P&P **£3.50**



POLICE STYLE HOLSTER HHC-2

Matches all hand helds. Can be worn on the belt or attached to the quick release body holster.

£19.95 +P&P **£1**

PalStar KH-6

Low Cost, High Quality & A

By Richard Newton G0RSN

Richard Newton G0RSN says a sensible 50MHz hand-held has been a long time coming but now it's here he's convinced it was worth the wait!

As a Novice Instructor I have long awaited the arrival of a sensible 50MHz hand-held f.m. transceiver that would be accessible to all, including Novice licensees. I am just amazed it took this long!

Therefore I was delighted when I saw the advert for the new Palstar KH-6 50MHz hand-held. My delight then turned to utter excitement when the team from *PW* contacted me to ask whether I would put it through its paces.

The Palstar KH-6 is a 50MHz hand-held transceiver, it covers 50-54MHz. It is supplied with a small helical antenna, carry strap and a belt clip. The battery pack is designed to take dry cell or NiCad type batteries. A sealed NiCad battery pack and charger are available as an optional extra.

Simple By Design

The KH-6 is simple by design and easy to operate. Both of these observations are very much to the radio's credit. The top panel has the **On/Off** and **volume** rotary knob and the **squelch** rotary knob.

The radio features a BNC antenna connection. It also has the standard 'Speaker Mic' jack plug connections. I connected a Speaker Mic that I use with my Icom hand-held, and this worked very well indeed.

The side panel of the KH-6 is 'home' to the **Press-to-Talk** button and the **Up/Down** buttons. It tunes using 10kHz steps, however 5kHz can be added to any frequency by use of a front panel button. For quick tuning, 1MHz steps can be achieved by the use of the '**F**' key and Up or

Down together.

The front panel buttons are used to access this little transceiver's many features. They are also used to access the KH-6's five standard memories and the 'Call' memory.

The KH-6 has all the features I would want in a radio of this type. It has full CTCSS encode and decode, five memories that can be very easily programmed and scanned.

There is a 'Call' channel that can be programmed for easy, one button access to a frequency. This could be used for your local repeater, the call frequency or perhaps a local Net frequency for example.

One of the features that immediately struck me was the display of the KH-6. The frequency read out is large and easily seen, even when the 5kHz step is activated. Other display items such as Low Power select and the 'S' Meter reading are also well defined and the back light is excellent.

The KH-6 is a splendid looking little radio. It's the size a hand-held should be. When you hold it, you know you are holding a radio!

However, the transceiver is small enough to be highly portable and by no means cumbersome. It's well finished in grey metal and plastic and I think the whole design is very tasteful.

Two Power Settings

The KH-6 has two power settings. With it's 12V supply it offers a choice of 5W on high power and 1W on low power.

The rig also features a 'power save' function, which is important for a waffler like me, as the battery pack

does not last long! An attachment to allow connection to external power is available as an optional extra.

In my opinion there will be no problem using the all new 50MHz repeaters with the Palstar KH-6. As I have already motioned it's fitted with CTCSS, it also has 'Repeater shift' function.

The repeater shift function itself is very easy to activate. It's a single button press operation. However, I could not find a way to easily reverse the repeater setting, so that the repeater input frequency could be monitored.

The flexi-whip antenna that is supplied with the KH-6 is rather small. It's neat looking and works well for short range communications such as around a rally site, but for anything else I am afraid it's of little use.

There is, however, a somewhat longer flexi-whip antenna available as an optional extra. This is about the most needed 'optional' extra I have ever come across!

I was loaned this longer antenna with the review radio and the difference was staggering. The efficiency of the KH-6 was tripled at the very least.

Making Contacts

It never ceases to amaze me that a band as diverse and exciting as 50MHz has been so neglected for so long. There is some 50MHz activity in my area so, I was looking forward to getting some contacts under my belt.

My first QSO using the KH-6 was a little bit of a cheat, as I set-up a sked with **Steve G1YNY**. I used the



REVIEW



The KH-6 operates from a battery pack which is designed to take dry cell or NiCad type batteries. Also shown here is the sealed NiCad battery pack which is available as an optional extra (see text).

Accessible To All

KH-6 mobile, using the long flexi-whip stuck out of the window (the passenger window I hasten to add!).

The initial trial did not go too well, the range seemed to be less than 144MHz would have taken us, however, there were many variants at work here, not least of which was the rather difficult to control antenna! What this test did illustrate though was the excellent audio the KH-6 boasts both on transmit and receive.

When I got home Steve and I tried again. Steve lives about 19km away from my home, we are both pretty well at sea level and we have the conurbations of Bournemouth and Christchurch between us.

I could just about hear Steve when I was using the long antenna on the KH-6. Steve could hear me in the background but that was about it. And even as I say that I still reckon that's a quite impressive for a hand-held over that distance and terrain.

I then connected the KH-6 to my W2000 triple band vertical for 50, 144 and 433MHz. As you can imagine this made somewhat of a difference.

With my triple band vertical in place my revised signal report from Steve was 5 and 9. And as I started to explain to Steve that I had not heard anything on the band I was proved wrong, as always!

Peter G0ROJ in Christchurch and **Alan G7MYI** in Cranborne some 24 to 32km away called in to say hello and give me a report. Both Peter and Alan gave me very good signal reports and very favourable reports on the transmitted audio. They were telling me that a couple of Novice stations they knew had got KH-6s and were using them to good effect.

As I was sat at my computer typing the final draft of this review I

had the KH-6 just sat on the table monitoring the local Net frequency. All of a sudden up 'popped' **Jerry G7JEZ**.

I had a chat with Jerry who was in QSO with **Stan G1LUM**, who sadly I could not hear as I was using the small flexi-whip antenna. We were then joined by **Alan G7MYI** from his home in the Cranborne area. To my amazement I could hear him.

Then to my utter surprise Alan said he could also hear me. A trip of about 24-32km on a hand-held with a small whip antenna, this I thought was very impressive.

Despite all this the 50MHz band still seems rather quiet. Although I expect some prefer it that way!

I'm certain that this wonderful KH-6 hand-held will go a long way to encourage a lot of people onto this band, at least I hope so. The 50MHz band has so much to offer.

Good short-to-medium range and medium-to-long range communications are achievable on 50MHz with good conditions or repeaters. Not forgetting the fantastic DX when conditions are really good. Well done to Palstar for doing what so many others should have done ages ago!

Exciting And Diverse

The Palstar KH-6 is simple but effective. I think it represents excellent value for money.

Amateur Radio is exciting because of its diversity and sense of adventure in things new and old, a fact some of us seem to forget sometimes. So, no matter if your interest is Packet radio, f.m. DXing, local 'chit chat' or having a bit of company in the car, the Palstar KH-6 is a low cost high quality way to

Manufacturer's Specifications

General

Frequency range	50 - 54MHz
Frequency control	Phase Lock Loop (PLL) Synthesiser
Frequency stability	± 0.001%
Operating temperature	-10°C - +55°C (14 to 131°F)
Power source	DC 7.2-12V
Dimensions	55 x 130 x 36mm
Weight	0.4kg without battery
Antenna connection	BNC (50Ω)

Transmit

Power output @ 12V	High 5W - Low 1W
Frequency modulation	Narrow band f.m. 5kHz maximum
Current drain	900mA @ full power
Distortion	3% normal @ 3kHz deviation
Microphone sensitivity	6mV nominal

Receive

Circuit type	Superheterodyne - Dual Conversion
Intermediate frequency	First i.f. 10.7MHz Second i.f. 455kHz
Audio output	400mW
Standby current	35mA w/o battery save
Sensitivity	0.3µV


experience a fun band. I look forward to meeting you all on 51.51MHz!

My thanks go to Nevada of **189 London Road, North End, Portsmouth, Hampshire PO2 9AE. Tel: (01705) 662145, FAX: (01705) 690626** for the loan of the Palstar KH-6 for review. The KH-6 complete with small whip antenna, carry strap and a belt clip costs **£149**, the **HF-50L Flexi Antenna** costs **£12.95**, the **NP-126 NiCad Pack (12V)**, **£29.95** and the **Nic/060 NiCad Mains Charger**, **£9.95**. Other accessories are also available, details of which can be obtained direct from Nevada.

Simple by design and easy to operate. The top panel houses the On/Off and volume rotary control together with the squelch control.

PW





By Richard Marris G2BZQ

Richard Marris G2BZQ describes a one valved transmitter for the 3.5 or 7MHz band. And although it's an old 'classic' it works well provided you take the necessary TVI precautions.

If you look back to the earlier days of amateur radio, in old magazines and textbooks, you'll see that many amateurs used a single valved transmitter. Initially it would consist of a Hartley, or other, oscillator operated with a Morse key and attached to a simple long wire antenna.

Although the frequency drift could be considerable, remarkable long distant communications were achieved with those simple sets. But in the 1930s, the crystal oscillator, often using a triode valve, became popular. This set-up provided frequency stability during transmission and a guaranteed known operating frequency.

The arrival of the 6V6 (and the larger 6L6) beam power tetrode valves, before the Second World War, meant that a single valve low power c.w. transmitter became an efficient and reliable item.

With a keyed single valve crystal oscillator, hooked onto a long wire or simple dipole antenna, the amateur

could 'work the world' on 7MHz. The power could be anything up to 10W input, depending on the circuit used, and the h.t. applied to the anode of the 6V6.

The 6V6 was extensively used for both a.f. and h.f. applications, in communications equipment throughout the second world war, and proved its reliability. It is interesting to note that in the 1940s literature the 6V6 appeared as an a.f. output valve, in many h.f. transmitter circuits and it also appeared as a 112MHz transmitter oscillator valve!

The 6V6 valve has lasted over 55 years and is still going strong. Recently I've found the 6V6 being used as the transmitter valve in the USA's 1750m long wave amateur band. I wonder if any of our present day semi-conductor devices will still be around in 50 years time?

At the end of Second World War the 6V6 became available, for a few (old ones) pennies, on the surplus market. While waiting for the restoration of the amateur radio licence after the war, a 6V6 crystal controlled c.w. transmitter was made up almost ready 'to go'.

When the Postmaster General (PMG), who was then the responsible authority, 'gave the off' for the resumption of amateur radio, the transmitter was quickly finished off and 'on air' within hours. It was connected to a very long wire antenna wire running from a bedroom window to a large tree down the garden.

Almost immediately the DX was being worked. And every other QSO seemed to be with someone else using a 6V6, 6L6 or an 807, with its differing base connector, in a single valved transmitter. Happy days! A simple TX would do the job and TVI had not been invented!

More recently it was decided to replicate this transmitter using 'junk box' or readily available components.

Description & Circuit

The circuit is shown in Fig. 1. The only real departure, from the original transmitter, is the use of modern .0047uF 400V polyester layer decoupling capacitors in lieu of the original .005uF 350V waxed paper ones. These paper capacitors though still obtainable, have a nasty habit of failing due to sheer old age. All component and wattage ratings have been given a generous safety margin in the interest of reliability.

The circuit uses a crystal controlled 6V6 metal 'bottle' valve, with an FT243 crystal in a conventional circuit (see later for a 3.5MHz option). A metal 6V6 was used in preference to the much larger glass bulb type, as it is smaller, more robust and has superior heat dissipation due to its matt black finish.

Cathode keying is employed in a switched power oscillator configuration. The circuit uses an internal Pi-network (L1 + C6 + C7a/b) a.t.u. to couple to the antenna. Although I've not found harmonics or TVI it might be preferable to fit an additional low-pass filter at the output.

Although it was designed for the 7MHz band using FT243 crystals, it can also be used on 3.5MHz with appropriate crystals and a larger coil for L1. Other bands could, no doubt, be covered with crystal and coil changes.

A suitable p.s.u. is shown in Fig. 2. The maximum h.t. voltage should be about 300V, but can be between 200 and 300V. At 300V h.t. the stage can be loaded to about 10W input, giving QRP(ish) power levels. However, with say 200/250V the set will give true QRP powers (5W or less).

The power supply used was kept separate and the TX power leads are





Fig. 1: The circuit for the single valve crystal controlled transmitter.



removing the power supply components from an old valve communications receiver, such as Heathkit RA1/RG1, which would give an h.t. voltage of at least 250V at around 80mA with 6.3V a.c. for valve heaters.

Carefully Recheck

After completing the construction, but before applying power, carefully recheck the wiring accuracy, a power meter with a 50Ω dummy load should be inserted onto the coaxial socket, a crystal into its socket and the unit connected to the p.s.u.

Set capacitor C6 about mid-range and C7 at maximum capacitance. After a couple of minutes warming up period, the h.t. can be switched on and the Morse key depressed.

Then C6 should be quickly rotated to resonance (a dip in the meter current). Loading capacitor C7 can then be adjusted for maximum into the load and C6 readjusted to dip as necessary.

Readjustment of both C6 and C7 should be carried out to put the maximum r.f. power into the 50Ω load. The set is now ready to be connected to the antenna via a low-pass filter.

Although the Pi-match could go direct to the antenna, I use another (external) a.t.u. Having adjusted the tuning you can now check the sound of the keying with a receiver.

Tickled Crystals

Some of the older type of crystals may not oscillate, or they may just oscillate spasmodically giving a 'chirping' note. This problem can often be cured with a 'Tickler'. The 'Tickler' is a small value capacitor (made from a short length of twin figure-of-eight well insulated wire). Fitted in the circuit between

anode and grid of the valve, a Tickler is only necessary if the crystal/valve combination will not oscillate, or will not oscillate smoothly.

A tiny capacity value produces a small amount of feedback from anode to grid of the valve giving the reluctant crystal an incentive to oscillate - hence the name Tickler. The Tickler, if it is required, is made of a short length of well insulated figure-of-eight twin wire, shown in Fig. 6.

At one end, the wires are slightly separated and soldered to the anode and grid pins (3 and 5) on the valve socket. The shortest possible Tickler should be used and a little trial and error will be needed starting with a 25mm length. Always switch off the power supply before adjusting the tickler.

Conclusion

The single valve transmitter is a simple, and quite inexpensive almost QRP level transmitter which will make an interesting and 'different' project for the home constructor. For the old timers, it should bring back happy days.

For the newcomer, weaned on low voltage transistor circuits, it will give an introduction to the wonderful magic of valves. The project is simple to make, simple to operate and will produce excellent results.

Warning

I must give a warning to the many home constructors only familiar with the low voltages associated with transistor equipment. With valved transmitters, high voltages are present and great care should be taken.

PW

Shopping List

Capacitors

Polyester layer 400V (min) working

4.7nF 5 C1, 2, 4, 5

1kV (min) high voltage disc ceramic

1n 1 C3

Variable (airspaced preferable)

365pF 1 C6

365+365pF 1 C7 (a and b)

Electrolytic 450V working (minimum)

16μF 2 C8, 9

Resistors

Carbon resistor (0.5W)

22kΩ 1 R1

Carbon resistor 2W rating

220Ω 1 R3

15kΩ 1 R2

Valves

6V6GT 1

V1 (metal jacketed preferred) or 6L6GT

EZ81 1

V2

Inductors

2.5mH 2 RFC1, 2

10H 1 L2

L1 see text

RFC3 see text

T1 is a 300-0-300V + 6.3V (@1A) + 6.3V (@1.5A)

Miscellaneous

You will also need two valve bases (get them from the valve supplier at the same time), a 50 (or 100)mA meter, a suitable box/chassis a suitable crystal and socket, adequately insulated hook-up wire (separated from mains cable perhaps), suitable switches for S1 and S2.




Fig. 4: This is a reasonable layout for the transmitter.




Fig. 5: The octal valve base pin numbering with the pinout details for the 6V6GT and the 6L6GT valves





Fig. 6: The 'Tickler' capacitor if the crystal/valve combination doesn't oscillate cleanly (or at all). See the text for more detail.

Errors & Updates


Back To The Drawing-Pin Board, page 52 PW October 1997

The gremlins managed to get at the overlay drawing of Steve Ortmyer's 7MHz pre-amplifier. However, the circuit diagram escaped their attention, and this is correct. A revised overlay diagram is shown here and replaces Fig. 2 on page 52 of the October issue of *PW*. In this correct version the end of R2 is connected to L2 as in circuit design.

My apologies for this mistake. Editor



Carrying On The Practical Way, pages 72/73 PW November 1997



In the article on creating your own p.s.u. on a standard 'island' style board, the gremlins were at it again. In Fig. 3 on page 73 an extraneous thin line appeared touching D3 in the overlay drawing. The overlay drawing of Fig. 5 is also unfortunately the wrong one, please insert the drawing shown here

My apologies for these mistakes. Editor

WK0779

SIMPLE AS 1 2 3

The Trio JR-599 Receiver & T-599 Transmitter

By Ben Nock G4BXD

Ben Nock G4BXD takes a look at a receiver and transmitter combination from the Trio 'stable'. And in his opinion they form a 'classic' combination' now available for a very reasonable price on the second-hand market.

The late 1960s through to the early 1970s saw the introduction of the Trio JR-599 communications receiver and its matching transmitter, the T-599S. Available on the second-hand market, I think these 'separates' could provide a cheap, easy introduction to the world of h.f. operating without the need for taking out a second mortgage!

As well as being available at a reasonable price, the receiver has the additional attraction of being capable of modification and additions. The factory 'up-graded' version being renamed the 'Custom Special'.

The Custom Special receiver has the extra i.f. filters needed for a.m. and f.m. reception. Another version has a 144MHz converter fitted (the M version), whilst another (the X version), has both the 144 and a 50MHz converters fitted.

The JR-599 Receiver

The JR-599 receiver is fully transistorised, and it's the same with the transmitter with the exception of a valve driver and a pair of p.a.

valves. (I've outlined the specifications for both the sets in Table 1).

The receiver uses 26 transistors, 5 f.e.t.s, one integrated circuit and 35 diodes. A 3SK22 device is used in the r.f., 1st mixer, 2nd mixer and v.f.o. circuits, the remaining transistors being of the 2SC460, 2SC378, 2SC733 variety.

The audio output stage is a 2SD90 and 2SB473 devices in a transformerless configuration. A TA7045M i.c. is used as the 1st i.f. amplifier. (The block diagram of the receiver is shown in Fig. 1).

In its basic form the receiver tunes the familiar 'old' amateur bands of 1.8, 3.5, 7, 14, 21 and 28MHz, plus reception of the WWV frequency standard on 10MHz. No coverage of the WARC bands, with the exception of 10MHz as mentioned, is available.

The M version includes a 144MHz converter, which is tuned using the 28MHz range on the receiver. The same technique is used for the X version which includes converters for 144 and 50MHz converter.

Double Conversion

The receiver, the front panel layout of which is shown in Fig. 1a, employs standard double conversion superhet principles. It incorporates a first 'broadband' i.f. of 8.295 to 8.895MHz feeding the second mixer to produce a fixed second i.f. of 3.395MHz. The second i.f. is where the various filters are fitted and where the selectivity factor is set.

If all the filters, c.w., s.s.b., a.m. and f.m. are fitted then selectivities of 500Hz for c.w., 2.5kHz for s.s.b., 5kHz for a.m. and 25kHz for f.m. are available.

An unusual feature of the receiver is that the i.f. filter can be selected either manually. This is regardless of the mode being received, or it can be left in an 'auto' mode that selects the more normal filter dependent upon the setting of the mode switch itself (for example: the 500Hz filter for c.w. reception).

A 10 position crystal oscillator is used in the first mixer stage with the main v.f.o. operating between 5.5 to 4.9MHz, employed in the second. In addition to the main v.f.o. tuning dial, a separate receiver incremental tuning (RIT) control is provided, and this will be useful if the receiver is used in conjunction with a separate transmitter.

Separate detector stages, balanced ring, diode and ratio, are used to resolve s.s.b., a.m. and f.m. signals respectively. In addition to the v.f.o., there's provision for a crystal oscillator with up to five crystal controlled frequencies selectable by switch.

As the crystals replace the v.f.o., and can be between 4.9 and 5.5MHz, each crystal used will in fact give a crystal controlled channel on every band. For example, using a crystal of 5.4MHz will result in monitoring of 1.9, 3.6, 7.1, 14.1, 21.1, 28.1, 28.6, 29.2MHz and the appropriate 50 or 144MHz frequencies.





Fig. 1: Block diagram of the Trio JR-599 receiver (see text)



A front panel switch operates a stepped resistive attenuator fitted in the antenna feed line. This facility provides fixed levels of r.f. reductions of 20, 40 and 60dB (a fully variable r.f. gain is not fitted to the set).

A 100kHz crystal oscillator is provided as a calibrator. This also drives a 25kHz multivibrator to supply 100 and 25kHz frequency marker pips.

Amplified a.g.c. voltage is used to drive both the S-meter circuit and provide gain regulation for the r.f. and i.f. amplifier stages, with the a.g.c. response time being selectable between fast and slow.

The receiver includes a built-in mains power supply unit and consumption is only 15W. However, it can also be run of a separate 12V source, a rear panel switch selecting the supply, and 1A supply is required for this option.

The rear panel also contains the antenna sockets (both h.f. and v.h.f. if fitted). It's also where the speaker terminals and a remote socket (for use with the matching transmitter) are located.

The T-599S Transmitter

The matching T-599S transmitter employs 30 transistors, four f.e.t.s, one integrated circuit, 38 diodes and three valves. The s.s.b., generated at 3.395MHz, is mixed with the v.f.o. to give a first mix of 8.895 to 8.295MHz, this is further mixed with a switched crystal oscillator to give the required operating frequency.

The mixing frequencies and intermediate frequencies are the same as the receiver. Because of this the pair can be used in transceiver operation with either v.f.o. controlling the operating frequency.

All the stages employ semiconductors with the exception of the driver stage, a 12BY7A, and the power amplifier stage which utilises a pair of S2001, or 6146Bs,

with a standard Pi type output circuit. The block diagram for the transmitter is shown in Fig. 2 and the front panel layout in Fig. 2a.

A built-in semiconductor power supply provides 850V for the p.a. stage valves and the various other supplies required by the set. Other facilities include automatic voice-controlled transmit-receive (VOX) operation, block bias keying for c.w. work and provision of sidetone monitoring.

The front panel mounted meter can be switched to monitor various parameters. These include the a.l.c. level, the p.a. stage cathode current, the r.f. output or the p.a. stage h.t. voltage.

The rear panel of the transmitter houses the main antenna socket and the receiver antenna output. There are also sockets for a.l.c. voltage feed from a linear, c.w. key socket, a low power transverter output and 'p.a. disable switch', a switch selecting transceiver or 'separates operation'.

Mains is applied through the rear-mounted power cable and there's a matching remote socket for use with the receiver. A rear mounted fan is provided to supply forced air cooling for the p.a. valves.

Whilst the pair are obviously styled to match each other a strange thing is that although the receiver is badged as a Trio the transmitter is badged as a Kenwood. Because of this, I think it was possible that versions badged in either logo were available.

I also believe there may have been slight differences in case colour available. The pair reviewed for this article were in silver for the receiver and dark grey for the transmitter, but the matching sets were the same colour.

(Incidentally...a matching speaker, the SP-55, was available to finish off the styling of these units).

In Use

So much for the technical details...but what are the units like in use! And to start, the receiver does lack the now familiar i.f. shift, and facilities like an audio notch filter, it has only one v.f.o. and no memories to fill. But as a straightforward, Amateur bands communication set, it does perform very well.

Feeding the receiver with a decent antenna there are plenty of signals to hear, and the s.s.b. filter proved to be quite adequate to the job on the crowded 7 and 14MHz bands. However, replacement of the r.f. and mixer f.e.t.s with lower noise and better quality devices could possibly improve the set a little.

In operation, the transmitter unit's mode switch has a **Tune** position. This apparently puts the transmitter into transmit mode without the microphone amplifier or p.a. stage being connected, thus allowing the tuning of the drive

Table: 1

Trio JR-599 Receiver Frequency Coverage

Band	Coverage
1.8MHz	1.8 to 2.30MHz
3.5MHz	3.5 to 4MHz
7MHz	7 to 7.5MHz
14MHz	14 to 14.5MHz
21MHz	21 to 21.5MHz
28MHz	28 to 28.5MHz
28.5MHz	28.5 to 29.1MHz
29.1MHz	29.1 to 29.7MHz
50MHz	50 to 53.4MHz (Model X Only)
144MHz	144 to 146MHz (Model M, X only)
WWV	10MHz




Fig. 1a: Diagram showing layout of the receiver front panel (see text).




Fig. 2: Block diagram of the T-599S transmitter (see text).




Fig. 2a: Diagram showing layout of the transmitter front panel (see text).

control first.

With the mode switch to c.w., and the key pressed (if connected) the p.a. is engaged and the normal procedure of 'dip' and 'load' for a Pi-output is undertaken with the p.a. 'plate' and 'load' controls. (You should remember of course, not to hold key down in the un-dipped state for too long if you wish to keep the p.a. bottles for a long time!).

No 'Top' Band

Whilst the transmitter can drive an external transverter, to match the 50 or 144MHz coverage option on the receiver, **the transmitter does not**

cover the 1.8MHz band. So, with no additional crystal positions or spare banks on the band change switch, it cannot be added easily. The front panel layout is shown in **Fig. 2a.**

In conclusion, it's my opinion that if a Trio JR-599 and T-599 combination can be obtained, in good condition and at a reasonable cost you're on to a good thing. I'm sure any newcomer to the bands would be able to enjoy many hours of fun, without the worry of a bank overdraft!

PW

Manufacturer's Specifications

Trio JR-599

Sensitivity

1.8 to 21MHz
28MHz band
50MHz band
144MHz band

(c.w./s.s.b.)

0.5µV for S/N 10dB or more
1.5µV for S/N 10dB or more
1/5µV for S/N 10dB or more
2µV for S/N 10dB or more

(Image ratio >50dB)

Sensitivity (a.m.)

1.8 -21MHz
28MHz band
50MHz band
144MHz band

2µV S/N 10dB or more
4µV S/N 10dB or more
2µV S/N 10dB or more
3µV S/N 10dB or more

Selectivity

On s.s.b.

-6dB at ±1.1kHz, -60dB at ±2.5kHz

On c.w.

-6dB at ±250Hz, -60dB at ±750Hz

On a.m.

-6dB at ±2.5kHz, -60dB at ±5kHz

On f.m.

-6dB at ±30kHz

Dimensions:

270 x 140 x 310mm

Weight:

5.7kg

Trio T-599 Transmitter

Frequency coverage

Band

1.8MHz
3.5MHz
7MHz
14MHz
21MHz
28MHz
28MHz
28MHz

Coverage

(Note: no coverage)

3.5 to 4MHz
7 to 7.3MHz
14 to 14.35MHz
21 to 21.45MHz
28 to 28.5MHz
28.5 to 29.1MHz
29.1 to 29.7MHz

Modes:

s.s.b., c.w., a.m.

Power amp.

stage input:

(s.s.b./c.w.) 3.5 to 21MHz 160W 28MHz 140W)

Amplitude mod.

p.a. stage input:

3.5 to 21MHz 80W (28MHz 60W)

Carrier suppression:

-40dB or more

Unwanted sideband:

-40dB or more

Output impedance:

50 to 70Ω

Microphone input impedance:

impedance:

600Ω or 50kΩ (switch selectable)

Dimensions:

270 x 140 x 310mm

Weight:

12.5kg




Fig. 3: Photograph illustrating the inside cabinet view of the JR-599 receiver. The built-in 144MHz converter can be seen at the top centre right, with space for the optional 50MHz converter alongside (see text).



Fig. 4: Inside view of the T-599S transmitter. The p.a. stage is on the top right within the screened compartment, and the v.f.o. on the bottom left. Linking between the variable capacitor control shafts and the capacitors is by substantial 'non slip' chain drives!

FIRST FOR MAIL ORDER

Cavendish House, Happisburgh,
Norfolk NR12 0RU

EASTCOMM

Fax: 01692 650925 **01692 650077**

Mon-Fri: 9 - 5.30, Sat: 9 - 4.00

KENWOOD YAESU ICOM PRICE MATCH

We match/better competitors advertised prices on current UK equipment - and give a better customer service. Phone us last for the best deal.



LEICESTER '97

Thank you to everyone who congratulated us on having the best stand once again. We sold a record amount of new equipment and therefore have an unrivalled selection of traded-in equipment.

PLEASE PHONE FOR AVAILABILITY

HF EQUIPMENT

ICOM IC735 HF Base	£495	SEM HF 100W dummy load	£25
ICOM IC2KL LINEAR + PSU	£1089	TIMEWAVE DSP9+E	£109
ICOM IC2KL LINEAR + PSU	£1195	TONO 9000E comms term	£169
KENWOOD TS850SAT with ATU	£995	TONO 9000E comms term	£189
KENWOOD TS850SAT with ATU	£1095	TOYO T430 2m/70cm swr mtr	£59
KENWOOD TS950S	£1395	OUTBACKER WL130 aerial + base	£129
LOWE HF150 HF RX	£279	VENUS data pack ++	£25
LOWE HF150 HF RX	£299	W720S 2m/70cm swr mtr	£109
LOWE AP/SP150	£139	WESTERN PM2000 SWR mtr	£89
LOWE PR150	£159	YAESU YO100 monitor scope	£109
MIZUHO MX-3.5S 80m QRP ++	£229		
ROBERTS R827 HF/VHF RX	£129		
TEN TEC PARAGON 585 + PSU	£769		
TRIO TS520SE	£259		
YAESU FT7 mobile 80-10m	£249		
YAESU FT7 mobile 80-10m	£289		
YAESU FT77 mobile 80-10m	£349		

VHF/UHF EQUIPMENT

BNOS LP50-10-50 6m linear	£109	AEK DSP232 + Kenwood lead	£369
BNOS LPM423-10-50 70cm linear	£169	ALINCO DX70T HF + 6m ex-demo	£569
ICOM IC449 70cm mobile	£279	CUSHCRAFT A3WS 12/17m	£189
AMERITRON AT15 1.5Kw ATU	£299	DIAMOND SX2000 SWR 1.8-200MHz	£109
YAESU FT203 2m h/held	£89	HARI 20/15/10 trap dipole	£75
YAESU FT790 Mk1	£199	ICOM H16 VHF h/held +	£279
YAESU FT790 Mk1	£219	JRC NRD535DG HR RX + ex-demo	£1699
YAESU FT290 Mk1	£179	JRC NVA319 ext. sp. ex-demo	£159
YAESU FT290 Mk1	£199	MFJ921 P2M 200W ATU	£69
YAESU FT727 2m/70cm h/held	£169	MFJ202B RX noise bridge	£49
YAESU FRT7700 RX tuner + FF5	£39	MFJ203 HF dip meter	£89

ACCESSORIES

DIAMOND DL1000 Dummy Load	£129	REXEX W544 SWR 140-460MHz	£89
DAIWA digital SWR 1.8-150MHz	£89	SAGANT ZA 1.9 160m end fed zepp	£99
GARMIN GPS38 + case	£125	YAESU FT51R 2m/70cm h/held	£389
KANTRONICS KAM plus	£249	YAESU FT11R 2m h/held	£239
KW E-ZEE match 80-10m	£69		

VHF & UHF BEAMS

Remember when VHF and UHF beams were made to last? They didn't bend double in the first puff of wind. Excellent bandwidth, and results. Coming soon to a mast near you. Watch this space for a new range of beams, designed for the UK, built in the UK, and built to last!

AUTEK RF ANTENNA ANALYSERS

RF1 HF £159.95 P&P 7.95

RF5 VHF/UHF £289.95 P&P 10.00

Protective Case £14.95 P&P 2.75

The RF1 adjusts antennas, feedlines, and RF networks, from 1.2 to 35MHz in 5 bands. It measures RF values of true impedance (0-2000Ω), SWR (1 to 15.1), C (0-9999pF) and L (<0.04 to 300μH). It instantly reads out impedance and SWR. Feedline loss and phasing, Q, tuned-circuit resonance can be accurately measured and adjusted. L and C are measured at the RF frequency of interest, not at 1kHz or 100kHz as with other L/C meters.



RF1

The RF5 is continuously adjustable from 35 to 530MHz in 3 bands. It measures RF values 6:1, and its INSTANT SWR mode finds command automatically. Both units fit into (or 7 - 12V).

NEW

75MHz, and 138 to 500MHz (typically) of true impedance (0-600Ω), SWR (1 to the frequency of minimum SWR (or Z) on the pocket, and run on a standard 9V battery

Mosley H.F. Antennas

END OF SEASON BARGAINS

HEAVY DUTY SERIES	TA31M	10/15/20M	1 EL	£225	£189	Carr £10
	TA33M WARC	10/12/15/17/20M	4 EL	£659	£499	£15
	TW33	12/17/30M	3 EL	£829	£349	£15
HEAVY DUTY CLASSIC SERIES	CL33M	10/15/20M	3 EL	£679	£569	£15
	CL33M WARC	10/12/15/17/20M	4 EL	£789	£599	£15
	CL36M	10/15/20M	6 EL	£989	£699	£15
VERTICAL ANTENNAS	RV4C	10/15/20/40M	Vertical	£269	£239	£10

Anti-Corrosion Compound for Aluminium Antennas: ACJ-2 Sachet £7.95 p&p £1.95

**WE NEED QUALITY, USED, BOXED
AMATEUR RADIO EQUIPMENT
BEST PRICES PAID. COLLECTION ARRANGED**

Anti-Corrosion Compound for Copper Wire Antennas: ACJ-1 Sachet £7.95 p&p £1.95

CALLSIGN CLOCK £39.95

includes world-wide delivery

Hand finished with CALLSIGN on the face. An ideal gift for Radio Amateurs. A useful addition to any radio shack, and a valuable operating aid. A large face gives excellent visibility across a radio room. The hour is indicated in 12/24 hour format. Three colour with blue sky effect background. Global map shows countries with their bearing in degrees. Models are available centred on other world areas.

WHEN ORDERING, STATE CALLSIGN AND AREA OF THE WORLD




ORIGINAL BUG
STANDARD £179
DELUXE £219
Left Handed DELUXE £239

VIBROPLEX

IAMBIC
STANDARD £169
DELUXE £199



DELUXE DOUBLE KEYS
SINGLE PADDLE £369
IAMBIC £369



STRAIGHT KEY
STANDARD £169
DELUXE £199

DELTA 1.5kW COAX SWITCHES

The only
switches with
built in
Arc Protection



2 WAY	SO239 to 600MHz	£69.95	£5.95 P&P
2 WAY	N TYPE to 1300MHz	£84.95	£5.95
4 WAY	SO239 to 600MHz	£94.95	£5.95
4 WAY	N TYPE to 1300MHz	£109.95	£6.95

SWR/POWER METERS



CROSS NEEDLE		P&P £5.95 each	
CN-220	1.8-250MHz	15/150/1500W	£109.95
CN-144	140-170MHz	15/150/1500W	£79.95
CN-V/UHF	140-170,410-450MHz	15/150/1500W	£89.95
PORTABLE			
W450	140-170,400-470MHz	0-150W	£34.95



Please add 2%
to total for card
orders

**Mail Order to: Eydon, Daventry,
Northants. NN11 3PT**
☎ 01327 260178



DC2000 built in HA22R hardware option

HOWES DC2000 Electronics kit: £22.90

(Extra band module kits: £7.90 each).

HA22R Hardware (case etc., pictured): £18.90

HOWES DC2000

Amateur SSB/CW Receiver Kit - £22.90

The ease of construction combined with excellent performance make this a great project for both the beginner and the experienced operator. Plug-in band modules (one included) give flexible frequency coverage. There is a full range of matching accessories including transmitters, so you can expand your receiver into a transceiver as you build up your station! There have been excellent reviews in many radio magazines, (UK and overseas). Enjoyable to build, great results, and expandable!

"Tune the receiver ... you will be amazed" - RadCom



Multiband SSB Receiver

DXR20. Covers SSB and CW on 20, 40 & 80M bands as standard. Optional extra plug-in band modules available. Can link to TX2000 or AT160 for transceive (by adding LM2000 linking module). Versatile and popular, with great performance!

DXR20 Kit: £39.90. DCS2 "S meter" Kit: £10.90. HA20R hardware pack: £28.90

Enjoy your radio more with great projects from HOWES!

ACCESSORY KITS

ASLS	SSB and CW AF external filter	£15.90	DFD5	Digital Frequency Counter/Readout	£54.90
ASL8	RX Antenna Selector/Attenuator	£27.90	SP4	Scanner Preamp. 4 to 1300MHz	£15.90
ISB3	Internal SSB & CW Filter for our RXs	£10.50	S72	Morse Side-tone/Practice Oscillator	£9.80
DCS2	"S Meter" for direct conversion RXs	£10.90	SWB30	SWR/Power Indicator, 30W 1-200MHz	£13.90
CBF2	Counter Buffer (fit to Rx to feed DFD5)	£5.90	XM1	Crystal Calibrator, 8 intervals + ident	£16.90
DD4	Add-on Digital Readout for superhets	£49.90		(optional hardware packs are available to suit most kits)	

The famous HOWES Active Antenna Kits

AA2. Covers 150kHz to 30MHz. The neat compact answer for those with limited space.
Kit: £8.90 Assembled PCB module: £14.90

AA4.Covers 25 to 1300MHz. Broad-band performance in a neat, compact package.
Kit: £19.90 Assembled PCB modules: £28.90

AB118. Optimised for long distance reception on 118 to 137MHz air-band.
Kit: £18.80 Assembled PCB modules: £27.90

MB156. 156 to 162MHz marine band active antenna system (the brother of AB118!)
Kit: £18.50 Assembled PCB modules: £27.60



QRP transmitter built with
TX2000 and HA22R

TRANSMITTERS

AT160	10W AM/DSB/CW 80 & 160M.Kit: £39.90	HA160R	Hardware for AT160: £22.90
TX2000	5W CW. Plug-in band filter. Kit: £24.90	HA23R	Hardware for TX2000: £16.90
LM2000	Links the above transmitters to DC2000 or DXR20 for transceive. Kit: £16.30		

Please add £4.00 P&P, or £1.50 P&P for electronics kits without hardware.

HOWES KITS contain good quality printed circuit boards with screen printed parts locations, full, clear instructions and all board mounted components. Sales, constructional and technical advice are available by phone during office hours. Please send an SAE for our **free catalogue** and specific product data sheets, or you can browse this information on our **Internet Website** (address at top). UK delivery is normally within seven days.

73 from Dave G4KOH. Technical Manager.

COLOMOR (ELECTRONICS) LIMITED

170 Goldhawk Road, London W12 8HJ Day Tel: 0181-743 0899 Fax: 0181-749 3934
E-Mail: giacomelli@colomor.demon.co.uk

★ Celebrating
30 years
1967-1997 ★

OVER 6,000 TYPES OF VALVE IN STOCK. PLEASE ASK FOR A QUOTE

£ p									
DG732	9.40	EL84	2.50	UBC41	3.80	6BR7	4.90	No 17 Junction Boxes	Army nickel-plated brass
EL180F	3.80	EL84A MUL.	10.60	UBF89	1.55	6B87	5.60	£17 65 ea.	£14.10 ea.
EAF42	1.50	EL84W	6.00	UBL1	4.80	6BW6	6.25	No 11 Mk2 Junction	No 24V, 50 ohm London
EBL1	5.80	EL86	3.80	UCH21	5.20	6BW7	1.55	Boxes £17.95 ea.	ACO with Burnsted
EBL21	4.80	EL95	1.85	UCH81	1.20	6BZ6	3.60	Control box type H £41.50	connectors £11.75
ECC81	2.50	EL360	7.60	UCL82	1.65	6C4	1.65	ea.	German Enigma Coder
ECC82	2.90	EL503	38.50	UF41	3.25	6CD6GA	4.80	Meter 19 set £29.50 ea.	EPOA.
ECC83	3.90	EL821	7.65	UF42	1.50	6CH6	3.50	Wireless Remote Control	£7 Johnson Roller Coaster
ECC83 MUL.	9.90	EM34	18.50	UF89	1.90	6CX8	4.70	37 turns 2" dia. 1/8" shaft	£25.85 ea.
ECC91	2.25	EM81	2.60	UL41	14.10	6F6	4.95	Set of RA17 valves	Turns counter for Roller
ECF80	1.00	EM91	3.60	UL41	1.55	6GF7A	4.10	E29.50.	Coaster. Dicast 36 turns.
ECH35	2.60	EZ80	2.20	UM84	1.35	6K7	2.25	Antenna Loading Coil - a	1/8" shaft £17 65 ea.
ECH42	1.20	EZ81	2.85	UY41	3.60	6L6GT/C	2.95	unit of model TC12 radio.	Ceramic Roller Coaster, 30
ECH81	1.90	GZ33	7.00	UY85	1.55	6L6	7.50	Type CML 47205, in metal	turns, 3" turns, 3" dia. 6"
ECL80	1.00	GZ34S	6.00	UY39	4.50	6VEGT	5.10	box,	long, 1/8" shaft £35.50 ea.
EF37	3.45	GZ34 MUL.	17.65	Z759	11.00	6X4	3.55	8 1/2" x 6 x 5 1/2" including	Flexible coupling, ceramic
EF37A MUL.	5.60	GZ37	4.70	2C51	4.50	6XGT	2.50	high power ceramic 6 way	insulated, 1/8" shaft £2.80
EF41	3.30	GZ37 MUL.	8.25	2K25	29.35	7Z4	3.80	switch 2 1/2" dia x 6" coil	ea.
EF50	1.90	KT66 RUS	9.00	5R4GY	6.80	12AT7	2.50	£21.00 ea.	
EF80	2.35	KT88	20.95	5U4G	3.50	12AU7	7.90		
EF86	5.10	MU14	3.50	5Y3	5.85	12AX7	2.05	Redifon synthesizer unit -	New mains isolation
EF86 MUL.	12.95	N78	10.10	6AH6	1.95	12E1	18.00	ARU11 £52.99 ea.	transformer
EF89	1.60	QQV03-6	12.00	6AK5	1.45	12H6	4.70		250V, 50Hz, 1 to 130kVA.
EF91	1.55	QQV03-10	7.65	6AL5	1.00	12HG7	7.70		13A fused class F, 13A Skt
EF95	1.45	QQV03-20A	14.00	6AM6	1.65	13CW4	32.90	Redifon ATU adaptor	& plug £112.00 ea.
EL32	1.45	QQV06-40A	22.00	6AM8A	4.10	813	29.15	common antenna ARU18	
EL34S	7.10	QY4-250	103.85	6AT6	1.95	5744WB	8.70	£41.50 ea.	Variable Capacitors
EL34B	7.20	SP61	3.25	6AUSGT	5.20	5763	8.85	500pF twin - 1 1/2" x 1 1/2" x	240V transformer, output
EL36	3.50	TD03-10	33.50	6AU6	1.80	5963/ECC82	4.00	2 1/4" £9.40 ea.	18.5V, 26V, 29V, 35A and
EL41	4.75	U19	12.20	6BJ8	4.10	6115A	299.95	500pF twin - 1 1/2" x 2 1/2" x	26V, 5A £35.25 ea.

We also sell oil-filled transformers, chokes, block-filled capacitors, diodes, ICs, and transistors.

P&P - Orders up to £3 @ £1.95, £5 @ £2.25, £15 @ £2.50, £20 @ £3.35. Over £20 @ £4.55 Telephone or Fax list for offers. Over 2Kg at cost. VAT included in all prices. Please quote ref PW

A40 CPRC-26 A41
A42 manpack radio
test set no. 2 with leads
and tools.
£25.00 + VAT

88 & 38 sets in stock

Marconi TF2300B
modulation and
deviation meter to
1GHz.

Marconi TF1152 A/1
RF wattmeter. 50
ohms. 10 and 25
watts.
£25.00 + VAT

**SMA leads OMI spectra
with cal chart to
18GHz.
£20.00 + VAT**

TFT Marconi microwave RF power meter
3MW and 3W. 18GHz
and 12GHz.
£125.00 + VAT

Andrews FSJ450
heliac. Discount for
reels.
£3.00 + VAT per mtr

LDF250
£2.00 + VAT per mtr
4CX-1000 and 1500
HF bases.
£100.00 for pair on
panel

'Doug' DeMaw W1FB

A Personal Tribute From Rev. George Dobbs G3RJV

It was with great sadness that I heard the news of the death of Doug DeMaw W1FB. After fighting leukaemia for several months, Doug died on September 28th 1997, aged 71.

I first got to know Doug through his writing in the early 1970s. At that time I was attempting to update my Amateur Radio technology from valves to solid state.

My local library was generous enough to keep copies of *QST* and in their pages I found Doug as a 'fellow traveller'. He was then WICER, and had just become the Technical Editor of the ARRL (Amateur Radio Relay League).

At the time Doug was shifting the emphasis of the ARRL *QST* magazine from valve to solid state design. My early introduction to transistor circuit design and the first solid state projects I built came directly from his writing. It was lucid, it was interesting and I understood it!

Licensed As W8HHS

Milton F. 'Doug' DeMaw was first licenced in 1950 as W8HHS. He was the son of a farmer in North Michigan. And Doug always spoke of his early days with a great fondness.

The family grew their vegetables and frequently hunted their own meat. Doug began his working life as an engineer at the University of Michigan, then working with an aeronautical research company in San Diego.

He also worked in radio and television engineering at WWTW and WATT radio in Cadillac, Michigan. Additionally, Doug was also chief engineer and part-time DJ for Radio WATT.

Founded Avtronics

In 1960 Doug founded Avtronics in Traverse City, a company manufacturing low frequency radio beacons for civilian airports. He sold Avtronics in 1963, and began Comaire Electronics, manufacturing v.h.f. and u.h.f. amateur radio equipment.

During his time running Avtronics, Doug established the *VHFer* magazine. This was taken over by Loren Parks K7AAD, when Doug joined the ARRL staff in

1965.

Doug began his work on the ARRL Headquarters staff as an assistant Technical Editor. In 1968 he was promoted to *The ARRL Handbook* Editor and Laboratory Supervisor.

In 1970 he succeeded the late **George Grammer W1DF**, as Senior Technical Editor and Technical Department Manager. This marked the beginning of what I can only call the 'Golden years' of *QST* magazine. Every issue seemed to be full of good technical articles and worthwhile projects to build.

Produced Books

Doug DeMaw produced and wrote several books during his time with the ARRL. His book *Solid State Design For The Radio Amateur*, which he co-authored with **Wes Hayward W7ZOI**, was the classic.

Personally, I believe *Solid State Design* to be probably the best technical book ever written on Amateur Radio. It was written exactly 20 years ago and I still use it constantly in my radio construction activities. I understand that the co-authorship was not an easy road...but it has entertained and informed me for all its 20 years.

Doug served on the ARRL staff for over 18 years and is said to have written more than 200 technical articles in *QST* magazine. He earned several patents for his research work and practically invented the concept of QRP construction.

Doug had a great love for low power h.f. band Amateur Radio and his many articles were largely responsible for popularising QRP operation with home made equipment. Doug's wife, **Jean WICKK**, also worked on the staff of the ARRL and their son **David** is licenced as **N8HLE**.

Retired Early

Doug retired early, in 1983, on the death of his father, and returned to live in the family farm in Michigan. It was then I believe he did some of his best writing.

The small series of what I call



Doug DeMaw W1FB & the Rev. George Dobbs G3RJV.

his 'farm books', are outstanding. These include: *W1FB's QRP Notebook*, *W1FB's Design Notebook* and *W1FB's Antenna Notebook* and they are three

books that I read constantly!

It's not difficult to work out that W1FB was my hero. I have been inspired by his work for many years and he has kept the hobby alive for so many people.

It's a lucky man indeed who can come to know a hero as a friend and I am glad to say that happened with Doug. When I began my writing for amateur radio magazines, Doug DeMaw was my model.

The ARRL staff used to say of Doug: "he wrote it once and it was done"! In the 1980s I was more than pleased when he subscribed to *SPRAT*, the journal I edit for the G-QRP Club and absolutely delighted when he began to write to me about *SPRAT* and even about the articles I wrote for UK radio magazines.

Visited In 1992

We exchanged mail for several years and I first visited Doug at the end of a trip to the Dayton HamVention in 1992. **Dick Pascoe G0BPS**, and I did the day's drive from central Ohio to northern Michigan to visit the Oak Hills Farm.

It was a visit to a deity! The farm house lies just outside the tiny village of Luther among the lakes and forests of north Michigan.

The house is beautifully restored and much of the surrounding land has been left to return to the wild. Here Doug followed his other great loves, black powder shooting, hunting and cooking with natural ingredients.

We were served wild deer and onions gathered from the local forest. Jean DeMaw was a lovely hostess as well as being a keen shot with a muzzled loaded rifle!

On my next visit to the Oak Hills Farm, I was presented with a wooden plaque which had my callsign burned on a deer jawbone. It had the inscription: "*Primitive Man Endorsement. In recognition of the accomplishments of Rev. George*

Doug DeMaw W1FB was G3RJV's hero and George was delighted to play the part of 'Mountain man & Buckskinner' in tribute to his friend.



Dobbs G3RJV, who has demonstrated at Luther, Michigan, his skill and deadly marksmanship with primitive muzzle-loading weapons, for having eaten wild deer meat and for quaffing native grog at the Luther tavern. Rev. Dobbs has earned the title of Mountain Man and Buckskinner. By the hand of Doug DeMaw W1FB, 1994".

I also cherish a small cup fashioned from deer horn by Doug and presented to me on condition that it would only ever contain spirits!

Hall Of Fame

In 1992, the American QRP ARCI, revived the 'QRP Hall of Fame Award' and Doug was the first named recipient. I was also chosen to receive the award at the same time as Doug.

My own Amateur Radio writing is modelled on Doug's style and I have always tried to make it as interesting and worthwhile as his work. Doug was presented with his plaque first and after I received mine I joined him, I looked up to him and said, "I don't know why they gave me one of these"!

Doug looked down from his great height and in the deep voice, that always reminded me of James Stewart said: "I reckon for about the same reason they gave me one". And that...without doubt, is the nicest thing anyone has ever said to me!

The last contact I had with Doug DeMaw was about 10 days before his death. He sent me an E-mail. It was a joke about a nun. (Nothing else). An era in Amateur Radio has ended!

PW

On Target-Second Time Round

AKD HF3E Target Receiver Review

by Rob Mannion G3XFD & Tex Swann G1TEX

Rob Mannion G3XFD
updates his opinion
on the original
'Target' receiver
manufactured in the
UK by AKD. And as
this model comes
equipped with
software for use with
computers, Tex Swann
G1TEX also reports on
his findings 'on the
computing side'.



Looking back at the review I did on the original 'Target' receiver from AKD which was published in the November 1996 issue of *PW*...I can remember being rather impressed with the budget-priced unit sat on the desk in front of me.

Time has flown by, it's over a year since the original receiver arrived on the market and now it's been joined by a more 'up market' version - with some rather special facilities.

Horses For Courses

It's a case of 'Horses For Courses' in this joint 'opinion' prepared by **Tex Swann G1TEX** and myself. I'm looking at the general receiving side and Tex is looking at the computing department - and his comments follow mine. So, what's arrived this time...is there any difference?

I was immediately impressed when I opened the packaging following Tex's turn with the new AKD receiver. What immediately strikes you is the neat finish and tidy look about the cabinet. It looks 'finished' and the controls are comfortable to use.

And as I usually do - I took a long and critical look - and then used the receiver on the bands. And what a surprise - a good little receiver has been made even better!

Sensitivity, selectivity and general receiver operator seem to have been improved greatly. The 'switchiness' of the synthesiser steps seem to be much less noticeable and the l.c.d. 'dial' on this model (illuminated) was clear and easy-to-read.

On the broadcast bands the receiver was quite excellent for its class. The 'acid' test down on the south coast is trying to receive the BBC World Service on 648kHz. Quite a challenge - and it did very well.

Up on the h.f. broadcasting bands I did a lot of listening and quite frankly I was again very impressed. The internal speaker was good and the (rather misnamed) 'headphone' output socket proved to give very adequate good quality drive to an 8Ω hi-fi loudspeaker. So, as I worked on another job for *PW* I listened - and enjoyed!

On The Air

During one evening I actually used the receiver during c.w. QSOs on 3.5MHz - very successfully. Okay, the selectivity is not up to the standard of my narrow filtered Alinco DX-70, but it proved very good indeed for a general purpose and still relatively budget priced receiver.

Both s.s.b. and c.w. reception

modes were easy to use and the receiver provided very acceptable performance. The only difficulty occurred whenever the station being received was awkwardly set for the synthesiser. But I quickly learned to tune up or down slightly before tuning in with the 'clarifier'.

The supplied antenna was adequate, but the receiver now works very well indeed on the 'main station' antenna, with switchable attenuation available on the rear of the receiver.



Using the supplied mains 'plug-in' power unit the receiver worked extremely well down to approximately 600kHz. Then the receiver became very sensitive to harmonics obviously being received from the power supply itself. I proved this because the same effect happened when I used a similar p.s.u. on the receiver.



The extremely annoying 'buzz' (obviously harmonics from the power supply, disappeared totally when I ran the receiver from a 12V d.c. battery source (an old car battery I keep in the shack). Using this, the receiver proved to be very quiet and superb in its class and I was able to receive some fascinating signals down to well below the 73kHz Amateur band. Even the l.f. aircraft beacons were romping in. Most impressive!

When I used the receiver on my main station (electronically smoothed and filtered) p.s.u. the l.f. performance was almost as good as on a battery supply. But I must point out that my comments are not a criticism of the receiver (it's obviously more towards the power supply) - but perhaps they only draw attention to its sensitivity!

What's The Score?

So, what's the score from G3XFD for the Target? Well, I'm pleased to say that I feel that the receiver is a little





gem. I thoroughly enjoyed using it and found the neat, tidy and 'no fussy' case and presentation to be to my liking.

I also think that with the simple presentation styling adopted by AKD, that the receiver could be incorporated into a portable station. I'd certainly consider this option as I could then concentrate on making a transmitter to suit my requirements. With this in mind I've recommended to AKD that they consider making the same receiver available without the software, because at around £200 or so...it would be a very competitive little receiver indeed.

Now it's Tex's turn to try receiver; so...over to you G1TEX:

All received Rob! I won't dwell on the basic reception capabilities of the new Target HF3E receiver from AKD, I'm sure that Rob will have said enough about it!

Instead I'm going to concentrate on the computer side of its use. The items that set this version of the receiver apart from its earlier model are two new leads and two 1.4Mbyte disks with IBM PC software on them. The software breaks down into two distinct parts.

The first of the two pieces of software I shall deal with is the AKD Receiver Control Software®. The initial issue of the software is a DOS based product that users of Windows (either 3.11 or 95) are warned to exit to the DOS (C:\) prompt before trying to run the program.

Procedure In Detail

The installation procedure is given in good detail in the slim, but complete manual. The commands needed to run the control program that is automatically put into the 'C:\AKD'

should be typed in to run it. The more adventurous could create their own batch file to run the programs from the DOS prompt (and if needed could call up windows again after it has terminated).

Once the software is installed on the hard drive comes the time to fit the control cable. The cable is fitted to the parallel (printer) port of the host computer and connects to a special nine pin socket on the rear of the rig. I experienced no problems at all in use, although I felt a switch box to select either the printer or the control cable would be a distinct advantage to many users.

One option would be to fit a second printer interface card and use this for the printer. However, after some period of use with both pieces of software I came to the conclusion that the switcher box was the better of the two. But I'll explain more about this later.

Calibration Mode

On first running, the software goes through a calibration mode. (Before carrying this out you must disconnect the antenna from the unit). This has two effects: one is that it checks to see how fast the display of the host computer is, and how fast the display can be updated.

The second part of the calibration checks the maximum and minimum signal strength readings from the particular receiver. A zero signal strength check is then made, followed by a full signal level, where the receiver is tuned to an internally generated carrier.

All the required steps for self calibration are quickly done and the various parameters are stored in a file. When running the control program (shown in Fig. 1), you can drive the

frequency and mode from computer stored memories (500 as opposed to the 10 of the rig alone) or directly by selecting frequency and mode.

You can recalibrate the signal strength set-up whenever you wish to as it is on the start-up menu. I then tried out the spectral display mode, in Figs 2 & 3, I've shown two typical displays.

When in spectrum mode, you chose the start frequency, then the scan width from six options (Fig. 4). The six options are bandwidths from 200kHz to a full 30MHz. In Fig. 2 I've shown a scan of the complete 30kHz to 30MHz spectrum scanned in 120kHz steps.

I was so distracted by the enormous signals in the short wave band that I almost missed the small signals in the 28MHz band. I would never have found these without the spectrum display!

The photograph Fig. 5 is of the bottom 500kHz spectrum where there are the large signals of the long wave band and the lower part of the medium wave band shown. One of the things I felt needed 'looking' at with the original AKD receiver was the noise floor on the l.f. band when using the supplied p.s.u.

Now with this spectral display I could look at it directly. I removed the antenna and chose a 30-230kHz display and I was rewarded with the display shown in Fig. 3. I found that the noise was now subjectively better than the original p.s.u. and rig.

The new regulated p.s.u. certainly works well, I found I could listen to the long wave stations with ease and the various utility stations came in quite strongly. I felt this really was a distinct improvement over the original Target receiver.

The Other Software

But now to the other software supplied with the AKD Target HF3 and that is a copy of FAX and RTTY reception software. I am not particularly familiar with this type of software and to make the most of it I needed to take a couple of books home with me for some 'homework'.

The 'Tarfax' data mode software installs itself as easily as the receiver control software, but this time chooses a sub-directory called 'WEATHER'. From within this sub-directory, typing the command 'Tarfax' starts the program up.

When using this software another lead must be plugged into the 3.5mm socket on a flying lead on the parallel port plug, and the parallel port plug must be disconnected from the host computer.

To complete the connections the other end of this new cable, fitted with a single nine-pin plug (like a PC mouse so you need a converter if your machine has only got a 25-way serial port) is connected into the serial socket of the host PC.

It's at this point I'll go back to the switcher box or a second printer port dilemma I mentioned earlier. If the printer port is left connected it is impossible to use the radio's own controls, other than the volume and Clarify ones.

So, even if you have a second printer port, you would still have to unplug the radio from it, and this must be done at the computer end. I think that the best option to aim for is definitely a switcher box. But the type I would recommend is the type where all 25 ways are switched between output sockets, so that the radio is completely isolated.

Now back to the screen, on choosing RTTY working from the initial menu a simple DOS style communications window is displayed. In the top part of the screen the incoming decoded text is shown. Underneath are indicators of the upper and lower frequency limit of the incoming audio tones, and if the decoded text seem to be in order.

Other than choosing which serial port is to be used, there is no other setting up to do, and I found that it worked quite well. Incoming text was displayed with only the occasional error that was due to a poor r.f. signal.

One nice touch with this decoding

software was by pressing 'H' a histogram of the audio passband of the audio signal was displayed. With little experience of this part of the hobby, and not knowing the sound I should be listening for, this alone was a great help.

The FAX software is a copy of NASA marine software, licenced especially for use with the AKD Target radio. However, as FAX via radio was even more of a 'black-hole' than RTTY, I needed more books to get me going and in the end a change of keyboard.

If there was an histogram screen, such as that available in decoding RTTY then it would have been much easier. In fact, I spent a period using the RTTY histogram screen 'training' my ears to the sound of a FAX signal so that I could get the audio signal right by using the Clarifier control.

This training paid off, as I found it easy then to tune around and looks at the various incoming FAX signals. However, I was unable to correct the tremendous slant on the 'picture'. It was this slant that, being unable to correct, I assumed I had to 'tweak' the Clarifier control.

After a change of keyboard all went much better. (I had a cheap one that I'd had to re-assign keys to produce the slashes. And the slash keys control the slant correction of the FAX decoding).

I also tried out JVFAX software which gave a much better more stable on-screen display of the incoming FAX signal. And I have to admit I'd recommend changing to this software when using the Target in this mode.

If you do use this software as I did, the recommended interface is a 'standard' comparator. Another advantage of this shareware (Try-before-buy) is that it also has a slow-scan TV capability not part of the Tarfax software.

All-in-all I felt that the AKD Receiver Control Software© worked well and did the job of controlling the frequency and mode of the rig. I found the spectrum display very useful allowing the whole 30MHz or a smaller portion to be scanned for activity.

Have I got anything against it? As with version one of any software, there were things I would have found useful. And with feedback I'm sure AKD will arrange to include as many as possible in the next version of the control software.

But with the FAX and RTTY decoding software, I feel they are both a little on the simple side to keep everyone happy. If I could I would keep the AKD receiver (and I would like to keep it!) it's a very nice and simple rig to operate at all times I would change to a rather more comprehensive decoding software package.

Editorial Note: AKD are looking to include HamComm and JVFax discs in the HF3E package. They have obtained permission from HamComm but are having difficulty contacting JVFax for their permission. Can anyone help? In the interim there is a registration form with each HF3E receiver to enable customers to receive their free discs, as and when (if?) permission to supply is obtained.

Receiver Improved


As to the radio side of the package I feel that the receiver itself has been improved and it gives a very clean sounding tone on a strong a.m. signal. But for my personal preference I would pass the audio to a selectable filter for long periods of listening to s.s.b. work.

I find listening to an audio signal with a large high frequency content very tiring. I found the audio of the Target receiver on s.s.b. to be just a little 'bright'. This is a personal preference and is not in any way a criticism of the AKD itself.

The set is very stable in frequency, it's small and light, using little power at 12V and is an interesting package with all the control and decode interface cables thrown in. All-in-all I feel it still good value for money. So, it's now time for me to hand back to Rob to 'sign-off'!

Thanks Tex! And our joint 'thanks' go to Val Wagstaffe and colleagues at AKD, Unit 5, Parsons Green Estate, Boulton Road, Stevenage, Hertfordshire SG1 4QG. FAX: (01438) 357591 for the loan of the receiver which costs £299 and is available from all leading stockists of AKD products or direct from AKD via their Mail Order Sales Dept. Contact Val on (01438) 351710 for a catalogue and further info on the HF3E.

PW



We are a small unit and give a one to one personal and professional service to people looking for top quality

Essex Amateur Radio Services

8am **01268 752522** 8pm

7 days

SPECIALIST IN BUYING & SELLING PRE-ENJOYED EQUIPMENT

Full in-house service department. All repairs undertaken. Fast turn around, LOW prices

HF
ICOM IC775 DSP
ICOM IC765
ICOM IC736 +6M
ICOM IC706 II
ICOM IC706 I
ICOM IC729 + 6M
ICOM IC735 II

YAESU
FT1000MP AC
FT920
FT990 DC
FT747 + FM
FT902 DM
FT1012D + FM
FT890AT
FT200 + PSU

KENWOOD
TS450S

TS440SAT
TS50S
TS570D
AKD
4001
6001
TENEC SCOUT + 5
MODULES + MIC

VHF/UHF
IC821H
IC275E
TS790E
TS711E
TS751E
FT736R
FT736R + 6M
FT290 I
FT290 II

DUAL BAND
FT8500R
FT8000R
FT5200
TM732
TM733
TM701E
IC2350H
ALINCO 610E

DRM06 SX
DR430
DR150
DJ180
DJ190
DJ580
DJ5EY
TH79E
TH78E
TH77E

FT50R
FT51R
FT10R
FT530
FT25R
ICW21 ET
FC902 ATU
SP801
FV901 DM
FV901 DM + 2M
FP707 PSU
FC707 ATU
TOKYO 400L ATU
PS55 PSU
PS15 PSU
DRAE 24A AMP PSU
SP950
ICSP3
2 KL LINEAR

IC500 ATU
AMMERTON AL80B
3/500 + GSK 5 CW OP
KW1000
FT21002 NEW TUBES
KAM + V8
KAM + V7
ADONIS MICS

AM708
AM608
AM308
MC60A
SM6
SM8
SM20

**SCANNERS/
RECEIVERS**
KW202 + SPEAKER
ICR7000

MVT9000
MVT7100
AOR 8000
ICR10D

**TRANSVERTERS/
LINEARS**
RN 2M-23CM
MICROWAVE
METERS 2M-23CM
2M-70CM
10M-2M

We also build computers to your spec. i.e. 200MHz. CPU. 2.5HDD. 3 1/2" floppy. 16Mg RAM. Sound blaster. Fan. 24 speed CD. 2Mb video card (upgradeable). Case. Mother board. **£899 incl VAT**

WE NEED YOUR PRE-ENJOYED EQUIPMENT. TOP PRICES PAID.

WE CAN ALSO SELL YOUR EQUIPMENT FOR YOU - AT A BETTER PRICE THAN PART EXCHANGE

E.A.R.S., 4 NORTHERN AVENUE, BENFLEET, ESSEX SS7 5SN - 01268 752522

Lake Electronics

7 Middleton Close, Nuthall, Nottingham NG16 1BX

Tel/Fax: 0115-938 2509

E-mail: 100775.730@compuserve.com

SAE WITH ENQUIRIES PLEASE. CALLERS BY APPOINTMENT ONLY



DTR Series Transceivers

A choice of three single band, CW, transceivers for 3.5, 7.0 or 10MHz. All rated at a nominal 5 watts output, all include a quality case,

hardware and ALL components. **Kit price: £97.80. Built to order: £160.00. Postage (UK) £4.**

TU4 Antenna Tuner

Conservatively rated at 80 watts and covers the HF spectrum. Incorporates a sensitive SWR meter - only needs 1/2 watt to give full scale deflection - and a 4:1 balun. SO239 connectors plus terminals for end-fed wires or balanced feeder operation.

Kit, including case and all hardware: £68.00.

Ready built: £88.00. Postage (UK) £4.



PM20 Power Meter/Dummy Load

A "terminated" (50Ω) power meter permitting power readings as low as 25mW and up to 20W to be made with

ease and accuracy. VSWR: typically less than 1.1:1 at 150MHz and less than 1.3:1 at 430MHz. **Kit price (with case and calibrated meter!) £22.50. Ready built: 30.50. Postage (UK) £1.50.**

KITS AND READY BUILT MODULES

RECEIVE PREAMPS for 2, or 4, or 6, or 10 metres. Gain >26dB and NF <1dB on 2, 4, 6m versions, gain >20dB, NF <2.5dB on 10m version. 100W through power handling. RP2S, RP4S, RP6S, or RP10S. PCB and hardware kit £29.00. Ready built £44.00.

MASTHEAD PREAMPS for 2, or 4, or 6 metres specification as above, together with station feed box. RP2SM, RP4SM, RP6SM. PCB and hardware kit £39.50. Ready built £49.00.

TRANSVERTERS for 2, 4, or 6 metres from 2m or 10m drive. 25W transmit output and 15dB receive gain. Standard version TRC2-10L or TRC4-10L or TRC6-10L are driven with 1-500mW on 10 meters. PCB and hardware kit £150.80. Ready built £208.50. Interface versions TRC4-10iL or TRC6-10iL or TRC6-2iL are driven from 0.5-10W on 2 or 10, respectively. PCB and hardware kit £160.00. Ready built £226.00. TRC4-2iL is also available ready built only.

SPEECH PROCESSOR will increase the average power of sideband transmissions by 10dB and together with enhancement of higher voice tones increase the intelligibility of your signal. It sounds nice too. SP1000, PCB and hardware kit £27.50. Ready built £42.75.

AUTO-TONEBURST provides 1750Hz for 500mS for repeater access, 28 x 28 x 14mm. AT1750, PCB kit £5.00. Built £7.50.

KAYTONE end of transmission morse letter K. Ideal for busy bands to help you be heard in the QRM. KT1000, PCB kit £9.00. Built £15.50.

SEND SAE FOR CATALOGUE.

SPECTRUM COMMUNICATIONS

UNIT 6B, POUNDBURY WEST ESTATE
DORCHESTER, DORSET DT1 2PG.

TEL: 01305 262250

Open 9am-1pm and 2pm-5pm Tuesday to Friday



■ **WEB SITE:** <http://www.martin-lynch.co.uk>
■ **E-MAIL:** sales@martin-lynch.co.uk

THE ONLY NUMBER TO REMEMBER IN AMATEUR RADIO!

07000 73 73 73

Since Martin Lynch first started what has now become the biggest retailer of Yaesu, Icom, Kenwood & Standard Amateur Radio products in the UK, few things have changed.

His priority is still Customer Service first, competitive prices a very close second.

If you want to experience "the complete picture" please call our new "07000" number today.

■ **CALL TODAY FOR THE LARGEST SELECTION OF NEW & USED EQUIPMENT IN EUROPE.**

■ **TEL:** 07000 73 73 73

■ **FAX:** 0181 - 566 1207

■ **CUSTOMER CARE:** 0181 - 566 0 566



OPENING TIMES

MON - SAT : 9.30 - 6.00

■ Martin Lynch can also offer finance terms up to 60 months. Deposits from a minimum of £25. We welcome your part exchange against any new (or used!) product, provided its clean and in good working order. Call the Sales Desk today. APR: 19.9%. Payment protection is also available up to 36 months.

■ All units are brand new and boxed and offered with full manufacturers RTB warranty. All prices quoted for cash/cheque or Switch/Delta card. No additional charges for credit cards.

■ Martin Lynch is a licensed credit broker. Full written details are available on request. Finance is subject to status. E&OE. £10 p&p on all major items.

* **Budget Plan requirements:** Full time employment (or disabled/retired), over 18 and below 71, Current bank account (or building society). For instant finance please ensure you have UK driving licence and cheque guarantee/credit card or Electricity/Gas/BT bill with your current name and address. Finance subject to status. APR 19.9%.

MARTIN LYNCH
& Son

THE AMATEUR RADIO EXCHANGE CENTRE

**140-142 NORTHFIELD
AVENUE, EALING,
LONDON W13 9SB**

A small selection of Superior Used Equipment all available on our super **BUDGET PLAN** - from **Martin Lynch & Son**

**All available with FIFTEEN MONTHS WARRANTY
at a small extra charge**

Icom IC-706mk1

Boxed as new, 1 owner never used mobile. 3 to choose at £695 or £21.39 deposit & 35 payments of £25

Icom IC-725

A 100W simple HF transceiver without all the frilly bits. Only £425 or £34.23 deposit & 18 payments of £25

Icom IC-735

The old bench mark HF Transceiver up until only three years ago. Thats how good it still is! 7 to choose from £495 or £30.97 deposit & 22 payments of £25

Icom IC-726

HF + 6M Transceiver, nice clean condition. Only £595 or £29.09 deposit & 28 payments of £25

Icom IC-729

HF + 6M Transceiver at least 3 to choose from. Only £629 or £31.14 deposit & 25 payments of £25

Icom IC-736

All mode HF + 6M Base with int ATU & PSU One owner from new, boxed. Only £1150 or £55.80 deposit & 60 payments of £28

Icom IC-751

Getting old but rather nice 100W HF Base transceiver. Only £450 or £22.04 deposit & 20 payments of £25

Icom IC-765

Its big, its bold & its got an auto ATU & PSU built in! 100W HF, brilliant RX Performance. Voice is available too! Only £1195 or £34.71 deposit & 59 payments of £30.

IC-775DSP

The ICOM Flag Ship. A monster 200W out, built in PSU & ATU. The Dogs Dangles. Only £1995 or £41.08 deposit & 60 payments of £50.

Icom IC-781

I've got one piece only, sold new by me just a couple of years ago. Unmarked in the original packing with a full one year warranty. You'll never find a cleaner one. Guaranteed. £1895 or £44.73 deposit & 55 payments of £50.

Icom IC-2KL + PSU

A no nonsense easy way of getting 500W plus on any HF band - with no tuning! Ideal for the IC-756, IC-706 or any 100W Icom HF Transceiver. Only £1195 or only £22.64 deposit & 60 payments of £30.

Kenwood R-5000

A special receiver that is an ideal shack accessory to monitor the SW bands - or your own signal! 6 to choose from starting at £695 or £21.39 deposit & 35 payments of £25.

Kenwood TL-922

Henry Lewis has used this "prime beef" HF 2kW input linear (at 400W output I might add) for almost 18 years. And he's still on the original valves! The best of Jap Engineering. Five in stock, all fully refurbished and ready to go. £1195 or £22.64 deposit & 60 payments of £30.

Kenwood TS-850SAT

Kenwood knocked the rest of the camp for six when they introduced this HF 100W masterpiece. All in brilliant condition and available with or without internal auto ATU. From £895 or £25.77 deposit & 50 payments of £25.

Kenwood TS-870S

The only fully DSP HF transceiver from the Japanese manufacturers. Offered in as new condition, with FIFTEEN months warranty as standard. Auto ATU included. Five to choose from all at £1495, or £32.13 deposit & 54 payments of £40.

TS-450SAT

A superb HF transceiver with features usually only found on the bigger base rigs. 2 now available. From £749 or £32.62 deposit & 38 payments of £25.

TS-440SAT

Its growing a beard but they were the biz yonks ago. Still a nice HF starter machine if you can find a clean one. We have three. From £595 or £29.09 deposit & 28 payments of £25.

TR-751E

Remember Angus G3OSS going on about how marvellous these 25W 2M multimodes were. He was right. They still are. 7 in stock from £495, or £30.97 deposit & 23 payments of £25.

TS-570S

The latest HF DSP transceiver from Kenwood. We have 5 refurbished units to choose from at a massive saving off list. All offered with full 1 year warranty. £995 each, or £28.09 deposit & 59 payments of £25

Yaesu FT-757GX

Despite their advancing years, if you pick the right one they still offer good value for money operating. Bit like that trusty old Ford Cortina. (?) Got a complete FT-757 line up including PSU & Auto ATU for only £595! From only £449 or £21.04 deposit & 20 payments of £25.

Yaesu FT-747GX

Can't say much about this one. Ever heard of Chad Valley? This is the RF equivalent. Works though and will get you on HF for under £300. Can't be all bad can it? £299. Take it away.

Yaesu FT-890AT

A great little HF Transceiver that Yaesu don't make anymore. Shame. We still get asked for new ones. £650 or £21.15 deposit & 32 payments of £25.

Yaesu FT-900AT

The same (basically) as the FT-890 but the front panel comes off. Yippee!! £749 or £32.62 deposit & 31 payments of £25.

Yaesu FT-990

One of Yaesu's all time greats. 100W Digital Bandwidth control, auto ATU and available with or without internal PSU. From £995, or £28.09 deposit & 59 payments of £25.

Yaesu FT-1000

The 200W hernia giver. Twin receivers, internal PSU & ATU. Weighs in at a stonking 28 kilos! From £1895, or £44.73 deposit & 55 payments of £50.

Yaesu FT-1000MP/AC

Yes, the current model and we've got two of them! The world's best selling HF transceiver. Bar None. Both with 12 months warranty. From £1695 or £52.33 deposit & 46 payments of £50.

Yaesu FL-7000

A nice cool 500 Watts out on HF with internal PSU & Auto ATU. A linear that is very easy to live with. Only £1450 or £40.80 deposit & 51 payments of £40.

ML&S will price match any advertised price by another authorised dealer providing the item is in stock at the time of ordering

price match!!!

£ PRICE MATCH £

NEW PRODUCTS

ICOM IC-746



The latest HF Transceiver from Icom, with a difference. Not only do you get 100 Watts on HF plus Six Metres but you also get a staggering 100 Watts on Two metres. All from a box not much bigger than the IC-706! Don't those Icom Designers ever go to bed?

- HF to 2M (incl 6M), 100W, 50W on 2M
- All modes on all bands PBT, APF
- Built in Keyer
- Auto ATU fitted
- Gen Cov receiver
- Built in spectrum scope (similar to IC-756)
- 100 Memories
- Excellent noise blanker. Automatic DSP for noise, notch and passband

RRP: £1695 approx.
Deposits now being taken.

ICOM IC-T8E

Who's first to have a **TRIPLE BAND 2/6/70 Handie** then? Icom of course! Enter the IC-T8E. Read the specification and get your deposit in quick!

- Triple Band 2/6/70
- Wide Band RX
- WBFM for FM Broadcast RX up to 5W output!
- First to use NiMH battery
- Splash resistant
- CTCSS as standard
- Switchable TX Narrow FM (12.5kHz) for 2M band
- 123 memories
- Very compact - smaller than most single banders!

RRP: £349 approx.
Deposits now being taken.



YAESU VX1-R

Latest edition from the Yaesu stable. Ultra-compact, Dual Band transceiver with wide band coverage receiver.

- 500mW output on 2/70
- Lithium Ion Battery
- 5-1300MHz receive
- 6 Character Alpha-Numeric display
- Built-in CTCSS function
- Dual watch feature
- AM Airband RX
- Size: 88x114x47mm
- Weight: 125g with antenna & battery

PRICE: £269



TS-570D

Only £26.64 deposit



£26.64 deposit followed by sixty payments of £30.
ML discounted price £1199

MARTIN LYNCH & SON
CATALOGUE NOW AVAILABLE.
PHONE 07000 73 73 73
FOR DETAILS

THE MARTIN LYNCH & SON
AMATEUR RADIO
'BUDGET PLAN'

SUPERDEAL 4

FT-1000MP/AC

We pay £199 towards your deposit!



Still the worlds favourite HF transceiver. Have one in your shack today for only £46.08! And Martin Lynch will pay the £199 extra required for the deposit.

RRP: £2499, ML Price: £2199
less £199 paid FREE towards your deposit, leaving £46.08 deposit from you and sixty payments of £50. DC version also available.

SUPERDEAL 6

IC-207

NO DEPOSIT!!



So you want a new Twin Band mobile Transceiver, but don't want to pay a deposit? Its a toughie, but you've got it. Take away a brand new 50W on Two, 35W on Seventy IC-207 and pay no deposit. We pay it for you!

RRP: £439

No deposit and 18 payments of only £25.

SUPERDEAL 5

JRC JST-245

Only £63.54 deposit



Possibly the ultimate HF transceiver. A huge 150-200W output on HF + 6M. Superb engineering from the premier Japanese manufacturer.

RRP: £3495, ML Price: £2295
Only £63.54 deposit. Forty payments of £75

SUPERDEAL 9

C510+CPB510D

NO DEPOSIT!!



The only twin band Handie with an optional plug in power booster giving you 35W on Seventy & 50W on Two! An ideal portable/mobile package. Better still, we pay the deposit for you!

RRP: £529.90

No Deposit and 24 payments of only £25.

SUPERDEAL 8

TS-870S

The only 'real' DSP H.F.



How about one for under £50 a month? Sounds good to me.

RRP: £2399 ML Price: £1899
£48.73 down payment and only fifty-five payments of £48.73.

SUPERDEAL 10

FT-736R

ADD A SIX METRE MODULE only £20!!



Still the reigning champion of the VHF/UHF/SHF spectrum. This month we're giving you the opportunity of buying a brand new transceiver at £1429 and adding a SIX Metre module for only £20!! I know its stupid, but buy it now before I change my mind.

RRP: £1998, ML Price: £1429
+ £20 for FEX-736/6B = £1449. Deposit £39.80 and fifty one payments of £40. Only whilst stocks last

SUPERDEAL 7

IC-756

HF, Six metres, 100 Watts on all bands and only £1899? (RRP: £2199).



Yep, add to the fact that ALL three top reviewers rate it and you can see why its so popular. Even more so at £48.73 deposit and fifty-five payments of £50. Now all you have to do is decide between them all....!

SUPERDEAL 11

IC-821H

NEW!!



If you are serious about your Two & Seventy operating then take a close look at the IC-281H. It's very good.

RRP: £1599, ML Price: £1399
£31.25 deposit and sixty payments of £35.

SUPERDEAL 1

Yaesu FT-920

Buy a new Yaesu FT-920 with only £38.60 deposit and £50 per month!



Buy a brand new FT-920 with only £38.60 down and £50 per month!

RRP: £1699
ML Discounted price of £1499, deposit £50 and thirty-nine payments of £50.

If you want to pay the loan off quicker, you can. This example is the maximum term for payment.

SUPERDEAL 2

IC-706MKII

New lower price



Icom have slashed £100 off the world's favourite HF/2M/6M mobile transceiver.

RRP: £1099
ML Discounted price of £995, deposit £29 and fifty nine payments of only £25.

SUPERDEAL 3

C5900D

Have one for only £25!



The only triple Band 2/6/70 mobile available! Buy one for only £25 deposit & forty-two payments of £25 and receive CTCSS & DTMF boards worth £100 FREE!

RRP: £799.95

Antenna Workshop

By Gerald Stancey G3MCK

Gerald Stancey G3MCK shows his Preferences, when he says there's only one antenna for the typical amateur.

When it comes to antennas, I've been told I am prejudiced, and I have to admit, it's true. I am prejudiced when it comes to antennas. I think the dipole is the premier antenna for the typical amateur. It is cheap, easy to install, effective and is good where electromagnetic compatibility (e.m.c.) or just plain radio interference (r.f.i.) is a problem.

The many standard handbooks give charts which show in great detail the properties of dipoles. But let's see what they mean for the typical amateur who puts up a horizontal dipole at about 10m above the ground.

With a dipole up at about at 10m, the s.w.r. on 3.5MHz should be close to unity. The s.w.r. figure may rise to about 2:1 on 10MHz, and then fall back down to about 1.5:1 on all the other h.f. bands.

Hence, with such an acceptable s.w.r. figure, an a.t.u. will not normally be needed. This removes a potential source of losses and of course it's one less box in the shack.

On 3.5 and 7MHz the dipole's horizontal radiation pattern will be virtually omni-directional. This means that you don't have to consider in which direction you erect it.

On the higher bands the maximum radiation is broadside to the wire. However, it is a broad beam, the lobe is about 90° wide, so it is not too important to align the antenna correctly. (If you can select from two dipoles erected at right angles all-round coverage will be available).

The Classic Dipole

The illustration of Fig. 1 shows the layout of the classic dipole, and this is of course an ideal arrangement for a dipole. Note that the feeder comes away at right angles for as far as possible then runs close to the ground.

The approach illustrated minimises r.f. pick up on the outer, or braid of the coaxial cable. On the dipole length B-X is the same as C-X, point A is a support point on the house.

There are purists who may wish to insert a balun at point 'X' in Fig. 1. But this is not usually necessary on the lower h.f. bands where the ratio of the length of the dipole to the diameter of the coaxial cable is very large.

In most cases 'pick up' on the braid is more likely to be caused by the feeder running too close to the dipole. And, if this is the case, then fitting a balun will do very little to prevent this.

However, there are known cases where the inclusion of a balun has cured an e.m.c. problem so keep an open mind on this. On the other hand excluding the balun does remove one other potential source of losses and also enables you to easily test that all is well.

Now I'm coming to the perennial problem of the length of the dipole. Here you should remember that the correct length of a dipole, at any one frequency, is a little less than half a wave-length.

But, the 'little less' figure depends on the dipole's height above the ground, the diameter of the wire and the nature of the ground beneath it. (Equations are available which to some degree take account of these variables which can make the maths side easier to work out).

Happily you can ignore these equations for the length of dipoles, as all you need to do is to adjust the dipole for minimum s.w.r. using a reflectometer type of s.w.r. meter.

A bridge, such as the one described by the Rev. George Dobbs G3RJV, in PW January 1997 is ideal. (A laboratory instrument, such as a Wheatstone bridge type of resistance measuring bridge is not satisfactory for this purpose).

In the real world of amateur radio, due to lack of space, it may not be possible to erect a dipole in the manner shown in Fig. 1. Fortunately however, all is not lost.

A dipole will accept quite a lot of abuse before its effectiveness is severely degraded. (There are two widely used methods of 'abusing' a dipole and these are to shorten it, or, the other method is to bend it).

In practice, either shortening or bending a dipole, will increase the losses or reduce the bandwidth. They will also lower the feed impedance which will probably show as an increase in the s.w.r.

But, on the plus side, if the length is not reduced by more than about 50% or the bending is done with care, losses should be acceptable and the s.w.r. should be no greater than two or three to one.

So, let's go into various implementations of these shortening and, bending dipole elements. As with the full size dipole all the following configurations are adjusted to give minimum s.w.r. using a reflectometer type of instrument.

The Loaded Dipole

Physically shortening a dipole is shown in Fig. 2. It shows how a short dipole can be brought to resonance by means of a loading stub. **And although this antenna may look like a G5RV but beware, it isn't.** The top (AB) should be made as long as possible and the length of the stub (CD) should be adjusted for minimum s.w.r. A good starting point is to make the total length of the wire in the antenna somewhat more than half a wave-length.

The diagram of Fig. 3, shows the use of loading coils (shown at




Fig. 1: This form of dipole is quite effective at h.f. and should work on all bands.




Fig. 2: Using a tuning stub (C-D) makes the dipole look like a G5RV antenna, but is still nonetheless a dipole.




Fig. 3: The dipole elements may be physically shortened by including an inductor (L) in each side at about the 50% point.




Fig. 4: Folding the ends of the dipole elements can allow a full length dipole to be fitted in the shorter overall space of a small garden.

points L in the drawing) to achieve the same effect. The optimum point for the coils is about 50-70% away from the centre point.

A dipole such as the one shown here should be adjusted for minimum s.w.r. by trimming the end sections at A and B. For guidance, if the top is $\lambda/4$ long and the coils are in the middle of each leg then the reactance of each coil should be about 900Ω at the desired frequency.

The efficiency the antenna shows, depends on the quality of the loading coils. A good design should incorporate air spaced coils made from thick wire. (When it rains or snows you may find that the antenna will not load; on such days you may be reduced to tidying the shack out).

A short dipole can be capacitively end-loaded to make it resonate as shown in Fig. 4. However, in practice a symmetrical layout is not usually necessary and just bending the ends (C-A or B-E) achieves the same effect.

The lighter lines A-D and B-F, shown in the illustration, are




Fig. 5: Looking like a loop antenna the Reinartz loop has important differences (see text).

alternative directions. But if they are additional then they add greater end loading capacitance, allowing a shorter distance between points A and B for resonance on any frequency.

Bend the wires where it's convenient. The ends do not have to be bent in the same direction or plane. But try to keep the straight centre section (A to B in the diagram) as long as possible.

Bent Dipoles

Now it's time to move from loading dipoles with coils or capacitors, to bending the whole dipole. Of the 'bent' dipoles, probably the most well known variant is the inverted-V dipole. (This antenna variation can be erected with only one support at the mid-point).

Using one of the variants of the 'bent' dipole, can have a big advantage as a (socially accepted) dummy TV antenna on the roof of your house can fulfil the role of support. As the centre support carries the weight of the feeder and centre insulator, the dipole itself can be made virtually invisible by using very thin wire and mono-filament nylon at the ends without end-insulators.

Finally in the bent dipoles department, Fig. 5 shows the Reinartz loop which is a highly bent dipole. In fact, this is so bent it resembles a loop antenna - but note that the ends of the dipole do not touch at the top.

Any insulator used at this point must be of good quality as very high r.f. voltages can be generated, even at QRP power levels.

Now I'll turn to hybrid and asymmetric dipoles. And it is perfectly

feasible to combine any of the above methods if circumstances so dictate, as Fig. 6 shows an inductively loaded bent inverted-V dipole.

In this case it's probably desirable to place the loading coils at the point where the antenna is bent. The bent ends can, as before, go in any direction, even perpendicular to the plane of the paper.

Another feasible configuration is when a dipole can be erected with one leg straight and the other leg bent to fit into the available space. In fact, the possible variations are only limited by your imagination.

All Work

All the above antennas work! Which variant of the dipole is best for you, will be driven by your circumstances as all antennas interact with their environment in unpredictable ways.

It will probably be necessary to experiment to get any of them to work. If the first configuration you try doesn't work very well, then try another. This is what amateur radio is about, experimenting and trying to get good results from impossible sites.

Good luck with your trials!




Fig. 6: Combining a loading coil into each leg of an inverted-V antenna can save a great deal of space for lower h.f. band antenna users.

To order any of the titles mentioned on these two pages please use the O


CHRISTMAS IS COMING-AN

Well, not quite! And although the *PW* Editorial team realise that the majority of readers do already have a good 'library' - we also know you are always on the look-out for new titles to add to the 'home collection'. So, to help you order that Christmas or New Year gift...we've got some ideas for you. And by the way...everyone here at *PW* hope the book you want ends up in your stocking or New Year's gift parcel.

An RAE Student's Notebook By Bob Griffiths G7NHB

£6.95

Thinking about tackling the Novice Radio Amateur's examination? **Bob Griffiths'** book takes the reader through the syllabus and in its easy style explains the necessary technicalities in neat text 'blocks'. Although useful for the individual, this book will come into its own for group study and there's a good chance of anyone receiving this for a present being tempted to take up a Novice Course when they see the technical side of the hobby is not too daunting. **A Helpful Textbook.**




Getting On Track With APRS By Stan Horzeppa WA1LOU

£10.95

Are you into Packet radio? If you, are you may like to find out about the 'Automatic Packet Reporting System'. The American-based author explains all about 'the hottest packet application since the DX cluster'.

Using mapping systems, graphics, versatile software, etc., and the power of the Global Positioning System the APRS software helps you track vehicles (including bikes!) during bicycling 'Marathons' and emergency communication units and weather fronts. And although obviously aimed at the American reader - this author who is well known as an authority on Packet Radio - will keep you up-to-date on what's going on. **Useful Introductory Guide.**




Simple GPS Navigation - Sea - Air - Land Mik Chinery

£10.95


If you're into 'gadgets & gismos' you've probably already bought yourself a portable Global Positioning System (GPS). And once you've bought one...this useful little book will explain (much better than the usual manual!) just what's going on.

And even if you don't have a hand-held GPS it's very interesting to see and learn how the fascinating GPS aid works. **A very helpful introductory book for the radio enthusiast and student navigator.**



To order any of the titles mentioned on these two pages please use the O

D THE BOOK SHELF's BARE!



Hints & Kinks For The Radio Amateur (New 14th Edition)

£11.50

There can't be many Radio Amateurs who've not seen any of the famous 'Hints & Kinks' series. Well-known for offering practical tips, ideas and mini-projects this (all new) edition carries hints and tips on such items as: commercially made equipment modifications, home-built amplifiers, batteries and generators, portable equipment, mobile stations, test gear, around the shack, antennas and antenna systems, TVI, etc. Presented in an extremely 'easily readable' style the book imparts important technical information in short 'snippets' and it's also a very subtle learning aid. It's very useful, very interesting and you won't close the book without learning something! **Very highly recommended.**

Understanding Basic Electronics


£16.50

This book is the reference and learning source which has been so highly recommended by **Rob Mannion G3XFD** in his series 'Discovering The Basics' in *PW*. In fact, Rob regularly refers readers to this book which he consider to be "excellent".

Older readers may well remember the famous 'Common Core' Series of Books entitled *Basic Electricity*, *Basic Electronics*, etc., - and these are the books which Rob considers to have been replaced by *Understanding Basic Electronic*. Rob says that: "the ARRL have produced an excellent textbook and I think that their statement that they **have** aimed the book at being a basic introductory source for all students (not just Amateur Radio) is spot on and they have scored a direct hit"!

The book covers the subject of introductory electronics in concise 'blocks' with excellent text, diagrams and occasional humorous cartoons and comment. **Very readable and very highly recommended.**

UNDERSTANDING BASIC ELECTRONICS




GMDSS For Small Craft By Allan Clemmetsen

£11.95

Allan Clemmetsen, a Radio Amateur himself, takes a look at how the **Global Maritime Distress & Safety System (GMDSS)** works. In this interesting and helpful book (of very great interest to the small boat owner of course) will prove to be helpful to any radio enthusiast wishing to learn about specialist satellite-based systems.

Its interesting, non-fussy approach with plenty of simple diagrams, illustrations and simulated displays and comments will prove very helpful to the radio enthusiast and student navigator alike. **Interesting and helpful introductory source.**



Amateur Radio in Germany

By Angelika Voss G0CCI/DF2XV

Angelika Voss G0CCI/DF2XV explains how Amateur Radio operates in her home country of Germany, as well as offering advice on what you need to do to operate from Germany, if you're visiting from abroad.



Angelika Voss G0CCI/DF2XV

As radio amateurs we are used to communicating with people from all over the world and having long chats with people we may never see in countries we may never have the privilege to visit. But do you ever stop to wonder what it's like to be a radio amateur in another country? How easy or otherwise it is to get a licence, how the national society operates and what the local clubs are like?

When travelling abroad do you make a point of taking radio equipment, or of establishing contact with local amateurs either before going, or whilst you are there? And would you know how to find out about rallies and other events?

Being one of the UK's near neighbours, the Federal Republic of Germany is one of the more accessible places, and one which most people are likely to have visited or passed through at some time in their lives. Germany has one of the largest radio amateur populations in Europe, and with just under 60,000 members, its National Society is one of the largest amateur radio societies in the world.

National Society

The national society in Germany is called the **Deutscher Amateur Radio Club** (DARC). Like most of the larger National Societies it is run as a business employing full-time staff.

The DARC Headquarters is located in Baunatal on the outskirts of Kassel. A total of 30 people look after the day-to-day running of the Society, with a further five working on the monthly magazine *CQ-DL*. Book publishing and distribution are looked after by a subsidiary company called **DARC Verlag**, which employs a staff of six.

The organisational structure of DARC is somewhat different from that of the **Radio Society of Great Britain** (RSGB) in that it's based on a four-tier system. This consists of Local Group, District Council, National Council and Executive Committee.

Unlike in the UK, local radio clubs are part of the national society and are funded out of national society subscriptions (which means that it's

impossible to be a member of a local club without being a member of the National Society, and vice versa). The membership of DARC is divided into geographical districts (similar to RSGB zones, but covering smaller areas).

There are 24 DARC districts made up of a total of over 1,000 local clubs. Each district has a district assembly which consists of the chairmen of the local clubs. The district assemblies each elect a representative to represent them on the National Council.

The National Council of the DARC (known as **Amateurrat**) is made up of the elected representatives of the 24 districts. Unlike in the UK, individual members have no direct say in who serves on their National Council, but have to trust their club chairmen to make the right choice.

The **Amateurrat** elects an Executive Committee consisting of the president and two vice-presidents, these are elected either from within their own ranks, or from the ranks of committee chairmen or other officers of the Society. The Executive Committee is elected for a term of two years, but its members may stand for re-election as often as they like.

The philosophy in Germany is that 'continuity is a good thing', and providing they did a good job in their initial term of office presidents and vice-presidents are generally encouraged to stay in office almost indefinitely. The current president is **Karl Vögele DK9HU** who was elected in May 1997 after having served as vice-president for two years. The vice-chairmen are **Walter Schlink DL3OAP** (on his second term of office) and **Jochen Hindrichs DL9KCX** (newly elected in May).

Like the RSGB, the DARC has a number of specialist committees (including h.f., v.h.f., Contests, Education, etc.), and these work

along similar lines to the committees of the RSGB. The main difference being that the DARC do most of their business by telephone or FAX and only meet once or twice a year. (The same goes for the National Council which only holds two formal meetings each year).

Local Clubs

To all intents and purposes DARC local groups are the same as local clubs in the UK. They meet once or twice a month, arrange talks and slide shows, run club stations, operate in contests, enter ARDF events, run RAE classes and put on barbecues and Christmas parties. Local clubs do not charge their own subscriptions but receive a 'per capita' grant from the National Society.

However, one additional function of DARC local groups is that they serve as QSL sub-bureaus. This simplifies the process of QSLing for the German amateur.

There is no need to post QSLs to headquarters, or to leave s.a.e.s with a sub-manager. All you need to do is take your cards to the local club meeting and collect any cards that have arrived.

The local club will forward the cards to the DARC Headquarters where they are sorted with the help of bar coding equipment and an electronic sorting machine (similar to those used at Royal Mail sorting offices). To simplify QSL sorting, clubs have been issued with individual codes (known as DOK numbers).

Award hunters will be quite familiar with DOK numbers, as they form the basis for a number of awards including the German equivalent to the Worked All Britain Awards. The DOK numbers are made up of a combination of one letter (representing the DARC district) and

★ SALE SALE SALE ★

Deduct 25% discount on orders of £30 and over before post and packing

The Authorised Biography of Sir Bernard Lovell. Includes detailed chapters on the development of wartime radar, H3S and various centimetric equipment, etc. 320 large format pages. Many illustrations. A big book. **£8.75 P&P £3.25.**

R1155 Receiver Data. Contains circuits and technical notes facsimile copy. 47 large format pages. **£11.75** including P&P.

The Ex-Government Surplus Wireless Equipment Handbook. Gives details, information and circuit diagrams and some photos for British and American equipment. Also useful valve information. Large format. Over 100 pages. Facsimile reprint. **£17.50** £2.50 postage.

Valve Communication Receiver Handbook. Contains circuits and technical information for valve communication receivers both commercial and of military origin, 1940s to 1960s. Incorporates a surplus/commercial cross-referenced valve guide. Large format, approx 100 pages. Facsimile copy. **£16.50** P&P £2.50.

Eddystone Communications Receiver Data 1950-1970. A facsimile reprint of the circuit diagrams, general description and some service notes for sets from 1950-1970. 50 pages. **£9.75** ind P&P.

Radar P. S. Hall (et al). An absorbing and informative study by authors from The Royal Military College of Science. Covers the origin, development and operation of military radar from Chain Home to Patriot, etc. Numerous photos and illustrations of equipment and its principles of operation. 170pp. Published by Brassey's Weapon Technology series at £25. Our price **£7.50** P&P £2.50.

Jane's Military Communications 12th Edition 1991-1992. A vast volume of 814 pages. Large format, wraps. Contains descriptions, photographs and basic details of the world's military communications equipment. Brand new. Published at over £100. **Special price £30.** Postage £5, overseas postage extra.

Compendium of Armaments and Military Hardware. By C. Chant. Published 1987. A large hard-back. Gives the salient technical and operational details of the most important weapons used in the land, sea and air-forces throughout the world. Gives details of armament and associated ammunition capabilities and of the electronics required for the weapons to be used. 568 pages. **£17.50** P&P £3.50.

A vintage wireless shop opening in Blackpool

As from 4 September we will be opening our small shop at the address below for the sale of vintage wireless equipment including broadcast receivers, valve communications receivers, Govt. surplus, valves, components, vintage and amateur radio gear, lots of junk and gems. Open Thurs, Fri and Sat 10am - 6pm. Other days by appointment, so please telephone before visiting on these days. We also wish to buy receivers and valve associated equipment and accessories.

(Dept PW) CHEVET SUPPLIES LTD.

157 Dickson Road, BLACKPOOL FY1 2EU

Tel: (01253) 751858. Fax: (01253) 302979.

Telephone orders accepted.



PHONE 0181 684 1166 LANGREX SUPPLIES LTD FAX 0181 684 3056
DISTRIBUTORS OF ELECTRONIC VALVES
TUBES AND SEMICONDUCTORS AND I.C.S.
1 MAYO ROAD • CROYDON • SURREY CR0 2QP
24 HOUR EXPRESS MAIL ORDER SERVICE ON STOCK ITEMS

£ p	KT66 China	10.00	524GT	3.00	6V6G	8.00
AZ31	KT88 China	12.00	6A05	2.00	6V6GT	4.00
CL33	N78	8.00	6AR5	20.00	6X4	3.00
E88CC	0A2	3.00	6AS7G	7.50	6X5GT	3.00
E180F	0B2	3.00	6AU5GT	4.00	12AT7	3.00
E180F	0C3	3.00	6AU6	2.00	12AU7	3.50
EABCB80	0D3	3.00	6AW8A	4.00	12AX7	5.00
EB91	PCF80	2.00	6B4G	22.00	12AX7A	7.50
EBF80	PCL82	2.00	6BA6	1.50	12AX7WA	6.00
EBF89	PCL85/805	2.50	6BE6	1.50	12BA6	2.00
EBL31	PCL86	2.50	6BH6	2.00	12BE6	2.00
ECC33	PD500	6.00	6BQ7A	2.00	12BH7/A	10.00
ECC35	PL36	3.00	6BR7	4.00	12BY7A	7.00
ECC81	PL81	2.00	6BR8	4.00	12DW7	15.00
ECC82	PL504	3.00	6BW6	4.00	12E1	10.00
ECC83	PL508	3.00	6BW7	3.00	13E1	85.00
ECC85	PL509/519	10.00	6BZ6	3.00	572B	95.00
ECC88	PL802	4.00	6C4	2.00	805	45.00
ECC808	PY500A	3.00	6CB6A	3.00	807	7.50
ECF80	PY800/801	1.50	6CD6G	5.00	811A	25.00
ECH35	QQV02-6	12.00	6CL6	3.00	812A	55.00
ECH42	QQV03-10	5.00	6CG7	7.50	813	27.50
ECH81	QQV03-20A	10.00	6CH6	3.00	833A	85.00
ECL82	QQV06-40A	12.00	6CW4	6.00	866A	20.00
ECL86	U19	8.00	6D05	17.50	872A	30.00
ECL1800	UABC80	1.50	6D06B	10.00	931A	25.00
EF37A	UCH42	5.50	6F6G	6.00	2050A	12.50
EF39	UCL82	2.00	6F07	7.50	5751	6.00
EF40	UCL83	2.00	6GK6	4.00	5763	6.00
EF86	UF89	4.00	6J5G	6.00	5814A	5.00
EF91	UL41	12.00	6J5M	4.00	5842	12.00
EF183/4	UL84	3.00	6J7	3.00	6072A	6.00
EL33	UY41	4.00	6JB6A	27.50	6080	6.00
EL34	UY85	2.00	6JE6C	27.50	6146B	15.00
EL34G	VR105/30	3.00	6JS6C	27.50	6201	8.50
EL36	VR150/30	3.00	6K6GT	4.00	6336A	35.00
EL41	Z759	10.00	6L6G	15.00	6550A	25.00
EL84	Z803U	15.00	6L6GC	15.00	6883B	15.00
EL95	2D21	3.50	6L6WGB	10.00	7025	7.50
EL360	3B28	12.00	6Q7	3.00	7027A	25.00
EL509/519	4CX250B	45.00	6SA7	3.00	7199	15.00
EM34	5R4GY	7.50	6SC7	3.00	7360	25.00
EM81/4/7	5U4G	10.00	6SG7	3.00	7581A	15.00
EN91	5U4GB	10.00	6SJ7	3.00	7586	15.00
EZ80/81	5V4G	4.00	6SK7	3.00	7587	20.00
GZ32	5Y3GT	2.50	6SL7GT	5.00		
GZ33/37	5Z3	5.00	6SN7GT	5.00		
KT61	5Z4G	6.00	6UBA	1.50		

Prices correct when going to press.

OPEN TO CALLERS MON - FRI 9AM - 4PM. CLOSED SATURDAY.
This is a selection from our stock of over 6000 types. Please enquire for types not listed. Obsolete items are our speciality. Valves are new mainly original British or American brands. Terms CWO/ min order £10 for credit cards.

P&P 1-3 valves £2.00. 4 - 6 valves £3.00.

Add 17.5% VAT to total including P&P.



Winter 97/98 Catalogue

Includes 32 page full colour Computer Equipment Catalogue

The Winter 97/98 Edition brings you:

- Our most comprehensive selection of Computer equipment ever, including all the latest CPU's, the fastest CD-ROM's, new ranges of Scanners, Printers, Motherboards, Graphic & Sound cards etc. etc., extending our range of PC components and accessories at unbeatable prices.

- £25 worth discount vouchers.

- 208 Page main Catalogue, plus 32 Page full Colour Computer Catalogue, incorporating 26 Sections with over 4000 Products from some of the Worlds Finest Manufacturers.

£2.20
+ 30p p&p

- Available at WH Smith, John Menzies and most large newsagents, or directly from Cirket.

- **Get your copy today!**

Cirket



Cirket Distribution Ltd

Park Lane · Broxbourne · Hertfordshire · EN10 7NQ

Tel: 01992 448899 · Fax: 01992 471314

Email: mailorder@cirket.co.uk

Website: <http://www.cirket.co.uk/cirket>

CHRISTMAS SUBSCRIPTION OFFER

Free Diary

OR

2 Free Issues!

To: PW Publishing Ltd., Subscription Offer,
Arrowsmith Court, Station Approach, Broadstone,
Dorset BH18 8PW.

Credit Card Orders taken on (01202) 659930.

PRACTICAL WIRELESS 1 YEAR SUBSCRIPTION RATES

- ☐ £25 (UK)
- ☐ £30 (Europe 1st class)
- ☐ £32 (Rest of World Airmail)
- ☐ £37 (Rest of World Airmail)

☐ Please send a one year subscription to *Practical Wireless*, starting with the January 1998 issue together with:

- ☐ Free A5 Sized Diary
- ☐ 2 Extra Issues of *PW* (14 for the price of 12) to:

Recipient's Name & Address

Name:

Address:

..... Postcode:

Name, Address And Payment Details Of Person Giving Gift

Name:

Address:

..... Postcode:

I enclose cheque/PO (payable to PW Publishing Ltd.) £

Charge to my Access/Visa card the amount of £

Card No:

Valid from to

Signature Date

If you do not want to cut your copy of *PW*, a photocopy of this form is acceptable

Does someone else read your copy of *Practical Wireless* every month?

Then why not surprise them and buy them a **PW GIFT SUBSCRIPTION?** In addition to this you can select them a christmas gift in the form of either a **Free 1998 A5 Diary** or **2 extra issues of *PW*** (14 issues for the price of 12)!

So, why not give your loved-one, your best friend or a fellow radio enthusiast (or why not treat yourself!) a subscription to their favourite magazine this Christmas.

Order a subscription to *Practical Wireless* now and we'll send a card telling them that their gift from you will be their own personal copy of *Practical Wireless* delivered by the postman every month next year.

To qualify for this offer please fill in the form on this page and send it back to us by **December 15** (UK orders only) and the order will be despatched in time for Christmas. But, remember, overseas orders take longer to reach their destination.

a two-figure number. The lists of DOK numbers are published annually by the DARC.

Operating In Germany

While Germany is not exactly 'DXpedition Country' it's well worth taking some radio equipment if you are visiting the country on holiday or business, especially if you are travelling by car. Getting on the air in Germany is straightforward for UK amateurs.

The introduction of the CEPT Common Licence in the mid-1980s means that holders of UK Class A and B licences can now operate in most European countries on a UK licence providing they do not stay for more than three months. (However, the CEPT agreement does not extend to Novice Licences). When operating in Germany you must use your own callsign prefixed by **DL/(UK Class A callsign)** or **DC/(UK Class B callsign)**.

If you are travelling around Germany on holiday, the bands you are most likely to use are 144 or 430MHz. All in all you should find operating quite simple and not really that different from operating in the UK (apart from the language, of course), but there are a few things you need to be aware of.

One thing to bear in mind when operating on 430MHz is that Continental repeater channels are different from those in the UK. When operating on the 144MHz band in Germany, it should be noted that very few people monitor 145.500MHz.

Local clubs normally have their own (unofficial) meeting frequencies. And most amateurs will listen out either on their club frequency or on a local repeater.

People take a fairly relaxed attitude to repeater use in Germany, no one objects to repeaters being used for QSOs between fixed stations or even for local Nets. Also, it's not uncommon for QSL cards to be exchanged for repeater QSOs.

While a few words of German are certainly helpful when using 'local' frequencies in Germany don't worry too much if you don't know the language. English is widely spoken in the Western states (where it has been a compulsory subject at school since the end of the Second World War), and even in the Eastern states (where school children were learning Russian until 1989) the ability to speak English is now becoming more widespread.

Holiday Events

If you'd like to combine your holiday to Germany with a radio event, then

there are a number of rallies and conventions worth going to.

Most people will have heard about Germany's main annual event, the 'Ham Radio' Convention held in Friedrichshafen on the shores of Lake Constance. This event takes place over three days in late June or early July and features a large trade show, gigantic flea market and a programme of talks, lectures and discussion groups.

The Weinheim VHF Convention, held every year in September, now attracts a growing international clientele. This German-Dutch Convention takes in the town of Bad Bentheim in late August and offers a two-day programme of activities and attractions for the whole family.

There are also numerous regional events ranging from half-day local flea markets to two-day meetings held over weekends. The two-day events usually include various social activities such as children's entertainment and a party or dinner dance on the Saturday night.

Obtaining A Licence

While the CEPT licence covers short-term visits, those wishing to stay in Germany for more than three months will need to apply for a German Amateur Radio Licence. Holders of UK Class A and B licences may obtain a German licence on the strength of their UK licence without having to take the German RAE.

If you do exchange your licence don't be surprised if your British Class A licence comes back as a German Klasse B, or your British Class B has been turned into a German Klasse C. The designation of German licence classes is somewhat illogical (for historical reasons).

There are three licence classes in Germany. These are Klasse B which is roughly equivalent to UK Class A, Klasse C which is equivalent to UK Class B while Klasse A is an intermediate licence allowing limited access to the h.f. spectrum in addition to v.h.f./u.h.f. privileges.

The written exams are the same for all three licence classes but there are different pass marks for the technical paper. These pass marks are 50% for Klasse C, 65% for Klasse A and 75% for Klasse B.

There is no Morse code requirement for Klasse C, Klasse A requires a pass at 30 characters per minute (c.p.m., approx 6w.p.m.) while a speed of 60c.p.m. (12w.p.m.) is required for Klasse B. There is no Novice Licence in Germany at present, but some discussions have been held between the DARC and the Licensing Authority about the possible introduction of a new licence



The Headquarters of the Deutscher Amateur Radio Club (DARC) is situated in Baunatal on the outskirts of Kassel.

class for beginners.

The callsign prefixes for Germany are: DF, DJ, DK and DL for Klasse B, DB, DC and DG for Klasse C and DH for Klasse A. Callsigns starting with DE are not real callsigns but 'honorary' ones awarded by the DARC to short wave listeners who have passed the voluntary s.w.l. exam. The DA prefix was reserved for members of Western Allied Forces stationed in Germany but has now been allocated as a prefix for club callsigns.

Quite A Difference

When it comes to licensing exams and Morse tests quite a few differences exist between Germany and the UK. The German RAE is a written exam (not multiple choice), and it comes in three parts which consist of a technical paper, a paper on rules and regulations, and a paper covering operating procedures. The Morse test also comes in three parts consisting of random five-letter groups, a passage of clear language, and a passage of typical QSO text.

Unlike the UK, there are no fixed dates for the RAE, as exam dates are set by local centres according to demand. The exam and Morse test are administered by the licensing authority (although this is expected to change in the near future as part of the privatisation process).

As the exams are also marked locally it is often possible to take the exam in the morning and pick up your licence before the close of business on the same day. Some people have even been known to take the RAE in the morning, sit the Morse test after lunch and appear on the air a few hours later with a brand new Klasse A or Klasse B callsign!

Until very recently the minimum age for obtaining a licence in Germany was 14, and amateurs under 16 were only able to operate under supervision. Both restrictions have now been lifted.

And finally I would like to thank DARC Head Quarters, and **Hans Berg DJ6TJ** (Chairman of the International Liaison Committee), for the assistance they have given me in compiling this article.

PW

More Information

If you want to find out more about operating in Germany the DARC maintain a large database of information at their headquarters in Baunatal, and their staff will always be more than happy to assist visiting amateurs from abroad. They can provide you with repeater lists, put you in touch with local clubs, and answer any specific questions you may have.

For those who need to apply for a short-term reciprocal licence (i.e., from countries which are not covered by the CEPT agreement) the DARC will handle the paperwork on behalf of the Licensing Authority. You can contact the DARC (in German or English) at **Postfach 1155, 34216 Baunatal, Germany** or by **FAX on 0049 561 9498850**.



Phone: (01908) 610625 (Photo Acoustics Ltd)
FAX: (01908) 216373
 E-Mail: 100304.71@Compuserve.com

58 High Street
Newport Pagnell
Bucks MK16 8AQ.

CLOSED
THURSDAYS

Alinco (New low prices)

From 1.8-50MHz



Alinco DX-70T (with CTCSS), 100W HF, 10W 6m, all mode. C/W SX-20C 3.5-30/50-54/130-150SWR/power meter.

£695.00 carr FREE

Alinco DX-70TH, 100W HF, 100W 6m, all mode C/W SX-20C 3.5-30/50-54/130-150 SWR/power meter.

£775.00 carr FREE

PACKAGE 1. Alinco DX-70TH, 100W HF, 100W 6m, c/w 25 amp PSU, VK5JR HF multiband vertical, VC-6 6m V dipole. (5 year warranty on DX-70).

PA price £1261.95

DEPOSIT £150.95, 24 PAYMENTS OF £58.74.
 COST OF LOAN, £298.76.

PACKAGE 2. Alinco DX-70TH, 100W HF, 100W 6m, c/w SG-230 Smarttuner ATU, HFM-1 3.5-30MHz mobile antenna and PRO-AM 6m mobile antenna. (5 year warranty on DX-70).

PA price £1250.90

DEPOSIT £150.90, 24 PAYMENTS OF £58.16.
 COST OF LOAN, £295.89.

YAESU FT-920 HF Transceiver




The new FT-920 has been released and offers some great features at a great price. 1.8MHz to 54MHz plus wideband receive, 33MPS digital signal processor, digital IF shift, auto notch filter, dual VFOs, 100 memories, band stacking VFO system, break-in CW with electronic keyer, TNC interfacing, digital voice recorder, 13.8V DC operation.

Yaesu FT-920 (5 year warranty), c/w 25 amp PSU & FM board.

PA price £1752.95

DEPOSIT £175.95, 36 PAYMENTS OF £61.87.
 COST OF LOAN, £650.32.



P-2512M

25-30 amp power supply with variable volts (3-15). Dual meters (VS + amps) and over voltage protected.

£89.95 carr £10

SAVE £10

IC-706MkII PACKAGE DEALS

IC-706MKII (£1095.00) Carr £10.00

PACKAGE 1. IC-706MKII c/w SG-230 Smarttuner auto ATU, HFM-1 3.5-30MHz mobile antenna. (5 year warranty on IC-706).

PA price £1449.95

DEPOSIT £150.95, 24 PAYMENTS OF £68.68.
 COST OF LOAN, £349.32.

PACKAGE 2. IC-706MKII c/w Comet CAHV HF+6m+2m mobile antenna, c/w Icom IC AT-180 Auto ATU. (5 year warranty on IC-706).

PA price £1500.95

DEPOSIT £160.95, 24 PAYMENTS OF £70.85. COST OF LOAN, £360.40.

PACKAGE 3. IC-706MKII c/w 25 amp PSU, VK5JR HF multiband vertical & TSB3608 6/2/70cms base antenna. (5 year warranty on IC-706).

PA price £1500.95

DEPOSIT £160.95, 24 PAYMENTS OF £70.85. COST OF LOAN, £360.40.

SG-230 Smarttuner®

Antenna Coupler SSB, AM, CW & DATA


(SG-230 special offer £299.00)

Carr £10.00

You can't buy a smarter tuner than this. An automatic antenna coupler so intelligent it precisely tunes any length antenna - 8 to 80ft - in the HF band.

The Smarttuner® automatically evaluates and switches 64 input and 32 output capacitance combinations, plus 256 inductance combinations in a "pi" network. The amazing result is over a half-million different ways to ensure a perfect match for your transceiver. And the most intelligent feature of all is that the Smarttuner® remembers the chosen frequency and tuning values, and will automatically reselect those values - in less than 10ms, each time you transmit on that frequency.

The SG-230 Smarttuner®. Buy Smart.



SMARTTUNER
INSIDE

ICOM IC-207H 2m/70cm Mobile



- 2m & 70cm
- 50W/30W
- Detachable head
- Packet 9600 bps ready ● 180

memory channels ● CTCSS & 1750Hz tone.

£389.00

IC-207H Deposit £40, 12 payments of £33.00.
 Cost of loan £47.00

ICOM IC-821H



2m/70cms base station (5 year warranty) c/w UT-84 CTCSS, AG-25 2m mast head amp, AG-35

70cms mast head amp & 25 amp PSU.
PA price £1823.95. Deposit £190.95, 36 payments of £64.06. Cost of loan £673.16

KENWOOD TM-V7E



- 144 & 430MHz
- 50/35W ● Dual Rx on same band
- 280 memories
- Detachable front head
- CTCSS & 1750Hz tone

● Large clear display. **£499.00**

TM-V7E Deposit £50, 24 payments of £23.74.
 Cost of loan £120.76

KENWOOD TS-570D

Setting the standard in performance

KENWOOD



Kenwood TS-570D

(5 year warranty), c/w 25 amp PSU, VK5JR HF multiband vertical, VC-6 6m V dipole.

PA price £1699.00

DEPOSIT £170.00.
 36 PAYMENTS OF £59.99.
 COST OF LOAN, £630.64.

AUTHORISED AGENTS FOR KENWOOD, ICOM, YAESU & ALINCO. FULL SERVICE FACILITIES AVAILABLE

SPEND UP TO £1,200 INSTANTLY WITH A PHOTO ACOUSTICS LTD. CREDIT CHARGE CARD
 PART EXCHANGE WELCOME, ASK FOR KERRY G6IZF, Jon or JANE.

RETAIL SHOWROOM OPEN MON - FRI 9.30 - 5.30, (Thursday 9.30 - 12.30) Saturday 9.30 - 4.30

Goods normally despatched within 24 hours. Please allow 7 banking days for cheque clearance. Prices correct at time of going to press - E&OE



Carrying on the Practical Way



*"At Christmas play and
make good cheer"*
(From The farmer's daily
diet by Thomas Tusser)

By George Dobbs G3RJV

*The Rev. George Dobbs
G3RJV says he's got a
few 'Tips & Twinkles'
for Christmas this
time. And along with
providing some useful
ideas and experience
with light-emitting
diodes George
says...it's 'fun
project' time!*

All that time off (for some of you...I'm very busy of course!) - all those old films on television - all those relatives to smile at - all those toys which haven't any batteries - all that food. Is it surprising that the constructor's idea of a good Christmas is to be locked away in the workshop with a full glass and a hot soldering iron.

Some of my best construction projects began on the evening of a Christmas Day. After work of course!

Escaped the family? Closed the door? Switched on the soldering iron? Well here are a few tips and a circuit.

The circuit is by way of a 'peace maker' for the season of good spirit and peace. And when you hear the prompt: "Where have you been"? or "What have you be doing all this time"? the answer can be "I have

been making this for you"!

But first some handy workshop tips to begin a new year at the bench. After you've tidied it up!

Sealing Wax & String

Many years ago I used to keep a supply of waxed string for cable harnessing. Making an harness for loose cable in a project can improve its appearance and help to gain access to the parts on the board.

Why make a neat circuit board and then cover it with a rat's nest of connecting wires? I used to rub wax into normal string and then carefully bind the loose cables, followed by a quick stroke of a hot soldering iron tip across the string melted the wax to keep the cables in place.

I said "used to" because I don't make up wiring harnesses any more. It's far too tedious even for the most tidy-minded builder!

My direct replacement is the use of mini cable ties. Just slip them over

the bundles of cables and pull them tight to have a neat line of cable.

No cable ties? Then try the kitchen for freezer bags grips. The small ones do the job very well. Dustbin bag ties work well for larger bundles of cables.

I have rarely used sealing wax in the workshop itself but a block of beeswax is always on the side of the bench. This is invaluable stuff which I first came to value through the wisdom of Ian Keyser G3ROO.

The dielectric properties of beeswax are good and it's easy to use. I use spots of it to hold items on to circuit boards, especially where stability is important, like in a v.f.o. project.

The wax melts very easily with the tip of a soldering iron and can be dripped on to the required place. The solder iron comes out of it well - the surplus wax just burns off without any problems.

My favourite use of beeswax is securing the windings in home-made




Fig. 1: George Dobbs G3RJV's 'Manx Clothes Peg' idea for producing a useful 'third hand' (see text).




Fig. 2: The modified multivibrator circuit used to provide a flashing l.e.d. novelty circuit.

coils. When the coil is wound, drip a little of the melted wax on the windings.

Then you should gently run the iron along the winding and as the wax melts it runs into the wires to hold them in place. Remember to let the inductor cool before expecting it to be frequency stable.

I have also lightly coated coil formers and toroids with beeswax before making a winding. This helps to hold the wire in place as the coil is wound.

Friendly Hand

One of the more useful small items on an electronics workbench is a 'third hand'. They're really useful because so many of the 'fiddly' jobs associated with the making of electronic circuit boards require manipulation not far short of juggling!

Holding the board, the soldering iron and the solder all at the same time and getting a good joint is not easy. A third hand is very useful!

I have a commercially made 'Third Hand' which consists of a couple of crocodile clips on universal joints, mounted on a heavy base. The work can be held in one, or both of the clip and the operator is free to perform the task.

Before I was bought the useful aid as a Christmas gift (too late to ask for one now?) I had a home-made version. This was a single 'Bulldog' stationery clip (the type you often see attached to 'clipboards' bolted to some stiff wire which was screwed to a heavy wooden block. It worked very well.

'Manx' Clothes Peg

My more recent home-made third hand has been even more useful because it's light and I can carry it around in my tool bag. I call it the 'Manx Clothes

Peg'. In reality it's made up from three clothes pegs mounted on flexible wire in a 'triform' shape similar to the 'Three legged' Isle of Man symbol...hence the name! (The photograph in **Fig. 1.**, shows how my version was made).

Choose three household wooden clothes pegs. It's an advantage if one of the three has a stronger than average grip. Loop over and twist some stiff copper wire - say about 16-18s.w.g.

Next, the looped end is screwed, or bolted, to the clothes peg. The other end, say about 40mm away, is opened up and soldered to the other three peg wires.

Your finished result will be a very useful little tool. The strongest gripping peg can be the anchor - to any convenient place. The other two pegs are the grips for the work.

The stiff wire should be firm enough to hold the job in place for soldering or other tasks. It only takes five minutes to make and can be put with the other tools ready for use.

Circuit To Please

Finally, here's a little circuit to please the family! And isn't it amazing how they misunderstand our intentions?

So often the family, think we are wasting our time, or merely escaping their company. And this belief is amazing because there are so many electronic items about that people love to buy. Yet they do not see any advantage in what we beaver away at in our workshops!

Perhaps if the results did something more interesting in their eyes, they would understand a little more? So, to help overcome the misunderstandings this little circuit, while not exactly a 'cyber pet', might just interest some members of the family!

The circuit is shown in **Fig. 2.**

There's not much to it - and you'll probably recognise the circuit. And of course it's a multivibrator circuit driving I.e.d.s. (in this case six). But what can it do you may ask?

In answering your likely question the circuit does the following: when one transistor is switched 'on', the other is switched 'off'. The 'switched on' transistor will illuminate the I.e.d.s in the respective collector circuit. The end result? - the circuit flashes the I.e.d.s on and off.

But why use **six** I.e.d.s? Answer: quite simply, it's more interesting and appears to be doing more than it really is doing!

Optical Trickery

The best optical trickery is produced by not having the two pairs of three I.e.d.s together. Mounting them so that they alternate between I.e.d.s from each side produces a good effect.

Your project will be quite 'twinkley' - ideal for a Christmas star, or mini bedroom disco effect. Having different coloured I.e.d.s is even better.


My version used all red I.e.d.s in the first model, as shown in **Fig. 3.** but changing these to one red, one green and one yellow per side produced a very pleasing effect. The effect goes far beyond what you might expect for a few I.e.d.s flashing alternately!

Try experimenting with the values for C1 and C2, this will vary the flash rate. Some combinations produce more pleasing effects.

Build it - package it nicely and go and show it to them before they come looking for you. The secret of a Happy Christmas and then you can get busy building more projects for yourself and your gift might encourage more of the family to join us in the hobby!

PW

Fig. 3: The G3RJV prototype I.e.d. project. It can prove amusing, provide useful training and pacify the family!



Amateur Radio Communications Ltd

38 Bridge Street, Earlestown, Newton-le-Willows, Merseyside WA12 9BA

OPEN Tue-Sat
10am-5pm
FREE PARKING

We are the largest stockists of both new and secondhand amateur radio equipment in the north of England – fact not fiction! Our company boasts a full time service department authorised by all the major suppliers. When you buy from us you have complete peace of mind!

HF TRANSCEIVERS



YAESU FT-920

"Easy to use, good RF performance and good value for money", these are just a few of the comments from the recent reviews! Why not see for yourselves. This competitively priced HF transceiver with 6m is available from stock. **£1699 RRP.**

PHONE FOR OUR SPECIAL PRICE!

ALINCO DX-70T

Alinco 10W on 6 meters version of the DX-70TH. CTCSS is fitted as standard. **£695 RRP**



ICOM IC-706 MkII

Icom have again produced the best selling mobile HF Transceiver on the market. Install it in your car, use it as a base station or take it with you on DX'peditions - this set offers versatility that can't be beat. **£1099 RRP. OUR PRICE £989**

ICOM IC-756

The perfect HF-6m all mode transceiver for hams who enjoy chasing rare DX's. Full of functions designed to give you the edge! It is an impressive looking radio, sure to be another Icom winner.

**PHONE NOW FOR OUR CASH PRICE!**

VHF/UHF MOBILES

ALINCO DR-605



Compact dualband receiver.

- ★ 2m & 70cm 50W/35W
- ★ 100 memories
- ★ Full duplex ★ CTSS encoder fitted.

£399.95 RRP

YAESU FT-8100R

The new FT-8100R from Yaesu combines high power and the industry's most versatile memory system with the ease of installation afforded by its remote-head capability. Be a part of the dual-band revolution with the FT-8100R. **£499 RRP.**

**OUR PRICE £449**

KENWOOD TM-V7E



RRP down to £569.95
Phone now for our cash price!
Fast selling dualbander! Now an even better buy than ever before.

USE YOUR CREDIT CARD FOR SAME DAY DISPATCH

VHF/UHF HANDHELDS

ICOM T-7E

Superb dualband handie plus CTCSS. Complete with nicads and charger.
RRP £329.00.

CASH PRICE £299.00

YAESU VX1-R

Smallest ever dualbander, seeing is believing! Already a top seller at ARC.

£269 RRP

ALINCO DJ-G5

A superb twin band handie that comes complete with nicads and charger. Just take a look at its features: ● Up to 5W RF output ● 100 memories ● Over air cloning ● Cross band repeater function ● Spectrum channel display ● Extended receive.

**£299.95 RRP****HP AVAILABLE UP TO 3 YEARS REPAYMENT PERIOD**

ACCESSORIES

POWER SUPPLIES

Watson

W-10A **£49.95**
W-20A **£89.95**

Manson

EP815 15A **£69.95**
EP-925 30 amp **£99.95**

DRAE

24amp PSU **£119.95**

Masts

Extends to 36'6" **£52.00**
Extends to 27'6" **£45.00**

Extends to 17'6" **£34.00**
D/Band mobile antennas from **£21.95**

D/Band verticals from **£39.95**
Magmounts **£16.95**

Duplexers **£26.95**
HF mobile antenna **£49.95**

(WHAT YOU WANT WE HAVE OR CAN GET!)

Packet terminals

PK-232MBX **£319.95**
TNC-2M 9K6 boxed **£179.00**

KAM plus **£395.00**

DSP-232



Including FREE Windows software worth £79.00. The latest all mode DSP driven TNC from AEA.

SPECIAL OFFER PRICE £465.00 cash/cheq**Tel: 01925 229881/Fax: 01925 229882**

PW PCB SERVICE

PRACTICAL WIRELESS PCB SERVICE

Printed Circuit Boards for *Practical Wireless* constructional projects are available from the Practical Wireless PCB Service.

The boards are made in 1.5mm glass-fibre and are fully tinned and drilled.

When ordering PCB's please state the article title, magazine cover date and the board number.

Mark your envelope **Practical Wireless PCB Service.**

Cheques to be crossed and made payable to: **Badger Boards.**

Please print your full name and address in block capitals and do not enclose any other *Practical Wireless* correspondence with your order. Please allow 28 days for delivery.

Send orders and remittances to:

**Badger Boards, 87 Blackberry Lane, Four Oaks,
Sutton Coldfield B74 4JF. Tel: 0956 374918**

ORDER FORM FOR CLASSIFIED ADS PLEASE WRITE IN BLOCK CAPITALS

The prepaid rate for classified advertisements is 42 pence per word (minimum 12 words), box number 70p extra. Semi-display setting £13.90 per single column centimetre (minimum 3cm). Please add 17.5% VAT to the total. All cheques, postal orders, etc., to be made payable to PW Publishing Ltd. Advertisements, together with remittance, should be sent to the Classified Advertisement Dept., Practical Wireless, Arrowsmith Court, Station Approach, Broadstone, Dorset BH18 8PW. Tel: (01202) 659920, Fax: (01202) 659950

Please insert this advertisement in the issue of Practical Wireless (if you do not specify an issue we will insert it in the next available issue of PW) for insertion/s. I enclose Cheque/P.O. for £..... (42p per word, 12 minimum, please add 17.5% VAT to total).

Name:

Address:

Telephone No.:

Box Number @ 70p: Tick if appropriate ☐

Category heading:

MULTICOMM 2000

WORLDWIDE MAIL ORDER
LARGE SHOWROOM BEST PRICES

LOOKING FOR ALINCO?

Get on the 6 metre repeaters with the new



Alinco DR-M06
10 watt FM mobile ~~£249.95~~



Alinco DX70T
All mode HF + 6 ~~£695.00~~

Multicomm 2000 are ALINCO specialists
Here's a selection of our stock

HANDHELDS

DJ-190E	2mtr h/h Tx + nicad & chgr.	£149.95
DJ-191E	2mtr h/h Tx + nicad & chgr.	£169.95
DJ-G5EY	Dual band h/h Tx	£299.95
DJ-S41C	UHF 340Mw h/h Tx	£129.95
DJ-S11E	VHF 140Mw h/h Tx	£99.95

MOBILES

DR-140E	2mtr 50W mobile FM Tx	£249.95
DR-150E	2mtr 50W mobile Tx + chs	£279.95
DR-430E	70cm 35W mobile FM Tx	£259.95
DR-610E	Dual band 50W mobile Tx	£525.00
DR-605F	Dual band mobile Tx	£399.95

TUNERS

EDX-1	Manual ATU for DX-70	£159.95
EDX-2	120W automatic ATU	£289.95

HF TRANSCEIVERS

DX-70T	10 band HF + 6mtr mobile	£695.00
DX-70TH	100 watt version of above	£775.00



Call this
number
NOW!

(01480)
406770

We guarantee:

- Best stocks
- Best P/X deal
- Best prices
- Fast deliveries

LOOKING FOR A RECEIVER?

AOR

AOR AR 8000
£295.00



AOR AR 7030
£689.00



AOR AR 5000
£1299.00



AOR
3000A
£699.00



AOR
3000A+
£759.00



JRC NRD-535D
Superb De-luxe Short Wave Receiver
£1499.00



DRAKE
SW-2 **£449.00**



STANDARD
AX700 MkII **£389.00**



ICOM
IC-R8500 **£1399.00**



JRC
NRD-345 **£699.00**



YAESU
FRG-100 **£459.00**



BEARCAT
9000-XLT **£259.00**

YUPITERU

MVT-9000
£355.00



MVT-7200
£315.00



MVT-7100
£220.00



MVT-7000
£210.00



VT-225
£225.00



SALES HOTLINE 01480 406770

★ USED EQUIPMENT ALWAYS WANTED
★ GUARANTEED TOP PRICES

LOOKING FOR ICOM?



IC-207H
2 + 70 mobile with
detachable head
£ 3



IC-706 MkII
We have this latest model in
stock now.
100 watts on HF + 6 and a full 20
watts on 2 meters. *We are offering
this set at an incredible price*
£



IC-756
This is our favourite rig. HF + 6
and fully featured. What a winner.
Clear LCD display with bandscope
and DSP. *Our very special price*
£ 1



IC-821H
The most advanced 2 + 70
base available
£

LOOKING FOR YAESU OR KENWOOD?



TS-570D
Kenwood's latest offering.
Full HF, DSP transceiver.
Special price



FT-1000MP
Super de-luxe transceiver
DC - £1989.00
AC - £2199.00



FT-920
Yaesu's latest HF + 6mtr base DSP transceiver
£ 1 4 4

LOOKING FOR ACCESSORIES?

CUSHCRAFT R-7000

HF vertical
£315.00



WMM1 Decoder.
Great value **£69.00**



TIMEWAVE DSP 599ZX
DSP Filter **£325.00**



MFJ 784B DSP filter
Special price **£225.00**



MFJ 969 HF + 6MTR
ATU Roller coaster
£189.00

DIAMOND CP-6

HF plus 6 metres
vertical **£220.00**



MFJ 949 ATU
Our most popular ATU **£139.00**




MIRAGE VHF/UHF linear
35/40W out **£135.00**

FOR OUR USED PRICE LIST ... SEE THE "TRADERS' TABLE"

****WE NEED YOUR USED EQUIPMENT****
TOP PRICES PAID...GUARANTEED !!!!
LET US SELL YOUR EQUIPMENT FOR YOU

UNIT 3, 86 CAMBRIDGE STREET, ST. NEOTS, CAMBS PE19 1PJ
SALES HOTLINE: 01480 406770 **FAX: 01480-356192**
EMAIL: Sales@multicomm2000.com **WEBSITE: www.multicomm2000.com**





Valve & Vintage

By Phil Cadman G4JCP

It's Phil Cadman G4JCP's turn to look after the vintage 'wireless shop'. This month he looks back at recent history as it was received by radio, ideas for Christmas, 'transmissions' from Bulgaria and Sri Lanka and finding the right knobs!

Over the years, radio and TV receivers have carried news and images of momentous events. Such it was in the early hours of Sunday, 31 August 1997, with news of the death of Diana, Princess of Wales. How many of you, like me, will now forever associate the news of that tragic event with one particular radio?

We tend to cherish our vintage radios as simply items of electronic equipment. Too often we forget why the sets were built, the news they carried, and the tears and laughter they generated in their audiences.

So, next time you see a forlorn old radio set, think of the events it may have told of and the people who might have listened so intently. You're looking at a bit of history that helped spread news which became history!

Christmas Is Coming!

On a brighter note, you may have noticed that Christmas is coming...and will soon be here! So, to help anyone who is having trouble I thought I'd mention a few books which might make ideal Christmas presents for the 'thermionically' inclined.

To begin, there are two really excellent books I haven't mentioned

before that are now available from the PW Book Store. Both are American volumes that have recently been reprinted by Lindsay Publications Inc. of Illinois.

The first is *The 1934 Official Short Wave Radio Manual* edited by Hugo Gernsback. The first half is mainly made up of constructional articles about short wave receivers. There are also a few articles of a more general nature, including one entitled 'Can We Radio the Planets?' (Yes, 'moonbounce' was being seriously talked about way back in 1934!).

The remainder of the book is a directory of (supposedly) all the commercial short wave receivers available in the USA at the time. There's also a 'sort-of' radio servicing guide, and each receiver has at least its circuit diagram reproduced and most have servicing information included too. This section is extremely useful for anyone interested in early commercial receivers.

The second book - *Henley's 222 Radio Circuit Designs* - was originally published in 1923. It has chapters on tuning, antennas, crystal sets, regenerative detectors, audio amplifiers and transmitters.

What interested me were two circuits of very early superheterodyne receivers. Because only triode valves were available the intermediate frequency had to be very low. One circuit even uses resistance-capacitance, as opposed to transformer, interstage coupling.

Still very much available and ideal stocking-fillers are the *RCA and General Electric Valve Manual* reprints. And don't forget the set of five

Radio Valve Guide Books, nor *The Handbook of Radio, TV, Industrial & Transmitting Tube & Valve Equivalents*. This last reprint is particularly useful to anyone with an interest in Military equipment, as it gives the commercial equivalents of both the British and American Services valve types and the CV series.

I recently got a copy of *Shortwave Receivers Past & Present* (second edition) by Fred Osterman. This is published by Universal Radio Research of Ohio (also available from the PW Book Store). *Shortwave Receivers Past & Present* is an extensive guide to over 500 amateur and commercial shortwave receivers that were manufactured between 1945 to 1996. Most of the receivers are from the USA although there are also some from Japan and the UK.


Each set featured has a photograph together with brief details about its specification, variants, reviews, cost and the period during which the receiver was available new. Most receivers have a second-hand (American) guide-price included. I'd recommend this book to any serious collector of short wave receivers, particularly to those whose primary interest lies with American receivers.

Finally, don't forget *Radio! Radio!* by Jonathan Hill. This popular book is now into its third edition and has been substantially expanded over the previous edition. The only problem is the price - (have a large brandy at the ready now!) - at around £35. I know this is regarded as one of the very best vintage radio books but it does alarm me when prices reach this level.

Those of you with deep pockets can

PAST & PRESENT

Communications Receivers 1945-1996



Second Edition


By Fred Osterman

Collective Noun?

Is there a collective noun for valve and vintage radio enthusiasts? And if there isn't, who's got any ideas? **Editor's suggestion:** How about a 'Pounce' of vintage collectors Phil, especially as I've seen some in 'action'?

And while on the subject of vintage radio devotees, there are, apparently, television enthusiasts who still hark back to the good-old 405-line days. Still reeling from the shock of finding that 405-line transmissions are no longer broadcast, they can now be found reminiscing within the pages of the magazine *405 Alive*.

Seriously though, for anyone with an interest in vintage television sets, subscribing to *405 Alive* could be a very sensible, even therapeutic, thing to do. Details can be obtained by sending an s.a.s.e. to: **Admin. Office, The Radiophile, 'Larkhill', Newport Road, Woodseaves, Stafford ST20 0NP.** Alternatively, a cheque or postal order for £4 made out to *The Radiophile* will get you a sample copy of the magazine.



obtain
Radio! Radio! from G C Arnold Partners, Telephone (01202) 658474 or send an s.a.s.e. to G C Arnold Partners, 9 Wetherby Close, Broadstone, Dorset BH18 8JB, for details. You might also find it in the larger book stores.

Restoration Topics

A couple of subjects relating to the restoration of old radios have arisen since I wrote my last column. The first concerns loudspeakers and that's my next topic.

In some cases, particularly if a radio has been kept in damp conditions, the loudspeaker cone and its support may have badly deteriorated. Alternatively, the voice-coil may be open-circuit or jammed solid due to the pole-pieces having rusted.

When the original loudspeaker is not easily repairable the question arises as to what to do. And although it is possible to re-cone the original loudspeaker the cost involved is hardly justified in the majority of cases.

The only realistic option is to replace the original loudspeaker with another. This is one reason why you ought never to simply throw away a perfectly good loudspeaker. You - or someone else - might well need it one day!

When replacing a loudspeaker please bear in mind the following points: Firstly there's physical size. If you have to obtain a new unit, double-check not only the diameter and location of any fixing holes but also the depth.

Impedance: The original loudspeaker will almost certainly have an impedance of 3Ω. Unfortunately new 3Ω units are next to impossible to get hold of,

so you'll probably be stuck with either a 4 or 8Ω unit. (A 4Ω loudspeaker will be okay but even these are now getting scarce other than those intended for in-car use).

Please don't be tempted to use an 8Ω loudspeaker 'as-is'. This is because an 8Ω unit will load the output stage too lightly and so lead to higher a.c. voltages being developed in the anode circuit of the output valve.

At high volumes the excess voltage may cause any capacitor across the primary of the output transformer to break down. Worse still, the insulation on the primary winding of the output transformer could also break down necessitating its replacement as well.

If you do have to use an 8Ω loudspeaker then either use a matching auto-transformer (if you can find one) or else connect a 10Ω, 2W (minimum) resistor across the loudspeaker terminals. This additional load should prevent any damage should the volume control be accidentally turned-up too high. **Note: Adding this resistor is particularly important if you're forced to use a relatively insensitive hi-fi loudspeaker.**

Field coil: When replacing a field-coil type loudspeaker with a permanent magnet type do remember to substitute a choke with approximately the same resistance to replace the field coil. The inductance isn't critical but try for 5H (Five Henries) as a minimum. The choke should, of course, be rated to take the full h.t. current. If you don't have a choke then use a high-wattage resistor instead.

Restoration Knobs

My second restoration topic has knobs on. Or rather, doesn't! Here I'm echoing comments made by Tudor Gwilliam-Rees in issue 159 of *The Antique Wireless Newsheet*. (This is published by Savoy Hill Publications - see the classified advertisements at the back of *PW* for the address.)

When a control knob belonging to an otherwise perfectly restorable radio has been either lost or broken it often proves impossible to replace. It's easy enough to pop on any old knob that'll fit but that's hardly playing the game.

What we need is a 'Control Knob Bank'. Don't laugh, apparently there is a real need for

Vintage In Bulgaria

I'm pleased to announce that this column has interested another vintage radio enthusiast, and it's someone who lives in Bulgaria. Back in March, Stiliyan Stankov from Sofia sent me an E-mail telling of how he was growing tired of computers and now intended to collect old radios.

After only six months Stiliyan has already collected eight sets (**stop press news:** as of September 24 he's amassed 13 sets and still within the six months of starting!) and is beginning to suffer from that bane of vintage radio collectors - where to keep the things! Well Stiliyan...you've really caught this vintage collecting 'bug' badly haven't you?

Here in the UK (and, of course, in the USA) there are specialist suppliers, groups and magazines that cater for vintage radio enthusiasts. However, enthusiasts in many other countries are far less fortunate than we. Even if sets are available getting information and spares may be difficult. Also, if the country has no appropriate indigenous magazine through which enthusiasts can readily communicate then the situation is made even worse.

An unlikely country in which to find a supplier of vintage bits and pieces would seem to be Sri Lanka. Yet 'Shackway', located at 67 Church Road, Kandana, Sri Lanka, does supply valves and vintage components as well as public address equipment, radio components and hardware. Their valve catalogue lists many vintage (and not so vintage) British and American valve types.

More than once I've been asked by overseas readers of *Practical Wireless* about where they can obtain components and information. Clearly, if I can indicate a source geographically close to them then that's usually a help. Also, some countries have restrictions when it comes to international currency movements and the import of goods.

With foreign based readers in mind, I'd be pleased to hear from any supplier of valves, vintage radio components and information from outside the UK and USA that I can mention in this column. And in a similar vein, I'd like to hear from readers who are resident outside the UK and USA!

What problems do you have in the pursuit of your hobby? And do you have difficulty finding others within your own country who share your interests?

I also want to hear from UK and USA readers. Tell me what valve and vintage topics interest you. Significantly, I haven't, as yet, received a letter from a lady vintage radio collector. Is this a male-only pursuit, I wonder?

something like this!

So, I ask you that for now, please keep all your 'orphaned' control knobs safe and, most important, labelled with their manufacturer, model number and function. The same applies to those irreplaceable old dial scales.

I would also like to include aerial and oscillator coils, intermediate frequency transformers and power and output transformers in any such spares bank. In fact the list could be endless!

The Epilogue

Ah, I see it's almost time for the Epilogue so, until it's my turn 'in the shop' again, I'll say cheerio and wish you all a very Merry Christmas and a happy and prosperous New Year.

Remember to send your comments and letters to me either via the PW offices, via E-mail to phil@oldpark.demon.co.uk or direct to: Phil Cadman G4JCP, 21 Scotts Green Close, Scotts Green, Dudley, West Midlands DY1 2DX.



Cheerio from Phil, see you in March.

Due to the fast turn around of popular secondhand items, readers should check on availability of advertised stock. In other words...if you spot something you fancy...don't delay or you could miss it!

Traders

YOUR GUIDE TO SECOND-HAND EQUIPMENT

WATERS & STANTON

01702 206835

PLEASE NOTE SECONDHAND ITEMS COME WITH FULL 3 MONTH PARTS & LABOUR GUARANTEE. FOR MORE INFORMATION PHONE ANDY TIETJEN 01702-206835 OR FAX 01702-205843.

HF TRANSCEIVERS
KENWOOD TS-930S HF base station transceiver £750
KENWOOD TS-430S HF base station transceiver £379
TENTEC SCOUT 555 HF mobile transceiver with 80m & 40m modules £379
TRIO TS-940SAT HF base station inc built in ATU £1199
YAESU FT-767GX HF base station £729

VHF/UHF TRANSCEIVERS MOBILE / BASE STATION

ICOM IC-260E 2m all mode transceiver £199
KENWOOD TS-711E 2m all mode transceiver £595
KENWOOD TM-241E 2m mobile transceiver £225
YAESU FT-290RX1 2m all mode portable transceiver £199
YAESU FT-8500 2m/70cms mobile transceiver £499

VHF/UHF TRANSCEIVERS HANDHELDS

ALINCO DJ-500E 2m/70cms handheld transceiver £179
ICOM IC-T42E 70cms handheld transceiver £189
ICOM IC-W21EX3 2m/70cms handheld with dry cell cases £199
ICOM IC-M11 VHF Marine handheld transceiver £219
KENWOOD TH-28E 2m handheld transceiver £199
YAESU FT-411 2m handheld transceiver £109

SHORTWAVE RECEIVERS

AKD HF3M Base station receiver inc weather fax £139
DRAKE R8E Base station receiver (PSALE) £695
DRAKE R8E Base station receiver £695
GRUNDIG VHF-206 Portable shortwave receiver £79
LOWE HF-150 High specification HF receiver £279
PANASONIC RFB-65 Portable shortwave receiver with SSB £109
SANGEAN ATS-803A Portable shortwave receiver with ATU (PSALE) £80
SONY ICF-SW100EX2 Portable shortwave receiver inc SSB + FM stereo £149
YAESU FRG-7700 Base station HF receiver with memory unit £329

SCANNERS MOBILE / BASE

AOR AR-2002 25-55MHz, 800-1300MHz Base scanner (PSale) £189
REALISTIC PRO-2039 66-88, 108-174, 380-512, 806-960MHz £129
REALISTIC PRO-2032 Base scanner 68-960MHz with gaps £129
YAESU FRG-9600 60-903MHz all mode base receiver £269

SCANNERS HANDHELD

AOR AR-1000x2 8-600MHz, 805-1300MHz AM/FM/PMW £99
COMMITEL COM204 68-999MHz with gaps £129
FAIRMATE HP-2000E 0.5 - 1300MHz AM/FM/PMW £139
REALISTIC PRO-31 66-512MHz with gaps £59
SONY PRO-80 x3 HF receiver £139
SIGNAL R-537S Airband receiver £35
WIN 108 Dedicated airband receiver £109
YUPITERU MVT-5000x2 25-550, 805-1300MHz FM/AM £99

LOWE ELECTRONICS

01629 580800

HF TRANSCEIVERS
Icom IC 706 Mk1 HF transceiver with 2m and 6m £650
Icom IC 728 HF transceiver £550
JST135 HF Transceiver £975
Kenwood TS50 Mobile HF Transceiver £550
Kenwood TS530S HF Transceiver £495
Kenwood TS820 HF Transceiver £395
Yaesu FT747GX HF Transceiver £400

DATACOMMS

Kantronics KAM Multimode TNC £185

VHF/UHF TRANSCEIVERS

Alinco DJ500E Dual Band Handheld £249
Alinco DJ560 Dual Band Handheld £199.00
Alinco DR599 Dual Band Mobile £425.00
Icom IC24ET Dual Band Handheld £269
Icom ICW2E Dual Band Handheld £249
Kenwood TH205E 2m Handheld £159
Kenwood TH78E Dual Band Handheld £290
Kenwood TM732E Dual Band Mobile / detachable front panel £380
Kenwood TR2500 2m Handheld £140
Yaesu FT290R 2m Multimode £250.00
Yaesu FT470R Dual Band Handheld £259
Yaesu FT2200 2m FM Mobile £289
Yaesu FT4700RH Dual Band Mobile with detachable front £375

HF RECEIVERS

Low HF225 HF Receiver with all accessories £345
Low HF225 Europa HF Receiver £450
Sony ICF5W55 World band Portable £229
Low HF150 Portable HF Receiver £295
Grundig YB217 Portable receiver £95

SCANNERS

AOR AR1000 Handheld £169
AOR AR2001 Base Scanner without PSU £159
AOR AR2700 Handheld Scanner £160
AOR AR2800 Base Scanner with SSB £195
Icom ICR1 Handheld Scanner £199
Yupiteru MVT7000 Handheld Scanner £200
Yupiteru MVT7100 Handheld Scanner £225
Yupiteru VT225 Airband Scanner £180
Yupiteru VT125 Airband Scanner £150
Yupiteru MVT5000 Handheld Scanner £180

Items are held at various branches, please contact our Matlock branch for further details on 01629 580 800

SOUTH EAST COMMUNICATIONS

(REP OF IRELAND)
00353 51 871278

HF TRANSCEIVERS:

Kenwood TS850sat with extra filters £1195
Kenwood TS570D latest DSP, ATU £1095
Yaesu FT1000MP/DC demo £1899
Icom IC735 with matching PSU £699
Icom IC737A auto ATU etc £899
Alinco DX70, HF mobile+6m, mint £575
FT990DC boxed mint, auto ATU £1099
Yaesu FT840 with FC-10 auto ATU £749

VHF/UHF TRANSCEIVERS:

Kenwood TM702E 2m/70cms 25 watt mobile £299
Alinco DR590E 2m/70cms mobile, 45/35 watts £249
Yaesu FT3000M 70 watt 2m £299
Yaesu FT51R Top spec handheld £299
Yaesu FT50R 2m/70cms mil spec handi £199
ADI 146 50watt 2m demo £219
Kenwood TH78E 2m/70cms handi £249

SHORTWAVE RECEIVERS:

Yaesu FRG8800 0-30mhz, mint £349
Yaesu FRG7700 0-30mhz, mint £289
Low HF225 plus FM, and keypad,boxed £349
Low HF150 inc keypad boxed £299
Realistic DX394 boxed as new £169
Sony SW55 as new, bargain £199
Sony PRO80 0-225mhz ssb £199
Sangean ATS 818 portable receiver £129

SCANNERS BASE/MOBILE:

AOR 5000 500khz-2.6GHZ boxed mint £1099
AOR 3000 0-2036mhz £400 memories £499
Icom ICR7000 25-2000mhz £699
AOR 3000A demo £699
Realistic PRO 2035, £1000 memories £299
AOR 8000 0-1900mhz boxed etc £269
Yupiteru MVT 7100 0-1650mhz £199
Bearcat 3000XLT 25-1300mhz £169
AOR 2000 0-1300mhz £179
Icom ICR10 latest hand held £249

STATION ACCESSORIES

Diamond DL 1000 dummy load £109
Diamond SX 100 3kw SWR/PWR £79
Yaesu MD-1 desk mic £69
Yaesu MB 100AX desk mic £89
Vectronics VC300DLP 300watt tuner £99
MFJ 948E 300watt tuner mint £89
Timewave DSP-59plus £149
Icom PS-55 20amp PSU £129
OPTO 3300 freq finder £89
MFJ 259 antenna analyzer £189

NEVADA

01705 662145

AMP UK HUNTER 600W £925
ALINCO DJ-S41C - 70cms £89
ALINCO G-5 Handie £235
AOR 3000 £495
AOR 3000A £575
AOR 7030 £599
BNOS 160W 2m Amp £199
DAIWA PS304 II - PSU £99
DRAE 24A PSU £79
DRAKE R8A £825
DRAKE R8E £750
ICOM IC-725 £595
ICOM IC-W2E £199
ICOM IC-706 £675
ICOM IC-728 £629
ICOM R-71 + HF £575
ICOM R-72 £675
ICOM IC-2400 TWINBAND £335
ICOM IC-7000 £595
JIL 400 BASE £185
JST 100 COMPLETE £499
KENWOOD TH-215E £145
KENWOOD TM-241E £225
KENWOOD TM-451E £299
KENWOOD TR-751E £425
KENWOOD TS-440s £525
KENWOOD TS-680s HF+6m £625
KENWOOD TS-930 BASE £599
KENWOOD TS-940S £899
KENWOOD TS-850 SAT £1299
LOWE AP 150 £155
LOWE HF 225 + Extras £425
MIRAGE B3016 2M AMP £245
PALSTAR KH6 + Extras £139
PHILLIPS D2999PL RX £135
RACAL RA17 £139
REALISTIC 2036 £179
REALISTIC PRO-50 £69
SANGEAN ATS-803A £85
SATCOM P40 (PAIR) £149
SENTEC 20M HANDIE £195
SONY SW77 RX £249
STANDARD C500 £185
STANDARD C8800 £189
TARGET HF3 RX £130
TEN TEC OMNI VI S.O.B. £1999
TIMEWAVE DSPs from £99
TOKYO HC-200 ATU £99
TOKYO HL-1KGX AMP £799
TRIO AT-200 ATU £175
TRIO AT-230 ATU £189
TRIO 120V 10W HF £259
TRIO 120S 100W HF £325
W9-GR DSP II £185
YAESU FL-110 HF Amp 100W £169
YAESU FP-707 20A PSU £139
YAESU FRG 9600 £379
YAESU FT-11R £169
YAESU FT-107M 100W £425
YAESU FT-208 + EXTRAS £179
YAESU FT-221R 2m BASE £299
YAESU FT-290 I £245
YAESU FT-290 II £325
YAESU FT-411 + EXTRAS £189
YAESU FT-470 + ACCS £225
YAESU FT-650 24-54MHZ £699
YAESU FT-707 £349
YAESU FT-727 £169
YAESU FT-747 FM £475
YAESU FT-757 AT £225
YAESU FT-900 AT £825
YAESU FT-990 DC as new £1249
YUPITERU MVT 7100 £215
6M Transverter 20W £75

MULTICOMM 2000

01480 406770

HF TRANSCEIVERS
ICOM IC-706 MK-1 HF / VHF TRANSCEIVER £675
ICOM IC-765 DELUXE HF TRANSCEIVER £1,100
ICOM IC-775DSP (8-MONTHS OLD) "THE BEST" £2,225
KENWOOD TS-440SAT GOOD CONDITION £649
KENWOOD TS-690SAT HF TRANSCEIVER + 6M £925
KENWOOD TS850SAT GOOD CONDITION £875
KENWOOD TS850SAT AS NEW CW FILTERS £950
KENWOOD TS-940 SAT WITH LOWE MODS (MINT) £1,050
KENWOOD TS-950SD THE ULTIMATE TRANSCEIVER £1,499
TENTEC OMNI 6 (COMPLETE) MINT CONDITION £995
YAESU FR-200B/FL-200B (PAIR) £125
YAESU FT-1000 MP AC (EX-DEMO) £1,875
YAESU FT-101B HF (GOOD CONDITION) £160
YAESU FT-101E (MINT CONDITION) CLASSIC £195
YAESU FT-101ZD (MINT) £269
YAESU FT-747GX "AS NEW" + FM £410
YAESU FT-747GX MINT CONDITION + FM £399
YAESU FT-840 GENERAL COVERAGE TRANSCEIVER £599
YAESU FT-840 GENERAL COVERAGE TRANSCEIVER £625
YAESU FT-900SAT (EX-DEMO) £875
VHF/UHF TRANSCEIVERS
AKD 6001 + REPEATER MODULE £149
FT-51 DUAL BAND HANDIE £265
ICOM IC-207H (EX-DEMO) £340
ICOM IC-290E 2-METER MULTI-MODE 25W £249
ICOM ICT-7E DUAL BAND HAND HELD (MINT) £205
ICOM ICV-200T 2-METER MOBILE £129
KENWOOD TH-79E HAND HELD £299
KENWOOD TM-741E 6/270 (EX-DEMO) £525
KENWOOD TM-751E 6/270 (EX-DEMO) £399
KENWOOD TR-751E 2-METER MULTIMODE £375
STANDARD C-156 2-METER HAND HELD (EX-DEMO) £125
STANDARD C-7800 70CMS MOBILE £120
YAESU FT-211 2-METER MOBILE £185
YAESU FT-221R 2-MTR BASE MULTIMODE £259
YAESU FT-290R MK-1 "GREAT" 2-MTR PORTABLE £210
YAESU FT-290R MK-2 2-MTR MULTIMODE £289
YAESU FT-290R MK2 2-MTR MULTIMODE £289
YAESU FT-3000M (3-WEEKS OLD) £335
YAESU FT-726 26/70CM BASE (MINT) £629
SHORT-WAVE RECEIVERS
AKD HF-3 (4 WEEKS OLD) £129
AOR AR-3030 BOXED (AS NEW) £399
ICOM ICR-71E FULLY LOADED £569
ICOM ICR-72E SHORT-WAVE RECEIVER £550
KENWOOD R-5000 DELUXE SHORT-WAVE RECEIVER £659
KENWOOD R-5000 DELUXE SHORT-WAVE RECEIVER £599
KENWOOD R-5000 DELUXE SHORT-WAVE RECEIVER £579
LOWE HF-225 GENERAL COVERAGE RECEIVER £319
PANASONIC RFB-10 £49
RACAL 1792 EX-GHQ RECEIVER £679
REALISTIC DX-394 (AS NEW) £195
TRIO R-600 (GREAT CONDITION) £215

PLEASE MENTION TRADERS' TABLE WHEN ENQUIRING ABOUT ANY ITEMS ON THESE PAGES!

Traders' Table

YOUR GUIDE TO SECOND-HAND EQUIPMENT

ARC EARLESTOWN 01925 229881

HF TRANSCEIVERS	
Yaesu FT-900AT - boxed	£950
2 x Icom IC-765 plus speaker	from £1500
2 x Yaesu FT-757GX1 + boxed	£TEL
Yaesu FT-980	£799
Yaesu FT-102 + FC-102	£475
Yaesu FT-101ZD MkIII + FC-902/FCV-901R incl 2m/6m	£799
Icom IC-735 boxed	£525
Yaesu FT-902DM + SP-901/SPC-300 ATU	£499
Yaesu FT-747 + FC-700 boxed	£TEL
Kenwood TS-830M +	£375
Yaesu FT-102	£375
Yaesu FT-101Z	£299
Yaesu FT-902	£250

MOBILE/BASE VHF/UHF TRANSCEIVERS	
Kenwood TS-700S	£450
Kenwood TM-742 + 10m module as new	£625
Icom IC-229 - boxed	£225
Icom IC-290D	£300
Kenwood TM-255E boxed VGC	£TEL
Yaesu FT-230	£175
Kenwood TW-4000 boxed	£225
Icom IC-271H + 100W internal PSU	£550
Icom IC-2410H boxed	£TEL
Yaesu FT-790R + linear	£TEL
2 x FT-290R1	from £200

RECEIVERS/SCANNERS	
Icom IC-R7000	£700
ICOM IC-R71E boxed	£599
2 x Kenwood R-1000 boxed	£250
Regency MX-7000	£TEL
AR-2500	£275
Drake R-8E	£699
2 x Lowe HF-225	from £275
Sony PRO-80	£150
Yaesu FRG-9600 - HF converter	£350
Yaesu FRG-7	£140
Icom IC-R7100 boxed	£TEL
2 x AOR AR-3000A	from £550
Sony SW-55 mint condition	£TEL
AOR AR-2800 boxed	£199
Grundig Satellite 500 + IC-FAX 1/Datong AD-270	£175

HANDHELDS	
Kenpro KT-22	£80
Alinco DJ-160	£150
Kenwood TH-21	£99
Icom IC-4E	£115
Standard C-528 boxed	£199
Standard C-558 boxed	£225

MISC.	
SDU-5000 Spectrum Display Unit - as new	£599
AT-230 - box	£175
MFJ-1278 Packet Unit + Software	£225
Datong ASP (wired for Kenwood)	£50
MML-144 - 100-3 + boxed	£TEL
Tokyo HL-160V linear	£175
Icom SP-20 speaker	£75

SHORTWAVE SHOP 01202 490099

HF TRANSCEIVERS	
Icom IC751 - 100W HF	£545
Icom IC725 inc AT150 - VGC	£645
Icom IC706 HF 6m and 2m Mobile	£625
Kenwood TS950SDX - The Ultimate HF Set	£1,995
Kenwood TS-850S inc ATU - Mint	£895
Kenwood TS-880S - HF & 6m	£695
Kenwood TS-570D - Latest HF with DSP	£1,050
Kenwood TS-140S - 100W HF	£525
Kenwood TS-120S - 100W HF	£295
Racal Synical - 10W HF with Handset	
Trio TS530SP - 100W HF	£375
Trio TS530SP - 100W HF Narrow CW Filter	£395
Trio TS120V - 10W HF - Ideal Novice Set	£275
Yaesu FT990 - AC PSU & ATU	£1,150

VHF/UHF	
Alinco DR510 - 2m/70cm Mobile LED Display	£275
Icom IC215 - 2m Channelised FM	£85
Icom IC2E 2m Thumbwheel H/Held	£75
Icom IC02A - No 1750Hz	£85
Kenwood TH22E - 2m H/Held c/w Keypad	£185
Kenwood TS711E 2m Multimode Base	£525
Kenwood TM733 - 2m/7cm Mobile	£399
Trio TR9130 2m Multimode Boxed	£350
Yaesu FT290R11 2m M/mode Mobile	£325

RECEIVERS	
AOR 7030 Acclaimed HF RX - Ex Demo	£645
Eddystone EC10 - General Coverage RX	£85
Icom R71E - General Coverage Receiver - Mint	£495
Icom ICR72 - General Coverage RX	£595
JIL SX400 - Base Scanner - Mint	£165
JRC NRDS25 with VHF and UHF	£595
Lowe ?125 - ? Gen Cov RX	£225
Lowe HF-150 - HF Gen Cov RX - Mint	£325
Realistic PRO-2036 - 400Ch Scanner (Choice of Two)	from £165
Signal R532 - Airband Receiver	£135
Sony Air7 Air and Marine Rec (Choice of Two)	from £145
Sony ICF PRO80 - SW and FM Broadcast	£135
Yaesu FRG8800 with VHF (Choice of Two)	£495
Yaesu FRG7700 - General Coverage RX	£295

MISCELLANEOUS	
Capco 1KW ATU	£125
Diawa CNA1001 - Auto ATU	£145
Diawa AP-606K Active Filter Unit	£85
Diawa PS30411 - 30A PSU	£95
Emotator 105TS - Heavy Duty Rotator - VGC	£185
Global AT2000 - RX ATU - New - No Box	£85
Icom PS15 - Matching PSU (IC745, IC751, etc)	£125
Kantronics KAM - Multimode TNC	£165
Kantronics SP950 - Deluxe Matching Speaker	£85
Kenwood PS31 - Matching PSU (850, etc)	£125
MFJ 407B - Keyer	£49
MFJ 259 Twin Meter Aerial Analyser with case	£195
Microset R432-90 - 90W 70cm Amplifier	£349
Optoelectronics 3300 - Frequency Counter	£100
Optoelectronics 3000A - Frequency Counter	£120
Tokyo Hy-power HC400L Deluxe ATU	£145
Tokyo Hy-Power HC240 - 2m HF Transverter	£145
Yaesu G500A Elevation Unit - VGC	£165
Yaesu G250 Rotator	£85

Please call for our latest used equipment list and details of our Sell-On-Behalf Scheme.

PHOTO ACOUSTICS 01908 610625

RECEIVERS	
Yaesu FRG-7 Receiver	£110.00
NRD-525 Receiver	£599.00
Lowe HF-250 Receiver c/w FM/AMS & speaker	£399.00
AOR-3030 Receiver	£425.00
Kenwood R5000 Receiver	£575.00
Realistic DX-394 Receiver	£189.00
Icom IC-R70 Receiver	£429.00
Lowe HF-225 Receiver	£329.00

SCANNERS	
AOR-3000 wideband scanner	£499.00
Icom IC-R7100 wideband receiver	£799.00
AOR-1500 Handheld scanner	£169.00

HF TRANSCEIVERS	
Kenwood TS-850S	£949.00
Icom IC-720A c/w PSU	£479.00
Yaesu FT-890AT	£639.00
Yaesu FT-102	£399.00
Icom IC-735	£549.00
Icom IC-745	£450.00
Icom IC-751	£589.00
Yaesu FT-757GX	£499.00
Icom IC-725	£499.00
Kenwood TS-680S HF + 6M	£649.00
Icom IC-745 (mains powered)	£489.00

VHF/UHF	
Yaesu FT-4700 dualband mobile	£279.00
Kenwood TM-733E dualband mobile	£399.00
Kenwood TM-701 dualband mobile	£299.00
Kenwood TM-255E 2m multimode	£599.00
Alinco DJ-580E Dualband handheld	£239.00
Kenwood TH-28E 2m handheld	£149.00
Alinco DJ-1 2M handheld	£159.00
Alinco ALM-203E 2M handheld	£50.00
Kenwood TH-75E 2m/70cms handheld	£229.00

SMC GROUP 01703 251549

HF TRANSCEIVERS	
PX TS450SAT Kenwood HF 100W	£899
PX HL7000B Tokyo HF L/amp	£899
PX FT747GX Yaesu HF 100W	£425
PX FC700 Yaesu Man ATU	£109
PX FT767GX Yaesu HF 2+6mtr	£1099
PX FT102 Yaesu HF 100W	£425
PX IC737 Icom HF 100W	£1060
LX FTONE Yaesu HF 100W	£675
LX FT890AT Yaesu HF 100W	£1250
LX IC-706 Icom HF + 2/6m	£779
LX FT7B Yaesu HF 50W	£235
AX FT990 Yaesu HF 100W	£1650
AX IC765 Icom HF 100W	£1699
RX FT980 Yaesu HF 100W	£625
RX FT101 Yaesu HF Valve	£260
RX FT757GX Yaesu HF 100W	£495
RX FT747 Yaesu HF Mobile	£450
RX FT107M Yaesu HF 100W	£275
RX TS520 Kenwood HF 100W	£260
RX TS440SAT Kenwood HF 100W	£750
RX IC726 Icom HF 100W	£850
RX IC761 Icom HF 100W	£995

VHF/UHF TRANSCEIVERS	
PX FT4700 Yaesu 2mtr/70cm	£329
PX FT2700 Yaesu 2mtr/70cm	£279
PX FT290R11 Yaesu 2mtr port	£375
PX FT736R Yaesu 2mtr/70cm	£1299
PX FT51R Yaesu 2mtr/70cm	£325
PX IC3201E Icom 2mtr/70cm	£309
PX C5800 Standard 2mtr m/mode	£259
LX DJ580E Alinco 2mtr/70cm	£245
LX TH21E Kenwood 2mtr port	£100
AX FT790R Yaesu UHF port	£310
AX TM-732E Kenwood 2mtr/70cm	£525
RX DJ160 Alinco 2mtr/70cm	£155
RX DJ560 Alinco 2mtr/70cm	£335
RX FT8500R Yaesu 2mtr/70cm	£575
RX FT212RH Yaesu 2mtr FM	£175

RECEIVERS	
PX DX-394 Realistic HF Gen. RX	£225
PX R2000 Kenwood HF Gen RX	£375
PX FRG7700 Yaesu HF Gen RX	£295
PX AR8000 AOR Scanner	£299
PX AR2800 AOR RX M/base	£359
PX AR1500ex AOR Scanner	£225
PX AR3030 AOR HF RX	£399
PX HF150 Lowe HF Gen RX	£375
PX FRG100 Yaesu HF Gen RX	£395
PX MVT8000 Yupiter Scanner	£269
PX SW-7600 Sony Portable RX	£139
PX PRO2032 Realistic B/Scanner	£149
LX ICR-72 Icom HF RX	£675
LX FRG00 Yaesu HF RX	£425
AX PRO-80 Sony S/wave RX	£120
AX 2001D Sony S/wave RX	£169
RX HF225 Lowe HF Gen RX	£385
RX AR1500 AOR H/H Scanner	£165
RX ICF-7600 Sony Port RX	£120
RX NRDS35 JRC HF Gen. RX	£850
RX FRG9600 Yaesu Base Scanner	£240

PX = Chandlers Ford HQ 01703 - 251549
RX = Reg Ward 01297 - 34918
LX = SMC Leeds 01132 - 350606
AX = ARE London 0181 - 9974476

Disclaimer

Advertisements from traders for equipment that is illegal to possess, use or which cannot be licensed in the U.K. will not be accepted. While the publishers will give whatever assistance they can to readers or buyers having complaints, under no circumstance will the magazine accept liability for non-receipt of goods ordered, late delivery or faults in manufacture.

PLEASE MENTION TRADERS' TABLE WHEN ENQUIRING ABOUT ANY ITEMS ON THESE PAGES!

PHONE NOW FOR THE BEST DEALS IN LONDON

WE PROMISE TO MATCH ANY GENUINE QUOTE

GPS
GARMIN




**GARMIN
12XL**

- ★ Powerful 12 channel receiver
- ★ Moving map graphics
- ★ Back light display
- ★ One-hand operations

£209.99

GPS 38.....	£124.99
GPS 12.....	£149.99
GPS II.....	£129.99
GPS II+.....	£219.99
GPS 12XL.....	£209.99
GPS 45XL.....	£219.99
GPS MAP 130.....	£499.99
GPS MAP 135.....	£call
GPS MAP 175.....	£call
GPS MAP 230.....	£call
GPS MAP 220.....	£call
GPS III (with map).....	£459.99
GPS 40 (re-worked).....	£99.99
GPS 45 (re-worked).....	£119.99

GPS
MAGELLAN



**MAGELLAN
3000XL**

(FREE CASE + FREE BRACKET)

- ★ Powerful 8 channel receiver
- ★ Built-in antenna

£169.99

GPS 2000XL.....	£159.99
GPS 3000XL.....	£169.99
GPS 4000XL.....	£219.99
Meridian XL.....	£239.99
DLX 10.....	£459.99
NAV 1200.....	£234.99
NAV 6000.....	£569.99
NAV 6500.....	£739.99



MAIL ORDER HOTLINE

0171-637 3727

Fax: 0171-637 3728 E-mail: sales@sun-rise.co.uk

**GPS
ACCESSORIES**

Marine antenna	£89.99	£69.99
Car antenna	£89.99	£69.99
PC kit	£80.99	£69.99
Cigarette lighter adaptor	£20.99	£19.99
Mounting bracket	£20.99	£24.99
Power data cables	£24.99	£19.99
Pouch case	£24.99	£14.99
GPS case	£20.99	£9.99
Training video	£14.99	£6.99
Universal holder	£12.99	£9.99
PC software available		£call

NIGHT VISION



MOONLIGHT

Moonlight NV-100	£319.00	£299.00
Moonlight Mini	£269.00	£259.00
ITT Quest 100		£699.99
ITT Quest 150		£899.99
ITT Quest 250		£1699.00
ITT Quest 300		£call

CENTRAL LONDON'S ONE-STOP COMMUNICATIONS CENTRE



229 Tottenham Court Road, London W1

All prices include VAT. Next day delivery available

**SCANNING
RECEIVER**

**YUPITERU
MVT-7100**

- ★ 580MHz-1600MHz
- ★ 1000 memory channels
- ★ Strength meter
- ★ Search & scan
- ★ Illuminated keypad
- ★ Back-light
- ★ 3-way power

£229.99



Welz WS1000.....	£229.99
Icom IC-R10.....	£334.99
Uniden 220XLT.....	£169.99
Uniden 60XLT.....	£99.99
Yupiteru MVT-9000.....	£349.99
Yupiteru MVT-7100.....	£229.99
Uniden BC80XLT.....	£99.99
AOR AR8000.....	£294.99
Alinco DJ-X10.....	£349.99
Yupiteru VT-125Mk2.....	£199.99
Netset PRO-44.....	£129.99
AOR AR3000.....	£call
Icom IC-R8500.....	£1499.99
Yaesu FRG-100.....	£489.99

TRANSCEIVER

**ICOM
IC-T22E**

- ★ Independent band control
- ★ Simultaneous receiving
- ★ 200 memory channels
- ★ Hand held to hand held cloning capability

£249.99



Alinco DJ-190.....	£149.99
Alinco DJ-541.....	£129.99
Icom IC-T7E.....	£284.99
Kenwood TH-22E.....	£229.99
Alinco DJ-45.....	£299.99
Yaesu FT-50.....	£289.99
Yaesu FT-11.....	£239.99
Alinco DR-140.....	£249.99
Alinco DR-430.....	£259.99
Yaesu FT-8100R.....	£499.99
Yaesu FT-3000M.....	£399.99
Icom IC-207H.....	£439.99
Icom IC-2710H.....	£494.99
Icom IC-W32E.....	£349.99

HF FAR & WIDE

Leighton Smart GWOLBI reports on YOUR activity on the h.f. bands, and as Leighton says....band conditions really do seem to be improving!

The good news this month is that our reporters have noticed a definite improvement in propagation conditions on the h.f. bands. Most notably improved is the 14MHz allocation, with strong signals from Australia and New Zealand coming in on the long path at around 0600UTC.

By the time you read this, the dark autumn/winter nights should be upon us, and we'll be working some nice DX with simple dipoles held up with string, perhaps!

Firstly, I have an up-date on the ZB2 callsign 'pirating' reported this year. It started several months ago when I mentioned that the callsign ZB2FUM had been pirated on the h.f. bands by a station reportedly operating from Gibraltar, following information given by **Mr W. Guerrero ZB2IB**, Secretary of the Gibraltar Amateur Radio Society.

However, this month I've received a couple of telephone calls from readers who have worked the similarly-titled **ZB2FU/M**, who has apparently been mistaken on a number of occasions for the ZB2FUM illegal operator!

It seems that ZB2FU, who works /Mobile quite often has told our readers that he's a little 'cheesed off' about being told that he's a pirate, and would like to set the record straight. No problem! So...let's get it straight: **ZB2FUM is a callsign that has not been issued in Gibraltar, and is thus illegal.** On the other hand **ZB2FU, (including ZB2FU/M), is legitimate! Okay?**

Your Reports

I'll start your reports this month with the 1.8 and 3.5MHz bands for a change, and the log from **Sean Gilbert G4UCJ** in Milton Keynes, who says he's been experimenting with a m.w. loop antenna on 1.8MHz, (or 'Top Band' as it's affectionately known).

Using the loop Sean made contacts with the well known VE1ZZ (Canada), and UA9ADD (Asiatic Russia) on s.s.b., while c.w. operation brought in 9A1HCD (Croatia), OK1DX/MM (off the Faroe Islands), EU1AI (Belarus), and LA5M/P (Norway), all between 2000 and midnight. On 3.5MHz he lists c.w.

contacts with VY2JG (Prince Edward Island), J69B (St. Lucia Island), BV5BG (Taiwan), and 9K2MU (Kuwait), all between 2130 and 2240UTC.

It's a big 'Welcome Back' to **Derek Blunden BRS171057** of Swindon, who has been tied up for quite a while with his studies. Hope everything goes well with the 'A' Levels, Derek! His long s.w.l. list this month shows 3.5MHz reception of N2BNA (USA) working G0LJT at 0007, LU2NI (Argentina) working EI8HZ in Eire at 2242, CY1FG (Canada) working G40BB at 2215, as well as WA2WVL (USA) in contact with M0ARU at midnight, and KD1WQ working GM3UHT at 2314UTC.

The 7MHz Band

Up to 'Forty' and now straight into the 7MHz band log from newly-licensed reporter **Dave Nolan EI5IN** from Mulingarr in Co. Westmeath, Ireland, who has been QRPing on the band. With powers of between 1 and 5W of c.w. the log includes contacts with RW4FE (Russia) at 2053, YU1WN (Serbia) at 2236, HB9CM (Switzerland) at 2100, YO3RX (Romania) at 0616, and HG5RVT (Hungary) at 2045. A warm welcome goes out to EI5IN.

Next comes **Ted Trowell G2HKU** on the Isle of Sheppey in Kent, and of course 'Our Ted' is an all-c.w. man. Ted has been 'invited' to the hospital again of late (hope you are fine now, Ted, keep that 'spark transmitter going'!).

For 7MHz, Ted lists contacts with FG/F2HE (Guadeloupe Island), CP6IV (Bolivia), VP2EXM (Anguilla Island), ZL1BM (New Zealand), CL8VP (Cuba) at around 0500. Later operation at 1700 brought Ted a contact with VK8AV (Alice Springs, Australia), and at 2000UTC saw 9K2RR come in with good signal strengths.

The G3NOF Report

The monthly propagation report from **Don McLean G3NOF** in Yeovil indicates that conditions on 14MHz and the other bands in August have improved somewhat (his report is a summary of conditions on 14MHz and all the DX bands). Don says "The



Fig. 1: The man himself - 'HF Far & Wide's 7MHz Correspondent' Charlie Blake M0AIJ operating /P while on holiday in Poole, Dorset.

long path to New Zealand has been opening lately between 0600 and 1000UTC, although the best conditions have seemed to be on the short path to Asia around 1500 to 1800, with some very strong signals indeed. During this time a few Australians were also heard".

Don continues: "Around the same time, west coast Americans came in, and African stations were heard mostly between 1500 and 1900. There were a few Africans heard around 2200, and north and south America were good signals around 2000UTC onwards".

Ted G2HKU's 14MHz band log includes s.s.b. contacts with A61AJ (United Arab Emirates) at 1800, BV5GO (Taiwan) at 1745, D44AB (Cape Verde Island) at 1754. He also worked DU1SAN (Philippines) at 1800, 4S7FS (Sri Lanka) at 1700, J38AI (Grenada) at 2242, Y11RS (Iraq) at 1745 (QSL to Adel, Box 55072, Baghdad, Iraq). Finally, Ted worked 8P9HA (Barbados) at 2314, 9M20M (Malaysia) at 1533, and 9V1ZB (Singapore) at 1700UTC.

Now I give a warm welcome to new reporter **Richard Lewis GW0WRI** of Ammanford in Carmarthen. Richard has sent in a short log, which shows his contacts with VK2CP (Australia) at 1450, CQ2AL (Cuba) at 1645, 4S7FS (Sri Lanka) at 1920, HB9VIO/AM at 37,000 feet over Morocco, ET3BA (Ethiopia) at 1852, and 4F4IX in the Philippines at 1800UTC (Don't forget to include equipment, antenna and power input details everyone!).

Next comes **Carl Mason GW0VSW** from Skewen in West Glamorgan, who has been 'bashing the key' yet again. His log for August shows his contacts with PY4PZ (Brazil) and WP4S (Puerto Rico) at around 1900, along with EP2MKP in Tehran at 1548, SV9/DJ4TR (Crete) at

0728, and CN18DKH (Morocco) on s.s.b. at 0750 (QSL via CN8SS, Box 299, Rabat).

Also on the 14MHz band was **Charlie Blake M0AIJ** who recently took a holiday down in Poole, (see Fig. 1) where he met up with Rob G3XFD for a bit of a 'ragchew'. A DXpedition in Poole eh, Charlie!

Charlie's log shows his /Portable contacts with Z32FD (Macedonia) at 1040, K9WR (USA) at 1315, ED5HQ (Columbretes Island) at 0838. Also worked were J41WCA at the World Championships Athletics in Athens at 1045, and CQ1I on Berlenga Island at 1245UTC.

And now back to Ted G2HKU to tie up the ribbons for this month. Ted's log shows that at 1500 he contacted TF/DJ7RU (Iceland), SV5/SM0CMH (Island of Rhodes), and JA7SSB (Japan), while operating at 1700 gave him a contact with EA5ND/EA9 (Ceuta & Melilla, north Africa).

Signing-Off

Well that just about wraps it up for this month, folks and it's signing-off time! I hope I managed to squeeze you all in, although it does become difficult sometimes to give all reporters a 'fair crack at the whip' so to speak.

Thanks again, and as usual, reports and information (**don't forget to include full details of your equipment, antennas, power inputs and photos!**) by the 15th of each month to: **Leighton Smart GWOLBI, 33 Nant Gwyn, Trelewis, Mid-Glamorgan CF46 6DB, Wales. Tel: (01443) 411459 or (01443) 710749 (9am - 6pm), FAX: (01443) 710789.**

END

VHF REPORT

David Butler G4ASR has reports of some excellent autumnal tropospheric propagation which enabled contacts to be made with stations in Scandinavia and Eastern Europe.

Some very good tropospheric propagation occurred on the v.h.f. and u.h.f. bands during September. Contacts from the UK were made with stations as far away as Scandinavia and eastern Europe.

There were also a number of weak auroral openings, predominantly on the 50MHz band, enabling contacts to be made with stations in northern England, Scotland and Scandinavia. Sporadic-E (Sp-E) propagation was still present on the 50MHz band during September although the openings were very much reduced compared to the frenetic activity of previous months. For the very observant, there was also a brief trans-equatorial propagation (t.e.p.) opening to southern Africa on the 50MHz band.

Tropospheric Enhancement

What was probably one of the best periods of tropospheric enhancement for some considerable time occurred in a multitude of openings throughout much of September. At the beginning of the month, September 2, the 144MHz band was reported open from eastern England into Scandinavia. This tropo opening fortunately coincided with one of the regular monthly Scandinavian activity periods (held on a Tuesday).

At the QTH of **Andy Cook G4PIQ** (JO01) stations worked on s.s.b. included OZ5V and OZ5W (both in JO55) and OZ1ALS/A (JO45). A little further to the north the station of **John Regnault G4SWX** (JO02) found DD0VF (JO61), OZ1KLU (JO46), OZ6ABA (JO57), OZ7UHF (JO65) and SM7ALC (JO65).

The IARU Region 1 144MHz contest on September 6-7 generated much activity but as usual 'Murphy' decided that propagation would not be spectacular. Nevertheless there was still some good DX being worked on the 144MHz band.

In southern Scotland the station of **Ray James GM4CXM** (IO75) heard EA2LU/P (IN93) over something like a 1400km path. Ray also reported F5KAR/P, TM2K (JN09), TM2DX (all in JN09) and ON4ASL/A (JO10).

At the QTH of **Alec Trusler G0FIG** (IO90) located on the south coast of England s.s.b. contacts

were made with EA2LU/P, EA3TI/P (JN12) and HB9S/P (JN36). Of course as soon as the contest had finished the conditions improved considerably!

In the period September 8-10 propagation on the v.h.f., u.h.f. and microwave bands were very good in an arc stretching from southern France, through Switzerland, Austria and south-east Germany. Among the DX reported on the 144MHz band were the stations of F5BUU (JN03) and F5SOH (IN93), both located near the Spanish border, F6KEX near the Italian border in JN35, OE9NHI (JN47) and DF1CF (JN57), DF9NP (JN58) and DK00G (JN68) all located near the Austrian border.

Activity from Switzerland seemed very high especially on the 144MHz band. Among those reported were the stations of HB9AOF, HB9IAM, HB9SLO, HB9SNR and HB9STY (all in JN36), HB9AMH/P, HB9BLF, HB9BQU, HB9DFG and HB9RDE (in JN37), HB9FAP/P (JN46)

an 80W solid-state amplifier and two stacked 12-element DJ9BV Yagis. In the period September 9-10 he made s.s.b. contacts with G0FIG (IO90), G3KEQ (JO01), G3NAQ (IO91), G4DOL (IO80), G4ARRA (IO91) and G16ATZ (IO74) for his best DX at 1242km.

On the 430MHz band the station of **Nick Peckett G4KUX** (IO94) reported working F8DKW (JO18), F6BSJ (JN26) at 1000km and F5FEN (JN25) for his best DX in the period at 1162km. Conditions were also very good on the 1.3GHz band with the station of **Eric Gedvilas G8XVJ** (IO83) spotting F5FEN (JN25), F5HRY and F6DKW (in JN18) and HB9AMH/P (JN37). This latter station also managed to work GD4XTT (IO74) over a path of some 1140km.

The prevailing high pressure weather system slipped away in the following days but slowly returned to provide yet another period of excellent tropo conditions between September 16-18. This opening was different from the previous event in

evening of September 17. **Ulrich DH0GHU** (JN38) reports that during the evening he worked the stations of G0FIG (IO90), G3KEQ (JO01) and G60DA (IO91) on the 144MHz band. Ulrich was running 100W into an 11-element DL6WU long Yagi.

On the 430MHz band, running 20W into an 18-element Yagi Ulrich contacted G0FIG again for a new locator square. Meanwhile G0FIG, now operating on the 430MHz band, made s.s.b. contacts with DL6LP (JN48), DL6WU and DG7SFL in JN49 and LX1JX (JO30).

Possibly some of the longest distance contacts were made in the period September 21-23. All bands from 144MHz and up were open via tropo ducting predominantly to areas of southern Scandinavia, northern Germany and Poland.

At the beginning of the opening, on September 21, stations in GD, GI, GM and GW were heard making c.w. and s.s.b. DX contacts on the 144MHz band with stations located throughout Germany. For example GW8JLY/P (IO81) worked DL2ABO (JO51) as did MD1BYG (IO74).

Also on the Isle of Man GD3TNS/P worked DG7EAI (JO31) and over in Northern Ireland the station of G16ATZ (IO74) contacted DB8KJ (JO30) and on the 430MHz band made it with PA0RDY (JO22). Ray GM4CXM, who incidentally runs 400W into two stacked 16-element F9FT Yagis, managed to work a small number of DL stations late in the evening but mentions that the Scottish Amateur Radio Convention was held on September 21 so there was very little activity from Scotland at the beginning of the opening.

Some German stations found conditions particularly good across the North Sea with DD3DX (JO31) amongst others reporting a 1500km QSO with OY9JD (IP62) located on the Faeroe Islands. Another German station, **Uwe DL8UD** (JO44), situated near the Danish border, also contacted OY9JD (best DX at 1286km) along with the stations of GM3JIJ (IO68) at 1070km, EI2FIB (IO63) at 1067km and EI3GE (IO63) 1042km.

Uwe used an FT-736R transceiver driving a 200W amplifier into a 17-element F9FT Yagi to make his contacts. He also contacted GU3EJL (IN89), GW4ZQV and GW8JLY (IO81) and numerous G




Fig. 1: The 448-element antenna array for the 144MHz band at the QTH of Michel Winiger HB9JAW.

and HB9QQ (JN47).

Also active was the station of **Michel Winiger HB9JAW** (JN47). He uses an antenna system consisting of 8 x 28-element crossed Yagis (a total of 448-elements!) as shown in the photograph, **Fig. 1**. All the HB9 stations mentioned were making s.s.b. contacts with stations located throughout much of southern and central England, GW, GD, GI and EI.

John F5IQA (JN36) sent a report mentioning that his 144MHz station consists of an FT-736R transceiver,

that propagation was generally restricted to the east of the UK extending into eastern Germany, Austria and the Czech Republic.

Lee Adams G4RKY (JO01) reports working strings of German stations on the 144MHz band in locator squares JN58, JN59, JN68 and JN69. He also contacted OK1JKT/P (JO60), OK2MWR/P (JN99) and OK2PQR/P (JN89).

Alec G0FIG was pleased to find two Austrian stations OE2JG/2 (JN67) and OE3LFA (JN88) during the

stations in I080, I081, I082, I083, I091, I092, I093 and I094.

Conditions in the following days, September 22-23, were excellent as a pronounced area of ducting formed between the UK and northern Europe. **John G1ZCW** was pleased to catch this opening as it was his first big event since coming onto the 144MHz band. His QTH is situated in locator square J003 which contains very few v.h.f. DXers and he was therefore in much demand during the tropo event. John uses a Yaesu FT-726R transceiver driving into a Nag 144XL amplifier producing about 200W output into a 19-element Yagi.

Numerous s.s.b. contacts were made during the evening of September 22 with operators located in DL, OZ, PA, SM and SP. Among John's best contacts were the stations of SP1E0I (J073), SP2IQW (J094), SP2SGZ (J082), SP3SFN (J082) and SQ3VAA (J072).

All of John's contacts were well in excess of 1000km but the star turn of the evening were contacts with SP4MPB (K003) at 1351km and SP4CHY in the same locator square at 1417km. Not a bad start at v.h.f. DXing!

Unusual Characteristics

Located near Glasgow the station of Ray GM4CXM mentions the unusual characteristics of the tropo opening. Ray noticed that the duct went a long way inland, overhead of the stations immediately to the east of his QTH. This meant that he didn't have to fight through the normal barrage of coastal stations who often get to the DX before Ray does.

Ray reports that propagation during the evening of September 22 was very good although signals from Polish stations (which had been worked for most of the day in G and GW) only appeared at his QTH for some 20 minutes just before midnight. However, he did manage to contact SP1E0I, SP2FAX (J083), SP20FW (J093) for his best DX of the evening at 1478km and SP3SFN (J082).

Ray also worked a number of stations in F, DL, OZ, PA and SM at distances ranging between 800-1200km. Propagation on the following day declined somewhat at the QTH of GM4CXM and although there were still some very big signals around it was difficult to find any real DX. There was still a path into DL, ON and PA but by the evening it had all disappeared.

The tropo duct fortunately extended to my QTH (I081) on the Welsh border and I was able to make many contacts on both c.w. and s.s.b. with stations in DL, OZ, SM and SP. Just as experienced by GM4CXM the duct went over the top of stations to the east and south-east of my QTH. The result was that there was far less competition for the DX stations.

A total of nine Polish stations were worked in locators J072, J073,

J082, J083, J084, J092 J093, J094 and K003 and if you look at a locator map you'll see how tightly grouped all these contacts were. Only two contacts were less than 1400km, the best DX being SP4MPB at a shade under 1600km.

Other contacts included OZ1DNN (J055), OZ5AGJ (J056), SH7ABV (J065) the SH-prefix indicating a novice licensee and SM7WT. For the record I was using a Yaesu FT-221R with a replacement MuTek front-end, 400W and a single 17-element F9FT Yagi.

Irec SP3SUX (J072) sent a message via Packet radio about his contacts made on the 144MHz band on September 22. He uses a Yaesu FT-290R transceiver and an 80W amplifier into a 14-element DJ9BV Yagi and made contact with EI2FIB, EI3GE, GD4XTT, GI6ATZ and GM4YXI.

Irec also made three contacts into England working G0EWN, G4PBP and G8XVJ. On the following morning he worked G8GXP and G4CYA/M (I093) who was using an arrangement of 2 x two-element beams on his car.

Jim Smith G00FE (I090) sent in a report covering the whole of September. On the 144MHz band he uses an Icom IC-820H transceiver, a solid-state 170W amplifier and a 12-element ZL Special beam at 15m a.g.l.

In the period September 7-9 Jim found that the best propagation was towards Switzerland working HB9S (JN36) during the contest on September 7, HB9QQ (JN47) on September 8, the first time he had heard Pierre via tropo and HB9DFG (JN37) plus an assortment of French stations in JN16, JN26 and JN27. The station of DL2ARD/P (J060) was worked on September 17 and a contact was made the next morning, at 0555UTC with OK1JKT/P (J060).

Jim reports the he was located too far south (near Bournemouth) to hear any of the Polish stations being worked on September 22 but he did make s.s.b. QSO's with OZ1PIF (J065), OZ5KM (J045), SK6HD (J068) and SM6VQW (J067) during the evening. However, by early morning of September 23 the necessary propagation had swung Jim's way and he was pleased to contact SP4MPB at 1558km for his furthest ever tropo contact. Jim mentions that he has now worked SP4MPB via aurora, Sporadic-E and tropo.

On the 430MHz band the station of **G1HWY** (I090) reported contacts on September 22 with SM7ECM, SM7FMX, SM7JUQ and SM7TUG. He also heard the low power beacons SK7MHH (J086) and OZ7IGY (J055).

Alec G0FIG also heard the Swiss beacons HB9F (432.984MHz) and HB9G (432.880MHz) and GD4GNH (Isle of Man) contacted a number of stations including DL8QS (J043). On the east coast of England **John Quarmby G3XDY** (J002) worked SP2FAX on the 430MHz band and OZ2LD on the 1.3GHz band.

Propagation still remained good in the following week, building up to

a peak on September 27-28. Yet again the 144MHz band was open into DL, HB9, LA, OE, OK and OZ. Among some of the stations being worked in this period were LA2PHA (J038), OE2JG/2 (JN67) and OK1AOV/P (J080). In Suffolk G4SWX even managed to copy traces of a weak signal from 9A1CAL (JN86) located in Croatia.

Auroral Openings

Weak openings via auroral backscatter were reported on September 3, 10, 17, 18 and 27. All openings were noted on the 50MHz band and nothing was reported at higher frequencies. There are probably two reasons for this.

Firstly the openings were quite weak on the 50MHz band and therefore any opening on a higher frequency band, such as 144MHz, would have been considerably weaker or non-existent. Secondly these auroral openings all occurred when excellent tropo conditions were occurring on the v.h.f. and u.h.f. bands. It's therefore very easy to miss the weak auroral DX when the band is full of very strong tropo signals.

Sporadic-E

During September there were some brief Sp-E openings on the 50MHz band but these were very much few and far between. Evening openings between 1900-2100UTC were observed at the beginning of the month, September 1 and 2, to I, SP, YU and 9A.

The only other significant period of activity occurred on Sunday September 7 when a number of openings were observed throughout the day between 0830-1600UTC. Surprisingly the propagation appeared to cover a very large area with stations such as EH6ADW (JM19) in the south, YU1QC (KN04) and 9A1CAL (JN86) to the south-east and UA1WJ (K047) to the north-east being worked from the UK.

Catch of the day though was an Austrian DXpedition to Libya using the special call sign **5A28** (commemorating 28 years of the Libyan Revolution). The group were active on the 50MHz band between August 30 to September 7, so it was fortunate that a Sp-E opening occurred on the very last day of their operation.

Using an Icom IC-706 and a 5-element F9FT Yagi a total of 23 UK stations were worked by 5A28 in an hour long opening commencing around 0930UTC. Contacts were made with stations in GJ, GW and G stations predominantly in southern England. (At my QTH in I081 they only peaked S2 for about 15 seconds!). This was the first time that Libya had been worked from the UK and it will be interesting to see if that country can be activated again next year, hopefully during the main summer Sp-E season.

Trans-Equatorial

Exactly one year ago I gave details of the timings of t.e.p. openings and mentioned that you should pay particular attention to the 50MHz band during the September/October period for these special type of propagation events. (Last year there were very brief openings on September 28/29 to Namibia and Malawi). Although very weak there have indeed been a few openings this year during the autumn equinox period.

What was probably the first event appears to have occurred on September 12 around 1845UTC when 7Q7RM in Malawi was heard by stations in Israel (4X). A few days later on September 16 the stations of G4HBA and G4IGO (both in I080) heard 7Q7RM between 1740-1750UTC.

The next t.e.p. event was on September 22 at 1710UTC when IK00KY (JN61) heard the V51VHF beacon (50.018MHz) peaking 579. On the following day at 1815UTC the Maltese station 9H5EE (JM75) heard 7Q7RM at 59 on s.s.b. As you read this the autumn t.e.p. peak will have disappeared but it may be worthwhile noting that similar conditions could occur next March during the spring equinox.

Satellite News

On October 4 1957 the Soviet Union launched the first artificial satellite, Sputnik-1, into Earth orbit. To commemorate its 40th anniversary a one-third scale model of Sputnik was scheduled to be hand-launched from the Mir Space Station on October 4 1997.

If all went to plan you should be able to hear the beep-beep sound of the beacon on-board the miniature working model. Running on dry batteries it is expected to have a lifetime of up to two months duration.

The transmitter power of between 100 and 200mW should deliver a readable signal to all but the smallest of receiving stations. At the time of writing the beacon frequency has not been finalised but was expected to lie between 145.810MHz and 145.850MHz. If you heard it please let me know.

Deadlines


That's it again for another month. Please forward any news, views, comments or photographs to reach me no later than **Saturday November 29**. Send them to me at **Yew Tree Cottage, Lower Maescoed, Herefordshire HR2 0HP**. You can also contact me via Packet radio @ **GB7MAD**, the UK DX Cluster @ **GB7DXC** or E-mail via **davebu@mdlhr1.agw.bt.co.uk**. Alternatively you can telephone me on (01873) 860679.

END



Radio Receiver Trainer

An Invaluable Learning and Design Tool for all Experimenters



The manual contains complete schematics and theory of operation of all the building blocks. Use this trainer to receive frequencies from 500kHz to 110MHz!

A set of proven alternate building block designs are included in the manual to get you started with your own designs. There is no need to get your complete receiver design working all at once. Build and test each block one at a time.

The Radio Receiver Trainer contains nine receiver building blocks and a comprehensive training manual.

Simply connect the building blocks to build AM, SW, Superhet and Direct Conversion receivers. Decode SSB, CW and FM!. Use proven building blocks to develop and test your own designs.

Pricing: Complete £129.00
Kit £89.00
(Kit excludes case & headphones)

P&P is £5 (UK), £8 (EC), £12 (World)
Add 17.5% Vat to Total Price

Building Blocks: RF Input Tuner
RF Oscillator
Mixer
IF Filter
IF Amplifier
AM Detector
Beat Frequency Oscillator
Audio Filter
Audio Amplifier

Mail Order To: **Pyramid Electronics LTD.**

204 Ferndale Road, Brixton, London SW9 8AG

Phone (0171) 738 4044 Fax (0171) 274 7997

(Out of office hours ordering by answering machine)



New Publications from the RSGB


The RSGB Yearbook

1998 Edition

Edited by Brett Rider, G4FLQ

This new edition of the ever-popular RSGB Call Book and Information Directory has been further enhanced with the inclusion of even more information on amateur radio than ever before!

This year you will find a trade listing, giving details of all the regular advertisers in RadCom, as well as the complete UK callsign listing. Over 100 pages of associated amateur radio information - an essential guide to keep close to hand in your shack.



Price: **£13.95** plus £1.25 P&P

The VHF/UHF Handbook

Edited by Dick Biddulph, G8DPS

This guide to the theory and practice of amateur radio reception and transmission on the VHF and UHF bands gives the reader the background to such essential topics as antennas, EMC, propagation, receivers and transmitters, together with constructional details for many items of equipment. As most amateurs today use commercial transceivers, the emphasis is on accessories and add-ons which are relatively simple to build. Specialized modes such as data and television are also covered, making this handbook one of the most complete guides around.

This new edition is the successor to the RSGB VHF/UHF Manual.

Don't be without it if you're a VHF/UHF radio operator.

Price: **£18.80** plus £1.25 P&P

RSGB CallSeeker '98 CD-ROM

Complete 1998 UK callsign listing

The first RSGB callsign listing on CD-ROM is available as a companion product to the 1998 Yearbook!

System requirements:

- 486 or higher processor and a CD-ROM drive
- VGA or high resolution screen supported by Microsoft Windows
- 10 - 15MB spare hard disk space
- Windows 95 or later with 8MB of RAM (16MB recommended) or Windows NT Workstation version 3.51 or later with 16MB of RAM (24MB recommended)



Price: **£13.95** plus £1.25 P&P

Your First Amateur Station

By Colin Redwood, G6MXL

The second book in the RSGB 'Pocket Guide' series, this book has been written to help the newly-licensed radio amateur move on to the next stage - setting up his or her very own radio shack. So many new licensees have asked the question "What do I do now?" that we decided to publish this guide to help all new amateurs through those early uncertain days.

Price: **£5.85** plus £1.25 P&P



To order any of the above books, or for a complete list of RSGB publications, contact the RSGB Sales Office on tel: 01707 660888; fax: 01707 645105; or E-mail: sales@rsgb.org.uk



Radio Society of Great Britain

Lambda House, Cranborne Road, Potters Bar, Herts EN6 3JE ☎ 01707 659015

<http://www.rsgb.org>

BITS & BYTES

This month Mike Richards G4WNC looks at the basics of digital mode operations such as ASCII and RTTY, but first starts off with a further update on DSP Blaster.

The DSP Blaster program from **Brian Beezley** really does seem to be causing quite a stir judging by the number of complimentary comments I've been receiving from readers. I've also just heard from **Mike Le Ves Conte** (UK distributor of registered copies) that the program is now up to version 2.07, so I'd better fill you in with the changes from the version 2.04 that I originally reviewed.

The first change is the elimination of the Noise Reduction 'pop' on start-up. This is supplemented with a new squelch facility which includes ten dither settings, digital/analogue deadband all featuring full control from within the a.g.c. box.

The configuration memory selector now highlights on selection and changes colour if the settings are altered. You can also label the selectors with their settings - this looks to be a particularly helpful change.

There has also been a general clean-up of the code and the main Fast Fourier Transform (FFT) is quicker. As a final add-on, all the hot-key functions except the volume are ignored when the bypass is activated.

Digital Modes

For many amateurs one of the main reasons for introducing a computer into the shack is to start getting into the digital modes that abound all over the spectrum. Whilst you can do this with very little knowledge by using commercial kits, this rather negates the whole point of amateur radio, which is self education.

If you're just going to buy commercial equipment for everything and not even attempt to understand the technicalities you might as well sign-up for Internet access and save the Amateur Radio licence fee! But enough of the controversial stuff.

If you do want to learn more you may have some difficulty in finding publications that approach the subject in a friendly manner. In an attempt to overcome this, I'm going to spend most of this month's column going through some of the basics.

If you really think about the

purpose of the data modes you will soon realise that the common factor with all the systems is that they have been designed for the movement of information. The most common forms being text messages, programs and pictures.

The systems which are used to transmit pictures are slightly different, so this time I'll concentrate on the transmission of messages and computer programs. In both text and computer programs it's easy to see that even the largest program or message is made-up from lots of smaller elements i.e. letters and program bytes.

I can't imagine how you could send a large message or program in one operation, so it's clear that you need to break them up into much more manageable chunks and reassemble them at the far end. But, let's take a closer look at how letters

Fig. 1: The ASCII Look-up Table.

Letter	Decimal Number	128	64	32	16	8	4	2	1
a	65	0	1	0	0	0	0	0	1
b	66	0	1	0	0	0	0	1	0
c	67	0	1	0	0	0	0	1	1
d	68	0	1	0	0	0	1	0	0
e	69	0	1	0	0	0	1	0	1
f	70	0	1	0	0	0	1	1	0
g	71	0	1	0	0	0	1	1	1

are represented inside a computer.

You probably already know that computers can only think in numbers and binary ones at that. So how on earth can they handle text characters?

The answer is to convert all the letters into binary numbers. Computers do this by using a simple

programming technique called a 'look-up' table.

Everytime you press a key the computer checks against the table to see which number it should use. Whilst this system is pretty simple, what happens when you send this numerical representation of your message to another computer? Fairly obviously the other computer needs to use the same look-up table or your message will turn into gibberish!


Fortunately, the requirement of look-up tables is well documented and there are a number of standards around to make sure all is well. For use within the PC the common standard is known as ASCII, which is an acronym for American Standard Code for Information Interchange.

The ASCII code uses a separate seven digit binary number to represent each letter, figure and a range of punctuation marks. Within the computer this number is usually made-up to an eight bit number to align with the computer's standard number length.

It just so happens that computer programs are also built-up from similar eight bit numbers. So, you can now see that the common factor between a computer program and a text message is that they're handled within the computer using identical formats.

Now you need to consider how these eight digit binary numbers can be transmitted over a radio link. To work this out you first need to remind yourself what a typical single side band (s.s.b.) transceiver is designed to do best.

The answer is that the s.s.b. transceiver is designed to convey the important parts of the spoken word.



Special Offers

If you'd like a copy of Hamcomm/JVFX, etc. I've arranged a very special offer with the **Public Domain and Shareware Library (PDSL)**. They have put together a library set of all five disks for just **£12**, all inclusive.

Using PDSL also makes ordering simpler as they accept all the usual credit cards so you can order by 'phone - you don't even have to write a letter. Please direct all orders and enquiries about this disk set to PDSL, **Winscombe House, Beacon Road, Crowborough, Sussex TN6 1UL. Tel: (01892) 663298** and request library volume: **H008739abcde**.

The software is only available as a set of five disks as follows: IBM PC Software (1.44Mb disks): **Disk A** - JVFX 7.1, HAMCOMM 3.1 and WXFAX 3.2; **Disk B** - DSP Starter plus Texas device selection software; **Disk C** - NuMorse 1.3; **Disk D** - UltraPak 4.0 and **Disk E** - Mscan 1.3 and 2.0.

In technical terms this means that it needs to be able to transmit the band of frequencies between around 300Hz and 3kHz, as these contain the important parts of the human voice.

In order to send our computer data using a standard s.s.b. transceiver you need to somehow make it fit in this range of frequencies. The solution comes from taking a closer look at an individual binary digit.

This can only ever be in one of two states which are ON or OFF. In electrical terms this means 5 or 0V for many computer systems.

If you were to arrange for the binary information to be sent out of the computer over a single wire you would get a varying voltage that would swing between 0 and 5V depending on the value of each bit as it emerged. This highly useful task is carried out by the part of your computer known as a serial port controller. The actual electrical signal appearing on one of the pins of the serial port.

The next step is to connect the signal from the serial port to a special voltage controlled oscillator that can switch between two frequencies in synchronisation with the 5 and 0V signal. If the frequencies were selected so that they fell within the 300Hz to 3kHz band they could be comfortably handled by an ordinary s.s.b. transceiver. This is precisely what happens in a real data transmission system.

As with the selection of an appropriate look-up table for each letter, there needs to be a few standards in place for the system to be really effective. The first thing that needs to be agreed is the rate at which the binary digits are sent from the computer.

The 'rate' factor is called the baud rate and in radio based systems can range from 45.5 baud through to 9600 and higher. Rather than using a completely variable figure, there are a number of pre-set rates, a typical sequence being 45, 50, 75, 100, 110, 300, 600, 1200, 2400, 4800, 9600, etc. Next, there needs to be some standardisation of the tones used to carry the information.

When using an s.s.b. transceiver it's not so much the actual audio frequencies that matter rather than the difference between them. This difference is called the shift and you

will find this mentioned in the specifications for many systems.

If, for example, you used 1800 and 2000Hz for the binary digits, the shift would be quoted as (2000 - 1800) = 200Hz. Now, that you have your basic data signal winging its way across the air waves - how on earth are you going to reverse the process and re-construct the original message or computer program? It's actually quite easy as I will now explain.

At the receiving end of the link you will hear the data signal as a warbling tone that changes in synchronisation with the data signals. All you now have to do is systematically unravel all the work that was done at the transmitter.

Convert Tones

So, the first thing is to convert the varying tones into an electrical signal that varies between 0 and 5V. This can be done in many ways, but is traditionally done with a device called a terminal unit.

A terminal unit uses either a filter or phase locked loop system to carry out the required decoding. With the original 0 and 5V signal re-created you just have to apply it to the serial port and you're back to square one!

There are a few points I need to clear-up though. First, the system I've described here using the ASCII look-up table is not generally used on its own in amateur radio.

For simple point-to-point communications Radio Teletype (RTTY) is one of these most common standards. The subtle difference with this system is that the International Telegraph Alphabet number 2 (known as ITA2) is used to provide the look-up between the alpha-numeric character and a binary digit.

A significant aspect of this code is that it only uses five binary numbers for each letter. This creates a few complications, as five elements are not enough to cover all the letters, numbers and basic punctuation.

As a result, two special shift characters are used to give each five digit number two possible interpretations. Although the system is fairly crude and prone to errors it has survived well and is still in regular use today both by amateurs

and commercial stations.

A second very important point to consider is the synchronisation between the transmitted signal and the receiver. Whilst it's relatively simple to get the decoding system to produce the 0 and 5V signal, how can the receiver know where each letter starts and finishes?

In order to achieve this the RTTY system adds some extra bits around the basic 5 bit number used to represent each letter. The first is a single bit known as a start bit. When this drops from 5 to 0V the receiver knows a new letter is on the way.

At the other end of each letter a further 1.5 bits are added to show the end of the letter. From this you can see that each letter or number in a RTTY signal comprises of a start bit followed by five data bits and a 1.5 bit stop bit. It's this distinctive pattern that the receiver looks out for to help it find its place when tuning into a new signal.

A number of decoding systems also use this distinctive 'fingerprint' to provide fully automated identification of both the transmission mode and speed. To work out the speed of the signal all the program has to do is measure the duration of the shortest element of the signal. This will normally be measured in milliseconds (ms).

The figure can then be used to directly calculate the transmission speed or baud rate. All you have to do is divide the duration in ms into 1000 to give the baud rate.

The mode analysis is simply a question of spotting that the signal uses five data bits, one start bit plus 1.5 stop bits. As no other mode uses this format the signal must therefore be RTTY.

In order to make all this happen on your PC you will need to run a special computer program that will convert your typed messages from ASCII to the RTTY code and arrange for them to be transmitted from the serial port at the appropriate speed with the various start and stop bits added. If I've sparked an interest in this part of the hobby and you're starting from scratch, the *Hamcomm* program is really very good and is available through many sources including my readers offers on this page. The current version of *Hamcomm* contains all the software necessary to send and receive RTTY plus some other modes that I'll describe another time.

In addition to the software and a PC you will also need an interface lead to make the connection between the serial port on your PC and your receiver. This is more than just a simple lead because it has to convert the audio signal from the receiver into a format that the computer can process.

The electronics are very simple and you will find plenty of interface kits around if you want to build your own. If you're rather impatient like me you can buy excellent quality ready made interface units from

Pervisell Ltd., 8 Temple End, High Wycombe, Bucks HP13 5DR. Tel: (01494) 443033, FAX: (01494) 448236 or E-Mail: ham@pervisell.com

Pervisell can also supply fully registered version of many of the popular programs. Once you've put together your station try tuning around 14.08MHz and you will soon come across some amateur RTTY.

Weather Update

If you're seriously into v.h.f. DXing then you will no doubt have learned the significant impact that the prevailing weather has on propagation conditions. As result many amateurs develop a very keen interest in the weather and use this knowledge to try and get ahead of the 'pile-ups' when an opening occurs.


With all the modern satellite and computer enhanced imagery available, the capture of weather information becomes an art form in itself. However, now many amateurs have access to the Internet there's even more information available.

However it can all get rather overwhelming so, I thought it might be helpful if I just run through a few of the sites that I've found to be particularly good. If you want to impress your friends as well as get useful data, the computer generated cloud cover forecast supplied by France Met is really good.

The site is best accessed via the excellent Jersey Met site at <http://user.super.net.uk/~jnet> If you want satellite pics to check what's going-on in and around Europe then the best ones are to be found at the Met Office site at <http://www.meto.govt.uk>

All the Meteosat images are regularly updated and the image quality is really excellent. If you know of some more sites that offer good data for Radio Amateurs please write or E-mail me with the details.

Fig. 2: A Typical RTTY Character.



That's all I have room for this time so until next month, cheerio and please keep your news and views coming to me **Mike Richards G4WNC at PO Box 1863, Ringwood, Hants BH24 2ZD** or via E-mail to: mike.richards@dia1.pipex.com My Web site address is <http://dialspace.dial.pipex.com/mike.richards/>

END

RF Power Modules from TDC & Mitsubishi



Standard parts stocked, replacement parts for many Yaesu/ Icom transceivers, ideal for linear PA designs.

Part	Frequency	Pwr/Mode	Price (1 off)
M57726	144-148MHz	43W/FM	£43.71
M57729	430-450MHz	30W/FM	£42.00
M57737	144-148MHz	30W/FM	£27.23
M57762	1.24-1.3GHz	18W/SSB	£67.53
M57788M	430-450MHz	40W/FM	£66.99
M67715	144-148MHz	13W/FM	£36.48
M67727	144-148MHz	37W/SSB	£124.59
M67728	430-450MHz	60W/SSB	£99.04
MI407-01	Pin diode up to 800MHz/25W		£1.21

Many other frequencies/ power combinations available, please call with your requirements. Data sheets available for specific items on request.

Call for Amateur/ Education discounts or volume pricing

COMING SOON - Linear power amplifier 'Starter Packs' for 2M & 70cm.



**MITSUBISHI
ELECTRIC**

TDC also stock Modem, Networking and GPS receiver and antenna products, visit our web site at <http://www.tdc.co.uk> for more information.



TDC

Stroudley Road
Basingstoke
Hampshire
RG24 8FN

Telephone : 01256 332800 Fax : 01256 332810
e-mail : sales@tdc.co.uk

Access/Visa accepted, prices include VAT @ 17.5%, Postage & Packing £5

SERVICE MANUALS & Technical Books

Available for most equipment, any make, age or model. Technical Book and Manual Compilations now on CD-ROM. Return the coupon for your FREE catalogue on Floppy Disks.

Price crash on all our CD-ROMs

MAURITRON TECHNICAL SERVICES (PW)

8 Cherry Tree Road, Chinnor, Oxon OX9 4QY.
TEL: 01844 351694. FAX: 01844 352554.

E-mail: sales@mauritron.co.uk Web Site: <http://dialspace.dial.pipex.com/mauritron/>
Please forward your latest disc catalogues for which I enclose 4 x 1st class stamps or £5.00 for the complete Service Manuals Index on PC disc plus catalogue.

NAME

ADDRESS

POSTCODE

Photocopy this coupon if you do not wish to cut the magazine

DEMODULATORS FOR JVFX HAMCOMM RADIORAFT DL4SAW SSTV & POCSAG

THE ORIGINAL RECEIVE ONLY with 25 way 'D' type £16.99
POCSAG RECEIVE version (as above, with variable hysteresis) £19.99

TRANSMIT version (Pocsag Rx + Fax/SSTV/HamComm Tx) £24.99

25 to 9 way Adaptor £3.00. Shareware on 3.5" HD Disks

JVFX7 + HamComm3.1 + PKTMON12 + NEW POCSAG (PD2.04) £2.50

RADIORAFT Version 2.12 £2.50 DL4SAW SSTV (V1.2) £2.50

REGISTERED VERSIONS OF SOFTWARE NOW ALSO INCLUDING RADIORAFT

DL4SAW (GSHPC) SSTV (V2.21) £34.99 HamComm3.1 £19.99

NEW POCSAG (PD2.04) £19.99 RadioRaft Version 2.12 £19.99

All prices UK/Eire inc VAT + P&P. For non-EU deduct 17.5% VAT


All products (except software) carry a full money back guarantee.

Minimum Credit Card order £15.00 Outside British Isles add £2.00

Pervisell Ltd, 8 Temple End, High Wycombe, Bucks.

HP13 5DR Tel: (01494) 443033 Fax: (01494) 448236

<http://www.pervisell.com> e-mail ham@pervisell.com



The Wireless Works

Everything for lovers of Valve & Vintage

We still offer old radios, valves, parts and everything wireless, over-the-counter and mail order, but now...

... We're moving to a larger shop, with more wireless in it!

40 Fore Street, Bugle, St. Austell, Cornwall PL26 8PE

Telephone (unchanged) 01726 852284

A THERMIONIC CHRISTMAS AND A WIRELESS NEW YEAR TO ALL OUR CUSTOMERS!

G6XBH G1RAS G8UUS

VISIT YOUR LOCAL EMPORIUM

Large selection of New/Used Equipment on Show

AGENTS FOR: YAESU • ICOM • KENWOOD • ALINCO
Accessories, ReVex/Diamond range of SWR/PWR, Adonis Mics,
Mutek products, Barenco equipment, MFJ products.

WE SPECIALIZE IN ALL TYPES OF PLUGS, ADP, ETC

★ ERA Microreader & BPS4 Filter, SEM Products ★

★ Full range of Scanning Receivers ★

AERIALS, Tonna, Maspro, plus full range of base/mobile antennas.

BRING YOUR S/H EQUIPMENT IN FOR SALE

JUST GIVE US A RING

Radio Amateur Supplies

3 Farndon Green, Wollaton Park, Nottingham NG8 1DU
Off Ring Rd., between A52 (Derby Road) & A609 (Ilkeston Road)

Monday: CLOSED. Tuesday-Friday 9.00am to 5.00pm. Saturday 9am to 4pm

INTERNET: <http://www.geocities.com/Eureka/1448> E-MAIL: ras-nottm@geocities.com

R.A.S. (Nottingham)

R.A.S. (Nottingham)

G6XBH G1RAS G8UUS Tel: 0115-928 0267

VERULAM RALLY 97

Sunday 14th December

10am to 4pm

WATFORD LEISURE CENTRE

Horseshoe Lane, Garston, Watford

5mins M1 junction 6, M25 junction 21A

off junction A405/412

Food and Bar

Trade stands, Bring and Buy

RSGB stand, PW & SWM stand, Morse Tests

Admission £1.50

(concessions £1.00 - Children under 14 free)

Talk-in S22

INFORMATION 01923 265572

BROADCAST

ROUND-UP

Peter Shore has news of winter schedules, along with a final broadcast, a station to close and a new name for Voice of Free China.

Since the introduction of the new winter schedules at the end of October, cash-stricken **Radio Vlaanderen Internationaal** has been co-operating with **Radio Netherlands** for the transmission of each other's programmes. Radio Netherlands, which has been renting the hugely expensive high-powered medium wave transmitter of RTL in Luxembourg, is now heard daily in English to Europe at 2130UTC until 2330 on 1512kHz, the Radio Vlaanderen medium wave channel, that offers good reception to listeners in the UK.

In return, Radio Vlaanderen has access to the Bonaire relay station owned and operated by Radio Netherlands to improve reception in the Americas, and the Madagascar relay which will boost audibility across Africa.

The complete Radio Vlaanderen International English language schedule is now: 0830-0855UTC on 6.130MHz from Wavre, Belgium to South Europe and 13.795MHz, also from Wavre, to Australia; 1300-1325UTC on 13.680MHz from Wavre to North America; 1730-1755UTC on 5.910MHz from Wavre to South Europe; 9.925MHz from Wavre to East Europe and 11.680MHz from Julich in Germany to the Middle East; 1830-1855UTC on 9.925 and 13.745MHz from Wavre to Africa.

Transmissions on medium wave in English can be heard in Europe on 1512kHz at 0830-0900, 1300-1330 and 1730-1800 using 25kW and at 1830-1900 and 2100-2130 with the output uprated to 300kW.

Relays via Radio Netherlands' overseas transmitting stations, and from a Russian h.f. facility, are all in Dutch at: 0430-0500UTC on 6.120MHz for North America's West Coast via Bonaire; 1000-1025UTC on 15.145MHz for South Africa via Madagascar; 1200-1230UTC on 6.170MHz via Petropavlovsk-Kamchatka for East Asia and Australia; 13.795MHz via Tashkent for South East Asia and 15.250MHz via Bonaire for South America; 2300-2325UTC on 9.555MHz via Bonaire for the East Coast of North America.

You can contact Radio Vlaanderen International at: **PO Box 26, B-1000 Brussels, Belgium.**

Final Broadcast

Radio Norway International's Fredrikstad transmitting station made its final broadcast on Saturday 18 October. The facility, inaugurated back in 1948, currently has a 500kW Thomcast-manufactured transmitter, although it has been radiating just 350kW for most of its life (it was installed in 1976, replacing a 100kW transmitter, which had been on the



air since the station opened).

Norway's public broadcaster, NRK, had hoped to lease time on the Fredrikstad facility, but with a glut in the short wave transmission market which has considerable over-capacity in Europe, was unable to find clients. The station is now being dismantled.

A special 30 minute broadcast at 1630UTC on 11.68MHz organised in conjunction with the Nordx '97 championships staged by the DX Listeners' Club of Norway, enabled listeners around the world to tune to this much-loved Norwegian transmitting station. **The Voice of America's** Greenville transmitter also participated in the championships, with an hour-long transmission the following day at 0400UTC on 5.89MHz, and a special QSL card was issued for both broadcasts.

If you heard either of the transmissions but have not yet sent in a report, hurry up! The address is: **Nordx '97, DX-Listeners' Club, PO**

Box 7080 Vestheiene, N-4602 Kristiansand, Norway.

Radio Norway continues to broadcast in English and Norwegian world-wide from its transmitters at Sveio. The English winter schedule (Sundays only) is: 0700-0730 on 9.59 and 11.625MHz; 0800-0830 on 11.625MHz; 1300-1330 on 9.59, 9.905, 13.80, 13.805MHz; 1400-1430 on 13.80MHz; 1600-1630 on 13.80, 13.805MHz; 1700-1730 on 7.56MHz; 1900-1930 on 7.485, 9.59 and 9.96MHz plus 1314kHz medium wave; 2000-2030 on 7.57MHz; 2200-2230 on 7.57MHz; 0100-0130 (Monday) on 7.465 and 7.545MHz; 0200-0230 (Monday) on 7.565MHz and 0400-0430 (Monday) on 7.52 MHz

Radio Norway celebrates its 50th anniversary next year. Watch out for more news in this column!

Winter Schedule

Radio Prague's winter schedule has been affected by budget cutbacks. The English service can be heard: 0830-0857 on 9.505 and 11.60MHz to Europe; 1000-1030 on 17.485 and 21.705MHz to West Africa, the Middle East and South Asia; 1130-1157 on 7.345 and 9.505MHz to Europe; 1400-1430 on 13.58 and 21.70MHz to N America, South Asia, Australia and East Africa; 1700-1727 on 5.93 and 9.43MHz to Europe and East Africa; 1800-1827 on 5.93 and 9.43MHz to Europe, South Asia and Australia; 2100-2127 on 5.93 and 7.345MHz to Europe, North America and West Africa; 2230-2257 and 0000-0027 on 5.93 and 7.345MHz to North America; 0100-0127 on 6.20 and 7.345MHz to North America and South West Asia; 0300-0327 on 5.93 and 7.345MHz to North America and 0330-0357 on 7.35 and 11.60MHz to the Middle East and South West Asia.

Radio Prague can also be heard on World Radio Network's Astra service to Europe, WRN1, daily at 1000UTC.

New Edition

A new edition of the annual *Radio Stations in the United Kingdom* has just been published by the British DX Club. This 1997-98 edition has been completely revised and updated to

include all UK domestic a.m. and f.m. stations currently on the air. It also comes with a free supplement covering radio stations in the Republic of Ireland.

Many new stations have come on the air since the last edition was published 18 months ago, and the new edition helps listeners find their way round the increasingly crowded UK radio dial by listing stations by frequency and name, with a helpful cross referencing of stations to show parallel channels. There is also data on transmitter power and individual sites, plus comprehensive contact information for each station.

The book costs £2.50 including postage in the UK, £3.00 in the rest of the world and can be ordered from the **British DX Club, 126 Bargery Road, Catford, London, SE6 2LR.**

Station News

Danish-based short wave station **World Music Radio**, beamed around the world from South Africa's Meyerton transmitters, closed at the end of August. The owner, well-known DXer **Stig Hartvig Nielsen**, blamed the station's inability to sell a single commercial and the lack of listeners who supported the station through sales of its merchandise. Nielsen said that the only interest from listeners was in the form of reception reports and requests for WMR's QSL card.

This is the last month to hear the **Voice of Free China**. The Taiwan station will be renamed on 1st January 1998 as **Taipei Radio International**. English is beamed to Europe at 2200UTC for an hour on 15.60 and 17.75MHz.

And Finally

That's all for this month - and this year. I'll be back in the January edition, reporting on more of the exciting developments in international short wave broadcasting that will keep you scanning the broadcast bands throughout the New Year. Until then, good listening and Merry Christmas!

END

FOCAL POINT

Graham Hankins G8EMX rounds off the year with some surprising information together with all your ATV news and views received over the last two months.

In October's 'Focal Point' I hinted at some surprise news - and here it is. Birmingham may soon have its own 10GHz (3cm) and 1.3GHz (24cm) Amateur Television repeaters! The 10GHz unit will be located in Sedgley, which is to the west of Birmingham, while a site on a high point north of the city has been offered for the 1.3GHz repeater.

The **Beacons Repeater Group**, (with **Alan Kendal G6WJJ** as chairman,) was formed on September 10 1997 to manage the 10 and 1.3GHz ATV services. Alan, who has already built, and is developing, some of the 3cm hardware, says: "The channel that I will be applying for is RT103, which uses frequencies of 10.135 for the transmitter and 10.425GHz for the receiver. In addition to the Radio Amateurs present at the Repeater Group meeting, several others have expressed their interest".

Hardware for the 24cm ATV repeater already exists, too. Your scribe G8EMX has a transmitter, p.a. and receiver available for use in a repeater, together with a substantial quantity of very high quality professional coaxial feeder in his loft!

In my opinion, putting an ATV repeater into service is no easy task. The Radio Society of Great Britain's Repeater Management Committee (formerly 'Group') provides *A Guide to Repeater Licencing* and Version 1997 runs to 92 pages. The technical specifications for any repeater are very 'tight' and a Repeater Group's responsibilities for on-going service and close-down compliance are considerable.

Here in Birmingham I have been attempting to start a 1.3GHz ATV repeater for some time. One of the first essential requirements is an available site.

Over the past few years three likely buildings in Birmingham, although offered, failed to become realities for various reasons. Access by close-down operators, at any time, is essential, so to, I consider, is straightforward access for periodic development - especially during the initial period of service. I trust that both of the sites now offered will prove quite satisfactory in these respects.

Incidentally, the *Guide to*

Repeater Licencing contains an Appendix 'A', titled 'Responsibilities of a Repeater Keeper'. Appendix 'A' states that the Keeper can delegate but remains **ultimately** responsible for, among many other things, Communication/Liaison; for example - "To be the contact for other parties who require information about the repeater". So, why is it that some repeater keepers, and occasionally other members of a Repeater Group's committee, are 'Particulars Withheld' in the RSGB *Callbook*?

Auckland ATV

"Hi Graham", says **Michael ZL1ABS**: "The **Auckland ATV Interest Group** (of the AK VHF Group inc.) attended the Hamilton Radio Club's sale day at the Claudelands showgrounds, along with a lot of amateurs from the top half of the North Island. Our table raised about \$40 NZ for ATV repeater funds from the sale of donated components magazines, cable, meters and old radios".

After the show, some of the ATVers from Auckland went on to **Jerry ZL1RN**'s home for more conversation and to see some of his steam railway tapes. Jerry used to work on the railways and is qualified as a Fireman for steam engines.

But back to ATV in New Zealand. Michael ZL1ABS continues: "Grant ZL1WTT and Wayne ZL1UJK have just achieved P4 copy on 23cm FMTV over 15km. They achieved this contact with a home-brew transmitter and a TV Receive Only rig with in-line preamplifier."

"Thanks to the **Sevenside ATV Group** (Bristol) for ideas from their newsletter 'P5', the **British Amateur**



Fig. 1: Anglesey 1.3GHz ATV repeater GB3TM as commonly received in Dublin by Dave Hooper EI2HR, with John Lawrence GW3JGA in vision.

TV Club's magazine 'CQ-TV' and 'Amateur EYE' from the **South East Queensland ATV Group** for material that helped get things going".

The knowledge gained from Wayne and Grant's contact will help with the construction of a translator to 23cm to extend the coverage of the **ZL1BQ** ATV repeater in Auckland.

One of these fine months I am hoping to go to New Zealand for a few weeks, see some of their repeaters and maybe meet up with some of the ATVers in person. When I do, Michael has given me the name of his excellent local fish shop!

Talking Television

Some Amateur Radio clubs have responded to my offer to give an ATV talk. The latest Club to request a visit is the **Moorlands and District ARC**, near Stoke-on-Trent.

Moorlands Secretary, **Warwick Hutchings**, has provided a map for me to find their meeting place and, very helpfully, an audio tape cassette of directions to use in my car as I drive there! Moorlands ARC meets in the area served by the Stoke ATV repeater **GB3UD**, so we may be able to use the repeater on the night.

My offer of an ATV talk and demonstration is still open to any Clubs with a 'speakers calendar' to fill.

Irish News

Now some brief but fascinating news from Dublin, Eire. **Dave Hooper EI2HR** writes: "During the weekend August 9/10, the Dartmoor 1.3GHz repeater **GB3WV** was received by **Dermot EI2AK** in Monasterboice, County Louth. Some 'P5' pictures (high quality) were exchanged with **G8CEQ**, **G1YHN** and **G6URM**; this is the first time that **GB3WV** has been received in Eire".

So I spread my map out. County Louth is not marked, but the straight-line path length from Dartmoor to Dublin looks like around 400km, which is quite remarkable. Of course, whatever their frequency, r.f. signals can and sometimes do behave in quite extraordinary ways. Thanks for the news Dave!

For instance, I remember reports of mobile radio calls propagating around the world, direct from handset to handset, under extremely rare meteorological conditions. Exceptionally long v.h.f., u.h.f. and microwave path lengths can happen, but don't depend on them occurring very often!

Amateur Television A to Z

Here's the final instalment of my ATV alphabet.

Up-converter: Enables a 436MHz ATV signal to be received on a domestic TV.

Weatherproofing: To prevent corrosion where a feeder meets its antenna. Self-amalgamating tape is effective.

Y: Symbol for Luminance, or the 'brightness' part of a colour TV waveform.

Z (Ω): Symbol for impedance. ATV uses two impedances, 50Ω for r.f. cables, 75Ω for video feeds. Mismatching causes standing waves at r.f., picture distortion along vision channels.

So, that has been the ATV 'picture' for 1997. I wish all readers of 'Focal Point' a very Happy Christmas and New Year.

Keep sending those reports, and newsletters to me, **Graham Hankins G8EMX**, **11 Cottesbrook Road, Acocks Green, Birmingham B27 6LE**, or by Packet to **G8aEMX @ GB7SOL.#29.GBR.EU** Cheerio for now!

END

Advertisements from traders or for equipment that is illegal to possess, use or which cannot be licensed in the UK, will not be accepted. No responsibility will be taken for errors.

You should state clearly in your advert whether the equipment is professionally built, home-brewed or modified.

The Publishers of *Practical Wireless* also wish to point out that it is the responsibility of the buyer to ascertain the suitability of goods offered for purchase.

BARGAIN

b a s e m e n t

Compiled by Zoë Crabb

For Sale

6m (50MHz) station. Spectrum 6-10m (28-50MHz) transverter, spectrum 30W linear amp, £80. G3FDW log periodic antenna for 6m (50MHz), 4m (70MHz) and useful on 2m (144MHz), £40. Dymar 2000 2m f.m., g.w.o., £40. Jim on (01202) 578427.

70cm (430MHz) video transmitter. 10W linear (home-brew), plus 70cm (430MHz) Tonna antenna, (brand new), buyer collects, £50 the lot. Dave on 0121-552 7560.

70cms (430MHz) Storno for modification. 100 channels, includes repeater shift, comes with full instructions, new crystals (worth £15), power leads, microphones and all connectors, P&P extra or buyer collects, Norwich area. James on (01603) 737111 after 4.35pm.

A large box of bits and pieces from home-made television, made in the 1950s, 'phone for details, £10 o.n.o. Peter GW4GCB, N. Wales. Tel: (01745) 720756.

Alinco DR599E dual-band 144/433MHz mic., m/bracket, boxed, £375. Not used mobile, only little use base station, consider exchange for WXSAT receiver. G8VHG, QTHR. Tel: Hull (01482) 809274.

Alinco DX70T h.f. + 6m (50MHz) transceiver, all-mode, mint, boxed, £475. Yaesu FT-790R 70cm (430MHz) multi-mode, NiCads, charger, soft case, manual, v.g.c., £195. MuTek 2m to h.f. 9-band transverter, manual, cost, £400, accept £165. Dave G4JXK on (01329) 220753 after 5pm please.

Andrew Helix LDF5-50A coaxial cable. approx 150 feet, also Andrew elliptical wave guide A1 CV approx 45 feet, both in single lengths and in new condition, offers. Peter on (01771) 623654.

AOR AR1000 hand-held scanner. 6-600MHz, 800-1300MHz, a.m., f.m., w.f.m., mint condition, all original, accessories inc. NiCads, charger, carry case, £125 boxed and manuals. Discone antenna, stainless transmit 6/4/2/70. £25. Ross G0I2P, Cirencester. Tel: (01285) 860896.

AOR AR8000 hand-held. 500kHz - 1900MHz, no gaps, 4XAA NiCad battery, mains charger, d.c. cigar lighter plug, belt clip, case, manual, two antennas, buyer collects, £200. Tel: Merseyside 0151-733 7860.

AR8000 and Opto Scout Counter. both still under warranty, £450. Peter on (01803) 552160.

AR88. no case, HRO5T with coils, R1155 + p.s.u., not original, R208, no case, FT-101E + Z match a.t.u., LFVVM D-100V, R107, fair condition, no

case, silent key sale. Frances, Southampton. Tel: (mobile) (0958) 276905.

Army receivers. valve tester, valves, two loud speaker BTH BBC BBC amps, etc. Tel: 0113-240 3496.

ATU. global AT1000 RX only, v.g.c., £55 o.n.o. Also Howes CTU8 a.t.u., £22 o.n.o. Sinclair Spectrum plus c.w., RTTY and FAX software, £30 o.n.o. Wanted h.f. bands TX a.t.u. Andy on 0116-212 1557 after 8.30pm or (0802) 623308 mobile or 0116-286 2259 work.

Auto a.t.u. - Daiwa 500W, will work with any rig, £150. Kenwood mobile antenna, unused, AT130 a.t.u., big mag mount, £100. G3PTN, QTHR. Tel: Leeds 0113-265 4644.

BNOS 2m (144MHz) mobile linear with 100W output and 10W input, model no: LPM144-10-100, cost £300 new, will accept £125, may deliver 75 miles of Bradford, Yorkshire. Barry M0APO, Yorkshire. Tel: (01274) 880895.

Boosey & Hawkes wire recorder. pre-war, sensible offers, plus other items, valves, Universal Avometer, Selectest Super 50, microphones, Eddystone receivers, wooden radio jigsaw, collectors items. Tel: Pontefract (01977) 678593 after 3pm.

Box of valves. 100 plus other wireless parts, condensers in good condition, leakage tester valve voltmeter, sine square generator, r.f. signal generator. T. R. Carless, 10 Anson Green, Royal Oak, Gwent. Tel: (01633) 279461.

Brand new boxed and never used BT DF50 telephone FAX machine with photocopy facility, hands free dialing, auto identity, bought for business that never took off, swap or sell computer, radio, etc. Tom on (01536) 522007, any offers considered.

Codart AT5 TX. Tel: SW London area 0181-946 6145.

Collection of 19 old fashioned transistor radios. £75 the lot. Also about 80 PW, SWM and RadCom magazines, offer, £20+. Tel: Guildford (01483) 233830.

Collins Model TC110 transmitter receiver with matching p.s.u., spare valves, dynamotor audio amp 1943 with original handbook, used for receive but will transmit, US Navy, very heavy, room needed, £325 + carriage. Tel: W. Midlands 0121-520 9686 after 6pm or weekends.

CR300 RX for restoration. £40. Crystal calibrator No 5 MkII, complete in wooden case, £20. Buyer collects or pay carriage, may swap, w.h.y.? Richard G7RVI on (01989) 769654.

Cubical quad suitable for

10/15m (28/21MHz) with rotator, mast support bracket, control box, cables, etc., £200. No offers. Vectronics VC300 DLP a.t.u., £80 or offers, all in good working order. Keith on (01642) 320008 or leave message on answerphone.

Diamond X700H 2m/70cm (144/430MHz) dual-band collinear, 7.2m long (in 4 sections) with 9.3dB on 2m (144MHz) and 13.0dB on 70cm (430MHz), cost over £200 new, will accept, £95, no offers. Barry M0APO, Yorkshire. Tel: (01274) 880895.

Disposing large quantity electronic large items. transmitters, receivers, teleprinters WW2 - 1965. VGA SVGA monitors, printers, 50MHz oscilloscope, etc., send stamped addressed envelope for list, 'phone first on (01908) 373114 (Bucks area).

DNT 10m (28MHz) mobile. 2.5/25W, Tonno 5000E data rec./send RTTY, AMPTOR, PACTOR, c.w., inbuilt Morse tutor, monitor internal. Buyer inspects and collects. Jack on (01946) 810043.

Drake R8E. 0.15-30MHz continuous coverage, RRP £965, plus fitted v.h.f. converter, 35-55MHz, 108-174MHz, RRP, £195, mint condition, boxed, manual, cash, collect for bargain price, £750. Tel: (01502) 711880.

DX394 receiver. 150kHz to 30MHz, pristine condition, full service manual, boxed, £170. Eddystone EC10, solid state h.f. RX, nice condition, g.w.o., mains p.s.u., spare battery box, service manual, no mods. R. Taylor, 23 Lancaster Close, Bolton BL1 1PJ.

Eddystone 358X. 870, 870A, 750, EC10, scrap 770U, some others. Peter Lepino, Surrey. Tel: (01372) 454381 or (0374) 128170 anytime!

Eddystone 840C. nice condition, working, classic h.f. RX, c/w copy handbook, circuit, alignment info, etc., £110 or straight swap for similar nice condition f.w.o. model 770R. Howard, 9 Pembroke Court, Northgate, Newark, Notts NG24 1HE.

Eddystone receivers. all v.g.c., 358X p.s.u. coils in box, £110. EC10, two available, £50 and £85. 870, 870A, £75 each. Some rare spares, ask! All plus post, etc., collection recommended. Peter Lepino, Surrey. Tel: (01372) 454381 or (0374) 128170 anytime.

Excellent condition Icom IC-T42E. complete with wall charger, battery pack, antenna and original packaging, very good over-all transceiver for all levels of skill, £175. Barry Martin, Margate. Tel: (01843) 226561.

Free, approx 3000, unboxed,

some used, but mainly new, assorted radio valves. Also free, approx 43,000 new, boxed, assorted radio valves, to the buyer of approx 13,000, tubes, cathode ray, picture, monitor, radar, industrial, medical, rectifiers, transmitting, receiving, amateur, professional, klystrons, audio, r.f. laboratory, special, nuvitors, nixie, diodes, triodes, tetrodes, pentodes, multi purpose, etc., manufactured by RCA, Sylvania, Heinz and Kaufman, US, G.E. Eimac, Taylor, International, Siemens, Philips, Mullard, Amperex, Marconi, Brit G.E.C., Osram, Raytheon, Eng Elect., etc., etc., all at £3 each. Also free expert packing in multi layer cartons for export. Also free documentation and UK customs declarations, no lists available. Please no agents or brokers. On site inspection invited and welcomed. Private seller Gerald Levien B.Sc (Eng), Electrical Engineer, Tel: 011 708 1157 Gauteng South Africa, FAX: 011 794 1938, Gauteng South Africa.

FT-26 Yaesu 2m (144MHz) hand-held with two NiCads, cell case, fast 1hr charger, cigar lead, case, boxed, £200 o.n.o. Icom U16T 99ch p.m.r. 70cm (430MHz) hand-held, cigar lead, Z cell, cases, boxed, £130 o.n.o., 12.5kHz. Steve G7PWH, Sussex. Tel: (01444) 441460 answerphone, please leave message if not in.

FT-26 Yaesu hand-held. 2m (144MHz) with two NiCads, cell case, cigar lead + 1 hour fast charger, soft case, 12.5kHz spacing, boxed, £200 o.n.o. Steve G7PWH on (01444) 441460 answerphone (Sussex) or (01444) 482034.

FT-26R 145MHz hand-held. NiCad and charger, soft case, speaker, mic., VOX headset, mobile mount, CTCSS fitted, excellent condition, boxed, £150 or exchange for 25/30 amp p.s.u., in excellent condition. Dave G1HDZ, Guildford. Tel: (01483) 892390.

FT-480 2m (144MHz) multi-mode. £230. Kenwood TH-215E hand-held, case, charger, boxed, £125. 2m (144MHz) base antenna, £30. S/steel discone with 2m (144MHz) TX, £35. Discone, £20. G- whip 2m (144MHz) antenna, £10. Barrie, N. Wales. Tel: (01745) 591704.

HRO receiver plus 9 coils. power unit and manual, also R1475 receiver with power unit and new copy of manual, £50 each plus carriage. Peter on (01771) 623654.

IC-706. £630. IC-721S special QRP model of IC-725, £450. KW107 a.t.u., £125. KW Match, £15. LP filter, £15. Heathkit IO18U scope, £20 (collect). Various KW Ten Tec manuals, £5 each. Class 'D' w/meter, £10. Tel: Sheerness (01795) 873100.

IC-P2E. £110. 2m (144MHz) hand-held, TR-7730 2m

FREE ADVERTS

Now's your chance to send in a photograph of your equipment (a good idea if it's really unusual) to accompany your advert. Please note that all photos will only be published at our discretion and are non-returnable.

When sending in your advert, please write clearly in **BLOCK CAPITALS** up to a maximum of 30 words, plus state your contact details. Please use the order form provided.

(144MHz) mobile, £120. FT-780 70cm (430MHz) all-mode mobile, £250. All v.g.c., all o.v.n.o. John G6UVU on (01902) 681961.

Icom 735. Icom HM-12, AH2, AT120, service manual, 735 instruction manual and service manual, all in mint condition, £550 o.n.o. Elvis G0MWM, QTHR. Tel: (01253) 852116.

Icom IC-451E 430MHz multi-mode transceiver. 10W output, mains or 12V, good condition, £275 o.n.o. Collect or carriage extra, 10GHz WG16 to SMA transition, £25. Bob G8VOI, Waterlooov. Tel: (01705) 250830 after 6pm please.

Icom IC-725 h.f. transceiver. general coverage RX, f.m. unit fitted, £495 o.v.n.o. AEA PK900 multi-mode terminal unit with PC Packrat v.2 and AEA FAXIII, £275 o.v.n.o. Both boxed and superb condition. G0FRQ, QTHR. Tel: (01757) 638551 or E-mail Peter_Charlesworth@email.msn.com

Icom IC-725 h.f. transceiver. Icom SM-8 desk mic., Welz s.w.r. power meter, mod SP225, £450. Tel: 0117-964 0809

Icom IC-735 with EX243 electronic keyer unit and 250Hz filter, AT150 auto a.t.u., £800 o.n.o. Yupiteru MVT2000 multi-band scanner, charger, etc., £250. Sony ICF SW7600, £100 as new, manuals, boxed. Colin GM0AVR, Shetland Islands. Tel: (01806) 242836.

Icom IC-745 h.f. TX general coverage RX, mint condition with box and manual, £375 o.n.o. Tel: Co. Down (012477) 29689.

Icom R70 GC/RX. new condition, manual, etc., Icom fitted c.w. and f.m., original carton packing, also KW Vespa 2 + mic., and KW p.s.u., manual, excellent condition, no mods, moving to smaller room. Raymond 2E1CQL, Northampton. Tel: (01604) 24486.

Icom R7000 in excellent condition with remote control and manual. £475. Timewave DSP599ZX, only months old, mint, £225. John, Tayside. Tel: (01356) 624039 anytime.

Icom T7E 2m/70cm (144/430MHz) handie. case, NiCads, charger, boxed, £195. AOR 8000 scanner, three months old, NiCads, charger, boxed, £230. Weller PS2D soldering station, boxed, £30. Would exchange some for FT-690R II. Terry G4OXD on (01462) 435248 after 6pm.

In very good condition copies of Practical Wireless and Practical Television, dating from 1945 to 1987, total, approx 500. To view or offer price, Tel: (01204) 592124.

Jaybeam six element quad Yagi

(144MHz), £20. Sangean ATS-803A with p.s.u., manual, boxed as new, £60. Dave, Glasgow. Tel: 0141-632 5408.

Kenpro KR400 RC horizontal rotor/controller/cable/clamps, new, BNOS L432-10-100 linear amp, new, BNOS power supply 12V/25A, new, Maldol HS-770 duplexor 2m/70cm (144/430MHz), new, sensible offers, must sell. Tel: (01953) 603470.

Kent keyer, speed pitch tune volume, £20. Kenwood TS-830S, VFO230, filters, 230 a.c., 12V d.c., £575. Daiwa 9-band a.t.u., £80. Eddystone bug key, Sony ICF-2001 L.w.-30MHz with adaptor, £75, all o.v.n.o. Tony G3KDP, Devon. Tel: (01752) 768298.

Kenwood 450S h.f. transceiver, mint with all original packing, £695. Icom 726 h.f. transceiver with 6m + p.s.u. PS55, mint condition and boxed, £595. Tel: Wimborne (01202) 695350.

Kenwood 751E, all-mode, £300. To include 8-element Yagi, also 2m (144MHz) antenna, G400 rotor with direct box and cable, stab power unit, also useful bits and bobs. G7HPZ on (01205) 750694.

Kenwood TM702 dual-band f.m., mobile, 25W, extended receive, excellent condition, inc. duplexer, £275, boxed and manuals. Ross G0IZP, Cirencester. Tel: (01285) 860896.

Kenwood TM732E dual-band mobile, boxed, with manual, mobile bracket, mic, and power lead, £280. G3FUN on (01795) 532608.

Kenwood TR9500 70cm (430MHz) multi, £250 o.n.o. Tri-band h.f. quad, brand new, cost £430, accept, £195 o.n.o. Vacuum capacitor, 8kV, 10pF to 1000pF, £35 new. Mike on 0181-423 0576.

Kenwood Trio TR7800 2m (144MHz) f.m. transceiver, £160. Yaesu FT-290R multi-mode, £190. Spectrum transverter, 2m (144MHz) to 6m (50MHz), 25W output, 2.5W input, £200 or FT-290 plus transverter, £365. G0XBO, Norfolk. Tel: (01485) 532638.

Kenwood TS-180S h.f. TX/RX intermittent fault on 160m (1.8MHz), mint condition, with manual, £220 o.n.o. Tel: Dereham (01362) 821102.

Kenwood TS-430 and PS-430, good condition, service manuals, £450. G4FOY on (01420) 82855.

Kenwood TS-440SAT, narrow s.s.b. filter, matching speaker, hand/desk mics, mint condition, £650, boxed and manual. Ross G0IZP, Cirencester. Tel: (01285) 860896.

Kenwood TS-530S, extra v.f.o., c.w. filter, etc., excellent, £325. Trio TS-700G 2m (144MHz) multi, mint, £225. Icom IC-271E 2m (144MHz) multi, mains/12V pre-amp, 100%, £325. KW201 receiver, exceptional, £85. Genuine items for cash/buyers collect. Tel: West Midlands 0121-474 4856.

Kenwood TS-670 four bander, 7, 21, 10, 50MHz, all modes, a.m., f.m., s.s.b., with extra filters, boxed, mint with GC-10 board making it RX, 500kHz to 30MHz, sell, £500 o.n.o. Swap dual mobile TX (new one). Mike 2E1FCG on (01226) 742971 after 5pm.

Keys, RAF, 10F/7741 in original packing, £20. RCAF 10F/556, £30. Early classic US telegraph key, AT&T 1A, £30. All post paid. Colin Waters, 1 Chantry Estate, Corbridge, Northumberland NE45 5JH.

KLM34XA 6-element beam, £300. Butternut HF2V Top Band coil, £115. TH3 tri-band, £100. MFJ 941D a.t.u., £75. Hy-gain 7MHz 2-element beam, model 402BA, £300. Tail Twister T2X rotor, £200. Tel/FAX: (01279) 503332 evenings 6pm.

KW Vespa MkII, mic., p.s.u., Philips PCR GD, silent key sale. Frances, Southampton. Tel: (mobile) (0958) 726905.

KW1000, new 572Bs, £300. KW107, immaculate, £100. Tait 2m (144MHz) 6 channels fitted, S20, S21, R4(VA), £50. Tait 70cm (430MHz) 6 channels fitted, SU20, SU16, 433.300, £50. Both 25W, FR100B, FL200B, pair, £100. Alex G0JZE, Chipping Norton. Tel: (01608) 643585 after 6pm please.

KW2000 CAT power supply, as new, £25 o.n.o. Peter GW4GCB, N. Wales. Tel: (01745) 720756.

KW2000B with matching p.s.u., both in v.g.c., plus manual, spare valves and s.w.r. meter, £145. G3AIO, QTHR. Tel: Kent (01892) 822836.

Lowe HF-150 and p.s.u., excellent condition, £250. Lowe IF-150 and s.ware, £30. Alinco DJ-X1 wide band hand-held receiver, £180 o.n.o. JIM p.s.u. 101A Mk5, £30. All items good order. Colin on (01475) 786831.

Lowe HF-150 receiver in excellent condition, £230. Yupiteru MVT-7100 scanner, all-mode, full coverage, £170. Kev on (01869) 600049 weekends/answerphone.

Marconi TF2015 signal generator, 10 to 520MHz, a.m./f.m., good condition, £120. Icom IC-451E 430MHz multi-mode base station, 10W output, mains or 12V, £275. Robot 400 SSTV clone, £20. Carriage extra. Bob G8VOI, Waterlooville. Tel: (01705) 250830 after 6pm please.

Motorola MC80 12 channel v.h.f. transceiver, £20. Pye Europa three channel v.h.f. high band, £15. Pye Westminster W15 a.m., v.h.f., dash mount, £15. Motorola Maxar v.h.f. dashmount, £15. Alistair GM4UQD. Tel: (01506) 467351.

Multi 700EX 2m (144MHz) f.m., 1-25W, boxed, good condition, power supply regulated 13-8 Watson W-30 ant., all as new, the lot for, £120 o.n.o. Tel: Chesterfield (01246) 236496.

PA valves 4CX250 (CCS1) B & O blocks, QQV06, QQ20 by EIMAC and STC, brand new, sealed, boxed, heat sinks for 4CX250B (conduction type), not many left, cheap, to clear shack. Ken G4ZLX on (01258) 455507 weekends only or write QTHR.

Pair magnetic loop antennas, 3.5-11MHz and 14-30MHz, £60 pair. 70cm (430MHz) 3 x 5/8 co-linear base antenna, £20. 2m (144MHz) 2 x 5/8 co-linear base antenna, £20. Tel: Worcester (01905) 451805.

Pye L434 1.5GHz data link equipment, complete system, dual RX/TX, 19in cabinets, ideal conver 23cm (1296MHz) packet node link, working 24V, buyer

collect (van), offers, s.a.e. for data sheet. Colin M0AFW, Sheffield. Tel: 0114-251 1098 evenings, QTHR.

Pye M4000 mobile telephone v.h.f. high band, on the old BT system 4, complete unit, very clean, good condition, 'phone for details, £25 o.n.o. Peter GW4GCB, N. Wales. Tel: (01745) 720756.

R1155, good working order, including power supply, £75. Plessey PR155G receiver, excellent condition, £150. Ex ministry 270 valves for sale, many new, ex-ministry, offers accepted, buyer collects. Keith on (01942) 745512.

R210, ex-mod h.f. receiver, 2-16MHz, good condition, includes manual, mains transformer, p.s.u. and G5RU antenna, £30. 'Phone for details. Tel: Cheshire (01606) 836133.

Racal RA117C2 h.f. RX (broadcast monitor version without crystal filter), g.w.o., manual, trade for RA17T18 or sell, £110 o.v.n.o. Also Murphy B40B, working, manual, £30. Neil G8LIU, Middlesex. Tel: (01895) 230006.

Racal RA17 MkII, g.w.o., 0.5 to 30MHz with handbook, £90. PCB UV lightbox, £25. Tel: Redruth (01209) 216434.

Racal RA17 receiver, good condition, full working order, £130. Ralph, Wakefield. Tel: (01924) 366072.

Racal RA17L receiver, very good condition with service manual, together with RA37 low frequency converter, £165 o.n.o. Peter GW4GCB, N. Wales. Tel: (01745) 720756.

RCA AR88LF receiver oscilloscope, type TF1330 oscillator, model D-890-A voltage stabilisers, Windsor signal generator, audio oscillator, type 440A (and many more). Geoff, Bristol. Tel: 0117-979 1477.

Realistic HTX100 28MHz s.s.b./c.w. mono bander, 5/25W out, as new, £120. Icom AT-160 auto a.t.u., £200. Icom PS55 p.s.u., £100. Both as new, boxed, Yaesu MD1 base mic., £60. 2m (144MHz) 9-element X tonna, £40. Rotator, £50. Tel: Watton (01953) 884305.

Realistic PRO-34 hand-held scanner, 200 channels, all usual frequencies, plus 806-960MHz, good condition, a.c./d.c., complete with charger, £100 inc. P&P. Dave Wilkinson on (01983) 854766.

Realistic PRO2004 and PRO2005 scanning receiver, 25-520MHz, 760-1300MHz, 400 memories with manuals, £150 each o.n.o. John Wilson on 0181-769 0147.

Robot 400 SSTV clone, £30. W9GR d.s.p. filter, kit version, £75. NEC PC8201 lap top computer, £30. Marconi TF2015 signal generator, £120, carriage extra. Bob G8VOI, Waterlooville. Tel: (01705) 250830 after 6pm. please.

Rotators: AR40, £75. G250, as new, £75. Daiwa M750 h/duty, £150. TS-700G v.h.f. multi-mode base, £225. Bird Thru-line, three inserts, offers, X30 colinear, new, £40, v.h.f. 30W amp, £40. Capco balun, £15. Tel: (0468) 756762 anytime.

Short Wave Magazines, Oct 1989-April 1993, £10. Practical

Wireless Encyclopaedia by F. J. Camm (9th edition), July 1941, in excellent condition, offers. Assortment of components, books by Mike Tooley, Electronic projects IV, test gear projects, £5. Tandy books, getting started in electronics with eight engineers handbooks, construction techniques using breadboards, £5. Mike, Livingston. Tel: (01506) 493959.

Shure 401 mic., £30. Yaesu YD844 mic., £25. Wanted Nye Viking key, Kenwood SP940 + MC85, G3XZF, QTHR. Tel: (01945) 588102.

Silent key sale: Yaesu FT-990, £900. FC-902, £60. FT-7, £80. FT-23R, £75. FT-290R, £140. FL-2100, £300. FT-101Z, £175. Altai dip meter, £20. Most manuals/boxes, prefer collect. Tel: (01270) 812312.

Six metre 5-element Tonna beam, v.g.c., nearly new, £45, plus postage. Tel: Newcastle-Upon-Tyne 0191-266 1255.

Sony SW800 world band, £70. Sony 7600DA 15-band, £70. Grundig Traveler MkII 7-band, Toshiba FIL 11-band, Philips AE 3405 12-band, Sony 7600D, Grundig Boy-230 16-band, Roberts R-808, Sony WA8800 radio + cassette, £70 each. FRG-7700 + FRV-770 + FRT-7700, v.g.c., £300. B40-D, £60. Trio 1000, £190. Tel: 0181-813 9193.

Ten Tec Scout 80m (3.5MHz) module, £20. Tel: Leics (01455) 273042.

Three Army sets, R107, R208, R308, two valve testers, lots of valves. Tel: 0113-240 3496.

Timewave DSP599XZ, top of the range d.s.p. filter, hardly used, mint condition, boxed, cost £350, sell for, £225. Derek on 0191-252 8417.

Tonno data decode/sender, c.w., RTTY, AMPTOR, Morse tutor, internal monitor, keyboard, good condition, DNT 10m mobile, 40 channel, 400mW-4W modded CB 29.3101-29.500, Tel: Cumbria (01946) 810043.

TR-751E 2m (144MHz) multi-mode, boxed, operating manual, v.g.c., £300. Alinco DR599E 2m (144MHz) + 70cm (430MHz) dual-band mobile, front demount kit, CTCSS mod, boxed, operating manual, v.g.c., £425. Allen, Romford. Tel: (01708) 764014.

Trio Kenwood TS-120S h.f., c.w., s.s.b. transceiver, 100W, v.g.c., £255. Complete with all leads, manual and microphone, very good value. Stan G3XON, 14 Dagden Road, Shalford, Guildford, Surrey GU4 8DD, Tel: (01483) 536953.

Trio R600 receiver, good condition, in original box with manual, £100 + carriage. Tel: (01389) 873563.

Trio TR-9130 2m (144MHz) all-mode transceiver with system base B0-91A and SP-120 speaker, £325. G4UVT, QTHR. Tel: N. Manchester 0161-655 3128.

Trio TS-430S, AT230, PS430S, SP430S, MC60 Morse key, multi dipole, all immaculate, £650 o.n.o. Tel: Derby (01332) 831300.

Trio TS-520 plus v.f.o. 520S, pair, £200 o.n.o. Also Yaesu FT-101ZD, £250. All mint condition, buyer collects. G3NSG, QTHR. Tel: (01282) 813892.

Trio TS-520 transceiver with s.s.b./c.w. filters, g.w.o., little used, good starter rig, £210. Howes DFD4 digital frequency counter for use with TS-520, £40. Tony G0WEK, High Wycombe. Tel: (01494) 520104.

Trio TS-700 multi-mode, analogue display transceiver, built in mains p.s.u., v.g.c., £250 o.n.o. Stan, Essex. Tel: (01279) 869214.

Trio TS700G, mint, £225. Kenwood TS-530S, mint with all the extras, £325. Icom IC-271E, mains, £325. Yaesu FT-5100 under guarantee, £300. Eddystone 770R with matching speaker, refurbished, £95. Daiwa 2m (144MHz) RX, £35. Wanted transverter 6/2m i.f. RN Electronics type preferred. Tel: West Midlands 0121-474 4856.

TS-850S, boxed, with manuals, hardly used, £750. 30A power supply, £50. KW107 a.t.u. and manual, £50. Kantronic KAM, boxed, £200. Low pass filter, £50. 2m/70cm (144/430MHz) s.w.r. meter, £25. Wedding forces sale! Adrian, Swansea. Tel: (01792) 299687 evenings or (0374) 645623 mobile.

TS-950, digital, all filters, txco, MC85 microphone, original packing, £1400. G3PTN, QTHR. Tel: 0113-265 4644.

Unitron 20 computer (286) with printer and mouse, suitable for packet, £130 or exchange for dual-bander. Tel: (01827) 58605.

Unwanted gift, complete CB base mobile station, antenna transv, s.w.r. meter, mic., cables, the lot for, £60 or exchange for s.w. receiver, w.h.y.? John on (01634) 233058 after 6pm.

US Army R-174 receiver, 1.5-18MHz, correct p.s.u., shock-mounted case, v. scarce, £170. Eddystone 504 receiver, 58-30.5MHz, manual, £110. 1/2kW h.f. c.w. TX, Geloso v.f.o., 813 final inc. valves, £95, pair AR88S (less valves), £60. Burndept v.h.f. a.t.u., no. 6, £35. Tel: Yorkshire (01482) 869682.

Yaesu FT-1, good condition, solid state, 100W full coverage h.f. transceiver, boxed, built-in p.s.u., £475. Also Collins TCS10 transceiver, 1943, very heavy spare valves, etc., room needed, £250 + carriage. Tel: 0121-520 9686 evenings or weekends.

Yaesu FT-290 MkII multi-mode, v.g.c. with 2 sets of NiCads, £325. MML 144MHz linear, 3W in, 100W out, as new, £150. RN 2-6 transverter, 25W, as new, £150. Tel: (01929) 520459.

Yaesu FT-290R with battery charger, NiCads, carrying case, power meter, mobile magnetic mount antenna, £200. 2m (144MHz) cross polarised Yagi antenna plus cables, (8-element), £30. Tel: Kent (01634) 300544.

Yaesu FT-301, Yaesu FC-301, both with manuals, also RMS 25 amp p.s.u., all in v.g.c., £450 o.n.o. A. Brown, 3 Tyn-y-Cae, Newborough, Anglesey, Wales LL61 6SW.

Yaesu FT-41R 70cm (430MHz) transceiver, excellent condition, boxed as new, has been wide banded and comes with various accessories, e.g. speaker mic. and charger, etc., £350 new, will sell for, £200. Richard on (01843) 220657.

Yaesu FT-690II multi-mode, FT57A, c.t.c.s.s. board, MMB1 mobile mount, telescopic whip antenna, BNOS, 50W

amp/Gasfet pre-amp, both totally as new, manual, boxed, never used outside shack, £425, postage extra. Tel: Norfolk (01953) 884305.

Yaesu FT-747GX f.m. board, narrow c.w. filter, boxed, manual, good condition, £350. Tel: Aylesbury (01296) 747013.

Yaesu FT-757GX h.f. all-mode 100W 2X FC-757 AT auto a.t.u., FP-757 H/D p.s.u., FP-757GX light duty p.s.u. 2X Kenwood TR2600A hand-held, mint, leather case, will split, swap, w.h.y.? up or down. Tel: (0831) 660944 day or (01438) 750450 evenings/weekends.

Yaesu FT-757GX plus FP-757HD, g.w.o., £450. Yaesu FRG-7, classic, g.w.o., £125. Realistic receiver, 15-30 DX160, g.w.o., £45. Lafayette KT320, g.w.o., £40. 1155, complete, rust, dust, spiders, £30. Buyer collects. John on (01795) 880301.

Yaesu FT-767 + 2m auto a.t.u., p.s.u., hand mic., boxed, manual, £725. Richard, Bedford. Tel: (01234) 781862.

Yaesu FT-8500 transceiver, mobile, boxed and very little used, in as new condition, £375. Tel: London 0181-785 7314.

Yaesu h.f. gear, FRDX 400 RX and FLDX 400 TX in good condition with built-in 6m (50MHz) and 2m (144MHz) RX inc. Yaesu spkr., £230 o.n.o. Can deliver approx 25 miles. John G6YDN, QTHR. Tel: (01298) 812172 or (0378) 545130.

Yupiteru MVT-7100 scanner, 100kHz to 1650MHz with s.b. with NiCads, etc., 1000 channels, boxed, as new, £200. Dave, Derby. Tel: (0831) 497004 or (01332) 672112.

Zetagi CS7 7 digit frequency meter, £45. Zycomm p.m.r., converted for use with Tiny 2 TNC with circuit diagrams, £35. Mr M Jones, N. Wales. Tel: (01407) 763988 after 6pm.

£1 each, 200 1930s wireless magazines: *Practical Wireless*, *Popular Wireless*, *Amateur Wireless*, *Wireless Constructor* R1475, £40. PSU and cables for above, £25. Above two items fair condition, buyer collects. B. Rampton, 7 Alderbrooke Drive, Nuneaton, Warwickshire CV11 6PL, Tel: (01203) 642116.

Howes kits, QRP 80m (3.5MHz) transceiver, d.c. RX, TX, S/one, filter boards made up for working R1475 with p.s.u. John G4VPU on 0191-252 2304.

Swap for Codar AT5 and p.s.u. for advance a.f. generator, as new, 2m (144MHz) r.f. switched pre-amp, Microwave Modules, perfect condition. Tel: (01254) 832350.

Trio TS-830S and remote VFO230 for Yaesu FT-726R. Tel: (01429) 234011.

Would someone like to swap a computer, without monitor, for brand new boxed, never used, FAX machine, BT DF50 telephone FAX, photocopy facility, hands free dialing, automatic identity, cost £229.99 Argos. Tom, Northants. Tel: (01536) 522007.

Yaesu FT-480R in v.g.c. for Yaesu FTV-901R transverter, must have 2m (144MHz) and 6m (50MHz) modules. Tom Burke on (01472) 602335 evenings.

Wanted

'Low Profile' speaker for Sony ICF-M20W radio, 3in dia, 4W, 8Ω. David, Southampton. Tel: (01703) 693370.

18kHz crystal for Rascal RA218 s.s.b. adapter, Rascal badges as fitted to RA17 front panel, scrap RA17/117, RA17M RX, defunct R390A, complete or sub units for spares/repair. Neil G8LIU, Middlesex. Tel: (01895) 230006.

80m (3.5MHz) bandspread coil pack for HRO, also matching loud speaker for HRO 'period' mic., working or not, w.h.y.? Peter G4VUN, works QTH. Tel: (01287) 634397 9-5pm.

AEA IsoLoop or MFJ1786 loop, also Yaesu FTV250 and FTV650 transverters, Yaesu FR101 with i.e.d. digital read-out and any FR101 or FL101 spares or U/S units. Pete, Bristol. Tel: (01454) 887461.

All early wireless gear, crystal sets, valves, horn speakers, top prices for items made by Marconi, Burndey, Pye, BTH, Gecophone, Ericsson. Serious collector, will pay well and collect any area. Jim Taylor G4ERU, 5 Luther Road, Winton, Bournemouth BH9 1LH, Tel/FAX: (01202) 510400.

Circuit diagram for Sinclair DM350 digital multimeter, any info. and if possible non-worker for spares, must be cheap for student. Mike Sharp, 1 Winfield Grove, Newdigate, Surrey RH5 5AZ.

Circuit diagram or manual for the Olympic T100 transmitter, all expenses reimbursed. John Fallon G3SGV on (01752) 660028.

Circuit diagram/construction details to rebuild 'HAC' 1 valve s.w. receiver, C1957 design using an LD210 triode valve, originally built on wooden baseboard and used 4-pin coils. Gordon GM3ULP, 12 Airbles Drive, Motherwell, N. Lanarkshire ML1 3AS, Tel: (01698) 253394.

Circuit or manual for Eddystone 870A, also address of Eddystone Users Group. Tom Kelly EI2AJ, 32 Rushbrook, Blanchardstown, Dublin 15, Ireland.

Circuit or manual for receiver radio No 40A, SN186 made by Eddystone for B.T. loan or purchase. Neville G8NCK, QTHR. Tel: Tamworth (01827) 59423.

Eddystone 940 and 1830 (analogue) receiver urgently required in g.w.o. and condition please. Jim McGowan, 20 Keats Avenue, Romford, Essex RM3 7AR, Tel: (01708) 340304.

Eddystone EC10 MkII, also Drake SW8, cash waiting. Tel: Barnet 0181-449 3921 after 7pm.

Filament transformer 2.5V centre tapped @ 10A, 10kV insulation, for two 866A rectifier tubes. Duncan Cadd G0UTY on (01604) 460851.

German WW2 radio radar, also parts, cypher equipment of all sorts. Clandestine sets, all periods, swap or cash, w.h.y.? R. Otterstad OZ8RO, Hosterkobb, 10 DK 3460 Birkeroed, Denmark.

Good home waiting for unwanted Morse computer disc, Apple Mac or IBM compatible, retired gent, keen to learn. Bill on (01684) 295770 anytime.

Handbook for Bang & Olufsen stereo unit Beocenter, 2002 photocopy would suffice. George, Daventry. Tel: (01327) 879023.

Have you got a Kenwood p.s.u. PS430 to match TS-430S you do not want, also mic. MC60A, if so, please let me know and ring. Tel: Cardiff (01222) 512959.

Icom IC-211E for spares, consider working set if price reasonable, also wanted R109 RX for sentimental reasons. Keith G3TLB, Crowborough. Tel: (01892) 655527.

Intelligent RS232 display unit with parallel printer port and 8k memory for the ERA Microreader MkII. Bill, Lincs. Tel/FAX: (01524) 833506.

Linear amplifier 2m (144MHz) required, s.s.b./f.m., about 50W for 10W input, also 6m (50MHz) f.m. transceiver with about 25W plus CTCSS and repeater shift, must have freq. read-out, not 'channels'. Tel: (01222) 703429 with details and price please.

Matching speaker for HRO RX, also period microphone, w.h.y.? Good prices paid + P&P. Peter, works QTH, on (01287) 634397 9-5pm.

Military items: RXs, TXs, etc., also old Morse keys, Eddystone EC-10 needed and valves VR18, VR27, VR21, VR118, VT50, VT51, CV465, CV466, CV469, EF72/3, EA76, QS1202 No11, 12, 21 Set. Ben, Worcestershire. Tel: (01562) 743253.

Morse Tutor, complete with key and manuals, also Antron 99 CB aerial. Tel: Hants (01329) 315789.

Original Admiralty Handbook on B40 series of Naval receivers, not photocopy. John G3SZM, Worthing. Tel: (01903) 241810 after 8pm and at weekends.

Rascal 1792, Redifon R500, Eddystone 1650 or Watkins Johnson 8626A-4 receiver in not working condition, at a reasonable price to repair for disabled s.w.l. Dave Jones, 50 New Dock Street, Llanelli, Dyfed SA15 2HB, Tel: (01554) 775790 or E-mail: Daiungoed@aol.com

Scrap WS38 MkIII, must have Bowden cable control switch, Soviet 'bloc' radios R106, R112, R116, R130, R323, others considered, also German WWII army radios, private collector. Bob Warner, 45 Eastry Close, Ashford, Kent TN23 5RS, Tel: (01233) 636185.

Software for CBM64 on disc, 5 1/4in floppy, to buy or copy. J. J. Sales G0AZJ, 6 Ennerdale Close, Lancaster LA1 3NB.

Spy 'clandestine' radio sets wanted by private collector, American, British, French, German, Polish, Russian, etc., good price paid for the right items, write with details and price wanted to: Bill MacDonald, 40 Latchett Road, London E18 1DJ.

Standard C58 2m (144MHz) multi-mode scrapped for spares, including any accessories. Mike G0IFN, Dorset. Tel: (01258) 456192 after 6pm.

Trio/Kenwood power supply PS-430, good condition, prefer boxed with instruction, output power cable for TS-430S, also SP430 external speaker. GW4XKE, Cardiff. Tel: (01222) 512959.

Universal M8000 or Wavecom decoder, must be as new, £750 offered with video unit and manual. Tel: Dublin 01 453 6452.

Woden mains transformer type SRS/152/T secondary 670/0/670V at 160mA wanted to repair old power supply. Denis G3UVR on 0151-652 7454 day or 0151-342 7880 evenings.

Yaesu FP-707 power supply wanted, might consider non-working one. Dave on 0141-632 5408.

Yaesu FRG-7700 memory unit, also YR-901 Morse code and/or RTTY monitor plus YVM1 video monitor, must be full working order, expenses repaid. Guy, Northants. Tel: (01327) 879902.

Yaesu FT-757GXII, FC-757AT automatic a.t.u., FP-757HD (p.s.u.), must all be in excellent condition. Paul M1BOY on (01702) 528288.

All adverts should be sent to:-

Zoë Crabb, PW, Bargain

Basement Free Ads,

Arrowsmith Court, Station

Approach, Broadstone,

Dorset BH18 8PW.

BARGAIN BASEMENT ORDER FORM

Please insert this advertisement in the next available issue of *Practical Wireless*.

☐ FOR SALE

☐ WANTED

☐ EXCHANGE

Name

Address

Telephone Number

CONTACT DETAILS FOR ADVERT.

Please only write in the contact details you wish to be published with your advert, ie. do you want your name & address, or just your telephone number?

Your advert, you decide!

please
write
in
block
capitals

(30)

(12)

SRP TRADING



Antenna Rotator AR-300XL
Max load 60kg (with support bearing). 360

deg rotation in approx 65 sec. (cable not supplied). Support bearing optional extra. **£49.95** + free P&P (mainland UK only).



Synchron SX-144/430
2m/70cm cross needle direct reading SWR/1000W

power meter. **£39.95** + free P&P (mainland UK only).



SRP Mini-Mag 2/70
2m/70cm dual band mobile antenna featuring super strength mini-magnet (only 30m diameter) c/w miniature coax and plug. **£19.95** + free P&P (mainland UK only).



SRP-905 Communications Speaker
5 watt 8 ohm filter/mute

extension speaker complete with 3.5mm mono jack. **£13.95** + free P&P (mainland UK only).



SRP Turbo Magmount
Very strong 7" diameter SO-239

magmount, with protective rubber base complete with cable and PL-259. Perfect for 6m 1/4 wave. **£17.95** + free P&P (mainland UK only).



Dummy Load DL-60

- ★ DC-500MHz
- ★ 60W max
- ★ PL-259 fitting

£15.99 + free P&P (mainland UK only)

STAR BUY. Super Synchro. 1100mAh NiMH AA size cell.

No memory effect, almost twice the capacity of Nicads. **£3.00** + free P&P (mainland UK only)

SRP Trading, 1686 Bristol Road South, Rednal, Birmingham B45 9TZ

Opening times: Mon-Sat 9.30am to 5.30pm. We are Kenwood, Yaesu, Icom, & Alinco dealers.

Call Rod (G8SUP), Richard (G60RA) or Mary (M1BUB) on




TEL: 0121-460 1581, 0121-457 7788 FAX: 0121-457 9009

StripboardMagic™

The innovative new computer-aided circuit layout program for stripboard

Windows 95/NT PC

Windows & Windows NT are registered trademarks of Microsoft Corporation.



Features:

- Fully-automatic physical circuit layout
- Stripboard or breadboard layout
- Assisted interactive layout options
- Simple drag-and-drop circuit editor
- Detailed construction diagram to guide the assembly stage
- Comprehensive, fully extensible component library
- Provision for off-board components
- Automatic generation of component order forms
- Printout function of all stages
- Full technical support

Don't solder on without it!

Only £39.95 incl VAT*

Tel/Fax: +44 (0) 1635-521285

StripboardMagic is a trademark of Ambyr Ltd.

Ambyr
a spark of genius

Email: info@ambyr.com
<http://www.ambyr.com>

Ambyr Limited. Reg office 84-86 Park Lane, Thatcham, Berkshire. RG18 3PG.

*Price does not include postage & packaging. Diagrams shown are for illustration purposes only. Ambyr & StripboardMagic are trademarks of Ambyr Ltd.

PRACTICAL WIRELESS INDEX VOLUME 73 JANUARY TO DECEMBER 1997

	Part	Pg/Mth
Antennas In Action		
20 to 2 Antenna by Perry Mountstevens G0IFI		60 Nov
Antenna Workshop - 'U' Listens On Low Bands by John Heys G3BDQ		38 May
Antenna Workshop - Antenna Switching Relays by David Butler G4ASR		26 July
Antenna Workshop - Direction Finding From The Attic by Ray Fautley G3ASG		26 Mar
Antenna Workshop - Hang The Antenna-And Hide It In Full View by John Heys G3BDQ		65 Nov
Antenna Workshop - The G3JVL Skeleton Aiford Slot Antenna by David Butler G4ASR		26 Jan
Antenna Workshop - Up The Ladder Safely by Allan Wightman		26 Sept
Books Bonanza		66 Nov
G2ATK's Match-Box by Trevor Talboys G2ATK		24 Sept
High As A Kite by Alec Adams G3YO		30 May
News/Products/Intro		23 Jan,
25 Mar, 29 May, 23 July, 23 Sept, 59 Nov.		
Old Antennas Never Die by Jack King G4EMC		24 July
Postage Stamp Loops by Des Heath G3ABS		24 Jan
Questionnaire		64 Nov
Tex Topics		28 Jan,
34 Mar, 37 May, 29 July, 28 Sept, 61 Nov.		
The T2FD Multi-Band Antenna by Glen Ross G8MWR		33 Mar
Up The Ladder by Allan Wightman		28 Mar

Book Reviews

The Babani Bunch - mini book reviews by Rob Mannion G3XFD	58 Feb
---	--------

Constructional

A Matchbox Midget Receiver by David Rowlands G6UEB	56 Sept
A Spectrum Wavemeter by Tony Fishpool G4WIF	24 June
A Transformerless Chatterbox by Doug Gibson G4RGN	22 Feb
Back To The Drawing Pin Board - 7MHz Pre-amplifier by Steve Ortmayer G4RAW	52 Oct
Chip In & Build Your Own Shack Desk by Noel Orrin G3BBK	52 July
Dip Meters - Dutch Style by Wim de Ruyter PA0PRW	51 May
Feed Point Resistance and Component Bridge by Denis Payne G3KCR	32 April
PW A5 Linking The Rugby Transmitter & Daventry Receiver by Dave Howes G4KQH	52 Aug
Safety ... In The Red Zone by Mike Rowe G8JVE	25 Oct
Tackling QRM - The Active Way by Adrian Knott G6KSN	33 Nov
The GDP-430 Hand-Held UHF Transceiver by Geoff Pike G1OGDP	67 Nov
The Probe by Richard Q. Marris G2BZQ	28 Aug
The Simple Two by Barry Sowter G3NAP	54 Feb
Topping's Timed Out by Colin Topping GM6HGW	22 Dec
Winding-Up Top-Band by Denis Payne G3KCR	32 Feb

Errors & Updates

Back To The Drawing-Pin Board pg 52 Oct '97	31 Dec
Carrying On The Practical Way pg 72 Nov '97	31 Dec

Features

'Doug' DeMaw W1FB A Personal Tribute by Rev. George Dobbs G3RJV	37 Dec
A British First ... From Uzbekistan by Phil Whitchurch G3SWH	42 Jan
Amateur Radio - A Hobby For Life by Steve Appleyard G3PND	58 Aug
Amateur Radio In Germany by Angelika Voss G0CCI/DF2XV	48 Dec
BBC Daventry A Potted History of a Famous Station by Keith Orchard G3TTC	26 April
Busby's Box Goes Sateside by Roger Cooke G3LDI	24 May
Channel Travel Radio by Dick Pascoe G0BPS	44 April
Crude But Effective - The No. 17 Transceiver by Billy Williamson GM8MMA	20 July
Cruise The Caribbean - The Yaesu Way by Rosemary Whelan	44 Feb
Digital Signal Processing - An Option? by Rob Mannion G3XFD	32 Oct
Discovering Amateur Radio by Mike Lawton GW4IQP	20 Sept
Dusting Off A Talking Antique by Peter Moir	51 June
Early Wireless Days by Brenda Belcher	21 Oct
Examination Time! - Rounding-Up To The RAE	16 Sept
Fleming - The Father of Electronics by Stephen Poole	52 April
FM DX Down Under by Graham Rogers VK6RO	56 Aug
Ham Radio Ticket - USA Style by John Teale N7FKV	44 Aug
Hand-Held Pioneers - The BC-611 & PRC-6 by Ben Nock G4BXD	28 Oct
He Who Persists Wins by Gerald Donington G4LNO	56 June
Icom To The Island - Remembering Marconi by Rob Mannion G3XFD	38 June

	Part	Pg/Mth
In Search Of Better Signals by Terry Brown G0NSA		25 May
In Tune With Piccolo by Malcolm McLernan F5VBU		20 Nov
Lasers - Leading Lights In Communications by Brian Dance		44 May
Longleat - 40 Years & Counting by Shaun O'Sullivan G8VPG & Ted Halliday G3JMY		31 July
Making It Go Further by Gordon King G4VJV		38 Nov
Manners Please! by Andrew Howlett G1HBE		39 Feb
Mobile Home 'Ham' by Dennis Hartwell G0VOV		42 Oct
On Secret Service With G6TW & 'Skyranger' by Leon Platt		55 July
Operating Abroad by Bruce Muscolino W6TOY		48 Sept
Over The Atlantic on 2m by Godfrey Hands PA3EUS		32 June
Plane Speaking by John Worthington GW3COI		41 July
Practice Makes Perfect by Richard Pigg G4MHW		28 Feb
Radio Amateurs On Track by Bruce McCartney GM4BDJ		22 Mar
Restoring Valved & Vintage Memories by Ian Liston-Smith G4JCT		36 Aug
Struck Off Almost! by Ben Nock G4BXD		40 Mar
The 6V6 Valved Transmitter by Richard Marris G2BZQ		28 Dec
The 15th Practical Wireless 144MHz QRP Contest Rules by Neill Taylor G4HLX		20 June
The 15th Practical Wireless 144MHz QRP Contest Results by Neill Taylor G4HLX		19 Dec
The Key to Comfortable CW by Rob Mannion G3XFD		38 April
The Trio JR-599 Receiver & T-599 Transmitter by Ben Nock G4BXD		32 Dec
Wagons Roll! - Dayton '97 Final Report by Rob Mannion G3XFD		34 Aug
Well Oiled Radio - On Board the Borgny Dolphin by Carl White G4VFU & Eddie Calthorpe G0HXL		40 June
Who Invented Radio? by Patrick Allely GW3KJW		40 Jan
Wireless Antenna by John Cunningham GM3JCC		55 April

Reviews

ADI AT-600 Dual-Band Hand-Held by John Goodall G0SKR	40 Aug
AKD HF3E Target Receiver Review by Rob Mannion G3XFD & Tex Swann G1TEX	38 Dec
Albrecht AE 550 144MHz FM Mobile Transceiver by Rob Mannion G3XFD	40 Feb
Alinco DJ-C1 144MHz and C4 430MHz Hand-Held Transceivers by Dick Pascoe G0BPS	54 Sept
Alinco DX-701 HF Transceiver by Rob Mannion G3XFD	28 June
Chelcom CAHFV1 Vertical Antenna by John Heys G3BDQ	21 April
Discovery Linear Amplifiers for 50 & 144MHz by David Butler G4ASR	26 Nov
EASY-PC Professional XM, ANALYSER III, LAYAN by Tex Swann G1TEX	18 Oct
Electronics Workbench Version 5 by Tex Swann G1TEX	49 May
Experimenting With PC Computers (Software Package) by Tex Swann G1TEX	44 July
Icom IC-207H Dual-Band Mobile Transceiver by Richard Newton G0RSN	50 July
Icom IC-706 MKII HF/VHF Transceiver by Richard Newton G0RSN	46 Aug
Icom IC-756 HF & 50MHz Transceiver by Rob Mannion G3XFD	34 Sept
Kenwood CS-4125, SAE 1001 and FCE 1131 Test Equipment by Gordon King G4VJV	34 July
Kenwood TH-235E Hand-Held 144MHz Transceiver by Richard Newton G0RSN	46 June
Kenwood TM-V7E Dual-Band FM Transceiver by Leighton Smart GWDLBI	66 Mar
Kenwood TS-570D HF Transceiver by Rob Mannion G3XFD	48 Jan
MFJ-490 Memory Keyer by John Goodall G0SKR	27 May
MFJ-914 Autotuner Extender by John Heys G3BDQ	34 June
Semaht UHF/VHF Digital Field Strength Meter by Gordon King G4VJV	18 May
Vibroplex Deluxe Hand Morse Key by John Goodall G0SKR	21 Feb
Watson WMM-1 Multimode by Roger Cooke G3LDI	29 April
Yaesu FT-8000R Dual-Band FM Transceiver by Richard Newton G0RSN	73 Mar
Yaesu FT-920 HF & 50MHz Transceiver by Rob Mannion G3XFD	23 Aug

Show Guides

The London Amateur Radio & Computer Show

Floor Plan	50 Mar
Finding Your Way ... To Picketts Lock	52 Mar
Win! A Yaesu FT-8000R Dual-Band Mobile Transceiver	57 Mar
Show News	58 Mar
New from PW Publishing Ltd. - Ferrells Confidential Frequency List 10th Edition	60 Mar
Of Special Interest	61 Mar

The Leicester Amateur Radio & Computer Show

Floor Plan	50 Nov
Looking Back - Changing Times, Faces & Places by Rob Mannion G3XFD	49 Nov
Mr 'Leicester Show' - A Tribute To Frank Elliott G4PDZ 1928 - 1997	48 Nov
Show News	46 Nov
Subscription Offer	53 Nov
Win! - A Kenwood TH-235 144MHz Hand-Held Transceiver	54 Nov

PRACTICAL WIRELESS INDEX VOLUME 73 JANUARY TO DECEMBER 1997

	Pg/Mth
Theory	
Antenna Workshop - Invisible Antennas by Dick Pascoe G0BPS	36 April
Antenna Workshop - Versatility of the Smith Chart by Gerald Stancey G3MCK	54 June
Antenna Workshop - What A Good Idea!	48 Aug
Health Hazards - What Level Radiation by Gordon King G4VFV	40 Sept
Maths - No Real Problem by Ray Fautley G3ASG	36 Oct
Non-Linear Scales by Andy Gayne G7KPF	38 Mar
Speech Processing - The Basics by Ian Poole G3YWX	32 Jan
Those Trying Transformers by Geoff Billington G3EAE	34 Feb
What Voltage? by Alec Melville	53 Sept
Regulars	
Bargain Basement	66 Jan,
74 Feb, 89 Mar, 74 April, 74 May, 74 June, 83 July, 74 Aug, 83 Sept, 48 Oct, 88 Nov, 72 Dec.	
Bits & Bytes - The Computer In Your Shack by Mike Richards G4WNC	51 Jan,
60 Feb, 80 Mar, 58 April, 72 May, 70 June, 76 July, 62 Aug, 77 Sept, 53 Oct, 84 Nov, 67 Dec.	
Book Profiles	72 Jan,
80 Feb, 96 Mar, 80 April, 54 May, 44 June, 58 July, 50 Aug, 50 Sept, 46 Oct, 42 Nov, 46 Dec.	
Broadcast Round-Up by Peter Shore	65 Jan,
72 Feb, 85 Mar, 72 April, 77 May, 72 June, 78 July, 73 Aug, 78 Sept, 66 Oct, 86 Nov, 70 Dec.	
Buyers Guide	52 Jan,
70 Feb.	
Carrying On The Practical Way by George Dobbs G3RJV	36 Jan,
26 Feb, 46 Mar, 49 April, 60 May, 59 June, 48 July, 32 Aug, 64 Sept, 44 Oct, 72 Nov, 53 Dec.	
Club Spotlight	18 Jan,
16 Feb, 14 Mar, 18 April, 10 May, 14 June, 16 July, 14 Aug, 12 Sept, 14 Oct, 14 Nov, 14 Dec.	
Competitions	
Christmas Competition - Find Santa	20 Jan
Data Diary by Roger Cooke	79 Sept,
87 Nov.	
Editor's Keylines by Rob Mannion G3XFD	7 Jan,
7 Feb, 7 Mar, 7 April, 7 May, 7 June, 7 July, 7 Aug, 7 Sept, 7 Oct, 7 Nov, 9 Dec.	
Focal Point - The World of ATV by Graham Hanks G8EMX	69 Feb,
68 April, 73 June, 76 Aug, 67 Oct, 71 Dec.	
Free Gifts	
The <i>Practical Wireless</i> 1997 Year Planner	Jan
Waters & Stanton 16-page <i>Radio Communications Catalogue</i>	Nov
HF Far & Wide by Leighton Smart GWOLBI	60 Jan,
66 Feb, 77 Mar, 64 April, 66 May, 62 June, 74 July, 70 Aug, 74 Sept, 64 Oct, 78 Nov, 63 Dec.	
News '97	10 Jan,
12 Feb, 21 Mar, 16 April, 14 May, 10 June, 10 July, 10 Aug, 10 Sept, 10 Oct, 10 Nov, 10 Dec.	
Packet Panorama by Roger Cooke	64 Jan,
82 Mar, 76 May, 79 July.	
PWBook Store	71 Jan,
79 Feb, 95 Mar, 79 April, 80 May, 80 June, 88 July, 80 Aug, 88 Sept, 72 Oct, 96 Nov, 80 Dec.	
Radio Diary	17 Jan,
9 Feb, 24 Mar, 7 April, 57 May, 36 June, 12 July, 20 Aug, 21 Sept, 12 Oct, 25 Nov, 17 Dec.	
Radio - Discover The Basics by Rob Mannion G3XFD	12 Jan,
18 Mar, 17 May, 19 July, 19 Sept, 16 Nov.	

	Pg/Mth
Receiving You	8 Jan,
10 Feb, 8 Mar, 8 April, 8 May, 8 June, 8 July, 8 Aug, 8 Sept, 8 Oct, 8 Nov, 12 Dec.	
Scene USA by Ed Taylor WT3U	56 Jan,
70 April, 66 July, 58 Oct.	
Special Offers	
<i>Basic Radio and Electronic Calculations</i> & The Casio FX-115s Calculator	20 Jan,
Howes DC2000 s.s.b./c.w. receiver kit	13 May
<i>Short Wave Listener's Guide</i> - Pre-publication offer	13 April
Kenwood FCE-1131 Frequency Counter, CS-4125 Oscilloscope & SAE 1001 Analyser	39 July
RA3 Telescopic Antenna, DB-770M Magnetic Mount & Serene TSB-3608 Antenna	33 Sept
Special Prize Competitions	
MyDel Multi-Trap Antenna - Wordsearch	48 June
Royal International Air Tattoo - Identify the Planes	39 June
EASY-PC Professional XM, ANALYSER III, LAYAN - Wordsearch	17 Nov
Star Buy	
<i>25 Simple Amateur Band Aerials, 25 Simple Indoor and Window Aerials, 25 Simple Shortwave Broadcast Band Aerials & 25 Simple Tropical and M.W. Aerials</i>	82 Aug
<i>The Radio Amateurs' Question & Answer Reference Manual</i>	82 May
<i>The RSGB Amateur Radio Callbook & Information Directory 1997</i>	70 Jan
<i>The Secret of Learning Morse Code</i>	82 June
<i>The UK Scanning Directory</i>	90 July
<i>World Radio & TV Handbook 1996</i>	78 Feb
<i>World Radio & TV Handbook 1997</i>	94 Mar
<i>W1FB's Antenna Notebook & Build Your Own Shortwave Antennas</i>	90 Sept
<i>An Introduction to Radio Wave Propagation, Setting Up An Amateur Radio Station, Projects For Radio Amateurs and S.W.L.s & An Introduction To Microwaves</i>	74 Oct
<i>Practical Wireless Binders</i>	98 Nov
<i>Circuit Source Book 1 & Circuit Source Book 2</i>	82 Dec
Subs Club Special Offers	
Bosch Drill Set	9 Feb
Valve & Vintage by Ben Nock G4BXD	50 Feb,
58 May, 60 Aug, 75 Nov.	
Valve & Vintage by Charles Miller	44 Jan,
56 April, 60 July, 50 Oct.	
Valve & Vintage by Phil Cadman G4JCP	62 Mar,
64 June, 60 Sept, 58 Dec.	
VHF Report by David Butler G4ASR	54 Jan,
63 Feb, 70 Mar, 62 April, 64 May, 66 June, 71 July, 66 Aug, 68 Sept, 60 Oct, 82 Nov, 64 Dec.	
What Is A? by Ian Poole G3YWX	
Semiconductor	18 Feb
PN Junction	10 April
Point Contact Diode	27 June
Schottky Diode	16 Aug
Zener Diode	13 Oct
Varactor Diode	16 Dec

Don't forget we still have available *PW* back issues for 1997 as well as 1992, 1993, 1994, 1995 and 1996. But hurry as stocks are limited. To order back issues either use the **Order Form on page 82** of this issue or telephone the **Credit Card Hotline on (01202) 659930**. Back issues for **1992 to 1995** are available for just **£1 including P&P, all others are £2.30 including P&P.**

Classified Ads

To advertise on this page see booking form below.

For Sale

QUARTZ CRYSTALS 2kHz-100MHz at £1.50. Transmission power and test equipment. For lists phone Electronic Design Associates. Tel: 0181 391 0545 Fax: 0181 391 5258.

TECHNICAL MANUALS, AR88, CR100, R210, HR0. £5 each. Circuits £1.50. Hundreds available. SAE list. Bentley, 27 De Vere Gardens, Ilford, Essex IG1 3EB. Tel: 0181-554 6631.

THE UK's LARGEST SOURCE for Vintage Service data, circuits and manuals from 1900 to the 1970s. Free brochure from Tudor Gwilliam-Rees, Savoy Hill Publications, 50 Meddon St, Bideford, The Little White Town, North Devon, EX39 2EQ. Tel: 01237 424280. E-mail: tudor.gwilliam-rees@virgin.net

INTERESTED in vintage wireless? Send 2 x 1st class stamps for latest list of books, bits & pieces etc. Old Time Supplies, PO Box 209, Banbury, Oxon OX16 7GR.

THE RIG REVIEW contains details of over 550 rigs and receivers. Tell an IC2SRE from an IC2SE. 55 pages. Covers 25 years of manufacture. Gives each rig's main features and original price. Price £5 post free from Twrog Press, see below:-

THE RECEIVER REVIEW contains details of 200 receivers. 44 pages. Price £5 post free from Twrog Press, see below:-

QSL CARDS - SAE for samples to Twrog Press, Penybont, Gellilydan, Blaenau Ffestiniog, Gwynedd LL41 4EP.

VINTAGE RADIO manuals, valves, components, radios. SAE for details. Practical Wireless, PO Box 42, Sleaford NG34 0TX.

Educational

CITY & GUILDS RADIO AMATEURS EXAM. Pass your exam the easy way with an RRC home study course. For details write or phone THE RAPID RESULTS COLLEGE, Dept. JX400, Tuition House, London SW19 4DS. Tel: 0181-947 2211.

Holidays

NORTH WALES HOLIDAYS - Caravan - bunkhouse - camping. Elevated rural site, two miles from beach, use of shack and antennas, open all year. Tynrhos, Mynytho, Pwllheli. Tel: 01758 740712.

Valves

VALVES GALORE Most valves available from stock. Otherwise obtained quickly. Please send SAE stating requirements or telephone. **VALVE & ELECTRONIC SUPPLIES** Chevet Books, 157 Dickson Road, Blackpool FY1 2EU. Tel: (01253) 751858 or Fax: (01253) 302979.

VALVES WANTED for cash: KT88, £60; PX4, £60; PX25, £105; DA100, £90; EL34, £15; EL37, £15; CV4004, £5; ECC83 £3. Valves must be Mullard/GEC, West European to achieve this price. Ask for free wanted list. Prompt and courteous service. Visitors by appointment only (we are a very busy Export Warehouse). Billington Export Ltd. Billingshurst, West Sussex RH14 9EZ. Tel: (01403) 784961. Fax: (01403) 783519.

VALVES:- OVER 50000 STOCKED Ham, Vintage, Military, Audio. SAE for FREE list to: Wilson Valves, (Jim Fish G4MH), 28 Banks Ave., Golcar, Huddersfield, West Yorks HD7 4LZ. Tel: 01484 654650. Fax: 01484 655699. E-mail: Wilsonvalves@surflink.co.uk Visa etc. Fast & personal service.

CASH FOR VALVES. ECC32 £10. ECC33/35 £6. ECC83/EF86 £3.50. KT66 £40. KT88 £65. EL34 £20. EL37 £18. PX4 £70. PX25 £130. GZ34 £8. GZ32 £8. DA100 £150. 4212E £150. PT15 £10. Ask for free wanted list. Colomor (Electronics) Ltd, 170 Goldhawk Road, London W12 8HJ. Tel: 0181-743 0899. Fax: 0181-749 3934. E-mail: giacomelli@colomor.demon.co.uk

TOP PRICES PAID

for all your valves, tubes, semi-conductors and ICs.

Langrex Supplies Ltd.
1 Mayo Road, Croydon
Surrey CR0 2QP.

TEL: 0181-684 1166. FAX: 0181-684 3056.

Miscellaneous

VALVE ENTHUSIASTS: Capacitors and other parts at attractive prices! Ring for free list. Geoff Davies (Radio), Tel: (01788) 574774.

USED AMATEUR EQUIPMENT? Buying or selling? See you at www.hamradio-mart.co.uk Cheap rates! No internet access? SAE: G4TNY, 41 Onslow Crescent, Colchester, Essex CO2 8UN.

Whilst prices of goods shown in advertisements are correct at the time of going to press, readers are advised to check both prices and availability of goods with the advertiser before ordering from non-current issues of the magazine.

Computer Software & Hardware

PC SSTV-DATA Tx/Rx pack £29.95. Other PC/AMIGA SSTV/Package Interfaces. SAE leaflets, £1/stamps 1.44 DEMO disk. Peter Lockwood G8SLB, 36 Davington Road, Dagenham RM8 2LR. Tel/Fax: 0181-595 0823.

COMPUTER COMPONENTS New and Second User Systems, Packet Radio Products by G3KFN, Used Ham Gear. We have access to large amounts of manufacturers end of line, surplus, and bankrupt stock, mostly computer related. For details phone, fax or see our Web Site at: <http://www.greystone.mcm.com> E-mail: g m 4 e w z @ m c m a i l . c o m (J Halford, GM4EWZ) Greystone Computers, Sanday, Orkney KW17 2AY. Phone/fax (01857) 600375.

Wanted

WANTED FOR CASH Valve or solid state communication receivers Pre-1980. Preferably working and in good condition. Non working sets considered also domestic valve radios. Items of Government surplus wireless equipment and obsolete test equipment. Pre-1965 wireless and audio components and accessories. Pre-1975 wireless and TV books and magazines. Also, most valves wanted for cash. Must be unused and boxed. CBS, 157 Dickson Road, Blackpool, FY1 2EU. Tel: (01253) 751858 or Fax: (01253) 302979.

SINCLAIR BLACK WATCH. Executive calculator. Mk14 computer. Enrico Tedeschi, 54 Easthill Drive, Brighton BN41 2FD. Tel: 01273 701650 anytime.

Practical Wireless Small Ads

Equipment For Sale, Equipment
Wanted, Holidays, Recruitment,
Computer Software.

Why not try our highly successful
Classified Advertising

For further details call Carol on

(01202) 659920


DISCLAIMER

Some of the products offered for sale in advertisements in this magazine may have been obtained from abroad or from unauthorised sources. *Practical Wireless* advises readers contemplating mail order to enquire whether the products are suitable for use in the UK and have full after-sales back-up available.

The publishers of *Practical Wireless* wish to point out that it is the responsibility of readers to ascertain the legality or otherwise of items offered for sale by advertisers in this magazine.

**SEE PAGE 55 FOR
THE CLASSIFIED
ORDER FORM**

MONITORING TIMES



PUBLISHED MONTHLY BY GROVE ENTERPRISES IN THE USA MT HAS PLENTY TO OFFER THE RADIO ENTHUSIAST. INCLUDED ARE 20 PAGES OF BROADCAST SCHEDULES FROM AROUND THE WORLD, REVIEWS OF NEW PRODUCTS, TECHNICAL FEATURES AND PROJECTS. ALL THIS AND MORE IS CONTAINED WITHIN ITS 100+ PAGES. THERE'S EVEN A COMPREHENSIVE BUYERS GUIDE COVERING EVERYTHING FROM BOOKS AND SOFTWARE TO THE LATEST EQUIPMENT.

SO, IF YOU ARE LOOKING TO ENHANCE YOUR HOBBY - LOOK NO FURTHER!

IF IT'S ON THE RADIO IT'S IN MONITORING TIMES!

Subs Rates (1 year):

£38 UK

£43 Europe (Airmail)

£49 Rest of World (Airmail)

SUBSCRIBE

NOW


AND GET 14 ISSUES
FOR THE
PRICE OF 12

TELEPHONE (01202) 659930

TO SUBSCRIBE TO MONITORING TIMES

We can also arrange subscriptions to Satellite Times - call for details.

TO QUALIFY FOR THIS OFFER PLEASE QUOTE MT12 WHEN ORDERING



Hurry up and purchase
**Practical Wireless
Magazine**
every month!

SEM

8 Fort William
Douglas
Isle of Man IM1 5BQ
Tel: 01624 662131

For full info. on our QRM
Eliminator, filters, preamps
(1-500MHz) converters, keyers,
ATUs EZITUNE, etc.
ask for our catalogue.

TELFORD ELECTRONICS

Old Officers Mess, Hoo Farm, Humbers Lane, Horton
Telford, Shropshire TF6 6DL

Tel: 01952 605451 Fax: 01952 677978

RACAL HF COMMUNICATIONS RECEIVER

- Type: RA1792. ● 150kHz - 30MHz ● Modes: LSB, USB, AM, CW & FM ● Filters fitted: 0.3kHz, 1.0kHz, 3.2kHz, 6kHz, & 16kHz ● Digital A.G.C. ● Scan facility
- 100 channel memory ● C/W documentation

PRICE: **£750.00** (CARRIAGE (UK) £20)

HESING TECHNOLOGY

41 Bushmead Road, Eaton Socon, Cambs PE19 3BT
Tel (01480) 386156 Fax (01480) 386157

Manuals Spares Repairs Technical Support

LAR COMMUNICATION CENTRE

ESTABLISHED 21 YEARS

12 Station Road, Crossgates, Leeds LS15 7JX

Tel: 0113-232 8400 Fax: 0113-232 8401

Approved dealers for Kenwood, AOR, Icom, Yaesu and many others. We sell amateur radio equipment, scanners, shortwave receivers, antennas and over 800 accessories. Books, PW and SWM. Our after sales service is second to none.

We are open Mon to Sat 9am to 5pm We have private customer parking.

MARTIN LYNCH
& Son

THE AMATEUR RADIO EXCHANGE CENTRE

NEWSFLASH

Don't forget our massive
four day Xmas sale.

27th, 29th, 30th & 31st
December 1997

07000
73 73 73

BOOK STORE



TO ORDER YOUR BOOKS:

E-MAIL: bookstore@pwpub.demon.co.uk

TEL: (01202) 659930 (24 HOURS)

FAX: (01202) 659950 (24 HOURS)

OR USE THE ORDER FORM ON PAGE 82

Please note: cash not accepted with mail orders.

The books listed have been selected as being of special interest to our readers. They are supplied direct to your door. Many titles are overseas in origin.

LISTENING GUIDES

AIRBAND

AIR BAND RADIO HANDBOOK 6th Edition. David J. Smith.	192 pages. \$9.99
AIRBAND RADIO GUIDE 3rd Edition. Graham Duke.	96 pages. \$6.99
AIR TRAFFIC CONTROL 6th Edition. Graham Duke.	112 pages. \$6.99
AIRWAVES 97.	100 pages. \$8.95
CALLSIGN 97.	144 pages. \$8.95
FLIGHT ROUTINGS 1997. Compiled by T.T. & S.J. Williams.	140 pages. \$6.95
INTERNATIONAL AIR BAND RADIO HANDBOOK. David J. Smith.	192 pages. \$9.99
UNDERSTANDING ACARS	
3rd Edition. Aircraft Communications Addressing and Reporting System. Ed Flynn.	80 pages. \$9.95
VHF/UHF AIRBAND FREQUENCY GUIDE & CALLSIGN GUIDE	280 pages. \$12.50
WORLDWIDE AERONAUTICAL COMMUNICATIONS FREQUENCY DIRECTORY	
2nd Edition. Robert E. Evans.	260 pages. \$19.95
WORLDWIDE AERONAUTICAL HF RADIO HANDBOOK. Martyn R. Cooke.	124 pages. \$6.95

In addition to these we stock other airband, titles mainly from the Ian Allan ABC range - ask for details.

BROADCAST

GLOBAL RADIO GUIDE JULY 97 (The Association of International Broadcasting).	30 pages. \$3.35
---	------------------

DATAMODES

FAX & RTTY WEATHER REPORTS. Philip Mitchell.	88 pages. \$11.50
GUIDE TO UTILITY STATIONS. 15th Edition. Joerg Klingenfuss.	588 pages. \$35.00
GUIDE TO WORLDWIDE WEATHERFAX SERVICES. 16th Edition. Joerg Klingenfuss.	436 pages. \$25.00
INTERNET RADIO GUIDE. 2nd Edition. Joerg Klingenfuss.	350 pages. \$22.00
WEATHER REPORTS FROM RADIO SOURCES. Philip Mitchell.	32 pages. \$7.50
RADIO DATA CODE MANUAL. 15th Edition. Joerg Klingenfuss.	604 pages. \$28.00

DXTV

DXTV FOR BEGINNERS. Simon Hamer.	31 pages. \$3.95
GUIDE TO DX-TV. Keith Hamer & Garry Smith.	36 pages. \$3.95
GUIDE TO WORLDWIDE TV TEST CARDS	\$4.95
THIS IS BBC TV - FIRST 30YRS OF TV GRAPHICS. Keith Hamer & Garry Smith.	38 pages. \$4.95

FREQUENCY GUIDES

1997 SUPER FREQUENCY LIST CD-ROM. Joerg Klingenfuss.	\$25.00
FERRIS CONFIDENTIAL FREQUENCY LIST 10th Edition.	450 pages. \$19.95
PASSPORT TO WORLD BAND RADIO 1998.	528 pages. \$15.50
UK SCANNING DIRECTORY. 5th Edition.	540 pages. \$18.50
VHF-UHF SCANNING FREQUENCY GUIDE. Bill Laver.	192 pages. \$12.95
WORLD RADIO TV HANDBOOK 1997.	608 pages. \$17.95

GENERAL

EAVESDROPPING ON THE BRITISH MILITARY. Michael Cannon.	\$17.50
GETTING ON TRACK WITH APRS. Stan Horzempa W1LOU.	165 pages. \$9.95
POP WENT THE PIRATES. Keith Skoos.	568 pages. \$15.95
SHORT WAVE COMMUNICATIONS. Peter Rouse GU1DKD.	187 pages. \$4.50
SHORTWAVE RECEIVERS PAST & PRESENT (1945-1996)	\$23.95
SHORTWAVE LISTENER'S GUIDE. Ian Poole	\$14.99
THE COMPLETE SHORT WAVE LISTENER'S HANDBOOK 4th Edition	
Hank Bennett, Harry Helms & David Hardy.	321 pages. \$19.95

MARINE

GMDSS EDITIONS MARINE SSB OPERATION. Michael Gale.	96 pages. \$11.95
GMDSS EDITIONS MARINE VHF OPERATION. Michael Gale.	\$7.95
SCANNING THE MARINE BANDS. F.F. O'Brian.	152 pages. \$9.50
SHORTWAVE MARITIME COMMUNICATIONS. B.E. Richardson.	195 pages. \$16.50
SHIP TO SHORE RADIO FREQUENCIES. Ken Davies.	95 pages. \$5.99
SIMPLE GPS NAVIGATION. Mik Chinery.	96 pages. \$10.95

SATELLITE

AN INTRODUCTION TO SATELLITE COMMUNICATIONS BP326.	
F. A. Wilson.	230 pages. \$5.95
ARRL SATELLITE ANTHOLOGY 4th Edition.	150 pages. \$8.95
NEWNES GUIDE TO SATELLITE TV. Derek Stephenson.	371 pages. \$18.95
NEWNES SATELLITE COMMUNICATIONS POCKET BOOK. James Wood.	220 pages. \$12.99
SATELLITE BOOK - A Complete Guide to Satellite TV Theory and Practice	
John Breeds.	280 pages. \$32.00
SATELLITE EXPERIMENTER'S HANDBOOK 2nd Edition.	

Martin Davidoff K2UBC.	313 pages. \$15.50
SATELLITE HACKERS HANDBOOK. Colin A. Grellis.	120 pages. \$18.75
SATELLITE PROJECTS HANDBOOK. L. Harris.	\$14.99
SATELLITE TELEVISION. A layman's guide. Peter Pearson.	73 pages. \$1.00
SATELLITE TELEVISION INSTALLATION GUIDE. 5th Edition. John Breeds.	76 pages. \$15.00
WEATHER SATELLITE HANDBOOK. 5th Edition. Dr Ralph E. Taggart WB8DQT.	192 pages. \$15.50
WRTH SATELLITE BROADCASTING GUIDE. 1997 Edition. Bart Kuperus.	366 pages. \$18.95

SCANNING

AN INTRODUCTION TO SCANNERS AND SCANNING BP311. I. D. Poole.	152 pages. \$4.99
SCANNER BUSTERS 2. D.C. Poole.	100 pages. \$6.00
SCANNERS 2 INTERNATIONAL. Peter Rouse GU1DKD.	261 pages. \$10.95
SCANNERS 3 PUTTING SCANNERS INTO PRACTICE.	
4th Revision. Peter Rouse.	271 pages. \$10.95
SCANNING SECRETS. Mark Francis.	280 pages. \$16.95

AMATEUR RADIO

AMATEUR TELEVISION

AN INTRODUCTION TO AMATEUR TELEVISION.	
Mike Wooding G6JQM & Trevor Brown G8CJS.	\$5.00
SLOW SCAN TELEVISION EXPLAINED. Mike Wooding G6JQM.	\$5.00
THE AMATEUR TV COMPENDIUM. Mike Wooding G6JQM.	\$3.50

ANTENNAS & TRANSMISSION LINES

25 SIMPLE AMATEUR BAND AERIALS BP125. E. M. Noll.	63 pages. \$1.95
25 SIMPLE INDOOR AND WINDOW AERIALS BP136. E. M. Noll.	50 pages. \$1.75
25 SIMPLE SHORT WAVE BROADCAST BAND AERIALS BP132. E. M. Noll.	63 pages. \$1.95
25 SIMPLE TROPICAL AND MW BAND AERIALS BP145. E. M. Noll.	54 pages. \$1.75
ALL ABOUT VERTICAL ANTENNAS. W. I. Orr W6SAI & S. D. Cowan W2LX.	192 pages. \$8.50
ANTENNA EXPERIMENTER'S GUIDE (RSGB). Peter Dodd G3LDO.	\$15.00
ANTENNA IMPEDANCE MATCHING (ARRL). Wilfred N. Caron.	195 pages. \$15.50
ANTENNAS FOR VHF AND UHF BP301. I. D. Poole.	104 pages. \$4.95
ANTENNAS & TECHNIQUES FOR LOW BAND DXING (ARRL).	394 pages. \$15.50
ARRL ANTENNA BOOK 18th Edition 1997.	732 pages. \$23.95
ARRL ANTENNA COMPENDIUM Volume One.	175 pages. \$10.00
ARRL ANTENNA COMPENDIUM Volume Two.	208 pages. \$10.00
ARRL ANTENNA COMPENDIUM Volume Three. Edited by Jerry Hall K1TD.	236 pages. \$12.50
ARRL ANTENNA COMPENDIUM Volume Four.	204 pages. \$15.50
ARRL ANTENNA COMPENDIUM Volume Five.	200 pages. \$16.50
BEAM ANTENNA HANDBOOK. W. I. Orr W6SAI & S. D. Cowan W2LX.	268 pages. \$8.50
BUILDING & USING BALUNS. Jerry Sevic.	125 pages. \$18.95
BUILD YOUR OWN SHORTWAVE ANTENNAS 2nd Edition. Andrew Yoder.	208 pages. \$15.95
CUBICAL QUAD ANTENNAS 3rd Edition. William Orr W6SAI and Stuart Cowan W2LX.	\$8.50
EXPERIMENTAL ANTENNA TOPICS BP278. H. C. Wright.	70 pages. \$3.50
G-QRP CLUB ANTENNA HANDBOOK.	

Compiled and edited by P. Linsley G3PDL & T. Nicholson KA9WRL/GW0LNQ.	155 pages. \$7.25
HF ANTENNA COLLECTION (RSGB). Edited by Erwin David G4LQL.	233 pages. \$10.99
HF ANTENNAS FOR ALL LOCATIONS (RSGB). Les Moxon G6XN.	322 pages. \$14.65
MORE OUT OF THIN AIR (PWP).	112 pages. \$6.95
PRACTICAL ANTENNAS FOR NOVICES. John Heys G3BDQ.	52 pages. \$6.30
PRACTICAL ANTENNA HANDBOOK 2nd Edition. Joseph J. Carr.	437 pages. \$26.95
PRACTICAL WIRE ANTENNAS RSGB. John Heys G3BDQ.	100 pages. \$8.95
RADIO AMATEUR ANTENNA HANDBOOK. W. I. Orr W6SAI & S. D. Cowan W2LX.	188 pages. \$8.50
RECEIVING ANTENNA HANDBOOK. Joe Carr. 1	89 pages. \$17.50
SIMPLE, LOW-COST WIRE ANTENNAS FOR RADIO AMATEURS.	
W. I. Orr W6SAI & S. D. Cowan W2LX.	188 pages. \$8.50
W1FB'S ANTENNA NOTEBOOK (ARRL). Doug DeMaw W1FB.	123 pages. \$7.50

BEGINNERS (INC RAE)

AMATEUR RADIO FOR BEGINNERS (RSGB). Victor Brand G3JNB.	65 Pages. \$3.50
AN RAE STUDENTS NOTEBOOK. Bob Griffiths G7NHB.	\$6.95
HOW TO PASS THE RADIO AMATEURS' EXAMINATION (RSGB)	
Clive Smith G4FZH and George Benbow G3HB.	88 pages. \$8.75
PRACTICAL RECEIVERS FOR BEGINNERS (RSGB). John Case GW4HWR.	165 pages. \$12.50
THE NOVICE RADIO AMATEURS EXAMINATION HANDBOOK (BP375)	
Ian Poole G3YWX.	150 pages. \$4.95
THE RADIO AMATEURS' QUESTION & ANSWER REFERENCE MANUAL.	
Fifth Edition.	Ray Petri G0OAT. \$13.95
RAE MANUAL (RSGB). G.L.Benbow G3HB.	127 pages. \$8.75
RAE REVISION NOTES (RSGB). G.L.Benbow G3HB.	92 pages. \$5.25
REVISION QUESTIONS FOR THE NOVICE RAE (RSGB). Esde Tyler G0AEC.	60 pages. \$5.75
THE NOVICE LICENCE STUDENT'S NOTEBOOK. John Case GW4HWR.	124 pages. \$5.00

SHORTWAVE RADIO LISTENING FOR BEGINNERS.

Anita Louise McCormick KA8KGL	176 pages. \$10.95
TRAINING FOR THE NOVICE LICENCE A MANUAL FOR THE INSTRUCTOR (RSGB)	
John Case GW4HWR	101 pages. \$6.75
W1FB'S HELP FOR NEW HAMS (ARRL) , Doug DeMaw W1FB	155 pages. \$8.95

CALLBOOKS

AMATEUR RADIO CALL BOOK AND INFORMATION DIRECTORY (RSGB)	
1998 Edition	529 pages. \$13.50
JOINT INT/N.AMERICAN CALLBOOK CD-ROM 1997	\$35

COMPUTING

ACCESS 95 ONE STEP AT A TIME BP408	115 pages. \$5.99
AN INTRODUCTION TO COMPUTER COMMUNICATIONS BP177	
R. A. Penfold	2 pages. \$2.95
ELECTRONIC PROJECTS FOR YOUR PC BP320 , R.A. Penfold	102 pages. \$3.99
EXPERIMENTING WITH PCs , P. Brunning	\$24
HOW TO EXPAND, MODERNISE AND REPAIR PCs AND COMPATIBLES BP271	
R. A. Penfold	166 pages \$ 5.99
INTERFACING PCs AND COMPATIBLES BP272 , R. A. Penfold	86 pages. \$4.99
MS-OFFICE ONE STEP AT A TIME (BP402)	77 pages. \$5.95
MS WORKS FOR WINDOWS 95 EXPLAINED BP405	175 pages. \$5.95
NEWNES COMPUTER ENGINEER'S POCKET BOOK Third Edition	
Michael Tooley	256 pages. \$12.95
PASSPORT TO WEB RADIO 1997	\$14.99
PERSONAL COMPUTERS IN THE HAM SHACK (ARRL)	\$12.50
THE INTERNET AND WORLD WIDE WEB EXPLAINED , J. Shelley	130 pages. \$5.95
WINDOWS 95 EXPLAINED (BP400)	175 pages. \$5.95

EMC

INTERFERENCE HANDBOOK , William R. Nelson WA6FQG	250 pages. \$9.50
THE RADIO AMATEUR'S GUIDE TO EMC (RSGB) , Robin Page-Jones G3JWL	117 pages. \$8.95

HISTORICAL

1934 OFFICIAL SHORT WAVE RADIO MANUAL , Edited by Hugo Gernsback	260 pages. \$11.85
OLD TIME RADIOS - RESTORATION & REPAIR , J. Carr	256 pages. \$17.95
CRYSTAL SET PROJECTS , Phil Anderson	\$7.50
EXPERIMENTAL TELEVISION (1932)	312 pages. \$11.75
HENLEYS 222 RADIO CIRCUIT DIAGRAMS (1924)	271 pages \$9.45
HOW TO BUILD YOUR RADIO RECEIVER (Popular Radio Handbook No. 1)	\$6.95
SECRETS OF HOMEBUILT REGENERATIVE RECEIVERS (Rockey)	127 pages. \$7.95
THE XTAL SET SOCIETY NEWSLETTER , Volume 1, Phil Anderson W0XI	\$6.50
THE XTAL SET SOCIETY NEWSLETTER , Volume 2, Phil Anderson W0XI	\$6.50
THE CRYSTAL SET HANDBOOK & VOL. 3 XTAL NEWSLETTER , Phil Anderson W0XI	\$6.50
THE XTAL SET SOCIETY NEWSLETTER , Volume 4, Phil Anderson W0XI	\$6.50
THE CRYSTAL SET HANDBOOK & VOL. 5 XTAL NEWSLETTER , Phil Anderson W0XI	\$6.50
CRYSTAL RADIO HISTORY, FUNDAMENTALS AND DESIGN , P. A. Kinzie	\$6.50
THOSE GREAT OLD HANDBOOK RECEIVERS (1929 + 1934)	94 pages. \$6.95
WIRELESS FOR THE WARRIOR VOL. 1 (Wireless Sets 1-88)	\$27.50
VISION BY RADIO (1925) (Jenkin)	140 pages. \$7.85

MAPS AND LOG BOOKS

AMATEUR RADIO LOGBOOK (RSGB)	\$3.75
NORTH ATLANTIC ROUTE CHART	740 x 520mm. \$8.50
QTH LOCATOR MAP OF EUROPE. NEW EDITION	1080 x 680mm. \$7.00
RADIO AMATEURS MAP OF THE WORLD. NEW EDITION	980 x 680mm. \$7.00
RECEIVING STATION LOG BOOK (RSGB)	\$3.75
RSGB PREFIX GUIDE	\$5.75

MORSE

MORSE CODE FOR RADIO AMATEURS (RSGB)	28 pages. \$4.25
SECRETS OF LEARNING MORSE CODE Mark Francis	84 pages. \$6.95

MICROWAVES

AN INTRODUCTION TO MICROWAVES (BP312) , F. A. Wilson	134 pages. \$3.95
ARRL UHF/MICROWAVE EXPERIMENTER'S MANUAL Various Authors	446 pages. \$15.50
ARRL UHF/MICROWAVES PROJECT MANUAL (ARRL)	400 pages. \$15.50
MICROWAVE HANDBOOK - COMPONENTS & OPERATING Vol 1 (RSGB)	\$10.50
MICROWAVE HANDBOOK - CONSTRUCTION & TESTING Vol 2 (RSGB)	\$15.75
MICROWAVE HANDBOOK - BANDS & EQUIPMENT Vol 3 (RSGB)	\$15.75 or buy all 3 for \$34

OPERATING AND HANDBOOKS

AMATEUR RADIO OPERATING MANUAL (RSGB) , Ray Eckersley G4FTJ	249 pages. \$12.23
ARRL HANDBOOK 1997 ON CDROM	\$30
ARRL OPERATING MANUAL 1997	\$16.50
BASIC RADIO & ELECTRONIC CALCULATIONS , Ray Petri G0OAT	\$13.95
COMPLETE DX'ER , Bob Locher	204 pages. \$8.95
HAM RADIO MADE EASY (ARRL) , Steve Ford	204 pages. \$12.50
HINTS AND KINKS FOR THE RADIO AMATEUR	
Edited by Charles L. Hutchinson and David Newkirk	129 pages. \$9.50
LOW PROFILE AMATEUR RADIO (ARRL) , Jim Kearman KR1S	124 pages. \$7.50
RADIO COMMUNICATION HANDBOOK (RSGB)	
6th Edition, Dick Biddulph G8PDS	750 pages. \$21.00
SETTING UP AN AMATEUR RADIO STATION BP300 , I. D. Poole	81 pages. \$3.95
TRANSMITTER HUNTING - RADIO DIRECTION FINDING SIMPLIFIED	
Joseph D. Moell & Thomas N. Curlee	325 pages. \$20.95

PACKET

PRACTICAL GUIDE TO PACKET OPERATION IN THE UK	
Mike Mansfield G6AWD NEW EDITION	220 pages. \$11.50
PACKET RADIO PRIMER (RSGB) , Dave Comber G8UYZ & Martyn Corfit G8NZU	266 pages. \$8.95
PACKET, SPEED & MORE SPEED APPLICATIONS	148 pages. \$10.50
YOUR PACKET COMPANION , Steve Ford WB8IMY	170 pages. \$5.95

Practical Wireless, December 1997

PROPAGATION

AN INTRODUCTION TO RADIO WAVE PROPAGATION BP293 , J.G. Lee	116 pages. \$3.95
---	-------------------

QRP

G-QRP CLUB CIRCUIT HANDBOOK , Edited by Rev. G. Dobbs G3RJV	96 pages. \$9.00
INTRODUCING QRP , Dick Pascoe G0BPS	\$6.95
W1FB'S QRP NOTEBOOK (ARRL) , 2nd Edition, Doug De Maw W1FB	175 pages. \$7.95

TEST EQUIPMENT

GETTING THE MOST FROM YOUR MULTIMETER BP239 , R. A. Penfold	102 pages. \$2.95
HANDS-ON GUIDE TO OSCILLOSCOPES , Barry Ross	228 pages. \$17.95
HOW TO USE OSCILLOSCOPES & OTHER TEST EQUIPMENT BP267	
R. A. Penfold	104 pages. \$3.50
MORE ADVANCED TEST EQUIPMENT CONSTRUCTION BP249 , R. A. Penfold	102 pages. \$3.50
MORE ADVANCED USES OF THE MULTIMETER BP265 , R. A. Penfold	96 pages. \$2.95
AN INTRODUCTION TO THE ELECTROMAGNETIC WAVE BP315	
F. A. Wilson	122 pages. \$4.95
PRACTICAL TRANSMITTERS FOR NOVICES , John Case GW4HWR	126 pages. \$10.00
TEST EQUIPMENT FOR THE RADIO AMATEUR , Clive Smith G4FZH	170 pages. \$10.95

VHF

ALL ABOUT VHF AMATEUR RADIO , W. I. Orr W6SAL	163 pages. \$9.50
--	-------------------

ELECTRONICS

A REFERENCE GUIDE TO PRACTICAL ELECTRONICS TERMS BP287	
F. A. Wilson	431 pages. \$5.95
CIRCUIT SOURCE BOOK 1 - BP321 , R.A. Penfold	182 pages. \$4.95
CIRCUIT SOURCE BOOK 2 - BP322 , R.A. Penfold	214 pages. \$4.95
GETTING STARTED IN PRACTICAL ELECTRONICS BP345 , Owen Bishop	198 pages. \$4.95
NEWNES AUDIO AND HI-FI ENGINEER'S POCKET BOOK Third Edition	
Vivian Capel	210 pages. \$12.95
NEWNES ELECTRONICS ENGINEER'S POCKET BOOK , Keith Brindley	306 pages. \$12.95
POWER SUPPLY PROJECTS BP76 , R. A. Penfold	89 pages. \$3.99
PREAMPLIFIER & FILTER CIRCUITS BP309 , R.A. Penfold	92 pages. \$3.95
PRACTICAL ELECTRONIC FILTERS BP299 , Owen Bishop	89 pages. \$4.95
PRACTICAL ELECTRONICS HANDBOOK , Ian Sinclair	439 pages. \$13.95
PRACTICAL OSCILLATOR CIRCUITS BP393 , A. Flind	136 pages. \$4.99
TEST EQUIPMENT CONSTRUCTION BP248 , R.A. Penfold	104 pages. \$3.99
THE ART OF SOLDERING BP324 , R. Brewster	\$3.99
UNDERSTANDING BASIC ELECTRONICS (ARRL)	\$16.50
W1FB'S DESIGN NOTEBOOK (ARRL) , Doug DeMAW W1FB	195 pages. \$8.50

DATA

ARRL ELECTRONICS DATA BOOK , Doug DeMaw W1FB	260 pages. \$8.95
ELECTRONIC HOBBYIST DATA BOOK BP396 , R.A. Penfold	242 pages. \$5.95
PRACTICAL ELECTRONICS CALCULATIONS AND FORMULAE BP53	
F. A. Wilson	249 pages. \$3.95
PRACTICAL ELECTRONIC DESIGN DATA BP316 , Owen Bishop	327 pages. \$5.99
RADIO AMATEUR AND LISTENER'S DATA HANDBOOK , Steve Money	40 pages. \$15.95
RADIO FREQUENCY TRANSISTORS PRINCIPLES AND PRACTICAL APPLICATIONS	
Norm Dye & Helge Granberg	235 pages. \$19.95
SECRETS OF RF CIRCUIT DESIGN , Joseph Carr	405 pages. \$19.95
SOLID STATE DESIGN FOR THE RADIO AMATEUR (ARRL)	
Les Hayward W7ZOI & Doug DeMaw W1FB	256 pages. \$10.50
TOWERS INTERNATIONAL MOSPOWER & OTHER FET SELECTOR	140 pages. \$19.95
TOWERS INTERNATIONAL TRANSISTOR SELECTOR - UPDATE 5	476 pages. \$24.95
TRANSISTOR DATA TABLES (BP401)	178 pages. \$5.95

PROJECTS

COIL DESIGN AND CONSTRUCTION MANUAL BP160 , B.B. Bahani	106 pages. \$3.95
HOW TO DESIGN AND MAKE YOUR OWN PCBs BP121 , R. A. Penfold	66 pages. \$2.50
MORE ADVANCED POWER SUPPLY PROJECTS BP192 , R. A. Penfold	92 pages. \$2.95
PROJECTS FOR RADIO AMATEURS AND SWLS BP304 , R. A. Penfold	92 pages. \$3.95
SHORT WAVE SUPERHET RECEIVER CONSTRUCTION BP276 , R.A. Penfold	80 pages. \$2.95
SIMPLE SHORT WAVE RECEIVER CONSTRUCTION BP275 , R. A. Penfold	88 pages. \$3.95

VALVES/TUBES

ELECTRON TUBE LOCATOR , George H. Fathauer	350 pages. \$21.95
ESSENTIAL CHARACTERISTICS (TUBES & TRANSISTORS)	
(Original Publishers General Electric) Re-published by Antique Electronic Supply (Arizona)	475 pages. \$10.50
HANDBOOK OF RADIO, TV, INDUSTRIAL & TRANSMITTING TUBE & VALVE EQUIVALENTS	60 pages. \$2.95
RADIO VALVE GUIDE BOOKS 1-5	\$2.95 each
RCA RECEIVING TUBE MANUAL (Original Publishers Radio Corporation Of America)	
Re-published by Antique Electronic Supply (Arizona)	384 pages. \$10.50
RCA TRANSMITTING TUBES	
(Original Publisher Radio Corporation of America) Re-published by Antique Electronic Supply (Arizona)	318 pages. \$10.50
TUBE SUBSTITUTION HANDBOOK	\$15.50

KITS

THE PW CADET RECEIVER KIT (as featured in PW Jan 1997)	\$23.95
BRUNNING KIT	
(as featured in PW July 1997 - see also <i>Experimenting with Computers</i> book in Computing section)	\$46

CALL THE CREDIT CARD HOTLINE ON
(01202) 659930

THE **UK'S** BEST SELLING **AMATEUR RADIO** MAGAZINE
COMING NEXT MONTH - JANUARY

PRACTICAL

wireless

START THE NEW YEAR WITH A BANG!

ANTENNAS IN ACTION!

Tex Swann G1TEX brings you another eight action packed pages of antennas and all things associated.

AMATEUR RADIO'S CENTENARY

Rob Micklewright G3MYM looks back at the first 100 Years of Amateur Radio.

REVIEWED!

Richard Newton G0RSN looks at the new Kenwood TH-G71E Dual-Bander.

REVIEWED!

Rob Mannion G3XFD tries out the Timewave DSP-599ZX Digital Audio Noise Filter.

FREE! 1998 YEAR PLANNER

CAN YOU AFFORD TO MISS IT? - ON SALE 11 DECEMBER 1997

* Contents subject to change

Coming up in the December Issue

ON SALE 27TH NOVEMBER

Mike Richards Reviews **The Target HF3E.**

Graham Tanner Reviews
Test The Optoelectronics R11 Reciever.

Designing Receiver Projects with the
NE-602 Chip by Joe Carr K4IVP.

John Wilson G3PCY Takes A Look At The **HF-150.**



* Contents subject to change



YOUR LOCAL DEALERS

N. IRELAND
micron electronics
 124 Great Victoria Street
BELFAST
 YAESU, ICOM, KENWOOD, ALINCO +
 AMATEUR & SW radio specialists
 PART EXCHANGE WELCOME
 TEL: (01232) 438610

SURREY
 Chris Rees
G3TUX
 The QRP Component Company
 PO Box 88 Haslemere Surrey GU27 2RF
 Tel: (01428) 661501
 Fax: (01428) 661794
KITS, KEYS & QRP
 MAIL ORDER - 9AM TO 6PM (NOT SUNDAYS)
 SAE FOR LISTS AND LITERATURE

MID GLAMORGAN
SANDPIPER
COMMUNICATIONS
 Unit 5, Enterprise House, Cwmbach
 Industrial Estate, Aberdare,
 Mid Glamorgan CF44 0AE
 Tel: (01685) 870425
 Fax: (01685) 876104
 A full range of transmitting & receiving
 antennas available for the amateur
 commercial market.

LONDON
MARTIN LYNCH
 & Son
 For all your amateur radio needs
 140-142 Northfield Avenue
 Ealing London W13 9SB
 Tel:
0181-566 1120
 Fax:
0181-566 1207

BIRMINGHAM
FREE CB
RADIO CATALOGUE
PHONE
0121-457 7788

SRP RADIO CENTRE

SCOTLAND
JAYCEE
ELECTRONICS LTD
 20 Woodside Way, Glenrothes, Fife KY7 5DF
 Tel: (01592) 756962 (Day or Night)
 Fax No. (01592) 610451
 Now open 7 days a week. Mon-Fri 9am - 5pm,
 Sat 9am - 4pm, Sun 12 noon - 4pm.
 KENWOOD, YAESU & ICOM APPROVED DEALERS
 A good stock of new and secondhand
 equipment always in stock

KENT
KANGA QRP KITS
 Our books: Introducing QRP £7.95
 Pascoe's Penny Pinchers £5.95
 (ALL ABOUT WIRE ANTENNAS)
 Send an SAE for our free catalogue
 Seaview House, Crete Road East
 Folkestone, Kent CT18 7EG
 Tel/Fax 01303 891106 (0930-1900)
 http://www.kanga.demon.co.uk

DORSET
BOOKS BOOKS
BOOKS
 PW PUBLISHING
 BOOK SERVICE
 Tel: (01202) 659930
 Fax: (01202) 659950

WEST YORKSHIRE
HUDDERSFIELD ELECTRONICS
 INC. THE AMATEUR RADIO SHOP
 Suppliers of new & used amateur/SWL/CB
 equipment. We also carry a full range of accessories.
 Part exchanges welcomed.
 4A Cross Church Street
 Huddersfield HD1 2PT.
 Tel/Fax 01484 420774
 Hours: Mon - Sat 9.00am to 5.30pm.

DORSET
THE SHORTWAVE
SHOP
 Novice/C.B./Amateur/SWL Equipment.
 Full range secondhand equipment
 always available.
 18 Fairmile Road, Christchurch,
 Dorset BH23 2LJ
 Tel/Fax: 01202 490099

AVON/SOMERSET
QSL
COMMUNICATIONS
 We stock all makes of equipment
 for the Amateur and Listener.
 Part Exchange Welcome
 Unit 6, Worle Industrial Centre, Coker Road,
 Worle, Weston-Super-Mare BS22 0BX
 Tel/Fax: (01934) 512757

SOUTHAMPTON
SMC Ltd
 Main Dealer for: Yaesu,
 Kenwood, Icom AOR &
 Cushcraft
 SM House, School Close, Chandlers Ford
 Industrial Estate, Eastleigh,
 Hampshire SO5 3BY
 Tel: (01703) 255111
 Fax: (01703) 263507

DERBYSHIRE
Lowe
Electronics
 THE HAM RADIO SUPERSTORE
 Kenwood, Yaesu, Icom etc. always in stock.
 Chesterfield Rd., Matlock, Derby DE4 5LE
 Tel: 01629 580800 Fax: 01629 580020
 E-mail: info@lowe.co.uk orders@lowe.co.uk

To reach almost
 40,000 readers
 every month,
ring Chris on
(01202) 659920
 and advertise
YOUR company

NORTHWEST
ARC Ltd.
 Everything for the radio
 amateur under one roof!
 38 Bridge Street, Earlestown, Newton-
 le-Willows,
 Merseyside WA12 9BA
 Tel: 01925 229881
 Fax: 01925 229882

SCOTLAND
TENNAMAST
SCOTLAND LTD
 Masts from 25ft - 40ft
 Adapt-A-Mast
 (01505) 503824
 81 Mains Road, Belth, Ayrshire. KA15 2HT

Index to Advertisers

Ambyr	75	Langrex Supplies	49	RSGB	66
ARC	55	Leeds Amateur Radio Centre.....	79	SEM	79
Castle Electronics	8	Lowe Electronics	18	Short Wave Magazine	83
Chevet Supplies.....	49	Martin Lynch & Son.....	42/43, 79	SMC	6/7
Cirkit Distribution	49	Mauritron Technical Services	69	Spectrum Communications.....	41
Colomor Electronics	36	Monitoring Times	79	SRP Trading.....	75
Eastern Communications	35	Multicomm 2000	56/57	Sunrise Electronics	62
Essex Amateur Radio Services.....	41	Nevada Communications	4/5	TDC.....	69
Haydon Communications	23, 24/25	PCB Services	55	Telford Electronics.....	79
Hesing Technology	79	Pervisell.....	69	Verulam AR Club rally	69
Howes, C M	36	Photo Acoustics	52	Waters & Stanton.....	IFC/1, 2
Icom UK.....	IBC	Pyramid Electronics	66	Wireless Works	69
Lake Electronics.....	41	RAS Notts	69	Yaesu.....	OBC

ICOM

IC-746

New Year's Revolution the transceiver that everyone's been asking for!

ICOM's latest mid-price transceiver

*The IC-746 is ICOM's latest HF/VHF transceiver, providing wideband coverage; HF to 50MHz through to 144MHz. Superior design, VHF base-station capabilities, DSP and 100 watt RF output will make this **THE** transceiver to own in '98.*

- 1.8MHz-144MHz multimode coverage
- 100W output for all HF, 50MHz and 144MHz bands
- DSP fitted as standard
- Continually adjustable noise reduction
- Auto notch filter
- Selectable APF with 3 passband widths
- Twin PBT capability, first in a mid-range radio
- Large, easy-to-read function display
- Auto antenna tuner with preset memories
- Compact dimensions 287 x 120 x 317 (mm)
- Memo pad with 10 channels
- Tone squelch standard with 50 tone frequencies
- Ample CW functions with 4-channel memory keyer
- 12.5kHz FM narrow capability
- Quick split, ideal for DX'ers
- 3 different antenna connections
- 2-step pre-amp (single for 144MHz)
- Optional UT-102 voice synthesizer



Icom (UK) Ltd. Sea Street Herne Bay Kent CT6 8LD. Telephone: 01227 741741. Fax: 01227 741742.
INTERNET: <http://www.icomuk.co.uk> E-MAIL: icomsales@icomuk.co.uk

Count on us!

"The VX-1R is smaller than most pagers!"

"Over 19 hours* of use from the rechargeable lithium ion battery!"




"VHF, UHF, AM, FM, Air Band, Police, Fire--TV" too? Wow"

"Looks like Yaesu did it again!"

The world's smallest HT with all the high-tech features you'd want in the world!

The ultra-compact size of the VX-1R Dual-Band is the first thing you notice as you cradle it in your palm. But the high-tech features make this radio one you must have now! Simple combinations, using seven buttons and one knob, control this marvel of engineering. One soft key touch and wide receive VHF/UHF 76~999 MHz Rx ; 144~146, 430~440 MHz Tx, or AM/FM Broadcast, Airband or other public services - even TV, spring to life! Touch again for Yaesu-exclusives, SmartSearch™ and ARTS™, or Priority Channel Alarm. Built-in CTCSS and DCS Encode/Decode for 2m/440 amateur bands, CTCSS/DCS Tone Search, and Dual Watch, are included along with 291 Memory Channels in 9 banks with 500 mW power output. Backlit LCD Display shows 6-character alphanumeric capability; backlit keypad makes operation easy in dim light. And, although the VX-1R is the world's smallest dual-band HT, you get over 19 hours* of use with just a 1 hour recharge from its long-lasting lithium ion battery! Big features, small size--the most satisfying combination in the world!



VX-1R

Ultra-Compact Dual-Band Handheld

Actual Size Shown
1 7/8" x 3 3/16" x 1 5/16"

Features

- Frequency Coverage
 - Wide Multi-Band Receive RX: 76~999 MHz**
 - TX: 144~146, 430~440 MHz
- AM/FM/TV Broadcast Receive
- AM Aircraft/Public Safety Receive
- CTCSS Encode/Decode
- DCS Encode/Decode
- CTCSS/DCS Tone Search
- Dual Watch
- SmartSearch™
- Auto Range Transpond System™ (ARTS™)
- Priority Channel Alarm
- ADMS-1D Windows™ Programmable
- 1 Watt External Power Supply
- 80 Minute Rapid Charger
- Flexible Antenna, Belt Clip, Hand Strap

**Cellular blocked

*Battery Life: 5-5-90 duty cycle.

FT-50R
Compact Dual Band Handheld



FT-51R
Dual Band Handheld

YAESU

...leading the way.™

<http://www.yaesu.co.uk>

Specifications subject to change without notice. Specifications guaranteed only within amateur bands. Some accessories and/or options are standard in certain areas. Check with your local Yaesu dealer for specific details.

YAESU UK LTD. Unit 2, Maple Grove Business Centre, Lawrence, Rd., Hounslow, Middlesex, TW4 6DR, U.K. 0181-814-2001