


Simulink® Coder™

Reference



MATLAB® & SIMULINK®

R2020a



How to Contact MathWorks



Latest news: www.mathworks.com
Sales and services: www.mathworks.com/sales_and_services
User community: www.mathworks.com/matlabcentral
Technical support: www.mathworks.com/support/contact_us



Phone: 508-647-7000



The MathWorks, Inc.
1 Apple Hill Drive
Natick, MA 01760-2098

Simulink[®] *Coder*[™] *Reference*

© COPYRIGHT 2011–2020 by The MathWorks, Inc.

The software described in this document is furnished under a license agreement. The software may be used or copied only under the terms of the license agreement. No part of this manual may be photocopied or reproduced in any form without prior written consent from The MathWorks, Inc.

FEDERAL ACQUISITION: This provision applies to all acquisitions of the Program and Documentation by, for, or through the federal government of the United States. By accepting delivery of the Program or Documentation, the government hereby agrees that this software or documentation qualifies as commercial computer software or commercial computer software documentation as such terms are used or defined in FAR 12.212, DFARS Part 227.72, and DFARS 252.227-7014. Accordingly, the terms and conditions of this Agreement and only those rights specified in this Agreement, shall pertain to and govern the use, modification, reproduction, release, performance, display, and disclosure of the Program and Documentation by the federal government (or other entity acquiring for or through the federal government) and shall supersede any conflicting contractual terms or conditions. If this License fails to meet the government's needs or is inconsistent in any respect with federal procurement law, the government agrees to return the Program and Documentation, unused, to The MathWorks, Inc.

Trademarks

MATLAB and Simulink are registered trademarks of The MathWorks, Inc. See www.mathworks.com/trademarks for a list of additional trademarks. Other product or brand names may be trademarks or registered trademarks of their respective holders.

Patents

MathWorks products are protected by one or more U.S. patents. Please see www.mathworks.com/patents for more information.

Revision History

April 2011	Online only	New for Version 8.0 (Release 2011a)
September 2011	Online only	Revised for Version 8.1 (Release 2011b)
March 2012	Online only	Revised for Version 8.2 (Release 2012a)
September 2012	Online only	Revised for Version 8.3 (Release 2012b)
March 2013	Online only	Revised for Version 8.4 (Release 2013a)
September 2013	Online only	Revised for Version 8.5 (Release 2013b)
March 2014	Online only	Revised for Version 8.6 (Release 2014a)
October 2014	Online only	Revised for Version 8.7 (Release 2014b)
March 2015	Online only	Revised for Version 8.8 (Release 2015a)
September 2015	Online only	Revised for Version 8.9 (Release 2015b)
October 2015	Online only	Rereleased for Version 8.8.1 (Release 2015aSP1)
March 2016	Online only	Revised for Version 8.10 (Release 2016a)
September 2016	Online only	Revised for Version 8.11 (Release 2016b)
March 2017	Online only	Revised for Version 8.12 (Release 2017a)
September 2017	Online only	Revised for Version 8.13 (Release 2017b)
March 2018	Online only	Revised for Version 8.14 (Release 2018a)
September 2018	Online only	Revised for Version 9.0 (Release 2018b)
March 2019	Online only	Revised for Version 9.1 (Release 2019a)
September 2019	Online only	Revised for Version 9.2 (Release 2019b)
March 2020	Online only	Revised for Version 9.3 (Release 2020a)

Check Bug Reports for Issues and Fixes

Software is inherently complex and is not free of errors. The output of a code generator might contain bugs, some of which are not detected by a compiler. MathWorks reports critical known bugs brought to its attention on its Bug Report system at www.mathworks.com/support/bugreports/. In the search bar, type the phrase "Incorrect Code Generation" to obtain a report of known bugs that produce code that might compile and execute, but still produce wrong answers. To save a search, click Save Search.

The bug reports are an integral part of the documentation for each release. Examine periodically all bug reports for a release, as such reports may identify inconsistencies between the actual behavior of a release you are using and the behavior described in this documentation.

In addition to reviewing bug reports, you should implement a verification and validation strategy to identify potential bugs in your design, code, and tools.

1	Simulink Code Generation Limitations	
	Simulink Code Generation Limitations	1-2
2		Apps
3	Simulink Coder Functions	
4	Simulink Coder Blocks	
5	Code Generation Parameters: Code Generation	
	Model Configuration Parameters: Code Generation	5-2
	Code Generation: General Tab Overview	5-5
	To get help on an option	5-5
	System target file	5-6
	Description	5-6
	Settings	5-6
	Tips	5-6
	Command-Line Information	5-6
	Recommended Settings	5-6
	Browse	5-8
	Description	5-8
	Tips	5-8

Language	5-9
Description	5-9
Settings	5-9
Dependencies	5-9
Command-Line Information	5-9
Recommended Settings	5-9
Description	5-11
Description	5-11
Toolchain	5-12
Description	5-12
Settings	5-12
Tip	5-12
Command-Line Information	5-12
Recommended Settings	5-12
Build configuration	5-14
Description	5-14
Settings	5-14
Tip	5-14
Dependencies	5-15
Command-Line Information	5-15
Recommended Settings	5-15
Tool/Options	5-16
Description	5-16
Settings	5-16
Dependencies	5-16
Command-Line Information	5-16
Compiler optimization level	5-17
Description	5-17
Settings	5-17
Tips	5-17
Dependencies	5-17
Command-Line Information	5-17
Recommended Settings	5-18
Custom compiler optimization flags	5-19
Description	5-19
Settings	5-19
Dependency	5-19
Command-Line Information	5-19
Recommended Settings	5-19
Generate makefile	5-20
Description	5-20
Settings	5-20
Dependencies	5-20
Command-Line Information	5-20
Recommended Settings	5-20
Make command	5-22
Description	5-22

Settings	5-22
Tip	5-22
Dependency	5-22
Command-Line Information	5-22
Recommended Settings	5-23
Template makefile	5-24
Description	5-24
Settings	5-24
Tips	5-24
Dependency	5-24
Command-Line Information	5-24
Recommended Settings	5-24
Select objective	5-26
Description	5-26
Settings	5-26
Dependency	5-26
Command-Line Information	5-26
Recommended Settings	5-26
Check Model	5-28
Description	5-28
Settings	5-28
Dependency	5-28
Check model before generating code	5-29
Description	5-29
Settings	5-29
Command-Line Information	5-29
Recommended Settings	5-29
Generate code only	5-31
Description	5-31
Settings	5-31
Tip	5-31
Command-Line Information	5-31
Recommended Settings	5-31
Package code and artifacts	5-32
Description	5-32
Settings	5-32
Dependency	5-32
Command-Line Information	5-32
Recommended Settings	5-32
Zip file name	5-33
Description	5-33
Settings	5-33
Dependency	5-33
Command-Line Information	5-33
Recommended Settings	5-33
Custom FFT library callback	5-34
Description	5-34

Settings	5-34
Limitation	5-34
Tip	5-34
Command-Line Information	5-34
Recommended Settings	5-34
Custom BLAS library callback	5-36
Description	5-36
Settings	5-36
Limitation	5-36
Tip	5-36
Command-Line Information	5-36
Recommended Settings	5-36
Custom LAPACK library callback	5-38
Description	5-38
Settings	5-38
Limitation	5-38
Tip	5-38
Command-Line Information	5-38
Recommended Settings	5-38
Verbose build	5-40
Description	5-40
Settings	5-40
Command-Line Information	5-40
Recommended Settings	5-40
Retain .rtw file	5-41
Description	5-41
Settings	5-41
Command-Line Information	5-41
Recommended Settings	5-41
Profile TLC	5-42
Description	5-42
Settings	5-42
Command-Line Information	5-42
Recommended Settings	5-42
Start TLC debugger when generating code	5-43
Description	5-43
Settings	5-43
Tips	5-43
Command-Line Information	5-43
Recommended Settings	5-43
Start TLC coverage when generating code	5-44
Description	5-44
Settings	5-44
Tip	5-44
Command-Line Information	5-44
Recommended Settings	5-44

Enable TLC assertion	5-45
Description	5-45
Settings	5-45
Command-Line Information	5-45
Recommended Settings	5-45
Show Custom Hardware App in Simulink Toolstrip	5-46
Description	5-46
Settings	5-46
Command-Line Information	5-46
Recommended Settings	5-46
Show Embedded Hardware App in Simulink Toolstrip	5-47
Description	5-47
Settings	5-47
Command-Line Information	5-47
Recommended Settings	5-47

Code Generation Parameters: Report

6

Model Configuration Parameters: Code Generation Report	6-2
Code Generation: Report Tab Overview	6-4
Configuration	6-4
Create code generation report	6-5
Description	6-5
Settings	6-5
Dependency	6-6
Command-Line Information	6-6
Recommended Settings	6-6
Open report automatically	6-7
Description	6-7
Settings	6-7
Dependency	6-7
Command-Line Information	6-7
Recommended Settings	6-7

Code Generation Parameters: Comments

7

Model Configuration Parameters: Comments	7-2
Auto generated comments	7-2
Custom comments	7-2
Code Generation: Comments Tab Overview	7-5

Include comments	7-6
Description	7-6
Settings	7-6
Dependencies	7-6
Command-Line Information	7-6
Recommended Settings	7-6
Simulink block comments	7-8
Description	7-8
Settings	7-8
Dependency	7-8
Command-Line Information	7-8
Recommended Settings	7-8
Stateflow object comments	7-9
Description	7-9
Settings	7-9
Dependency	7-9
Command-Line Information	7-9
Recommended Settings	7-9
MATLAB source code as comments	7-11
Description	7-11
Settings	7-11
Dependency	7-11
Command-Line Information	7-11
Recommended Settings	7-11
Show eliminated blocks	7-13
Description	7-13
Settings	7-13
Dependency	7-13
Command-Line Information	7-13
Recommended Settings	7-13
Verbose comments for 'Model default' storage class	7-14
Description	7-14
Settings	7-14
Dependency	7-14
Command-Line Information	7-14
Recommended Settings	7-15

Code Generation Parameters: Identifiers

8

Model Configuration Parameters: Code Generation Identifiers	8-2
Code Generation: Identifiers Tab Overview	8-4
Maximum identifier length	8-5
Description	8-5
Settings	8-5

Tips	8-5
Command-Line Information	8-5
Recommended Settings	8-5
Use the same reserved names as Simulation Target	8-7
Description	8-7
Settings	8-7
Command-Line Information	8-7
Recommended Settings	8-7
Reserved names	8-8
Description	8-8
Settings	8-8
Tips	8-8
Command-Line Information	8-8
Recommended Settings	8-8
Duplicate enumeration member names	8-10
Description	8-10
Settings	8-10
Command-Line Information	8-10
Example	8-10
Recommended Settings	8-11

Code Generation Parameters: Custom Code

9

Model Configuration Parameters: Code Generation Custom Code	9-2
Code Generation: Custom Code Tab Overview	9-3
Configuration	9-3
Use the same custom code settings as Simulation Target	9-4
Description	9-4
Settings	9-4
Command-Line Information	9-4
Recommended Settings	9-4
Source file	9-5
Description	9-5
Settings	9-5
Command-Line Information	9-5
Recommended Settings	9-5
Header file	9-6
Description	9-6
Settings	9-6
Command-Line Information	9-6
Recommended Settings	9-6
Initialize function	9-7
Description	9-7

Settings	9-7
Command-Line Information	9-7
Recommended Settings	9-7
Terminate function	9-8
Description	9-8
Settings	9-8
Dependency	9-8
Command-Line Information	9-8
Recommended Settings	9-8
Include directories	9-9
Description	9-9
Settings	9-9
Command-Line Information	9-9
Recommended Settings	9-9
Source files	9-11
Description	9-11
Settings	9-11
Limitation	9-11
Tip	9-11
Command-Line Information	9-11
Recommended Settings	9-11
Libraries	9-12
Description	9-12
Settings	9-12
Limitation	9-12
Tip	9-12
Command-Line Information	9-12
Recommended Settings	9-12
Defines	9-13
Description	9-13
Settings	9-13
Command-Line Information	9-13
Recommended Settings	9-13

Code Generation Parameters: Interface

10

Model Configuration Parameters: Code Generation Interface	10-2
Code Generation: Interface Tab Overview	10-8
Code replacement library	10-9
Description	10-9
Settings	10-9
Tips	10-9
Command-Line Information	10-9
Recommended Settings	10-10

Shared code placement	10-11
Description	10-11
Settings	10-11
Command-Line Information	10-11
Recommended Settings	10-11
Support: non-finite numbers	10-13
Description	10-13
Settings	10-13
Dependencies	10-13
Command-Line Information	10-13
Recommended Settings	10-13
Code interface packaging	10-15
Description	10-15
Settings	10-15
Tips	10-15
Dependencies	10-16
Command-Line Information	10-16
Recommended Settings	10-16
Multi-instance code error diagnostic	10-18
Description	10-18
Settings	10-18
Dependencies	10-18
Command-Line Information	10-18
Recommended Settings	10-18
Generate C API for: signals	10-20
Description	10-20
Settings	10-20
Command-Line Information	10-20
Recommended Settings	10-20
Generate C API for: parameters	10-21
Description	10-21
Settings	10-21
Command-Line Information	10-21
Recommended Settings	10-21
Generate C API for: states	10-22
Description	10-22
Settings	10-22
Command-Line Information	10-22
Recommended Settings	10-22
Generate C API for: root-level I/O	10-23
Description	10-23
Settings	10-23
Command-Line Information	10-23
Recommended Settings	10-23
ASAP2 interface	10-24
Description	10-24
Settings	10-24

Command-Line Information	10-24
Recommended Settings	10-24
External mode	10-25
Description	10-25
Settings	10-25
Command-Line Information	10-25
Recommended Settings	10-25
Transport layer	10-26
Description	10-26
Settings	10-26
Tips	10-26
Dependency	10-27
Command-Line Information	10-27
Recommended Settings	10-27
MEX-file arguments	10-28
Description	10-28
Settings	10-28
Dependency	10-29
Command-Line Information	10-29
Recommended Settings	10-29
Static memory allocation	10-30
Description	10-30
Settings	10-30
Tips	10-30
Dependencies	10-30
Command-Line Information	10-30
Recommended Settings	10-30
Static memory buffer size	10-32
Description	10-32
Settings	10-32
Tips	10-32
Dependency	10-32
Command-Line Information	10-32
Recommended Settings	10-32
LUT object struct order for even spacing specification	10-34
Description	10-34
Settings	10-34
Command-Line Information	10-34
Recommended Settings	10-34
LUT object struct order for explicit value specification	10-35
Description	10-35
Settings	10-35
Command-Line Information	10-35
Recommended Settings	10-35
Buffer size of dynamically-sized string (bytes)	10-36
Description	10-36
Settings	10-36

Command-Line Information	10-36
Recommended Settings	10-36
Array layout	10-37
Description	10-37
Settings	10-37
Command-Line Information	10-37
Recommended Settings	10-37
External functions compatibility for row-major code generation	10-39
Description	10-39
Settings	10-39
Dependencies	10-39
Command-Line Information	10-39
Recommended Settings	10-39
Standard math library	10-41
Description	10-41
Settings	10-41
Tips	10-41
Dependencies	10-42
Command-Line Information	10-42
Recommended Settings	10-42
Maximum word length	10-43
Description	10-43
Settings	10-43
Tips	10-43
Dependencies	10-43
Command-Line Information	10-43
Recommended Settings	10-44
Classic call interface	10-45
Description	10-45
Settings	10-45
Tips	10-45
Dependencies	10-45
Command-Line Information	10-45
Recommended Settings	10-46
Single output/update function	10-47
Description	10-47
Settings	10-47
Tips	10-47
Dependencies	10-47
Command-Line Information	10-48
Recommended Settings	10-48
MAT-file logging	10-49
Description	10-49
Settings	10-49
Dependencies	10-49
Limitations	10-50
Command-Line Information	10-50
Recommended Settings	10-50

Simulink Coder Parameters: Advanced Parameters

11

Use Simulink Coder Features	11-2
Description	11-2
Settings	11-2
Dependencies	11-2
Command-Line Information	11-2

Configuration Parameters for Simulink Models

12

Code Generation Pane: RSim Target	12-2
Code Generation: RSim Target Tab Overview	12-2
Enable RSim executable to load parameters from a MAT-file	12-2
Solver selection	12-3
Force storage classes to AUTO	12-4
Code Generation Pane: S-Function Target	12-5
Code Generation S-Function Target Tab Overview	12-5
Create new model	12-5
Use value for tunable parameters	12-6
Include custom source code	12-6
Code Generation Pane: Tornado Target	12-8
Code Generation: Tornado Target Tab Overview	12-9
Standard math library	12-9
Code replacement library	12-10
Shared code placement	12-11
MAT-file logging	12-12
MAT-file variable name modifier	12-13
Code Format	12-14
StethoScope	12-14
Download to VxWorks target	12-15
Base task priority	12-16
Task stack size	12-17
External mode	12-17
Transport layer	12-18
MEX-file arguments	12-19
Static memory allocation	12-20
Static memory buffer size	12-20
Recommended Settings Summary for Model Configuration Parameters	12-22

13

Simulink Coder Checks	13-2
Simulink Coder Checks Overview	13-2
Identify blocks using one-based indexing	13-2
Check solver for code generation	13-3
Check for blocks not supported by code generation	13-4
Check and update model to use toolchain approach to build generated code	13-4
Check and update embedded target model to use ert.tlc system target file	13-6
Check and update models that are using targets that have changed significantly across different releases of MATLAB	13-7
Check for blocks that have constraints on tunable parameters	13-8
Check for model reference configuration mismatch	13-9
Check sample times and tasking mode	13-10
Check for code generation identifier formats used for model reference	13-11
Available Checks for Code Generation Objectives	13-11
Identify questionable blocks within the specified system	13-18
Check model configuration settings against code generation objectives	13-19
Code Generation Advisor Checks	13-20
Available Checks for Code Generation Objectives	13-20
Identify questionable blocks within the specified system	13-26
Check model configuration settings against code generation objectives	13-27

Parameters for Creating Protected Models

14

Create Protected Model	14-2
Create Protected Model: Overview	14-2
Open read-only view of model	14-2
Simulate	14-3
Use generated code	14-3
Code interface	14-4
Content type	14-5
Use generated HDL code	14-6
Create protected model in	14-6
Create harness model for protected model	14-7

Optimization Parameters

Model Configuration Parameters: Code Generation Optimization	16-2
Optimization Pane: Tab Overview	16-5
Tips	16-5
To get help on an option	16-5
Remove code from floating-point to integer conversions that wraps out-of-range values	16-6
Description	16-6
Settings	16-6
Tips	16-6
Dependency	16-6
Command-Line Information	16-6
Recommended Settings	16-7
Buffer for reusable subsystems	16-8
Description	16-8
Settings	16-8
Command-Line Information	16-8
Recommended Settings	16-8
Default parameter behavior	16-9
Description	16-9
Settings	16-9
Tips	16-9
Dependencies	16-9
Command-Line Information	16-10
Recommended Settings	16-10
Inline invariant signals	16-11
Description	16-11
Settings	16-11
Dependencies	16-11
Command-Line Information	16-11
Recommended Settings	16-11
Use memcopy for vector assignment	16-13
Description	16-13
Settings	16-13
Dependencies	16-13
Command-Line Information	16-13
Recommended Settings	16-13
Memcopy threshold (bytes)	16-15
Description	16-15

Settings	16-15
Dependencies	16-15
Command-Line Information	16-15
Recommended Settings	16-15
Loop unrolling threshold	16-16
Description	16-16
Settings	16-16
Dependency	16-16
Command-Line Information	16-16
Recommended Settings	16-16
Maximum stack size (bytes)	16-17
Description	16-17
Settings	16-17
Tips	16-17
Command-Line Information	16-17
Recommended Settings	16-18
Use bitsets for storing state configuration	16-19
Description	16-19
Settings	16-19
Tips	16-19
Dependency	16-19
Command-Line Information	16-19
Recommended Settings	16-19
Use bitsets for storing Boolean data	16-21
Description	16-21
Settings	16-21
Tips	16-21
Dependency	16-21
Command-Line Information	16-21
Recommended Settings	16-21
Base storage type for automatically created enumerations	16-23
Description	16-23
Settings	16-23
Tips	16-23
Dependency	16-23
Command-Line Information	16-23
Enable local block outputs	16-25
Description	16-25
Settings	16-25
Tips	16-25
Dependencies	16-25
Command-Line Information	16-25
Recommended Settings	16-25
Reuse local block outputs	16-27
Description	16-27
Settings	16-27
Dependencies	16-27
Command-Line Information	16-27

Recommended Settings	16-27
Eliminate superfluous local variables (Expression folding)	16-29
Description	16-29
Settings	16-29
Dependencies	16-29
Command-Line Information	16-29
Recommended Settings	16-29
Remove code from floating-point to integer conversions with saturation that maps NaN to zero	16-31
Description	16-31
Settings	16-31
Tips	16-31
Dependencies	16-31
Command-Line Information	16-31
Recommended Settings	16-32
Use memset to initialize floats and doubles to 0.0	16-33
Description	16-33
Settings	16-33
Dependency	16-33
Command-Line Information	16-33
Recommended Settings	16-33
Signal storage reuse	16-35
Description	16-35
Settings	16-35
Tips	16-35
Dependencies	16-35
Command-Line Information	16-36
Recommended Settings	16-36

Simulink Code Generation Limitations

Simulink Code Generation Limitations

The following topics identify Simulink code generation limitations:

- “C++ Language Support Limitations”
- “Limitations”
- “Tunable Expression Limitations”
- “Generate Reentrant Code from Subsystems”
- “Code Generation Model Referencing Limitations”
- “TCP/IP and Serial External Mode Limitations”
- “Noninlined S-Function Parameter Type Limitations”
- “S-Function Target Limitations”
- “Rapid Simulation Target Limitations”
- “Asynchronous Support Limitations”
- “C API Limitations”
- “Blocks and Products Supported for Code Generation”

Apps

Simulink Coder

Generate and execute C and C++ code from Simulink models, Stateflow charts, and MATLAB functions for use in applications such as simulation acceleration, rapid prototyping, and hardware-in-the-loop (HIL) simulations

Description

To generate C or C++ code from a model that represents a discrete-time system, use the **Simulink Coder** app. When you open the app, a **C Code** tab is added to the toolstrip. The **C Code** tab contains sections that represent steps of the Simulink Coder workflow. You can iterate through model preparation for code generation, code generation and builds, and code verification by using the editor window panels.

Use the app to:

- Access help. On the left side of the Simulink Editor window, click the **Code Perspective Help** tab.
- Learn product basics while quickly configuring a model for code generation. If you are new to Simulink Coder, use the Simulink Coder Quick Start to prepare a model for code generation. The Simulink Coder Quick Start chooses fundamental code generation settings based on your goals and application. To open the Simulink Coder Quick Start, click **Quick Start**.
- Set code generation objectives and prepare a model for code generation. Click **C/C++ Code Generation Advisor**.
- Configure model-wide code generation parameter settings. Click **Settings**.
- Configure data. At the bottom of the editor window, click the **Model Data Editor** tab. On the left side of the editor window, click the **Property Inspector** tab.
- Generate code or build an executable program. Select **Build > Generate Code** or **Build > Build**.
- Review generated code. Click **Open Report**.
- Create a protected model for simulation and code generation to share with a third party. Select **Share > Generate Protected Model**.
- Package generated code and artifacts for deployment to another computer system. Select **Share > Generate Code and Package**.

Open the Simulink Coder App

In the **Apps** gallery, under **Code generation**, click **Simulink Coder**. The **C Code** tab opens.

Examples

- “Generate Code by Using the Quick Start Tool”
- “Generate Code Using Simulink® Coder™”
- “Design Models for Rapid Prototyping Deployment”

Tips

- If you are working with a model hierarchy, open the **Simulink Coder** app in the Simulink Editor window for the top model of the hierarchy that you are generating code for. On the **C Code** tab, the functionalities apply to the top model of the hierarchy that is open in the editor.
- To configure code for a referenced model, navigate to the model in the hierarchy and use the Model Data Editor and the Property Inspector. These views apply to the active model, which can be the top model or a referenced model.

See Also

Topics

“Generate Code by Using the Quick Start Tool”

“Generate Code Using Simulink® Coder™”

“Design Models for Rapid Prototyping Deployment”

Introduced in R2019b

Run on Custom Hardware

Run external mode simulations

Description

The Run on Custom Hardware app enables you to run external mode simulations on your development computer or other target hardware. In an external mode simulation, you can tune parameters in real time and monitor target application signals.

To run an external mode simulation, you:

- 1 Build the target application on your development computer.
- 2 Deploy the target application to the target hardware.
- 3 Connect Simulink to the target application that runs on the target hardware.
- 4 Start execution of generated code on the target hardware.

Using the app, you can:

- Perform the steps separately or with one click.
- Register custom launchers that deploy the target application.

Open the Run on Custom Hardware App

On the **Apps** tab, click **Run on Custom Hardware**. Or, on the **C Code** tab, select **Verify Code > Run on Custom Hardware**.

Examples

Run XCP External Mode Simulation

For an example that uses the Run on Custom Hardware app, see “Run XCP External Mode Simulation on Development Computer”.

See Also

Topics

“External Mode Simulation by Using XCP Communication”

“External Mode Simulation with TCP/IP or Serial Communication”

Introduced in R2019b

Simulink Coder Functions

addCompileFlags

Add compiler options to model build information

Syntax

```
addCompileFlags(buildinfo,options,groups)
```

Description

`addCompileFlags(buildinfo,options,groups)` specifies the compiler options to add to the build information.

The function requires the *buildinfo* and *options* arguments. You can use an optional *groups* argument to group your options.

The code generator stores the compiler options in a build information object. The function adds options to the object based on the order in which you specify them.

Examples

Add Compiler Flags to OPTS Group

Add the compiler option `-O3` to the build information `myModelBuildInfo` and place the option in the group `OPTS`.

```
myModelBuildInfo = RTW.BuildInfo;  
addCompileFlags(myModelBuildInfo,'-O3','OPTS');
```

Add Compiler Flags to OPT_OPTS Group

Add the compiler options `-Zi` and `-Wall` to the build information `myModelBuildInfo` and place the options in the group `OPT_OPTS`.

```
myModelBuildInfo = RTW.BuildInfo;  
addCompileFlags(myModelBuildInfo,'-Zi -Wall','OPT_OPTS');
```

Add Compiler Flags to Build Information

For a non-makefile build environment, add the compiler options `-Zi`, `-Wall`, and `-O3` to the build information `myModelBuildInfo`. Place the options `-Zi` and `-Wall` in the group `Debug` and the option `-O3` in the group `MemOpt`.

```
myModelBuildInfo = RTW.BuildInfo;
addCompileFlags(myModelBuildInfo,{'-Zi -Wall' '-O3'}, ...
    {'Debug' 'MemOpt'});
```

Input Arguments

buildinfo — Build information object

object

RTW.BuildInfo object that contains information for compiling and linking generated code.

options — List of compiler options to add to build information

character vector | array of character vectors | string

You can specify the *options* argument as a character vector, as an array of character vectors, or as a string. You can specify the *options* argument as multiple compiler flags within a single character vector, for example `'-Zi -Wall'`. If you specify the *options* argument as multiple character vectors, for example, `'-Zi -Wall'` and `'-O3'`, the *options* argument is added to the build information as an array of character vectors.

Example: `{'-Zi -Wall' '-O3'}`

groups — Optional group name for the added compiler options

character vector | array of character vectors | string

You can specify the *groups* argument as a character vector, as an array of character vectors, or as a string. If you specify multiple *groups*, for example, `'Debug' 'MemOpt'`, the function relates the *groups* to the *options* in order of appearance. For example, the *options* argument `{'-Zi -Wall' '-O3'}` is an array of character vectors with two elements. The first element is in the `'Debug'` group and the second element is in the `'MemOpt'` group.

Note The template makefile-based build process considers only compiler options in the `'OPTS'`, `'OPT_OPTS'`, and `'OPTIMIZATION_FLAGS'` groups when generating the makefile.

Example: `{'Debug' 'MemOpt'}`

See Also

`addDefines` | `addLinkFlags` | `getCompileFlags`

Topics

“Customize Post-Code-Generation Build Processing”

Introduced in R2006a

addDefines

Add preprocessor macro definitions to model build information

Syntax

```
addDefines(buildinfo,macrodefs,groups)
```

Description

`addDefines(buildinfo,macrodefs,groups)` specifies the preprocessor macro definitions to add to the build information.

The function requires the *buildinfo* and *macrodefs* arguments. You can use an optional *groups* argument to group your options.

The code generator stores the definitions in a build information object. The function adds definitions to the object based on the order in which you specify them.

Examples

Add Macro Definitions to OPTS Group

Add the macro definition `-DPRODUCTION` to the build information `myModelBuildInfo` and place the definition in the group `OPTS`.

```
myModelBuildInfo = RTW.BuildInfo;  
addDefines(myModelBuildInfo, '-DPRODUCTION', 'OPTS');
```

Add Macro Definitions to OPT_OPTS Group

Add the macro definitions `-DPROTO` and `-DDEBUG` to the build information `myModelBuildInfo` and place the definitions in the group `OPT_OPTS`.

```
myModelBuildInfo = RTW.BuildInfo;  
addDefines(myModelBuildInfo, ...  
    '-DPROTO -DDEBUG', 'OPT_OPTS');
```

Add Macro Definitions to Build Information

For a non-makefile build environment, add the macro definitions `-DPROTO`, `-DDEBUG`, and `-DPRODUCTION` to the build information `myModelBuildInfo`. Place the definitions `-DPROTO` and `-DDEBUG` in the group `Debug` and the definition `-DPRODUCTION` in the group `Release`.

```
myModelBuildInfo = RTW.BuildInfo;  
addDefines(myModelBuildInfo, ...
```

```
{'-DPROTO -DDEBUG' '-DPRODUCTION'}, ...
{'Debug' 'Release'});
```

Input Arguments

buildinfo — Name of build information object returned by RTW.BuildInfo object

macrodefs — List of macro definitions to add to build information
character vector | array of character vectors | string

You can specify the *macrodefs* argument as a character vector, as an array of character vectors, or as a string. You can specify the *macrodefs* argument as multiple definitions within a single character vector, for example `'-DRT -DDEBUG'`. If you specify the *macrodefs* argument as multiple character vectors, for example `'-DPROTO -DDEBUG'` and `'-DPRODUCTION'`, the *macrodefs* argument is added to the build information as an array of character vectors.

Example: `{'-DPROTO -DDEBUG' '-DPRODUCTION'}`

groups — Optional group name for the added compiler options
character vector | array of character vectors | string

You can specify the *groups* argument as a character vector, as an array of character vectors, or as a string. If you specify multiple *groups*, for example `'Debug' 'Release'`, the function relates the *groups* to the *macrodefs* in order of appearance. For example, the *macrodefs* argument `{'-DPROTO -DDEBUG' '-DPRODUCTION'}` is an array of character vectors with two elements. The first element is in the `'Debug'` group and the second element is in the `'Release'` group.

Note The template makefile-based build process considers only macro definitions in the `'OPTS'`, `'OPT_OPTS'`, `'OPTIMIZATION_FLAGS'`, and `'Custom'` groups when generating the makefile.

Example: `{'Debug' 'Release'}`

See Also

[addCompileFlags](#) | [addLinkFlags](#) | [getDefines](#)

Topics

“Customize Post-Code-Generation Build Processing”

Introduced in R2006a

addIncludeFiles

Add include files to model build information

Syntax

```
addIncludeFiles(buildinfo,filenames,paths,groups)
```

Description

`addIncludeFiles(buildinfo,filenames,paths,groups)` specifies included files and paths to add to the build information.

The function requires the *buildinfo* and *filenames* arguments. You can use an optional *paths* argument to specify the included file paths and use an optional *groups* argument to group your options.

The code generator stores the included file and path options in a build information object. The function adds options to the object based on the order in which you specify them.

The function does not add the file paths to the compiler search path.

Examples

Add Included File to SysFiles Group

Add the include file `mytypes.h` to the build information `myModelBuildInfo` and place the file in the group `SysFiles`.

```
myModelBuildInfo = RTW.BuildInfo;  
addIncludeFiles(myModelBuildInfo, ...  
    'mytypes.h', '/proj/src', 'SysFiles');
```

Add Included Files to AppFiles Group

Add the include files `etc.h` and `etc_private.h` to the build information `myModelBuildInfo`, and place the files in the group `AppFiles`.

```
myModelBuildInfo = RTW.BuildInfo;  
addIncludeFiles(myModelBuildInfo, ...  
    {'etc.h' 'etc_private.h'}, ...  
    '/proj/src', 'AppFiles');
```

Add Included Files to SysFiles and AppFiles Groups

Add the include files `etc.h`, `etc_private.h`, and `mytypes.h` to the build information `myModelBuildInfo`. Group the files `etc.h` and `etc_private.h` with the character vector `AppFiles` and the file `mytypes.h` with the character vector `SysFiles`.

```
myModelBuildInfo = RTW.BuildInfo;
addIncludeFiles(myModelBuildInfo, ...
{'etc.h' 'etc_private.h' 'mytypes.h'}, ...
 '/proj/src', ...
 {'AppFiles' 'AppFiles' 'SysFiles'});
```

Add Included Files with Wildcard to HFiles Group

Add the include files (.h files identified with a wildcard character) in a specified folder to the build information myModelBuildInfo, and place the files in the group HFiles.

```
myModelBuildInfo = RTW.BuildInfo;
addIncludeFiles(myModelBuildInfo, ...
 '*.h', '/proj/src', 'HFiles');
```

Input Arguments

buildinfo — Name of build information object returned by RTW.BuildInfo

object

filenames — List of included files to add to build information

character vector | array of character vectors | string

You can specify the *filenames* argument as a character vector, as an array of character vectors, or as a string. If you specify the *filenames* argument as multiple character vectors, for example, 'etc.h' 'etc_private.h', the *filenames* argument is added to the build information as an array of character vectors.

If the dot delimiter (.) is present, the file name text can include wildcard characters. Examples are '*.*', '*.h', and '*.h*'.

The function removes duplicate included file entries with an exact match of a path and file name to a previously defined entry in the build information object.

Example: '*.h'

paths — List of included file paths to add to build information

character vector | array of character vectors | string

You can specify the *paths* argument as a character vector, as an array of character vectors, or as a string. If you specify a single path as a character vector, the function uses that path for all files. If you specify the *paths* argument as multiple character vectors, for example, '/proj/src' and '/proj/inc', the *paths* argument is added to the build information as an array of character vectors.

Example: '/proj/src'

groups — Optional group name for the added included files

character vector | array of character vectors | string

You can specify the *groups* argument as a character vector, as an array of character vectors, or as a string. If you specify multiple *groups*, for example, 'AppFiles' 'AppFiles' 'SysFiles', the function relates the *groups* to the *filenames* in order of appearance. For example, the *filenames* argument 'etc.h' 'etc_private.h' 'mytypes.h' is an array of character vectors with three

elements. The first element is in the 'AppFiles' group, the second element is in the 'AppFiles' group, and the third element is in the 'SysFiles' group.

Example: 'AppFiles' 'AppFiles' 'SysFiles'

See Also

`addIncludePaths` | `addSourceFiles` | `addSourcePaths` | `findIncludeFiles` | `getIncludeFiles` | `updateFilePathsAndExtensions` | `updateFileSeparator`

Topics

“Customize Post-Code-Generation Build Processing”

Introduced in R2006a

addIncludePaths

Add include paths to model build information

Syntax

```
addIncludePaths(buildinfo,paths,groups)
```

Description

`addIncludePaths(buildinfo,paths,groups)` specifies included file paths to add to the build information.

The function requires the *buildinfo* and *paths* arguments. You can use an optional *groups* argument to group your options.

The code generator stores the included file path options in a build information object. The function adds options to the object based on the order in which you specify them.

The function adds the file paths to the compiler search path.

The code generator does not check whether a specified path is valid.

Examples

Add Include File Path to Build Information

Add the include path `/etcproj/etc/etc_build` to the build information `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addIncludePaths(myModelBuildInfo,...
    '/etcproj/etc/etc_build');
```

Add Include File Paths to a Group

Add the include paths `/etcproj/etclib` and `/etcproj/etc/etc_build` to the build information `myModelBuildInfo` and place the files in the group `etc`.

```
myModelBuildInfo = RTW.BuildInfo;
addIncludePaths(myModelBuildInfo,...
    {'/etcproj/etclib' '/etcproj/etc/etc_build'},'etc');
```

Add Include File Paths to Groups

Add the include paths `/etcproj/etclib`, `/etcproj/etc/etc_build`, and `/common/lib` to the build information `myModelBuildInfo`. Group the paths `/etc/proj/etclib` and `/etcproj/etc/etc_build` with the character vector `etc` and the path `/common/lib` with the character vector `shared`.

```
myModelBuildInfo = RTW.BuildInfo;  
addIncludePaths(myModelBuildInfo,...  
    {'/etc/proj/etclib' '/etcproj/etc/etc_build'...  
    '/common/lib'}, {'etc' 'etc' 'shared'});
```

Input Arguments

buildinfo — Name of build information object returned by `RTW.BuildInfo`
object

paths — List of included file paths to add to build information
character vector | array of character vectors | string

You can specify the *paths* argument as a character vector, as an array of character vectors, or as a string. If you specify a single path as a character vector, the function uses that path for all files. If you specify the *paths* argument as multiple character vectors, for example, `'/proj/src'` and `'/proj/inc'`, the *paths* argument is added to the build information as an array of character vectors.

The function removes duplicate include file path entries with an exact match of a path and file name to a previously defined entry in the build information object.

Example: `'/proj/src'`

groups — Optional group name for the added included files
character vector | array of character vectors | string

You can specify the *groups* argument as a character vector, as an array of character vectors, or as a string. If you specify multiple *groups*, for example, `'etc' 'etc' 'shared'`, the function relates the *groups* to the *paths* in order of appearance. For example, the *paths* argument `'/etc/proj/etclib' '/etcproj/etc/etc_build' '/common/lib'` is an array of character vectors with three elements. The first element is in the `'etc'` group, the second element is in the `'etc'` group, and the third element is in the `'shared'` group.

Example: `'etc' 'etc' 'shared'`

See Also

`addIncludeFiles` | `addSourceFiles` | `addSourcePaths` | `getIncludePaths` | `updateFilePathsAndExtensions` | `updateFileSeparator`

Topics

“Customize Post-Code-Generation Build Processing”

Introduced in R2006a

addLinkFlags

Add link options to model build information

Syntax

```
addLinkFlags(buildinfo,options,groups)
```

Description

`addLinkFlags(buildinfo,options,groups)` specifies the linker options to add to the build information.

The function requires the *buildinfo* and *options* arguments. You can use an optional *groups* argument to group your options.

The code generator stores the linker options in a build information object. The function adds options to the object based on the order in which you specify them.

Examples

Add Linker Flags to OPTS Group

Add the linker -T option to the build information `myModelBuildInfo` and place the option in the group OPTS.

```
myModelBuildInfo = RTW.BuildInfo;  
addLinkFlags(myModelBuildInfo, '-T', 'OPTS');
```

Add Linker Flags to OPT_OPTS Group

Add the linker options -MD and -Gy to the build information `myModelBuildInfo` and place the options in the group OPT_OPTS.

```
myModelBuildInfo = RTW.BuildInfo;  
addLinkFlags(myModelBuildInfo, '-MD -Gy', 'OPT_OPTS');
```

Add Linker Flags to Build Information

For a non-makefile build environment, add the linker options -MD, -Gy, and -T to the build information `myModelBuildInfo`. Place the options -MD and -Gy in the group Debug and the option -T in the groupTemp.

```
myModelBuildInfo = RTW.BuildInfo;  
addLinkFlags(myModelBuildInfo, {'-MD -Gy' '-T'}, ...  
    {'Debug' 'Temp'});
```

Input Arguments

buildinfo — Name of build information object returned by `RTW.BuildInfo` object

options — List of linker options to add to build information

character vector | array of character vectors | string

You can specify the *options* argument as a character vector, as an array of character vectors, or as a string. You can specify the *options* argument as multiple compiler flags within a single character vector, for example `'-MD -Gy'`. If you specify the *options* argument as multiple character vectors, for example, `'-MD -Gy'` and `'-T'`, the *options* argument is added to the build information as an array of character vectors.

Example: `{'-MD -Gy' '-T'}`

groups — Optional group name for the added linker options

character vector | array of character vectors | string

You can specify the *groups* argument as a character vector, as an array of character vectors, or as a string. If you specify multiple *groups*, for example, `'Debug' 'Temp'`, the function relates the *groups* to the *options* in order of appearance. For example, the *options* argument `{'-MD -Gy' '-T'}` is an array of character vectors with two elements. The first element is in the `'Debug'` group and the second element is in the `Temp` group.

Example: `{'Debug' 'Temp'}`

See Also

`addCompileFlags` | `addDefines` | `getLinkFlags`

Topics

“Customize Post-Code-Generation Build Processing”

Introduced in R2006a

addLinkObjects

Add link objects to model build information

Syntax

```
addLinkObjects(buildinfo, linkobjs, paths, priority, precompiled, linkonly, groups)
```

Description

`addLinkObjects(buildinfo, linkobjs, paths, priority, precompiled, linkonly, groups)` specifies included files and paths to add to the build information.

The function requires the *buildinfo*, *linkobjs*, and *paths* arguments. You can optionally select *priority* for link objects, select whether the objects are *precompiled*, select whether the objects are *linkonly* objects, and apply a *groups* argument to group your options.

The code generator stores the included link object and path options in a build information object. The function adds options to the object based on the order in which you specify them.

Examples

Add Link Objects to Build Information

Add the linkable objects `libobj1` and `libobj2` to the build information `myModelBuildInfo`. Mark both objects as link-only. Since individual priorities are not specified, the function adds the objects to the vector in the order specified.

```
myModelBuildInfo = RTW.BuildInfo;
addLinkObjects(myModelBuildInfo, {'libobj1' 'libobj2'}, ...
    {'/proj/lib/lib1' '/proj/lib/lib2'}, 1000, ...
    false, true);
```

Add Prioritized Link-Only Link Objects to Build Information

Add the linkable objects `libobj1` and `libobj2` to the build information `myModelBuildInfo`. Set the priorities of the objects to 26 and 10, respectively. Because `libobj2` is assigned the lower numeric priority value and has the higher priority, the function orders the objects such that `libobj2` precedes `libobj1` in the vector.

```
myModelBuildInfo = RTW.BuildInfo;
addLinkObjects(myModelBuildInfo, {'libobj1' 'libobj2'}, ...
    {'/proj/lib/lib1' '/proj/lib/lib2'}, [26 10]);
```

Add Precompiled Link Objects to MyTest Group

Add the linkable objects `libobj1` and `libobj2` to the build information `myModelBuildInfo`. Set the priorities of the objects to 26 and 10, respectively. Mark both objects as precompiled. Group them under the name `MyTest`.

```
myModelBuildInfo = RTW.BuildInfo;
addLinkObjects(myModelBuildInfo,{'libobj1' 'libobj2'}, ...
    {'/proj/lib/lib1' '/proj/lib/lib2'},[26 10], ...
    true,false,'MyTest');
```

Input Arguments

buildinfo — Name of build information object returned by `RTW.BuildInfo`
object

linkobjs — List of linkable object files to add to build information
character vector | array of character vectors | string

You can specify the *linkobjs* argument as a character vector, as an array of character vectors, or as a string. If you specify the *linkobjs* argument as multiple character vectors, for example, `'libobj1' 'libobj2'`, the *linkobjs* argument is added to the build information as an array of character vectors.

The function removes duplicate linkable object entries with an exact match of a path and file name to a previously defined entry in the build information object.

Example: `'libobj1'`

paths — List of included file paths to add to build information
character vector | array of character vectors | string

You can specify the *paths* argument as a character vector, as an array of character vectors, or as a string. If you specify a single path as a character vector, the function uses that path for all files. If you specify the *paths* argument as multiple character vectors, for example, `'/proj/lib/lib1' and '/proj/lib/lib2'`, the *paths* argument is added to the build information as an array of character vectors. The number of elements in *paths* must match the number of elements in the *linkobjs* argument.

Example: `'/proj/lib/lib1'`

priority — List of priority values for link objects to add to build information
1000 (default) | numeric value | array of numeric values

A numeric value or an array of numeric values that indicates the relative priority of each specified link object. Lower values have higher priority.

Example: `1000`

precompiled — List of precompiled indicators for link objects to add to build information
false (default) | true | array of logical values

A logical value or an array of logical values that indicates whether each specified link object is precompiled. The logical value `true` indicates precompiled.

Example: `false`

Linkonly — List of link-only indicators for link objects to add to build information`false` (default) | `true`

A logical value or an array of logical values that indicates whether each specified link object is link-only (not precompiled). The logical value `true` indicates link-only. If *linkonly* is `true`, the value of the *precompiled* argument is ignored.

Example: `false`

groups — Optional group name for the added link object files`character vector` | `array of character vectors` | `string`

You can specify the *groups* argument as a character vector, as an array of character vectors, or as a string. If you specify multiple *groups*, for example, `'MyTest1' 'MyTest2'`, the function relates the *groups* to the *linkobjs* in order of appearance. For example, the *linkobjs* argument `'libobj1' 'libobj2'` is an array of character vectors with two elements. The first element is in the `'MyTest1'` group, and the second element is in the `'MyTest2'` group.

Example: `'MyTest1' 'MyTest2'`

See Also

`addIncludePaths` | `addSourceFiles` | `addSourcePaths` | `findIncludeFiles` | `getIncludeFiles` | `updateFilePathsAndExtensions` | `updateFileSeparator`

Topics

“Customize Post-Code-Generation Build Processing”

Introduced in R2006a

addNonBuildFiles

Add nonbuild-related files to model build information

Syntax

```
addNonBuildFiles(buildinfo, filenames, paths, groups)
```

Description

`addNonBuildFiles(buildinfo, filenames, paths, groups)` specifies nonbuild-related files and paths to add to the build information.

The function requires the *buildinfo* and *filenames* arguments. You can use an optional *paths* argument to specify the included file paths and use an optional *groups* argument to group your options.

The code generator stores the nonbuild-related file and path options in a build information object. The function adds options to the object based on the order in which you specify them.

Examples

Add Nonbuild File to DocFiles Group

Add the nonbuild-related file `readme.txt` to the build information `myModelBuildInfo`, and place the file in the group `DocFiles`.

```
myModelBuildInfo = RTW.BuildInfo;  
addNonBuildFiles(myModelBuildInfo, ...  
    'readme.txt', '/proj/docs', 'DocFiles');
```

Add Nonbuild Files to DLLFiles Group

Add the nonbuild-related files `myutility1.dll` and `myutility2.dll` to the build information `myModelBuildInfo`, and place the files in the group `DLLFiles`.

```
myModelBuildInfo = RTW.BuildInfo;  
addNonBuildFiles(myModelBuildInfo, ...  
    {'myutility1.dll' 'myutility2.dll'}, ...  
    '/proj/dlls', 'DLLFiles');
```

Add Nonbuild Files with Wildcard to DLLFiles Group

Add nonbuild-related files (`.dll` files identified with a wildcard character) in a specified folder to the build information `myModelBuildInfo`, and place the files in the group `DLLFiles`.

```
myModelBuildInfo = RTW.BuildInfo;
addNonBuildFiles(myModelBuildInfo, ...
    '*.dll', '/proj/dlls', 'DLLFiles');
```

Input Arguments

buildinfo — Name of build information object returned by `RTW.BuildInfo` object

filenames — List of nonbuild-related files to add to build information
character vector | array of character vectors | string

You can specify the *filenames* argument as a character vector, as an array of character vectors, or as a string. If you specify the *filenames* argument as multiple character vectors, for example, 'etc.dll' 'etc_private.dll', the *filenames* argument is added to the build information as an array of character vectors.

If the dot delimiter (.) is present, the file name text can include wildcard characters. Examples are '*.*', '*.dll', and '*.d*'.

The function removes duplicate nonbuild-related file entries with an exact match of a path and file name to a previously defined entry in the build information object.

Example: '*.dll'

paths — List of nonbuild-related file paths to add to build information
character vector | array of character vectors | string

You can specify the *paths* argument as a character vector, as an array of character vectors, or as a string. If you specify a single path as a character vector, the function uses that path for all files. If you specify the *paths* argument as multiple character vectors, for example, '/proj/dll' and '/proj/docs', the *paths* argument is added to the build information as an array of character vectors.

Example: '/proj/dll'

groups — Optional group name for the added nonbuild-related files
character vector | array of character vectors | string

You can specify the *groups* argument as a character vector, as an array of character vectors, or as a string. If you specify multiple *groups*, for example, 'DLLFiles' 'DLLFiles' 'DocFiles', the function relates the *groups* to the *filenames* in order of appearance. For example, the *filenames* argument 'myutility1.dll' 'myutility2.dll' 'readme.txt' is an array of character vectors with three elements. The first element is in the 'DLLFiles' group, the second element is in the 'DLLFiles' group, and the third element is in the 'DocFiles' group.

Example: 'DLLFiles' 'DLLFiles' 'DocFiles'

See Also

getNonBuildFiles

Topics

“Customize Post-Code-Generation Build Processing”

Introduced in R2008a

addSourceFiles

Add source files to model build information

Syntax

```
addSourceFiles(buildinfo,filenames,paths,groups)
```

Description

`addSourceFiles(buildinfo,filenames,paths,groups)` specifies source files and paths to add to the build information.

The function requires the *buildinfo* and *filenames* arguments. You can use an optional *groups* argument to group your options.

The code generator stores the source file and path options in a build information object. The function adds options to the object based on the order in which you specify them.

Examples

Add Source File to Drivers Group

Add the source file `driver.c` to the build information `myModelBuildInfo` and place the file in the group `Drivers`.

```
myModelBuildInfo = RTW.BuildInfo;  
addSourceFiles(myModelBuildInfo,'driver.c', ...  
    '/proj/src', 'Drivers');
```

Add Source Files to a Group

Add the source files `test1.c` and `test2.c` to the build information `myModelBuildInfo` and place the files in the group `Tests`.

```
myModelBuildInfo = RTW.BuildInfo;  
addSourceFiles(myModelBuildInfo, ...  
    {'test1.c' 'test2.c'}, ...  
    '/proj/src', 'Tests');
```

Add Source Files to Groups

Add the source files `test1.c`, `test2.c`, and `driver.c` to the build information `myModelBuildInfo`. Group the files `test1.c` and `test2.c` with the character vector `Tests`. Group the file `driver.c` with the character vector `Drivers`.

```
myModelBuildInfo = RTW.BuildInfo;  
addSourceFiles(myModelBuildInfo, ...
```

```
{'test1.c' 'test2.c' 'driver.c'}, ...
'/proj/src', ...
{'Tests' 'Tests' 'Drivers'}});
```

Add Source Files with Wildcard to CFiles Group

Add the .c files in a specified folder to the build information myModelBuildInfo and place the files in the group CFiles.

```
myModelBuildInfo = RTW.BuildInfo;
addIncludeFiles(myModelBuildInfo, ...
    '*.c', '/proj/src', 'CFiles');
```

Input Arguments

buildinfo — Name of build information object returned by RTW.BuildInfo
object

filenames — List of source files to add to build information
character vector | array of character vectors | string

You can specify the *filenames* argument as a character vector, as an array of character vectors, or as a string. If you specify the *filenames* argument as multiple character vectors, for example, 'etc.c' 'etc_private.c', the *filenames* argument is added to the build information as an array of character vectors.

If the dot delimiter (.) is present, the file name text can include wildcard characters. Examples are '*.*', '*.c', and '*.c*'.

The function removes duplicate included file entries with an exact match of a path and file name to a previously defined entry in the build information object.

Example: '*.c'

paths — List of source file paths to add to build information
character vector | array of character vectors | string

You can specify the *paths* argument as a character vector, as an array of character vectors, or as a string. If you specify a single path as a character vector, the function uses that path for all files. If you specify the *paths* argument as multiple character vectors, for example, '/proj/src' and '/proj/inc', the *paths* argument is added to the build information as an array of character vectors.

Example: '/proj/src'

groups — Optional group name for the added source files
character vector | array of character vectors | string

You can specify the *groups* argument as a character vector, as an array of character vectors, or as a string. If you specify multiple *groups*, for example, 'Tests' 'Tests' 'Drivers', the function relates the *groups* to the *filenames* in order of appearance. For example, the *filenames* argument 'test1.c' 'test2.c' 'driver.c' is an array of character vectors with three elements. The first element is in the 'Tests' group, and the second element is in the 'Tests' group, and the third element is in the 'Drivers' group.

Example: 'Tests' 'Tests' 'Drivers'

See Also

[addIncludeFiles](#) | [addIncludePaths](#) | [addSourcePaths](#) | [getSourceFiles](#) | [updateFilePathsAndExtensions](#) | [updateFileSeparator](#)

Topics

“Customize Post-Code-Generation Build Processing”

Introduced in R2006a

addSourcePaths

Add source paths to model build information

Syntax

```
addSourcePaths(buildinfo, paths, groups)
```

Description

`addSourcePaths(buildinfo, paths, groups)` specifies source file paths to add to the build information.

The function requires the *buildinfo* and *paths* arguments. You can use an optional *groups* argument to group your options.

The code generator stores the source file path options in a build information object. The function adds options to the object based on the order in which you specify them.

The code generator does not check whether a specified path is valid.

Note If you want to add source files and the corresponding file paths to model build information, use the `addSourceFiles` function. Do not use `addSourcePaths`.

Examples

Add Source File Path to Build Information

Add the source path `/etcproj/etc/etc_build` to the build information `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;  
addSourcePaths(myModelBuildInfo, ...  
    '/etcproj/etc/etc_build');
```

Add Source File Paths to a Group

Add the source paths `/etcproj/etclib` and `/etcproj/etc/etc_build` to the build information `myModelBuildInfo` and place the files in the group `etc`.

```
myModelBuildInfo = RTW.BuildInfo;  
addSourcePaths(myModelBuildInfo, ...  
    {'/etcproj/etclib' '/etcproj/etc/etc_build'}, 'etc');
```

Add Source File Paths to Groups

Add the source paths `/etcproj/etclib`, `/etcproj/etc/etc_build`, and `/common/lib` to the build information `myModelBuildInfo`. Group the paths `/etc/proj/etclib` and `/etcproj/etc/`

`etc_build` with the character vector `etc` and the path `/common/lib` with the character vector `shared`.

```
myModelBuildInfo = RTW.BuildInfo;
addSourcePaths(myModelBuildInfo,...
    {'/etc/proj/etclib' '/etcproj/etc/etc_build'...
    '/common/lib'}, {'etc' 'etc' 'shared'});
```

Input Arguments

buildinfo — Name of build information object returned by `RTW.BuildInfo`
object

paths — List of source file paths to add to build information
character vector | array of character vectors | string

You can specify the *paths* argument as a character vector, as an array of character vectors, or as a string. If you specify a single path as a character vector, the function uses that path for all files. If you specify the *paths* argument as multiple character vectors, for example, `'/proj/src'` and `'/proj/inc'`, the *paths* argument is added to the build information as an array of character vectors.

The function removes duplicate source file path entries with an exact match of a path and file name to a previously defined entry in the build information object.

Example: `'/proj/src'`

groups — Optional group name for the added source files
character vector | array of character vectors | string

You can specify the *groups* argument as a character vector, as an array of character vectors, or as a string. If you specify multiple *groups*, for example, `'etc' 'etc' 'shared'`, the function relates the *groups* to the *paths* in order of appearance. For example, the *paths* argument `'/etc/proj/etclib' '/etcproj/etc/etc_build' '/common/lib'` is an array of character vectors with three elements. The first element is in the `'etc'` group, the second element is in the `'etc'` group, and the third element is in the `'shared'` group.

Example: `'etc' 'etc' 'shared'`

See Also

`addIncludeFiles` | `addIncludePaths` | `addSourceFiles` | `getSourcePaths` | `updateFilePathsAndExtensions` | `updateFileSeparator`

Topics

“Customize Post-Code-Generation Build Processing”

Introduced in R2006a

addTMFTokens

Add template makefile (TMF) tokens to model build information

Syntax

```
addTMFTokens(buildinfo, tokennames, tokenvalues, groups)
```

Description

`addTMFTokens(buildinfo, tokennames, tokenvalues, groups)` specifies TMF tokens and values to add to the build information.

To provide build-time information to help customize makefile generation, call the `addTMFTokens` function inside a post-code-generation command. The tokens specified in the `addTMFTokens` function call must be handled in the template makefile (TMF) for the target selected for your model. For example, you can call `addTMFTokens` in a post-code-generation command to add a TMF token named `|>CUSTOM_OUTNAME<|` with a token value that specifies an output file name for the build. To achieve the result you want, the TMF must apply an action with the value of `|>CUSTOM_OUTNAME<|`. (See “Examples” on page 3-0 .)

The `addTMFTokens` function adds specified TMF token names and values to the model build information. The code generator stores the TMF tokens in a vector. The function adds the tokens to the end of the vector in the order that you specify them.

The function requires the *buildinfo*, *tokennames*, and *tokenvalues* arguments. You can use an optional *groups* argument to group your options. You can specify *groups* as a character vector or as an array of character vectors.

Examples

Add TMF Tokens to Build Information

Inside a post-code-generation command, add the TMF token `|>CUSTOM_OUTNAME<|` and its value to build information `myModelBuildInfo`, and place the token in the group `LINK_INFO`.

```
myModelBuildInfo = RTW.BuildInfo;
addTMFTokens(myModelBuildInfo, ...
    '|>CUSTOM_OUTNAME<|', 'foo.exe', 'LINK_INFO');
```

Apply Build Information as Tokens in TMF Build

In the TMF for the target selected for your model, this code uses the token value to achieve the result that you want:

```
CUSTOM_OUTNAME = |>CUSTOM_OUTNAME<|
...
```

```
target:  
$(LD) -o $(CUSTOM_OUTNAME) ...
```

Input Arguments

buildinfo — Name of build information object returned by `RTW.BuildInfo` object

tokennames — Specifies names of TMF tokens to add to the build information
character vector | array of character vectors | string

You can specify the *tokennames* argument as a character vector, as an array of character vectors, or as a string. If you specify the *tokennames* argument as multiple character vectors, for example, '|>CUSTOM_OUTNAME<|' '|>COMPUTER<|', the *tokennames* argument is added to the build information as an array of character vectors.

Example: '|>CUSTOM_OUTNAME<|' '|>COMPUTER<|'

tokenvalues — Specifies TMF token values (for the added tokens) to add to the build information

character vector | array of character vectors | string

You can specify the *tokenvalues* argument as a character vector, as an array of character vectors, or as a string. If you specify the *tokenvalues* argument as multiple character vectors, for example, '|>CUSTOM_OUTNAME<|' 'PCWIN64', the *tokennames* argument is added to the build information as an array of character vectors.

Example: 'foo.exe' 'PCWIN64'

groups — Optional group name for the added TMF tokens

character vector | array of character vectors | string

You can specify the *groups* argument as a character vector, as an array of character vectors, or as a string. If you specify multiple *groups*, for example, 'LINK_INFO' 'COMPUTER_INFO', the function relates the *groups* to the *tokennames* in order of appearance. For example, the *tokennames* argument '|>CUSTOM_OUTNAME<|' '|>COMPUTER<|' is an array of character vectors with two elements. The first element is in the 'LINK_INFO' group, and the second element is in the 'COMPUTER_INFO' group.

Example: 'LINK_INFO' 'COMPUTER_INFO'

See Also

Topics

“Customize Post-Code-Generation Build Processing”

Introduced in R2009b

buildStandaloneCoderAssumptions

Create application to check code generator assumptions

Syntax

```
buildStandaloneCoderAssumptions(buildFolder)
```

Description

`buildStandaloneCoderAssumptions(buildFolder)` creates an application for your target hardware to check code generator assumptions. The application checks that code generator assumptions based on model parameter settings or build configuration settings are correct with reference to the target hardware.

The function creates the target application in the `buildFolder\coderassumptions\standalone` subfolder.

Examples

Create Application to Check Code Generator Assumptions

For an example that shows how to create an application to check code generator assumptions, see “Check Code Generator Assumptions for Development Computer” (Embedded Coder).

Input Arguments

`buildFolder` — Build folder

character vector | string scalar

Path to the build folder that contains the generated code.

See Also

Topics

“Check Code Generation Assumptions” (Embedded Coder)

Introduced in R2018b

coder.buildstatus.close

Close Build Status window

Syntax

```
coder.buildstatus.close()  
coder.buildstatus.close(model)  
coder.buildstatus.close(subsystem)
```

Description

`coder.buildstatus.close()` closes Build Status windows.

The Build Status window supports parallel builds of referenced model hierarchies. Do not use the Build Status window for serial builds.

`coder.buildstatus.close(model)` closes the Build Status window for `model`.

`coder.buildstatus.close(subsystem)` closes the Build Status window for `subsystem`.

Examples

Close Build Status Windows

Close Build Status windows that are open.

```
coder.buildstatus.close()
```

Close Build Status Window for a Model

After generating code for `rtwdemo_counter`, close the Build Status window for the model.

```
coder.buildstatus.close('rtwdemo_counter')
```

Close Build Status Window for a Subsystem

Close the Build Status window for the subsystem 'Amplifier' in model 'rtwdemo_counter'.

```
coder.buildstatus.close('rtwdemo_counter/Amplifier')
```

Input Arguments

model — Model name

character vector

Model name specified as a character vector

Example: 'rtwdemo_counter'

Data Types: char

subsystem – Subsystem name

character vector

Subsystem name specified as a character vector

Example: 'rtwdemo_counter/Amplifier'

Data Types: char

See Also

coder.buildstatus.open | coder.report.close | rtwbuild | slbuild

Topics

“Monitor Parallel Building of Referenced Models”

Introduced in R2018a

coder.buildstatus.open

Open Build Status window

Syntax

```
coder.buildstatus.open(model)
coder.buildstatus.open(model,systemTarget)
```

Description

`coder.buildstatus.open(model)` opens the Build Status window for `model`.

The Build Status window supports parallel builds of referenced model hierarchies. Do not use the Build Status window for serial builds.

If the current working folder is the model build folder and the folder contains information from a previous parallel build, opening the Build Status window displays the previous build information. When you start a model parallel build, the current build information replaces the previous build information in the window.

`coder.buildstatus.open(model,systemTarget)` opens the Build Status window for `model` and displays the `model` tab. The available tabs are **Simulation Targets** and **Code Generation Targets**

Examples

Open Build Status Window for a Model

After generating code for model 'rtwdemo_parabuild_a_1', open the Build Status window for the model.

```
coder.buildstatus.open('rtwdemo_parabuild_a_1')
```

Open Build Status Window with Simulation Targets

Open the Build Status window for the model 'rtwdemo_parabuild_a_1' and display the **Simulation Targets** tab.

```
coder.buildstatus.open('rtwdemo_parabuild_a_1','sim')
```

Input Arguments

model — Model name

character vector | string scalar

Model name specified as a character vector or a string scalar

Example: 'rtwdemo_parabuild_a_1'

Data Types: char | string

systemTarget – System targets name

sim | rtw

System targets tab name specified as a character vector or string scalar, `sim` for **Simulation Targets** and `rtw` for **Code Generation Targets**. When build information is available for a system target from a previous build, the *systemTarget* argument directs the **Build Status** dialog box to display the tab for the system target. If this optional argument is omitted, when build information is available, dialog opens both the **Simulation Targets** tab and **Code Generation Targets** tab. If build information for a target is not available, the dialog does not open the corresponding system targets tab.

Example: 'rtw'

Data Types: char | string

See Also

`coder.buildstatus.close` | `coder.report.open` | `rtwbuild` | `slbuild`

Topics

“Monitor Parallel Building of Referenced Models”

Introduced in R2018a

coder.codedescriptor.CodeDescriptor class

Package: coder.codedescriptor

Return information about generated code

Description

Create a `coder.codedescriptor.CodeDescriptor` object to access all the methods defined within the code descriptor API. The `coder.codedescriptor.CodeDescriptor` object describes the data interfaces, function interfaces, global data stores, local and global parameters in the generated code.

Creation

`codeDescObj = coder.getCodeDescriptor(model)` creates a `coder.codedescriptor.CodeDescriptor` object for the specified model.

`codeDescObj = coder.getCodeDescriptor(folder)` creates a `coder.codedescriptor.CodeDescriptor` object for the model in the build folder specified in `folder`.

Properties

modelName — Name of the model

character vector (default)

Name of the model for which the code descriptor object is invoked.

Example: 'rtwdemo_comments'

BuildFolder — Build folder

character vector (default)

Path of the build folder where the model is built.

Example: 'C:\Users\Desktop\Work\rtwdemo_comments_ert_rtw'

Methods

Public Methods

<code>getAllDataInterfaceTypes</code>	Return data interface types
<code>getAllFunctionInterfaceTypes</code>	Return function interface types
<code>getArrayLayout</code>	Return array layout of the generated code
<code>getDataInterfaceTypes</code>	Return data interface types in the generated code
<code>getDataInterfaces</code>	Return information of the specified data interface
<code>getFunctionInterfaceTypes</code>	Return function interface types in the generated code
<code>getFunctionInterfaces</code>	Return information of the specified function interface

`getReferencedModelCodeDescriptor` Return `coder.codedescriptor.CodeDescriptor` object for the specified referenced model

`getReferencedModelNames` Return names of the referenced models

Examples

Create `coder.codedescriptor.CodeDescriptor` Object

- 1 Build the model.

```
rtwbuild('rtwdemo_comments')
```

- 2 Create a `coder.codedescriptor.CodeDescriptor` object for the required model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_comments')
```

```
    ModelName: 'rtwdemo_comments'
```

```
    BuildDir: 'C:\Users\Desktop\Work\rtwdemo_comments_ert_rtw'
```

- 3 Return a list of all available function interface types.

```
allFunctionInterfaceTypes = getAllFunctionInterfaceTypes(codeDescObj)
```

```
    {'Initialize'}
```

```
    {'Output' }
```

```
    {'Update' }
```

```
    {'Terminate' }
```

See Also

`getCodeDescriptor` | `coder.descriptor.DataInterface` |
`coder.descriptor.FunctionInterface`

Topics

“Get Code Description of Generated Code”

Introduced in R2018a

getAllDataInterfaceTypes

Class: `coder.codedescriptor.CodeDescriptor`

Package: `coder.codedescriptor`

Return data interface types

Syntax

```
allDataInterfaceTypes = getAllDataInterfaceTypes(codeDescObj)
```

Description

`allDataInterfaceTypes = getAllDataInterfaceTypes(codeDescObj)` returns a list of the data interface types. This list is not specific to any model.

Input Arguments

codeDescObj — Code Descriptor object

`coder.codedescriptor.CodeDescriptor` object

`coder.codedescriptor.CodeDescriptor` object for which you want to retrieve the information about generated code.

Output Arguments

allDataInterfaceTypes — Data interface types available

cell array of character vectors

A list of available data interface types.

Examples

Create a `coder.codedescriptor.CodeDescriptor` object for the required model that is built, then list the available data interface types.

- 1 Build the model.

```
rtwbuild('rtwdemo_comments')
```

- 2 Create a `coder.codedescriptor.CodeDescriptor` object for the required model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_comments')
```

- 3 Return a list of available data interface types.

```
allDataInterfaceTypes = getAllDataInterfaceTypes(codeDescObj)
```

`allDataInterfaceTypes` has these values:

```
{'Inports'           }  
{'Outports'          }  
{'Parameters'       }
```

```
{'GlobalDataStores'      }  
{'SharedLocalDataStores'}  
{'ExternalParameterObjects'  }  
{'ModelParameters'        }  
{'InternalData'           }
```

In a model, there can be `ExternalParameterObjects` and/or `LocalParameters`. The data interface type `Parameters` consist of a consolidated list of both types of parameters.

See Also

`coder.codedescriptor.CodeDescriptor` | `coder.descriptor.DataInterface` |
`getDataInterfaceTypes` | `getDataInterfaces` | `getCodeDescriptor`

Topics

“Get Code Description of Generated Code”

Introduced in R2018a

getAllFunctionInterfaceTypes

Class: `coder.codedescriptor.CodeDescriptor`

Package: `coder.codedescriptor`

Return function interface types

Syntax

```
allFunctionInterfaceTypes = getAllFunctionInterfaceTypes(codeDescObj)
```

Description

`allFunctionInterfaceTypes = getAllFunctionInterfaceTypes(codeDescObj)` returns a list of the function interface types. The returned list is not specific to any model.

Input Arguments

codeDescObj — Code Descriptor object

`coder.codedescriptor.CodeDescriptor` object

`coder.codedescriptor.CodeDescriptor` object for which you want to retrieve the information about generated code.

Output Arguments

allFunctionInterfaceTypes — Function interface types available

cell array of character vectors

A list of the available function interface types.

Examples

Create a `coder.codedescriptor.CodeDescriptor` object for the required model which is built, then list the available function interface types.

- 1 Build the model.

```
rtwbuild('rtwdemo_comments')
```

- 2 Create a `coder.codedescriptor.CodeDescriptor` object for the required model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_comments')
```

- 3 Return a list of available function interface types.

```
allFunctionInterfaceTypes = getAllFunctionInterfaceTypes(codeDescObj)
```

`allFunctionInterfaceTypes` has these values:

```
{'Allocation'}  
{'Initialize'}  
{'Output' }
```

```
{'Update'   }  
{'Terminate'}  
}
```

See Also

`coder.codedescriptor.CodeDescriptor` | `getAllFunctionInterfaceTypes` |
`getAllFunctionInterfaces` | `getCodeDescriptor` | `coder.descriptor.FunctionInterface`

Topics

“Get Code Description of Generated Code”

“Configure Code Generation for Model Entry-Point Functions”

Introduced in R2018a

getArrayLayout

Class: `coder.codedescriptor.CodeDescriptor`

Package: `coder.codedescriptor`

Return array layout of the generated code

Syntax

```
arrayLayout = getArrayLayout(codeDescObj)
```

Description

`arrayLayout = getArrayLayout(codeDescObj)` returns the array layout of the model for which the code is generated.

Input Arguments

codeDescObj — Code Descriptor object

`coder.codedescriptor.CodeDescriptor` object

`coder.codedescriptor.CodeDescriptor` object for which you want to retrieve the information about generated code.

Output Arguments

arrayLayout — Array layout of the generated code

character vectors

Array layout specified for the model by using the model configuration parameter **Array layout** on page 10-37.

Examples

Create a `coder.codedescriptor.CodeDescriptor` object for the model that is built, then list the array layout of the generated code.

- 1 Open a model.

```
rtwdemo_comments
```

- 2 Specify the model configuration parameter **Array layout** as Row-major. Alternatively, in the command window, use these commands:

```
set_param('rtwdemo_comments', 'ArrayLayout', 'Row-major');
```

- 3 Build the model.

```
rtwbuild('rtwdemo_comments')
```

- 4 Create a `coder.codedescriptor.CodeDescriptor` object for the model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_comments')
```

- 5** Return the array layout of the generated code.

```
arrayLayout = getArrayLayout(codeDescObj)
```

arrayLayout has this value:

```
'Row-major'
```

See Also

`coder.codedescriptor.CodeDescriptor` | `getCodeDescriptor`

Topics

“Get Code Description of Generated Code”

“Code Generation of Matrices and Arrays”

Introduced in R2018b

getDataInterfaces

Class: `coder.codedescriptor.CodeDescriptor`

Package: `coder.codedescriptor`

Return information of the specified data interface

Syntax

```
dataInterface = getDataInterfaces(codeDescObj, dataInterfaceName)
```

Description

`dataInterface = getDataInterfaces(codeDescObj, dataInterfaceName)` returns the type of data, SID, graphical name, timing, implementation, and variant information on the data interface that `dataInterfaceName` specifies.

Input Arguments

codeDescObj — Code Descriptor object

`coder.codedescriptor.CodeDescriptor` object

`coder.codedescriptor.CodeDescriptor` object for which you want to retrieve the information about generated code.

dataInterfaceName — Name of data interface

Inports | Outports | Parameters | GlobalDataStores | SharedLocalDataStores | ExternalParameterObjects | ModelParameters | InternalData

`dataInterfaceName` specifies the name of a data interface. To get a list of all the data interfaces in the generated code, call `getDataInterfaceTypes()`.

Data Types: `string`

Output Arguments

dataInterface — `coder.descriptor.DataInterface` object with properties of specified data interface type

`coder.descriptor.DataInterface` object | array of `coder.descriptor.DataInterface` objects

The `coder.descriptor.DataInterface` object describes information about the specified data interface such as type of data, SID, graphical name, timing, implementation, and variant information.

Examples

- 1 Build the model.

```
rtwbuild('rtwdemo_comments')
```
- 2 Create a `coder.codedescriptor.CodeDescriptor` object for the required model.

- `codeDescObj = coder.getCodeDescriptor('rtwdemo_comments')`
- 3** Return a list of all data interface types in the generated code.

```
dataInterfaceTypes = getDataInterfaceTypes(codeDescObj)
```

`dataInterfaceTypes` has these values:

```
{'Inports'      }
{'Outports'     }
{'Parameters'   }
{'ExternalParameterObjects'}
```

- 4** Return properties of Inport blocks in the generated code.

```
dataInterface = getDataInterfaces(codeDescObj, 'Inports')
```

`dataInterface` is an array of `coder.descriptor.DataInterface` objects. Obtain the details of the first Inport block of the model by accessing the first location in the array.

```
dataInterface(1)
```

The first `coder.descriptor.DataInterface` object with properties is returned.

```
Type: [1x1 coder.descriptor.types.Double]
SID: 'rtwdemo_comments:1'
GraphicalName: 'In1'
VariantInfo: [0x0 coder.descriptor.VariantInfo]
Implementation: [1x1 coder.descriptor.StructExpression]
Timing: [1x1 coder.descriptor.TimingInterface]
```

See Also

`coder.codedescriptor.CodeDescriptor` | `getAllDataInterfaceTypes` | `getDataInterfaceTypes` | `coder.descriptor.DataInterface`

Topics

“Get Code Description of Generated Code”

Introduced in R2018a

getDataInterfaceTypes

Class: `coder.codedescriptor.CodeDescriptor`

Package: `coder.codedescriptor`

Return data interface types in the generated code

Syntax

```
dataInterfaceTypes = getDataInterfaceTypes(codeDescObj)
```

Description

`dataInterfaceTypes = getDataInterfaceTypes(codeDescObj)` returns a list of the data interface types in the generated code. To get a list of the available data interfaces, call `getAllDataInterfaceTypes()`.

Input Arguments

codeDescObj — Code Descriptor object

`coder.codedescriptor.CodeDescriptor` object

`coder.codedescriptor.CodeDescriptor` object for which you want to retrieve the information about generated code.

Output Arguments

dataInterfaceTypes — Data interface types in the generated code

cell array of character vectors

A list of the data interface types in the generated code.

Examples

1 Build the model.

```
rtwbuild('rtwdemo_counter')
```

2 Create a `coder.codedescriptor.CodeDescriptor` object for the required model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_counter')
```

3 Return a list of data interface types in the generated code.

```
dataInterfaceTypes = getDataInterfaceTypes(codeDescObj)
```

`dataInterfaceTypes` has these values for model `rtwdemo_counter`:

```
{'Inports'      }  
{'Outports'    }  
{'InternalData' }
```

See Also

`coder.codedescriptor.CodeDescriptor` | `getAllDataInterfaceTypes` | `getDataInterfaces` | `getCodeDescriptor`

Topics

“Get Code Description of Generated Code”

Introduced in R2018a

getFunctionInterfaces

Class: `coder.codedescriptor.CodeDescriptor`

Package: `coder.codedescriptor`

Return information of the specified function interface

Syntax

```
functionInterface = getFunctionInterfaces(codeDescObj, functionInterfaceName)
```

Description

`functionInterface = getFunctionInterfaces(codeDescObj, functionInterfaceName)` returns the function prototype, input arguments, return arguments, variant conditions, and timing information of the function interface that `functionInterfaceName` specifies.

Input Arguments

codeDescObj — Code Descriptor object

`coder.codedescriptor.CodeDescriptor` object

`coder.codedescriptor.CodeDescriptor` object for which you want to retrieve the information about generated code.

functionInterfaceName — Name of function interface

`Allocation` | `Initialize` | `Output` | `Update` | `Terminate`

`functionInterfaceName` specifies the name of a function interface. A list of all the function interfaces in the generated code is returned by `getFunctionInterfaceTypes()`.

Data Types: `string`

Output Arguments

functionInterface — `coder.descriptor.FunctionInterface` object with properties of specified function interface type

`coder.descriptor.FunctionInterface` object | array of `coder.descriptor.FunctionInterface` objects

The `coder.descriptor.FunctionInterface` object describes information about the specified function interface such as function prototype, input arguments, return arguments, variant conditions, and timing information.

Examples

- 1 Build the model.

```
rtwbuild('rtwdemo_comments')
```
- 2 Create a `coder.codedescriptor.CodeDescriptor` object for the required model.

- ```
codeDescObj = coder.getCodeDescriptor('rtwdemo_comments')
```
- 3** Return a list of all function interface types in the generated code.

```
functionInterfaceTypes = getFunctionInterfaceTypes(codeDescObj)
```

These are the function interface types in the generated code of model `rtwdemo_comments`:

```
{'Initialize'}
{'Output' }
```

- 4** Return properties of a specified function interface in the generated code.

```
functionInterface = getFunctionInterfaces(codeDescObj, 'Output')
```

`functionInterface` is a `coder.descriptor.FunctionInterface` object.

```
Prototype: [1x1 coder.descriptor.types.Prototype]
ActualReturn: [0x0 coder.descriptor.DataInterface]
VariantInfo: [0x0 coder.descriptor.VariantInfo]
Timing: [1x1 coder.descriptor.TimingInterface]
ActualArgs: [1x0 coder.descriptor.DataInterface List]
```

## See Also

`coder.codedescriptor.CodeDescriptor` | `getAllFunctionInterfaceTypes` | `getFunctionInterfaceTypes` | `coder.descriptor.FunctionInterface`

## Topics

“Get Code Description of Generated Code”

**Introduced in R2018a**

## getFunctionInterfaceTypes

**Class:** `coder.codedescriptor.CodeDescriptor`

**Package:** `coder.codedescriptor`

Return function interface types in the generated code

### Syntax

```
functionInterfaceTypes = getFunctionInterfaceTypes(codeDescObj)
```

### Description

`functionInterfaceTypes = getFunctionInterfaceTypes(codeDescObj)` returns a list of the function interface types in the generated code. To get a list of the available function interfaces, call `getAllFunctionInterfaceTypes()`.

### Input Arguments

**codeDescObj** — Code Descriptor object

`coder.codedescriptor.CodeDescriptor` object

`coder.codedescriptor.CodeDescriptor` object for which you want to retrieve the information about generated code.

### Output Arguments

**functionInterfaceTypes** — Function interface types in the generated code

cell array of character vectors

A list of the data interface types in the generated code.

### Examples

- 1 Build the model.

```
rtwbuild('rtwdemo_counter')
```

- 2 Create a `coder.codedescriptor.CodeDescriptor` object for the required model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_counter')
```

- 3 Return a list of function interface types in the generated code.

```
functionInterfaceTypes = getFunctionInterfaceTypes(codeDescObj)
```

`functionInterfaceTypes` has these values for model `rtwdemo_counter`:

```
{'Initialize'}
{'Output' }
```

## **See Also**

`coder.codedescriptor.CodeDescriptor` | `getAllFunctionInterfaceTypes` |  
`getFunctionInterfaces` | `getCodeDescriptor`

## **Topics**

“Get Code Description of Generated Code”

**Introduced in R2018a**

## getReferenceModelCodeDescriptor

**Class:** `coder.codedescriptor.CodeDescriptor`

**Package:** `coder.codedescriptor`

Return `coder.codedescriptor.CodeDescriptor` object for the specified referenced model

### Syntax

```
refCodeDescriptor = getReferenceModelCodeDescriptor(codeDescObj,
refModelName)
```

### Description

`refCodeDescriptor = getReferenceModelCodeDescriptor(codeDescObj, refModelName)` returns the `coder.codedescriptor.CodeDescriptor` object for the referenced model specified in `refModelName`.

### Input Arguments

**codeDescObj — Code Descriptor object**

`coder.codedescriptor.CodeDescriptor` object

`coder.codedescriptor.CodeDescriptor` object for which you want to retrieve the information about generated code.

**refModelName — Name of referenced model**

string

`refModelName` can take any name from the list of referenced models returned by `getReferenceModelNames()`.

### Output Arguments

**refCodeDescriptor — `coder.codedescriptor.CodeDescriptor` object for the specified referenced model**

`coder.codedescriptor.CodeDescriptor` object

`coder.codedescriptor.CodeDescriptor` object for the specified referenced model.

### Examples

- 1 Build the model.  

```
rtwbuild('rtwdemo_async_mdleftop')
```
- 2 Create a `coder.codedescriptor.CodeDescriptor` object for the required model.  

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_async_mdleftop')
```
- 3 Return a list of referenced models.  

```
refModels = getReferenceModelNames(codeDescObj)
```

`refModels` contains the list of referenced models for `rtwdemo_async_mdltreftop`.

```
{'rtwdemo_async_mdltreftop'}
```

Obtain the `coder.CodeDescriptor` object for any of the referenced models.

```
refCodeDescriptorObj = getReferencedModelCodeDescriptor(codeDescObj, 'rtwdemo_async_mdltreftop')
```

`refCodeDescriptorObj` is the `coder.CodeDescriptor` object for `rtwdemo_async_mdltreftop` model.

```
ModelName: 'rtwdemo_async_mdltreftop'
BuildDir: 'C:\Users\Desktop\Work\slprj\tornado\rtwdemo_async_mdltreftop'
```

## See Also

`coder.CodeDescriptor` | `getReferencedModelNames` | `getCodeDescriptor`

## Topics

“Get Code Description of Generated Code”

**Introduced in R2018a**

## getReferenceModelNames

**Class:** `coder.codedescriptor.CodeDescriptor`

**Package:** `coder.codedescriptor`

Return names of the referenced models

### Syntax

```
refModels = getReferencedModelNames(codeDescObj)
```

### Description

`refModels = getReferencedModelNames(codeDescObj)` returns a list of referenced models for a `coder.codedescriptor.CodeDescriptor` object.

### Input Arguments

**codeDescObj** — Code Descriptor object

`coder.codedescriptor.CodeDescriptor` object

`coder.codedescriptor.CodeDescriptor` object for which you want to retrieve the information about generated code.

### Output Arguments

**refModels** — Names of referenced models

cell array of character vectors

A list of referenced models.

### Examples

1 Build the model.

```
rtwbuild('rtwdemo_async_mdltreftop')
```

2 Create a `coder.codedescriptor.CodeDescriptor` object for the required model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_async_mdltreftop')
```

3 Return a list of referenced models.

```
refModels = getReferencedModelNames(codeDescObj)
```

`refModels` has the list of referenced models.

```
{'rtwdemo_async_mdltreftop'}
```

### See Also

`coder.codedescriptor.CodeDescriptor` | `getReferenceModelCodeDescriptor`

**Topics**

“Get Code Description of Generated Code”

**Introduced in R2018a**

## isLookupTableDataInterface

Determine whether object is a `coder.descriptor.LookupTableDataInterface` object

### Syntax

```
lookupTableDataInterface = isLookupTableDataInterface(parameterObj)
```

### Description

`lookupTableDataInterface = isLookupTableDataInterface(parameterObj)` returns a logical value indicating whether the object is a `coder.descriptor.LookupTableDataInterface` object.

### Input Arguments

**parameterObj** — `coder.descriptor.LookupTableDataInterface` object

`coder.descriptor.LookupTableDataInterface` object

`coder.descriptor.LookupTableDataInterface` object that represents a Lookup Table block in the model.

Data Types: `string`

### Output Arguments

**lookupTableDataInterface** — logical value

1 | 0

Logical value indicating whether the object is a `coder.descriptor.LookupTableDataInterface`.

Data Types: `logical`

### Examples

**Determine if the object is a `coder.descriptor.LookupTableDataInterface` object**

- 1 Build the model.  

```
rtwbuild('rtwdemo_asap2')
```
- 2 Create a `coder.codeDescriptor.CodeDescriptor` object for the model.  

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_asap2')
```
- 3 Return properties of the Lookup Table parameters in the model.  

```
params = getDataInterfaces(codeDescObj, 'Parameters')
```

The `params` variable is an array of `coder.descriptor.DataInterface`, `coder.descriptor.LookupTableDataInterface`, and `coder.descriptor.BreakpointDataInterface` objects.

- 4 Obtain the details of the model Lookup Table block by accessing the sixth location in the array.

```
parameterObj = params(6)
```

- 5 Determine if the object stored in `parameterObj` variable is a `coder.descriptor.LookupTableDataInterface` object.

```
lookupTableDataInterface = isLookupTableDataInterface(parameterObj)
```

```
lookupTableDataInterface =
```

```
 logical
```

```
 1
```

The code generator returns a logical value of 1 indicating if `parameterObj` is a `coder.descriptor.LookupTableDataInterface` object. Otherwise, the code generator returns a logical value of 0.

## See Also

`coder.descriptor.LookupTableDataInterface` | `isBreakpointDataInterface`

**Introduced in R2020a**

## isBreakpointDataInterface

Determine whether object is a `coder.descriptor.BreakpointDataInterface` object

### Syntax

```
breakpointTableDataInterface = isBreakpointDataInterface(parameterObj)
```

### Description

`breakpointTableDataInterface = isBreakpointDataInterface(parameterObj)` returns a logical value indicating whether the object is a `coder.descriptor.BreakpointDataInterface` object or not.

### Input Arguments

**parameterObj** — `coder.descriptor.BreakpointDataInterface` object

`coder.descriptor.BreakpointDataInterface`

`coder.descriptor.BreakpointDataInterface` object that represents a breakpoint set in the model.

Data Types: `string`

### Output Arguments

**breakpointTableDataInterface** — logical value

1 | 0

Logical value indicating whether the object is a `coder.descriptor.BreakpointDataInterface`.

Data Types: `logical`

### Examples

**Determine if the object is a `coder.descriptor.BreakpointDataInterface` object**

1 Build the model.

```
rtwbuild('rtwdemo_asap2')
```

2 Create a `coder.codeDescriptor.CodeDescriptor` object for the model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_asap2')
```

3 Return properties of the breakpoint set data in the model.

```
params = getDataInterfaces(codeDescObj, 'Parameters')
```

The `params` variable is an array of `coder.descriptor.DataInterface`, `coder.descriptor.LookupTableDataInterface`, and `coder.descriptor.BreakpointDataInterface` objects.

- 4 Obtain the details of the breakpoint set attached to the model Lookup Table block by accessing the first location in the array.

```
parameterObj = params(6).Breakpoints(1)
```

- 5 Determine if the object stored in `parameterObj` variable is a `coder.descriptor.BreakpointDataInterface` object.

```
breakpointDataInterface = isBreakpointDataInterface(parameterObj)
```

```
lookupTableDataInterface =
```

```
 logical
```

```
 1
```

The code generator returns a logical value of 1 indicating if `parameterObj` is a `coder.descriptor.BreakpointDataInterface` object. Otherwise, the code generator returns a logical value of 0.

## See Also

`isLookupTableDataInterface` | `coder.descriptor.BreakpointDataInterface`

**Introduced in R2020a**

## getAllParameters

Return all associated `coder.descriptor.LookupTableDataInterface` and `coder.descriptor.BreakpointDataInterface` objects

### Syntax

```
dataInterface = getAllParameters(parameterObj)
```

### Description

`dataInterface = getAllParameters(parameterObj)` returns all associated `coder.descriptor.LookupTableDataInterface` and `coder.descriptor.BreakpointDataInterface` objects.

### Input Arguments

**parameterObj** — `coder.descriptor.LookupTableDataInterface` object

`coder.descriptor.LookupTableDataInterface` object

The `coder.descriptor.LookupTableDataInterface` object that represents a Lookup Table block in the model.

Data Types: `string`

### Output Arguments

**dataInterface** — array of `coder.descriptor.LookupTableDataInterface` and/or `coder.descriptor.BreakpointDataInterface` objects

`coder.descriptor.LookupTableDataInterface` object | array of `coder.descriptor.LookupTableDataInterface` and/or `coder.descriptor.BreakpointDataInterface` objects

The `coder.descriptor.LookupTableDataInterface` object represents a Lookup Table block in the model. The `coder.descriptor.BreakpointDataInterface` object represents the breakpoint set data associated with the Lookup Table block.

### Examples

**Return all associated `coder.descriptor.LookupTableDataInterface` and `coder.descriptor.BreakpointDataInterface` objects**

- 1 Build the model.  

```
rtwbuild('rtwdemo_asap2')
```
- 2 Create a `coder.codeDescriptor.CodeDescriptor` object for the required model.  

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_asap2')
```
- 3 Return properties of the Lookup Table parameters in the model.

```
params = getDataInterfaces(codeDescObj, 'Parameters')
```

The params variable is an array of `coder.descriptor.DataInterface`, `coder.descriptor.LookupTableDataInterface`, and `coder.descriptor.BreakpointDataInterface` objects.

- 4 Obtain the details of the model Lookup Table block by accessing the sixth location in the array.

```
parameterObj = params(6)
```

- 5 Retrieve all the associated `coder.descriptor.LookupTableDataInterface` and `coder.descriptor.BreakpointDataInterface` objects by using the `parameterObj`.

```
dataInterface = getAllParameters(parameterObj)
```

The code generator returns an array of `coder.descriptor.LookupTableDataInterface` and `coder.descriptor.BreakpointDataInterface` objects.

1×3 heterogeneous `DataInterface` (`LookupTableDataInterface`, `BreakpointDataInterface`) array with properties:

```
Type
SID
GraphicalName
VariantInfo
Implementation
Timing
Unit
Range
```

## See Also

`coder.descriptor.LookupTableDataInterface` |  
`coder.descriptor.BreakpointDataInterface` | `coder.descriptor.DataInterface`

**Introduced in R2020a**

## coder.descriptor.DataInterface class

**Package:** coder.descriptor

Return information about different types of data interfaces

### Description

The `coder.descriptor.DataInterface` object describes various properties for a specified data interface in the generated code. The different types of data interfaces are:

- Root-level inports and outports: An interface between the model and external models or systems, for exchanging data.
- Parameters: Local and global parameters that describe the data for the block, lookup table, and the associated breakpoint set data.
- Data Stores: A repository to store global and shared data that can be written and read.
- Internal data: Internal data structures including DWork vectors, block I/O, and zero-crossings.

If your model has a Stateflow chart that uses machine-parented data, the code generator generates a DWork structure in the generated code. When you use the `getDataInterfaces` method, you cannot access these structures as `InternalData`.

### Creation

`dataInterface = getDataInterfaces(codeDescObj, dataInterfaceName)` creates a `coder.descriptor.DataInterface` object. The `codeDescObj` object is the `coder.codedescriptor.CodeDescriptor` object created for the model by using the `getCodeDescriptor` function.

### Input Arguments

#### **dataInterfaceName — Name of data interface**

Inports | Outports | Parameters | GlobalDataStores | SharedLocalDataStores | ExternalParameterObjects | ModelParameters | InternalData

Name of the specified data interface.

Example: 'Inports'

Data Types: string

### Properties

#### **Type — Type of data**

`coder.descriptor.types` object

The data type associated with the data such as `integer`, `double`, `matrix`, and its properties.

#### **SID — Simulink identifier**

character vector

The Simulink identifier (SID) is a unique number within the model that Simulink assigns to the block.

### **GraphicalName — Name of graphical entity**

character vector

The name of the associated graphical entity.

### **VariantInfo — Variant conditions in the model**

`coder.descriptor.VariantInfo` object

The variant conditions in the model that interact with the data interface.

### **Implementation — Description of implementation of data**

`coder.descriptor.DataImplementation` object

The description of how the data in the generated code is implemented. This property describes characteristics such as data type and size. In addition, it describes how the data is accessed or declared in the code. The property describes if the data is declared as a variable or structure member.

### **Timing — Data access rate in run-time environment**

`coder.descriptor.TimingInterface` object

The rate at which data is accessed in a run-time environment.

### **Unit — Physical unit as attribute on signals**

character vector

Specified physical units as attributes on signals at the boundaries of model components.

### **Range — Range of output value**

`coder.descriptor.Range` object

The range of valid values for the block output signals.

## **Limitations**

A bitfield data structure is generated if you select these configuration parameters:

- **Pack Boolean data into bitfields**
- **Use bitset for storing state configuration**
- **Use bitset for storing Boolean data**

If the `coder.descriptor.DataInterface` represents a bitfield data structure, the `Implementation` property of the `coder.descriptor.DataInterface` object is empty.

## **Examples**

### **Get All Data Interface Types**

- 1 Build the model.
 

```
rtwbuild('rtwdemo_comments')
```

- 2 Create a `coder.codeDescriptor.CodeDescriptor` object for the required model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_comments')
```

- 3 Return a list of all data interface types in the generated code.

```
dataInterfaceTypes = getDataInterfaceTypes(codeDescObj)
```

```
 {'Inports' }
 {'Outports' }
 {'Parameters' }
 {'ExternalParameterObjects'}
 {'InternalData' }
```

- 4 Return properties of a specified data interface in the generated code.

```
dataInterface = getDataInterfaces(codeDescObj, 'Inports')
```

`dataInterface` is an array of `coder.descriptor.DataInterface` objects. Obtain the details of the first Inport block of the model by accessing the first location in the array.

```
dataInterface(1)
```

The first `coder.descriptor.DataInterface` object with properties is returned.

```
 Type: [1x1 coder.descriptor.types.Double]
 SID: 'rtwdemo_comments:1'
 GraphicalName: 'In1'
 VariantInfo: [0x0 coder.descriptor.VariantInfo]
 Implementation: [1x1 coder.descriptor.StructExpression]
 Timing: [1x1 coder.descriptor.TimingInterface]
```

## See Also

`coder.codeDescriptor.CodeDescriptor` | `getAllDataInterfaceTypes` | `getDataInterfaceTypes` | `getDataInterfaces`

## Topics

“Get Code Description of Generated Code”

**Introduced in R2018a**

# coder.descriptor.FunctionInterface class

**Package:** coder.descriptor

Return information about entry-point functions

## Description

The function interfaces are the entry-point functions in the generated code. The `coder.descriptor.FunctionInterface` object describes various properties for a specified function interface. The different types of function interfaces are:

- **Allocation:** Contains memory allocation code based on the target of the model. See `model_initialize`.
- **Initialize:** Contains initialization code for the model and is called once at the start of your application code. See `model_initialize`.
- **Output:** Contains the output code for the blocks in the model. See `model_step`.
- **Update:** Contains the update code for the blocks in the model. See `model_step`.
- **Terminate:** Contains the termination code for the model and is called as part of a system shutdown. See `model_terminate`.

## Creation

`functionInterface = getFunctionInterfaces(codeDescObj, functionInterfaceName)` creates a `coder.descriptor.FunctionInterface` object. `codeDescObj` is the `coder.codedescriptor.CodeDescriptor` object created for the model by using the `getCodeDescriptor` function.

### Input Arguments

**functionInterfaceName — Name of function interface**

Allocation | Initialize | Output | Update | Terminate

Name of the specified function interface

Example: 'Output'

Data Types: string

### Properties

**Prototype — Description of function prototype**

`coder.descriptor.types` object

The description of the function prototype including function return value, name, arguments, header, and source files.

**ActualReturn — Return arguments from the function**

`coder.descriptor.DataInterface` object

The data that the function returns as a return argument. When there is no data returned from the function, this field is empty.

**VariantInfo — Variant conditions in the model**

`coder.descriptor.VariantInfo` object

The variant conditions in the model that interact with the function interface.

**Timing — Function access rate in run-time environment**

`coder.descriptor.TimingInterface` object

The rate at which function is accessed in a run-time environment.

**ActualArgs — Input arguments to the function**

`coder.descriptor.DataInterfaceList` object

The data passed as arguments to the function. When there is no data passed as an argument to the function, this field is empty.

## Examples

**Get All Function Interface Types**

- 1 Build the model.

```
rtwbuild('rtwdemo_comments')
```

- 2 Create a `coder.codedescriptor.CodeDescriptor` object for the required model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_comments')
```

- 3 Return a list of all function interface types in the generated code.

```
functionInterfaceTypes = getFunctionInterfaceTypes(codeDescObj)
```

```
 {'Initialize'}
 {'Output' }
```

- 4 Return properties of a specified function interface in the generated code.

```
functionInterface = getFunctionInterfaces(codeDescObj, 'Output')
```

```
 Prototype: [1x1 coder.descriptor.types.Prototype]
 ActualReturn: [0x0 coder.descriptor.DataInterface]
 VariantInfo: [0x0 coder.descriptor.VariantInfo]
 Timing: [1x1 coder.descriptor.TimingInterface]
 ActualArgs: [1x0 coder.descriptor.DataInterface List]
```

**See Also**

`coder.codedescriptor.CodeDescriptor` | `getAllFunctionInterfaceTypes` | `getFunctionInterfaceTypes` | `getFunctionInterfaces`

**Topics**

“Get Code Description of Generated Code”

**Introduced in R2018a**

# coder.descriptor.LookupTableDataInterface class

**Package:** coder.descriptor

**Superclasses:** coder.descriptor.DataInterface

Return information about Lookup Table blocks that have tunable parameters

## Description

The `coder.descriptor.LookupTableDataInterface` object describes various properties for these Lookup Table blocks that have tunable parameters in the generated code:

- 1-D Lookup Table
- 2-D Lookup Table
- n-D Lookup Table
- Interpolation Using Prelookup
- Direct Lookup Table (n-D)
- Sine
- Cosine

## Creation

`params = getDataInterfaces(codeDescObj, dataInterfaceName)` creates a `coder.descriptor.LookupTableDataInterface` object if the model has a Lookup Table block with tunable parameters. The `codeDescObj` object is the `coder.codedescriptor.CodeDescriptor` object created for the model by using the `getCodeDescriptor` function.

The `coder.descriptor.LookupTableDataInterface` object is created only if all parameters in the lookup table data and breakpoint set data are tunable. For example, if you have a lookup table with tunable table data, and three breakpoints, two of which have tunable data and one that does not, there is no `coder.descriptor.LookupTableDataInterface` created.

## Input Arguments

**dataInterfaceName** — Name of data interface

Parameters

Specify the Parameters data interface type.

Example: Parameters

## Properties

**Type** — Type of data

`coder.descriptor.types` object

The data type associated with the data such as `integer`, `double`, `matrix`, and its properties.

**SID — Simulink identifier**

character vector

The Simulink identifier (SID) is a unique number within the model that Simulink assigns to the block.

**GraphicalName — Name of the tunable parameter for the table data**

character vector

The name of the associated tunable parameter for the table data.

**VariantInfo — Variant conditions in the model**

coder.descriptor.VariantInfo object

The variant conditions in the model that interact with the data interface.

**Implementation — Description of implementation of data**

coder.descriptor.DataImplementation object

Description of how the data in the generated code is implemented. This property describes characteristics such as data type and size. It also describes how the data is accessed or declared in the code. The property describes if the data is declared as a variable or structure member.

**Timing — Data access rate in run-time environment**

coder.descriptor.TimingInterface object

The rate at which data is accessed in a run-time environment.

**Unit — Physical unit as attribute on signals**

character vector

Specified physical units as attributes on signals at the boundaries of model components.

**Range — Range of output value**

coder.descriptor.Range object

The range of valid values for the block output signals.

**SupportTunableSize — Tunability of table size**

1 (default) | 0

Value that represents whether table is enabled for tunability of the effective size of the table, represented as 0 or 1.

Data Types: logical

**BreakpointSpecification — Source of breakpoint set information in Simulink.LookupTable**

'Explicit values' (default) | 'Reference' | 'Even spacing'

Source of the breakpoint set information, specified as 'Explicit values' (default), 'Even spacing', or 'Reference'. See the **Breakpoints > Specification** parameter.

Data Types: char

**Output — Data interface for the output of Lookup Table block**

coder.descriptor.DataInterface object

Return value of the lookup table operation.

### Breakpoints — Breakpoint set data

`coder.descriptor.BreakpointDataInterface` object

Vector of `coder.descriptor.BreakpointDataInterface` objects that are used in the Lookup Table block. These objects contain the breakpoint set data.

## Methods

### Public Methods

|                                         |                                                                                                                                                |
|-----------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| <code>isLookupTableDataInterface</code> | Determine whether object is a <code>coder.descriptor.LookupTableDataInterface</code> object                                                    |
| <code>getAllParameters</code>           | Return all associated <code>coder.descriptor.LookupTableDataInterface</code> and <code>coder.descriptor.BreakpointDataInterface</code> objects |

## Examples

### Get Lookup Table block information

- 1 Build the model.

```
rtwbuild('rtwdemo_asap2')
```

- 2 Create a `coder.codeDescriptor.CodeDescriptor` object for the model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_asap2')
```

- 3 Return properties of the Lookup Table parameters in the model.

```
params = getDataInterfaces(codeDescObj, 'Parameters')
```

The `params` variable is an array of `coder.descriptor.DataInterface` and `coder.descriptor.LookupTableDataInterface` objects. The model `rtwdemo_asap2` contains three Lookup Table blocks. Only two of them have tunable breakpoint set data. The code generator creates only two corresponding `coder.descriptor.LookupTableDataInterface` objects.

Obtain the details of the `Standard_Axis` block by accessing the sixth location in the array.

```
params(6)
```

The `coder.descriptor.LookupTableDataInterface` object with properties is returned.

```

Type: [1x1 coder.descriptor.types.Type]
SID: 'rtwdemo_asap2:14'
GraphicalName: 'tabledata'
VariantInfo: [1x0 coder.descriptor.VariantInfo]
Implementation: [1x1 coder.descriptor.DataImplementation]
Timing: [1x0 coder.descriptor.TimingInterface]
Unit: ''
Range: [1x0 coder.descriptor.Range]
SupportTunableSize: 0
BreakpointSpecification: 'Explicit values'
Output: [1x1 coder.descriptor.DataInterface]
Breakpoints: [1x2 coder.descriptor.BreakpointDataInterface Sequence]

```

**See Also**

`coder.codedescriptor.CodeDescriptor` | `coder.descriptor.DataInterface` |  
`coder.descriptor.BreakpointDataInterface`

**Introduced in R2020a**

## coder.descriptor.BreakpointDataInterface class

**Package:** coder.descriptor

**Superclasses:** coder.descriptor.DataInterface

Return information about tunable breakpoint set data for a lookup table that has tunable parameters

### Description

The `coder.descriptor.BreakpointDataInterface` object describes various properties for breakpoint set data for these Lookup Table blocks that have tunable parameters in the generated code:

- 1-D Lookup Table
- 2-D Lookup Table
- n-D Lookup Table
- Interpolation Using Prelookup
- Direct Lookup Table (n-D)
- Sine
- Cosine

### Creation

`params = getDataInterfaces(codeDescObj, dataInterfaceName)` creates a `coder.descriptor.BreakpointDataInterface` object for each dimension in the lookup table. The `codeDescObj` object is the `coder.codedescriptor.CodeDescriptor` object created for the model by using the `getCodeDescriptor` function.

The `coder.descriptor.BreakpointDataInterface` object is created only if all parameters in the lookup table data and breakpoint set data are tunable. For example, if you have a lookup table with tunable table data and three breakpoints, two of which have tunable data and one that does not, there is no `coder.descriptor.BreakpointDataInterface` created.

### Input Arguments

**dataInterfaceName** — Name of data interface

Parameters

Specify the Parameters data interface type.

Example: Parameters

### Properties

**Type** — Type of data

`coder.descriptor.types` object

The data type associated with the data such as `integer`, `double`, `matrix`, and its properties.

**SID — Simulink identifier**

character vector

The Simulink identifier (SID) is a unique number within the model that Simulink assigns to a block.

**GraphicalName — Name of the tunable parameter for the breakpoints**

character vector

The name of the associated tunable parameter for the breakpoints.

**VariantInfo — Variant conditions in the model**`coder.descriptor.VariantInfo` object

The variant conditions in the model that interact with the data interface.

**Implementation — Description of implementation of data**`coder.descriptor.DataImplementation` object

Description of how the data in the generated code is implemented. This property describes characteristics such as data type and size. It also describes how the data is accessed or declared in the code. The property describes if the data is declared as a variable or structure member.

**Timing — Data access rate in run-time environment**`coder.descriptor.TimingInterface` object

The rate at which data is accessed in a run-time environment.

**Unit — Physical unit as attribute on signals**

character vector

Specified physical units as attributes on signals at the boundaries of model components.

**Range — Range of output value**`coder.descriptor.Range` object

The range of valid values for the block output signals.

**OperatingPoint — Input value to the lookup table relative to each breakpoint**`coder.descriptor.DataInterface` object

To find the input value in the table, the operating point uses relative breakpoint set data.

**SupportTunableSize — Option to generate code that enables tunability of table size**

1 (default) | 0

Option to generate code that enables tunability of the effective size of the table, specified as 0 or 1.

Data Types: `logical`**Methods****Public Methods**

`isBreakpointDataInterface` Determine whether object is a `coder.descriptor.BreakpointDataInterface` object

## Examples

### Get breakpoint data set information

- 1 Build the model.

```
rtwbuild('rtwdemo_asap2')
```

- 2 Create a `coder.codedescriptor.CodeDescriptor` object for the model.

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_asap2')
```

- 3 Return properties of the Lookup Table parameters in the model.

```
params = getDataInterfaces(codeDescObj, 'Parameters')
```

The `params` variable is an array of `coder.descriptor.DataInterface` and `coder.descriptor.LookupTableDataInterface` objects. The model `rtwdemo_asap2` contains three Lookup Table blocks. Only two of them have tunable breakpoint set data. The code generator creates only two corresponding `coder.descriptor.LookupTableDataInterface` objects.

Obtain the details of the `Standard_Axis` block by accessing the sixth location in the array.

```
params(6)
```

The `coder.descriptor.LookupTableDataInterface` object with properties is returned.

```

Type: [1x1 coder.descriptor.types.Type]
SID: 'rtwdemo_asap2:14'
GraphicalName: 'tabledata'
VariantInfo: [1x0 coder.descriptor.VariantInfo]
Implementation: [1x1 coder.descriptor.DataImplementation]
Timing: [1x0 coder.descriptor.TimingInterface]
Unit: ''
Range: [1x0 coder.descriptor.Range]
SupportTunableSize: 0
BreakpointSpecification: 'Explicit values'
Output: [1x1 coder.descriptor.DataInterface]
Breakpoints: [1x2 coder.descriptor.BreakpointDataInterface Sequence]

```

- 4 The Breakpoints property of the `coder.descriptor.LookupTableDataInterface` object holds a vector of `coder.descriptor.BreakpointDataInterface` objects. Obtain the details of the breakpoint set attached to the model Lookup Table block by accessing the first location in the array.

```
params(6).Breakpoints(1)
```

The `coder.descriptor.BreakpointDataInterface` object with properties is returned.

```

Type: [1x1 coder.descriptor.types.Type]
SID: 'rtwdemo_asap2:14'
GraphicalName: 'tabledata'
VariantInfo: [1x0 coder.descriptor.VariantInfo]
Implementation: [1x1 coder.descriptor.DataImplementation]
Timing: [1x0 coder.descriptor.TimingInterface]
Unit: ''
Range: [1x0 coder.descriptor.Range]
OperatingPoint: [1x1 coder.descriptor.DataInterface]
SupportTunableSize: 0

```

## See Also

[coder.codedescriptor.CodeDescriptor](#) | [coder.descriptor.DataInterface](#) | [coder.descriptor.LookupTableDataInterface](#)

**Introduced in R2020a**

## **coder.report.close**

Close HTML code generation report

### **Syntax**

```
coder.report.close()
```

### **Description**

`coder.report.close()` closes the HTML code generation report.

### **Examples**

#### **Close code generation report for a model**

After opening a code generation report for `rtwdemo_counter`, close the report.

```
coder.report.close()
```

### **See Also**

`coder.report.generate` | `coder.report.open`

### **Topics**

“Reports for Code Generation”

**Introduced in R2012a**

## **coder.report.generate**

Generate HTML code generation report

### **Syntax**

```
coder.report.generate(model)
coder.report.generate(subsystem)
coder.report.generate(model,Name,Value)
```

### **Description**

`coder.report.generate(model)` generates a code generation report for the `model`. The build folder for the model must be present in the current working folder.

`coder.report.generate(subsystem)` generates the code generation report for the `subsystem`. The build folder for the subsystem must be present in the current working folder.

`coder.report.generate(model,Name,Value)` generates the code generation report using the current model configuration and additional options specified by one or more `Name,Value` pair arguments. Possible values for the `Name,Value` arguments are parameters on the **Code Generation > Report** pane. Without modifying the model configuration, using the `Name,Value` arguments you can generate a report with a different report configuration.

### **Examples**

#### **Generate Code Generation Report for Model**

Open the model `rtwdemo_counter`.

```
open rtwdemo_counter
```

Build the model. The model is configured to create and open a code generation report.

```
rtwbuild('rtwdemo_counter');
```

Close the code generation report.

```
coder.report.close;
```

Generate a code generation report.

```
coder.report.generate('rtwdemo_counter');
```

#### **Generate Code Generation Report for Subsystem**

Open the model `rtwdemo_counter`.

```
open rtwdemo_counter
```

Build the subsystem. The model is configured to create and open a code generation report.

```
rtwbuild('rtwdemo_counter/Amplifier');
```

Close the code generation report.

```
coder.report.close;
```

Generate a code generation report for the subsystem.

```
coder.report.generate('rtwdemo_counter/Amplifier');
```

### Generate Code Generation Report to Include Static Code Metrics Report

Generate a code generation report to include a static code metrics report after the build process, without modifying the model.

Open the model `rtwdemo_hyperlinks`.

```
open rtwdemo_hyperlinks
```

Build the model. The model is configured to create and open a code generation report.

```
rtwbuild('rtwdemo_hyperlinks');
```

Close the code generation report.

```
coder.report.close;
```

Generate a code generation report that includes the static code metrics report.

```
coder.report.generate('rtwdemo_hyperlinks',
'GenerateCodeMetricsReport', 'on');
```

The code generation report opens. In the left navigation pane, click **Static Code Metrics Report** to view the report.

## Input Arguments

### **model** — Model name

character vector

Model name specified as a character vector

Example: 'rtwdemo\_counter'

Data Types: char

### **subsystem** — Subsystem name

character vector

Subsystem name specified as a character vector

Example: 'rtwdemo\_counter/Amplifier'

Data Types: char

### Name-Value Pair Arguments

Specify optional comma-separated pairs of `Name`, `Value` arguments. `Name` is the argument name and `Value` is the corresponding value. `Name` must appear inside quotes. You can specify several name and value pair arguments in any order as `Name1, Value1, . . . , NameN, ValueN`.

Each `Name`, `Value` argument corresponds to a parameter on the Configuration Parameters **Code Generation > Report** pane. When the configuration parameter `GenerateReport` is on, the parameters are enabled. The `Name`, `Value` arguments are used only for generating the current report. The arguments will override, but not modify, the parameters in the model configuration. The following parameters require an Embedded Coder® license.

Example: `'GenerateWebview', 'on', 'GenerateCodeMetricsReport', 'on'` includes a model Web view and static code metrics in the code generation report.

### Navigation

#### IncludeHyperlinkInReport — Code-to-model hyperlinks

`'off' | 'on'`

Code-to-model hyperlinks, specified as `'on'` or `'off'`. Specify `'on'` to include code-to-model hyperlinks in the code generation report. The hyperlinks link code to the corresponding blocks, Stateflow® objects, and MATLAB® functions in the model diagram. For more information see “Code-to-model” (Embedded Coder).

Example: `'IncludeHyperlinkInReport', 'on'`

Data Types: char

#### GenerateTraceInfo — Model-to-code highlighting

`'off' | 'on'`

Model-to-code highlighting, specified as `'on'` or `'off'`. Specify `'on'` to include model-to-code highlighting in the code generation report. For more information see “Model-to-code” (Embedded Coder).

Example: `'GenerateTraceInfo', 'on'`

Data Types: char

#### GenerateWebview — Model Web view

`'off' | 'on'`

Model Web view, specified as `'on'` or `'off'`. Specify `'on'` to include the model Web view in the code generation report. For more information, see “Generate model Web view” (Embedded Coder).

Example: `'GenerateWebview', 'on'`

Data Types: char

### Traceability Report Contents

#### GenerateTraceReport — Summary of eliminated and virtual blocks

`'off' | 'on'`

Summary of eliminated and virtual blocks, specified as `'on'` or `'off'`. Specify `'on'` to include a summary of eliminated and virtual blocks in the code generation report. For more information, see “Eliminated / virtual blocks” (Embedded Coder).

Example: `'GenerateTraceReport','on'`

Data Types: char

### **GenerateTraceReportSl — Summary of Simulink blocks and the corresponding code location**

`'off' | 'on'`

Summary of the Simulink blocks and the corresponding code location, specified as `'on'` or `'off'`. Specify `'on'` to include a summary of the Simulink blocks and the corresponding code location in the code generation report. For more information, see “Traceable Simulink blocks” (Embedded Coder).

Example: `'GenerateTraceReportSl','on'`

Data Types: char

### **GenerateTraceReportsSf — Summary of Stateflow objects and the corresponding code location**

`'off' | 'on'`

Summary of the Stateflow objects and the corresponding code location, specified as `'on'` or `'off'`. Specify `'on'` to include a summary of Stateflow objects and the corresponding code location in the code generation report. For more information, see “Traceable Stateflow objects” (Embedded Coder).

Example: `'GenerateTraceReportsSf','on'`

Data Types: char

### **GenerateTraceReportEmL — Summary of MATLAB functions and the corresponding code location**

`'off' | 'on'`

Summary of the MATLAB functions and the corresponding code location, specified as `'on'` or `'off'`. Specify `'on'` to include a summary of the MATLAB objects and the corresponding code location in the code generation report. For more information, see “Traceable MATLAB functions” (Embedded Coder).

Example: `'GenerateTraceReportEmL','on'`

Data Types: char

## **Metrics**

### **GenerateCodeMetricsReport — Static code metrics**

`'off' | 'on'`

Static code metrics, specified as `'on'` or `'off'`. Specify `'on'` to include static code metrics in the code generation report. For more information, see “Generate static code metrics” (Embedded Coder).

Example: `'GenerateCodeMetricsReport','on'`

Data Types: char

## **See Also**

`coder.report.close` | `coder.report.open`

## **Topics**

“Reports for Code Generation”

“Generate a Code Generation Report”

“Generate Code Generation Report After Build Process”

**Introduced in R2012a**

# coder.report.open

Open existing HTML code generation report

## Syntax

```
coder.report.open(model)
coder.report.open(subsystem)
```

## Description

`coder.report.open(model)` opens a code generation report for the `model`. The build folder for the model must be present in the current working folder.

`coder.report.open(subsystem)` opens a code generation report for the `subsystem`. The build folder for the subsystem must be present in the current working folder.

## Examples

### Open code generation report for a model

After generating code for `rtwdemo_counter`, open a code generation report for the model.

```
coder.report.open('rtwdemo_counter')
```

### Open code generation report for a subsystem

Open a code generation report for the subsystem 'Amplifier' in model 'rtwdemo\_counter'.

```
coder.report.open('rtwdemo_counter/Amplifier')
```

## Input Arguments

### **model** — Model name

character vector

Model name specified as a character vector

Example: 'rtwdemo\_counter'

Data Types: char

### **subsystem** — Subsystem name

character vector

Subsystem name specified as a character vector

Example: 'rtwdemo\_counter/Amplifier'

Data Types: char

## **See Also**

`coder.report.close` | `coder.report.generate`

## **Topics**

“Reports for Code Generation”

“Open Code Generation Report”

**Introduced in R2012a**

## coder.xcp.a2l.addCoderXCPIInfo

Create ASAP2 file with IF\_DATA XCP block that describes the Simulink Coder XCP slave configuration

### Syntax

```
coder.xcp.a2l.addCoderXCPIInfo
coder.xcp.a2l.addCoderXCPIInfo(buildFolder)
coder.xcp.a2l.addCoderXCPIInfo(myModel)
coder.xcp.a2l.addCoderXCPIInfo(buildFolder, Name,Value)
```

### Description

`coder.xcp.a2l.addCoderXCPIInfo` creates the ASAP2 file *modelName\_CoderXCPSlave.a2l* in the code generation folder. The ASAP2 file contains the IF\_DATA XCP block that describes the Simulink Coder XCP slave configuration.

The function:

- Runs `rtw.asap2MergeMdlRefs` to merge the ASAP2 files generated from referenced models into a single ASAP2 file.
- Runs `rtw.asap2SetAddress` to replace placeholder address strings with addresses extracted from the debug symbol file specified by `ExtModeMexArgs`.
- In the ASAP2 file, creates:
  - An A2ML block for the *ASAM MCD-1 XCP* communication channel.
  - An IF\_DATA XCP block that describes configuration of Simulink Coder XCP slave.

`coder.xcp.a2l.addCoderXCPIInfo(buildFolder)` creates the ASAP2 file for the code generated in `buildFolder`.

`coder.xcp.a2l.addCoderXCPIInfo(myModel)` creates the ASAP2 file containing the Simulink Coder XCP slave information for `myModel`.

`coder.xcp.a2l.addCoderXCPIInfo(buildFolder, Name,Value)` creates the ASAP2 file using one or more name-value pair arguments.

### Examples

#### Tune Parameters and Monitor Signals Through XCP and Third-Party Tools

For a workflow description, see “Calibrate Generated Code and Monitor Signals Through XCP and Third-Party Tools”.

### Input Arguments

#### **buildFolder** — Generated code folder

character vector | string

Folder that contains generated model code.

**myModel — Model name**

character vector | string

Name of model that is configured for XCP external mode simulation.

**Name-Value Pair Arguments**

Specify optional comma-separated pairs of `Name`, `Value` arguments. `Name` is the argument name and `Value` is the corresponding value. `Name` must appear inside quotes. You can specify several name and value pair arguments in any order as `Name1, Value1, ..., NameN, ValueN`.

Example: `coder.xcp.a2l.addCoderXCPInfo(buildFolder, 'OutputFile', 'myOutputFile')`

**MergeMdlRefs — Run `rtw.asap2MergeMdlRefs`**

true (default) | false

If true, run `rtw.asap2MergeMdlRefs`.

If false, do not run `rtw.asap2MergeMdlRefs`.

**SetAddress — Run `rtw.asap2SetAddress`**

true (default) | false

If true, run `rtw.asap2SetAddress`.

If false, do not run `rtw.asap2SetAddress`.

**InputFile — Source ASAP file**

character vector | string

Source ASAP file to use instead of `buildFolder/modelName.a2l`.

**OutputFile — Name of ASAP2 file with `IF_DATA` XCP block**

character vector | string

Output ASAP2 file name.

**See Also****Topics**

“Calibrate Generated Code and Monitor Signals Through XCP and Third-Party Tools”

**Introduced in R2019b**

# extmodeBackgroundRun

Perform external mode background activity

## Syntax

```
errorCode = extmodeBackgroundRun();
```

## Description

`errorCode = extmodeBackgroundRun()`; performs external mode background activity, for example, retrieving packets from the network, running the packets protocol layer, and sending packets to the development computer.

Do not invoke the function in a thread with real-time constraints.

Use this function with other external mode functions to enable communication between Simulink and the target application during an external mode simulation.

## Examples

### Set Up External Mode Communication

For a pseudo-code example that shows how you can provide external mode communication by using the function with related functions, see “External Mode Abstraction Layer”.

## Output Arguments

### errorCode — Error detection

`extmodeErrorCode_T` enumeration

Error code, returned as an `extmodeErrorCode_T` enumeration with one of these values:

- `EXTMODE_SUCCESS` (0) -- No error detected.
- `EXTMODE_BUSY` (-6) -- Resource busy detected, try later
- `EXTMODE_INV_MSG_FORMAT` (-7) -- Invalid message format detected by external mode communication protocol.
- `EXTMODE_INV_SIZE` (-8) -- Invalid size detected by the external mode communication protocol.
- `EXTMODE_NOT_INITIALIZED` (-9) -- External mode not initialized yet.
- `EXTMODE_NO_MEMORY` (-10) -- No memory available on the target hardware.
- `EXTMODE_ERROR` (-12) -- External mode generic error detected.
- `EXTMODE_PKT_CHECKSUM_ERROR` (-13) -- Checksum inconsistency detected by external mode communication protocol.
- `EXTMODE_PKT_RX_TIMEOUT_ERROR` (-14) -- Timeout error detected during the reception of a packet.
- `EXTMODE_PKT_TX_TIMEOUT_ERROR` (-15) -- Timeout error detected during the transmission of a packet.

## **See Also**

[extmodeEvent](#) | [extmodeGetFinalSimulationTime](#) | [extmodeInit](#) | [extmodeParseArgs](#) | [extmodeReset](#) | [extmodeSetFinalSimulationTime](#) | [extmodeSimulationComplete](#) | [extmodeStopRequested](#) | [extmodeWaitForHostRequest](#)

## **Topics**

[“External Mode Simulation by Using XCP Communication”](#)  
[“Customize XCP Slave Software”](#)

**Introduced in R2018a**

# extmodeEvent

External mode event trigger

## Syntax

```
errorCode = extmodeEvent(eventId, simulationTime)
```

## Description

`errorCode = extmodeEvent(eventId, simulationTime)` informs the external mode abstraction layer of the occurrence of an event.

`eventId` is the sample time ID of the model, for example, 0 for base rate, 1 for first subrate, and so on.

The function:

- Samples all signals associated with a given sample time.
- Stores signal values in a new packet buffer.
- Passes the packet buffer to the underlying transport layer for subsequent transmission to the development computer.

Use this function with other external mode functions to enable communication between Simulink and the target application during an external mode simulation.

For correct sampling of signal values, run the function immediately after `model_step()` for the corresponding sample time ID. You can invoke the function with different sample time IDs in separate threads because the function is thread-safe.

The `extmodeBackgroundRun` function performs the transmission of signal values to the development computer.

## Examples

### Set Up External Mode Communication

For a pseudo-code example that shows how you can provide external mode communication by using the function with related functions, see “External Mode Abstraction Layer”.

## Input Arguments

### eventId — Event ID

`uint16_T`

Sample time ID of the model, which is 0 for base rate, 1 for first subrate, 2 for second subrate, and so on.

### simulationTime — Simulation time

`real_T`

Time when event occurs.

## Output Arguments

### **errorCode** — Error detection

`extmodeErrorCode_T` enumeration

Error code, returned as an `extmodeErrorCode_T` enumeration with one of these values:

- `EXTMODE_SUCCESS` (0) -- No error detected.
- `EXTMODE_INV_ARG` (-1) -- Arguments invalid.
- `EXTMODE_NOT_INITIALIZED` (-9) -- External mode not initialized yet.
- `EXTMODE_NO_MEMORY` (-10) -- No memory available on the target hardware.

## See Also

`extmodeBackgroundRun` | `extmodeGetFinalSimulationTime` | `extmodeInit` |  
`extmodeParseArgs` | `extmodeReset` | `extmodeSetFinalSimulationTime` |  
`extmodeSimulationComplete` | `extmodeStopRequested` | `extmodeWaitForHostRequest`

### Topics

“External Mode Simulation by Using XCP Communication”

“Customize XCP Slave Software”

**Introduced in R2018a**

## extmodeGetFinalSimulationTime

Get final simulation time for external mode platform abstraction layer

### Syntax

```
errorCode = extmodeGetFinalSimulationTime(finalTime);
```

### Description

`errorCode = extmodeGetFinalSimulationTime(finalTime);` gets the model's final simulation time for the external mode platform abstraction layer. The function is a complementary function for `extmodeSetFinalSimulationTime`.

### Output Arguments

#### **finalTime** – Final simulation time

`real_T` pointer

Final simulation time of model.

#### **errorCode** – Error detection

`extmodeErrorCode_T` enumeration

Error code, returned as an `extmodeErrorCode_T` enumeration with one of these values:

- `EXTMODE_SUCCESS` (0) -- No error detected.
- `EXTMODE_INV_ARG` (-1) -- Arguments invalid.
- `EXTMODE_NOT_INITIALIZED` (-9) -- External mode not initialized yet.

### See Also

`extmodeBackgroundRun` | `extmodeEvent` | `extmodeInit` | `extmodeParseArgs` | `extmodeReset` | `extmodeSetFinalSimulationTime` | `extmodeSimulationComplete` | `extmodeStopRequested` | `extmodeWaitForHostRequest`

### Topics

“External Mode Simulation by Using XCP Communication”  
 “Customize XCP Slave Software”

**Introduced in R2018a**

## extmodeInit

Initialize external mode target connectivity

### Syntax

```
errorCode = extmodeInit(extmodeInfo, finalTime);
```

### Description

`errorCode = extmodeInit(extmodeInfo, finalTime);` initializes the external mode target connectivity, including the underlying communication stack.

Use this function with other external mode functions to enable communication between Simulink and the target application during an external mode simulation.

### Examples

#### Set Up External Mode Communication

For a pseudo-code example that shows how you can provide external mode communication by using the function with related functions, see “External Mode Abstraction Layer”.

### Input Arguments

#### **extmodeInfo** — External mode information structure

RTWExtModeInfo structure

Model structure that contains information for the external mode simulation. RTWExtModeInfo is defined in `matlabroot/simulink/include/rtw_extmode.h`.

#### **finalTime** — Final simulation time

real\_T pointer

If the model’s final simulation time in the external mode abstraction layer is initialized, then `finalTime` is an output and the pointer location is updated with the initialized value. You might initialize the final simulation time through the `'-tf'` option detected by `extmodeParseArgs()` or `extmodeSetFinalSimulationTime()`

If the model’s final simulation time in the external mode abstraction layer is not initialized, then `finalTime` is an input and the model’s final simulation time in external mode is updated accordingly.

### Output Arguments

#### **errorCode** — Error detection

extmodeErrorCode\_T enumeration

Error code, returned as an `extmodeErrorCode_T` enumeration with one of these values:

- EXTMODE\_SUCCESS (0) -- No error detected.
- EXTMODE\_INV\_ARG (-1) -- Arguments invalid.
- EXTMODE\_ERROR (-12) -- External mode generic error detected.

### **See Also**

[extmodeBackgroundRun](#) | [extmodeEvent](#) | [extmodeGetFinalSimulationTime](#) |  
[extmodeParseArgs](#) | [extmodeReset](#) | [extmodeSetFinalSimulationTime](#) |  
[extmodeSimulationComplete](#) | [extmodeStopRequested](#) | [extmodeWaitForHostRequest](#)

### **Topics**

[“External Mode Simulation by Using XCP Communication”](#)  
[“Customize XCP Slave Software”](#)

**Introduced in R2018a**

## extmodeParseArgs

Extract values of configuration parameters supported by external mode abstraction layer

### Syntax

```
errorCode = extmodeParseArgs(argCount, argValues);
```

### Description

`errorCode = extmodeParseArgs(argCount, argValues);` extracts the values of the configuration parameters that are supported by the external mode abstraction layer. The function parses the array of strings passed as input arguments. The array of strings is from the command-line arguments of the executable file running on the target hardware.

The external mode abstraction layer interprets only two options and passes the other arguments to `rtIOStreamOpen` for the initialization of the communication driver.

Use this function with other external mode functions to enable communication between Simulink and the target application during an external mode simulation.

If your target hardware does not support the parsing of command-line arguments, define the preprocessor macro `EXTMODE_DISABLE_ARGS_PROCESSING`. See information about parsing command-line arguments in “Other Platform Abstraction Layer Functionality”.

### Examples

#### Set Up External Mode Communication

For a pseudo-code example that shows how you can provide external mode communication by using the function with related functions, see “External Mode Abstraction Layer”.

### Input Arguments

#### **argCount** — Number of arguments

`int_T` scalar

Number of elements in `argValues` array.

#### **argValues** — Command-line arguments

array of null-terminated strings

Command-line arguments of the executable file running on the target hardware. The external mode abstraction layer interprets only these options:

- `'-w'` - Enables the `extmodeWaitForStartRequest()` function, which waits for a model start request from Simulink in external mode. If you do not specify this option, the `extmodeWaitForStartRequest()` function has no effect.
- `'-tf finalSimulationTime'` - `finalSimulationTime` overrides the Simulink configuration parameter, `StopTime`.

If the command contains more options, they are passed to `rtIOStreamOpen` as configuration parameters for the communication driver.

## Output Arguments

### **errorCode** – Error detection

`extmodeErrorCode_T` enumeration

Error code, returned as an `extmodeErrorCode_T` enumeration with one of these values:

- `EXTMODE_SUCCESS` (0) -- No error detected.
- `EXTMODE_INV_ARG` (-1) -- Arguments invalid.

## See Also

`extmodeBackgroundRun` | `extmodeEvent` | `extmodeGetFinalSimulationTime` | `extmodeInit` | `extmodeReset` | `extmodeSetFinalSimulationTime` | `extmodeSimulationComplete` | `extmodeStopRequested` | `extmodeWaitForHostRequest`

## Topics

“External Mode Simulation by Using XCP Communication”

“Customize XCP Slave Software”

## Introduced in R2018a

## extmodeReset

Reset external mode target connectivity

### Syntax

```
errorCode = extmodeReset();
```

### Description

`errorCode = extmodeReset();` restores the external mode abstraction layer, including the communication stack, to the initial, default state.

Use this function with other external mode functions to enable communication between Simulink and the target application during an external mode simulation.

### Examples

#### Set Up External Mode Communication

For a pseudo-code example that shows how you can provide external mode communication by using the function with related functions, see “External Mode Abstraction Layer”.

### Output Arguments

#### **errorCode** — Error detection

`extmodeErrorCode_T` enumeration

Error code, returned as an `extmodeErrorCode_T` enumeration with one of these values:

- `EXTMODE_SUCCESS` (0) -- No error detected.
- `EXTMODE_ERROR` (-12) -- External mode generic error detected.

### See Also

`extmodeBackgroundRun` | `extmodeEvent` | `extmodeGetFinalSimulationTime` | `extmodeInit` | `extmodeParseArgs` | `extmodeSetFinalSimulationTime` | `extmodeSimulationComplete` | `extmodeStopRequested` | `extmodeWaitForHostRequest`

### Topics

“External Mode Simulation by Using XCP Communication”

“Customize XCP Slave Software”

**Introduced in R2018a**

# extmodeSetFinalSimulationTime

Set final simulation time in external mode platform abstraction layer

## Syntax

```
errorCode = extmodeSetFinalSimulationTime(finalTime);
```

## Description

`errorCode = extmodeSetFinalSimulationTime(finalTime);` sets the final simulation time of the model in the external mode platform abstraction layer.

In the main function of your external mode target application, before `extmodeInit`, you can call `extmodeSetFinalSimulationTime` to set the final simulation time if:

- You do not want to use `extmodeParseArgs`.
- Your target hardware does not support parsing of command-line arguments but you want to override `StopTime` from the target application.

`extmodeGetFinalSimulationTime` and `extmodeSetFinalSimulationTime` are complementary functions.

## Input Arguments

### **finalTime** – Final simulation time

`real_T`

Final simulation time of model.

## Output Arguments

### **errorCode** – Error detection

`extmodeErrorCode_T` enumeration

Error code, returned as an `extmodeErrorCode_T` enumeration with one of these values:

- `EXTMODE_SUCCESS` (0) -- No error detected.
- `EXTMODE_INV_ARG` (-1) -- Arguments invalid.

## See Also

[extmodeBackgroundRun](#) | [extmodeEvent](#) | [extmodeGetFinalSimulationTime](#) | [extmodeInit](#) | [extmodeParseArgs](#) | [extmodeReset](#) | [extmodeSimulationComplete](#) | [extmodeStopRequested](#) | [extmodeWaitForHostRequest](#)

## Topics

“External Mode Simulation by Using XCP Communication”  
 “Customize XCP Slave Software”

**Introduced in R2018a**

# extmodeSimulationComplete

Check that external mode simulation is complete

## Syntax

```
simComplete = extmodeSimulationComplete();
```

## Description

`simComplete = extmodeSimulationComplete();` during an external mode simulation, checks whether the model simulation time has reached the final simulation time specified by the command-line `-tf` option or the Simulink configuration parameter, `StopTime`.

Use this function with other external mode functions to enable communication between Simulink and the target application during an external mode simulation.

## Examples

### Set Up External Mode Communication

For a pseudo-code example that shows how you can provide external mode communication by using the function with related functions, see “External Mode Abstraction Layer”.

## Output Arguments

### `simComplete` — Simulation complete

true | false

true if model simulation time has reached the specified final simulation time. Otherwise, returns false.

## See Also

`extmodeBackgroundRun` | `extmodeEvent` | `extmodeGetFinalSimulationTime` | `extmodeInit` | `extmodeParseArgs` | `extmodeReset` | `extmodeSetFinalSimulationTime` | `extmodeStopRequested` | `extmodeWaitForHostRequest`

## Topics

“External Mode Simulation by Using XCP Communication”  
“Customize XCP Slave Software”

**Introduced in R2018a**

## extmodeStopRequested

Check whether request to stop external mode simulation is received from model

### Syntax

```
stopRequest = extmodeStopRequested();
```

### Description

`stopRequest = extmodeStopRequested()`; checks whether a request to stop the external mode simulation is received from the Simulink model on the development computer.

Use this function with other external mode functions to enable communication between Simulink and the target application during an external mode simulation.

### Examples

#### Set Up External Mode Communication

For a pseudo-code example that shows how you can provide external mode communication by using the function with related functions, see “External Mode Abstraction Layer”.

### Output Arguments

#### **stopRequest** — Stop request

true | false

true if request to stop external mode simulation is received. Otherwise, returns false.

### See Also

`extmodeBackgroundRun` | `extmodeEvent` | `extmodeGetFinalSimulationTime` | `extmodeInit` | `extmodeParseArgs` | `extmodeReset` | `extmodeSetFinalSimulationTime` | `extmodeSimulationComplete` | `extmodeWaitForHostRequest`

### Topics

“External Mode Simulation by Using XCP Communication”

“Customize XCP Slave Software”

**Introduced in R2018a**

# extmodeWaitForHostRequest

Wait for request from development computer to start or stop external mode simulation

## Syntax

```
errorCode = extmodeWaitForHostRequest(timeoutInMicroseconds);
```

## Description

`errorCode = extmodeWaitForHostRequest(timeoutInMicroseconds);` waits for a start or stop request from the development computer and times out when the timeout value is reached.

Use this function with other external mode functions to enable communication between Simulink and the target application during an external mode simulation. Use the function during initialization because the function is a blocking function.

## Examples

### Set Up External Mode Communication

For a pseudo-code example that shows how you can provide external mode communication by using the function with related functions, see “External Mode Abstraction Layer”.

## Input Arguments

### timeoutInMicroseconds — Timeout

uint32\_T

Specifies the timeout value. If the value is set to `EXTMODE_WAIT_FOREVER`, the function waits indefinitely. If `'-w'` is not extracted by `extmodeParseArgs()`, the function has no effect.

## Output Arguments

### errorCode — Error detection

extmodeErrorCode\_T enumeration

Error code, returned as an `extmodeErrorCode_T` enumeration with one of these values:

- `EXTMODE_SUCCESS` (0) -- No error detected.
- `EXTMODE_INV_ARG` (-1) -- Arguments invalid.
- `EXTMODE_TIMEOUT_ERROR` (-100) -- External mode timeout error detected.

## See Also

[extmodeBackgroundRun](#) | [extmodeEvent](#) | [extmodeGetFinalSimulationTime](#) | [extmodeInit](#) | [extmodeParseArgs](#) | [extmodeReset](#) | [extmodeSetFinalSimulationTime](#) | [extmodeSimulationComplete](#) | [extmodeStopRequested](#)

**Topics**

“External Mode Simulation by Using XCP Communication”  
“Customize XCP Slave Software”

**Introduced in R2018a**

# findBuildArg

Find a specific build argument in model build information

## Syntax

```
[identifier,value] = findBuildArg(buildinfo,buildArgName)
```

## Description

[identifier,value] = findBuildArg(buildinfo,buildArgName) searches for a build argument from the build information.

If the build argument is present in the model build information, the function returns the name and value.

## Examples

### Find Build Argument in Build Information

Find a build argument and its value stored in build information myModelBuildInfo. Then, view the argument identifier and value.

```
load buildInfo.mat
myModelBuildInfo = buildInfo;
myBuildArgExtmodeStaticAlloc = 'EXTMODE_STATIC_ALLOC';
[buildArgId buildArgValue] = findBuildArg(buildInfo, ...
 myBuildArgExtmodeStaticAlloc);
```

```
>> buildArgId
```

```
buildArgId =
```

```
 'EXTMODE_STATIC_ALLOC'
```

```
>> buildArgValue
```

```
buildArgValue =
```

```
 '0'
```

## Input Arguments

**buildinfo** — Name of build information object returned by RTW.BuildInfo object

**buildArgName** — Name of build argument to find in build information  
character vector | string scalar

To get the build argument identifiers from the build information, use the getBuildArgs function.

## **Output Arguments**

**identifier** — Name of the build argument

character vector | string scalar

**value** — Value of the build argument

character vector | string scalar

## **See Also**

getBuildArgs

## **Topics**

“Customize Post-Code-Generation Build Processing”

**Introduced in R2014a**

# findIncludeFiles

Find and add include (header) files to model build information

## Syntax

```
findIncludeFiles(buildinfo,extPatterns)
```

## Description

`findIncludeFiles(buildinfo,extPatterns)` searches for and adds include files to the build information.

Use the `findIncludeFiles` function to:

- Search for include files in source and include paths from the build information.
- Apply the optional *extPatterns* argument to specify file name extension patterns for search.
- Add the found files with their full paths to the build information.
- Delete duplicate include file entries from the build information.

## Examples

### Find and Add Include Files to Build Information

Find include files with file name extension `.h` that are in the build information, `myModelBuildInfo`. Add the full paths for these files to the build information. View the include files from the build information.

```
myModelBuildInfo = RTW.BuildInfo;
addSourcePaths(myModelBuildInfo,{fullfile(pwd,...
 'mycustomheaders')},'myheaders');
findIncludeFiles(myModelBuildInfo);
headerfiles = getIncludeFiles(myModelBuildInfo,true,false);
```

```
>> headerfiles
```

```
headerfiles =
```

```
 'W:\work\mycustomheaders\myheader.h'
```

## Input Arguments

**buildinfo** — Name of build information object returned by `RTW.BuildInfo` object

**extPatterns** — Patterns of file name extensions that specify files for the search  
'\*.h' (default) | cell array of character vectors | string array

To specify files for the search, the character vectors or strings in the *extPatterns* argument:

- Must start with an asterisk immediately followed by a period (\*.)
- Can include a combination of alphanumeric and underscore (\_) characters

Example: '\*.h' '\*.hpp' '\*.x\*'

### **See Also**

[addIncludeFiles](#) | [getIncludeFiles](#) | [packNGo](#)

### **Topics**

["Customize Post-Code-Generation Build Processing"](#)

**Introduced in R2006b**

# getBuildArgs

Get build arguments from model build information

## Syntax

```
[identifiers,values] = getBuildArgs(buildinfo,includeGroupIDs,
excludeGroupIDs)
```

## Description

[*identifiers*,*values*] = `getBuildArgs`(*buildinfo*,*includeGroupIDs*,*excludeGroupIDs*) returns build argument identifiers and values from model build information.

The function requires the *buildinfo*, *identifiers*, and *values* arguments. You can use optional *includeGroupIDs* and *excludeGroupIDs* arguments. These optional arguments let you include or exclude groups selectively from the build arguments returned by the function.

If you choose to specify *excludeGroupIDs* and omit *includeGroupIDs*, specify a null character vector ( ' ') for *includeGroupIDs*.

## Examples

### Get Build Arguments from Build Information

After you build a model, the build information is available in the `buildInfo.mat` file. Retrieve the build arguments from the build information object.

```
load buildInfo.mat
[buildArgIds,buildArgValues] = getBuildArgs(buildInfo);
```

To get the value of a single build argument from the build information, you can use the `findBuildArg` function.

To view the build argument identifiers, enter:

```
buildArgIds
```

To view the build argument values, enter:

```
buildArgValues
```

## Input Arguments

**buildinfo** — Name of build information object returned by `RTW.BuildInfo`  
object

**includeGroupIDs** — Group identifiers of build arguments to include in the return from the function

cell array of character vectors | string

To use the *includeGroupIDs* argument, view available build argument identifier groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

**excludeGroupIDs – Group identifiers of build arguments to exclude from the return from the function**

cell array of character vectors | string

To use the *excludeGroupIDs* argument, view available build argument identifier groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

## Output Arguments

**identifiers – Names of the build arguments**

cell array of character vectors

**values – Values of the build arguments**

cell array of character vectors

## See Also

`findBuildArg`

### Topics

“Customize Post-Code-Generation Build Processing”

**Introduced in R2014a**

# getCodeDescriptor

Create `coder.codedescriptor.CodeDescriptor` object for model

## Syntax

```
getCodeDescriptor(model)
getCodeDescriptor(folder)
```

## Description

`getCodeDescriptor(model)` creates a `coder.codedescriptor.CodeDescriptor` object for the specified model.

`getCodeDescriptor(folder)` creates a `coder.codedescriptor.CodeDescriptor` object for the specified build folder.

## Examples

### Create a Code Descriptor Object Using Model Name

Create a `coder.codedescriptor.CodeDescriptor` object by using model name:

```
codeDescObj = coder.getCodeDescriptor('rtwdemo_comments')
```

### Create a Code Descriptor Object Using Build Folder

Create a `coder.codedescriptor.CodeDescriptor` object by using build folder:

```
codeDescObj = coder.getCodeDescriptor('C:\Users\Desktop\work\rtwdemo_comments_ert_rtw')
```

## Input Arguments

### **model** — Name of the model

string

Model object or name for which to obtain the `coder.codedescriptor.CodeDescriptor` object. You can get the `coder.codedescriptor.CodeDescriptor` object only for the top model if the model has referenced models.

Example: `rtwdemo_comments`

Data Types: `string`

### **folder** — Build folder of the model

string

Build folder of the model for which to obtain the `coder.codedescriptor.CodeDescriptor` object. You can get the `coder.codedescriptor.CodeDescriptor` object only for the top model if the model has referenced models.

Example: `C:\Users\Desktop\Work\rtwdemo_comments_ert_rtw`

Data Types: `string`

**See Also**

`coder.codedescriptor.CodeDescriptor`

**Topics**

“Get Code Description of Generated Code”

**Introduced in R2018a**

# getCompileFlags

Get compiler options from model build information

## Syntax

```
options = getCompileFlags(buildinfo,includeGroups,excludeGroups)
```

## Description

`options = getCompileFlags(buildinfo,includeGroups,excludeGroups)` returns compiler options from the build information.

The function requires the *buildinfo* argument. You can use optional *includeGroups* and *excludeGroups* arguments. These optional arguments let you include or exclude groups selectively from the compiler options returned by the function.

If you choose to specify *excludeGroups* and omit *includeGroups*, specify a null character vector ( `' '`) for *includeGroups*.

## Examples

### Get Compiler Options from Build Information

Get the compiler options stored in the build information `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addCompileFlags(myModelBuildInfo,{'-Zi -Wall' '-O3'}, ...
 'OPTS');
compflags = getCompileFlags(myModelBuildInfo);
```

```
>> compflags
```

```
compflags =
```

```
 '-Zi -Wall' '-O3'
```

### Get Compiler Options with Include Group Argument

Get the compiler options stored with the group name `Debug` in the build information `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addCompileFlags(myModelBuildInfo,{'-Zi -Wall' '-O3'}, ...
 {'Debug' 'MemOpt'});
compflags = getCompileFlags(myModelBuildInfo,'Debug');
```

```
>> compflags
```

```
compflags =
 '-Zi -Wall'
```

### Get Compiler Options with Exclude Group Argument

Get the compiler options stored in the build information `myModelBuildInfo`, except those options with the group name `Debug`.

```
myModelBuildInfo = RTW.BuildInfo;
addCompileFlags(myModelBuildInfo,{'-Zi -Wall' '-O3'}, ...
 {'Debug' 'MemOpt'});
compflags = getCompileFlags(myModelBuildInfo, '', 'Debug');
```

```
>> compflags

compflags =
 '-O3'
```

## Input Arguments

**buildinfo** — Name of the build information object returned by `RTW.BuildInfo`  
object

**includeGroups** — Group names of compiler options to include in the return from the function  
cell array of character vectors | string

To use the *includeGroups* argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

**excludeGroups** — Group names of compiler options to exclude from the return from the function  
cell array of character vectors | string

To use the *excludeGroups* argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

## Output Arguments

**options** — Compiler options from the build information  
cell array of character vectors

## See Also

`addCompileFlags` | `getDefines` | `getLinkFlags`

**Topics**

“Customize Post-Code-Generation Build Processing”

**Introduced in R2006a**

## getDefines

Get preprocessor macro definitions from model build information

### Syntax

```
[macrodefs,identifiers,values] = getDefines(buildinfo,includeGroups,
excludeGroups)
```

### Description

[macrodefs,identifiers,values] = getDefines(buildinfo,includeGroups,excludeGroups) returns preprocessor macro definitions from the build information.

The function requires the *buildinfo*, *macrodefs*, *identifiers*, and *values* arguments. You can use optional *includeGroups* and *excludeGroups* arguments. These optional arguments let you include or exclude groups selectively from the preprocessor macro definitions returned by the function.

If you choose to specify *excludeGroups* and omit *includeGroups*, specify a null character vector ( ' ') for *includeGroups*.

### Examples

#### Get Macro Definitions from Build Information

Get the preprocessor macro definitions stored in the build information `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addDefines(myModelBuildInfo, ...
 {'PROTO=first' '-DDEBUG' 'test' '-dPRODUCTION'}, 'OPTS');
[defs,names,values] = getDefines(myModelBuildInfo);
```

```
>> defs
```

```
defs =
```

```
 '-DPROTO=first' '-DDEBUG' '-Dtest' '-DPRODUCTION'
```

```
>> names
```

```
names =
```

```
 'PROTO'
 'DEBUG'
 'test'
 'PRODUCTION'
```

```
>> values
```

```
values =
```

```
'first'
''
''
''
```

### Get Macro Definitions with Include Group Argument

Get the preprocessor macro definitions stored with the group name `Debug` in the build information `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addDefines(myModelBuildInfo, ...
 {'PROTO=first' '-DDEBUG' 'test' '-dPRODUCTION'}, ...
 {'Debug' 'Debug' 'Debug' 'Release'});
[defs,names,values] = getDefines(myModelBuildInfo,'Debug');
```

```
>> defs

defs =

 '-DPROTO=first' '-DDEBUG' '-Dtest'
```

### Get Macro Definitions with Exclude Group Argument

Get the preprocessor macro definitions stored in the build information `myModelBuildInfo`, except those definitions with the group name `Debug`.

```
myModelBuildInfo = RTW.BuildInfo;
addDefines(myModelBuildInfo, ...
 {'PROTO=first' '-DDEBUG' 'test' '-dPRODUCTION'}, ...
 {'Debug' 'Debug' 'Debug' 'Release'});
[defs,names,values] = getDefines(myModelBuildInfo,'','Debug');
```

```
>> defs

defs =

 '-DPRODUCTION'
```

## Input Arguments

**buildinfo** — Name of the build information object returned by `RTW.BuildInfo` object

**includeGroups** — Group names of macro definitions to include in the return from the function

cell array of character vectors | string

To use the *includeGroups* argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

**excludeGroups** — Group names of macro definitions to exclude from the return from the function

cell array of character vectors | string

To use the *excludeGroups* argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

## Output Arguments

**macrodefs** — Macro definitions from the build information

cell array of character vectors

The *macrodefs* provide the complete macro definitions with a -D prefix. When the function returns a definition:

- If the -D was not specified when the definition was added to the build information, prepends a -D to the definition.
- Changes a lowercase -d to -D.

**identifiers** — Names of the macros from the build information

cell array of character vectors

**values** — Values assigned to the macros from the build information

cell array of character vectors

The *values* provide anything specified to the right of the first equal sign in the macro definition. The default is an empty character vector ('').

## See Also

`addDefines` | `getCompileFlags` | `getLinkFlags`

### Topics

“Customize Post-Code-Generation Build Processing”

**Introduced in R2006a**

# getFullFileList

Get list of files from model build information

## Syntax

```
[fPathNames, names] = getFullFileList(buildinfo, fcase)
```

## Description

[fPathNames, names] = getFullFileList(buildinfo, fcase) returns the fully qualified paths and names of files, or files of a selected type (source, include, or nonbuild), from the build information.

The function requires the *buildinfo*, *fPathNames*, and *names* arguments. You can use the optional *fcase* argument. This optional argument lets you include or exclude file cases selectively from file list returned by the function.

To ensure that header files are added to the file list (for example, header files in the `_sharedutils` on page 12-11 folder), run `findIncludeFiles` before `getFullFileList`.

The `packNGo` function calls `getFullFileList` to return a list of files in the build information before processing files for packaging.

The makefile for the model build resolves file locations based on source paths and rules. The build process does not require you to resolve the path of every file in the build information. The `getFullFileList` function returns the path for each file:

- If a path was explicitly associated with the file when it was added.
- If you called `updateFilePathsAndExtensions` to resolve file paths and extensions before calling `getFullFileList`.

## Examples

### Get Full List of Files

After building a model and loading the generated `buildInfo.mat` file, you can list the files stored in the build information object, `buildInfo`. This example returns information for the current model and its submodels.

From the code generation folder that contains the `buildInfo.mat` file, run:

```
bi = load('buildInfo.mat');
findIncludeFiles(bi.buildInfo);
[fPathNames, names] = getFullFileList(bi.buildInfo);
```

### Get List of Source Files

If you use an *fcase* option, you limit the listing to the files stored in the build information object for the current model. This example returns information for the current model only (not for submodels).

```
[fPathNames,names] = getFullFileList(bi.buildInfo,'source');
```

## Input Arguments

**buildinfo** — Name of the build information object returned by `RTW.BuildInfo`  
object

**fcase** — File case to return from the build information  
' ' (default) | 'source' | 'include' | 'nonbuild'

The *fcase* argument selects whether the function returns the full list for files in the build information or returns selected cases of files. If you omit the argument or specify a null character vector ( ' '), the function returns the files from the build information.

| Specify    | Function Action                                    |
|------------|----------------------------------------------------|
| 'source'   | Returns source files from the build information.   |
| 'include'  | Returns include files from the build information.  |
| 'nonbuild' | Returns nonbuild files from the build information. |

Example: 'source'

## Output Arguments

**fPathNames** — Fully qualified file paths from the build information  
cell array of character vectors

**names** — File names from the build information  
cell array of character vectors

## See Also

`findIncludeFiles`

## Topics

“Customize Post-Code-Generation Build Processing”

**Introduced in R2008a**

# getIncludeFiles

Get include files from model build information

## Syntax

```
files = getIncludeFiles(buildinfo,concatenatePaths,replaceMatlabroot,
includeGroups,excludeGroups)
```

## Description

`files = getIncludeFiles(buildinfo,concatenatePaths,replaceMatlabroot,includeGroups,excludeGroups)` returns the names of include files from the build information.

The function requires the *buildinfo*, *concatenatePaths*, and *replaceMatlabroot* arguments. You can use optional *includeGroups* and *excludeGroups* arguments. These optional arguments let you include or exclude groups selectively from the include files returned by the function.

If you choose to specify *excludeGroups* and omit *includeGroups*, specify a null character vector ( ' ') for *includeGroups*.

The makefile for the model build resolves file locations based on source paths and rules. The build process does not require you to resolve the path of every file in the build information. If you specify `true` for the *concatenatePaths* argument, the `getIncludeFiles` function returns the path for each file:

- If a path was explicitly associated with the file when it was added.
- If you called `updateFilePathsAndExtensions` to resolve file paths and extensions before calling `getIncludeFiles`.

## Examples

### Get Include Paths and Files from Build Information

Get the include paths and file names from the build information, `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addIncludeFiles(myModelBuildInfo,{'etc.h' 'etc_private.h' ...
 'mytypes.h'},{'/etc/proj/etclib' '/etcproj/etc/etc_build' ...
 '/common/lib'},{'etc' 'etc' 'shared'});
incfiles=getIncludeFiles(myModelBuildInfo,true,false);
```

```
>> incfiles
```

```
incfiles =
```

```
 [1x22 char] [1x36 char] [1x21 char]
```

### Get Include Paths and Files with Include Group Argument

Get the names of include files in group `etc` from the build information, `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addIncludeFiles(myModelBuildInfo,{'etc.h' 'etc_private.h' ...
 'mytypes.h'},{'/etc/proj/etclib' '/etcproj/etc/etc_build' ...
 '/common/lib'},{'etc' 'etc' 'shared'});
incfiles = getIncludeFiles(myModelBuildInfo,false,false, ...
 'etc');
```

```
>> incfiles
```

```
incfiles =
 'etc.h' 'etc_private.h'
```

### Input Arguments

**buildinfo** — Name of the build information object returned by `RTW.BuildInfo` object

**concatenatePaths** — Choice of whether to concatenate paths and file names in return  
false | true

| Specify | Function Action                                                      |
|---------|----------------------------------------------------------------------|
| true    | Concatenates and returns each file name with its corresponding path. |
| false   | Returns only file names.                                             |

Example: true

**replaceMatlabroot** — Choice of whether to replace the `$(MATLAB_ROOT)` token with absolute paths in return  
false | true

Use the `replaceMatlabroot` argument to control whether the function includes the MATLAB root definition in the output it returns.

| Specify | Function Action                                                                                             |
|---------|-------------------------------------------------------------------------------------------------------------|
| true    | Replaces the token <code>\$(MATLAB_ROOT)</code> with the absolute path for your MATLAB installation folder. |
| false   | Does not replace the token <code>\$(MATLAB_ROOT)</code> .                                                   |

Example: true

**includeGroups** — Group names of include paths and files to include in the return from the function

cell array of character vectors | string

To use the `includeGroups` argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

**excludeGroups — Group names of include paths and files to exclude from the return from the function**

cell array of character vectors | string

To use the *excludeGroups* argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

**Output Arguments****files — Names of include files from the build information**

cell array of character vectors

The names of include files that you add with the `addIncludeFiles` function. If you call the `packNGo` function, the names include files that `packNGo` found and added while packaging model code.

**See Also**

`addIncludeFiles` | `findIncludeFiles` | `getIncludePaths` | `getSourceFiles` | `getSourcePaths` | `updateFilePathsAndExtensions`

**Topics**

"Customize Post-Code-Generation Build Processing"

**Introduced in R2006a**

## getIncludePaths

Get include paths from model build information

### Syntax

```
paths = getIncludePaths(buildinfo,replaceMatlabroot,includeGroups,
excludeGroups)
```

### Description

`paths = getIncludePaths(buildinfo,replaceMatlabroot,includeGroups,excludeGroups)` returns the names of include file paths from the build information.

The function requires the *buildinfo* and *replaceMatlabroot* arguments. You can use optional *includeGroups* and *excludeGroups* arguments. These optional arguments let you include or exclude groups selectively from the include paths returned by the function.

If you choose to specify *excludeGroups* and omit *includeGroups*, specify a null character vector (' ') for *includeGroups*.

### Examples

#### Get Include Paths from Build Information

Get the include paths from the build information, `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addIncludePaths(myModelBuildInfo,{'/etc/proj/etc/lib' ...
 '/etcproj/etc/etc_build' '/common/lib'}, ...
 {'etc' 'etc' 'shared'});
incpaths = getIncludePaths(myModelBuildInfo,false);
```

```
>> incpaths
```

```
incpaths =
```

```
 '\etc\proj\etc\lib' [1x22 char] '\common\lib'
```

#### Get Include Paths with Include Group Argument

Get the paths in group `shared` from the build information, `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addIncludePaths(myModelBuildInfo,{'/etc/proj/etc/lib' ...
 '/etcproj/etc/etc_build' '/common/lib'}, ...
 {'etc' 'etc' 'shared'});
incpaths = getIncludePaths(myModelBuildInfo,false,'shared');
```

```
>> incpaths
incpaths =
 '\common\lib'
```

## Input Arguments

**buildinfo** — Name of the build information object returned by `RTW.BuildInfo` object

**replaceMatlabroot** — Choice of whether to replace the `$(MATLAB_ROOT)` token with absolute paths in return from the function  
false | true

Use the *replaceMatlabroot* argument to control whether the function includes the MATLAB root definition in the output that it returns.

| Specify | Function Action                                                                                             |
|---------|-------------------------------------------------------------------------------------------------------------|
| true    | Replaces the token <code>\$(MATLAB_ROOT)</code> with the absolute path for your MATLAB installation folder. |
| false   | Does not replace the token <code>\$(MATLAB_ROOT)</code> .                                                   |

Example: true

**includeGroups** — Group names of include paths to include in the return from the function  
cell array of character vectors | string

To use the *includeGroups* argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

**excludeGroups** — Group names of include paths to exclude from the return from the function

cell array of character vectors | string

To use the *excludeGroups* argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

## Output Arguments

**paths** — Paths of include files from the build information  
cell array of character vectors

## See Also

`addIncludePaths` | `getIncludeFiles` | `getSourceFiles` | `getSourcePaths`

## Topics

“Customize Post-Code-Generation Build Processing”

**Introduced in R2006a**

# getLinkFlags

Get link options from model build information

## Syntax

```
options = getLinkFlags(buildinfo,includeGroups,excludeGroups)
```

## Description

`options = getLinkFlags(buildinfo,includeGroups,excludeGroups)` returns linker options from the build information.

The function requires the *buildinfo* argument. You can use optional *includeGroups* and *excludeGroups* arguments. These optional arguments let you include or exclude groups selectively from the compiler options returned by the function.

If you choose to specify *excludeGroups* and omit *includeGroups*, specify a null character vector ( `' '`) for *includeGroups*.

## Examples

### Get Linker Options from Build Information

Get the linker options from the build information, `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addLinkFlags(myModelBuildInfo,{'-MD -Gy' '-T'},'OPTS');
linkflags = getLinkFlags(myModelBuildInfo);
```

```
>> linkflags
```

```
linkflags =
```

```
 '-MD -Gy' '-T'
```

### Get Linker Options with Include Group Argument

Get the linker options with the group name `Debug` from the build information, `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addLinkFlags(myModelBuildInfo,{'-MD -Gy' '-T'}, ...
 {'Debug' 'MemOpt'});
linkflags = getLinkFlags(myModelBuildInfo,{'Debug'});
```

```
>> linkflags
```

```
linkflags =
```

```
'-MD -Gy'
```

### Get Linker Options with Exclude Group Argument

Get the linker options from the build information `myModelBuildInfo`, except those options with the group name `Debug`.

```
myModelBuildInfo = RTW.BuildInfo;
addLinkFlags(myModelBuildInfo,{'-MD -Gy' '-T'}, ...
 {'Debug' 'MemOpt'});
linkflags = getLinkFlags(myModelBuildInfo, '', {'Debug'});
```

```
>> linkflags
```

```
linkflags =
```

```
'-T'
```

## Input Arguments

**buildinfo** — Name of the build information object returned by `RTW.BuildInfo`  
object

**includeGroups** — Group names of linker options to include in the return from the function  
cell array of character vectors | string

To use the *includeGroups* argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

**excludeGroups** — Group names of linker options to exclude from the return from the function  
cell array of character vectors | string

To use the *excludeGroups* argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

## Output Arguments

**options** — Linker options from the build information  
cell array of character vectors

## See Also

`addLinkFlags` | `getCompileFlags` | `getDefines`

### Topics

“Customize Post-Code-Generation Build Processing”

**Introduced in R2006a**

## getNonBuildFiles

Get nonbuild-related files from model build information

### Syntax

```
files = getNonBuildFiles(buildinfo, concatenatePaths, replaceMatlabroot,
includeGroups, excludeGroups)
```

### Description

`files = getNonBuildFiles(buildinfo, concatenatePaths, replaceMatlabroot, includeGroups, excludeGroups)` returns the names of non-build files from the build information, such as DLL files required for a final executable or a README file.

The function requires the *buildinfo*, *concatenatePaths*, and *replaceMatlabroot* arguments. You can use optional *includeGroups* and *excludeGroups* arguments. These optional arguments let you include or exclude groups selectively from the non-build files returned by the function.

If you choose to specify *excludeGroups* and omit *includeGroups*, specify a null character vector ( ' ') for *includeGroups*.

The makefile for the model build resolves file locations based on source paths and rules. The build process does not require you to resolve the path of every file in the build information. If you specify `true` for the *concatenatePaths* argument, the `getNonBuildFiles` function returns the path for each file:

- If a path was explicitly associated with the file when it was added.
- If you called `updateFilePathsAndExtensions` to resolve file paths and extensions before calling `getIncludeFiles`.

### Examples

#### Get Nonbuild Files from Build Information

Get the nonbuild file names stored in the build information, `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addNonBuildFiles(myModelBuildInfo, {'readme.txt' 'myutility1.dll' ...
 'myutility2.dll'});
nonbuildfiles = getNonBuildFiles(myModelBuildInfo, false, false);
```

```
>> nonbuildfiles
```

```
nonbuildfiles =
```

```
'readme.txt' 'myutility1.dll' 'myutility2.dll'
```

## Input Arguments

**buildinfo** — Name of the build information object returned by `RTW.BuildInfo` object

**concatenatePaths** — Choice of whether to concatenate paths and file names in return from function

false | true

| Specify | Function Action                                                      |
|---------|----------------------------------------------------------------------|
| true    | Concatenates and returns each file name with its corresponding path. |
| false   | Returns only file names.                                             |

Example: true

**replaceMatlabroot** — Choice of whether to replace the `$(MATLAB_ROOT)` token with absolute paths in return from function

false | true

Use the `replaceMatlabroot` argument to control whether the function includes the MATLAB root definition in the output that it returns.

| Specify | Function Action                                                                                             |
|---------|-------------------------------------------------------------------------------------------------------------|
| true    | Replaces the token <code>\$(MATLAB_ROOT)</code> with the absolute path for your MATLAB installation folder. |
| false   | Does not replace the token <code>\$(MATLAB_ROOT)</code> .                                                   |

Example: true

**includeGroups** — Group names of non-build files to include in the return from the function

cell array of character vectors | string

To use the `includeGroups` argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

**excludeGroups** — Group names of non-build files to exclude from the return from the function

cell array of character vectors | string

To use the `excludeGroups` argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

## Output Arguments

**files** — Names of non-build files from the build information

cell array of character vectors

**See Also**

addNonBuildFiles

**Topics**

“Customize Post-Code-Generation Build Processing”

**Introduced in R2008a**

# getSourceFiles

Get source files from model build information

## Syntax

```
srcfiles = getSourceFiles(buildinfo, concatenatePaths, replaceMatlabroot,
includeGroups, excludeGroups)
```

## Description

`srcfiles = getSourceFiles(buildinfo, concatenatePaths, replaceMatlabroot, includeGroups, excludeGroups)` returns the names of source files from the build information.

The function requires the *buildinfo*, *concatenatePaths*, and *replaceMatlabroot* arguments. You can use optional *includeGroups* and *excludeGroups* arguments. These optional arguments let you include or exclude groups selectively from the source files returned by the function.

If you choose to specify *excludeGroups* and omit *includeGroups*, specify a null character vector ( ' ') for *includeGroups*.

The makefile for the model build resolves file locations based on source paths and rules. The build process does not require you to resolve the path of every file in the build information. If you specify `true` for the *concatenatePaths* argument, the `getSourceFiles` function returns the path for each file:

- If a path was explicitly associated with the file when it was added.
- If you called `updateFilePathsAndExtensions` to resolve file paths and extensions before calling `getSourceFiles`.

## Examples

### Get Source Files from Build Information

Get the source paths and file names from the build information, `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addSourceFiles(myModelBuildInfo, ...
 {'test1.c' 'test2.c' 'driver.c'}, '', ...
 {'Tests' 'Tests' 'Drivers'});
srcfiles = getSourceFiles(myModelBuildInfo, false, false);
```

```
>> srcfiles
```

```
srcfiles =
```

```
 'test1.c' 'test2.c' 'driver.c'
```

### Get Source Files with Include Group Argument

Get the names of source files in group `tests` from the build information, `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addSourceFiles(myModelBuildInfo,{'test1.c' 'test2.c'...
 'driver.c'}, {'/proj/test1' '/proj/test2'...
 '/drivers/src'}, {'tests', 'tests', 'drivers'});
incfiles = getSourceFiles(myModelBuildInfo,false,false,...
 'tests');
```

```
>> incfiles
```

```
incfiles =
```

```
 'test1.c' 'test2.c'
```

### Input Arguments

**buildinfo** — Name of the build information object returned by `RTW.BuildInfo` object

**concatenatePaths** — Choice of whether to concatenate paths and file names in return  
false | true

| Specify | Function Action                                                      |
|---------|----------------------------------------------------------------------|
| true    | Concatenates and returns each file name with its corresponding path. |
| false   | Returns only file names.                                             |

Example: true

**replaceMatlabroot** — Choice of whether to replace the `$(MATLAB_ROOT)` token with absolute paths in return  
false | true

Use the `replaceMatlabroot` argument to control whether the function includes the MATLAB root definition in the output it returns.

| Specify | Function Action                                                                                             |
|---------|-------------------------------------------------------------------------------------------------------------|
| true    | Replaces the token <code>\$(MATLAB_ROOT)</code> with the absolute path for your MATLAB installation folder. |
| false   | Does not replace the token <code>\$(MATLAB_ROOT)</code> .                                                   |

Example: true

**includeGroups** — Group names of source files to include in the return from the function  
cell array of character vectors | string

To use the `includeGroups` argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

**excludeGroups — Group names of source files to exclude from the return from the function**

cell array of character vectors | string

To use the *excludeGroups* argument, view available groups by using `myGroups = getGroups(buildInfo)`.

Example: ''

**Output Arguments****srcfiles — Names of source files from the build information**

cell array of character vectors

The names of source files that you add with the `addSourceFiles` function. If you call the `packNGo` function, the names include files that `packNGo` found and added while packaging model code.

**See Also**

`addSourceFiles` | `getIncludeFiles` | `getIncludePaths` | `getSourcePaths` | `updateFilePathsAndExtensions`

**Topics**

“Customize Post-Code-Generation Build Processing”

**Introduced in R2006a**

## getSourcePaths

Get source paths from model build information

### Syntax

```
srcpaths = getSourcePaths(buildinfo,replaceMatlabroot,includeGroups,
excludeGroups)
```

### Description

`srcpaths = getSourcePaths(buildinfo,replaceMatlabroot,includeGroups,excludeGroups)` returns the names of source file paths from the build information.

The function requires the *buildinfo* and *replaceMatlabroot* arguments. You can use optional *includeGroups* and *excludeGroups* arguments. These optional arguments let you include or exclude groups selectively from the source paths returned by the function.

If you choose to specify *excludeGroups* and omit *includeGroups*, specify a null character vector ( ' ') for *includeGroups*.

### Examples

#### Get Source Paths from Build Information

Get the source paths from the build information, `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addSourcePaths(myModelBuildInfo,{'/proj/test1' ...
 '/proj/test2' '/drivers/src'}, {'tests' 'tests' ...
 'drivers'});
srcpaths = getSourcePaths(myModelBuildInfo,false);
```

```
>> srcpaths
```

```
srcpaths =
```

```
 '\proj\test1' '\proj\test2' '\drivers\src'
```

#### Get Source Paths with Include Group Argument

Get the paths in group `tests` from the build information, `myModelBuildInfo`.

```
myModelBuildInfo = RTW.BuildInfo;
addSourcePaths(myModelBuildInfo,{'/proj/test1' ...
 '/proj/test2' '/drivers/src'}, {'tests' 'tests' ...
 'drivers'});
srcpaths = getSourcePaths(myModelBuildInfo,true,'tests');
```

```
>> srcpaths

srcpaths =

 '\proj\test1' '\proj\test2'
```

### Get Source Paths from Build Information

Get a source path from the build information, `myModelBuildInfo`. First, get the path without replacing `$(MATLAB_ROOT)` with an absolute path. Then, get it with replacement. Here, the MATLAB root folder is `\\myserver\myworkspace\matlab`.

```
myModelBuildInfo = RTW.BuildInfo;
addSourcePaths(myModelBuildInfo, fullfile(matlabroot, ...
 'rtw', 'c', 'src'));
srcpaths = getSourcePaths(myModelBuildInfo, false);
```

```
>> srcpaths{:}

ans =

$(MATLAB_ROOT)\rtw\c\src

>> srcpaths = getSourcePaths(myModelBuildInfo, true);
>> srcpaths{:}

ans =

\\myserver\myworkspace\matlab\rtw\c\src
```

## Input Arguments

**buildinfo** — Name of the build information object returned by `RTW.BuildInfo` object

**replaceMatlabroot** — Choice of whether to replace the `$(MATLAB_ROOT)` token with absolute paths in return

false | true

Use the *replaceMatlabroot* argument to control whether the function includes the MATLAB root definition in the output it returns.

| Specify | Function Action                                                                                             |
|---------|-------------------------------------------------------------------------------------------------------------|
| true    | Replaces the token <code>\$(MATLAB_ROOT)</code> with the absolute path for your MATLAB installation folder. |
| false   | Does not replace the token <code>\$(MATLAB_ROOT)</code> .                                                   |

Example: true

**includeGroups** — Group names of source paths to include in the return from the function  
cell array of character vectors | string

To use the *includeGroups* argument, view available groups with `myGroups = getGroups(buildInfo)`.

Example: ''

**excludeGroups — Group names of source paths to exclude from the return from the function**

cell array of character vectors | string

To use the *excludeGroups* argument, view available groups with `myGroups = getGroups(buildInfo)`.

Example: ''

## Output Arguments

**srcpaths — Paths of source files from the build information**

cell array of character vectors

## See Also

`addSourcePaths` | `getIncludeFiles` | `getIncludePaths` | `getSourceFiles`

## Topics

“Customize Post-Code-Generation Build Processing”

**Introduced in R2006a**

# model\_initialize

Initialization entry-point function in generated code for Simulink model

## Syntax

```
void model_initialize(void)
```

## Calling Interfaces

The calling interface generated for this function differs depending on the value of the model configuration parameter **Code interface packaging** on page 10-15:

- **C++ class** (default for C++ language) — Generated function is encapsulated into a C++ class method. Required model data is encapsulated into C++ class attributes.
- **Nonreusable function** (default for C language) — Generated function passes `(void)`. Model data structures are statically allocated, global, and accessed directly in the model code.
- **Reusable function** — Generated function passes the real-time model data structure, by reference, as an input argument. The real-time model data structure is exported with the `model.h` header file.

For an ERT-based model, you can use model configuration parameter **Pass root-level I/O as** to control how root-level input and output arguments are passed to the function. They can be included in the real-time model data structure, passed as individual arguments, or passed as references to an input structure and an output structure.

For a GRT-based model, the generated `model.c` source file contains an allocation function that dynamically allocates model data for each instance of the model. For an ERT-based model, you can use model configuration parameter **Use dynamic memory allocation for model initialization** to control whether an allocation function is generated.

- When set, you can restart code generated from the model from a single execution instance. The sequence of function calls from the `main.c` is `allocfcn`, `model_init`, `model_term`, `allocfcn`, `model_init`, `model_term`.
- When cleared,

If you have an Embedded Coder license, for **Nonreusable function** code interface packaging, you can use the Code Mapping Editor to customize the name of the initialize function interface. See “Override Default Naming for Individual C Entry-Point Functions” (Embedded Coder).

## Description

The generated `model_initialize` function contains initialization code for a Simulink model and should be called once at the start of your application code.

Do not use the `model_initialize` function to reset the real-time model data structure (rtM).

## See Also

`model_step` | `model_terminate`

**Topics**

“Configure Code Generation for Model Entry-Point Functions”

“Generate Code That Responds to Initialize, Reset, and Terminate Events”

**Introduced before R2006a**

## model\_step

Step routine entry point in generated code for Simulink model

### Syntax

```
void model_step(void)
```

```
void model_stepN(void)
```

### Calling Interfaces

The `model_step` default function prototype varies depending on the setting of model configuration parameter **Treat each discrete rate as a separate task** (Simulink) (EnableMultiTasking) :

| Parameter Value                   | Function Prototype                                                        |
|-----------------------------------|---------------------------------------------------------------------------|
| Off<br>(single rate or multirate) | <code>void model_step(void);</code>                                       |
| On<br>(multirate)                 | <code>void model_stepN (void);</code><br>( <i>N</i> is a task identifier) |

The calling interface generated for this function also differs depending on the value of the model configuration parameter **Code interface packaging** on page 10-15:

- **C++ class** (default for C++ language) — Generated function is encapsulated into a C++ class method. Required model data is encapsulated into C++ class attributes.
- **Nonreusable function** (default for C language) — Generated function passes `(void)`. Model data structures are statically allocated, global, and accessed directly in the model code.
- **Reusable function** — Generated function passes the real-time model data structure, by reference, as an input argument. The real-time model data structure is exported with the `model.h` header file.

For an ERT-based model, you can use model configuration parameter **Pass root-level I/O as** to control how root-level input and output arguments are passed to the function. They can be included in the real-time model data structure, passed as individual arguments, or passed as references to an input structure and an output structure.

If you have an Embedded Coder license:

- For **Nonreusable function** code interface packaging, you can use the **Configure C Step Function Interface** dialog box to customize a C step function interface. See “Override Default C Step Function Interface” (Embedded Coder) “Customize Generated C Function Interfaces” (Embedded Coder).
- For **C++ class** code interface packaging, you can use the **Configure C++ Class Interface** button and related controls on the **Interface** pane of the Configuration Parameters dialog box. For more information, see “Customize Generated C++ Class Interfaces” (Embedded Coder).

## Description

The generated `model_step` function contains the output and update code for the blocks in a Simulink model. The `model_step` function computes the current value of the blocks. If logging is enabled, `model_step` updates logging variables. If the model's stop time is finite, `model_step` signals the end of execution when the current time equals the stop time.

Under the following conditions, `model_step` does not check the current time against the stop time:

- The model's stop time is set to `inf`.
- Logging is disabled.
- Parameter **Terminate function required** is not selected.

If one or more of these conditions are true, the program runs indefinitely.

For a GRT- or ERT-based model, the software generates a `model_step` function when model configuration parameter **Single output/update function** is selected (the default).

`model_step` is designed to be called at interrupt level from `rt_OneStep`, which is assumed to be invoked as a timer ISR. `rt_OneStep` calls `model_step` to execute processing for one clock period of the model. For a description of how calls to `model_step` are generated and scheduled, see “`rt_OneStep` and Scheduling Considerations” (Embedded Coder).

If model configuration parameter **Single output/update function** is not selected, the software generates these model entry-point functions in place of `model_step`:

- `model_output`: Contains the output code for the blocks in the model
- `model_update`: Contains the update code for the blocks in the model

## See Also

`model_initialize` | `model_terminate`

## Topics

“Configure Code Generation for Model Entry-Point Functions”

**Introduced before R2006a**

# model\_terminate

Termination entry point in generated code for Simulink model

## Syntax

```
void model_terminate(void)
```

## Calling Interfaces

The calling interface generated for this function also differs depending on the setting of model configuration parameter **Code interface packaging** on page 10-15:

- **C++ class** (default for C++ language) — Generated function is encapsulated into a C++ class method. Required model data is encapsulated into C++ class attributes.
- **Nonreusable function** (default for C language) — Generated function passes (`void`). Model data structures are statically allocated, global, and accessed directly in the model code.
- **Reusable function** — Generated function passes the real-time model data structure, by reference, as an input argument. The real-time model data structure is exported with the `model.h` header file.

For an ERT-based model, you can use model configuration parameter **Pass root-level I/O as** to control how root-level input and output arguments are passed to the function. They can be included in the real-time model data structure, passed as individual arguments, or passed as references to an input structure and an output structure.

## Description

The generated `model_terminate` function contains the termination code for a Simulink model and should be called as part of system shutdown.

When `model_terminate` is called, blocks that have a terminate function execute their terminate code. If logging is enabled, `model_terminate` ends data logging.

Call the `model_terminate` function once.

For an ERT-based model, the code generator produces the `model_terminate` function for a model when model configuration parameter **Terminate function required** is selected (the default). If your application runs indefinitely, you do not need the `model_terminate` function. To suppress the function, clear model configuration parameter **Terminate function required**.

## See Also

`model_initialize` | `model_step`

## Topics

“Configure Code Generation for Model Entry-Point Functions”

“Generate Code That Responds to Initialize, Reset, and Terminate Events”

**Introduced before R2006a**

# packNGo

Package generated code in zip file for relocation

## Syntax

```
packNGo(buildInfo,Name,Value)
```

## Description

`packNGo(buildInfo,Name,Value)` packages the code files in a compressed zip file so that you can relocate, unpack, and rebuild them in another development environment. The list of name-value pairs is optional.

The types of code files in the zip file include:

- Source files (for example, `.c` and `.cpp` files)
- Header files (for example, `.h` and `.hpp` files)
- MAT-file that contains the build information object (`.mat` file)
- Nonbuild-related files (for example, `.dll` files and `.txt` informational files) required for a final executable
- Build-generated binary files (for example, executable `.exe` file or dynamic link library `.dll`).

The code generator includes the build-generated binary files (if present) in the zip file. The **ignoreFileMissing** property does not apply to build-generated binary files.

Use this function to relocate files. You can then recompile the files for a specific target environment or rebuild them in a development environment in which MATLAB is not installed. By default, the function packages the files as a flat folder structure in a zip file within the code generation folder. You can customize the output by specifying name-value pairs. After relocating the zip file, use a standard zip utility to unpack the compressed file.

The `packNGo` function can potentially modify the build information passed in the first `packNGo` argument. As part of code packaging, `packNGo` can find additional files from source and include paths recorded in the build information. When these files are found, `packNGo` adds them to the build information.

## Examples

### Run packNGo from Command Window

After the build process is complete, you can run `packNGo` from the Command Window. Use `packNGo` for zip file packaging of generated code in the file `portzingbit.zip`. Maintain the relative file hierarchy.

- 1 Change folders to the code generation folder. For example, using MATLAB Coder, `codegen/dll/zingbit`, or for Simulink code generation, `zingbit_grt_rtw`.
- 2 Load the `buildInfo` object that describes the build.

- 3 Run packNGo with property settings for packType and fileName.

```
cd codegen/dll/zingbit;
load buildInfo.mat
packNGo(buildInfo,'packType', 'hierarchical', ...
 'fileName', 'portzingbit');
```

### Configure packNGo in the Simulink Editor

If you configure zip file packaging from the code generation pane, the code generator uses packNGo to output a zip file during the build process.

- 1 Select **Code Generation > Package code and artifacts**. Optionally, provide a **Zip file name**. To apply the changes, click **OK**.
- 2 Build the model. At the end of the build process, the code generator outputs the zip file. The folder structure in the zip file is hierarchical.

### Configure packNGo for Simulink from the Command Line

If you configure zip file packaging with set\_param, the code generator uses packNGo to output a zip file during the build process.

Use set\_param to configure zip file packaging for model zingbit in the file zingbit.zip.

```
set_param('zingbit','PostCodeGenCommand', ...
 'packNGo(buildInfo);');
```

## Input Arguments

### buildInfo — Object that provides build information

buildInfo object

During the build process, the code generator places buildInfo.mat in the code generation folder. This MAT-file contains the buildInfo object. The object provides information that packNGo uses to produce the zip file.

### Name-Value Pair Arguments

Specify optional comma-separated pairs of Name, Value arguments. Name is the argument name and Value is the corresponding value. Name must appear inside quotes. You can specify several name and value pair arguments in any order as Name1, Value1, ..., NameN, ValueN.

Example: 'packType', 'flat', 'nestedZipFiles', true

### packType — Determines whether the primary zip file contains secondary zip files or folders

'flat' (default) | 'hierarchical'

If 'flat', package the generated code files in a zip file as a single, flat folder.

If 'hierarchical', package the generated code files hierarchically in a primary zip file. The hierarchy contains top model, referenced model, and shared utility folders. The function also packages the corresponding buildInfo.mat files for the folders.

Example: 'packType', 'flat'

**nestedZipFiles — Determines whether the paths for files in the secondary zip files are relative to the root folder of the primary zip file**

true (default) | false

If true, create a primary zip file that contains three secondary zip files:

- `mlrFiles.zip` — Files in your *matlabroot* folder tree
- `sDirFiles.zip` — Files in and under your code generation folder
- `otherFiles.zip` — Required files not in the *matlabroot* or *start* folder trees

If false, create a primary zip file that contains folders, for example, your code generation folder and *matlabroot*.

Example: 'nestedZipFiles', true

**fileName — Specifies a file name for the primary zip file**

'modelOrFunctionName.zip' (default) | 'myName'

If you do not specify the 'fileName'-value pair, the function packages the files in a zip file named *modelOrFunctionName.zip* and places the zip file in the code generation folder.

If you specify 'fileName' with the value, 'myName', the function creates *myName.zip* in the code generation folder.

To specify another location for the primary zip file, provide the absolute path to the location, *fullPath/myName.zip*

Example: 'fileName', '/home/user/myModel.zip'

**minimalHeaders — Selects whether to include only the minimal header files**

true (default) | false

If true, include only the minimal header files required to build the code in the zip file.

If false, include header files found on the include path in the zip file.

Example: 'minimalHeaders', true

**includeReport — Selects whether to include the html folder for your code generation report**

false (default) | true

If false, do not include the html folder in the zip file.

If true, include the html folder in the zip file.

Example: 'includeReport', false

**ignoreParseError — Instruct packNGo not to terminate on parse errors**

false (default) | true

If false, terminate on parse errors.

If true, do not terminate on parse errors.

Example: `'ignoreParseError',false`

### **ignoreFileMissing** — Instruct packNGo not to terminate if files are missing

false (default) | true

If `false`, terminate on missing file errors.

If `true`, do not terminate on missing files errors.

Example: `'ignoreFileMissing',false`

## **Limitations**

- The function operates on source files only, such as `*.c`, `*.cpp`, and `*.h` files. The function does not support compile flags, defines, or makefiles.
- The function does not package source files for reusable library subsystems.
- Unnecessary files might be included. The function might find additional files from source paths and include paths recorded in the build information, even if those files are not used.

## **See Also**

**Introduced in R2006b**

# rtiostreamtest

Test custom `rtiostream` interface implementation

## Syntax

```
rtiostreamtest(connection, parameterOne, parameterTwo, verbosityFlag)
rtiostreamtest('tcp', host, port)
rtiostreamtest('serial', port, baud)
```

## Description

`rtiostreamtest(connection, parameterOne, parameterTwo, verbosityFlag)` runs a test suite to verify your custom `rtiostream` interface implementation.

`rtiostreamtest('tcp', host, port)`, via TCP/IP communication, connects MATLAB to the target hardware using the specified host and port.

`rtiostreamtest('serial', port, baud)`, via serial communication, connects MATLAB to the target hardware using the specified port and baud value.

During initialization, the function uses basic `rtiostream` I/O. The function determines:

- Byte ordering of data on the target hardware.
- Granularity of memory address.
- Size of data types.
- Whether `rtIOStreamRecv` blocks, that is, when there is no data whether `rtIOStreamRecv` waits for data or returns immediately with `size received == 0`.
- The size (`BUFFER_SIZE`) of its internal buffer for receiving or transmitting data through `rtiostream`. The default is 128 bytes.

In Test 1 (fixed size data exchange), the function:

- Checks data can be sent and received correctly in different chunk sizes. The chunk sizes for your development computer and target hardware are *symmetric*.
- Sends data as a known sequence that it can validate.
- Performs “host-to-target” tests. Your development computer sends data and your target hardware receives data in successive chunks of 1, 4, and 128 bytes.
- Performs “target-to-host” tests. Your target hardware sends data and your development computer receives data in successive chunks of 1, 4, and 128 bytes.

In Test 2 (varying size data exchange), the function:

- Checks that data can be sent and received correctly in different chunk sizes. The chunk sizes for your development computer and target hardware are *asymmetric*.
- Sends data as a known sequence that it can validate.
- Performs “host-to-target” tests:

- Your development computer sends data in chunks of 128 bytes and your target hardware receives data in chunks of 64 bytes.
- Your development computer sends data in chunks of 64 bytes and your target hardware receives data in chunks of 128 bytes.
- Performs “target-to-host” tests:
  - Your target hardware sends data in chunks of 64 bytes and your development computer receives data in chunks of 128 bytes.
  - Your target hardware sends data in chunks of 128 bytes and your development computer receives data in chunks of 64 bytes.

In Test 3 (receive buffer detection), the function determines the data that it can store in between calls to `rtIOStreamRecv` on the target hardware. The function uses an iterative process:

- 1 The development computer transmits a data sequence while the target hardware sleeps. `rtIOStreamRecv` is not called while the target hardware sleeps.
- 2 When the target hardware wakes up, it calls `rtIOStreamRecv` to receive data from the internal buffer of the driver.
- 3 The function determines whether the internal buffer overflowed by checking for errors and checking the received data values.
- 4 If there are no overflow errors and the transmitted data is received correctly, the function starts another iteration, performing step 1 with a larger data sequence.

The function reports the size of the last known good buffer.

## Examples

### Verify Behavior of Custom `rtiostream` Interface Implementation

The test suite consists of two parts. One part of the test suite is an application that runs on the target hardware. The other part runs in MATLAB.

- 1 To create the target application, compile and link these files:
  - `rtiostreamtest.c`
  - `rtiostreamtest.h`
  - `rtiostream.h`
  - The `rtiostream` implementation under investigation, for example, `rtiostream_tcpip.c`.
  - `main.c`

`rtiostreamtest.c`, `rtiostreamtest.h`, and `main.c` are located in `matlabroot/toolbox/coder/rtiostream/src/rtiostreamtest`.

- 2 Download and run the application on your target hardware.
- 3 To run the MATLAB part of the test suite, invoke the `rtiostreamtest` function. For example:

```
rtiostreamtest('tcp', 'myProcessor', '2345')
```

The function produces an output like this:

```
Test suite for rtiostream ###
Initializing connection with target...
```


```
Hardware characteristics discovered
Size of char : 8 bit
Size of short : 16 bit
Size of int : 32 bit
Size of long : 32 bit
Size of float : 32 bit
Size of double : 64 bit
Size of pointer: 64 bit
Byte ordering : Little Endian

rtiostream characteristics discovered
Round trip time : 0.25098 ms
rtIOStreamRecv behavior : non-blocking

Test results
Test 1 (fixed size data exchange): PASS
Test 2 (varying size data exchange): PASS

Test suite for rtiostream finished successfully
```

The function also generates the average bandwidth profile.



## Input Arguments

**connection** — Transport protocol

'tcp' | 'serial'

Specify transport protocol for communication channel:

- 'tcp' -- TCP/IP
- 'serial' -- RS-232 serial

**parameterOne — Host name or COM port**

character vector | string scalar

If connection is 'tcp', specify name of target processor. For example, if your development computer is the target processor, you can specify 'localhost'.

If connection is 'serial', specify serial port ID, for example, 'COM1' for COM1, 'COM2' for COM2, and so on.

**parameterTwo — Port number or baud value**

integer

If connection is 'tcp', specify port number of TCP/IP server, an integer value between 256 and 65535.

If connection is 'serial', specify baud value, for example, 9600.

**verbosityFlag — Verbosity**

'' (default) | 'verbose'

If you specify 'verbose', the function displays messages that contain progress information. You can use the messages to debug runtime failures.

**See Also****Topics**

“Customize XCP Slave Software”

**Introduced in R2013a**

# rsimgetrtp

Global model parameter structure

## Syntax

```
parameter_structure = rsimgetrtp('model')
```

## Description

`parameter_structure = rsimgetrtp('model')` forces a block update diagram action for *model*, a model for which you are running rapid simulations, and returns the global parameter structure for that model. The function includes tunable parameter information in the parameter structure.

The model parameter structure contains the following fields:

| Field                      | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
|----------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <code>modelChecksum</code> | A four-element vector that encodes the structure. The code generator uses the <i>checksum</i> to check whether the structure has changed since the RSim executable was generated. If you delete or add a block, and then generate a new version of the structure, the new <i>checksum</i> will not match the original <i>checksum</i> . The RSim executable detects this incompatibility in model parameter structures and exits to avoid returning incorrect simulation results. If the structure changes, you must regenerate code for the model. |
| <code>parameters</code>    | A structure that defines model global parameters.                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |

The `parameters` substructure includes the following fields:

| Field                        | Description                                                       |
|------------------------------|-------------------------------------------------------------------|
| <code>dataTypeName</code>    | Name of the parameter data type, for example, <code>double</code> |
| <code>dataTypeID</code>      | An internal data type identifier                                  |
| <code>complex</code>         | Value 1 if parameter values are complex and 0 if real             |
| <code>dtTransIdx</code>      | Internal use only                                                 |
| <code>values</code>          | Vector of parameter values                                        |
| <code>structParamInfo</code> | Information about structure and bus parameters in the model       |

The `structParamInfo` substructure contains these fields:

| Field                   | Description                                                                |
|-------------------------|----------------------------------------------------------------------------|
| <code>Identifier</code> | Name of the parameter                                                      |
| <code>ModelParam</code> | Value 1 if parameter is a model parameter and 0 if it is a block parameter |

| Field     | Description                                                                 |
|-----------|-----------------------------------------------------------------------------|
| BlockPath | Block path for a block parameter. This field is empty for model parameters. |
| CAPIDx    | Internal use only                                                           |

Do not modify fields in `structParamInfo`.

The function also includes an array of substructures `map` that represents tunable parameter information with these fields:

| Field         | Description                            |
|---------------|----------------------------------------|
| Identifier    | Parameter name                         |
| ValueIndicies | Vector of indices to parameter values  |
| Dimensions    | Vector indicating parameter dimensions |

## Examples

Return global parameter structure for model `rtwdemo_rsimtf` to `param_struct`:

```
rtwdemo_rsimtf
param_struct = rsimgetrtp('rtwdemo_rsimtf')

param_struct =

 modelChecksum: [1.7165e+009 3.0726e+009 2.6061e+009
2.3064e+009]
 parameters: [1x1 struct]
```

## See Also

`rsimsetrtpparam`

## Topics

“Create a MAT-File That Includes a Model Parameter Structure”  
 “Update Diagram and Run Simulation” (Simulink)  
 “Default parameter behavior” on page 16-9  
 “Block Authoring and Simulation Integration” (Simulink)  
 “Tune Parameters”

**Introduced in R2006a**

# rsimsetrtpparam

Set parameters of rtP model parameter structure

## Syntax

```
rtP = rsimsetrtpparam(rtP,idx)
rtP = rsimsetrtpparam(rtP,'paramName',paramValue)
rtP = rsimsetrtpparam(rtP,idx,'paramName',paramValue)
```

## Description

`rtP = rsimsetrtpparam(rtP,idx)` expands the `rtP` structure to have `idx` sets of parameters. The `rsimsetrtpparam` utility defines the values of an existing `rtP` parameter structure. The `rtP` structure matches the format of the structure returned by `rsimgetrtp('modelName')`.

`rtP = rsimsetrtpparam(rtP,'paramName',paramValue)` takes an `rtP` structure with tunable parameter information and sets the values associated with `'paramName'` to be `paramValue` if possible. There can be more than one name-value pair.

`rtP = rsimsetrtpparam(rtP,idx,'paramName',paramValue)` takes an `rtP` structure with tunable parameter information and sets the values associated with `'paramName'` to be `paramValue` in the `nth` `idx` parameter set. There can be more than one name-value pair. If the `rtP` structure does not have `idx` parameter sets, the first set is copied and appended until there are `idx` parameter sets. Subsequently, the `nth` `idxset` is changed.

## Examples

### Expand Parameter Sets

Expand the number of parameter sets in the `rtp` structure to 10.

```
rtp = rsimsetrtpparam(rtp,10);
```

### Add Parameter Sets

Add three parameter sets to the parameter structure `rtp`.

```
rtp = rsimsetrtpparam(rtp,idx,'X1',iX1,'X2',iX2,'Num',iNum);
```

## Input Arguments

**rtP** — A parameter structure that contains the sets of parameter names and their respective values

parameter structure

**idx** — An index used to indicate the number of parameter sets in the `rtP` structure

index of parameter sets

**paramValue** — The value of the `rtP` parameter `paramName`

value of `paramName`

**paramName** — The name of the parameter set to add to the rtP structure  
name of the parameter set

## Output Arguments

**rtP** — An expanded rtP parameter structure that contains **idx** additional parameter sets defined by the **rsimsetrtpparam** function call  
expanded rtP parameter structure

## See Also

`rsimgetrtP`

## Topics

“Create a MAT-File That Includes a Model Parameter Structure”  
“Update Diagram and Run Simulation” (Simulink)  
“Default parameter behavior” on page 16-9  
“Block Authoring and Simulation Integration” (Simulink)  
“Tune Parameters”

**Introduced in R2009b**

# rtw\_precompile\_libs

Rebuild precompiled libraries within model without building model

## Syntax

```
rtw_precompile_libs(model,build_spec)
```

## Description

`rtw_precompile_libs(model,build_spec)` builds libraries within *model*, according to the *build\_spec* field values, and places the libraries in a precompiled folder. Model builds that use the template makefile approach support the `rtw_precompile_libs` function. Toolchain approach model builds do not support the `rtw_precompile_libs` function.

## Examples

### Precompile Libraries for Model

Build the libraries in *my\_model* without building *my\_model*.

```
% Specify the library suffix
if isunix
 suffix = '_std.a';
elseif ismac
 suffix = '_std.a';
else
 suffix = '_vcx64.lib';
end
open_system(my_model);
set_param(my_model, 'TargetLibSuffix',suffix);

% Set the precompiled library folder
set_param(my_model, 'TargetPreCompLibLocation',fullfile(pwd,'lib'));

% Define a build specification that specifies
% the location of the files to compile.
my_build_spec = [];
my_build_spec.rtwmakecfgDirs = {fullfile(pwd,'src')};

% Build the libraries in 'my_model'
rtw_precompile_libs(my_model,my_build_spec);
```

## Input Arguments

**model** — Model object or name for which to build libraries

*object* | 'modelName'

Name of the model containing the libraries that you want to build.

**build\_spec — Structure with field values that provides the build specification**

struct

Structure with fields that define a build specification. Fields except `rtwmakecfgDirs` are optional.

**Field Values in build\_spec**

Specify the structure field values of the `build_spec`.

```
Example: build_spec.rtwmakecfgDirs = {fullfile(pwd, 'src')};
```

**rtwmakecfgDirs — Fully qualified paths to the folders containing rtwmakecfg files for libraries to precompile**

array of paths

Uses the `Name` and `Location` elements of `makeInfo.library`, as returned by the `rtwmakecfg` function, to specify name and location of precompiled libraries. If you use the `TargetPreCompLibLocation` parameter to specify the library folder, it overrides the `makeInfo.library.Location` setting.

The specified model must contain S-function blocks that use precompiled libraries, which the `rtwmakecfg` files specify. The makefile that the build approach generates contains the library rules only if the conversion requires the libraries.

```
Example: build_spec.rtwmakecfgDirs = {fullfile(pwd, 'src')};
```

**libSuffix — Suffix, including the file type extension, to append to the name of each library (for example, `_std.a` or `_vcx64.lib`)**

character vector

The suffix must include a period (`.`). Set the suffix by using either this field or the `TargetLibSuffix` parameter. If you specify a suffix with both mechanisms, the `TargetLibSuffix` setting overrides the setting of this field.

```
Example: build_spec.libSuffix = '_vcx64.lib';
```

**intOnlyBuild — Selects library optimization**

'false' (default) | 'true'

When set to `true`, indicates that the function optimizes the libraries so that they compile from integer code only. Applies to ERT-based targets only.

```
Example: build_spec.intOnlyBuild = 'false';
```

**makeOpts — Specifies an option for rtwMake**

character vector

Specifies an option to include in the `rtwMake` command line.

```
Example: build_spec.makeOpts = '';
```

**addLibs — Specifies libraries to build**

cell array of structures

This cell array of structures specifies the libraries to build that an `rtwmakecfg` function does not specify. Define each structure with two fields that are character arrays:

- `libName` — Name of the library without a suffix
- `libLoc` — Location for the precompiled library

The build approach (toolchain approach or template makefile approach) lets you specify other libraries and how to build them. Use this field if you must precompile libraries.

Example: `build_spec.addLibs = 'libs_list';`

## See Also

### Topics

“Precompile S-Function Libraries”

“Recompile Precompiled Libraries”

“Choose Build Approach and Configure Build Process”

“Use `rtwmakecfg.m` API to Customize Generated Makefiles”

**Introduced in R2009b**

## rtwbuild

Build generated code from a model

### Syntax

```
rtwbuild(model)
rtwbuild(model,Name,Value)

rtwbuild(subsystem)

rtwbuild(subsystem,'Mode','ExportFunctionCalls')
blockHandle = rtwbuild(subsystem,'Mode','ExportFunctionCalls')
```

### Description

`rtwbuild(model)` generates code from `model` based on current model configuration parameter settings. If `model` is not already loaded into the MATLAB environment, `rtwbuild` loads it before generating code.

If you clear the **Generate code only** model configuration parameter, the function generates code and builds an executable image.

To reduce code generation time, when rebuilding a model, `rtwbuild` provides incremental model build. The code generator rebuilds a model or submodels only when they have changed since the most recent model build. To force a top-model build, see the `'ForceTopModelBuild'` argument.

`rtwbuild(model,Name,Value)` uses additional options specified by one or more `Name,Value` pair arguments.

`rtwbuild(subsystem)` generates code from `subsystem` based on current model configuration parameter settings. Before initiating the build, open (or load) the parent model.

If you clear the **Generate code only** model configuration parameter, the function generates code and builds an executable image.

`rtwbuild(subsystem,'Mode','ExportFunctionCalls')` generates code from `subsystem` that includes function calls that you can export to external application code if you have Embedded Coder.

`blockHandle = rtwbuild(subsystem,'Mode','ExportFunctionCalls')` returns the handle to a SIL block created for code generated from the specified subsystem if the **Create block** configuration parameter is set to SIL and if you have Embedded Coder. You can then use the SIL block for numerical equivalence testing.

### Examples

#### Generate Code and Build Executable Image for Model

Generate C code for model `rtwdemo_rtwintr0`.

```
rtwbuild('rtwdemo_rtwintr0')
```

For the GRT system target file, the code generator produces the following code files and places them in folders `rtwdemo_rtwintr_grt_rtw` and `slprj/grt/_sharedutils`.

| Model Files                            | Shared Files                        | Interface Files        | Other Files               |
|----------------------------------------|-------------------------------------|------------------------|---------------------------|
| <code>rtwdemo_rtwintr.c</code>         | <code>rtGetInf.c</code>             | <code>rtmodel.h</code> | <code>rt_logging.c</code> |
| <code>rtwdemo_rtwintr.h</code>         | <code>rtGetInf.h</code>             |                        |                           |
| <code>rtwdemo_rtwintr_private.h</code> | <code>rtGetNaN.c</code>             |                        |                           |
| <code>rtwdemo_rtwintrtypes.h</code>    | <code>rtGetNaN.h</code>             |                        |                           |
|                                        | <code>rt_nonfinite.c</code>         |                        |                           |
|                                        | <code>rt_nonfinite.h</code>         |                        |                           |
|                                        | <code>rtwtypes.h</code>             |                        |                           |
|                                        | <code>multiword_types.h</code>      |                        |                           |
|                                        | <code>builtin_typeid_types.h</code> |                        |                           |

If the following model configuration parameters settings apply, the code generator produces additional results.

| Parameter Setting                                                                 | Results                                                                                                                                                                                   |
|-----------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Code Generation &gt; Generate code only</b> is cleared                         | Executable image <code>rtwdemo_rtwintr.exe</code>                                                                                                                                         |
| <b>Code Generation &gt; Report &gt; Create code generation report</b> is selected | Report that provides information and links to generated code files, subsystem and code interface reports, entry-point functions, inports, outports, interface parameters, and data stores |

### Force Top Model Build

Generate code and build an executable image for `rtwdemo_mdltreftop`, which refers to model `rtwdemo_mdltreftop`, regardless of model checksums and parameter settings.

```
rtwbuild('rtwdemo_mdltreftop', ...
 'ForceTopModelBuild', true)
```

### Display Error Messages in Diagnostic Viewer

Introduce an error to model `rtwdemo_mdltreftop` and save the model as `rtwdemo_mdltreftop_witherr`. Display build error messages in the Diagnostic Viewer and in the Command Window while generating code and building an executable image for model `rtwdemo_mdltreftop_witherr`.

```
rtwbuild('rtwdemo_mdleftop_witherr', ...
 'OkayToPushNags',true)
```

### Generate Code and Build Executable Image for Subsystem

Generate C code for subsystem Amplifier in model rtwdemo\_rtwintr.

```
rtwbuild('rtwdemo_rtwintr/Amplifier')
```

For the GRT target, the code generator produces the following code files and places them in folders Amplifier\_grt\_rtw and slprj/grt/\_sharedutils.

| Model Files         | Shared Files           | Interface Files | Other Files  |
|---------------------|------------------------|-----------------|--------------|
| Amplifier.c         | rtGetInf.c             | rtmodel.h       | rt_logging.c |
| Amplifier.h         | rtGetInf.h             |                 |              |
| Amplifier_private.h | rtGetNaN.c             |                 |              |
| Amplifier_types.h   | rtGetNaN.h             |                 |              |
|                     | rt_nonfinite.c         |                 |              |
|                     | rt_nonfinite.h         |                 |              |
|                     | rtwtypes.h             |                 |              |
|                     | multiword_types.h      |                 |              |
|                     | builtin_typeid_types.h |                 |              |

If you apply the parameter settings listed in the table, the code generator produces the results listed.

| Parameter Setting                                                                 | Results                                                                                                                                                                                   |
|-----------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Code Generation &gt; Generate code only</b> is cleared                         | Executable image Amplifier.exe                                                                                                                                                            |
| <b>Code Generation &gt; Report &gt; Create code generation report</b> is selected | Report that provides information and links to generated code files, subsystem and code interface reports, entry-point functions, inports, outports, interface parameters, and data stores |

### Build Subsystem for Exporting Code to External Application

To export the image to external application code, build an executable image from a function-call subsystem.

```
rtwdemo_exporting_functions
rtwbuild('rtwdemo_exporting_functions/rtwdemo_subsystem', 'Mode', 'ExportFunctionCalls')
```

The executable image rtwdemo\_subsystem.exe appears in your working folder.

## Create SIL Block for Verification

From a function-call subsystem, create a SIL block that you can use to test the code generated from a model.

Open subsystem `rtwdemo_subsystem` in model `rtwdemo_exporting_functions` and set the **Create block** model configuration parameter to SIL.

Create the SIL block.

```
mysilblockhandle = rtwbuild('rtwdemo_exporting_functions/rtwdemo_subsystem',...
 'Mode','ExportFunctionCalls')
```

The code generator produces a SIL block for the generated subsystem code. You can add the block to an environment or test harness model that supplies test vectors or stimulus input. You can then run simulations that perform SIL tests and verify that the generated code in the SIL block produces the same result as the original subsystem.

## Name Exported Initialization Function

Name the initialization function generated when building an executable image from a function-call subsystem.

```
rtwdemo_exporting_functions
rtwbuild('rtwdemo_exporting_functions/rtwdemo_subsystem',...
 'Mode','ExportFunctionCalls','ExportFunctionInitializeFunctionName','subsysinit')
```

The initialization function name `subsysinit` appears in `rtwdemo_subsystem_ert_rtw/ert_main.c`.

## Display Status Information in Build Status Window

Display build information in the Build Status window while generating code and running a parallel build of model `rtwdemo_mdltreftop_witherr`.

```
rtwbuild('rtwdemo_mdltreftop_witherr', ...
 'OpenBuildStatusAutomatically',true)
```

## Input Arguments

### **model** — Model object or name for which to generate code or build an executable image

*object* | 'modelName'

Model for which to generate code or build an executable image, specified as an object or a character vector representing the model name.

Example: 'rtwdemo\_exporting\_functions'

### **subsystem** — Subsystem name for which to generate code or build executable image

'subsystemName'

Subsystem for which to generate code or build an executable image, specified as a character vector representing the subsystem name or the full block path.

Example: 'rtwdemo\_exporting\_functions/rtwdemo\_subsystem'

### Name-Value Pair Arguments

Specify optional comma-separated pairs of `Name`, `Value` arguments. `Name` is the argument name and `Value` is the corresponding value. `Name` must appear inside quotes. You can specify several name and value pair arguments in any order as `Name1, Value1, ..., NameN, ValueN`.

Example: `rtwbuild('rtwdemo_mdltreftop', 'ForceTopModelBuild', true)`

#### ForceTopModelBuild — Force regeneration of top model code

`false` (default) | `true`

Force regeneration of top model code, specified as `true` or `false`.

| Action                                                                                                                    | Specify            |
|---------------------------------------------------------------------------------------------------------------------------|--------------------|
| Force the code generator to regenerate code for the top model of a system that includes referenced models                 | <code>true</code>  |
| Specify that the code generator determine whether to regenerate top model code based on model and model parameter changes | <code>false</code> |

Consider forcing regeneration of code for a top model if you change items associated with external or custom code, such as code for a custom target. For example, set `ForceTopModelBuild` to `true` if you change:

- TLC code
- S-function source code, including `rtwmakecfg.m` files
- Integrated custom code

Alternatively, you can force regeneration of top model code by deleting folders in the code generation folder (Simulink), such as `s_lprj` or the generated model code folder.

#### OkayToPushNags — Display build error messages in Diagnostic Viewer

`false` (default) | `true`

Display error messages from the build in Diagnostic Viewer, specified as `true` or `false`.

| Action                                                                          | Specify            |
|---------------------------------------------------------------------------------|--------------------|
| Display build error messages in the Diagnostic Viewer and in the Command Window | <code>true</code>  |
| Display build error messages in the Command Window only                         | <code>false</code> |

#### generateCodeOnly — Generate code only

`false` | `true`

If you do not specify a value, the **Generate code only** (`GenCodeOnly`) option on the **Code Generation** pane controls build process behavior.

If you specify a value, the argument overrides the **Generate code only** (`GenCodeOnly`) option on the **Code Generation** pane.

| Action              | Specify           |
|---------------------|-------------------|
| Generate code only. | <code>true</code> |

| Action                                   | Specify |
|------------------------------------------|---------|
| Generate code and build executable file. | false   |

### Mode — (for subsystem builds only) Direct code generator to export function calls

'ExportFunctionCalls' (default)

If you have Embedded Coder, generates code from subsystem that includes function calls that you can export to external application code.

### ExportFunctionInitializeFunctionName — Function name

character vector

Name the exported initialization function for specified subsystem.

Example:

```
rtwbuild(subsystem, 'Mode', 'ExportFunctionCalls', 'ExportFunctionInitializeFunctionName', fcname)
```

### OpenBuildStatusAutomatically — Display build information in the Build Status window

false (default) | true

Display build information in the Build Status window, specified as true or false. For more information about using the Build Status window, see “Monitor Parallel Building of Referenced Models”.

The Build Status window supports parallel builds of referenced model hierarchies. Do not use the Build Status window for serial builds.

| Action                                               | Specify |
|------------------------------------------------------|---------|
| Display build information in the Build Status window | true    |
| No action                                            | false   |

### ObfuscateCode — Generate obfuscated C code

false (default) | true

Specify whether to generate obfuscated C code, specified as true or false.

| Action                                                                                                                          | Specify |
|---------------------------------------------------------------------------------------------------------------------------------|---------|
| Generate obfuscated C code that you can share with third parties with reduced likelihood of compromising intellectual property. | true    |
| No action.                                                                                                                      | false   |

## Output Arguments

### blockHandle — Handle to SIL block created for generated subsystem code

handle

Handle to SIL block created for generated subsystem code. Returned only if both of the following conditions apply:

- You are licensed to use Embedded Coder software.

- **Create block** model configuration parameter is set to SIL.

## Tips

You can initiate code generation and the build process by:

- Pressing **Ctrl+B**.
- Selecting **Code > C/C++ Code > Build Model**.
- Invoking the `slbuild` command from the MATLAB command line.

## Extended Capabilities

### Automatic Parallel Support

Accelerate code by automatically running computation in parallel using Parallel Computing Toolbox™.

To build referenced models in parallel, in the top model, select the configuration parameter check box **Enable parallel model reference builds**. For more information, see “Reduce Build Time for Referenced Models by Using Parallel Builds”.

In Parallel Computing Toolbox™ commands, for example, a `parfor` or `spmd` loop, do not invoke `rtwbuild`, `rtwrebuild`, or `slbuild` commands that build models that are configured for parallel builds.

## See Also

`coder.buildstatus.close` | `coder.buildstatus.open` | `rtwrebuild` | `slbuild`

### Topics

“Build and Run a Program”

“Choose Build Approach and Configure Build Process”

“Control Regeneration of Top Model Code”

“Generate Component Source Code for Export to External Code Base” (Embedded Coder)

“Software-in-the-Loop Simulation” (Embedded Coder)

### Introduced in R2009a

# RTW.BuildInfo

Provide information for compiling and linking generated code

## Description

An `RTW.BuildInfo` object contains information for compiling and linking generated code.

## Creation

### Syntax

```
buildInformation = RTW.BuildInfo
```

### Description

`buildInformation = RTW.BuildInfo` returns a build information object. You can use the object to specify information for compiling and linking generated code. For example:

- Compiler options
- Preprocessor identifier definitions
- Linker options
- Source files and paths
- Include files and paths
- Precompiled external libraries

## Object Functions

|                               |                                                                 |
|-------------------------------|-----------------------------------------------------------------|
| <code>addCompileFlags</code>  | Add compiler options to model build information                 |
| <code>addDefines</code>       | Add preprocessor macro definitions to model build information   |
| <code>addIncludeFiles</code>  | Add include files to model build information                    |
| <code>addIncludePaths</code>  | Add include paths to model build information                    |
| <code>addLinkFlags</code>     | Add link options to model build information                     |
| <code>addLinkObjects</code>   | Add link objects to model build information                     |
| <code>addNonBuildFiles</code> | Add nonbuild-related files to model build information           |
| <code>addSourceFiles</code>   | Add source files to model build information                     |
| <code>addSourcePaths</code>   | Add source paths to model build information                     |
| <code>addTMFTokens</code>     | Add template makefile (TMF) tokens to model build information   |
| <code>findBuildArg</code>     | Find a specific build argument in model build information       |
| <code>findIncludeFiles</code> | Find and add include (header) files to model build information  |
| <code>getBuildArgs</code>     | Get build arguments from model build information                |
| <code>getCompileFlags</code>  | Get compiler options from model build information               |
| <code>getDefines</code>       | Get preprocessor macro definitions from model build information |
| <code>getFullFileList</code>  | Get list of files from model build information                  |
| <code>getIncludeFiles</code>  | Get include files from model build information                  |
| <code>getIncludePaths</code>  | Get include paths from model build information                  |

|                              |                                                                                                          |
|------------------------------|----------------------------------------------------------------------------------------------------------|
| getLinkFlags                 | Get link options from model build information                                                            |
| getNonBuildFiles             | Get nonbuild-related files from model build information                                                  |
| getSourceFiles               | Get source files from model build information                                                            |
| getSourcePaths               | Get source paths from model build information                                                            |
| setTargetProvidesMain        | Disable inclusion of code generator provided (generated or static) main.c source file during model build |
| updateFilePathsAndExtensions | Update files in model build information with missing paths and file extensions                           |
| updateFileSeparator          | Update file separator character for file lists in model build information                                |

## Examples

### Retrieve Build Information Object

When you build generated code, the build process stores an `RTW.BuildInfo` object in the `buildInfo.mat` file. To retrieve the object, from the code generation folder that contains the `buildInfo.mat` file, run:

```
bi=load('buildInfo.mat');
bi.buildInfo
```

The object contains build information. For example:

```
ans =
```

```
BuildInfo with properties:
```

```

 ModelHandle: 1.2207e-04
 ModelName: 'myAircraftExample'
 Viewer: []
 Tokens: [29x1 RTW.BuildInfoKeyValuePair]
 BuildArgs: [14x1 RTW.BuildInfoKeyValuePair]
 MakeVars: []
 MakeArgs: ''
TargetPreCompLibLoc: ''
 TargetLibSuffix: ''
InstallDirmexopts: ''
 TemplateMakefile: ''
 LinkObj: [1x1 RTW.BuildInfoLinkObj]
 ModelRefs: []
 SysLib: [1x1 RTW.BuildInfoModules]
ReportInfo: [1x1 rtw.report.ReportInfo]
 Maps: [1x1 struct]
BuildTools: [1x1 coder.internal.BuildTools]
 Options: [1x1 RTW.BuildInfoOptions]
 Inc: [1x1 RTW.BuildInfoModules]
 Src: [1x1 RTW.BuildInfoModules]
 Other: [1x1 RTW.BuildInfoModules]
 Path: []
 Settings: [1x1 RTW.BuildInfoSettings]
DisplayLabel: 'Build Info'
 Group: ''

```

## **See Also**

### **Topics**

“Customize Post-Code-Generation Build Processing”

**Introduced in R2006a**

## RTW.getBuildDir

Get build folder information from model build information

### Syntax

```
RTW.getBuildDir(model)
folderStruct = RTW.getBuildDir(model)
```

### Description

RTW.getBuildDir(model) displays build folder information for model.

If the model is closed, the function opens and then closes the model, leaving it in its original state. If the model is large and closed, the RTW.getBuildDir function can take longer to execute.

folderStruct = RTW.getBuildDir(model) returns a structure containing build folder information.

You can use this function in automated scripts to determine the build folder in which the generated code for a model is placed.

This function can return build folder information for protected models.

### Examples

#### Display Build Folder Information

Display build folder information for the model 'sldemo\_fuelsys'.

```
>> RTW.getBuildDir('sldemo_fuelsys')
```

```
ans =
```

```
BuildDirectory: 'C:\work\modelref\sldemo_fuelsys_ert_rtw'
CacheFolder: 'C:\work\modelref'
CodeGenFolder: 'C:\work\modelref'
RelativeBuildDir: 'sldemo_fuelsys_ert_rtw'
BuildDirSuffix: '_ert_rtw'
ModelRefRelativeRootSimDir: 'slprj\sim'
ModelRefRelativeRootTgtDir: 'slprj\ert'
ModelRefRelativeBuildDir: 'slprj\ert\sldemo_fuelsys'
ModelRefRelativeSimDir: 'slprj\sim\sldemo_fuelsys'
ModelRefRelativeHdlDir: 'slprj\hdl\sldemo_fuelsys'
ModelRefDirSuffix: ''
SharedUtilsSimDir: 'slprj\sim_sharedutils'
SharedUtilsTgtDir: 'slprj\ert_sharedutils'
```

## Get Build Folder Information

Return a structure `my_folderStruct` that contains build folder information for the model 'MyModel'.

```
>> my_folderStruct = RTW.getBuildDir('MyModel')
```

```
my_folderStruct =
```

```
 BuildDirectory: 'H:\MyModel_ert_rtw'
 CacheFolder: 'H:\'
 CodeGenFolder: 'H:\'
 RelativeBuildDir: 'MyModel_ert_rtw'
 BuildDirSuffix: '_ert_rtw'
 ModelRefRelativeRootSimDir: 'slprj\sim'
 ModelRefRelativeRootTgtDir: 'slprj\ert'
 ModelRefRelativeBuildDir: 'slprj\ert\MyModel'
 ModelRefRelativeSimDir: 'slprj\sim\MyModel'
 ModelRefRelativeHdlDir: 'slprj\hdl\MyModel'
 ModelRefDirSuffix: ''
 SharedUtilsSimDir: 'slprj\sim_sharedutils'
 SharedUtilsTgtDir: 'slprj\ert_sharedutils'
```

## Input Arguments

**model** — Model object or name for which to get the build folders

*object* | 'modelName'

Model for which to get the build folder, specified as an object or a character vector representing the model name.

Example: 'sldemo\_fuelsys'

## Output Arguments

**folderStruct** — Structure with field values that provide build folder information

struct

Structure with fields that provides build folder information.

Example: folderstruct = RTW.getBuildDir('MyModel')

**BuildDirectory** — Character vector specifying fully qualified path to build folder for model

character vector

**CacheFolder** — Character vector specifying root folder in which to place model build artifacts used for simulation

character vector

**CodeGenFolder** — Character vector specifying root folder in which to place code generation files

character vector

**RelativeBuildDir** — Character vector specifying build folder relative to the current working folder (pwd)

character vector

**BuildDirSuffix** — Character vector specifying suffix appended to model name to create build folder

character vector

**ModelRefRelativeRootSimDir** — Character vector specifying the relative root folder for the model reference target simulation folder

character vector

**ModelRefRelativeRootTgtDir** — Character vector specifying the relative root folder for the model reference target build folder

character vector

**ModelRefRelativeBuildDir** — Character vector specifying model reference target build folder relative to current working folder (pwd)

character vector

**ModelRefRelativeSimDir** — Character vector specifying model reference target simulation folder relative to current working folder (pwd)

character vector

**ModelRefRelativeHdlDir** — Character vector specifying model reference target HDL folder relative to current working folder (pwd)

character vector

**ModelRefDirSuffix** — Character vector specifying suffix appended to system target file name to create model reference build folder

character vector

**SharedUtilsSimDir** — Character vector specifying the shared utility folder for simulation

character vector

**SharedUtilsTgtDir** — Character vector specifying the shared utility folder for code generation

character vector

## See Also

rtwbuild

## Topics

“Working Folder”

“Manage Build Process Folders”

**Introduced in R2008b**

# rtwrebuild

Rebuild generated code from model

## Syntax

```
rtwrebuild()
```

```
rtwrebuild(model)
```

```
rtwrebuild(path)
```

## Description

`rtwrebuild()` assumes that the current working folder is the build folder of the model (not the model location) and invokes the makefile in the build folder. If the current working folder is not the build folder, the function exits with an error.

`rtwrebuild` invokes the makefile generated during the previous build to recompile files you modified since that build. Operation of this function depends on the current working folder, not the current loaded model. If your model includes referenced models, `rtwrebuild` invokes the makefile for referenced model code recursively before recompiling the top model.

In Parallel Computing Toolbox commands, for example, a `parfor` or `spmd` loop, do not invoke `rtwbuild`, `rtwrebuild`, or `slbuild` commands that build models that are configured for parallel builds. For information about parallel builds of referenced models, see “Reduce Build Time for Referenced Models by Using Parallel Builds”.

`rtwrebuild(model)` assumes that the current working folder is one level above the build folder and invokes the makefile in the build folder. If the current working folder (`pwd`) is not one level above the build folder, the function exits with an error.

`rtwrebuild(path)` finds the build folder indicated with the *path* argument and invokes the makefile in the build folder. The *path* argument syntax lets the function operate without regard to the relationship between the current working folder and the build folder of the model.

## Examples

### Rebuild Code from Build Folder

Invoke the makefile and recompile code when the current working folder is the build folder. For example,

- If the model name is `mymodel`
- And, if the model build was initiated in the `C:\work` folder
- And, if the system target is `GRT`

Invoke the previously generated makefile in the current working folder (build folder) `C:\work\mymodel_grt_rtw`.

```
rtwrebuild()
```

### Rebuild Code from Parent Folder of Build Folder

When the current working folder is one level above the build folder, invoke the makefile and recompile code.

```
rtwrebuild('mymodel')
```

### Rebuild Code from a Folder

Invoke the makefile and recompile code from a current folder by specifying a path to the model build folder, C:\work\mymodel\_grt\_rtw.

```
rtwrebuild(fullfile('C:', 'work', 'mymodel_grt_rtw'))
```

## Input Arguments

**model** — Model object or name for which to regenerate code or rebuild an executable image  
*object* | 'modelName'

Model for which to regenerate code or rebuild an executable image, specified as an object or a character vector representing the model name.

Example: 'rtwdemo\_exporting\_functions'

**path** — Model path object or fully qualified path to the build folder for the model for which to regenerate code or rebuild an executable image  
*object* | *modelPath*

Example: fullfile('C:', 'work', 'mymodel\_grt\_rtw')

## See Also

rtwbuild | slbuild

### Topics

“Rebuild a Model”

**Introduced in R2009a**

# rtwreport

Create generated code report for model with Simulink Report Generator

## Syntax

```
rtwreport(model)
rtwreport(model, folder)
```

## Description

`rtwreport(model)` creates a report of code generation information for a model. Before creating the report, the function loads the model and generates code. The code generator names the report `codegen.html`. It places the file in your current folder. The report includes:

- Snapshots of the model, including subsystems.
- Block execution order list.
- Code generation summary with a list of generated code files, configuration settings, a subsystem map, and a traceability report.
- Full listings of generated code that reside in the build folder.

`rtwreport(model, folder)` specifies the build folder, `model_target_rtw`. The build folder (`folder`) and `s1prj` folder must reside in the code generation folder (Simulink). If the software cannot find the folder, an error occurs and code is not generated.

## Examples

### Create Report Documenting Generated Code

Create a report for model `rtwdemo_secondOrderSystem`:

```
rtwreport('rtwdemo_secondOrderSystem');
```

### Create Report Specifying Build Folder

Create a report for model `rtwdemo_secondOrderSystem` using build folder, `rtwdemo_secondOrderSystem_grt_rtw`:

```
rtwreport('rtwdemo_secondOrderSystem', ...
 'rtwdemo_secondOrderSystem_grt_rtw');
```

## Input Arguments

### **model** — Model name

character vector

Model name for which the report is generated, specified as a character vector.

Example: `'rtwdemo_secondOrderSystem'`

Data Types: `char`

**folder — Build folder name**

character vector

Build folder name, specified as a character vector. When you have multiple build folders, include a folder name. For example, if you have multiple builds using different targets, such as GRT and ERT.

Example: 'rtwdemo\_secondOrderSystem\_grt\_rtw'

Data Types: char

**See Also****Topics**

"Document Generated Code with Simulink Report Generator"

Import Generated Code

"Working with the Report Explorer" (Simulink Report Generator)

Code Generation Summary

**Introduced in R2007a**

# rtwtrace

Trace a block to generated code in code generation report

## Syntax

```
rtwtrace('blockpath')
rtwtrace('Simulink_identifier')
rtwtrace('blockpath', 'hdl')
rtwtrace('blockpath', 'plc')
```

## Description

`rtwtrace('blockpath')` opens a code generation report that displays contents of the source code file and highlights the line of code corresponding to the specified block.

Before calling `rtwtrace`, make sure that:

- You select an ERT-based model and enable model to code navigation.  
In the Configuration Parameters dialog box, select the **Model-to-code** (Embedded Coder) parameter.
- You generate code for the model by using the code generator.
- Your build folder is under the current working folder. Otherwise, `rtwtrace` might produce an error.

`rtwtrace('Simulink_identifier')` opens a code generation report that displays contents of the source code file and highlights the line of code corresponding to the block identified by the Simulink identifier (SID). SID is a unique designation for each block or element in the model. For more information, see “Locate Diagram Components Using Simulink Identifiers” (Simulink).

`rtwtrace('blockpath', 'hdl')` opens a code generation report in HDL Coder™ that displays contents of the source code file and highlights the line of code corresponding to the specified block.

`rtwtrace('blockpath', 'plc')` opens a code generation report in Simulink PLC Coder™ that displays contents of the source code file and highlights the line of code corresponding to the specified block.


## Examples

### Display Generated Code for a Block

Display the generated code for block `Out1` in the model `rtwdemo_comments` in code generation report:

```
% Using block path
rtwtrace('rtwdemo_comments/Out1')

% Using Simulink identifier
rtwtrace('rtwdemo_comments:33')
```



## Input Arguments

### **blockpath** — block path

character vector (default)

**blockpath** is a character vector enclosed in quotes specifying the full Simulink block path, for example, '*model\_name/block\_name*'.

Example: 'rtwdemo\_comments/Out1'

Data Types: char

### **Simulink\_identifier** — Simulink identifier

character vector (default)

**Simulink\_identifier** is a character vector enclosed in quotes specifying the Simulink identifier, for example, '*model\_name:number*'.

Example: 'rtwdemo\_comments:33'

Data Types: char

**hdl — HDL Coder**

character vector

`hdl` is a character vector enclosed in quotes specifying that the code report is from HDL Coder.

Example: 'Out1'

Data Types: char

**plc — PLC Coder**

character vector

`plc` is a character vector enclosed in quotes specifying that the code report is from Simulink PLC Coder.

Example: 'Out1'

Data Types: char

**Alternatives**

To trace from a block in the model diagram, right-click a block and select **C/C++ Code > Navigate to C/C++ Code**.

**See Also****Topics**

“Verify Generated Code by Using Code Tracing” (Embedded Coder)

“Model-to-Code Traceability” (Embedded Coder)

“Model-to-code” (Embedded Coder)

**Introduced in R2009b**

## setTargetProvidesMain

Disable inclusion of code generator provided (generated or static) `main.c` source file during model build

### Syntax

```
setTargetProvidesMain(buildinfo,providesmain)
```

### Description

`setTargetProvidesMain(buildinfo,providesmain)` disables the code generator from including a sample `main.c` source file.

To replace the sample `main.c` file from the code generator with a custom `main.c` file, call the `setTargetProvidesMain` function during the `'after_tlc'` case in the `ert_make_rtw_hook.m` or `grt_make_rtw_hook.m` file.

### Examples

#### Workflow for setTargetProvidesMain

To apply the `setTargetProvidesMain` function:

Add `buildInfo` to the arguments in the function call.

```
function ert_make_rtw_hook(hookMethod,modelName,rtwroot, ...
 templateMakefile,buildOpts,buildArgs,buildInfo)
```

Add the `setTargetProvidesMain` function to the `'after_tlc'` stage.

```
case 'after_tlc'
 % Called just after to invoking TLC Compiler (actual code generation.)
 % Valid arguments at this stage are hookMethod, modelName, and
 % buildArgs, buildInfo
 %
 setTargetProvidesMain(buildInfo,true);
```

Use the **Configuration Parameters > Code Generation > Custom Code > Source Files** field to add your custom `main.c` to the model. When you indicate that the target provides `main.c`, the model requires this file to build without errors.

### Input Arguments

**buildinfo** — Name of build information object returned by `RTW.BuildInfo` object

**providesmain** — Logical value that specifies whether the code generator includes the target provided `main.c` file

false (default) | true

The *providesmain* argument specifies whether the code generator includes a (generated or static) `main.c` source file.

- `false` — The code generator includes a sample `main.obj` object file.
- `true` — The target provides the `main.c` source file.

## See Also

[addSourceFiles](#) | [addSourcePaths](#)

## Topics

“Customize Build Process with `STF_make_rtw_hook` File”

**Introduced in R2009a**

## Simulink.fileGenControl

Specify root folders for files generated by diagram updates and model builds

### Syntax

```
cfg = Simulink.fileGenControl('getConfig')
Simulink.fileGenControl(Action,Name,Value)
```

### Description

`cfg = Simulink.fileGenControl('getConfig')` returns a handle to an instance of the `Simulink.FileGenConfig` object, which contains the current values of these file generation control parameters:

- `CacheFolder` - Specifies the root folder for model build artifacts that are used for simulation, including Simulink® cache files.
- `CodeGenFolder` - Specifies the root folder for code generation files.
- `CodeGenFolderStructure` - Controls the folder structure within the code generation folder.

To get or set the parameter values, use the `Simulink.FileGenConfig` object.

These Simulink preferences determine the initial parameter values for the MATLAB session:

- Simulation cache folder (Simulink) - `CacheFolder`
- Code generation folder (Simulink) - `CodeGenFolder`
- Code generation folder structure (Simulink) - `CodeGenFolderStructure`

`Simulink.fileGenControl(Action,Name,Value)` performs an action that uses the file generation control parameters of the current MATLAB session. Specify additional options with one or more `name,value` pair arguments.

### Examples

#### Get File Generation Control Parameter Values

To obtain the file generation control parameter values for the current MATLAB session, use `getConfig`.

```
cfg = Simulink.fileGenControl('getConfig');

myCacheFolder = cfg.CacheFolder;
myCodeGenFolder = cfg.CodeGenFolder;
myCodeGenFolderStructure = cfg.CodeGenFolderStructure;
```

#### Set File Generation Control Parameters by Using Simulink.FileGenConfig Object

To set the file generation control parameter values for the current MATLAB session, use the `setConfig` action. First, set values in an instance of the `Simulink.FileGenConfig` object. Then,

pass the object instance. This example assumes that your system has `aNonDefaultCacheFolder` and `aNonDefaultCodeGenFolder` folders.

```
% Get the current configuration
cfg = Simulink.fileGenControl('getConfig');

% Change the parameters to non-default locations
% for the cache and code generation folders
cfg.CacheFolder = fullfile('C:', 'aNonDefaultCacheFolder');
cfg.CodeGenFolder = fullfile('C:', 'aNonDefaultCodeGenFolder');
cfg.CodeGenFolderStructure = 'TargetEnvironmentSubfolder';

Simulink.fileGenControl('setConfig', 'config', cfg);
```

### Set File Generation Control Parameters Directly

You can set file generation control parameter values for the current MATLAB session without creating an instance of the `Simulink.FileGenConfig` object. This example assumes that your system has `aNonDefaultCacheFolder` and `aNonDefaultCodeGenFolder` folders.

```
myCacheFolder = fullfile('C:', 'aNonDefaultCacheFolder');
myCodeGenFolder = fullfile('C:', 'aNonDefaultCodeGenFolder');

Simulink.fileGenControl('set', 'CacheFolder', myCacheFolder, ...
 'CodeGenFolder', myCodeGenFolder, ...
 'CodeGenFolderStructure', ...
 Simulink.filegen.CodeGenFolderStructure.TargetEnvironmentSubfolder);
```

If you do not want to generate code for different target environments in separate folders, for `'CodeGenFolderStructure'`, specify the value `Simulink.filegen.CodeGenFolderStructure.ModelSpecific`.

### Reset File Generation Control Parameters

You can reset the file generation control parameters to values from Simulink preferences.

```
Simulink.fileGenControl('reset');
```

### Create Simulation Cache and Code Generation Folders

To create file generation folders, use the `set` action with the `'createDir'` option. You can keep previous file generation folders on the MATLAB path through the `'keepPreviousPath'` option.

```
%
myCacheFolder = fullfile('C:', 'aNonDefaultCacheFolder');
myCodeGenFolder = fullfile('C:', 'aNonDefaultCodeGenFolder');

Simulink.fileGenControl('set', ...
 'CacheFolder', myCacheFolder, ...
 'CodeGenFolder', myCodeGenFolder, ...
 'createDir', true, ...
 'keepPreviousPath', true);
```

```
'keepPreviousPath',true, ...
'createDir',true);
```

## Input Arguments

### Action — Specify action

'reset' | 'set' | 'setConfig'

Specify an action that uses the file generation control parameters of the current MATLAB session:

- 'reset' - Reset file generation control parameters to values from Simulink preferences.
- 'set' - Set file generation control parameters for the current MATLAB session by directly passing values.
- 'setConfig' - Set file generation control parameters for the current MATLAB session by using an instance of a `Simulink.FileGenConfig` object.

### Name-Value Pair Arguments

Specify optional comma-separated pairs of `Name`, `Value` arguments. `Name` is the argument name and `Value` is the corresponding value. `Name` must appear inside quotes. You can specify several name and value pair arguments in any order as `Name1,Value1,...,NameN,ValueN`.

Example: `Simulink.fileGenControl(Action, Name, Value);`

### config — Specify instance of Simulink.FileGenConfig

object handle

Specify the `Simulink.FileGenConfig` object instance containing file generation control parameters that you want to set.

Option for `setConfig`.

Example: `Simulink.fileGenControl('setConfig', 'config', cfg);`

### CacheFolder — Specify simulation cache folder

character vector

Specify a simulation cache folder path value for the `CacheFolder` parameter.

Option for `set`.

Example: `Simulink.fileGenControl('set', 'CacheFolder', myCacheFolder);`

### CodeGenFolder — Specify code generation folder

character vector

Specify a code generation folder path value for the `CodeGenFolder` parameter. You can specify an absolute path or a path relative to build folders. For example:

- 'C:\Work\mymodelsimcache' and '/mywork/mymodelgencode' specify absolute paths.
- 'mymodelsimcache' is a path relative to the current working folder (`pwd`). The software converts a relative path to a fully qualified path at the time the `CacheFolder` or `CodeGenFolder` parameter is set. For example, if `pwd` is '/mywork', the result is '/mywork/mymodelsimcache'.

- `'../test/mymodelgencode'` is a path relative to `pwd`. If `pwd` is  `'/mywork'`, the result is  `'/test/mymodelgencode'`.

Option for `set`.

Example: `Simulink.fileGenControl('set', 'CodeGenFolder', myCodeGenFolder);`

### **CodeGenFolderStructure — Specify generated code folder structure**

`Simulink.filegen.CodeGenFolderStructure.ModelSpecific` (default) |  
`Simulink.filegen.CodeGenFolderStructure.TargetEnvironmentSubfolder`

Specify the layout of subfolders within the generated code folder:

- `Simulink.filegen.CodeGenFolderStructure.ModelSpecific` (default) - Place generated code in subfolders within a model-specific folder.
- `Simulink.filegen.CodeGenFolderStructure.TargetEnvironmentSubfolder` - If models are configured for different target environments, place generated code for each model in a separate subfolder. The name of the subfolder corresponds to the target environment.

Option for `set`.

Example: `Simulink.fileGenControl('set', 'CacheFolder', myCacheFolder, ...  
'CodeGenFolder', myCodeGenFolder, ... 'CodeGenFolderStructure', ...  
Simulink.filegen.CodeGenFolderStructure.TargetEnvironmentSubfolder);`

### **keepPreviousPath — Keep previous folder paths on MATLAB path**

`false` (default) | `true`

Specify whether to keep the previous values of `CacheFolder` and `CodeGenFolder` on the MATLAB path:

- `true` - Keep previous folder path values on MATLAB path.
- `false` (default) - Remove previous folder path values from MATLAB path.

Option for `reset`, `set`, or `setConfig`.

Example: `Simulink.fileGenControl('reset', 'keepPreviousPath', true);`

### **createDir — Create folders for file generation**

`false` (default) | `true`

Specify whether to create folders for file generation if the folders do not exist:

- `true` - Create folders for file generation.
- `false` (default) - Do not create folders for file generation.

Option for `set` or `setConfig`.

Example: `Simulink.fileGenControl('set', 'CacheFolder', myCacheFolder,  
'CodeGenFolder', myCodeGenFolder, 'keepPreviousPath', true,  
'createDir', true);`

### **Avoid Naming Conflicts**

Using `Simulink.fileGenControl` to set `CacheFolder` and `CodeGenFolder` adds the specified folders to your MATLAB search path. This function has the same potential for introducing a naming

conflict as using `addpath` to add folders to the search path. For example, a naming conflict occurs if the folder that you specify for `CacheFolder` or `CodeGenFolder` contains a model file with the same name as an open model. For more information, see “What Is the MATLAB Search Path?” (MATLAB) and “Files and Folders that MATLAB Accesses” (MATLAB).

To use a nondefault location for the simulation cache folder or code generation folder:

- 1 Delete any potentially conflicting artifacts that exist in:
  - The current working folder, `pwd`.
  - The nondefault simulation cache and code generation folders that you intend to use.
- 2 Specify the nondefault locations for the simulation cache and code generation folders by using `Simulink.fileGenControl` or Simulink preferences.

## Output Arguments

### **cfg** — Current values of file generation control parameters

object handle

Instance of a `Simulink.FileGenConfig` object, which contains the current values of file generation control parameters.

## See Also

“Simulation cache folder” (Simulink) | “Code generation folder” (Simulink) | Code generation folder structure (Simulink)

## Topics

“Manage Build Process Folders”

“Share Simulink Cache Files for Faster Simulation” (Simulink)

## Introduced in R2010b

# Simulink.ModelReference.modifyProtectedModel

Modify existing protected model

## Syntax

```
Simulink.ModelReference.modifyProtectedModel(model)
Simulink.ModelReference.modifyProtectedModel(model,Name,Value)

[harnessHandle] = Simulink.ModelReference.modifyProtectedModel(model, '
Harness',true)
[~,neededVars] = Simulink.ModelReference.modifyProtectedModel(model)
```

## Description

`Simulink.ModelReference.modifyProtectedModel(model)` modifies options for an existing protected model created from the specified model. If `Name,Value` pair arguments are not specified, the modified protected model is updated with default values and supports only simulation.

`Simulink.ModelReference.modifyProtectedModel(model,Name,Value)` uses additional options specified by one or more `Name,Value` pair arguments. These options are the same options that are provided by the `Simulink.ModelReference.protect` function. However, these options have additional options to change encryption passwords for read-only view, simulation, and code generation. When you add functionality to the protected model or change encryption passwords, the unprotected model must be available. The software searches for the model on the MATLAB path. If the model is not found, the software reports an error.

`[harnessHandle] = Simulink.ModelReference.modifyProtectedModel(model, 'Harness',true)` creates a harness model for the protected model. It returns the handle of the harnessed model in `harnessHandle`.

`[~,neededVars] = Simulink.ModelReference.modifyProtectedModel(model)` returns a cell array that includes the names of base workspace variables used by the protected model.

## Examples

### Update Protected Model with Default Values

Create a modifiable protected model with support for code generation, then reset it to default values.

Add the password for when a protected model is modified. If you skip this step, you are prompted to set a password when a modifiable protected model is created.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'sldemo_mdhref_counter','password');
```

Create a modifiable protected model with support for code generation and Web view.

```
Simulink.ModelReference.protect('sldemo_mdhref_counter','Mode',...
'CodeGeneration','Modifiable',true,'Report',true);
```

Provide the password to modify the protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'sldemo_mdref_counter', 'password');
```

Modify the model to use default values.

```
Simulink.ModelReference.modifyProtectedModel(...
'sldemo_mdref_counter');
```

The resulting protected model is updated with default values and supports only simulation.

### **Remove Functionality from Protected Model**

Create a modifiable protected model with support for code generation and Web view, then modify it to remove the Web view support.

Add the password for when a protected model is modified. If you skip this step, you are prompted to set a password when a modifiable protected model is created.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'sldemo_mdref_counter', 'password');
```

Create a modifiable protected model with support for code generation and Web view.

```
Simulink.ModelReference.protect('sldemo_mdref_counter', 'Mode', ...
'CodeGeneration', 'Webview', true, 'Modifiable', true, 'Report', true);
```

Provide the password to modify the protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'sldemo_mdref_counter', 'password');
```

Remove support for Web view from the protected model that you created.

```
Simulink.ModelReference.modifyProtectedModel(...
'sldemo_mdref_counter', 'Mode', 'CodeGeneration', 'Report', true);
```

### **Change Encryption Password for Code Generation**

Change an encryption password for a modifiable protected model.

Add the password for when a protected model is modified. If you skip this step, you are prompted to set a password when a modifiable protected model is created.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'sldemo_mdref_counter', 'password');
```

Add the password that the protected model user must provide to generate code.

```
Simulink.ModelReference.ProtectedModel.setPasswordForSimulation(...
'sldemo_mdref_counter', 'cgpassword');
```

Create a modifiable protected model with a report and support for code generation with encryption.

```
Simulink.ModelReference.protect('sldemo_mdhref_counter', 'Mode', ...
'CodeGeneration', 'Encrypt', true, 'Modifiable', true, 'Report', true);
```

Provide the password to modify the protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'sldemo_mdhref_counter', 'password');
```

Change the encryption password for simulation.

```
Simulink.ModelReference.modifyProtectedModel(
'sldemo_mdhref_counter', 'Mode', 'CodeGeneration', 'Encrypt', true, ...
'Report', true, 'ChangeSimulationPassword', ...
{'cgpassword', 'new_password'});
```

### Add Harness Model for Protected Model

Add a harness model for an existing protected model.

Add the password for when a protected model is modified. If you skip this step, you are prompted to set a password when a modifiable protected model is created.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'sldemo_mdhref_counter', 'password');
```

Create a modifiable protected model with a report and support for code generation with encryption.

```
Simulink.ModelReference.protect('sldemo_mdhref_counter', 'Mode', ...
'CodeGeneration', 'Modifiable', true, 'Report', true);
```

Provide the password to modify the protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'sldemo_mdhref_counter', 'password');
```

Add a harness model for the protected model.

```
[harnessHandle] = Simulink.ModelReference.modifyProtectedModel(...
'sldemo_mdhref_counter', 'Mode', 'CodeGeneration', 'Report', true, ...
'Harness', true);
```

## Input Arguments

### model — Model name

string or character vector (default)

Model name, specified as a string or character vector. It contains the name of a model or the path name of a Model block that references the protected model.

### Name-Value Pair Arguments

Specify optional comma-separated pairs of Name, Value arguments. Name is the argument name and Value is the corresponding value. Name must appear inside quotes. You can specify several name and value pair arguments in any order as Name1, Value1, ..., NameN, ValueN.

Example: `'Mode', 'CodeGeneration', 'OutputFormat', 'Binaries', 'ObfuscateCode', true` specifies that obfuscated code be generated for the protected model. It also specifies that only binary files and headers in the generated code be visible to users of the protected model.

### General

#### **Path — Folder for protected model**

current working folder (default) | string or character vector

Folder for protected model, specified as a string or character vector.

Example: `'Path', 'C:\Work'`

#### **Report — Option to generate a report**

false (default) | true

Option to generate a report, specified as a Boolean value.

To view the report, right-click the protected-model badge icon and select **Display Report**. Or, call the `Simulink.ProtectedModel.open` function with the `report` option.

The report is generated in HTML format. It includes information on the environment, functionality, license requirements, and interface for the protected model.

Example: `'Report', true`

#### **hdl — Option to generate HDL code**

false (default) | true

Option to generate HDL code, specified as a Boolean value.

This option requires HDL Coder license. When you enable this option, make sure that you specify the **Mode**. You can set this option to `true` in conjunction with the **Mode** set to `CodeGeneration` to enable both C code and HDL code generation support for the protected model.

If you want to enable only simulation and HDL code generation support, but not C code generation, set **Mode** to `HDLCodeGeneration`. You do not have to set the **hdl** option to `true`.

Example: `'hdl', true`

#### **Harness — Option to create a harness model**

false (default) | true

Option to create a harness model, specified as a Boolean value.

Example: `'Harness', true`

#### **CustomPostProcessingHook — Option to add postprocessing function for protected model files**

function handle

Option to add a postprocessing function for protected model files, specified as a function handle. The function accepts a `Simulink.ModelReference.ProtectedModel.HookInfo` object as an input variable. This object provides information on the source code files and other files generated during protected model creation. The object also provides information on exported symbols that you must not modify. Prior to packaging the protected model, the postprocessing function is called.

For a protected model with a top model interface, the `Simulink.ModelReference.ProtectedModel.HookInfo` object cannot provide information on exported symbols.

Example: `'CustomPostProcessingHook',@(protectedMdlInf)myHook(protectedMdlInf)`

### Functionality

#### Mode — Model protection mode

'Normal' (default) | 'Accelerator' | 'CodeGeneration' | 'HDLCodeGeneration' | 'ViewOnly'

Model protection mode. Specify one of the following values:

- 'Normal': If the top model is running in 'Normal' mode, the protected model runs as a child of the top model.
- 'Accelerator': The top model can run in 'Normal', 'Accelerator', or 'Rapid Accelerator' mode.
- 'CodeGeneration': The top model can run in 'Normal', 'Accelerator', or 'Rapid Accelerator' mode and support code generation.
- 'HDLCodeGeneration': The top model can run in 'Normal', 'Accelerator', or 'Rapid Accelerator' mode and support HDL code generation.
- 'ViewOnly': Turns off Simulate and Generate code functionality modes. Turns on the read-only view mode.

Example: `'Mode', 'Accelerator'`

#### OutputFormat — Protected code visibility

'CompiledBinaries' (default) | 'MinimalCode' | 'AllReferencedHeaders'

---

**Note** This argument affects the output only when you specify `Mode` as 'Accelerator' or 'CodeGeneration'. When you specify `Mode` as 'Normal', only a MEX-file is part of the output package.

---

Protected code visibility. This argument determines what part of the code generated for a protected model is visible to users. Specify one of the following values:

- 'CompiledBinaries': Only binary files and headers are visible.
- 'MinimalCode': Includes only the minimal header files required to build the code with the chosen build settings. Code in the build folder is visible. Users can inspect the code in the protected model report and recompile it for their purposes.
- 'AllReferencedHeaders': Includes header files found on the include path. Code in the build folder is visible. Header files referenced by the code are also visible.

Example: `'OutputFormat', 'AllReferencedHeaders'`

#### ObfuscateCode — Option to obfuscate generated code

true (default) | false

Option to obfuscate generated code, specified as a Boolean value. Applicable only when code generation is enabled for the protected model. Obfuscation is not supported for HDL code generation.

Example: 'ObfuscateCode',true

### **Webview — Option to include a Web view**

false (default) | true

Option to include a read-only view of protected model, specified as a Boolean value.

To open the Web view of a protected model, use one of the following methods:

- Right-click the protected-model badge icon and select **Show Web view**.
- Use the `Simulink.ProtectedModel.open` function. For example, to display the Web view for protected model `sldemo_mdhref_counter`, you can call:

```
Simulink.ProtectedModel.open('sldemo_mdhref_counter', 'webview');
```

- Double-click the `.slxp` protected model file in the Current Folder browser.
- In the Block Parameter dialog box for the protected model, click **Open Model**.

Example: 'Webview',true

### **Encryption**

#### **ChangeSimulationPassword — Option to change the encryption password for simulation**

cell array of two character vectors

Option to change the encryption password for simulation, specified as a cell array of two character vectors. The first vector is the old password, the second vector is the new password.

Example: 'ChangeSimulationPassword',{'old\_password','new\_password'}

#### **ChangeViewPassword — Option to change the encryption password for read-only view**

cell array of two character vectors

Option to change the encryption password for read-only view, specified as a cell array of two character vectors. The first vector is the old password, the second vector is the new password.

Example: 'ChangeViewPassword',{'old\_password','new\_password'}

#### **ChangeCodeGenerationPassword — Option to change the encryption password for code generation**

cell array of two character vectors

Option to change the encryption password for code generation, specified as a cell array of two character vectors. The first vector is the old password, the second vector is the new password.

Example: 'ChangeCodeGenerationPassword',{'old\_password','new\_password'}

### **Encrypt — Option to encrypt protected model**

false (default) | true

Option to encrypt a protected model, specified as a Boolean value. Applicable when you have specified a password during protection, or by using the following methods:

- Password for read-only view of model:  
`Simulink.ModelReference.ProtectedModel.setPasswordForView`
- Password for simulation:  
`Simulink.ModelReference.ProtectedModel.setPasswordForSimulation`

- Password for code generation:  
`Simulink.ModelReference.ProtectedModel.setPasswordForCodeGeneration`
- Password for HDL code generation:  
`Simulink.ModelReference.ProtectedModel.setPasswordForHDLCodeGeneration`

Example: `'Encrypt',true`

## Output Arguments

### **harnessHandle** — Handle of the harness model

double

Handle of the harness model, returned as a double or 0, depending on the value of `Harness`.

If `Harness` is `true`, the value is the handle of the harness model; otherwise, the value is 0.

### **neededVars** — Names of base workspace variables

cell array

Names of base workspace variables used by the protected model, returned as a cell array.

The cell array can also include variables that the protected model does not use.

## See Also

`Simulink.ModelReference.ProtectedModel.setPasswordForModify` |  
`Simulink.ModelReference.protect`

**Introduced in R2014b**

## Simulink.ModelReference.protect

Obscure referenced model contents to hide intellectual property

### Syntax

```
Simulink.ModelReference.protect(model)
Simulink.ModelReference.protect(model,Name,Value)

[harnessHandle] = Simulink.ModelReference.protect(model,'Harness',true)
[~,neededVars] = Simulink.ModelReference.protect(model)
```

### Description

`Simulink.ModelReference.protect(model)` creates a protected model from the specified model. It places the protected model in the current working folder. The protected model has the same name as the source model. It has the extension `.slxp`.

`Simulink.ModelReference.protect(model,Name,Value)` uses additional options specified by one or more `Name,Value` pair arguments.

`[harnessHandle] = Simulink.ModelReference.protect(model,'Harness',true)` creates a harness model for the protected model. It returns the handle of the harnessed model in `harnessHandle`.

`[~,neededVars] = Simulink.ModelReference.protect(model)` returns a cell array that includes the names of base workspace variables used by the protected model.

### Examples

#### Protect Referenced Model

Protect a referenced model and place the protected model in the current working folder.

```
sldemo_mdhref_bus;
model= 'sldemo_mdhref_counter_bus'
```

```
Simulink.ModelReference.protect(model);
```

A protected model named `sldemo_mdhref_counter_bus.slxp` is created. The protected model file is placed in the current working folder.

#### Place Protected Model in Specified Folder

Protect a referenced model and place the protected model in a specified folder.

```
sldemo_mdhref_bus;
model= 'sldemo_mdhref_counter_bus'

Simulink.ModelReference.protect(model,'Path','C:\Work');
```

A protected model named `sldemo_mdhref_counter_bus.slxp` is created. The protected model file is placed in `C:\Work`.

### Generate Code for Protected Model

Protect a referenced model, generate code for it in normal mode, and obfuscate the code.

```
sldemo_mdhref_bus;
model= 'sldemo_mdhref_counter_bus'

Simulink.ModelReference.protect(model, 'Path', 'C:\Work', 'Mode', 'CodeGeneration', ...
'ObfuscateCode', true);
```

A protected model named `sldemo_mdhref_counter_bus.slxp` is created. The protected model file is placed in the `C:\Work` folder. The protected model runs as a child of the parent model. The code generated for the protected model is obfuscated by the software.

### Generate HDL Code for Protected Model

Protect a referenced model, and generate HDL code for it in normal mode.

```
parent_model= 'hdlcoder_protected_model_parent_harness';
reference_model_to_protect = 'hdlcoder_referenced_model_gain';

Simulink.ModelReference.protect(reference_model_to_protect, ...
'Mode', 'HDLCodeGeneration')
```

A protected model named `hdlcoder_referenced_model_gain.slxp` is created. The protected model file is placed in the same folder as the parent model and the referenced model. The protected model runs as a child of the parent model.

Set the **hdl** option to `true` with **Mode** set to `CodeGeneration` to enable both C code generation and HDL code generation support for a protected model that you create.

```
parent_model= 'hdlcoder_protected_model_parent_harness';
reference_model_to_protect = 'hdlcoder_referenced_model_gain';

Simulink.ModelReference.protect(reference_model_to_protect, ...
'Mode', 'CodeGeneration', 'hdl', true)
```

### Control Code Visibility for Protected Model

Control code visibility by allowing users to view only binary files and headers in the code generated for a protected model.

```
sldemo_mdhref_bus;
model= 'sldemo_mdhref_counter_bus'

Simulink.ModelReference.protect(model, 'Mode', 'CodeGeneration', 'OutputFormat', ...
'CompiledBinaries');
```

A protected model named `sldemo_mdhref_counter_bus.slxp` is created. The protected model file is placed in the current working folder. Users can view only binary files and headers in the code generated for the protected model.

### Create Harness Model for Protected Model

Create a harness model for a protected model and generate an HTML report.

```
sldemo_mdhref_bus;
modelPath= 'sldemo_mdhref_bus/CounterA'

[harnessHandle] = Simulink.ModelReference.protect(modelPath, 'Path', 'C:\Work', ...
'Harness', true, 'Report', true);
```

A protected model named `sldemo_mdhref_counter_bus.slxp` is created, along with an untitled harness model. The protected model file is placed in the `C:\Work` folder. The folder also contains an HTML report. The handle of the harness model is returned in `harnessHandle`.

## Input Arguments

### model — Model name

string or character vector (default)

Model name, specified as a string or character vector. It contains the name of a model or the path name of a Model block that references the model to be protected.

### Name-Value Pair Arguments

Specify optional comma-separated pairs of **Name**, **Value** arguments. **Name** is the argument name and **Value** is the corresponding value. **Name** must appear inside quotes. You can specify several name and value pair arguments in any order as `Name1, Value1, ..., NameN, ValueN`.

Example: `'Mode', 'CodeGeneration', 'OutputFormat', 'Binaries', 'ObfuscateCode', true` specifies that obfuscated code be generated for the protected model. It also specifies that only binary files and headers in the generated code be visible to users of the protected model.

### Harness — Option to create a harness model

false (default) | true

Option to create a harness model, specified as a Boolean value.

Example: `'Harness', true`

### Mode — Model protection mode

'Normal' (default) | 'Accelerator' | 'CodeGeneration' | 'HDLCodeGeneration' | 'ViewOnly'

Model protection mode. Specify one of the following values:

- `'Normal'`: If the top model is running in `'Normal'` mode, the protected model runs as a child of the top model.
- `'Accelerator'`: The top model can run in `'Normal'`, `'Accelerator'`, or `'Rapid Accelerator'` mode.

- `'CodeGeneration'`: The top model can run in `'Normal'`, `'Accelerator'`, or `'Rapid Accelerator'` mode and support code generation.
- `'HDLCodeGeneration'`: The top model can run in `'Normal'`, `'Accelerator'`, or `'Rapid Accelerator'` mode and support HDL code generation. (Requires HDL Coder license)
- `'ViewOnly'`: Turns off Simulate and Generate code functionality modes. Turns on the read-only view mode.

Example: `'Mode', 'Accelerator'`

### **CodeInterface — Interface through which generated code is accessed by Model block**

`'Model reference'` (default) | `'Top model'`

Applies only if the system target file (`SystemTargetFile`) is set to an ERT-based system target file (for example, `ert.tlc`). Requires Embedded Coder license.

Specify one of the following values:

- `'Model reference'`: Code access through the model reference code interface, which allows use of the protected model within a model reference hierarchy. Users of the protected model can generate code from a parent model that contains the protected model. In addition, users can run Model block SIL/PIL simulations with the protected model.
- `'Top model'`: Code access through the standalone interface. Users of the protected model can run Model block SIL/PIL simulations with the protected model.

Example: `'CodeInterface', 'Top model'`

### **ObfuscateCode — Option to obfuscate generated code**

`true` (default) | `false`

Option to obfuscate generated code, specified as a Boolean value. Applicable only when code generation during protection is enabled. Obfuscation is not supported for HDL code generation.

Example: `'ObfuscateCode', true`

### **Path — Folder for protected model**

current working folder (default) | string or character vector

Folder for protected model, specified as a string or character vector.

Example: `'Path', 'C:\Work'`

### **Report — Option to generate a report**

`false` (default) | `true`

Option to generate a report, specified as a Boolean value.

To view the report, right-click the protected-model badge icon and select **Display Report**. Or, call the `Simulink.ProtectedModel.open` function with the report option.

The report is generated in HTML format. It includes information on the environment, functionality, and interface for the protected model.

Example: `'Report', true`

### **hdl — Option to generate HDL code**

`false` (default) | `true`

Option to generate HDL code, specified as a Boolean value.

This option requires HDL Coder license. When you enable this option, make sure that you specify the **Mode**. You can set this option to `true` in conjunction with the **Mode** set to `CodeGeneration` to enable both C code and HDL code generation support for the protected model.

If you want to enable only simulation and HDL code generation support, but not C code generation, set **Mode** to `HDLCodeGeneration`. You do not have to set the **hdl** option to `true`.

Example: `'hdl',true`

### **OutputFormat — Protected code visibility**

`'CompiledBinaries'` (default) | `'MinimalCode'` | `'AllReferencedHeaders'`

---

**Note** This argument affects the output only when you specify **Mode** as `'Accelerator'` or `'CodeGeneration'`. When you specify **Mode** as `'Normal'`, only a MEX-file is part of the output package.

---

Protected code visibility. This argument determines what part of the code generated for a protected model is visible to users. Specify one of the following values:

- `'CompiledBinaries'`: Only binary files and headers are visible.
- `'MinimalCode'`: Includes only the minimal header files required to build the code with the chosen build settings. All code in the build folder is visible. Users can inspect the code in the protected model report and recompile it for their purposes.
- `'AllReferencedHeaders'`: Includes header files found on the include path. All code in the build folder is visible. All headers referenced by the code are also visible.

Example: `'OutputFormat','AllReferencedHeaders'`

### **Webview — Option to include a Web view**

`false` (default) | `true`

Option to include a read-only view of protected model, specified as a Boolean value.

To open the Web view of a protected model, use one of the following methods:

- Right-click the protected-model badge icon and select **Show Web view**.
- Use the `Simulink.ProtectedModel.open` function. For example, to display the Web view for protected model `sldemo_mdhref_counter`, you can call:

```
Simulink.ProtectedModel.open('sldemo_mdhref_counter', 'webview');
```

- Double-click the `.slxp` protected model file in the Current Folder browser.
- In the Block Parameter dialog box for the protected model, click **Open Model**.

Example: `'Webview',true`

### **Encrypt — Option to encrypt protected model**

`false` (default) | `true`

Option to encrypt a protected model, specified as a Boolean value. Applicable when you have specified a password during protection, or by using the following methods:

- Password for read-only view of model:  
`Simulink.ModelReference.ProtectedModel.setPasswordForView`
- Password for simulation:  
`Simulink.ModelReference.ProtectedModel.setPasswordForSimulation`
- Password for code generation:  
`Simulink.ModelReference.ProtectedModel.setPasswordForCodeGeneration`
- Password for HDL code generation:  
`Simulink.ModelReference.ProtectedModel.setPasswordForHDLCodeGeneration`

Example: `'Encrypt',true`

### **CustomPostProcessingHook — Option to add postprocessing function for protected model files**

function handle

Option to add a postprocessing function for protected model files, specified as a function handle. The function accepts a `Simulink.ModelReference.ProtectedModel.HookInfo` object as an input variable. This object provides information on the source code files and other files generated during protected model creation. It also provides information on exported symbols that you must not modify. Prior to packaging the protected model, the postprocessing function is called.

For a protected model with a top model interface, the `Simulink.ModelReference.ProtectedModel.HookInfo` object cannot provide information on exported symbols.

Example: `'CustomPostProcessingHook',@(protectedMdlInf)myHook(protectedMdlInf)`

### **Modifiable — Option to create a modifiable protected model**

false (default) | true

Option to create a modifiable protected model, specified as a Boolean value. To use this option:

- Add a password for modification by using the `Simulink.ModelReference.ProtectedModel.setPasswordForModify` function. If a password has not been added at the time that you create the modifiable protected model, you are prompted to create one.
- Modify the options of your protected model by first providing the modification password by using the `Simulink.ModelReference.ProtectedModel.setPasswordForModify` function. Then use the `Simulink.ModelReference.modifyProtectedModel` function to make your option changes.

Example: `'Modifiable',true`

### **Callbacks — Option to specify protected model callbacks**

cell array

Option to specify callbacks for a protected model, specified as a cell array of `Simulink.ProtectedModel.Callback` objects.

Example: `'Callbacks',{pmcallback_sim, pmcallback_cg}`

### **Sign — Option to sign with digital certificate**

character vector | string scalar

The digital certificate to use to sign a protected model, specified as a character vector or string scalar. If the certificate file is password-protected, use the `Simulink.ModelReference.ProtectedModel.setPasswordForCertificate` function to provide the password before you use the certificate.

Example: `'Sign','my_certificate.pfx'`

## Output Arguments

### **harnessHandle** — Handle of the harness model

double

Handle of the harness model, returned as a double or 0, depending on the value of `Harness`.

If `Harness` is `true`, the value is the handle of the harness model. Otherwise, the value is 0.

### **neededVars** — Names of base workspace variables

cell array

Names of base workspace variables that the protected model uses, returned as a cell array.

The cell array can also include variables that the protected model does not use.

## Alternatives

“Protect Models to Conceal Contents”

## See Also

`Simulink.ModelReference.ProtectedModel.clearPasswords` |  
`Simulink.ModelReference.ProtectedModel.clearPasswordsForModel` |  
`Simulink.ModelReference.ProtectedModel.setPasswordForCodeGeneration` |  
`Simulink.ModelReference.ProtectedModel.setPasswordForHDLCodeGeneration` |  
`Simulink.ModelReference.ProtectedModel.setPasswordForModify` |  
`Simulink.ModelReference.ProtectedModel.setPasswordForSimulation` |  
`Simulink.ModelReference.ProtectedModel.setPasswordForView` |  
`Simulink.ModelReference.modifyProtectedModel`

## Topics

“Protect Models to Conceal Contents”

“Protected Models for Model Reference” (Simulink)

“Test Protected Models”

“Package and Share Protected Models”

“Specify Custom Obfuscators for Protected Models”

“Configure and Run SIL Simulation” (Embedded Coder)

“Define Callbacks for Protected Models”

“Reference Protected Models from Third Parties” (Simulink)

“Code Interfaces for SIL and PIL” (Embedded Coder)

## Introduced in R2012b

# Simulink.ModelReference.ProtectedModel.clearPasswords

Clear cached passwords for protected models

## Syntax

```
Simulink.ModelReference.ProtectedModel.clearPasswords()
```

## Description

`Simulink.ModelReference.ProtectedModel.clearPasswords()` clears protected model passwords that have been cached during the current MATLAB session. If this function is not called, cached passwords are cleared at the end of a MATLAB session.

## Examples

### Clear cached passwords for protected models

After using protected models, clear passwords cached for the models during the MATLAB session.

```
Simulink.ModelReference.ProtectedModel.clearPasswords()
```

## See Also

`Simulink.ModelReference.ProtectedModel.clearPasswordsForModel`

## Topics

“Protect Models to Conceal Contents”

**Introduced in R2014b**

## Simulink.ModelReference.ProtectedModel.clearPasswordsForModel

Clear cached passwords for a protected model

### Syntax

```
Simulink.ModelReference.ProtectedModel.clearPasswordsForModel(model)
```

### Description

`Simulink.ModelReference.ProtectedModel.clearPasswordsForModel(model)` clears protected model passwords for `model` that have been cached during the current MATLAB session. If this function is not called, cached passwords are cleared at the end of a MATLAB session.

### Examples

#### Clear cached passwords for a protected model

After using a protected model, clear passwords cached for the model during the MATLAB session.

```
Simulink.ModelReference.ProtectedModel.clearPasswordsForModel(model)
```

### Input Arguments

#### **model** — Protected model name

string or character vector

Model name specified as a string or character vector

Example: 'rtwdemo\_counter'

Data Types: char

### See Also

`Simulink.ModelReference.ProtectedModel.clearPasswords`

### Topics

"Protect Models to Conceal Contents"

**Introduced in R2014b**

# Simulink.ModelReference.ProtectedModel.HookInfo class

**Package:** Simulink.ModelReference.ProtectedModel

Represent files and exported symbols generated by creation of protected model

## Description

Specifies information about files and symbols generated when creating a protected model. The creator of a protected model can use this information for postprocessing of the generated files prior to packaging. Information includes:

- List of source code files (\*.c, \*.h, \*.cpp, \*.hpp).
- List of other related files (\*.mat, \*.rsp, \*.prj, etc.).
- List of exported symbols that you must not modify.

## Construction

To access the properties of this class, use the 'CustomPostProcessingHook' option of the Simulink.ModelReference.protect function. The value for the option is a handle to a postprocessing function accepting a Simulink.ModelReference.ProtectedModel.HookInfo object as input.

## Properties

### ExportedSymbols — Exported Symbols

cell array of character vectors

A list of exported symbols generated by protected model that you must not modify. Default value is empty.

For a protected model with a top model interface, the HookInfo object cannot provide information on exported symbols.

### NonSourceFiles — Non source code files

cell array of character vectors

A list of non-source files generated by protected model creation. Examples are \*.mat, \*.rsp, and \*.prj. Default value is empty.

### SourceFiles — Source code files

cell array of character vectors

A list of source code files generated by protected model creation. Examples are \*.c, \*.h, \*.cpp, and \*.hpp. Default value is empty.

## **Copy Semantics**

Handle. To learn how handle classes affect copy operations, see Copying Objects (MATLAB).

### **See Also**

`Simulink.ModelReference.protect`

### **Topics**

“Specify Custom Obfuscators for Protected Models”

# Simulink.ModelReference.ProtectedModel.setPasswordForCertificate

Provide password for digital certificate

## Syntax

```
Simulink.ModelReference.ProtectedModel.setPasswordForCertificate(
certificateFile,password)
```

## Description

`Simulink.ModelReference.ProtectedModel.setPasswordForCertificate(certificateFile,password)` provides the required password to access the certificate file to digitally sign a protected model.

## Examples

### Sign a Protected Model by Using Password Protected Certificate

Protect a model, and then digitally sign it by using a password protected certificate.

Open and protect the model that you want to sign. For this example, protect the model `sldemo_mdhref_counter`.

```
sldemo_mdhref_counter
Simulink.ModelReference.protect('sldemo_mdhref_counter');
```

Locate the certificate file that you want to use to sign the protected model. Enter the password for the certificate.

```
Simulink.ModelReference.ProtectedModel.setPasswordForCertificate('certificate_file.pfx','password');
```

Sign the protected model by using the certificate file.

```
Simulink.ProtectedModel.sign('sldemo_mdhref_counter.slxp','certificate_file.pfx');
```

## Input Arguments

### certificateFile — Certificate file to use for signing

character vector | string scalar

Certificate file to use for signing the protected model, specified as a character vector or string scalar. The certificate must be a PKCS #12 file with the extension `.pfx` or `.p12`.

Example: `'my_cert.pfx'`

Example: `'InstitutionCertificate.p12'`

### password — Password for certificate file

string or character vector

Password, specified as a string or character vector. If the certificate is encrypted for code generation, the password is required.

**See Also**

`Simulink.ProtectedModel.sign`

**Topics**

“Sign a Protected Model”

**Introduced in R2020a**

# Simulink.ModelReference.ProtectedModel.setPasswordForCodeGeneration

Add or provide encryption password for code generation from protected model

## Syntax

```
Simulink.ModelReference.ProtectedModel.setPasswordForCodeGeneration(model, password)
```

## Description

`Simulink.ModelReference.ProtectedModel.setPasswordForCodeGeneration(model, password)` adds an encryption password for code generation if you create a protected model. If you use a protected model, the function provides the required password to generate code from the model.

## Examples

### Create a Protected Model with Encryption

Create a protected model with encryption for code generation.

```
Simulink.ModelReference.ProtectedModel.setPasswordForCodeGeneration(...
'sldemo_mdref_counter', 'password');
Simulink.ModelReference.protect('sldemo_mdref_counter', ...
'Mode', 'Code Generation', 'Encrypt', true, 'Report', true);
```

A protected model named `sldemo_mdref_counter.slxp` is created that requires an encryption password for code generation.

### Generate Code from an Encrypted Protected Model

Use a protected model with encryption for code generation.

Provide the encryption password required for code generation from the protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForCodeGeneration(...
'sldemo_mdref_counter', 'password');
```

After you have provided the encryption password, you can generate code from the protected model.

## Input Arguments

### **model** — Model name

string or character vector

Model name, specified as a string or character vector. It contains the name of a model or the path name of a Model block that references the protected model.

**password — Password for protected model code generation**

string or character vector

Password, specified as a string or character vector. If the protected model is encrypted for code generation, the password is required.

**See Also**

`Simulink.ModelReference.ProtectedModel.setPasswordForHDLCodeGeneration` |  
`Simulink.ModelReference.ProtectedModel.setPasswordForSimulation` |  
`Simulink.ModelReference.ProtectedModel.setPasswordForView` |  
`Simulink.ModelReference.protect`

**Introduced in R2014b**

# Simulink.ModelReference.ProtectedModel.setPasswordForModify

Add or provide password for modifying protected model

## Syntax

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(model,password)
```

## Description

`Simulink.ModelReference.ProtectedModel.setPasswordForModify(model,password)` adds a password for a modifiable protected model. After the password has been created, the function provides the password for modifying the protected model.

## Examples

### Add Functionality to Protected Model

Create a modifiable protected model with support for code generation, then modify it to add Web view support.

Add the password for when a protected model is modified. If you skip this step, you are prompted to set a password when a modifiable protected model is created.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'sldemo_mdhref_counter','password');
```

Create a modifiable protected model with support for code generation and Web view.

```
Simulink.ModelReference.protect('sldemo_mdhref_counter','Mode',...
'CodeGeneration','Modifiable',true,'Report',true);
```

Provide the password to modify the protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'sldemo_mdhref_counter','password');
```

Add support for Web view to the protected model that you created.

```
Simulink.ModelReference.modifyProtectedModel(...
'sldemo_mdhref_counter','Mode','CodeGeneration','Webview',true,...
'Report',true);
```

## Input Arguments

**model** — Model name

string or character vector

Model name, specified as a string or character vector. It contains the name of a model or the path name of a Model block that references the protected model to be modified.

**password — Password to modify protected model**

string or character vector

Password, specified as a string or character vector. The password is required for modification of the protected model.

**See Also**

`Simulink.ModelReference.modifyProtectedModel` | `Simulink.ModelReference.protect`

**Introduced in R2014b**

# Simulink.ModelReference.ProtectedModel.setPasswordForSimulation

Add or provide encryption password for simulation of protected model

## Syntax

```
Simulink.ModelReference.ProtectedModel.setPasswordForSimulation(model,
password)
```

## Description

`Simulink.ModelReference.ProtectedModel.setPasswordForSimulation(model, password)` adds an encryption password for simulation if you create a protected model. If you use a protected model, the function provides the required password to simulate the model.

## Examples

### Create a Protected Model with Encryption

Create a protected model with encryption for simulation.

```
Simulink.ModelReference.ProtectedModel.setPasswordForSimulation(...
'sldemo_mdhref_counter', 'password');
Simulink.ModelReference.protect('sldemo_mdhref_counter', ...
'Encrypt', true, 'Report', true);
```

A protected model named `sldemo_mdhref_counter.slxp` is created that requires an encryption password for simulation.

### Simulate an Encrypted Protected Model

Use a protected model with encryption for simulation.

Provide the encryption password required for simulation of the protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForSimulation(...
'sldemo_mdhref_counter', 'password');
```

After you have provided the encryption password, you can simulate the protected model.

## Input Arguments

### **model** — Model name

string or character vector

Model name, specified as a string or character vector. It contains the name of a model or the path name of a Model block that references the protected model.

**password — Password for protected model simulation**

string or character vector

Password, specified as a string or character vector. If the protected model is encrypted for simulation, the password is required.

**See Also**

`Simulink.ModelReference.ProtectedModel.setPasswordForCodeGeneration` |  
`Simulink.ModelReference.ProtectedModel.setPasswordForHDLCodeGeneration` |  
`Simulink.ModelReference.ProtectedModel.setPasswordForView` |  
`Simulink.ModelReference.protect`

**Introduced in R2014b**

# Simulink.ModelReference.ProtectedModel.setPasswordForView

Add or provide encryption password for read-only view of protected model

## Syntax

```
Simulink.ModelReference.ProtectedModel.setPasswordForView(model,password)
```

## Description

`Simulink.ModelReference.ProtectedModel.setPasswordForView(model,password)` adds an encryption password for read-only view if you create a protected model. If you use a protected model, the function provides the required password for a read-only view of the model.

## Examples

### Create a Protected Model with Encryption

Create a protected model with encryption for read-only view.

```
Simulink.ModelReference.ProtectedModel.setPasswordForView(...
'sldemo_mdhref_counter','password');
Simulink.ModelReference.protect('sldemo_mdhref_counter',...
'Webview',true,'Encrypt',true,'Report',true);
```

A protected model named `sldemo_mdhref_counter.slxp` is created that requires an encryption password for read-only view.

### View an Encrypted Protected Model

Use a protected model with encryption for read-only view.

Provide the encryption password required for the read-only view of the protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForView(...
'sldemo_mdhref_counter','password');
```

After you have provided the encryption password, you have access to the read-only view of the protected model.

## Input Arguments

### model — Model name

string or character vector

Model name, specified as a string or character vector. It contains the name of a model or the path name of a Model block that references the protected model.

**password — Password for read-only view of protected model**

string or character vector

Password, specified as a string or character vector. If the protected model is encrypted for read-only view, the password is required.

**See Also**

`Simulink.ModelReference.ProtectedModel.setPasswordForCodeGeneration` |  
`Simulink.ModelReference.ProtectedModel.setPasswordForHDLCodeGeneration` |  
`Simulink.ModelReference.ProtectedModel.setPasswordForSimulation` |  
`Simulink.ModelReference.protect`

**Introduced in R2014b**

# Simulink.ProtectedModel.addTarget

Add code generation support for current target to protected model

## Syntax

```
Simulink.ProtectedModel.addTarget(model)
```

## Description

`Simulink.ProtectedModel.addTarget(model)` adds code generation support for the current `model` target to a protected model of the same name. Each target that the protected model supports is identified by the root of the **Code Generation > System Target file** (`SystemTargetFile`) parameter. For example, if the **System Target file** is `ert.tlc`, the target identifier is `ert`.

To add the current target:

- The model and the protected model of the same name must be on the MATLAB path.
- The protected model must have the `Modifiable` option enabled and have a password for modification.
- The target must be unique in the protected model.

If you add a target to a protected model that did not previously support code generation, the software switches the protected model `Mode` to `CodeGeneration` and `ObfuscateCode` to `true`.

## Examples

### Add a Target to a Protected Model

Add the currently configured model target to the protected model.

Load the model and save a local copy.

```
sldemo_mdref_counter
save_system('sldemo_mdref_counter','mdref_counter.slx');
```

Add a required password for modifying a protected model. If you do not add a password, you are prompted to set a password when you create a modifiable, protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'mdref_counter','password');
```

Create a modifiable, protected model with support for code generation.

```
Simulink.ModelReference.protect('mdref_counter','Mode',...
'CodeGeneration','Modifiable',true,'Report',true);
```

Get a list of targets that the protected model supports.

```
st = Simulink.ProtectedModel.getSupportedTargets('mdref_counter')
```

Configure the unprotected model to support a new target.

```
set_param('mdlref_counter', 'SystemTargetFile', 'ert.tlc');
save_system('mdlref_counter');
```

Add support to the protected model for the new target. You are prompted for the modification password.

```
Simulink.ProtectedModel.addTarget('mdlref_counter');
```

Verify that support for the new target has been added to the protected model.

```
st = Simulink.ProtectedModel.getSupportedTargets('mdlref_counter')
```

## Input Arguments

### **model** — Model name

string or character vector

Model name, specified as a string or character vector. It contains the name of a model or the path name of a Model block that references the protected model.

## See Also

[Simulink.ModelReference.protect](#) | [Simulink.ProtectedModel.getConfigSet](#) |  
[Simulink.ProtectedModel.getCurrentTarget](#) |  
[Simulink.ProtectedModel.getSupportedTargets](#) |  
[Simulink.ProtectedModel.removeTarget](#) | [Simulink.ProtectedModel.setCurrentTarget](#)

## Topics

“Create Protected Models with Multiple Targets”

**Introduced in R2015a**

# Simulink.ProtectedModel.Callback class

**Package:** Simulink.ProtectedModel

Represents callback code that executes in response to protected model events

## Description

For a protected model functionality, the `Simulink.ProtectedModel.Callback` object specifies code to execute in response to an event. The callback code can be a character vector of MATLAB commands or a MATLAB script. The object includes:

- The code to execute for the callback.
- The event that triggers the callback.
- The protected model functionality that the event applies to.
- The option to override the protected model build.

When you create a protected model, to specify callbacks, call the `Simulink.ModelReference.protect` on page 3-184 function with the `'Callbacks'` option. The value of this option is a cell array of `Simulink.ProtectedModel.Callback` objects.

## Construction

`pmCallback = Simulink.ProtectedModel.Callback(event,functionality,callbackText)` creates a callback object for a specific protected model functionality and event. The `callbackText` specifies MATLAB commands to execute for the callback.

`pmCallback = Simulink.ProtectedModel.Callback(event,functionality,callbackFile)` creates a callback object for a specific protected model functionality and event. The `callbackFile` specifies a MATLAB script to execute for the callback. The script must be on the MATLAB path.

## Input Arguments

### event — Event that triggers callback

'PreAccess' | 'Build'

Callback trigger event. Specify one of the following values:

- `'PreAccess'`: Callback code is executed before simulation, build, or read-only viewing.
- `'Build'`: Callback code is executed before build. Valid only for `'CODEGEN'` functionality.

### functionality — Protected model functionality

'CODEGEN' | 'SIM' | 'VIEW' | 'AUTO'

Protected model functionality that the event applies to. Specify one of the following values:

- `'CODEGEN'`: Code generation.
- `'SIM'`: Simulation.

- 'VIEW': Read-only Web view.
- 'AUTO': If the event is 'PreAccess', the callback executes for each functionality. If the event is 'Build', the callback executes only for 'CODEGEN' functionality.

If you do not specify a functionality, the default behavior is 'AUTO'.

**callbackText — Callback code to execute**

string or character vector

MATLAB commands to execute in response to an event, specified as a string or character vector.

**callbackFile — Callback script to execute**

string or character vector

MATLAB script to execute in response to an event, specified as a string or character vector. Script must be on the MATLAB path.

## Properties

**AppliesTo — Protected model functionality**

'CODEGEN' | 'SIM' | 'VIEW' | 'AUTO'

Protected model functionality that the event applies to. Value is one of the following:

- 'CODEGEN': Code generation.
- 'SIM': Simulation.
- 'VIEW': Read-only Web view.
- 'AUTO': If the event is 'PreAccess', the callback executes for each functionality. If the event is 'Build', the callback executes only for 'CODEGEN' functionality.

If you do not specify a functionality, the default behavior is 'AUTO'.

**CallbackFileName — Callback script to execute**

string or character vector

MATLAB script to execute in response to an event, specified as a string or character vector. Script must be on the MATLAB path.

Example: 'pmCallback.m'

**callbackText — Callback code to execute**

string or character vector

MATLAB commands to execute in response to an event, specified as a string or character vector.

Example: 'A = [15 150];disp(A)'

**Event — Event that triggers callback**

'PreAccess' | 'Build'

Callback trigger event. Value is one of the following:

- 'PreAccess': Callback code is executed before simulation, build, or read-only viewing.

- 'Build': Callback code is executed before build. Valid only for 'CODEGEN' functionality.

### OverrideBuild — Option to override protected model build

false (default) | true

Option to override the protected model build process, specified as a Boolean value. Applies only to a callback object that you define for a 'Build' event for 'CODEGEN' functionality. You set this option using the `setOverrideBuild` method.

## Methods

`setOverrideBuild` Specify option to override protected model build

## Copy Semantics

Handle. To learn how handle classes affect copy operations, see Copying Objects (MATLAB).

## Examples

### Create Protected Model Using a Callback

Create a callback object with a character vector of MATLAB commands for the callback code. Specify the object when you create a protected model.

```
pmCallback = Simulink.ProtectedModel.Callback('PreAccess',...
'SIM','disp('Hello world!')')
Simulink.ModelReference.protect('sldemo_mdref_counter',...
'Callbacks',{pmCallback})
sim('sldemo_mdref_basic')
```

For each instance of the protected model reference in the top model, the output is listed.

```
Hello world!
Hello world!
Hello world!
```

### Create Protected Model With a Callback Script

Create a callback object with a MATLAB script for the callback code. Specify the object when you create a protected model.

```
pmCallback = Simulink.ProtectedModel.Callback('Build',...
'CODEGEN','pm_callback.m')
Simulink.ModelReference.protect('sldemo_mdref_counter',...
'Mode','CodeGeneration','Callbacks',{pmCallback})
rtwbuild('sldemo_mdref_basic')
```

Before the protected model build process begins, code in `pm_callback.m` executes.

## See Also

`Simulink.ModelReference.protect` | `Simulink.ProtectedModel.getCallbackInfo`

## Topics

“Define Callbacks for Protected Models”

“Protect Models to Conceal Contents”  
“Code Generation Requirements and Limitations”

**Introduced in R2016a**

# setOverrideBuild

**Class:** Simulink.ProtectedModel.Callback

**Package:** Simulink.ProtectedModel

Specify option to override protected model build

## Syntax

```
setOverrideBuild(override)
```

## Description

`setOverrideBuild(override)` specifies whether a `Simulink.ProtectedModel.Callback` object can override the build process. This method is valid only for callbacks that execute in response to a 'Build' event for 'CODEGEN' functionality.

## Input Arguments

**override — Option to override protected model build process**

false (default) | true

Option to override the protected model build process, specified as a Boolean value. This option applies only to a callback object defined for a 'Build' event for 'CODEGEN' functionality.

Example: `pmcallback.setOverrideBuild(true)`

## Examples

### Create Code Generation Callback to Override Build Process

Create a callback object with a character vector of MATLAB commands for the callback code. Specify that the callback override the build process.

```
pmCallback = Simulink.ProtectedModel.Callback('Build',...
'CODEGEN','disp('Hello world!')')
pmCallback.setOverrideBuild(true);
Simulink.ModelReference.protect('sldemo_mdref_counter',...
'Mode', 'CodeGeneration','Callbacks',{pmCallback})
rtwbuild('sldemo_mdref_basic')
```

## See Also

`Simulink.ModelReference.protect` | `Simulink.ProtectedModel.Callback`

## Topics

“Define Callbacks for Protected Models”

“Protect Models to Conceal Contents”

“Code Generation Requirements and Limitations”

**Introduced in R2016a**

# Simulink.ProtectedModel.CallbackInfo class

**Package:** Simulink.ProtectedModel

Protected model information for use in callbacks

## Description

A `Simulink.ProtectedModel.CallbackInfo` object contains information about a protected model that you can use in the code executed for a callback. The object provides:

- Model name.
- List of models and submodels in the protected model container.
- Callback event.
- Callback functionality.
- Code interface.
- Current target. This information is available only for code generation callbacks.

## Construction

`cbinfoobj = Simulink.ProtectedModel.getCallbackInfo(modelName,event,functionality)` creates a `Simulink.ProtectedModel.CallbackInfo` object.

## Properties

### CodeInterface — Code interface generated by protected model

'Top model' | 'Model reference'

Code interface that the protected model generates.

### Event — Event that triggered callback

'PreAccess' | 'Build'

Callback trigger event. Value is one of the following:

- 'PreAccess': Callback code executed before simulation, build, or read-only viewing.
- 'Build': Callback code executed before build. Valid only for 'CODEGEN' functionality.

### Functionality — Protected model functionality

'CODEGEN' | 'SIM' | 'VIEW' | 'AUTO'

Protected model functionality that the event applies to. Value is one of the following:

- 'CODEGEN': Code generation.
- 'SIM': Simulation.
- 'VIEW': Read-only Web view.
- 'AUTO': If the event is 'PreAccess', the callback executes for each functionality. If the event is 'Build', the callback executes only for 'CODEGEN' functionality.

If the value of `functionality` is blank, the default behavior is `'AUTO'`.

**modelName — Protected model name**

character vector

Protected model name, specified as a character vector.

**SubModels — Models and submodels in the protected model container**

cell array of character vectors

Names of all models and submodels in the protected model container, specified as a cell array of character vectors.

**Target — Current target**

character vector

Current target identifier for the protected model, specified as a character vector. This property is available only for code generation callbacks.

## Methods

`getBuildInfoForModel`                      Get build information object for specified model

## Copy Semantics

Handle. To learn how handle classes affect copy operations, see [Copying Objects \(MATLAB\)](#).

## Examples

**Use Protected Model Information in Simulation Callback**

Create a protected model callback that uses information from the `Simulink.ProtectedModel.Callback` object.

First, on the MATLAB path, create a callback script, `pm_callback.m`, containing:

```
s1 = 'Simulating protected model: ';
cbinfoobj = Simulink.ProtectedModel.getCallbackInfo(...
'sldemo_mdref_counter', 'PreAccess', 'SIM');
disp([s1 cbinfoobj.ModelName])
```

When you create a protected model with a simulation callback, use the script.

```
pmCallback = Simulink.ProtectedModel.Callback('PreAccess'...
, 'SIM', 'pm_callback.m')
Simulink.ModelReference.protect('sldemo_mdref_counter',...
'Callbacks', {pmCallback})
```

Simulate the protected model. For each instance of the protected model reference in the top model, the output from the callback is listed.

```
sim('sldemo_mdref_basic')
```

```
Simulating protected model: sldemo_mdref_counter
Simulating protected model: sldemo_mdref_counter
Simulating protected model: sldemo_mdref_counter
```

## See Also

[Simulink.ModelReference.protect](#) | [Simulink.ProtectedModel.getCallbackInfo](#)

## Topics

[“Define Callbacks for Protected Models”](#)

[“Protect Models to Conceal Contents”](#)

[“Code Generation Requirements and Limitations”](#)

## Introduced in R2016a

## Simulink.ProtectedModel.getCallbackInfo

Get `Simulink.ProtectedModel.CallbackInfo` object for use by callbacks

### Syntax

```
cbinfoobj = Simulink.ProtectedModel.getCallbackInfo(modelName,event,
functionality)
```

### Description

`cbinfoobj = Simulink.ProtectedModel.getCallbackInfo(modelName,event,functionality)` returns a `Simulink.ProtectedModel.CallbackInfo` object that provides information for protected model callbacks. The object contains information about the protected model, including:

- Model name.
- List of models and submodels in the protected model container.
- Callback event.
- Callback functionality.
- Code interface.
- Current target. This information is available only for code generation callbacks.

### Examples

#### Use Protected Model Information in Code Generation Callback

On the MATLAB path, create a callback script, `pm_callback.m`, containing:

```
s1 = 'Code interface is: '
cbinfoobj = Simulink.ProtectedModel.getCallbackInfo(...
'sldemo_mdref_counter','Build','CODEGEN');
disp([s1 cbinfoobj.CodeInterface]);
```

When you create a protected model with a simulation callback, use the script.

```
pmCallback = Simulink.ProtectedModel.Callback('Build',...
'CODEGEN','pm_callback.m')
Simulink.ModelReference.protect('sldemo_mdref_counter',...
'Mode','CodeGeneration','Callbacks',{pmCallback})
```

Build the protected model. Before the start of the protected model build process, the code interface is displayed.

```
rtwbuild('sldemo_mdref_basic')
```

### Input Arguments

**modelName** — Protected model name

string or character vector

Protected model name, specified as a string or character vector.

#### **event — Event that triggered callback**

'PreAccess' | 'Build'

Callback trigger event. Value is one of the following:

- 'PreAccess': Callback code executed before simulation, build, or read-only viewing.
- 'Build': Callback code executed before build. Valid only for 'CODEGEN' functionality.

#### **functionality — Protected model functionality**

'CODEGEN' | 'SIM' | 'VIEW' | 'AUTO'

Protected model functionality that the event applies to. Value is one of the following:

- 'CODEGEN': Code generation.
- 'SIM': Simulation.
- 'VIEW': Read-only Web view.
- 'AUTO': If the event is 'PreAccess', the callback executes for each functionality. If the event is 'Build', the callback executes only for 'CODEGEN' functionality.

If the value of `functionality` is blank, the default behavior is 'AUTO'.

## **Output Arguments**

#### **cbinfoobj — Callback information object**

Simulink.ProtectedModel.CallbackInfo

Callback information, specified as a Simulink.ProtectedModel.CallbackInfo object.

## **See Also**

Simulink.ModelReference.protect | Simulink.ProtectedModel.CallbackInfo

### **Topics**

“Define Callbacks for Protected Models”

“Protect Models to Conceal Contents”

“Code Generation Requirements and Limitations”

### **Introduced in R2016a**

## getBuildInfoForModel

**Class:** Simulink.ProtectedModel.CallbackInfo

**Package:** Simulink.ProtectedModel

Get build information object for specified model

### Syntax

```
bldobj = getBuildInfoForModel(model)
```

### Description

`bldobj = getBuildInfoForModel(model)` returns a handle to an `RTW.BuildInfo` object. This object specifies the build toolchain and arguments. The `model` name must be in the list of model names in the `SubModels` property of the `Simulink.ProtectedModel.CallbackInfo` object. You can call this method only for code generation callbacks in response to a 'Build' event.

### Input Arguments

**model** — Model name

string or character vector

Model name, specified as a string or character vector. The `model` name must be in the list of model names in the `SubModels` property of the `Simulink.ProtectedModel.CallbackInfo` object. You can call this method only for code generation callbacks in response to a 'Build' event.

### Output Arguments

**bldobj** — Object for build toolchain and arguments

`RTW.BuildInfo`

Build toolchain and arguments, specified as a `RTW.BuildInfo` object. If you do not call the method for a code generation callback and 'Build' event, the return value is an empty array.

### Examples

#### Get Build Information from a Code Generation Callback

On the MATLAB path, create a callback script, `pm_callback.m`, containing:

```
cbinfoobj = Simulink.ProtectedModel.getCallbackInfo(...
'sldemo_mdref_counter', 'Build', 'CODEGEN');
bldinfo = cbinfoobj.getBuildInfoForModel(cbinfoobj.ModelName);
buildargs = getBuildArgs(bldinfo)
```

When you create a protected model with a simulation callback, use the script.

```
pmCallback = Simulink.ProtectedModel.Callback('Build', ...
'CODEGEN', 'pm_callback.m')
```

```
Simulink.ModelReference.protect('sldemo_mdref_counter',...
'Mode', 'CodeGeneration', 'Callbacks', {pmCallback})
```

Build the protected model. Before the start of the protected model build, the build arguments are displayed.

```
rtwbuild('sldemo_mdref_basic')
```

## See Also

[Simulink.ModelReference.protect](#) | [Simulink.ProtectedModel.CallbackInfo](#)

## Topics

“Define Callbacks for Protected Models”

“Protect Models to Conceal Contents”

“Code Generation Requirements and Limitations”

## Introduced in R2016a

## Simulink.ProtectedModel.getConfigSet

Get configuration set for current protected model target or for specified target

### Syntax

```
configSet = Simulink.ProtectedModel.getConfigSet(protectedModel)
configSet = Simulink.ProtectedModel.getConfigSet(protectedModel,targetID)
```

### Description

`configSet = Simulink.ProtectedModel.getConfigSet(protectedModel)` returns the configuration set object for the current, protected model target.

`configSet = Simulink.ProtectedModel.getConfigSet(protectedModel,targetID)` returns the configuration set object for a specified target that the protected model supports.

### Examples

#### Get Configuration Set for Current Target

Get the configuration set for the currently configured, protected model target.

Load the model and save a local copy.

```
sldemo_mdref_counter
save_system('sldemo_mdref_counter','mdref_counter.slx');
```

Add a required password for modifying a protected model. If you do not add a password, you are prompted to set a password when you create a modifiable, protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'mdref_counter','password');
```

Create a modifiable, protected model with support for code generation.

```
Simulink.ModelReference.protect('mdref_counter','Mode',...
'CodeGeneration','Modifiable',true,'Report',true);
```

Get the configuration set for the currently configured target.

```
cs = Simulink.ProtectedModel.getConfigSet('mdref_counter')
```

#### Get Configuration Set for Specified Target

Get the configuration set for a specified target that the protected model supports.

Load the model and save a local copy.

```
sldemo_mdref_counter
save_system('sldemo_mdref_counter','mdref_counter.slx');
```

Add a required password for modifying a protected model. If you do not add a password, you are prompted to set a password when you create a modifiable, protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'mdlref_counter', 'password');
```

Create a modifiable, protected model with support for code generation.

```
Simulink.ModelReference.protect('mdlref_counter', 'Mode', ...
'CodeGeneration', 'Modifiable', true, 'Report', true);
```

Configure the unprotected model to support a new target.

```
set_param('mdlref_counter', 'SystemTargetFile', 'ert.tlc');
save_system('mdlref_counter');
```

Add support to the protected model for the new target. You are prompted for the modification password.

```
Simulink.ProtectedModel.addTarget('mdlref_counter');
```

Verify that support for the new target has been added to the protected model.

```
st = Simulink.ProtectedModel.getSupportedTargets('mdlref_counter')
```

Get the configuration set for the added target.

```
cs = Simulink.ProtectedModel.getConfigSet('mdlref_counter', 'ert')
```

## Input Arguments

### **protectedModel** — Model name

string or character vector

Protected model name, specified as a string or character vector.

### **targetID** — Target identifier

string or character vector

Identifier for selected target, specified as a string or character vector. The target identifier is the root of the **Code Generation** > **System Target file** (SystemTargetFile) parameter. For example, if the **System Target file** is `ert.tlc`, the target identifier is `ert`.

## Output Arguments

### **configSet** — Configuration object

Simulink.ConfigSet

Configuration set, specified as a Simulink.ConfigSet object

## See Also

Simulink.ModelReference.protect | Simulink.ProtectedModel.addTarget |  
 Simulink.ProtectedModel.getCurrentTarget |  
 Simulink.ProtectedModel.getSupportedTargets |  
 Simulink.ProtectedModel.removeTarget | Simulink.ProtectedModel.setCurrentTarget

**Topics**

“Create Protected Models with Multiple Targets”

“Reference Protected Models from Third Parties” (Simulink)

**Introduced in R2015a**

# Simulink.ProtectedModel.getCurrentTarget

Get current protected model target

## Syntax

```
currentTarget = Simulink.ProtectedModel.getCurrentTarget(protectedModel)
```

## Description

`currentTarget = Simulink.ProtectedModel.getCurrentTarget(protectedModel)` returns the target identifier for the target that is currently configured for the protected model. At the start of a MATLAB session, the default current target is the last target added to the protected model. Otherwise, the current target is the last target that you used. You can change the current target using the `Simulink.ProtectedModel.setCurrentTarget` function.

When building the model, the software changes the target to match the parent if the currently selected target does not match the target of the parent model.

## Examples

### Get Currently Configured Target for Protected Model

Add a target to a protected model, and then get the currently configured target for the protected model.

Load the model and save a local copy.

```
sldemo_mdref_counter
save_system('sldemo_mdref_counter','mdlref_counter.slx');
```

Add a required password for modifying a protected model. If you do not add a password, you are prompted to set a password when you create a modifiable, protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'mdlref_counter','password');
```

Create a modifiable, protected model with support for code generation.

```
Simulink.ModelReference.protect('mdlref_counter','Mode',...
'CodeGeneration','Modifiable',true,'Report',true);
```

Configure the unprotected model to support a new target.

```
set_param('mdlref_counter','SystemTargetFile','ert.tlc');
save_system('mdlref_counter');
```

Add support to the protected model for the new target. You are prompted for the modification password.

```
Simulink.ProtectedModel.addTarget('mdlref_counter');
```

Verify that support for the new target has been added to the protected model.

```
st = Simulink.ProtectedModel.getSupportedTargets('mdlref_counter')
```

Get the currently configured target for the protected model.

```
ct = Simulink.ProtectedModel.getCurrentTarget('mdlref_counter')
```

## Input Arguments

### **protectedModel** — Model name

string or character vector

Protected model name, specified as a string or character vector.

## Output Arguments

### **currentTarget** — Current target

character vector

Current target for protected model, specified as a character vector.

## See Also

[Simulink.ModelReference.protect](#) | [Simulink.ProtectedModel.addTarget](#) |  
[Simulink.ProtectedModel.getConfigSet](#) |  
[Simulink.ProtectedModel.getSupportedTargets](#) |  
[Simulink.ProtectedModel.removeTarget](#) | [Simulink.ProtectedModel.setCurrentTarget](#)

## Topics

“Create Protected Models with Multiple Targets”

“Reference Protected Models from Third Parties” (Simulink)

## Introduced in R2015a

# Simulink.ProtectedModel.getSupportedTargets

Get list of targets that protected model supports

## Syntax

```
supportedTargets = Simulink.ProtectedModel.getSupportedTargets(
protectedModel)
```

## Description

`supportedTargets = Simulink.ProtectedModel.getSupportedTargets(protectedModel)` returns a list of target identifiers for the code generation targets supported by the specified protected model. The target identifier `sim` represents simulation support.

## Examples

### Get List of Supported Targets for a Protected Model

Add a target to a protected model, and then get a list of supported targets to verify the addition of the new target.

Load the model and save a local copy.

```
sldemo_mdref_counter
save_system('sldemo_mdref_counter','mdref_counter.slx');
```

Add a required password for modifying a protected model. If you do not add a password, you are prompted to set a password when you create a modifiable, protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'mdref_counter','password');
```

Create a modifiable, protected model with support for code generation.

```
Simulink.ModelReference.protect('mdref_counter','Mode',...
'CodeGeneration','Modifiable',true,'Report',true);
```

Configure the unprotected model to support a new target.

```
set_param('mdref_counter','SystemTargetFile','ert.tlc');
save_system('mdref_counter');
```

Add support to the protected model for the new target. You are prompted for the modification password.

```
Simulink.ProtectedModel.addTarget('mdref_counter');
```

Verify that support for the new target has been added to the protected model.

```
st = Simulink.ProtectedModel.getSupportedTargets('mdlref_counter')
```

## Input Arguments

### **protectedModel** — Model name

string or character vector

Protected model name, specified as a string or character vector.

## Output Arguments

### **supportedTargets** — List of target identifiers

cell array of character vectors

List of target identifiers for the targets that the protected model supports, specified as a cell array of character vectors.

## See Also

[Simulink.ModelReference.protect](#) | [Simulink.ProtectedModel.addTarget](#) |  
[Simulink.ProtectedModel.getConfigSet](#) | [Simulink.ProtectedModel.getCurrentTarget](#)  
| [Simulink.ProtectedModel.removeTarget](#) |  
[Simulink.ProtectedModel.setCurrentTarget](#)

## Topics

“Create Protected Models with Multiple Targets”

“Reference Protected Models from Third Parties” (Simulink)

## Introduced in R2015a

# Simulink.ProtectedModel.open

Open protected model

## Syntax

```
Simulink.ProtectedModel.open(model)
Simulink.ProtectedModel.open(model,type)
```

## Description

`Simulink.ProtectedModel.open(model)` opens a protected model. If you do not specify how to view the protected model, the software first tries to open the Web view. If the Web view is not enabled for the protected model, the software then tries to open the report. If you did not create a report, the software reports an error.

`Simulink.ProtectedModel.open(model,type)` opens a protected model using the specified viewing method. If you specify 'webview', the software opens the Web view for the protected model. If you specify 'report', the software opens the protected model report. If the method that you specify is not enabled, the software reports an error. The protected model is not opened.

## Examples

### Open a Protected Model

Open a protected model without a specified method.

Load the model and save a local copy.

```
sldemo_mdhref_counter
save_system('sldemo_mdhref_counter','mdhref_counter.slx');
```

Create a protected model enabling support for code generation and reporting.

```
Simulink.ModelReference.protect('mdhref_counter','Mode',...
'CodeGeneration','Report',true);
```

Open the protected model without specifying how to view it.

```
Simulink.ProtectedModel.open('mdhref_counter')
```

The protected model does not have Web view enabled, so the protected model report is opened.

### Open a Protected Model Web View

Open a protected model, specifying the Web view.

Load the model and save a local copy.

```
sldemo_mdref_counter
save_system('sldemo_mdref_counter','mdlref_counter.slx');
```

Create a protected model with support for code generation, Web view, and reporting.

```
Simulink.ModelReference.protect('mdlref_counter','Mode',...
'CodeGeneration','Webview',true,'Report',true);
```

Open the protected model and specify that you want to see the Web view.

```
Simulink.ProtectedModel.open('mdlref_counter','webview')
```

The protected model Web view is opened.

## Input Arguments

### **model** — Model name

string or character vector

Protected model name, specified as a string or character vector.

### **type** — Open method

'webview' | 'report'

Method for viewing the protected model. If you specify 'webview', the software opens the Web view for the protected model. If you specify 'report', the software opens the protected model report.

## See Also

Simulink.ModelReference.protect

**Introduced in R2015a**

# Simulink.ProtectedModel.removeTarget

Remove support for specified target from protected model

## Syntax

```
Simulink.ProtectedModel.removeTarget(protectedModel,targetID)
```

## Description

`Simulink.ProtectedModel.removeTarget(protectedModel,targetID)` removes code generation support for the specified target from a protected model. You must provide the modification password to make this update. Removing a target does not require access to the unprotected model.

---

**Note** You cannot remove the `sim` target. If you do not want the protected model to support simulation, use the `Simulink.ModelReference.modifyProtectedModel` function to change the protected model mode to `ViewOnly`.

---

## Examples

### Remove Target Support from a Protected Model

Remove a supported target from a protected model.

Load the model and save a local copy.

```
sldemo_mdhref_counter
save_system('sldemo_mdhref_counter','mdhref_counter.slx');
```

Add a required password for modifying a protected model. If you do not add a password, you are prompted to set a password when you create a modifiable, protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'mdhref_counter','password');
```

Create a modifiable, protected model with support for code generation.

```
Simulink.ModelReference.protect('mdhref_counter','Mode',...
'CodeGeneration','Modifiable',true,'Report',true);
```

Configure the unprotected model to support a new target.

```
set_param('mdhref_counter','SystemTargetFile','ert.tlc');
save_system('mdhref_counter');
```

Add support to the protected model for the new target. You are prompted for the modification password.

```
Simulink.ProtectedModel.addTarget('mdhref_counter');
```

Verify that support for the new target has been added to the protected model.

```
st = Simulink.ProtectedModel.getSupportedTargets('mdlref_counter')
```

Remove support for the ert target from the protected model. You are prompted for the modification password.

```
Simulink.ProtectedModel.removeTarget('mdlref_counter','ert');
```

Verify that support for the ert target has been removed from the protected model.

```
st = Simulink.ProtectedModel.getSupportedTargets('mdlref_counter')
```

## Input Arguments

### **protectedModel** — Model name

string or character vector

Protected model name, specified as a string or character vector.

### **targetID** — Target to be removed

string or character vector

Identifier for target to be removed, specified as a string or character vector.

## See Also

[Simulink.ModelReference.modifyProtectedModel](#) | [Simulink.ModelReference.protect](#) | [Simulink.ProtectedModel.addTarget](#) | [Simulink.ProtectedModel.getConfigSet](#) | [Simulink.ProtectedModel.getCurrentTarget](#) | [Simulink.ProtectedModel.getSupportedTargets](#) | [Simulink.ProtectedModel.setCurrentTarget](#)

## Topics

“Create Protected Models with Multiple Targets”

## Introduced in R2015a

# Simulink.ProtectedModel.setCurrentTarget

Configure protected model to use specified target

## Syntax

```
Simulink.ProtectedModel.setCurrentTarget(protectedModel, targetID)
```

## Description

`Simulink.ProtectedModel.setCurrentTarget(protectedModel, targetID)` configures the protected model to use the target that the target identifier specifies.

---

**Note** If you include the protected model in a model reference hierarchy, the software tries to change the current target to match the target of the parent model. If the software cannot match the target of the parent, it reports an error.

---

## Examples

### Set Current Target for Protected Model

After you get a list of supported targets, set the current target for a protected model.

Load the model and save a local copy.

```
sldemo_mdref_counter
save_system('sldemo_mdref_counter','mdref_counter.slx');
```

Add a required password for modifying a protected model. If you do not add a password, you are prompted to set a password when you create a modifiable, protected model.

```
Simulink.ModelReference.ProtectedModel.setPasswordForModify(...
'mdref_counter','password');
```

Create a modifiable, protected model with support for code generation.

```
Simulink.ModelReference.protect('mdref_counter','Mode',...
'CodeGeneration','Modifiable',true,'Report',true);
```

Get a list of targets that the protected model supports.

```
st = Simulink.ProtectedModel.getSupportedTargets('mdref_counter')
```

Configure the unprotected model to support a new target.

```
set_param('mdref_counter','SystemTargetFile','ert.tlc');
save_system('mdref_counter');
```

Add support to the protected model for the new target. You are prompted for the modification password.

```
Simulink.ProtectedModel.addTarget('mdlref_counter');
```

Verify that support for the new target has been added to the protected model.

```
st = Simulink.ProtectedModel.getSupportedTargets('mdlref_counter')
```

Configure the protected model to use the new target.

```
Simulink.ProtectedModel.setCurrentTarget('mdlref_counter','ert');
```

Verify that the current target is the new target.

```
ct = Simulink.ProtectedModel.getCurrentTarget('mdlref_counter')
```

## Input Arguments

### **protectedModel** — Model name

string or character vector

Protected model name, specified as a string or character vector.

### **targetID** — Target identifier

string or character vector

Identifier for selected target, specified as a string or character vector.

## See Also

`Simulink.ModelReference.protect` | `Simulink.ProtectedModel.addTarget` |  
`Simulink.ProtectedModel.getConfigSet` | `Simulink.ProtectedModel.getCurrentTarget` |  
`Simulink.ProtectedModel.getSupportedTargets` |  
`Simulink.ProtectedModel.removeTarget`

## Topics

“Create Protected Models with Multiple Targets”

“Reference Protected Models from Third Parties” (Simulink)

## Introduced in R2015a

# Simulink.ProtectedModel.sign

Attach digital signature to protected model

## Syntax

```
Simulink.ProtectedModel.sign(protectedModel,certificateFile)
```

## Description

`Simulink.ProtectedModel.sign(protectedModel,certificateFile)` attaches a digital signature with the certificate `certificateFile` to the protected model `protectedModel`.

## Examples

### Sign a Protected Model

Protect a model, and then digitally sign it with a certificate.

Open and protect the model that you want to sign. For this example, protect the model `sldemo_mdhref_counter`.

```
sldemo_mdhref_counter
Simulink.ModelReference.protect('sldemo_mdhref_counter');
```

Locate the certificate file that you want to use to sign the protected model. Sign the model by using the certificate file.

```
Simulink.ProtectedModel.sign('sldemo_mdhref_counter.slxp','certificate_file.pfx');
```

In the dialog box, enter the password for the certificate file.

## Input Arguments

### **protectedModel** — Name of protected model

character vector | string scalar

Name of the protected model that you want to sign, specified as a character vector or string scalar. The protected model has a `.slxp` extension.

Example: `'my_model.slxp'`

### **certificateFile** — Certificate file to use for signing

character vector | string scalar

Certificate file to use for signing the protected model, specified as a character vector or string scalar. The certificate must be a PKCS #12 file with the extension `.pfx` or `.p12`.

Example: `'my_cert.pfx'`

Example: `'InstitutionCertificate.p12'`

**See Also**

`Simulink.ModelReference.protect`

**Topics**

“Sign a Protected Model”

**Introduced in R2020a**

# slConfigUIGetVal

Return current value for custom target configuration option

## Syntax

```
value = slConfigUIGetVal(hDlg,hSrc,'OptionName')
```

## Input Arguments

hDlg

Handle created in the context of a `SelectCallback` function and used by the System Target File Callback Interface functions. Pass this variable but do not set it or use it for another purpose.

hSrc

Handle created in the context of a `SelectCallback` function and used by the System Target File Callback Interface functions. Pass this variable but do not set it or use it for another purpose.

'OptionName'

Quoted name of the TLC variable defined for a custom target configuration option.

## Output Arguments

Current value of the specified option. The data type of the return value depends on the data type of the option.

## Description

The `slConfigUIGetVal` function is used in the context of a user-written `SelectCallback` function, which is triggered when you:

- Load the model.
- Update configuration settings in the Configuration Parameters dialog box.
- Build the model.

You use `slConfigUIGetVal` to read the current value of a specified target option.

## Examples

In the following example, the `slConfigUIGetVal` function returns the value of the **Configuration Parameters > Code Generation > Interface > Advanced parameters > Terminate function required** option.

```
function usertarget_selectcallback(hDlg,hSrc)

 disp(['*** Select callback triggered:',sprintf('\n'), ...
 ' Uncheck and disable "Terminate function required".']);

 disp(['Value of IncludeMdlTerminateFcn was ', ...
 slConfigUIGetVal(hDlg,hSrc,'IncludeMdlTerminateFcn')]);
```

```
slConfigUISetVal(hDlg,hSrc,'IncludeMdlTerminateFcn','off');
slConfigUISetEnabled(hDlg,hSrc,'IncludeMdlTerminateFcn',false);
```

### See Also

[slConfigUISetEnabled](#) | [slConfigUISetVal](#)

### Topics

“Define and Display Custom Target Options”

“Custom Target Optional Features”

**Introduced in R2006b**

# slConfigUISetEnabled

Enable or disable custom target configuration option

## Syntax

```
slConfigUISetEnabled(hDlg,hSrc,'OptionName',true)
```

```
slConfigUISetEnabled(hDlg,hSrc,'OptionName',false)
```

## Arguments

hDlg

Handle created in the context of a `SelectCallback` function and used by the System Target File Callback Interface functions. Pass this variable but do not set it or use it for another purpose.

hSrc

Handle created in the context of a `SelectCallback` function and used by the System Target File Callback Interface functions. Pass this variable but do not set it or use it for another purpose.

'OptionName'

Quoted name of the TLC variable defined for a custom target configuration option.

true

Specifies that the option should be enabled.

false

Specifies that the option should be disabled.

## Description

The `slConfigUISetEnabled` function is used in the context of a user-written `SelectCallback` function, which is triggered when the custom target is selected in the System Target File Browser in the Configuration Parameters dialog box. You use `slConfigUISetEnabled` to enable or disable a specified target option.

If you use this function to disable a parameter that is represented in the Configuration Parameters dialog box, the parameter appears greyed out in the dialog context.

## Examples

In the following example, the `slConfigUISetEnabled` function disables the **Configuration Parameters > Code Generation > Interface > Advanced parameters > Terminate function required** option.

```
function usertarget_selectcallback(hDlg,hSrc)
 disp(['*** Select callback triggered:',sprintf('\n'), ...
 ' Uncheck and disable "Terminate function required".']);
 disp(['Value of IncludeMdlTerminateFcn was ', ...
 slConfigUIGetVal(hDlg,hSrc,'IncludeMdlTerminateFcn')]);
```

```
slConfigUISetVal(hDlg,hSrc,'IncludeMdlTerminateFcn','off');
slConfigUISetEnabled(hDlg,hSrc,'IncludeMdlTerminateFcn',false);
```

### See Also

[slConfigUIGetVal](#) | [slConfigUISetVal](#)

### Topics

“Define and Display Custom Target Options”

“Custom Target Optional Features”

**Introduced in R2006b**

# slConfigUISetVal

Set value for custom target configuration option

## Syntax

```
slConfigUISetVal(hDlg,hSrc,'OptionName',OptionValue)
```

## Arguments

**hDlg**

Handle created in the context of a `SelectCallback` function and used by the System Target File Callback Interface functions. Pass this variable but do not set it or use it for another purpose.

**hSrc**

Handle created in the context of a `SelectCallback` function and used by the System Target File Callback Interface functions. Pass this variable but do not set it or use it for another purpose.

**'OptionName'**

Quoted name of the TLC variable defined for a custom target configuration option.

**OptionValue**

Value to be set for the specified option.

## Description

The `slConfigUISetVal` function is used in the context of a user-written `SelectCallback` function, which is triggered when the custom target is selected in the System Target File Browser in the Configuration Parameters dialog box. You use `slConfigUISetVal` to set the value of a specified target option.

## Examples

In the following example, the `slConfigUISetVal` function sets the value 'off' for the **Configuration Parameters > Code Generation > Interface > Advanced parameters > Terminate function required** option.

```
function usertarget_selectcallback(hDlg,hSrc)
 disp(['*** Select callback triggered:',sprintf('\n'), ...
 ' Uncheck and disable "Terminate function required".']);
 disp(['Value of IncludeMdlTerminateFcn was ', ...
 slConfigUIGetVal(hDlg,hSrc,'IncludeMdlTerminateFcn')]);
 slConfigUISetVal(hDlg,hSrc,'IncludeMdlTerminateFcn','off');
 slConfigUISetEnabled(hDlg,hSrc,'IncludeMdlTerminateFcn',false);
```

## See Also

[slConfigUIGetVal](#) | [slConfigUISetEnabled](#)

## Topics

“Define and Display Custom Target Options”

“Custom Target Optional Features”

**Introduced in R2006b**

# switchTarget

Select target for model configuration set

## Syntax

```
switchTarget(myConfigObj,systemTargetFile,[])
switchTarget(myConfigObj,systemTargetFile,targetOptions)
```

## Description

switchTarget(myConfigObj,systemTargetFile,[]) changes the selected system target file for the active configuration set.

switchTarget(myConfigObj,systemTargetFile,targetOptions) sets the configuration parameters specified by targetOptions.

## Examples

### Get ConfigSet, Default Options, and Switch Target

This example shows how to get the active configuration set for model, and change the system target file for the configuration set.

```
% Get configuration set for model
myConfigObj = getActiveConfigSet(model);
% Switch system target file
switchTarget(myConfigObj,'ert.tlc',[]);
```

### Get ConfigSet, Set Options, Switch Target

This example shows how to get the active configuration set for the current model (gcs), set various targetOptions, then change the system target file selection.

```
% Get configuration set for current model
myConfigObj=getActiveConfigSet(gcs);

% Specify target options
targetOptions.TLCOptions = '-aVarName=1';
targetOptions.MakeCommand = 'make_rtw';
targetOptions.Description = 'my target';
targetOptions.TemplateMakefile = 'grt_default_tmf';

% Define a system target file
targetSystemFile='grt.tlc';

% Switch system target file
switchTarget(myConfigObj,targetSystemFile,targetOptions);
```

Use targetOptions to verify values (optional).

```
% Verify values (optional)
targetOptions

 TLCOptions: '-aVarName=1'
 MakeCommand: 'make_rtw'
 Description: 'my target'
 TemplateMakefile: 'grt_default_tmf'
```

### Get ConfigSet, Set Options for MSVC Solution Build, Switch Target to MSVC ERT

This example shows how to get the active configuration set for `model`, then change the system target file to the ERT Create Visual C/C++ Solution File for Embedded Coder.

```
model='rtwdemo_rtwintr0';
open_system(model);

% Get configuration set for model
myConfigObj = getActiveConfigSet(model);

% Specify target options for MSVC build
targetOptions.MakeCommand = 'make_rtw';
targetOptions.Description = ...
 'Create Visual C/C++ Solution File for Embedded Coder';
targetOptions.TemplateMakefile = 'RTW.MSVCCBuild';

% Switch system target file
switchTarget(myConfigObj,'ert.tlc',targetOptions);
```

### Get ConfigSet, Set Options for Toolchain Build, and Switch Target

Use options to select default ERT target file, instead of `set_param(model,'SystemTargetFile','ert.tlc')`.

```
% use switchTarget to select toolchain build of default ERT target
model='rtwdemo_rtwintr0';
open_system(model);

% Get configuration set for model
myConfigObj = getActiveConfigSet(model);

% Specify target options for toolchain build approach
targetOptions.MakeCommand = '';
targetOptions.Description = 'Embedded Coder';
targetOptions.TemplateMakefile = '';

% Switch system target file
switchTarget(myConfigObj,'ert.tlc',targetOptions);
```

## Input Arguments

**myConfigObj** — Configuration set object  
*object*

A configuration set object of `ConfigSet` or configuration reference object of `Simulink.ConfigSetRef`. Call `getActiveConfigSet` to get the configuration set object.

Example: `myConfigObj = getActiveConfigSet(model);`

### **systemTargetFile — Name of system target file**

character vector

Specify the name of the system target file (such as `ert.tlc` for Embedded Coder or `grt.tlc` for Simulink Coder) as the name appears in the **System Target File Browser**.

Example: `systemTargetFile = 'ert.tlc';`

### **targetOptions — Structure with field values that provide configuration parameter options**

struct

Structure with fields that define a code generation target options. You can choose to modify certain configuration parameters by filling in values in a structure field. If you do not want to use options, specify an empty structure (`[]`).

#### **Field Values in targetOptions**

Specify the structure field values of the `targetOptions`. If you choose not to specify options, use an empty structure (`[]`).

Example: `targetOptions = [];`

#### **TemplateMakefile — Character vector specifying file name of template makefile**

character vector

Example: `targetOptions.TemplateMakefile = 'RTW.MSVCBuild';`

#### **TLCOptions — Character vector specifying TLC argument**

character vector

Example: `targetOptions.TLCOptions = '-aVarName=1';`

#### **MakeCommand — Character vector specifying make command MATLAB language file**

character vector

Example: `targetOptions.MakeCommand = 'make_rtw';`

#### **Description — Character vector specifying description of the system target file**

character vector

Example: `targetOptions.Description = 'Create Visual C/C++ Solution File for Embedded Coder';`

## **See Also**

`ConfigSet` | `Simulink.ConfigSetRef` | `getActiveConfigSet`

## **Topics**

“Select a System Target File Programmatically”

“Configure a System Target File”

“Set Target Language Compiler Options”

**Introduced in R2009b**

# target Package

Register new target hardware

## Description

Manage target hardware information

### Classes

|                               |                                                         |
|-------------------------------|---------------------------------------------------------|
| target.Alias                  | Create alternative identifier for target feature object |
| target.LanguageImplementation | Provide C and C++ compiler implementation details       |
| target.Object                 | Base class for target feature classes                   |
| target.Processor              | Provide target processor information                    |

### Functions

|                |                                                   |
|----------------|---------------------------------------------------|
| target.add     | Add target feature object to MATLAB memory        |
| target.create  | Create target feature object                      |
| target.export  | Export target feature data                        |
| target.get     | Retrieve target feature object from MATLAB memory |
| target.remove  | Remove target feature object from MATLAB memory   |
| target.upgrade | Upgrade existing definitions of hardware devices  |

### See Also

#### Topics

“Register New Hardware Devices”

**Introduced in R2019a**

## target.add

**Package:** target

Add target feature object to MATLAB memory

### Syntax

```
target.add(targetFeatureObject)
target.add(targetFeatureObject, 'UserInstall', dataPersistence)
```

### Description

`target.add(targetFeatureObject)` adds the specified target feature object to MATLAB memory. By default, the target data is available only for the current MATLAB session.

`target.add(targetFeatureObject, 'UserInstall', dataPersistence)` controls persistence of target data over MATLAB sessions.

### Examples

#### Create New Hardware Implementation

For workflow examples that use this function, see:

- “Specify Hardware Implementation for New Device”
- “Create Hardware Implementation by Modifying Existing Implementation”
- “Create Hardware Implementation by Reusing Existing Implementation”

### Input Arguments

#### **targetFeatureObject** — Target feature object

object

Specify the target feature object that you want to add to MATLAB memory.

Example: `target.add(myTargetFeatureObject);`

#### **dataPersistence** — Target data persistence

false (default) | true

Control persistence of target data in MATLAB memory:

- `true` -- Target data persists over multiple MATLAB sessions.
- `false` -- Target data is available only for the current MATLAB session.

Example: `target.add(myTargetFeatureObject, 'UserInstall', true);`

Data Types: `logical`

## **See Also**

`target.create` | `target.get` | `target.remove`

## **Topics**

“Register New Hardware Devices”

**Introduced in R2019a**

## target.Alias class

**Package:** target

Create alternative identifier for target feature object

### Description

Use the `target.Alias` class to create alternative identifiers for target feature objects. For example, if a target feature object has a long class identifier, you can create a `target.Alias` object that provides a short identifier for the target feature object.

To create a `target.Alias` object, use the `target.create` function.

### Properties

#### Name — Alternative identifier

character vector | string

Alternative identifier for target feature object.

#### Attributes:

|           |        |
|-----------|--------|
| GetAccess | public |
| SetAccess | public |

#### For — Target feature object

object

Original target feature object.

#### Attributes:

|           |        |
|-----------|--------|
| GetAccess | public |
| SetAccess | public |

### Examples

#### Create Short Identifier for Target Feature Object

For an example that uses this class, see “Create Alternative Identifier for Target Feature Object”.

### See Also

`target.create`

### Topics

“Register New Hardware Devices”

**Introduced in R2019a**

# target.create

**Package:** target

Create target feature object

## Syntax

```
targetFeatureObject = target.create(targetFeatureClass)
targetFeatureObject = target.create(targetFeatureClass,Name,Value)
```

## Description

`targetFeatureObject = target.create(targetFeatureClass)` creates and returns an object of the specified class.

`targetFeatureObject = target.create(targetFeatureClass,Name,Value)` configures the object using one or more name-value pair arguments.

## Examples

### Create New Hardware Implementation

For workflow examples that use this function, see:

- “Specify Hardware Implementation for New Device”
- “Create Hardware Implementation by Modifying Existing Implementation”
- “Create Hardware Implementation by Reusing Existing Implementation”

## Input Arguments

### targetFeatureClass — Target feature class

character vector | string

Specify class of object:

- 'Processor' -- Create `target.Processor` object.
- 'LanguageImplementation' -- Create `target.LanguageImplementation` object.
- 'Alias' -- Create `target.Alias` object.

Example: 'Processor'

### Name-Value Pair Arguments

Specify optional comma-separated pairs of `Name`, `Value` arguments. `Name` is the argument name and `Value` is the corresponding value. `Name` must appear inside quotes. You can specify several name and value pair arguments in any order as `Name1,Value1,...,NameN,ValueN`.

```
Example: myLangImp = target.create('LanguageImplementation', 'Name',
'myLanguageImplementation', 'Copy', 'ARM Compatible-ARM Cortex');
```

```
Example: myProc = target.create('Processor', 'Name', 'myProcessor',
'Manufacturer', 'myProcessorManufacturer');
```

**Copy – Copy existing target feature object**

character vector | string

Create a target feature object by copying values from an existing target feature object.

***propertyName* – Property name**

character vector | string

Create the target feature object with properties that are set to values that you specify.

**Output Arguments****targetFeatureObject – Target feature object**

object

The returned object is a:

- `target.Processor` object if `targetFeatureClass` is `'Processor'`
- `target.LanguageImplementation` object if `targetFeatureClass` is `'LanguageImplementation'`
- `target.Alias` object if `targetFeatureClass` is `'Alias'`

**See Also**`target.add` | `target.get` | `target.remove`**Topics**

“Register New Hardware Devices”

**Introduced in R2019a**

# target.export

**Package:** target

Export target feature data

## Syntax

```
target.export(targetFeatureObject)
target.export(targetFeatureObject,Name,Value)
```

## Description

`target.export(targetFeatureObject)` exports the specified target feature data to a MATLAB function, `registerTargets.m`. Use the generated file to share target feature data between sessions and computers. When you run `registerTargets.m`, it recreates the target feature object and adds the object to MATLAB memory.

`target.export(targetFeatureObject,Name,Value)` exports the specified target feature data using one or more name-value pair arguments.

## Examples

### Share Hardware Device Data

For a workflow example that uses this function, see “Export Hardware Device Data” .

## Input Arguments

### targetFeatureObject — Target feature object

object

Specify the target feature object that you want to export.

Example: `target.export(myTargetFeatureObject);`

### Name-Value Pair Arguments

Specify optional comma-separated pairs of `Name,Value` arguments. `Name` is the argument name and `Value` is the corresponding value. `Name` must appear inside quotes. You can specify several name and value pair arguments in any order as `Name1,Value1,...,NameN,ValueN`.

Example: `target.export(myTargetFeatureObject,'FileName', 'exportMyTargetFeatureFn');`

### FileName — File name

character vector | string

Specify name of MATLAB function file that contains exported target feature data.

### Overwrite — Overwrite flag

false (default) | true

- `true` -- Overwrite MATLAB function file if it exists.
- `false` -- Generate error if MATLAB function file exists. File is not overwritten.

### **See Also**

`target.add` | `target.create`

### **Topics**

“Register New Hardware Devices”

**Introduced in R2019b**

# target.get

**Package:** target

Retrieve target feature object from MATLAB memory

## Syntax

```
targetFeatureObject = target.get(targetFeatureClass, targetFeatureObjectId)
```

## Description

`targetFeatureObject = target.get(targetFeatureClass, targetFeatureObjectId)` retrieves a target feature object from MATLAB memory.

## Examples

### Remove Target Feature Object

This example shows how you can remove a `target.LanguageImplementation` object associated with an object identifier, *myLanguageImplementationID*.

Retrieve the object from MATLAB memory.

```
objectToRemove = target.get('LanguageImplementation', myLanguageImplementationID);
```

Remove the object.

```
target.remove(objectToRemove);
```

## Input Arguments

### targetFeatureClass — Target feature class

character vector | string

Specify the class of the object that you want to retrieve. For example, to retrieve:

- A `target.Processor` object, specify 'Processor'.
- A `target.LanguageImplementation` object, specify 'LanguageImplementation'.

### targetFeatureObjectId — Target feature object identifier

character vector | string

Specify the unique identifier of the object that you want to retrieve, that is, the `Id` property value of the object.

## Output Arguments

### targetFeatureObject — Target feature object

object

Retrieved target feature object. For example:

- If `targetFeatureClass` is 'Processor', the returned object is a `target.Processor` object.
- If `targetFeatureClass` is 'LanguageImplementation', the returned object is a `target.LanguageImplementation` object.

### See Also

`target.add` | `target.create` | `target.remove`

### Topics

"Register New Hardware Devices"

**Introduced in R2019a**

# target.LanguageImplementation class

**Package:** target

Provide C and C++ compiler implementation details

## Description

Use the `target.LanguageImplementation` class to provide implementation details about the C and C++ compiler for your target hardware. For example, byte ordering.

To create a `target.LanguageImplementation` object, use the `target.create` function.

## Properties

### AtomicFloatSize — Largest atomic float size

integer

Size in bits of the largest floating-point data type that you can atomically load and store on the hardware

#### Attributes:

|           |        |
|-----------|--------|
| GetAccess | public |
| SetAccess | public |

Data Types: int32

### AtomicIntegerSize — Largest atomic integer size

integer

Size in bits of the largest integer that you can atomically load and store on the hardware

#### Attributes:

|           |        |
|-----------|--------|
| GetAccess | public |
| SetAccess | public |

Data Types: int32

### Endianness — Byte ordering

'Little' (default) | 'Big' | 'Unspecified'

Byte ordering implemented by target hardware.

#### Attributes:

|           |        |
|-----------|--------|
| GetAccess | public |
| SetAccess | public |

### DataTypes — Data type definitions

object



Data Types: `int32`

## Examples

### Create New Hardware Implementation

For examples that use this class, see:

- “Specify Hardware Implementation for New Device”
- “Create Hardware Implementation by Modifying Existing Implementation”
- “Create Hardware Implementation by Reusing Existing Implementation”

## See Also

`target.Processor` | `target.create`

## Topics

“Register New Hardware Devices”

**Introduced in R2019a**

## target.Object class

**Package:** target

Base class for target feature classes

### Description

target.Object is an abstract base class that enables target feature classes to inherit common functionality.

### Class Attributes

|                  |      |
|------------------|------|
| Abstract         | true |
| HandleCompatible | true |

For information on class attributes, see “Class Attributes” (MATLAB).

### Properties

#### IsValid — Data validity

true | false

#### Attributes:

|           |         |
|-----------|---------|
| GetAccess | public  |
| SetAccess | private |

Data Types: logical

### Methods

#### Public Methods

validate Validate data integrity of target feature object

### Examples

#### Validate Hardware Device Data

For an example that uses this class, see “Validate Hardware Device Data”.

### See Also

#### Topics

“Register New Hardware Devices”

**Introduced in R2019b**

# validate

**Class:** target.Object

**Package:** target

Validate data integrity of target feature object

## Syntax

```
myTargetFeature.validate()
```

## Description

*myTargetFeature*.validate() runs a procedure to validate the data integrity of the object *myTargetFeature*. If the validation procedure fails, the method produces an error.

## Examples

### Validate Hardware Device Data

For an example that uses this method, see “Validate Hardware Device Data”.

## See Also

### Topics

“Register New Hardware Devices”

### Introduced in R2019b

## target.Processor class

**Package:** target

Provide target processor information

### Description

Use the `target.Processor` class to provide information about your target processor. For example, name, manufacturer, and language implementation.

To create a `target.Processor` object, use the `target.create` function.

### Properties

#### Id — Object identifier

character vector | string

The object identifier is the hyphenated combination of the `Manufacturer` and `Name` property values. If the `Manufacturer` property is empty, the object identifier is the `Name` property value.

#### Attributes:

|                        |                      |
|------------------------|----------------------|
| <code>GetAccess</code> | <code>public</code>  |
| <code>SetAccess</code> | <code>private</code> |

#### LanguageImplementations — Language implementation

object

Associated `target.LanguageImplementation` object.

#### Attributes:

|                        |                     |
|------------------------|---------------------|
| <code>GetAccess</code> | <code>public</code> |
| <code>SetAccess</code> | <code>public</code> |

#### Name — Processor name

character vector | string

Name of the target processor.

Example: 'Cortex-A53'

#### Attributes:

|                        |                     |
|------------------------|---------------------|
| <code>GetAccess</code> | <code>public</code> |
| <code>SetAccess</code> | <code>public</code> |

#### Manufacturer — Processor manufacturer

character vector | string

Optional description of the target processor manufacturer.

Example: 'ARM Compatible'

**Attributes:**

|           |        |
|-----------|--------|
| GetAccess | public |
| SetAccess | public |

**Examples****Create New Hardware Implementation**

For examples that use this class, see:

- “Specify Hardware Implementation for New Device”
- “Create Hardware Implementation by Modifying Existing Implementation”
- “Create Hardware Implementation by Reusing Existing Implementation”

**See Also**

`target.LanguageImplementation` | `target.create`

**Topics**

“Register New Hardware Devices”

**Introduced in R2019a**

## target.remove

**Package:** target

Remove target feature object from MATLAB memory

### Syntax

```
target.remove(targetFeatureObject)
target.remove(targetFeatureClass, targetFeatureObjectId)
```

### Description

`target.remove(targetFeatureObject)` removes the target feature object from MATLAB memory.

`target.remove(targetFeatureClass, targetFeatureObjectId)` removes the target feature object specified by class and identifier.

### Examples

#### Remove Target Feature Object From Memory

You can specify and save a hardware device implementation to MATLAB memory.

```
armv8 = target.create('LanguageImplementation', ...
 'Name', 'Armv8-A LP64');
a53 = target.create('Processor', 'Name', 'Cortex-A53', ...
 'Manufacturer', 'ARM Compatible');
a53.LanguageImplementations = armv8;
target.add(a53)
```

When target feature objects are not required, you can use the function to remove the objects from MATLAB memory.

To remove only the `target.Processor` object, run:

```
target.remove(a53)
```

or:

```
target.remove('Processor', 'ARM Compatible-Cortex-A53');
```

### Input Arguments

**targetFeatureObject** — Target feature object  
object

Specify the target feature object that you want to remove.

**targetFeatureClass** — Target feature class  
character vector | string

Specify the class of the target feature object that you want to remove. For example:

- If the class is `target.Processor`, specify `'Processor'`.
- If the class is `target.LanguageImplementation`, specify `'LanguageImplementation'`.

Example: `'Processor'`

### **targetFeatureObjectId — Target feature object identifier**

character vector | string

Specify the unique identifier of the object that you want to remove, that is, the `Id` property value of the object.

### **See Also**

`target.add` | `target.create` | `target.get`

### **Topics**

“Register New Hardware Devices”

**Introduced in R2019a**

# target.upgrade

**Package:** target

Upgrade existing definitions of hardware devices

## Syntax

```
target.upgrade(upgraderForRegistrationMechanism, pathToRegistrationFile)
```

## Description

`target.upgrade(upgraderForRegistrationMechanism, pathToRegistrationFile)` uses an upgrade procedure to create objects from data definitions in current artifacts. The function creates `registerUpgradedTargets.m` in the current working folder.

To register the upgraded data definitions with MATLAB, run `registerUpgradedTargets()`.

For persistence across MATLAB sessions, run `registerUpgradedTargets('UserInstall', true)`.

## Examples

### Upgrade Hardware Device Data Definitions

For a workflow example that uses the function, see “Upgrade Data Definitions for Hardware Devices”.

## Input Arguments

### **upgraderForRegistrationMechanism** — Upgrade procedure

'rtwTargetInfo' | 'sl\_customization'

Select upgrade procedure for current registration mechanism.

### **pathToRegistrationFile** — Full file name

character vector | string

Specify file that contains current registration mechanism.

Example: `target.upgrade('rtwTargetInfo', 'myPath/mySubfolder/rtwTargetInfo.m')`

## See Also

`target.add` | `target.create`

## Topics

“Register New Hardware Devices”

**Introduced in R2019b**

# updateFilePathsAndExtensions

Update files in model build information with missing paths and file extensions

## Syntax

```
updateFilePathsAndExtensions(buildinfo,extensions)
```

## Description

`updateFilePathsAndExtensions(buildinfo,extensions)` specifies the file name extensions (file types) to include in search and update processing.

Using paths from the build information, the `updateFilePathsAndExtensions` function checks whether file references in the build information require an updated path or file extension. Use this function to:

- Maintain build information for a toolchain that requires the use of file extensions.
- Update multiple customized instances of build information for a given model.

If you use `updateFilePathsAndExtensions`, you call it after you add files to the build information. This approach minimizes the potential performance impact of the required disk I/O.

## Examples

### Update File Paths and Extensions in Build Information

In your working folder, create the folder path `etcproj/etc`, add files `etc.c`, `test1.c`, and `test2.c` to the folder `etc`. For this example, the working folder is `w:\work\BuildInfo`. From the working folder, update build information `myModelBuildInfo` with missing paths or file extensions.

```
myModelBuildInfo = RTW.BuildInfo;
addSourcePaths(myModelBuildInfo,fullfile(pwd, ...
 'etcproj','/etc'),'test');
addSourceFiles(myModelBuildInfo,{'etc' 'test1' ...
 'test2'},',' 'test');
before = getSourceFiles(myModelBuildInfo,true,true);
```

```
>> before
```

```
before =
```

```
 '\etc' '\test1' '\test2'
```

```
updateFilePathsAndExtensions(myModelBuildInfo);
after = getSourceFiles(myModelBuildInfo,true,true);
```

```
>> after{:}
```

```
ans =
 'w:\work\BuildInfo\etcproj\etc\etc.c'

ans =
 'w:\work\BuildInfo\etcproj\etc\test1.c'

ans =
 'w:\work\BuildInfo\etcproj\etc\test2.c'
```

## Input Arguments

**buildinfo** — Name of build information object returned by `RTW.BuildInfo` object

**extensions** — File name extensions to include in search and update processing

' .c ' (default) | cell array of character vectors | string

The *extensions* argument specifies the file name extensions (file types) to include in search and update processing. The function checks files and updates paths and extensions based on the order in which you list the extensions in the cell array. For example, if you specify {'.c' '.cpp'} and a folder contains `myfile.c` and `myfile.cpp`, an instance of `myfile` is updated to `myfile.c`.

Example: '.c' '.cpp'

## See Also

`addIncludeFiles` | `addIncludePaths` | `addSourceFiles` | `addSourcePaths` | `updateFileSeparator`

## Topics

“Customize Post-Code-Generation Build Processing”

**Introduced in R2006a**

# updateFileSeparator

Update file separator character for file lists in model build information

## Syntax

```
updateFileSeparator(buildinfo,separator)
```

## Description

`updateFileSeparator(buildinfo,separator)` changes instances of the current file separator (/ or \) in the model build information to the specified file separator.

The default value for the file separator matches the value returned by the MATLAB command `filesep`. For template makefile (TMF) approach builds, you can override the default by defining a separator with the `MAKEFILE_FILESEP` macro in the template makefile. If the `GenerateMakefile` parameter is set, the code generator overrides the default separator and updates the model build information after evaluating the `PostCodeGenCommand` configuration parameter.

## Examples

### Update File Separator in Build Information

Update object `myModelBuildInfo` to apply the Windows® file separator.

```
myModelBuildInfo = RTW.BuildInfo;
updateFileSeparator(myModelBuildInfo, '\');
```

## Input Arguments

### **buildinfo** — RTW.BuildInfo object

object

RTW.BuildInfo object that contains information for compiling and linking generated code.

### **separator** — File separator character for path specifications in the build information

'\ ' | '/'

The separator argument specifies the file separator \ (Windows) or / (UNIX®) to use in file path specifications in the build information.

Example: '\'

## See Also

[addIncludeFiles](#) | [addIncludePaths](#) | [addSourceFiles](#) | [addSourcePaths](#) | [updateFilePathsAndExtensions](#)

## Topics

“Customize Post-Code-Generation Build Processing”

**Introduced in R2006a**

# Simulink Coder Blocks

---

## Async Interrupt

Generate Versa Module Eurocard (VME) interrupt service routines (ISRs) that execute downstream subsystems or Task Sync blocks

**Library:** Simulink Coder / Asynchronous / Interrupt Templates



### Description

For each specified VME interrupt level in the example RTOS (VxWorks®), the Async Interrupt block generates an interrupt service routine (ISR) that calls one of the following:

- A function call subsystem
- A Task Sync block
- A Stateflow chart configured for a function call input event

---

**Note** You can use the blocks in the `vxLib1` library (Async Interrupt and Task Sync) for simulation and code generation. These blocks provide starting point examples to help you develop custom blocks for your target environment.

---

### Assumptions and Limitations

- The block supports VME interrupts 1 through 7.
- The block uses these RTOS (VxWorks) system calls:
  - `sysIntEnable`
  - `sysIntDisable`
  - `intConnect`
  - `intLock`
  - `intUnlock`
  - `tickGet`

### Performance Considerations

Execution of large subsystems at interrupt level can have a significant impact on interrupt response time for interrupts of equal and lower priority in the system. Usually, it is best to keep ISRs as short as possible. Connect only function-call subsystems that contain a few blocks to an Async Interrupt block.

A better solution for large subsystems is using the Task Sync block to synchronize the execution of the function-call subsystem to an RTOS task. Place the Task Sync block between the Async Interrupt block and the function-call subsystem. The Async Interrupt block then uses the Task Sync block as the ISR. The ISR releases a synchronization semaphore (performs a `semGive`) to the task, and returns immediately from interrupt level. The example RTOS (VxWorks) then schedules and runs the task. See the description of the Task Sync block.

## Ports

### Input

#### Input — Simulated interrupt source

scalar

A simulated interrupt source.

### Output Arguments

#### Output — Control signal

scalar

Control signal for a:

- Function-call subsystem
- Task Sync block
- Stateflow chart configured for a function call input event

## Parameters

#### VME interrupt number(s) — VME interrupt numbers for the interrupts to be installed

[1 2] (default) | integer array

An array of VME interrupt numbers for the interrupts to be installed. The valid range is 1 . . 7.

The width of the Async Interrupt block output signal corresponds to the number of VME interrupt numbers specified.

---

**Note** A model can contain more than one Async Interrupt block. However, if you use more than one Async Interrupt block, do not duplicate the VME interrupt numbers specified in each block.

---

#### VME interrupt vector offset(s) — Interrupt vector offset numbers corresponding to the VME interrupt numbers

[192 193] (default) | integer array

An array of unique interrupt vector offset numbers corresponding to the VME interrupt numbers entered for parameter **VME interrupt number(s)**. The Stateflow software passes the offsets to the RTOS (VxWorks) call `intConnect(INUM_TO_IVEC(offset), . . .)`.

#### Simulink task priority(s) — Priority of downstream blocks

[10 11] (default) | integer array

The Simulink priority of downstream blocks. Each output of the Async Interrupt block drives a downstream block (for example, a function-call subsystem). Specify an array of priorities corresponding to the VME interrupt numbers that you specify for parameter **VME interrupt number(s)**.

Parameter **Simulink task priority** values are required to generate a rate transition code (see “Rate Transitions and Asynchronous Blocks”). Simulink task priority values are also required to maintain

absolute time integrity when the asynchronous task must obtain real time from its base rate or its caller. The assigned priorities typically are higher than the priorities assigned to periodic tasks.

---

**Note** The Simulink software does not simulate asynchronous task behavior. The task priority of an asynchronous task is for code generation purposes only and is not honored during simulation.

---

#### **Preemption flag(s); preemptable-1; non-preemptable-0 — Selects preemption**

[0 1] (default) | integer array

Set this option to 1 if an output signal of the Async Interrupt block drives a Task Sync block.

Higher priority interrupts can preempt lower priority interrupts in the example RTOS (VxWorks). To lock out interrupts during the execution of an ISR, set the pre-emption flag to 0. This setting causes generation of `intLock()` and `intUnlock()` calls at the beginning and end of the ISR code. Use interrupt locking carefully, as it increases the interrupt response time of the system for interrupts at the `intLockLevelSet()` level and below. Specify an array of flags corresponding to the VME interrupt numbers entered for parameter **VME interrupt number(s)**.

---

**Note** The number of elements in the arrays specifying parameters **VME interrupt vector offset(s)** and **Simulink task priority** must match the number of elements in the array specified for parameter **VME interrupt number(s)**.

---

#### **Manage own timer — Select timer manager**

on (default) | off

If selected, the ISR generated by the Async Interrupt block manages its own timer by reading absolute time from the hardware timer. Specify the size of the hardware timer with parameter **Timer size**.

#### **Timer resolution (seconds) — Resolution of ISR timer**

1/60 (default)

The resolution of the ISRs timer. ISRs generated by the Async Interrupt block maintain their own absolute time counters. By default, these timers obtain their values from the RTOS (VxWorks) kernel by using the `tickGet` call. Parameter **Timer resolution** determines the resolution of these counters. The default resolution is 1/60 second. The `tickGet` resolution for your board support package (BSP) can be different. Determine the `tickGet` resolution for your BSP and enter it for parameter **Timer resolution**.

If you are targeting an RTOS other than the example RTOS (VxWorks), replace the `tickGet` call with an equivalent call to the target RTOS. Or, generate code to read the timer register on the target hardware. For more information, see “Timers in Asynchronous Tasks” and “Async Interrupt Block Implementation”.

#### **Timer size — Number of bits to store the clock tick**

32bits (default) | 16bits | 8bits | auto

The number of bits to store the clock tick for a hardware timer. The ISR generated by the Async Interrupt block uses the timer size when you select parameter **Manage own timer**. The size can be 32bits (the default), 16bits, 8bits, or auto. If you select auto, the code generator determines

the timer size based on the settings of parameters **Application lifespan (days)** and **Timer resolution**.

By default, timer values are stored as 32-bit integers. When parameter **Timer size** is set to **auto**, you can indirectly control the word size of the counters by setting parameter **Application lifespan (days)**. If you set **Application lifespan (days)** to a value that is too large for the code generator to handle as a 32-bit integer of the specified resolution, the code generator uses a second 32-bit integer to address overflows.

For more information, see “Control Memory Allocation for Time Counters”. See also “Timers in Asynchronous Tasks”.

### **Enable simulation input – Select add simulation input port**

on (default) | off

If selected, the Simulink software adds an input port to the Async Interrupt block. This port is for simulation only. Connect one or more simulated interrupt sources to the simulation input.

---

**Note** Before generating code, consider removing blocks that drive the simulation input to prevent the blocks from contributing to the generated code. Alternatively, you can use the Environment Controller block, as explained in “Dual-Model Approach: Code Generation”. If you use the Environment Controller block, the sample times of driving blocks contribute to the sample times supported in the generated code.

---

## **See Also**

Task Sync

### **Topics**

“Asynchronous Events”


“Asynchronous Events”

**Introduced in R2006a**

## Asynchronous Task Specification

Specify priority of asynchronous task represented by referenced model triggered by asynchronous interrupt

**Library:** Simulink Coder / Asynchronous




### Description

The Asynchronous Task Specification block specifies parameters, such as the task priority, of an asynchronous task represented by a function-call subsystem with a trigger from an asynchronous interrupt. Use this block to control scheduling of function-call subsystems with triggers from asynchronous events. You control the scheduling by assigning a priority to each function-call subsystem within a referenced model.

To use this block, follow the procedure in “Convert an Asynchronous Subsystem into a Model Reference”.

Observe in the figure:

- The block must reside in a referenced model between a root-level Inport block and a function-call subsystem. The Asynchronous Task Specification block must immediately follow and connect directly to the Inport block.
- The Inport block must receive an interrupt signal from an Async Interrupt block that is in the parent model.
- The Inport block must be configured to receive and send function-call trigger signals.



## Ports

### Input

#### Port\_1 – Interrupt input signal

scalar

Interrupt input signal received from a root-level Inport block.

### Output

#### Port\_1 – Interrupt signal with priority

scalar

Interrupt signal with specified task priority that triggers a function-call subsystem.

## Parameters

#### Task priority – Priority of asynchronous task that calls function-call subsystem


10 (default)

Specify an integer or [] as the priority of the asynchronous task that calls the connected function-call subsystem. The priority must be a value that generates relevant rate transition behaviors.


- If you specify an integer, it must match the priority value of the interrupt signal initiator in the parent model.

- If you specify [], the priority does not have to match the priority of the interrupt signal initiator in the top model. The rate transition algorithm is conservative (not optimized). The priority is unknown but static.

Consider the following model.



The referenced model has the following content.



If the **Task priority** parameter is set to 10, the Async Interrupt block in the parent model must also have a priority of 10. If the parameter is set to [], the priority of the Async Interrupt block can be a value other than 10.

## See Also

### Blocks

Function-Call Subsystem | Inport

### Topics

- “Asynchronous Events”
- “Spawn and Synchronize Execution of RTOS Task”
- “Pass Asynchronous Events in RTOS as Input To a Referenced Model”
- “Convert an Asynchronous Subsystem into a Model Reference”
- “Rate Transitions and Asynchronous Blocks”
- “Asynchronous Support”
- “Asynchronous Events”
- “Model References” (Simulink)

**Introduced in R2011a**

# Generated S-Function

Represent model or subsystem as generated S-function code

**Library:** Simulink Coder / S-Function Target



## Description

An instance of the Generated S-Function block represents code that the code generator produces from its S-function system target file for a model or subsystem. For example, you extract a subsystem from a model and build a Generated S-Function block from it by using the S-function target. This mechanism can be useful for:

- Converting models and subsystems to application components
- Reusing models and subsystems
- Optimizing simulation—often, an S-function simulates more efficiently than the original model

For details on how to create a Generated S-Function block from a subsystem, see “Create S-Function Blocks from a Subsystem”.

## Requirements

- The S-Function block must perform identically to the model or subsystem from which it was generated.
- Before creating the block, explicitly specify Inport block signal attributes, such as signal widths or sample times. The sole exception to this rule concerns sample times, as described in “Sample Time Propagation in Generated S-Functions”.
- Set the solver parameters of the Generated S-Function block to be the same as the parameters of the original model or subsystem. The generated S-function code operates identically to the original subsystem (for an exception to this rule, see “Choose a Solver Type”).

## Ports

### Input

#### Input — S-function input

varies

See requirements.

### Output Arguments

#### Output — S-function output

varies

See requirements.

## Parameters

### **Generated S-function name (model\_sf) — Name of S-function**

model\_sf (default) | character vector

The name of the generated S-function. The code generator derives the name by appending `_sf` to the name of the model or subsystem from which the block is generated.

### **Show module list — Select display module list**

off (default) | on

If selected, displays modules generated for the S-function.

## See Also

### **Topics**


“Generate S-Function from Subsystem”

“Create S-Function Blocks from a Subsystem”

### **Introduced in R2011b**

# Model Header

Specify external header code



## Description

For a model that includes the Model Header block, the code generator adds external code that you specify to the header file (*model.h*) that it generates. You can specify code for the code generator to add near the top and bottom of the header file.

If you include this block in a referenced model, the code generator ignores the block for simulation target builds, but processes the block for other system target files.

## Parameters

### Top of Model Header — Code to add near top of generated header file

Specify code that you want the code generator to add near the top of the header file for the model. The code generator places the code in the section labeled `user code (top of header file)`.

### Bottom of Model Header — Code to add at bottom of generated header file

Specify code that you want the code generator to add at the bottom of the header file for the model. The code generator places the code in the section labeled `user code (bottom of header file)`.

## See Also

[Model Source](#) | [System Disable](#) | [System Outputs](#) | [System Update](#) | [System Derivatives](#) | [System Enable](#) | [System Initialize](#) | [System Start](#) | [System Terminate](#)

## Topics

“Place External C/C++ Code in Generated Code” (Embedded Coder)

**Introduced in R2006a**

## Model Source

Specify external source code



### Description

For a model that includes the Model Source block, the code generator adds external code that you specify to the source file (*model.c* or *model.cpp*) that it generates. You can specify code for the code generator to add near the top and bottom of the source file.

If you include this block in a referenced model, the code generator ignores the block for simulation target builds, but processes the block for other system target files.

### Parameters

#### Top of Model Source — Code to add near top of generated source file

Specify code that you want the code generator to add near the top of the source file for the model. The code generator places the code in the section labeled `user code (top of source file)`.

#### Bottom of Model Source — Code to add at bottom of generated source file

Specify code that you want the code generator to add at the bottom of the source file for the model. The code generator places the code in the section labeled `user code (bottom of source file)`.

### Example

See “Add External Code to Generated Start Function”.

### See Also

[Model Header](#) | [System Disable](#) | [System Outputs](#) | [System Update](#) | [System Derivatives](#) | [System Enable](#) | [System Initialize](#) | [System Start](#) | [System Terminate](#)


### Topics

“Place External C/C++ Code in Generated Code” (Embedded Coder)

**Introduced in R2006a**

# System Derivatives

Specify external system derivative code



## Description

For a model or nonvirtual subsystem that includes the System Derivatives block and a block that computes continuous states, the code generator adds external code, which you specify, to the `SystemDerivatives` function that it generates. You can specify code for the code generator to add to the declaration, execution, and exit sections of the function code.

---

**Note** If you include this block in a referenced model, the code generator ignores the block for simulation target builds, but processes the block for other system target files.

---

## Parameters

### **System Derivatives Function Declaration Code — Code to add to the declaration section of the generated function**

Specify code that you want the code generator to add to the declaration section of the `SystemDerivatives` function for the model or subsystem.

### **System Derivatives Function Execution Code — Code to add to the execution section of the generated function**

Specify code that you want the code generator to add to the execution section of the `SystemDerivatives` function for the model or subsystem.

### **System Derivatives Function Exit Code — Code to add to the exit section of the generated function**

Specify code that you want the code generator to add to the exit section of the `SystemDerivatives` function for the model or subsystem.

## See Also

[Model Header](#) | [Model Source](#) | [System Initialize](#) | [System Disable](#) | [System Enable](#) | [System Outputs](#) | [System Start](#) | [System Terminate](#) | [System Update](#)


## Topics

“Place External C/C++ Code in Generated Code” (Embedded Coder)

**Introduced in R2006a**

# System Disable

Specify external system disable code



## Description

For a model or nonvirtual subsystem that includes the System Disable block and a block that uses a `SystemDisable` function, the code generator adds external code, which you specify, to the `SystemDisable` function that it generates. You can specify code for the code generator to add to the declaration, execution, and exit sections of the function code.

---

**Note** If you include this block in a referenced model, the code generator ignores the block for simulation target builds, but processes the block for other system target files.

---

## Parameters

### **System Disable Function Declaration Code — Code to add to the declaration section of the generated function**

Specify code that you want the code generator to add to the declaration section of the `SystemDisable` function for the model or subsystem.

### **System Disable Function Execution Code — Code to add to the execution section of the generated function**

Specify code that you want the code generator to add to the execution section of the `SystemDisable` function for the model or subsystem.

### **System Disable Function Exit Code — Code to add to the exit section of the generated function**

Specify code that you want the code generator to add to the exit section of the `SystemDisable` function for the model or subsystem.

## See Also

Model Header | Model Source | System Initialize | System Derivatives | System Enable | System Outputs | System Start | System Terminate | System Update


## Topics

“Place External C/C++ Code in Generated Code” (Embedded Coder)

**Introduced in R2006a**

# System Enable

Specify external system enable code



## Description

For a model or nonvirtual subsystem that includes the System Enable block and a block that uses a SystemEnable function, the code generator adds external code, which you specify, to the SystemEnable function that it generates. You can specify code for the code generator to add to the declaration, execution, and exit sections of the function code.

---

**Note** If you include this block in a referenced model, the code generator ignores the block for simulation target builds, but processes the block for other system target files.

---

## Parameters

### **System Enable Function Declaration Code — Code to add to the declaration section of the generated function**

Specify code that you want the code generator to add to the declaration section of the SystemEnable function for the model or subsystem.

### **System Enable Function Execution Code — Code to add to the execution section of the generated function**

Specify code that you want the code generator to add to the execution section of the SystemEnable function for the model or subsystem.

### **System Enable Function Exit Code — Code to add to the exit section of the generated function**

Specify code that you want the code generator to add to the exit section of the SystemEnable function for the model or subsystem.

## See Also

[Model Header](#) | [Model Source](#) | [System Initialize](#) | [System Derivatives](#) | [System Disable](#) | [System Outputs](#) | [System Start](#) | [System Terminate](#) | [System Update](#)


## Topics

“Place External C/C++ Code in Generated Code” (Embedded Coder)

**Introduced in R2006a**

# System Initialize

Specify external system initialization code



## Description

For a model or nonvirtual subsystem that includes the System Initialize block and a block that uses a SystemInitialize function, the code generator adds external code, which you specify, to the SystemInitialize function that it generates. You can specify code for the code generator to add to the declaration, execution, and exit sections of the function code.

---

**Note** If you include this block in a referenced model, the code generator ignores the block for simulation target builds, but processes the block for other system target files.

---

## Parameters

### **System Initialize Function Declaration Code — Code to add to the declaration section of the generated function**

Specify code that you want the code generator to add to the declaration section of the SystemInitialize function for the model or subsystem.

### **System Initialize Function Execution Code — Code to add to the execution section of the generated function**

Specify code that you want the code generator to add to the execution section of the SystemInitialize function for the model or subsystem.

### **System Initialize Function Exit Code — Code to add to the exit section of the generated function**

Specify code that you want the code generator to add to the exit section of the SystemInitialize function for the model or subsystem.

## See Also

Model Header | Model Source | System Enable | System Derivatives | System Disable | System Outputs | System Start | System Terminate | System Update


## Topics

“Place External C/C++ Code in Generated Code” (Embedded Coder)

**Introduced in R2006a**

# System Outputs

Specify external system outputs code



## Description

For a model or nonvirtual subsystem that includes the System Outputs block and a block that uses a SystemOutputs function, the code generator adds external code, which you specify, to the SystemOutputs function that it generates. You can specify code for the code generator to add to the declaration, execution, and exit sections of the function code.

---

**Note** If you include this block in a referenced model, the code generator ignores the block for simulation target builds, but processes the block for other system target files.

---

## Parameters

### **System Outputs Function Declaration Code — Code to add to the declaration section of the generated function**

Specify code that you want the code generator to add to the declaration section of the SystemOutputs function for the model or subsystem.

### **System Outputs Function Execution Code — Code to add to the execution section of the generated function**

Specify code that you want the code generator to add to the execution section of the SystemOutputs function for the model or subsystem.

### **System Outputs Function Exit Code — Code to add to the exit section of the generated function**

Specify code that you want the code generator to add to the exit section of the SystemOutputs function for the model or subsystem.

## See Also

[Model Header](#) | [Model Source](#) | [System Enable](#) | [System Derivatives](#) | [System Disable](#) | [System Initialize](#) | [System Start](#) | [System Terminate](#) | [System Update](#)


## Topics

“Place External C/C++ Code in Generated Code” (Embedded Coder)

**Introduced in R2006a**

# System Start

Specify external system startup code



## Description

For a model or nonvirtual subsystem that includes the System Start block and a block that uses a SystemStart function, the code generator adds external code, which you specify, to the SystemStart function that it generates. You can specify code for the code generator to add to the declaration, execution, and exit sections of the function code.

---

**Note** If you include this block in a referenced model, the code generator ignores the block for simulation target builds, but processes the block for other system target files.

---

## Parameters

### **System Start Function Declaration Code — Code to add to the declaration section of the generated function**

Specify code that you want the code generator to add to the declaration section of the SystemStart function for the model or subsystem.

### **System Start Function Execution Code — Code to add to the execution section of the generated function**

Specify code that you want the code generator to add to the execution section of the SystemStart function for the model or subsystem.

### **System Start Function Exit Code — Code to add to the exit section of the generated function**

Specify code that you want the code generator to add to the exit section of the SystemStart function for the model or subsystem.

## See Also

[Model Header](#) | [Model Source](#) | [System Enable](#) | [System Terminate](#) | [System Derivatives](#) | [System Disable](#) | [System Initialize](#) | [System Outputs](#) | [System Update](#)


## Topics

“Place External C/C++ Code in Generated Code” (Embedded Coder)

**Introduced in R2006a**

# System Terminate

Specify external system termination code



## Description

For a model or nonvirtual subsystem that includes the System Terminate block and a block that uses a SystemTerminate function, the code generator adds external code, which you specify, to the SystemTerminate function that it generates. You can specify code for the code generator to add to the declaration, execution, and exit sections of the function code.

---

**Note** If you include this block in a referenced model, the code generator ignores the block for simulation target builds, but processes the block for other system target files.

---

## Parameters

### **System Terminate Function Declaration Code — Code to add to the declaration section of the generated function**

Specify code that you want the code generator to add to the declaration section of the SystemTerminate function for the model or subsystem.

### **System Disable Terminate Execution Code — Code to add to the execution section of the generated function**

Specify code that you want the code generator to add to the execution section of the SystemTerminate function for the model or subsystem.

### **System Disable Terminate Exit Code — Code to add to the exit section of the generated function**

Specify code that you want the code generator to add to the exit section of the SystemTerminate function for the model or subsystem.

## See Also

[Model Header](#) | [Model Source](#) | [System Enable](#) | [System Start](#) | [System Derivatives](#) | [System Disable](#) | [System Initialize](#) | [System Outputs](#) | [System Update](#)


## Topics

“Place External C/C++ Code in Generated Code” (Embedded Coder)

**Introduced in R2006a**

# System Update

Specify external system update code



## Description

For a model or nonvirtual subsystem that includes the System Update block and a block that uses a `SystemUpdate` function, the code generator adds external code, which you specify, to the `SystemUpdate` function that it generates. You can specify code for the code generator to add to the declaration, execution, and exit sections of the function code.

---

**Note** If you include this block in a referenced model, the code generator ignores the block for simulation target builds, but processes the block for other system target files.

---

## Parameters

### System Update Function Declaration Code — Code to add to the declaration section of the generated function

Specify code that you want the code generator to add to the declaration section of the `SystemUpdate` function for the model or subsystem.

### System Update Function Execution Code — Code to add to the execution section of the generated function

Specify code that you want the code generator to add to the execution section of the `SystemUpdate` function for the model or subsystem.

### System Update Function Exit Code — Code to add to the exit section of the generated function

Specify code that you want the code generator to add to the exit section of the `SystemUpdate` function for the model or subsystem.

## See Also

[Model Header](#) | [Model Source](#) | [System Enable](#) | [System Start](#) | [System Derivatives](#) | [System Disable](#) | [System Initialize](#) | [System Outputs](#) | [System Terminate](#)

## Topics

“Place External C/C++ Code in Generated Code” (Embedded Coder)

**Introduced in R2006a**

## Task Sync

Run code of downstream function-call subsystem or Stateflow chart by spawning an example RTOS (VxWorks) task

**Library:** Simulink Coder / Asynchronous / Interrupt Templates



### Description

The Task Sync block spawns an example RTOS (VxWorks) task that calls a function-call subsystem or Stateflow chart. Typically, you place the Task Sync block between an Async Interrupt block and a function-call subsystem block or Stateflow chart. Alternatively, you could connect the Task Sync block to the output port of a Stateflow diagram that has an event, **Output to Simulink**, configured as a function call.

The Task Sync block:

- Uses the RTOS (VxWorks) system call `taskSpawn` to spawn an independent task. When the task is activated, it calls the downstream function-call subsystem code or Stateflow chart. The block calls `taskDelete` to delete the task during model termination.
- Creates a semaphore to synchronize the connected subsystem with execution of the block.
- Wraps the spawned task in an infinite `for` loop. In the loop, the spawned task listens for the semaphore by using `semTake`. The first call to `semTake` specifies `NO_WAIT`. This setting lets the task determine whether a second `semGive` has occurred before the completion of the function-call subsystem or chart. This sequence indicates that the interrupt rate is too fast or the task priority is too low.
- Generates synchronization code (for example, `semGive()`). This code lets the spawned task run. The task in turn calls the connected function-call subsystem code. The synchronization code can run at interrupt level. The connection between the Async Interrupt and Task Sync blocks accomplishes this operation and triggers execution of the Task Sync block within an ISR.
- Supplies absolute time if blocks in the downstream algorithmic code require it. The time comes from the timer maintained by the Async Interrupt block or comes from an independent timer maintained by the task associated with the Task Sync block.

When you design your application, consider when timer and signal input values could be taken for the downstream function-call subsystem that is connected to the Task Sync block. By default, the time and input data are read when the RTOS (VxWorks) activates the task. For this case, the data (input and time) are synchronized to the task itself. If you select the **Synchronize the data transfer of this task with the caller task** option and the Task Sync block driver is an Async Interrupt block, the time and input data are read when the interrupt occurs (that is, within the ISR). For this case, data is synchronized with the caller of the Task Sync block.

---

**Note** You can use the blocks in the `vxlib1` library (Async Interrupt and Task Sync) for simulation and code generation. These blocks provide starting point examples to help you develop custom blocks for your target environment.

---

## Ports

### Input

#### **Input — Call from interrupt block**

call

A call from an Async Interrupt block.

### Output Arguments

#### **Output — Call to function-call subsystem**

call

A call to a function-call subsystem.

## Parameters

#### **Taskname (10 characters or less) — Task function name**

Task0 (default) | character vector

The first argument passed to the `taskSpawn` system call in the RTOS. The RTOS (VxWorks) uses this name as the task function name. This name also serves as a debugging aid. Routines use the task name to identify the task from which they are called.

#### **Simulink task priority (0–255) — RTOS task priority**

50 (default) | integer

The RTOS task priority assigned to the function-call subsystem task when spawned. RTOS (VxWorks) priorities range from 0 to 255, with 0 representing the highest priority.

---

**Note** The Simulink software does not simulate asynchronous task behavior. The task priority of an asynchronous task is for code generation purposes only and is not honored during simulation.

---

#### **Stack size (bytes) — Maximum size for stack of the task**

1024 (default) | integer

Maximum size to which the stack of the task can grow. The stack size is allocated when the RTOS (VxWorks) spawns the task. Choose a stack size based on the number of local variables in the task. Determine the size by examining the generated code for the task (and functions that are called from the generated code).

#### **Synchronize the data transfer of this task with the caller task — Select synchronization**

off (default) | on

If not selected (the default),

- The block maintains a timer that provides absolute time values required by the computations of downstream blocks. The timer is independent of the timer maintained by the Async Interrupt block that calls the Task Sync block.

- A **Timer resolution** option appears.
- The **Timer size** option specifies the word size of the time counter.

If selected,

- The block does not maintain an independent timer and does not display the **Timer resolution** field.
- Downstream blocks that require timers use the timer maintained by the Async Interrupt block that calls the Task Sync block (see “Timers in Asynchronous Tasks”). The timer value is read at the time the asynchronous interrupt is serviced. Data transfers to blocks called by the Task Sync block execute within the task associated with the Async Interrupt block. Therefore, data transfers are synchronized with the caller.

#### **Timer resolution (seconds) — Resolution for timer of the block**

1/60 (default)

The resolution of the timer of the block in seconds. This option appears only if **Synchronize the data transfer of this task with the caller task** is not selected. By default, the block gets the timer value by calling the tickGet function in the RTOS (VxWorks). The default resolution is 1/60 second.

#### **Timer size — Number of bits to store clock tick**

32bits (default) | 16bits | 8bits | auto

The number of bits to store the clock tick for a hardware timer. The size can be 32bits (the default), 16bits, 8bits, or auto. If you select auto, the code generator determines the timer size based on the settings of **Application lifespan (days)** and **Timer resolution**.

By default, timer values are stored as 32-bit integers. When **Timer size** is auto, you can indirectly control the word size of the counters by setting the **Application lifespan (days)** option. If you set **Application lifespan (days)** to a value that is too large for the code generator to handle as a 32-bit integer of the specified resolution, it uses a second 32-bit integer to address overflows.

For more information, see “Control Memory Allocation for Time Counters”. See also “Timers in Asynchronous Tasks”.

### **See Also**

Async Interrupt

### **Topics**

“Asynchronous Events”

**Introduced in R2006a**



# Code Generation Parameters: Code Generation

---

## Model Configuration Parameters: Code Generation

The **Code Generation** category includes parameters for defining the code generation process including target selection. It also includes parameters for inserting comments and pragmas into the generated code for data and functions. These parameters require a Simulink Coder license. Additional parameters available with an ERT-based target require an Embedded Coder license.

These configuration parameters appear in the **Configuration Parameters > Code Generation** general category.

| Parameter                                                              | Description                                                                                        |
|------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------|
| "System target file" on page 5-6                                       | Specify which target file configuration will be used.                                              |
| "Browse" on page 5-8                                                   | Browse file configuration options.                                                                 |
| "Language" on page 5-9                                                 | Specify C or C++ code generation.                                                                  |
| "Description" on page 5-11                                             | A description of the target file.                                                                  |
| "Generate code only" on page 5-31                                      | Specify code generation versus an executable build.                                                |
| "Package code and artifacts" on page 5-32                              | Specify whether to automatically package generated code and artifacts for relocation.              |
| "Zip file name" on page 5-33                                           | Specify the name of the .zip file in which to package generated code and artifacts for relocation. |
| "Compiler optimization level" on page 5-17                             | Control compiler optimizations for building generated code.                                        |
| "Custom compiler optimization flags" on page 5-19                      | Specify custom compiler optimization flags.                                                        |
| "Toolchain" on page 5-12                                               | Specify the toolchain to use when building an executable or library.                               |
| "Build configuration" on page 5-14                                     | Specify compiler optimization or debug settings for toolchain.                                     |
| "Tool/Options" on page 5-16                                            | Display or customize build configuration settings.                                                 |
| "Generate makefile" on page 5-20                                       | Enable generation of a makefile based on a template makefile.                                      |
| "Make command" on page 5-22                                            | Specify a make command and optionally append makefile options.                                     |
| "Template makefile" on page 5-24                                       | Specify the template makefile from which to generate the makefile.                                 |
| "Select objective" on page 5-26                                        | Select a code generation objective to use with the Code Generation Advisor.                        |
| "Prioritized objectives" (Embedded Coder)                              | List of prioritized code generation objectives.                                                    |
| "Set Objectives" (Embedded Coder)                                      | Open Configuration Set Objectives dialog box.                                                      |
| "Set Objectives — Code Generation Advisor Dialog Box" (Embedded Coder) | Select and prioritize code generation objectives.                                                  |

| Parameter                                         | Description                                                                  |
|---------------------------------------------------|------------------------------------------------------------------------------|
| "Check model before generating code" on page 5-29 | Choose whether to run Code Generation Advisor checks before generating code. |
| "Check Model" on page 5-28                        | Check whether the model meets code generation objectives.                    |

These configuration parameters are under the **Advanced parameters**.

| Parameter                                                       | Description                                                                                                   |
|-----------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------|
| "Custom FFT library callback" on page 5-34                      | Specify a callback class for FFTW library calls in code generated for FFT functions in MATLAB code.           |
| "Custom BLAS library callback" on page 5-36                     | Specify BLAS library callback class for BLAS calls in code generated from MATLAB code.                        |
| "Custom LAPACK library callback" on page 5-38                   | Specify LAPACK library callback class for LAPACK calls in code generated from MATLAB code.                    |
| "Verbose build" on page 5-40                                    | Display code generation progress.                                                                             |
| "Retain .rtw file" on page 5-41                                 | Specify <i>model.rtw</i> file retention.                                                                      |
| "Profile TLC" on page 5-42                                      | Profile the execution time of TLC files.                                                                      |
| "Enable TLC assertion" on page 5-45                             | Produce the TLC stack trace.                                                                                  |
| "Start TLC coverage when generating code" on page 5-44          | Generate the TLC execution report.                                                                            |
| "Start TLC debugger when generating code" on page 5-43          | Specify use of the TLC debugger                                                                               |
| "Show Custom Hardware App in Simulink Toolstrip" on page 5-46   | Read-only internal parameter for Simulink toolstrip.                                                          |
| "Show Embedded Hardware App in Simulink Toolstrip" on page 5-47 | Read-only internal parameter for Simulink toolstrip.                                                          |
| "Package" (Embedded Coder)                                      | Specify a package that contains memory sections you want to apply to model-level functions and internal data. |
| "Refresh package list" (Embedded Coder)                         | Add user-defined packages that are on the search path to list of packages.                                    |
| "Initialize/Terminate" (Embedded Coder)                         | Specify whether to apply a memory section to Initialize/Start and Terminate functions.                        |
| "Execution" (Embedded Coder)                                    | Specify whether to apply a memory section to execution functions.                                             |
| "Shared utility" (Embedded Coder)                               | Specify whether to apply memory sections to shared utility functions.                                         |
| "Constants" (Embedded Coder)                                    | Specify whether to apply a memory section to constants.                                                       |
| "Inputs/Outputs" (Embedded Coder)                               | Specify whether to apply a memory section to root input and output.                                           |

| Parameter                             | Description                                                 |
|---------------------------------------|-------------------------------------------------------------|
| “Internal data” (Embedded Coder)      | Specify whether to apply a memory section to internal data. |
| “Parameters” (Embedded Coder)         | Specify whether to apply a memory section to parameters.    |
| “Validation results” (Embedded Coder) | Display the results of memory section validation.           |

The following parameters under **Advanced parameters** are infrequently used and have no other documentation.

| Parameter                                          | Description                                                                |
|----------------------------------------------------|----------------------------------------------------------------------------|
| PostCodeGenCommand<br><i>character vector - ''</i> | Add the specified post code generation command to the model build process. |
| TLCOptions<br><i>character vector - ''</i>         | Specify additional TLC command-line options.                               |

The following parameters are for MathWorks use only.

| Parameter                                              | Description                                                                                                                                                                                |
|--------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Comment                                                | For MathWorks use only.                                                                                                                                                                    |
| PreserveName                                           | For MathWorks use only.                                                                                                                                                                    |
| PreserveNameWithParent                                 | For MathWorks use only.                                                                                                                                                                    |
| SignalNamingFcn                                        | For MathWorks use only.                                                                                                                                                                    |
| TargetTypeEmulationWarnSuppressLevel<br>int - <b>0</b> | For MathWorks use only.<br><br>When greater than or equal to 2, suppress warning messages that the code generator displays when emulating integer sizes in rapid prototyping environments. |

The Configuration Parameters dialog box also includes other code generation parameters:

- “Model Configuration Parameters: Code Generation Optimization” on page 16-2
- “Model Configuration Parameters: Code Generation Report” on page 6-2
- “Model Configuration Parameters: Comments” on page 7-2
- “Model Configuration Parameters: Code Generation Identifiers” on page 8-2
- “Model Configuration Parameters: Code Generation Custom Code” on page 9-2
- “Model Configuration Parameters: Code Generation Interface” on page 10-2

## See Also

### More About

- “Model Configuration”
- “Control Data and Function Placement in Memory by Inserting Pragmas” (Embedded Coder)

## Code Generation: General Tab Overview

Set up general information about code generation for a model's active configuration set, including target selection, documentation, and build process parameters.

To open the **Code Generation** pane, select **Configuration Parameters > Code Generation**.

### To get help on an option

- 1 Right-click the option's text label.
- 2 Select **What's This** from the popup menu.



### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2

## System target file

### Description

Specify the system target file.

**Category:** Code Generation

### Settings

**Default:** `grt.tlc`

You can specify the system target file in these ways:

- Use the System Target File Browser. Click the **Browse** button, which lets you select a preset target configuration consisting of a system target file, template makefile, and make command.
- Enter the name of your system target file in this field.

### Tips

- The System Target File Browser lists system target files found on the MATLAB path. Some system target files require additional licensed products.
- Using ERT-based system target files such as `ert.tlc` to generate code requires an Embedded Coder license.
- When you switch from a system target file that is not ERT-based to a file that is ERT-based, the configuration parameter **Default parameter behavior** sets to **Inlined** by default. However, you can change the setting of **Default parameter behavior** later. For more information, see “Default parameter behavior” on page 16-9.
- To configure your model for rapid simulation, select `rsim.tlc`.
- To configure your model for Simulink Real-Time™, select `slrt.tlc`.

### Command-Line Information

**Parameter:** SystemTargetFile

**Type:** character vector

**Value:** valid system target file

**Default:** `'grt.tlc'`

### Recommended Settings

| Application       | Setting                                                  |
|-------------------|----------------------------------------------------------|
| Debugging         | No impact                                                |
| Traceability      | No impact                                                |
| Efficiency        | No impact                                                |
| Safety precaution | No impact<br>ERT based (requires Embedded Coder license) |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Compare System Target File Support Across Products”

## Browse

### Description

Open the System Target File Browser, which lets you select a preset target configuration consisting of a system target file, template makefile, and make command. The value you select is filled into **“System target file”** on page 5-6.

**Category:** Code Generation

### Tips

- The System Target File Browser lists system target files found on the MATLAB path. Some system target files require additional licensed products, such as the Embedded Coder product.
- To configure your model for rapid simulation, select `rsim.tlc`.
- To configure your model for Simulink Real-Time, select `slrt.tlc`.

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Configure a System Target File”
- “Compare System Target File Support Across Products”

# Language

## Description

Specify C or C++ code generation.

**Category:** Code Generation

## Settings

**Default:** C

C

Generates C code and places the generated files in your build folder.

C++

Generates C++ code and places the generated files in your build folder.

On the **Code Generation > Interface** pane, if you additionally set the **Code interface packaging** parameter to C++ class, the build generates a C++ class interface to model code. The generated interface encapsulates required model data into C++ class attributes and model entry point functions into C++ class methods.

If you set **Code interface packaging** to a value other than C++ class, the build generates C++ compatible .cpp files containing model interfaces enclosed within an extern "C" link directive.

You might need to configure the Simulink Coder software to use a compiler before you build a system.

## Dependencies

Selecting C++ enables and selects the value C++ class for the **Code interface packaging** parameter on the **Code Generation > Interface** pane.

## Command-Line Information

**Parameter:** TargetLang

**Type:** character vector

**Value:** 'C' | 'C++'

**Default:** 'C'

## Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Select C or C++ Programming Language”
- “Select and Configure C or C++ Compiler”
- “Customize Generated C Function Interfaces” (Embedded Coder)
- “Customize Generated C++ Class Interfaces” (Embedded Coder)

## Description

### Description

This field displays the description of the system target file. You can use this description to differentiate between two system target files that have the same file name. To change the value of this description, click the Browse button.

**Category:** Code Generation

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Browse” on page 5-8

## Toolchain

### Description

Specify the toolchain to use when building an executable or library.

---

**Note** This parameter only appears when the model is configured to use a toolchain-based code generation target, as described in “Choose Build Approach and Configure Build Process”.

---

**Category:** Code Generation

### Settings

**Default:** Automatically locate an installed toolchain

The list of available toolchains depends on the host computer platform, and can include custom toolchains that you added.

When **Toolchain** is set to Automatically locate an installed toolchain, the code generator:

- 1 Searches your host computer for installed toolchains.
- 2 Selects the most current toolchain.
- 3 Displays the name of the selected toolchain immediately below the drop down menu.

### Tip

Click the **Configuration Parameters > Code Generation > Advanced parameters > Toolchain > Validate Toolchain** button to verify that the registration information for the toolchain is valid. When the validation process is complete, a separate **Validation report** window opens and displays the results. The Validation report states whether the toolchain registration Passed or Failed and provides status for each step and build tool in the validation process. If the tool chain definition omits a build tool, validation skips the unspecified tool. To fix a failure (for example, the build tool definition omits a required build tool such as compiler or linker), edit the toolchain definition and repeat the registration process.

### Command-Line Information

**Parameter:** Toolchain

**Type:** character vector

**Value:** 'Automatically locate an installed toolchain' | A valid toolchain name

**Default:** 'Automatically locate an installed toolchain'

### Recommended Settings

| Application | Setting   |
|-------------|-----------|
| Debugging   | No impact |

---

| <b>Application</b> | <b>Setting</b> |
|--------------------|----------------|
| Traceability       | No impact      |
| Efficiency         | No impact      |
| Safety precaution  | No impact      |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Toolchain Configuration”
- “Adding a Custom Toolchain” (MATLAB Coder)

## Build configuration

### Description

Specify compiler optimization or debug settings for toolchain.

---

**Note** This parameter only appears when the model is configured to use a toolchain-based code generation target, as described in “Choose Build Approach and Configure Build Process”.

---

**Category:** Code Generation

### Settings

**Default:** Faster Builds

Faster Builds

Optimize for shorter build times.

Faster Runs

Optimize for faster-running executable.

Debug

Optimize for debugging.

Specify

Selecting `Specify` displays a table of tools with editable options. Use this table to customize settings for the current model. See “Tool/Options” on page 5-16.

This interaction helps synchronize the **Toolchain** value and manually specified **Build configuration** values.

Modifying the **Build configuration** value can change the **Toolchain** value. The `Automatically locate an installed toolchain` is the only value for **Toolchain** that is affected by changing the **Build configuration** to `Specify`.

- Changing the **Build configuration** to `Specify`, changes the **Toolchain** value `Automatically locate an installed toolchain` (default) to the value of the toolchain that was located (for example, `Microsoft Visual C++ 2012 v11.0 |(64-bit Windows)`).
- Changing the **Build configuration** from `Specify` to another value does not change the **Toolchain** value.

### Tip

Click **Show settings** to display a table of tools with options for the current build configuration. See “Tool/Options” on page 5-16.

Customize the toolchain options for the `Specify` build configuration. These options only apply to the current project.

To extract macro definitions (including compiler optimization flags) from the generated makefile for toolchain approach builds on Windows or UNIX systems, see the *model.bat* description in “Manage Build Process Files”.

## Dependencies

Selecting **Specify** displays a table of tools with editable options. Use this table to customize settings for the current model. See “Tool/Options” on page 5-16.

## Command-Line Information

**Parameter:** BuildConfiguration

**Type:** character vector

**Value:** 'Faster Builds' | 'Faster Runs' | 'Debug' | 'Specify'

**Default:** 'Faster Builds'

## Recommended Settings

| Application       | Setting     |
|-------------------|-------------|
| Debugging         | Debug       |
| Traceability      | No impact   |
| Efficiency        | Faster Runs |
| Safety precaution | No impact   |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Toolchain Configuration”
- “Adding a Custom Toolchain” (MATLAB Coder)
- “Control Compiler Optimizations”

## Tool/Options

### Description

Display or customize build configuration settings.

---

**Note** These parameters only appear when the model is configured to use the toolchain approach, as described in “Choose Build Approach and Configure Build Process”

---

**Category:** Code Generation

### Settings

The tools column can include: Assembler, C Compiler, Linker, Shared Library Linker, C++ Compiler, C++ Linker, C++ Shared Library Linker, Archiver, Download, Execute, Make Tool. The options can vary by tool and toolchain and can contain macros. Consult third-party toolchain documentation for more information about options you can use with a specific tool.

### Dependencies

To display a table of tools and options for the current build configuration, click **Show settings**, next to **Build configuration**.

To create a custom build configuration by editing a table of Tool/Options, set **Build configuration** to Specify.

### Command-Line Information

**Parameter:** CustomToolchainOptions

**Type:** character vector

**Value:** Specify the baseline toolchain settings. Use a new-line-delineated character vector to specify each option and its values.

**Default:** ' '

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Toolchain Configuration”
- “Adding a Custom Toolchain” (MATLAB Coder)

# Compiler optimization level

## Description

Control compiler optimizations for building generated code, using flexible, generalized controls.

---

**Note** This parameter only appears when the model is configured to use a template makefile-based code generation target, as described in “Choose Build Approach and Configure Build Process”.

---

**Category:** Code Generation

## Settings

**Default:** Optimizations off (faster builds)

Optimizations off (faster builds)

Customizes compilation during the build process to minimize compilation time.

Optimizations on (faster runs)

Customizes compilation during the makefile build process to minimize run time.

Custom

Allows you to specify custom compiler optimization flags to be applied during the makefile build process.

## Tips

- Target-independent values `Optimizations on (faster runs)` and `Optimizations off (faster builds)` allow you to easily toggle compiler optimizations on and off during code development.
- `Custom` allows you to enter custom compiler optimization flags at Simulink GUI level, rather than editing compiler flags into template makefiles (TMFs) or supplying compiler flags to make commands.
- If you specify compiler options for your makefile build using `OPT_OPTS`, `MEX_OPTS` (except `MEX_OPTS="-v"`), or `MEX_OPT_FILE`, the value of **Compiler optimization level** is ignored and a warning is issued about the ignored parameter.

## Dependencies

This parameter enables **Custom compiler optimization flags**.

## Command-Line Information

**Parameter:** RTWCompilerOptimization

**Type:** character vector

**Value:** 'off' | 'on' | 'custom'

**Default:** 'off'

## Recommended Settings

| <b>Application</b> | <b>Setting</b>                                                   |
|--------------------|------------------------------------------------------------------|
| Debugging          | Optimizations off (faster builds)                                |
| Traceability       | Optimizations off (faster builds)                                |
| Efficiency         | Optimizations on (faster runs) (execution), No impact (ROM, RAM) |
| Safety precaution  | No impact                                                        |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Custom compiler optimization flags” on page 5-19
- “Control Compiler Optimizations”

# Custom compiler optimization flags

## Description

Specify compiler optimization flags to be applied to building the generated code for your model.

---

**Note** This parameter only appears when the model is configured to use a template makefile-based code generation target, as described in “Choose Build Approach and Configure Build Process”.

---

**Category:** Code Generation

## Settings

**Default:** ''

Specify compiler optimization flags without quotes, for example, -O2.

## Dependency

This parameter is enabled by selecting the value `Custom` for the parameter **Compiler optimization level**.

## Command-Line Information

**Parameter:** RTWCustomCompilerOptimizations

**Type:** character vector

**Value:** '' | user-specified flags

**Default:** ''

## Recommended Settings

See “Compiler optimization level” on page 5-17.

## See Also

## Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Compiler optimization level” on page 5-17
- “Control Compiler Optimizations”

## Generate makefile

### Description

Enable generation of a makefile based on a template makefile.

---

**Note** This option only appears when the model is configured to use a template makefile-based code generation target, as described in “Choose Build Approach and Configure Build Process”.

---

**Category:** Code Generation

### Settings

**Default:** on

On

Generates a makefile for a model during the build process.

Off

Suppresses the generation of a makefile. You must set up post code generation build processing, including compilation and linking, as a user-defined command.

### Dependencies

This parameter enables:

- **Make command**
- **Template makefile**

### Command-Line Information

**Parameter:** GenerateMakefile

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Customize Post-Code-Generation Build Processing”
- “Customize Build Process with STF\_make\_rtw\_hook File”
- “Target Development and the Build Process”

## Make command

### Description

Specify a make command and optionally append makefile options.

---

**Note** This parameter only appears when the model is configured to use a template makefile-based code generation target, as described in “Choose Build Approach and Configure Build Process”.

---

**Category:** Code Generation

### Settings

**Default:** make\_rtw

An internal MATLAB command used by code generation software to control the build process. The specified make command is invoked when you start a build.

- Each target has an associated make command, automatically supplied when you select a target file using the System Target File Browser.
- Some third-party targets supply a make command. See the vendor's documentation.
- You can supply makefile options in the **Make command** field. The options are passed to the command-line invocation of the `make` utility, which adds them to the overall flags passed to the compiler. Append the options after the make command, as in the following example:

```
make_rtw OPTS="-DMYDEFINE=1"
```

The syntax for makefile options differs slightly for different compilers.

### Tip

- Most targets use the default command.
- You should not invoke `make_rtw` or other internal make commands directly from MATLAB code. To initiate a model build from MATLAB code, use documented build commands such as `slbuild` or `rtwbuild`.

### Dependency

This parameter is enabled by **Generate makefile**.

### Command-Line Information

**Parameter:** MakeCommand

**Type:** character vector

**Value:** valid make command MATLAB language file

**Default:** 'make\_rtw'

## Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | No impact         |
| Traceability      | No impact         |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Template Makefiles and Make Options”
- “Customize Build Process with STF\_make\_rtw\_hook File”
- “Target Development and the Build Process”

## Template makefile

### Description

Specify the template makefile from which to generate the makefile.

---

**Note** This parameter only appears when the model is configured to use a template makefile-based code generation target, as described in “Choose Build Approach and Configure Build Process”.

---

**Category:** Code Generation

### Settings

**Default:** grt\_default\_tmf

The template makefile determines which compiler runs, during the make phase of the build, to compile the generated code. You can specify template makefiles in the following ways:

- Generate a value by selecting a target configuration using the System Target File Browser.
- Explicitly enter a custom template makefile filename (including the extension). The file must be on the MATLAB path.

### Tips

- If you do not include a filename extension for a custom template makefile, the code generator attempts to find and execute a MATLAB language file.
- You can customize your build process by modifying an existing template makefile or by providing your own template makefile.

### Dependency

This parameter is enabled by **Generate makefile**.

### Command-Line Information

**Parameter:** TemplateMakefile

**Type:** character vector

**Value:** valid template makefile filename

**Default:** 'grt\_default\_tmf'

### Recommended Settings

| Application  | Setting   |
|--------------|-----------|
| Debugging    | No impact |
| Traceability | No impact |
| Efficiency   | No impact |

| <b>Application</b> | <b>Setting</b> |
|--------------------|----------------|
| Safety precaution  | No impact      |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Template Makefiles and Make Options”
- “Compare System Target File Support Across Products”

## Select objective

### Description

Select a code generation objective for reviewing your model configuration settings by using the Code Generation Advisor.

**Category:** Code Generation

### Settings

**Default:** Unspecified

#### Unspecified

No objective specified. Do not optimize code generation settings by using the Code Generation Advisor.

#### Debugging

Specifies debugging objective. Optimize code generation settings for debugging the code generation build process by using the Code Generation Advisor.

#### Execution efficiency

Specifies execution efficiency objective. Optimize code generation settings to achieve fast execution time by using the Code Generation Advisor.

### Dependency

This parameter name appears only for GRT-based targets. For ERT-based targets, the parameter **Prioritized objectives** lists the code generation objectives.

### Command-Line Information

**Parameter:** 'ObjectivePriorities'

**Type:** cell array of character vectors or string array

**Value:** {' '} | {'Debugging'} | {'Execution efficiency'}

**Default:** {' '}

### Recommended Settings

| Application       | Setting                              |
|-------------------|--------------------------------------|
| Debugging         | Debugging                            |
| Traceability      | Not applicable for GRT-based targets |
| Efficiency        | Execution efficiency                 |
| Safety precaution | No recommendation                    |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Prioritized objectives” (Embedded Coder)
- “Configure Model for Code Generation Objectives by Using Code Generation Advisor” (Embedded Coder)
- “Application Objectives Using Code Generation Advisor”

## Check Model

### Description

Run the Code Generation Advisor checks.

**Category:** Code Generation

### Settings

- 1 Specify code generation objectives using the **Select objective** parameter (available with GRT-based targets) or in the Configuration Set Objectives dialog box, by clicking **Set Objectives** (available with ERT-based targets).
- 2 Click **Check Model**. The Code Generation Advisor runs the code generation objectives checks and provide suggestions for changing your model to meet the objectives.

### Dependency

You must specify objectives before checking the model.

### See Also

#### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Configure Model for Code Generation Objectives by Using Code Generation Advisor” (Embedded Coder)
- “Application Objectives Using Code Generation Advisor”

# Check model before generating code

## Description

Choose whether to run Code Generation Advisor checks before generating code.

**Category:** Code Generation

## Settings

**Default:** Off

Off

Generates code without checking whether the model meets code generation objectives. The code generation report summary and file headers indicate the specified objectives and that the validation was not run.

On (proceed with warnings)

Checks whether the model meets code generation objectives using the Code Generation Objectives checks in the Code Generation Advisor. If the Code Generation Advisor reports a warning, the code generator continues producing code. The code generation report summary and file headers indicate the specified objectives and the validation result.

On (stop for warnings)

Checks whether the model meets code generation objectives using the Code Generation Objectives checks in the Code Generation Advisor. If the Code Generation Advisor reports a warning, the code generator does not continue producing code.

## Command-Line Information

**Parameter:** CheckMdlBeforeBuild

**Type:** character vector

**Value:** 'Off' | 'Warning' | 'Error'

**Default:** 'Off'

## Recommended Settings

| Application       | Setting                                              |
|-------------------|------------------------------------------------------|
| Debugging         | On (proceed with warnings) or On (stop for warnings) |
| Traceability      | On (proceed with warnings) or On (stop for warnings) |
| Efficiency        | On (proceed with warnings) or On (stop for warnings) |
| Safety precaution | On (proceed with warnings) or On (stop for warnings) |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Configure Model for Code Generation Objectives by Using Code Generation Advisor” (Embedded Coder)
- “Application Objectives Using Code Generation Advisor”

## Generate code only

### Description

Specify code generation versus an executable build.

**Category:** Code Generation

### Settings

**Default:** off

On

The build process generates code and a makefile, but it does not invoke the make command.

Off

The build process generates and compiles code, and creates an executable file.

### Tip

**Generate code only** generates a makefile only if you select **Generate makefile**.

### Command-Line Information

**Parameter:** GenCodeOnly

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | Off       |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Customize Post-Code-Generation Build Processing”

## Package code and artifacts

### Description

Specify whether to automatically package generated code and artifacts for relocation.

**Category:** Code Generation

### Settings

**Default:** off

On

The build process runs the packNGo function after code generation to package generated code and artifacts for relocation.

Off

The build process does not run packNGo after code generation.

### Dependency

Selecting this parameter enables **Zip file name** and clearing this parameter disables **Zip file name**.

### Command-Line Information

**Parameter:** PackageGeneratedCodeAndArtifacts

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Relocate Code to Another Development Environment”
- “Limitations”

## Zip file name

### Description

Specify the name of the .zip file in which to package generated code and artifacts for relocation.

**Category:** Code Generation

### Settings

**Default:** ''

You can enter the name of the zip file in which to package generated code and artifacts for relocation. The file name can be specified with or without the .zip extension. If you do not specify an extension or an extension other than .zip, the zip utility adds the .zip extension. If a value is not specified, the build process uses the name *model.zip*, where *model* is the name of the top model for which code is being generated.

### Dependency

This parameter is enabled by **Package code and artifacts**.

### Command-Line Information

**Parameter:** PackageName

**Type:** character vector

**Value:** valid name for a .zip file

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Relocate Code to Another Development Environment”
- “Limitations”

## Custom FFT library callback

### Description

Specify a callback class for FFTW library calls in code generated for FFT functions in MATLAB code. This parameter applies to MATLAB code in a MATLAB Function block, a Stateflow chart, or a System object™ associated with a MATLAB System block.

To improve the execution speed of FFT functions, the code generator produces calls to the FFTW library that you specify in the callback class.

**Category:** Code Generation

### Settings

**Default:** ''

Specify the name of an FFT library callback class. If this parameter is empty, the code generator uses its own algorithms for FFT functions instead of calling the FFTW library.

### Limitation

The class definition file must be in a folder on the MATLAB path.

### Tip

Specify only the name of the class. Do not specify the name of the class definition file.

### Command-Line Information

**Parameter:** CustomFFTCallback

**Type:** character vector

**Value:** class name

**Default:** ''

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

#### More About

- “Model Configuration Parameters: Code Generation” on page 5-2

- “Speed Up Fast Fourier Transforms in Code Generated from a MATLAB Function Block”

### **External Websites**

- [www.fftw.org](http://www.fftw.org)

## Custom BLAS library callback

### Description

Specify BLAS library callback class for BLAS calls in code generated from MATLAB code. This parameter applies to MATLAB code in a MATLAB Function block, a Stateflow chart, or a System object associated with a MATLAB System block.

**Category:** Code Generation

### Settings

**Default:** ''

Specify the name of a BLAS callback class that derives from `coder.BLASCallback`. If you specify a BLAS callback class, for certain low-level vector and matrix operations, the code generator produces BLAS calls by using the CBLAS C interface to your BLAS library. The callback class provides the CBLAS header and data type information and the information required to link to your BLAS library. If this parameter is empty, the code generator produces code for the vector and matrix functions instead of a BLAS call.

### Limitation

The class definition file must be in a folder on the MATLAB path.

### Tip

Specify only the name of the class. Do not specify the name of the class definition file.

### Command-Line Information

**Parameter:** CustomBLASCallback

**Type:** character vector

**Value:** class name

**Default:** ''

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Speed Up Matrix Operations in Code Generated from a MATLAB Function Block”

## Custom LAPACK library callback

### Description

Specify LAPACK library callback class for LAPACK calls in code generated from MATLAB code. This parameter applies to MATLAB code in a MATLAB Function block, a Stateflow chart, or a System object associated with a MATLAB System block.

**Category:** Code Generation

### Settings

**Default:** ''

Specify the name of a LAPACK callback class that derives from `coder.LAPACKCallback`. If you specify a LAPACK callback class, for certain linear algebra functions, the code generator produces LAPACK calls by using the LAPACKE C interface to your LAPACK library. The callback class provides the name of your LAPACKE header file and the information required to link to your LAPACK library. If this parameter is empty, the code generator produces code for linear algebra functions instead of a LAPACK call.

### Limitation

The class definition file must be in a folder on the MATLAB path.

### Tip

Specify only the name of the class. Do not specify the name of the class definition file.

### Command-Line Information

**Parameter:** CustomLAPACKCallback

**Type:** character vector

**Value:** class name

**Default:** ''

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Speed Up Linear Algebra in Code Generated from a MATLAB Function Block”

## Verbose build

### Description

Display code generation progress.

**Category:** Code Generation

### Settings

**Default:** on

On

The MATLAB Command Window displays progress information indicating code generation stages and compiler output during code generation.

Off

Does not display progress information.

### Command-Line Information

**Parameter:** RTWVerbose

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | No impact         |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

### See Also

#### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Configure Model for Debugging”

## Retain .rtw file

### Description

Specify *model*.rtw file retention.

**Category:** Code Generation

### Settings

**Default:** off

On

Retains the *model*.rtw file in the current build folder. This parameter is useful if you are modifying the target files and need to look at the file.

Off

Deletes the *model*.rtw from the build folder at the end of the build process.

### Command-Line Information

**Parameter:** RetainRTWFile

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | On        |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Configure Model for Debugging”

## Profile TLC

### Description

Profile the execution time of TLC files.

**Category:** Code Generation

### Settings

**Default:** off

On

The TLC profiler analyzes the performance of TLC code executed during code generation, and generates an HTML report.

Off

Does not profile the performance.

### Command-Line Information

**Parameter:** ProfileTLC

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | On        |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

#### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Configure Model for Debugging”

## Start TLC debugger when generating code

### Description

Specify use of the TLC debugger

**Category:** Code Generation

### Settings

**Default:** Off

- On  
The TLC debugger starts during code generation.
- Off  
Does not start the TLC debugger.

### Tips

- You can also start the TLC debugger by entering the `-dc` argument into the **System target file** field.
- To invoke the debugger and run a debugger script, enter the `-df filename` argument into the **System target file** field.

### Command-Line Information

**Parameter:** TLCDebug

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | On        |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Configure Model for Debugging”

## Start TLC coverage when generating code

### Description

Generate the TLC execution report.

**Category:** Code Generation

### Settings

**Default:** off

On

Generates .log files containing the number of times each line of TLC code is executed during code generation.

Off

Does not generate a report.

### Tip

You can also generate the TLC execution report by entering the `-dg` argument into the **System target file** field.

### Command-Line Information

**Parameter:** TLCCoverage

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | On        |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Configure Model for Debugging”

## Enable TLC assertion

### Description

Produce the TLC stack trace

**Category:** Code Generation

### Settings

**Default:** off

On

The build process halts if a user-supplied TLC file contains an `%assert` directive that evaluates to FALSE.

Off

The build process ignores TLC assertion code.

### Command-Line Information

**Parameter:** TLCAssert

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | No impact         |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation” on page 5-2
- “Configure Model for Debugging”

## Show Custom Hardware App in Simulink Toolstrip

### Description

Read-only internal parameter for Simulink toolstrip

**Category:** Code Generation

### Settings

**Default:** off

On

Run on Custom Hardware app is active.

Off

Run on Custom Hardware app is not active.

### Command-Line Information

**Parameter:** ShowCustomHardwareApp

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | No impact         |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

## Show Embedded Hardware App in Simulink Toolstrip

### Description

Read-only internal parameter for Simulink toolstrip

**Category:** Code Generation

### Settings

**Default:** off

On

Run on Hardware Board app is active.

Off

Run on Hardware Board app is not active.

### Command-Line Information

**Parameter:** ShowEmbeddedHardwareApp

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | No impact         |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |



# Code Generation Parameters: Report

---

## Model Configuration Parameters: Code Generation Report

The **Code Generation > Report** category includes parameters for generating and customizing the code generation report. These parameters require a Simulink Coder license. Additional parameters available with an ERT-based target require an Embedded Coder license.

On the Configuration Parameters dialog box, the following configuration parameters are on the **Code Generation > Report** pane.

| Parameter                                       | Description                                                                                                             |
|-------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------|
| "Create code generation report" on page 6-5     | Document generated code in an HTML report.                                                                              |
| "Open report automatically" on page 6-7         | Specify whether to display code generation reports automatically.                                                       |
| "Generate model Web view" (Embedded Coder)      | Include the model Web view in the code generation report to navigate between the code and model within the same window. |
| "Generate static code metrics" (Embedded Coder) | Include static code metrics report in the code generation report.                                                       |

These configuration parameters are under the **Advanced parameters**.

| Parameter                                                             | Description                                                                                                                                                                                                      |
|-----------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| "Code-to-model" (Embedded Coder)                                      | Include hyperlinks in the code generation report that link code to the corresponding Simulink blocks, Stateflow objects, and MATLAB functions in the model diagram.                                              |
| "Model-to-code" (Embedded Coder)                                      | Link Simulink blocks, Stateflow objects, and MATLAB functions in a model diagram to corresponding code segments in a generated HTML report so that the generated code for a block can be highlighted on request. |
| "Configure" (Embedded Coder)                                          | Open the <b>Model-to-code navigation</b> dialog box for specifying a build folder containing previously-generated model code to highlight.                                                                       |
| "Eliminated / virtual blocks" (Embedded Coder)                        | Include summary of eliminated and virtual blocks in code generation report.                                                                                                                                      |
| "Traceable Simulink blocks" (Embedded Coder)                          | Include summary of Simulink blocks in code generation report.                                                                                                                                                    |
| "Traceable Stateflow objects" (Embedded Coder)                        | Include summary of Stateflow objects in code generation report.                                                                                                                                                  |
| "Traceable MATLAB functions" (Embedded Coder)                         | Include summary of MATLAB functions in code generation report.                                                                                                                                                   |
| "Summarize which blocks triggered code replacements" (Embedded Coder) | Include code replacement report summarizing replacement functions used and their associated blocks in the code generation report.                                                                                |

## **See Also**

### **More About**

- [“Report Generation”](#)
- [“Model Configuration”](#)

## Code Generation: Report Tab Overview

Control the code generation report that the code generator automatically creates.

### Configuration

To create a code generation report during the build process, select the **Create code generation report** parameter.

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Report” on page 6-2
- “Generate a Code Generation Report”
- “Reports for Code Generation”
- “HTML Code Generation Report Extensions” (Embedded Coder)

# Create code generation report

## Description

Document generated code in an HTML report.

**Category:** Code Generation > Report

## Settings

**Default:** Off

On

Generates a summary of code generation source files in an HTML report. Places the report files in an `html` subfolder within the build folder. In the report,

- The **Summary** section lists version and date information. The **Configuration Settings at the Time of Code Generation** link opens a noneditable view of the Configuration Parameters dialog that shows the Simulink model settings, including TLC options, at the time of code generation.
- The **Subsystem Report** section contains information on nonvirtual subsystems in the model.
- The **Code Interface Report** section provides information about the generated code interface, including model entry point functions and input/output data (requires an Embedded Coder license and the ERT target).
- The **Traceability Report** section allows you to account for **Eliminated / Virtual Blocks** that are untraceable, versus the listed **Traceable Simulink Blocks / Stateflow Objects / MATLAB Scripts**, providing a complete mapping between model elements and code (requires an Embedded Coder license and the ERT system target file).
- The **Static Code Metrics Report** section provides statistics of the generated code. Metrics are estimated from static analysis of the generated code.
- The **Code Replacements Report** section allows you to account for code replacement library (CRL) functions that were used during code generation, providing a mapping between each replacement instance and the Simulink block that triggered the replacement.

In the **Generated Files** section, you can click the names of source code files generated from your model to view their contents in a MATLAB Web browser window. In the displayed source code,

- Global variable instances are hyperlinked to their definitions.
- If you selected the traceability option **Code-to-model**, hyperlinks within the displayed source code let you view the blocks or subsystems from which the code was generated. Click on the hyperlinks to view the relevant blocks or subsystems in a Simulink model window (requires an Embedded Coder license and the ERT system target file).
- If you selected the traceability option **Model-to-code**, you can view the generated code for a block in the model. To highlight a block's generated code in the HTML report, right-click the block and select **C/C++ Code > Navigate to C/C++ Code** (requires an Embedded Coder license and the ERT system target file).
- If you set the **Code coverage tool** parameter on the **Code Generation > Verification** pane, you can view the code coverage data and annotations in the generated code in the HTML

Code Generation Report (requires an Embedded Coder license and the ERT system target file).

Off

Does not generate a summary of files.

## Dependency

This parameter enables

- **Open report automatically** on page 6-7
- **Code-to-model** (Embedded Coder) (ERT target)
- **Model-to-code** (Embedded Coder) (ERT target)
- **Eliminated / virtual blocks** (Embedded Coder) (ERT target)
- **Traceable Simulink blocks** (Embedded Coder) (ERT target)
- **Traceable Stateflow objects** (Embedded Coder) (ERT target)
- **Traceable MATLAB functions** (Embedded Coder) (ERT target)

## Command-Line Information

**Parameter:** GenerateReport

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

## Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | On                |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Report” on page 6-2
- “Reports for Code Generation”
- “HTML Code Generation Report Extensions” (Embedded Coder)
- “Configure Code Coverage with Third-Party Tools” (Embedded Coder)

## Open report automatically

### Description

Specify whether to display code generation reports automatically.

**Category:** Code Generation > Report

### Settings

**Default:** Off

On

Displays the code generation report automatically in a new browser window.

Off

Does not display the code generation report, but the report is still available in the html folder.

### Dependency

This parameter is enabled by **Create code generation report**.

### Command-Line Information

**Parameter:** LaunchReport

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | On        |
| Traceability      | On        |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

#### Related Examples

- “Model Configuration Parameters: Code Generation Report” on page 6-2
- “Reports for Code Generation”
- “HTML Code Generation Report Extensions” (Embedded Coder)



# **Code Generation Parameters: Comments**

## Model Configuration Parameters: Comments

The **Code Generation > Comments** category includes parameters for configuring the comments in the generated code. These parameters require a Simulink Coder license. Additional parameters available with an ERT-based target require an Embedded Coder license.

Code Comments are generated automatically or you can add them to the code.

Code comments have the following uses:

- Enhance the readability and traceability of code
- Convey information among users
- Enhance code search in code base

Code Comments can be classified into Auto generated and Custom comments. Auto generated comments are automatically generated by the software during code generation and the user adds Custom comments.

On the Configuration Parameters dialog box, the following configuration parameters are on the **Code Generation > Comments** pane.

### Auto generated comments

| Parameter                                                         | Description                                                                                       |
|-------------------------------------------------------------------|---------------------------------------------------------------------------------------------------|
| "Include comments" on page 7-6                                    | Specify which comments are in generated files.                                                    |
| "Simulink block comments" on page 7-8                             | Specify whether to insert Simulink block comments.                                                |
| "Trace to model using" (Embedded Coder)                           | Specify format of comments for Simulink blocks, Stateflow elements and MATLAB function blocks.    |
| "Stateflow object comments" on page 7-9                           | Specify whether to insert Stateflow object comments.                                              |
| "MATLAB source code as comments" on page 7-11                     | Specify whether to insert MATLAB source code as comments.                                         |
| "Show eliminated blocks" on page 7-13                             | Specify whether to insert eliminated block's comments.                                            |
| "Verbose comments for 'Model default' storage class" on page 7-14 | Reduce code size or improve code traceability by controlling the generation of comments.          |
| "Operator annotations" (Embedded Coder)                           | Specify whether to include operator annotations for Polyspace® in the generated code as comments. |

### Custom comments

| Parameter                                      | Description                                                                       |
|------------------------------------------------|-----------------------------------------------------------------------------------|
| "Simulink block descriptions" (Embedded Coder) | Specify whether to insert descriptions of blocks into generated code as comments. |

| Parameter                                             | Description                                                                                                                             |
|-------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------|
| “Stateflow object descriptions” (Embedded Coder)      | Specify whether to insert descriptions of Stateflow objects into generated code as comments.                                            |
| “Simulink data object descriptions” (Embedded Coder)  | Specify whether to insert descriptions of Simulinkdata objects into generated code as comments.                                         |
| “Requirements in block comments” (Embedded Coder)     | Specify whether to include requirement descriptions assigned to Simulink blocks in generated code as comments.                          |
| “Custom comments (MPT objects only)” (Embedded Coder) | Specify whether to include custom comments for module packaging tool (MPT) signal and parameter data objects in generated code.         |
| “MATLAB user comments” (Embedded Coder)               | Specify whether to include MATLAB user comments as comments.                                                                            |
| “Custom comments function” (Embedded Coder)           | Specify a file that contains comments to be included in generated code for module packing tool (MPT) signal and parameter data objects. |

The following configuration parameters are under the **Advanced parameters**.

| Parameter                                    | Description                                                                    |
|----------------------------------------------|--------------------------------------------------------------------------------|
| “Comment style” (Embedded Coder)             | Specify a multi-line or single-line comment style for generated C or C++ code. |
| “Insert Polyspace comments” (Embedded Coder) | Specify whether to insert code comments for Polyspace block annotations.       |

- The code generation software automatically inserts comments into the generated code for custom blocks. Therefore, you do not need to include block comments in the associated TLC file for a custom block.

---

**Note** If you have existing TLC files with manually inserted comments for block descriptions, the code generation process emits these comments instead of the automatically generated comments. Consider removing existing block comments from your TLC files. Manually inserted comments might be poorly formatted in the generated code and code-to-model traceability might not work.

---

- For virtual blocks or blocks that have been removed due to block reduction, comments are not generated.
- When you configure the code generator to produce code that includes comments, the code generator includes text for model parameters, block names, signal names, and Stateflow object names in the generated code comments. If the text includes characters that are unrepresented in the character set encoding for the model, the code generator replaces the characters with XML escape sequences. For example, the code generator replaces the Japanese full-width Katakana letter  $\text{ア}$  with the escape sequence `&#x30A2`; . For more information, see “Internationalization and Code Generation”.

## **See Also**

### **More About**

- [“Configure Code Comments”](#)
- [“Verify Generated Code by Using Code Tracing” \(Embedded Coder\)](#)

## Code Generation: Comments Tab Overview

Control the comments that the code generator creates and inserts into the generated code.

### See Also

### Related Examples

- “Model Configuration Parameters: Comments” on page 7-2

## Include comments

### Description

Specify which comments are in generated files.

**Category:** Code Generation > Comments

### Settings

**Default:** On

On

Places comments in the generated files based on the selections in the **Auto generated comments** pane.

Off

Omits comments from the generated files.

---

**Note** This parameter does not apply to copyright notice comments in the generated code.

---

### Dependencies

This parameter enables:

- **Simulink block comments** on page 7-8
- **Stateflow object comments** on page 7-9
- **MATLAB source code as comments** on page 7-11
- **Show eliminated blocks** on page 7-13
- **Verbose comments for 'Model default' storage class** on page 7-14

### Command-Line Information

**Parameter:** GenerateComments

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | On                |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

## See Also

### Related Examples

- “Model Configuration Parameters: Comments” on page 7-2
- “Configure Code Comments”
- “Verify Generated Code by Using Code Tracing” (Embedded Coder)

## Simulink block comments

### Description

Specify whether to insert Simulink block comments.

**Category:** Code Generation > Comments

### Settings

**Default:** On

On

Inserts automatically generated comments that describe a block's code. The comments precede generated code in the generated file.

Off

Suppresses comments.

### Dependency

- **Include comments** on page 7-6 enables this parameter.
- This parameter enables **Trace to model using** (Embedded Coder).

### Command-Line Information

**Parameter:** SimulinkBlockComments

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | On                |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

### See Also

### Related Examples

- “Model Configuration Parameters: Comments” on page 7-2
- “Trace Simulink Model Elements in Generated Code” (Embedded Coder)

## Stateflow object comments

### Description

Specify whether to insert Stateflow object comments.

**Category:** Code Generation > Comments

### Settings

**Default:** Off

On

Inserts automatically generated comments that contain Stateflow object IDs or MATLAB code line locations. The comments precede the generated code in the generated file. For example,

```
/* Entry 'First': '<S2>:2' */
rtY.Out1 = 1;
```

'<S2>:2' is a hyperlinked traceability tag that facilitates tracing of generated code to corresponding Stateflow element.

Off

Suppresses comments.

### Dependency

- **Include comments** on page 7-6 enables this parameter.
- This parameter enables **Trace to model using** (Embedded Coder).

### Command-Line Information

**Parameter:** StateflowObjectComments

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | On                |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Comments” on page 7-2
- “Trace Stateflow Elements in Generated Code” (Embedded Coder)

## MATLAB source code as comments

### Description

Specify whether to insert MATLAB source code as comments.

**Category:** Code Generation > Comments

### Settings

**Default:** Off

On

Inserts MATLAB source code as comments in the generated code. The comment appears after the traceability tag and precedes the associated generated code. For example,

```
/* '<S2>:1:22' xb1 = x-1; */
xb1 = x;
```

Selecting this parameter adds the MATLAB code `xb1 = x-1;` in the traceability comment.

Includes the function signature in the function banner.

Off

Suppresses comments and does not include the function signature in the function banner.

### Dependency

**Include comments** on page 7-6 enables this parameter.

### Command-Line Information

**Parameter:** MATLABSourceComments

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | On                |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Comments” on page 7-2
- “Include MATLAB Code as Comments in the Generated Code” (Embedded Coder)

## Show eliminated blocks

### Description

Specify whether to insert eliminated block's comments.

**Category:** Code Generation > Comments

### Settings

**Default:** On

On

Inserts statements in the generated code from blocks eliminated as the result of optimizations (such as parameter inlining).

Off

Suppresses statements.

### Dependency

**Include comments** on page 7-6 enables this parameter.

### Command-Line Information

**Parameter:** ShowEliminatedStatement

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | On                |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

### See Also

### Related Examples

- “Model Configuration Parameters: Comments” on page 7-2

## Verbose comments for 'Model default' storage class

### Description

Reduce code size or improve code traceability by controlling the generation of comments. The comments appear interleaved in the code that initializes the fields of the model parameter structure, which appears in the *model\_data.c* file or the *model.c* file. Each comment indicates the name of a parameter object (`Simulink.Parameter`) or MATLAB variable and the blocks that use the object or variable to set parameter values.

Parameter objects and MATLAB variables appear in the model parameter structure under either of these conditions:

- You apply the storage class `Model default` to the object or variable and, in the Code Mappings editor, you set the storage class of the corresponding category of data to the default setting, `Default`.
- You apply the storage class `Auto` to the object or variable and set the model configuration parameter **Default parameter behavior** to `Tunable`. In the Code Mappings editor, you set the storage class of the corresponding category of data to the default setting, `Default`.

For more information about parameter representation in the generated code, see “How Generated Code Stores Internal Signal, State, and Parameter Data”.

**Category:** Code Generation > Comments

### Settings

**Default:** On

On

Generate comments regardless of the number of parameter values stored in the parameter structure. Use this setting to improve traceability between the generated code and the parameter objects or variables that the model uses.

Off

Generate comments only if the parameter structure contains fewer than 1000 parameter values. An array parameter with  $n$  elements represents  $n$  values. For large models, use this setting to reduce the size of the generated file.

### Dependency

**Include comments** on page 7-6 enables this parameter.

### Command-Line Information

**Parameter:** `ForceParamTrailComments`

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on'

## Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | On                |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

## See Also

### Related Examples

- “Model Configuration Parameters: Comments” on page 7-2
- “How Generated Code Stores Internal Signal, State, and Parameter Data”



# **Code Generation Parameters: Identifiers**

---

## Model Configuration Parameters: Code Generation Identifiers

The **Code Generation > Identifiers** category includes parameters for configuring the comments in the generated code. These parameters require a Simulink Coder license. Additional parameters available with an ERT-based target require an Embedded Coder license.

On the Configuration Parameters dialog box, the following configuration parameters are on the **Code Generation > Identifiers** pane.

| Parameter                                                      | Description                                                                                                                              |
|----------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------|
| "Global variables" (Embedded Coder)                            | Customize generated global variable identifiers.                                                                                         |
| "Global types" (Embedded Coder)                                | Customize generated global type identifiers.                                                                                             |
| "Field name of global types" (Embedded Coder)                  | Customize generated field names of global types.                                                                                         |
| "Subsystem methods" (Embedded Coder)                           | Customize generated function names for reusable subsystems.                                                                              |
| "Subsystem method arguments" (Embedded Coder)                  | Customize generated function argument names for reusable subsystems.                                                                     |
| "Local temporary variables" (Embedded Coder)                   | Customize generated local temporary variable identifiers.                                                                                |
| "Local block output variables" (Embedded Coder)                | Customize generated local block output variable identifiers.                                                                             |
| "Constant macros" (Embedded Coder)                             | Customize generated constant macro identifiers.                                                                                          |
| "Shared utilities identifier format" (Embedded Coder)          | Customize shared utility identifiers.                                                                                                    |
| "Minimum mangle length" (Embedded Coder)                       | Specify the minimum number of characters for generating name-mangling text to help avoid name collisions.                                |
| "Maximum identifier length" on page 8-5                        | Specify maximum number of characters in generated function, type definition, variable names.                                             |
| "System-generated identifiers" (Embedded Coder)                | Specify whether the code generator uses shorter, more consistent names for the \$N token in system-generated identifiers.                |
| "Generate scalar inlined parameters as" (Embedded Coder)       | Control expression of scalar inlined parameter values in the generated code.                                                             |
| "Use the same reserved names as Simulation Target" on page 8-7 | Specify whether to use the same reserved names as those specified in the <b>Simulation Target</b> pane.                                  |
| "Reserved names" on page 8-8                                   | Enter the names of variables or functions in the generated code that match the names of variables or functions specified in custom code. |

The following configuration parameters are under the **Advanced parameters**.

| Parameter                                                        | Description                                                                                                                                                                                                               |
|------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| “Shared checksum length” (Embedded Coder)                        | Specify character length of \$C token.                                                                                                                                                                                    |
| “EMX array utility functions identifier format” (Embedded Coder) | Customize generated identifiers for emxArray (embeddable mxArray) utility functions.                                                                                                                                      |
| “EMX array types identifier format” (Embedded Coder)             | Customize generated identifiers for emxArray (embeddable mxArray ) types.                                                                                                                                                 |
| “Custom token text” (Embedded Coder)                             | Specify text to insert for \$U token.                                                                                                                                                                                     |
| “Duplicate enumeration member names” on page 8-10                | Select the diagnostic action to take if the code generator detects two enumeration types with same member names. This parameter applies to only enumeration with imported data scope and the same storage type and value. |
| “Signal naming” (Embedded Coder)                                 | Specify rules for naming signals in generated code.                                                                                                                                                                       |
| “M-function” (Embedded Coder)                                    |                                                                                                                                                                                                                           |
| “Parameter naming” (Embedded Coder)                              | Specify rule for naming parameters in generated code.                                                                                                                                                                     |
| “M-function” (Embedded Coder)                                    |                                                                                                                                                                                                                           |
| “#define naming” (Embedded Coder)                                | Specify rule for naming #define parameters (defined with storage class Define (Custom)) in generated code.                                                                                                                |
| “M-function” (Embedded Coder)                                    |                                                                                                                                                                                                                           |

## See Also

### More About

- “Code Appearance”
- “Model Configuration”

## Code Generation: Identifiers Tab Overview

Select the automatically generated identifier naming rules.

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Identifiers” on page 8-2
- “Construction of Generated Identifiers”
- “Identifier Name Collisions and Mangling”
- “Specify Identifier Length to Avoid Naming Collisions”
- “Specify Reserved Names for Generated Identifiers”
- “Customize Generated Identifier Naming Rules” (Embedded Coder)

# Maximum identifier length

## Description

Specify maximum number of characters in generated function, type definition, variable names.

**Category:** Code Generation > Identifiers

## Settings

**Default:** 31

**Minimum:** 31

**Maximum:** 256

You can use this parameter to limit the number of characters in function, type definition, and variable names.

## Tips

- Consider increasing identifier length for models having a deep hierarchical structure.
- When generating code from a model that uses model referencing, the **Maximum identifier length** must be large enough to accommodate the root model name, and possibly, the name-mangling text. A code generation error occurs if **Maximum identifier length** is too small.
- This parameter must be the same for both top-level and referenced models.
- When a name conflict occurs between a symbol within the scope of a higher level model and a symbol within the scope of a referenced model, the symbol from the referenced model is preserved. Name mangling is performed on the symbol from the higher level model.

## Command-Line Information

**Parameter:** MaxIdLength

**Type:** integer

**Value:** valid value

**Default:** 31

## Recommended Settings

| Application       | Setting     |
|-------------------|-------------|
| Debugging         | Valid value |
| Traceability      | >30         |
| Efficiency        | No impact   |
| Safety precaution | >30         |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation Identifiers” on page 8-2
- “Construction of Generated Identifiers”
- “Identifier Name Collisions and Mangling”
- “Identifier Format Control” (Embedded Coder)

## Use the same reserved names as Simulation Target

### Description

Specify whether to use the same reserved names as those specified in the **Simulation Target** pane.

**Category:** Code Generation > Identifiers

### Settings

**Default:** Off

On

Enables using the same reserved names as those specified in the **Simulation Target** pane.

Off

Disables using the same reserved names as those specified in the **Simulation Target** pane.

### Command-Line Information

**Parameter:** UseSimReservedNames

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Identifiers” on page 8-2

## Reserved names

### Description

Enter the names of variables or functions in the generated code that match the names of variables or functions specified in custom code.

**Category:** Code Generation > Identifiers

### Settings

**Default:** {}

This action changes the names of variables or functions in the generated code to avoid name conflicts with identifiers in custom code. Reserved names must be shorter than 256 characters.

### Tips

- Do not enter code generator keywords since these names cannot be changed in the generated code. For a list of keywords to avoid, see “Reserved Keywords”.
- Start each reserved name with a letter or an underscore to prevent error messages.
- Each reserved name must contain only letters, numbers, or underscores.
- Separate the reserved names using commas or spaces.
- You can also specify reserved names by using the command line:

```
config_param_object.set_param('ReservedNameArray', {'abc', 'xyz'})
```

where `config_param_object` is the object handle to the model settings in the Configuration Parameters dialog box.

### Command-Line Information

**Parameter:** ReservedNameArray

**Type:** cell array of character vectors or string array

**Value:** reserved names shorter than 256 characters

**Default:** {}

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation Identifiers” on page 8-2

## Duplicate enumeration member names

### Description

Select the diagnostic action to take if the code generator detects two enumeration types with same member names. This parameter applies to only enumeration with imported data scope and the same storage type and value.

**Category:** Code Generation > Identifiers

### Settings

**Default:** error

none

When the code generator detects two enumeration types with the same member names, the code generation proceeds.

warning

When the code generator detects two enumeration types with the same member names, the software issues a warning message and the code generation proceeds.

error

When the code generator detects two enumeration types with the same member names, the software issues an error message and terminates the code generation.

### Command-Line Information

**Parameter:** EnumMemberNameClash

**Type:** character vector

**Value:** 'none' | 'warning' | 'error'

**Default:** 'error'

### Example

Consider these enumerations:

```
typedef int32_T enumA;
#define a (0)
#define p (1)

typedef int32_T enumB;
#define b (0)
#define p (1)
```

The enumerations have the same `int32` storage type. The enumeration member `p` with value 1 is the same for `enumA` and `enumB`.

Generate an error or warning message or allow code generation for duplicate enumeration member names by using the **Duplicate enumeration member names** configuration parameter.

## Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## See Also

### Related Examples

- “Use Enumerated Data in Generated Code”
- “Use Enumerated Data in Simulink Models” (Simulink)
- “Model Configuration Parameters: Code Generation Identifiers” on page 8-2



# Code Generation Parameters: Custom Code

---

## Model Configuration Parameters: Code Generation Custom Code

The **Code Generation > Custom Code** category includes parameters for inserting custom C code into the generated code. These parameters require a Simulink Coder license.

On the Configuration Parameters dialog box, the following configuration parameters are on the **Code Generation > Custom Code** pane.

| Parameter                                                            | Description                                                                                                          |
|----------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------|
| "Use the same custom code settings as Simulation Target" on page 9-4 | Specify whether to use the same custom code settings as those in the <b>Simulation Target &gt; Custom Code</b> pane. |
| "Source file" on page 9-5                                            | Specify custom code to include near the top of the generated model source file.                                      |
| "Header file" on page 9-6                                            | Specify custom code to include near the top of the generated model header file.                                      |
| "Initialize function" on page 9-7                                    | Specify custom code to include in the generated model initialize function.                                           |
| "Terminate function" on page 9-8                                     | Specify custom code to include in the generated model terminate function.                                            |
| "Include directories" on page 9-9                                    | Specify a list of include folders to add to the include path.                                                        |
| "Source files" on page 9-11                                          | Specify a list of additional source files to compile and link with the generated code.                               |
| "Libraries" on page 9-12                                             | Specify a list of additional libraries to link with the generated code.                                              |
| "Defines" on page 9-13                                               | Specify preprocessor macro definitions to be added to the compiler command line.                                     |

### See Also

### More About

- "Model Configuration"

## Code Generation: Custom Code Tab Overview

Enter custom code to include in generated model files and create a list of additional folders, source files, and libraries to use when building the model.

### Configuration

- 1 Select the type of information to include from the list on the left side of the pane.
- 2 Enter custom code or enter text to identify a folder, source file, or library.
- 3 Click **Apply**.

### See Also

#### Related Examples

- “Model Configuration Parameters: Code Generation Custom Code” on page 9-2
- “Integrate External Code by Using Model Configuration Parameters”

## Use the same custom code settings as Simulation Target

### Description

Specify whether to use the same custom code settings as those in the **Simulation Target > Custom Code** pane.

**Category:** Code Generation > Custom Code

### Settings

**Default:** Off

On

Enables using the same custom code settings as those in the **Simulation Target > Custom Code** pane.

Off

Disables using the same custom code settings as those in the **Simulation Target > Custom Code** pane.

### Command-Line Information

**Parameter:** RTWUseSimCustomCode

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Custom Code” on page 9-2
- “Integrate External Code by Using Model Configuration Parameters”

## Source file

### Description

Specify custom code to include near the top of the generated model source file.

**Category:** Code Generation > Custom Code

### Settings

**Default:** ' '

The code generator places code near the top of the generated *model.c* or *model.cpp* file, outside of any function.

### Command-Line Information

**Parameter:** CustomSourceCode

**Type:** character vector

**Value:** C code

**Default:** ' '

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Custom Code” on page 9-2
- “Integrate External Code by Using Model Configuration Parameters”

## Header file

### Description

Specify custom code to include near the top of the generated model header file.

**Category:** Code Generation > Custom Code

### Settings

**Default:** ''

The code generator places this code near the top of the generated *model.h* header file. If you are including a header file, in your custom header file add `#ifndef` code. This avoids multiple inclusions. For example, in *rtwtypes.h* the following `#include` guards are added:

```
#ifndef RTW_HEADER_rtwtypes_h_
#define RTW_HEADER_rtwtypes_h_
...
#endif /* RTW_HEADER_rtwtypes_h_ */
```

### Command-Line Information

**Parameter:** CustomHeaderCode

**Type:** character vector

**Value:** C code

**Default:** ''

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Custom Code” on page 9-2
- “Integrate External Code by Using Model Configuration Parameters”

# Initialize function

## Description

Specify custom code to include in the generated model initialize function.

**Category:** Code Generation > Custom Code

## Settings

**Default:** ''

The code generator places code inside the model's initialize function in the *model.c* or *model.cpp* file.

## Command-Line Information

**Parameter:** CustomInitializer

**Type:** character vector

**Value:** C code

**Default:** ''

## Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## See Also

## Related Examples

- "Model Configuration Parameters: Code Generation Custom Code" on page 9-2
- "Integrate External Code by Using Model Configuration Parameters"

## Terminate function

Specify custom code to include in the generated model terminate function.

### Description

Specify custom code to include in the generated model terminate function.

**Category:** Code Generation > Custom Code

### Settings

**Default:** ''

Specify code to appear in the model's generated terminate function in the *model.c* or *model.cpp* file.

### Dependency

A terminate function is generated only if you select the **Terminate function required** check box.

### Command-Line Information

**Parameter:** CustomTerminator

**Type:** character vector

**Value:** C code

**Default:** ''

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Custom Code” on page 9-2
- “Integrate External Code by Using Model Configuration Parameters”

## Include directories

### Description

Specify a list of include folders to add to the include path.

**Category:** Code Generation > Custom Code

### Settings

**Default:** ' '

Enter a space-separated list of include folders to add to the include path when compiling the generated code.

- Specify absolute or relative paths to the folders.
- Relative paths must be relative to the folder containing your model files, not relative to the build folder.
- The order in which you specify the folders is the order in which they are searched for header, source, and library files.

---

**Note** If you specify a Windows path containing one or more spaces, you must enclose the path in double quotes. For example, the second and third paths in the **Include directories** entry below must be double-quoted:

```
C:\Project "C:\Custom Files" "C:\Library Files"
```

If you set the equivalent command-line parameter `CustomInclude`, each path containing spaces must be separately double-quoted within the single-quoted third argument character vector, for example,

```
>> set_param('myModel', 'CustomInclude', ...
 'C:\Project "C:\Custom Files" "C:\Library Files"')
```

---

### Command-Line Information

**Parameter:** CustomInclude

**Type:** character vector

**Value:** folder path

**Default:** ' '

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation Custom Code” on page 9-2
- “Integrate External Code by Using Model Configuration Parameters”

## Source files

### Description

Specify a list of additional source files to compile and link with the generated code.

**Category:** Code Generation > Custom Code

### Settings

**Default:** ' '

Enter a space-separated list of source files to compile and link with the generated code.

### Limitation

This parameter does not support Windows file names that contain embedded spaces.

### Tip

You can specify just the file name if the file is in the current MATLAB folder or in one of the include folders.

### Command-Line Information

**Parameter:** CustomSource

**Type:** character vector

**Value:** file name

**Default:** ' '

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Custom Code” on page 9-2
- “Integrate External Code by Using Model Configuration Parameters”

## Libraries

### Description

Specify a list of additional libraries to link with the generated code.

**Category:** Code Generation > Custom Code

### Settings

**Default:** ''

Enter a space-separated list of static library files to link with the generated code.

### Limitation

This parameter does not support Windows file names that contain embedded spaces.

### Tip

You can specify just the file name if the file is in the current MATLAB folder or in one of the include folders.

### Command-Line Information

**Parameter:** CustomLibrary

**Type:** character vector

**Value:** library file name

**Default:** ''

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Custom Code” on page 9-2
- “Integrate External Code by Using Model Configuration Parameters”

## Defines

### Description

Specify preprocessor macro definitions to be added to the compiler command line.

**Category:** Code Generation > Custom Code

### Settings

**Default:** ''

Enter a list of macro definitions for the compiler command line. Specify the parameters with a space-separated list of macro definitions. If a makefile is generated, these macro definitions are added to the compiler command line in the makefile. The list can include simple definitions (for example, -DDEF1), definitions with a value (for example, -DDEF2=1), and definitions with a space in the value (for example, -DDEF3="my value"). Definitions can omit the -D (for example, -DF00=1 and F00=1 are equivalent). If the toolchain uses a different flag for definitions, the code generator overrides the -D and uses the appropriate flag for the toolchain.

### Command-Line Information

**Parameter:** CustomDefine

**Type:** character vector

**Value:** preprocessor macro definition

**Default:** ''

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- "Model Configuration Parameters: Code Generation Custom Code" on page 9-2
- "Integrate External Code by Using Model Configuration Parameters"



# Code Generation Parameters: Interface

---

## Model Configuration Parameters: Code Generation Interface

The **Code Generation > Interface** category includes parameters for configuring the interface of the generated code. These parameters require a Simulink Coder license. Additional parameters available with an ERT-based target require an Embedded Coder license.

On the Configuration Parameters dialog box, the following configuration parameters are on the **Code Generation > Interface** pane.

| Parameter                                                                      | Description                                                                                                                                         |
|--------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------|
| "Code replacement library" on page 10-9                                        | Specify a code replacement library the code generator uses when producing code for a model.                                                         |
| "Shared code placement" on page 10-11                                          | Specify the location for generating utility functions, exported data type definitions, and declarations of exported data with custom storage class. |
| "Support: floating-point numbers" (Embedded Coder)                             | Specify whether to generate floating-point data and operations.                                                                                     |
| "Support: non-finite numbers" on page 10-13                                    | Specify whether to generate non-finite data and operations on non-finite data.                                                                      |
| "Support: complex numbers" (Embedded Coder)                                    | Specify whether to generate complex data and operations.                                                                                            |
| "Support: absolute time" (Embedded Coder)                                      | Specify whether to generate and maintain integer counters for absolute and elapsed time values.                                                     |
| "Support: continuous time" (Embedded Coder)                                    | Specify whether to generate code for blocks that use continuous time.                                                                               |
| "Support: variable-size signals" (Embedded Coder)                              | Specify whether to generate code for models that use variable-size signals.                                                                         |
| "Code interface packaging" on page 10-15                                       | Select the packaging for the generated C or C++ code interface.                                                                                     |
| "Multi-instance code error diagnostic" on page 10-18                           | Select the severity level for diagnostics displayed when a model violates requirements for generating multi-instance code.                          |
| "Pass root-level I/O as" (Embedded Coder)                                      | Control how root-level model input and output are passed to the reusable <code>model_step</code> function.                                          |
| "Remove error status field in real-time model data structure" (Embedded Coder) | Specify whether to log or monitor error status.                                                                                                     |
| "Include model types in model class" (Embedded Coder)                          | Specify whether to generate model type definitions in a model class.                                                                                |
| "Array layout" on page 10-37                                                   | Specify layout of array data for code generation as column-major or row-major                                                                       |
| "External functions compatibility for row-major code generation" on page 10-39 | Select diagnostic action if Simulink encounters a function that has no specified array layout                                                       |

| Parameter                                          | Description                                                                                                                                                               |
|----------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| "Parameter visibility" (Embedded Coder)            | Specify whether to generate the block parameter structure as a <code>public</code> , <code>private</code> , or <code>protected</code> data member of the C++ model class. |
| "Parameter access" (Embedded Coder)                | Specify whether to generate access methods for block parameters for the C++ model class.                                                                                  |
| "External I/O visibility" (Embedded Coder)         | Specify whether to generate the root-level I/O structure as a <code>public</code> , <code>private</code> , or <code>protected</code> data member of the C++ model class.  |
| "External I/O access" (Embedded Coder)             | Specify whether to generate access methods for root-level I/O signals for the C++ model class.                                                                            |
| "Configure C++ Class Interface" (Embedded Coder)   | Customize the C++ class interface for your model code.                                                                                                                    |
| "Generate C API for: signals" on page 10-20        | Generate C API data interface code with a signals structure.                                                                                                              |
| "Generate C API for: parameters" on page 10-21     | Generate C API data interface code with parameter tuning structures.                                                                                                      |
| "Generate C API for: states" on page 10-22         | Generate C API data interface code with a states structure.                                                                                                               |
| "Generate C API for: root-level I/O" on page 10-23 | Generate C API data interface code with a root-level I/O structure.                                                                                                       |
| "ASAP2 interface" on page 10-24                    | Generate code for the ASAP2 data interface.                                                                                                                               |
| "External mode" on page 10-25                      | Generate code for the external mode data interface.                                                                                                                       |
| "Transport layer" on page 10-26                    | Specify the transport protocol for communications.                                                                                                                        |
| "MEX-file arguments" on page 10-28                 | Specify arguments to pass to an external mode interface MEX-file for communicating with executing targets.                                                                |
| "Static memory allocation" on page 10-30           | Control memory buffer for external mode communication.                                                                                                                    |
| "Static memory buffer size" on page 10-32          | Specify the memory buffer size for external mode communication.                                                                                                           |

These configuration parameters are under the **Advanced parameters**.

| Parameter                                                                   | Description                                                                                                                                                                                                                                                                                                                                                      |
|-----------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| "Standard math library" on page 10-41                                       | Specify the standard math library for your execution environment. Verify that your compiler supports the library you want to use; otherwise compile-time errors can occur.<br>C89/C90 (ANSI) - ISO®/IEC 9899:1990 C standard math library<br>C99 (ISO) - ISO/IEC 9899:1999 C standard math library<br>C++03 (ISO) - ISO/IEC 14882:2003 C++ standard math library |
| "Support non-inlined S-functions" (Embedded Coder)                          | Specify whether to generate code for non-inlined S-functions.                                                                                                                                                                                                                                                                                                    |
| "Maximum word length" on page 10-43                                         | Specify a maximum word length, in bits, for which the code generation process generates system-defined multiword type definitions.                                                                                                                                                                                                                               |
| "Buffer size of dynamically-sized string (bytes)" on page 10-36             | Number of bytes of the character buffer generated for dynamic string signals without maximum length.                                                                                                                                                                                                                                                             |
| "Multiword type definitions" (Embedded Coder)                               | Specify whether to use system-defined or user-defined type definitions for multiword data types in generated code.                                                                                                                                                                                                                                               |
| "Classic call interface" on page 10-45                                      | Specify whether to generate model function calls compatible with the main program module of the GRT target in models created before R2012a.                                                                                                                                                                                                                      |
| "Use dynamic memory allocation for model initialization" (Embedded Coder)   | Control how the generated code allocates memory for model data.                                                                                                                                                                                                                                                                                                  |
| "Single output/update function" on page 10-47                               | Specify whether to generate the <i>model_step</i> function.                                                                                                                                                                                                                                                                                                      |
| "Terminate function required" (Embedded Coder)                              | Specify whether to generate the <i>model_terminate</i> function.                                                                                                                                                                                                                                                                                                 |
| "Combine signal/state structures" (Embedded Coder)                          | Specify whether to combine global block signals and global state data into one data structure in the generated code                                                                                                                                                                                                                                              |
| "Generate separate internal data per entry-point function" (Embedded Coder) | Generate a model's block signals (block I/O) and discrete states (DWork) acting at the same rate into the same data structure.                                                                                                                                                                                                                                   |
| "MAT-file logging" on page 10-49                                            | Specify MAT-file logging.                                                                                                                                                                                                                                                                                                                                        |
| "MAT-file variable name modifier" (Embedded Coder)                          | Select the text to add to MAT-file variable names.                                                                                                                                                                                                                                                                                                               |
| "Existing shared code" (Embedded Coder)                                     | Specify folder that contains existing shared code                                                                                                                                                                                                                                                                                                                |
| "Remove disable function" (Embedded Coder)                                  | Remove unreachable (dead-code) instances of the <i>disable</i> functions from the generated code for ERT-based systems that include model referencing hierarchies.                                                                                                                                                                                               |

| Parameter                                                                      | Description                                                                                                                                                                                                                                                 |
|--------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| “Remove reset function” (Embedded Coder)                                       | Remove unreachable (dead-code) instances of the <code>reset</code> functions from the generated code for ERT-based systems that include model referencing hierarchies.                                                                                      |
| “LUT object struct order for even spacing specification” on page 10-34         | Change the order of the fields in the generated structure for a lookup table object whose specification parameter is set to even spacing.                                                                                                                   |
| “LUT object struct order for explicit value specification” on page 10-35       | Change the order of the fields in the generated structure for a lookup table object whose specification parameter is set to explicit value.                                                                                                                 |
| “Generate destructor” (Embedded Coder)                                         | Specify whether to generate a destructor for the C++ model class.                                                                                                                                                                                           |
| “Internal data access” (Embedded Coder)                                        | Specify whether to generate access methods for internal data structures, such as Block I/O, DWork vectors, Run-time model, Zero-crossings, and continuous states, for the C++ model class.                                                                  |
| “Internal data visibility” (Embedded Coder)                                    | Specify whether to generate internal data structures such as Block I/O, DWork vectors, Run-time model, Zero-crossings, and continuous states as <code>public</code> , <code>private</code> , or <code>protected</code> data members of the C++ model class. |
| “Use dynamic memory allocation for model block instantiation” (Embedded Coder) | Specify whether generated code uses the operator <code>new</code> , during model object registration, to instantiate objects for referenced models configured with a C++ class interface.                                                                   |
| “Code replacement library” on page 10-9                                        | Create custom Code Replacement libraries using code replacement tool.                                                                                                                                                                                       |
| “Ignore custom storage classes” (Embedded Coder)                               | Specify whether to apply or ignore custom storage classes.                                                                                                                                                                                                  |
| “Ignore test point signals” (Embedded Coder)                                   | Specify allocation of memory buffers for test points.                                                                                                                                                                                                       |
| “Implement each data store block as a unique access point” (Embedded Coder)    | Create unique variables for each read/write operation of a Data Store Memory block.                                                                                                                                                                         |

The following parameters under the **Advanced parameters** are infrequently used and have no other documentation.

| Parameter                            | Description                                                                                                                                                                                                      |
|--------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <code>GenerateSharedConstants</code> | Control whether the code generator generates code with shared constants and shared functions. Default is <code>on</code> . When turned <code>off</code> , the code generator does not generate shared constants. |

| Parameter                                                    | Description                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                |
|--------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| InferredTypesCompatibility                                   | For compatibility with legacy code including <code>tmwtypes.h</code> , specify that the code generator creates a preprocessor directive <code>#define_TMWYPES_</code> inside <code>rtwtypes.h</code>                                                                                                                                                                                                                                                                                                       |
| TargetLibSuffix<br><i>character vector - ''</i>              | Control the suffix used for naming a target's dependent libraries (for example, <code>_target.lib</code> or <code>_target.a</code> ). If specified, the character vector must include a period (.). (For generated model reference libraries, the library suffix defaults to <code>_rtwlib.lib</code> on Windows systems and <code>_rtwlib.a</code> on UNIX systems.).<br><br><b>Note</b> This parameter does not apply for model builds that use the toolchain approach, see "Library Control Parameters" |
| TargetPreCompLibLocation<br><i>character vector - ''</i>     | Control the location of precompiled libraries. If you do not set this parameter, the code generator uses the location specified in <code>rtwmakecfg.m</code> .                                                                                                                                                                                                                                                                                                                                             |
| IsERTTarget                                                  | Indicates whether or not the currently selected target is derived from the ERT target.                                                                                                                                                                                                                                                                                                                                                                                                                     |
| CPPClassGenCompliant                                         | Indicates whether the target supports the ability to generate and configure C++ class interfaces to model code.                                                                                                                                                                                                                                                                                                                                                                                            |
| ConcurrentExecutionCompliant                                 | Indicates whether the target supports concurrent execution                                                                                                                                                                                                                                                                                                                                                                                                                                                 |
| UseToolchainInfoCompliant                                    | Indicate a custom target is toolchain-compliant.                                                                                                                                                                                                                                                                                                                                                                                                                                                           |
| ModelStepFunctionPrototypeControlCompliant                   | Indicates whether the target supports the ability to control the function prototypes of initialize and step functions that are generated for a Simulink model.                                                                                                                                                                                                                                                                                                                                             |
| ParMdlRefBuildCompliant                                      | Indicates if the model is configured for parallel builds when building a model that includes referenced models.                                                                                                                                                                                                                                                                                                                                                                                            |
| CompOptLevelCompliant<br><i>off, on</i>                      | Set in <code>SelectCallback</code> for a target to indicate whether the target supports the ability to use the <b>Compiler optimization level</b> parameter to control the compiler optimization level for building generated code.<br><br>Default is <code>off</code> for custom targets and <code>on</code> for targets provided with the Simulink Coder and Embedded Coder products.                                                                                                                    |
| ModelReferenceCompliant<br><i>character vector - off, on</i> | Set in <code>SelectCallback</code> for a target to indicate whether the target supports model reference.                                                                                                                                                                                                                                                                                                                                                                                                   |

| Parameter          | Description                                                                                                                             |
|--------------------|-----------------------------------------------------------------------------------------------------------------------------------------|
| GenerateFullHeader | Generate full header including time stamp.<br><br>For ERT targets, this parameter is on the <b>Code Generation &gt; Templates</b> pane. |

The following parameters are for MathWorks use only.

| Parameter         | Description             |
|-------------------|-------------------------|
| ExtModeTesting    | For MathWorks use only. |
| ExtModeIntrfLevel | For MathWorks use only. |
| ExtModeMexFile    | For MathWorks use only. |

## See Also

### More About

- “Model Configuration”

## **Code Generation: Interface Tab Overview**

Select the target software environment, output variable name modifier, and data exchange interface.

### **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Run-Time Environment Configuration”

# Code replacement library

## Description

Specify a code replacement library the code generator uses when producing code for a model.

**Category:** Code Generation > Interface

## Settings

**Default:** None

None

Does not use a code replacement library.

*Named code replacement library*

Generates calls to a specific platform, compiler, or standards code replacement library. The list of named libraries depends on:

- Installed support packages.
- System target file, language, standard math library, and device vendor configuration.
- Whether you created and registered code replacement libraries, using the Embedded Coder product.

## Tips

- Before setting this parameter, verify that your compiler supports the library that you want to use. If you select a parameter value that your compiler does not support, compiler errors can occur.
- If you set parameter **Shared code placement** to `Shared location` or you generate code for models in a model reference hierarchy,
  - Models that are sharing the location or are in the model hierarchy must specify the same code replacement library (same name, tables, and table entries).
  - If you change the name or contents of the code replacement library and rebuild the model from the same folder as the previous build, the code generator reports a checksum warning (see “Manage the Shared Utility Code Checksum”). The warning prompts you to remove the existing folder and stop or stop code generation.
- If both of the following conditions exist for a model that contains Stateflow charts, the Simulink software regenerates code for the charts and recompiles the generated code.
  - You *do not* set parameter **Shared code placement** to `Shared location`.
  - You change the code replacement library name or contents before regenerating code.

## Command-Line Information

**Parameter:** CodeReplacementLibrary

**Type:** character vector

**Value:** 'None' | 'GNU C99 extensions' | 'Intel IPP for x86-64 (Windows)' | 'Intel IPP/SSE for x86-64 (Windows)' | 'Intel IPP for x86-64 (Windows for MinGW

```
compiler)'|'Intel IPP/SSE for x86-64 (Windows for MinGW compiler)'|'Intel IPP
for x86/Pentium (Windows)'|'Intel IPP/SSE x86/Pentium (Windows)'|'Intel IPP
for x86-64 (Linux)'|'Intel IPP/SSE with GNU99 extensions for x86-64 (Linux)'
Default: 'None'
```

## Recommended Settings

| Application       | Setting       |
|-------------------|---------------|
| Debugging         | No impact     |
| Traceability      | No impact     |
| Efficiency        | Valid library |
| Safety precaution | No impact     |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Run-Time Environment Configuration”
- “What Is Code Replacement Customization?” (Embedded Coder)
- “Develop a Code Replacement Library” (Embedded Coder)

# Shared code placement

## Description

Specify the location for generating utility functions, exported data type definitions, and declarations of exported data with custom storage class.

**Category:** Code Generation > Interface

## Settings

**Default:** Auto

### Auto

The code generator places utility code within the `codeGenFolder/slprj/target/_sharedutils` (or `codeGenFolder/targetSpecific/_shared`) folder for a model that contains Existing Shared Code (Embedded Coder) or at least one of the following blocks:

- Model blocks
- Simulink Function blocks
- Function Caller blocks
- Calls to Simulink Functions from Stateflow or MATLAB Function blocks
- Stateflow graphical functions when you select the **Export Chart Level Functions** parameter

If a model does not contain one of the above blocks or Existing Shared Code (Embedded Coder), the code generator places utility code in the build folder (generally, the folder that contains `model.c` or `model.cpp`).

### Shared location

Directs code for utilities to be placed within the `codeGenFolder/slprj/target/_sharedutils` (or `codeGenFolder/targetSpecific/_shared`) folder.

## Command-Line Information

**Parameter:** UtilityFuncGeneration

**Type:** character vector

**Value:** 'Auto' | 'Shared location'

**Default:** 'Auto'

## Recommended Settings

| Application  | Setting                                             |
|--------------|-----------------------------------------------------|
| Debugging    | Shared location (GRT)<br>No impact (ERT)            |
| Traceability | Shared location (GRT)<br>No impact (ERT)            |
| Efficiency   | No impact (execution, RAM)<br>Shared location (ROM) |

| <b>Application</b> | <b>Setting</b> |
|--------------------|----------------|
| Safety precaution  | No impact      |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Run-Time Environment Configuration”
- “Manage Build Process Folders”
- “Sharing Utility Code”

## Support: non-finite numbers

### Description

Specify whether to generate non-finite data and operations on non-finite data.

**Category:** Code Generation > Interface

### Settings

**Default:** on

On

Generates non-finite data (for example, NaN and Inf) and related operations.

Off

Does not generate non-finite data and operations. If you clear this option, an error occurs if the code generator encounters non-finite data or expressions. The error message reports offending blocks and parameters.

---

**Note** Code generation is optimized with the assumption that non-finite data are absent. However, if your application produces non-finite numbers through signal data or MATLAB code, the behavior of the generated code might be inconsistent with simulation results when processing non-finite data.

---

### Dependencies

- For ERT-based targets, parameter **Support: floating-point numbers** enables **Support: non-finite numbers**.
- If off for top model, must be off for referenced models.
- When you select parameter **MAT-File Logging**, you must also select **Support: non-finite numbers** and, if you use an ERT-based system target file, **Support: floating-point numbers**.

### Command-Line Information

**Parameter:** SupportNonFinite

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application  | Setting                               |
|--------------|---------------------------------------|
| Debugging    | No impact                             |
| Traceability | No impact                             |
| Efficiency   | Off (execution, ROM), No impact (RAM) |

| <b>Application</b> | <b>Setting</b>    |
|--------------------|-------------------|
| Safety precaution  | No recommendation |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation Interface” on page 10-2

# Code interface packaging

## Description

Select the packaging for the generated C or C++ code interface.

**Category:** Code Generation > Interface

## Settings

**Default:** Nonreusable function if parameter **Language** is set to C; C++ class if **Language** is set to C++

### C++ class

Generate a C++ class interface to model code. The generated interface encapsulates required model data into C++ class attributes and model entry point functions into C++ class methods.

### Nonreusable function

Generate nonreusable code. Model data structures are statically allocated and accessed by model entry point functions directly in the model code.

### Reusable function

Generate reusable, multi-instance code that is reentrant, as follows:

- For a GRT-based model, the generated *model.c* source file contains an allocation function that dynamically allocates model data for each instance of the model. For an ERT-based model, you can use parameter **Use dynamic memory allocation for model initialization** to control whether an allocation function is generated.
- The generated code passes the real-time model data structure in, by reference, as an argument to *model\_step* and the other model entry point functions.
- The real-time model data structure is exported with the *model.h* header file.

For an ERT-based model, you can use parameter **Pass root-level I/O as** to control how root-level input and output arguments are passed to the reusable model entry-point functions. They can be included in the real-time model data structure that is passed to the functions, passed as individual arguments, or passed as references to an input structure and an output structure.

## Tips

- Entry points are exported with *model.h*. To call the entry-point functions from handwritten code, add an `#include model.h` directive to the code.
- When you select **Reusable function**, the code generator generates a pointer to the real-time model object (*model\_M*).
- When you select **Reusable function**, the code generator can generate code that compiles but is not reentrant. For example, if a signal, DWork structure, or parameter data has a storage class other than `Auto`, global data structures are generated.

## Dependencies

- The value `C++ class` is available only if parameter **Language** is set to `C++`.
- Selecting `Reusable function` or `C++ class` enables parameter **Multi-instance code error diagnostic**.
- For an ERT-based system target file, selecting `Reusable function` enables parameters **Pass root-level I/O as** and **Use dynamic memory allocation for model initialization**.
- To enable parameter **Classic call interface**, select `Nonreusable function`.
- For an ERT-based system target file, selecting `C++ class` enables the following model configuration controls for customizing the model class interface:
  - **Configure C++ Class Interface** button
  - **Data Member Visibility/Access Control** subpane
  - Parameters **Generate destructor** and **Use dynamic memory allocation for model block instantiation**
- For an ERT-based system target file, you can select `Reusable function` with the static `ert_main.c` module, if you do the following:
  - Set parameter **Pass root-level I/O as** to `Part of model data structure`.
  - Select parameter **Use dynamic memory allocation for model initialization**.
- For an ERT-based system target file, you cannot select `Reusable function` if you are:
  - Customizing the `model_step` function prototype
  - Selecting subsystem block parameter **Function with separate data**
  - Using a subsystem that
    - Has multiple ports that share source
    - Has a port that is used by multiple instances of the subsystem and has different sample times, data types, complexity, frame status, or dimensions across the instances
    - Has output marked as a global signal
    - For each instance contains identical blocks with different names or parameter settings
- Selecting `Reusable function` does not change the code generated for function-call subsystems.

## Command-Line Information

**Parameter:** `CodeInterfacePackaging`

**Type:** character vector

**Value:** `'C++ class' | 'Nonreusable function' | 'Reusable function'`

**Default:** `'Nonreusable function'` if `TargetLang` is set to `'C'`; `'C++ class'` if `TargetLang` is set to `'C++'`

## Recommended Settings

| Application  | Setting   |
|--------------|-----------|
| Debugging    | No impact |
| Traceability | No impact |

| <b>Application</b> | <b>Setting</b>                 |
|--------------------|--------------------------------|
| Efficiency         | Reusable function or C++ class |
| Safety precaution  | No impact                      |

## See Also

`model_step`

## Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Configure Code Generation for Model Entry-Point Functions”
- “Generate Reentrant Code from Top Models”
- “Combine Code Generated for Multiple Models or Multiple Instances of a Model”
- “Generate Reentrant Code from Top Models”
- “Generate C++ Class Interface to Model or Subsystem Code”
- “Customize Generated C++ Class Interfaces” (Embedded Coder)
- “Control Generation of Functions for Subsystems”
- “Generate Reentrant Code from Subsystems”
- “S-Functions That Support Code Reuse”
- “Static Main Program Module” (Embedded Coder)
- “Customize Generated C Function Interfaces” (Embedded Coder)
- “Generate Modular Function Code for Nonvirtual Subsystems” (Embedded Coder)
- “Generate Component Source Code for Export to External Code Base” (Embedded Coder)

## Multi-instance code error diagnostic

### Description

Select the severity level for diagnostics displayed when a model violates requirements for generating multi-instance code.

**Category:** Code Generation > Interface

### Settings

**Default:** Error

None

Proceed with build without displaying a diagnostic message.

Warning

Proceed with build after displaying a warning message.

Error

Abort build after displaying an error message.

Under certain conditions, the software can:

- Generate code that compiles but is not reentrant. For example, if a signal or DWork structure has a storage class other than `Auto`, global data structures are generated.
- Be unable to generate valid and compilable code. For example, if the model contains an S-function that is not code-reuse compliant or a subsystem triggered by a wide function-call trigger, the code generator produces invalid code, displays an error message, and terminates the build.

### Dependencies

This parameter is enabled by setting parameter **Code interface packaging** to `Reusable function` or `C++ class`.

### Command-Line Information

**Parameter:** `MultiInstanceErrorCode`

**Type:** character vector

**Value:** `'None' | 'Warning' | 'Error'`

**Default:** `'Error'`

### Recommended Settings

| Application       | Setting          |
|-------------------|------------------|
| Debugging         | Warning or Error |
| Traceability      | No impact        |
| Efficiency        | None             |
| Safety precaution | No impact        |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Configure Code Generation for Model Entry-Point Functions”
- “Generate Reentrant Code from Top Models”
- “Generate C++ Class Interface to Model or Subsystem Code”
- “Control Generation of Functions for Subsystems”
- “Generate Reentrant Code from Subsystems”
- “Generate Reentrant Code from Subsystems”
- “Generate Modular Function Code for Nonvirtual Subsystems” (Embedded Coder)

## Generate C API for: signals

### Description

Generate C API data interface code with a signals structure.

**Category:** Code Generation > Interface

### Settings

**Default:** off

On

Generates C API interface to global block outputs.

Off

Does not generate C API signals.

### Command-Line Information

**Parameter:** RTWCAPISignals

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting                                                            |
|-------------------|--------------------------------------------------------------------|
| Debugging         | No impact                                                          |
| Traceability      | No impact                                                          |
| Efficiency        | No impact                                                          |
| Safety precaution | No impact during development<br>Off for production code generation |

### See Also

#### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Exchange Data Between Generated and External Code Using C API”

## Generate C API for: parameters

### Description

Generate C API data interface code with parameter tuning structures.

**Category:** Code Generation > Interface

### Settings

**Default:** off

On

Generates C API interface to global block parameters.

Off

Does not generate C API parameters.

### Command-Line Information

**Parameter:** RTWCAPIParams

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting                                                            |
|-------------------|--------------------------------------------------------------------|
| Debugging         | No impact                                                          |
| Traceability      | No impact                                                          |
| Efficiency        | No impact                                                          |
| Safety precaution | No impact during development<br>Off for production code generation |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Exchange Data Between Generated and External Code Using C API”

## Generate C API for: states

### Description

Generate C API data interface code with a states structure.

**Category:** Code Generation > Interface

### Settings

**Default:** off

On

Generates C API interface to discrete and continuous states.

Off

Does not generate C API states.

### Command-Line Information

**Parameter:** RTWCAPIStates

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting                                                            |
|-------------------|--------------------------------------------------------------------|
| Debugging         | No impact                                                          |
| Traceability      | No impact                                                          |
| Efficiency        | No impact                                                          |
| Safety precaution | No impact during development<br>Off for production code generation |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Exchange Data Between Generated and External Code Using C API”

## Generate C API for: root-level I/O

### Description

Generate C API data interface code with a root-level I/O structure.

**Category:** Code Generation > Interface

### Settings

**Default:** off

On

Generates a C API interface to root-level inputs and outputs.

Off

Does not generate a C API interface to root-level inputs and outputs.

### Command-Line Information

**Parameter:** RTWCAPIRootIO

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting                                                            |
|-------------------|--------------------------------------------------------------------|
| Debugging         | No impact                                                          |
| Traceability      | No impact                                                          |
| Efficiency        | No impact                                                          |
| Safety precaution | No impact during development<br>Off for production code generation |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Exchange Data Between Generated and External Code Using C API”

## ASAP2 interface

### Description

Generate code for the ASAP2 data interface.

**Category:** Code Generation > Interface

### Settings

**Default:** off

On

Generates code for the ASAP2 data interface.

Off

Does not generate code for the ASAP2 data interface.

### Command-Line Information

**Parameter:** GenerateASAP2

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting                                                            |
|-------------------|--------------------------------------------------------------------|
| Debugging         | No impact                                                          |
| Traceability      | No impact                                                          |
| Efficiency        | No impact                                                          |
| Safety precaution | No impact during development<br>Off for production code generation |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Export ASAP2 File for Data Measurement and Calibration”

## External mode

### Description

Generate code for the external mode data interface.

**Category:** Code Generation > Interface

### Settings

**Default:** off

On

Generates code for the external mode data interface.

Off

Does not generate code for the external mode data interface.

### Command-Line Information

**Parameter:** ExtMode

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting                                                            |
|-------------------|--------------------------------------------------------------------|
| Debugging         | No impact                                                          |
| Traceability      | No impact                                                          |
| Efficiency        | No impact                                                          |
| Safety precaution | No impact during development<br>Off for production code generation |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “External Mode Simulations for Parameter Tuning and Signal Monitoring”
- “External Mode Simulation by Using XCP Communication”
- “External Mode Simulation with TCP/IP or Serial Communication”

## Transport layer

### Description

Specify the transport protocol for communications.

**Category:** Code Generation > Interface

### Settings

**Default:** tcpip

tcpip

Use a TCP/IP transport mechanism. Selecting this parameter sets parameter **MEX-file name** to `ext_comm`.

serial

Use a serial transport mechanism. Selecting this parameter sets parameter **MEX-file name** to `ext_serial_win32_comm`.

XCP on TCP/IP

Use XCP protocol with TCP/IP transport layer. Selecting this parameter sets parameter **MEX-file name** to `ext_xcp`.

XCP on Serial

Use XCP protocol with serial transport layer. Selecting this parameter sets parameter **MEX-file name** to `ext_xcp`.

*customTransportLayer*

Use custom transport layer.

### Tips

The Configuration Parameters dialog box displays parameter **MEX-file name** next to **Transport layer**. You cannot edit the value for **MEX-file name**. The value is specified either in `matlabroot/toolbox/simulink/simulink/extmode_transports.m` for targets provided by MathWorks®, or in an `sl_customization.m` file for custom targets and transport mechanisms.

The command-line parameter is an index. To get the transport layer index, use these commands:

```
cs = getActiveConfigSet(modelName);
index = Simulink.ExtMode.Transports.getExtModeTransportIndex(cs, transportLayer);
```

*transportLayer* is one of these values:

- 'tcpip'
- 'serial'
- 'XCP on TCP/IP'
- 'XCP on Serial'
- *customTransportLayer*

To select the transport layer:

```
set_param(cs, 'ExtModeTransport', index)
```

To determine the transport layer:

```
transportLayerName = Simulink.ExtMode.Transports.getExtModeTransport(cs, index)
```

## Dependency

Selecting parameter **External mode** enables this parameter.

## Command-Line Information

**Parameter:** ExtModeTransport

**Type:** integer

**Value:** See “Tips” on page 10-26

**Default:** 0

## Recommended Settings

| Application       | No impact |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “External Mode Simulation by Using XCP Communication”
- “External Mode Simulation with TCP/IP or Serial Communication”
- “Customize XCP Slave Software”
- “Create a Transport Layer for TCP/IP or Serial External Mode Communication”

## MEX-file arguments

### Description

Specify arguments to pass to an external mode interface MEX-file for communicating with executing targets.

**Category:** Code Generation > Interface

### Settings

**Default:** ''

For XCP communication with a TCP/IP transport layer, there are four optional arguments:

- Network name of your target processor -- For example, 'localhost' if the target process is your development computer or the IP address '148.27.151.12'.
- Verbosity level -- 0 for no information or 1 to display detailed information during data transfer.
- Port number of TCP/IP server -- An integer value between 256 and 65535, with a default of 17725.
- Symbols file name -- File format is PDB for Windows or ELF for Linux®.

For XCP communication with a serial transport layer, there are four optional arguments:

- Verbosity level -- 0 for no information or 1 for detailed information.
- Serial port ID -- On Windows, 'COM1' or 1 for COM1, 'COM2' or 2 for COM2, etc. On Linux, '/dev/ttyS0', etc.
- Baud -- 1200, 2400, 4800, 9600, 14400, 19200, 38400, 57600 (default), or 115200.
- Symbols file name -- File format is PDB for Windows or ELF for Linux.

For TCP/IP interfaces, `ext_comm` allows three optional arguments:

- Network name of your target processor -- For example, 'myComputer' or '148.27.151.12'.
- Verbosity level -- 0 for no information or 1 to display detailed information during data transfer.
- Port number of TCP/IP server -- An integer value between 256 and 65535, with a default of 17725.

For a serial transport, `ext_serial_win32_comm` allows three optional arguments:

- Verbosity level -- 0 for no information or 1 for detailed information.
- Serial port ID -- 1 for COM1, etc.
- Baud -- 1200, 2400, 4800, 9600, 14400, 19200, 38400, 57600 (default), or 115200.

Specify the arguments in the list order. For example, if you want to specify the verbosity level (the second argument), then you must also specify the network name of the target processor (the first argument). You can use white space or commas as argument delimiters.

```
'148.27.151.12' 1 30000
```

## Dependency

Selecting parameter **External mode** enables this parameter.

## Command-Line Information

**Parameter:** ExtModeMexArgs

**Type:** character vector

**Value:** valid arguments

**Default:** ''

## Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “External Mode Simulation by Using XCP Communication”
- “External Mode Simulation with TCP/IP or Serial Communication”

## Static memory allocation

### Description

Control memory buffer for external mode communication.

**Category:** Code Generation > Interface

### Settings

**Default:** off

On

Enables parameter **Static memory buffer size** for allocating dynamic memory.

Off

Uses a static memory buffer for external mode simulation instead of allocating dynamic memory (calls to `malloc`).

### Tips

To determine how much memory to allocate, select verbose mode on the target. That selection displays the amount of memory the target tries to allocate and the amount of memory available.

If you set parameter **Transport layer** to `XCP on TCP/IP` or `XCP on Serial`, you can use parameter **Static memory buffer size** to specify the size of XCP slave memory that is allocated for signal logging.

### Dependencies

- Selecting parameter **External mode** enables this parameter.
- This parameter enables parameter **Static memory buffer size**.
- If parameter **Transport layer** is set to `XCP on TCP/IP` or `XCP on Serial`, you cannot disable this parameter.

### Command-Line Information

**Parameter:** ExtModeStaticAlloc

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application  | Setting   |
|--------------|-----------|
| Debugging    | No impact |
| Traceability | No impact |

---

| <b>Application</b> | <b>Setting</b> |
|--------------------|----------------|
| Efficiency         | No impact      |
| Safety precaution  | No impact      |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “External Mode Simulation with TCP/IP or Serial Communication”
- “Control Memory Allocation for Communication Buffers in Target”
- “XCP Platform Abstraction Layer”

## Static memory buffer size

### Description

Specify the memory buffer size for external mode communication.

**Category:** Code Generation > Interface

### Settings

**Default:** 1000000

Enter the number of bytes to preallocate for external mode communications buffers in the target.

### Tips

- If you enter too small a value for your application, external mode issues an out-of-memory error.
- To determine how much memory to allocate, select verbose mode on the target. That selection displays the amount of memory the target tries to allocate and the amount of memory available.
- If parameter **Transport layer** is set to **XCP on TCP/IP** or **XCP on Serial**, you can use this parameter to specify the size of XCP slave memory allocated for signal logging.

### Dependency

Selecting parameter **Static memory allocation** enables this parameter.

### Command-Line Information

**Parameter:** ExtModeStaticAllocSize

**Type:** integer

**Value:** valid value

**Default:** 1000000

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “External Mode Simulation with TCP/IP or Serial Communication”

- “Control Memory Allocation for Communication Buffers in Target”

## LUT object struct order for even spacing specification

### Description

Change the order of the fields in the generated structure for a lookup table object whose specification parameter is set to even spacing.

**Category:** Code Generation > Interface > Advanced Parameters

### Settings

**Default:** Size,Breakpoints,Table

Size,Breakpoints,Table

Display structure in the order size, breakpoints, table.

Size,Table,Breakpoints

Display structure in the order size, table, breakpoints.

### Command-Line Information

**Parameter:** LUTObjectStructOrderEvenSpacing

**Type:** character vector

**Value:** 'Size,Breakpoints,Table' | 'Size,Table,Breakpoints'

**Default:** 'Size,Breakpoints,Table'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## LUT object struct order for explicit value specification

### Description

Change the order of the fields in the generated structure for a lookup table object whose specification parameter is set to explicit value.

**Category:** Code Generation > Interface > Advanced Parameters

### Settings

**Default:** Size,Breakpoints,Table

Size,Breakpoints,Table

Display structure in the order size, breakpoints, table.

Size,Table,Breakpoints

Display structure in the order size, table, breakpoints.

### Command-Line Information

**Parameter:** LUTObjectStructOrderExplicitValues

**Type:** character vector

**Value:** 'Size,Breakpoints,Table' | 'Size,Table,Breakpoints'

**Default:** 'Size,Breakpoints,Table'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## Buffer size of dynamically-sized string (bytes)

### Description

Number of bytes of the character buffer generated for dynamic string signals without maximum length.

**Category:** Code Generation > Interface

### Settings

**Default:** 256

### Command-Line Information

**Parameter:** DynamicStringBufferSize

**Type:** character vector

**Value:** scalar

**Default:** 256

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

# Array layout

## Description

Specify the layout of array data for code generation as column-major or row-major.

**Category:** Code Generation > Interface

## Settings

**Default:** Column-major

### Column-major

Generate code in column-major array layout. For example, consider matrix A, which is a 4x3 matrix:

```
A =
 1 2 3
 4 5 6
 7 8 9
 10 11 12
```

In column-major array layout, the elements of the columns are contiguous in memory. A is represented in the generated code as:

```
1 4 7 10 2 5 8 11 3 6 9 12
```

### Row-major

Generate code in row-major array layout. For example, for matrix A, in row-major array layout, the elements of the rows are contiguous. A is represented in the generated code as:

```
1 2 3 4 5 6 7 8 9 10 11 12
```

Select parameter **Use algorithms optimized for row-major array layout** (Simulink) to enable efficient row-major algorithms.

## Command-Line Information

**Parameter:** ArrayLayout

**Type:** character vector

**Value:** 'Column-major' | 'Row-major'

**Default:** 'Column-major'

## Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## **See Also**

### **Related Examples**

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Code Generation of Matrices and Arrays”

# External functions compatibility for row-major code generation

## Description

Select the diagnostic action if Simulink encounters a function that has no specified array layout.

**Category:** Code Generation > Interface

## Settings

**Default:** error

none

The code generator produces code without generating an error or warning.

warning

The code generator builds the model and displays a warning message.

error

The code generator terminates the build and displays an error message.

## Dependencies

To enable this parameter, set parameter **Array layout** on page 10-37 to Row-major.

This parameter works only if your S-function or custom C function has a multidimensional array.

## Command-Line Information

**Parameter:** UnsupportedSFcnMsg

**Type:** character vector

**Value:** 'none' | 'warning' | 'error'

**Default:** 'error'

## Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | warning   |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | error     |

## See Also

## Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Generate Row-Major Code for S-Functions”

- “Code Generation of Matrices and Arrays”

# Standard math library

## Description

Specify standard math library for model.

**Category:** Code Generation > Interface

## Settings

**Default:** C99 (ISO) or, if **Language** is set to C++, C++03 (ISO)

C89/C90 (ANSI)

Generates calls to the ISO/IEC 9899:1990 C standard math library.

C99 (ISO)

Generates calls to the ISO/IEC 9899:1999 C standard math library.

C++03 (ISO)

Generates calls to the ISO/IEC 14882:2003 C++ standard math library.

## Tips

- Before setting this parameter, verify that your compiler supports the library you want to use. If you select a parameter value that your compiler does not support, compiler errors can occur.
- If you are using a compiler that does not support ISO/IEC 9899:1999 C, set this parameter to C89/C90 (ANSI).
- The build process checks whether the specified standard math library and toolchain are compatible. If they are not compatible, a warning occurs during code generation and the build process continues.
- If you specify this parameter for a Linux gcc build process, the software adds compiler flags to enforce the specified language standard. For example, if you set this parameter to C89/90 (ANSI), the software specifies:
  - For C code: `-ansi -pedantic`
  - For C++ code: `-std=c++98 -pedantic`

If the build process includes custom code that does not conform with the version of the language standard, for example, custom C++ code that uses C++11 features, then the code might fail to compile.

If your model is configured to use a toolchain for building code, use this workaround:

- 1 In the Configuration Parameters dialog box, set **Build configuration** to Specify.
- 2 Under **Toolchain details**, in the C Compiler and C++ Compiler **Options** fields, replace C\_STANDARD\_OPTS and CPP\_STANDARD\_OPTS with your required compiler flags, omitting `-pedantic` and flags that specifies a language standard. You can determine default values for C\_STANDARD\_OPTS and CPP\_STANDARD\_OPTS by inspecting a previously generated makefile.

## Dependencies

- C++03 is available for use only if you select C++ for the **Language** parameter.
- When you change the value of the **Language** parameter, the standard math library updates to C99 (ISO) for C and C++03 (ISO) for C++.

## Command-Line Information

**Parameter:** TargetLangStandard

**Type:** character vector

**Value:** 'C89/C90 (ANSI)' | 'C99 (ISO)' | 'C++03 (ISO)'

**Default:** For C, 'C99 (ISO)'; for C++ 'C++03 (ISO)'

## Recommended Settings

| Application       | Setting       |
|-------------------|---------------|
| Debugging         | No impact     |
| Traceability      | No impact     |
| Efficiency        | Valid library |
| Safety precaution | No impact     |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Specify Single-Precision Data Type for Embedded Application”
- “Run-Time Environment Configuration”

# Maximum word length

## Description

Specify a maximum word length, in bits, for which the code generation process generates system-defined multiword type definitions.

**Category:** Code Generation > Interface

## Settings

**Default:** 256 for ERT targets, 2048 for GRT targets

Specify a maximum word length, in bits, for which the code generation process generates multiword type definitions into the file `multiword_types.h`. All multiword type definitions up to and including this number of bits are generated. If you select 0, multiword type definitions are not generated into the file `multiword_types.h`.

The maximum word length for multiword types only determines the type definitions generated and does not impact the efficiency of the generated code. If the maximum word length for multiword types is set to 0 or too small, an error occurs when the generated code is compiled. This error is caused by the generated code using a type that does not have the required type definition. To resolve the error, increase the maximum word length and regenerate the code. If the maximum word length for multiword types is larger than required, then `multiword_types.h` might contain unused type definitions. Unused type definitions do not consume target resources.

## Tips

- Adding a model to a model hierarchy or changing an existing model in the hierarchy can result in updates to the shared `multiword_types.h` file during code generation. These updates occur when the new model uses multiword types of length greater than those of the other models. You must then recompile and, depending on your development process, reverify previously generated code. To prevent updates to `multiword_types.h`, determine a maximum word length sufficiently big to cover the needs of all models in the hierarchy. Configure every model in the hierarchy to use that same maximum word length.
- The majority of embedded designs do not need multiword types. By setting maximum word length for multiword types to 0, you can prevent use of multiword variables on the target. If you use multiword variables with a maximum word length that is 0 or smaller than required, you are alerted with an error when the generated code is compiled.

## Dependencies

- This parameter requires an Embedded Coder license when generating code.
- This parameter is enabled by selecting the value `User defined` for the parameter **Multiword type definitions**.

## Command-Line Information

**Parameter:** MultiwordLength

**Type:** integer

**Value:** valid quantity of bits representing a word size

**Default:** 256 for ERT targets, 2048 for GRT targets

## Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | No impact         |
| Traceability      | No impact         |
| Efficiency        | No impact         |
| Safety precaution | No recommendation |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2

# Classic call interface

## Description

Specify whether to generate model function calls compatible with the main program module of the GRT target in models created before R2012a.

**Category:** Code Generation > Interface

## Settings

**Default:** off (except on for GRT models created before R2012a)

On

Generates model function calls that are compatible with the main program module of the GRT system target file (`grt_main.c` or `grt_main.cpp`) in models created before R2012a.

This option provides a quick way to use code generated in the current release with a GRT-based custom target that has a main program module based on pre-R2012a `grt_main.c` or `grt_main.cpp`.

Off

Disables the classic call interface.

## Tips

The following are unsupported:

- Data type replacement
- **Code interface packaging** set to Reusable function or C++ class.
- Nonvirtual subsystem option **Function with separate data**

## Dependencies

- Setting **Code interface packaging** to C++ class disables this option.
- Selecting this option disables the incompatible option **Single output/update function**. Clearing this option enables (but does not select) **Single output/update function**.

## Command-Line Information

**Parameter:** GRTInterface

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off' (except 'on' for GRT models created before R2012a)

## Recommended Settings

| Application       | Setting                               |
|-------------------|---------------------------------------|
| Debugging         | No impact                             |
| Traceability      | Off                                   |
| Efficiency        | Off (execution, ROM), No impact (RAM) |
| Safety precaution | No recommendation                     |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Use Discrete and Continuous Time” (Embedded Coder)

## Single output/update function

### Description

Specify whether to generate the *model\_step* function.

**Category:** Code Generation > Interface

### Settings

**Default:** on

On

Generates the *model\_step* function for a model. This function contains the output and update function code for the blocks in the model and is called by *rt\_OneStep* to execute processing for one clock period of the model at interrupt level.

Off

Does not combine output and update function code into a single function, and instead generates the code in separate *model\_output* and *model\_update* functions.

### Tips

Errors or unexpected behavior can occur if a Model block is part of a cycle, the Model block is a direct feedthrough block, and an algebraic loop results. For more information about direct feed through, see “Algebraic Loop Concepts” (Simulink).

Simulink Coder ignores this parameter for a referenced model if any of the following conditions apply to that model:

- Is multi-rate
- Has a continuous sample time
- Is logging states (using the **States** or **Final states** parameters in the **Configuration Parameters > Data Import/Export** pane)

### Dependencies

- Setting **Code interface packaging** to C++ `class` forces on and disables this option.
- This option and **Classic call interface** are mutually incompatible and cannot both be selected through the GUI. Selecting **Classic call interface** forces off and disables this option and clearing **Classic call interface** enables (but does not select) this option.
- When you use this option, you must clear the option **Minimize algebraic loop occurrences** on the **Model Referencing** pane.
- If you customize `ert_main.c` or `.cpp` to read model outputs after each base-rate model step, selecting both parameters **Support: continuous time** and **Single output/update function** can cause output values read from `ert_main` for a continuous output port to differ from the corresponding output values in the logged data for the model. This is because, while logged data is a snapshot of output at major time steps, output read from `ert_main` after the base-rate model

step potentially reflects intervening minor time steps. The following table lists workarounds that eliminate the discrepancy.

| Work Around                                                                                                                                                                                                                                                                                                                                                                                                                                                                  | Customized ert_main.c | Customized ert_main.cpp |
|------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------------|-------------------------|
| Separate the generated output and update functions (clear the <b>Single output/update function</b> parameter), and insert code in <code>ert_main</code> to read model output values reflecting only the major time steps. For example, in <code>ert_main</code> , between the <code>model_output</code> call and the <code>model_update</code> call, read the model <code>External outputs</code> global data structure (defined in <code>model.h</code> ).                  | X                     |                         |
| Select the <b>Single output/update function</b> parameter and insert code in the generated <code>model.c</code> or <code>.cpp</code> file to return model output values reflecting only major time steps. For example, in the model step function, between the output code and the update code, save the value of the model <code>External outputs</code> global data structure (defined in <code>model.h</code> ). Then, restore the value after the update code completes. | X                     | X                       |
| Place a Zero-Order Hold block before the continuous output port.                                                                                                                                                                                                                                                                                                                                                                                                             | X                     | X                       |

### Command-Line Information

**Parameter:** CombineOutputUpdateFcns

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | On                |
| Traceability      | On                |
| Efficiency        | On                |
| Safety precaution | No recommendation |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “rt\_OneStep and Scheduling Considerations” (Embedded Coder)

# MAT-file logging

## Description

Specify MAT-file logging

**Category:** Code Generation > Interface

## Settings

**Default:** on for the GRT target, off for ERT-based targets

On

Enable MAT-file logging. When you select this option, the generated code saves to MAT-files simulation data specified in one of the following ways:

- **Configuration Parameters > Data Import/Export** (see “Model Configuration Parameters: Data Import/Export” (Simulink))
- To Workspace blocks
- To File blocks
- Scope blocks with the **Log data to workspace** parameter enabled

In simulation, this data would be written to the MATLAB workspace, as described in “Export Simulation Data” (Simulink) and “Configure Signal Data for Logging”. Setting MAT-file logging redirects the data to a MAT-file instead. The file is named *model.mat*, where *model* is the name of your model.

Off

Disable MAT-file logging. Clearing this option has the following benefits:

- Eliminates overhead associated with supporting a file system, which typically is not a requirement for embedded applications
- Eliminates extra code and memory usage required to initialize, update, and clean up logging variables
- Under certain conditions, eliminates code and storage associated with root output ports
- Omits the comparison between the current time and stop time in the *model\_step*, allowing the generated program to run indefinitely, regardless of the stop time setting

## Dependencies

- When you select **MAT-file logging**, you must also select the configuration parameters **Support: non-finite numbers** and, if you use an ERT-based system target file, **Support: floating-point numbers**.
- Selecting this option enables **MAT-file variable name modifier**.
- For ERT-based system target files, clear this parameter if you are using exported function calls.

## Limitations

- The code generator does not support MAT-file logging for custom data types (data types that are not built into Simulink).
- MAT-file logging does not support file-scoped data, for example, data items to which you apply the built-in storage class `FileScope`.
- In a referenced model, only the following data logging features are supported:
  - To File blocks
  - State logging — the software stores the data in the MAT-file for the top model.
- In the context of the Embedded Coder product, MAT-file logging does not support the following IDEs: Analog Devices® VisualDSP++®, Texas Instruments™ Code Composer Studio™, Wind River® DIAB/GCC.
- MAT-file logging does not support Outport blocks to which you apply the storage class `ImportedExternPointer` or storage classes that yield nonaddressable data in the generated code. For example, the storage class `GetSet` causes the Outport to appear in the generated code as a function call, which is not addressable. This limitation applies whether you apply the storage class directly by using, for example, the Model Data Editor, or by resolving the Outport to a `Simulink.Signal` object that uses the storage class. As a workaround, apply the storage class to the signal that enters the Outport block.

## Command-Line Information

**Parameter:** `MatFileLogging`

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on' for the GRT target, 'off' for ERT-based targets

## Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | On        |
| Traceability      | No impact |
| Efficiency        | Off       |
| Safety precaution | Off       |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Interface” on page 10-2
- “Log Program Execution Results”
- “Log Data for Analysis”
- “Virtualized Output Ports Optimization” (Embedded Coder)
- “Virtualized Output Ports Optimization” (Embedded Coder)

# Simulink Coder Parameters: Advanced Parameters

---

## Use Simulink Coder Features

### Description

Enable “Simulink Coder” features for models deployed to “Simulink Supported Hardware” (Simulink).

---

**Note** If you enable this parameter in a model where Simulink Coder is not installed or available in the environment, a question dialog box prompts you to update the model to build without Simulink Coder features.

---

**Category:** Hardware Implementation

### Settings

On

Enable the Simulink Coder features.

Off

Disable the Simulink Coder features.



Indicates that this parameter is enabled. To disable it, first disable the “Use Embedded Coder Features” (Embedded Coder) parameter.

### Dependencies

This parameter requires a Simulink Coder or Embedded Coder license.

### Command-Line Information

**Parameter:** UseSimulinkCoderFeatures

**Value:** 'on' or 'off'

**Default:** 'on'

### See Also

### Related Examples

- “Model Configuration”

# Configuration Parameters for Simulink Models

---

- “Code Generation Pane: RSim Target” on page 12-2
- “Code Generation Pane: S-Function Target” on page 12-5
- “Code Generation Pane: Tornado Target” on page 12-8
- “Recommended Settings Summary for Model Configuration Parameters” on page 12-22

## Code Generation Pane: RSim Target

The **Code Generation > RSim Target** pane includes these parameters when the Simulink Coder product is installed on your system and you specify the `rsim.tlc` system target file.

Parameter loading

Enable RSim executable to load parameters from a MAT-file

Solver

Solver selection:

Storage classes

Force storage classes to AUTO

### In this section...

“Code Generation: RSim Target Tab Overview” on page 12-2  
 “Enable RSim executable to load parameters from a MAT-file” on page 12-2  
 “Solver selection” on page 12-3  
 “Force storage classes to AUTO” on page 12-4

## Code Generation: RSim Target Tab Overview

Set configuration parameters for rapid simulation.

### Configuration

This tab appears only if you specify `rsim.tlc` as the “System target file” on page 5-6.

### See Also

- “Configure and Build Model for Rapid Simulation”
- “Run Rapid Simulations”
- “Code Generation Pane: RSim Target” on page 12-2

## Enable RSim executable to load parameters from a MAT-file

Specify whether to load RSim parameters from a MAT-file.

### Settings

**Default:** on

- On  
 Enables RSim to load parameters from a MAT-file.
- Off  
 Disables RSim from loading parameters from a MAT-file.

**Command-Line Information****Parameter:** RSIM\_PARAMETER\_LOADING**Type:** character vector**Value:** 'on' | 'off'**Default:** 'on'**Recommended Settings**

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

**See Also**

“Create a MAT-File That Includes a Model Parameter Structure”

**Solver selection**

Instruct the target how to select the solver.

**Settings****Default:** auto

auto

Lets the code generator choose the solver. The code generator uses the Simulink solver module if you specify a variable-step solver on the Solver pane. Otherwise, the code generator uses a built-in solver.

Use Simulink solver module

Instructs the code generator to use the variable-step solver that you specify on the **Solver** pane.

Use fixed-step solvers

Instructs the code generator to use the fixed-step solver that you specify on the **Solver** pane.

**Command-Line Information****Parameter:** RSIM\_SOLVER\_SELECTION**Type:** character vector**Value:** 'auto' | 'usesolvermodule' | 'usefixstep'**Default:** 'auto'**Recommended Settings**

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## Force storage classes to AUTO

Specify whether to retain your storage class settings in a model or to use the automatic settings.

### Settings

**Default:** on

On

Forces the Simulink software to determine storage classes.

Off

Causes the model to retain storage class settings.

### Tips

- Turn this parameter on for flexible custom code interfacing.
- Turn this parameter off to retain storage class settings such as `ExportedGlobal` or `ImportExtern`.

### Command-Line Information

**Parameter:** `RSIM_STORAGE_CLASS_AUTO`

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## Code Generation Pane: S-Function Target

The **Code Generation > S-Function Target** pane includes the following parameters when the Simulink Coder product is installed on your system and you specify the `rtwsfcn.tlc` system target file.

- Create new model
- Use value for tunable parameters
- Include custom source code

### In this section...

“Code Generation S-Function Target Tab Overview” on page 12-5

“Create new model” on page 12-5

“Use value for tunable parameters” on page 12-6

“Include custom source code” on page 12-6

## Code Generation S-Function Target Tab Overview

Control code generated for the S-function target (`rtwsfcn.tlc`).

### Configuration

This tab appears only if you specify the S-function target (`rtwsfcn.tlc`) as the “System target file” on page 5-6.

### See Also

- “Accelerate Simulation, Reuse Code, or Protect Intellectual Property by Using S-Function Target”
- “Code Generation Pane: S-Function Target” on page 12-5

## Create new model

Create a new model containing the generated S-function block.

### Settings

**Default:** on

On

Creates a new model, separate from the current model, containing the generated S-function block.

Off

Generates code but a new model is not created.

### Command-Line Information

**Parameter:** CreateModel

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on'

### See Also

“Accelerate Simulation, Reuse Code, or Protect Intellectual Property by Using S-Function Target”

## Use value for tunable parameters

Use the variable value instead of the variable name in generated block mask edit fields for tunable parameters.

### Settings

**Default:** off

On

Uses variable values for tunable parameters instead of the variable name in the generated block mask edit fields.

Off

Uses variable names for tunable parameters in the generated block mask edit fields.

### Command-Line Information

**Parameter:** UseParamValues

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### See Also

“Accelerate Simulation, Reuse Code, or Protect Intellectual Property by Using S-Function Target”

## Include custom source code

Include custom source code in the code generated for the S-function.

### Settings

**Default:** off

On

Include provided custom source code in the code generated for the S-function.

Off

Do not include custom source code in the code generated for the S-function.

### Command-Line Information

**Parameter:** AlwaysIncludeCustomSrc

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

**See Also**

“Accelerate Simulation, Reuse Code, or Protect Intellectual Property by Using S-Function Target”

## Code Generation Pane: Tornado Target

The **Code Generation > Tornado Target** pane includes the following parameters when the Simulink Coder product is installed on your system and you specify the `tornado.tlc` system target file.

**Software environment**

Code replacement library:

Shared code placement:

**Tornado**

MAT-file Logging

Code Format

StethoScope

Download to VxWorks target

**VxWorks**

Base task priority

Task stack size

**External mode options**

External mode

### In this section...

“Code Generation: Tornado Target Tab Overview” on page 12-9

“Standard math library” on page 12-9

“Code replacement library” on page 12-10

“Shared code placement” on page 12-11

“MAT-file logging” on page 12-12

“MAT-file variable name modifier” on page 12-13

“Code Format” on page 12-14

“StethoScope” on page 12-14

“Download to VxWorks target” on page 12-15

“Base task priority” on page 12-16

“Task stack size” on page 12-17

“External mode” on page 12-17

“Transport layer” on page 12-18

“MEX-file arguments” on page 12-19

**In this section...**

“Static memory allocation” on page 12-20

“Static memory buffer size” on page 12-20

**Code Generation: Tornado Target Tab Overview**

Control generated code for the Tornado target.

**Configuration**

This tab appears only if you specify `tornado.tlc` as the “System target file” on page 5-6.

**See Also**

- *Tornado User's Guide* from Wind River Systems
- *StethoScope User's Guide* from Wind River Systems
- “Asynchronous Support”
- “Code Generation Pane: Tornado Target” on page 12-8

**Standard math library**

Specify a standard math library for your model.

**Settings**

**Default:** C99 (ISO)

C89/C90 (ANSI)

Generates calls to the ISO/IEC 9899:1990 C standard math library.

C99 (ISO)

Generates calls to the ISO/IEC 9899:1999 C standard math library.

C++03 (ISO)

Generates calls to the ISO/IEC 14882:2003 C++ standard math library.

**Tips**

- The build process checks whether the specified standard math library and toolchain are compatible. If they are not compatible, a warning occurs during code generation and the build process continues.
- When you change the value of parameter **Language**, the standard math library updates to ISO/IEC 9899:1999 C (C99 (ISO)) for C and ISO/IEC 14882:2003 C++ (C++03 (ISO)) for C++.

**Dependencies**

The C++03 (ISO) math library is available for use only if you set parameter **Language** to C++.

**Command-Line Information**

**Parameter:** TargetLangStandard

**Type:** character vector

**Value:** 'C89/C90 (ANSI)' | 'C99 (ISO)' | 'C++03 (ISO)'  
**Default:** 'C99 (ISO)'

**Recommended Settings**

| Application       | Setting       |
|-------------------|---------------|
| Debugging         | No impact     |
| Traceability      | No impact     |
| Efficiency        | Valid library |
| Safety precaution | No impact     |

**See Also**

“Run-Time Environment Configuration”

**Code replacement library**

Specify a code replacement library the code generator uses when producing code for a model.

**Settings**

**Default:** None

None

Does not use a code replacement library.

Named code replacement library

Generates calls to a specific platform, compiler, or standards code replacement library. The list of named libraries depends on:

- Installed support packages.
- System target file, language, standard math library, and device vendor configuration.
- Whether you created and registered code replacement libraries, using the Embedded Coder product.

For more information about selections for this parameter, see “Code replacement library” on page 10-9.

**Tip**

Before setting this parameter, verify that your compiler supports the library you want to use. If you select a parameter value that your compiler does not support, compiler errors can occur.

**Command-Line Information**

**Parameter:** CodeReplacementLibrary

**Type:** character vector

**Value:** 'None' | 'GNU C99 extensions' | 'Intel IPP for x86-64 (Windows)' | 'Intel IPP/SSE for x86-64 (Windows)' | 'Intel IPP for x86-64 (Windows for MinGW compiler)' | 'Intel IPP/SSE for x86-64 (Windows for MinGW compiler)' | 'Intel IPP for x86/Pentium (Windows)' | 'Intel IPP/SSE x86/Pentium (Windows)' | 'Intel IPP for x86-64 (Linux)' | 'Intel IPP/SSE with GNU99 extensions for x86-64 (Linux)'

**Default:** 'None '

### Recommended Settings

| Application       | Setting       |
|-------------------|---------------|
| Debugging         | No impact     |
| Traceability      | No impact     |
| Efficiency        | Valid library |
| Safety precaution | No impact     |

### See Also

“Run-Time Environment Configuration”

## Shared code placement

Specify the location for generating utility functions, exported data type definitions, and declarations of exported data with custom storage class.

### Settings

**Default:** Auto

#### Auto

Operates as follows:

- When the model contains Model blocks, places utility code within the `slprj/target/_sharedutils` folder.
- When the model does not contain Model blocks, places utility code in the build folder (generally, in `model.c` or `model.cpp`).

#### Shared location

Directs code for utilities to be placed within the `slprj` folder in your working folder.

### Command-Line Information

**Parameter:** UtilityFuncGeneration

**Type:** character vector

**Value:** 'Auto' | 'Shared location'

**Default:** 'Auto'

### Recommended Settings

| Application       | Setting                                             |
|-------------------|-----------------------------------------------------|
| Debugging         | Shared location                                     |
| Traceability      | Shared location                                     |
| Efficiency        | No impact (execution, RAM)<br>Shared location (ROM) |
| Safety precaution | No impact                                           |

### See Also

- “Run-Time Environment Configuration”
- “Sharing Utility Code”

## MAT-file logging

Specify whether to enable MAT-file logging.

### Settings

**Default:** off

On

Enables MAT-file logging. When you select this option, the generated code saves to MAT-files simulation data specified in one of the following ways:

- Configuration Parameters dialog box, **Data Import/Export** pane (see “Model Configuration Parameters: Data Import/Export” (Simulink))
- To Workspace blocks
- Scope blocks with block parameter **Log data to workspace** enabled

In simulation, this data would be written to the MATLAB workspace, as described in “Export Simulation Data” (Simulink) and “Configure Signal Data for Logging”. Setting MAT-file logging redirects the data to a MAT-file instead. The file is named *model.mat*, where *model* is the name of your model.

Off

Disables MAT-file logging. Clearing this option has the following benefits:

- Eliminates overhead associated with supporting a file system, which typically is not required for embedded applications
- Eliminates extra code and memory usage required to initialize, update, and clean up logging variables
- Under certain conditions, eliminates code and storage associated with root output ports
- Omits the comparison between the current time and stop time in the *model\_step*, allowing the generated program to run indefinitely, regardless of the stop time setting

### Dependencies

Selecting this parameter enables parameter **MAT-file variable name modifier**.

### Limitation

MAT-file logging does not support file-scoped data, for example, data items to which you apply the built-in custom storage class `FileScope`.

MAT-file logging does not work in a referenced model, and code is not generated to implement it.

### Command-Line Information

**Parameter:** `MatFileLogging`

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | On        |
| Traceability      | No impact |
| Efficiency        | Off       |
| Safety precaution | Off       |

### See Also

- “Log Program Execution Results”
- “Log Data for Analysis”
- “Virtualized Output Ports Optimization” (Embedded Coder)

## MAT-file variable name modifier

Select the text to add to the MAT-file variable names.

### Settings

**Default:** rt\_

rt\_

Adds prefix text.

\_rt

Adds suffix text.

none

Does not add text.

### Dependency

If you have an Embedded Coder license, this parameter is enabled by parameter **MAT-file logging**.

### Command-Line Information

**Parameter:** LogVarNameModifier

**Type:** character vector

**Value:** 'none' | 'rt\_' | '\_rt'

**Default:** 'rt\_'

### Recommended Settings

| Application  | Setting   |
|--------------|-----------|
| Debugging    | No impact |
| Traceability | No impact |

| Application       | Setting   |
|-------------------|-----------|
| Efficiency        | No impact |
| Safety precaution | No impact |

**See Also**

- “Log Program Execution Results”
- “Log Data for Analysis”

**Code Format**

Specify the code format (generated code features).

**Settings**

**Default:** RealTime

RealTime

Specifies the Real-Time code generation format.

RealTimeMalloc

Specifies the Real-Time Malloc code generation format.

**Command-Line Information**

**Parameter:** CodeFormat

**Type:** character vector

**Value:** 'RealTime' | 'RealTimeMalloc'

**Default:** 'RealTime'

**Recommended Settings**

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

**See Also**

“Compare System Target File Support Across Products”

**StethoScope**

Specify whether to enable StethoScope, an optional data acquisition and data monitoring tool.

**Settings**

**Default:** off

On

Enables StethoScope.

Off

Disables StethoScope.

### Tips

You can optionally monitor and change the parameters of the executing real-time program using either StethoScope or Simulink External mode, but not both with the same compiled image.

### Dependencies

Enabling parameter **StethoScope** disables parameter **External mode**, and vice versa.

### Command-Line Information

**Parameter:** StethoScope

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | On        |
| Traceability      | No impact |
| Efficiency        | Off       |
| Safety precaution | Off       |

### See Also

- *Tornado User's Guide* from Wind River Systems
- *StethoScope User's Guide* from Wind River Systems

## Download to VxWorks target

Specify whether to automatically download the generated program to the VxWorks target.

### Settings

**Default:** off

 On

Automatically downloads the generated program to VxWorks after each build.

 Off

Does not automatically download to VxWorks, you must download generated programs manually.

### Tips

- Automatic download requires specifying the target name and host name in the makefile.

- Before every build, reset VxWorks by pressing **Ctrl+X** on the host console or power-cycling the VxWorks chassis. This clears dangling processes or stale data that exists in VxWorks when the automatic download occurs.

**Command-Line Information**

**Parameter:** DownloadToVxWorks

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

**Recommended Settings**

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | Off       |

**See Also**

- *Tornado User's Guide* from Wind River Systems
- "Asynchronous Support"

**Base task priority**

Specify the priority with which the base rate task for the model is to be spawned.

**Settings**

**Default:** 30

**Tips**

- For a multirate, multitasking model, the code generator increments the priority of each subrate task by one.
- The value you specify for this option will be overridden by a base priority specified in a call to the `rt_main()` function spawned as a task.

**Command-Line Information**

**Parameter:** BasePriority

**Type:** integer

**Value:** valid value

**Default:** 30

**Recommended Settings**

| Application  | Setting   |
|--------------|-----------|
| Debugging    | No impact |
| Traceability | No impact |

| Application       | Setting                                                       |
|-------------------|---------------------------------------------------------------|
| Efficiency        | Might impact efficiency, depending on other task's priorities |
| Safety precaution | No impact                                                     |

**See Also**

- *Tornado User's Guide* from Wind River Systems
- “Asynchronous Support”

**Task stack size**

Stack size in bytes for each task that executes the model.

**Settings**

**Default:** 16384

**Command-Line Information**

**Parameter:** TaskStackSize

**Type:** integer

**Value:** valid value

**Default:** 16384

**Recommended Settings**

| Application       | Setting                                          |
|-------------------|--------------------------------------------------|
| Debugging         | No impact                                        |
| Traceability      | No impact                                        |
| Efficiency        | Larger stack may waste space                     |
| Safety precaution | Larger stack reduces the possibility of overflow |

**See Also**

- *Tornado User's Guide* from Wind River Systems
- “Asynchronous Support”

**External mode**

Specify whether to enable communication between the Simulink model and an application based on a client/server architecture.

**Settings**

**Default:** on

On

Enables External mode. The client (Simulink model) transmits messages requesting the server (application) to accept parameter changes or to upload signal data. The server responds by executing the request.



Disables External mode.

### Dependencies

Selecting this parameter enables these parameters:

- **Transport layer**
- **MEX-file arguments**
- **Static memory allocation**

### Command-Line Information

**Parameter:** ExtMode

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

“External Mode Simulations for Parameter Tuning and Signal Monitoring”

## Transport layer

Specify the transport protocol for External mode communications.

### Settings

**Default:** tcpip

tcpip

Applies a TCP/IP transport mechanism. The MEX-file name is `ext_comm`.

### Tip

You cannot edit the value of the **MEX-file name** parameter displayed next to parameter **Transport layer**. For system target files provided by MathWorks, the value is specified in `matlabroot/toolbox/simulink/simulink/extmode_transports.m`.

### Dependency

This parameter is enabled by parameter **External mode**.

**Command-Line Information****Parameter:** ExtModeTransport**Type:** integer**Value:** 0**Default:** 0**Recommended Settings**

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

**See Also**

“External Mode Simulation with TCP/IP or Serial Communication”

**MEX-file arguments**

Specify arguments to pass to an External mode interface MEX-file for communicating with executing targets.

**Settings****Default:** ''

For TCP/IP interfaces, `ext_comm` allows three optional arguments:

- Network name of your target (for example, 'myPuter' or '148.27.151.12')
- Verbosity level (0 for no information or 1 for detailed information)
- TCP/IP server port number (an integer value between 256 and 65535, with a default of 17725)

**Dependency**

This parameter is enabled by parameter **External mode**.

**Command-Line Information****Parameter:** ExtModeMexArgs**Type:** character vector**Value:** valid arguments**Default:** ''**Recommended Settings**

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

**See Also**

- “External Mode Simulation with TCP/IP or Serial Communication”
- “Choose Communication Protocol for Client and Server”

**Static memory allocation**

Control the memory buffer for External mode communication.

**Settings**

**Default:** off

On

Enables parameter **Static memory buffer size** for allocating dynamic memory.

Off

Uses a static memory buffer for External mode instead of allocating dynamic memory (calls to malloc).

**Tip**

To determine how much memory you need to allocate, select verbose mode on the target to display the amount of memory it tries to allocate and the amount of memory available.

**Dependencies**

- This parameter is enabled by parameter **External mode**.
- This parameter enables parameter **Static memory buffer size**.

**Command-Line Information**

**Parameter:** ExtModeStaticAlloc

**Type:** character vector

**Value:** 'on' | 'off'

**Default:** 'off'

**Recommended Settings**

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

**See Also**

“Control Memory Allocation for Communication Buffers in Target”

**Static memory buffer size**

Specify the memory buffer size for External mode communication.

## Settings

**Default:** 1000000

Enter the number of bytes to preallocate for External mode communications buffers in the target.

### Tips

- If you enter too small a value for your application, External mode issues an out-of-memory error.
- To determine how much memory you need to allocate, select verbose mode on the target to display the amount of memory it tries to allocate and the amount of memory available.

### Dependency

This parameter is enabled by parameter **Static memory allocation**.

### Command-Line Information

**Parameter:** ExtModeStaticAllocSize

**Type:** integer

**Value:** valid value

**Default:** 1000000

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

### See Also

“Control Memory Allocation for Communication Buffers in Target”

## **Recommended Settings Summary for Model Configuration Parameters**

The following table summarizes the impact of each configuration parameter on debugging, traceability, efficiency, and safety considerations, and indicates the factory default configuration settings for the GRT and ERT targets, unless otherwise specified.

For parameters that are available only when an ERT target is specified, see “Recommended Settings Summary for Model Configuration Parameters” (Embedded Coder).

For additional details, click the links in the Configuration Parameter column.

## Mapping Application Requirements to the Solver Pane

| Configuration Parameter                                                    | Settings for Building Code |                                                                                               |            |                                                                                                                                       | Factory Default                                                   |
|----------------------------------------------------------------------------|----------------------------|-----------------------------------------------------------------------------------------------|------------|---------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------|
|                                                                            | Debugging                  | Traceability                                                                                  | Efficiency | Safety precaution                                                                                                                     |                                                                   |
| <b>“Start time” (Simulink)</b>                                             | No impact                  | No impact                                                                                     | No impact  | 0.0                                                                                                                                   | 0.0 seconds                                                       |
| <b>“Stop time” (Simulink)</b>                                              | No impact                  | No impact                                                                                     | No impact  | A positive value                                                                                                                      | 10.0 seconds                                                      |
| <b>“Type” (Simulink)</b>                                                   | Fixed-step                 | Fixed-step                                                                                    | Fixed-step | Fixed-step                                                                                                                            | Variable-step (you must change to Fixed-step for code generation) |
| <b>“Solver” (Simulink)</b>                                                 | No impact                  | No impact                                                                                     | No impact  | Discrete (no continuous states)                                                                                                       | ode3 (Bogacki-Shampine)                                           |
| <b>“Periodic sample time constraint” (Simulink)</b>                        | No impact                  | No impact                                                                                     | No impact  | Specified or Ensure sample time independent                                                                                           | Unconstrained                                                     |
| <b>“Sample time properties” (Simulink)</b>                                 | No impact                  | No impact                                                                                     | No impact  | Period, offset, and priority of each sample time in the model; faster sample times must have higher priority than slower sample times | ''                                                                |
| <b>“Treat each discrete rate as a separate task” (Simulink)</b>            | No impact                  | No impact                                                                                     | No impact  | No impact                                                                                                                             | On                                                                |
| <b>“Automatically handle rate transition for data transfer” (Simulink)</b> | No impact                  | No impact (for simulation and during development)<br><br>Off (for production code generation) | No impact  | Off                                                                                                                                   | Off                                                               |

**Mapping Application Requirements to the Data Import/Export Pane**

| Configuration Parameter                                                       | Settings for Building Code |              |                   |                   | Factory Default |
|-------------------------------------------------------------------------------|----------------------------|--------------|-------------------|-------------------|-----------------|
|                                                                               | Debugging                  | Traceability | Efficiency        | Safety precaution |                 |
| <b>“Input” (Simulink)</b>                                                     | No impact                  | No impact    | No recommendation | No recommendation | Off             |
| <b>“Initial state” (Simulink)</b>                                             | No impact                  | No impact    | No recommendation | No recommendation | Off             |
| <b>“Time” (Simulink)</b>                                                      | No impact                  | No impact    | No recommendation | No recommendation | On              |
| <b>“States” (Simulink)</b>                                                    | No impact                  | No impact    | No recommendation | No recommendation | Off             |
| <b>“Output” (Simulink)</b>                                                    | No impact                  | No impact    | No recommendation | No recommendation | On              |
| <b>“Final states” (Simulink)</b>                                              | No impact                  | No impact    | No recommendation | No recommendation | Off             |
| <b>“Signal logging” (Simulink)</b>                                            | No impact                  | No impact    | No recommendation | No recommendation | On              |
| <b>“Record logged workspace data in Simulation Data Inspector” (Simulink)</b> | No impact                  | No impact    | No recommendation | No recommendation | Off             |
| <b>“Limit data points” (Simulink)</b>                                         | No impact                  | No impact    | No recommendation | No recommendation | On              |
| <b>“Decimation” (Simulink)</b>                                                | No impact                  | No impact    | No recommendation | No recommendation | 1               |
| <b>“Format” (Simulink)</b>                                                    | No impact                  | No impact    | No recommendation | No recommendation | Array           |
| <b>“Output options” (Simulink)</b>                                            | No impact                  | No impact    | No recommendation | No recommendation | Refine output   |
| <b>“Refine factor” (Simulink)</b>                                             | No impact                  | No impact    | No recommendation | No recommendation | 1               |

| Configuration Parameter   | Settings for Building Code |              |                   |                   | Factory Default |
|---------------------------|----------------------------|--------------|-------------------|-------------------|-----------------|
|                           | Debugging                  | Traceability | Efficiency        | Safety precaution |                 |
| “Output times” (Simulink) | No impact                  | No impact    | No recommendation | No recommendation | ' [] '          |

### Mapping Application Requirements to the Math and Data Types Pane

| Configuration Parameter                                                        | Settings for Building Code |              |                                                                                    |                   | Factory Default |
|--------------------------------------------------------------------------------|----------------------------|--------------|------------------------------------------------------------------------------------|-------------------|-----------------|
|                                                                                | Debugging                  | Traceability | Efficiency                                                                         | Safety precaution |                 |
| “Default for underspecified data type” (Simulink)                              | No impact                  | No impact    | single                                                                             | No impact         | double          |
| “Use division for fixed-point net slope computation” (Simulink)                | No impact                  | No impact    | On (when target hardware supports efficient division)<br><br>Off (otherwise)       | No impact         | off             |
| “Application lifespan (days)” (Simulink)                                       | No impact                  | No impact    | Finite value                                                                       | inf               | auto            |
| “Use floating-point multiplication to handle net slope corrections” (Simulink) | No impact                  | No impact    | On (when target hardware supports efficient multiplication)<br><br>Off (otherwise) | No recommendation | Off             |

\*The command-line value is reverse of the listed value.

**Mapping Application Requirements to the Optimization Pane**

| Configuration Parameter                                                                              | Settings for Building Code     |              |                                                           |                   | Factory Default                |
|------------------------------------------------------------------------------------------------------|--------------------------------|--------------|-----------------------------------------------------------|-------------------|--------------------------------|
|                                                                                                      | Debugging                      | Traceability | Efficiency                                                | Safety precaution |                                |
| “Default parameter behavior” on page 16-9                                                            | Tunable (GRT)<br>Inlined (ERT) | Inlined      | Inlined                                                   | No impact         | Tunable (GRT)<br>Inlined (ERT) |
| “Loop unrolling threshold” on page 16-16                                                             | No impact                      | No impact    | >0                                                        | No impact         | 5                              |
| “Maximum stack size (bytes)” on page 16-17                                                           | No impact                      | No impact    | No impact                                                 | No impact         | Inherit from target            |
| “Use memcpy for vector assignment” on page 16-13                                                     | No impact                      | No impact    | On                                                        | No impact         | On                             |
| “Memcpy threshold (bytes)” on page 16-15                                                             | No impact                      | No impact    | Accept default or determine target-specific optimal value | No impact         | 64                             |
| “Inline invariant signals” on page 16-11                                                             | Off                            | Off          | On                                                        | No impact         | Off                            |
| “Remove code from floating-point to integer conversions that wraps out-of-range values” on page 16-6 | Off                            | Off          | On (execution, ROM)<br>No impact (RAM)                    | No impact         | Off                            |
| “Use bitsets for storing state configuration” on page 16-19                                          | Off                            | Off          | Off (execution, ROM)<br>On (RAM)                          | No impact         | Off                            |
| “Use bitsets for storing Boolean data” on page 16-21                                                 | Off                            | Off          | Off (execution, ROM)<br>On (RAM)                          | No impact         | Off                            |

**Mapping Application Requirements to the Diagnostics Pane: Solver Tab**

| Configuration Parameter                                       | Settings for Building Code |              |            |                   | Factory Default |
|---------------------------------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                                               | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| <b>“Algebraic loop” (Simulink)</b>                            | error                      | No impact    | No impact  | error             | warning         |
| <b>“Minimize algebraic loop” (Simulink)</b>                   | No impact                  | No impact    | No impact  | error             | warning         |
| <b>“Block priority violation” (Simulink)</b>                  | No impact                  | No impact    | No impact  | error             | warning         |
| <b>“Consecutive zero-crossings violation” (Simulink)</b>      | No impact                  | No impact    | No impact  | warning or error  | error           |
| <b>“Unspecified inheritability of sample time” (Simulink)</b> | No impact                  | No impact    | No impact  | error             | warning<br>     |
| <b>“Solver data inconsistency” (Simulink)</b>                 | warning                    | No impact    | none       | No impact         | warning         |
| <b>“Automatic solver parameter selection” (Simulink)</b>      | No impact                  | No impact    | No impact  | error             | warning         |

**Mapping Application Requirements to the Diagnostics Pane: Sample Time Tab**

| Configuration Parameter                                                    | Settings for Building Code |              |            |                   | Factory Default |
|----------------------------------------------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                                                            | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| “Source block specifies -1 sample time” (Simulink)                         | No impact                  | No impact    | No impact  | error             | none            |
| “Multitask rate transition” (Simulink)                                     | No impact                  | No impact    | No impact  | error             | error           |
| “Single task rate transition” (Simulink)                                   | No impact                  | No impact    | No impact  | none or error     | none            |
| “Multitask conditionally executed subsystem” (Simulink)                    | No impact                  | No impact    | No impact  | error             | error           |
| “Tasks with equal priority” (Simulink)                                     | No impact                  | No impact    | No impact  | none or error     | warning         |
| “Enforce sample times specified by Signal Specification blocks” (Simulink) | No impact                  | No impact    | No impact  | error             | warning         |

## Mapping Application Requirements to the Diagnostics Pane: Data Validity Tab

| Configuration Parameter                  | Settings for Building Code |                  |            |                   | Factory Default                                              |
|------------------------------------------|----------------------------|------------------|------------|-------------------|--------------------------------------------------------------|
|                                          | Debugging                  | Traceability     | Efficiency | Safety precaution |                                                              |
| “Signal resolution” (Simulink)           | No impact                  | No impact        | No impact  | Explicit only     | Explicit only                                                |
| “Division by singular matrix” (Simulink) | No impact                  | No impact        | No impact  | error             | none                                                         |
| “Underspecified data types” (Simulink)   | No impact                  | No impact        | No impact  | error             | none                                                         |
| “Simulation range checking” (Simulink)   | warning or error           | warning or error | none       | error             | none                                                         |
| “Wrap on overflow” (Simulink)            | No impact                  | No impact        | No impact  | error             | warning                                                      |
| “Saturate on overflow” (Simulink)        | No impact                  | No impact        | No impact  | error             | warning                                                      |
| “Inf or NaN block output” (Simulink)     | No impact                  | No impact        | No impact  | error             | none                                                         |
| ““rt” prefix for identifiers” (Simulink) | No impact                  | No impact        | No impact  | error             | error                                                        |
| “Detect downcast” (Simulink)             | No impact                  | No impact        | No impact  | error             | error                                                        |
| “Detect overflow” (Simulink)             | No impact                  | No impact        | No impact  | error             | error                                                        |
| “Detect underflow” (Simulink)            | No impact                  | No impact        | No impact  | error             | none                                                         |
| “Detect precision loss” (Simulink)       | No impact                  | No impact        | No impact  | error             | error                                                        |
| “Detect loss of tunability” (Simulink)   | No impact                  | No impact        | No impact  | error             | warning for GRT-based targets<br>error for ERT-based targets |
| “Detect read before write” (Simulink)    | No impact                  | No impact        | No impact  | error             | Enable all as warnings                                       |
| “Detect write after read” (Simulink)     | No impact                  | No impact        | No impact  | error             | Enable all as warning                                        |
| “Detect write after write” (Simulink)    | No impact                  | No impact        | No impact  | error             | Enable all as errors                                         |
| “Multitask data store” (Simulink)        | No impact                  | No impact        | No impact  | error             | warning                                                      |
| “Duplicate data store names” (Simulink)  | warning                    | No impact        | none       | No impact         | none                                                         |

| Configuration Parameter                                | Settings for Building Code |              |            |                   | Factory Default |
|--------------------------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                                        | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| “Check undefined subsystem initial output” (Simulink)  | No impact                  | No impact    | No impact  | On                | On              |
| “Check runtime output of execution context” (Simulink) | No impact                  | No impact    | No impact  | On                | Off             |

**Mapping Application Requirements to the Diagnostics Pane: Type Conversion Tab**

| Configuration Parameter                                          | Settings for Building Code |              |            |                   | Factory Default |
|------------------------------------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                                                  | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| “Unnecessary type conversions” (Simulink)                        | No impact                  | No impact    | No impact  | warning           | none            |
| “Vector/matrix block input conversion” (Simulink)                | No impact                  | No impact    | No impact  | error             | none            |
| “32-bit integer to single precision float conversion” (Simulink) | No impact                  | No impact    | No impact  | warning           | warning         |

**Mapping Application Requirements to the Diagnostics Pane: Connectivity Tab**

| Configuration Parameter                                  | Settings for Building Code |              |            |                   | Factory Default    |
|----------------------------------------------------------|----------------------------|--------------|------------|-------------------|--------------------|
|                                                          | Debugging                  | Traceability | Efficiency | Safety precaution |                    |
| “Signal label mismatch” (Simulink)                       | No impact                  | No impact    | No impact  | error             | none               |
| “Unconnected block input ports” (Simulink)               | No impact                  | No impact    | No impact  | error             | warning            |
| “Unconnected block output ports” (Simulink)              | No impact                  | No impact    | No impact  | error             | warning            |
| “Unconnected line” (Simulink)                            | No impact                  | No impact    | No impact  | error             | none               |
| “Unspecified bus object at root Output block” (Simulink) | No impact                  | No impact    | No impact  | error             | warning            |
| “Element name mismatch” (Simulink)                       | No impact                  | No impact    | No impact  | error             | warning            |
| “Bus signal treated as vector” (Simulink)                | No impact                  | No impact    | No impact  | error             | none               |
| “Context-dependent inputs” (Simulink)                    | No impact                  | No impact    | No impact  | Enable all        | Use local settings |

**Mapping Application Requirements to the Diagnostics Pane: Compatibility Tab**

| Configuration Parameter                 | Settings for Building Code |              |            |                   | Factory Default |
|-----------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                         | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| “S-function upgrades needed” (Simulink) | No impact                  | No impact    | No impact  | error             | none            |

**Mapping Application Requirements to the Diagnostics Pane: Model Referencing Tab**

| Configuration Parameter                                    | Settings for Building Code |              |            |                   | Factory Default |
|------------------------------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                                            | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| “Model block version mismatch” (Simulink)                  | No impact                  | No impact    | No impact  | No recommendation | none            |
| “Port and parameter mismatch” (Simulink)                   | No impact                  | No impact    | No impact  | error             | none            |
| “Invalid root Inport/ Outport block connection” (Simulink) | No impact                  | No impact    | No impact  | error             | none            |
| “Unsupported data logging” (Simulink)                      | No impact                  | No impact    | No impact  | error             | warning         |

**Mapping Application Requirements to the Diagnostics Pane: Saving Tab**

| Configuration Parameter                                         | Settings for Building Code |              |            |                   | Factory Default |
|-----------------------------------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                                                 | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| “Block diagram contains disabled library links” (Simulink)      | No impact                  | No impact    | No impact  | No impact         | warning         |
| “Block diagram contains parameterized library links” (Simulink) | No impact                  | No impact    | No impact  | No impact         | none            |

## Mapping Application Requirements to the Diagnostics Pane: Stateflow Tab

| Configuration Parameter                                               | Settings for Building Code |              |                                                                                                |                   | Factory Default |
|-----------------------------------------------------------------------|----------------------------|--------------|------------------------------------------------------------------------------------------------|-------------------|-----------------|
|                                                                       | Debugging                  | Traceability | Efficiency                                                                                     | Safety precaution |                 |
| <b>“Unused data, events, messages, and functions” (Simulink)</b>      | warning                    | No impact    | No impact (for simulation and during development)<br><br>none (for production code generation) | warning           | warning         |
| <b>“Unexpected backtracking” (Simulink)</b>                           | warning                    | No impact    | No impact                                                                                      | error             | warning         |
| <b>“Invalid input data access in chart initialization” (Simulink)</b> | warning                    | No impact    | No impact                                                                                      | error             | warning         |
| <b>“No unconditional default transitions” (Simulink)</b>              | warning                    | No impact    | No impact (for simulation and during development)<br><br>none (for production code generation) | error             | warning         |
| <b>“Transition outside natural parent” (Simulink)</b>                 | warning                    | No impact    | No impact (for simulation and during development)<br><br>none (for production code generation) | error             | warning         |

Mapping Application Requirements to the Hardware Implementation Pane

| Configuration Parameter    | Settings for Building Code |              |            |                                                                                                                                                                                                                                   | Factory Default                                                                                                                                                                     |
|----------------------------|----------------------------|--------------|------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
|                            | Debugging                  | Traceability | Efficiency | Safety precaution                                                                                                                                                                                                                 |                                                                                                                                                                                     |
| “Device vendor” (Simulink) | No impact                  | No impact    | No impact  | Select your <b>Device vendor</b> and <b>Device type</b> if they are available in the drop-down list. If your <b>Device vendor</b> and <b>Device type</b> are not available, set device-specific values by using Custom Processor. | None if specified system target file is <code>ert.tlc</code> , <code>realtime.tlc</code> , or <code>autosar.tlc</code> . Otherwise, Determine by Code Generation system target file |
| “Device vendor” (Simulink) | No impact                  | No impact    | No impact  | Select your <b>Device vendor</b> and <b>Device type</b> if they are available in the drop-down list. If your <b>Device vendor</b> and <b>Device type</b> are not available, set device-specific values by using Custom Processor. | Intel                                                                                                                                                                               |
| “Device type” (Simulink)   | No impact                  | No impact    | No impact  | Select your <b>Device vendor</b> and <b>Device type</b> if they are available in the drop-down list. If your <b>Device vendor</b> and <b>Device type</b> are not available, set device-specific values by using Custom Processor. | x86–64 (Windows64)                                                                                                                                                                  |

| Configuration Parameter                          | Settings for Building Code |              |                 |                                                                                                                                                                                                                                                                                                                                  | Factory Default                                                                             |
|--------------------------------------------------|----------------------------|--------------|-----------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------|
|                                                  | Debugging                  | Traceability | Efficiency      | Safety precaution                                                                                                                                                                                                                                                                                                                |                                                                                             |
| <b>“Number of bits: char” (Simulink)</b>         | No impact                  | No impact    | Target specific | No recommendation for simulation without code generation. For simulation with code generation, select your <b>Device vendor</b> and <b>Device type</b> if they are available in the drop-down list. If your <b>Device vendor</b> and <b>Device type</b> are not available, set device-specific values by using Custom Processor. | char 8, short 16, int 32, long 32, long long 64, float 32, double 64, native 32, pointer 32 |
| <b>“Largest atomic size: integer” (Simulink)</b> | No impact                  | No impact    | Target specific | No recommendation for simulation without code generation. For simulation with code generation, select your <b>Device vendor</b> and <b>Device type</b> if they are available in the drop-down list. If your <b>Device vendor</b> and <b>Device type</b> are not available, set device-specific values by using Custom Processor. | integer Char, floating-point Float                                                          |

| Configuration Parameter                                      | Settings for Building Code                                                                             |                                                                                                            |                                                                                                   |                                                                                                                                                                                                                                                                                                                                         | Factory Default |
|--------------------------------------------------------------|--------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------|
|                                                              | Debugging                                                                                              | Traceability                                                                                               | Efficiency                                                                                        | Safety precaution                                                                                                                                                                                                                                                                                                                       |                 |
| <p><b>“Byte ordering” (Simulink)</b></p>                     | No impact                                                                                              | No impact                                                                                                  | No impact                                                                                         | No recommendation for simulation without code generation. For simulation with code generation, select your <b>Device vendor</b> and <b>Device type</b> if they are available in the drop-down list. If your <b>Device vendor</b> and <b>Device type</b> are not available, set device-specific values by using Custom Processor.        | Little Endian   |
| <p><b>“Signed integer division rounds to” (Simulink)</b></p> | <p>No impact for simulation and during development</p> <p>Undefined for production code generation</p> | <p>No impact for simulation and during development</p> <p>Zero or Floor for production code generation</p> | <p>No impact for simulation and during development</p> <p>Zero for production code generation</p> | <p>No recommendation for simulation without code generation. For simulation with code generation, select your <b>Device vendor</b> and <b>Device type</b> if they are available in the drop-down list. If your <b>Device vendor</b> and <b>Device type</b> are not available, set device-specific values by using Custom Processor.</p> | Zero            |

| Configuration Parameter                                          | Settings for Building Code |              |                     |                                                                                                                                                                                                                                                                                                                                  | Factory Default |
|------------------------------------------------------------------|----------------------------|--------------|---------------------|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|-----------------|
|                                                                  | Debugging                  | Traceability | Efficiency          | Safety precaution                                                                                                                                                                                                                                                                                                                |                 |
| “Shift right on a signed integer as arithmetic shift” (Simulink) | No impact                  | No impact    | On                  | No recommendation for simulation without code generation. For simulation with code generation, select your <b>Device vendor</b> and <b>Device type</b> if they are available in the drop-down list. If your <b>Device vendor</b> and <b>Device type</b> are not available, set device-specific values by using Custom Processor. | On              |
| “Support long long” (Simulink)                                   | No impact                  | No impact    | On (execution, ROM) | No recommendation for simulation without code generation. For simulation with code generation, select your <b>Device vendor</b> and <b>Device type</b> if they are available in the drop-down list. If your <b>Device vendor</b> and <b>Device type</b> are not available, set device-specific values by using Custom Processor. | Off             |

Mapping Application Requirements to the Model Referencing Pane

| Configuration Parameter                                                      | Settings for Building Code |              |            |                                                                                                                                                           | Factory Default            |
|------------------------------------------------------------------------------|----------------------------|--------------|------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------|----------------------------|
|                                                                              | Debugging                  | Traceability | Efficiency | Safety precaution                                                                                                                                         |                            |
| “Rebuild” (Simulink)                                                         | No impact                  | No impact    | No impact  | If any changes detected or Never<br><br>If you use the Never setting, then set the <b>Never rebuild diagnostic</b> parameter to Error if rebuild required | If any changes detected    |
| “Never rebuild diagnostic” (Simulink)                                        | No impact                  | No impact    | No impact  | error if rebuild required                                                                                                                                 | error if rebuild required  |
| “Enable parallel model reference builds” (Simulink)                          | No impact                  | No impact    | No impact  | No impact                                                                                                                                                 | Off                        |
| “MATLAB worker initialization for builds” (Simulink)                         | No impact                  | No impact    | No impact  | No impact                                                                                                                                                 | None                       |
| “Total number of instances allowed per top model” (Simulink)                 | No impact                  | No impact    | No impact  | No recommendation                                                                                                                                         | Multiple                   |
| “Pass fixed-size scalar root inputs by value for code generation” (Simulink) | No impact                  | No impact    | No impact  | No recommendation                                                                                                                                         | Off                        |
| “Minimize algebraic loop occurrences” (Simulink)                             | No impact                  | No impact    | No impact  | No recommendation                                                                                                                                         | Off                        |
| “Propagate sizes of variable-size signals” (Simulink)                        | No impact                  | No impact    | No impact  | No recommendation                                                                                                                                         | Infer from blocks in model |
| “Model dependencies” (Simulink)                                              | No impact                  | No impact    | No impact  | No recommendation                                                                                                                                         | ''                         |

**Mapping Application Requirements to the Simulation Target Pane: General Tab**

| Configuration Parameter                          | Settings for Building Code |                   |                   |                   | Factory Default   |
|--------------------------------------------------|----------------------------|-------------------|-------------------|-------------------|-------------------|
|                                                  | Debugging                  | Traceability      | Efficiency        | Safety precaution |                   |
| “Ensure memory integrity” (Simulink)             | On                         | No impact         | No recommendation | On                | On                |
| “Echo expressions without semicolons” (Simulink) | On                         | No impact         | Off               | No impact         | On                |
| “Ensure responsiveness” (Simulink)               | On                         | No recommendation | No recommendation | No recommendation | On                |
| “Simulation target build mode” (Simulink)        | No impact                  | No impact         | No impact         | No impact         | Incremental build |

**Mapping Application Requirements to the Simulation Target Pane: Symbols Tab**

| Configuration Parameter     | Settings for Building Code |              |            |                   | Factory Default |
|-----------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                             | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| “Reserved names” (Simulink) | No impact                  | No impact    | No impact  | No recommendation | {}              |

**Mapping Application Requirements to the Simulation Target Pane: Custom Code Tab**

| Configuration Parameter                 | Settings for Building Code |                   |                   |                   | Factory Default |
|-----------------------------------------|----------------------------|-------------------|-------------------|-------------------|-----------------|
|                                         | Debugging                  | Traceability      | Efficiency        | Safety precaution |                 |
| <b>“Import custom code” (Simulink)</b>  | On                         | No impact         | No impact         | On                | On              |
| <b>“Source file” (Simulink)</b>         | No recommendation          | No recommendation | No recommendation | No recommendation | ''              |
| <b>“Header file” (Simulink)</b>         | No recommendation          | No recommendation | No recommendation | No recommendation | ''              |
| <b>“Initialize function” (Simulink)</b> | No recommendation          | No recommendation | No recommendation | No recommendation | ''              |
| <b>“Terminate function” (Simulink)</b>  | No recommendation          | No recommendation | No recommendation | No recommendation | ''              |
| <b>“Include directories” (Simulink)</b> | No impact                  | No impact         | No impact         | No recommendation | ''              |
| <b>“Source files” (Simulink)</b>        | No impact                  | No impact         | No impact         | No recommendation | ''              |
| <b>“Libraries” (Simulink)</b>           | No impact                  | No impact         | No impact         | No recommendation | ''              |
| <b>“Defines” (Simulink)</b>             | No impact                  | No impact         | No impact         | No recommendation | ''              |

## Mapping Application Requirements to the Code Generation Pane: General Tab

| Configuration Parameter                                     | Settings for Building Code                              |                                                         |                                                                                     |                                                         | Factory Default                         |
|-------------------------------------------------------------|---------------------------------------------------------|---------------------------------------------------------|-------------------------------------------------------------------------------------|---------------------------------------------------------|-----------------------------------------|
|                                                             | Debugging                                               | Traceability                                            | Efficiency                                                                          | Safety precaution                                       |                                         |
| System target file on page 5-6                              | No impact                                               | No impact                                               | No impact                                                                           | No impact (GRT)<br>ERT based (ERT)                      | grt.tlc                                 |
| “Language” on page 5-9                                      | No impact                                               | No impact                                               | No impact                                                                           | No impact                                               | C                                       |
| compexcep="155"<br>Compiler optimization level on page 5-17 | Optimization<br>s off<br>(faster<br>builds)             | Optimization<br>s off<br>(faster<br>builds)             | Optimization<br>s on (faster<br>runs)<br>(execution)<br><br>No impact<br>(ROM, RAM) | No impact                                               | Optimizations<br>off (faster<br>builds) |
| “Custom compiler optimization flags” on page 5-19           | Optimization<br>s off<br>(faster<br>builds)             | Optimization<br>s off<br>(faster<br>builds)             | Optimization<br>s on (faster<br>runs)                                               | No impact                                               | Optimizations<br>off (faster<br>builds) |
| “Generate makefile” on page 5-20                            | No impact                                               | No impact                                               | No impact                                                                           | No impact                                               | On                                      |
| “Make command” on page 5-22                                 | No impact                                               | No impact                                               | No impact                                                                           | No recommendation                                       | make_rtw                                |
| “Template makefile” on page 5-24                            | No impact                                               | No impact                                               | No impact                                                                           | No impact                                               | grt_default_tmf                         |
| “Select objective” on page 5-26                             | Debugging                                               | Not applicable for GRT-based targets                    | Execution efficiency                                                                | No recommendation                                       | Unspecified                             |
| “Check model before generating code” on page 5-29           | On (proceed with warnings) or<br>On (stop for warnings) | On (proceed with warnings) or<br>On (stop for warnings) | On (proceed with warnings) or<br>On (stop for warnings)                             | On (proceed with warnings) or<br>On (stop for warnings) | Off                                     |
| “Generate code only” on page 5-31                           | Off                                                     | No impact                                               | No impact                                                                           | No impact                                               | Off                                     |
| “Verbose build” on page 5-40                                | On                                                      | No impact                                               | No impact                                                                           | No recommendation                                       | On                                      |
| “Retain .rtw file” on page 5-41                             | On                                                      | No impact                                               | No impact                                                                           | No impact                                               | Off                                     |
| “Profile TLC” on page 5-42                                  | On                                                      | No impact                                               | No impact                                                                           | No impact                                               | Off                                     |
| “Start TLC debugger when generating code” on page 5-43      | On                                                      | No impact                                               | No impact                                                                           | No impact                                               | Off                                     |

| Configuration Parameter                                | Settings for Building Code |              |            |                   | Factory Default |
|--------------------------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                                        | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| “Start TLC coverage when generating code” on page 5-44 | On                         | No impact    | No impact  | No impact         | Off             |
| “Enable TLC assertion” on page 5-45                    | On                         | No impact    | No impact  | No recommendation | Off             |

**Mapping Application Requirements to the Code Generation Pane: Report Tab**

| Configuration Parameter                     | Settings for Building Code |              |            |                   | Factory Default |
|---------------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                             | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| “Create code generation report” on page 6-5 | On                         | On           | No impact  | No recommendation | Off             |
| “Open report automatically” on page 6-7     | On                         | On           | No impact  | No impact         | Off             |

**Mapping Application Requirements to the Code Generation Pane: Comments Tab**

| Configuration Parameter                                           | Settings for Building Code |              |            |                   | Factory Default |
|-------------------------------------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                                                   | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| “Include comments” on page 7-6                                    | On                         | On           | No impact  | No recommendation | On              |
| “Simulink block comments” on page 7-8                             | On                         | On           | No impact  | No recommendation | On              |
| “Stateflow object comments” on page 7-9                           | On                         | On           | No impact  | No recommendation | Off             |
| “Show eliminated blocks” on page 7-13                             | On                         | On           | No impact  | No recommendation | On              |
| “Verbose comments for 'Model default' storage class” on page 7-14 | On                         | On           | No impact  | No recommendation | On              |
| “Operator annotations” (Embedded Coder)                           | No impact                  | On           | No impact  | No recommendation | On              |

**Mapping Application Requirements to the Code Generation Pane: Identifiers Tab**

| Configuration Parameter                                               | Settings for Building Code |              |            |                   | Factory Default |
|-----------------------------------------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                                                       | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| <b>“Maximum identifier length” on page 8-5</b>                        | Valid value                | >30          | No impact  | >30               | 31              |
| <b>“Use the same reserved names as Simulation Target” on page 8-7</b> | No impact                  | No impact    | No impact  | No impact         | Off             |
| <b>“Reserved names” on page 8-8</b>                                   | No impact                  | No impact    | No impact  | No impact         | {}              |

**Mapping Application Requirements to the Code Generation Pane: Custom Code Tab**

| Configuration Parameter                                                     | Settings for Building Code |              |            |                   | Factory Default |
|-----------------------------------------------------------------------------|----------------------------|--------------|------------|-------------------|-----------------|
|                                                                             | Debugging                  | Traceability | Efficiency | Safety precaution |                 |
| <b>“Use the same custom code settings as Simulation Target” on page 9-4</b> | No impact                  | No impact    | No impact  | No impact         | Off             |
| <b>“Source file” on page 9-5</b>                                            | No impact                  | No impact    | No impact  | No impact         | ''              |
| <b>“Header file” on page 9-6</b>                                            | No impact                  | No impact    | No impact  | No impact         | ''              |
| <b>“Initialize function” on page 9-7</b>                                    | No impact                  | No impact    | No impact  | No impact         | ''              |
| <b>“Terminate function” on page 9-8</b>                                     | No impact                  | No impact    | No impact  | No impact         | ''              |
| <b>“Include directories” on page 9-9</b>                                    | No impact                  | No impact    | No impact  | No impact         | ''              |
| <b>“Source files” on page 9-11</b>                                          | No impact                  | No impact    | No impact  | No impact         | ''              |
| <b>“Libraries” on page 9-12</b>                                             | No impact                  | No impact    | No impact  | No impact         | ''              |
| <b>“Defines” on page 9-13</b>                                               | No impact                  | No impact    | No impact  | No impact         | ''              |

**Mapping Application Requirements to the Code Generation Pane: Interface Tab**

| Configuration Parameter                              | Settings for Building Code |                       |                                             |                   | Factory Default                                                                                 |
|------------------------------------------------------|----------------------------|-----------------------|---------------------------------------------|-------------------|-------------------------------------------------------------------------------------------------|
|                                                      | Debugging                  | Traceability          | Efficiency                                  | Safety precaution |                                                                                                 |
| “Standard math library” on page 10-41                | No impact                  | No impact             | Valid library                               | No impact         | C99 (ISO)                                                                                       |
| “Code replacement library” on page 10-9              | No impact                  | No impact             | Valid library                               | No impact         | None                                                                                            |
| “Shared code placement” on page 10-11                | Shared location (GRT)      | Shared location (GRT) | No impact (execution, RAM)                  | No impact         | Auto                                                                                            |
|                                                      | No impact (ERT)            | No impact (ERT)       | Shared location (ROM)                       |                   |                                                                                                 |
| “Support: non-finite numbers” on page 10-13          | No impact                  | No impact             | Off (Execution, ROM)<br><br>No impact (RAM) | Norecommendation  | On                                                                                              |
| “Code interface packaging” on page 10-15             | No impact                  | No impact             | Reusable function or C++ class              | No impact         | Nonreusable function if <b>Language</b> is set to C; C++ class if <b>Language</b> is set to C++ |
| “Multi-instance code error diagnostic” on page 10-18 | Warning or Error           | No impact             | None                                        | No impact         | Error                                                                                           |
| “Classic call interface” on page 10-45               | No impact                  | Off                   | Off (execution, ROM), No impact (RAM)       | No recommendation | Off (except On for GRT models created before R2012a)                                            |
| “Single output/update function” on page 10-47        | On                         | On                    | On                                          | No recommendation | On                                                                                              |
| “MAT-file logging” on page 10-49                     | On                         | No impact             | Off                                         | Off               | On (GRT)<br>Off (ERT)                                                                           |
| “MAT-file variable name modifier” (Embedded Coder)   | No impact                  | No impact             | No impact                                   | No impact         | rt_                                                                                             |

| Configuration Parameter                                   | Settings for Building Code |              |            |                                             | Factory Default |
|-----------------------------------------------------------|----------------------------|--------------|------------|---------------------------------------------|-----------------|
|                                                           | Debugging                  | Traceability | Efficiency | Safety precaution                           |                 |
| <b>“Generate C API for: signals” on page 10-20</b>        | No impact                  | No impact    | No impact  | No impact (development)<br>Off (production) | Off             |
| <b>“Generate C API for: parameters” on page 10-21</b>     | No impact                  | No impact    | No impact  | No impact (development)<br>Off (production) | Off             |
| <b>“Generate C API for: states” on page 10-22</b>         | No impact                  | No impact    | No impact  | No impact (development)<br>Off (production) | Off             |
| <b>“Generate C API for: root-level I/O” on page 10-23</b> | No impact                  | No impact    | No impact  | No impact (development)<br>Off (production) | Off             |
| <b>“ASAP2 interface” on page 10-24</b>                    | No impact                  | No impact    | No impact  | No impact (development)<br>Off (production) | Off             |
| <b>“External mode” on page 10-25</b>                      | No impact                  | No impact    | No impact  | No impact (development)<br>Off (production) | Off             |
| <b>“Transport layer” on page 10-26</b>                    | No impact                  | No impact    | No impact  | No impact                                   | tcpip           |
| <b>“MEX-file arguments” on page 10-28</b>                 | No impact                  | No impact    | No impact  | No impact                                   | ' '             |
| <b>“Static memory allocation” on page 10-30</b>           | No impact                  | No impact    | No impact  | No impact                                   | Off             |
| <b>“Static memory buffer size” on page 12-20</b>          | No impact                  | No impact    | No impact  | No impact                                   | 1000000         |



# Model Advisor Checks

---

- “Simulink Coder Checks” on page 13-2
- “Code Generation Advisor Checks” on page 13-20

## Simulink Coder Checks

### In this section...

“Simulink Coder Checks Overview” on page 13-2  
 “Identify blocks using one-based indexing” on page 13-2  
 “Check solver for code generation” on page 13-3  
 “Check for blocks not supported by code generation” on page 13-4  
 “Check and update model to use toolchain approach to build generated code” on page 13-4  
 “Check and update embedded target model to use ert.tlc system target file” on page 13-6  
 “Check and update models that are using targets that have changed significantly across different releases of MATLAB” on page 13-7  
 “Check for blocks that have constraints on tunable parameters” on page 13-8  
 “Check for model reference configuration mismatch” on page 13-9  
 “Check sample times and tasking mode” on page 13-10  
 “Check for code generation identifier formats used for model reference” on page 13-11  
 “Available Checks for Code Generation Objectives” on page 13-11  
 “Identify questionable blocks within the specified system” on page 13-18  
 “Check model configuration settings against code generation objectives” on page 13-19

### Simulink Coder Checks Overview

Use Simulink Coder Model Advisor checks to configure your model for code generation.

#### See Also

- “Run Model Advisor Checks” (Simulink)
- “Simulink Checks” (Simulink)
- “Embedded Coder Checks” (Embedded Coder)

### Identify blocks using one-based indexing

**Check ID:** `mathworks.codegen.cgs1_0101`

Identify blocks using one-based indexing.

#### Description

Zero-based indexing is more efficient in the generated code than one-based indexing.

Using zero-based indexing increases execution efficiency of the generated code.

Available with Simulink Coder.

## Results and Recommended Actions

| Condition                                                                 | Recommended Action                                                          |
|---------------------------------------------------------------------------|-----------------------------------------------------------------------------|
| The model or subsystem contains blocks configured for one-based indexing. | Configure the blocks for zero-based indexing. Update the supporting blocks. |

## Capabilities and Limitations

You can:

- Run this check on your library models.
- Exclude blocks and charts from this check if you have a Simulink Check™ license.

## See Also

- “cgsl\_0101: Zero-based indexing” (Simulink).
- “Model Advisor Exclusion Overview” (Simulink Check)

## Check solver for code generation

**Check ID:** mathworks.codegen.SolverCodeGen

Check model solver and sample time configuration settings.

## Description

Incorrect configuration settings can stop the code generator from producing code. Underspecifying sample times can lead to undesired results. Avoid generating code that might corrupt data or produce unpredictable behavior.

Available with Simulink Coder.

## Results and Recommended Actions

| Condition                                                           | Recommended Action                                                                                                                                                                                                                                                                                                                                                                        |
|---------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| The solver type is set incorrectly for model level code generation. | In the Configuration Parameters dialog box, on the <b>Solver</b> pane, set <b>Type</b> (Simulink) to <b>Fixed-step</b> .                                                                                                                                                                                                                                                                  |
| Multitasking diagnostic options are not set to error.               | In the Configuration Parameters dialog box, on the <b>Diagnostics</b> pane, set <ul style="list-style-type: none"> <li>• <b>Sample Time &gt; Multitask conditionally executed subsystem</b> (Simulink) to error</li> <li>• <b>Sample Time &gt; Multitask rate transition</b> (Simulink) to error</li> <li>• <b>Data Validity &gt; Multitask data store</b> (Simulink) to error</li> </ul> |

## Tips

You do not have to modify the solver settings to generate code from a subsystem. The build process automatically changes **Solver type** to **fixed-step** when you right-click on the subsystem and select

**C/C++ Code > Build This Subsystem** or **C/C++ Code > Generate S-Function** from the subsystem context menu.

#### See Also

- “Configure Time-Based Scheduling”
- “Execute Multitasking Models”

## Check for blocks not supported by code generation

**Check ID:** `mathworks.codegen.codeGenSupport`

Identify blocks not supported by code generation.

#### Description

This check partially identifies model constructs that are not suited for code generation as identified in the Simulink Block Support tables for Simulink Coder and Embedded Coder. If you are using blocks with support notes for code generation, review the information and follow the given advice.

Available with Simulink Coder.

#### Results and Recommended Actions

| Condition                                                                           | Recommended Action                                                                                                             |
|-------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------|
| The model or subsystem contains blocks that should not be used for code generation. | Consider replacing the blocks listed in the results. Click an element from the list of questionable items to locate condition. |

#### Capabilities and Limitations

You can:

- Run this check on your library models.
- Analyzes content of library linked blocks.
- Analyzes content in masked subsystems.
- Exclude blocks and charts from this check if you have a Simulink Check license.

#### See Also

- “Blocks and Products Supported for Code Generation”
- “Model Advisor Exclusion Overview” (Simulink Check)

## Check and update model to use toolchain approach to build generated code

**Check ID:** `mathworks.codegen.toolchainInfoUpgradeAdvisor.check`

Check if model uses Toolchain settings to build generated code.

## Description

Checks whether the model uses the template makefile approach or the toolchain approach to build the generated code.

Available with Simulink Coder.

When you open a model created before R2013b that has **System target file** set to `ert.tlc`, `ert_shrllib.tlc`, or `grt.tlc` the software automatically tries to upgrade the model from using the template makefile approach to using the toolchain approach.

If the software did not upgrade the model, this check determines the cause, and if available, recommends actions you can perform to upgrade the model.

To determine which approach your model is using, you can also look at the Code Generation pane in the Configuration Parameters dialog box. The toolchain approach uses the following parameters to build generated code:

- “Toolchain” on page 5-12
- “Build configuration” on page 5-14

The template makefile approach uses the following settings to build generated code:

- **Compiler optimization level**
- **Custom compiler optimization flags**
- **Generate makefile**
- **Template makefile**

## Results and Recommended Actions

| Condition                                                                                             | Recommended Action                                                                             | Comment                                                                                                                                                                                                                                                                                                                                                                                                                     |
|-------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Model is configured to use the toolchain approach.                                                    | No action.                                                                                     | The model was automatically upgraded.                                                                                                                                                                                                                                                                                                                                                                                       |
| Model is not configured to use the toolchain approach.                                                | Model cannot be automatically upgraded to use the toolchain approach.                          | The system target file is not toolchain-compliant. Set <b>System target file</b> to a toolchain-compliant target, such as <code>ert.tlc</code> , <code>ert_shrllib.tlc</code> , or <code>grt.tlc</code> .                                                                                                                                                                                                                   |
| Model is not configured to use the toolchain approach. (Parameter values are not the default values.) | Model can be automatically upgraded to use the toolchain approach. Click <b>Update Model</b> . | The parameters are set to their default values, except <b>Compiler Optimization Level</b> , which is set Optimizations on (faster runs). Clicking <b>Update Model</b> sets <b>Compiler Optimization Level</b> to its default value, Optimizations off (faster builds), and then upgrades the model. The upgraded model has <b>Build Configuration</b> set to Faster Builds. Saving the model makes these changes permanent. |

| Condition                                                                                             | Recommended Action                                                    | Comment                                                                                                                                                                                                                                                                                                                                                                                                                                                                         |
|-------------------------------------------------------------------------------------------------------|-----------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Model is not configured to use the toolchain approach. (Parameter values are not the default values.) | Model cannot be automatically upgraded to use the toolchain approach. | <p>One or more of the following parameters is not set to its default value:</p> <ul style="list-style-type: none"> <li>• <b>Generate makefile</b> (default: Enabled)</li> <li>• <b>Template makefile</b> (default: Target-specific default TMF)</li> <li>• <b>Compiler optimization level</b> (default: Optimizations off (faster builds))</li> <li>• <b>Make command</b> (default: make_rtw without arguments)</li> </ul> <p>See “Upgrade Model to Use Toolchain Approach”</p> |

**Action Results**

Clicking **Update model** upgrades the model to use the toolchain approach to build generated code.

**See Also**

- “Upgrade Model to Use Toolchain Approach”

**Check and update embedded target model to use ert.tlc system target file**

**Check ID:** mathworks.codegen.codertarget.check

Check and update the embedded target model to use ert.tlc system target file.

**Description**

Check and update models whose **System target file** is set to a file other than ert.tlc and whose target hardware is one of the supported Texas Instruments C2000™ processors to use ert.tlc and similar settings.

Available with Simulink Coder.

**Results and Recommended Actions**

| Condition                                                     | Recommended Action |
|---------------------------------------------------------------|--------------------|
| <b>System target file</b> is set to ert.tlc - Embedded Coder. | No action          |

| Condition                                                                                                                                                                                                                                   | Recommended Action                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                   |
|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <p><b>System target file</b> is set to a file other than <code>ert.tlc</code> and <b>Hardware board</b> parameter is set to a processor that is supported by the Embedded Coder Support Package for Texas Instruments C2000 Processors.</p> | <p>Run the corresponding check in Upgrade Advisor:</p> <ol style="list-style-type: none"> <li><b>1</b> In the <b>Modeling</b> tab of Simulink Editor, click <b>Model Advisor</b>.</li> <li><b>2</b> Open the <b>Upgrade Advisor</b> pane and select check <b>Check and update embedded target model to use ert.tlc system target file</b>.</li> <li><b>3</b> Right-click on the check and select <b>Run This Check</b>.</li> <li><b>4</b> After the check passes, open the Configuration Parameters dialog box, go to <b>Hardware Implementation</b> pane and confirm that the correct <b>Hardware board</b> is selected.</li> </ol> |

### Action Results

Clicking **Run This Check** automatically sets the following parameters on the **Code Generation** pane in the model Configuration Parameters dialog box:

- **System target file** parameter to `ert.tlc`.
- **Toolchain** parameter to match the previous toolchain.
- **Build configuration** parameter to match the build configuration.

### Capabilities and Limitations

The new workflow uses the toolchain approach, which relies on enhanced makefiles to build generated code. It does not provide an equivalent to setting the **Build format** parameter to Project in the previous configuration. Therefore, the new workflow cannot automatically generate IDE projects within the CCS 3.3 IDE.

### See Also

“Toolchain Configuration”

## Check and update models that are using targets that have changed significantly across different releases of MATLAB

**Check ID:** `mathworks.codegen.realtime2CoderTargetInfoUpgradeAdvisor.check`

Check and update models with Simulink targets that have changed significantly across different releases of MATLAB.

### Description

Save a model that you have updated to work with the current installation of MATLAB.

Available with Simulink Coder.

### Results and Recommended Actions

| Condition                                                                                                        | Recommended Action                                                                                                                                               |
|------------------------------------------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Model uses a target that has changed significantly since the release of MATLAB in which it was originally saved. | Save model                                                                                                                                                       |
| Model does not use a Simulink target or is using the latest version of the target.                               | No action                                                                                                                                                        |
| Model is automatically updated.                                                                                  | Save model                                                                                                                                                       |
| Invalid external mode configuration.                                                                             | In the <b>Configuration Parameters &gt; Interface</b> pane, update the external mode parameter settings to match characteristics of your host-target connection. |
| Model is corrupted.                                                                                              | Close and reopen the model. If the issue persists, reset <b>Configuration Parameters &gt; Hardware Implementation &gt; Hardware board</b> .                      |

### Action Results

Clicking **Save model** updates the model to work with the current installation of MATLAB and saves the model.

### See Also

“Configure Production and Test Hardware”

## Check for blocks that have constraints on tunable parameters

**Check ID:** `mathworks.codegen.ConstraintsTunableParam`

Identify blocks with constraints on tunable parameters.

### Description

Lookup Table blocks have strict constraints when they are tunable. If you violate lookup table block restrictions, the generated code produces incorrect answers.

Available with Simulink Coder.

## Results and Recommended Actions

| Condition                                          | Recommended Action                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                                              |
|----------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Lookup Table blocks have tunable parameters.       | <p>When tuning parameters during simulation or when running the generated code, you must:</p> <ul style="list-style-type: none"> <li>• Preserve monotonicity of the setting for the <b>Vector of input values</b> parameter.</li> <li>• Preserve the number and location of zero values that you specify for <b>Vector of input values</b> and <b>Vector of output values</b> parameters if you specify multiple zero values for the <b>Vector of input values</b> parameter.</li> </ul>                                                                                                                        |
| Lookup Table (2-D) blocks have tunable parameters. | <p>When tuning parameters during simulation or when running the generated code, you must:</p> <ul style="list-style-type: none"> <li>• Preserve monotonicity of the setting for the <b>Row index input values</b> and <b>Column index of input values</b> parameters.</li> <li>• Preserve the number and location of zero values that you specify for <b>Row index input values</b>, <b>Column index of input values</b>, and <b>Vector of output values</b> parameters if you specify multiple zero values for the <b>Row index input values</b> or <b>Column index of input values</b> parameters.</li> </ul> |
| Lookup Table (n-D) blocks have tunable parameters. | <p>When tuning parameters during simulation or when running the generated code, you must preserve the increasing monotonicity of the breakpoint values for each table dimension <b>Breakpoints n</b>.</p>                                                                                                                                                                                                                                                                                                                                                                                                       |

## Capabilities and Limitations

If you have a Simulink Check license, you can exclude blocks and charts from this check.

### See Also

- 1-D Lookup Table
- 2-D Lookup Table
- “Model Advisor Exclusion Overview” (Simulink Check)

## Check for model reference configuration mismatch

**Check ID:** `mathworks.codegen.MdlrefConfigMismatch`

Identify referenced model configuration parameter settings that do not match the top model configuration parameter settings.

**Description**

The code generator cannot create code for top models that contain referenced models with different, incompatible configuration parameter settings.

Available with Simulink Coder.

**Results and Recommended Actions**

| Condition                                                                                        | Recommended Action                                 |
|--------------------------------------------------------------------------------------------------|----------------------------------------------------|
| The top model and the referenced model have inconsistent model configuration parameter settings. | Modify the specified model configuration settings. |

**See Also**

- “Model Reference Basics” (Simulink)
- “Set Configuration Parameters for Model Hierarchies” (Simulink)

**Check sample times and tasking mode**

**Check ID:** `mathworks.codegen.SampleTimesTaskingMode`

Set up the sample time and tasking mode for your system.

**Description**

Incorrect tasking mode can result in inefficient code execution or incorrect generated code.

Available with Simulink Coder.

**Results and Recommended Actions**

| Condition                                                                                                                                                                                                                                                                                                                  | Recommended Action                                                                                                                                                                                                                                                                                                             |
|----------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| The model represents a multirate system but is not configured for multitasking.                                                                                                                                                                                                                                            | Select model configuration parameter <b>“Treat each discrete rate as a separate task” (Simulink)</b> . When you select the parameter, multitasking execution is applied for a multirate model. For more information, see “Time-Based Scheduling and Code Generation”.                                                          |
| The model is configured for multitasking, but multitasking is not desirable on the target hardware. For example, the operating system does not support multiprocessing or the target hardware is bare metal (is not running an operating system) and the application does not provide for a multitasking execution scheme. | Clear model configuration parameter <b>“Treat each discrete rate as a separate task” (Simulink)</b> . When you clear the parameter, single-tasking execution is applied. Alternatively, change the settings on the <b>Hardware Implementation</b> pane. For more information, see “Time-Based Scheduling and Code Generation”. |

**See Also**

“Time-Based Scheduling and Code Generation”

## Check for code generation identifier formats used for model reference

**Check ID:** mathworks.codegen.ModelRefRTWConfigCompliance

Checks for referenced models in a model referencing hierarchy for which code generation changes configuration parameter settings that involve identifier formats.

### Description

In referenced models, if the following **Configuration Parameters > Code Generation > Identifiers** parameters have settings that do not contain a \$R token (which represents the name of the reference model), code generation prepends the \$R token to the identifier format.

- **Global variables**
- **Global types**
- **Subsystem methods**
- **Constant macros**

Available with Simulink Coder.

### Results and Recommended Actions

| Condition                                                                               | Recommended Action                                                                  |
|-----------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|
| A script that operates on generated code uses model names that code generation changes. | Update the script to use the generated name (which includes an appended \$R token). |

## Available Checks for Code Generation Objectives

Code generation objectives checks facilitate designing and troubleshooting Simulink models and subsystems that you want to use to generate code.

The Code Generation Advisor includes the following checks from Simulink, Simulink Coder, and Embedded Coder for each of the code generation objectives. Two checks unique to the Code Generation Advisor are included below the list.

| Check                                                                                 | Execution efficiency (all targets)                                                  | ROM efficiency (ERT-based targets)                                                  | RAM efficiency (ERT-based targets) | Safety precaution (ERT-based targets) | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|---------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------|------------------------------------|---------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Check model configuration settings against code generation objectives” on page 13-19 | Included                                                                            | Included                                                                            | Included                           | Included                              | Included                         | Included                | Included (see <b>Note</b> below)            | Included                      |
| “Check for optimal bus virtuality” (Simulink)                                         | Included                                                                            | Included                                                                            | Included                           | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify questionable blocks within the specified system” on page 13-18              | Included                                                                            | Included                                                                            | Included                           | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check the hardware implementation” (Embedded Coder)                                  | Included if Embedded Coder is available                                             | Included if Embedded Coder is available                                             | N/A                                | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify questionable software environment specifications” (Embedded Coder)          | Included when Traceability is not a higher priority and Embedded Coder is available | Included when Traceability is not a higher priority and Embedded Coder is available | N/A                                | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |

| Check                                                                    | Execution efficiency (all targets)                                                                | ROM efficiency (ERT-based targets)                                                                | RAM efficiency (ERT-based targets)                                                                | Safety precaution (ERT-based targets) | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|--------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------|---------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Identify questionable code instrumentation (data I/O)” (Embedded Coder) | Included when Traceability or Debugging are not higher priorities and Embedded Coder is available | Included when Traceability or Debugging are not higher priorities and Embedded Coder is available | Included when Traceability or Debugging are not higher priorities and Embedded Coder is available | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify questionable subsystem settings” (Embedded Coder)              | N/A                                                                                               | Included if Embedded Coder is available                                                           | Included if Embedded Coder is available                                                           | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify blocks that generate expensive rounding code” (Embedded Coder) | Included if Embedded Coder is available                                                           | Included if Embedded Coder is available                                                           | N/A                                                                                               | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify questionable fixed-point operations” (Embedded Coder)          | Included if Embedded Coder or Fixed-Point Designer™ is available                                  | Included if Embedded Coder or Fixed-Point Designer is available                                   | N/A                                                                                               | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify blocks using one-based indexing” on page 13-2                  | Included                                                                                          | Included                                                                                          | N/A                                                                                               | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |

| Check                                                                                              | Execution efficiency (all targets)      | ROM efficiency (ERT-based targets)      | RAM efficiency (ERT-based targets) | Safety precaution (ERT-based targets) | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|----------------------------------------------------------------------------------------------------|-----------------------------------------|-----------------------------------------|------------------------------------|---------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Identify lookup table blocks that generate expensive out-of-range checking code” (Embedded Coder) | Included if Embedded Coder is available | Included if Embedded Coder is available | N/A                                | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check output types of logic blocks” (Embedded Coder)                                              | Included if Embedded Coder is available | N/A                                     | N/A                                | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify unconnected lines, input ports, and output ports” (Simulink)                             | N/A                                     | N/A                                     | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check Data Store Memory blocks for multitasking, strong typing, and shadowing issues” (Simulink)  | N/A                                     | N/A                                     | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |

| Check                                                                                                   | Execution efficiency (all targets) | ROM efficiency (ERT-based targets) | RAM efficiency (ERT-based targets) | Safety precaution (ERT-based targets) | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|---------------------------------------------------------------------------------------------------------|------------------------------------|------------------------------------|------------------------------------|---------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Identify block output signals with continuous sample time and non-floating point data type” (Simulink) | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check for blocks that have constraints on tunable parameters” on page 13-8                             | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check if read/write diagnostics are enabled for data store blocks” (Simulink)                          | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check structure parameter usage with bus signals” (Simulink)                                           | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check data store block sample times for modeling errors” (Simulink)                                    | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |

| Check                                                                                    | Execution efficiency (all targets) | ROM efficiency (ERT-based targets) | RAM efficiency (ERT-based targets) | Safety precaution (ERT-based targets) | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|------------------------------------------------------------------------------------------|------------------------------------|------------------------------------|------------------------------------|---------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Check for potential ordering issues involving data store access” (Simulink)             | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check for blocks not recommended for C/C++ production code deployment” (Embedded Coder) | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check for blocks not recommended for MISRA C:2012” (Embedded Coder)                     | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check for unsupported block names” (Embedded Coder)                                     | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check usage of Assignment blocks” (Embedded Coder)                                      | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |

| Check                                                                                           | Execution efficiency (all targets)      | ROM efficiency (ERT-based targets)      | RAM efficiency (ERT-based targets) | Safety precaution (ERT-based targets)   | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|-------------------------------------------------------------------------------------------------|-----------------------------------------|-----------------------------------------|------------------------------------|-----------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Check for bitwise operations on signed integers” (Embedded Coder)                              | N/A                                     | N/A                                     | N/A                                | N/A                                     | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check for recursive function calls” (Embedded Coder)                                           | N/A                                     | N/A                                     | N/A                                | N/A                                     | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check for equality and inequality operations on floating-point values” (Embedded Coder)        | N/A                                     | N/A                                     | N/A                                | N/A                                     | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check for switch case expressions without a default case” (Embedded Coder)                     | N/A                                     | N/A                                     | N/A                                | N/A                                     | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check configuration parameters for generation of inefficient saturation code” (Embedded Coder) | Included if Embedded Coder is available | Included if Embedded Coder is available | N/A                                | Included if Embedded Coder is available | N/A                              | N/A                     | N/A                                         | N/A                           |

---

**Note** When the Code Generation Advisor checks your model against the MISRA C:2012 guidelines objective, the tool does not consider all of the configuration parameter settings that are checked by the MISRA C:2012 guidelines checks in the Model Advisor. For a complete check of configuration parameter settings:

- 1 Open the Model Advisor.
- 2 Navigate to **By Task > Modeling Guidelines for MISRA C:2012**.
- 3 Run the checks in the folder.

For more information on using the Model Advisor, see “Check Your Model Using the Model Advisor” (Simulink).

---

### See Also

- “Application Objectives Using Code Generation Advisor”
- “Configure Model for Code Generation Objectives by Using Code Generation Advisor” (Embedded Coder)
- “Run Model Advisor Checks” (Simulink)
- “Simulink Checks” (Simulink)
- “Simulink Coder Checks” on page 13-2
- “Simulink Check Checks” (Simulink Check)

## Identify questionable blocks within the specified system

Identify blocks not supported by code generation or not recommended for deployment.

### Description

The code generator creates code only for the blocks that it supports. Some blocks are not recommended for production code deployment.

### Results and Recommended Actions

| Condition                                                  | Recommended Action                                                                         |
|------------------------------------------------------------|--------------------------------------------------------------------------------------------|
| A block is not supported by the code generator.            | Remove the specified block from the model or replace the block with the recommended block. |
| A block is not recommended for production code deployment. | Remove the specified block from the model or replace the block with the recommended block. |
| Check for Gain blocks whose value equals 1.                | Replace Gain blocks with Signal Conversion blocks.                                         |

### Capabilities and Limitations

You can:

- Run this check on your library models.
- Exclude blocks and charts from this check if you have a Simulink Check license.

**See Also**

“Blocks and Products Supported for Code Generation”

“Model Advisor Exclusion Overview” (Simulink Check)

## Check model configuration settings against code generation objectives

Check the configuration parameter settings for the model against the code generation objectives.

**Description**

Each parameter in the Configuration Parameters dialog box might have different recommended settings for code generation based on your objectives. This check helps you identify the recommended setting for each parameter so that you can achieve optimized code based on your objective.

**Results and Recommended Actions**

| Condition                                                                                   | Recommended Action                                                                                                                                                              |
|---------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| Parameters are set to values other than the value recommended for the specified objectives. | Set the parameters to the recommended values.<br><br><b>Note</b> A change to one parameter value can impact other parameters. Passing the check might take multiple iterations. |

**Action Results**

Clicking **Modify Parameters** changes the parameter values to the recommended values.

**See Also**

- “Recommended Settings Summary for Model Configuration Parameters” (Embedded Coder)
- “Application Objectives Using Code Generation Advisor”
- “Configure Model for Code Generation Objectives by Using Code Generation Advisor” (Embedded Coder)

## Code Generation Advisor Checks

| In this section...                                                                    |
|---------------------------------------------------------------------------------------|
| “Available Checks for Code Generation Objectives” on page 13-20                       |
| “Identify questionable blocks within the specified system” on page 13-26              |
| “Check model configuration settings against code generation objectives” on page 13-27 |

### Available Checks for Code Generation Objectives

Code generation objectives checks facilitate designing and troubleshooting Simulink models and subsystems that you want to use to generate code.

The Code Generation Advisor includes the following checks from Simulink, Simulink Coder, and Embedded Coder for each of the code generation objectives. Two checks unique to the Code Generation Advisor are included below the list.

| Check                                                                                 | Execution efficiency (all targets) | ROM efficiency (ERT-based targets) | RAM efficiency (ERT-based targets) | Safety precaution (ERT-based targets) | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|---------------------------------------------------------------------------------------|------------------------------------|------------------------------------|------------------------------------|---------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Check model configuration settings against code generation objectives” on page 13-27 | Included                           | Included                           | Included                           | Included                              | Included                         | Included                | Included (see <b>Note</b> below)            | Included                      |
| “Check for optimal bus virtuality” (Simulink)                                         | Included                           | Included                           | Included                           | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify questionable blocks within the specified system” on page 13-26              | Included                           | Included                           | Included                           | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |

| Check                                                                        | Execution efficiency (all targets)                                                                | ROM efficiency (ERT-based targets)                                                                | RAM efficiency (ERT-based targets)                                                                | Safety precaution (ERT-based targets) | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------|---------------------------------------------------------------------------------------------------|---------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Check the hardware implementation” (Embedded Coder)                         | Included if Embedded Coder is available                                                           | Included if Embedded Coder is available                                                           | N/A                                                                                               | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify questionable software environment specifications” (Embedded Coder) | Included when Traceability is not a higher priority and Embedded Coder is available               | Included when Traceability is not a higher priority and Embedded Coder is available               | N/A                                                                                               | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify questionable code instrumentation (data I/O)” (Embedded Coder)     | Included when Traceability or Debugging are not higher priorities and Embedded Coder is available | Included when Traceability or Debugging are not higher priorities and Embedded Coder is available | Included when Traceability or Debugging are not higher priorities and Embedded Coder is available | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify questionable subsystem settings” (Embedded Coder)                  | N/A                                                                                               | Included if Embedded Coder is available                                                           | Included if Embedded Coder is available                                                           | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify blocks that generate expensive rounding code” (Embedded Coder)     | Included if Embedded Coder is available                                                           | Included if Embedded Coder is available                                                           | N/A                                                                                               | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |

| Check                                                                                              | Execution efficiency (all targets)                              | ROM efficiency (ERT-based targets)                              | RAM efficiency (ERT-based targets) | Safety precaution (ERT-based targets) | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|----------------------------------------------------------------------------------------------------|-----------------------------------------------------------------|-----------------------------------------------------------------|------------------------------------|---------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Identify questionable fixed-point operations” (Embedded Coder)                                    | Included if Embedded Coder or Fixed-Point Designer is available | Included if Embedded Coder or Fixed-Point Designer is available | N/A                                | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify blocks using one-based indexing” on page 13-2                                            | Included                                                        | Included                                                        | N/A                                | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify lookup table blocks that generate expensive out-of-range checking code” (Embedded Coder) | Included if Embedded Coder is available                         | Included if Embedded Coder is available                         | N/A                                | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check output types of logic blocks” (Embedded Coder)                                              | Included if Embedded Coder is available                         | N/A                                                             | N/A                                | N/A                                   | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify unconnected lines, input ports, and output ports” (Simulink)                             | N/A                                                             | N/A                                                             | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |

| Check                                                                                                   | Execution efficiency (all targets) | ROM efficiency (ERT-based targets) | RAM efficiency (ERT-based targets) | Safety precaution (ERT-based targets) | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|---------------------------------------------------------------------------------------------------------|------------------------------------|------------------------------------|------------------------------------|---------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Check Data Store Memory blocks for multitasking, strong typing, and shadowing issues” (Simulink)       | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Identify block output signals with continuous sample time and non-floating point data type” (Simulink) | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check for blocks that have constraints on tunable parameters” on page 13-8                             | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check if read/write diagnostics are enabled for data store blocks” (Simulink)                          | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check structure parameter usage with bus signals” (Simulink)                                           | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |

| Check                                                                                    | Execution efficiency (all targets) | ROM efficiency (ERT-based targets) | RAM efficiency (ERT-based targets) | Safety precaution (ERT-based targets) | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|------------------------------------------------------------------------------------------|------------------------------------|------------------------------------|------------------------------------|---------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Check data store block sample times for modeling errors” (Simulink)                     | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check for potential ordering issues involving data store access” (Simulink)             | N/A                                | N/A                                | N/A                                | Included                              | N/A                              | N/A                     | N/A                                         | N/A                           |
| “Check for blocks not recommended for C/C++ production code deployment” (Embedded Coder) | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check for blocks not recommended for MISRA C:2012” (Embedded Coder)                     | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check for unsupported block names” (Embedded Coder)                                     | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |

| Check                                                                                    | Execution efficiency (all targets) | ROM efficiency (ERT-based targets) | RAM efficiency (ERT-based targets) | Safety precaution (ERT-based targets) | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|------------------------------------------------------------------------------------------|------------------------------------|------------------------------------|------------------------------------|---------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Check usage of Assignment blocks” (Embedded Coder)                                      | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check for bitwise operations on signed integers” (Embedded Coder)                       | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check for recursive function calls” (Embedded Coder)                                    | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check for equality and inequality operations on floating-point values” (Embedded Coder) | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |
| “Check for switch case expressions without a default case” (Embedded Coder)              | N/A                                | N/A                                | N/A                                | N/A                                   | N/A                              | N/A                     | Included if Embedded Coder is available     | N/A                           |

| Check                                                                                           | Execution efficiency (all targets)      | ROM efficiency (ERT-based targets)      | RAM efficiency (ERT-based targets) | Safety precaution (ERT-based targets)   | Traceability (ERT-based targets) | Debugging (all targets) | MISRA C:2012 guidelines (ERT-based targets) | Polyspace (ERT-based targets) |
|-------------------------------------------------------------------------------------------------|-----------------------------------------|-----------------------------------------|------------------------------------|-----------------------------------------|----------------------------------|-------------------------|---------------------------------------------|-------------------------------|
| “Check configuration parameters for generation of inefficient saturation code” (Embedded Coder) | Included if Embedded Coder is available | Included if Embedded Coder is available | N/A                                | Included if Embedded Coder is available | N/A                              | N/A                     | N/A                                         | N/A                           |

**Note** When the Code Generation Advisor checks your model against the MISRA C:2012 guidelines objective, the tool does not consider all of the configuration parameter settings that are checked by the MISRA C:2012 guidelines checks in the Model Advisor. For a complete check of configuration parameter settings:

- 1 Open the Model Advisor.
- 2 Navigate to **By Task > Modeling Guidelines for MISRA C:2012**.
- 3 Run the checks in the folder.

For more information on using the Model Advisor, see “Check Your Model Using the Model Advisor” (Simulink).

### See Also

- “Application Objectives Using Code Generation Advisor”
- “Configure Model for Code Generation Objectives by Using Code Generation Advisor” (Embedded Coder)
- “Run Model Advisor Checks” (Simulink)
- “Simulink Checks” (Simulink)
- “Simulink Coder Checks” on page 13-2
- “Simulink Check Checks” (Simulink Check)

## Identify questionable blocks within the specified system

Identify blocks not supported by code generation or not recommended for deployment.

### Description

The code generator creates code only for the blocks that it supports. Some blocks are not recommended for production code deployment.

## Results and Recommended Actions

| Condition                                                  | Recommended Action                                                                         |
|------------------------------------------------------------|--------------------------------------------------------------------------------------------|
| A block is not supported by the code generator.            | Remove the specified block from the model or replace the block with the recommended block. |
| A block is not recommended for production code deployment. | Remove the specified block from the model or replace the block with the recommended block. |
| Check for Gain blocks whose value equals 1.                | Replace Gain blocks with Signal Conversion blocks.                                         |

## Capabilities and Limitations

You can:

- Run this check on your library models.
- Exclude blocks and charts from this check if you have a Simulink Check license.

## See Also

“Blocks and Products Supported for Code Generation”

“Model Advisor Exclusion Overview” (Simulink Check)

## Check model configuration settings against code generation objectives

Check the configuration parameter settings for the model against the code generation objectives.

### Description

Each parameter in the Configuration Parameters dialog box might have different recommended settings for code generation based on your objectives. This check helps you identify the recommended setting for each parameter so that you can achieve optimized code based on your objective.

## Results and Recommended Actions

| Condition                                                                                   | Recommended Action                                                                                                         |
|---------------------------------------------------------------------------------------------|----------------------------------------------------------------------------------------------------------------------------|
| Parameters are set to values other than the value recommended for the specified objectives. | Set the parameters to the recommended values.                                                                              |
|                                                                                             | <b>Note</b> A change to one parameter value can impact other parameters. Passing the check might take multiple iterations. |

## Action Results

Clicking **Modify Parameters** changes the parameter values to the recommended values.

### See Also


- “Recommended Settings Summary for Model Configuration Parameters” (Embedded Coder)
- “Application Objectives Using Code Generation Advisor”
- “Configure Model for Code Generation Objectives by Using Code Generation Advisor” (Embedded Coder)

# Parameters for Creating Protected Models

---

## Create Protected Model

This figure illustrates the various options in the Create Protected Model dialog box.



### Create Protected Model: Overview

Create a protected model (.slxp) that allows read-only view, simulation, and code generation of the model with optional password protection.

To open the Create Protected Model dialog box, right-click the model block that references the model for which you want to generate protected model code. From the context menu, select **Subsystem & Model Reference > Create Protected Model for Selected Model Block**.

#### See Also

- “Reference Protected Models from Third Parties” (Simulink)
- “Protect Models to Conceal Contents”

### Open read-only view of model

Share a view-only version of your protected model with optional password protection. View-only version includes the contents and block parameters of the model.

## Settings

**Default:** Off

On

Share a Web view of the protected model. For password protection, create and verify a password with a minimum of four characters.

Off

Do not share a Web view of the protected model.

## Alternatives

`Simulink.ModelReference.protect`

## See Also

- “Protect Models to Conceal Contents” (Embedded Coder)

## Simulate

Enable user to simulate a protected model with optional password-protection. Selecting **Simulate:**

- Enables protected model Simulation Report.
- Sets Mode to Accelerator. You can run normal, accelerator, and rapid accelerator mode simulations.
- Displays only binaries and headers.
- Enables code obfuscation.

## Settings

**Default:** On

On

User can simulate the protected model. For password protection, create and verify a password with a minimum of four characters.

Off

User cannot simulate the protected model.

## Alternatives

`Simulink.ModelReference.protect`

## See Also

- “Protect Models to Conceal Contents” (Embedded Coder)

## Use generated code

Allows user to generate code for the protected model with optional password protection. Selecting **Use generated code:**

- Enables Simulation Report and Code Generation Report for the protected model.
- Enables code generation.
- Enables support for simulation.

### Settings

**Default:** Off

On

User can generate code for the protected model. For password protection, create and verify a password with a minimum of four characters.

Off

User cannot generate code for the protected model.

### Dependencies

- To generate code, you must also select the **Simulate** check box.
- This parameter enables **Code interface** and **Content type**.

### Alternatives

`Simulink.ModelReference.protect`

### See Also

- “Code Generation Requirements and Limitations” (Embedded Coder)
- “Protect Models to Conceal Contents” (Embedded Coder)

## Code interface

Specify the interface for the generated code.

### Settings

**Default:** Model reference

Model reference

Specifies the model reference interface, which allows use of the protected model within a model reference hierarchy. Users of the protected model can generate code from a parent model that contains the protected model. In addition, users can run Model block software-in-the-loop (SIL) or processor-in-the-loop (PIL) simulations to verify code.

Top model

Specifies the standalone interface. Users of the protected model can run Model block SIL or PIL simulations to verify the protected model code.

### Dependencies

- Requires an Embedded Coder license
- This parameter is enabled if you:

- Specify an ERT (`ert.tlc`) system target file.
- Select the **Use generated code** check box.

### Alternatives

`Simulink.ModelReference.protect`

### See Also

- “Code Generation Requirements and Limitations” (Embedded Coder)
- “Protect Models to Conceal Contents” (Embedded Coder)

## Content type

Select the appearance of the generated code.

### Settings

**Default:** Obfuscated source code

#### Binaries

Includes only compiled binaries for the generated code.

#### Obfuscated source code

Includes obfuscated source code.

#### Readable source code

Includes readable source code and readable code comments.

The options `Obfuscated source code` and `Readable source code` by default include only the minimal header files required to build the code with the chosen build settings. These options correspond to using the `Simulink.ModelReference.protect` with the `'OutputFormat'` option set to `'MinimalCode'`. To include header files found on the include path in the protected model, use the `Simulink.ModelReference.protect` function and set the `'OutputFormat'` option to `'AllReferencedHeaders'`.

The `Binaries` option corresponds to using the `Simulink.ModelReference.protect` function with the `'OutputFormat'` option set to `'CompiledBinaries'`.

### Dependencies

This parameter is enabled by selecting the **Use generated code** check box.

### Alternatives

`Simulink.ModelReference.protect`

### See Also

- “Protect Models to Conceal Contents” (Embedded Coder)

## Use generated HDL code

Allows user to generate HDL code for the protected model with optional password protection. Selecting **Use generated HDL code**:

- Enables Simulation Report and HDL Code Generation Report for the protected model.
- Enables support for HDL code generation.
- Enables support for simulation.

### Settings

**Default:** Off

On

User can generate HDL code for the protected model. For password protection, create and verify a password with a minimum of eight characters.

Off

User can simulate but cannot generate HDL code for the protected model.

### Dependencies

To generate HDL code, you must also select the **Simulate** check box.

### Alternatives

`Simulink.ModelReference.protect`

### See Also

- “Code Generation Requirements and Limitations” (Embedded Coder)
- “Protect Models to Conceal Contents” (Embedded Coder)

## Create protected model in

Specify the folder path for the protected model.

### Settings

**Default:** Current working folder

### Dependencies

A model that you protect must be available on the MATLAB path.

### Alternatives

`Simulink.ModelReference.protect`

### See Also

- “Protect Models to Conceal Contents” (Embedded Coder)

## Create harness model for protected model

Create a harness model for the protected model. The harness model contains only a Model block that references the protected model.

### Settings

**Default:** Off



On

Create a harness model for the protected model.



Off

Do not create a harness model for the protected model.

### Alternatives

`Simulink.ModelReference.protect`

### See Also

- “Protect Models to Conceal Contents” (Embedded Coder)



# Simulink Coder Tools

---

# Code Replacement Viewer

Explore content of code replacement libraries

## Description

The Code Replacement Viewer displays the content of code replacement libraries and tables. You can use this tool to explore and choose a code replacement library or to view a predefined code replacement table. If you develop a custom code replacement library, you can use this viewer to verify table entries for the following properties:

- Argument order is correct.
- Conceptual argument names match code generator naming conventions.
- Implementation argument names are correct.
- Header or source file specification is not missing.
- I/O types are correct.
- Relative priority of entries is correct (highest priority is 0, and lowest priority is 100).
- Saturation or rounding mode specifications are not missing.

If you specify a library name when you open the viewer, the viewer displays the code replacement tables for that library. If you specify a table name when you open the viewer, the viewer displays the function and operator code replacement entries for that table. The viewer can only display code replacement tables that are defined. For more information on creating code replacement tables, see “Define Code Replacement Library Optimizations” (Embedded Coder).

### Abbreviated Entry Information

In the middle pane, the viewer displays entries that are in the selected code replacement table, along with abbreviated information for each entry.

| Field                 | Description                                                                                                                                                                                                                                                                                                                                                                                                        |
|-----------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Name</b>           | Name or identifier of the function or operator being replaced (for example, <code>cos</code> or <code>RTW_OP_ADD</code> ).                                                                                                                                                                                                                                                                                         |
| <b>Implementation</b> | Name of the implementation function, which can match or differ from <b>Name</b> .                                                                                                                                                                                                                                                                                                                                  |
| <b>NumIn</b>          | Number of input arguments.                                                                                                                                                                                                                                                                                                                                                                                         |
| <b>In1Type</b>        | Data type of the first conceptual input argument.                                                                                                                                                                                                                                                                                                                                                                  |
| <b>In2Type</b>        | Data type of the second conceptual input argument.                                                                                                                                                                                                                                                                                                                                                                 |
| <b>OutType</b>        | Data type of the conceptual output argument.                                                                                                                                                                                                                                                                                                                                                                       |
| <b>Priority</b>       | The entry's match priority, relative to other entries of the same name and to the conceptual argument list within the selected code replacement library. The priority can range from 0 to 100, with 0 being the highest priority. The default is 100. If the library provides two implementations for a function or operator, the implementation with the higher priority shadows the one with the lower priority. |

| Field      | Description |
|------------|-------------|
| UsageCount | Not used.   |

### Detailed Entry Information

In the middle pane, when you select an entry, the viewer displays entry details.

| Field                        | Description                                                                                                                                                                                                                                                                                                                                                                                                        |
|------------------------------|--------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Description</b>           | Text description of the table entry (can be empty).                                                                                                                                                                                                                                                                                                                                                                |
| <b>Key</b>                   | Name or identifier of the function or operator being replaced (for example, <code>cos</code> or <code>RTW_OP_ADD</code> ), and the number of conceptual input arguments.                                                                                                                                                                                                                                           |
| <b>Implementation</b>        | Name of the implementation function, and the number of implementation input arguments.                                                                                                                                                                                                                                                                                                                             |
| <b>Implementation type</b>   | Type of implementation: <code>FCN_IMPL_FUNCT</code> for function or <code>FCN_IMPL_MACRO</code> for macro.                                                                                                                                                                                                                                                                                                         |
| <b>Saturation mode</b>       | Saturation mode that the implementation function supports. One of:<br><code>RTW_SATURATE_ON_OVERFLOW</code><br><code>RTW_WRAP_ON_OVERFLOW</code><br><code>RTW_SATURATE_UNSPECIFIED</code>                                                                                                                                                                                                                          |
| <b>Rounding modes</b>        | Rounding modes that the implementation function supports. One or more of:<br><code>RTW_ROUND_FLOOR</code><br><code>RTW_ROUND_CEILING</code><br><code>RTW_ROUND_ZERO</code><br><code>RTW_ROUND_NEAREST</code><br><code>RTW_ROUND_NEAREST_ML</code><br><code>RTW_ROUND_SIMPLEST</code><br><code>RTW_ROUND_CONV</code><br><code>RTW_ROUND_UNSPECIFIED</code>                                                          |
| <b>GenCallback file</b>      | Not used.                                                                                                                                                                                                                                                                                                                                                                                                          |
| <b>Implementation header</b> | Name of the header file that declares the implementation function.                                                                                                                                                                                                                                                                                                                                                 |
| <b>Implementation source</b> | Name of the implementation source file.                                                                                                                                                                                                                                                                                                                                                                            |
| <b>Priority</b>              | The entry's match priority, relative to other entries of the same name and to the conceptual argument list within the selected code replacement library. The priority can range from 0 to 100, with 0 being the highest priority. The default is 100. If the library provides two implementations for a function or operator, the implementation with the higher priority shadows the one with the lower priority. |
| <b>Total Usage Count</b>     | Not used.                                                                                                                                                                                                                                                                                                                                                                                                          |
| <b>Entry class</b>           | Class from which the current table entry is instantiated.                                                                                                                                                                                                                                                                                                                                                          |
| <b>Conceptual arguments</b>  | Name, I/O type ( <code>RTW_IO_OUTPUT</code> or <code>RTW_IO_INPUT</code> ), and data type for each conceptual argument.                                                                                                                                                                                                                                                                                            |
| <b>Implementation</b>        | Name, I/O type ( <code>RTW_IO_OUTPUT</code> or <code>RTW_IO_INPUT</code> ), data type, and alignment requirement for each implementation argument.                                                                                                                                                                                                                                                                 |

### Fixed-Point Entry Information

When you select an operator entry that specifies net slope fixed-point parameters, the viewer displays fixed-point information.

| Field                                | Description                                                                                                                                                                                                                                                                                                               |
|--------------------------------------|---------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Net slope adjustment factor F</b> | Slope adjustment factor (F) part of the net slope factor, $F2^E$ , for net slope table entries. You use this factor with fixed-point multiplication and division replacement to map a range of slope and bias values to a replacement function.                                                                           |
| <b>Net fixed exponent E</b>          | Fixed exponent (E) part of the net slope factor, $F2^E$ , for net slope table entries. You use this fixed exponent with fixed-point multiplication and division replacement to map a range of slope and bias values to a replacement function.                                                                            |
| <b>Slopes must be the same</b>       | Indicates whether code replacement request processing must check that the slopes on arguments (input and output) are equal. You use this information with fixed-point addition and subtraction replacement to disregard specific slope and bias values, and map relative slope and bias values to a replacement function. |
| <b>Must have zero net bias</b>       | Indicates whether code replacement request processing must check that the net bias on arguments is zero. You use this information with fixed-point addition and subtraction replacement to disregard specific slope and bias values, and map relative slope and bias values to a replacement function.                    |

## Open the Code Replacement Viewer


Open from the MATLAB command prompt using `crviewer`.

### Examples

#### Display Contents of Code Replacement Library

This example opens the registered code replacement library `GNU C99 extensions`.


```
crviewer('GNU C99 extensions')
```



### Display Contents of Code Replacement Table

This example opens a predefined code replacement table `crl_table_sinfcn`. To learn how to create this example table, see "Define Code Replacement Library Optimizations" (Embedded Coder).

```
crviewer(crl_table_sinfcn)
```



- “Choose a Code Replacement Library”

## Programmatic Use

`crviewer('library')` opens the Code Replacement Viewer and displays the contents of `library`, where `library` is a character vector that names a registered code replacement library.

`crviewer(table)` opens the Code Replacement Viewer and displays the contents of a predefined `table`, where `table` is a MATLAB file that defines code replacement tables. The table must be user predefined and the file must be in the current folder or on the MATLAB path.

## See Also

### Topics

- “Choose a Code Replacement Library”
- “What Is Code Replacement?”
- “Code Replacement Libraries”
- “Code Replacement Terminology”

**Introduced in R2014b**

# Optimization Parameters

---

## Model Configuration Parameters: Code Generation Optimization

The **Code Generation > Optimization** category includes parameters for improving the simulation speed of your models and improving the performance of the generated code. Model configuration parameters to improve the generated code require Simulink Coder or Embedded Coder.

| Parameter                                                                            | Description                                                                                                                                               |
|--------------------------------------------------------------------------------------|-----------------------------------------------------------------------------------------------------------------------------------------------------------|
| "Default parameter behavior" on page 16-9                                            | Transform numeric block parameters into constant inlined values in the generated code.                                                                    |
| "Pass reusable subsystem outputs as" (Embedded Coder)                                | Specify how a reusable subsystem passes outputs.                                                                                                          |
| "Remove root level I/O zero initialization" (Embedded Coder)                         | Specify whether to generate initialization code for root-level inports and outports set to zero.                                                          |
| "Remove internal data zero initialization" (Embedded Coder)                          | Specify whether to generate initialization code for internal work structures, such as block states and block outputs, to zero.                            |
| "Level" (Embedded Coder)                                                             | Choose the optimization level that you want to apply to the generated code.                                                                               |
| "Priority" (Embedded Coder)                                                          | Optimize the generated code for increased execution efficiency, decreased RAM consumption, or a balance between the two.                                  |
| "Specify custom optimizations" (Embedded Coder)                                      | Instead of applying an optimization level, select this parameter to select the optimization parameters in the <b>Details</b> section.                     |
| "Use memcpy for vector assignment" on page 16-13                                     | Optimize code generated for vector assignment by replacing for loops with memcpy.                                                                         |
| "Memcpy threshold (bytes)" on page 16-15                                             | Specify the minimum array size in bytes for which memcpy and memset function calls should replace for loops for vector assignments in the generated code. |
| "Enable local block outputs" on page 16-25                                           | Specify whether block signals are declared locally or globally.                                                                                           |
| "Reuse local block outputs" on page 16-27                                            | Specify whether Simulink Coder software reuses signal memory.                                                                                             |
| "Eliminate superfluous local variables (Expression folding)" on page 16-29           | Collapse block computations into single expressions.                                                                                                      |
| "Reuse global block outputs" (Embedded Coder)                                        | Reuse global memory for block outputs.                                                                                                                    |
| "Perform in-place updates for Assignment and Bus Assignment blocks" (Embedded Coder) | Reuse the input and output variables of Bus Assignment and Assignment blocks if possible.                                                                 |
| "Reuse buffers for Data Store Read and Data Store Write blocks" (Embedded Coder)     | Remove temporary buffers for Data Store Read and Data Store Write blocks. Use the Data Store Memory block directly if possible.                           |

| Parameter                                                                                                    | Description                                                                                                                         |
|--------------------------------------------------------------------------------------------------------------|-------------------------------------------------------------------------------------------------------------------------------------|
| "Simplify array indexing" (Embedded Coder)                                                                   | Replace multiply operations in array indices when accessing arrays in a loop.                                                       |
| "Pack Boolean data into bitfields" (Embedded Coder)                                                          | Specify whether Boolean signals are stored as one-bit bitfields or as a Boolean data type.                                          |
| "Bitfield declarator type specifier" (Embedded Coder)                                                        | Specify the bitfield type when selecting configuration parameter "Pack Boolean data into bitfields" (Embedded Coder).               |
| "Reuse buffers of different sizes and dimensions" (Embedded Coder)                                           | Reduce memory consumption by reusing buffers to store data of different sizes and dimensions.                                       |
| "Optimize global data access" (Embedded Coder)                                                               | Select global variable optimization.                                                                                                |
| "Optimize block operation order in the generated code" (Embedded Coder)                                      | Reorder block operations in the generated code for improved code execution speed.                                                   |
| "Use bitsets for storing state configuration" on page 16-19                                                  | Use bitsets to reduce the amount of memory required to store state configuration variables.                                         |
| "Use bitsets for storing Boolean data" on page 16-21                                                         | Use bitsets to reduce the amount of memory required to store Boolean data.                                                          |
| "Maximum stack size (bytes)" on page 16-17                                                                   | Specify the maximum stack size in bytes for your model.                                                                             |
| "Loop unrolling threshold" on page 16-16                                                                     | Specify the minimum signal or parameter width for which a for loop is generated.                                                    |
| "Optimize using the specified minimum and maximum values" (Embedded Coder)                                   | Optimize generated code using the specified minimum and maximum values for signals and parameters in the model.                     |
| <b>Maximum number of arguments for subsystem outputs</b>                                                     | Set maximum number of subsystem outputs to pass individually.                                                                       |
| "Inline invariant signals" on page 16-11                                                                     | Transform symbolic names of invariant signals into constant values.                                                                 |
| "Remove code from floating-point to integer conversions with saturation that maps NaN to zero" on page 16-31 | Remove code that handles floating-point to integer conversion results for NaN values.                                               |
| "Use memset to initialize floats and doubles to 0.0" on page 16-33                                           | Specify whether to generate code that explicitly initializes floating-point data to 0.0.                                            |
| "Remove code from floating-point to integer conversions that wraps out-of-range values" on page 16-6         | Remove wrapping code that handles out-of-range floating-point to integer conversion results.                                        |
| "Remove Code from Tunable Parameter Expressions That Saturate Out-of-Range Values" (Embedded Coder)          | Remove wrapping code of tunable parameters.                                                                                         |
| "Remove code that protects against division arithmetic exceptions" (Embedded Coder)                          | Specify whether to generate code that guards against division by zero and INT_MIN/ -1 operations for integers and fixed-point data. |
| "Buffer for reusable subsystems" on page 16-8                                                                | Improve reuse by inserting buffers at reusable subsystem boundaries.                                                                |

| <b>Parameter</b>                                                             | <b>Description</b>                                                                                                                             |
|------------------------------------------------------------------------------|------------------------------------------------------------------------------------------------------------------------------------------------|
| <b>Disable incompatible optimizations</b>                                    | Specify whether to disable optimizations that are incompatible with Simulink Code Inspector.                                                   |
| “Base storage type for automatically created enumerations” on page 16-23     | Set the storage type and size for enumerations created with active state output.                                                               |
| “Base storage type for automatically created enumerations” on page 16-23     | For signals with the same label, the code generator attempts to use the same signal memory.                                                    |
| “Generate parallel for-loops” (Embedded Coder)                               | Specify whether for-loops in the generated code shall be implement in parallel for Matlab Function, Matlab System or a For Each block.         |
| “Signal storage reuse” on page 16-35                                         | Specify reuse of memory buffers allocated to store block input and output signals thereby reducing the memory requirement of real-time program |
| “Operator to represent Bitwise and Logical Operator blocks” (Embedded Coder) | Specify whether the generated code contains bitwise or logical operators or both.                                                              |

## See Also

## Related Examples

- “Performance”

## Optimization Pane: Tab Overview

Set up optimizations for a model's active configuration set. Optimizations are set for both simulation and code generation.

### Tips

- To open the Optimization pane For ERT-based targets, in the Simulink Editor, select **Apps > Embedded Coder > Settings > Configuration Parameters > Optimization**.
- To open the Optimization pane For GRT-based targets, in the Simulink Editor, select **Apps > Simulink Coder > Settings > Configuration Parameters > Optimization**.
- Simulink Coder optimizations appear only when the Simulink Coder product is installed on your system. Selecting a GRT-based or ERT-based system target file changes the available options. ERT-based target optimizations require a Embedded Coder license when generating code. See the **Dependencies** sections below for licensing information for each parameter.

### To get help on an option

- 1 Right-click the option text label.
- 2 From the context menu, select **What's This**.



### See Also

#### Related Examples

- “Model Configuration Parameters: Code Generation Optimization” on page 16-2
- “Perform Acceleration” (Simulink)
- “Performance”

## Remove code from floating-point to integer conversions that wraps out-of-range values

### Description

Remove wrapping code that handles out-of-range floating-point to integer conversion results.

**Category:** Optimization

### Settings

**Default:** Off

**On**

Removes code when out-of-range conversions occur. Select this check box if code efficiency is critical to your application and the following conditions are true for at least one block in the model:

- Computing the outputs or parameters of a block involves converting floating-point data to integer or fixed-point data.
- The **Saturate on integer overflow** check box is cleared in the Block Parameters dialog box.

---

**Caution** Execution of generated code might not produce the same results as simulation.

---

**Off**

Results for simulation and execution of generated code match when out-of-range conversions occur. The generated code is larger than when you select this check box.

### Tips

- Selecting this check box reduces the size and increases the speed of the generated code at the cost of potentially producing results that do not match simulation in the case of out-of-range values.
- Selecting this check box affects code generation results only for out-of-range values and cannot cause code generation results to differ from simulation results for in-range values.

### Dependency

This parameter requires a Simulink Coder license.

### Command-Line Information

**Parameter:** EfficientFloat2IntCast

**Value:** 'on' | 'off'

**Default:** 'off'

## Recommended Settings

| Application       | Setting                              |
|-------------------|--------------------------------------|
| Debugging         | Off                                  |
| Traceability      | Off                                  |
| Efficiency        | On (execution, ROM), No impact (RAM) |
| Safety precaution | No impact                            |

## See Also

### Related Examples

- “Remove Code From Floating-Point to Integer Conversions That Wraps Out-of-Range Values”
- “Model Configuration Parameters: Code Generation Optimization” on page 16-2

## Buffer for reusable subsystems

### Description

Specify whether to generate code that has buffers to enhance the reuse of subsystems.

**Category:** Optimization

### Settings

**Default:** On

On

Generates code that has extra buffers that enable the reuse of subsystems in the generated code which enhances ROM efficiency.

Off

Generates code that does not have extra buffers that could have potentially increased the reuse of a subsystem in the generated code. This code generation reduces ROM efficiency. The absence of the extra buffers might avoid extra data copies in the generated code, which improves code execution speed.

### Command-Line Information

**Parameter:** BufferReusableBoundary

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application       | Setting                         |
|-------------------|---------------------------------|
| Debugging         | No Impact                       |
| Traceability      | No Impact                       |
| Efficiency        | Off (Execution Speed), On (ROM) |
| Safety precaution | No Impact                       |

### See Also

#### Related Examples

- “Model Configuration Parameters: Code Generation Optimization” on page 16-2
- “Specify Buffer Reuse by Using Simulink.Signal Objects” (Embedded Coder)

# Default parameter behavior

## Description

Transform numeric block parameters into constant inlined values in the generated code.

**Category:** Optimization

## Settings

**Default:** Tunable for GRT targets | Inlined for ERT targets

### Inlined

Set **Default parameter behavior** to Inlined to reduce global RAM usage and increase efficiency of the generated code. The code does not allocate memory to represent numeric block parameters such as the **Gain** parameter of a Gain block. Instead, the code inlines the literal numeric values of these block parameters.

### Tunable

Set **Default parameter behavior** to Tunable to enable tunability of numeric block parameters in the generated code. The code represents numeric block parameters and variables that use the storage class Auto, including numeric MATLAB variables, as tunable fields of a global parameters structure.

## Tips

- Whether you set **Default parameter behavior** to Inlined or to Tunable, create parameter data objects to preserve tunability for block parameters. For more information, see “Create Tunable Calibration Parameter in the Generated Code”.
- When you switch from a system target file that is not ERT-based to one that is ERT-based, **Default parameter behavior** sets to Inlined by default. However, you can change the setting of **Default parameter behavior** later.
- When a top model uses referenced models or if a model is referenced by another model:
  - Referenced models must set **Default parameter behavior** to Inlined if the top model has **Default parameter behavior** set to Inlined.
  - The top model can specify **Default parameter behavior** as Tunable or Inlined.
- If your model contains an Environment Controller block, you can suppress code generation for the branch connected to the Sim port if you set **Default parameter behavior** to Inlined and the branch does not contain external signals.

## Dependencies

When you set **Default parameter behavior** to Inlined, you enable “Inline invariant signals” on page 16-11 configuration parameter.

## Command-Line Information

**Parameter:** DefaultParameterBehavior

**Type:** character vector

**Value:** 'Inlined' | 'Tunable'

**Default:** 'Tunable' for GRT targets | 'Inlined' for ERT targets

## Recommended Settings

| Application       | Setting                                                              |
|-------------------|----------------------------------------------------------------------|
| Debugging         | Tunable during development<br>Inlined for production code generation |
| Traceability      | Inlined                                                              |
| Efficiency        | Inlined                                                              |
| Safety precaution | No impact                                                            |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Optimization” on page 16-2
- “Inline Numeric Values of Block Parameters”
- “How Generated Code Stores Internal Signal, State, and Parameter Data”

# Inline invariant signals

## Description

Transform symbolic names of invariant signals into constant values.

**Category:** Optimization

## Settings

**Default:** Off

**On**

Simulink Coder software uses the numerical values of model parameters, instead of their symbolic names, in generated code. An invariant signal is not inline if it is nonscalar, complex, or the block inport the signal is attached to takes the address of the signal.

**Off**

Uses symbolic names of model parameters in generated code.

## Dependencies

- This parameter requires a Simulink Coder license.
- This parameter is enabled when you set **Default parameter behavior** to Inlined.

## Command-Line Information

**Parameter:** InlineInvariantSignals

**Value:** 'on' | 'off'

**Default:** 'off'

## Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | Off       |
| Traceability      | Off       |
| Efficiency        | On        |
| Safety precaution | No impact |

## See Also

## Related Examples

- “Model Configuration Parameters: Code Generation Optimization” on page 16-2
- “Inline Invariant Signals”

- “Performance”

# Use memcpy for vector assignment

## Description

Optimize code generated for vector assignment by replacing for loops with memcpy.

**Category:** Optimization

## Settings

**Default:** On

**On**

Enables use of memcpy for vector assignment based on the associated threshold parameter **Memcpy threshold (bytes)**. memcpy is used in the generated code if the number of array elements times the number of bytes per element is greater than or equal to the specified value for **Memcpy threshold (bytes)**. One byte equals the width of a character in this context.

**Off**

Disables use of memcpy for vector assignment.

## Dependencies

- This parameter requires a Simulink Coder license.
- When selected, this parameter enables the associated parameter **Memcpy threshold (bytes)**.

## Command-Line Information

**Parameter:** EnableMemcpy

**Value:** 'on' | 'off'

**Default:** 'on'

## Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | On        |
| Safety precaution | No impact |

## See Also

## Related Examples

- “Model Configuration Parameters: Code Generation Optimization” on page 16-2
- “Use memcpy Function to Optimize Generated Code for Vector Assignments”

- “Performance”

## Memcpy threshold (bytes)

### Description

Specify the minimum array size in bytes for which memcpy and memset function calls should replace for loops for vector assignments in the generated code.

**Category:** Optimization

### Settings

**Default:** 64

### Dependencies

- This parameter requires a Simulink Coder license.
- For the memcpy optimization, this parameter is enabled when you select **Use memcpy for vector assignment**.

### Command-Line Information

**Parameter:** MemcpyThreshold

**Type:** integer

**Value:** valid quantity of bytes

**Default:** 64

### Recommended Settings

| Application       | Setting                                                   |
|-------------------|-----------------------------------------------------------|
| Debugging         | No impact                                                 |
| Traceability      | No impact                                                 |
| Efficiency        | Accept default or determine target-specific optimal value |
| Safety precaution | No impact                                                 |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Optimization” on page 16-2
- “Use memcpy Function to Optimize Generated Code for Vector Assignments”
- “Performance”

## Loop unrolling threshold

### Description

Specify the minimum array size width for which a `for` loop is generated.

**Category:** Optimization

### Settings

**Default:** 5

Specify the array size at which the code generator begins to use a `for` loop instead of separate assignment statements to assign values..

When there are perfectly nested loops, the code generator uses a `for` loop if the product of the loop counts for loops in the perfect loop nest is greater than or equal to the threshold.

### Dependency

This parameter requires a Simulink Coder license.

### Command-Line Information

**Parameter:** RollThreshold

**Type:** character vector

**Value:** valid value

**Default:** '5'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | >0        |
| Safety precaution | No impact |

### See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Optimization” on page 16-2
- “Configure Loop Unrolling Threshold”
- “Performance”

## Maximum stack size (bytes)

### Description

Specify the maximum stack size in bytes for your model.

**Category:** Optimization

### Settings

**Default:**Inherit from target

Inherit from target

The Simulink Coder software assigns the maximum stack size to the smaller value of the following:

- The default value (200,000 bytes) set by the Simulink Coder software
- Value of the TLC variable `MaxStackSize` in the system target file

<Specify a value>

Specify a positive integer value. Simulink Coder software assigns the maximum stack size to the specified value.

---

**Note** If you specify a maximum stack size for a model, the estimated required stack size of a referenced model must be less than the specified maximum stack size of the parent model.

---

### Tips

- If you specify the maximum stack size to be zero, then the generated code implements all variables as global data.
- If you specify the maximum stack to be `inf`, then the generated code contains the least number of global variables.
- If your model contains a variable that is larger than 4096 bytes, the code generator implements it in global memory by default. You can increase the size of variables that the code generator places in local memory by changing the value of the TLC variable `MaxStackVariableSize`. You can change this value by typing the following command in MATLAB Command Window:  
`set_param(modelName, 'TLCOptions', '-aMaxStackVariableSize=N')`

### Command-Line Information

**Parameter:** `MaxStackSize`

**Type:** `int`

**Value:** valid value

**Default:** Inherit from target

## Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | No impact |
| Traceability      | No impact |
| Efficiency        | No impact |
| Safety precaution | No impact |

## See Also

### Related Examples

- “Model Configuration Parameters: Code Generation Optimization” on page 16-2
- “Customize Stack Space Allocation”
- “Performance”

## Use bitsets for storing state configuration

### Description

Use bitsets to reduce the amount of memory required to store state configuration variables.

**Category:** Optimization

### Settings

**Default:** Off

On

Stores state configuration variables in bitsets. Potentially reduces the amount of memory required to store the variables. Potentially requires more instructions to access state configuration, which can result in less optimal code.

Off

Stores state configuration variables in unsigned bytes. Potentially increases the amount of memory required to store the variables. Potentially requires fewer instructions to access state configuration, which can result in more optimal code.

### Tips

- Selecting this check box can significantly reduce the amount of memory required to store the variables. However, it can increase the amount of memory required to store target code if the target processor does not include instructions for manipulating bitsets.
- Select this check box for Stateflow charts that have a large number of sibling states at a given level of the hierarchy.
- Clear this check box for Stateflow charts with a small number of sibling states at a given level of the hierarchy.

### Dependency

This parameter requires a Simulink Coder license.

### Command-Line Information

**Parameter:** StateBitsets

**Value:** 'on' | 'off'

**Default:** 'off'

### Recommended Settings

| Application  | Setting |
|--------------|---------|
| Debugging    | Off     |
| Traceability | Off     |

| <b>Application</b> | <b>Setting</b>                 |
|--------------------|--------------------------------|
| Efficiency         | Off (execution, ROM), On (RAM) |
| Safety precaution  | No impact                      |

## **See Also**

### **Related Examples**

- “Reduce Memory Usage for Boolean and State Configuration Variables”
- “Design Tips for Optimizing Generated Code for Stateflow Objects”

# Use bitsets for storing Boolean data

## Description

Use bitsets to reduce the amount of memory required to store Boolean data.

**Category:** Optimization

## Settings

**Default:** Off

On

Stores Boolean data in bitsets. Potentially reduces the amount of memory required to store the data. Potentially requires more instructions to access the data, which can result in less optimal code.

Off

Stores Boolean data in unsigned bytes. Potentially increases the amount of memory required to store the data. Potentially requires fewer instructions to access the data, which can result in more optimal code.

## Tips

- Select this check box for Stateflow charts that reference Boolean data infrequently.
- Clear this check box for Stateflow charts that reference Boolean data frequently.

## Dependency

This parameter requires a Simulink Coder license.

## Command-Line Information

**Parameter:** DataBitsets

**Value:** 'on' | 'off'

**Default:** 'off'

## Recommended Settings

| Application       | Setting                        |
|-------------------|--------------------------------|
| Debugging         | Off                            |
| Traceability      | Off                            |
| Efficiency        | Off (execution, ROM), On (RAM) |
| Safety precaution | No impact                      |

## **See Also**

### **Related Examples**

- “Reduce Memory Usage for Boolean and State Configuration Variables”
- “Design Tips for Optimizing Generated Code for Stateflow Objects”

## Base storage type for automatically created enumerations

### Description

Set the storage type and size for enumerations created with active state output.

**Category:** Optimization

### Settings

**Default:** 'Native Integer'

'Native Integer'

Default target integer type

int32

32 bit signed integer type

int16

16 bit signed integer type

int8

8 bit signed integer type

uint16

16 bit unsigned integer type

uint8

8 bit unsigned integer type

### Tips

- The default 'Native Integer' is recommended for most models.
- If you need a smaller memory footprint for the generated enumerations, set the storage type to a smaller size. The size must be large enough to hold the number of states in the chart.

### Dependency

This parameter requires a Simulink Coder license.

### Command-Line Information

**Parameter:** ActiveStateOutputEnumStorageType

**Value:** 'Native Integer' | 'int32' | 'int16' | 'int8' | 'uint16' | 'uint8'

**Default:** 'Native Integer'

### See Also

### Related Examples

- “Monitor State Activity Through Active State Data” (Stateflow)

- “Design Tips for Optimizing Generated Code for Stateflow Objects”

## Enable local block outputs

### Description

Specify whether block signals are declared locally or globally.

**Category:** Optimization

### Settings

**Default:** On

**On**

Block signals are declared locally in functions.

**Off**

Block signals are declared globally.

### Tips

- If it is not possible to declare an output as a local variable, the generated code declares the output as a global variable.
- If you are constrained by limited stack space, you can turn **Enable local block outputs** off and still benefit from memory reuse.

### Dependencies

- This parameter requires a Simulink Coder license.
- This parameter is enabled by **Signal storage reuse**.

### Command-Line Information

**Parameter:** LocalBlockOutputs

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | Off       |
| Traceability      | Off       |
| Efficiency        | On        |
| Safety precaution | No impact |

## **See Also**

### **Related Examples**

- “Enable and Reuse Local Block Outputs in Generated Code”
- “Performance”
- “Model Configuration Parameters: Code Generation Optimization” on page 16-2

## Reuse local block outputs

### Description

Specify whether Simulink Coder software reuses signal memory.

**Category:** Optimization

### Settings

**Default:** On

**On**

- Simulink Coder software tries to reuse signal memory, reducing stack size where signals are being buffered in local variables.
- Selecting this parameter trades code traceability for code efficiency.

**Off**

Signals are stored in unique locations.

### Dependencies

This parameter:

- Is enabled by **Signal storage reuse**.
- Requires a Simulink Coder license.

### Command-Line Information

**Parameter:** BufferReuse

**Value:** 'on' | 'off'

**Default:** 'on'

### Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | Off       |
| Traceability      | Off       |
| Efficiency        | On        |
| Safety precaution | No impact |

## **See Also**

### **Related Examples**

- “Enable and Reuse Local Block Outputs in Generated Code”
- “Performance”
- “Model Configuration Parameters: Code Generation Optimization” on page 16-2

# Eliminate superfluous local variables (Expression folding)

## Description

Collapse block computations into single expressions.

**Category:** Optimization

## Settings

**Default:** On

**On**

- Enables expression folding.
- Eliminates local variables, incorporating the information into the main code statement.
- Improves code readability and efficiency.

**Off**

Disables expression folding.

## Dependencies

- This parameter requires a Simulink Coder license.
- This parameter is enabled by **Signal storage reuse**.

## Command-Line Information

**Parameter:** ExpressionFolding

**Value:** 'on' | 'off'

**Default:** 'on'

## Recommended Settings

| Application       | Setting                                                                              |
|-------------------|--------------------------------------------------------------------------------------|
| Debugging         | Off                                                                                  |
| Traceability      | No impact for simulation or during development<br>Off for production code generation |
| Efficiency        | On                                                                                   |
| Safety precaution | No impact                                                                            |

## See Also

## Related Examples

- “Minimize Computations and Storage for Intermediate Results at Block Outputs”

- “Performance”
- “Model Configuration Parameters: Code Generation Optimization” on page 16-2

# Remove code from floating-point to integer conversions with saturation that maps NaN to zero

## Description

Remove code that handles floating-point to integer conversion results for NaN values.

**Category:** Optimization

## Settings

**Default:** On

**On**

Removes code when mapping from NaN to integer zero occurs. Select this check box if code efficiency is critical to your application and the following conditions are true for at least one block in the model:

- Computing outputs or parameters of a block involves converting floating-point data to integer or fixed-point data.
- The **Saturate on integer overflow** check box is selected in the Block Parameters dialog box.

---

**Caution** Execution of generated code might not produce the same results as simulation.

---

**Off**

Results for simulation and execution of generated code match when mapping from NaN to integer zero occurs. The generated code is larger than when you select this check box.

## Tips

- Selecting this check box reduces the size and increases the speed of the generated code at the cost of producing results that do not match simulation in the case of NaN values.
- Selecting this check box affects code generation results only for NaN values and cannot cause code generation results to differ from simulation results for other values.

## Dependencies

- This parameter requires a Simulink Coder license.
- For ERT-based targets, this parameter is enabled when you select the **floating-point numbers** and **non-finite numbers** check boxes in the **Code Generation > Interface** pane.

## Command-Line Information

**Parameter:** EfficientMapNaN2IntZero

**Value:** 'on' | 'off'

**Default:** 'on'

## Recommended Settings

| Application       | Setting           |
|-------------------|-------------------|
| Debugging         | Off               |
| Traceability      | Off               |
| Efficiency        | On                |
| Safety precaution | No recommendation |

## See Also

### Related Examples

- “Remove Code That Maps NaN to Integer Zero”
- “Model Configuration Parameters: Code Generation Optimization” on page 16-2

## Use memset to initialize floats and doubles to 0.0

### Description

Specify whether to generate code that explicitly initializes floating-point data to 0.0.

**Category:** Optimization

### Settings

**Default:** On (GUI), 'off' (command line)

On

Uses `memset` to clear internal storage for floating-point data to integer bit pattern 0 (all bits 0), regardless of type. If your compiler and target CPU both represent floating-point zero with the integer bit pattern 0, use this parameter to gain execution and ROM efficiency.

This parameter requires that you turn on the configuration parameter **Memcpy threshold** to enable the memset functionality. Check that the value of the threshold is set high enough.

Off

Generates code to explicitly initialize storage for data of types `float` and `double` to 0.0. The resulting code is slightly less efficient than code generated when you select the option.

### Dependency

This parameter requires a Simulink Coder license.

### Command-Line Information

**Parameter:** `InitFltsAndDblsToZero`

**Value:** 'on' | 'off'

**Default:** 'off'

---

**Note** The command-line values are reverse of the settings values. Therefore, 'on' in the command line corresponds to the description of "Off" in the settings section, and 'off' in the command line corresponds to the description of "On" in the settings section.

---

### Recommended Settings

| Application       | Setting                                                          |
|-------------------|------------------------------------------------------------------|
| Debugging         | No impact                                                        |
| Traceability      | No impact                                                        |
| Efficiency        | On (GUI), 'off' (command line) (execution, ROM), No impact (RAM) |
| Safety precaution | No impact                                                        |

## **See Also**

### **Related Examples**

- “Optimize Generated Code Using memset Function”
- “Model Configuration Parameters: Code Generation Optimization” on page 16-2

# Signal storage reuse

## Description

Reuse signal memory.

**Category:** Optimization

## Settings

**Default:** On

**On**

Simulink software reuses memory buffers allocated to store block input and output signals, reducing the memory requirement of your real-time program.

**Off**

Simulink software allocates a separate memory buffer for each block's outputs. This makes all block outputs global and unique, which in many cases significantly increases RAM and ROM usage.

## Tips

- This option applies only to signals with storage class **Auto**.
- Signal storage reuse can occur only among signals that have the same data type.
- Clearing this option can substantially increase the amount of memory required to simulate large models.
- Clear this option if you need to:
  - Debug a C-MEX S-function
  - Use a Floating Scope or a Floating Scope block with the **Floating display** option selected to inspect signals in a model that you are debugging
- Simulink software opens an error dialog if **Signal storage reuse** is enabled and you attempt to use a Floating Scope or floating Display block to display a signal whose buffer has been reused.

## Dependencies

This parameter enables:

- **Enable local block outputs** on page 16-25
- **Reuse local block outputs** on page 16-27
- **Eliminate superfluous local variables (Expression folding)** on page 16-29

If you have an Embedded Coder license, this parameter enables:

- **Optimize global data access** (Embedded Coder)
- **Perform in-place updates for Assignment and Bus Assignment blocks** (Embedded Coder)

- **Reuse global block outputs** (Embedded Coder)
- **Optimize block operation order in the generated code** (Embedded Coder)
- **Reuse buffers for Data Store Read and Data Store Write blocks** (Embedded Coder)

## Command-Line Information

**Parameter:**OptimizeBlockIOStorage

**Value:** 'on' | 'off'

**Default:** 'on'

## Recommended Settings

| Application       | Setting   |
|-------------------|-----------|
| Debugging         | Off       |
| Traceability      | Off       |
| Efficiency        | On        |
| Safety precaution | No impact |

## See Also

### Related Examples

- “Minimize Computations and Storage for Intermediate Results at Block Outputs”
- “Performance”
- “Model Configuration Parameters: Code Generation Optimization” on page 16-2