

NAG C Library Function Document

nag_pde_parab_1d_coll_ode (d03pjc)

1 Purpose

nag_pde_parab_1d_coll_ode (d03pjc) integrates a system of linear or nonlinear parabolic partial differential equations (PDEs), in one space variable with scope for coupled ordinary differential equations (ODEs). The spatial discretisation is performed using a Chebyshev C^0 collocation method, and the method of lines is employed to reduce the PDEs to a system of ODEs. The resulting system is solved using a backward differentiation formula (BDF) method or a Theta method (switching between Newton's method and functional iteration).

2 Specification

```
void nag_pde_parab_1d_coll_ode (Integer npde, Integer m, double *ts, double tout,
    void (*pdedef)(Integer npde, double t, const double x[], Integer npdl,
        const double u[], const double ux[], Integer ncode, const double v[],
        const double vdot[], double p[], double q[], double r[], Integer *ires,
        Nag_Comm *comm),
    void (*bndary)(Integer npde, double t, const double u[], const double ux[],
        Integer ncode, const double v[], const double vdot[], Integer ibnd,
        double beta[], double gamma[], Integer *ires, Nag_Comm *comm),
    double u[], Integer nbkpts, const double xbkpts[], Integer npoly, Integer npts,
    double x[], Integer ncode,
    void (*odedef)(Integer npde, double t, Integer ncode, const double v[],
        const double vdot[], Integer nxi, const double xi[], const double ucp[],
        const double ucpx[], const double rcp[], const double ucpt[],
        const double ucptx[], double f[], Integer *ires, Nag_Comm *comm),
    Integer nxi, const double xi[], Integer neqn,
    void (*uvinit)(Integer npde, Integer npts, const double x[], double u[],
        Integer ncode, double v[], Nag_Comm *comm),
    const double rtol[], const double atol[], Integer itol, Nag_NormType norm,
    Nag_LinAlgOption laopt, const double algopt[], double rsave[], Integer lrsave,
    Integer isave[], Integer lisave, Integer itask, Integer itrace, const char *outfile,
    Integer *ind, Nag_Comm *comm, Nag_D03_Save *saved, NagError *fail)
```

3 Description

nag_pde_parab_1d_coll_ode (d03pjc) integrates the system of parabolic-elliptic equations and coupled ODEs

$$\sum_{j=1}^{\text{npde}} P_{i,j} \frac{\partial U_j}{\partial t} + Q_i = x^{-m} \frac{\partial}{\partial x} (x^m R_i), \quad i = 1, 2, \dots, \text{npde}, \quad a \leq x \leq b, \quad t \geq t_0, \quad (1)$$

$$F_i(t, V, \dot{V}, \xi, U^*, U_x^*, R^*, U_t^*, U_{xt}^*) = 0, \quad i = 1, 2, \dots, \text{ncode}, \quad (2)$$

where (1) defines the PDE part and (2) generalizes the coupled ODE part of the problem.

In (1), $P_{i,j}$ and R_i depend on x, t, U, U_x , and V ; Q_i depends on x, t, U, U_x, V and **linearly** on \dot{V} . The vector U is the set of PDE solution values

$$U(x, t) = [U_1(x, t), \dots, U_{\text{npde}}(x, t)]^T,$$

and the vector U_x is the partial derivative with respect to x . Note that $P_{i,j}, Q_i$ and R_i must not depend on $(\partial U)/(\partial t)$. The vector V is the set of ODE solution values

$$V(t) = [V_1(t), \dots, V_{\mathbf{ncode}}(t)]^T,$$

and \dot{V} denotes its derivative with respect to time.

In (2), ξ represents a vector of n_ξ spatial coupling points at which the ODEs are coupled to the PDEs. These points may or may not be equal to some of the PDE spatial mesh points. U^* , U_x^* , R^* , U_t^* and U_{xt}^* are the functions U , U_x , R , U_t and U_{xt} evaluated at these coupling points. Each F_i may only depend linearly on time derivatives. Hence the equation (2) may be written more precisely as

$$F = G - A\dot{V} - B \begin{pmatrix} U_t^* \\ U_{xt}^* \end{pmatrix}, \quad (3)$$

where $F = [F_1, \dots, F_{\mathbf{ncode}}]^T$, G is a vector of length \mathbf{ncode} , A is an \mathbf{ncode} by \mathbf{ncode} matrix, B is an \mathbf{ncode} by $(n_\xi \times \mathbf{npde})$ matrix and the entries in G , A and B may depend on t , ξ , U^* , U_x^* and V . In practice the user needs only to supply a vector of information to define the ODEs and not the matrices A and B . (See Section 5 for the specification of the user-supplied procedure **odedef**.)

The integration in time is from t_0 to t_{out} , over the space interval $a \leq x \leq b$, where $a = x_1$ and $b = x_{\mathbf{nbkpts}}$ are the leftmost and rightmost of a user-defined set of break-points $x_1, x_2, \dots, x_{\mathbf{nbkpts}}$. The co-ordinate system in space is defined by the value of m ; $m = 0$ for Cartesian co-ordinates, $m = 1$ for cylindrical polar co-ordinates and $m = 2$ for spherical polar co-ordinates.

The PDE system which is defined by the functions $P_{i,j}$, Q_i and R_i must be specified in a function **pdedef** supplied by the user.

The initial values of the functions $U(x, t)$ and $V(t)$ must be given at $t = t_0$. These values are calculated in a user-supplied function, **uvinit**.

The functions R_i which may be thought of as fluxes, are also used in the definition of the boundary conditions. The boundary conditions must have the form

$$\beta_i(x, t)R_i(x, t, U, U_x, V) = \gamma_i(x, t, U, U_x, V, \dot{V}), \quad i = 1, 2, \dots, \mathbf{npde}, \quad (4)$$

where $x = a$ or $x = b$. The functions γ_i may only depend **linearly** on \dot{V} .

The boundary conditions must be specified in a function **bdary** provided by the user.

The algebraic-differential equation system which is defined by the functions F_i must be specified in a function **odedef** supplied by the user. The user must also specify the coupling points ξ in the array **xi**. Thus, the problem is subject to the following restrictions:

- (i) in (1), $\dot{V}_j(t)$, for $j = 1, 2, \dots, \mathbf{ncode}$, may only appear **linearly** in the functions Q_i , for $i = 1, 2, \dots, \mathbf{npde}$, with a similar restriction for γ ;
- (ii) $P_{i,j}$ and the flux R_i must not depend on any time derivatives;
- (iii) $t_0 < t_{\text{out}}$, so that integration is in the forward direction;
- (iv) the evaluation of the functions $P_{i,j}$, Q_i and R_i is done at both the break-points and internally selected points for each element in turn, that is $P_{i,j}$, Q_i and R_i are evaluated twice at each break-point. Any discontinuities in these functions **must** therefore be at one or more of the mesh points;
- (v) at least one of the functions $P_{i,j}$ must be non-zero so that there is a time derivative present in the PDE problem;
- (vi) if $m > 0$ and $x_1 = 0.0$, which is the left boundary point, then it must be ensured that the PDE solution is bounded at this point. This can be done either by specifying the solution at $x = 0.0$ or by specifying a zero flux there, that is $\beta_i = 1.0$ and $\gamma_i = 0.0$.

The parabolic equations are approximated by a system of ODEs in time for the values of U_i at the mesh points. This ODE system is obtained by approximating the PDE solution between each pair of break-points by a Chebyshev polynomial of degree **npoly**. The interval between each pair of break-points is treated by `nag_pde_parab_1d_coll_ode` (d03pjc) as an element, and on this element, a polynomial and its space and time derivatives are made to satisfy the system of PDEs at **npoly** – 1 spatial points, which are chosen internally by the code and the break-points. The user-defined break-points and the internally

selected points together define the mesh. The smallest value that **npoly** can take is one, in which case, the solution is approximated by piecewise linear polynomials between consecutive break-points and the method is similar to an ordinary finite element method.

In total there are $(\mathbf{nbkpts} - 1) \times \mathbf{npoly} + 1$ mesh points in the spatial direction, and $\mathbf{npde} \times ((\mathbf{nbkpts} - 1) \times \mathbf{npoly} + 1) + \mathbf{ncode}$ ODEs in the time direction; one ODE at each break-point for each PDE component, $\mathbf{npoly} - 1$ ODEs for each PDE component between each pair of break-points, and \mathbf{ncode} coupled ODEs. The system is then integrated forwards in time using a Backward Differentiation Formula (BDF) method or a Theta method.

4 References

Berzins M (1990) Developments in the NAG Library software for parabolic equations *Scientific Software Systems* (ed J C Mason and M G Cox) 59–72 Chapman and Hall

Berzins M and Dew P M (1991) Algorithm 690: Chebyshev polynomial software for elliptic-parabolic systems of PDEs *ACM Trans. Math. Software* **17** 178–206

Berzins M, Dew P M and Furzeland R M (1988) Software tools for time-dependent equations in simulation and optimisation of large systems *Proc. IMA Conf. Simulation and Optimization* (ed A J Osiadcz) 35–50 Clarendon Press, Oxford

Berzins M and Furzeland R M (1992) An adaptive theta method for the solution of stiff and nonstiff differential equations *Appl. Numer. Math.* **9** 1–19

Zaturka N B, Drazin P G and Banks W H H (1988) On the flow of a viscous fluid driven along a channel by a suction at porous walls *Fluid Dynamics Research* **4**

5 Parameters

- 1: **npde** – Integer *Input*
On entry: the number of PDEs to be solved.
Constraint: $\mathbf{npde} \geq 1$.
- 2: **m** – Integer *Input*
On entry: the co-ordinate system used:
m = 0
 Indicates Cartesian co-ordinates.
m = 1
 Indicates cylindrical polar co-ordinates.
m = 2
 Indicates spherical polar co-ordinates.
Constraint: $0 \leq \mathbf{m} \leq 2$.
- 3: **ts** – double * *Input/Output*
On entry: the initial value of the independent variable t .
On exit: the value of t corresponding to the solution values in **u**. Normally **ts** = **tout**.
Constraint: **ts** < **tout**.
- 4: **tout** – double *Input*
On entry: the final value of t to which the integration is to be carried out.

5: **pdedef**

Function

pdedef must compute the functions $P_{i,j}$, Q_i and R_i which define the system of PDEs. The functions may depend on x , t , U , U_x and V ; Q_i may depend linearly on \dot{V} . The functions must be evaluated at a set of points.

<pre>void pdedef (Integer npde, double t, const double x[], Integer nptl, const double u[], const double ux[], Integer ncode, const double v[], const double vdot[], double p[], double q[], double r[], Integer *ires, Nag_Comm *comm)</pre>	
1:	<p>npde – Integer Input</p> <p><i>On entry:</i> the number of PDEs in the system.</p>
2:	<p>t – double Input</p> <p><i>On entry:</i> the current value of the independent variable t.</p>
3:	<p>x[nptl] – const double Input</p> <p><i>On entry:</i> contains a set of mesh points at which $P_{i,j}$, Q_i and R_i are to be evaluated. x[0] and x[nptl – 1] contain successive user-supplied break-points and the elements of the array will satisfy $\mathbf{x}[0] < \mathbf{x}[1] < \dots < \mathbf{x}[\mathbf{nptl} - 1]$.</p>
4:	<p>nptl – Integer Input</p> <p><i>On entry:</i> the number of points at which evaluations are required (the value of npoly + 1).</p>
5:	<p>u[npde × nptl] – const double Input</p> <p>Note: where $\mathbf{U}(i, j)$ appears in this document it refers to the array element u[npde × (j – 1) + i – 1]. We recommend using a #define to make the same definition in your calling program.</p> <p><i>On entry:</i> $\mathbf{U}(i, j)$ contains the value of the component $U_i(x, t)$ where $x = \mathbf{x}[j - 1]$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{nptl}$.</p>
6:	<p>ux[npde × nptl] – const double Input</p> <p>Note: where $\mathbf{UX}(i, j)$ appears in this document it refers to the array element ux[npde × (j – 1) + i – 1]. We recommend using a #define to make the same definition in your calling program.</p> <p><i>On entry:</i> $\mathbf{UX}(i, j)$ contains the value of the component $(\partial U_i(x, t))/(\partial x)$ where $x = \mathbf{x}[j - 1]$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{nptl}$.</p>
7:	<p>ncode – Integer Input</p> <p><i>On entry:</i> the number of coupled ODEs in the system.</p>
8:	<p>v[ncode] – const double Input</p> <p><i>On entry:</i> v[i – 1] contains the value of component $V_i(t)$, for $i = 1, 2, \dots, \mathbf{ncode}$.</p>
9:	<p>vdot[ncode] – const double Input</p> <p><i>On entry:</i> vdot[i – 1] contains the value of component $\dot{V}_i(t)$, for $i = 1, 2, \dots, \mathbf{ncode}$.</p> <p>Note: $\dot{V}_i(t)$, for $i = 1, 2, \dots, \mathbf{ncode}$, may only appear linearly in Q_j, for $j = 1, 2, \dots, \mathbf{npde}$.</p>
10:	<p>p[npde × npde × nptl] – double Output</p> <p>Note: where $\mathbf{P}(i, j, k)$ appears in this document it refers to the array element</p>

$\mathbf{p}[\mathbf{npde} \times (\mathbf{npde} \times (k - 1) + j - 1) + i - 1]$. We recommend using a #define to make the same definition in your calling program.

On exit: $\mathbf{P}(i, j, k)$ must be set to the value of $P_{i,j}(x, t, U, U_x, V)$ where $x = \mathbf{x}[k - 1]$, for $i, j = 1, 2, \dots, \mathbf{npde}$; $k = 1, 2, \dots, \mathbf{nptl}$.

11: $\mathbf{q}[\mathbf{npde} \times \mathbf{nptl}]$ – double *Output*

Note: where $\mathbf{Q}(i, j)$ appears in this document it refers to the array element $\mathbf{q}[\mathbf{npde} \times (j - 1) + i - 1]$. We recommend using a #define to make the same definition in your calling program.

On exit: $\mathbf{Q}(i, j)$ must be set to the value of $Q_i(x, t, U, U_x, V, \dot{V})$ where $x = \mathbf{x}[j - 1]$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{nptl}$.

12: $\mathbf{r}[\mathbf{npde} \times \mathbf{nptl}]$ – double *Output*

Note: where $\mathbf{R}(i, j)$ appears in this document it refers to the array element $\mathbf{r}[\mathbf{npde} \times (j - 1) + i - 1]$. We recommend using a #define to make the same definition in your calling program.

On exit: $\mathbf{R}(i, j)$ must be set to the value of $R_i(x, t, U, U_x, V)$ where $x = \mathbf{x}[i - 1]$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{nptl}$.

13: **ires** – Integer * *Input/Output*

On entry: set to -1 or 1 .

On exit: should usually remain unchanged. However, the user may set **ires** to force the integration function to take certain actions as described below:

ires = 2

Indicates to the integrator that control should be passed back immediately to the calling function with the error indicator set to **fail.code** = **NE_USER_STOP**.

ires = 3

Indicates to the integrator that the current time step should be abandoned and a smaller time step used instead. The user may wish to set **ires** = 3 when a physically meaningless input or output value has been generated. If the user consecutively sets **ires** = 3, then nag_pde_parab_1d_coll_ode (d03pjc) returns to the calling function with the error indicator set to **fail.code** = **NE_FAILED_DERIV**.

14: **comm** – NAG_Comm * *Input/Output*

The NAG communication parameter (see the Essential Introduction).

6: **bdnary** *Function*

bdnary must compute the functions β_i and γ_i which define the boundary conditions as in equation (4).

```
void bdnary (Integer npde, double t, const double u[], const double ux[],
            Integer ncode, const double v[], const double vdot[], Integer ibnd,
            double beta[], double gamma[], Integer *ires, Nag_Comm *comm)
```

1: **npde** – Integer *Input*

On entry: the number of PDEs in the system.

2: **t** – double *Input*

On entry: the current value of the independent variable t .

3:	u[npde] – const double	<i>Input</i>
	<i>On entry:</i> u [$i - 1$] contains the value of the component $U_i(x, t)$ at the boundary specified by ibnd , for $i = 1, 2, \dots, \text{npde}$.	
4:	ux[npde] – const double	<i>Input</i>
	<i>On entry:</i> ux [$i - 1$] contains the value of the component $(\partial U_i(x, t))/(\partial x)$ at the boundary specified by ibnd , for $i = 1, 2, \dots, \text{npde}$.	
5:	ncode – Integer	<i>Input</i>
	<i>On entry:</i> the number of coupled ODEs in the system.	
6:	v[ncode] – const double	<i>Input</i>
	<i>On entry:</i> v [$i - 1$] contains the value of component $V_i(t)$, for $i = 1, 2, \dots, \text{ncode}$.	
7:	vdot[ncode] – const double	<i>Input</i>
	<i>On entry:</i> vdot [$i - 1$] contains the value of component $\dot{V}_i(t)$, for $i = 1, 2, \dots, \text{ncode}$.	
	Note: $\dot{V}_i(t)$, for $i = 1, 2, \dots, \text{ncode}$, may only appear linearly in Q_j , for $j = 1, 2, \dots, \text{npde}$.	
8:	ibnd – Integer	<i>Input</i>
	<i>On entry:</i> specifies which boundary conditions are to be evaluated. If ibnd = 0, then boundary must set up the coefficients of the left-hand boundary, $x = a$. If ibnd \neq 0, then boundary must set up the coefficients of the right-hand boundary, $x = b$.	
9:	beta[npde] – double	<i>Output</i>
	<i>On exit:</i> beta [$i - 1$] must be set to the value of $\beta_i(x, t)$ at the boundary specified by ibnd , for $i = 1, 2, \dots, \text{npde}$.	
10:	gamma[npde] – double	<i>Output</i>
	<i>On exit:</i> gamma [$i - 1$] must be set to the value of $\gamma_i(x, t, U, U_x, V, \dot{V})$ at the boundary specified by ibnd , for $i = 1, 2, \dots, \text{npde}$.	
11:	ires – Integer *	<i>Input/Output</i>
	<i>On entry:</i> set to -1 or 1 .	
	<i>On exit:</i> should usually remain unchanged. However, the user may set ires to force the integration function to take certain actions as described below:	
	ires = 2	
	Indicates to the integrator that control should be passed back immediately to the calling function with the error indicator set to fail.code = NE_USER_STOP .	
	ires = 3	
	Indicates to the integrator that the current time step should be abandoned and a smaller time step used instead. The user may wish to set ires = 3 when a physically meaningless input or output value has been generated. If the user consecutively sets ires = 3, then <code>nag_pde_parab_1d_coll_ode</code> (d03pjc) returns to the calling function with the error indicator set to fail.code = NE_FAILED_DERIV .	
12:	comm – NAG_Comm *	<i>Input/Output</i>
	The NAG communication parameter (see the Essential Introduction).	

- 7: **u[neqn]** – double *Input/Output*
On entry: if **ind** = 1 the value of **u** must be unchanged from the previous call.
On exit: the computed solution $U_i(x_j, t)$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{npts}$ and $V_k(t)$, for $k = 1, 2, \dots, \mathbf{ncode}$, evaluated at $t = S$, as follows:
u[$\mathbf{npde} \times (j - 1) + i - 1$] contain $U_i(x_j, t)$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{npts}$ and
u[$\mathbf{npts} \times \mathbf{npde} + i - 1$] contain $V_i(t)$, for $i = 1, 2, \dots, \mathbf{ncode}$.
- 8: **nbkpts** – Integer *Input*
On entry: the number of break-points in the interval $[a, b]$.
Constraint: **nbkpts** ≥ 2 .
- 9: **xbkpts[nbkpts]** – const double *Input*
On entry: the values of the break-points in the space direction. **xbkpts**[0] must specify the left-hand boundary, a , and **xbkpts**[**nbkpts** – 1] must specify the right-hand boundary, b .
Constraint: **xbkpts**[0] < **xbkpts**[1] < \dots < **xbkpts**[**nbkpts** – 1].
- 10: **npoly** – Integer *Input*
On entry: the degree of the Chebyshev polynomial to be used in approximating the PDE solution between each pair of break-points.
Constraint: $1 \leq \mathbf{npoly} \leq 49$.
- 11: **npts** – Integer *Input*
On entry: the number of mesh points in the interval $[a, b]$.
Constraint: **npts** = (**nbkpts** – 1) \times **npoly** + 1.
- 12: **x[npts]** – double *Output*
On exit: the mesh points chosen by nag_pde_parab_1d_coll_ode (d03pjc) in the spatial direction. The values of **x** will satisfy **x**[0] < **x**[1] < \dots < **x**[**npts** – 1].
- 13: **ncode** – Integer *Input*
On entry: the number of coupled ODE components.
Constraint: **ncode** ≥ 0 .
- 14: **odedef** *Function*
odedef must evaluate the functions F , which define the system of ODEs, as given in (3). If the user wishes to compute the solution of a system of PDEs only (**ncode** = 0), **odedef** must be the dummy function d03pck. (d03pck is included in the NAG C Library; however, its name may be implementation-dependent: see the Users' Note for your implementation for details.)

```
void odedef (Integer npde, double t, Integer ncode, const double v[],
            const double vdot[], Integer nxi, const double xi[], const double ucp[],
            const double ucpx[], const double rcp[], const double ucpt[],
            const double ucptx[], double f[], Integer *ires, Nag_Comm *comm)
```

1: **npde** – Integer *Input*

On entry: the number of PDEs in the system.

2: **t** – double *Input*

On entry: the current value of the independent variable t .

3:	<p>ncode – Integer</p> <p><i>On entry:</i> the number of coupled ODEs in the system.</p>	<i>Input</i>
4:	<p>v[ncode] – const double</p> <p><i>On entry:</i> v[$i - 1$] contains the value of component $V_i(t)$, for $i = 1, 2, \dots, \mathbf{ncode}$.</p>	<i>Input</i>
5:	<p>vdot[ncode] – const double</p> <p><i>On entry:</i> vdot[$i - 1$] contains the value of component $\dot{V}_i(t)$, for $i = 1, 2, \dots, \mathbf{ncode}$.</p>	<i>Input</i>
6:	<p>nxl – Integer</p> <p><i>On entry:</i> the number of ODE/PDE coupling points.</p>	<i>Input</i>
7:	<p>xi[nxl] – const double</p> <p><i>On entry:</i> xi[$i - 1$] contains the ODE/PDE coupling points, ξ_i, $i = 1, 2, \dots, \mathbf{nxl}$.</p>	<i>Input</i>
8:	<p>ucp[npde \times nxl] – const double</p> <p>Note: where UCP(i, j) appears in this document it refers to the array element ucp[$\mathbf{npde} \times (j - 1) + i - 1$]. We recommend using a #define to make the same definition in your calling program.</p> <p><i>On entry:</i> UCP(i, j) contains the value of $U_i(x, t)$ at the coupling point $x = \xi_j$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{nxl}$.</p>	<i>Input</i>
9:	<p>ucpx[npde \times nxl] – const double</p> <p>Note: where UCPX(i, j) appears in this document it refers to the array element ucpx[$\mathbf{npde} \times (j - 1) + i - 1$]. We recommend using a #define to make the same definition in your calling program.</p> <p><i>On entry:</i> UCPX(i, j) contains the value of $(\partial U_i(x, t))/(\partial x)$ at the coupling point $x = \xi_j$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{nxl}$.</p>	<i>Input</i>
10:	<p>rcp[npde \times nxl] – const double</p> <p>Note: where RCP(i, j) appears in this document it refers to the array element rcp[$\mathbf{npde} \times (j - 1) + i - 1$]. We recommend using a #define to make the same definition in your calling program.</p> <p><i>On entry:</i> RCP(i, j) contains the value of the flux R_i at the coupling point $x = \xi_j$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{nxl}$.</p>	<i>Input</i>
11:	<p>ucpt[npde \times nxl] – const double</p> <p>Note: where UCPT(i, j) appears in this document it refers to the array element ucpt[$\mathbf{npde} \times (j - 1) + i - 1$]. We recommend using a #define to make the same definition in your calling program.</p> <p><i>On entry:</i> UCPT(i, j) contains the value of $(\partial U_i)/(\partial t)$ at the coupling point $x = \xi_j$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{nxl}$.</p>	<i>Input</i>
12:	<p>ucptx[npde \times nxl] – const double</p> <p>Note: where UCPTX(i, j) appears in this document it refers to the array element ucptx[$\mathbf{npde} \times (j - 1) + i - 1$]. We recommend using a #define to make the same definition in your calling program.</p> <p><i>On entry:</i> UCPTX(i, j) contains the value of $(\partial^2 U_i)/(\partial x \partial t)$ at the coupling point $x = \xi_j$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{nxl}$.</p>	<i>Input</i>

13:	<p>f[ncode] – double <i>Output</i></p> <p><i>On exit:</i> f[<i>i</i> – 1] must contain the <i>i</i>th component of <i>F</i>, for <i>i</i> = 1, 2, ..., ncode, where <i>F</i> is defined as</p> $F = G - A\dot{V} - B \begin{pmatrix} U_t^* \\ U_{xt}^* \end{pmatrix}, \quad (5)$ <p>or</p> $F = -A\dot{V} - B \begin{pmatrix} U_t^* \\ U_{xt}^* \end{pmatrix}. \quad (6)$ <p>The definition of <i>F</i> is determined by the input value of ires.</p>
14:	<p>ires – Integer * <i>Input/Output</i></p> <p><i>On entry:</i> the form of <i>F</i> that must be returned in the array f. If ires = 1, then the equation (5) above must be used. If ires = –1, then the equation (6) above must be used.</p> <p><i>On exit:</i> should usually remain unchanged. However, the user may reset ires to force the integration function to take certain actions as described below:</p> <p>ires = 2</p> <p style="padding-left: 2em;">Indicates to the integrator that control should be passed back immediately to the calling function with the error indicator set to fail.code = NE_USER_STOP.</p> <p>ires = 3</p> <p style="padding-left: 2em;">Indicates to the integrator that the current time step should be abandoned and a smaller time step used instead. The user may wish to set ires = 3 when a physically meaningless input or output value has been generated. If the user consecutively sets ires = 3, then nag_pde_parab_1d_coll_ode (d03pjc) returns to the calling function with the error indicator set to fail.code = NE_FAILED_DERIV.</p>
15:	<p>comm – NAG_Comm * <i>Input/Output</i></p> <p>The NAG communication parameter (see the Essential Introduction).</p>

- 15: **nxl** – Integer *Input*
- On entry:* the number of ODE/PDE coupling points.
- Constraints:*
- if **ncode** = 0, **nxl** = 0;
if **ncode** > 0, **nxl** ≥ 0.
- 16: **xi[dim]** – const double *Input*
- Note:** the dimension, *dim*, of the array **xi** must be at least max(1, **nxl**).
- On entry:* **xi**[*i* – 1], *i* = 1, 2, ..., **nxl**, must be set to the ODE/PDE coupling points.
- Constraint:* **xbkpts**[0] ≤ **xi**[0] < **xi**[1] < ... < **xi**[**nxl** – 1] ≤ **xbkpts**[**nbkpts** – 1].
- 17: **neqn** – Integer *Input*
- On entry:* the number of ODEs in the time direction.
- Constraint:* **neqn** = **npde** × **npts** + **ncode**.
- 18: **uvinit** *Function*
- uvinit** must compute the initial values of the PDE and the ODE components $U_i(x_j, t_0)$, for *i* = 1, 2, ..., **npde**; *j* = 1, 2, ..., **npts**, and $V_k(t_0)$, for *k* = 1, 2, ..., **ncode**.

```
void uvinit (Integer npde, Integer npts, const double x[], double u[],
             Integer ncode, double v[], Nag_Comm *comm)
```

- | | | |
|----|--|---------------------|
| 1: | npde – Integer | <i>Input</i> |
| | <i>On entry:</i> the number of PDEs in the system. | |
| 2: | npts – Integer | <i>Input</i> |
| | <i>On entry:</i> the number of mesh points in the interval $[a, b]$. | |
| 3: | x [npts] – const double | <i>Input</i> |
| | <i>On entry:</i> x [$i - 1$], for $i = 1, 2, \dots, \mathbf{npts}$, contains the current values of the space variable x_i . | |
| 4: | u [npde \times npts] – double | <i>Output</i> |
| | Note: where $\mathbf{U}(i, j)$ appears in this document it refers to the array element u [npde \times ($j - 1$) + $i - 1$]. We recommend using a #define to make the same definition in your calling program. | |
| | <i>On exit:</i> $\mathbf{U}(i, j)$ contains the value of the component $U_i(x_j, t_0)$, for $i = 1, 2, \dots, \mathbf{npde}$; $j = 1, 2, \dots, \mathbf{npts}$. | |
| 5: | ncode – Integer | <i>Input</i> |
| | <i>On entry:</i> the number of coupled ODEs in the system. | |
| 6: | v [ncode] – double | <i>Output</i> |
| | <i>On exit:</i> v [$i - 1$] contains the value of component $V_i(t_0)$, for $i = 1, 2, \dots, \mathbf{ncode}$. | |
| 7: | comm – NAG_Comm * | <i>Input/Output</i> |
| | The NAG communication parameter (see the Essential Introduction). | |

- 19: **rtol**[*dim*] – const double *Input*
- Note:** the dimension, *dim*, of the array **rtol** must be at least 1 when **itol** = 1 or 2 and at least **neqn** when **itol** = 3 or 4.
- On entry:* the relative local error tolerance.
- Constraint:* **rtol**[$i - 1$] ≥ 0 for all relevant i .
- 20: **atol**[*dim*] – const double *Input*
- Note:** the dimension, *dim*, of the array **atol** must be at least 1 when **itol** = 1 or 3 and at least **neqn** when **itol** = 2 or 4.
- On entry:* the absolute local error tolerance.
- Constraint:* **atol**[$i - 1$] ≥ 0 for all relevant i .
- 21: **itol** – Integer *Input*
- On entry:* a value to indicate the form of the local error test. **itol** indicates to nag_pde_parab_1d_coll_ode (d03pjc) whether to interpret either or both of **rtol** or **atol** as a vector or scalar. The error test to be satisfied is $\|e_i/w_i\| < 1.0$, where w_i is defined as follows:

itol	rtol	atol	w_i
1	scalar	scalar	rtol [0] \times $ U_i $ + atol [0]
2	scalar	vector	rtol [0] \times $ U_i $ + atol [$i - 1$]
3	vector	scalar	rtol [$i - 1$] \times $ U_i $ + atol [0]
4	vector	vector	rtol [$i - 1$] \times $ U_i $ + atol [$i - 1$]

In the above, e_i denotes the estimated local error for the i th component of the coupled PDE/ODE system in time, $\mathbf{u}[i - 1]$, for $i = 1, 2, \dots, \mathbf{neqn}$.

The choice of norm used is defined by the parameter **norm**, see below.

Constraint: $1 \leq \mathbf{itol} \leq 4$.

22: **norm** – Nag_NormType *Input*

On entry: the type of norm to be used. Two options are available:

norm = Nag_MaxNorm

Maximum norm.

norm = Nag_TwoNorm

Averaged L_2 norm.

If \mathbf{u}_{norm} denotes the norm of the vector \mathbf{u} of length **neqn**, then for the averaged L_2 norm

$$\mathbf{u}_{norm} = \sqrt{\frac{1}{\mathbf{neqn}} \sum_{i=1}^{\mathbf{neqn}} (\mathbf{u}[i - 1]/w_i)^2},$$

while for the maximum norm

$$\mathbf{u}_{norm} = \max_i |\mathbf{u}[i - 1]/w_i|.$$

See the description of the **itol** parameter for the formulation of the weight vector w .

Constraint: **norm = Nag_MaxNorm** or **Nag_TwoNorm**.

23: **laopt** – Nag_LinAlgOption *Input*

On entry: the type of matrix algebra required. The possible choices are:

laopt = Nag_LinAlgFull

Full matrix methods to be used.

laopt = Nag_LinAlgBand

Banded matrix methods to be used.

laopt = Nag_LinAlgSparse

Sparse matrix methods to be used.

Constraint: **laopt = Nag_LinAlgFull**, **Nag_LinAlgBand** or **Nag_LinAlgSparse**.

Note: the user is recommended to use the banded option when no coupled ODEs are present (i.e., **ncode** = 0).

24: **algot**[30] – const double *Input*

On entry: **algot** may be set to control various options available in the integrator. If the user wishes to employ all the default options, then **algot**[0] should be set to 0.0. Default values will also be used for any other elements of **algot** set to zero. The permissible values, default values, and meanings are as follows:

algot[0] selects the ODE integration method to be used. If **algot**[0] = 1.0, a BDF method is used and if **algot**[0] = 2.0, a Theta method is used. The default value is **algot**[0] = 1.0.

If **algot**[0] = 2.0, then **algot**[i], for $i = 1, 2, 3$ are not used.

- algopt**[1] specifies the maximum order of the BDF integration formula to be used. **algopt**[1] may be 1.0, 2.0, 3.0, 4.0 or 5.0. The default value is **algopt**[1] = 5.0.
- algopt**[2] specifies what method is to be used to solve the system of nonlinear equations arising on each step of the BDF method. If **algopt**[2] = 1.0 a modified Newton iteration is used and if **algopt**[2] = 2.0 a functional iteration method is used. If functional iteration is selected and the integrator encounters difficulty, then there is an automatic switch to the modified Newton iteration. The default value is **algopt**[2] = 1.0.
- algopt**[3] specifies whether or not the Petzold error test is to be employed. The Petzold error test results in extra overhead but is more suitable when algebraic equations are present, such as $P_{i,j} = 0.0$, for $j = 1, 2, \dots$, **npde** for some i or when there is no $\dot{V}_i(t)$ dependence in the coupled ODE system. If **algopt**[3] = 1.0, then the Petzold test is used. If **algopt**[3] = 2.0, then the Petzold test is not used. The default value is **algopt**[3] = 1.0.
- If **algopt**[0] = 1.0, then **algopt**[i], for $i = 4, 5, 6$ are not used.
- algopt**[4] specifies the value of Theta to be used in the Theta integration method. $0.51 \leq \mathbf{algopt}[4] \leq 0.99$. The default value is **algopt**[4] = 0.55.
- algopt**[5] specifies what method is to be used to solve the system of nonlinear equations arising on each step of the Theta method. If **algopt**[5] = 1.0, a modified Newton iteration is used and if **algopt**[5] = 2.0, a functional iteration method is used. The default value is **algopt**[5] = 1.0.
- algopt**[6] specifies whether or not the integrator is allowed to switch automatically between modified Newton and functional iteration methods in order to be more efficient. If **algopt**[6] = 1.0, then switching is allowed and if **algopt**[6] = 2.0, then switching is not allowed. The default value is **algopt**[6] = 1.0.
- algopt**[10] specifies a point in the time direction, t_{crit} , beyond which integration must not be attempted. The use of t_{crit} is described under the parameter **itask**. If **algopt**[0] \neq 0.0, a value of 0.0 for **algopt**[10], say, should be specified even if **itask** subsequently specifies that t_{crit} will not be used.
- algopt**[11] specifies the minimum absolute step size to be allowed in the time integration. If this option is not required, **algopt**[11] should be set to 0.0.
- algopt**[12] specifies the maximum absolute step size to be allowed in the time integration. If this option is not required, **algopt**[12] should be set to 0.0.
- algopt**[13] specifies the initial step size to be attempted by the integrator. If **algopt**[13] = 0.0, then the initial step size is calculated internally.
- algopt**[14] specifies the maximum number of steps to be attempted by the integrator in any one call. If **algopt**[14] = 0.0, then no limit is imposed.
- algopt**[22] specifies what method is to be used to solve the nonlinear equations at the initial point to initialise the values of U , U_t , V and \dot{V} . If **algopt**[22] = 1.0, a modified Newton iteration is used and if **algopt**[22] = 2.0, functional iteration is used. The default value is **algopt**[22] = 1.0.
- algopt**[28] and **algopt**[29] are used only for the sparse matrix algebra option, **laopt** = **Nag_LinAlgSparse**.
- algopt**[28] governs the choice of pivots during the decomposition of the first Jacobian matrix. It should lie in the range $0.0 < \mathbf{algopt}[28] < 1.0$, with smaller values biasing the algorithm towards maintaining sparsity at the expense of numerical stability. If **algopt**[28] lies outside this range then the default value is used. If the functions regard the Jacobian matrix as numerically singular then increasing **algopt**[28]

towards 1.0 may help, but at the cost of increased fill-in. The default value is $\mathbf{algot}[28] = 0.1$.

algot[29] is used as a relative pivot threshold during subsequent Jacobian decompositions (see **algot[28]**) below which an internal error is invoked. If **algot[29]** is greater than 1.0 no check is made on the pivot size, and this may be a necessary option if the Jacobian is found to be numerically singular (see **algot[28]**). The default value is $\mathbf{algot}[29] = 0.0001$.

25: **rsave[*lrsave*]** – double *Input/Output*

On entry: if **ind** = 0, **rsave** need not be set. If **ind** = 1 then it must be unchanged from the previous call to the function.

On exit: contains information about the iteration required for subsequent calls.

26: **lrsave** – Integer *Input*

On entry: the dimension of the array **rsave** as declared in the function from which `nag_pde_parab_1d_coll_ode (d03pic)` is called. Its size depends on the type of matrix algebra selected:

if **laopt** = **Nag_LinAlgFull**, $\mathbf{lrsave} \geq \mathbf{neqn} \times \mathbf{neqn} + \mathbf{neqn} + \mathbf{nwkres} + \mathbf{lenode}$;

if **laopt** = **Nag_LinAlgBand**, $\mathbf{lrsave} \geq (3 \times \mathbf{mlu} + 1) \times \mathbf{neqn} + \mathbf{nwkres} + \mathbf{lenode}$;

if **laopt** = **Nag_LinAlgSparse**, $\mathbf{lrsave} \geq 4 \times \mathbf{neqn} + 11 \times \mathbf{neqn}/2 + 1 + \mathbf{nwkres} + \mathbf{lenode}$,

where \mathbf{mlu} = the lower or upper half bandwidths, and
 $\mathbf{mlu} = 3 \times \mathbf{npde} - 1$, for PDE problems only, and
 $\mathbf{mlu} = \mathbf{neqn} - 1$, for coupled PDE/ODE problems.

$\mathbf{nwkres} = \mathbf{npde} \times (2 \times \mathbf{npts} + 6 \times \mathbf{nxi} + 3 \times \mathbf{npde} + 26) + \mathbf{nxi} + \mathbf{ncode} + 7 \times \mathbf{npts} + 2$,
 when $\mathbf{ncode} > 0$ and $\mathbf{nxi} > 0$, and

$\mathbf{nwkres} = \mathbf{npde} \times (2 \times \mathbf{npts} + 3 \times \mathbf{npde} + 32) + \mathbf{ncode} + 7 \times \mathbf{npts} + 3$, when $\mathbf{ncode} > 0$
 and $\mathbf{nxi} = 0$, and

$\mathbf{nwkres} = \mathbf{npde} \times (2 \times \mathbf{npts} + 3 \times \mathbf{npde} + 32) + 7 \times \mathbf{npts} + 4$, when $\mathbf{ncode} = 0$.

$\mathbf{lenode} = (6 + \text{int}(\mathbf{algot}[1])) \times \mathbf{neqn} + 50$, when the BDF method is used, and
 $\mathbf{lenode} = 9 \times \mathbf{neqn} + 50$, when the Theta method is used.

Note: when **laopt** = **Nag_LinAlgSparse**, the value of **lrsave** may be too small when supplied to the integrator. An estimate of the minimum size of **lrsave** is printed on the current error message unit if **itrace** > 0 and the function returns with **fail.code** = **NE.INT_2**.

27: **isave[*lisave*]** – Integer *Input/Output*

On entry: if **ind** = 0, **isave** need not be set. If **ind** = 1 then it must be unchanged from the previous call to the function.

On exit: contains information about the iteration required for subsequent calls. In particular:

isave[0] contains the number of steps taken in time.

isave[1] contains the number of residual evaluations of the resulting ODE system used. One such evaluation involves computing the PDE functions at all the mesh points, as well as one evaluation of the functions in the boundary conditions.

isave[2] contains the number of Jacobian evaluations performed by the time integrator.

isave[3] contains the order of the ODE method last used in the time integration.

isave[4] contains the number of Newton iterations performed by the time integrator. Each iteration involves residual evaluation of the resulting ODE system followed by a back-substitution using the *LU* decomposition of the Jacobian matrix.

28: **lisave** – Integer *Input*

On entry: the dimension of the array **isave** as declared in the function from which `nag_pde_parab_1d_coll_ode` (d03pjc) is called. Its size depends on the type of matrix algebra selected:

if **laopt** = **Nag_LinAlgFull**, **lisave** \geq 24

if **laopt** = **Nag_LinAlgBand**, **lisave** \geq **neqn** + 24

if **laopt** = **Nag_LinAlgSparse**, **lisave** \geq 25 \times **neqn** + 24

Note: when using the sparse option, the value of **lisave** may be too small when supplied to the integrator. An estimate of the minimum size of **lisave** is printed if **itrace** > 0 and the function returns with **fail.code** = **NE.INT.2**.

29: **itask** – Integer *Input*

On entry: specifies the task to be performed by the ODE integrator. The permitted values of **itask** and their meanings are detailed below:

itask = 1

Normal computation of output values **u** at $t = \mathbf{tout}$.

itask = 2

One step and return.

itask = 3

Stop at first internal integration point at or beyond $t = \mathbf{tout}$.

itask = 4

Normal computation of output values **u** at $t = \mathbf{tout}$ but without overshooting $t = t_{\text{crit}}$ where t_{crit} is described under the parameter **algopt**.

itask = 5

Take one step in the time direction and return, without passing t_{crit} , where t_{crit} is described under the parameter **algopt**.

Constraint: $1 \leq \mathbf{itask} \leq 5$.

30: **itrace** – Integer *Input*

On entry: the level of trace information required from `nag_pde_parab_1d_coll_ode` (d03pjc) and the underlying ODE solver. **itrace** may take the value -1, 0, 1, 2, or 3. If **itrace** < -1, then -1 is assumed and similarly if **itrace** > 3, then 3 is assumed. If **itrace** = -1, no output is generated. If **itrace** = 0, only warning messages from the PDE solver are printed. If **itrace** > 0, then output from the underlying ODE solver is printed. This output contains details of Jacobian entries, the nonlinear iteration and the time integration during the computation of the ODE system. The advisory messages are given in greater detail as **itrace** increases.

31: **outfile** – char * *Input*

On entry: the name of a file to which diagnostic output will be directed. If **outfile** is NULL the diagnostic output will be directed to standard output.

32: **ind** – Integer * *Input/Output*

On entry: **ind** must be set to 0 or 1.

ind = 0

Starts or restarts the integration in time.

ind = 1

Continues the integration after an earlier exit from the function. In this case, only the parameters **tout** and **fail** should be reset between calls to `nag_pde_parab_1d_coll_ode` (`d03pjc`).

Constraint: $0 \leq \mathbf{ind} \leq 1$.

On exit: **ind** = 1.

- 33: **comm** – NAG_Comm * *Input/Output*
The NAG communication parameter (see the Essential Introduction).
- 34: **saved** – Nag_D03_Save * *Input/Output*
Note: **saved** is a NAG defined structure. See Section 2.2.1.1 of the Essential Introduction.
On entry: if the current call to `nag_pde_parab_1d_coll_ode` (`d03pjc`) follows a previous call to a Chapter d03 function then **saved** must contain the unchanged value output from that previous call.
On exit: data to be passed unchanged to any subsequent call to a Chapter d03 function.
- 35: **fail** – NagError * *Input/Output*
The NAG error parameter (see the Essential Introduction).

6 Error Indicators and Warnings

NE_INT

On entry, **npde** = $\langle value \rangle$.

Constraint: **npde** ≥ 1 .

On entry, **nbkpts** = $\langle value \rangle$.

Constraint: **nbkpts** ≥ 2 .

On entry, **npoly** = $\langle value \rangle$.

Constraint: $1 \leq \mathbf{npoly} \leq 49$.

On entry, **ncode** = $\langle value \rangle$.

Constraint: **ncode** ≥ 0 .

On entry, **npoly** = $\langle value \rangle$.

Constraint: **npoly** ≥ 1 .

On entry, **m** is not equal to 0, 1, or 2: **m** = $\langle value \rangle$.

On entry, **ind** is not equal to 0 or 1: **ind** = $\langle value \rangle$.

On entry, **itask** is not equal to 1, 2, 3, 4 or 5: **itask** = $\langle value \rangle$.

On entry, **itol** is not equal to 1, 2, 3, or 4: **itol** = $\langle value \rangle$.

On entry, **ncode** = 0, but **nxi** is not equal to 0: **nxi** = $\langle value \rangle$.

On entry, **nxi** = $\langle value \rangle$.

Constraint: **nxi** ≥ 0 .

ires set to an invalid value in call to **pdedef**, **bdnary**, or **odedef**.

On entry, **npoly** = $\langle value \rangle$.

Constraint: **npoly** ≤ 49 .

NE_INT_2

On entry, **ncode** = $\langle value \rangle$, **nxi** = $\langle value \rangle$.
 Constraint: if **ncode** = 0, **nxi** = 0;
 if **ncode** > 0, **nxi** ≥ 0.

On entry, **lrsave** is too small: **lrsave** = $\langle value \rangle$. Minimum possible dimension: $\langle value \rangle$.

On entry, **lisave** is too small: **lisave** = $\langle value \rangle$. Minimum possible dimension: $\langle value \rangle$.

When using the sparse option **lisave** or **lrsave** is too small: **lisave** = $\langle value \rangle$, **lrsave** = $\langle value \rangle$.

On entry, corresponding elements **atol**[$i - 1$] and **rtol**[$j - 1$] are both zero. $i = \langle value \rangle$, $j = \langle value \rangle$.

NE_INT_3

On entry, **npts** is not equal to $(\mathbf{nbkpts} - 1) \times \mathbf{npoly} + 1$: **npts** = $\langle value \rangle$, **nbkpts** = $\langle value \rangle$,
npoly = $\langle value \rangle$.

NE_INT_4

On entry, **neqn** = $\langle value \rangle$, **npde** = $\langle value \rangle$, **npts** = $\langle value \rangle$, **ncode** = $\langle value \rangle$.
 Constraint: **neqn** = **npde** × **npts** + **ncode**.

On entry, **neqn** is not equal to **npde** × **npts** + **ncode**: **neqn** = $\langle value \rangle$, **npde** = $\langle value \rangle$,
npts = $\langle value \rangle$, **ncode** = $\langle value \rangle$.

NE_ACC_IN_DOUBT

Integration completed, but small changes in **atol** or **rtol** are unlikely to result in a changed solution.

NE_ENUM_CHARACTER

On entry, **norm** is not equal to A or m: **norm** = $\langle value \rangle$.

NE_FAILED_DERIV

In setting up the ODE system an internal auxiliary was unable to initialize the derivative. This could be due to user setting **ires** = 3 in **pdedef** or **bdary**.

NE_FAILED_START

atol and **rtol** were too small to start integration.

NE_FAILED_STEP

Repeated errors in an attempted step of underlying ODE solver. Integration was successful as far as **ts**: **ts** = $\langle value \rangle$.

Underlying ODE solver cannot make further progress from the point **ts** with the supplied values of **atol** and **rtol**. **ts** = $\langle value \rangle$.

Error during Jacobian formulation for ODE system. Increase **itrace** for further details.

NE_INCOMPAT_PARAM

On entry, **m** > 0 and **xbkpts**[0] < 0.0: **m** = $\langle value \rangle$, **xbkpts**[0] = $\langle value \rangle$.

NE_INTERNAL_ERROR

Serious error in internal call to an auxiliary. Increase **itrace** for further details.

NE_ITER_FAIL

In solving ODE system, the maximum number of steps **algopt**[14] has been exceeded.
algopt[14] = $\langle value \rangle$.

NE_NOT_STRICTLY_INCREASING

On entry $\mathbf{xi}[i] \leq \mathbf{xi}[i - 1]$: $i = \langle value \rangle$, $\mathbf{xi}[i] = \langle value \rangle$, $\mathbf{xi}[i - 1] = \langle value \rangle$.

On entry, break points \mathbf{xbkpts} badly ordered: $i = \langle value \rangle$, $\mathbf{xbkpts}[i - 1] = \langle value \rangle$ $j = \langle value \rangle$, $\mathbf{xbkpts}[j - 1] = \langle value \rangle$.

NE_REAL

On entry, $\mathbf{algopt}[0]$ is not equal to 0.0, 1.0, or 2.0: $\mathbf{algopt}[0] = \langle value \rangle$.

NE_REAL_2

On entry, at least one point in \mathbf{xi} lies outside $[\mathbf{xbkpts}[0], \mathbf{xbkpts}[\mathbf{nbkpts} - 1]]$: $\mathbf{xbkpts}[0] = \langle value \rangle$, $\mathbf{xbkpts}[\mathbf{nbkpts} - 1] = \langle value \rangle$.

On entry, $\mathbf{tout} - \mathbf{ts}$ is too small: $\mathbf{tout} = \langle value \rangle$, $\mathbf{ts} = \langle value \rangle$.

On entry, $\mathbf{tout} \leq \mathbf{ts}$: $\mathbf{tout} = \langle value \rangle$, $\mathbf{ts} = \langle value \rangle$.

NE_REAL_ARRAY

On entry, $\mathbf{rtol}[i - 1] < 0.0$: $i = \langle value \rangle$, $\mathbf{rtol}[i - 1] = \langle value \rangle$.

On entry, $\mathbf{atol}[i - 1] < 0.0$: $i = \langle value \rangle$, $\mathbf{atol}[i - 1] = \langle value \rangle$.

NE_SING_JAC

Singular Jacobian of ODE system. Check problem formulation.

NE_TIME_DERIV_DEP

Flux function appears to depend on time derivatives.

NE_USER_STOP

In evaluating residual of ODE system, $\mathbf{ires} = 2$ has been set in \mathbf{pdedef} , \mathbf{bndary} , or \mathbf{odedef} . Integration is successful as far as \mathbf{ts} : $\mathbf{ts} = \langle value \rangle$.

NE_ZERO_WTS

Zero error weights encountered during time integration.

NE_ALLOC_FAIL

Memory allocation failed.

NE_BAD_PARAM

On entry, parameter $\langle value \rangle$ had an illegal value.

NE_NOT_WRITE_FILE

Cannot open file $\langle value \rangle$ for writing.

NE_NOT_CLOSE_FILE

Cannot close file $\langle value \rangle$.

NE_INTERNAL_ERROR

An internal error has occurred in this function. Check the function call and any array sizes. If the call is correct then please consult NAG for assistance.

7 Accuracy

The function controls the accuracy of the integration in the time direction but not the accuracy of the approximation in space. The spatial accuracy depends on both the number of mesh points and on their distribution in space. In the time integration only the local error over a single step is controlled and so the accuracy over a number of steps cannot be guaranteed. The user should therefore test the effect of varying the accuracy parameter **atol** and **rtol**.

8 Further Comments

The parameter specification allows the user to include equations with only first-order derivatives in the space direction but there is no guarantee that the method of integration will be satisfactory for such systems. The position and nature of the boundary conditions in particular are critical in defining a stable problem.

The time taken depends on the complexity of the parabolic system and on the accuracy requested.

9 Example

This problem provides a simple coupled system of one PDE and one ODE.

$$(V_1)^2 \frac{\partial U_1}{\partial t} - x V_1 \dot{V}_1 \frac{\partial U_1}{\partial x} = \frac{\partial^2 U_1}{\partial x^2}$$

$$\dot{V}_1 = V_1 U_1 + \frac{\partial U_1}{\partial x} + 1 + t,$$

for $t \in [10^{-4}, 0.1 \times 2^i]$, $i = 1, 2, \dots, 5$, $x \in [0, 1]$.

The left boundary condition at $x = 0$ is

$$\frac{\partial U_1}{\partial x} = -V_1 \exp t.$$

The right boundary condition at $x = 1$ is

$$U_1 = -V_1 \dot{V}_1.$$

The initial conditions at $t = 10^{-4}$ are defined by the exact solution:

$$V_1 = t, \quad \text{and} \quad U_1(x, t) = \exp\{t(1-x)\} - 1.0, \quad x \in [0, 1],$$

and the coupling point is at $\xi_1 = 1.0$.

9.1 Program Text

```

/* nag_pde_parab_1d_coll_ode (d03pjc) Example Program.
 *
 * Copyright 2001 Numerical Algorithms Group.
 *
 * Mark 7, 2001.
 */

#include <stdio.h>
#include <math.h>
#include <nag.h>
#include <nag_stdlib.h>
#include <nagd03.h>

static void pdedef(Integer, double, const double[], Integer, const double[],
                  const double[], Integer, const double[], const double[],
                  double[], double[], double[], Integer *, Nag_Comm *);

static void bndary(Integer, double, const double[], const double[], Integer,
                  const double[], const double[], Integer, double[],
                  double [], Integer *, Nag_Comm *);

```

```

static void odedef(Integer, double, Integer, const double[], const double[],
                  Integer, const double[], const double[], const double[],
                  const double[], const double[], const double[], double[],
                  Integer *, Nag_Comm *);

static void uvinit(Integer, Integer, const double[], double[], Integer,
                  double[], Nag_Comm *);

static void exact(double, Integer, double *, double *);

#define U(I,J) u[npde*((J)-1)+(I)-1]
#define UX(I,J) ux[npde*((J)-1)+(I)-1]
#define UCP(I,J) ucp[npde*((J)-1)+(I)-1]
#define UCPX(I,J) ucpx[npde*((J)-1)+(I)-1]
#define P(I,J,K) p[npde*(npde*((K)-1)+(J)-1)+(I)-1]
#define Q(I,J) q[npde*((J)-1)+(I)-1]
#define R(I,J) r[npde*((J)-1)+(I)-1]

int main(void)
{
  const Integer npde=1, ncode=1, npoly=2, m=0, nbkpts=11,
    nel=nbkpts-1, npts=nel*npoly+1, neqn=npde*npts+ncode,
    nxi=1, lisave=24, npl1=npoly+1, nwkres=3*npl1*npl1+npl1*
    (npde*npde+6*npde+nbkpts+1)+8*npde+nxi*(5*npde+1)+ncode+3,
    lenode=11*neqn+50, lrsave=neqn*neqn+neqn+nwkres+lenode;
  double tout, ts;
  Integer exit_status, i, ind, it, itask, itol, itrace;
  Boolean theta;
  double *algotp=0, *atol=0, *exy=0, *rsave=0, *rtol=0,
    *u=0, *x=0, *xbkpts=0, *xi=0;
  Integer *isave=0;
  NagError fail;
  Nag_Comm comm;
  Nag_D03_Save saved;

  /* Allocate memory */

  if ( !(algotp = NAG_ALLOC(30, double)) ||
    !(atol = NAG_ALLOC(1, double)) ||
    !(exy = NAG_ALLOC(nbkpts, double)) ||
    !(rsave = NAG_ALLOC(lrsave, double)) ||
    !(rtol = NAG_ALLOC(1, double)) ||
    !(u = NAG_ALLOC(neqn, double)) ||
    !(x = NAG_ALLOC(npts, double)) ||
    !(xbkpts = NAG_ALLOC(nbkpts, double)) ||
    !(xi = NAG_ALLOC(nxi, double)) ||
    !(isave = NAG_ALLOC(lisave, Integer)) )
  {
    Vprintf("Allocation failure\n");
    exit_status = 1;
    goto END;
  }

  Vprintf(" d03pic Example Program Results\n");
  INIT_FAIL(fail);
  exit_status = 0;

  itrace = 0;
  itol = 1;
  atol[0] = 1e-4;
  rtol[0] = atol[0];
  Vprintf(" Degree of Polynomial =%4ld", npoly);
  Vprintf("   No. of elements =%4ld\n\n", nbkpts-1);
  Vprintf(" Simple coupled PDE using BDF\n ");
  Vprintf(" Accuracy requirement =%10.3e", atol[0]);
  Vprintf(" Number of points = %4ld\n\n", npts);

  /* Set break-points */

  for (i = 0; i < nbkpts; ++i) xbkpts[i] = i/(nbkpts-1.0);

```

```

xi[0] = 1.0;
ind = 0;
itask = 1;

/* Set theta = TRUE if the Theta integrator is required */

theta = FALSE;
for (i = 0; i < 30; ++i) algopt[i] = 0.0;

if (theta) {
    algopt[0] = 2.0;
} else {
    algopt[0] = 0.0;
}

/* Loop over output value of t */

ts = 1.e-4;
comm.p = (Pointer)
tout = 0.0;
Vprintf(" x          %9.3f%9.3f%9.3f%9.3f%9.3f\n\n",
        xbkpts[0], xbkpts[2], xbkpts[4], xbkpts[6], xbkpts[10]);

for (it = 0; it < 5; ++it)
{
    tout = 0.1*pow(npoly, (it+1.0));

    d03pjc(npde, m, &ts, tout, pdedef, bndary, u, nbkpts,
           xbkpts, npoly, npts, x, ncode, odedef, nxi, xi,
           neqn, uvinit, rtol, atol, itol, Nag_TwoNorm,
           Nag_LinAlgFull, algopt, rsave, lsave, isave,
           lisave, itask, itrace, 0, &ind, &comm, &saved, &fail);

    if (fail.code != NE_NOERROR)
    {
        Vprintf("Error from d03pjc.\n%s\n", fail.message);
        exit_status = 1;
        goto END;
    }

    /* Check against the exact solution */

    exact(tout, nbkpts, xbkpts, exy);
    Vprintf(" t = %6.3f\n", ts);
    Vprintf(" App. sol. %7.3f%9.3f%9.3f%9.3f%9.3f",
            u[0], u[4], u[8], u[12], u[20]);
    Vprintf(" ODE sol. =%8.3f\n", u[21]);
    Vprintf(" Exact sol. %7.3f%9.3f%9.3f%9.3f%9.3f",
            exy[0], exy[2], exy[4], exy[6], exy[10]);
    Vprintf(" ODE sol. =%8.3f\n\n", ts);
}
Vprintf(" Number of integration steps in time = %6ld\n", isave[0]);
Vprintf(" Number of function evaluations = %6ld\n", isave[1]);
Vprintf(" Number of Jacobian evaluations = %6ld\n", isave[2]);
Vprintf(" Number of iterations = %6ld\n\n", isave[4]);
END:
if (algot) NAG_FREE(algot);
if (atol) NAG_FREE(atol);
if (exy) NAG_FREE(exy);
if (rsave) NAG_FREE(rsave);
if (rtol) NAG_FREE(rtol);
if (u) NAG_FREE(u);
if (x) NAG_FREE(x);
if (xbkpts) NAG_FREE(xbkpts);
if (xi) NAG_FREE(xi);
if (isave) NAG_FREE(isave);

return exit_status;
}

static void uvinit(Integer npde, Integer npts, const double x[],

```

```

        double u[], Integer ncode, double v[],
        Nag_Comm *comm)
{
    /* Routine for PDE initial values (start time is 0.1e-6) */

    double *ts = (double *)comm->p;
    Integer i;

    v[0] = *ts;
    for (i = 1; i <= npts; ++i) U(1, i) = exp(*ts*(1.0- x[i-1])) - 1.0;
    return;
}

static void odedef(Integer npde, double t, Integer ncode,
    const double v[], const double vdot[],
    Integer nxi, const double xi[], const double ucp[],
    const double ucpx[], const double rcp[],
    const double ucpt[], const double ucptx[],
    double f[], Integer *ires, Nag_Comm *comm)
{
    if (*ires == 1)
    {
        f[0] = vdot[0] - v[0]*UCP(1, 1) - UCPX(1, 1) - 1.0 - t;
    } else if (*ires == -1) {
        f[0] = vdot[0];
    }
    return;
}

static void pdedef(Integer npde, double t, const double x[], Integer npt1,
    const double u[], const double ux[], Integer ncode,
    const double v[], const double vdot[], double p[],
    double q[], double r[], Integer *ires, Nag_Comm *comm)
{
    Integer i;
    for (i = 1; i <= npt1; ++i)
    {
        P(1, 1, i) = v[0]*v[0];
        R(1, i) = UX(1, i);
        Q(1, i) = -x[i-1]*UX(1, i)*v[0]*vdot[0];
    }
    return;
}

static void bndary(Integer npde, double t, const double u[],
    const double ux[], Integer ncode, const double v[],
    const double vdot[], Integer ibnd, double beta[],
    double gamma[], Integer *ires, Nag_Comm *comm)
{
    beta[0] = 1.0;
    if (ibnd == 0) {
        gamma[0] = -v[0]*exp(t);
    } else {
        gamma[0] = -v[0]*vdot[0];
    }
    return;
}

static void exact(double time, Integer npts, double *x, double *u)
{
    /* Exact solution (for comparison purposes) */

    Integer i;

    for (i = 0; i < npts; ++i) u[i] = exp(time*(1.0 - x[i])) - 1.0;

    return;
}

```

9.2 Program Data

None.

9.3 Program Results

d03pjc Example Program Results

Degree of Polynomial = 2 No. of elements = 10

Simple coupled PDE using BDF

Accuracy requirement = 1.000e-04 Number of points = 21

x	0.000	0.200	0.400	0.600	1.000		
t = 0.200							
App. sol.	0.222	0.174	0.128	0.084	0.001	ODE sol. =	0.200
Exact sol.	0.221	0.174	0.127	0.083	0.000	ODE sol. =	0.200
t = 0.400							
App. sol.	0.492	0.378	0.272	0.174	0.000	ODE sol. =	0.400
Exact sol.	0.492	0.377	0.271	0.174	0.000	ODE sol. =	0.400
t = 0.800							
App. sol.	1.226	0.897	0.617	0.378	0.000	ODE sol. =	0.800
Exact sol.	1.226	0.896	0.616	0.377	0.000	ODE sol. =	0.800
t = 1.600							
App. sol.	3.954	2.597	1.612	0.896	-0.001	ODE sol. =	1.600
Exact sol.	3.953	2.597	1.612	0.896	0.000	ODE sol. =	1.600
t = 3.200							
App. sol.	23.534	11.932	5.815	2.590	-0.008	ODE sol. =	3.202
Exact sol.	23.533	11.936	5.821	2.597	0.000	ODE sol. =	3.200
Number of integration steps in time = 39							
Number of function evaluations = 462							
Number of Jacobian evaluations = 15							
Number of iterations = 121							
