

NAG C Library Function Document

nag_ztpcon (f07uuc)

1 Purpose

nag_ztpcon (f07uuc) estimates the condition number of a complex triangular matrix, using packed storage.

2 Specification

```
void nag_ztpcon (Nag_OrderType order, Nag_NormType norm, Nag_UptoType uplo,
                 Nag_DiagType diag, Integer n, const Complex ap[], double *rcond,
                 NagError *fail)
```

3 Description

nag_ztpcon (f07uuc) estimates the condition number of a complex triangular matrix A , in either the 1-norm or the infinity-norm, using packed storage:

$$\kappa_1(A) = \|A\|_1 \|A^{-1}\|_1 \quad \text{or} \quad \kappa_\infty(A) = \|A\|_\infty \|A^{-1}\|_\infty.$$

Note that $\kappa_\infty(A) = \kappa_1(A^T)$.

Because the condition number is infinite if A is singular, the function actually returns an estimate of the **reciprocal** of the condition number.

The function computes $\|A\|_1$ or $\|A\|_\infty$ exactly, and uses Higham's implementation of Hager's method (Higham (1988)) to estimate $\|A^{-1}\|_1$ or $\|A^{-1}\|_\infty$.

4 References

Higham N J (1988) FORTRAN codes for estimating the one-norm of a real or complex matrix, with applications to condition estimation *ACM Trans. Math. Software* **14** 381–396

5 Parameters

1: **order** – Nag_OrderType *Input*

On entry: the **order** parameter specifies the two-dimensional storage scheme being used, i.e., row-major ordering or column-major ordering. C language defined storage is specified by **order** = Nag_RowMajor. See Section 2.2.1.4 of the Essential Introduction for a more detailed explanation of the use of this parameter.

Constraint: **order** = Nag_RowMajor or Nag_ColMajor.

2: **norm** – Nag_NormType *Input*

On entry: indicates whether $\kappa_1(A)$ or $\kappa_\infty(A)$ is estimated as follows:

- if **norm** = Nag_OneNorm, then $\kappa_1(A)$ is estimated;
- if **norm** = Nag_InfNorm, then $\kappa_\infty(A)$ is estimated.

Constraint: **norm** = Nag_OneNorm or Nag_InfNorm.

3: **uplo** – Nag_UptoType *Input*

On entry: indicates whether A is upper or lower triangular as follows:

if **uplo** = **Nag_Upper**, A is upper triangular;
 if **uplo** = **Nag_Lower**, A is lower triangular.

Constraint: **uplo** = **Nag_Upper** or **Nag_Lower**.

4: **diag** – Nag_DiagType *Input*

On entry: indicates whether A is a non-unit or unit triangular matrix as follows:

if **diag** = **Nag_NonUnitDiag**, A is a non-unit triangular matrix;
 if **diag** = **Nag_UnitDiag**, A is a unit triangular matrix; the diagonal elements are not referenced and are assumed to be 1.

Constraint: **diag** = **Nag_NonUnitDiag** or **Nag_UnitDiag**.

5: **n** – Integer *Input*

On entry: n , the order of the matrix A .

Constraint: **n** ≥ 0 .

6: **ap**[*dim*] – const Complex *Input*

Note: the dimension, *dim*, of the array **ap** must be at least $\max(1, \mathbf{n} \times (\mathbf{n} + 1)/2)$.

On entry: the n by n triangular matrix A , packed by rows or columns. The storage of elements a_{ij} depends on the **order** and **uplo** parameters as follows:

if **order** = **Nag_ColMajor** and **uplo** = **Nag_Upper**,
 a_{ij} is stored in **ap**[($j - 1$) \times $j/2 + i - 1$], for $i \leq j$;
 if **order** = **Nag_ColMajor** and **uplo** = **Nag_Lower**,
 a_{ij} is stored in **ap**[($2n - j$) \times ($j - 1$) $/2 + i - 1$], for $i \geq j$;
 if **order** = **Nag_RowMajor** and **uplo** = **Nag_Upper**,
 a_{ij} is stored in **ap**[($2n - i$) \times ($i - 1$) $/2 + j - 1$], for $i \leq j$;
 if **order** = **Nag_RowMajor** and **uplo** = **Nag_Lower**,
 a_{ij} is stored in **ap**[($i - 1$) \times $i/2 + j - 1$], for $i \geq j$.

7: **rcond** – double * *Output*

On exit: an estimate of the reciprocal of the condition number of A . **rcond** is set to zero if exact singularity is detected or the estimate underflows. If **rcond** is less than **machine precision**, A is singular to working precision.

8: **fail** – NagError * *Output*

The NAG error parameter (see the Essential Introduction).

6 Error Indicators and Warnings

NE_INT

On entry, **n** = $\langle value \rangle$.

Constraint: **n** ≥ 0 .

NE_ALLOC_FAIL

Memory allocation failed.

NE_BAD_PARAM

On entry, parameter $\langle value \rangle$ had an illegal value.

NE_INTERNAL_ERROR

An internal error has occurred in this function. Check the function call and any array sizes. If the call is correct then please consult NAG for assistance.

7 Accuracy

The computed estimate **rcond** is never less than the true value ρ , and in practice is nearly always less than 10ρ , although examples can be constructed where **rcond** is much larger.

8 Further Comments

A call to nag_ztpcon (f07uuc) involves solving a number of systems of linear equations of the form $Ax = b$ or $A^H x = b$; the number is usually 5 and never more than 11. Each solution involves approximately $4n^2$ real floating-point operations but takes considerably longer than a call to nag_zptrs (f07usc) with one right-hand side, because extra care is taken to avoid overflow when A is approximately singular.

The real analogue of this function is nag_dtpcon (f07ugc).

9 Example

To estimate the condition number in the 1-norm of the matrix A , where

$$A = \begin{pmatrix} 4.78 + 4.56i & 0.00 + 0.00i & 0.00 + 0.00i & 0.00 + 0.00i \\ 2.00 - 0.30i & -4.11 + 1.25i & 0.00 + 0.00i & 0.00 + 0.00i \\ 2.89 - 1.34i & 2.36 - 4.25i & 4.15 + 0.80i & 0.00 + 0.00i \\ -1.89 + 1.15i & 0.04 - 3.69i & -0.02 + 0.46i & 0.33 - 0.26i \end{pmatrix},$$

using packed storage. The true condition number in the 1-norm is 70.27.

9.1 Program Text

```
/* nag_ztpcon (f07uuc) Example Program.
*
* Copyright 2001 Numerical Algorithms Group.
*
* Mark 7, 2001.
*/
#include <stdio.h>
#include <nag.h>
#include <nag_stlib.h>
#include <nagf07.h>
#include <nagx02.h>

int main(void)
{
    /* Scalars */
    double rcond;
    Integer ap_len, i, j, n;
    Integer exit_status=0;
    Nag_UptoType uplo_enum;

    NagError fail;
    Nag_OrderType order;
    /* Arrays */
    char uplo[2];
    Complex *ap=0;

#ifndef NAG_COLUMN_MAJOR
#define A_UPPER(I,J) ap[J*(J-1)/2 + I - 1]
#define A_LOWER(I,J) ap[(2*n-J)*(J-1)/2 + I - 1]
    order = Nag_ColMajor;
#else

```

```

#define A_LOWER(I,J) ap[I*(I-1)/2 + J - 1]
#define A_UPPER(I,J) ap[(2*n-I)*(I-1)/2 + J - 1]
    order = Nag_RowMajor;
#endif

INIT_FAIL(fail);
Vprintf("f07uuc Example Program Results\n");

/* Skip heading in data file */
Vscanf("%*[^\n] ");
Vscanf("%ld%*[^\n] ", &n);
ap_len = n * (n + 1)/2;

/* Allocate memory */
if ( !(ap = NAG_ALLOC(n * n, Complex)) )
{
    Vprintf("Allocation failure\n");
    exit_status = -1;
    goto END;
}

/* Read A from data file */
Vscanf(' ', %ls '%*[^\n] ', uplo);
if (*(unsigned char *)uplo == 'L')
    uplo_enum = Nag_Lower;
else if (*(unsigned char *)uplo == 'U')
    uplo_enum = Nag_Upper;
else
{
    Vprintf("Unrecognised character for Nag_UptoType type\n");
    exit_status = -1;
    goto END;
}
if (uplo_enum == Nag_Upper)
{
    for (i = 1; i <= n; ++i)
    {
        for (j = i; j <= n; ++j)
            Vscanf(" ( %lf , %lf )", &A_UPPER(i,j).re, &A_UPPER(i,j).im);
    }
    Vscanf("%*[^\n] ");
}
else
{
    for (i = 1; i <= n; ++i)
    {
        for (j = 1; j <= i; ++j)
            Vscanf(" ( %lf , %lf )", &A_LOWER(i,j).re, &A_LOWER(i,j).im);
    }
    Vscanf("%*[^\n] ");
}

/* Estimate condition number */
f07uuc(order, Nag_OneNorm, uplo_enum, Nag_NonUnitDiag, n,
        ap, &rcond, &fail);
if (fail.code != NE_NOERROR)
{
    Vprintf("Error from f07uuc.\n%s\n", fail.message);
    exit_status = 1;
    goto END;
}
Vprintf("\n");
if (rcond >= X02AJC)
    Vprintf("Estimate of condition number =%10.2e\n", 1.0/rcond);
else
    Vprintf("A is singular to working precision\n");
END:
    if (ap) NAG_FREE(ap);

    return exit_status;
}

```

9.2 Program Data

```
f07uuc Example Program Data
 4                               :Value of N
 'L'                            :Value of UPLO
 ( 4.78, 4.56)
 ( 2.00,-0.30) (-4.11, 1.25)
 ( 2.89,-1.34) ( 2.36,-4.25) ( 4.15, 0.80)
 (-1.89, 1.15) ( 0.04,-3.69) (-0.02, 0.46) ( 0.33,-0.26) :End of matrix A
```

9.3 Program Results

```
f07uuc Example Program Results
Estimate of condition number = 3.74e+01
```
